

US Patent & Trademark Office

Patent Public Search | Text View

United States Patent	12418812
Kind Code	B2
Date of Patent	September 16, 2025
Inventor(s)	Zhou; Shanyu et al.

Enhanced signaling for beam failure detection reference signal with UE predicted beam failure

Abstract

This disclosure provides systems, methods and apparatus, including computer programs encoded on computer storage media, for enhanced signaling related to beam failure prediction. A user equipment (UE) predicts a beam failure condition prior to a number of beam failure instances within a time period reaching a configured threshold number of beam failures. The UE transmits an indicator of the predicted beam failure condition to a serving cell. The indicator may include a request for a change to a beam failure detection reference signal (BFD-RS) or to UE scheduling. The serving cell transmits a notification of a change to the BFD-RS or to UE scheduling in response to the indicator. The UE may continue to monitor for a beam failure condition based on the change or may adjust reception during a predicted duration of the beam failure based on the change.

Inventors: Zhou; Shanyu (San Diego, CA), Damnjanovic; Jelena (Del Mar, CA), Luo; Tao (San Diego, CA)

Applicant: QUALCOMM Incorporated (San Diego, CA)

Family ID: 1000008821162

Assignee: QUALCOMM Incorporated (San Diego, CA)

Appl. No.: 17/687219

Filed: March 04, 2022

Prior Publication Data

Document Identifier	Publication Date
US 20230284054 A1	Sep. 07, 2023

Publication Classification

Int. Cl.: H04W24/08 (20090101); H04L5/00 (20060101)

U.S. Cl.:

CPC H04W24/08 (20130101); H04L5/0048 (20130101);

Field of Classification Search

CPC: H04W (24/08); H04L (5/0048); H04L (5/0025); H04L (5/0053); H04L (5/0094)

References Cited

U.S. PATENT DOCUMENTS

Patent No.	Issued Date	Patentee Name	U.S. Cl.	CPC
11277302	12/2021	Cirik	N/A	H04W 76/28
11349548	12/2021	Mohandoss	N/A	H04B 17/17
2019/0238658	12/2018	Shimizu	N/A	H04W 4/46
2019/0261193	12/2018	Torsner	N/A	H04W 24/10
2020/0413273	12/2019	Turtinen	N/A	H04W 76/28
2021/0092003	12/2020	Zhou	N/A	H04B 7/0695
2021/0184748	12/2020	Luo	N/A	H04W 52/143
2021/0218457	12/2020	Xu	N/A	H04B 7/088
2021/0243073	12/2020	Pezeshki	N/A	H04L 41/16
2021/0258063	12/2020	Ottersten	N/A	H04W 24/10
2022/0022065	12/2021	Wang	N/A	H04W 24/08
2022/0029286	12/2021	Cho	N/A	H01Q 21/06
2022/0109547	12/2021	Svedman	N/A	H04B 7/0626
2022/0140884	12/2021	Shi	370/329	H04W 76/19
2022/0247474	12/2021	Rune	N/A	H04W 24/10
2023/0006727	12/2022	Jang	N/A	H04L 5/0051
2023/0084028	12/2022	Karimidehkordi	370/216	H04B 7/06964
2023/0088966	12/2022	Kocagoez	370/241	H04W 24/08
2023/0107880	12/2022	Zhu	370/329	H04L 5/0094
2023/0171836	12/2022	Butt	370/216	H04W 76/19
2023/0337277	12/2022	Niu	N/A	H04W 74/0808
2024/0349092	12/2023	Echigo	N/A	H04W 74/0833
2025/0030475	12/2024	Li	N/A	H04W 72/21
2025/0150918	12/2024	Löhr	N/A	H04W 76/27

Primary Examiner: Vu; Hoang-Chuong Q

Attorney, Agent or Firm: Arent Fox, LLP

Background/Summary

TECHNICAL FIELD

(1) The present disclosure relates to wireless communications including enhanced signaling for beam failure detection reference signal (BFD-RS) with user equipment (UE) predicted beam

failure.

DESCRIPTION OF THE RELATED TECHNOLOGY

(2) Wireless communication systems are widely deployed to provide various telecommunication services such as telephony, video, data, messaging, and broadcasts. Typical wireless communication systems may employ multiple-access technologies capable of supporting communication with multiple users by sharing available system resources. Examples of such multiple-access technologies include code division multiple access (CDMA) systems, time division multiple access (TDMA) systems, frequency division multiple access (FDMA) systems, orthogonal frequency division multiple access (OFDMA) systems, single-carrier frequency division multiple access (SC-FDMA) systems, and time division synchronous code division multiple access (TD-SCDMA) systems.

(3) These multiple access technologies have been adopted in various telecommunication standards to provide a common protocol that enables different wireless devices to communicate on a municipal, national, regional, and even global level. An example telecommunication standard is 5G New Radio (NR). 5G NR is part of a continuous mobile broadband evolution promulgated by Third Generation Partnership Project (3GPP) to meet new requirements associated with latency, reliability, security, scalability (such as with Internet of Things (IoT)), and other requirements. 5G NR includes services associated with enhanced mobile broadband (eMBB), massive machine type communications (mMTC), and ultra-reliable low latency communications (URLLC). Some aspects of 5G NR may be based on the 4G Long Term Evolution (LTE) standard.

SUMMARY

(4) The systems, methods and devices of this disclosure each have several innovative aspects, no single one of which is solely responsible for the desirable attributes disclosed herein.

(5) In some aspects, the techniques described herein relate to a method of wireless communication for a user equipment (UE), including: predicting a beam failure prior to a number of beam failure instances within a time period reaching a configured threshold number of beam failures; transmitting an indicator of the predicted beam failure to a serving cell; and receiving a notification of a change to a beam failure detection reference signal (BFD-RS) or to UE scheduling in response to the indicator.

(6) The present disclosure also provides an apparatus (e.g., a UE) including a memory storing computer-executable instructions and at least one processor configured to execute the computer-executable instructions to perform the above method, an apparatus including means for performing the above method, and a non-transitory computer-readable medium storing computer-executable instructions for performing the above method.

(7) One innovative aspect of the subject matter described in this disclosure can be implemented in a method of wireless communication at an apparatus of a transmitting device such as a base station (BS). In some aspects, the techniques described herein relate to a method of wireless communication at a serving cell, including: receiving an indicator of a predicted beam failure at a UE; and transmitting a notification of a change to a beam failure detection reference signal (BFD-RS) or to UE scheduling in response to the indicator.

(8) The present disclosure also provides an apparatus (e.g., a BS) including a memory storing computer-executable instructions and at least one processor configured to execute the computer-executable instructions to perform the above method, an apparatus including means for performing the above method, and a non-transitory computer-readable medium storing computer-executable instructions for performing the above method.

(9) Details of one or more implementations of the subject matter described in this disclosure are set forth in the accompanying drawings and the description below. Other features, aspects, and advantages will become apparent from the description, the drawings and the claims. Note that the relative dimensions of the following figures may not be drawn to scale.

Description

BRIEF DESCRIPTION OF THE DRAWINGS

- (1) FIG. 1 is a diagram illustrating an example of a wireless communications system and an access network.
- (2) FIG. 2A is a diagram illustrating an example of a first frame.
- (3) FIG. 2B is a diagram illustrating an example of DL channels within a subframe.
- (4) FIG. 2C is a diagram illustrating an example of a second frame.
- (5) FIG. 2D is a diagram illustrating an example of a subframe.
- (6) FIG. 3 is a diagram illustrating an example of a base station (BS) and user equipment (UE) in an access network.
- (7) FIG. 4 shows a diagram illustrating an example disaggregated base station architecture.
- (8) FIG. 5 is a diagram illustrating an example of a beam failure detection procedure.
- (9) FIG. 6 is a diagram illustrating an example of a beam failure detection procedure with prediction.
- (10) FIG. 7 is a message diagram illustrating example messages between a base station and a UE.
- (11) FIG. 8 is a conceptual data flow diagram illustrating the data flow between different means/components in an example base station.
- (12) FIG. 9 is a conceptual data flow diagram illustrating the data flow between different means/components in an example UE.
- (13) FIG. 10 is a flowchart of an example method for a UE to perform beam failure detection procedures using beam failure prediction.
- (14) FIG. 11 is a flowchart of an example method for a base station to control beam failure prediction at a UE.
- (15) Like reference numbers and designations in the various drawings indicate like elements.

DETAILED DESCRIPTION

(16) The following description is directed to certain implementations for the purposes of describing the innovative aspects of this disclosure. However, a person having ordinary skill in the art will readily recognize that the teachings herein can be applied in a multitude of different ways. Some of the examples in this disclosure are based on wireless and wired local area network (LAN) communication according to the Institute of Electrical and Electronics Engineers (IEEE) 802.11 wireless standards, the IEEE 802.3 Ethernet standards, and the IEEE 1901 Powerline communication (PLC) standards. However, the described implementations may be implemented in any device, system or network that is capable of transmitting and receiving RF signals according to any of the wireless communication standards, including any of the IEEE 802.11 standards, the Bluetooth® standard, code division multiple access (CDMA), frequency division multiple access (FDMA), time division multiple access (TDMA), Global System for Mobile communications (GSM), GSM/General Packet Radio Service (GPRS), Enhanced Data GSM Environment (EDGE), Terrestrial Trunked Radio (TETRA), Wideband-CDMA (W-CDMA), Evolution Data Optimized (EV-DO), 1×EV-DO, EV-DO Rev A, EV-DO Rev B, High Speed Packet Access (HSPA), High Speed Downlink Packet Access (HSDPA), High Speed Uplink Packet Access (HSUPA), Evolved High Speed Packet Access (HSPA+), Long Term Evolution (LTE), AMPS, or other known signals that are used to communicate within a wireless, cellular or internet of things (IOT) network, such as a system utilizing 3G, 4G or 5G, or further implementations thereof, technology.

(17) In wireless communications, beamforming may be used to compensate for power loss in communication between a transmitter and receiver. For example, in millimeter wave (mmW or mmWave) communications, the frequency may be relatively high compared to conventional communication channels and signal attenuation may be relatively large. However, due to the uncertain nature of a wireless environment and unexpected blocking, beam may be vulnerable to

beam failure. 5G systems may implement a beam failure detection (BFD) procedure to assist in maintaining a strong channel connection between a user equipment (UE) and a base station. In a BFD procedure, the UE may be configured with rules for determining whether a beam failure has occurred based on physical layer measurements of a beam failure detection reference signal (BFD-RS). For example, the UE may count a number of beam failure instances during a measurement window. If the number of beam failure instances satisfies a threshold during the measurement window, the UE may declare a beam failure.

(18) In some cases, a UE may be able to predict a beam failure before the UE has satisfied the configured rules for declaring a beam failure. For example, a UE may include additional sensors such as a camera or radar that can be used to predict a blockage scenario before the threshold number of beam failure instances occur. As another example, a UE may train a machine-learning model based on the beam failure detection and/or other measurements to predict how likely a beam failure is to occur.

(19) In an aspect, the present disclosure provides for enhanced signaling related to beam failure detection. For example, when the UE predicts a likely beam failure, the UE may indicate the predicted beam failure to the base station. The base station may modify the BFD-RS or UE scheduling in response to the indicator. For example, the base station may change a BFD-RS pattern or periodicity. For instance, reducing the periodicity of the BFD-RS such that the UE is able to perform the physical layer measurements more frequently may allow the UE to declare a beam failure more quickly. In some implementations, for example, where the UE is able to detect a limited blockage, the indicator of the predicted beam failure may include a request not to schedule the UE or a request not to transmit the BFD-RS.

(20) Particular implementations of the subject matter described in this disclosure can be implemented to realize one or more of the following potential advantages. The enhanced signaling for BFD-RS may allow a UE to detect a beam failure more quickly. Accordingly, the UE may be able to recover from the failed beam. Additionally, the base station may improve scheduling or power efficiency based on prediction of a beam failure.

(21) Several aspects of telecommunication systems will now be presented with reference to various apparatus and methods. These apparatus and methods will be described in the following detailed description and illustrated in the accompanying drawings by various blocks, components, circuits, processes, algorithms, etc. (collectively referred to as “elements”). These elements may be implemented using electronic hardware, computer software, or any combination thereof. Whether such elements are implemented as hardware or software depends upon the particular application and design constraints imposed on the overall system.

(22) By way of example, an element, or any portion of an element, or any combination of elements may be implemented as a “processing system” that includes one or more processors. Examples of processors include microprocessors, microcontrollers, graphics processing units (GPUs), central processing units (CPUs), application processors, digital signal processors (DSPs), reduced instruction set computing (RISC) processors, systems on a chip (SoC), baseband processors, field programmable gate arrays (FPGAs), programmable logic devices (PLDs), state machines, gated logic, discrete hardware circuits, and other suitable hardware configured to perform the various functionality described throughout this disclosure. The processor may include an interface or be coupled to an interface that can obtain or output signals. The processor may obtain signals via the interface and output signals via the interface. In some implementations, the interface may be a printed circuit board (PCB) transmission line. In some other implementations, the interface may include a wireless transmitter, a wireless transceiver, or a combination thereof. For example, the interface may include a radio frequency (RF) transceiver which can be implemented to receive or transmit signals, or both. One or more processors in the processing system may execute software. Software shall be construed broadly to mean instructions, instruction sets, code, code segments, program code, programs, subprograms, software components, applications, software applications,

software packages, routines, subroutines, objects, executables, threads of execution, procedures, functions, etc., whether referred to as software, firmware, middleware, microcode, hardware description language, or otherwise.

(23) Accordingly, in one or more example implementations, the functions described may be implemented in hardware, software, or any combination thereof. If implemented in software, the functions may be stored on or encoded as one or more instructions or code on a computer-readable medium. Computer-readable media includes computer storage media, which may be referred to as non-transitory computer-readable media. Non-transitory computer-readable media may exclude transitory signals. Storage media may be any available media that can be accessed by a computer. By way of example, and not limitation, such computer-readable media can include a random-access memory (RAM), a read-only memory (ROM), an electrically erasable programmable ROM (EEPROM), optical disk storage, magnetic disk storage, other magnetic storage devices, combinations of the aforementioned types of computer-readable media, or any other medium that can be used to store computer executable code in the form of instructions or data structures that can be accessed by a computer.

(24) FIG. 1 is a diagram illustrating an example of a wireless communications system and an access network **100**. The wireless communications system (also referred to as a wireless wide area network (WWAN)) includes base stations **102**, UEs **104**, relay devices **105**, an Evolved Packet Core (EPC) **160**, and another core network **190** (such as a 5G Core (5GC)). The base stations **102** may include macrocells (high power cellular base station) or small cells (low power cellular base station). The macrocells include base stations. The small cells include femtocells, picocells, and microcells. The small cells include femtocells, picocells, and microcells. The base stations **102** can be configured in a Disaggregated RAN (D-RAN) or Open RAN (O-RAN) architecture, where functionality is split between multiple units such as a central unit (CU), one or more distributed units (DUs), or a radio unit (RU). Such architectures may be configured to utilize a protocol stack that is logically split between one or more units (such as one or more CUs and one or more DUs). In some aspects, the CUs may be implemented within an edge RAN node, and in some aspects, one or more DUs may be co-located with a CU, or may be geographically distributed throughout one or multiple RAN nodes. The DUs may be implemented to communicate with one or more RUs. Each of the CU, DU and RU also can be implemented as virtual units, i.e., a virtual central unit (VCU), a virtual distributed unit (VDU), or a virtual radio unit (VRU).

(25) Base station-type operation or network design may consider aggregation characteristics of base station functionality. For example, disaggregated base stations may be utilized in an integrated access backhaul (IAB) network, an open radio access network (O-RAN (such as the network configuration sponsored by the O-RAN Alliance)), or a virtualized radio access network (vRAN, also known as a cloud radio access network (C-RAN)). Disaggregation may include distributing functionality across two or more units at various physical locations, as well as distributing functionality for at least one unit virtually, which can enable flexibility in network design. The various units of the disaggregated base station, or disaggregated RAN architecture, can be configured for wired or wireless communication with at least one other unit.

(26) In some implementations, one or more of the receiving devices such as UEs **104** may include beam management component **140** adapts a beam failure detection procedure based on a predicted beam failure. The beam management component **140** may include a BF prediction component **142** configured to predict a beam failure prior to a number of beam failure instances within a time period reaching a configured threshold number of beam failures. The beam management component **140** may include an indicator component **144** configured to transmit an indicator of the predicted beam failure to a serving cell. The beam management component **140** may include a notification component **146** configured to receive a notification of a change to a BFD-RS or UE scheduling in response to the indicator. The beam management component **140** may optionally include a configuration component **148** configured to receive a configuration of a triggering

condition to predict the beam failure or a configuration of the indicator. The beam management component **140** may optionally include an activation component **149** configured to receive an activation or a deactivation of beam failure prediction.

(27) In some implementations, one or more of the base stations **102** may include a prediction control component **120** configured to control beam failure prediction for a UE. The prediction control component **120** may include an indicator Rx component **122** configured to receive an indicator of a predicted beam failure at a UE. The prediction control component **120** may include a notification Tx component **124** configured to transmit a notification of a change to a BFD-RS or UE scheduling in response to the indicator.

(28) The base stations **102** configured for 4G LTE (collectively referred to as Evolved Universal Mobile Telecommunications System (UMTS) Terrestrial Radio Access Network (E-UTRAN)) may interface with the EPC **160** through first backhaul links **132** (such as S1 interface), which may be wired or wireless. The base stations **102** configured for 5G NR (collectively referred to as Next Generation RAN (NG-RAN)) may interface with core network **190** through second backhaul links **184**, which may be wired or wireless. In addition to other functions, the base stations **102** may perform one or more of the following functions: transfer of user data, radio channel ciphering and deciphering, integrity protection, header compression, mobility control functions (such as handover, dual connectivity), inter-cell interference coordination, connection setup and release, load balancing, distribution for non-access stratum (NAS) messages, NAS node selection, synchronization, radio access network (RAN) sharing, multimedia broadcast multicast service (MBMS), subscriber and equipment trace, RAN information management (RIM), paging, positioning, and delivery of warning messages. The base stations **102** may communicate directly or indirectly (such as through the EPC **160** or core network **190**) with each other over third backhaul links **134** (such as X2 interface). The third backhaul links **134** may be wired or wireless.

(29) The base stations **102** may wirelessly communicate with the UEs **104**. Each of the base stations **102** may provide communication coverage for a respective geographic coverage area **110**. There may be overlapping geographic coverage areas **110**. For example, the small cell **102'** may have a coverage area **110'** that overlaps the coverage area **110** of one or more macro base stations **102**. A network that includes both small cell and macrocells may be known as a heterogeneous network. A heterogeneous network also may include Home Evolved Node Bs (eNBs) (HeNBs), which may provide service to a restricted group known as a closed subscriber group (CSG). The communication links **112** between the base stations **102** and the UEs **104** may include UL (also referred to as reverse link) transmissions from a UE **104** to a base station **102** or DL (also referred to as forward link) transmissions from a base station **102** to a UE **104**. The communication links **112** may use multiple-input and multiple-output (MIMO) antenna technology, including spatial multiplexing, beamforming, or transmit diversity. The communication links may be through one or more carriers. The base stations **102**/UEs **104** may use spectrum up to Y MHz (such as 5, 10, 15, 20, 100, 400, etc. MHz) bandwidth per carrier allocated in a carrier aggregation of up to a total of Yx MHz (x component carriers) used for transmission in each direction. The carriers may or may not be adjacent to each other. Allocation of carriers may be asymmetric with respect to DL and UL (such as more or fewer carriers may be allocated for DL than for UL). The component carriers may include a primary component carrier and one or more secondary component carriers. A primary component carrier may be referred to as a primary cell (PCell) and a secondary component carrier may be referred to as a secondary cell (SCell).

(30) Certain UEs **104** may communicate with each other using device-to-device (D2D) communication link **158**. The D2D communication link **158** may use the DL/UL WWAN spectrum. The D2D communication link **158** may use one or more sidelink channels, such as a physical sidelink broadcast channel (PSBCH), a physical sidelink discovery channel (PSDCH), a physical sidelink shared channel (PSSCH), and a physical sidelink control channel (PSCCH). D2D communication may be through a variety of wireless D2D communications systems, such as for

example, FlashLinQ, WiMedia, Bluetooth, ZigBee, Wi-Fi based on the IEEE 802.11 standard, LTE, or NR.

(31) The wireless communications system may further include a Wi-Fi access point (AP) **150** in communication with Wi-Fi stations (STAs) **152** via communication links **154** in a 5 GHz unlicensed frequency spectrum. When communicating in an unlicensed frequency spectrum, the STAs **152**/AP **150** may perform a clear channel assessment (CCA) prior to communicating in order to determine whether the channel is available.

(32) The small cell **102'** may operate in a licensed or an unlicensed frequency spectrum. When operating in an unlicensed frequency spectrum, the small cell **102'** may employ NR and use the same 5 GHz unlicensed frequency spectrum as used by the Wi-Fi AP **150**. The small cell **102'**, employing NR in an unlicensed frequency spectrum, may boost coverage to or increase capacity of the access network.

(33) A base station **102**, whether a small cell **102'** or a large cell (such as macro base station), may include an eNB, gNodeB (gNB), or other type of base station. Some base stations, such as gNB **180** may operate in one or more frequency bands within the electromagnetic spectrum.

(34) The electromagnetic spectrum is often subdivided, based on frequency/wavelength, into various classes, bands, channels, etc. In 5G NR two initial operating bands have been identified as frequency range designations FR1 (410 MHz-7.125 GHz) and FR2 (24.25 GHz-52.6 GHz). The frequencies between FR1 and FR2 are often referred to as mid-band frequencies. Although a portion of FR1 is greater than 6 GHz, FR1 is often referred to (interchangeably) as a “Sub-6 GHz” band in various documents and articles. A similar nomenclature issue sometimes occurs with regard to FR2, which is often referred to (interchangeably) as a “millimeter wave” (mmW) band in documents and articles, despite being different from the extremely high frequency (EHF) band (30 GHz-300 GHz) which is identified by the International Telecommunications Union (ITU) as a “millimeter wave” band.

(35) With the above aspects in mind, unless specifically stated otherwise, it should be understood that the term “sub-6 GHz” or the like if used herein may broadly represent frequencies that may be less than 6 GHz, may be within FR1, or may include mid-band frequencies. Further, unless specifically stated otherwise, it should be understood that the term “millimeter wave” or the like if used herein may broadly represent frequencies that may include mid-band frequencies, may be within FR2, or may be within the EHF band. Communications using the mmW radio frequency band have extremely high path loss and a short range. The mmW base station **180** may utilize beamforming **182** with the UE **104** to compensate for the path loss and short range.

(36) The EPC **160** may include a Mobility Management Entity (MME) **162**, other MMES **164**, a Serving Gateway **166**, a Multimedia Broadcast Multicast Service (MBMS) Gateway **168**, a Broadcast Multicast Service Center (BM-SC) **170**, and a Packet Data Network (PDN) Gateway **172**. The MME **162** may be in communication with a Home Subscriber Server (HSS) **174**. The MME **162** is the control node that processes the signaling between the UEs **104** and the EPC **160**. Generally, the MME **162** provides bearer and connection management. All user Internet protocol (IP) packets are transferred through the Serving Gateway **166**, which itself is connected to the PDN Gateway **172**. The PDN Gateway **172** provides UE IP address allocation as well as other functions. The PDN Gateway **172** and the BM-SC **170** are connected to the IP Services **176**. The IP Services **176** may include the Internet, an intranet, an IP Multimedia Subsystem (IMS), a PS Streaming Service, or other IP services. The BM-SC **170** may provide functions for MBMS user service provisioning and delivery. The BM-SC **170** may serve as an entry point for content provider MBMS transmission, may be used to authorize and initiate MBMS Bearer Services within a public land mobile network (PLMN), and may be used to schedule MBMS transmissions. The MBMS Gateway **168** may be used to distribute MBMS traffic to the base stations **102** belonging to a Multicast Broadcast Single Frequency Network (MBSFN) area broadcasting a particular service, and may be responsible for session management (start/stop) and for collecting eMBMS related

charging information.

(37) The core network **190** may include an Access and Mobility Management Function (AMF) **192**, other AMFs **193**, a Session Management Function (SMF) **194**, and a User Plane Function (UPF) **195**. The AMF **192** may be in communication with a Unified Data Management (UDM) **196**. The AMF **192** is the control node that processes the signaling between the UEs **104** and the core network **190**. Generally, the AMF **192** provides QoS flow and session management. All user Internet protocol (IP) packets are transferred through the UPF **195**. The UPF **195** provides UE IP address allocation as well as other functions. The UPF **195** is connected to the IP Services **197**. The IP Services **197** may include the Internet, an intranet, an IP Multimedia Subsystem (IMS), a PS Streaming Service, or other IP services.

(38) The base station may include or be referred to as a gNB, Node B, eNB, an access point, a base transceiver station, a radio base station, a radio transceiver, a transceiver function, a basic service set (BSS), an extended service set (ESS), a transmit reception point (TRP), or some other suitable terminology. The base station **102** provides an access point to the EPC **160** or core network **190** for a UE **104**. Examples of UEs **104** include a cellular phone, a smart phone, a session initiation protocol (SIP) phone, a laptop, a personal digital assistant (PDA), a satellite radio, a global positioning system, a multimedia device, a video device, a digital audio player (such as a MP3 player), a camera, a game console, a tablet, a smart device, a wearable device, a vehicle, an electric meter, a gas pump, a large or small kitchen appliance, a healthcare device, an implant, a sensor/actuator, a display, or any other similar functioning device. Some of the UEs **104** may be referred to as IoT devices (such as a parking meter, gas pump, toaster, vehicles, heart monitor, etc.). The UE **104** also may be referred to as a station, a mobile station, a subscriber station, a mobile unit, a subscriber unit, a wireless unit, a remote unit, a mobile device, a wireless device, a wireless communications device, a remote device, a mobile subscriber station, an access terminal, a mobile terminal, a wireless terminal, a remote terminal, a handset, a user agent, a mobile client, a client, or some other suitable terminology.

(39) Although the following description may be focused on 5G NR, the concepts described herein may be applicable to other similar areas, such as LTE, LTE-A, CDMA, GSM, and other wireless technologies including future 6G technologies.

(40) FIG. 2A is a diagram **200** illustrating an example of a first frame. FIG. 2B is a diagram **230** illustrating an example of DL channels within a subframe. FIG. 2C is a diagram **250** illustrating an example of a second frame. FIG. 2D is a diagram **280** illustrating an example of a subframe. The 5G NR frame structure may be FDD in which for a particular set of subcarriers (carrier system bandwidth), subframes within the set of subcarriers are dedicated for either DL or UL, or may be TDD in which for a particular set of subcarriers (carrier system bandwidth), subframes within the set of subcarriers are dedicated for both DL and UL. A subset of the total cell bandwidth of a cell is referred to as a Bandwidth Part (BWP) and bandwidth adaptation is achieved by configuring the UE with BWP(s) and telling the UE which of the configured BWPs is currently the active one.

(41) In the examples provided by FIGS. 2A, 2C, the 5G NR frame structure is assumed to be TDD, with subframe 4 being configured with slot format 28 (with mostly DL), where D is DL, U is UL, and X is flexible for use between DL/UL, and subframe 3 being configured with slot format 34 (with mostly UL). While subframes 3, 4 are shown with slot formats 34, 28, respectively, any particular subframe may be configured with any of the various available slot formats 0-61. Slot formats 0, 1 are all DL, UL, respectively. Other slot formats 2-61 include a mix of DL, UL, and flexible symbols. UEs are configured with the slot format (dynamically through DL control information (DCI), or semi-statically/statically through radio resource control (RRC) signaling) through a received slot format indicator (SFI). Note that the description infra applies also to a 5G NR frame structure that is TDD.

(42) Other wireless communication technologies may have a different frame structure or different channels. A frame (10 milliseconds (ms)) may be divided into 10 equally sized subframes (1 ms).

Each subframe may include one or more time slots. Subframes also may include mini-slots, which may include 7, 4, or 2 symbols. Each slot may include 7 or 14 symbols, depending on the slot configuration. For slot configuration 0, each slot may include 14 symbols, and for slot configuration 1, each slot may include 7 symbols. The symbols on DL may be cyclic prefix (CP) OFDM (CP-OFDM) symbols. The symbols on UL may be CP-OFDM symbols (for high throughput scenarios) or discrete Fourier transform (DFT) spread OFDM (DFT-s-OFDM) symbols (also referred to as single carrier frequency-division multiple access (SC-FDMA) symbols) (for power limited scenarios; limited to a single stream transmission). The number of slots within a subframe is based on the slot configuration and the numerology. For slot configuration 0, different numerologies μ 0 to 5 allow for 1, 2, 4, 8, 16, and 32 slots, respectively, per subframe. For slot configuration 1, different numerologies 0 to 2 allow for 2, 4, and 8 slots, respectively, per subframe. Accordingly, for slot configuration 0 and numerology μ , there are 14 symbols/slot and $2 \cdot \sup.\mu$ slots/subframe. The subcarrier spacing and symbol length/duration are a function of the numerology. The subcarrier spacing may be equal to $2 \cdot \sup.\mu \cdot 15$ kHz, where μ is the numerology 0 to 5. As such, the numerology $\mu=0$ has a subcarrier spacing of 15 kHz and the numerology $\mu=5$ has a subcarrier spacing of 480 kHz. The symbol length/duration is inversely related to the subcarrier spacing. FIGS. 2A-2D provide an example of slot configuration 0 with 14 symbols per slot and numerology $\mu=2$ with 4 slots per subframe. The slot duration is 0.25 ms, the subcarrier spacing is 60 kHz, and the symbol duration is approximately 16.67 microseconds (μ s).

(43) A resource grid may be used to represent the frame structure. Each time slot includes a resource block (RB) (also referred to as physical RBs (PRBs)) that extends 12 consecutive subcarriers. The resource grid is divided into multiple resource elements (REs). The number of bits carried by each RE depends on the modulation scheme.

(44) As illustrated in FIG. 2A, some of the REs carry reference (pilot) signals (RS) for the UE. The RS may include demodulation RS (DM-RS) (indicated as R.sub.x for one particular configuration, where 100x is the port number, but other DM-RS configurations are possible) and channel state information reference signals (CSI-RS) for channel estimation at the UE. The RS also may include beam measurement RS (BRS), beam refinement RS (BRRS), and phase tracking RS (PT-RS).

(45) FIG. 2B illustrates an example of various DL channels within a subframe of a frame. The physical downlink control channel (PDCCH) carries DCI within one or more control channel elements (CCEs), each CCE including nine RE groups (REGs), each REG including four consecutive REs in an OFDM symbol. A primary synchronization signal (PSS) may be within symbol 2 of particular subframes of a frame. The PSS is used by a UE 104 to determine subframe/symbol timing and a physical layer identity. A secondary synchronization signal (SSS) may be within symbol 4 of particular subframes of a frame. The SSS is used by a UE to determine a physical layer cell identity group number and radio frame timing. Based on the physical layer identity and the physical layer cell identity group number, the UE can determine a physical cell identifier (PCI). Based on the PCI, the UE can determine the locations of the aforementioned DM-RS. The physical broadcast channel (PBCH), which carries a master information block (MIB), may be logically grouped with the PSS and SSS to form a synchronization signal (SS)/PBCH block (SSB). The MIB provides a number of RBs in the system bandwidth and a system frame number (SFN). The physical downlink shared channel (PDSCH) carries user data, broadcast system information not transmitted through the PBCH such as system information blocks (SIBs), and paging messages.

(46) As illustrated in FIG. 2C, some of the REs carry DM-RS (indicated as R for one particular configuration, but other DM-RS configurations are possible) for channel estimation at the base station. The UE may transmit DM-RS for the physical uplink control channel (PUCCH) and DM-RS for the physical uplink shared channel (PUSCH). The PUSCH DM-RS may be transmitted in the first one or two symbols of the PUSCH. The PUCCH DM-RS may be transmitted in different configurations depending on whether short or long PUCCHs are transmitted and depending on the

particular PUCCH format used.

(47) The UE may transmit sounding reference signals (SRS). An SRS resource set configuration may define resources for SRS transmission. For example, as illustrated, an SRS configuration may specify that SRS may be transmitted in the last symbol of a subframe. The SRS may have a comb structure, and a UE may transmit SRS on one comb for each SRS port. The SRS may be used by a base station for channel quality estimation to enable frequency-dependent scheduling on the UL. The SRS may also be used for channel estimation to select a precoder for downlink MIMO.

(48) FIG. 2D illustrates an example of various UL channels within a subframe of a frame. The PUCCH may be located as indicated in one configuration. The PUCCH carries uplink control information (UCI), such as scheduling requests, a channel quality indicator (CQI), a precoding matrix indicator (PMI), a rank indicator (RI), and HARQ ACK/NACK feedback. The PUSCH carries data, and may additionally be used to carry a buffer status report (BSR), a power headroom report (PHR), or UCI.

(49) FIG. 3 is a diagram of an example of a base station **310** and a UE **350** in an access network. The UE **350** may be an example of a receiving device. In the DL, IP packets from the EPC **160** may be provided to a controller/processor **375**. The controller/processor **375** implements layer 3 and layer 2 functionality. Layer 3 includes a radio resource control (RRC) layer, and layer 2 includes a service data adaptation protocol (SDAP) layer, a packet data convergence protocol (PDCP) layer, a radio link control (RLC) layer, and a medium access control (MAC) layer. The controller/processor **375** provides RRC layer functionality associated with broadcasting of system information (such as MIB, SIBs), RRC connection control (such as RRC connection paging, RRC connection establishment, RRC connection modification, and RRC connection release), inter radio access technology (RAT) mobility, and measurement configuration for UE measurement reporting; PDCP layer functionality associated with header compression/decompression, security (ciphering, deciphering, integrity protection, integrity verification), and handover support functions; RLC layer functionality associated with the transfer of upper layer packet data units (PDUs), error correction through ARQ, concatenation, segmentation, and reassembly of RLC service data units (SDUs), re-segmentation of RLC data PDUs, and reordering of RLC data PDUs; and MAC layer functionality associated with mapping between logical channels and transport channels, multiplexing of MAC SDUs onto transport blocks (TBs), demultiplexing of MAC SDUs from TBs, scheduling information reporting, error correction through HARQ, priority handling, and logical channel prioritization.

(50) The transmit (Tx) processor **316** and the receive (Rx) processor **370** implement layer 1 functionality associated with various signal processing functions. Layer 1, which includes a physical (PHY) layer, may include error detection on the transport channels, forward error correction (FEC) coding/decoding of the transport channels, interleaving, rate matching, mapping onto physical channels, modulation/demodulation of physical channels, and MIMO antenna processing. The Tx processor **316** handles mapping to signal constellations based on various modulation schemes (such as binary phase-shift keying (BPSK), quadrature phase-shift keying (QPSK), M-phase-shift keying (M-PSK), M-quadrature amplitude modulation (M-QAM)). The coded and modulated symbols may be split into parallel streams. Each stream may be mapped to an OFDM subcarrier, multiplexed with a reference signal (such as a pilot) in the time or frequency domain, and combined together using an Inverse Fast Fourier Transform (IFFT) to produce a physical channel carrying a time domain OFDM symbol stream. The OFDM stream is spatially precoded to produce multiple spatial streams. Channel estimates from a channel estimator **374** may be used to determine the coding and modulation scheme, as well as for spatial processing. The channel estimate may be derived from a reference signal or channel condition feedback transmitted by the UE **350**. Each spatial stream may be provided to a different antenna **320** via a separate transmitter **318Tx**. Each transmitter **318Tx** may modulate an RF carrier with a respective spatial stream for transmission.

(51) At the UE **350**, each receiver **354Rx** receives a signal through its respective antenna **352**. Each receiver **354Rx** recovers information modulated onto an RF carrier and provides the information to the receive (Rx) processor **356**. The Tx processor **368** and the Rx processor **356** implement layer 1 functionality associated with various signal processing functions. The Rx processor **356** may perform spatial processing on the information to recover any spatial streams destined for the UE **350**. If multiple spatial streams are destined for the UE **350**, they may be combined by the Rx processor **356** into a single OFDM symbol stream. The Rx processor **356** converts the OFDM symbol stream from the time-domain to the frequency domain using a Fast Fourier Transform (FFT). The frequency domain signal includes a separate OFDM symbol stream for each subcarrier of the OFDM signal. The symbols on each subcarrier, and the reference signal, are recovered and demodulated by determining the most likely signal constellation points transmitted by the base station **310**. These soft decisions may be based on channel estimates computed by the channel estimator **358**. The soft decisions are decoded and deinterleaved to recover the data and control signals that were originally transmitted by the base station **310** on the physical channel. The data and control signals are provided to the controller/processor **359**, which implements layer 3 and layer 2 functionality.

(52) The controller/processor **359** can be associated with a memory **360** that stores program codes and data. The memory **360** may be referred to as a computer-readable medium. In the UL, the controller/processor **359** provides demultiplexing between transport and logical channels, packet reassembly, deciphering, header decompression, and control signal processing to recover IP packets from the EPC **160**. The controller/processor **359** is also responsible for error detection using an ACK or NACK protocol to support HARQ operations.

(53) Similar to the functionality described in connection with the DL transmission by the base station **310**, the controller/processor **359** provides RRC layer functionality associated with system information (such as MIB, SIBs) acquisition, RRC connections, and measurement reporting; PDCP layer functionality associated with header compression/decompression, and security (ciphering, deciphering, integrity protection, integrity verification); RLC layer functionality associated with the transfer of upper layer PDUs, error correction through ARQ, concatenation, segmentation, and reassembly of RLC SDUs, re-segmentation of RLC data PDUs, and reordering of RLC data PDUs; and MAC layer functionality associated with mapping between logical channels and transport channels, multiplexing of MAC SDUs onto TBs, demultiplexing of MAC SDUs from TBs, scheduling information reporting, error correction through HARQ, priority handling, and logical channel prioritization.

(54) Channel estimates derived by a channel estimator **358** from a reference signal or feedback transmitted by the base station **310** may be used by the Tx processor **368** to select the appropriate coding and modulation schemes, and to facilitate spatial processing. The spatial streams generated by the Tx processor **368** may be provided to different antenna **352** via separate transmitters **354Tx**. Each transmitter **354Tx** may modulate an RF carrier with a respective spatial stream for transmission.

(55) The UL transmission is processed at the base station **310** in a manner similar to that described in connection with the receiver function at the UE **350**. Each receiver **318Rx** receives a signal through its respective antenna **320**. Each receiver **318Rx** recovers information modulated onto an RF carrier and provides the information to a Rx processor **370**.

(56) The controller/processor **375** can be associated with a memory **376** that stores program codes and data. The memory **376** may be referred to as a computer-readable medium. In the UL, the controller/processor **375** provides demultiplexing between transport and logical channels, packet reassembly, deciphering, header decompression, control signal processing to recover IP packets from the UE **350**. IP packets from the controller/processor **375** may be provided to the EPC **160**. The controller/processor **375** is also responsible for error detection using an ACK or NACK protocol to support HARQ operations.

(57) At least one of the Tx processor **368**, the Rx processor **356**, and the controller/processor **359** may be configured to perform aspects in connection with the beam management component **140** of FIG. **1**. For example, the memory **360** may include executable instructions defining the beam management component **140**. The Tx processor **368**, the Rx processor **356**, and/or the controller/processor **359** may be configured to execute the beam management component **140**.

(58) At least one of the Tx processor **316**, the Rx processor **370**, and the controller/processor **375** may be configured to perform aspects in connection with the prediction control component **120** of FIG. **1**. For example, the memory **376** may include executable instructions defining the prediction control component **120**. The Tx processor **316**, the Rx processor **370**, and/or the controller/processor **375** may be configured to execute the prediction control component **120**.

(59) FIG. **4** shows a diagram illustrating an example disaggregated base station **400** architecture. The disaggregated base station **400** architecture may include one or more central units (CUs) **410** that can communicate directly with a core network **420** via a backhaul link, or indirectly with the core network **420** through one or more disaggregated base station units (such as a Near-Real Time (Near-RT) RAN Intelligent Controller (MC) **425** via an E2 link, or a Non-Real Time (Non-RT) RIC **415** associated with a Service Management and Orchestration (SMO) Framework **405**, or both). A CU **410** may communicate with one or more distributed units (DUs) **430** via respective midhaul links, such as an F1 interface. The DUs **430** may communicate with one or more radio units (RUs) **440** via respective fronthaul links. The RUs **440** may communicate with respective UEs **104** via one or more radio frequency (RF) access links. In some implementations, the UE **104** may be simultaneously served by multiple RUs **440**.

(60) Each of the units, i.e., the CUs **410**, the DUs **430**, the RUs **440**, as well as the Near-RT RICs **425**, the Non-RT RICs **415** and the SMO Framework **405**, may include one or more interfaces or be coupled to one or more interfaces configured to receive or transmit signals, data, or information (collectively, signals) via a wired or wireless transmission medium. Each of the units, or an associated processor or controller providing instructions to the communication interfaces of the units, can be configured to communicate with one or more of the other units via the transmission medium. For example, the units can include a wired interface configured to receive or transmit signals over a wired transmission medium to one or more of the other units. Additionally, the units can include a wireless interface, which may include a receiver, a transmitter or transceiver (such as a radio frequency (RF) transceiver), configured to receive or transmit signals, or both, over a wireless transmission medium to one or more of the other units.

(61) In some aspects, the CU **410** may host one or more higher layer control functions. Such control functions can include radio resource control (RRC), packet data convergence protocol (PDCP), service data adaptation protocol (SDAP), or the like. Each control function can be implemented with an interface configured to communicate signals with other control functions hosted by the CU **410**. The CU **410** may be configured to handle user plane functionality (i.e., Central Unit-User Plane (CU-UP)), control plane functionality (i.e., Central Unit-Control Plane (CU-CP)), or a combination thereof. In some implementations, the CU **410** can be logically split into one or more CU-UP units and one or more CU-CP units. The CU-UP unit can communicate bidirectionally with the CU-CP unit via an interface, such as the E1 interface when implemented in an O-RAN configuration. The CU **410** can be implemented to communicate with the DU **430**, as necessary, for network control and signaling.

(62) The DU **430** may correspond to a logical unit that includes one or more base station functions to control the operation of one or more RUs **440**. In some aspects, the DU **430** may host one or more of a radio link control (RLC) layer, a medium access control (MAC) layer, and one or more high physical (PHY) layers (such as modules for forward error correction (FEC) encoding and decoding, scrambling, modulation and demodulation, or the like) depending, at least in part, on a functional split, such as those defined by the 3GPP Generation Partnership Project (3GPP). In some aspects, the DU **430** may further host one or more low PHY layers. Each layer (or module)

can be implemented with an interface configured to communicate signals with other layers (and modules) hosted by the DU **430**, or with the control functions hosted by the CU **410**.

(63) Lower-layer functionality can be implemented by one or more RUs **440**. In some deployments, an RU **440**, controlled by a DU **430**, may correspond to a logical node that hosts RF processing functions, or low-PHY layer functions (such as performing fast Fourier transform (FFT), inverse FFT (iFFT), digital beamforming, physical random access channel (PRACH) extraction and filtering, or the like), or both, based at least in part on the functional split, such as a lower layer functional split. In such an architecture, the RU(s) **440** can be implemented to handle over the air (OTA) communication with one or more UEs **104**. In some implementations, real-time and non-real-time aspects of control and user plane communication with the RU(s) **440** can be controlled by the corresponding DU **430**. In some scenarios, this configuration can enable the DU(s) **430** and the CU **410** to be implemented in a cloud-based RAN architecture, such as a vRAN architecture.

(64) The SMO Framework **405** may be configured to support RAN deployment and provisioning of non-virtualized and virtualized network elements. For non-virtualized network elements, the SMO Framework **405** may be configured to support the deployment of dedicated physical resources for RAN coverage requirements which may be managed via an operations and maintenance interface (such as an O1 interface). For virtualized network elements, the SMO Framework **405** may be configured to interact with a cloud computing platform (such as an open cloud (O-Cloud) **490**) to perform network element life cycle management (such as to instantiate virtualized network elements) via a cloud computing platform interface (such as an O2 interface). Such virtualized network elements can include, but are not limited to, CUs **410**, DUs **430**, RUs **440** and Near-RT RICs **425**. In some implementations, the SMO Framework **405** can communicate with a hardware aspect of a 4G RAN, such as an open eNB (O-eNB) **411**, via an O1 interface. Additionally, in some implementations, the SMO Framework **405** can communicate directly with one or more RUs **440** via an O1 interface. The SMO Framework **405** also may include a Non-RT RIC **415** configured to support functionality of the SMO Framework **405**.

(65) The Non-RT RIC **415** may be configured to include a logical function that enables non-real-time control and optimization of RAN elements and resources, Artificial Intelligence/Machine Learning (AI/ML) workflows including model training and updates, or policy-based guidance of applications/features in the Near-RT RIC **425**. The Non-RT RIC **415** may be coupled to or communicate with (such as via an A1 interface) the Near-RT RIC **425**. The Near-RT RIC **425** may be configured to include a logical function that enables near-real-time control and optimization of RAN elements and resources via data collection and actions over an interface (such as via an E2 interface) connecting one or more CUs **410**, one or more DUs **430**, or both, as well as an O-eNB, with the Near-RT RIC **425**.

(66) In some implementations, to generate AI/ML models to be deployed in the Near-RT RIC **425**, the Non-RT RIC **415** may receive parameters or external enrichment information from external servers. Such information may be utilized by the Near-RT RIC **425** and may be received at the SMO Framework **405** or the Non-RT RIC **415** from non-network data sources or from network functions. In some examples, the Non-RT RIC **415** or the Near-RT RIC **425** may be configured to tune RAN behavior or performance. For example, the Non-RT RIC **415** may monitor long-term trends and patterns for performance and employ AI/ML models to perform corrective actions through the SMO Framework **405** (such as reconfiguration via O1) or via creation of RAN management policies (such as A1 policies).

(67) FIG. 5 is a diagram **500** illustrating an example of a beam failure detection procedure. A UE **104** may be configured with a periodic BFD-RS **510**. For example, the BFD-RS **510** may be a synchronization signal block (SSB) or a channel state information reference signal (CSI-RS) that is transmitted on an active beam for the UE. The BFD-RS **510** may have a periodicity that defines a period **512**. The UE **104** may measure the BFD-RS at the PHY layer. For example, the UE **104** may measure a signal to interference plus noise ratio (SINR) of the BFD-RS **510**. The UE **104** may

detect a beam failure instance at the PHY layer when the PHY measurement does not satisfy a threshold. The PHY layer may report a beam failure instance (BFI) to a MAC layer **530**.

(68) The MAC layer **530** may be configured with a BFD timer **520** and a BFI threshold **522**. The BFD timer **520** may define a time period for counting BFIs from the PHY layer. The BFI threshold **522** may define a number of BFIs when a beam failure is declared. The MAC layer **530** may maintain a BFI count **524** of BFIs received from the PHY layer during the BFD timer **520**. If the MAC layer **530** receives a BFI from the PHY layer, the MAC layer **530** may increment the BFI count **524**. The MAC layer **530** may measure the BFD timer **520** starting when the MAC layer **530** increments the BFI count from 0 to 1. If a BFD-RS is received where the PHY layer measurement satisfies the threshold, the PHY layer may not report a BFI and the BFI count **524** may remain unchanged. If the BFI count **524** satisfies the BFI threshold **522** during the BFD timer **520**, the UE **104** may initiate a beam failure recovery (BFR) procedure **540**. For example, as illustrated, the BFI threshold **522** may be set to 4, and the UE **104** may initiate the BFR procedure **540** when the BFI count **524** reaches a value of 4. Initiating the BFR procedure **540** may include transmitting a random access preamble on a physical random access channel (PRACH) based on a candidate beam.

(69) FIG. **6** is a diagram **600** illustrating an example of a beam failure detection procedure with prediction. The UE **104** may be configured with the BFD-RS **410** having the period **512**, the BFD timer **520**, and BFI threshold **522**. Similar to FIG. **5**, the MAC layer **530** may receive beam failure indications from the PHY layer and track the BFI count **524** during the BFD timer **520**. The UE **104** may generate a prediction **610** that a beam failure is likely to occur. For example, the prediction **610** may be based on another sensor and/or a machine-learning model trained at the UE **104**. In some implementations, the prediction may be based on a condition indicated by the base station **102**. For example, the prediction **610** may be when the BFI count **524** exceeds a defined percentage of the threshold **522** or when a consecutive number of BFI counts are reported. The prediction **610** may occur before the BFI count **524** reaches the BFI threshold **522**.

(70) In response to the prediction **610**, the UE **104** may transmit an indicator **620** of the prediction **610** to the serving cell. The indicator **620** may indicate that a beam failure is likely to occur. In some implementations, the indicator **620** may further include a request for the serving cell to take an action. For example, the indicator **620** may include a request for the serving cell not to schedule the UE for a period of time, a request for the serving cell not to transmit the BFD-RS for a period of time, a request for the serving cell to change a periodicity of the BFD-RS, or a request for additional aperiodic BFD-RS. The UE **104** may transmit the indicator **620** as a MAC control element (MAC-CE) or as an element of uplink control information (UCI).

(71) The serving cell may respond to the indicator **620** with a notification **630** of a change to the BFD-RS **510** or to UE scheduling in response to the indicator. In some implementations, the notification **630** may increase an intensity of the BFD-RS **510**. That is, the BFD-RS **510** may be transmitted more frequently by changing a pattern or period of the BFD-RS **510**. For example, the notification **630** may reduce the period **512** of the BFD-RS **510**. For instance, the BFD-RS **510** may be transmitted at times **632** and/or **634**. The shorter period **512** may increase the number of occasions for measuring the BFD-RS. Accordingly, the PHY layer may generate more BFIs during the BFD timer **520**, and the MAC layer **530** may declare a beam failure earlier. For instance, the UE **104** may initiate the BFR procedure **640** earlier than the BFR procedure **540**. In some implementations, the notification **630** may schedule one or more aperiodic BFD-RS, which may similarly increase the number of occasions for measuring the BFD-RS such that the BFR procedure **640** may be declared earlier if the beam is failing.

(72) FIG. **7** is a message diagram **700** illustrating example messages between a base station **702** and a UE **704**. The UE **704** may be an example of a UE **104** including the beam management component **140**. The base station **702** may be an example of a base station **102** including the prediction control component **120**.

(73) In some implementations, the UE **704** may optionally transmit a capability message **710** to the base station **702**. For example, the capability message **710** may be a RRC message. The capability message **710** may indicate, for example, that the UE **704** is capable of predicting beam failure.

(74) In some implementations, the base station **702** may optionally transmit a configuration **715**. The configuration **715** may be a RRC message. For example, the configuration **715** may include a configuration of a triggering condition to predict the beam failure or a configuration of the indicator **620**. For instance, the configuration may specify one or more conditions for predicting a beam failure such as a sensor or a machine-learning model. The configuration of the indicator **620** may indicate, for example, a length of a field in a UCI or MAC-CE or a mapping of field values to requests.

(75) In some implementations, the UE **704** may optionally transmit an activation request **720** for BFD prediction. The activation request **720** may be, for example, a MAC-CE or UCI. The UE **704** may request activation of BFD prediction based on UE discontinuous reception (DRX) configuration such as a length of a DRX cycle, on duration, or off duration, or based on a power or capacity restraint of the UE **704**. The base station **702** may optionally respond to the activation request **720** with an activation command **725**. The activation command **725** may be a MAC-CE or DCI. The base station **702** may also autonomously issue the activation command **725**. For example, the base station **702** may grant the activation request **720** or issue the activation command **725** based on a quality of service (QoS) requirement of serving traffic, the UE DRX configuration, and/or scheduling considerations. When BFD prediction is activated for the UE **704**, the UE **704** may transmit the indicator **620**. If BFD prediction is deactivated for the UE **704**, the UE **704** may not predict a BFD prior to the BFI count **524** reaching the threshold **522** and may not transmit the indicator **620**.

(76) The base station **702** may periodically transmit the BFD-RS **510** as discussed above regarding FIG. 5 and FIG. 6. The UE **704** may generate the beam failure prediction **610**. The beam failure prediction **610** may be based on prediction techniques configured by the configuration **715**. For example, the prediction may be based on a machine-learning model applied to the BFD-RS **510** or other signals received at the UE **704**. In some implementations, the machine-learning model may be trained specifically for the UE, for example, based on a state of the UE **704** when previous beam failure detections occurred. As another example, a sensor at the UE **704** may detect blockage. For instance, a camera may detect an object moving in the direction of the beam, or a radar or capacitance sensor may detect an object in close proximity to an antenna. In some implementations, the beam failure prediction **610** may include predicting a duration of the beam failure condition. For instance, the camera may sense a size of the object or a rate of movement to predict a duration of the beam failure condition.

(77) The UE **704** may transmit the indicator **620** in response to the beam failure prediction **610**. In some implementations, the indicator **620** may simply indicate the prediction **610**. For instance, the indicator **620** may be a single bit flag in UCI or a MAC-CE. In other implementations, the indicator **620** may include a request **730**. For example, the request **730** may be a request for no scheduling **731** of the UE **704** for a period of time **735**. As another example, the request **730** may be a request for no BFD-RS **732** to be transmitted by the serving cell for a period of time **735**. As another example, the request **730** may be a request to change the periodicity **733** of the BFD-RS **732**. For instance, the request to change the periodicity **733** may decrease the period **512** of the BFD-RS **732**. As another example, the request **730** may be a request for additional aperiodic BFD-RS **734**, either a number of additional transmissions or additional transmissions during a period of time **735**. For example, the request for additional aperiodic BFD-RS **734** may be a request for the base station **702** to schedule additional periodic BFD-RS transmissions during the next X milliseconds. For any of the requests **730**, the period of time **735** may be fixed, or the indicator **620** may identify the period of time **735**.

(78) In response to the indicator **620**, the base station **702** may transmit the notification **630** to

notify the UE **704** of a change to the BFD-RS **510** or to UE scheduling. For instance, the notification **630** may indicate that BFD-RS **510** will not be transmitted for a period of time **735** or that the period **512** of the BFD-RS will change. As another example, the notification **630** may schedule one or more aperiodic BFD-RS **745**. As another example, the notification **630** may indicate that the UE **704** will not be scheduled to receive a downlink transmission for the period of time **735**. In some cases, the UE **704** may enter a sleep mode during the period of time **735**, for example, to conserve power.

(79) As discussed above regarding FIG. **6**, the UE **704** may continue to monitor the BFD-RS **510** and any aperiodic BFD-RS **735**. If the BFI count **524** reaches the BFI threshold **522**, the UE **704** may initiate the BFR procedure **640**. For example, the UE **704** may transmit a beam failure recovery request **750** and receive a beam failure recovery response **755**. In this case, the prediction **610** may be considered correct. If the BFI count **524** does not reach the BFI threshold **522** during the BFD timer **520**, the UE **704** may reset the BFD timer **520** and continue to monitor the BFD-RS. In some implementations, the decision of whether to initiate the BFR procedure **640** may be logged as training data for training a machine-learning model to improve prediction of beam failure.

(80) In some implementations, the UE **704** may transmit a deactivation request **760** for BFD prediction. The deactivation request **760** may be based on similar factors to the activation request **720**. The base station **702** may transmit a deactivation command **765** in response to the deactivation request **760** or autonomously based on similar factors.

(81) FIG. **8** is a conceptual data flow diagram **800** illustrating the data flow between different means/components in an example base station **802**, which may be an example of the base station **102** including the prediction control component **120**. The prediction control component **120** may be implemented by the memory **376** and the Tx processor **316**, the Rx processor **370**, and/or the controller/processor **375** of FIG. **3**. For example, the memory **376** may store executable instructions defining the prediction control component **120** and the Tx processor **316**, the Rx processor **370**, and/or the controller/processor **375** may execute the instructions.

(82) The base station **802** may include a receiver component **850**, which may include, for example, a radio frequency (RF) receiver for receiving the signals described herein. The base station **802** may include a transmitter component **852**, which may include, for example, an RF transmitter for transmitting the signals described herein. In an aspect, the receiver component **850** and the transmitter component **852** may co-located in a transceiver such as illustrated by the Tx/Rx **318** in FIG. **3**.

(83) As discussed with respect to FIG. **1**, the prediction control component **120** may include the indicator Rx component **122** and the notification Tx component **124**. In some implementations, the prediction control component **120** may optionally include a configuration component **810**, an activation component **820**, a RS component **830**, and/or a scheduler **840**.

(84) The receiver component **850** may receive UL signals from the UE **704** including the capability message **710**, the activation request **720**, the indicator **620**, the beam failure recovery message, or the deactivation request **760**. The receiver component **850** may provide the capability message **710** to the configuration component **810**. The receiver component **850** may provide the activation request **720** or the deactivation request **760** to the activation component **820**. The receiver component **850** may provide the indicator **620** to the indicator Rx component **122**. The receiver component **850** may provide the beam failure recovery message to the scheduler **840**.

(85) The indicator Rx component **122** may be configured to receive the indicator **620** of a predicted beam failure at a UE via the receiver component **850**. The indicator Rx component **122** may identify the BFD-RS corresponding to the indicator **620**. The indicator Rx component **122** may determine whether the indicator **620** includes a request **730**, and the period of time **735** for any request. The indicator Rx component **122** may provide the BFD-RS, request **730**, and/or period of time **735** to the notification Tx component **124**.

(86) The notification Tx component **124** may be configured to transmit a notification of a change to

the BFD-RS to UE scheduling in response to the indicator **620**. The notification Tx component **124** may determine an appropriate change. In some implementations, where the indicator **620** includes a request **730**, the notification Tx component **124** may determine whether the request is feasible. For example, the notification Tx component **124** may determine whether additional resources are available for an aperiodic BFD-RS (e.g., by checking scheduler **840**). The notification Tx component **124** may transmit the notification via the transmitter component **852**, for example, as a MAC-CE or DCI. The notification Tx component **124** may provide the RS component **830** with any changes to the BFD-RS. The notification Tx component **124** may provide the scheduler **840** with any changes to UE scheduling.

(87) In some implementations, the configuration component **810** may configure the UE with a triggering condition to predict the beam failure or a configuration of the indicator **620**. For example, the triggering condition may indicate which prediction technique to use or a parameter of a condition such as a percentage of the threshold **522** or a number of consecutive BFIs. The configuration of the indicator **620** may define a length of the indicator or map field values to requests. The configuration component **810** may transmit the configuration via the transmitter component **852**.

(88) In some implementations, the activation component **820** may receive activation or deactivation requests and transmit activation or deactivation commands. The activation component **820** may receive the activation request **720** or the deactivation request **760** via the receiver component **850**. The activation component **820** may determine whether to activate or deactivate beam failure prediction based on one or more of: a QoS requirement of traffic for the UE, a DRX configuration of the UE, or a restraint on power or capacity of the UE. The activation component **820** may transmit the activation command **725** or the deactivation command **765** via the transmitter component **852**.

(89) In some implementations, the RS component **830** may be configured to generate and transmit the BFD-RS **510** and/or an aperiodic BFD-RS **745**. The RS component **830** may select the BFD-RS **510** based on a beam for the UE. The RS component **830** may receive changes to the BFD-RS **510** from the notification Tx component **124**. The RS component **830** may transmit the BFD-RS **510** and/or an aperiodic BFD-RS via the transmitter component **852**.

(90) In some implementations, the scheduler **840** may schedule the UE to receive downlink communications. In some implementations, the scheduler **840** may determine whether a request from the UE is feasible. The scheduler **840** may receive a change to the UE schedule from the notification Tx component **124**. For example, the scheduler **840** may receive a request not to schedule the UE for a time period, in which case, the scheduler **840** may cancel scheduled communications such as semi-persistent scheduling and refrain from dynamically scheduling the UE during the time period.

(91) FIG. **9** is a conceptual data flow diagram **900** illustrating the data flow between different means/components in an example UE **904**, which may be an example of the UE **704**, or the UE **104** and include the beam management component **140**. The beam management component **140** may be implemented by the memory **360** and the Tx processor **368**, the Rx processor **356**, and/or the controller/processor **359**. For example, the memory **360** may store executable instructions defining the beam management component **140** and the Tx processor **368**, the Rx processor **356**, and/or the controller/processor **359** may execute the instructions.

(92) The UE **904** may include a receiver component **970**, which may include, for example, a RF receiver for receiving the signals described herein. The UE **904** may include a transmitter component **972**, which may include, for example, an RF transmitter for transmitting the signals described herein. In an aspect, the receiver component **970** and the transmitter component **972** may co-located in a transceiver such as the Tx/Rx **352** in FIG. **3**.

(93) As discussed with respect to FIG. **1**, the beam management component **140** may include the BF prediction component **142**, the indicator component **144**, and the notification component **146**.

In some implementations, the beam management component **140** may optionally include the configuration component **148**, the activation component **149**, or a BFD component **910**.

(94) The receiver component **970** may receive DL signals described herein such as the configuration **715**, the activation command **725**, the notification **630**, the BFD-RS **510**, the aperiodic BFD-RS **745**, or the deactivation command **765**. The receiver component **970** may provide the configuration **715** to the configuration component **148**. The receiver component **970** may provide the activation command **725** and/or the deactivation command **765** to the activation component **149**. The receiver component **970** may provide the notification **630** to the notification component **146**. The receiver component **970** may provide the BFD-RS **510** and/or the aperiodic BFD-RS **745** to the BFD component **910**.

(95) In some implementations, the configuration component **148** may be configured to receive a configuration of a triggering condition to predict the beam failure or a configuration of the indicator **620** via the receiver component **970**. The configuration component **148** may configure the BF prediction component **142** with the triggering condition. The configuration component **148** may configure the indicator component **144** with a format of the indicator **620**.

(96) In some implementations, the activation component **149** may transmitting a request for activation (e.g., activation request **720**) or deactivation (e.g., deactivation request **760**) of beam failure prediction. For example, the request for activation may be based on a UE DRX configuration and/or a restraint on UE power or capacity. In some implementations, the activation component **149** may receive an activation (e.g., activation command **725**) or a deactivation (e.g., deactivation command **765**) of beam failure prediction. The activation component **149** may activate or deactivate the BF prediction component **142** based on the activation command **725** or the deactivation command **765**.

(97) The BF prediction component **142** may be configured to predict a beam failure prior to a number of beam failure instances (e.g., BFI count **524**) within a time period (BFD timer **520**) reaching a configured threshold number of beam failures (e.g., BFI threshold **522**). For example, the BF prediction component **142** may include a sensor **920**, ML model **930**, and/or condition **940** for predicting beam failure. The BF prediction component **142** may provide the prediction **610** to the indicator component **144**.

(98) The indicator component **144** may be configured to transmit an indicator of the predicted beam failure to a serving cell. For example, the indicator component **144** may transmit the indicator **620** via the transmitter component **972** as a MAC-CE or UCI. In some implementations the indicator component **144** may include the request **730** in the indicator **620**. The request **730** may be associated with a period of time **735**.

(99) The notification component **146** may be configured to receive a notification of a change to a BFD-RS or to UE scheduling in response to the indicator via the receiver component **970**. The notification component **146** may provide any changes to the BFD-RS to the BFD component **910**. For example, the notification component **146** may configure the BFD component **910** to receive the BFD-RS **510** with a different periodicity or configure the BFD component **910** to receive the aperiodic BFD-RS **745**. The notification component **146** may configure the receiver component **970** based on a change to UE scheduling. For example, the notification component **146** may put the receiver component **970** into a sleep mode if the notification indicates that the UE will not be scheduled during the period of time **735**.

(100) In some implementations, the BFD component **910** may be configured to declare a beam failure based on the BFI count **524** reaching the BFI threshold **522** within the BFD timer **520**. The BFD component **910** may count BFIs indicated by a PHY layer based on measurements of the BFD-RS **510** and/or the aperiodic BFD-RS **745**. The BFD component **910** may transmit the beam failure recovery request **750** via the transmitter component **972**. The BFD component **910** may receive a beam failure recovery response **755** via the receiver component **970**.

(101) FIG. **10** is a flowchart of an example method **1000** for a UE (e.g., UE **104**, UE **704**, or UE

904) to perform beam failure detection procedures using beam failure prediction. The method **1000** may be performed by a UE **904** (such as the UE **104**, which may include the memory **360** and which may be the entire UE **104** or a component of the UE **104** such as the beam management component **140**, Tx processor **368**, the Rx processor **356**, or the controller/processor **359**). The method **1000** may be performed by the beam management component **140** in communication with the prediction control component **120** of the base station **102**. Optional blocks are shown with dashed lines.

(102) At block **1010**, the method **1000** may optionally include receiving a configuration of a triggering condition to predict the beam failure or a configuration of the indicator. In some implementations, for example, the UE **104**, the Rx processor **356** or the controller/processor **359** may execute the beam management component **140** or the configuration component **148** to receive a configuration **715** of a triggering condition to predict the beam failure or a configuration **715** of the indicator. Accordingly, the UE **104**, the Rx processor **356**, or the controller/processor **359** executing the beam management component **140** or the configuration component **148** may provide means for receiving a configuration of a triggering condition to predict the beam failure or a configuration of the indicator.

(103) At block **1020**, the method **1000** may optionally include transmitting a request for activation or deactivation of beam failure prediction. In some implementations, for example, the UE **104**, the Tx processor **368** or the controller/processor **359** may execute the beam management component **140** or the activation component **149** to transmit the request for activation (e.g., activation request **720**) or deactivation (e.g., deactivation request **760**) of beam failure prediction. Accordingly, the UE **104**, the Tx processor **368**, or the controller/processor **359** executing the beam management component **140** or the activation component **149** may provide means for transmitting a request for activation or deactivation of beam failure prediction.

(104) At block **1030**, the method **1000** may include receiving an activation or a deactivation of beam failure prediction. In some implementations, for example, the UE **104**, the Rx processor **356** or the controller/processor **359** may execute the beam management component **140** or the activation component **149** to receive the activation (e.g., activation command **725**) or a deactivation (e.g., deactivation command **765**) of beam failure prediction. Accordingly, the UE **104**, the Rx processor **356**, or the controller/processor **359** executing the beam management component **140** or the activation component **149** may provide means for receiving an activation or a deactivation of beam failure prediction.

(105) At block **1040**, the method **1000** may include predicting a beam failure prior to a number of beam failure instances within a time period reaching a configured threshold number of beam failures. In some implementations, for example, the UE **104**, the Rx processor **356**, the Tx processor **368**, or the controller/processor **359** may execute the beam management component **140** or the BF prediction component **142** to predict the beam failure prior to a number of beam failure instances (e.g., BFI count **524**) within a time period (e.g., BFD timer **520**) reaching a configured threshold (e.g., BFI threshold **522**) number of beam failures. Accordingly, the UE **104**, the Rx processor **356**, the Tx processor **368**, or the controller/processor **359** executing the beam management component **140** or the BF prediction component **142** may provide means for predicting a beam failure prior to a number of beam failure instances within a time period reaching a configured threshold number of beam failures.

(106) At block **1050**, the method **1000** may include transmitting an indicator of the predicted beam failure condition to a serving cell. In some implementations, for example, the UE **104**, the Rx processor **356**, or the controller/processor **359** may execute the beam management component **140** or the indicator component **144** to transmit the indicator **620** of the predicted beam failure condition to the serving cell (e.g., of base station **702**). For example, at sub-block **1052**, the block **1050** may include transmitting the indicator **620** via a MAC-CE or UCI. In some implementations, the indicator includes a request for the serving cell not to schedule the UE for a period of time. The

indicator **620** may identify the period of time. In some implementations, the indicator **620** includes a request for the serving cell not to transmit the BFD-RS for a period of time. The period of time may be based on a predicted duration of the beam failure condition. In some implementations, the indicator includes a request for the serving cell to change a periodicity of the BFD-RS. In some implementations, the indicator includes a request for additional aperiodic BFD-RS. The request for additional aperiodic BFD-RS may include a period of validity for the additional aperiodic BFD-RS. Accordingly, the UE **104**, the Rx processor **356**, the Tx processor **368**, or the controller/processor **359** executing the beam management component **140** the indicator component **144** may provide means for transmitting an indicator of the predicted beam failure condition to a serving cell.

(107) At block **1060**, the method **1000** may include receiving a notification of a change to a BFD-RS or to UE scheduling in response to the indicator. In some implementations, for example, the UE **104**, the Rx processor **356**, or the controller/processor **359** may execute the beam management component **140** or notification component **146** to receive the notification **630** of a change to a BFD-RS or to UE scheduling in response to the indicator **620**. Accordingly, the UE **104**, the Tx processor **368**, or the controller/processor **359** executing the beam management component **140** or the notification component **146** may provide means for receiving a notification of a change to a BFD-RS or to UE scheduling in response to the indicator.

(108) FIG. **11** is a flowchart of an example method **1100** for a base station to control beam failure prediction at a UE. The method **1100** may be performed by a base station (such as the base station **102**, which may include the memory **376** and which may be the entire base station **102** or a component of the base station **102** such as the prediction control component **120**, the Tx processor **316**, the Rx processor **370**, or the controller/processor **375**). The method **1100** may be performed by the prediction control component **120** in communication with the beam management component **140** of the UE **104**.

(109) At block **1110**, the method **1100** may optionally include transmitting a configuration of a triggering condition to predict the beam failure condition or a configuration of the indicator. In some implementations, for example, the base station **102**, the Tx processor **316**, or the controller/processor **375** may execute the prediction control component **120** or the configuration component **810** to transmit the configuration **715** of a triggering condition to predict the beam failure condition or a configuration **715** of the indicator **620**. Accordingly, the base station **102**, the Tx processor **316**, or the controller/processor **375** executing the prediction control component **120** or the configuration component **810** may provide means for transmitting a configuration of a triggering condition to predict the beam failure condition or a configuration of the indicator.

(110) At block **1120**, the method **1100** may optionally include receiving a request for activation or deactivation of beam failure prediction. In some implementations, for example, the base station **102**, the Tx processor **316**, or the controller/processor **375** may execute the prediction control component **120** or the activation component **820** to receive a request for activation (e.g., activation request **720**) or deactivation (e.g., deactivation request **760**) of beam failure prediction.

Accordingly, the base station **102**, the Tx processor **316**, or the controller/processor **375** executing the prediction control component **120** or the activation component **820** may provide means receiving a request for activation or deactivation of beam failure prediction.

(111) At block **1130**, the method **1100** may include transmitting an activation or a deactivation of beam failure prediction. In some implementations, for example, base station **102**, the Tx processor **316**, or the controller/processor **375** may execute the prediction control component **120** or the activation component **820** to transmit an activation (e.g., activation command **725**) or a deactivation (e.g., deactivation command **765**) of beam failure prediction. Accordingly, the base station **102**, the Tx processor **316**, or the controller/processor **375** executing the prediction control component **120** or the activation component **820** may provide means for transmitting an activation or a deactivation of beam failure prediction.

(112) At block **1140**, the method **1100** may include receiving an indicator of the predicted beam

failure at a UE. In some implementations, for example, the base station **102**, the Rx processor **370**, or the controller/processor **375** may execute the prediction control component **120** or the indicator Rx component **122** to receive an indicator **620** of the predicted beam failure at the UE. For example, at sub-block **1142**, the block **1040** may include receiving the indicator **620** via a MAC-CE or UCI. In some implementations, the indicator **620** includes a request for the serving cell not to schedule the UE for a period of time. The indicator **620** may identify the period of time. In some implementations, the indicator **620** includes a request for the serving cell not to transmit the BFD-RS for a period of time. The period of time may be based on a predicted duration of the beam failure. In some implementations, the indicator includes a request for the serving cell to change a periodicity of the BFD-RS. In some implementations, the indicator includes a request for additional aperiodic BFD-RS. The request for additional aperiodic BFD-RS may include a period of validity for the additional aperiodic BFD-RS. Accordingly, the base station **102**, the Rx processor **370**, or the controller/processor **375** executing the prediction control component **120** or the indicator Rx component **122** may provide means for receiving an indicator of the predicted beam failure at a UE.

(113) At block **1150**, the method **1100** may include transmitting a notification of a change to a BFD-RS or to UE scheduling in response to the indicator. In some implementations, for example, base station **102**, the Tx processor **316**, or the controller/processor **375** may execute the prediction control component **120** or the notification Tx component **124** to transmit a notification **630** of a change to a BFD-RS or to UE scheduling in response to the indicator **620**. Accordingly, the base station **102**, the Tx processor **316**, or the controller/processor **375** executing the prediction control component **120** or the notification Tx component **124** may provide means for transmitting a notification of a change to a BFD-RS or to UE scheduling in response to the indicator.

(114) The various illustrative logics, logical blocks, modules, circuits and algorithm processes described in connection with the implementations disclosed herein may be implemented as electronic hardware, computer software, or combinations of both. The interchangeability of hardware and software has been described generally, in terms of functionality, and illustrated in the various illustrative components, blocks, modules, circuits and processes described above. Whether such functionality is implemented in hardware or software depends upon the particular application and design constraints imposed on the overall system.

(115) The hardware and data processing apparatus used to implement the various illustrative logics, logical blocks, modules and circuits described in connection with the aspects disclosed herein may be implemented or performed with a general purpose single- or multi-chip processor, a digital signal processor (DSP), an application specific integrated circuit (ASIC), a field programmable gate array (FPGA) or other programmable logic device, discrete gate or transistor logic, discrete hardware components, or any combination thereof designed to perform the functions described herein. A general purpose processor may be a microprocessor, or any conventional processor, controller, microcontroller, or state machine. A processor also may be implemented as a combination of computing devices, such as a combination of a DSP and a microprocessor, a plurality of microprocessors, one or more microprocessors in conjunction with a DSP core, or any other such configuration. In some implementations, particular processes and methods may be performed by circuitry that is specific to a given function.

(116) In one or more aspects, the functions described may be implemented in hardware, digital electronic circuitry, computer software, firmware, including the structures disclosed in this specification and their structural equivalents thereof, or in any combination thereof.

Implementations of the subject matter described in this specification also can be implemented as one or more computer programs, i.e., one or more modules of computer program instructions, encoded on a computer storage media for execution by, or to control the operation of, data processing apparatus.

(117) If implemented in software, the functions may be stored on or transmitted over as one or

more instructions or code on a computer-readable medium. The processes of a method or algorithm disclosed herein may be implemented in a processor-executable software module which may reside on a computer-readable medium. Computer-readable media includes both computer storage media and communication media including any medium that can be enabled to transfer a computer program from one place to another. A storage media may be any available media that may be accessed by a computer. By way of example, and not limitation, such computer-readable media may include RAM, ROM, EEPROM, CD-ROM or other optical disk storage, magnetic disk storage or other magnetic storage devices, or any other medium that may be used to store desired program code in the form of instructions or data structures and that may be accessed by a computer. Also, any connection can be properly termed a computer-readable medium. Disk and disc, as used herein, includes compact disc (CD), laser disc, optical disc, digital versatile disc (DVD), floppy disk, and Blu-ray disc where disks usually reproduce data magnetically, while discs reproduce data optically with lasers. Combinations of the above should also be included within the scope of computer-readable media. Additionally, the operations of a method or algorithm may reside as one or any combination or set of codes and instructions on a machine readable medium and computer-readable medium, which may be incorporated into a computer program product.

(118) Various modifications to the implementations described in this disclosure may be readily apparent to those skilled in the art, and the generic principles defined herein may be applied to other implementations without departing from the spirit or scope of this disclosure. Thus, the claims are not intended to be limited to the implementations shown herein, but are to be accorded the widest scope consistent with this disclosure, the principles and the novel features disclosed herein.

(119) Additionally, a person having ordinary skill in the art will readily appreciate, the terms “upper” and “lower” are sometimes used for ease of describing the figures, and indicate relative positions corresponding to the orientation of the figure on a properly oriented page, and may not reflect the proper orientation of any device as implemented.

(120) Certain features that are described in this specification in the context of separate implementations also can be implemented in combination in a single implementation. Conversely, various features that are described in the context of a single implementation also can be implemented in multiple implementations separately or in any suitable subcombination. Moreover, although features may be described above as acting in certain combinations and even initially claimed as such, one or more features from a claimed combination can in some cases be excised from the combination, and the claimed combination may be directed to a subcombination or variation of a subcombination.

(121) Similarly, while operations are depicted in the drawings in a particular order, this should not be understood as requiring that such operations be performed in the particular order shown or in sequential order, or that all illustrated operations be performed, to achieve desirable results. Further, the drawings may schematically depict one more example processes in the form of a flow diagram. However, other operations that are not depicted can be incorporated in the example processes that are schematically illustrated. For example, one or more additional operations can be performed before, after, simultaneously, or between any of the illustrated operations. In certain circumstances, multitasking and parallel processing may be advantageous. Moreover, the separation of various system components in the implementations described above should not be understood as requiring such separation in all implementations, and it should be understood that the described program components and systems can generally be integrated together in a single software product or packaged into multiple software products. Additionally, other implementations are within the scope of the following claims. In some cases, the actions recited in the claims can be performed in a different order and still achieve desirable results.

(122) The following numbered clauses provide an overview of aspects of the present disclosure: 1. A method of wireless communication for a user equipment (UE), comprising: predicting a beam

failure condition prior to a number of beam failure instances within a time period reaching a configured threshold number of beam failures; transmitting an indicator of the predicted beam failure condition to a serving cell; and receiving a notification of a change to a beam failure detection reference signal (BFD-RS) or to UE scheduling in response to the indicator. 2. The method of clause 1, wherein the indicator includes a request for the serving cell not to schedule the UE for a period of time. 3. The method of clause 2, wherein the indicator identifies the period of time. 4. The method of any of clauses 1-3, wherein the indicator includes a request for the serving cell not to transmit the BFD-RS for a period of time. 5. The method of clause 4, wherein the period of time is based on a predicted duration of the beam failure. 6. The method of any of clauses 1-3, wherein the indicator includes a request for the serving cell to change a periodicity of the BFD-RS. 7. The method of any of clauses 1-3, wherein the indicator includes a request for additional aperiodic BFD-RS. 8. The method of clause 7, wherein the request for additional aperiodic BFD-RS includes a period of validity for the additional aperiodic BFD-RS. 9. The method of any of clauses 1-8, wherein transmitting the indicator comprises transmitting the indicator via a media access control (MAC) control element (CE) or uplink control information (UCI). 10. The method of any of clauses 1-9, further comprising receiving a configuration of a triggering condition to predict the beam failure or a configuration of the indicator. 11. The method of any of clauses 1-10, further comprising receiving an activation or a deactivation of beam failure prediction. 12. The method of clause 11, further comprising transmitting a request for activation or deactivation of beam failure prediction. 13. A method of wireless communication at a serving cell, comprising: receiving an indicator of a predicted beam failure at a UE; and transmitting a notification of a change to a beam failure detection reference signal (BFD-RS) or to UE scheduling in response to the indicator. 14. The method of clause 13, wherein the indicator includes a request for the serving cell not to schedule the UE for a period of time. 15. The method of clause 14, wherein the indicator identifies the period of time. 16. The method of any of clauses 13-15, wherein the indicator includes a request for the serving cell not to transmit the BFD-RS for a period of time. 17. The method of any of clauses 13-15, wherein the indicator includes a request for the serving cell to change a periodicity of the BFD-RS. 18. The method of any of clauses 13-15, wherein the indicator includes a request for additional aperiodic BFD-RS. 19. The method of clause 18, wherein the notification includes a period of validity for the additional aperiodic BFD-RS. 20. The method of any of clauses 13-19, wherein receiving the indicator comprises receiving the indicator via a media access control (MAC) control element (CE) or uplink control information (UCI). 21. The method of any of clauses 13-20, further comprising transmitting a configuration of a triggering condition to predict the beam failure or a configuration of the indicator. 22. The method of any of clauses 13-21, further comprising transmitting an activation of beam failure prediction. 23. The method of clause 22, wherein transmitting the activation of beam failure prediction is based on one or more of: a quality of service (QoS) requirement of traffic for the UE, a discontinuous reception (DRX) configuration of the UE, or a restraint on power or capacity of the UE. 24. The method of clause 22, further comprising receiving a request for activation of beam failure prediction, wherein the activation of beam failure prediction is in response to the request for activation of beam failure prediction. 25. An apparatus for wireless communication for a user equipment (UE), comprising: a memory storing computer-executable instructions; and at least one processor coupled to the memory and configured to execute the computer-executable instructions to perform the method of any of clauses 1-12. 25. An apparatus for wireless communication for a user equipment (UE), comprising means for performing the method of any of clauses 1-12. 26. A non-transitory computer-readable medium storing computer executable code, the code when executed by a processor of a user equipment (UE) causes the processor to perform the method of any of clauses 1-12. 27. An apparatus for wireless communication for a base station, comprising: a memory storing computer-executable instructions; and at least one processor coupled to the memory and configured to execute the computer-executable instructions to: perform the method of any of

clauses 13-24. 28. An apparatus for wireless communication for a base station, comprising means for performing the method of any of clauses 13-24. 29. A non-transitory computer-readable medium storing computer executable code, the code when executed by a processor of a base station causes the processor to perform the method of any of clauses 13-24.

(123) The previous description is provided to enable any person skilled in the art to practice the various aspects described herein. Various modifications to these aspects will be readily apparent to those skilled in the art, and the generic principles defined herein may be applied to other aspects. Thus, the claims are not intended to be limited to the aspects shown herein, but is to be accorded the full scope consistent with the language claims, wherein reference to an element in the singular is not intended to mean “one and only one” unless specifically so stated, but rather “one or more.” The word “exemplary” is used herein to mean “serving as an example, instance, or illustration.” Any aspect described herein as “exemplary” is not necessarily to be construed as preferred or advantageous over other aspects. Unless specifically stated otherwise, the term “some” refers to one or more. Combinations such as “at least one of A, B, or C,” “one or more of A, B, or C,” “at least one of A, B, and C,” “one or more of A, B, and C,” and “A, B, C, or any combination thereof” include any combination of A, B, and/or C, and may include multiples of A, multiples of B, or multiples of C. Specifically, combinations such as “at least one of A, B, or C,” “one or more of A, B, or C,” “at least one of A, B, and C,” “one or more of A, B, and C,” and “A, B, C, or any combination thereof” may be A only, B only, C only, A and B, A and C, B and C, or A and B and C, where any such combinations may contain one or more member or members of A, B, or C. All structural and functional equivalents to the elements of the various aspects described throughout this disclosure that are known or later come to be known to those of ordinary skill in the art are expressly incorporated herein by reference and are intended to be encompassed by the claims. Moreover, nothing disclosed herein is intended to be dedicated to the public regardless of whether such disclosure is explicitly recited in the claims. The words “module,” “mechanism,” “element,” “device,” and the like may not be a substitute for the word “means.” As such, no claim element is to be construed as a means plus function unless the element is expressly recited using the phrase “means for.”

Claims

1. A method of wireless communication for a user equipment (UE), comprising: predicting a beam failure condition prior to a number of beam failure instances within a time period reaching a configured threshold number of beam failures; transmitting an indicator of the predicted beam failure condition to a serving cell, wherein the indicator includes a request for the serving cell to change a periodicity of a beam failure detection reference signal (BFD-RS) transmitted by the serving cell; and receiving a notification of a change to the periodicity of the BFD-RS or a change to UE scheduling in response to the indicator.
2. The method of claim 1, wherein the indicator includes a request for the serving cell not to schedule the UE for a period of time.
3. The method of claim 2, wherein the indicator identifies the period of time.
4. The method of claim 1, wherein the indicator includes a request for the serving cell not to transmit the BFD-RS for a period of time.
5. The method of claim 4, wherein the period of time is based on a predicted duration of the beam failure condition.
6. The method of claim 1, wherein the indicator includes a request for additional aperiodic BFD-RS.
7. The method of claim 6, wherein the request for additional aperiodic BFD-RS includes a period of validity for the additional aperiodic BFD-RS.
8. The method of claim 1, wherein transmitting the indicator comprises transmitting the indicator

- via a media access control (MAC) control element (CE) or uplink control information (UCI).
9. The method of claim 1, further comprising receiving a configuration of a triggering condition to predict the beam failure condition or a configuration of the indicator.
 10. The method of claim 1, further comprising receiving an activation or a deactivation of beam failure prediction.
 11. The method of claim 10, further comprising transmitting a request for activation or deactivation of beam failure prediction.
 12. A method of wireless communication at a serving cell, comprising: receiving an indicator of a predicted beam failure at a UE, wherein the indicator includes a request for the serving cell to change a periodicity of a beam failure detection reference signal (BFD-RS) transmitted by the serving cell; and transmitting a notification of a change to the periodicity of the BFD-RS or a change to UE scheduling in response to the indicator.
 13. The method of claim 12, wherein the indicator includes a request for the serving cell not to schedule the UE for a period of time.
 14. The method of claim 13, wherein the indicator identifies the period of time.
 15. The method of claim 12, wherein the indicator includes a request for the serving cell not to transmit the BFD-RS for a period of time.
 16. The method of claim 12, wherein the indicator includes a request for additional aperiodic BFD-RS.
 17. The method of claim 16, wherein the notification includes a period of validity for the additional aperiodic BFD-RS.
 18. The method of claim 12, wherein receiving the indicator comprises receiving the indicator via a media access control (MAC) control element (CE) or uplink control information (UCI).
 19. The method of claim 12, further comprising transmitting a configuration of a triggering condition to predict the beam failure or a configuration of the indicator.
 20. The method of claim 12, further comprising transmitting an activation of beam failure prediction.
 21. The method of claim 20, wherein transmitting the activation of beam failure prediction is based on one or more of: a quality of service (QoS) requirement of traffic for the UE, a discontinuous reception (DRX) configuration of the UE, or a restraint on power or capacity of the UE.
 22. The method of claim 20, further comprising receiving a request for activation of beam failure prediction, wherein the activation of beam failure prediction is in response to the request for activation of beam failure prediction.
 23. An apparatus for wireless communication for a user equipment (UE), comprising: a memory storing computer-executable instructions; and at least one processor coupled to the memory and configured to execute the computer-executable instructions to: predict a beam failure condition prior to a number of beam failure instances within a time period reaching a configured threshold number of beam failures; transmit an indicator of the predicted beam failure condition to a serving cell, wherein the indicator includes a request for the serving cell to change a periodicity of a beam failure detection reference signal (BFD-RS) transmitted by the serving cell; and receive a notification of a change to the periodicity of the BFD-RS or a change to UE scheduling in response to the indicator.
 24. The apparatus of claim 23, wherein the indicator includes a request for the serving cell not to schedule the UE for a period of time.
 25. The apparatus of claim 23, wherein the indicator includes a request for the serving cell not to transmit the BFD-RS for a period of time.
 26. The apparatus of claim 23, wherein the at least one processor is configured to receive a configuration of a triggering condition to predict the beam failure or a configuration of the indicator.
 27. The apparatus of claim 23, wherein the indicator includes a request for additional aperiodic

BFD-RS.

28. An apparatus for wireless communication for a base station, comprising: a memory storing computer-executable instructions; and at least one processor coupled to the memory and configured to execute the computer-executable instructions to: receive an indicator of a predicted beam failure at a UE, wherein the indicator includes a request for a serving cell of the base station to change a periodicity of a beam failure detection reference signal (BFD-RS) transmitted by the serving cell; and transmit a notification of a change to the periodicity of the BFD-RS or a change to UE scheduling in response to the indicator.

29. The apparatus of claim 28, wherein the indicator includes a request for additional aperiodic BFD-RS.
