

US Patent & Trademark Office

Patent Public Search | Text View

United States Patent	12418250
Kind Code	B2
Date of Patent	September 16, 2025
Inventor(s)	Kawai; Shusuke

Electronic circuitry, power conversion device, and method

Abstract

In one embodiment, electronic circuitry includes a processing circuit. The processing circuit generates waveform data of a drive current to be supplied to the switching element, provides the waveform data to a drive circuit of the switching element, and at turn-on of the switching element, corrects the waveform data based on a load current flowing through a load connected to the switching element and a surge current of the switching element.

Inventors:	Kawai; Shusuke (Yokohama Kanagawa, JP)
Applicant:	KABUSHIKI KAISHA TOSHIBA (Tokyo, JP)
Family ID:	1000008818903
Assignee:	Kabushiki Kaisha Toshiba (Tokyo, JP)
Appl. No.:	18/185304
Filed:	March 16, 2023

Prior Publication Data

Document Identifier	Publication Date
US 20240079970 A1	Mar. 07, 2024

Foreign Application Priority Data

JP	2022-142445	Sep. 07, 2022
----	-------------	---------------

Publication Classification

Int. Cl.: H02M7/00 (20060101); H02M1/00 (20060101); H02M1/088 (20060101); H02M7/539 (20060101)

U.S. Cl.:

CPC **H02M7/539** (20130101); **H02M1/0009** (20210501); **H02M1/0025** (20210501);
H02M1/0067 (20210501); **H02M1/088** (20130101);

Field of Classification Search

CPC: H02M (7/539); H02M (1/0009); H02M (1/0025); H02M (1/0067)

References Cited

U.S. PATENT DOCUMENTS

Patent No.	Issued Date	Patentee Name	U.S. Cl.	CPC
10333509	12/2018	Kaeriyama	N/A	N/A
10554202	12/2019	Nomura	N/A	N/A
11894837	12/2023	Matsubara	N/A	N/A
2003/0048086	12/2002	Takahashi	318/430	H02M 7/53803
2018/0269869	12/2017	Mukhopadhyay et al.	N/A	N/A
2022/0045641	12/2021	Hattori	N/A	H02M 1/0009

FOREIGN PATENT DOCUMENTS

Patent No.	Application Date	Country	CPC
2008-78816	12/2007	JP	N/A
2011-172446	12/2010	JP	N/A
2017-229151	12/2016	JP	N/A
2018-38174	12/2017	JP	N/A
6355775	12/2017	JP	N/A
2021-191088	12/2020	JP	N/A

OTHER PUBLICATIONS

Yang Wen et al., “Active Gate Driver for Improving Current Sharing Performance of Paralleled High-Power SiC MOSFET Modules”, IEEE Trans. on Power Elecs., vol. 36, No. 2, pp. 1491-1505 (2021). cited by applicant

Japan Patent Office, Office Action in JP Patent App. No. 2022-142445 (Apr. 25, 2025). cited by applicant

Primary Examiner: Berhane; Adolf D

Assistant Examiner: Demisse; Afework S

Attorney, Agent or Firm: Finnegan, Henderson, Farabow, Garrett & Dunner, LLP

Background/Summary

REFERENCE TO RELATED APPLICATIONS

(1) This application is based upon and claims the benefit of priority from the prior Japanese Patent Application No. 2022-142445, filed on Sep. 7, 2022, the entire contents of which are incorporated

herein by reference.

FIELD

(2) The present embodiment relates to electronic circuitry, a power conversion device, and a method.

BACKGROUND ART

(3) In the field of power electronics, semiconductor switching elements such as MOSFETs (metal oxide semiconductor field effect transistors) or IGBTs (insulated gate bipolar transistors) are used. In a circuit including these switching elements, power loss can be reduced by increasing the speed of switching operations of the elements. However, when the speed of switching operations of the elements is excessively increased, ringing occurs in current flowing at turn-on or at turn-off of the elements. Such current ringing causes noise to occur. In other words, reduction of power loss and suppression of noise have a trade-off relationship.

(4) As a method for optimizing the above-described trade-off, active gate control technology has been studied. In the active gate control technology, waveforms of drive signals at turn-on and at turn-off of switching elements are experimentally or theoretically determined in advance so as to achieve both reduction of power loss and suppression of noise, and these waveform data are stored in a storage circuit. Drive circuits of the switching elements generate drive signals in accordance with waveform data provided from the storage circuit, and drive the switching elements by the drive signals.

(5) The present embodiment has an object to provide electronic circuitry that generates waveform data of a drive current such that reduction of power loss and suppression of noise at turn-on of a switching element are both achieved.

(6) In order to achieve the above-described object, an electronic circuitry according to the present embodiment comprises a processing circuit configured to: generate waveform data of a drive current to be supplied to a switching element, provide the waveform data to a drive circuit of the switching element, and at turn-on of the switching element, correct the waveform data based on a load current flowing through a load connected to the switching element and a surge current of the switching element.

(7) In addition, a power conversion device according to the present embodiment comprises a power conversion circuit including two switching elements that constitute an arm pair, and two drive circuits configured to supply a drive current to the two switch elements respectively, and a processing circuit configured to: generate waveform data of the drive current, provide the waveform data to the drive circuits, and at turn-on of the switching elements, correct the waveform data based on a load current flowing through a load connected to the switching elements and a surge current of the switching elements.

(8) In addition, a method according to the present embodiment comprising: generating waveform data of a drive current to be supplied to a switching element, providing the waveform data to a drive circuit of the switching element, and at turn-on of the switching element, correcting the waveform data based on a load current flowing through a load connected to the switching element and a surge current of the switching element.

Description

BRIEF DESCRIPTION OF THE DRAWINGS

- (1) FIG. 1 illustrates a configuration of a motor control system according to Embodiment 1;
- (2) FIG. 2 is an equivalent circuit at turn-on of a switching element;
- (3) FIG. 3 is a timing chart describing an operation at turn-on of a switching element;
- (4) FIG. 4 is a timing chart describing a preferable operation at turn-on of a switching element;
- (5) FIG. 5 is a timing chart describing an unpreferable operation at turn-on of a switching element;

- (6) FIG. 6 is a timing chart describing an unpreferable operation at turn-on of a switching element;
- (7) FIG. 7 illustrates an inner configuration of electronic circuitry;
- (8) FIG. 8 shows an example for selecting waveform data by a selection circuit,
- (9) FIG. 9 is a flow chart describing an operation of determining waveform data performed by electronic circuitry;
- (10) FIG. 10 shows a way until waveform data is determined;
- (11) FIG. 11 shows an example of determined waveform data; and
- (12) FIG. 12 shows another example of determined waveform data.

DETAILED DESCRIPTION

(13) Hereinafter, an embodiment will be described with reference to the drawings. The same or corresponding elements in the drawings are denoted by the same reference, and detailed description will be omitted as appropriate.

Embodiment 1

- (14) FIG. 1 illustrates a configuration of a motor control system **100** according to Embodiment 1. The motor control system **100** comprises a three-phase AC motor **1** as a load, a DC power supply V_{dc} , switching elements **11a** to **11f** constituting a three-phase inverter circuit **10**, and drive circuits **12a** to **12f** which drive the switching elements **11a** to **11f** respectively.
- (15) The switching elements **11a** and **11b** are N-channel MOSFETs. The switching elements **11a** and **11b** constitute a U-phase arm pair of the inverter circuit **10**. The drive circuit **12a** controls a gate current (drive current) of the switching element **11a** to control switching operation, i.e., turn-on and turn-off of the switching element **11a**. The drive circuit **12b** controls a gate current of the switching element **11b** to control switching operation of the switching element **11b**.
- (16) Similarly, the switching elements **11c** and **11d** are N-channel MOSFETs. The switching elements **11c** and **11d** constitute a V-phase arm pair of the inverter circuit **10**. The drive circuit **12c** controls a gate current of the switching element **11c** to control switching operation of the switching element **11c**. The drive circuit **12d** controls a gate current of the switching element **11d** to control switching operation of the switching element **11d**.
- (17) Similarly, the switching elements **11e** and **11f** are N-channel MOSFETs. The switching elements **11e** and **11f** constitute a W-phase arm pair of the inverter circuit **10**. The drive circuit **12e** controls a gate current of the switching element **11e** to control switching operation of the switching element **11e**. The drive circuit **12f** controls a gate current of the switching element **11f** to control switching operation of the switching element **11f**.
- (18) The motor control system **100** also comprises electronic circuitry **20**. electronic circuitry **20** determines and stores waveform data of the gate currents of the switching elements **11a** to **11f** prior to running of the motor control system **100**. Electronic circuitry **20** provides waveform data of the gate currents to the drive circuits **12a** to **12f** for the switching elements **11a** to **11f** based on U-phase, V-phase, and W-phase currents of the motor **1** when the motor control system **100** is running.
- (19) In particular, electronic circuitry **20** provides waveform data of the gate currents to the drive circuits **12a** and **12b** based on the U-phase current of the motor **1**. The drive circuit **12a** generates a gate current in accordance with the waveform data provided from electronic circuitry **20**, and supplies the gate current to the switching element **11a**. The drive circuit **12b** generates a gate current in accordance with the waveform data provided from electronic circuitry **20**, and supplies the gate current to the switching element **11b**.
- (20) Similarly, electronic circuitry **20** provides waveform data of the gate currents to the drive circuits **12c** and **12d** based on the V-phase current of the motor **1**. The drive circuit **12c** generates a gate current in accordance with the waveform data provided from electronic circuitry **20**, and supplies the gate current to the switching element **11c**. The drive circuit **12d** generates a gate current in accordance with the waveform data provided from electronic circuitry **20**, and supplies the gate current to the switching element **11d**.

(21) Similarly, electronic circuitry **20** provides waveform data of the gate currents to the drive circuits **12e** and **12f** based on the W-phase current of the motor **1**. The drive circuit **12e** generates a gate current in accordance with the waveform data provided from electronic circuitry **20**, and supplies the gate current to the switching element **11e**. The drive circuit **12f** generates a gate current in accordance with the waveform data provided from electronic circuitry **20**, and supplies the gate current to the switching element **11f**.

(22) Herein, an operation at turn-on of the switching elements **11a** to **11f** in FIG. **1** will be described. The following description focuses on the switching element **11a**, and an operation when the switching element **11a** is turned on will be described. However, the following description also similarly holds for the other switching elements **11b** to **11f**.

(23) FIG. **2** is an equivalent circuit at turn-on of the switching element **11a** in FIG. **1**. When the switching element **11a** is turned on, the switching element **11b** that constitutes the U-phase arm pair together with the switching element **11a** is OFF. In FIG. **2**, the switching element **11b** in OFF is represented by a diode Dio and a parasitic capacitor Cdio.

(24) An inductor Lload represents inductance of the motor **1** which is a load. An inductor Ld represents parasitic inductance of a wiring between the drain terminals of the switching elements **11a** and **11b**.

(25) The switching element **11a** has a gate-source parasitic capacitor Cgs, a gate-drain parasitic capacitor Cgd and a drain-source parasitic capacitor Cds. The drive circuit **12a** supplies a gate current Ig to the gate terminal of the switching element **11a**.

(26) FIG. **3** is a timing chart describing an operation at turn-on of the switching element **11a**. In an initial state on the left end of FIG. **3**, the gate current Ig supplied from the drive circuit **12a** is 0, and the gate voltage of the switching element **11a** is also 0. Consequently, the switching element **11a** is OFF, the drain current Id is 0, and the drain voltage Vd is equal to an anode-side voltage Vdio of the diode Dio.

(27) At time t1, the drive circuit **12a** increases the gate current Ig stepwise. This causes charging of the gate-source parasitic capacitor Cgs of the switching element **11a** to be started, and the gate voltage of the switching element **11a** rises.

(28) At time t2, when the gate voltage of the switching element **11a** exceeds a threshold voltage, a channel is formed and the drain current Id starts flowing. The drain current Id increases along with the rise in gate voltage. In FIG. **3**, the increase of the drain current Id is approximated by a linear function.

(29) At this time, the diode Dio is ON, and the anode-side voltage Vdio of the diode Dio does not change and is constant. On the other hand, the flow of the drain current Id produces a voltage Vo across both terminals of the inductor Ld, and the drain voltage Vd decreases.

(30) At time t3, when the drain current Id becomes equal to a stationary component of current flowing through the inductor Lload, i.e., the load current Idc, the diode Dio is turned off, and the anode-side voltage Vdio of the diode Dio decreases. At this time, a resonance loop as shown in FIG. **2** is formed, and ringing of the drain current Id occurs. A peak value of an amplitude of ringing of the drain current Id, i.e., the magnitude of the surge current Isurge, is proportionate to the terminal-to-terminal voltage Vo of the inductor Ld at the start time of resonance.

(31) As described earlier, Embodiment 1 intends to achieve both reduction of power loss and suppression of noise at turn-on of the switch element **11a**.

(32) First, from the point of view of reduction of power loss, it is desirable that the gate current Ig be larger. When the gate current Ig is large, the gate voltage rapidly rises, and the inclination of the drain current Id increases. As a result, the time period until turn-on has completed is shortened, and power loss is reduced.

(33) On the other hand, from the point of view of suppression of noise, it is desirable that the gate current Ig be smaller. As described earlier, the peak value of the amplitude of ringing of the drain current Id responsible for noise, i.e., the magnitude of the surge current Isurge, is proportionate to

the terminal-to-terminal voltage V_o of the inductor L_d at the start time of resonance. Thus, the surge current I_{surge} responsible for noise can be decreased by decreasing the terminal-to-terminal voltage V_o of the inductor L_d at the start time of resonance.

(34) In order to decrease the terminal-to-terminal voltage V_o of the inductor L_d at the start time of resonance, it is desirable that the gate current I_g be smaller. When the gate current I_g is small, the inclination of the drain current I_d decreases, and the rate of change of current flowing through the inductor L_d is reduced. Thus, the terminal-to-terminal voltage V_o of the inductor L_d at the start time of resonance decreases. Consequently, it is desirable that the gate current I_g be smaller from the point of view of suppression of noise.

(35) From the above-described consideration, in order to achieve both reduction of power loss and suppression of noise in the switching element **11a**, it is preferable that a large gate current (a first current value I_{g1}) be supplied in a period TP from the start time of supply of the gate current I_g until immediately before time t_3 at which the resonance loop is formed, and a small gate current (a second current value I_{g2}) be supplied in a subsequent period, as shown in FIG. 4.

(36) By supplying a large gate current until immediately before the resonance loop is formed, the time period until turn-on has completed is shortened, and power loss is reduced. In addition, by supplying a small gate current from immediately before the resonance loop is formed, the terminal-to-terminal voltage V_o of the inductor L_d at the start time of resonance decreases, and the peak value of ringing of the drain current I_d responsible for noise, i.e., the surge current I_{surge} , decreases.

(37) Note that as shown in FIG. 5, if the period TP being excessively long makes the time at which the gate current I_g is reduced later than time t_3 at which the resonance loop is formed, ringing of the drain current I_d responsible for noise is not suppressed because the terminal-to-terminal voltage V_o at the start time of resonance of the inductor L_d is large although power loss is reduced.

(38) As shown in FIG. 6, if the period TP being excessively short makes the time at which the gate current I_g is reduced excessively earlier than time t_3 at which the resonance loop is formed, the effect of reducing power loss is low although ringing of the drain current I_d responsible for noise is suppressed.

(39) Consequently, it is most preferable that the length of the period TP , i.e., the time at which the gate current I_g is reduced, is immediately before time t_3 at which the resonance loop is formed, as shown in FIG. 4 described earlier.

(40) Herein, as described earlier, time t_3 at which the resonance loop is formed is the time at which the drain current I_d and the load current I_{dc} flowing through the motor **1** become equal, and the diode D_{io} is turned on. In other words, time t_3 at which the resonance loop is formed changes in accordance with the value of the load current I_{dc} flowing through the motor **1**. Considering this fact, in Embodiment 1, the length of the period TP of the first current value I_{g1} in the gate current I_g is changed in accordance with the value of the load current I_{dc} .

(41) FIG. 7 illustrates an inner configuration of electronic circuitry **20** in FIG. 1. Electronic circuitry **20** comprises a setting circuit **21**, a generation circuit **22**, a provision circuit **23**, a determination circuit **24**, a storage circuit **25** and a selection circuit **26**. Electronic circuitry **20** also comprises a first detection circuit **27** that detects the load current I_{dc} which is a stationary component of current flowing through the motor **1** and a second detection circuit **28** that detects the surge current I_{surge} which is the peak value of the amplitude of ringing of the drain current I_d .

(42) At least one of the setting circuit **21**, the generation circuit **22**, the provision circuit **23**, the determination circuit **24** and the selection circuit **26** may be included in a processing circuit **30**. The processing circuit **30** is implemented by at least one processor. The processor includes a control circuit and an arithmetic circuit, for example, and is implemented by a circuit that performs analog signal processing, a circuit that performs digital signal processing, or the like. The processor may be a CPU (central processing unit), a DSP (digital signal processor), a general purpose processor, a microprocessor, ASIC, FPGA, a semiconductor chip, a discrete part, and a combination thereof.

- (43) The setting circuit **21** sets values of N reference currents **I1** to **IN** to be used as references when generating and selecting waveform data of the gate current **Ig** of the switching elements **11a** to **11f**, where $I1 > \dots > IN > 0$.
- (44) The generation circuit **22** generates waveform data of the gate current **Ig** supplied from the drive circuits **12a** to **12f** to the switching elements **11a** to **11f** when turning on the switching elements **11a** to **11f** prior to running of the motor control system **100**. Alternatively, the generation circuit **22** corrects the waveform data based on the load current **Idc** flowing through the motor **1** and the surge current **Isurge** of the switching elements **11a** to **11f**.
- (45) The provision circuit **23** provides the waveform data generated or corrected by the generation circuit **22** to the drive circuits **12a** to **12f** of the switching elements **11a** to **11f** prior to running of the motor control system **100**, and drives the switching elements **11a** to **11f** with the gate current **Ig** in accordance with the waveform data.
- (46) The determination circuit **24** determines waveform data in accordance with the load current **Idc** flowing through the motor **1** and the surge current **Isurge** of the switching elements **11a** to **11f** when turning on the switching elements **11a** to **11f** prior to running of the motor control system **100**. The determination circuit **24** determines N waveform data in which the lengths of the period **TP** of the first current value **Ig1** are different from each other, in accordance with the value of the load current **Idc**.
- (47) The storage circuit **25** includes N look-up tables (**LUT_1** to **LUT_N**). **LUT_1** to **LUT_N** store the N waveform data determined by the determination circuit **24**.
- (48) The selection circuit **26** selects one of the N waveform data stored in **LUT_1** to **LUT_N** of the storage circuit **25** based on the load current **Idc** of the motor **1** detected by the first detection circuit **27** when turning on the switching elements **11a** to **11f** at running of the motor control system **100**, and provides the selected waveform data to the drive circuits **12a** to **12f** of the switching elements **11a** to **11f**.
- (49) In particular, when turning on the switching element **11a** or **11b** that constitutes the U-phase arm pair, the selection circuit **26** selects one of the N waveform data stored in **LUT_1** to **LUT_N** of the storage circuit **25** based on the load current **Idc** in U-phase detected by the first detection circuit **27**.
- (50) Similarly, when turning on the switching element **11c** or **11d** that constitutes the V-phase arm pair, the selection circuit **26** selects one of the N waveform data stored in **LUT_1** to **LUT_N** of the storage circuit **25** based on the load current **Idc** in V-phase detected by the first detection circuit **27**.
- (51) Similarly, when turning on the switching element **11e** or **11f** that constitutes the W-phase arm pair, the selection circuit **26** selects one of the N waveform data stored in **LUT_1** to **LUT_N** of the storage circuit **25** based on the load current **Idc** in W-phase detected by the first detection circuit **27**.
- (52) FIG. 8 shows an example for selecting waveform data by the selection circuit **26**, where $N=3$. Waveform data **D1** to **D3**, in which the lengths of the period **TP** are different from each other, are stored in **LUT_1** to **LUT_3**. In addition, the three reference currents **I1** to **I3** to be used as references when selecting waveform data are defined, where $I1 > I2 > I3 > 0$.
- (53) When the load current **Idc** is more than or equal to the reference current **I1**, i.e., $dc \geq I1$, the waveform data **D1** stored in **LUT_1** is selected.
- (54) When the load current **Idc** is smaller than the reference current **I1** and more than or equal to the reference current **I2**, i.e., $I2 \leq Idc < I1$, the waveform data **D2** stored in **LUT_2** is selected.
- (55) When the load current **Idc** is smaller than the reference current **I2** and more than or equal to the reference current **I3**, i.e., $I3 \leq Idc < I2$, the waveform data **D3** stored in **LUT_3** is selected.
- (56) Next, a detailed operation when electronic circuitry **20** according to Embodiment 1 determines waveform data of the gate current **Ig** of the switching elements **11a** to **11f** will be described. FIG. 9 is a flow chart describing an operation when electronic circuitry **20** determines waveform data of the gate current **Ig**. In addition, the following description will be given focusing on the switching element **11a**. However, the following description also similarly holds for the other switching

elements **11b** to **11f**.

(57) In Step **S1**, the setting circuit **21** sets the values of the reference currents I_n ($n=1$ to N) to be used as references when generating waveform data of the gate current I_g . In the case $N=3$, for example, the setting circuit **21** sets the values of I_1 , I_2 and I_3 , where $I_1>I_2>I_3>0$. In Step **S2**, the setting circuit **21** sets the value of an index n at **1**.

(58) In Step **S3**, the generation circuit **22** sets an initial value of the length of period TP in accordance with the value of the index n , and generates (temporary) waveform data D_n . In the case $n=1$, for example, the initial value of the length of the period TP in the waveform data **D1** is set at the maximum value allowed in terms of specifications of the switching element **11a**. In the case $n>1$, the initial value of the length of the period TP in the waveform data D_n is set at the length of the period TP in the waveform data D_{n-1} determined in Step **S8** which will be described later.

(59) In Step **S4**, the provision circuit **23** provides the waveform data D_n generated in Step **S3** described above or the waveform data D_n corrected in Step **S7** which will be described later to the drive circuit **12a**. In the case $n=1$, for example, the waveform data **D1** is provided to the drive circuit **12a**. The drive circuit **12a** generates the gate current I_g in accordance with the provided waveform data D_n , and supplies the gate current I_g to the switching element **11a**. This causes turn-on of the switching element **11a** to be started, and the load current I_{dc} of the motor **1** detected by the first detection circuit **27** increases.

(60) In Step **S5**, the determination circuit **24** acquires, from the second detection circuit **28**, a first surge current value when the load current I_{dc} =the reference current $I_n - \Delta I_a$ and a second surge current value when the load current I_{dc} =the reference current $I_n + \Delta I_b$. Where ΔI_a and ΔI_b are predetermined first small value and second small value.

(61) In the case $n=1$, for example, the first surge current value when the load current I_{dc} =the reference current $I_1 - \Delta I_a$ and the second surge current value when the load current I_{dc} =the reference current $I_1 + \Delta I_b$ are acquired. Note that the first small value ΔI_a and the second small value ΔI_b may have any magnitudes. For example, they are set to about 1 to 10% of a difference between the reference current I_n and the reference current I_{n+1} .

(62) In Step **S6**, the determination circuit **24** determines whether the difference between the first surge current value and the second surge current value is more than or equal to a predetermined value ΔTH . If the difference between the first surge current value and the second surge current value is less than the predetermined value ΔTH (Step **S6**=NO), the process proceeds to Step **S7**. On the other hand, if the difference between the first surge current value and the second surge current value is more than or equal to the predetermined value ΔTH (Step **S6**=YES), the process proceeds to Step **S8**.

(63) In Step **S7**, the generation circuit **22** corrects the waveform data D_n provided in Step **S4** to the waveform data D_n in which the length of the period TP is shortened by a predetermined amount. In the case $n=1$, for example, the waveform data **D1** is corrected to the waveform data **D1** in which the length of the period TP is shortened by the predetermined amount. Thereafter, the process returns to Step **S4** described above.

(64) In Step **S8**, the determination circuit **24** acquires the present value of the period TP from the generation circuit **22**, and determines the length of the period TP in the waveform data D_n to be the acquired value. The determination circuit **24** causes the waveform data D_n having the determined period TP to be stored in a corresponding one of the look-up tables. In the case $n=1$, for example, the waveform data **D1** having the determined period TP is stored in **LUT_1**.

(65) In Step **S9**, the setting circuit **21** determines whether the index $n=N$. In case $n<N$, i.e., storing process of the N waveform data into the look-up tables has not been completed (Step **S9**=NO), the setting circuit **21** adds 1 to the value of the index n (Step **S10**), the process returns to Step **S3**. On the other hand, in the case $n=N$, i.e., storing process of the N waveform data into the look-up tables has been completed (Step **S9**=YES), the process ends.

(66) FIG. **10** shows a way until the length of the period TP in the waveform data **D1** is shortened

stepwise by the predetermined amount and determined. At the top of FIG. 10, the first surge current value and the second surge current value are equal, both of which is a large value, and the difference between the first surge current value and the second surge current value is less than the predetermined value ΔTH (Step S6=NO in FIG. 9). This means that the period TP being excessively long makes the time at which the gate current I_g is reduced later than the time at which the resonance loop is formed. In this case, ringing of the drain current I_d responsible for noise is not suppressed although power loss is reduced. Consequently, the generation circuit 22 shortens the length of the period TP in the waveform data D1 by the predetermined amount (Step S7 in FIG. 9). (67) At the middle of FIG. 10, the first surge current value and the second surge current value are slightly different but are both large values, and the difference between the first surge current value and the second surge current value is less than the predetermined value ΔTH (Step S6=NO in FIG. 9). This means that the period TP being still excessively long makes the time at which the gate current I_g is reduced later than the time at which the resonance loop is formed. In this case, ringing of the drain current I_d responsible for noise is not sufficiently suppressed although power loss is reduced. Consequently, the generation circuit 22 further shortens the length of the period TP in the waveform data D1 by the predetermined amount (Step S7 in FIG. 9).

(68) At the bottom of FIG. 10, the first surge current value and the second surge current value are greatly different, and the difference between the first surge current value and the second surge current value is more than or equal to the predetermined value ΔTH (Step S6=YES in FIG. 9). In other words, the surge current value abruptly changes in the vicinity of the load current I_{dc} =the reference current I_1 . This means that the time at which the gate current I_g is reduced and the time at which the resonance loop is formed are substantially equal. In this case, power loss is reduced, and ringing of the drain current I_d responsible for noise is also sufficiently suppressed. In other words, reduction of power loss and suppression of noise are both achieved. Consequently, the determination circuit 24 determines the length of the period TP in the waveform data D at the present value (Step S8 in FIG. 7).

(69) FIG. 11 shows an example of waveform data D_n determined in accordance with the flowchart of FIG. 9, where $N=3$. The waveform data D1 to D3, in which the lengths of the period TP are different from each other, are determined in accordance with the value of the load current I_{dc} . In this example, as the value of the load current I_{dc} is larger, the period TP is longer. This is because the drain current I_d becomes equal to the load current I_{dc} as the value of the load current I_{dc} is larger, so that a longer time is required until the resonance loop is formed.

(70) FIG. 12 shows another example of waveform data. The gate current I_g may be increased again after time t_3 after determining the waveform as shown in FIG. 11, as indicated by a dotted line at the bottom of FIG. 12. By increasing the gate current I_g again, the time at which the gate voltage of a switching element reaches a power supply voltage of the drive circuit can be accelerated, which can prevent the gate voltage from fluctuating due to unexpected noise and the power device from performing an unintended operation.

(71) As described above, electronic circuitry 20 according to Embodiment 1 comprises the processing circuit 30. The processing circuit 30 is configured to: generate waveform data of a drive current to be supplied to a switching element, provide the waveform data to a drive circuit of the switching element, and at turn-on of the switching element, correct the waveform data based on the load current I_{dc} flowing through the load connected to the switching element and the surge current I_{surge} of the switching element, and determine waveform data in accordance with the load current I_{dc} and the surge current I_{surge} .

(72) According to the above features, electronic circuitry 20 according to Embodiment 1 can generate waveform data of a drive current such that reduction of power loss and suppression of noise at turn-on of a switching element are both achieved.

(73) In electronic circuitry 20 according to Embodiment 1, the reference current I_n includes N reference currents from I_1 to I_N . The processing circuit 30 is configured to correct and determine

the waveform data for each of the N reference currents **I1** to **IN** in the above determination process. In particular, waveform data determined for the first reference current **I1** is waveform data corresponding to a time at which the load current **Idc** is more than or equal to the first reference current **I1**. Waveform data determined for an n-th reference current **In** is waveform data corresponding to a time at which the load current **Idc** is more than or equal to the n-th reference current **In** and less than an n-1-th reference current **In-1**.

(74) According to the above features, electronic circuitry **20** according to Embodiment 1 can determine waveform data of a drive current such that reduction of power loss and suppression of noise at turn-on of the switching element are both achieved in accordance with the value of the load current **Idc**.

(75) Note that when determining the length of the period **TP** in Step **S8** in FIG. 7 in Embodiment 1, the length of the period **TP** may be corrected to be still shorter than a present value and determined. By providing a margin in this manner, noise is suppressed more reliably.

(76) In Embodiment 1, when correcting and determining the length of the period **TP** in the waveform data, the period **TP** is shortened stepwise by the predetermined amount after setting the initial value of the period **TP** to be as long as possible. This means that the period **TP** is shortened from an initial state in which suppression of noise is insufficient although the effect of reducing power loss is great until a state in which the surge current responsible for noise is sufficiently suppressed is brought about while weakening the effect of reducing power loss little by little. In other words, it means that greater importance is placed on suppression of noise than on reduction of power loss.

(77) Instead, when correcting and determining the length of the period **TP** in the waveform data, the period **TP** may be extended stepwise by the predetermined amount after setting the initial value of the period **TP** to be as short as possible. In this case, it means that the period **TP** is extended from the initial state in which power loss is great although the effect of suppression of noise is sufficient to the last place where the effect of suppression of noise is kept in order to reduce power loss. In other words, it means that greater importance is placed on reduction of power loss than on suppression of noise.

MODIFICATIONS

(78) In Embodiment 1, the three-phase inverter circuit **10** is constituted by the switching elements **11a** to **11f**. In each pair of switching elements, the switching elements are both N-channel MOSFETs. Instead, in a case of constituting a converter circuit, for example, one of the switching elements in each pair of switching elements is an N-channel MOSFET, and the other switching element is a diode.

(79) The switching elements **11a** to **11f** are not limited to MOSFETs. For example, the switching elements **11a** to **11f** may be IGBTs or BJTs (bipolar junction transistors). Various materials such as Si (silicon), SiC (silicon carbide), or GaN (gallium nitride) can be used as semiconductor that constitutes the switching elements **11a** to **11f**.

(80) Although some embodiments have been described, these embodiments have been presented as examples. These embodiments, not intended to limit the scope of embodiments, can be embodied in other various forms, and various omissions, replacements, changes, and combinations can be carried out without departing from the spirit of the embodiments. These embodiments and their modifications are embraced in the scope and spirit of the embodiments, and are similarly embraced in claims and equivalents thereof.

(81) Note that the present embodiment can also be configured as indicated below.

(82) [1]

(83) An electronic circuitry comprising a processing circuit configured to: generate waveform data of a drive current to be supplied to a switching element, provide the waveform data to a drive circuit of the switching element, and at turn-on of the switching element, correct the waveform data based on a load current flowing through a load connected to the switching element and a surge

current of the switching element.

[2]

(84) The electronic circuitry according to 1, wherein the processing circuit configured to: set a reference current, and correct the waveform data based on a first surge current value when the load current is smaller than the reference current by a predetermined first value and a second surge current value when the load current is larger than the reference current by a predetermined second value.

[3]

(85) The electronic circuitry according to 1 or 2, wherein the waveform data includes a period of a first current value and a period of a second current value which is smaller than the period of the first current value, and the processing circuit is configured to: correct the waveform data by correcting the period of the first current value.

[4]

(86) The electronic circuitry according to 3, wherein the processing circuit configured to: shorten or extend a length of the period of the first current value stepwise by a predetermined amount, and when a difference between the first surge current value and the second surge current value becomes more than or equal to a predetermined value, determine the period of the first current value.

[5]

(87) The electronic circuitry according to any one of 2 to 4, wherein the reference current includes a first to an N-th, N reference currents (where N is an integer of more than or equal to 2), and the processing circuit is configured to: determine the waveform data for each of the N reference currents.

[6]

(88) The electronic circuitry according to 5, wherein the first value and the second value are set between 1 to 10% of a difference between an n-th reference current (where n is an integer of 1 to N) and an n+1-th reference current.

[7]

(89) The electronic circuitry according to 5 or 6, wherein the waveform data determined for the first reference current is waveform data corresponding to a time at which the load current is more than or equal to the first reference current, and the waveform data determined for an n-th reference current (where n is an integer of 2 to N) is waveform data corresponding to a time at which the load current is more than or equal to the n-th reference current and less than an n-1-th reference current.

[8]

(90) The electronic circuitry according to any one of 1 to 7, further comprising a first detection circuit configured to detect the load current.

(91) [9]

(92) The electronic circuitry according to any one of 1 to 8, further comprising a second detection circuit configured to detect the surge current.

(93) [10]

(94) The electronic circuitry according to any one of 1 to 9, further comprising a storage circuit configured to store a corrected waveform data.

(95) [11]

(96) The electronic circuitry according to any one of 1 to 10, further comprising the drive circuit configured to generate a drive current in accordance with the waveform data of the drive current provided from the electronic circuitry, and supply the drive current to the switching element.

(97) [12]

(98) The electronic circuitry according to any one of 1 to 11, further comprising the switching element to be driven by the drive current supplied from the drive circuit.

(99) [13]

(100) A power conversion device comprising: a power conversion circuit including two switching

elements that constitute an arm pair, and two drive circuits configured to supply a drive current to the two switching elements respectively; and a processing circuit configured to: generate waveform data of the drive current, provides the waveform data to the drive circuits, and at turn-on of the switching elements, correct the waveform data based on a load current flowing through a load connected to the switching elements and a surge current of the switching elements.

[14]

(101) The power conversion device according to 13, further comprising three power conversion circuits, each being the power conversion circuit.

(102) [15]

(103) A method comprising: generating waveform data of a drive current to be supplied to a switching element; providing the waveform data to a drive circuit of the switching element; and at turn-on of the switching element, correcting the waveform data based on a load current flowing through a load connected to the switching element and a surge current of the switching element.

Claims

1. An electronic circuitry comprising a processing circuit configured to: generate waveform data of a drive current to be supplied to a switching element, provide the waveform data to a drive circuit of the switching element, at turn-on of the switching element, correct the waveform data based on a load current flowing through a load connected to the switching element and a surge current of the switching element, set a reference current, and correct the waveform data based on a first surge current value when the load current is smaller than the reference current by a predetermined first value and a second surge current value when the load current is larger than the reference current by a predetermined second value.
2. The electronic circuitry according to claim 1, wherein the waveform data includes a period of a first current value and a period of a second current value which is smaller than the period of the first current value, and the processing circuit is configured to: correct the waveform data by correcting the period of the first current value.
3. The electronic circuitry according to claim 2, wherein the processing circuit is configured to: shorten or extend a length of the period of the first current value stepwise by a predetermined amount, and when a difference between the first surge current value and the second surge current value becomes more than or equal to a predetermined value, determine the period of the first current value.
4. The electronic circuitry according to claim 1, wherein the reference current includes a first to an N-th, N reference currents (where N is an integer of more than or equal to 2), and the processing circuit is configured to: determine the waveform data for each of the N reference currents.
5. The electronic circuitry according to claim 4, wherein the first value and the second value are set between 1 to 10% of a difference between an n-th reference current (where n is an integer of 1 to N) and an n+1-th reference current.
6. The electronic circuitry according to claim 4, wherein the waveform data determined for the first reference current is waveform data corresponding to a time at which the load current is more than or equal to the first reference current, and the waveform data determined for an n-th reference current (where n is an integer of 2 to N) is waveform data corresponding to a time at which the load current is more than or equal to the n-th reference current and less than an n-1-th reference current.
7. The electronic circuitry according to claim 1, further comprising a first detection circuit configured to detect the load current.
8. The electronic circuitry according to claim 1, further comprising a second detection circuit configured to detect the surge current.
9. The electronic circuitry according to claim 1, further comprising a storage circuit configured to store a corrected the waveform data.

10. The electronic circuitry according to claim 1, further comprising the drive circuit configured to generate a drive current in accordance with the waveform data of the drive current provided from the electronic circuitry, and supply the drive current to the switching element.
11. The electronic circuitry according to claim 10, further comprising the switching element to be driven by the drive current supplied from the drive circuit.
12. A power conversion device comprising: a power conversion circuit including two switching elements that constitute an arm pair, and two drive circuits configured to supply a drive current to the two switching elements respectively; and a processing circuit configured to: generate waveform data of the drive current, provides the waveform data to the drive circuits, at turn-on of the switching elements, correct the waveform data based on a load current flowing through a load connected to the switching elements and a surge current of the switching elements, set a reference current, and correct the waveform data based on a first surge current value when the load current is smaller than the reference current by a predetermined first value and a second surge current value when the load current is larger than the reference current by a predetermined second value.
13. The power conversion device according to claim 12, further comprising three power conversion circuits, each being the power conversion circuit.
14. A method comprising: generating waveform data of a drive current to be supplied to a switching element; providing the waveform data to a drive circuit of the switching element; at turn-on of the switch element, correcting the waveform data based on a load current flowing through a load connected to the switching element and a surge current of the switch element; setting a reference current; and correcting the waveform data based on a first surge current value when the load current is smaller than the reference current by a predetermined first value and a second surge current value when the load current is larger than the reference current by a predetermined second value.
-