

# US Patent & Trademark Office

## Patent Public Search | Text View

---

|                      |                    |
|----------------------|--------------------|
| United States Patent | 12407094           |
| Kind Code            | B2                 |
| Date of Patent       | September 02, 2025 |
| Inventor(s)          | Bongard; Frederic  |

---

### Antenna array with independently rotated radiating elements

---

#### Abstract

An antenna array that can include a plurality of antenna cells positioned in a global coordinate system of the antenna array. Each of the plurality of antenna cells has a respective local coordinate system and can include a radiating element having a predetermined angle of rotation defined in the global coordinate system and an antenna port coupled to the radiating element, the antenna port being positioned at a particular set of coordinates in the respective local coordinate system. The particular set of coordinates of the antenna port of each of the plurality of antenna cells can be the same.

---

|                   |                                      |
|-------------------|--------------------------------------|
| <b>Inventors:</b> | <b>Bongard; Frederic (Pully, CH)</b> |
| <b>Applicant:</b> | <b>VIASAT, INC. (Carlsbad, CA)</b>   |
| <b>Family ID:</b> | <b>67470650</b>                      |
| <b>Assignee:</b>  | <b>VIASAT, INC. (Carlsbad, CA)</b>   |
| <b>Appl. No.:</b> | <b>18/318403</b>                     |
| <b>Filed:</b>     | <b>May 16, 2023</b>                  |

#### Prior Publication Data

|                            |                         |
|----------------------------|-------------------------|
| <b>Document Identifier</b> | <b>Publication Date</b> |
| US 20240021983 A1          | Jan. 18, 2024           |

#### Related U.S. Application Data

continuation parent-doc US 17815721 20220728 US 11688938 child-doc US 18318403  
continuation parent-doc US 16901279 20200615 US 11404775 20220802 child-doc US 17815721  
continuation parent-doc US 16728799 20191227 US 10727581 20200728 child-doc US 16901279  
continuation parent-doc US 16118094 20180830 US 10553940 20200204 child-doc US 16728799

---

## Publication Classification

**Int. Cl.:** **H01Q1/52** (20060101); **H01Q1/38** (20060101); **H01Q3/36** (20060101); **H01Q21/00** (20060101); **H04W16/28** (20090101)

**U.S. Cl.:**

**CPC** **H01Q1/523** (20130101); **H01Q1/38** (20130101); **H01Q3/36** (20130101); **H01Q21/0025** (20130101); **H04W16/28** (20130101);

## Field of Classification Search

**CPC:** H01Q (1/523); H01Q (1/38); H01Q (3/36); H01Q (21/0025); H01Q (3/40); H01Q (21/0093); H01Q (21/24); H01Q (21/064); H04W (16/28)

---

## References Cited

### U.S. PATENT DOCUMENTS

| Patent No.   | Issued Date | Patentee Name          | U.S. Cl. | CPC          |
|--------------|-------------|------------------------|----------|--------------|
| 3825932      | 12/1973     | Hockham                | N/A      | N/A          |
| 5966102      | 12/1998     | Runyon                 | N/A      | N/A          |
| 6154183      | 12/1999     | Wolf                   | N/A      | N/A          |
| 6184828      | 12/2000     | Shoki                  | N/A      | N/A          |
| 6317094      | 12/2000     | Wu et al.              | N/A      | N/A          |
| 6377217      | 12/2001     | Zhu et al.             | N/A      | N/A          |
| 6670931      | 12/2002     | O'Connell              | N/A      | N/A          |
| 7307596      | 12/2006     | West                   | N/A      | N/A          |
| 7339520      | 12/2007     | Chang et al.           | N/A      | N/A          |
| 8085209      | 12/2010     | Llorens Del Rio et al. | N/A      | N/A          |
| 8659494      | 12/2013     | Bellows                | N/A      | N/A          |
| 9041074      | 12/2014     | Hong et al.            | N/A      | N/A          |
| 9231311      | 12/2015     | Tiezzi et al.          | N/A      | N/A          |
| 9653801      | 12/2016     | Milroy                 | N/A      | N/A          |
| 9755306      | 12/2016     | Ogilvie                | N/A      | N/A          |
| 9905921      | 12/2017     | Sazegar et al.         | N/A      | N/A          |
| 10553940     | 12/2019     | Bongard                | N/A      | H01Q 1/523   |
| 10727581     | 12/2019     | Bongard                | N/A      | H01Q 3/36    |
| 11404775     | 12/2021     | Bongard                | N/A      | H01Q 21/0025 |
| 11688938     | 12/2022     | Bongard                | 343/893  | H01Q 1/523   |
| 2003/0008654 | 12/2002     | Senarath et al.        | N/A      | N/A          |
| 2003/0095070 | 12/2002     | O'Connell              | N/A      | N/A          |
| 2004/0239565 | 12/2003     | Brachat                | N/A      | N/A          |
| 2005/0128028 | 12/2004     | Sanchez et al.         | N/A      | N/A          |
| 2009/0096702 | 12/2008     | Vassilakis et al.      | N/A      | N/A          |
| 2011/0102263 | 12/2010     | Angeletti              | N/A      | N/A          |
| 2013/0181880 | 12/2012     | Shen et al.            | N/A      | N/A          |
| 2015/0022421 | 12/2014     | Vigano et al.          | N/A      | N/A          |
| 2016/0054439 | 12/2015     | Brookner et al.        | N/A      | N/A          |

|              |         |                  |     |            |
|--------------|---------|------------------|-----|------------|
| 2016/0294065 | 12/2015 | Lindmark         | N/A | N/A        |
| 2017/0040710 | 12/2016 | Woollen          | N/A | N/A        |
| 2017/0077610 | 12/2016 | Bongard et al.   | N/A | N/A        |
| 2017/0179595 | 12/2016 | Ogawa            | N/A | H01Q 1/246 |
| 2017/0229774 | 12/2016 | Schuehler et al. | N/A | N/A        |
| 2023/0019123 | 12/2022 | Bongard          | N/A | N/A        |

#### **FOREIGN PATENT DOCUMENTS**

| <b>Patent No.</b> | <b>Application Date</b> | <b>Country</b> | <b>CPC</b> |
|-------------------|-------------------------|----------------|------------|
| 105655723         | 12/2015                 | CN             | N/A        |
| 108199135         | 12/2017                 | CN             | N/A        |
| 329079            | 12/1993                 | EP             | N/A        |
| 2159878           | 12/2009                 | EP             | N/A        |
| 2337152           | 12/2016                 | EP             | N/A        |
| 2823532           | 12/2017                 | EP             | N/A        |
| 3220481           | 12/2019                 | EP             | N/A        |
| 3032648           | 12/2020                 | EP             | N/A        |
| 1992-038001       | 12/1991                 | JP             | N/A        |
| H05121935         | 12/1992                 | JP             | N/A        |
| 2004-096286       | 12/2003                 | JP             | N/A        |
| 2017153094        | 12/2016                 | JP             | N/A        |
| 2000635           | 12/1992                 | RU             | N/A        |
| 8164              | 12/1997                 | RU             | N/A        |
| 2003007423        | 12/2002                 | WO             | N/A        |
| 2013134585        | 12/2012                 | WO             | N/A        |

#### **OTHER PUBLICATIONS**

Afonin, et al., “Antenna Array of Patch Radiators with Controlled Polarization”, 2017 Radiation and Scattering of Electromagnetic Waves RSEMW, Jun. 26-30, 2017 Divnomorskoe, Russia, pp. 55-57. cited by applicant

Ghasemi, et al.: “Beam Steering Slotted Waveguide Antenna Using Rotating Dielectric Slabs for Meteorology Radar”, found at <https://arxiv.org/ftp/arxiv/papers/1703/1703.00964.pdf> on Sep. 25, 2017. cited by applicant

International Search Report from corresponding PCT/US2019/040175 mailed Oct. 14, 2019. All art has been previously cited. cited by applicant

Natera, et al.: “New Antenna Array Architectures for Satellite Communications”; INTECH Open Access Publisher, 2011. cited by applicant

Wang, et al.: “Wideband Circularly Polarized Square Slot Array Fed by Slotted Waveguide for Satellite Communication”; found on the internet Aug. 30, 2018 at:

<http://www.jpier.org/PIERL/pierl61/17.16030603.pdf>; Progress In Electromagnetics Research Letters, vol. 61, 111-118, 2016. cited by applicant

*Primary Examiner:* Lotter; David E

*Attorney, Agent or Firm:* F. CHAU & ASSOCIATES, LLC

#### **Background/Summary**

RELATED APPLICATIONS (1) This application is a continuation of U.S. application Ser. No. 17/815,721, filed on Jul. 28, 2022, which is a continuation of U.S. application Ser. No. 16/901,279, filed Jun. 15, 2020; which is a continuation of U.S. application Ser. No. 16/728,799 filed on Dec. 27, 2019 (now U.S. Pat. No. 10,727,581) and entitled Antenna Array with Independently Rotated Radiating Elements; which is a continuation application of U.S. application Ser. No. 16/118,094 filed on Aug. 30, 2018 (now U.S. Pat. No. 10,553,940), the entirety of each is incorporated herein by reference.

## TECHNICAL FIELD

(1) This relates generally to antennas and more particularly to an antenna array with rotated radiating elements.

## BACKGROUND

(2) An antenna array (or array antenna) is a set of multiple radiating elements that work together as a single antenna to transmit or receive radio waves. The individual radiating elements (often referred to simply as “elements”) can be connected to a receiver and/or transmitter by circuitry that applies appropriate amplitude and/or phase adjustment of signals received and/or transmitted by the radiating elements. When used for transmitting, the radio waves radiated by each individual radiating element combine and superpose with each other, adding together (interfering constructively) to enhance the power radiated in desired directions, and cancelling (interfering destructively) to reduce the power radiated in other directions. Similarly, when used for receiving, the separate received signals from the individual radiating elements are combined with the appropriate amplitude and/or phase relationship to enhance signals received from the desired directions and cancel signals from undesired directions.

(3) An antenna array can achieve an elevated gain (directivity) with a narrower beam of radio waves, than can be achieved by a single antenna. In general, the larger the number of individual antenna elements used, the higher the gain and the narrower the beam. Some antenna arrays (such as phased array radars) can be composed of thousands of individual antennas. Arrays can be used to achieve higher gain (which increases communication reliability), to cancel interference from specific directions, to steer the radio beam electronically to point in different directions and/or for radio direction finding.

## SUMMARY

(4) One example relates to an antenna array that can include a plurality of antenna cells positioned in a global coordinate system of the antenna array. Each of the plurality of antenna cells has a respective local coordinate system and can include a radiating element having a predetermined angle of rotation defined in the global coordinate system and an antenna port coupled to the radiating element, the antenna port being positioned at a particular set of coordinates in the respective local coordinate system. The particular set of coordinates of the antenna port of each of the plurality of antenna cells can be the same. Additionally, the predetermined angle of rotation of the radiating element of a first antenna cell of the plurality of antenna cells is a first rotation angle in the global coordinate system. The predetermined angle of rotation of the radiating element of a second antenna cell of the plurality of antenna cells can be a second rotation angle in the global coordinate system. The second rotation angle can be different than the first rotation angle.

(5) Another example relates to a multi-layer printed circuit board (PCB) that can include a beam-forming layer having a plurality of traces that form a beam-forming network (BFN), wherein the beam-forming network is coupled to a plurality of antenna ports forming vias extending away from the beam-forming network (BFN). The BFN can include a plurality of combiners/dividers that convert between an input signal and a plurality of sub-signals. Each of the plurality of sub-signals can have an equal power and an array of phases. Each of the plurality of sub-signals can be communicated to an antenna port of the plurality of antenna ports. The multi-layer PCB can also include a plurality of antenna cells being positioned in a global coordinate system of the multi-

layered PCB to form a regular tiling pattern. Each of the plurality of antenna cells can have a respective local coordinate system. Each antenna cell can include a radiating layer comprising a radiating element that has a predetermined angle of rotation in the global coordinate system. Each antenna cell can also include a feedline layer that can have a feedline that couples a corresponding antenna port of the plurality of antenna ports to the radiating element. Each antenna port can intersect with the feedline layer at a particular set of coordinates in the respective local coordinate system. The particular set of coordinates for each of the plurality of antenna cells can be the same. Additionally, the predetermined angle of rotation of the radiating element of a first antenna cell of the plurality of antenna cells can be a first rotation angle in the global coordinate system. The predetermined angle of rotation of the radiating element of a second antenna cell of the plurality of antenna cells can be a second rotation angle in the global coordinate system, the second rotation angle can be different than the first rotation angle.

---

## Description

### BRIEF DESCRIPTION OF THE DRAWINGS

- (1) FIG. 1 illustrates a plan view of an antenna array with a plurality of antenna cells.
- (2) FIG. 2 illustrates a plan view of a beam-forming network (BFN) in communication with the antenna array of FIG. 1.
- (3) FIG. 3 illustrates an extended plan view of a BFN.
- (4) FIG. 4 illustrates an example of a BFN array.
- (5) FIG. 5 illustrates plan view of another antenna array with a plurality of antenna cells.
- (6) FIG. 6 illustrates a plan view of another BFN in communication with the antenna array of FIG. 5.
- (7) FIG. 7 illustrates another extended plan view of another BFN.
- (8) FIG. 8 illustrates plan view of yet another antenna array with a plurality of antenna cells.
- (9) FIG. 9 illustrates a plan view of yet another BFN in communication with the antenna array of FIG. 8.
- (10) FIG. 10 illustrates an extended plan view of yet another BFN.
- (11) FIG. 11 illustrates a stack-up view of a multi-layer printed circuit board for implementing a system with an antenna array and a BFN.
- (12) FIG. 12 illustrates a block diagram of a system that implements an antenna array and a BFN.

### DETAILED DESCRIPTION

(13) This disclosure describes an antenna array with a plurality of antenna cells positioned in a global coordinate system, and each antenna cell has its own respective local coordinate system. Each antenna cell in the antenna array can have a radiating element (e.g., a slot-coupled patch antenna) with a predetermined angle of rotation in the global coordinate system. Moreover, each antenna cell can have an antenna port that can be coupled to the corresponding radiating element. The antenna port can be positioned at a particular set of coordinates in the respective local coordinate system. In some examples, this particular set of coordinates can be the same for each respective local coordinate system of the antenna cells. In other words, in some examples, the angle of rotation of each antenna cell in the plurality of antenna cells in the global coordinate system does not change the position of the antenna port in each respective local coordinate system.

(14) The antenna port of each of the plurality of antenna cells can be coupled to a beam-forming network (BFN) through an integrated circuit (IC) chip, as explained herein. By positioning each antenna port in the same coordinates in each local coordinate system, the design of the BFN can be simplified. In particular, the positions of the antenna ports can be regular, such that the BFN can be designed systematically and independent of the angle of rotation of the radiating elements of the antenna cells. Additionally, rotation of the antenna elements can improve polarization purity. In

other words, rotation of the antenna elements increases the ratio of a desired polarization component relative to an undesired component.

(15) FIG. 1 illustrates a plan view of an example of an antenna array **100** with a plurality of antenna cells **102**. The antenna array **100** can be implemented, for example, as a phased array antenna. The antenna cells **102** can be arranged in a regular tiling pattern. The antenna array **100** can be formed on a top layer and/or region of a multi-layer printed circuit board (PCB), which can alternatively be referred to as a multi-layer printed wire board (PWB). For purposes of simplification of explanation, some layers are omitted and/or illustrated as being transparent. In the present example, there are twelve (12) antenna cells **102**, but in other examples, there can be more or less antenna cells **102**. In fact, in some examples, there can be one-hundred, one-thousand or more antenna cells **102**. Each of the twelve (12) antenna cells are labeled A-L. Accordingly, a given antenna cell **102** can be identified and referenced specifically. For instance, a first antenna cell **102** can be referenced as “antenna cell A **102**”, and an eighth antenna cell can be referenced as “antenna cell H **102**”. The antenna cells B-L **102** can also be referenced in this manner.

(16) In the example illustrated, each antenna cell **102** has a hexagonal shape. In other examples, other shapes can be employed to implement the plurality of antenna cells **102**, including shapes such as squares, rectangles or rhombuses that provide regular tiling.

(17) The antenna array **100** includes a global coordinate system **104** that defines a global position for the entire antenna array **100**. More particularly, the global coordinate system **104** identifies a relative position of each of the plurality of antenna cells **102**. Each of the antenna cells **102** can have a predetermined angle of rotation in the global coordinate system **104**. Additionally, each of the antenna cells **102** can include a radiating element **106** with a predetermined angle of rotation in the global coordinate system **104** that may be different (or the same) as the angle of rotation of the antenna cell **102** in the global coordinate system **104**. In other words, the angle of rotation in the global coordinate system **104** of the radiating element **106** in a given antenna cell **102** can be selected independently of the angle of rotation in the global coordinate system **104** of the antenna cell **102**.

(18) Each of the plurality of the antenna cell **102** can have a predetermined angle of rotation in the global coordinate system **104**. Additionally, each antenna cell **102** can include a local coordinate system. In the example illustrated in FIG. 1, an origin of each local coordinate system is positioned at a given vertex of the corresponding antenna cell **102**. As an example, the local coordinate system for antenna cell A **102** is labeled as XA, YA to denote respective X and Y axes for the local coordinate system of the antenna cell A **102**. Antenna cells B-H are labeled in a similar manner.

(19) As described herein, each radiating element **106** includes a plurality of constituent structural components. In particular in the antenna array **100**, each radiating element **106** can include N number of slot elements **110**, where N is an integer greater than or equal to one (1) and a metallic patch radiator **114**. Each slot element **110** can have an ‘H’ or dumbbell shape. Moreover, although in the illustrated and described example the radiating element **106** includes the N number of slot elements **110** and the metallic patch radiator **114**, other types of radiators for the radiating element **106** are possible. In the example illustrated, there are two (2) slot elements **110**, which can be individually referenced with a subscript number. More particularly, in the illustrated example, each radiating element includes a first slot element **110.sub.1** and a second slot element **110.sub.2** that are orthogonally orientated with respect to each other. In other words, the first slot element **110.sub.1** can have a predetermined angle of rotation in the global coordinate system **104** and the second slot element **110.sub.2** can be rotated by 90 degrees relative to the first slot element **110.sub.1**. Thus, collectively, the first slot element **110.sub.1** and the second slot antenna **110.sub.2** can have a predetermined angle of rotation in the global coordinate system **104** that can define the predetermined angle of rotation of the radiating element **106** for the antenna cell **102**. Additionally, in some examples, there can be more or less slot elements **110** than the first slot element **110.sub.1** and the second slot element **110.sub.2**. The angle of rotation in the global coordinate system **104**

can be defined relative to a particular structural element or a set of elements of a given antenna cell **102**, such as, but not limited to a port **118** (or multiple ports **118**). Similarly, in such a situation, the same particular structural element or set of element in other antenna cells **102** can be employed to define the angle of rotation of the other antenna cells **102**. In other words, the angle of rotation in the global coordinate system **102** is defined in the same manner across each of the A-L antenna cells **102**.

(20) In some examples, the angle of rotation in the global coordinate system **104** for each radiating element **106** can be, for example one of 0 degrees,  $\pm 30$  degrees,  $\pm 90$  degrees and  $\pm 150$  degrees. In other examples, other angles of rotation in the global coordinate system **104** may be used. Moreover, the pattern of the angle of rotation of the radiating elements **106** of antenna cells **102** can vary based on desired operational characteristics of the antenna array **100**. For example, it can be desirable to select a pattern for the antenna elements **106** that provides a high degree of polarization purity in a main beam for scanning in multiple directions and maintaining side lobes of a radiation pattern below a certain level.

(21) The first slot element **110.sub.1** and the second slot element **110.sub.2** can be designed to communicate signals without substantially affecting the relative phase difference between signals of the first slot element **110.sub.1** and the second slot element **110.sub.2**. For example, each radiating element **106** of each respective antenna cell **102** can be designed to communicate circularly polarized signals. For example, the first slot element **110.sub.1** of the radiating element **106** can be designed to communicate signals with a first linear polarization and the second slot element **110.sub.2** of the radiating element **106** can be designed to communicate signals with a second polarization. As one example, the first polarization can be offset relative to the second polarization. Additionally, as noted, there are examples where there is only one slot element **110** for each radiating element **106** and/or other types of radiators are employed for the radiating element **106**. In these situations, the radiating element **106** can also be designed to communicate signals circular polarization or with other polarizations, such as linear or elliptical polarization.

(22) Moreover, as noted, the radiating element **106** of each antenna cell **102** can include a metallic patch radiator **114** that can overlay the first slot element **110.sub.1** and the second slot element **110.sub.2**. The metallic patch radiator **114** can overlay a center of the antenna cells **102**. In some examples, the metallic patch radiator **114** can be formed on an upper surface of the antenna array **100**. In such a situation, the metallic patch radiator **114** can be formed by etching away a portion a (top) thin metal layer, with the un-etched portion forming the metallic patch radiator **114**.

(23) For purposes of simplification of explanation the terms “overlay”, “overlying”, “underlay” and “underlying” (and derivatives) are employed throughout this disclosure to denote a relative position of two adjacent surfaces in a selected orientation. Additionally, the terms “top” and “bottom” are employed throughout this disclosure to denote opposing surfaces in the selected orientation. Similarly, the terms “upper” and “lower” are employed to denote relative positions in the selected orientation. In fact, the examples used throughout this disclosure denote one selected orientation. However, in the described examples, the selected orientation is arbitrary, and other orientations are possible (e.g., upside down, rotated by 90 degrees, etc.) within the scope of the present disclosure.

(24) Each antenna cell **102** can include N number of ports **118**. Each port **118** can electrically couple a BFN to a corresponding slot element **110**. Thus, in the illustrated example, each antenna cell **102** can include a first port **118.sub.1** and a second port **118.sub.2**. Each antenna cell **102** can also include N number of feedlines **122** formed in a feedline layer (conductive traces) that intersects with a corresponding port **118** at a particular set of coordinates in the corresponding local coordinate system. Moreover, each feedline **122** can connect each slot element **110** with a corresponding port **118**. More particularly, in the example illustrated in FIG. 1, a first feedline **122.sub.1** (a conductive trace) can connect a first port **118.sub.1** with a first slot element **110.sub.1**. Similarly, a second feedline **122.sub.2** (a conductive trace) can connect a second port **118.sub.2** and

a second slot element **110.sub.2**. Each feedline **122** in a given antenna cell **102** can have the same length. Thus, the first feedline **122.sub.1** and the second feedline **122.sub.2** of the antenna cell **A 102** can be the same length. In some examples, the feedlines **122** of each different antenna cells **102** can have the same lengths. To offset (counteract) the effects of rotation in each antenna cell **102**, additional phase adjustment (e.g., through subsequent or prior signal conditioning, as described herein) can be applied to signals communicated by particular antenna cells **102**. As an example, antenna cell **A 102** and antenna cell **D 102** can have feedlines **122** that are the same length, but signals communicated with antenna cell **A 102** and antenna cell **D 102** have different phases. The phase adjustment can be employed to offset for these different phases.

(25) In some examples, each port **118** can be positioned near a perimeter (e.g., near a vertex) of the corresponding antenna cell **102**. Accordingly, in the plan view illustrated by FIG. 1, each port **118** is located between the corresponding radiating element **106** and the perimeter of the corresponding antenna cell **102**. In the example illustrated by the antenna array **100** of FIG. 1, the first port **118.sub.1** and the second port **118.sub.2** are positioned near vertices of the antenna cell **102**. Additionally, the first port **118.sub.1** and the second port **118.sub.2** are separated by the given (single) vertex that includes the origin of the local coordinate system. Accordingly, in some examples, each set of ports **118** for a given antenna cell **102** can be positioned at a same set of local coordinates. In other words, the first port **118.sub.1** for each antenna cell **102** can be positioned at the same set of local coordinates in each of the antenna cells **A-H 102**. Similarly, the second port **118.sub.2** for each antenna cell **102** can be positioned at the same set of local coordinates of each of the antenna cells **A-L**. Alternatively, in other examples, the position of each of the **N** number of ports can vary in the local coordinates of each antenna cell **102**.

(26) Each of the **N** number of ports **118** in each antenna cell **102** can be formed as a via (also referred to as a plated through hole) that extends through one or more layers to IC chips and/or the BFN, depending on the design of the BFN. In this manner, each of the illustrated ports **118** (including the first port **118.sub.1** and the second port **118.sub.2**) of each antenna cell **102** can represent a terminal of the via. In some examples, each port **118** can be considered as a long transition through the whole multi-layer PCB, on which the antenna array **100** can be formed. Additionally or alternatively, the **N** number of ports **118** can be other types of interfaces for communicating signals between the BFN and each antenna cell **102**. Positioning each port **118** near a perimeter of the antenna cell **102** and away from the radiating element **106** of the antenna cell **102** (positioned near a center) can reduce electromagnetic coupling. In some examples, each port **118** (or some subset thereof) can be environed by a plurality of isolation vias **130** positioned equidistant to a corresponding port **118**, which can alternatively be referred to as shielding vias. In other examples, the plurality of isolation vias **130** can be positioned at differing distances to a corresponding port **118**. The isolation vias **130** can mimic co-axial shielding for the port **118**. For purposes of simplification of illustration, only some of the isolation vias **130** are labeled. The isolation vias **130** can extend fully or partially between the plurality of antenna cells **102** of the antenna array **100** and the BFN. The antenna array **100** can be designed such that each port **118** is in close proximity to five (5) isolation vias **130**.

(27) As illustrated, each port **118** of a given antenna cell **102** can be positioned near two other ports **118** on two other antenna cells **102**. Additionally, each of the isolation vias **130** can be located near a vertex and/or on a perimeter of an antenna cell **102**. In this manner, the same isolation via **130** can provide shielding for multiple ports **118**. For example, an isolation via **130** located at a vertex common to antenna cells **B, D and E 102** can concurrently provide shielding for the first port **118.sub.1** of antenna cells **B, D and E 102**. Accordingly, by rotating each antenna cell **102** in the global coordinate system **104** in the manner illustrated, the total number of isolation vias **130** needed to provide shielding on five (5) sides of each port **118** can be reduced.

(28) As noted, each antenna cell **102** can have an angle of rotation in the global coordinate system **104**. In some examples, a given antenna cell **102** can be rotated relative to another antenna cell **102**.

For instance, antenna cell B **102** can be rotated in the global coordinate system **104** relative to antenna cell A **102** by 120 degrees.

(29) Additionally, although the radiating elements **106** of each antenna cell **102** have an angle of rotation defined in the global coordinate system **104**, each radiating element **106** can also have a local angle of rotation defined in the corresponding local coordinate system. In such a situation, the local angle of rotation for a radiating element **106** of a given antenna cell **102** can be offset from the local angle of rotation for a radiating element **106** of another antenna cell **102**. For example, the local angle of rotation of the radiating element **106** in the local coordinate system of the antenna cell B **102** can be offset from the local angle of rotation of the radiating element **106** in the local coordinate system of the antenna cell A **102** by 120 degrees.

(30) Further still, in a given example, a given antenna cell **102** can have an angle of rotation in the global coordinate system **104** that is different than the angle of rotation in the global coordinate system **104** for another antenna cell **102**. Additionally, in the given example, the radiating elements **106** of the given and the other antenna cells **102** can have the same angle of rotation in the global coordinate system **104**. For example, antenna cell D **102** and antenna cell G **102** can have different angles of rotation in the global coordinate system **104**. However, the radiating element **106** of the antenna cells D and G **102** can have the same angle of rotation in the global coordinate system **104** since the radiating element **106** of antenna cells D and G **102** can have different angles of rotation in the respective local coordinate systems. As discussed herein, to account for the different angles of rotation of the antenna cells **102** in the global coordinate system **104**, phases of signals communicated by the radiating elements **106** of the antenna cells can be adjusted.

(31) In some examples, each antenna cell **102** can be a member of a group of antenna cells **102**. In some examples, a given group of antenna cells **102** can share an intersecting point (e.g., such as a common vertex in examples where the antenna cells **102** are polygons). Accordingly, in the example illustrated in FIG. 1, a first group of antenna cells could be formed with antenna cells A, B and C **102**. Additionally, a second group of antenna cells **102** can be formed with antenna cells D, F and G **102**. The antenna array **100** can be designed such that the rotation angle of each radiating element **106** in a given group of antenna cells **102** defines a group rotation pattern. As used herein, the term “group rotation pattern” denotes a specific set of rotations of the radiating element **106** for each member of the group. As one example, if the radiating element **106** of the antenna cell A **102** has a rotation angle of 0 degrees, the antenna cell B **102** has a rotation angle of 30 degrees and the antenna cell C **102** has an angle of rotation of -30 degrees, the combined set of 0 degrees, 30 degrees and -30 degrees in the relative locations of cells A, B and C **102** defines the group rotation pattern. In some examples, the antenna array **100** can be designed such that adjacent groups of antenna cells have different group rotation patterns. Additionally, in some examples, it can be desirable to avoid repeating the same angle of rotation of the radiating element **106** for a group of antenna cells **102** throughout the antenna array **100** to avoid elevated side lobes for the overall radiation pattern of the antenna array **100**.

(32) In operation, the antenna array **100** can communicate signals between free space and the BFN. In particular, in a receiving mode, an electromagnetic (EM) signal transmitted in free space can be provided to the N number of slot elements **110** by the corresponding metallic patch radiator **114**. The N number of slot elements **110** on the corresponding antenna cell **102** can convert a radiated EM signal into a guided EM signal. Each of the N number of feedlines **122** can provide the electrical signals to the corresponding port **118**. Each port **118** can provide the electrical signal to an IC chip coupled to the BFN. In some examples, the IC chip can be an integrated component of the BFN. In other examples, the IC chip and the BFN can be separate, but coupled components. The IC chip can adjust (e.g., combine, amplify and/or phase adjust) the electrical signal and provide an adjusted electrical signal to the BFN. The BFN can combine the adjusted electrical signal to form a received beam signal and provide the received beam signal to an external system for further processing and/or decoding.

(33) In a transmitting mode, an electrical signal can be provided from the BFN to the IC chips. The IC chips can adjust the signals and provide the adjusted signals to the N number of ports **118** at each of the antenna cells **102**. The electrical signals can be provided to the corresponding slot elements **110** of the antenna cells **102**. The slot elements **110** can convert a guided EM signal into a radiated EM signal that is transmitted to the corresponding metallic patch radiator **114** of each antenna cell **102**. The patch antennas **114** can transmit the EM signal into free space.

(34) In some examples, the antenna array **100** can be designed to operate exclusively in either the receiving mode or the transmitting mode. In other examples, the antenna array **100** can operate in a half-duplexing mode, such that the antenna array **100** can operate in the receiving mode and the transmitting mode periodically and/or asynchronously. In still other examples, the antenna array **100** can operate in a full-duplexing mode, such that the antenna array **100** can operate in the receiving mode and the transmitting mode concurrently.

(35) By implementing the antenna array **100**, the radiating elements **106** of each antenna cell **102** can be selected to have an angle of rotation in the global coordinate system **104** that is independent on the location of the N number of ports **118** at each antenna cell **102**. Stated differently, the N number of slot elements **110** for each antenna cell **102** (namely, the first slot element **110.sub.1** and the second slot element **110.sub.2**) can be rotated in the global coordinate system **104** without necessitating a change in the location of the corresponding N number of ports **118**, namely the first port **118.sub.1** and the second port **118.sub.2**. Rather, each antenna cell **102** can be designed such that the location of the ports **118** varies based on the angle of rotation of the entire individual antenna cell **102**, and that the angle of rotation of the slot elements **110** can vary independently of the angle of rotation of the antenna cell **102**. Accordingly, the antenna array **100** can be designed such that the location of the ports **118** occurs at regular, predetermined positions in the global coordinate system **104**. In this manner, as described herein, the BFN underlying the antenna array **100** can be designed independently from the antenna array **100**. In fact, as explained in detail, the BFN underlying the antenna array **100** can have a systematic design.

(36) FIG. 2 illustrates a plan view of an example of a BFN **200** that can be employed to adjust signals communicated with the antenna array **100** of FIG. 1. The BFN **200** can be formed on an interior layer (e.g., a BFN layer) of the multi-layer PCB employed for the antenna array **100**. The BFN layer can include a plurality of traces (conductive traces). For purposes of simplification of explanation, the same reference numbers are employed in FIGS. 1 and 2 to denote the same structure. The BFN **200** can be partitioned into a plurality of BFN cells **202** that are each rotated in the global coordinate system **104**. As noted, the BFN **200** can underlay the antenna array **100** of FIG. 1. Moreover, each BFN cell **202** can have the same size and shape (e.g., a hexagon) as an overlaying antenna cell **102**. Accordingly, the BFN cells **202** are labeled A-L to correspond to the overlaying antenna cells **102**. Thus, BFN cell A **202** can underlay antenna cell A **102**. Each BFN cell **202** can have the same local coordinate system as the corresponding antenna cell **102**.

Accordingly, BFN cell A **202** can have the same local coordinate system as the antenna cell A **102**.

(37) Each BFN cell **202** can include N number of ports **118**. In the example illustrated by the BFN **200**, each BFN cell **202** includes a first port **118.sub.1** and a second port **118.sub.2**. Each port **118** can be representative of a terminal of a via to a port illustrated in the antenna array **100**. For example, the first port **118.sub.1** of BFN cell A **202** can represent a terminal end of the via corresponding to the first port **118.sub.1** of the antenna cell A **102**. Each of the N number of ports **118** can be at a same set of coordinates in each respective local coordinate system. Each of the N number of ports **118** can extend away from the BFN **200** and toward the antenna array **100**. As explained with respect to the antenna array **100**, each of the N number of ports **118** can be at a same set of coordinates in each local coordinate system.

(38) Each of the N number of ports **118** can be environed by a plurality of isolation vias **130**, only some of which are labeled. The isolation vias **130** can correspond to the isolation vias **130** of FIG. 1. In the example illustrated, there are five (5) isolation vias in close proximity to each port **118**.

However, in other examples, there can be more or less isolation vias **130**. Moreover, the isolation vias **130** can be shared between ports **118** on different BFN cells **202**, thereby reducing the overall number of isolation vias **130** needed to provide sufficient shielding for the ports **118**. Additionally, in some examples, some of the isolation vias **130** can extend only partially between the BFN **200** and the antenna array **100** of FIG. 1.

(39) The BFN **200** can include an input/output (I/O) port **206** that can be coupled to an external system or to another BFN of additional antenna cells in a manner described herein. The I/O port **206** can be coupled to a first stage combiner/divider **208**, which can be coupled to two (2) second stage combiners/dividers **210**. In this manner, the first stage combiner/divider **208** and the second stage combiners/dividers **210** have a cascade (hierarchical) relationship. In other words, the first stage combiners/dividers **208** can operate as a first stage of the BFN **200**, and the second beam forming stage combiners/dividers **210** can operate as second beam forming stage of the BFN **200**. Each of the second stage combiners/dividers **210** can be coupled to two (2) 1-to-3 combiners/dividers **212**, which can operate as a third beam forming stage of the BFN **200**. Each 1-to-3 combiner/divider **212** can be positioned at an intersection of three (3) BFN cells **202**.

(40) The second stage combiners/dividers **210** can be symmetrically arranged relative to the first stage combiners/dividers **208**. The second stage combiners/dividers **210** can be fabricated on different layers of the BFN **200** than the BFN cells **202**. For purposes of simplification of illustration, different line weights and/or patterns are employed to denote different layers of the BFN. A set of BFN cells **202**, 1-to-3 combiner/divider **212** and a second stage divider **210** can define a beam forming stage that has a local coordinate system. In this manner, each beam forming stage (a combination of BFN cells **202**, 1-to-3 combiner/divider **212** and a second stage divider **210**) can have the same geometric shape in the local coordinate system. Moreover, the beam forming stages can be rotated in the global coordinate system **104** to facilitate the systematic design of the BFN **200**. Furthermore, the systematic nature of the beam forming stages of the BFN **200** having the same geometric shape can also be present at additional stages across a sub-array, such as shown in FIG. 3. In other words, in FIG. 3, the geometric shape of the first three beam forming stages have the same geometric shape as other instances of the first three beam forming stages in an array. Thus, taken one step further in some examples, the geometric shape of a first four stages can have the same geometric shape as other first four stages in the array. Accordingly, each instance of the beam forming stage has the same geometric shape as another instance of the beam forming stage of the same stage. In other words, a given beam forming stage of the BFN **200** has the same geometric shape as another beam forming stage of the BFN **200** if the given and the other beam forming stages are the same stage (e.g., both the given and the other stages are first stages, second stages, etc.).

(41) As used herein, the concept of each beam forming stage having the same geometric shape indices that the beam forming stage has the same shape with mirroring and/or rotation in the global coordinate system, such as illustrated in FIG. 3. Moreover, two beam forming stages can also be considered to have the same geometric shape if the two beam forming stages are symmetric about one or more lines of symmetry. Still further, two beam forming stages are considered to have the same geometric shape if the two beam forming stages are substantially identical without mirroring and/or rotation.

(42) Each BFN cell **202** can be coupled to an integrated circuit (IC) chip **220** (or multiple IC chips) and/or other circuits that can adjust signals. The IC chip **220** can be mounted on a bottom of the multi-layer PCB that implements the BFN. Thus, each IC chip **220** can underlay the BFN **200**. Each IC chip **220** can be coupled to a 1-to-3 combiner/divider **212** and to the N number of ports **118** of the BFN cell **202**. As an example, the first port **118.sub.1** and the second port **118.sub.2** of the BFN cell A **102** can be coupled to the IC chip **220** of the BFN cell A **202**, which is coupled to the 1-to-3 combiner/divider **212** positioned between BFN cell A **202**, BFN cell B **202** and BFN cell C **202**. Each IC chip **220** can adjust electrical signals. Such adjustment can include amplifying,

phase adjusting, combining and/or dividing signals. In some examples, the IC chip **220** of three different BFN cells **202**, such as BFN cells A, B and C **202** can adjust signal communicated with the corresponding 1-to-3 combiner **212** by an amount to compensate for rotation of radiating elements, such as the radiating elements **106** of FIG. **1**.

(43) The combiners/dividers described herein can execute one or both a dividing operation and a combining operation that convert between an input/output signal and a plurality of sub-signals. In the examples described herein, each dividing operation executed can divide an input signal into a plurality of sub-signals that have equal power and an array of phases. Conversely, in the examples described herein, in a combining operation, multiple sub-signals with an array of phases can be combined into a single combined signal.

(44) In the transmitting mode, the first stage combiners/divider **208** can be designed to divide (e.g., equally or unequally, in-phase or out-of-phase) a signal input to the I/O port **206** into sub-signals that are provided to the second stage combiners/dividers **210**. Similarly, in the transmit mode, each second stage combiner/divider **210** can divide (e.g., equally or unequally, in-phase or out-of-phase) a signal received from the first stage combiner/divider **208** into two (2) sub-signals that are coupled to 1-to-3 combiners/dividers **212**. Each 1-to-3 combiner/divider can divide (e.g., equally or unequally, in-phase or out-of-phase) the signal to three (3) sub-signals that are each provided to an IC chip **220** corresponding to three (3) different BFN cells **202**. For example, the 1-to-3 combiner/divider **212** positioned at the intersection of BFN cells A, B and C **202** can provide a signal to the IC chip **220** of BFN cells A, B and C **202**.

(45) Continuing in the transmitting mode, the IC chip **220** of each BFN cell **202** can be designed/programmed to adjust (amplify, phase adjust and/or divide) the signal into N number of signals that are provided to the N number of ports **118**. For example, the IC chip **220** of the BFN cell **202** can be designed to amplify and divide the signal from the 1-to-3 combiner/divider **212** into two (2) sub-signals that are provided to the first port **118.sub.1** and the second port **118.sub.2** of the BFN cell A **202**. The signals can then be transmitted in the manner described with respect to FIG. **1**.

(46) In the receiving mode, signals received at each of the N number of ports **118** in each of the BFN cells **202** can be combined and adjusted (amplified and/or phase adjusted) by the corresponding IC chip **220** and provided to a corresponding 1-to-3 combiner/divider **212**. As an example, the IC chip **220** corresponding to BFN cells A, B and C **202** can each provide an adjusted signal to the 1-to-3 combiner/divider **212** at the intersection of the BFN cells A, B, and C **202**.

(47) Continuing in the receiving mode, each of the 1-to-3 combiners/dividers **212** can combine adjusted sub-signals and provide a combined signal to a corresponding second stage combiner/divider **210**. In turn, the second stage combiners/dividers **212** can again combine the sub-signals and provide the combined signal to the first stage combiner/divider **208**. The first stage combiner/divider **208** can combine the sub-signals, and output the combined signal at the I/O port **206**.

(48) Similar to the antenna array **100** of FIG. **1**, the BFN **200** can be designed to operate exclusively in the transmitting mode or the receiving mode. Additionally, the BFN **200** can be designed to switch periodically and/or asynchronously between the transmitting mode and the receiving mode. Still further, in some examples, the BFN **200** can operate in the transmitting mode and the receiving mode concurrently.

(49) As illustrated with the antenna array **100** of FIG. **1** and the BFN **200** of FIG. **2**, the antenna cells **102** and the BFN cells **202** can communicate through the N number of ports **118**. Moreover, the antenna array **100** can be designed such that the radiating elements **106** can be rotated independently from the location of the ports **118**. Accordingly, the angle of rotation of the radiating elements **106** does not necessarily impact the physical layout of the BFN **200**. Therefore, the BFN **200** and the antenna array **100** can be designed independently based on predetermined positions of each of the N number of ports **118** for each BFN cell **202** and each antenna cell **102**. Thus, the

overall design of the BFN **200** and the antenna array **100** can be simplified. In fact, the systematic design of the BFN **200** further demonstrates possibilities of a BFN when the BFN **200** is matched with the antenna array **100** of FIG. **1** (or a variant thereof). In particular, a designer of the BFN can be unburdened with concern for the individual placement of the ports **118**. Instead, the ports **118** appear in regular, predictable positions that are readily accommodated by the various types of the antenna cells **102** of the antenna array **100**.

(50) In some examples, the BFN **200** can be designed with systematically symmetric modules that are scalable to accommodate nearly any number of levels of hierarchy. In particular, although the BFN **200** is described with two (2) stages of combiners/dividers, namely the first stage combiner/divider **208** and the second stage combiners/dividers **208**, the BFN **200** illustrated can be employed as module or circuit to implement a larger scale BFN, including the BFN **300** illustrated in FIG. **3**.

(51) In the BFN **300**, four (4) instances of the BFN **200** of FIG. **2** are connected in a cascade (hierarchical) arrangement. In particular, an I/O port **302** is coupled to a first stage combiner/divider **304**, which is coupled to two (2) second stage combiners/dividers **306**. Each second stage combiner/divider **306** can be coupled to a port **206** of an instance of the BFN **200** (a module of the BFN **300**). In this manner, the four (4) instances of the BFN **200** are connected together in a cascade arrangement. Further, in other examples, multiple instances of the BFN **300** can be coupled in another cascade arrangement, thus providing a systematic design for the BFN **300**. Further, in some examples, multiple BFNs **300** can be included in a BFN array, such as the BFN array **320** illustrated in FIG. **4**.

(52) In the BFN array **320**, three (3) instances of the BFN **300** of FIG. **3** are arranged in an array. Moreover, although the instances of the BFN **300** are not coupled in FIG. **4**, in other examples of the BFN array **320**, each instance of the BFN **300** or some subset thereof can be coupled to provide another cascade (hierarchical) arrangement.

(53) FIG. **5** illustrates another plan view of an example of an antenna array **400**. The antenna array **400** can be formed on a top layer and/or region of a multi-layer PCB. The antenna array **400** can include a plurality of antenna cells **402** arranged in a tile pattern. Each antenna cell **402** can have a square shape. The example illustrated by the antenna array **400** includes eight (8) antenna cells **402**, labeled as antenna cells A-H. Each of the plurality of antenna cells **402** can be arranged in a global coordinate system **404**. Moreover, each antenna cell **402** can include an instance of a radiant element **406**. Each radiating element **406** can include N number of slot elements **408**. In the example illustrated, each antenna cell **402** includes two orthogonally positioned slot elements **408**, namely a first slot element **408.sub.1** and a second slot element **408.sub.2**. Each radiating element **406** can also include a metallic patch radiator **410**.

(54) Each of the N number of slot elements **408** can be rotated in the global coordinate system **404**. Additionally, each antenna cell **402** can include a local coordinate system labeled with an origin axis positioned near a corner of each antenna cell **402**. Each antenna cell **402** can include N number of ports **414** that couple each respective antenna cell **402** to a BFN that underlays the antenna array **400**. Each port **414** can include a via to couple each respective antenna cell **402** to the BFN. Moreover, each port **414** in FIG. **5** can be representative of a terminal of the via. In the illustrated example, each antenna cell includes two (2) ports **414**, namely a first port **414.sub.1** and a second port **414.sub.2**. Additionally, in the example illustrated, each of the first port **414.sub.1** and the second port **414.sub.2** can be positioned at adjacent corners of the antenna cells **402**. As used herein, "adjacent corners" are defined as two corners that share a side of a polygon. Each antenna cell **402** can include N number of feedlines **416** that are formed on a feedline layer of the antenna array **400**. In the example illustrated, there are two (2) feedlines, namely a first feedline **416.sub.1** and a second feedline **416.sub.2**. Each feedline **416** can couple a port **414** with a corresponding slot element **408**. Each of the N number of feedlines **416** of the antenna array **400** have the same length. Signals communicated with the radiating elements **406** can be phase adjusted to compensate

(counteract) the rotation of the radiating elements **406**.

(55) Each of the ports **414** can be environed by a plurality of isolation vias **415** positioned equidistant to a corresponding port **414**. In the example illustrated, there are four (4) isolation vias **415** in close proximity to each port **414**. However, in other examples, there can be more or less isolation vias **415**. Moreover, the isolation vias **415** can be shared between ports **414** on different antenna cells **402**, thereby reducing the overall number of isolation vias **415** needed to provide sufficient shielding for the ports **414**. Additionally, in some examples, some of the isolation vias **415** can extend only partially between the BFN and the antenna array **400**.

(56) Each of the N number of ports **414** in each antenna cell **402** can be positioned at a set of coordinates in a corresponding local coordinate system, which can be the same set of coordinates in each local coordinate system. In such examples, the ports **414** can intersect the feedline layer that contains the feedlines **416** at the set of coordinates in the local coordinate system of each antenna cell **402**. In other words, the first port **414.sub.1** of the antenna cell A **402** can have the same set of coordinates in the corresponding local coordinate system as the first port **414.sub.1** of the antenna cell B **402**. In this manner, the ports **414** can be located at regular, predetermined positions throughout the antenna array **400**.

(57) In some examples, the angle of rotation of each radiating element **406** in the global coordinate system **404** can be 0 degrees,  $\pm 90$  degrees,  $\pm 180$  degrees and  $\pm 270$  degrees. In other examples, other angles of rotation in the global coordinate system **104** are possible. Additionally, the antenna array **400** can operate in the same (or similar manner) as the antenna array **100** of FIG. 1. Accordingly, each antenna cell **402** of the antenna array **400** can be designed to communicate RF signals with free space. In other words, the antenna array **400** can be designed to at least one of transmit RF signals into free space and receive RF signals from free space. Such communicated signals can be adjusted by a BFN and (in some examples), IC chips, as explained herein.

(58) FIG. 6 illustrates a plan view of an example of a BFN **500** that can be employed to communicate with the antenna array **400** of FIG. 5. Some elements of the BFN **500** can be formed on an interior layer of the multi-layer PCB employed for the antenna array **400**, and other elements can be formed on an exterior layer of the BFN **500**, such as a bottom layer of the BFN **500**. For purposes of simplification of explanation, the same reference numbers are employed in FIGS. 5 and 6 to denote the same structure. The BFN **500** can be partitioned into a plurality of BFN cells **502** that are each rotated in the global coordinate system **404**. As noted, the BFN **500** can underlay the antenna array **400** of FIG. 5. Moreover, each BFN cell **502** can have the same size and shape (e.g., a square) as an overlaying antenna cell **402**. Accordingly, the BFN cells **502** are labeled A-H to correspond to the overlaying antenna cell **402** with the same label A-H. Thus, BFN cell A **502** underlies antenna cell A **402**. Each BFN cell **502** can have the same local coordinate system as the corresponding antenna cell **402**.

(59) Each BFN cell **502** can include N number of ports **414**. In the example illustrated by the BFN **500**, each BFN cell **502** includes a first port **414.sub.1** and a second port **414.sub.2**. Each port **414** can be representative of a terminal of a via to a port **414** illustrated in the antenna array **400**. As explained with respect to the antenna array **400**, each of the N number of ports **414** can be at a same set of coordinates in each respective local coordinate system.

(60) Each of the N number of ports **414** can be environed by a plurality of isolation vias **415**, only some of which are labeled. The isolation vias **415** can correspond to the isolation vias **415** of FIG. 5. In some examples, some of the isolation vias **415** can extend only partially between the BFN **500** and the antenna array **400** of FIG. 5.

(61) The BFN **500** can include an I/O port **506** that can be coupled to an external system. The I/O port **506** can be coupled to a first stage combiner/divider **508**, which can be coupled to two (2) second stage combiners/dividers **510** through vias **512**. In some examples, the vias **512** can be shorter than the vias of the ports **414**. Additionally, the first stage combiner/divider **508** and the second stage combiners/dividers **510** have a cascade arrangement.

(62) The second stage combiners/dividers **510** can be symmetrically arranged relative to the first stage **508**. Moreover, in such a situation, BFN cells **502** and a second stage combiner/divider **510** can define a beam forming stage that has a local coordinate system. In this manner, each beam forming stage (a combination of BFN cells **502** and a second stage divider **510**) can have the same geometric shape in the local coordinate system. Moreover, each beam forming stage can be rotated in the global coordinate system **404**.

(63) Each BFN cell **502** can correspond to an IC chip **520** (or multiple IC chips) that can adjust signals. Each IC chip **520** can be positioned on the bottom layer of the BFN **500**. In some examples, each IC chip **520** can be integrated with the BFN **500**, and in other examples, each IC chip **520** can be a separate component that communicates with the BFN **500**. Each IC chip **520** can be coupled to a combiner/divider **510** and to the N number of ports **414** of the BFN cell **502**. As some examples, each IC chip **520** can amplify, phase adjust, combine and/or divide signals.

(64) The BFN **500** can operate in a manner similar to the BFN **200** of FIG. 2. Thus, the BFN **500** can operate in at least one of the transmitting mode and the receiving mode.

(65) As illustrated with the antenna array **400** of FIG. 5 and the BFN **500** of FIG. 6, the antenna cells **402** and the BFN cells **502** can communicate through the N number of ports **414**. Moreover, the antenna array **400** can be designed such that the slot elements **408** can be rotated independently from the location of the ports **414**. Accordingly, the angle of rotation of the slot elements **408** does not necessarily impact the physical layout of the BFN **500**. Therefore, the BFN **500** and the antenna array **400** can be designed independently based on predetermined positions of each of the N number of ports **414** for each BFN cell **502** and each antenna cell **402**. Thus, the overall design of the BFN **500** and the antenna array **400** can be simplified.

(66) In some examples, the BFN **500** can be designed systematically with symmetric modules that are scalable to accommodate nearly any number of levels. In particular, although the BFN **500** is described with two (2) stages of combiners/dividers, namely the first stage combiner/divider **508** and the second stage of combiners/dividers **510**, the BFN **500** illustrated can be employed as a module or circuit to implement a larger scale BFN, including the BFN **600** illustrated in FIG. 7.

(67) In the BFN **600**, eight (8) instances of the BFN **500** of FIG. 6 are connected in a cascade (hierarchical) arrangement. In particular, an I/O port **602** is coupled to a first stage combiner/divider **604**, which is coupled to two (2) second stage combiners/dividers **606**. Each second stage combiner/divider **606** can be coupled to two (2) third stage combiners/dividers **608**. Each third stage combiner/divider **608** can be coupled to two instances of an input port **506** of an instance of the BFN **500** (a module of the BFN **600**). In this manner, the eight (8) instances of the BFN **600** are connected together in a cascade arrangement. Further, in other examples, multiple instances of the BFN **600** can be coupled in a cascade arrangement.

(68) FIG. 8 illustrates another plan view of an example of an antenna array **700**. The antenna array **700** can be formed on a top layer and/or region of a multi-layer PCB. The antenna array **700** can include a plurality of antenna cells **702** that can be arranged in regular tiling pattern. Each antenna cell **702** can have a square shape. The example illustrated by the antenna array **700** includes eight (8) antenna cells **702**, labeled as antenna cells A-H. Each of the plurality of antenna cells **702** can be arranged in a global coordinate system **704**. Moreover, each antenna cell **702** can include an instance of a radiating element **706**. Each radiating element **706** can include N number of slot elements **708**. In the example illustrated, each antenna cell **702** includes two orthogonally positioned slot elements **708**, namely a first slot element **708.sub.1** and a second slot element **708.sub.2**. Each radiating element **706** can also include a metallic patch radiator **710**.

(69) Each of the N number of slot elements **708** can be rotated in the global coordinate system **704**. Additionally, each antenna cell **702** can include a local coordinate system labeled with an origin axis positioned near a corner of each antenna cell **702**. Each antenna cell **702** can include N number of ports **714** that couple each respective antenna cell **702** to a BFN that underlays the antenna array **700**. In the illustrated example, each antenna cell include two (2) ports **714**, namely a first port

714.sub.1 and a second port 714.sub.2. Additionally, in the example illustrated, each of the first port 714.sub.1 and the second port 714.sub.2 can be positioned at opposing corners of the antenna cells 702. In other words, the first port 714.sub.1 and the second port 714.sub.2 are positioned catty-corner relative to each other. Each port 714 can be environed by a plurality of isolation vias 715 spaced equidistant from a corresponding port 714, only some of which are labeled. In the example illustrated, there are four (4) isolation vias 715 in close proximity to each port 714. However, in other examples, there can be more or less isolation vias 715. Moreover, the isolation vias 715 can be shared between ports 714 on different antenna cells 702, thereby reducing the overall number of isolation vias 715 needed to provide sufficient shielding for the ports 714. Additionally, in some examples, some of the isolation vias 715 can extend only partially between the BFN and the antenna array 700.

(70) Each antenna cell 702 can include N number of feedlines 716 formed on a feedline layer. In the example illustrated, there are two (2) feedlines 716 in each antenna cell 702, namely a first feedline 716.sub.1 and a second feedline 716.sub.2. Each feedline 716 can couple a port 714 with a corresponding slot element 708. In some examples, the first feedline 716.sub.1 and the second feedline 716.sub.2 within a given antenna cell 702 can have the same length.

(71) Each of the N number of ports 714 in each antenna cell 702 can be positioned at a set of coordinates in a corresponding local coordinate system, which can be the same set of coordinates in each local coordinate system. Accordingly, in some examples, the N number of ports 714 in each antenna cell 702 can intersect the feedline layer at the same set of coordinates in the corresponding local coordinate system. Consequently, the first port 714.sub.1 of the antenna cell A 702 can have the same set of coordinates in the corresponding local coordinate system as the first port 714.sub.1 of the antenna cell B 702. In this manner, the ports 714 are located at regular positions throughout the antenna array 700.

(72) In some examples, the angle of rotation of each radiating element 706 in the global coordinate system 704 can be 0 degrees,  $\pm 90$  degrees,  $\pm 180$  degrees and  $\pm 270$  degrees. In other examples, other angle of rotations in the global coordinate system 704 are possible. The antenna array 700 can operate in the same (or similar manner) as the antenna array 100 of FIG. 1.

Accordingly, each antenna cell 702 of the antenna array 700 can be designed to communicate RF signals with free space. In other words, the antenna array 700 can be designed to at least one of transmit RF signals into free space and receive RF signals from free space. Such communicated signals can be adjusted by a BFN and (in some examples), IC chips, as explained herein.

(73) FIG. 9 illustrates another plan view of an example of a BFN 800 that can be employed to communicate with the antenna array 700 of FIG. 8. Some components of the BFN 800 can be formed on an interior layer of the multi-layer PCB employed for the antenna array 700. Moreover, as explained herein, some components of the BFN 800 can be formed or mounted on an exterior layer (e.g., a bottom layer) of the BFN 800. For purposes of simplification of explanation, the same reference numbers are employed in FIGS. 8 and 9 to denote the same structure. The BFN 800 can be partitioned into a plurality of BFN cells 802 that are each rotated in the global coordinate system 704. As noted, the BFN 800 can underlay the antenna array 700 of FIG. 8. Moreover, each BFN cell 802 can have the same size and shape (e.g., a square) as an overlaying antenna cell 702. Accordingly, the BFN cells 802 are labeled A-H to correspond to the overlaying antenna cell 702. Thus, BFN cell A 802 underlies antenna cell A 702. Each BFN cell 802 can have the same local coordinate system as the corresponding antenna cell 702.

(74) Each BFN cell 802 can include N number of ports 714. In the example illustrated by the BFN 800, each BFN cell includes a first port 714.sub.1 and a second port 714.sub.2. Each port 714 can be representative of a terminal of a via to a port illustrated in the antenna array 700. Each of the N number of ports 714 can be at a same set of coordinates in each respective local coordinate system. As explained with respect to the antenna array 700, each of the N number of ports 714 can be at a same set of coordinates in each local coordinate system.

(75) Each of the N number of ports **714** can be envisioned by a plurality of isolation vias **715**, only some of which are labeled. The isolation vias **715** can correspond to the isolation vias **715** of FIG. **8**. Additionally, in some examples, some of the isolation vias **715** can extend only partially between the BFN **800** and the antenna array **700** of FIG. **8**.

(76) The BFN **800** can include an I/O port **806** that can be coupled to an external system. The I/O port **806** can be coupled to a first stage combiner/divider **808**, which can be coupled to two (2) second stage combiners/dividers **810** through vias **812**. In some examples, the vias **812** can be shorter than the vias of the ports **714**. the first stage combiner/divider **808** and the second stage combiners/dividers **810** can have a cascade arrangement.

(77) Each BFN cell **802** can correspond to an IC chip **820** (or multiple IC chips) that can adjust signals. Each IC chip **820** can be positioned on the bottom layer of the BFN **800**. In some examples, each IC chip **820** can be integrated with the BFN **800**, and in other examples, each IC chip **820** can be a separate component that communicates with the BFN **800**. Each IC chip **820** can be coupled to a second stage combiner/divider **810** and to the N number of ports **714** of the BFN cell **802**. Each IC chip **820** can amplify, phase adjust, combine and/or divide signals.

(78) The second stage combiners/dividers **810** can be symmetrically arranged relative to the first stage **808**. Moreover, in such a situation, BFN cells **802** and a second stage combiner/divider **810** can define a beam forming stage that has a local coordinate system. In this manner, each beam forming stage (a combination of BFN cells **802** and a second stage combiner/divider **810**) can have the same geometric shape in the local coordinate system. Moreover, each beam forming stage can be rotated in the global coordinate system **704**.

(79) The BFN **800** can operate in a manner similar to the BFN **200** of FIG. **2**. Thus, the BFN **800** can operate in at least one of the transmitting mode and the receiving mode.

(80) As illustrated with the antenna array **700** of FIG. **8** and the BFN **800** of FIG. **9**, the antenna cells **702** and the BFN cells **802** can communicate through the N number of ports **714**. Moreover, the antenna array **700** can be designed such that the slot elements **708** can be rotated independently from the location of the ports **714**. Accordingly, the angle of rotation of the slot elements **708** does not necessarily impact the physical layout of the BFN **800**. Therefore, the BFN **800** and the antenna array **700** can be designed independently based on predetermined positions of each of the N number of ports **714** for each BFN cell **802** and each antenna cell **702**. Thus, the overall design of the BFN **800** and the antenna array **700** can be simplified.

(81) In some examples, the BFN **800** can be designed systematically with symmetric modules that are scalable to accommodate nearly any number of levels. In particular, although the BFN **800** is described with two (2) stages of combiners/dividers, namely the first stage combiner/divider **808** and the second stage combiners/dividers **810**, the BFN **800** illustrated can be employed as a module or circuit to implement a larger scale BFN, including the BFN **900** illustrated in FIG. **10**.

(82) In the BFN **900**, eight (8) instances of the BFN **800** of FIG. **9** are connected in a cascade (hierarchical) arrangement. In particular, an I/O port **902** is coupled to a first stage combiner/divider **904**, which can each be coupled to two (2) second stage combiners/dividers **906**. Each second stage combiner/divider **906** can be coupled to two (2) third stage combiners/dividers **908**. Each third stage combiner/divider **908** can be coupled to two instances of an input port **806** of an instance of the BFN **800** (a module of the BFN **900**). In this manner, the eight (8) instances of the BFN **900** are connected together in a cascade arrangement. Further, in other examples, multiple instances of the BFN **900** can be coupled in a cascade arrangement.

(83) FIG. **11** illustrates a stack-up (cross-sectional) view of a multi-layer PCB **1000** (or other dielectric substrate) that can include an antenna array **1002** overlaying a BFN **1004** formed on a BFN layer. The multi-layer PCB **1000** can be employed to implement a system that can at least one of transmit and receive RF signals. The antenna array **1002** can be implemented, for example, with the antenna array **100** of FIG. **1**, the antenna array **400** of FIG. **5** or the antenna array **700** of FIG. **8**. The BFN **1004** formed on the BFN layer can have a plurality of traces (e.g., conductive traces).

The BFN **1004** can be implemented, for example, as the BFN **200** of FIG. 2, the BFN **300** of FIG. 3, a portion of the BFN array **320** of FIG. 4, the BFN **500** of FIG. 6, the BFN **600** of FIG. 7, the BFN **800** of FIG. 9 or the BFN **900** of FIG. 10. In FIG. 11, a portion of the multi-layer PCB **1000** is included. The multi-layer PCB **1000** can include core material (e.g., dielectric laminate) layers **1008**, pre-preg material (a pre-impregnated material, such as an epoxy-based material) layers **1010** and conductive material (e.g., ground plane) layers **1012**.

(84) An IC chip region **1014** can include layers for mounting an IC chip **1016** onto a lower surface of the BFN **1004**. The IC chip **1016** can be implemented, for example, as an instance of the IC chip **220** of FIG. 2, the IC chip **520** of FIG. 6 or the IC chip **820** of FIG. 9. The multi-layer PCB **1000** can include a port **1018** implemented as a via that communicatively couples the IC chip **1016** to the antenna array **1002**. The multi-layer PCB **1000** can also include an isolation via **1020** that provides shielding for the port **1018**. The IC chip region **1014** can communicate with the BFN **1004** through a via **1022** that communicatively couples a combiner/divider that can be formed on a bottom (exterior) layer of the BFN **1004** to the IC chip **1016**. The combiner/divider can be implemented, for example, as the 3-to-1 combiner/divider **212** of FIG. 2, the second stage combiner/divider **510** of FIG. 6 or the second stage combiner divider **810** of FIG. 9. Additionally, the IC chip **1016** can be connected to a power supply through a via **1026** that can couple the IC chip **1016** to direct current (DC) power supply region **1028** of the multi-layer PCB **1000**. Further, the IC chip **1016** can be connected to an electrically neutral node (e.g., ground) through a via **1030**.

(85) A feeder layer **1032** of the antenna array **100** can underlay radiating elements **1034** of the antenna array **1002**. The feeder layer **1032** can include an instance of a feedline **1036**. The feed line **1036** can couple the port **1018** to a slot element **1038** of the radiating elements **1034**. The slot element **1038** can be electromagnetically coupled to a patch antenna **1039** of the radiating elements **1034**.

(86) FIG. 11 includes an arrow representing a signal **1040** flowing through the multi-layer PCB **1000** operating in the transmitting mode. The signal **1040** can be provided, for example, as an electrical signal (a guided EM signal) from an external system. The signal **1040** traverses the combiner/divider **1024** and is provided to the IC chip **1016** through the via **1022**. The IC chip **1016** can adjust (e.g., amplify, phase adjust and/or divide) the signal **1040**. Moreover, the signal **1040** can be provided to the port **1018**, and the signal **1040** is received at the antenna array **1002**. The signal **1040** can be provided to the slot element **1038** through the feedline **1036**. The slot element **1038** can convert a guided EM signal into a radiated EM signal that is transmitted by the patch antenna **1039** into free space. In the receiving mode, signals operate in reverse of the signal **1040**.

(87) FIG. 12 illustrates a block diagram of a system **1100** that depicts the logical interconnection of an antenna array **1102** and a BFN **1104**. The antenna array **1002** can be implemented, for example, with the antenna array **100** of FIG. 1, the antenna array **400** of FIG. 5 or the antenna array **700** of FIG. 8. The BFN **1004** can be implemented, for example, as the BFN **200** of FIG. 2, the BFN **300** of FIG. 3, the BFN **500** of FIG. 6, the BFN **600** of FIG. 7, the BFN **800** of FIG. 9 or the BFN **900** of FIG. 10.

(88) In some examples, the antenna array **1102** can operate exclusively in the transmitting mode or the receiving mode. In other examples, the antenna array **1102** can operate in a half-duplexing mode, wherein the antenna array **1102** switches between the receiving mode and the transmitting mode. In still other examples, the antenna array **1102** can operate in a full-duplexing mode, wherein the antenna array **1102** operates concurrently in the receiving mode and the transmitting mode.

(89) In the illustrated example, K number of antenna cells **1106** communicate with the BFN **1104**, where K is an integer greater than or equal to two (2). Each of the K number of antenna cells **1106** can include a radiating element **1108**. The radiating element **1108** can be representative of N number of orthogonally arranged slot elements **1110** and a patch antenna **1114**. In the example illustrated there are two slot elements **1110**, namely a first slot element **1110.sub.1** and a second slot element **1110.sub.2**. Each of the K number of antenna cells **1106** can communicate with a

corresponding IC chip **1116**. In the illustrated example, each IC chip **1116** can include a combiner/divider **1120** that can combine and/or divide signals traversing the IC chip **1116**. Additionally, each IC chip **1116** can include N number of paths for communicating with the N number of slot elements **1110** of the corresponding antenna cell **1106**. In the present example, each IC chip **1116** can include a first path **1122** and a second path **1124**. Additionally, in some examples, the first path **1122** and the second path **1124** of each IC chip **1116** can be representative of multiple paths that can be further sub-divided into a receiving path and a transmitting path.

(90) The first path **1122** and the second path **1124** can each include an amplifier **1130** and a phase shifter **1132** for adjusting signals communicated with the corresponding radiating element **1108** and/or the BFN **1104**.

(91) The first path **1122** can be coupled to a first port **1134.sub.1** of the corresponding antenna cell **1106** and the second path **1124** can be coupled to a second port **1134.sub.2** of the corresponding antenna cell **1106**. The first port **1134.sub.1** of the antenna cell **1106** can be designed to communicate signals between the first path **1122** of the IC chip **1116** and the first slot element **1110.sub.1** that are in a first polarization. The second port **1134.sub.2** of the antenna cell **1106** can be designed to communicate signals between the second slot element **1110.sub.2** with a second polarization, orthogonal to the first polarization. For instance, the first polarization can be horizontal polarization and the second polarization can be vertical polarization, or vice versa. In such a situation, the antenna array **1102** can communicate signals with right hand circular polarization (RHCP) or left hand circular polarization (LHCP). Alternatively, in some examples, there can be only one slot element **1110**, and the polarization can be a linear polarization.

(92) The IC chips **1116** can receive control signals from a controller **1140** that can be implemented on an external system. In some examples, the controller **1140** can be implemented as a microcontroller with embedded instructions. In other examples, the controller **1140** can be implemented as a general-purpose computer with software executing thereon. In some examples, the control signals can control mode of operation of the system **1100**. That is, in some examples, the control signals can cause the IC chips **1116** to switch the antenna array **1102** from the receiving mode to the transmitting mode, or vice-versa. Additionally, in some examples, the control signals provided from the controller **1140** can control a variable amount of amplitude adjustment applied by each amplifier **1130**. Thus, in some examples, each amplifier **1130** can be implemented as a variable gain amplifier, a switched attenuator circuit, etc. Similarly, in some examples, the control signals provided from the controller **1140** can control a variable amount of phase adjustment applied by each phase shifter **1132**.

(93) During operation in the receiving mode, the controller **1140** can cause the IC chips **1116** to route signals from the K number of antenna cells **1106** to the BFN **1104**. Moreover, in the receiving mode, an EM signal (an RF signal) in the first polarization can be received at the patch antenna **1114** and detected by the first slot elements **1110.sub.1** by each of the K number of antenna cells **1106** (or some subset thereof). Similarly, an EM signal (RF) in the second polarization can be received at the patch antenna **1114** and detected by the second slot element **1110.sub.2**. Each of the first slot elements **1110.sub.1** and the second slot elements **1110.sub.2** can convert the received EM signals into an electrical signal that can be provided to a corresponding IC chip **1116** for adjustment. Signals provided from the first slot element **1110.sub.1** can be provided to the first path to the IC chip **1116** and signals provided from the second slot element **1110.sub.2** can be provided to the second path **1124** of the IC chip **1116**.

(94) Continuing in the receiving mode, each amplifier **1130** in the first path **1122** of the IC chips **1116** can amplify the signal provided from the first slot element **1110.sub.1** and each phase shifter **1132** of the first path **1122** can apply a phase adjustment to output a signal to the combiner/divider **1120**. Similarly, each amplifier **1130** in the second path **1124** of the IC chips **1116** can amplify the signal provided from the second slot element **1110.sub.2** and each phase shifter **1132** of the second path **1124** can apply a phase adjustment to output a signal to the combiner/divider **1120**. Each

combiner/divider **1120** can combine a signal from the first path **1122** with a signal from the second path **1124**, such that the K number of IC chips **1116** can output K number of sub-signals. The K number of sub-signals can be provided to the BFN **1104**. The BFN **1104** can combine the K number of sub-signals to form a received beam signal that can be provided to the external system for demodulating and processing.

(95) During operation in the transmitting mode, the controller **1140** can set the IC chips **1116** to provide a signal from the BFN **1104** to the K number of antenna cells **1106**. The K number of antenna cells **1106** can thus transmit a transmit beam signal that can be provided from the external system to the BFN **1104**. The BFN **1104** can divide the transmit beam signal into K number of sub-signals that can be provided to the K number of IC chips **1116**. Each IC chip **1116** of the K number of IC chips **1116** can adjust a corresponding sub-signal to generate an adjusted signal that can be provided to a corresponding antenna cell **1106**. In the example illustrated, the adjusting can include dividing the corresponding sub-signal into a first signal and a second signal.

(96) The first signal can be provided on the first path **1122** of the IC chip **1116** and the second signal can be provided on the second path **1124** of the IC chip **1116**. The phase shifter **1132** of the first path **1122** can apply a phase adjustment to the first signal and the amplifier **1130** of the first path **1122** can amplify the first signal. The first signal can be provided to the first slot element **1110.sub.1**. The first slot element **1110.sub.1** can convert the first signal into an EM signal (an RF signal) in the first polarization that can be transmitted to the patch antenna **1114**. Similarly, the phase shifter **1132** of the second path **1124** can apply a phase adjustment to the second signal and the amplifier **1130** of the second path **1124** can amplify the second signal. The second signal can be provided to the second slot element **1110.sub.2**. The second slot element **1110.sub.2** can convert the second signal into an EM signal (an RF signal) in the second polarization that can be transmitted to the patch antenna **1114**. The patch antenna **1114** can transmit the EM signal in the first polarization and the EM signal in the second polarization into free space.

(97) What have been described above are examples. It is, of course, not possible to describe every conceivable combination of components or methodologies, but one of ordinary skill in the art will recognize that many further combinations and permutations are possible. Accordingly, the disclosure is intended to embrace all such alterations, modifications, and variations that fall within the scope of this application, including the appended claims. As used herein, the term “includes” means includes but not limited to, the term “including” means including but not limited to. The term “based on” means based at least in part on. Additionally, where the disclosure or claims recite “a,” “an,” “a first,” or “another” element, or the equivalent thereof, it should be interpreted to include one or more than one such element, neither requiring nor excluding two or more such elements.

## Claims

1. A method of manufacturing a multi-layer printed circuit board (PCB), the method comprising: positioning a beam-forming network (BFN) in a coordinate system, wherein: the BFN comprises a plurality of beam forming stages, and a given beam forming stage of the plurality of beam forming stages has a same geometric shape as a different beam forming stage of the plurality of beam forming stages; positioning a plurality of antenna cells in the coordinate system to form a regular tiling pattern; and interconnecting each of the plurality of antenna cells with the BFN through a via extending between the BFN and the antenna cell, wherein: each of the plurality of antenna cells is positioned with a predetermined angle of rotation defined in the coordinate system, and at least two of the plurality of antenna cells have different predetermined angles of rotation.
2. The method of claim 1, further comprising rotating the given beam forming stage in the coordinate system relative to the different beam forming stage.
3. The method of claim 2, wherein the given beam forming stage is rotated by 180 degrees relative

to the different beam forming stage.

4. The method of claim 2, further comprising arranging each of the plurality of beam forming stages of the BFN in a hierarchical relationship.

5. The method of claim 4, wherein the given beam forming stage and the different beam forming stage are on a same level within the hierarchical relationship of the BFN.

6. The method of claim 4, further comprising the given beam forming stage and the different beam forming stage to a given combiner/divider.

7. The method of claim 6, wherein the given beam forming stage is a first beam forming stage and the different beam forming stage is a second beam forming stage, and the given combiner/divider is a first combiner/divider, the BFN comprising a third beam forming stage, wherein the third beam forming stage comprises: a second combiner/divider coupled to the first combiner/divider and a third combiner/divider, wherein the third combiner/divider is coupled to a fourth beam forming stage and a fifth beam forming stage.

8. The method of claim 7, wherein the third beam forming stage and the fifth beam forming stage are on a same level as the first beam forming stage and the second beam forming stage within the hierarchical relationship of the BFN.

9. The method of claim 1, wherein the coordinate system is a global coordinate system, and each of the plurality of antenna cells has a respective local coordinate system, and each of the plurality of antenna cells intersects a respective via extending from the BFN at a particular set of coordinates in the respective local coordinate system.

10. The method of claim 9, wherein the particular set of coordinates in the respective local coordinate system is the same for each of the plurality of antenna cells.

11. The method of claim 1, wherein the BFN comprises a plurality of BFN cells, further comprising coupling each BFN cell to a respective integrated circuit (IC) chip that is coupled to the multi-layered PCB for adjusting signals communicated with the plurality of antenna cells through the respective vias.

12. The method of claim 1, wherein each of the plurality of BFN cells overlays the respective IC chip.

13. The method of claim 1, further comprising interconnecting each of the plurality of antenna cells with the BFN through two vias.

14. A method of forming a beam-forming network (BFN), the method comprising: positioning each beam forming stage of a plurality of beam forming stages within a coordinate system of a multi-layered PCB, wherein a given beam forming stage of the plurality of beam forming stages has a same geometric shape as a different beam forming stage of the plurality of beam forming stages; positioning a plurality of antenna cells in the coordinate system to form a regular tiling pattern; and interconnecting each of the plurality of antenna cells with the BFN through a via extending between the BFN and the antenna cell, wherein: the BFN communicates with the plurality of antenna cells, each of the plurality of antenna cells has a predetermined angle of rotation defined in the coordinate system, and at least two of the plurality of antenna cells have different predetermined angles of rotation.

15. The method of claim 14, further comprising rotating the given beam forming stage in the coordinate system relative to the different beam forming stage.

16. The method of claim 14, further comprising arranging each of the plurality of beam forming stages of the BEN in a hierarchical relationship, wherein the given beam forming stage and the different beam forming stage are on a same level within the hierarchical relationship of the BFN.

17. The method of claim 16, wherein the given beam forming stage and the different beam forming stage are both connected to a given combiner/divider, and each of the plurality of antenna cells is interconnected with the BFN through two vias.

18. The method of claim 14, wherein the BFN comprises a plurality of BFN cells, wherein each BFN cell overlays and is coupled to a respective integrated circuit (IC) chip that is coupled to the

multi-layered PCB for adjusting signals communicated with the plurality of antenna cells through the respective vias.

19. The method of claim 14, wherein the coordinate system is a global coordinate system, and each of the plurality of antenna cells has a respective local coordinate system, and each of the plurality of antenna cells intersects a respective via extending from the BFN at a particular set of coordinates in the respective local coordinate system and the particular set of coordinates in the respective local coordinate system is the same for each of the plurality of antenna cells.

20. A communication system comprising: a plurality of antenna cells positioned in a coordinate system; and a beam-forming network (BFN) positioned in the coordinate system, wherein the BFN comprises a plurality of beam forming stages, wherein a given beam forming stage of the plurality of beam forming stages has a same geometric shape as a different beam forming stage of the plurality of beam forming stages, wherein each of the plurality of antenna cells is interconnected with the BFN through a via extending between the BFN and the antenna cell, wherein each of the plurality of antenna cells has a predetermined angle of rotation defined in the coordinate system, and wherein at least two of the plurality of antenna cells have different predetermined angles of rotation.

---