

US Patent & Trademark Office

Patent Public Search | Text View

United States Patent	12413371
Kind Code	B2
Date of Patent	September 09, 2025
Inventor(s)	Abedini; Navid et al.

Signaling support for different timing cases in IAB nodes

Abstract

An integrated access and backhaul (IAB) node receives, from a parent IAB node, a time difference parameter for over-the-air (OTA) synchronization in an IAB network. The IAB node adjusts transmission or reception of the IAB node based on the time difference parameter for one of multiple types of IAB node alignment.

Inventors: Abedini; Navid (Basking Ridge, NJ), Blessent; Luca (Whitehouse Station, NJ), Luo; Jianghong (Skillman, NJ)

Applicant: QUALCOMM Incorporated (San Diego, CA)

Family ID: 83004695

Assignee: QUALCOMM Incorporated (San Diego, CA)

Appl. No.: 17/811005

Filed: July 06, 2022

Prior Publication Data

Document Identifier	Publication Date
US 20230071894 A1	Mar. 09, 2023

Related U.S. Application Data

us-provisional-application US 63236663 20210824

Publication Classification

Int. Cl.: H04L5/00 (20060101); H04W56/00 (20090101); H04W88/08 (20090101); H04W84/04 (20090101)

U.S. Cl.:

CPC **H04L5/0078** (20130101); **H04W56/005** (20130101); **H04W88/085** (20130101);
H04W84/047 (20130101)

Field of Classification Search

CPC: H04L (5/0078); H04W (56/0015); H04W (56/004); H04W (84/047); H04W (88/085)

References Cited

U.S. PATENT DOCUMENTS

Patent No.	Issued Date	Patentee Name	U.S. Cl.	CPC
12075378	12/2023	Song	N/A	H04W 56/0045
2021/0089495	12/2020	Lemke	N/A	G06F 16/183
2021/0410058	12/2020	Dey	N/A	H04W 40/24
2022/0070809	12/2021	Song	N/A	H04W 72/20
2022/0110077	12/2021	Abedini	N/A	H04W 56/0045
2022/0124652	12/2021	Wanuga	N/A	H04W 56/0015
2023/0050110	12/2022	Akkarakaran	N/A	H04W 56/0065
2023/0276389	12/2022	Ko	370/350	H04W 56/0005
2024/0080363	12/2023	Wang	N/A	H04L 67/12

FOREIGN PATENT DOCUMENTS

Patent No.	Application Date	Country	CPC
3223812	12/2022	CA	H04W 52/146
100413351	12/2007	CN	H04L 65/1016
2607486	12/2021	GB	H04B 1/692

OTHER PUBLICATIONS

Ericsson: “Timing, CLI and Power Control in Enhanced IAB”, 3GPP TSG-RAN WG1 Meeting #104-e, R1-2101696, 3rd Generation Partnership Project, Mobile Competence Centre, 650, Route Des Lucioles, F-06921 Sophia-Antipolis Cedex , France, vol. RAN WG1, No. eMeeting, Jan. 25, 2021-Feb. 5, 2021, Jan. 18, 2021, XP051971849, 17 Pages, Paragraph [0002]. cited by applicant
International Search Report and Written Opinion—PCT/US2022/038908—ISA/EPO—Nov. 9, 2022. cited by applicant

Nokia, et al., “Other Enhancements for Simultaneous Operation of IAB-Node's Child and Parent Links”, 3GPP TSG RAN WG1 #106-e, R1-2106829, 3rd Generation Partnership Project, Mobile Competence Centre, 650, Route Des Lucioles, F-06921 Sophia-Antipolis Cedex, France, vol. RAN WG1, No. e-Meeting, Aug. 16, 2021-Aug. 27, 2021, Aug. 6, 2021, 14 Pages, XP052033275, Paragraph [0002]. cited by applicant

Background/Summary

CROSS REFERENCE TO RELATED APPLICATION(S) (1) This application claims the benefit of and priority to U.S. Provisional Application Ser. No. 63/236,663, entitled “Signaling Support for Different Timing Cases in IAB Nodes” and filed on Aug. 24, 2021, which is expressly incorporated by reference herein in its entirety.

TECHNICAL FIELD

(1) The present disclosure relates generally to communication systems, and more particularly, to communication in integrated access and backhaul (IAB) networks.

INTRODUCTION

(2) Wireless communication systems are widely deployed to provide various telecommunication services such as telephony, video, data, messaging, and broadcasts. Typical wireless communication systems may employ multiple-access technologies capable of supporting communication with multiple users by sharing available system resources. Examples of such multiple-access technologies include code division multiple access (CDMA) systems, time division multiple access (TDMA) systems, frequency division multiple access (FDMA) systems, orthogonal frequency division multiple access (OFDMA) systems, single-carrier frequency division multiple access (SC-FDMA) systems, and time division synchronous code division multiple access (TD-SCDMA) systems.

(3) These multiple access technologies have been adopted in various telecommunication standards to provide a common protocol that enables different wireless devices to communicate on a municipal, national, regional, and even global level. An example telecommunication standard is 5G New Radio (NR). 5G NR is part of a continuous mobile broadband evolution promulgated by Third Generation Partnership Project (3GPP) to meet new requirements associated with latency, reliability, security, scalability (e.g., with Internet of Things (IoT)), and other requirements. 5G NR includes services associated with enhanced mobile broadband (eMBB), massive machine type communications (mMTC), and ultra-reliable low latency communications (URLLC). Some aspects of 5G NR may be based on the 4G Long Term Evolution (LTE) standard. There exists a need for further improvements in 5G NR technology. These improvements may also be applicable to other multi-access technologies and the telecommunication standards that employ these technologies.

BRIEF SUMMARY

(4) The following presents a simplified summary of one or more aspects in order to provide a basic understanding of such aspects. This summary is not an extensive overview of all contemplated aspects. This summary neither identifies key or critical elements of all aspects nor delineates the scope of any or all aspects. Its sole purpose is to present some concepts of one or more aspects in a simplified form as a prelude to the more detailed description that is presented later.

(5) In an aspect of the disclosure, a method, a computer-readable medium, and an apparatus are provided at an integrated access and backhaul (IAB) node. The apparatus receives from a parent IAB node, a time difference parameter for over-the-air (OTA) synchronization in an IAB network and to adjust transmission or reception of the IAB node based on the time difference parameter for one of multiple types of IAB node alignment.

(6) In an aspect of the disclosure, a method, a computer-readable medium, and an apparatus are provided at a parent IAB node. The apparatus transmits or receives communication with a IAB node that is a child node of a parent IAB node and transmits a time difference parameter for over-

the-air synchronization in an IAB network, the time difference parameter being applicable for one of multiple types of IAB node alignment.

(7) To the accomplishment of the foregoing and related ends, the one or more aspects comprise the features hereinafter fully described and particularly pointed out in the claims. The following description and the drawings set forth in detail certain illustrative features of the one or more aspects. These features are indicative, however, of but a few of the various ways in which the principles of various aspects may be employed, and this description is intended to include all such aspects and their equivalents.

Description

BRIEF DESCRIPTION OF THE DRAWINGS

- (1) FIG. 1 is a diagram illustrating an example of a wireless communications system and an access network, in accordance with various aspects of the present disclosure.
- (2) FIG. 2A is a diagram illustrating an example of a first frame, in accordance with various aspects of the present disclosure.
- (3) FIG. 2B is a diagram illustrating an example of DL channels within a subframe, in accordance with various aspects of the present disclosure.
- (4) FIG. 2C is a diagram illustrating an example of a second frame, in accordance with various aspects of the present disclosure.
- (5) FIG. 2D is a diagram illustrating an example of UL channels within a subframe, in accordance with various aspects of the present disclosure.
- (6) FIG. 3 is a diagram illustrating an example of an IAB node and user equipment (UE) in a network, in accordance with various aspects of the present disclosure.
- (7) FIG. 4 is a diagram illustrating an example IAB network, in accordance with various aspects of the present disclosure.
- (8) FIG. 5 is a diagram illustrating an example IAB network and components thereof, in accordance with various aspects of the present disclosure.
- (9) FIG. 6 is a diagram illustrating an example connections for an IAB network, in accordance with various aspects of the present disclosure.
- (10) FIGS. 7A, 7B, and 7C illustrate various examples of different types of timing alignment for IAB nodes, in accordance with various aspects of the present disclosure.
- (11) FIG. 8 illustrates a timing diagram for communication with a parent IAB node and a child IAB node, in accordance with various aspects of the present disclosure.
- (12) FIG. 9 is a communication flow diagram illustrating example aspects of timing alignment based on a time difference parameter indicated by a parent IAB node, in accordance with various aspects of the present disclosure.
- (13) FIG. 10 is a communication flow diagram illustrating example aspects of timing alignment based on a time difference parameter indicated by a parent IAB node, in accordance with various aspects of the present disclosure.
- (14) FIG. 11 is a communication flow diagram illustrating example aspects of timing alignment based on a time difference parameter indicated by a parent IAB node, in accordance with various aspects of the present disclosure.
- (15) FIG. 12 is a flowchart of a method of wireless communication including timing adjustment based on a time difference parameter from a parent IAB node, in accordance with various aspects of the present disclosure.
- (16) FIG. 13 is a flowchart of a method of wireless communication including indicating a time difference parameter to a child IAB node, in accordance with various aspects of the present disclosure.

(17) FIG. 14 is a diagram illustrating an example of a hardware implementation for an apparatus employing a processing system that may be configured to transmit and/or receive a time difference parameter for association with one of multiple types of timing alignment.

(18) FIG. 15 shows a diagram illustrating an example disaggregated base station architecture.

DETAILED DESCRIPTION

(19) The method may enable an IAB node to apply a time difference parameter for over-air-synchronization, e.g., $T_{\text{sub}}.\text{delta}$ and/or $N_{\text{sub}}.\text{delta}$, among multiple alignment types. For example, a time difference parameter for over-the-air (OTA) synchronization in an IAB network may be received from a parent IAB node, and the IAB node that receives the time difference parameter may adjust transmission or reception of the IAB node based on the time difference parameter for one of multiple types of alignment at the IAB node and/or the parent IAB node. The IAB node may apply the time difference parameter for one of multiple potential types of alignment at the IAB. A first type of alignment (e.g., which may be referred to as case 1 alignment) may include downlink transmission timing alignment across each IAB node of the IAB network. A second type of alignment (e.g., which may be referred to as case 6 alignment) may be between uplink transmission at an IAB mobile termination (IAB-MT) of the child IAB node and downlink transmission at an IAB distributed unit (IAB-DU) of the child IAB node. A third type of alignment (e.g., which may be referred to as case 7 alignment) may be between downlink reception at the IAB-MT of the child IAB node and uplink reception at the IAB-DU of the child IAB node.

(20) The detailed description set forth below in connection with the drawings describes various configurations and does not represent the only configurations in which the concepts described herein may be practiced. The detailed description includes specific details for the purpose of providing a thorough understanding of various concepts. However, these concepts may be practiced without these specific details. In some instances, well known structures and components are shown in block diagram form in order to avoid obscuring such concepts.

(21) Several aspects of telecommunication systems are presented with reference to various apparatus and methods. These apparatus and methods are described in the following detailed description and illustrated in the accompanying drawings by various blocks, components, circuits, processes, algorithms, etc. (collectively referred to as “elements”). These elements may be implemented using electronic hardware, computer software, or any combination thereof. Whether such elements are implemented as hardware or software depends upon the particular application and design constraints imposed on the overall system.

(22) By way of example, an element, or any portion of an element, or any combination of elements may be implemented as a “processing system” that includes one or more processors. Examples of processors include microprocessors, microcontrollers, graphics processing units (GPUs), central processing units (CPUs), application processors, digital signal processors (DSPs), reduced instruction set computing (RISC) processors, systems on a chip (SoC), baseband processors, field programmable gate arrays (FPGAs), programmable logic devices (PLDs), state machines, gated logic, discrete hardware circuits, and other suitable hardware configured to perform the various functionality described throughout this disclosure. One or more processors in the processing system may execute software. Software, whether referred to as software, firmware, middleware, microcode, hardware description language, or otherwise, shall be construed broadly to mean instructions, instruction sets, code, code segments, program code, programs, subprograms, software components, applications, software applications, software packages, routines, subroutines, objects, executables, threads of execution, procedures, functions, or any combination thereof.

(23) Accordingly, in one or more example embodiments, the functions described may be implemented in hardware, software, or any combination thereof. If implemented in software, the functions may be stored on or encoded as one or more instructions or code on a computer-readable medium. Computer-readable media includes computer storage media. Storage media may be any available media that can be accessed by a computer. By way of example, and not limitation, such

computer-readable media can comprise a random-access memory (RAM), a read-only memory (ROM), an electrically erasable programmable ROM (EEPROM), optical disk storage, magnetic disk storage, other magnetic storage devices, combinations of the types of computer-readable media, or any other medium that can be used to store computer executable code in the form of instructions or data structures that can be accessed by a computer.

(24) While aspects, implementations, and/or use cases are described in this application by illustration to some examples, additional or different aspects, implementations and/or use cases may come about in many different arrangements and scenarios. Aspects, implementations, and/or use cases described herein may be implemented across many differing platform types, devices, systems, shapes, sizes, and packaging arrangements. For example, aspects, implementations, and/or use cases may come about via integrated chip implementations and other non-module-component based devices (e.g., end-user devices, vehicles, communication devices, computing devices, industrial equipment, retail/purchasing devices, medical devices, artificial intelligence (AI)-enabled devices, etc.). While some examples may or may not be specifically directed to use cases or applications, a wide assortment of applicability of described examples may occur. Aspects, implementations, and/or use cases may range a spectrum from chip-level or modular components to non-modular, non-chip-level implementations and further to aggregate, distributed, or original equipment manufacturer (OEM) devices or systems incorporating one or more techniques herein. In some practical settings, devices incorporating described aspects and features may also include additional components and features for implementation and practice of claimed and described aspect. For example, transmission and reception of wireless signals necessarily includes a number of components for analog and digital purposes (e.g., hardware components including antenna, RF-chains, power amplifiers, modulators, buffer, processor(s), interleaver, adders/summers, etc.). Techniques described herein may be practiced in a wide variety of devices, chip-level components, systems, distributed arrangements, aggregated or disaggregated components, end-user devices, etc. of varying sizes, shapes, and constitution.

(25) FIG. 1 is a diagram illustrating an example of a wireless communications system and an access network **100**. The wireless communication system and access network **100** may include an integrated access and backhaul (IAB) network that includes multiple cells in communication with each other to provide an access network and a backhaul network to a core network such as core network **190** or Evolved Packet Core (EPC) **160**. The core network **190** may be a 5G Core (5GC) a core network that supports new radio (NR) communication or another type of core network. The IAB network may include one or more IAB nodes **103**. The IAB nodes may exchange communication with other IAB nodes **103**, with a base station **102** or **180**, and/or with UEs **104**.

(26) In some aspects, an IAB Node **103** may include a time delta component **198** and/or a time delta indication component **199**. The time delta component **198** may be configured to receive from a parent IAB node, a time difference parameter for over-the-air (OTA) synchronization in an IAB network and to adjust transmission or reception of the IAB node based on the time difference parameter for one of multiple types of alignment at the IAB node and/or the parent IAB node. The time delta indication component may be configured to transmit, e.g., to a child IAB node, a time difference parameter for OTA synchronization in an IAB network, the time difference parameter being applicable for one of multiple types of alignment at the child IAB node and/or the IAB node. A first type of alignment (e.g., which may be referred to as case 1 alignment) may include downlink transmission timing alignment across each IAB node of the IAB network. A second type of alignment (e.g., which may be referred to as case 6 alignment) may be between uplink transmission at an IAB mobile termination (IAB-MT) of the child IAB node and downlink transmission at an IAB distributed unit (IAB-DU) of the child IAB node. A third type of alignment (e.g., which may be referred to as case 7 alignment) may be between downlink reception at the IAB-MT of the child IAB node and uplink reception at the IAB-DU of the child IAB node. In some aspects, an IAB node may include both a time delta component **198** and/or a time delta indication

component **199**, because the IAB node may perform some aspects of wireless communication as a parent IAB node and may perform other aspects as a child IAB node, e.g., the IAB node may have a parent IAB node and a child IAB node. Although examples in the following description may be focused on 5G NR, the concepts described herein may be applicable to other similar areas, such as LTE, LTE-A, CDMA, GSM, and other wireless technologies.

(27) The wireless communications system (also referred to as a wireless wide area network (WWAN)). The base stations **102** illustrated in FIG. **1** may support macrocells (high power cellular base station) and/or small cells (low power cellular base station). The macrocells include base stations. The small cells include femtocells, picocells, and microcells.

(28) The base stations **102** configured for 4G LTE (collectively referred to as Evolved Universal Mobile Telecommunications System (UMTS) Terrestrial Radio Access Network (E-UTRAN)) may interface with the EPC **160** through first backhaul links **132** (e.g., S1 interface). The base stations **102** configured for 5G NR (collectively referred to as Next Generation RAN (NG-RAN)) may interface with core network **190** through second backhaul links **184**. In addition to other functions, the base stations **102** may perform one or more of the following functions: transfer of user data, radio channel ciphering and deciphering, integrity protection, header compression, mobility control functions (e.g., handover, dual connectivity), inter-cell interference coordination, connection setup and release, load balancing, distribution for non-access stratum (NAS) messages, NAS node selection, synchronization, radio access network (RAN) sharing, multimedia broadcast multicast service (MBMS), subscriber and equipment trace, RAN information management (RIM), paging, positioning, and delivery of warning messages. The base stations **102** may communicate directly or indirectly (e.g., through the EPC **160** or core network **190**) with each other over third backhaul links **134** (e.g., X2 interface). The first backhaul links **132**, the second backhaul links **184** (e.g., an Xn interface), and the third backhaul links **134** may be wired or wireless.

(29) In some aspects, a base station **102** or **180** may be referred as a RAN and may include aggregated or disaggregated components. As an example of a disaggregated RAN, a base station may include a central unit (CU) **111**, one or more distributed units (DU) **105**, and/or one or more remote units (RU) **109**, as illustrated in FIG. **1**. A RAN may be disaggregated with a split between an RU **109** and an aggregated CU/DU. A RAN may be disaggregated with a split between the CU **111**, the DU **105**, and the RU **109**. A RAN may be disaggregated with a split between the CU **111** and an aggregated DU/RU. The CU **111** and the one or more DUs **105** may be connected via an F1 interface. A DU **105** and an RU **109** may be connected via a fronthaul interface. A connection between the CU **111** and a DU **105** may be referred to as a midhaul, and a connection between a DU **105** and an RU **109** may be referred to as a fronthaul. The connection between the CU **111** and the core network may be referred to as the backhaul. The RAN may be based on a functional split between various components of the RAN, e.g., between the CU **111**, the DU **105**, or the RU **109**. The CU **111** may be configured to perform one or more aspects of a wireless communication protocol, e.g., handling one or more layers of a protocol stack, and the DU(s) may be configured to handle other aspects of the wireless communication protocol, e.g., other layers of the protocol stack. In different implementations, the split between the layers handled by the CU **111** and the layers handled by the DU may occur at different layers of a protocol stack. As one, non-limiting example, a DU **105** may provide a logical node to host a radio link control (RLC) layer, a medium access control (MAC) layer, and at least a portion of a physical (PHY) layer based on the functional split. An RU may provide a logical node configured to host at least a portion of the PHY layer and radio frequency (RF) processing. A CU **111** may host higher layer functions, e.g., above the RLC layer, such as a service data adaptation protocol (SDAP) layer, a packet data convergence protocol (PDCP) layer. In other implementations, the split between the layer functions provided by the CU, DU, or RU may be different.

(30) An access network may include one or more integrated access and backhaul (IAB) nodes **103** that exchange wireless communication with a UE **104** or other IAB node **103** to provide access and

backhaul to a core network, e.g., as described in more detail in connection with FIGS. 4-6. In an IAB network of multiple IAB nodes, an anchor node may be referred to as an IAB donor. The IAB donor may be a base station **102** or **180** that provides access to a core network **190** or EPC **160** and/or control to one or more IAB nodes **103**. The IAB donor may include a CU **111** and a DU **105**. IAB nodes **103** may include a DU **105** and a mobile termination (MT). The DU **105** of an IAB node **103** may operate as a parent node, and the MT may operate as a child node.

(31) The base stations **102** may wirelessly communicate with the UEs **104**. Each of the base stations **102** may provide communication coverage for a respective geographic coverage area **110**. There may be overlapping geographic coverage areas **110**. For example, the small cell **102'** may have a coverage area **110'** that overlaps the coverage area **110** of one or more macro base stations **102**. A network that includes both small cell and macrocells may be known as a heterogeneous network. A heterogeneous network may also include Home Evolved Node Bs (eNBs) (HeNBs), which may provide service to a restricted group known as a closed subscriber group (CSG). The communication links **120** between the base stations **102** and the UEs **104** may include uplink (UL) (also referred to as reverse link) transmissions from a UE **104** to a base station **102** and/or downlink (DL) (also referred to as forward link) transmissions from a base station **102** to a UE **104**. The communication links **120** may use multiple-input and multiple-output (MIMO) antenna technology, including spatial multiplexing, beamforming, and/or transmit diversity. The communication links may be through one or more carriers. The base stations **102**/UEs **104** may use spectrum up to Y MHz (e.g., 5, 10, 15, 20, 100, 400, etc. MHz) bandwidth per carrier allocated in a carrier aggregation of up to a total of Yx MHz (x component carriers) used for transmission in each direction. The carriers may or may not be adjacent to each other. Allocation of carriers may be asymmetric with respect to DL and UL (e.g., more or fewer carriers may be allocated for DL than for UL). The component carriers may include a primary component carrier and one or more secondary component carriers. A primary component carrier may be referred to as a primary cell (PCell) and a secondary component carrier may be referred to as a secondary cell (SCell).

(32) Certain UEs **104** may communicate with each other using device-to-device (D2D) communication link **158**. The D2D communication link **158** may use the DL/UL WWAN spectrum. The D2D communication link **158** may use one or more sidelink channels, such as a physical sidelink broadcast channel (PSBCH), a physical sidelink discovery channel (PSDCH), a physical sidelink shared channel (PSSCH), and a physical sidelink control channel (PSCCH). D2D communication may be through a variety of wireless D2D communications systems, such as for example, WiMedia, Bluetooth, ZigBee, Wi-Fi based on the Institute of Electrical and Electronics Engineers (IEEE) 802.11 standard, LTE, or NR.

(33) Some examples of sidelink communication may include vehicle-based communication devices that can communicate from vehicle-to-vehicle (V2V), vehicle-to-infrastructure (V2I) (e.g., from the vehicle-based communication device to road infrastructure nodes such as a Road Side Unit (RSU)), vehicle-to-network (V2N) (e.g., from the vehicle-based communication device to one or more network nodes, such as a base station), vehicle-to-pedestrian (V2P), cellular vehicle-to-everything (C-V2X), and/or a combination thereof and/or with other devices, which can be collectively referred to as vehicle-to-anything (V2X) communications. Sidelink communication may be based on V2X or other D2D communication, such as Proximity Services (ProSe), etc. In addition to UEs, sidelink communication may also be transmitted and received by other transmitting and receiving devices, such as Road Side Unit (RSU) **107**, etc.

(34) The wireless communications system may further include a Wi-Fi access point (AP) **150** in communication with Wi-Fi stations (STAs) **152** via communication links **154**, e.g., in a 5 GHz unlicensed frequency spectrum or the like. When communicating in an unlicensed frequency spectrum, the STAs **152**/AP **150** may perform a clear channel assessment (CCA) prior to communicating in order to determine whether the channel is available.

(35) The small cell **102'** may operate in a licensed and/or an unlicensed frequency spectrum. When

operating in an unlicensed frequency spectrum, the small cell **102'** may employ NR and use the same unlicensed frequency spectrum (e.g., 5 GHz or the like) as used by the Wi-Fi AP **150**. The small cell **102'**, employing NR in an unlicensed frequency spectrum, may boost coverage to and/or increase capacity of the access network.

(36) The electromagnetic spectrum is often subdivided, based on frequency/wavelength, into various classes, bands, channels, etc. In 5G NR, two initial operating bands have been identified as frequency range designations FR1 (410 MHz-7.125 GHz) and FR2 (24.25 GHz-52.6 GHz). Although a portion of FR1 is greater than 6 GHz, FR1 is often referred to (interchangeably) as a “sub-6 GHz” band in various documents and articles. A similar nomenclature issue sometimes occurs with regard to FR2, which is often referred to (interchangeably) as a “millimeter wave” band in documents and articles, despite being different from the extremely high frequency (EHF) band (30 GHz-300 GHz) which is identified by the International Telecommunications Union (ITU) as a “millimeter wave” band.

(37) The frequencies between FR1 and FR2 are often referred to as mid-band frequencies. Recent 5G NR studies have identified an operating band for these mid-band frequencies as frequency range designation FR3 (7.125 GHz-24.25 GHz). Frequency bands falling within FR3 may inherit FR1 characteristics and/or FR2 characteristics, and thus may effectively extend features of FR1 and/or FR2 into mid-band frequencies. In addition, higher frequency bands are currently being explored to extend 5G NR operation beyond 52.6 GHz. For example, three higher operating bands have been identified as frequency range designations FR4a or FR4-1 (52.6 GHz-71 GHz), FR4 (52.6 GHz-114.25 GHz), and FR5 (114.25 GHz-300 GHz). Each of these higher frequency bands falls within the EHF band.

(38) With the above aspects in mind, unless specifically stated otherwise, it should be understood that the term “sub-6 GHz” or the like if used herein may broadly represent frequencies that may be less than 6 GHz, may be within FR1, or may include mid-band frequencies. Further, unless specifically stated otherwise, it should be understood that the term “millimeter wave” or the like if used herein may broadly represent frequencies that may include mid-band frequencies, may be within FR2, FR4, FR4-a or FR4-1, and/or FR5, or may be within the EHF band.

(39) A base station **102**, whether a small cell **102'** or a large cell (e.g., macro base station), may include and/or be referred to as an eNB, gNodeB (gNB), or another type of base station. Some base stations, such as gNB **180** may operate in a traditional sub 6 GHz spectrum, in mmW frequencies, and/or near mmW frequencies in communication with the UE **104**. When the gNB **180** operates in mmW or near mmW frequencies, the gNB **180** may be referred to as an mmW base station.

Extremely high frequency (EHF) is part of the RF in the electromagnetic spectrum. EHF has a range of 30 GHz to 300 GHz and a wavelength between 1 millimeter and 10 millimeters. Radio waves in the band may be referred to as a mmW waves. Near mmW may extend down to a frequency of 3 GHz with a wavelength of 100 millimeters. The super high frequency (SHF) band extends between 3 GHz and 30 GHz, also referred to as centimeter wave. Communications using the mmW/near mmW radio frequency (RF) band (e.g., 3 GHz-300 GHz) has extremely high path loss and a short range. The mmW base station **180** may utilize beamforming **182** with the UE **104** to compensate for the extremely high path loss and short range. The base station **180** and the UE **104** may each include a plurality of antennas, such as antenna elements, antenna panels, and/or antenna arrays to facilitate the beamforming.

(40) The base station **180** may transmit a beamformed signal to the UE **104** in one or more transmit directions **182'**. The UE **104** may receive the beamformed signal from the base station **180** in one or more receive directions **182''**. The UE **104** may also transmit a beamformed signal to the base station **180** in one or more transmit directions. The base station **180** may receive the beamformed signal from the UE **104** in one or more receive directions. The base station **180**/UE **104** may perform beam training to determine the best receive and transmit directions for each of the base station **180**/UE **104**. The transmit and receive directions for the base station **180** may or may not be

the same. The transmit and receive directions for the UE **104** may or may not be the same.

(41) The EPC **160** may include a Mobility Management Entity (MME) **162**, other MMEs **164**, a Serving Gateway **166**, a Multimedia Broadcast Multicast Service (MBMS) Gateway **168**, a Broadcast Multicast Service Center (BM-SC) **170**, and a Packet Data Network (PDN) Gateway **172**. The MME **162** may be in communication with a Home Subscriber Server (HSS) **174**. The MME **162** is the control node that processes the signaling between the UEs **104** and the EPC **160**. Generally, the MME **162** provides bearer and connection management. All user Internet protocol (IP) packets are transferred through the Serving Gateway **166**, which itself is connected to the PDN Gateway **172**. The PDN Gateway **172** provides UE IP address allocation as well as other functions. The PDN Gateway **172** and the BM-SC **170** are connected to the IP Services **176**. The IP Services **176** may include the Internet, an intranet, an IP Multimedia Subsystem (IMS), a PS Streaming Service, and/or other IP services. The BM-SC **170** may provide functions for MBMS user service provisioning and delivery. The BM-SC **170** may serve as an entry point for content provider MBMS transmission, may be used to authorize and initiate MBMS Bearer Services within a public land mobile network (PLMN), and may be used to schedule MBMS transmissions. The MBMS Gateway **168** may be used to distribute MBMS traffic to the base stations **102** belonging to a Multicast Broadcast Single Frequency Network (MBSFN) area broadcasting a particular service, and may be responsible for session management (start/stop) and for collecting eMBMS related charging information.

(42) The core network **190** may include an Access and Mobility Management Function (AMF) **192**, other AMFs **193**, a Session Management Function (SMF) **194**, and a User Plane Function (UPF) **195**. The AMF **192** may be in communication with a Unified Data Management (UDM) **196**. The AMF **192** is the control node that processes the signaling between the UEs **104** and the core network **190**. Generally, the AMF **192** provides QoS flow and session management. All user Internet protocol (IP) packets are transferred through the UPF **195**. The UPF **195** provides UE IP address allocation as well as other functions. The UPF **195** is connected to the IP Services **197**. The IP Services **197** may include the Internet, an intranet, an IP Multimedia Subsystem (IMS), a Packet Switch (PS) Streaming (PSS) Service, and/or other IP services.

(43) The base station may include and/or be referred to as a gNB, Node B, eNB, an access point, a base transceiver station, a radio base station, a radio transceiver, a transceiver function, a basic service set (BSS), an extended service set (ESS), a transmit reception point (TRP), or some other suitable terminology. The base station **102** provides an access point to the EPC **160** or core network **190** for a UE **104**. Examples of UEs **104** include a cellular phone, a smart phone, a session initiation protocol (SIP) phone, a laptop, a personal digital assistant (PDA), a satellite radio, a global positioning system, a multimedia device, a video device, a digital audio player (e.g., MP3 player), a camera, a game console, a IAB let, a smart device, a wearable device, a vehicle, an electric meter, a gas pump, a large or small kitchen appliance, a healthcare device, an implant, a sensor/actuator, a display, or any other similar functioning device. Some of the UEs **104** may be referred to as IoT devices (e.g., parking meter, gas pump, toaster, vehicles, heart monitor, etc.). The UE **104** may also be referred to as a station, a mobile station, a subscriber station, a mobile unit, a subscriber unit, a wireless unit, a remote unit, a mobile device, a wireless device, a wireless communications device, a remote device, a mobile subscriber station, an access terminal, a mobile terminal, a wireless terminal, a remote terminal, a handset, a user agent, a mobile client, a client, or some other suitable terminology. In some scenarios, the term UE may also apply to one or more companion devices such as in a device constellation arrangement. One or more of these devices may collectively access the network and/or individually access the network.

(44) Deployment of communication systems, such as 5G new radio (NR) systems, may be arranged in multiple manners with various components or constituent parts. In a 5G NR system, or network, a network node, a network entity, a mobility element of a network, a radio access network (RAN) node, a core network node, a network element, or a network equipment, such as a base station (BS),

or one or more units (or one or more components) performing base station functionality, may be implemented in an aggregated or disaggregated architecture. For example, a BS (such as a Node B (NB), evolved NB (eNB), NR BS, 5G NB, access point (AP), a transmit receive point (TRP), or a cell, etc.) may be implemented as an aggregated base station (also known as a standalone BS or a monolithic BS) or a disaggregated base station.

(45) An aggregated base station may be configured to utilize a radio protocol stack that is physically or logically integrated within a single RAN node. A disaggregated base station may be configured to utilize a protocol stack that is physically or logically distributed among two or more units (such as one or more central or centralized units (CUs), one or more distributed units (DUs), or one or more radio units (RUs)). In some aspects, a CU may be implemented within a RAN node, and one or more DUs may be co-located with the CU, or alternatively, may be geographically or virtually distributed throughout one or multiple other RAN nodes. The DUs may be implemented to communicate with one or more RUs. Each of the CU, DU and RU also can be implemented as virtual units, i.e., a virtual central unit (VCU), a virtual distributed unit (VDU), or a virtual radio unit (VRU).

(46) Base station-type operation or network design may consider aggregation characteristics of base station functionality. For example, disaggregated base stations may be utilized in an integrated access backhaul (IAB) network, an open radio access network (O-RAN (such as the network configuration sponsored by the O-RAN Alliance)), or a virtualized radio access network (vRAN, also known as a cloud radio access network (C-RAN)). Disaggregation may include distributing functionality across two or more units at various physical locations, as well as distributing functionality for at least one unit virtually, which can enable flexibility in network design. The various units of the disaggregated base station, or disaggregated RAN architecture, can be configured for wired or wireless communication with at least one other unit.

(47) FIG. 15 shows a diagram illustrating an example disaggregated base station **1500** architecture. The disaggregated base station **1500** architecture may include one or more central units (CUs) **1510** that can communicate directly with a core network **1520** via a backhaul link, or indirectly with the core network **1520** through one or more disaggregated base station units (such as a Near-Real Time (Near-RT) RAN Intelligent Controller (RIC) **1525** via an E2 link, or a Non-Real Time (Non-RT) RIC **1515** associated with a Service Management and Orchestration (SMO) Framework **1505**, or both). A CU **1510** may communicate with one or more distributed units (DUs) **1530** via respective midhaul links, such as an F1 interface. The DUs **1530** may communicate with one or more radio units (RUs) **1540** via respective fronthaul links. The RUs **1540** may communicate with respective UE **104** via one or more radio frequency (RF) access links. In some implementations, the UE **104** may be simultaneously served by multiple RUs **1540**.

(48) Each of the units, i.e., the CUs **1510**, the DUs **1530**, the RUs **1540**, as well as the Near-RT RICs **1525**, the Non-RT RICs **1515** and the SMO Framework **1505**, may include one or more interfaces or be coupled to one or more interfaces configured to receive or transmit signals, data, or information (collectively, signals) via a wired or wireless transmission medium. Each of the units, or an associated processor or controller providing instructions to the communication interfaces of the units, can be configured to communicate with one or more of the other units via the transmission medium. For example, the units can include a wired interface configured to receive or transmit signals over a wired transmission medium to one or more of the other units. Additionally, the units can include a wireless interface, which may include a receiver, a transmitter or transceiver (such as a radio frequency (RF) transceiver), configured to receive or transmit signals, or both, over a wireless transmission medium to one or more of the other units.

(49) In some aspects, the CU **1510** may host one or more higher layer control functions. Such control functions can include radio resource control (RRC), packet data convergence protocol (PDCP), service data adaptation protocol (SDAP), or the like. Each control function can be implemented with an interface configured to communicate signals with other control functions

hosted by the CU **1510**. The CU **1510** may be configured to handle user plane functionality (i.e., Central Unit-User Plane (CU-UP)), control plane functionality (i.e., Central Unit-Control Plane (CU-CP)), or a combination thereof. In some implementations, the CU **1510** can be logically split into one or more CU-UP units and one or more CU-CP units. The CU-UP unit can communicate bidirectionally with the CU-CP unit via an interface, such as the E1 interface when implemented in an O-RAN configuration. The CU **1510** can be implemented to communicate with the DU **1530**, as necessary, for network control and signaling.

(50) The DU **1530** may correspond to a logical unit that includes one or more base station functions to control the operation of one or more RUs **1540**. In some aspects, the DU **1530** may host one or more of a radio link control (RLC) layer, a medium access control (MAC) layer, and one or more high physical (PHY) layers (such as modules for forward error correction (FEC) encoding and decoding, scrambling, modulation and demodulation, or the like) depending, at least in part, on a functional split, such as those defined by the 3GPP. In some aspects, the DU **1530** may further host one or more low PHY layers. Each layer (or module) can be implemented with an interface configured to communicate signals with other layers (and modules) hosted by the DU **1530**, or with the control functions hosted by the CU **1510**.

(51) Lower-layer functionality can be implemented by one or more RUs **1540**. In some deployments, an RU **1540**, controlled by a DU **1530**, may correspond to a logical node that hosts RF processing functions, or low-PHY layer functions (such as performing fast Fourier transform (FFT), inverse FFT (iFFT), digital beamforming, physical random access channel (PRACH) extraction and filtering, or the like), or both, based at least in part on the functional split, such as a lower layer functional split. In such an architecture, the RU(s) **1540** can be implemented to handle over the air (OTA) communication with one or more UEs **104**. In some implementations, real-time and non-real-time aspects of control and user plane communication with the RU(s) **1540** can be controlled by the corresponding DU **1530**. In some scenarios, this configuration can enable the DU(s) **1530** and the CU **1510** to be implemented in a cloud-based RAN architecture, such as a vRAN architecture.

(52) The SMO Framework **1505** may be configured to support RAN deployment and provisioning of non-virtualized and virtualized network elements. For non-virtualized network elements, the SMO Framework **1505** may be configured to support the deployment of dedicated physical resources for RAN coverage requirements which may be managed via an operations and maintenance interface (such as an O1 interface). For virtualized network elements, the SMO Framework **1505** may be configured to interact with a cloud computing platform (such as an open cloud (O-Cloud) **1590**) to perform network element life cycle management (such as to instantiate virtualized network elements) via a cloud computing platform interface (such as an O2 interface). Such virtualized network elements can include, but are not limited to, CUs **1510**, DUs **1530**, RUs **1540** and Near-RT RICs **1525**. In some implementations, the SMO Framework **1505** can communicate with a hardware aspect of a 4G RAN, such as an open eNB (O-eNB) **1511**, via an O1 interface. Additionally, in some implementations, the SMO Framework **1505** can communicate directly with one or more RUs **1540** via an O1 interface. The SMO Framework **1505** also may include a Non-RT RIC **1515** configured to support functionality of the SMO Framework **1505**.

(53) The Non-RT RIC **1515** may be configured to include a logical function that enables non-real-time control and optimization of RAN elements and resources, Artificial Intelligence/Machine Learning (AI/ML) workflows including model training and updates, or policy-based guidance of applications/features in the Near-RT RIC **1525**. The Non-RT RIC **1515** may be coupled to or communicate with (such as via an A1 interface) the Near-RT RIC **1525**. The Near-RT RIC **1525** may be configured to include a logical function that enables near-real-time control and optimization of RAN elements and resources via data collection and actions over an interface (such as via an E2 interface) connecting one or more CUs **1510**, one or more DUs **1530**, or both, as well as an O-eNB, with the Near-RT RIC **1525**.

(54) In some implementations, to generate AI/ML models to be deployed in the Near-RT RIC 1525, the Non-RT RIC 1515 may receive parameters or external enrichment information from external servers. Such information may be utilized by the Near-RT RIC 1525 and may be received at the SMO Framework 1505 or the Non-RT RIC 1515 from non-network data sources or from network functions. In some examples, the Non-RT RIC 1515 or the Near-RT RIC 1525 may be configured to tune RAN behavior or performance. For example, the Non-RT RIC 1515 may monitor long-term trends and patterns for performance and employ AI/ML models to perform corrective actions through the SMO Framework 1505 (such as reconfiguration via O1) or via creation of RAN management policies (such as A1 policies).

(55) FIG. 2A is a diagram 200 illustrating an example of a first subframe within a 5G/NR frame structure. FIG. 2B is a diagram 230 illustrating an example of DL channels within a 5G/NR subframe. FIG. 2C is a diagram 250 illustrating an example of a second subframe within a 5G/NR frame structure. FIG. 2D is a diagram 280 illustrating an example of UL channels within a 5G/NR subframe. The 5G/NR frame structure may be frequency division duplexed (FDD) in which for a particular set of subcarriers (carrier system bandwidth), subframes within the set of subcarriers are dedicated for either DL or UL, or may be time division duplexed (TDD) in which for a particular set of subcarriers (carrier system bandwidth), subframes within the set of subcarriers are dedicated for both DL and UL. In the examples provided by FIGS. 2A, 2C, the 5G/NR frame structure is assumed to be TDD, with subframe 4 being configured with slot format 28 (with mostly DL), where D is DL, U is UL, and X is flexible for use between DL/UL, and subframe 3 being configured with slot format 34 (with mostly UL). While subframes 3, 4 are shown with slot formats 34, 28, respectively, any particular subframe may be configured with any of the various available slot formats 0-61. Slot formats 0, 1 are all DL, UL, respectively. Other slot formats 2-61 include a mix of DL, UL, and flexible symbols. UEs are configured with the slot format (dynamically through DL control information (DCI), or semi-statically/statically through radio resource control (RRC) signaling) through a received slot format indicator (SFI). Note that the description infra applies also to a 5G/NR frame structure that is TDD.

(56) FIGS. 2A-2D illustrate a frame structure, and the aspects of the present disclosure may be applicable to other wireless communication technologies, which may have a different frame structure and/or different channels. A frame (10 ms) may be divided into 10 equally sized subframes (1 ms). Each subframe may include one or more time slots. Subframes may also include mini-slots, which may include 7, 4, or 2 symbols. Each slot may include 14 or 12 symbols, depending on whether the cyclic prefix (CP) is normal or extended. For normal CP, each slot may include 14 symbols, and for extended CP, each slot may include 12 symbols. The symbols on DL may be CP orthogonal frequency division multiplexing (OFDM) (CP-OFDM) symbols. The symbols on UL may be CP-OFDM symbols (for high throughput scenarios) or discrete Fourier transform (DFT) spread OFDM (DFT-s-OFDM) symbols (also referred to as single carrier frequency-division multiple access (SC-FDMA) symbols) (for power limited scenarios; limited to a single stream transmission). The number of slots within a subframe is based on the CP and the numerology. The numerology defines the subcarrier spacing (SCS) and, effectively, the symbol length/duration, which is equal to $1/\text{SCS}$.

(57) TABLE-US-00001 SCS μ $\Delta f = 2^{\mu} \cdot \Delta f_{\text{ref}}$ [kHz] Cyclic prefix 0 15 Normal 1 30 Normal 2 60 Normal, Extended 3 120 Normal 4 240 Normal

(58) For normal CP (14 symbols/slot), different numerologies μ 0 to 4 allow for 1, 2, 4, 8, and 16 slots, respectively, per subframe. For extended CP, the numerology 2 allows for 4 slots per subframe. Accordingly, for normal CP and numerology μ , there are $14 \cdot 2^{\mu}$ symbols/slot and 2^{μ} slots/subframe. The subcarrier spacing may be equal to $2^{\mu} \cdot 15$ kHz, where μ is the numerology 0 to 4. As such, the numerology $\mu=0$ has a subcarrier spacing of 15 kHz and the numerology $\mu=4$ has a subcarrier spacing of 240 kHz. The symbol length/duration is inversely related to the subcarrier spacing. FIGS. 2A-2D provide an example of normal CP with 14 symbols per slot and

numerology $\mu=2$ with 4 slots per subframe. The slot duration is 0.25 ms, the subcarrier spacing is 60 kHz, and the symbol duration is approximately 16.67 μ s. Within a set of frames, there may be one or more different bandwidth parts (BWPs) (see FIG. 2B) that are frequency division multiplexed. Each BWP may have a particular numerology and CP (normal or extended).

(59) A resource grid may be used to represent the frame structure. Each time slot includes a resource block (RB) (also referred to as physical RBs (PRBs)) that extends 12 consecutive subcarriers. The resource grid is divided into multiple resource elements (REs). The number of bits carried by each RE depends on the modulation scheme.

(60) As illustrated in FIG. 2A, some of the REs carry reference (pilot) signals (RS) for the UE. The RS may include demodulation RS (DM-RS) (indicated as R for one particular configuration, but other DM-RS configurations are possible) and channel state information reference signals (CSI-RS) for channel estimation at the UE. The RS may also include beam measurement RS (BRS), beam refinement RS (BRRS), and phase tracking RS (PT-RS).

(61) FIG. 2B illustrates an example of various DL channels within a subframe of a frame. The physical downlink control channel (PDCCH) carries DCI within one or more control channel elements (CCEs) (e.g., 1, 2, 4, 8, or 16 CCEs), each CCE including six RE groups (REGs), each REG including 12 consecutive REs in an OFDM symbol of an RB. A PDCCH within one BWP may be referred to as a control resource set (CORESET). A UE is configured to monitor PDCCH candidates in a PDCCH search space (e.g., common search space, UE-specific search space) during PDCCH monitoring occasions on the CORESET, where the PDCCH candidates have different DCI formats and different aggregation levels. Additional BWPs may be located at greater and/or lower frequencies across the channel bandwidth. A primary synchronization signal (PSS) may be within symbol 2 of particular subframes of a frame. The PSS is used by a UE 104 to determine subframe/symbol timing and a physical layer identity. A secondary synchronization signal (SSS) may be within symbol 4 of particular subframes of a frame. The SSS is used by a UE to determine a physical layer cell identity group number and radio frame timing. Based on the physical layer identity and the physical layer cell identity group number, the UE can determine a physical cell identifier (PCI). Based on the PCI, the UE can determine the locations of the DM-RS. The physical broadcast channel (PBCH), which carries a master information block (MIB), may be logically grouped with the PSS and SSS to form a synchronization signal (SS)/PBCH block (also referred to as SS block (SSB)). The MIB provides a number of RBs in the system bandwidth and a system frame number (SFN). The physical downlink shared channel (PDSCH) carries user data, broadcast system information not transmitted through the PBCH such as system information blocks (SIBs), and paging messages.

(62) As illustrated in FIG. 2C, some of the REs carry DM-RS (indicated as R for one particular configuration, but other DM-RS configurations are possible) for channel estimation at the base station. The UE may transmit DM-RS for the physical uplink control channel (PUCCH) and DM-RS for the physical uplink shared channel (PUSCH). The PUSCH DM-RS may be transmitted in the first one or two symbols of the PUSCH. The PUCCH DM-RS may be transmitted in different configurations depending on whether short or long PUCCHs are transmitted and depending on the particular PUCCH format used. The UE may transmit sounding reference signals (SRS). The SRS may be transmitted in the last symbol of a subframe. The SRS may have a comb structure, and a UE may transmit SRS on one of the combs. The SRS may be used by a base station for channel quality estimation to enable frequency-dependent scheduling on the UL.

(63) FIG. 2D illustrates an example of various UL channels within a subframe of a frame. The PUCCH may be located as indicated in one configuration. The PUCCH carries uplink control information (UCI), such as scheduling requests, a channel quality indicator (CQI), a precoding matrix indicator (PMI), a rank indicator (RI), and hybrid automatic repeat request (HARQ) acknowledgment (ACK) (HARQ-ACK) feedback (i.e., one or more HARQ ACK bits indicating one or more ACK and/or negative ACK (NACK)). The PUSCH carries data, and may additionally

be used to carry a buffer status report (BSR), a power headroom report (PHR), and/or UCI.

(64) FIG. 3 is a block diagram of an IAB node **310** in communication with a UE **350** in an access network. In the DL, IP packets from the EPC **160** or core network **190** may be provided to a controller/processor **375**. The controller/processor **375** implements layer 3 and/or layer 2 functionality. Layer 3 includes a radio resource control (RRC) layer, and may be performed if the IAB node is a donor IAB node. Layer 2 includes a service data adaptation protocol (SDAP) layer, a packet data convergence protocol (PDCP) layer, a radio link control (RLC) layer, and a medium access control (MAC) layer. The controller/processor **375** provides RRC layer functionality associated with broadcasting of system information (e.g., MIB, SIBs), RRC connection control (e.g., RRC connection paging, RRC connection establishment, RRC connection modification, and RRC connection release), inter radio access technology (RAT) mobility, and measurement configuration for UE measurement reporting; PDCP layer functionality associated with header compression/decompression, security (ciphering, deciphering, integrity protection, integrity verification), and handover support functions; RLC layer functionality associated with the transfer of upper layer packet data units (PDUs), error correction through ARQ, concatenation, segmentation, and reassembly of RLC service data units (SDUs), re-segmentation of RLC data PDUs, and reordering of RLC data PDUs; and MAC layer functionality associated with mapping between logical channels and transport channels, multiplexing of MAC SDUs onto transport blocks (TBs), demultiplexing of MAC SDUs from TBs, scheduling information reporting, error correction through HARQ, priority handling, and logical channel prioritization.

(65) The transmit (TX) processor **316** and the receive (RX) processor **370** implement layer 1 functionality associated with various signal processing functions. Layer 1, which includes a physical (PHY) layer, may include error detection on the transport channels, forward error correction (FEC) coding/decoding of the transport channels, interleaving, rate matching, mapping onto physical channels, modulation/demodulation of physical channels, and MIMO antenna processing. The TX processor **316** handles mapping to signal constellations based on various modulation schemes (e.g., binary phase-shift keying (BPSK), quadrature phase-shift keying (QPSK), M-phase-shift keying (M-PSK), M-quadrature amplitude modulation (M-QAM)). The coded and modulated symbols may then be split into parallel streams. Each stream may then be mapped to an OFDM subcarrier, multiplexed with a reference signal (e.g., pilot) in the time and/or frequency domain, and then combined together using an Inverse Fast Fourier Transform (IFFT) to produce a physical channel carrying a time domain OFDM symbol stream. The OFDM stream is spatially precoded to produce multiple spatial streams. Channel estimates from a channel estimator **374** may be used to determine the coding and modulation scheme, as well as for spatial processing. The channel estimate may be derived from a reference signal and/or channel condition feedback transmitted by the UE **350**. Each spatial stream may then be provided to a different antenna **320** via a separate transmitter **318Tx**. Each transmitter **318Tx** may modulate an RF carrier with a respective spatial stream for transmission.

(66) At the UE **350**, each receiver **354Rx** receives a signal through its respective antenna **352**. Each receiver **354Rx** recovers information modulated onto an RF carrier and provides the information to the receive (RX) processor **356**. The TX processor **368** and the RX processor **356** implement layer 1 functionality associated with various signal processing functions. The RX processor **356** may perform spatial processing on the information to recover any spatial streams destined for the UE **350**. If multiple spatial streams are destined for the UE **350**, they may be combined by the RX processor **356** into a single OFDM symbol stream. The RX processor **356** then converts the OFDM symbol stream from the time-domain to the frequency domain using a Fast Fourier Transform (FFT). The frequency domain signal comprises a separate OFDM symbol stream for each subcarrier of the OFDM signal. The symbols on each subcarrier, and the reference signal, are recovered and demodulated by determining the most likely signal constellation points transmitted by the IAB node **310**. These soft decisions may be based on channel estimates computed by the

channel estimator **358**. The soft decisions are then decoded and deinterleaved to recover the data and control signals that were originally transmitted by the IAB node **310** on the physical channel. The data and control signals are then provided to the controller/processor **359**, which implements layer 3 and layer 2 functionality.

(67) The controller/processor **359** can be associated with a memory **360** that stores program codes and data. The memory **360** may be referred to as a computer-readable medium. In the UL, the controller/processor **359** provides demultiplexing between transport and logical channels, packet reassembly, deciphering, header decompression, and control signal processing to recover IP packets from the EPC **160**. The controller/processor **359** is also responsible for error detection using an ACK and/or NACK protocol to support HARQ operations.

(68) Similar to the functionality described in connection with the DL transmission by the IAB node **310**, the controller/processor **359** provides RRC layer functionality associated with system information (e.g., MIB, SIBs) acquisition, RRC connections, and measurement reporting; PDCP layer functionality associated with header compression/decompression, and security (ciphering, deciphering, integrity protection, integrity verification); RLC layer functionality associated with the transfer of upper layer PDUs, error correction through ARQ, concatenation, segmentation, and reassembly of RLC SDUs, re-segmentation of RLC data PDUs, and reordering of RLC data PDUs; and MAC layer functionality associated with mapping between logical channels and transport channels, multiplexing of MAC SDUs onto TBs, demultiplexing of MAC SDUs from TBs, scheduling information reporting, error correction through HARQ, priority handling, and logical channel prioritization.

(69) Channel estimates derived by a channel estimator **358** from a reference signal or feedback transmitted by the IAB node **310** may be used by the TX processor **368** to select the appropriate coding and modulation schemes, and to facilitate spatial processing. The spatial streams generated by the TX processor **368** may be provided to different antenna **352** via separate transmitters **354Tx**. Each transmitter **354Tx** may modulate an RF carrier with a respective spatial stream for transmission.

(70) The UL transmission is processed at the IAB node **310** in a manner similar to that described in connection with the receiver function at the UE **350**. Each receiver **318Rx** receives a signal through its respective antenna **320**. Each receiver **318Rx** recovers information modulated onto an RF carrier and provides the information to a RX processor **370**.

(71) The controller/processor **375** can be associated with a memory **376** that stores program codes and data. The memory **376** may be referred to as a computer-readable medium. In the UL, the controller/processor **375** provides demultiplexing between transport and logical channels, packet reassembly, deciphering, header decompression, control signal processing to recover IP packets from the UE **350**. IP packets from the controller/processor **375** may be provided to the EPC **160** or core network **190**, e.g., via a donor IAB node if the IAB node is not a donor IAB node. The controller/processor **375** is also responsible for error detection using an ACK and/or NACK protocol to support HARQ operations.

(72) At least one of the TX processor **368**, the RX processor **356**, and the controller/processor **359** may be configured to perform aspects in connection with a time delta component **198** and/or a time delta indication component **199**, e.g., as described in connection with FIG. 1.

(73) At least one of the TX processor **316**, the RX processor **370**, and the controller/processor **375** may be configured to perform aspects in connection with a time delta component **198** and/or a time delta indication component **199**, e.g., as described in connection with FIG. 1.

(74) FIG. 4 is a diagram illustrating an IAB network **400**. The IAB network provides access network functionality between access nodes (ANs) and other ANs/UEs, and backhaul network functionality between ANs. The ANs include IAB-donors, which have a wireline connection to the core network, and IAB nodes, which operate wirelessly and relay traffic to/from IAB-donors through one or more AN hops. The IAB ANs share resources between the access and backhaul.

That is, the resources used for access communication between the ANs and ANs/UEs are also used for backhaul communication between the ANs.

(75) The IAB network **400** may include an anchor node (that may be referred to herein as an “IAB donor”) **410** and access nodes (that may be referred to herein as “IAB nodes”) **420**. The IAB donor **410** may be a base station, such as a gNB or eNB, and may perform functions to control the IAB network **400**. The IAB nodes **420** may comprise L2 relay nodes, etc. Together, the IAB donor **410** and the IAB nodes **420** share resources to provide an access network and a backhaul network to core network **490**. For example, resources may be shared between access links and backhaul links in the IAB network.

(76) UEs **430** interface with the IAB nodes **420** or the IAB donor **410** through access links **470**. The IAB nodes **420** communicate with each other and with the IAB donor **410** through backhaul links **460**. The IAB donor **410** is connected to the core network **490** via a wireline backhaul link **450**. UEs **430** communicate with the core network by relaying messages through their respective access link **470** to the IAB node **420**, which then may relay the message through backhaul links **460** to the IAB donor **410** to communicate to the core network through the wireline backhaul link **450**. Similarly, the core network may communicate with a UE **430** by sending a message to the IAB donor **410** through the wireline backhaul link **450**. The IAB donor **410** sends the message through the IAB network **400** via backhaul links **460** to the IAB node **420** connected to the UE **430**, and the IAB node **420** sends the message to the UE **430** via the access link **470**.

(77) Each IAB node, e.g., including IAB donor **410** and each IAB node **420**, may use a PCI value. The PCI value may serve as an identifier for that IAB donor **410** or IAB node **420**. The PCI value may be used to determine a scrambling sequence that is applied to physical signals and/or channels that are transmitted by a particular IAB node. For example, a PSS and/or the SSS transmitted by the respective IAB donor **410** or IAB node **420** may be scrambled using a scrambling sequence that is based on the PCI used by the respective IAB node.

(78) FIG. 5 illustrates a second diagram illustrating an IAB network **500** and components thereof. The IAB network **500** includes an IAB donor **510** and IAB nodes **520a** and **520b**. The IAB nodes, as well as the IAB donor, may provide wireless access links to UEs **530a**, **530b**, **530c**.

(79) The IAB donor **510** may be considered a root node of the tree structure of the IAB network **500**. The IAB donor node **510** may be connected to the core network **590** via a wired connection **591**. The wired connection may comprise, e.g., a wireline fiber. The IAB donor node **510** may provide a connection to one or more IAB nodes **520a**. The IAB nodes **520a** may each be referred to as a child node of the IAB donor node **510**. The IAB donor node **510** may also provide a connection to one or more UE **530a**, which may be referred to as a child UE of IAB donor **510**. The IAB donor **510** may be connected to its child IAB nodes **520a** via backhaul links **560**, and may be connected to the child UEs **530a** via access links **570**. The IAB nodes **520a** that are children nodes of IAB node **510** may also have IAB node(s) **520b** and/or UE(s) **530b** as children. For example, IAB nodes **520b** may further connect to child nodes and/or child UEs. FIG. 5 illustrates IAB nodes **520b** providing an access link to UEs **530c**, respectively.

(80) The IAB donor **510** may include a central unit (CU) and a distributed unit (DU). The central unit CU may provide control for the IAB nodes **520a**, **520b** in the IAB network **500**. For example, the CU may control the IAB network **500** through configuration. The CU may perform RRC/PDCP layer functions. The IAB donors **510** further include a DU that performs scheduling. For example, the DU may schedule resources for communication by the child IAB nodes **520a** and/or UEs **530a** of the IAB donor **510**. The DU holds radio link control (RLC), media access control (MAC), a physical (PHY) layer functions.

(81) The IAB nodes **520a**, **520b** may include a mobile termination (MT) and a DU. The IAB node is an L2 relay node. The MT of IAB node **520a** may operate as a scheduled node, scheduled similar to a UE **530a** by the DU of the parent node, e.g., IAB donor **510**. The MT of IAB node **520b** may operate as a scheduled node of parent node **520a**. The DU may schedule the child IAB nodes **520b**

and UEs **530b** of the IAB node **520a**. As an IAB node may provide a connection to an IAB node that in turn provides a connection for another IAB node. The pattern of a parent IAB node comprising a DU that schedules a child IAB node/child UE may continue to more connections that illustrated in FIG. 5.

(82) FIG. 6 is a diagram **600** illustrating RLC channels in an IAB network. As discussed supra, the IAB network provides both access network functionality and backhaul network functionality. The IAB network includes an IAB donor with a CU **602** and DU **604**. Per the access network functionality, IAB ANs **606a**, **606b**, and **606c** may communicate with other UEs **608a** and **608b** and/or MTs of other IAB ANs through access RLC channels. Per the backhaul network functionality, IAB ANs **606a**, **606b**, and **606c** may route traffic to other ANs (e.g., **606a**, **606b**, and **606c**) through backhaul RLC channels. Access RLC channels include UE-to-DU/DU-to-UE, carrying PDCP for RRC or data radio bearers (DRBs), and MT-to-DU/DU-to-MT, carrying PDCP for RRC (or DRBs). Backhaul RLC channels include MT-to-DU/DU-to-MT, carrying backhaul adaptation protocol (BAP) messages for backhauling access traffic.

(83) FIGS. 7A, 7B, and 7C illustrate example aspects of different timing modes for IAB communication. FIG. 7A illustrates a timing example **700** of downlink transmission timing alignment across IAB nodes **702** and **704**. In some aspects, the downlink transmission timing may be aligned across each IAB node in an IAB network. The downlink transmission timing alignment may be referred to as “case 1” alignment or may be called by another name. FIG. 7A illustrates that DL transmission **708** by the DU of the IAB node **702** is aligned in time with the DL transmission **706** from the DU of the IAB node **704**. An uplink timing adjustment framework may be applied, in which a child IAB node (e.g., IAB node **704**) receives an uplink timing adjustment from a parent IAB node to apply for uplink transmissions to the parent IAB node (e.g., IAB node **702**). FIGS. 7B and 7C illustrate time diagrams **725** and **750**, respectively that illustrate aspects of additional timing modes that may be used, e.g., for providing or improving a duplexing capability between an IAB-MT and an IAB DU of an IAB node. The additional timing modes may provide improved timing alignment between the MT and DU of an IAB node for spatial division multiplexing, e.g., when the IAB node performs simultaneous, e.g., overlapping at least partially in time and/or frequency, IAB-MT downlink reception in one direction and IAB-DU uplink reception in another direction and/or performs IAB-MT uplink transmission in one direction and IAB-DU downlink transmission in another direction.

(84) FIG. 7B illustrates an example time diagram **725** showing a mode or type of timing alignment that aligns uplink transmission timing of the IAB-MT of the IAB node (e.g., the IAB node **704**) with the downlink transmission timing of the IAB-DU of the IAB node, e.g., which facilitates simultaneous (e.g., overlapping at least partially in time) transmissions at the IAB node (e.g., the IAB node **704**) by the IAB-MT (e.g., UL transmission **710**) and the IAB-DU (e.g., DL transmission **706**). The mode of alignment in FIG. 7B with the transmission alignment among the MT and DU of the IAB node may be referred to as “case 6” alignment or may be called by another name. The timing alignment, as shown in FIG. 7B, may further include the downlink transmission timing alignment across IAB nodes (e.g., case 1 alignment) as described in connection with FIG. 7A.

(85) FIG. 7C illustrates an example time diagram **750** showing a mode or type of timing alignment that aligns downlink reception timing of the IAB-MT of the IAB node (e.g., the IAB node **704**) with the uplink reception timing of the IAB-DU of the IAB node, e.g., which facilitates simultaneous (e.g., overlapping at least partially in time) reception at the IAB node (e.g., the IAB node **704**) by the IAB-MT (e.g., DL reception **716**) and the IAB-DU (e.g., UL reception **714**). The mode of alignment in FIG. 7C with the reception alignment among the MT and DU of the IAB node may be referred to as “case 7” alignment or may be called by another name. The timing alignment, as shown in FIG. 7C, may further include the downlink transmission timing alignment across IAB nodes (e.g., case 1 alignment) as described in connection with FIG. 7A.

(86) For an alignment mode that aligns transmissions of the MT and DU of an IAB node (e.g., case

6), the timing at a given IAB node may include the IAB-MT transmission timing being set by the IAB node to the timing obtained for the node's downlink transmission. For an alignment mode that aligns reception of the MT and DU of an IAB node (e.g., case 7), the timing at a parent IAB node (e.g., in contrast to the given IAB node for the transmission alignment mode) may include the IAB-MT transmission timing being obtained based on a timing advance loop plus an offset from a parent IAB node. Aspects presented herein provide for the timing alignment that also supports OTA synchronizations among IAB nodes.

(87) OTA synchronization provides a mechanism for an IAB node to set its downlink transmission timing based on OTA signals received from one or more parent IAB node. OTA synchronization enables the IAB nodes of an IAB network to synchronize with each other, e.g., in order to provide the DL transmission alignment across IAB nodes described in connection with FIG. 7A, separate from an independent synchronization source such as a global navigation satellite system (GNSS). OTA synchronization is based on a timing advance (TA) control for uplink transmission and an extra offset (T.sub.delta) that is indicated by a parent IAB node. The parent IAB node may indicate the TA and T.sub.delta to the child IAB node in a MAC-CE in some examples, e.g., to the child IAB node's MT.

(88) FIG. 8 illustrates an example time diagram **800** that shows timing differences between uplink transmission at a child IAB node **804** and uplink reception at a parent IAB node relative to downlink transmission timing at the parent IAB node. The difference between the uplink reception and the downlink transmission corresponds to delta (Δ). As the parent IAB node **802** and the child IAB node **804** operate in timing alignment between downlink transmissions from the DU of each IAB node, the transmission times are aligned with $Tx.sub.D = Tx.sup.P.sub.D$, in which the transmission time of the DU of the IAB node **804** is $Tx.sub.D$ and the transmission time of the DU of the parent IAB node is $Tx.sup.P.sub.D$. The timing advance may correspond to $TA = 2 Tp + \Delta$ and $\Delta = TA - 2Tp$, in which Tp corresponds to a propagation time between the parent IAB node **802** and the child IAB node **804**, as shown for the difference between the time that the DL TX **806** ends and the reception DL RX **808** at the IAB node **804** ends for the corresponding transmission from the parent IAB node **802**. The same propagation time is shown between the end of the uplink transmission **810** from the IAB node **804** and the end of reception **812** of the corresponding uplink transmission at the parent IAB node **802**. In this example, the $Tx.sub.D = Rx.sub.D - Tp = Rx.sub.D - (TA - \Delta)/2$, where $Rx.sub.D$ correspond to downlink reception at the DU of the IAB node **804**. As well, $Tp = TA/2 + T.sub.delta$ so that $T.sub.delta = -\Delta/2 = (Rx.sup.P.sub.U - Tx.sup.P.sub.D)/2$, where $Rx.sup.P.sub.U$ corresponds to uplink reception time at the parent IAB node **802** (e.g., **812**).

(89) As well, If an IAB node is provided an index T.sub.delta in a Timing Delta MAC CE from a serving cell, the IAB node may assume that

$(N.sub.TA/2 + N.sub.delta + T.sub.delta.Math.G.sub.step).Math.T.sub.c$, is a time difference between a DU transmission of a signal from the serving cell and a reception of the signal by the IAB-MT when $N.sub.TA/2 + N.sub.delta + T.sub.delta.Math.G.sub.step > 0$. $N.sub.TA$ may obtained in a similar manner as for a UE in a TAG containing the serving cell. $N.sub.delta$ and $G.sub.step$ may be determined as:

$N.sub.delta = -70528$ and $G.sub.step = 64$, if the serving cell providing the Timing Delta MAC CE operates in FR1,

$N.sub.delta = -17664$ and $G.sub.step = 32$, if the serving cell providing the Timing Delta MAC CE operates in FR2

(90) The IAB node may use the time difference to determine a DU transmission time.

(91) If an IAB node is operating based on transmission timing alignment between the MT and DU of the IAB node, e.g., as described in connection with FIG. 7B (e.g., case 6), the IAB-MT sets its own uplink transmission timing to be aligned with the downlink transmission timing of the IAB node's DU (e.g., which may be referred to as a co-located DU that is co-located with the MT of the IAB node). In this example, there is no uplink timing advance, as the parent IAB node does not

control the uplink transmission timing of the child IAB-MT and does not send a TA command. Without the closed-loop feedback in a TA command from the parent IAB node, the child IAB node may not reliably synchronize the downlink transmission timing of its IAB-DU (e.g., the downlink transmission timing being synchronized for all DUs in the IAB network, as described in connection with FIG. 7A) and the IAB node's synchronization with the other IAB nodes may experience drift.

(92) In some aspects, the IAB node may use T.sub.delta to assist with OTA synchronization along with transmission timing alignment at the IAB node (e.g., as in FIG. 7B) and/or reception timing alignment at the IAB node (as in FIG. 7C). T.sub.delta is a function of, and captures, the offset (e.g., the delta or difference) between the uplink reception timing and the downlink transmission timing at the parent node. As an IAB node operates in a mode for transmission timing alignment at the IAB node (e.g., case 6 or the alignment described in FIG. 7B), the parent IAB node may track the reception timing from the IAB node and its offset to the downlink transmission timing of the parent IAB node. The offset may be equal to the one-way propagation delay from the IAB node to the parent IAB node (e.g., because the uplink transmission timing of the IAB node in case 6 is the same as the downlink transmission timing of that IAB node, as shown for **710** and **706** in FIG. 7B, which is also aligned with the downlink transmission timing of the parent IAB node based on the downlink transmission timing, as shown for **706** and **708** in FIGS. 7A and 7B). The parent IAB node may send an updated T.sub.delta value to the child IAB node, e.g., if the parent IAB node determines that the timing offset between DL transmission and UL reception (based on the UL reception of the signal from the child IAB node) changes by more than a threshold amount of time. The child IAB node receives the updated T.sub.delta value and can adjust its downlink transmission timing to address possible drift in synchronization between the parent and child IAB nodes.

(93) In some aspects, an IAB node may change between timing alignment modes, e.g., between downlink transmission alignment across the DUs of the IAB network (e.g., case 1) and transmission timing alignment at a given IAB node (e.g., case 6) and/or reception timing alignment at an IAB node (e.g., case 7). As the IAB node may change between these at least these three different timing alignment modes, and possibly other timing alignment modes, the indication and/or interpretation of the T.sub.delta value from a parent IAB node may be different.

(94) As an example, if the IAB-MT follows the downlink transmission timing alignment among DUs (e.g., Case 1 alignment) without transmission alignment or reception alignment at an IAB node, the IAB node's uplink signal will arrive at a first time reference with a first offset to the parent node's downlink transmission timing. The first offset is configured or decided by the parent IAB node, e.g., based on its choice of implementation. In contrast, if the IAB-MT operates based on transmission timing alignment at a given IAB node (e.g. Case 6) and selects its own uplink transmission timing to align with its downlink transmission timing, the IAB node's uplink signal will arrive at a second time reference with a second offset to the parent IAB node's downlink transmission timing. The second offset is a function of one-way propagation delay between the IAB node and the parent node, for example. If the IAB node operates based on reception timing alignment at the IAB node (e.g., Case 7) with the IAB-MT transmission timing of the node obtained from the parent IAB node through a TA that instructs the IAB-MT to adjust its uplink transmission timing, the IAB node's uplink signal will arrive at the parent node a third time with a third offset to the parent IAB node's downlink transmission timing. The third offset is a function of one-way propagation delay between the parent IAB node and its own parent.

(95) Aspects presented herein enable an IAB node to apply or maintain OTA synchronization as the IAB node applies one of multiple different types of timing alignment, such as case 1, case 6, or case 7.

(96) In some aspects, there may be no indication of T.sub.delta from a parent IAB node to a child IAB node for a mode involving transmission timing alignment at the child IAB node (e.g., case 6) and/or a mode involving reception timing alignment at the child IAB node (e.g., case 7). If the IAB node receives T.sub.delta from a parent IAB node, the child IAB node may determine that the

T.sub.delta is associated with downlink transmission timing across DUs (e.g., case 1) and corresponds to the first offset in the examples described above. The IAB node may apply the T.sub.delta to synchronize its downlink transmission timing with the parent IAB node according to case 1 and not to alignment for case 6 or case 7.

(97) FIG. 9 illustrates an example **900** communication flow between an IAB node **902** and a parent IAB node **904**. At **906**, the IAB node **902** operates based on one of multiple different timing alignment modes. For example, the IAB node **902** may operate based on any of a case 1 timing alignment of downlink transmissions among DUs (such as in FIG. 7A), case 6 timing alignment of transmissions an IAB node (e.g., such as in FIG. 7B), and/or case 7 timing alignment of reception at an IAB node (e.g., such as in FIG. 7C). At **908**, the IAB node **902** receives a time difference parameter T.sub.delta from the parent IAB node **904**. The IAB node **902** determines that the T.sub.delta is applicable to case 1 timing alignment of downlink transmissions among DUs. At **912**, the IAB node **902** applies the T.sub.delta for case 1 timing alignment to adjust the downlink transmission timing of the DU of the IAB node to align with the DU of the parent IAB node **904**. Then, the IAB node **902** transmits downlink transmission(s) **914** having the timing adjusted based on T.sub.delta to synchronize the alignment to the downlink transmission **916** of the parent IAB node. As a further aspect, the IAB node may avoid drift and perform OTA synchronization if the IAB node is configured to operate based on case 1 timing alignment on a frequent set of resources, which may provide the IAB node with feedback from the parent IAB node to set and/or discipline the timing of the IAB node. As one example, the IAB node may be configured to operate based on case 1 timing at least one every 100 ms. In other examples, the IAB node may be configured to operate based on case 1 timing with a shorter frequency or with a longer frequency than 100 ms, such as every 200 ms, 300 ms, 400 ms, 500 ms, 600 ms, or 640 ms. As an example, the frequency may be associated with a length of hundreds of ms.

(98) In some aspects, the IAB-MT transmission timing of the IAB node may be obtained from a TA command from the parent IAB node plus an offset from the parent node. The IAB node operating in timing alignment according to case 7 may determine that $T.sub.delta(\text{for application in case 7 timing alignment}) = T.sub.delta(\text{associated with case 1 alignment}) + \text{an indicated offset}$.

(99) In some aspects, T.sub.delta may be indicated for use in various types of timing alignment at the IAB node. The parent IAB node may provide information to the child IAB node that indicates the association between the indicated T.sub.delta and the associated type of timing alignment. For example, the indication may indicate whether the T.sub.delta was measured while the parent node was operating in case 1 and the child node was not operating in case 6. The indication may indicate whether the T.sub.delta was measured while the parent node was operating in case 7 and the child node was not operating in case 6. The indication may indicate whether the T.sub.delta was measured while the child node was operating in case 6. The indication may assist the IAB node in determining the type of timing alignment to which the IAB node should apply the received T.sub.delta.

(100) In some aspects, the parent IAB node may provide a new T.sub.delta and/or N.sub.delta that is associated with transmission timing alignment between an MT and a DU at an IAB node (e.g., case 6). FIG. 10 illustrates an example communication flow **1000** that shows an example of a parent IAB node **1004** providing an additional T.sub.delta and/or N.sub.delta **1009** to an IAB node **1002** (e.g., that is a child node of parent IAB node **1004**). In some aspects, the additional T.sub.delta and/or N.sub.delta **1009** may be configured and/or indicated in addition to a first T.sub.delta and/or N.sub.delta **1008** that is applicable for case 1. The additional T.sub.delta and/or N.sub.delta **1009** may be signaled to the IAB node **1002** in a MAC-CE and/or a DCI. The additional T.sub.delta and/or N.sub.delta for case 6 timing alignment may be indicated to the IAB node separately from the T.sub.delta and/or N.sub.delta **1008** for case 1 alignment, e.g., in separate messages. In other aspects, the additional T.sub.delta and/or N.sub.delta **1009** may be signaled to the IAB node **1002** together with the T.sub.delta and/or N.sub.delta **1008** for the case 1 timing

alignment, e.g., in same message.

(101) In some aspects, the parent IAB node **1004** may indicate an additional offset value **1010** relative to the T.sub.delta and/or N.sub.delta **1008** for case 1 alignment. The additional offset **1010** may be configured an indicated in addition to the T.sub.delta and/or N.sub.delta **1008** for case 1 alignment and may be offset parameter(s) that are associated with case 6 timing alignment. The additional offset **1010**, relative to the T.sub.delta and/or N.sub.delta **1008**, for case 6 timing alignment may be indicated to the IAB node **1002** separately from the T.sub.delta and/or N.sub.delta **1008** for case 1 alignment, e.g., in separate messages. In other aspects, the additional offset **1010** may be signaled to the IAB node **1002** together with the T.sub.delta and/or N.sub.delta **1008** for the case 1 timing alignment, e.g., in same message. The offset **1010** for case 6 timing alignment may be signaled to the IAB node **1002** in a MAC-CE and/or a DCI.

(102) At **1012**, the IAB node **1002** applies the additional T.sub.delta and/or N.sub.delta **1009** or the offset **1010** for case 6 timing alignment to adjust the transmission timing of the MT/DU of the IAB node. Then, the IAB node **1002** transmits downlink transmission(s) **1014** having the timing adjusted based on the T.sub.delta and/or N.sub.delta **1009** or the offset **1010**. In some aspects, the IAB node **1002** may interpret the reception of T.sub.delta and/or N.sub.delta **1009** or the offset **1010** to indicate to switch from a different timing alignment mode to case 6 timing alignment, at **1010**. For example, at **1006**, the IAB node **1002** may operate in/perform a case 1 or case 7 timing alignment, and the IAB node **1002** may switch to perform a case 6 timing alignment in response to the reception of T.sub.delta and/or N.sub.delta **1009** or the offset **1010**. Although this example is described for case 6, in some aspects, the additional T.sub.delta and/or N.sub.delta **1009** or the offset **1010** may be associated with case 7 timing alignment. Thus, at **1014** and **1016**, the IAB node **1002** may adjust transmission or reception timing according to case 6 or case 7 timing alignment.

(103) In some aspects, the same T.sub.delta and/or N.sub.delta parameters may be used among different types of timing alignment. When a parent IAB node indicates the T.sub.delta and/or N.sub.delta, the parent node may also indicate the type of timing alignment to which the parameter applies. FIG. 11 illustrates an example communication flow **1100** that shows an example of a parent IAB node **1104** providing an T.sub.delta and/or N.sub.delta **1108** to an IAB node **1102** (e.g., that is a child node of parent IAB node **1104**). The transmission indicating the T.sub.delta and/or N.sub.delta **1108** may further indicate the type of timing alignment associated with the indicated parameter, e.g., the type of timing alignment on which the parameter is based and/or for which the parameter is intended to be applied. The T.sub.delta and/or N.sub.delta **1108** may be signaled to the IAB node **1102** in a MAC-CE and/or a DCI. In some aspects, a flag (e.g., a one or more bit flag in the message carrying the T.sub.delta and/or N.sub.delta **1108**) may indicate one of different types of timing alignment (e.g., case 1, case 6, and/or case 7). The inclusion of the flag itself and/or a particular value of the flag may indicate, for example, that the T.sub.delta and/or N.sub.delta **1108** are associated with case 6 transmission timing alignment at a given IAB node. Similarly, the inclusion of the flag itself and/or a particular value of the flag may indicate, for example, that the T.sub.delta and/or N.sub.delta **1108** are associated with case 7 reception timing alignment at the IAB node. If the flag indicates between case 1 and case 6, the flag may include a single bit. As an example, “1” may indicate case 6 and “0” may indicate case 1, or the opposite with “0” indicating case 6 and “1” indicating case 1. If the flag indicates between case 1, case 6, and case 7, or other timing alignment cases, the flag may include two or more bits.

(104) In some aspects, the resource on which the indication is sent may indicate the associated type of timing alignment. The IAB node **1102** may infer, or otherwise determine, the type of timing alignment associated with the T.sub.delta and/or N.sub.delta **1108** based on resources of the message carrying the parameter(s). As an example, if the IAB node **1102** receives the T.sub.delta and/or N.sub.delta **1108** on a time resource within a time offset before or after the resources in which Case 1 or Case 6 is adopted, the time resource of the T.sub.delta and/or N.sub.delta **1108** may indicate an association with case 1 timing alignment or case 6 timing alignment, respectively.

As another example, Case 1 and Case 6 timing alignment may be associated with separate spatial resources. The IAB-MT may use beam 1 when operating with Case 1 (which may be associated with a multiplexing scenario such as TDM-only), and beam 2 when operating with Case 6 (which may be associated with a multiplexing scenario such as SDM-TX or (MT-TX&DU-TX))—in this case, if the IAB node **1102** (e.g., MT) receives the T.sub.delta and/or N.sub.delta **1108** on a given beam, the IAB node may associate it with the corresponding timing Case.

(105) At **1112**, the IAB node **1102** applies the received T.sub.delta and/or N.sub.delta **1108** for the indicated type of timing alignment to adjust the transmission/reception timing of the MT/DU of the IAB node **1102**, as illustrated at **1114** and **1116**. In some aspects, the IAB node **1102** may interpret the reception of T.sub.delta and/or N.sub.delta **1108** with an indication of a particular type of timing alignment as an indication to switch to perform the indicated type of timing alignment, at **1110**. For example, at **1106**, the IAB node **1102** may operate in/perform a first type of timing alignment and may switch at **1110** to a different type of timing alignment associated with the T.sub.delta and/or N.sub.delta **1108**.

(106) FIG. **12** is a flowchart **1200** of a method of wireless communication. The method may be performed by an IAB node (e.g., the IAB node **103**, **310**, **410**, **420**, **510**, **520a**, **520b**, **704**, **902**, **1002**, **1102**; the apparatus **1402**; the baseband unit **1404**, which may include the memory **376** and which may be the entire IAB node **310** or a component of the IAB node **310**, such as the TX processor **316**, the RX processor **370**, and/or the controller/processor **375**). The method may enable an IAB node to apply a time difference parameter for over-air-synchronization, e.g., T.sub.delta and/or N.sub.delta, among multiple alignment types.

(107) FIG. **1202**, the IAB node receives, from a parent IAB node, a time difference parameter for over-the-air synchronization in an IAB network. FIGS. **9**, **10**, and **11** illustrate examples of an IAB node receiving a time difference parameter from an parent IAB node. For example, the time difference parameter may comprise a T.sub.delta and/or N.sub.delta, e.g., as described in connection with FIG. **9** or **11**. For example, the T.sub.delta may be based on a time difference between an uplink reception time and a downlink transmission time at the parent IAB node, as described in connection with FIG. **8**. The time difference parameter may correspond to an additional T.sub.delta and/or N.sub.delta **1009** or a time offset **1010** to T.sub.delta and/or N.sub.delta, e.g., as described in connection with FIG. **10**. In some aspects, the reception of the time difference parameter may be performed by the time difference parameter reception component **1440** via the reception component **1430** and/or the RF transceiver **1422** of the apparatus **1402** in FIG. **14**.

(108) At **1204**, the IAB node adjusts transmission or reception of the IAB node based on the time difference parameter for one of multiple types of IAB node alignment, e.g., to provide alignment among IAB nodes (as in case 1), at the IAB node (as in case 6) and/or at the parent IAB node (as in case 7). The multiple types of timing alignment may include a first type of alignment (e.g., case 1) comprising downlink transmission timing alignment across each IAB node of the IAB network, a second type of alignment (e.g., case 6) between uplink transmission at an IAB-MT of the IAB node and downlink transmission at an IAB-DU of the IAB node, and a third type of alignment (e.g., case 7) between downlink reception at the IAB-MT of the IAB node and uplink reception at the IAB-DU of the IAB node. The adjustment of the transmission or reception may be performed by the timing alignment component **1442** of the apparatus **1402** in FIG. **14**. For example, the IAB node may adjust the downlink transmission timing based on the time difference parameter T.sub.delta to align with the downlink transmission timing of other IAB nodes according to case 1 alignment. In other examples, the IAB node may adjust the uplink transmission timing and/or the DL transmission timing of the IAB node to provide alignment between UL and DL transmission at the IAB node according to case 6 alignment. In other examples, the IAB node may adjust the uplink reception timing or the downlink reception timing to provide alignment between the UL and DL reception according to case 7 alignment.

(109) In some aspects, the time difference parameter may correspond to a T.sub.delta, and the IAB node may adjust a downlink transmission time of the IAB node based on T.sub.delta according to the first type of alignment. For example, the reception of the T.sub.delta, at **1202**, may indicate to the IAB node to apply the first type of alignment. FIG. **9** illustrates an example in which the T.sub.delta is associated with a case 1 timing alignment.

(110) In some aspects, the time difference parameter may correspond to an offset parameter indicated with a timing advance command for the third type of alignment, and the IAB node may calculate a T.sub.delta from the offset parameter, e.g., and a TA command, and may adjust the transmission or the reception of the IAB node with the calculated T.sub.delta based on the third type of alignment (e.g., case 7).

(111) In some aspects, the indication of the time difference parameter that is received from the parent IAB node may indicate an association to one of the multiple types of alignment. For example, a first time difference parameter (T.sub.delta and/or N.sub.delta) may be associated with the first type of alignment and a second time difference parameter (additional T.sub.delta and/or N.sub.delta **1009** or a time offset **1010** to T.sub.delta and/or N.sub.delta) may be associated with the second type of alignment. The IAB node may receive both the first time difference parameter and the second time difference parameter from the parent IAB node, e.g., as described in connection with the example in FIG. **10**. The IAB node may receive the first time difference parameter and the second time difference parameter in separate messages from the parent IAB node. The IAB node may receive the first time difference parameter and the second time difference parameter in a same message from the parent IAB node. The first time difference parameter (e.g., T.sub.delta and/or N.sub.delta **1008**) may be associated with the first type of alignment and the second time difference parameter may be a time offset (offset **1010** to T.sub.delta and/or N.sub.delta) associated with the second type of alignment, the time offset being relative to the first time difference parameter. The IAB node may receive both the first time difference parameter and the second time difference parameter from the parent IAB node. The IAB node may receive the first time difference parameter and the second time difference parameter in separate messages from the parent IAB node. The IAB node may receive the first time difference parameter and the second time difference parameter in a same message from the parent IAB node.

(112) In some aspects, the indication of the time difference parameter may comprise a flag corresponding to a type of alignment associated with the time difference parameter, e.g., as described in connection with the example in FIG. **11**. In some aspects, a resource in which the indication of the time difference parameter is received may indicate a type of alignment associated with the time difference parameter, e.g., as described in connection with the example in FIG. **11**.

(113) FIG. **13** is a flowchart **1300** of a method of wireless communication. The method may be performed by a parent IAB node (e.g., the IAB node **103**, **310**, **410**, **420**, **510**, **520a**, **520b**, **702**, **904**, **1004**, **1104**; the apparatus **1402**; the baseband unit **1404**, which may include the memory **376** and which may be the entire IAB node **310** or a component of the IAB node **310**, such as the TX processor **316**, the RX processor **370**, and/or the controller/processor **375**). The method may enable an IAB node to apply a time difference parameter for over-air-synchronization, e.g., T.sub.delta and/or N.sub.delta, among multiple alignment types.

(114) At **1302**, the parent IAB node transmits or receives communication with a child IAB node. The communication may be based on any of the aspects described in connection with FIG. **4**, **5**, **6**, **7**, **9**, **10**, or **11**. The communication may be based on one of multiple types of timing alignment. In some aspects, the transmission and reception may be performed, e.g., by the reception component **1430** and the transmission component **1434** of the apparatus **1402** in FIG. **10**.

(115) At **1304**, the parent IAB node transmits a time difference parameter for over-the-air synchronization in an IAB network, the time difference parameter being applicable for one of multiple types of IAB node alignment, e.g., to provide alignment among IAB nodes (as in case 1), at the IAB node (as in case 6) and/or at the parent IAB node (as in case 7). FIGS. **9**, **10**, and **11**

illustrate examples of a parent IAB node transmitting a time difference parameter from an parent IAB node. For example, the time difference parameter may comprise a T.sub.delta and/or N.sub.delta, e.g., as described in connection with FIG. 9 or 11. For example, the T.sub.delta may be based on a time difference between an uplink reception time and a downlink transmission time at the parent IAB node, as described in connection with FIG. 8. The time difference parameter may correspond to an additional T.sub.delta and/or N.sub.delta **1009** or an offset **1010** to T.sub.delta and/or N.sub.delta, e.g., as described in connection with FIG. 10. In some aspects, the transmission of the time difference parameter may be performed by the time difference parameter indicator component **1444** via the transmission component **1434** and/or the RF transceiver **1422** of the apparatus **1402** in FIG. 14.

(116) The multiple types of timing alignment may include a first type of alignment (e.g., case 1) comprising downlink transmission timing alignment across each IAB node of the IAB network, a second type of alignment (e.g., case 6) between uplink transmission at an IAB-MT of the IAB node and downlink transmission at an IAB-DU of the IAB node, and a third type of alignment (e.g., case 7) between downlink reception at the IAB-MT of the IAB node and uplink reception at the IAB-DU of the IAB node.

(117) In some aspects, the time difference parameter may correspond to a T.sub.delta and may be associated with the first type of alignment. For example, the transmission of the T.sub.delta, at **1304**, may indicate to the child IAB node to apply the first type of alignment. FIG. 9 illustrates an example in which the T.sub.delta is associated with a case 1 timing alignment.

(118) In some aspects, the time difference parameter may correspond to an offset parameter indicated with a timing advance command for the third type of alignment and for calculation of a T.sub.delta from the offset parameter, e.g., and a TA command, and may be associated with adjustment of the transmission or the reception of the IAB node with the calculated T.sub.delta based on the third type of alignment (e.g., case 7).

(119) In some aspects, the indication of the time difference parameter that is transmitted from the parent IAB node may indicate an association to one of the multiple types of alignment. For example, a first time difference parameter (T.sub.delta and/or N.sub.delta) may be associated with the first type of alignment and a second time difference parameter (additional T.sub.delta and/or N.sub.delta **1009** or an offset **1010** to T.sub.delta and/or N.sub.delta) may be associated with the second type of alignment. The parent IAB node may transmit both the first time difference parameter and the second time difference parameter to the child IAB node, e.g., as described in connection with the example in FIG. 10. The parent IAB node may transmit the first time difference parameter and the second time difference parameter in separate messages to the child IAB node. The parent IAB node may transmit the first time difference parameter and the second time difference parameter in a same message to the child IAB node. The first time difference parameter (e.g., T.sub.delta and/or N.sub.delta **1008**) may be associated with the first type of alignment and the second time difference parameter may be a time offset (offset **1010** to T.sub.delta and/or N.sub.delta) associated with the second type of alignment, the time offset being relative to the first time difference parameter. The parent IAB node may transmit both the first time difference parameter and the second time difference parameter to the child IAB node. The parent IAB node may transmit the first time difference parameter and the second time difference parameter in separate messages to the child IAB node. The parent IAB node may transmit the first time difference parameter and the second time difference parameter in a same message to the child IAB node.

(120) In some aspects, the indication of the time difference parameter may comprise a flag corresponding to a type of alignment associated with the time difference parameter, e.g., as described in connection with the example in FIG. 11. In some aspects, a resource in which the indication of the time difference parameter is transmitted may indicate a type of alignment associated with the time difference parameter, e.g., as described in connection with the example in

FIG. 11.

(121) FIG. 14 is a diagram 1400 illustrating an example of a hardware implementation for an apparatus 1402. The apparatus 1402 may be an IAB node, a component of an IAB node, or may implement IAB node functionality. The apparatus 1402 may correspond to the IAB node 103, 310, 420, 520a-b, 606a, 606b, 702, 704, 802, 804, 902, 904, 1002, 1004, 1102, or 1104. In some aspects, the apparatus may include a baseband unit 1404. The baseband unit 1404 may communicate through a cellular RF transceiver with one or more UEs 104. The baseband unit 1404 may also communicate through a cellular RF transceiver with one or more IAB nodes 103. The IAB node 103 may be a parent node of the apparatus or may be a child node of the apparatus. The baseband unit 1404 may include a computer-readable medium/memory. The baseband unit 1404 is responsible for general processing, including the execution of software stored on the computer-readable medium/memory. The software, when executed by the baseband unit 1404, causes the baseband unit 1404 to perform the various functions described supra. The computer-readable medium/memory may also be used for storing data that is manipulated by the baseband unit 1404 when executing software. The baseband unit 1404 further includes a reception component 1430, a communication manager 1432, and a transmission component 1434. The communication manager 1432 includes the one or more illustrated components. The components within the communication manager 1432 may be stored in the computer-readable medium/memory and/or configured as hardware within the baseband unit 1404. The baseband unit 1404 may be a component of the IAB node 310 and may include the memory 376 and/or at least one of the TX processor 316, the RX processor 370, and the controller/processor 375.

(122) The communication manager 1432 includes time difference parameter reception component 1440 that is configured to receive, from a parent IAB node, a time difference parameter for over-the-air synchronization in an IAB network, e.g., as described in connection with 1202 in FIG. 12. The communication manager 1432 includes time difference parameter indicator component 1444 that is configured to indicate, to a child IAB node, a time difference parameter for over-the-air synchronization in an IAB network, e.g., as described in connection with 1304 in FIG. 13. The communication manager 1432 further includes a timing alignment component 1442 that is configured to adjust transmission or reception of the IAB node based on the time difference parameter for one of multiple types of alignment at the IAB node and/or the parent IAB node, e.g., as described in connection with 1204 in FIG. 12. The apparatus 1402 further includes a reception component 1430 and transmission component 1434 configured to transmit and receive communication with a child IAB node, e.g., as described in connection with 1302 in FIG. 13.

(123) The apparatus may include additional components that perform each of the blocks of the algorithm in the flowcharts of FIG. 12 or 13, and/or the aspects performed by the IAB node in any of FIG. 9, 10, or 11. As such, each block in the flowcharts of FIGS. 12 or 13, and/or the aspects performed by the IAB node in any of FIG. 9, 10, or 11 may be performed by a component and the apparatus may include one or more of those components. The components may be one or more hardware components specifically configured to carry out the stated processes/algorithm, implemented by a processor configured to perform the stated processes/algorithm, stored within a computer-readable medium for implementation by a processor, or some combination thereof.

(124) As shown, the apparatus 1402 may include a variety of components configured for various functions. In one configuration, the apparatus 1402, and in particular the baseband unit 1404, may include means for receiving, from a parent IAB node, a time difference parameter for OTA synchronization in an IAB network and means for adjusting transmission or reception of the IAB node based on the time difference parameter for one of multiple types of alignment at the IAB node and/or the parent IAB node. The apparatus 1402 may further include means for transmitting or receiving communication with a child IAB node and means for transmitting a time difference parameter for over-the-air synchronization in an IAB network, the time difference parameter being applicable for one of multiple types of alignment at the child IAB node. The apparatus 1402 may

include means for performing the aspects of FIG. 12 and FIG. 13 in some aspects, because the apparatus 1402 may operate as a parent node to one or more child nodes and may operate as a child node to a parent node. The means may be one or more of the components of the apparatus 1402 configured to perform the functions recited by the means. As described supra, the apparatus 1402 may include the TX Processor 316, the RX Processor 370, and the controller/processor 375. As such, in one configuration, the means may be the TX Processor 316, the RX Processor 370, and the controller/processor 375 configured to perform the functions recited by the means.

(125) It is understood that the specific order or hierarchy of blocks in the processes/flowcharts disclosed is an illustration of example approaches. Based upon design preferences, it is understood that the specific order or hierarchy of blocks in the processes/flowcharts may be rearranged. Further, some blocks may be combined or omitted. The accompanying method claims present elements of the various blocks in a sample order, and are not meant to be limited to the specific order or hierarchy presented.

(126) The previous description is provided to enable any person skilled in the art to practice the various aspects described herein. Various modifications to these aspects will be readily apparent to those skilled in the art, and the generic principles defined herein may be applied to other aspects. Thus, the claims are not limited to the aspects described herein, but are to be accorded the full scope consistent with the language claims. Reference to an element in the singular does not mean “one and only one” unless specifically so stated, but rather “one or more.” Terms such as “if,” “when,” and “while” do not imply an immediate temporal relationship or reaction. That is, these phrases, e.g., “when,” do not imply an immediate action in response to or during the occurrence of an action, but simply imply that if a condition is met then an action will occur, but without requiring a specific or immediate time constraint for the action to occur. The word “exemplary” is used herein to mean “serving as an example, instance, or illustration.” Any aspect described herein as “exemplary” is not necessarily to be construed as preferred or advantageous over other aspects. Unless specifically stated otherwise, the term “some” refers to one or more. Combinations such as “at least one of A, B, or C,” “one or more of A, B, or C,” “at least one of A, B, and C,” “one or more of A, B, and C,” and “A, B, C, or any combination thereof” include any combination of A, B, and/or C, and may include multiples of A, multiples of B, or multiples of C. Specifically, combinations such as “at least one of A, B, or C,” “one or more of A, B, or C,” “at least one of A, B, and C,” “one or more of A, B, and C,” and “A, B, C, or any combination thereof” may be A only, B only, C only, A and B, A and C, B and C, or A and B and C, where any such combinations may contain one or more member or members of A, B, or C. Sets should be interpreted as a set of elements where the elements number one or more. Accordingly, for a set of X, X would include one or more elements. If a first apparatus receives data from or transmits data to a second apparatus, the data may be received/transmitted directly between the first and second apparatuses, or indirectly between the first and second apparatuses through a set of apparatuses. All structural and functional equivalents to the elements of the various aspects described throughout this disclosure that are known or later come to be known to those of ordinary skill in the art are expressly incorporated herein by reference and are encompassed by the claims. Moreover, nothing disclosed herein is dedicated to the public regardless of whether such disclosure is explicitly recited in the claims. The words “module,” “mechanism,” “element,” “device,” and the like may not be a substitute for the word “means.” As such, no claim element is to be construed as a means plus function unless the element is expressly recited using the phrase “means for.”

(127) As used herein, the phrase “based on” shall not be construed as a reference to a closed set of information, one or more conditions, one or more factors, or the like. In other words, the phrase “based on A” (where “A” may be information, a condition, a factor, or the like) shall be construed as “based at least on A” unless specifically recited differently.

(128) The following aspects are illustrative only and may be combined with other aspects or teaching described herein, without limitation.

(129) Aspect 1 is a method of wireless communication at an IAB node, comprising: receiving, from a parent IAB node, a time difference parameter for over-the-air synchronization in an IAB network; and adjusting transmission or reception of the IAB node based on the time difference parameter for one of multiple types of IAB node alignment.

(130) In aspect 2, the method of aspect 1 further includes that the multiple types of IAB node alignment include a first type of alignment comprising downlink transmission timing alignment across each IAB node of the IAB network, a second type of alignment between uplink transmission at an IAB-MT of the IAB node and downlink transmission at an IAB-DU of the IAB node, and a third type of alignment between downlink reception at the IAB-MT of the IAB node and uplink reception at the IAB-DU of the IAB node.

(131) In aspect 3, the method of aspect 1 or aspect 2 further includes that the time difference parameter is associated with the first type of alignment and the third type of alignment.

(132) In aspect 4, the method of aspect 1 or aspect 2 further includes that the time difference parameter corresponds to a $T_{\text{sub}}\Delta$ based on a time difference between an uplink reception time and a downlink transmission time at the parent IAB node, and the IAB node adjusts a downlink transmission time of the IAB node based on $T_{\text{sub}}\Delta$ according to the first type of alignment.

(133) In aspect 5, the method of aspect 4 further includes that reception of the $T_{\text{sub}}\Delta$ indicates to the IAB node to apply the first type of alignment.

(134) In aspect 6, the method of aspect 1 or aspect 2 further includes that the time difference parameter corresponds to an offset parameter indicated with a timing advance command for the third type of alignment, the method further comprising: calculating a $T_{\text{sub}}\Delta$ from the offset parameter and adjusting the transmission or the reception of the IAB node with the $T_{\text{sub}}\Delta$ based on the third type of alignment.

(135) In aspect 7, the method of any of aspects 1-3 further includes that an indication of the time difference parameter that is received from the parent IAB node indicates an association to one of the multiple types of IAB node alignment.

(136) In aspect 8, the method of aspect 1 or aspect 7 further include that a first time difference parameter is associated with the first type of alignment and a second time difference parameter is associated with the second type of alignment.

(137) In aspect 9, the method of aspect 8 further includes that the IAB node receives both the first time difference parameter and the second time difference parameter from the parent IAB node.

(138) In aspect 10, the method of aspect 9 further includes that the IAB node receives the first time difference parameter and the second time difference parameter in separate messages from the parent IAB node.

(139) In aspect 11, the method of aspect 9 further includes that the IAB node receives the first time difference parameter and the second time difference parameter in a same message from the parent IAB node.

(140) In aspect 12, the method of aspect 8 further includes that the first time difference parameter is associated with the first type of alignment and the second time difference parameter is a time offset associated with the second type of alignment, the time offset being relative to the first time difference parameter.

(141) In aspect 13, the method of aspect 8 further includes that the IAB node receives both the first time difference parameter and the second time difference parameter from the parent IAB node.

(142) In aspect 14, the method of aspect 13 further includes that the IAB node receives the first time difference parameter and the second time difference parameter in separate messages from the parent IAB node.

(143) In aspect 15, the method of aspect 13 further includes that the IAB node receives the first time difference parameter and the second time difference parameter in a same message from the parent IAB node.

(144) In aspect 16, the method of any of aspects 7-15 further includes that the indication of the time

difference parameter comprises a flag corresponding to a type of alignment associated with the time difference parameter.

(145) In aspect 17, the method of any of aspects 7-16 further includes that a resource in which the indication of the time difference parameter is received indicates a type of alignment associated with the time difference parameter.

(146) Aspect 18 is an apparatus for wireless communication, comprising: means for performing the method of any of aspects 1-17.

(147) In aspect 19, the apparatus of aspect 18 further includes at least one antenna and a transceiver coupled to the at least one antenna.

(148) Aspect 20 is an apparatus for wireless communication, comprising: a memory; and at least one processor coupled to the memory and, based at least in part on information stored in the memory, the at least one processor is configured to perform the method of any of aspects 1-17.

(149) In aspect 21, the apparatus of aspect 20 further includes at least one of an antenna or a transceiver coupled to the at least one antenna and the at least one processor.

(150) Aspect 22 is a non-transitory computer-readable medium storing computer executable code, the code when executed by a processor cause the processor to perform the method of any of aspects 1-17.

(151) Aspect 23 is a method of wireless communication at an IAB parent node, comprising: transmitting or receiving communication with an IAB node that is a child node of the parent IAB node; and transmitting a time difference parameter for over-the-air synchronization in an IAB network, the time difference parameter being applicable for one of multiple types of IAB node alignment.

(152) In aspect 24, the method of aspect 23 further includes that the multiple types of IAB node alignment include: a first type of alignment comprising downlink transmission timing alignment across each IAB node of the IAB network, a second type of alignment between uplink transmission at an IAB-MT of the IAB node and downlink transmission at an IAB-DU of the IAB node, and a third type of alignment between downlink reception at the IAB-MT of the IAB node and uplink reception at the IAB-DU of the IAB node.

(153) In aspect 25, the method of aspect 23 or aspect 24 further includes that the time difference parameter corresponds to a T_{sub_delta} associated with the first type of alignment, the T_{sub_delta} being based on a time difference between an uplink reception time and a downlink transmission time at the parent IAB node.

(154) In aspect 26, the method of aspect 25 further includes that transmission of the T_{sub_delta} indicates to the IAB node to apply the first type of alignment.

(155) In aspect 27, the method of aspect 23 or aspect 24 further includes that an indication of the time difference parameter from the parent IAB node indicates an association to one of the multiple types of IAB node alignment.

(156) In aspect 28, the method of aspect 23, 24, or 27 further includes that a first time difference parameter is associated with the first type of alignment and a second time difference parameter is associated with the second type of alignment.

(157) In aspect 29, the method of aspect 23, 24, 27, or 28 further includes that the parent IAB node transmits both the first time difference parameter and the second time difference parameter to the IAB node.

(158) In aspect 30, the method of aspect 29 further includes that the parent IAB node transmits the first time difference parameter and the second time difference parameter in separate messages to the IAB node.

(159) In aspect 31, the method of aspect 29 further includes that the parent IAB node transmits the first time difference parameter and the second time difference parameter in a same message to the IAB node.

(160) In aspect 32, the method of aspect 23, 24, or 27 further includes that the first time difference

parameter is associated with the first type of alignment and the second time difference parameter is a time offset associated with the second type of alignment, the time offset being relative to the first time difference parameter.

(161) In aspect 33, the method of aspect 32 further includes that the parent IAB node transmits both the first time difference parameter and the second time difference parameter to the IAB node.

(162) In aspect 34, the method of aspect 33 further includes that the parent IAB node transmits the first time difference parameter and the second time difference parameter in separate messages to the IAB node.

(163) In aspect 35, the method of aspect 33 further includes that the parent IAB node transmits the first time difference parameter and the second time difference parameter in a same message to the IAB node.

(164) In aspect 36, the method of any of aspects 27-35 includes that the indication of the time difference parameter further comprises a flag corresponding to a type of alignment associated with the time difference parameter.

(165) In aspect 37, the method of any of aspects 27-36 includes that a resource in which the indication of the time difference parameter is transmitted further indicates a type of alignment associated with the time difference parameter.

(166) Aspect 38 is an apparatus for wireless communication, comprising: means for performing the method of any of aspects 23-37.

(167) In aspect 39, the apparatus of aspect 38 further includes at least one of an antenna or a transceiver coupled to the at least one antenna.

(168) Aspect 40 is an apparatus for wireless communication, comprising: a memory; and at least one processor coupled to the memory and, based at least in part on information stored in the memory, the at least one processor is configured to perform the method of any of aspects 23-37.

(169) In aspect 41, the apparatus of aspect 40 further includes at least one of an antenna or a transceiver coupled to the at least one antenna and the at least one processor.

(170) Aspect 42 is a non-transitory computer-readable medium storing computer executable code, the code when executed by a processor cause the processor to perform the method of any of aspects 23-37.

Claims

1. An apparatus for wireless communication at an integrated access and backhaul (IAB) node, comprising: a memory; and at least one processor coupled to the memory and, based at least in part on information stored in the memory, the at least one processor is configured to: receive, from a parent IAB node, a time difference parameter for over-the-air synchronization in an IAB network; and adjust transmission or reception timing at the IAB node based on the time difference parameter for one of multiple types of IAB node alignment, wherein the multiple types of the IAB node alignment include: a first type of alignment comprising downlink transmission timing alignment across each IAB node of the IAB network, a second type of alignment between uplink transmission at an IAB mobile termination (IAB-MT) of the IAB node and downlink transmission at an IAB distributed unit (IAB-DU) of the IAB node, and a third type of alignment between downlink reception at the IAB-MT of the IAB node and uplink reception at the IAB-DU of the IAB node.
2. The apparatus of claim 1, further comprising: at least one transceiver coupled to the at least one processor and configured to receive the time difference parameter, wherein the multiple types of the IAB node alignment include: a first type of alignment comprising downlink transmission timing alignment across each IAB node of the IAB network, a second type of alignment between uplink transmission at an IAB mobile termination (IAB-MT) of the IAB node and downlink transmission at an IAB distributed unit (IAB-DU) of the IAB node, and a third type of alignment between downlink reception at the IAB-MT of the IAB node and uplink reception at the IAB-DU of the

IAB node.

3. The apparatus of claim 2, wherein the time difference parameter is associated with the first type of alignment and the third type of alignment.
4. The apparatus of claim 2, wherein the time difference parameter corresponds to a timing delta (Tdelta) based on a time difference between an uplink reception time and a downlink transmission time at the parent IAB node, and the IAB node adjusts a downlink transmission time of the IAB node based on the Tdelta according to the first type of alignment from the multiple types of the IAB node alignment.
5. The apparatus of claim 4, wherein reception of the Tdelta indicates to the IAB node to apply the first type of alignment.
6. The apparatus of claim 2, wherein the time difference parameter corresponds to an offset parameter indicated with a timing advance command for the third type of alignment, wherein the at least one processor is further configured to: calculate a Tdelta from the offset parameter and adjusting the transmission or the reception of the IAB node with the Tdelta based on the third type of alignment.
7. The apparatus of claim 2, wherein a first time difference parameter is associated with the first type of alignment and a second time difference parameter is associated with the second type of alignment.
8. The apparatus of claim 7, wherein the at least one processor is configured to receive both the first time difference parameter and the second time difference parameter from the parent IAB node.
9. The apparatus of claim 8, wherein the at least one processor is configured to receive the first time difference parameter and the second time difference parameter in separate messages from the parent IAB node or in a same message from the parent IAB node.
10. The apparatus of claim 7, wherein the first time difference parameter is associated with the first type of alignment and the second time difference parameter is a time offset associated with the second type of alignment, the time offset being relative to the first time difference parameter.
11. The apparatus of claim 10, wherein the at least one processor is configured to receive both the first time difference parameter and the second time difference parameter from the parent IAB node.
12. The apparatus of claim 11, wherein the at least one processor is configured to receive the first time difference parameter and the second time difference parameter in separate messages from the parent IAB node.
13. The apparatus of claim 11, wherein the at least one processor is configured to receive the first time difference parameter and the second time difference parameter in a same message from the parent IAB node.
14. The apparatus of claim 2, wherein an indication of the time difference parameter that is received from the parent IAB node indicates an association to one of the multiple types of the IAB node alignment.
15. The apparatus of claim 14, wherein the indication of the time difference parameter comprises a flag corresponding to a type of alignment associated with the time difference parameter.
16. The apparatus of claim 14, wherein a resource in which the indication of the time difference parameter is received indicates a type of alignment associated with the time difference parameter.
17. An apparatus for wireless communication at a parent integrated access and backhaul (IAB) node, comprising: a memory; and at least one processor coupled to the memory and, based at least in part on information stored in the memory, the at least one processor is configured to: transmit or receive communication with an IAB node that is a child node of the parent IAB node; and transmit a time difference parameter for over-the-air synchronization in an IAB network, the time difference parameter being applicable for one of multiple types of IAB node alignment, wherein the multiple types of the IAB node alignment include: a first type of alignment comprising downlink transmission timing alignment across each IAB node of the IAB network, a second type of alignment between uplink transmission at an IAB mobile termination (IAB-MT) of the IAB node

and downlink transmission at an IAB distributed unit (IAB-DU) of the IAB node, and a third type of alignment between downlink reception at the IAB-MT of the IAB node and uplink reception at the IAB-DU of the IAB node.

18. The apparatus of claim 17, further comprising: at least one transceiver coupled to the at least one processor, wherein the multiple types of the IAB node alignment include: a first type of alignment comprising downlink transmission timing alignment across each IAB node of the IAB network, a second type of alignment between uplink transmission at an IAB mobile termination (IAB-MT) of the IAB node and downlink transmission at an IAB distributed unit (IAB-DU) of the IAB node, and a third type of alignment between downlink reception at the IAB-MT of the IAB node and uplink reception at the IAB-DU of the IAB node.

19. The apparatus of claim 18, wherein the time difference parameter corresponds to a timing delta (Tdelta) associated with the first type of alignment, the Tdelta being based a time difference between an uplink reception time and a downlink transmission time at the parent IAB node.

20. The apparatus of claim 19, wherein transmission of the Taeta indicates to the IAB node to apply the first type of alignment.

21. The apparatus of claim 18, wherein an indication of the time difference parameter from the parent IAB node indicates an association to one of the multiple types of IAB node alignment.

22. The apparatus of claim 21, wherein a first time difference parameter is associated with the first type of alignment and a second time difference parameter is associated with the second type of alignment.

23. The apparatus of claim 22, wherein the at least one processor is configured to transmit both the first time difference parameter and the second time difference parameter to the IAB node, and wherein the at least one processor is configured to: transmit the first time difference parameter and the second time difference parameter in separate messages to the IAB node, or transmit the first time difference parameter and the second time difference parameter in a same message to the IAB node.

24. The apparatus of claim 22, wherein the first time difference parameter is associated with the first type of alignment and the second time difference parameter is a time offset associated with the second type of alignment, the time offset being relative to the first time difference parameter, wherein the at least one processor is configured to: transmit the first time difference parameter and the second time difference parameter in separate messages to the IAB node, or transmit the first time difference parameter and the second time difference parameter in a same message to the IAB node.

25. The apparatus of claim 21, wherein the indication of the time difference parameter comprises a flag corresponding to a type of alignment associated with the time difference parameter.

26. A method of wireless communication at an integrated access and backhaul (IAB) node, comprising: receiving, from a parent IAB node, a time difference parameter for over-the-air synchronization in an IAB network; and adjusting transmission or reception timing at the IAB node based on the time difference parameter for one of multiple types of IAB node alignment, wherein the multiple types of the IAB node alignment include: a first type of alignment comprising downlink transmission timing alignment across each IAB node of the IAB network, a second type of alignment between uplink transmission at an IAB mobile termination (IAB-MT) of the IAB node and downlink transmission at an IAB distributed unit (IAB-DU) of the IAB node, and a third type of alignment between downlink reception at the IAB-MT of the IAB node and uplink reception at the IAB-DU of the IAB node.

27. The method of claim 26, wherein the time difference parameter corresponds to a timing delta (Tdelta) based on a time difference between an uplink reception time and a downlink transmission time at the parent IAB node.

28. A method of wireless communication at a parent integrated access and backhaul (IAB) node, comprising: transmitting or receiving communication with an IAB node that is a child node of the

parent IAB node; and transmitting a time difference parameter for over-the-air synchronization in an IAB network, the time difference parameter being applicable for one of multiple types of IAB node alignment, wherein the multiple types of the IAB node alignment include: a first type of alignment comprising downlink transmission timing alignment across each IAB node of the IAB network, a second type of alignment between uplink transmission at an IAB mobile termination (IAB-MT) of the IAB node and downlink transmission at an IAB distributed unit (IAB-DU) of the IAB node, and a third type of alignment between downlink reception at the IAB-MT of the IAB node and uplink reception at the IAB-DU of the IAB node, adjusting transmission or reception timing at the IAB node based on the time difference parameter for one of multiple types of IAB node alignment, wherein the multiple types of the IAB node alignment include: a first type of alignment comprising downlink transmission timing alignment across each IAB node of the IAB network, a second type of alignment between uplink transmission at an IAB mobile termination (IAB-MT) of the IAB node and downlink transmission at an IAB distributed unit (IAB-DU) of the IAB node, and a third type of alignment between downlink reception at the IAB-MT of the IAB node and uplink reception at the IAB-DU of the IAB node.
