

US Patent & Trademark Office

Patent Public Search | Text View

United States Patent	12413870
Kind Code	B2
Date of Patent	September 09, 2025
Inventor(s)	Asakura; LuongHung

Solid-state imaging element

Abstract

To improve image quality in a solid-state imaging element that simultaneously performs exposure in all pixels. The solid-state imaging element includes a predetermined number of capacitive elements, a pre-stage circuit, a selection circuit, a post-stage circuit, and a vertical scanning circuit. The pre-stage circuit generates a predetermined reset level and a signal level corresponding to an exposure amount, and causes each of the capacitive elements to hold a corresponding one of the reset level and the signal level. In the selection circuit, a selection transistor that opens and closes a path between one end of each capacitive element and a predetermined node is arranged. The post-stage circuit sequentially reads the reset level and the signal level via the node. The vertical scanning circuit performs control to lower the potential of the one end when the reset level and the signal level are held.

Inventors:	Asakura; LuongHung (Kanagawa, JP)
Applicant:	Sony Semiconductor Solutions Corporation (Kanagawa, JP)
Family ID:	83320211
Assignee:	Sony Semiconductor Solutions Corporation (Kanagawa, JP)
Appl. No.:	18/550180
Filed (or PCT Filed):	January 13, 2022
PCT No.:	PCT/JP2022/000864
PCT Pub. No.:	WO2022/190657
PCT Pub. Date:	September 22, 2022

Prior Publication Data

Document Identifier	Publication Date
US 20240187752 A1	Jun. 06, 2024

Foreign Application Priority Data

JP 2021-045378 Mar. 19, 2021

Publication Classification

Int. Cl.: H04N25/616 (20230101); H04N25/532 (20230101); H04N25/766 (20230101);
H04N25/77 (20230101); H04N25/78 (20230101)

U.S. Cl.:

CPC H04N25/616 (20230101); H04N25/532 (20230101); H04N25/766 (20230101);
H04N25/77 (20230101); H04N25/78 (20230101);

Field of Classification Search

CPC: H04N (25/532); H04N (25/616); H04N (25/766); H04N (25/77); H04N (25/771); H04N
(25/78)

References Cited

U.S. PATENT DOCUMENTS

Patent No.	Issued Date	Patentee Name	U.S. Cl.	CPC
2015/0341582	12/2014	Sakaguchi	348/301	H04N 25/771
2020/0260034	12/2019	Moue	N/A	H10F 39/802
2021/0144330	12/2020	Otake	N/A	H04N 25/443

FOREIGN PATENT DOCUMENTS

Patent No.	Application Date	Country	CPC
2015119340	12/2014	JP	N/A
2018207488	12/2017	JP	N/A
2019057873	12/2018	JP	N/A

OTHER PUBLICATIONS

International Search Report (PCT/ISA/210), International Application No. PCT/JP2022/000864, dated Mar. 22, 2022. cited by applicant

Geunsook Park et al., "A 2.2 μ m Stacked Back Side Illuminated Voltage Domain Global Shutter CMOS Image Sensor," 2019 IEEE International Electron Devices Meeting, pp. 16.4.1-16.4.4. cited by applicant

Primary Examiner: Ye; Lin

Assistant Examiner: Yoder, III; Chriss S

Attorney, Agent or Firm: Michael Best & Friedrich LLP

Background/Summary

TECHNICAL FIELD

(1) The present technology relates to a solid-state imaging element. Specifically, the present technology relates to a solid-state imaging element that performs analog to digital (AD) conversion for each column.

BACKGROUND ART

(2) Conventionally, for a solid-state imaging element, in order to miniaturizing pixels, a column analog to digital converter (ADC) method in which with an ADC arranged for each column outside a pixel array unit, pixel signals are sequentially read row by row has been used. In this column ADC method, in a case where exposure is performed by a rolling shutter method in which exposure starts row by row, there is a possibility that rolling shutter distortion occurs. Therefore, in order to realize a global shutter method in which exposure simultaneously starts in all pixels, a solid-state imaging element in which a pair of capacitors is provided for each pixel, and the capacitors hold a reset level and a signal level has been proposed (for example, refer to Non-Patent Document 1). A pair of transistors is arranged between the pair of capacitors and a pre-stage circuit, and the reset level and the signal level are supplied to the capacitors via the transistors.

CITATION LIST

Non-Patent Document

(3) Non-Patent Document 1: Geunsook Park et al., A 2.2 μm Stacked Back Side Illuminated Voltage Domain Global Shutter CMOS Image Sensor, 2019 IEEE International Electron Devices Meeting.

SUMMARY OF THE INVENTION

Problems to be Solved by the Invention

(4) In the above-described conventional technology, the reset level and the signal level are held in the pair of capacitors for each pixel, thereby realizing the global shutter method based on the column ADC method. In the above-described conventional technology, however, the longer the time during which a signal (reset level or signal level) is held in the pair of capacitors, the more likely that leakage current will occur at a pn junction between a high-impedance drain of a transistor or the like and a semiconductor substrate. When leakage current occurs, noise is generated in image data due to variations in leakage current for each pixel, and the image quality of the image data may deteriorate accordingly.

(5) The present technology has been made in view of such circumstances, and it is therefore an object of the present technology to improve image quality for a solid-state imaging element in which all pixels are simultaneously exposed.

Solutions to Problems

(6) The present technology has been made to solve the above-described problems, and a first aspect of the present technology is a solid-state imaging element including a predetermined number of capacitive elements, a pre-stage circuit that generates a predetermined reset level and a signal level corresponding to an exposure amount and causes each of the capacitive elements to hold a corresponding one of the reset level and the signal level, a selection circuit in which a selection transistor that opens and closes a path between one end of each of the capacitive elements and a predetermined node is arranged, a post-stage circuit that sequentially reads the reset level and the signal level via the node, and a vertical scanning circuit that performs control to lower a potential of the one end when the reset level and the signal level are held. This configuration brings about an effect of suppressing the occurrence of leakage current.

(7) Furthermore, according to the first aspect, the node may be a post-stage node that is a connection point between the selection circuit and the post-stage circuit, the capacitive elements may include first and second capacitive elements, the selection circuit may include a first selection transistor that opens and closes a path between one end of the first capacitive element and the post-stage node, and a second selection transistor that opens and closes a path between one end of the

second capacitive element and the post-stage node, the first and second capacitive elements having their respective other ends commonly connected to a predetermined pre-stage node, the pre-stage circuit may include a pre-stage selection transistor that outputs each of the reset level and the signal level to the pre-stage node in accordance with a predetermined pre-stage selection signal input to a gate, and the vertical scanning circuit may lower a voltage of the pre-stage selection signal when the reset level and the signal level are held. This configuration brings about an effect of suppressing the occurrence of leakage current by means of control of reference voltage.

(8) Furthermore, according to the first aspect, the node may be a pre-stage node that is a connection point between the pre-stage circuit and the selection circuit, the predetermined number of capacitive elements may include first and second capacitive elements, the selection circuit may include a first selection transistor that opens and closes a path between one end of the first capacitive element and the pre-stage node, and a second selection transistor that opens and closes a path between one end of the second capacitive element and the pre-stage node, and the vertical scanning circuit may lower a reference voltage of a signal line to which their respective other ends of the first and second capacitive elements are commonly connected when the reset level and the signal level are held. This configuration brings about an effect of suppressing the occurrence of leakage current by means of control of reference voltage.

(9) Furthermore, according to the first aspect, the node may be a pre-stage node that is a connection point between the pre-stage circuit and the selection transistor, the predetermined number of capacitive elements may include a first capacitive element inserted between the selection transistor and a predetermined signal line and a second capacitive element inserted between the selection transistor and the post-stage circuit, and the vertical scanning circuit may lower a reference voltage of the signal line when the reset level and the signal level are held. This configuration brings about an effect of suppressing the occurrence of leakage current by means of control of reference voltage.

(10) Furthermore, according to the first aspect, the node may be a connection node between the pre-stage circuit and the post-stage circuit, the predetermined number of capacitive elements may include first and second capacitive elements, the selection circuit may include a first selection transistor that opens and closes a path between one end of the first capacitive element and the connection node, and a second selection transistor that opens and closes a path between one end of the second capacitive element and the connection node, and the vertical scanning circuit may lower a reference voltage of a signal line to which their respective other ends of the first and second capacitive elements are commonly connected when the reset level and the signal level are held. This configuration brings about an effect of suppressing the occurrence of leakage current by means of control of reference voltage.

(11) Furthermore, according to the first aspect, a post-stage reset transistor may be further provided, the node may be a post-stage node that is a connection point between the selection circuit and the post-stage circuit, the pre-stage circuit may be arranged in a pre-stage circuit block that generates each of the reset level and a plurality of the signal levels corresponding to the exposure amount and causes each of the capacitive elements to hold a corresponding one of the reset level and the plurality of signal levels, the selection circuit may be arranged in a selection unit that sequentially performs control to connect a capacitive element in which the reset level is held among the predetermined number of capacitive elements to a predetermined post-stage node, control to disconnect the predetermined number of capacitive elements from the post-stage node, and control to connect a capacitive element in which one of the plurality of signal levels is held among the predetermined number of capacitive elements to the post-stage node, and the post-stage reset transistor may initialize a level of the post-stage node when the predetermined number of capacitive elements are disconnected from the post-stage node. This configuration brings about an effect of reducing kTC noise.

(12) Furthermore, according to the first aspect, the predetermined number of capacitive elements may include first and second capacitive elements and third and fourth capacitive elements, the pre-

stage circuit block may include a first pre-stage circuit that sequentially generates a first reset level and a first signal level and causes the first and second capacitive elements to hold the first reset level and the first signal level, and a second pre-stage circuit that sequentially generates a second reset level and a second signal level and causes the third and fourth capacitive elements to hold the second reset level and the second signal level, and the selection unit may include a first selection circuit that connects one of the first and second capacitive elements to the post-stage node, and a second selection circuit that connects one of the third and fourth capacitive elements to the post-stage node. This configuration brings about an effect of holding the reset level and the signal level of each of the two pixels.

(13) Furthermore, according to the first aspect, the first pre-stage circuit may include a first photoelectric conversion element, a first pre-stage transfer transistor that transfers charges from the first photoelectric conversion element to a first floating diffusion layer, a first reset transistor that initializes the first floating diffusion layer, and a first pre-stage amplification transistor that amplifies a voltage of the first floating diffusion layer, and the second pre-stage circuit may include a second photoelectric conversion element, a second pre-stage transfer transistor that transfers charges from the second photoelectric conversion element to a second floating diffusion layer, a second reset transistor that initializes the second floating diffusion layer, and a second pre-stage amplification transistor that amplifies a voltage of the second floating diffusion layer. This configuration brings about an effect of holding the level corresponding to the voltage of the floating diffusion layer.

(14) Furthermore, according to the first aspect, the first pre-stage circuit may further include a first current source transistor connected to a first pre-stage node, the second pre-stage circuit may further include a second current source transistor connected to a second pre-stage node, the first pre-stage amplification transistor may amplify the voltage of the first floating diffusion layer, and outputs the amplified voltage to the first pre-stage node, the second pre-stage amplification transistor may amplify the voltage of the second floating diffusion layer, and outputs the amplified voltage to the second pre-stage node, the first and second capacitive elements may have their respective one ends commonly connected to the first pre-stage node, and have their respective another ends connected to the first selection circuit, and the third and fourth capacitive elements may have their respective one ends commonly connected to the second pre-stage node, and have their respective another ends connected to the second selection circuit. This configuration brings about an effect of supplying a constant current to each pixel.

(15) Furthermore, according to the first aspect, at predetermined exposure start timing, the first and second pre-stage transfer transistors may transfer the charges to the first and second floating diffusion layers, and the first and second reset transistors may initialize the first and second floating diffusion layers and the first and second photoelectric conversion elements, and at predetermined exposure end timing, the first and second pre-stage transfer transistors may transfer the charges to the first and second floating diffusion layers. This configuration brings about an effect of simultaneously exposing all pixels.

(16) Furthermore, according to the first aspect, the selection unit may sequentially perform control to connect one of the first and second capacitive elements to the post-stage node, control to connect the other of the first and second capacitive elements to the post-stage node, control to connect one of the third and fourth capacitive elements to the post-stage node, and control to connect the other of the third and fourth capacitive elements to the post-stage node. This configuration brings about an effect of sequentially reading the reset level and the signal level of each of the two pixels.

(17) Furthermore, according to the first aspect, in a predetermined addition mode, the selection unit may sequentially perform control to connect both one of the first and second capacitive elements and one of the third and fourth capacitive elements to the post-stage node and control to connect both the other of the first and second capacitive elements and the other of the third and fourth capacitive elements to the post-stage node. This configuration brings about an effect of reading the

signal obtained by pixel addition.

(18) Furthermore, according to the first aspect, the first pre-stage circuit may further include a first pre-stage selection transistor that outputs a voltage amplified by the first pre-stage amplification transistor to a predetermined pre-stage node in accordance with a predetermined first selection signal, the second pre-stage circuit may further include a second pre-stage selection transistor that outputs a voltage amplified by the second pre-stage amplification transistor to the pre-stage node in accordance with a predetermined second selection signal, and a current source transistor connected to the pre-stage node, the first and second capacitive elements may have their respective one ends commonly connected to the pre-stage node, and have their respective another ends connected to the first selection circuit, and the third and fourth capacitive elements may have their respective one ends commonly connected to the pre-stage node, and have their respective another ends connected to the second selection circuit. This configuration brings about an effect of sharing the current source transistor by two pixels.

(19) Furthermore, according to the first aspect, the first and second pre-stage selection transistors may sequentially shift to a closed state immediately before a predetermined exposure end timing and after the exposure end timing, the first reset transistor may initialize the first floating diffusion layer in a case where the first pre-stage selection transistor is in the closed state, the second reset transistor may initialize the second floating diffusion layer in a case where the second pre-stage selection transistor is in the closed state, the first and second pre-stage selection transistors may sequentially shift to the closed state immediately after the exposure end timing, and the first and second pre-stage transfer transistors may transfer the charges at the predetermined exposure end timing. This configuration in which the current source transistor is shared by two pixels brings about an effect of simultaneously exposing all pixels.

(20) Furthermore, according to the first aspect, a short-circuit transistor that opens and closes a path between a first post-stage node and a second post-stage node may be further provided, the predetermined number of capacitors may include first, second, third, fourth, fifth, sixth, seventh, and eighth capacitive elements, and the selection unit may include a first selection circuit that connects one of the first and second capacitive elements to the first post-stage node, a second selection circuit that connects one of the third and fourth capacitive elements to the first post-stage node, a third selection circuit that connects one of the fifth and sixth capacitive elements to the second post-stage node, and a fourth selection circuit that connects one of the seventh and eighth capacitive elements to the second post-stage node. This configuration brings about an effect of short-circuiting the first post-stage node and the second post-stage node.

(21) Furthermore, according to the first aspect, in a predetermined non-addition mode, the short-circuit transistor may be in an open state, and in the non-addition mode, the selection unit may perform, in a predetermined order, control to sequentially connect each of the first and second capacitive elements to the first post-stage node, control to sequentially connect each of the third and fourth capacitive elements to the first post-stage node, control to sequentially connect each of the fifth and sixth capacitive elements to the second post-stage node, and control to sequentially connect each of the seventh and eighth capacitive elements to the second post-stage node. This configuration brings about an effect of sequentially reading the reset level and the signal level of each of the four pixels in the non-addition mode.

(22) Furthermore, according to the first aspect, in a predetermined addition mode, the short-circuit transistor may be in a closed state, and in the addition mode, the selection unit may sequentially perform control to connect one of the fifth and sixth capacitive elements and one of the seventh and eighth capacitive elements to the second post-stage node while connecting one of the first and second capacitive elements and one of the third and fourth capacitive elements to the first post-stage node, and control to connect the other of the fifth and sixth capacitive elements and the other of the seventh and eighth capacitive elements to the second post-stage node while connecting the other of the first and second capacitive elements and the other of the third and fourth capacitive

elements to the first post-stage node. This configuration brings about an effect of adding four pixels in the pixel addition mode.

(23) Furthermore, according to the first aspect, the predetermined number of capacitive elements may include first and second capacitive elements and a third capacitor, the pre-stage circuit block may include a first photoelectric conversion element, a first pre-stage transfer transistor that transfers charges from the first photoelectric conversion element to a predetermined floating diffusion layer, a second photoelectric conversion element, a second pre-stage transfer transistor that transfers charges from the second photoelectric conversion element to a predetermined floating diffusion layer, a reset transistor that initializes the floating diffusion layer, and a pre-stage amplification transistor that amplifies a voltage of the floating diffusion layer and outputs the amplified voltage to a predetermined pre-stage node, and the first and second capacitive elements and the third capacitive element may have their respective one ends commonly connected to the pre-stage node, and have their respective another ends connected to the selection unit. This brings about an effect of holding the reset level and the plurality of signal levels.

(24) Furthermore, according to the first aspect, at predetermined exposure start timing, the first and second pre-stage transfer transistors may transfer the charges to the floating diffusion layer, and the reset transistor may initialize the floating diffusion layer and the first and second photoelectric conversion elements, and at predetermined exposure end timing, the first and second pre-stage transfer transistors may sequentially transfer the charges to the first and second floating diffusion layers. This brings about an effect of exposing all pixels.

(25) Furthermore, according to the first aspect, the selection unit may sequentially perform control to connect one of the first and second capacitive elements to the post-stage node, control to connect the other of the first and second capacitive elements to the post-stage node, and control to connect the third capacitive element to the post-stage node. This brings about an effect of sequentially reading the reset level and the plurality of signal levels.

Description

BRIEF DESCRIPTION OF DRAWINGS

(1) FIG. 1 is a block diagram depicting a configuration example of an imaging device in a first embodiment of the present technology.

(2) FIG. 2 is a block diagram depicting a configuration example of a solid-state imaging element in the first embodiment of the present technology.

(3) FIG. 3 is a circuit diagram depicting a configuration example of a pixel in the first embodiment of the present technology.

(4) FIG. 4 is an example of a cross-sectional view of a pre-stage selection transistor in the first embodiment of the present technology.

(5) FIG. 5 is a block diagram depicting a configuration example of a column signal processing circuit in the first embodiment of the present technology.

(6) FIG. 6 is a timing chart depicting an example of a global shutter operation in the first embodiment of the present technology.

(7) FIG. 7 is a timing chart depicting an example of a read operation of the pixel in the first embodiment of the present technology.

(8) FIG. 8 is a circuit diagram depicting a configuration example of a pixel in a comparative example.

(9) FIG. 9 is a diagram depicting an example of states of the pixel at the time of reading a reset level and at the time of initialization of a post-stage node in the first embodiment of the present technology.

(10) FIG. 10 is a diagram depicting an example of a state of the pixel at the time of reading a signal

level in the first embodiment of the present technology.

(11) FIG. 11 is a circuit diagram depicting a configuration example of a pixel block in a second embodiment of the present technology.

(12) FIG. 12 is a circuit diagram depicting a configuration example of a pre-stage circuit and a selection circuit in the second embodiment of the present technology.

(13) FIG. 13 is a timing chart depicting an example of a global shutter operation in the second embodiment of the present technology.

(14) FIG. 14 is a timing chart depicting an example of a read operation of a first pixel in the pixel block in the second embodiment of the present technology.

(15) FIG. 15 is a timing chart depicting an example of a read operation of a second pixel in the pixel block in the second embodiment of the present technology.

(16) FIG. 16 is a flowchart depicting an example of an operation of a solid-state imaging element in the second embodiment of the present technology.

(17) FIG. 17 is a timing chart depicting an example of a read operation of a reset level and a signal level in a first modification example of the second embodiment of the present technology.

(18) FIG. 18 is a diagram depicting an example of a laminated structure of a solid-state imaging element in a second modification example of the second embodiment of the present technology.

(19) FIG. 19 is a circuit diagram depicting a configuration example of a pixel block in the second modification example of the second embodiment of the present technology.

(20) FIG. 20 is a diagram depicting an example of a laminated structure of a solid-state imaging element in a third modification example of the second embodiment of the present technology.

(21) FIG. 21 is a plan view depicting a configuration example of a pixel array unit in a third embodiment of the present technology.

(22) FIG. 22 is a circuit diagram depicting a configuration example of a pixel block in the third embodiment of the present technology.

(23) FIG. 23 is a circuit diagram depicting a configuration example of a pre-stage circuit and a selection circuit in the third embodiment of the present technology.

(24) FIG. 24 is a timing chart depicting an example of a read operation of first and second pixels in the pixel block in the third embodiment of the present technology.

(25) FIG. 25 is a timing chart depicting an example of a read operation of third and fourth pixels in the pixel block in the third embodiment of the present technology.

(26) FIG. 26 is a timing chart depicting an example of a read operation in an addition mode in the third embodiment of the present technology.

(27) FIG. 27 is a circuit diagram depicting a configuration example of a pixel block in a fourth embodiment of the present technology.

(28) FIG. 28 is a timing chart depicting an example of a global shutter operation in the fourth embodiment of the present technology.

(29) FIG. 29 is a timing chart depicting an example of control immediately after the end of exposure in the fourth embodiment of the present technology.

(30) FIG. 30 is a circuit diagram depicting a configuration example of a pixel block in a fifth embodiment of the present technology.

(31) FIG. 31 is a timing chart depicting an example of a global shutter operation in the fifth embodiment of the present technology.

(32) FIG. 32 is a timing chart depicting an example of a read operation of a reset level and a signal level in the fifth embodiment of the present technology.

(33) FIG. 33 is a circuit diagram depicting a configuration example of a pixel in a sixth embodiment of the present technology.

(34) FIG. 34 is a timing chart depicting an example of a global shutter operation in the sixth embodiment of the present technology.

(35) FIG. 35 is a timing chart depicting an example of a read operation of the pixel in the sixth

embodiment of the present technology.

(36) FIG. **36** is a circuit diagram depicting a configuration example of a pixel in a seventh embodiment of the present technology.

(37) FIG. **37** is a timing chart depicting an example of a global shutter operation in the seventh embodiment of the present technology.

(38) FIG. **38** is a timing chart depicting an example of a read operation of the pixel in the seventh embodiment of the present technology.

(39) FIG. **39** is a circuit diagram depicting a configuration example of a pixel in an eighth embodiment of the present technology.

(40) FIG. **40** is a timing chart depicting an example of a read operation of the pixel in the eighth embodiment of the present technology.

(41) FIG. **41** is a block diagram depicting a schematic configuration example of a vehicle control system.

(42) FIG. **42** is an explanatory diagram depicting an example of an installation position of an imaging section.

MODE FOR CARRYING OUT THE INVENTION

(43) Hereinafter, modes for carrying out the present technology (hereinafter referred to as embodiments) will be described. The description will be given in the following order. 1. First Embodiment (example of controlling pre-stage selection transistor) 2. Second Embodiment (example of sharing circuit by two pixels and controlling pre-stage selection transistor) 3. Third Embodiment (example of short-circuiting post-stage nodes and controlling pre-stage selection transistor) 4. Fourth Embodiment (example of sharing current source and controlling pre-stage selection transistor) 5. Fifth Embodiment (example of causing one capacitor to hold reset level, causing a plurality of capacitors to hold signal level, and controlling pre-stage selection transistor) 6. Sixth Embodiment (example of controlling reference voltage) 7. Seventh Embodiment (example of controlling reference voltage) 8. Eighth Embodiment (example of controlling reference voltage) 9. Application Example to Mobile Body

1. First Embodiment

Configuration Example of Imaging Device

(44) FIG. **1** is a block diagram depicting a configuration example of an imaging device **100** in a first embodiment of the present technology. The imaging device **100** is a device that captures image data, and includes an imaging lens **110**, a solid-state imaging element **200**, a recording unit **120**, and an imaging control unit **130**. As the imaging device **100**, a digital camera, and an electronic device (a smartphone, a personal computer, or the like) having an imaging function are assumed.

(45) The solid-state imaging element **200** captures the image data under control of the imaging control unit **130**. The solid-state imaging element **200** supplies the image data to the recording unit **120** via a signal line **209**.

(46) The imaging lens **110** condenses light and guides the light to the solid-state imaging element **200**. The imaging control unit **130** controls the solid-state imaging element **200** to capture the image data. For example, the imaging control unit **130** supplies an imaging control signal including a vertical synchronization signal VSYNC to the solid-state imaging element **200** via a signal line **139**. The recording unit **120** records the image data.

(47) Here, the vertical synchronization signal VSYNC is a signal indicating imaging timing, and a periodic signal of a constant frequency (such as 60 hertz) is used as the vertical synchronization signal VSYNC.

(48) Note that although the imaging device **100** records the image data, the image data may be transmitted to the outside of the imaging device **100**. In this case, an external interface for transmitting the image data is further provided. Alternatively, the imaging device **100** may further display the image data. In this case, a display section is further provided.

Configuration Example of Solid-State Imaging Element

(49) FIG. 2 is a block diagram depicting a configuration example of the solid-state imaging element **200** in the first embodiment of the present technology. The solid-state imaging element **200** includes a vertical scanning circuit **211**, a pixel array unit **220**, a timing control circuit **212**, a digital to analog converter (DAC) **213**, a load MOS circuit block **250**, and a column signal processing circuit **260**. In the pixel array unit **220**, a plurality of pixels such as pixels **301** is arranged in a two-dimensional lattice pattern. Furthermore, each circuit in the solid-state imaging element **200** is provided in, for example, a single semiconductor chip.

(50) The timing control circuit **212** controls the operation timing of each of the vertical scanning circuit **211**, the DAC **213**, and the column signal processing circuit **260** in synchronization with the vertical synchronization signal VSYNC from the imaging control unit **130**.

(51) The DAC **213** generates a sawtooth wave-like ramp signal by digital-to-analog (DA) conversion. The DAC **213** supplies the generated ramp signal to the column signal processing circuit **260**.

(52) The vertical scanning circuit **211** sequentially selects and drives rows, and outputs analog pixel signals. The pixel photoelectrically converts incident light to generate an analog pixel signal. This pixel supplies the pixel signal to the column signal processing circuit **260** via the load MOS circuit block **250**.

(53) In the load MOS circuit block **250**, a MOS transistor that supplies a constant current is provided for each column.

(54) The column signal processing circuit **260** performs signal processing such as AD conversion processing and correlated double sampling (CDS) processing on the pixel signal for each column. The column signal processing circuit **260** supplies the image data including the processed signals to the recording unit **120**.

Configuration Example of Pixel

(55) FIG. 3 is a circuit diagram depicting a configuration example of the pixel **301** in the first embodiment of the present technology. In the pixel **301**, a pre-stage circuit **310**, capacitive elements **331** and **332**, a selection circuit **350**, a post-stage reset transistor **361**, and a post-stage circuit **370** are arranged. As the capacitive elements **331** and **332**, for example, a capacitor having a metal-insulator-metal (MIM) structure is used. Note that the capacitive elements **331** and **332** are examples of first and second capacitive elements described in the claims.

(56) The pre-stage circuit **310** sequentially generates a reset level and a signal level, and causes the capacitive elements **331** and **332** to hold the reset level and the signal level. The pre-stage circuit **310** includes a photoelectric conversion element **311**, a transfer transistor **312**, a floating diffusion (FD) reset transistor **313**, an FD **314**, a pre-stage amplification transistor **315**, a current source transistor **316**, and a pre-stage selection transistor **317**.

(57) The photoelectric conversion element **311** generates charges by the photoelectric conversion. The transfer transistor **312** transfers the charges from the photoelectric conversion element **311** to the FD **314** in accordance with a transfer signal trg from the vertical scanning circuit **211**.

(58) The FD reset transistor **313** extracts the charges from the FD **314** to initialize the FD **314** in accordance with an FD reset signal rst from the vertical scanning circuit **211**. The FD **314** accumulates charges, and generates a voltage corresponding to a charge amount.

(59) The pre-stage amplification transistor **315** amplifies the level of the voltage of the FD **314**. The pre-stage selection transistor **317** outputs the level amplified by the pre-stage amplification transistor **315** to a pre-stage node **330** in accordance with a pre-stage selection signal sela from the vertical scanning circuit **211**.

(60) The FD reset transistor **313** and the pre-stage amplification transistor **315** have their respective drains connected to a power supply voltage VDD. The current source transistor **316** is connected to the source of the pre-stage selection transistor **317**. The current source transistor **316** supplies a current id1 under the control of the vertical scanning circuit **211**.

(61) The capacitive elements **331** and **332** have their respective one ends commonly connected to

the pre-stage node **330**, and have their respective other ends connected to the selection circuit **350**.
(62) The selection circuit **350** includes selection transistors **351** and **352**. The selection transistor **351** opens and closes a path between the capacitive element **331** and a post-stage node **360** in accordance with a selection signal Φ_r from the vertical scanning circuit **211**. The selection transistor **352** opens and closes a path between the capacitive element **332** and the post-stage node **360** in accordance with a selection signal Φ_s from the vertical scanning circuit **211**.

(63) The post-stage reset transistor **361** initializes the level of the post-stage node **360** to a predetermined potential V_{reg} in accordance with a post-stage reset signal $rstb$ from the vertical scanning circuit **211**. A potential different from the power supply voltage VDD (for example, a potential lower than VDD) is set as the potential V_{reg} .

(64) The post-stage circuit **370** includes a post-stage amplification transistor **371**, and a post-stage selection transistor **372**. The post-stage amplification transistor **371** amplifies the level of the post-stage node **360**. The post-stage selection transistor **372** outputs a signal at the level amplified by the post-stage amplification transistor **371** to a vertical signal line **309** as a pixel signal in accordance with a post-stage selection signal $selb$ from the vertical scanning circuit **211**.

(65) Note that, for example, n-channel metal oxide semiconductor (nMOS) transistors are used as various transistors (transfer transistor **312** and the like) in the pixel **301**.

(66) The vertical scanning circuit **211** supplies a high-level FD reset signal rst and a high-level transfer signal trg to all rows at the start of exposure. Therefore, the photoelectric conversion element **311** is initialized. Hereinafter, this control is referred to as “PD reset”.

(67) Then, the vertical scanning circuit **211** supplies the high-level FD reset signal rst over the pulse period while setting the pre-stage selection signal $sela$, the post-stage reset signal $rstb$, and the selection signal Φ_r to the high level for all the rows immediately before the end of the exposure. Therefore, the FD **314** is initialized, and a level corresponding to the level of the FD **314** at that time is held in the capacitive element **331**. This control is hereinafter referred to as “FD reset”.

(68) The level of the FD **314** at the time of FD reset and the level (the level held in the capacitive element **331** and the level of the vertical signal line **309**) corresponding to the level of the FD **314** are hereinafter collectively referred to as “P-phase” or “reset level”.

(69) At the end of the exposure, the vertical scanning circuit **211** supplies the high-level transfer signal trg over the pulse period while setting the pre-stage selection signal $sela$, the post-stage reset signal $rstb$, and the selection signal Φ_s to the high level for all the rows. Therefore, signal charges corresponding to the exposure amount are transferred to the FD **314**, and a level corresponding to the level of the FD **314** at that time is held in the capacitive element **332**.

(70) The level of the FD **314** at the time of signal charge transfer and the level (the level held in the capacitive element **332** and the level of the vertical signal line **309**) corresponding to the level of the FD **314** are hereinafter collectively referred to as “D-phase” or “signal level”.

(71) The exposure control of simultaneously starting and ending the exposure for all the pixels in this manner is called a global shutter method. By this exposure control, the pre-stage circuit **310** of all the pixels sequentially generates the reset level and the signal level. The reset level is held in the capacitive element **331**, and the signal level is held in the capacitive element **332**.

(72) After the end of the exposure, the vertical scanning circuit **211** sequentially selects a row, and sequentially outputs the reset level and the signal level of the row. In a case of outputting the reset level, the vertical scanning circuit **211** supplies the high-level selection signal Φ_r over a predetermined period while setting the pre-stage selection signal $sela$ and the post-stage selection signal $selb$ of the selected row to the high level. Therefore, the capacitive element **331** is connected to the post-stage node **360**, and the reset level is read.

(73) After the reset level is read, the vertical scanning circuit **211** opens the selection transistors **351** and **352** over a certain period to disconnect the capacitive elements **331** and **332** from the post-stage node **360**. Note that, at this time, the post-stage reset transistor **361** of the selected row may initialize the level of the post-stage node **360**.

(74) The vertical scanning circuit **211** supplies the high-level selection signal Φ_s over a predetermined period with the pre-stage selection signal $sela$ and the post-stage selection signal $selb$ of the selected row kept at the high level. Therefore, the capacitive element **332** is connected to the post-stage node **360**, and the signal level is read.

(75) By the above-described read control, the selection circuit **350** of the selected row sequentially performs control to connect the capacitive element **331** to the post-stage node **360**, control to disconnect the capacitive elements **331** and **332** from the post-stage node **360**, and control to connect the capacitive element **332** to the post-stage node **360**.

(76) Furthermore, the post-stage circuit **370** of the selected row sequentially read the reset level and the signal level from the capacitive elements **331** and **332** via the post-stage node **360**, and output the reset level and the signal level to the vertical signal line **309**.

(77) Here, a node **353** between the capacitive element **331** and the selection transistor **351** in the drawing is in a high-impedance state while the signal (the reset level or the signal level) is held in the capacitive element **331**. Furthermore, a node **354** between the capacitive element **332** and the selection transistor **352** is also in the high-impedance state. A gray semicircle in the drawing indicates a node that becomes high impedance during hold.

(78) The column signal processing circuit **260** sequentially performs the reading row by row after the end of the exposure by the global shutter method, so that the capacitive elements **331** and **332** need to hold the reset level and the signal level over a period from the end of the exposure to the reading. The later a row is in the read order, the longer the hold time, and the hold time may reach several tens of milliseconds for a row that is last in the read order, for example. The longer the hold time and the higher the potentials of the high-impedance nodes **353** and **354**, the more likely that leakage current will occur at a pn junction between the nodes and a semiconductor substrate.

(79) When leakage current occurs, noise is generated in image data due to variations in leakage current for each pixel, and there is a possibility that the image quality of the image data deteriorates. Therefore, in order to suppress the occurrence of leakage current, the vertical scanning circuit **211** lowers the pre-stage selection signal $sela$ from the high level (the power supply voltage VDD or the like) to a middle level V_m when the reset level and the signal level are held. The middle level V_m is a voltage between the high level and a low level (such as a ground voltage). In response to the decrease in the voltage of the pre-stage selection signal $sela$, the potential of the pre-stage node **330** decreases, and the potentials of the nodes **353** and **354** also shift to the lower level accordingly. It is therefore possible to suppress the occurrence of leakage current.

(80) FIG. **4** is an example of a cross-sectional view of the selection transistor **351** in the first embodiment of the present technology. In a p.sup.+ semiconductor substrate **501**, n.sup.+ regions **502** and **504** are formed. Furthermore, a gate electrode **503** is formed between these regions with an oxide film interposed between the gate electrode **503** and the regions.

(81) The n.sup.+ regions **502** and **504** and the gate electrode **503** function as the selection transistor **351**. The n.sup.+ region **502** is a drain of the selection transistor **351** and is connected to one end of the capacitive element **331**. The node **353** is in a high-impedance state while the signal level or the like is held.

(82) The higher the potential of the high-impedance node **353**, the more likely that leakage current will occur at the pn junction between the node **353** and the semiconductor substrate **501**. A dotted line in the drawing indicates leakage current that occurs in a case where the potential is high. The same applies to the node **354**.

(83) Therefore, as described above, the vertical scanning circuit **211** lowers the potentials of the nodes **353** and **354** by lowering the pre-stage selection signal $sela$ to the middle level V_m . Therefore, the leakage current that occurs at the pn junction can be suppressed.

(84) However, when the potentials of the nodes **353** and **354** are too low, leakage current may increase between the drain and the source of the selection transistors **351** and **352**. A long dashed short dashed line in the drawing indicates leakage current that occurs in a case where the potential

is too low.

(85) Therefore, the middle level V_m is adjusted to an optimum value at which the occurrence of both the leakage current from the drain to the semiconductor substrate **501** and the leakage current between the drain and the source can be suppressed.

Configuration Example of Column Signal Processing Circuit

(86) FIG. 5 is a block diagram depicting a configuration example of the column signal processing circuit **260** in the first embodiment of the present technology.

(87) In the load MOS circuit block **250**, the vertical signal line **309** is wired for each column. In a case where the number of columns is I (I is an integer), I vertical signal lines **309** are wired.

Furthermore, a load MOS transistor **251** that supplies a constant current id_2 is connected to each of the vertical signal lines **309**.

(88) In the column signal processing circuit **260**, a plurality of ADCs **261** and a digital signal processing unit **262** are arranged. The ADC **261** is arranged for each column. In a case where the number of columns is I , I ADCs **261** are arranged.

(89) The ADC **261** converts an analog pixel signal from the corresponding column into a digital signal using a ramp signal Rmp from the DAC **213**. The ADC **261** supplies the digital signal to the digital signal processing unit **262**. For example, a single-slope ADC including a comparator and a counter is arranged as the ADC **261**.

(90) The digital signal processing unit **262** performs predetermined signal processing such as CDS processing on each of the digital signals for each column. The digital signal processing unit **262** supplies image data including the processed digital signal to the recording unit **120**.

Operation Example of Solid-State Imaging Element

(91) FIG. 6 is a timing chart depicting an example of a global shutter operation in the first embodiment of the present technology. The vertical scanning circuit **211** sets the post-stage reset signal r_{stb} and the selection signal Φ_r to the high level for all the rows (in other words, all the pixels) at timing T_0 immediately before the start of the exposure.

(92) Furthermore, the vertical scanning circuit **211** supplies the high-level FD reset signal r_{st} and the high-level transfer signal trg to all the rows over a period from timing T_0 to timing T_1 after the pulse period elapses. Therefore, all the pixels are PD reset, and the exposure simultaneously starts in all the rows.

(93) Here, $r_{st}[n]$, $trg[n]$, $sela[n]$, $selb[n]$, $r[n]$, and $\Phi_s[n]$ in the drawing indicate signals to pixels in an n -th row among N rows. N is an integer indicating the total number of rows, and n is an integer from 1 to N .

(94) At timing T_2 immediately before the end of the exposure period, the vertical scanning circuit **211** turns on the current source transistor **316** while setting the pre-stage selection signal $sela$ to the high level, and supplies the high-level FD reset signal r_{st} over the pulse period for all the rows. Therefore, all the pixels are FD reset, and the reset level is sampled and held.

(95) At timing T_3 after timing T_2 , the vertical scanning circuit **211** returns the selection signal Φ_r to the low level.

(96) At timing T_4 of the end of the exposure, the vertical scanning circuit **211** sets the selection signal Φ_s to the high level and supplies the high-level transfer signal trg over the pulse period for all the rows. Therefore, the signal level is sampled and held. Furthermore, the potential of the pre-stage node **330** decreases from $VDD - V_{gs}$ to $VDD - V_{gs} - V_{sig}$. Here, V_{gs} represents a gate-source voltage of the pre-stage selection transistor **317**, and V_{sig} represents the signal level.

(97) At timing T_5 after timing T_4 , the vertical scanning circuit **211** returns the selection signal Φ_s to the low level. At timing T_6 immediately after that, the vertical scanning circuit **211** returns the post-stage reset signal r_{stb} to the low level.

(98) At timing T_7 after timing T_6 , the vertical scanning circuit **211** sets the FD reset signal r_{st} to the high level and lowers the pre-stage selection signal $sela$ from the high level (the power supply voltage VDD or the like) to the middle level V_m . Therefore, the potential of the pre-stage node

decreases from $VDD - V_{gs} - V_{sig}$ and becomes $V_m - V_{gs}$ at timing **T8**.

(99) In response to the change in the potential of the pre-stage node **330**, the high-impedance node **353** on the reset side decreases from V_{reg} to $V_{reg} - (VDD - V_m)$. The high-impedance node **354** on the signal side decreases from V_{reg} to $V_{reg} - (VDD - V_m) + V_{sig}$.

(100) At timing **T8** when the potentials of the nodes **353** and **354** decrease, the vertical scanning circuit **211** turns off the current source transistor **316** to stop the current i_{d1} . At subsequent timing **T9**, the vertical scanning circuit **211** sets the pre-stage selection signal s_{ela} to the low-level (the ground voltage VSS or the like).

(101) If the pre-stage selection transistor **317** is not provided, the potential of the node **354** increases to $V_{reg} + V_{sig}$ while the potential of the node **353** remains at V_{reg} at timing **T7**. A long dashed short dashed line in the drawing indicates changes in the potentials of the nodes **353** and **354** in a case where the pre-stage selection transistor **317** is not provided. In this case, since the nodes **353** and **354** have high potentials, there is a possibility that leakage current occurs at the pn junction.

(102) However, since the pre-stage selection transistor **317** is provided, and the vertical scanning circuit **211** lowers the pre-stage selection signal s_{ela} to the middle level V_m , it is possible to lower the potentials of the nodes **353** and **354**. It is therefore possible to suppress the occurrence of leakage current.

(103) FIG. 7 is a timing chart depicting an example of a read operation of the pixel in the first embodiment of the present technology. During the read period of the n-th row after timing **T10**, the vertical scanning circuit **211** sets the pre-stage selection signal s_{ela} and the post-stage selection signal s_{elb} of the n-th row to the high level with the FD reset signal r_{st} kept at the high level. Furthermore, the vertical scanning circuit **211** supplies the high-level post-stage reset signal r_{stb} to the n-th row over the pulse period from timing **T10**.

(104) The vertical scanning circuit **211** supplies the high-level selection signal Φ_r to the n-th row over a period from timing **T11** immediately after timing **T10** to timing **T12**. The potential of the pre-stage node **330** increases back to the power supply voltage VDD , and the potentials of the nodes **353** and **354** increase accordingly. Furthermore, the potential of the post-stage node **360** becomes the reset level. This reset level is AD-converted by the ADC **261**.

(105) Furthermore, the vertical scanning circuit **211** supplies the high-level post-stage reset signal r_{stb} over the pulse period from timing **T13**.

(106) Then, the vertical scanning circuit **211** supplies the high-level selection signal Φ_s to the n-th row over a period from timing **T14** to timing **T15**. The potential of the post-stage node **360** becomes the signal level. This signal level is AD-converted by the ADC **261**. A difference between the reset level and the signal level corresponds to a net signal level from which reset noise and offset noise of the FD have been removed.

(107) As illustrated in the drawing, the high-level selection signals Φ_r and Φ_s are sequentially supplied. In accordance with these selection signals, a selection unit **340** sequentially connects the capacitive elements **331** and **332** to the post-stage node **360**. Then, the reset level and the signal level of the first pixel in a pixel block **300** are sequentially read.

(108) If the pre-stage selection signal s_{ela} remains at the low level during the read period (period from timing **T10** to **T15**), the potentials of the nodes **353** and **354** decrease, and the potential of the vertical signal line **309** also decreases. In this case, there is a possibility that the operating point and range of the post-stage circuit cannot be sufficiently secured. Therefore, the vertical scanning circuit **211** returns the pre-stage selection signal s_{ela} to the high level during the read period.

(109) Note that the solid-state imaging element **200** reads the signal level after the reset level, but is not limited to this order. The solid-state imaging element **200** can also read the reset level after the signal level. In this case, the vertical scanning circuit **211** supplies the high-level selection signal Φ_r after the high-level selection signal Φ_s . Furthermore, in this case, it is necessary to reverse the slope of the slope of the ramp signal.

(110) FIG. 8 is a circuit diagram depicting a configuration example of a pixel in a comparative example. In this comparative example, the selection circuit 350 is not provided, and a transfer transistor is inserted between the pre-stage node 330 and the pre-stage circuit. Furthermore, capacitors C1 and C2 are inserted instead of the capacitive elements 331 and 332. The capacitor C1 is inserted between the pre-stage node 330 and the ground terminal, and the capacitor C2 is inserted between the pre-stage node 330 and the post-stage node 360.

(111) The exposure control and the read control of the pixel in this comparative example are described in FIG. 5.5.2 of “Jae-kyu Lee, et al., A 2.1e-Temporal Noise and -105 dB Parasitic Light Sensitivity Backside-Illuminated 2.3 μm -Pixel Voltage-Domain Global Shutter CMOS Image Sensor Using High-Capacity DRAM Capacitor Technology, ISSCC 2020”, for example. In this comparative example, assuming that the capacitance value of each of the capacitors C1 and C2 is C, a level V_n of kTC noise at the time of exposure and reading is expressed by the following expression.

$$V_n = (3 * kT / C)^{.sup.1/2} \quad \text{Expression 1}$$

(112) In the above expression, k is a Boltzmann constant, and the unit is, for example, Joule per Kelvin (J/K). T is an absolute temperature, and the unit is, for example, Kelvin (K). Furthermore, the unit of V_n is, for example, volt (V), and the unit of C is, for example, farad (F).

(113) FIG. 9 is a diagram depicting an example of states of the pixel 301 at the time of reading the reset level and at the time of initialization of the post-stage node in the first embodiment of the present technology. In the drawing, a indicates the state of the pixel 301 at the time of reading the reset level, and b in the drawing indicates the state of the pixel 301 at the time of initialization of the post-stage node 360. Furthermore, in the drawing, the selection transistor 351, the selection transistor 352, and the post-stage reset transistor 361 are represented by graphical symbols of switches for convenience of description.

(114) As illustrated in a of the drawing, the vertical scanning circuit 211 closes the selection transistor 351, and opens the selection transistor 352 and the post-stage reset transistor 361. Therefore, the reset level of the first pixel is read through the post-stage circuit 370.

(115) As illustrated in b of the drawing, after the reset level is read, the vertical scanning circuit 211 opens the selection transistor 351 and the selection transistor 352, and closes the post-stage reset transistor 361. Therefore, the capacitive elements 331 and 332 are disconnected from the post-stage node 360, and the level of the post-stage node 360 is initialized.

(116) The capacitance value of a parasitic capacitance C_p of the post-stage node 360 disconnected from the capacitive elements 331 and 332 in this manner is assumed to be very small as compared with the capacitive elements 331 and 332. For example, assuming that the parasitic capacitance C_p is several femtofarads (fF), the capacitive elements 331 and 332 are on the order of several tens of femtofarads.

(117) FIG. 10 is a diagram depicting an example of a state of the pixel 301 at the time of reading the signal level in the first embodiment of the present technology.

(118) After the initialization of the post-stage node 360, the vertical scanning circuit 211 closes the selection transistor 352, and opens the selection transistor 351 and the post-stage reset transistor 361. Therefore, the signal level of the first pixel is read through the post-stage circuit 370.

(119) Here, kTC noise at the time of exposure of pixels is considered. At the time of the exposure, kTC noise occurs in each of sampling of the reset level and sampling of the signal level immediately before the end of the exposure. Assuming that the capacitance value of each of the capacitive elements 331 and 332 is C, the level V_n of the kTC noise at the time of the exposure is expressed by the following expression.

$$V_n = (2 * kT / C)^{.sup.1/2} \quad \text{Expression 2}$$

(120) Furthermore, as illustrated in FIGS. 9 and 10, since the post-stage reset transistor 361 is driven at the time of the reading, the kTC noise occurs at that time. However, the capacitive elements 331 and 332 are disconnected at the time of driving the post-stage reset transistor 361,

and the parasitic capacitance C_p at that time is small. Therefore, the kTC noise at the time of the reading can be ignored as compared with the kTC noise at the time of the exposure. Therefore, the kTC noise at the time of the exposure and reading is expressed by Expression 7.

(121) With Expressions 1 and 2, in the pixel block **300** in which the capacitor is disconnected at the time of the reading, the kTC noise is smaller than that in the comparative example in which the capacitor cannot be disconnected at the time of the reading. Therefore, the image quality of the image data can be improved.

(122) As described above, according to the first embodiment of the present technology, since the held potentials of the nodes **353** and **354** are lowered by means of the control of the pre-stage selection transistor **317**, it is possible to suppress the occurrence of the leakage current at the pn junction. Therefore, the image quality of the image data can be improved.

2. Second Embodiment

(123) In the first embodiment described above, the post-stage reset transistor and the selection circuit are arranged for each pixel, but with this configuration, it is difficult to reduce the circuit scale. The solid-state imaging element **200** of the second embodiment is different from that of the first embodiment in that two adjacent pixels share a post-stage reset transistor and a selection circuit.

(124) FIG. **11** is a circuit diagram depicting a configuration example of the pixel block **300** in the second embodiment of the present technology. In the pixel array unit **220** of the second embodiment, a plurality of pixel blocks **300** is arranged. In each of the pixel blocks **300**, the pixel **301** and a pixel **302** are arranged.

(125) In the pixel block **300**, a pre-stage circuit block **305**, capacitive elements **331**, **332**, **336**, and **337**, the selection unit **340**, the post-stage reset transistor **361**, and the post-stage circuit **370** are arranged.

(126) Furthermore, pre-stage circuits **310** and **320** are arranged in the pre-stage circuit block **305**. In the selection unit **340**, selection circuits **350** and **355** are arranged. The post-stage circuit **370** includes the post-stage amplification transistor **371**, and the post-stage selection transistor **372**.

(127) The selection circuit **350** connects one of the capacitive elements **331** and **332** to the post-stage node **360**. The selection circuit **355** connects one of the capacitive elements **336** and **337** to the post-stage node **360**. Note that the selection circuit **350** is an example of a first selection circuit described in the claims, and the selection circuit **355** is an example of a second selection circuit described in the claims.

(128) FIG. **12** is a circuit diagram depicting a configuration example of the pre-stage circuits **310** and **320** and the selection circuits **350** and **355** in the second embodiment of the present technology.

(129) The pre-stage circuit **310** includes the photoelectric conversion element **311**, the transfer transistor **312**, the FD reset transistor **313**, the FD **314**, the pre-stage amplification transistor **315**, the current source transistor **316**, and the pre-stage selection transistor **317**.

(130) Furthermore, the pre-stage circuit **320** includes a photoelectric conversion element **321**, a transfer transistor **322**, an FD reset transistor **323**, an FD **324**, a pre-stage amplification transistor **325**, a current source transistor **326**, and a pre-stage selection transistor **327**. The pre-stage selection signal *sela* is supplied to the pre-stage selection transistors **317** and **327**.

(131) The photoelectric conversion elements **311** and **321** generate charges by photoelectric conversion. The transfer transistor **312** transfers the charges from the photoelectric conversion element **311** to the FD **314** in accordance with a transfer signal *trg1* from the vertical scanning circuit **211**. The transfer transistor **322** transfers the charges from the photoelectric conversion element **321** to the FD **324** in accordance with a transfer signal *trg2* from the vertical scanning circuit **211**.

(132) Note that the photoelectric conversion elements **311** and **321** are examples of first and second photoelectric conversion elements described in the claims. Note that the transfer transistors **312** and **322** are examples of first and second transfer transistors described in the claims.

(133) The FD reset transistor **313** extracts the charges from the FD **314** to initialize the FD **314** in accordance with an FD reset signal **rst1** from the vertical scanning circuit **211**. The FD reset transistor **323** extracts the charges from the FD **324** to initialize the FD **324** in accordance with an FD reset signal **rst2** from the vertical scanning circuit **211**. The FDs **314** and **324** accumulate charges, and generate a voltage corresponding to a charge amount.

(134) Note that the FD reset transistors **313** and **323** are examples of first and second reset transistors described in the claims. The FDs **314** and **324** are examples of first and second floating diffusion layers described in the claims.

(135) The pre-stage amplification transistor **315** amplifies the level of the voltage of the FD **314**, and outputs the amplified voltage to the pre-stage node **330** via the pre-stage selection transistor **317**. The pre-stage amplification transistor **325** amplifies the level of the voltage of the FD **324**, and outputs the amplified voltage to a pre-stage node **335** via the pre-stage selection transistor **327**. Note that the pre-stage amplification transistors **315** and **325** are examples of first and second pre-stage amplification transistors described in the claims.

(136) The FD reset transistors **313** and **323** and the pre-stage amplification transistors **315** and **325** have their respective drains connected to the power supply voltage **VDD**. The current source transistor **316** is connected to the source of the pre-stage selection transistor **317**. The current source transistor **316** supplies a current **id11** under the control of the vertical scanning circuit **211**. The current source transistor **326** is connected to the source of the pre-stage selection transistor **327**. The current source transistor **326** supplies a current **id12** under the control of the vertical scanning circuit **211**.

(137) Note that the current source transistors **316** and **326** are examples of first and second current source transistors described in the claims.

(138) The capacitive elements **331** and **332** have their respective one ends commonly connected to the pre-stage node **330** and have their respective other ends connected to the selection circuit **350**. The capacitive elements **336** and **337** have their respective one ends commonly connected to the pre-stage node **335** and have their respective other ends connected to the selection circuit **355**.

(139) The selection circuit **350** includes the selection transistors **351** and **352**. The selection transistor **351** opens and closes a path between the capacitive element **331** and the post-stage node **360** in accordance with a selection signal Φ_{r1} from the vertical scanning circuit **211**. The selection transistor **352** opens and closes a path between the capacitive element **332** and the post-stage node **360** in accordance with a selection signal Φ_{s1} from the vertical scanning circuit **211**.

(140) The selection circuit **355** includes selection transistors **356** and **357**. The selection transistor **356** opens and closes a path between the capacitive element **336** and the post-stage node **360** in accordance with a selection signal Φ_{r2} from the vertical scanning circuit **211**. The selection transistor **357** opens and closes a path between the capacitive element **337** and the post-stage node **360** in accordance with a selection signal Φ_{s2} from the vertical scanning circuit **211**.

(141) Note that, for example, nMOS transistors are used as various transistors (transfer transistor **312** and the like) in the pixel block **300**.

(142) The circuit including the pre-stage circuit **310**, the capacitive elements **331** and **332**, the selection circuit **350**, the post-stage reset transistor **361**, and the post-stage circuit **370** described above functions as one pixel. Furthermore, the circuit including the pre-stage circuit **320**, the capacitive elements **336** and **337**, the selection circuit **355**, the post-stage reset transistor **361**, and the post-stage circuit **370** described above also functions as one pixel. The post-stage reset transistor **361** and the post-stage circuit **370** are shared by these two pixels.

(143) Furthermore, the two pixels in the pixel block **300** are arranged in the column direction, for example. In other words, these two pixels are arranged in an odd row and an even row. Note that the positional relationship between the two pixels in the pixel block **300** is not limited to such an odd row and an even row. For example, the two pixels can be arranged in an odd column and an even column. Alternatively, one of the two pixels can be arranged diagonally above the other pixel.

(144) FIG. 13 is a timing chart depicting an example of a global shutter operation in the second embodiment of the present technology. The vertical scanning circuit **211** supplies high-level FD reset signals rst1 and rst2 and high-level transfer signals trg1 and trg2 to all the rows (in other words, all the pixels) over a period from timing T0 immediately before the start of the exposure to timing T1 after the pulse period elapses. Therefore, all the pixels are PD reset, and the exposure simultaneously starts in all the rows.

(145) Here, rst1_[n], rst2_[n], trg1_[n], and trg2_[n] in the drawing indicate signals to pixels in the n-th row among the N rows. N is an integer indicating the total number of rows in which the pixel blocks **300** are arranged, and n is an integer from 1 to N. In a case where two pixels in the pixel block **300** are pixels in an even row and an odd row, the n-th row of the pixel block **300** includes two rows, an odd row and an even row.

(146) At timing T2 immediately before the end of the exposure period, the vertical scanning circuit **211** supplies the high-level FD reset signals rst1 and rst2 over the pulse period while setting the post-stage reset signal rstb and the selection signals $\Phi r1$ and $\Phi r2$ to the high level for all the rows. Therefore, all the pixels are FD reset, and the reset level is sampled and held. Here, rstb_[n], $\Phi r1$ _[n], and $\Phi r2$ _[n] in the drawing indicate signals to pixels in the n-th row.

(147) At timing T3 after timing T2, the vertical scanning circuit **211** returns the selection signals $\Phi r1$ and $\Phi r2$ to the low level.

(148) At timing T4 of the end of the exposure, the vertical scanning circuit **211** supplies the high-level transfer signals trg1 and trg2 over the pulse period while setting the post-stage reset signal rstb and the selection signals $\Phi s1$ and $\Phi s2$ to the high level for all the rows. Therefore, the signal level is sampled and held. Furthermore, $\Phi s1$ _[n] and $\Phi s2$ _[n] in the drawing indicates signals to pixels in the n-th row.

(149) At timing T5 after timing T4, the vertical scanning circuit **211** returns the selection signals $\Phi s1$ and $\Phi s2$ to the low level.

(150) FIG. 14 is a timing chart depicting an example of a read operation of the first pixel in the pixel block **300** in the second embodiment of the present technology. During the read period of the n-th row after timing T10, the vertical scanning circuit **211** sets the FD reset signals rst1 and rst2 and the post-stage selection signal selb of the n-th row to the high level. Furthermore, at timing T10, the post-stage reset signal rstb of all the rows are controlled to the low level. Here, selb_[n] in the drawing indicates signals to pixels in the n-th row.

(151) The vertical scanning circuit **211** supplies the high-level selection signal $\Phi r1$ to the n-th row over a period from timing T11 immediately after timing T10 to timing T12. The potential of the post-stage node **360** becomes a reset level Vrst1. This reset level is AD-converted by the ADC **261**.

(152) The vertical scanning circuit **211** supplies the high-level post-stage reset signal rstb to the n-th row over the pulse period from timing T13 immediately after timing T12. Therefore, in a case where a parasitic capacitance exists in the post-stage node **360**, the history of the previous signal held in the parasitic capacitance can be erased.

(153) The vertical scanning circuit **211** supplies the high-level selection signal $\Phi s1$ to the n-th row over a period from timing T14 immediately after initialization of the post-stage node **360** to timing T15. The potential of the post-stage node **360** becomes a signal level Vsig1. This signal level is AD-converted by the ADC **261**. A difference between the reset level Vrst1 and the signal level Vsig1 corresponds to the net signal level from which reset noise and offset noise of the FD have been removed.

(154) FIG. 15 is a timing chart depicting an example of a read operation of the second pixel in the pixel block **300** in the second embodiment of the present technology.

(155) The vertical scanning circuit **211** supplies the high-level post-stage reset signal rstb to the n-th row over the pulse period from timing T16 immediately after timing T15.

(156) The vertical scanning circuit **211** supplies the high-level selection signal $\Phi r2$ to the n-th row over a period from timing T17 immediately after initialization of the post-stage node **360** to timing

T18. The potential of the post-stage node **360** becomes a reset level **Vrst2**. This reset level is AD-converted by the ADC **261**.

(157) The vertical scanning circuit **211** supplies the high-level post-stage reset signal **rstb** to the *n*-th row over the pulse period from timing **T19** immediately after timing **T18**.

(158) The vertical scanning circuit **211** supplies the high-level selection signal $\Phi s2$ to the *n*-th row over a period from timing **T20** immediately after initialization of the post-stage node **360** to timing **T21**. The potential of the post-stage node **360** becomes a signal level **Vsig2**. This signal level is AD-converted by the ADC **261**.

(159) Furthermore, at timing **T21**, the vertical scanning circuit **211** returns the FD reset signals **rst1** and **rst2** and the post-stage selection signal **selb** of the *n*-th row to the low level.

(160) As illustrated in FIGS. **14** and **15**, the high-level selection signals $\Phi r1$, $\Phi s1$, $\Phi 2$, and $\Phi s2$ are sequentially supplied. In accordance with these selection signals, the selection unit **340** sequentially connects the capacitive elements **331**, **332**, **336**, and **337** to the post-stage node **360**. Then, the reset level **Vrst1** and the signal level **Vsig1** of the first pixel and the reset level **Vrst2** and the signal level **Vsig2** of the second pixel in the pixel block **300** are read sequentially.

(161) FIG. **16** is a flowchart depicting an example of the operation of the solid-state imaging element **200** in the second embodiment of the present technology. The operation is started, for example, in a case where a predetermined application for capturing image data is executed.

(162) The vertical scanning circuit **211** exposes all the pixels (step **S901**). Then, the vertical scanning circuit **211** selects a row of the pixel block **300** to be read (step **S902**). The column signal processing circuit **260** reads the reset level of the first pixel in the pixel block **300** of the row (step **S903**), and then reads the signal level of the pixel (step **S904**). Subsequently, the column signal processing circuit **260** reads the reset level of the second pixel (step **S905**), and then reads the signal level of the pixel (step **S906**).

(163) The solid-state imaging element **200** determines whether or not reading of all the rows has been completed (step **S907**). In a case where the reading of all the rows has not been completed (step **S907**: No), the solid-state imaging element **200** repeatedly executes step **S902** and subsequent steps. On the other hand, in a case where the reading of all the rows has been completed (step **S907**: Yes), the solid-state imaging element **200** performs CDS processing or the like, and ends the operation for imaging. In a case where a plurality of pieces of image data is continuously captured, steps **S901** to **S907** are repeatedly executed in synchronization with the vertical synchronization signal.

(164) As described above, according to the second embodiment of the present technology, since two pixels share the post-stage reset transistor **361** and the post-stage circuit **370**, the circuit scale of the pixel array unit **220** can be reduced as compared with a case where two pixels do not share the post-stage reset transistor **361** and the post-stage circuit **370**.

First Modification Example

(165) In the second embodiment described above, the solid-state imaging element **200** sequentially reads the pixel signal of each of the two pixels in the pixel block **300**, but with this configuration, there is a possibility that the reading speed is insufficient. The solid-state imaging element **200** of the first modification example of the second embodiment is different from that of the second embodiment in that pixel addition is performed.

(166) FIG. **17** is a timing chart depicting an example of a read operation of the reset level and the signal level in the first modification example of the second embodiment of the present technology. Any of a plurality of modes including a non-addition mode in which pixel addition is not performed and an addition mode in which pixel addition is performed is set in the solid-state imaging element **200** in the first modification example of the second embodiment. The global shutter operation and the read operation in the non-addition mode are similar to those in the second embodiment. The global shutter operation in the addition mode is similar to that in the non-addition mode.

(167) In a case where reading is performed in the addition mode, as illustrated in the drawing, the vertical scanning circuit **211** supplies the high-level FD reset signals **rst1** and **rst2** over the pulse period at timing **T10** of the start of the reading of the n-th row. Furthermore, during the read period from timing **T10** to timing **T15**, the vertical scanning circuit **211** sets the post-stage selection signal **selb** to the high level.

(168) The vertical scanning circuit **211** supplies the high-level selection signals $\Phi r1$ and $\Phi s2$ to the n-th row over a period from timing **T11** immediately after timing **T10** to timing **T12**. Therefore, the potential of the post-stage node **360** becomes a reset level **Vrst**. The reset level **Vrst** is a value obtained by adding the reset levels of the two pixels in the pixel block **300**.

(169) The vertical scanning circuit **211** supplies the high-level post-stage reset signal **rstb** to the n-th row over the pulse period from timing **T13** immediately after timing **T12**.

(170) The vertical scanning circuit **211** supplies the high-level selection signals $\Phi r2$ and $\Phi s2$ to the n-th row over a period from timing **T14** immediately after initialization of the post-stage node **360** to timing **T15**. Therefore, the potential of the post-stage node **360** becomes a signal level **Vsig**. The signal level **Vsig** is a value obtained by adding the signal levels of the two pixels in the pixel block **300**.

(171) As illustrated in the drawing, the high-level selection signals $\Phi r1$ and $\Phi s1$ are supplied, and the selection unit **340** connects the capacitive elements **331** and **336** to the post-stage node **360** in accordance with these selection signals. In other words, the capacitive element **331** and the capacitive element **336** are short-circuited. Therefore, the reset levels of the two pixels are added. Furthermore, the high-level selection signals $\Phi r2$ and $\Phi s2$ are supplied, and the selection unit **340** connects the capacitive elements **332** and **337** to the post-stage node **360** in accordance with these selection signals. In other words, the capacitive element **332** and the capacitive element **337** are short-circuited. Therefore, the signal levels of the two pixels are added. By such pixel addition, the sensitivity and the reading speed can be improved as compared with a case where addition is not performed. Furthermore, since the number of rows to be read for pixel addition is reduced, power consumption can be reduced.

(172) Note that the solid-state imaging element **200** reads the signal level after the reset level, but is not limited to this order, and can read the reset level after the signal level.

(173) As described above, according to the first modification example of the second embodiment of the present technology, since the selection unit **340** connects the capacitive elements **331** and **336** to the post-stage node **360** and connects the capacitive elements **332** and **337** to the post-stage node **360**, it is possible to add the respective pixel signals of the two pixels. Therefore, as compared with the case where the addition is not performed, the sensitivity and the reading speed can be improved and the power consumption can be reduced.

Second Modification Example

(174) In the second embodiment described above, the circuits in the solid-state imaging element **200** are provided in a single semiconductor chip, but with this configuration, there is a possibility that the element does not fit in the semiconductor chip in a case where the pixel is miniaturized. The solid-state imaging element **200** of the second modification example of the second embodiment is different from that of the second embodiment in that the circuits in the solid-state imaging element **200** are dispersedly arranged in two semiconductor chips.

(175) FIG. **18** is a diagram depicting an example of a laminated structure of the solid-state imaging element **200** in the second modification example of the second embodiment of the present technology. The solid-state imaging element **200** of the second modification example of the second embodiment includes a circuit chip **202** and a pixel chip **201** stacked on the circuit chip **202**. These chips are electrically connected by, for example, Cu—Cu bonding. Note that, in addition to the Cu—Cu bonding, connection can be made by a via or a bump.

(176) An upper pixel array unit **221** is arranged in the pixel chip **201**. A lower pixel array unit **222** and the column signal processing circuit **260** are arranged in the circuit chip **202**. For each pixel in

the pixel array unit **220**, a part of the pixel is arranged in the upper pixel array unit **221**, and the rest is arranged in the lower pixel array unit **222**.

(177) Furthermore, in the circuit chip **202**, the vertical scanning circuit **211**, the timing control circuit **212**, the DAC **213**, and the load MOS circuit block **250** are also arranged. These circuits are omitted in the drawing.

(178) Furthermore, the pixel chip **201** is manufactured, for example, by a pixel-dedicated process, and the circuit chip **202** is manufactured, for example, by a complementary MOS (CMOS) process. Note that the pixel chip **201** is an example of a first chip described in the claims, and the circuit chip **202** is an example of a second chip described in the claims.

(179) FIG. **19** is a circuit diagram depicting a configuration example of the pixel block **300** in the second modification example of the second embodiment of the present technology. In the pixel block **300**, the pre-stage circuit block **305** is arranged in the pixel chip **201**, and other circuits and elements (such as the capacitive elements **331** and **332**) are arranged in the circuit chip **202**. Note that the current source transistors **316** and **326** can be further arranged in the circuit chip **202**. As illustrated in the drawing, by dispersedly arranging the elements in the pixel block **300** in the stacked pixel chip **201** and circuit chip **202**, the pixel area can be reduced, and pixel miniaturization is facilitated.

(180) As described above, according to the second modification example of the second embodiment of the present technology, since the circuits and elements in the pixel block **300** are dispersedly arranged in the two semiconductor chips, pixel miniaturization is facilitated.

Third Modification Example

(181) In the second modification example of the second embodiment described above, a part of the pixel block **300** and the peripheral circuit (such as the column signal processing circuit **260**) are provided in the circuit chip **202** on the lower side. However, with this configuration, the arrangement area of the circuits and elements on the circuit chip **202** side is larger than that of the pixel chip **201** by the peripheral circuit, and there is a possibility that an unnecessary space without circuits and elements is generated in the pixel chip **201**. The solid-state imaging element **200** of the third modification example of the second embodiment is different from that of the second modification example of the second embodiment in that the circuits in the solid-state imaging element **200** are dispersedly arranged in three semiconductor chips.

(182) FIG. **20** is a diagram depicting an example of a laminated structure of the solid-state imaging element **200** in the third modification example of the second embodiment of the present technology. The solid-state imaging element **200** of the third modification example of the second embodiment includes an upper pixel chip **203**, a lower pixel chip **204**, and the circuit chip **202**. These chips are stacked, and are electrically connected by, for example, Cu—Cu bonding. Note that, in addition to the Cu—Cu bonding, connection can be made by a via or a bump.

(183) The upper pixel array unit **221** is arranged in the upper pixel chip **203**. The lower pixel array unit **222** is arranged in the lower pixel chip **204**. For each pixel in the pixel array unit **220**, a part of the pixel is arranged in the upper pixel array unit **221**, and the rest is arranged in the lower pixel array unit **222**.

(184) Furthermore, in the circuit chip **202**, the column signal processing circuit **260**, the vertical scanning circuit **211**, the timing control circuit **212**, the DAC **213**, and the load MOS circuit block **250** are arranged. Circuits other than the column signal processing circuit **260** are omitted in the drawing.

(185) By adopting the three-layer configuration as illustrated in the drawing, it is possible to reduce unnecessary space and further miniaturize the pixel as compared with the two-layer configuration. Furthermore, the lower pixel chip **204** that is a second layer can be manufactured by a dedicated process for the capacitor and switch.

(186) As described above, in the third modification example of the second embodiment of the present technology, since the circuits in the solid-state imaging element **200** are dispersedly

arranged in the three semiconductor chips, the pixel can be further miniaturized as compared with a case where the circuits are dispersedly arranged in the two semiconductor chips.

3. Third Embodiment

(187) In the second embodiment described above, the solid-state imaging element **200** sequentially reads the pixel signal of each of the two pixels in the pixel block **300**, but with this configuration, there is a possibility that the reading speed is insufficient. The solid-state imaging element **200** of the third embodiment is different from that of the second embodiment in that pixel addition is performed.

(188) FIG. **21** is a plan view depicting a configuration example of the pixel array unit **220** in the third embodiment of the present technology. In the drawing, a is a plan view depicting an example of the pixel array unit **220** in the Bayer array. In the drawing, b is a plan view depicting an example of the pixel array unit **220** in the Quad Bayer array.

(189) As illustrated in a of the drawing, in the pixel array unit **220** of the second embodiment, red (R), green (G), and blue (B) pixels are arranged in the Bayer array. Among these pixels, the solid-state imaging element **200** can add the respective pixel signals of the R pixel **301**, and neighboring R pixels **302** to **304**. Similarly, for the G pixel and the B pixel, the solid-state imaging element **200** can add the pixel signals of the four neighboring pixels.

(190) Note that, instead of the Bayer array, the pixels can be arranged in the Quad Bayer array as illustrated in b of the drawing. In the Quad Bayer array, four pixels of the same color are arranged adjacent to each other in 2 rows×2 columns. Then, focusing on the four R pixels, the four B pixels are arranged at the lower right of the four R pixels, and the four G pixels are arranged at the right side and at the lower side. Among these pixels, the solid-state imaging element **200** can add the pixel signals of adjacent four pixels (pixels **301** to **304** and the like) of the same color.

(191) Note that the arrangement of the pixels is not limited to the Bayer array or the Quad Bayer array. For example, R, G, B, and W (white) pixels can be arranged.

(192) FIG. **22** is a circuit diagram depicting a configuration example of the pixel block **300** in the third embodiment of the present technology. In the pixel block **300** of the third embodiment, four pixels to be added in a case where pixel addition is performed are arranged. For example, the pixels **301** to **304** in FIG. **21** are arranged in the pixel block **300**.

(193) The pixel block **300** of the third embodiment is further provided with capacitive elements **431**, **432**, **436**, and **437**, a short-circuit transistor **480**, a post-stage reset transistor **461**, and a post-stage circuit **470**. Furthermore, in the third embodiment, pre-stage circuits **410** and **420** are further arranged in the pre-stage circuit block **305**, and selection circuits **450** and **455** are further arranged in the selection unit **340**. The vertical scanning circuit **211** supplies a post-stage reset signal rstb1 to the post-stage reset transistor **361**, and supplies a post-stage reset signal rstb2 to the post-stage reset transistor **461**.

(194) A post-stage amplification transistor **471** and a post-stage selection transistor **472** are arranged in the post-stage circuit **470**. As these transistors, for example, nMOS transistors are used. Furthermore, the circuit configurations of the post-stage reset transistor **461** and the post-stage circuit **470** are similar to those of the post-stage reset transistor **361** and the post-stage circuit **370**. The post-stage circuits **370** and **470** are connected to the same vertical signal line **309**. The vertical scanning circuit **211** supplies a post-stage selection signal selb1 to the post-stage selection transistor **372**, and supplies a post-stage selection signal selb2 to the post-stage selection transistor **472**.

(195) The pre-stage circuit **410** sequentially generates the reset level and the signal level, and causes the capacitive elements **431** and **432** to hold the reset level and the signal level. The pre-stage circuit **420** sequentially generates the reset level and the signal level, and causes the capacitive elements **436** and **437** to hold the reset level and the signal level. Note that the capacitive elements **431** and **432** are examples of fifth and sixth capacitive elements described in the claims, and the capacitive elements **436** and **437** are examples of seventh and eighth capacitive elements

described in the claims.

(196) Furthermore, the selection circuit **450** connects one of the capacitive elements **431** and **432** to a post-stage node **460**, and the selection circuit **455** connects one of the capacitive elements **436** and **437** to the post-stage node **460**. Note that the selection circuit **450** is an example of a third selection circuit described in the claims, and the selection circuit **455** is an example of a fourth selection circuit described in the claims. Furthermore, the post-stage node **360** is an example of a first post-stage node described in the claims, and the post-stage node **460** is an example of a second post-stage node described in the claims.

(197) The short-circuit transistor **480** opens and closes a path between the post-stage node **360** and the post-stage node **460** in accordance with a short-circuit signal *sht* from the vertical scanning circuit **211**. As the short-circuit transistor **480**, for example, an nMOS transistor is used.

(198) FIG. **23** is a circuit diagram depicting a configuration example of the pre-stage circuits **410** and **420** and the selection circuits **450** and **455** in the third embodiment of the present technology.

(199) The pre-stage circuit **410** includes a photoelectric conversion element **411**, a transfer transistor **412**, an FD reset transistor **413**, an FD **414**, a pre-stage amplification transistor **415**, a current source transistor **416**, and a pre-stage selection transistor **417**. The vertical scanning circuit **211** supplies a transfer signal *trg3* and an FD reset signal *rst3* to the transfer transistor **412** and the FD reset transistor **413**.

(200) Furthermore, the pre-stage circuit **420** includes a photoelectric conversion element **421**, a transfer transistor **422**, an FD reset transistor **423**, an FD **424**, a pre-stage amplification transistor **425**, a current source transistor **426**, and a pre-stage selection transistor **427**. The vertical scanning circuit **211** supplies a transfer signal *trg4* and an FD reset signal *rst4* to the transfer transistor **422** and the FD reset transistor **423**. The pre-stage selection signal *sela* is supplied to the pre-stage selection transistors **417** and **427**.

(201) The selection circuit **450** includes selection transistors **451** and **452**, and the selection circuit **455** includes selection transistors **456** and **457**. The vertical scanning circuit **211** supplies selection signals $\Phi r3$ and $\Phi s3$ to the selection transistors **451** and **452**, and supplies selection signals $\Phi r4$ and $\Phi s4$ to the selection transistors **456** and **457**.

(202) The circuit configurations of the pre-stage circuits **410** and **420** are similar to those of the pre-stage circuits **310** and **320**. Furthermore, the circuit configurations of the selection circuits **450** and **455** are similar to those of the selection circuits **350** and **355**.

(203) FIG. **24** is a timing chart depicting an example of a read operation of first and second pixels in the pixel block **300** in the third embodiment of the present technology. Any of a plurality of modes including the non-addition mode in which pixel addition is not performed and the addition mode in which pixel addition is performed is set in the solid-state imaging element **200** in the third embodiment. The global shutter operation and the read operation in the non-addition mode are similar to those in the second embodiment. The global shutter operation in the addition mode is similar to that in the non-addition mode.

(204) In the non-addition mode, the vertical scanning circuit **211** sets the short-circuit signal *sht* to the low level. Furthermore, at timing **T10** of the start of the reading of the *n*-th row of the pixel block **300**, the vertical scanning circuit **211** sets the FD reset signals *rst1* to *rst4* to the high level. Furthermore, during the period from timing **T10** to timing **T18**, the vertical scanning circuit **211** sets the post-stage selection signal *selb1* to the high level, and sets the post-stage selection signal *selb2* to the low level.

(205) Furthermore, the vertical scanning circuit **211** supplies the high-level post-stage reset signal *rstb1* during the pulse period from timing **T10** to timing **T11**, and supplies the high-level selection signal $\Phi r1$ during a period from timing **T11** to timing **T12**. During this period, the reset level *Vrst1* of the first pixel is read through the vertical signal line **309**.

(206) The vertical scanning circuit **211** supplies the high-level post-stage reset signal *rstb1* during the pulse period from timing **T12** to timing **T13**, and supplies the high-level selection signal $\Phi s1$

during a period from timing T13 to timing T14. During this period, the signal level Vsig1 of the first pixel is read through the vertical signal line 309.

(207) Subsequently, the vertical scanning circuit 211 supplies the high-level post-stage reset signal rstb1 during the pulse period from timing T14 to timing T15, and supplies the high-level selection signal $\Phi r2$ during a period from timing T15 to timing T16. During this period, the reset level Vrst2 of the second pixel is read through the vertical signal line 309.

(208) The vertical scanning circuit 211 supplies the high-level post-stage reset signal rstb1 during the pulse period from timing T16 to timing T17, and supplies the high-level selection signal $\Phi s2$ during the period from timing T17 to timing T18. During this period, the signal level Vsig2 of the second pixel is read through the vertical signal line 309.

(209) FIG. 25 is a timing chart depicting an example of a read operation of third and fourth pixels in the pixel block 300 in the third embodiment of the present technology.

(210) During a period from timing T18 to timing T26, the vertical scanning circuit 211 sets the post-stage selection signal selb1 to the low level, and sets the post-stage selection signal selb2 to the high level.

(211) Furthermore, the vertical scanning circuit 211 supplies the high-level post-stage reset signal rstb2 during the pulse period from timing T18 to timing T19, and supplies the high-level selection signal $\Phi r3$ during a period from timing T19 to timing T20. During this period, the reset level Vrst3 of the third pixel is read through the vertical signal line 309.

(212) The vertical scanning circuit 211 supplies the high-level post-stage reset signal rstb2 during the pulse period from timing T20 to timing T21, and supplies the high-level selection signal $\Phi s3$ during a period from timing T21 to timing T22. During this period, the signal level Vsig3 of the third pixel is read through the vertical signal line 309.

(213) Subsequently, the vertical scanning circuit 211 supplies the high-level post-stage reset signal rstb2 during the pulse period from timing T22 to timing T23, and supplies the high-level selection signal $\Phi r4$ during a period from timing T23 to timing T24. During this period, the reset level Vrst4 of the fourth pixel is read through the vertical signal line 309.

(214) The vertical scanning circuit 211 supplies the high-level post-stage reset signal rstb2 during the pulse period from timing T24 to timing T25, and supplies the high-level selection signal $\Phi s4$ during the period from timing T25 to timing T26. During this period, the signal level Vsig4 of the fourth pixel is read through the vertical signal line 309.

(215) Furthermore, at timing T26 of the end of the reading of the n-th row, the vertical scanning circuit 211 sets the FD reset signals rst1 to rst4 to the low level.

(216) As illustrated in FIGS. 24 and 25, in the non-addition mode, the short-circuit transistor 480 is controlled to the open state. Furthermore, the capacitive elements 331 and 332 are sequentially connected to the post-stage node 360, and the reset level and the signal level of the first pixel are sequentially read. The capacitive elements 336 and 337 are sequentially connected to the post-stage node 360, and the reset level and the signal level of the second pixel are sequentially read.

Subsequently, the capacitive elements 431 and 432 are sequentially connected to the post-stage node 460, and the reset level and the signal level of the third pixel are sequentially read. The capacitive elements 436 and 437 are sequentially connected to the post-stage node 460, and the reset level and the signal level of the fourth pixel are sequentially read. In this manner, the reset level and the signal level of each of the four pixels in the pixel block 300 are sequentially read.

(217) FIG. 26 is a timing chart depicting an example of a read operation in the addition mode in the third embodiment of the present technology. In the addition mode, the vertical scanning circuit 211 sets the short-circuit signal sht to the high level. From timing T10 to timing T14 as the read period of the n-th row of the pixel block 300, the vertical scanning circuit 211 sets the FD reset signals rst1 to rst4 and the post-stage selection signals selb1 and selb2 to the high level.

(218) Furthermore, the vertical scanning circuit 211 supplies the high-level post-stage reset signals rstb1 and rstb2 during the pulse period from timing T10 to timing T11, and supplies the high-level

selection signals $\Phi r1$ to $\Phi r4$ during a period from timing T11 to timing T12. During this period, the reset level Vrst is read through the vertical signal line 309. The reset level Vrst is a value obtained by adding the reset levels of the four pixels in the pixel block 300.

(219) Subsequently, the vertical scanning circuit 211 supplies the high-level post-stage reset signals rstb1 and rstb2 during the pulse period from timing T12 to timing T13, and supplies the high-level selection signals $\Phi s1$ to $\Phi s4$ during a period from timing T13 to timing T14. During this period, the signal level Vsig is read through the vertical signal line 309. The signal level Vsig is a value obtained by adding the signal levels of the four pixels in the pixel block 300.

(220) Here, in the pixel block 300 of the second embodiment, four pixels can be added by increasing the number of pixels sharing the post-stage circuit 370 to four. However, an increase in the number of pixels sharing the post-stage circuit 370 causes adverse effects. In a case where the number of pixels sharing the post-stage circuit 370 is four, the wiring of the post-stage node 360 extends over four pixels, and the parasitic capacitance of the post-stage node 360 increases accordingly. Due to the increase in the parasitic capacitance, the gain of the signal in a case where pixel addition is not performed decreases. This is because the voltage held in the capacitive element 331 or 332 is reduced by the parasitic capacitance in a case where the capacitive element 331 or 332 is connected to the post-stage node 360. This decrease in gain causes a decrease in signal-noise (SN) ratio.

(221) On the other hand, in the third embodiment in which the short-circuit transistor 480 is provided, by setting the short-circuit transistor 480 in the open state in the non-addition mode, the number of pixels sharing each of the post-stage circuits 370 and 470 can be two. Therefore, it is possible to suppress an increase in the parasitic capacitance of the post-stage node as compared with a case where four pixels share the post-stage circuit 370. With such a configuration, it is possible to suppress a decrease in the SN ratio in the non-addition mode while realizing addition of more than two pixels.

(222) Note that, in the pixel block 300 illustrated in FIG. 22, one vertical signal line 309 is shared by the post-stage circuits 370 and 470, but the present technology is not limited to this configuration. Vertical signal lines 309-1 and 309-2 can be wired, the post-stage circuit 370 can be connected to the vertical signal line 309-1, and the post-stage circuit 470 can be connected to the vertical signal line 309-2. In this case, it is necessary to double not only the number of vertical signal lines, but also the number of load MOS transistors 251 and the number of ADCs 261 in the post stage. Instead, in the non-addition mode, one of two pixels sharing the post-stage circuit 370 and one of two pixels sharing the post-stage circuit 470 can be simultaneously read, and therefore, the reading speed can be improved. Furthermore, in the addition mode, only one of the vertical signal lines 309-1 and 309-2 is used, and the load MOS transistor 251 corresponding to the other of the vertical signal lines 309-1 and 309-2 is controlled to the off state.

(223) Note that the second and third modification examples of the second embodiment can also be applied to the third embodiment.

(224) As described above, according to the third embodiment of the present technology, since the short-circuit transistor 480 short-circuits the post-stage node 360 and the post-stage node 460, the pixel block 300 can add the respective pixel signals of the four pixels. Therefore, as compared with the case where the addition is not performed, the sensitivity and the reading speed can be improved and the power consumption can be reduced.

4. Fourth Embodiment

(225) In the first embodiment described above, the current source transistor (316 or 326) is arranged for each pixel, but with this configuration, there is a possibility that pixel miniaturization becomes difficult. The solid-state imaging element 200 of the fourth embodiment is different from that of the first embodiment in that the current source transistor is shared by a plurality of pixels.

(226) FIG. 27 is a circuit diagram depicting a configuration example of the pixel block 300 in the fourth embodiment of the present technology. The pixel block 300 of the fourth embodiment is

different from that of the second embodiment in that the current source transistor **316** is not provided.

(227) The pre-stage selection transistor **317** outputs a voltage amplified by the pre-stage amplification transistor **315** to a pre-stage node **338** in accordance with a pre-stage selection signal **sela1** from the vertical scanning circuit **211**. The pre-stage selection transistor **327** outputs a voltage amplified by the pre-stage amplification transistor **325** to the pre-stage node **338** in accordance with a pre-stage selection signal **sela2** from the vertical scanning circuit **211**. Furthermore, the current source transistor **326** is connected to the pre-stage node **338**.

(228) Furthermore, the capacitive elements **331**, **332**, **336**, and **337** have their respective one ends commonly connected to a pre-stage node **339**, and have their respective other ends connected to the selection circuits **350** and **355**. The pre-stage node **339** is connected to the pre-stage node **338**.

(229) Furthermore, circuits and elements in the solid-state imaging element **200** are dispersedly arranged in the upper pixel chip **203** and the lower pixel chip **204**. For example, the pre-stage circuits **310** and **320** are arranged in the upper pixel chip **203**, and circuits in the post stages thereof are arranged in the circuit chip **204**. Then, the pre-stage node **338** and the pre-stage node **339** are connected by Cu—Cu connection or the like.

(230) In the second embodiment in which the current source transistor is arranged for each pixel, it is necessary to perform Cu—Cu connection for each pixel as illustrated in FIG. **19** in a case of using a laminated structure. In particular, in a case where the capacitive element **331** having the MIM structure or the like is arranged in the circuit chip **202**, the thickness of the chip increases, it becomes difficult to planarize the surfaces connecting the upper and lower chips, and the pitch of the Cu—Cu connection is restricted. For example, while the size of the fine pixel of the image sensor for mobile use is micrometers (μm) or less, the pitch of the Cu—Cu connection is several micrometers (μm). Therefore, in the configuration in which the current source transistor is arranged for each pixel, miniaturization is difficult.

(231) On the other hand, in the configuration in FIG. **27** in which the current source transistor **326** is shared by two pixels, the number of Cu—Cu connections can be reduced. Therefore, pixel miniaturization is facilitated. Furthermore, the current in a case of the global shutter operation can be reduced. Furthermore, the current source transistor **326** generally has a cascade configuration in order to suppress current fluctuations due to the transistor channel-length modulation effect. By sharing the current source transistor **326** having a relatively large size, the transistor area can be reduced.

(232) Note that, although the current source transistor **326** is shared by two pixels, the number of pixels sharing the current source transistor **326** is not limited to two, and may be three or more.

(233) FIG. **28** is a timing chart depicting an example of a global shutter operation in the fourth embodiment of the present technology. The vertical scanning circuit **211** supplies the high-level FD reset signals **rst1** and **rst2** and the high-level transfer signals **trg1** and **trg2** to all the rows from timing **T0** immediately before the start of the exposure to timing **T1** after the pulse period elapses. Therefore, all the pixels are PD reset, and the exposure simultaneously starts in all the rows.

(234) During a period from timing **T2** immediately before the end of the exposure to timing **T5**, the vertical scanning circuit **211** sets the pre-stage selection signal **sela1** of all the rows to the high level. At timing **T3** in the period, the vertical scanning circuit **211** supplies the high-level FD reset signal **rst1** over the pulse period while setting the post-stage reset signal **rstb** and the selection signal Φr1 to the high level for all the rows. Therefore, the first pixel in the pixel block **300** is FD reset, and the reset level is sampled and held.

(235) At timing **T4**, the vertical scanning circuit **211** returns the selection signal Φr1 to the low level. Furthermore, during a period from timing **T5** to timing **T8**, the vertical scanning circuit **211** sets the pre-stage selection signal **sela1** of all the rows to the low level, and sets the pre-stage selection signal **sela2** to the high level. At timing **T6** in the period, the vertical scanning circuit **211** supplies the high-level FD reset signal **rst2** over the pulse period while setting the post-stage reset

signal rstb and the selection signal $\Phi r2$ to the high level for all the rows. Therefore, the second pixel in the pixel block **300** is FD reset, and the reset level is sampled and held.

(236) Then, the vertical scanning circuit **211** returns the selection signal $\Phi r2$ of all the rows to the low level at timing T7, and sets the pre-stage selection signal sela2 to the low level and sets the pre-stage selection signal sela1 to the high level at timing T8.

(237) Here, sela1_[n] and sela2_[n] in the drawing indicates signals to pixels in the n-th row.

(238) As illustrated in the drawing, the vertical scanning circuit **211** sequentially closes the pre-stage selection transistors **317** and **327** immediately before the end of the exposure. Then, in a case where the pre-stage selection transistor **317** is in the closed state, the FD reset transistor **313** performs the FD reset, and in a case where the pre-stage selection transistor **327** is in the closed state, the FD reset transistor **323** performs the FD reset.

(239) FIG. **29** is a timing chart depicting an example of control immediately after the end of the exposure in the fourth embodiment of the present technology. At timing T9 of the end of the exposure, the vertical scanning circuit **211** supplies the high-level transfer signals trg1 and trg2 over the pulse period for all the rows.

(240) Then, the vertical scanning circuit **211** sets the selection signal $\Phi s1$ to the high level for all the rows during a period from timing T10 to timing T11. Therefore, the signal level of the first pixel in the pixel block **300** is sampled and held.

(241) At timing T12, the vertical scanning circuit **211** sets the pre-stage selection signal sela1 of all the rows to the low level, and sets the pre-stage selection signal sela2 to the high level.

(242) Then, the vertical scanning circuit **211** sets the selection signal $\Phi s2$ to the high level for all the rows during a period from timing T13 to timing T14. Therefore, the signal level of the second pixel in the pixel block **300** is sampled and held.

(243) The vertical scanning circuit **211** lowers the pre-stage selection signal sela2 of all the rows to the middle level Vm at timing T15.

(244) As illustrated in the drawing, the vertical scanning circuit **211** sequentially closes the pre-stage selection transistors **317** and **327** at the end of the exposure. Then, the vertical scanning circuit **211** causes the transfer transistors **312** and **322** to transfer charges at the end of the exposure, and then sequentially closes the pre-stage selection transistors **317** and **327**.

(245) Note that the first and third modification examples of the second embodiment, and the third embodiment can be applied to the fourth embodiment.

(246) As described above, according to the fourth embodiment of the present technology, since the current source transistor **326** is shared by two pixels, the number of Cu—Cu connections between chips can be reduced. Therefore, pixel miniaturization is facilitated.

5. Fifth Embodiment

(247) In the first embodiment described above, a pair of capacitors is arranged for each pixel, but with this configuration, pixel miniaturization is difficult. The solid-state imaging element **200** of the fifth embodiment is different from that of the first embodiment in that the number of capacitors is reduced.

(248) FIG. **30** is a circuit diagram depicting a configuration example of the pixel block **300** in the fifth embodiment of the present technology. In the pixel block **300** of the fifth embodiment, the pre-stage circuit block **305**, capacitive elements **331**, **332**, **531**, **532**, and **533**, the selection unit **340**, the post-stage reset transistor **361**, and the post-stage circuit **370** are arranged. In the pixel block **300** of the fifth embodiment, four pixels are arranged. For example, the pixels **301** to **304** in FIG. **21** are arranged in the pixel block **300**.

(249) The pre-stage circuit block **305** includes the photoelectric conversion element **311**, photoelectric conversion elements **511**, **512**, and **513**, the transfer transistor **312**, and transfer transistors **514**, **515**, and **516**. The pre-stage circuit block **305** further includes the FD reset transistor **313**, the FD **314**, the pre-stage amplification transistor **315**, the current source transistor **316**, and the pre-stage selection transistor **317**. As the transfer transistors **312**, **514**, **515**, and **516**,

for example, nMOS transistors are used.

(250) Furthermore, the selection unit **340** includes selection transistors **351**, **352**, **551**, **552**, and **553**. As the selection transistors **551**, **552**, and **553**, for example, nMOS transistors are used.

(251) The connection configuration of the photoelectric conversion element **311**, the transfer transistor **312**, the FD reset transistor **313**, the FD **314**, the pre-stage amplification transistor **315**, the current source transistor **316**, and the pre-stage selection transistor **317** of the fourth embodiment is similar to that of the first embodiment. However, the FD reset signal rst is input from the vertical scanning circuit **211** to the FD reset transistor **313**.

(252) The photoelectric conversion elements **511** to **513** generate charges by photoelectric conversion. The transfer transistor **514** transfers the charges from the photoelectric conversion element **511** to the FD **314** in accordance with the transfer signal trg2 from the vertical scanning circuit **211**. The transfer transistor **515** transfers the charges from the photoelectric conversion element **512** to the FD **314** in accordance with the transfer signal trg3 from the vertical scanning circuit **211**. The transfer transistor **516** transfers the charges from the photoelectric conversion element **513** to the FD **314** in accordance with the transfer signal trg4 from the vertical scanning circuit **211**.

(253) The connection configuration of the capacitive elements **331** and **332**, and the selection transistors **351** and **352** of the fourth embodiment is similar to that of the first embodiment. However, the selection signal Φ_r is input from the vertical scanning circuit **211** to the selection transistor **351**.

(254) The capacitive elements **531**, **532**, and **533** have their respective one ends commonly connected to the pre-stage node **330**, and have their respective other ends connected to the selection unit **340**.

(255) The selection transistor **551** opens and closes a path between the capacitive element **531** and the post-stage node **360** in accordance with the selection signal Φ_r2 from the vertical scanning circuit **211**. The selection transistor **552** opens and closes a path between the capacitive element **532** and the post-stage node **360** in accordance with the selection signal Φ_r3 from the vertical scanning circuit **211**. The selection transistor **553** opens and closes a path between the capacitive element **533** and the post-stage node **360** in accordance with the selection signal Φ_r4 from the vertical scanning circuit **211**.

(256) The circuit configuration of the post-stage reset transistor **361** and the post-stage circuit **370** of the fifth embodiment is similar to that of the first embodiment.

(257) Furthermore, circuits and elements in the solid-state imaging element **200** are dispersedly arranged in the pixel chip **201** and the circuit chip **202**. For example, the pre-stage circuit block **305** is arranged in the pixel chip **201**, and circuits in the post stages thereof are arranged in the circuit chip **202**.

(258) As illustrated in FIG. **30**, the one FD **314**, the post-stage reset transistor **361**, and the post-stage circuit **370** are shared by the four pixels. Furthermore, the reset level of the four pixels is held in the capacitive element **331**, and the signal level of each of the four pixels is held in a corresponding one of the capacitive elements **332**, **531**, **532**, and **533**. In the first embodiment, it is necessary to arrange the capacitor for holding the reset level for each pixel, but in the fourth embodiment, since the capacitor is shared by the four pixels, the number of capacitors can be reduced. Therefore, as compared with a case where the capacitor is not shared, pixel miniaturization is facilitated.

(259) Note that the FD **314** and the like are shared by the four pixels, but the number of sharing pixels is not limited to four. Furthermore, the capacitive elements **331** and **332** are examples of first and second capacitive elements described in the claims. The capacitive elements **531**, **532**, and **533** are examples of a third capacitive element described in the claims.

(260) FIG. **31** is a timing chart depicting an example of a global shutter operation in the fourth embodiment of the present technology. The vertical scanning circuit **211** supplies the high-level FD

reset signal rst to all the rows during a period from timing T0 at the start of the exposure to timing T4. At timing T0, timing T1, timing T2, and timing T3 in this period, the vertical scanning circuit 211 supplies the transfer signals trg1, trg2, trg3, and trg4 to all the rows over the pulse period. Therefore, all the pixels are PD reset.

(261) Then, the vertical scanning circuit 211 supplies the high-level post-stage reset signal rstb to all the rows during a period from timing T5 at the end of the exposure to timing T15. Furthermore, at timing T5, the vertical scanning circuit 211 supplies the FD reset signal rst to all the rows over the pulse period. At timing T6 immediately after timing T5, the vertical scanning circuit 211 supplies the selection signal Φ_r to all the rows over the pulse period. Therefore, all the pixels are FD reset.

(262) Furthermore, at timing T7, the vertical scanning circuit 211 supplies the transfer signal trg1 to all the rows over the pulse period. At timing T8 immediately after timing T7, the vertical scanning circuit 211 supplies the selection signal Φ_{s1} to all the rows over the pulse period. Therefore, the signal level of the first pixel in the pixel block 300 is sampled and held. Furthermore, at timing T9, the vertical scanning circuit 211 supplies the transfer signal trg2 to all the rows over the pulse period. At timing T10 immediately after timing T9, the vertical scanning circuit 211 supplies the selection signal Φ_{s2} to all the rows over the pulse period. Therefore, the sum of the signal levels of the first and second pixels in the pixel block 300 is sampled and held.

(263) Furthermore, at timing T11, the vertical scanning circuit 211 supplies the transfer signal trg3 to all the rows over the pulse period. At timing T12 immediately after timing T11, the vertical scanning circuit 211 supplies the selection signal Φ_{s3} to all the rows over the pulse period. Therefore, the sum of the signal levels of the first to third pixels in the pixel block 300 is sampled and held.

(264) Furthermore, at timing T13, the vertical scanning circuit 211 supplies the transfer signal trg4 to all the rows over the pulse period. At timing T14 immediately after timing T13, the vertical scanning circuit 211 supplies the selection signal Φ_{s4} to all the rows over the pulse period. Therefore, the sum of the signal levels of the first to fourth pixels in the pixel block 300 is sampled and held.

(265) Here, rst[n] and r[n] indicate signals to pixels in the n-th row among the N rows.

(266) In the fifth embodiment, since the FD 314 is shared by the four pixels, the charge transfer of each of the four pixels cannot be simultaneously performed as illustrated in the drawing. However, since the sampling of the four capacitors (capacitive elements 332, 531, 532 and 533) each serving as a charge transfer destination can be realized on the order of several microseconds (μs), a difference in exposure time between the pixels does not become too large.

(267) FIG. 32 is a timing chart depicting an example of a read operation of the reset level and the signal level in the fifth embodiment of the present technology.

(268) During a period from timing T20 to timing T26 during which the n-th row is read, the vertical scanning circuit 211 sets the FD reset signal rst to the high level.

(269) Furthermore, at timing T20, the vertical scanning circuit 211 supplies the high-level post-stage reset signal rstb to the n-th row over the pulse period. Then, at timing T21 immediately after timing T20, the vertical scanning circuit 211 supplies the high-level selection signal Φ_r to the n-th row over the pulse period. Immediately after this control, the reset level commonly used for the four pixels is read through the vertical signal line 309.

(270) Then, at timing T22 after the reset level is read, the vertical scanning circuit 211 supplies the high-level selection signal Φ_{s1} to the n-th row over the pulse period. Immediately after this control, the signal level Vsig1 of the first pixel is read through the vertical signal line 309. The column signal processing circuit 260 obtains a difference between the reset level Vrst and the signal level Vsig1 as a net signal level of the first pixel by the CDS processing.

(271) Then, at timing T23 after the signal level Vsig1 is read, the vertical scanning circuit 211 supplies the high-level selection signal Φ_{s2} to the n-th row over the pulse period. Immediately after

this control, Vsig2 is read through the vertical signal line 309. This Vsig2 corresponds to the sum of the signal levels of the first and second pixels. The column signal processing circuit 260 obtains a difference between Vsig1 and Vsig2 as a signal level of the second pixel after the CDS processing.

(272) Then, at timing T24 after Vsig2 is read, the vertical scanning circuit 211 supplies the high-level selection signal $\Phi s3$ to the n-th row over the pulse period. Immediately after this control, Vsig3 is read through the vertical signal line 309. This Vsig3 corresponds to the sum of the signal levels of the first to third pixels. The column signal processing circuit 260 obtains a difference between Vsig2 and Vsig3 as a signal level of the third pixel after the CDS processing.

(273) Then, at timing T25 after Vsig3 is read, the vertical scanning circuit 211 supplies the high-level selection signal $\Phi s4$ to the n-th row over the pulse period. Immediately after this control, Vsig 4 is read through the vertical signal line 309. This Vsig4 corresponds to the sum of the signal levels of the first to fourth pixels. The column signal processing circuit 260 obtains a difference between Vsig 3 and Vsig 4 as a signal level of the fourth pixel after the CDS processing.

(274) Note that the third modification example of the second embodiment can also be applied to the fifth embodiment.

(275) As described above, in the fifth embodiment of the present technology, since the capacitive element 331 that holds the reset level is shared by the four pixels, pixel miniaturization is facilitated as compared with a case where the capacitive element is not shared.

6. Sixth Embodiment

(276) In the first embodiment described above, the potentials of the high-impedance nodes 353 and 354 are lowered by means of the control of the pre-stage selection transistor 317, but the potentials of these nodes can also be lowered by means of control of a voltage of a reference signal line. The solid-state imaging element 200 of the sixth embodiment is different from that of the first embodiment in that the voltage of the reference signal line is controlled.

(277) FIG. 33 is a circuit diagram depicting a configuration example of the pixel 301 in the sixth embodiment of the present technology. The pixel 301 of the sixth embodiment is different from that of the first embodiment in that neither the pre-stage selection transistor 317 nor the post-stage reset transistor 361 is arranged, and a post-stage circuit 380 is further arranged.

(278) A connection node between the pre-stage amplification transistor 315 and the current source transistor 316 is the pre-stage node 330. The selection transistor 351 opens and closes a path between the pre-stage node 330 and one end of the capacitive element 331, and the selection transistor 352 opens and closes a path between the pre-stage node 330 and one end of the capacitive element 332. Furthermore, the capacitive elements 331 and 332 have their respective other ends commonly connected to a reference signal line 307. The reference signal line 307 is wired in the horizontal direction for each row. The vertical scanning circuit 211 can control a reference voltage Vref that is a voltage of the reference signal line 307 for each row.

(279) Furthermore, the post-stage circuit 370 further includes a load MOS transistor 373 connected to the post-stage selection transistor 372. The post-stage amplification transistor 371 has a gate connected to the node 353 between the selection transistor 351 and the capacitive element 331. The post-stage selection transistor 372 supplies a potential vsl to the column signal processing circuit 260 through a vertical signal line 308.

(280) Furthermore, the post-stage circuit 380 includes a post-stage amplification transistor 381, a post-stage selection transistor 382, and a load MOS transistor 383. The configuration of the post-stage circuit 380 is similar to that of the post-stage circuit 370. The post-stage amplification transistor 381, however, has a gate connected to the node 354 between the selection transistor 352 and the capacitive element 332. Furthermore, the post-stage selection transistor 382 supplies a potential vslp to the column signal processing circuit 260 through the vertical signal line 309.

(281) In the sixth embodiment, two ADCs are arranged for each column in the column signal processing circuit 260, and are connected to the vertical signal lines 308 and 309 of the

corresponding column.

(282) In the circuit configuration in the drawing, the node **353** between the selection transistor **351** and the capacitive element **331** is in a high-impedance state while the capacitive element **331** holds the level. Furthermore, the node **354** between the selection transistor **352** and the capacitive element **332** is also in a high-impedance state. A gray semicircle in the drawing indicates a node that becomes high impedance during hold. The higher the potentials of these nodes **353** and **354**, the more likely that leakage current will occur at a pn junction between these nodes and the semiconductor substrate.

(283) Therefore, in order to suppress the occurrence of leakage current, the vertical scanning circuit **211** lowers the reference voltage V_{ref} from the high level to the low level when the reset level and the signal level are held. In response to the decrease in the reference voltage V_{ref} , the potentials of the nodes **353** and **354** also shift to the lower level. It is therefore possible to suppress the occurrence of leakage current.

(284) FIG. **34** is a timing chart depicting an example of a global shutter operation in the sixth embodiment of the present technology.

(285) The vertical scanning circuit **211** supplies the high-level FD reset signal rst and the high-level transfer signal trg to all the rows over a period from timing $T0$ to timing $T1$ after the pulse period elapses. Therefore, the exposure simultaneously starts in all the rows. At timing $T2$ immediately before the end of the exposure period, the vertical scanning circuit **211** supplies the high-level FD reset signal rst to all the rows over the pulse period.

(286) The vertical scanning circuit **211** supplies the high-level selection signal Φ_r to all the rows over the pulse period from timing $T3$ after timing $T2$. The vertical scanning circuit **211** supplies the high-level transfer signal trg to all the rows over the pulse period from timing $T4$ of the end of the exposure. Then, the vertical scanning circuit **211** supplies the high-level selection signal Φ_s to all the rows over the pulse period from subsequent timing $T5$.

(287) Furthermore, the vertical scanning circuit **211** changes the reference voltage V_{ref} of all the rows from the low level to the high level at timing $T2$. In the drawing, $V_{ref}[n]$ indicates a reference voltage of the n-th row. Then, the vertical scanning circuit **211** changes the reference voltage V_{ref} of all the rows from the high level to the low level at timing $T6$ after timing $T5$. A difference between the high level and the low level of the reference voltage V_{ref} is denoted as A .

(288) As described above, the vertical scanning circuit **211** sets the reference voltage V_{ref} to the high level during the signal sampling period (period from timing $T2$ to timing $T6$), and shifts the reference voltage V_{ref} to the low level when the sampling period elapses. By this control, immediately after timing $T6$, the high-impedance node **353** on the reset side of all the rows decreases from $VDD-V_{gs}$ to $VDD-V_{gs}-A$. Furthermore, the high-impedance node **354** on the signal side of all the rows decreases from $VDD-V_{gs}-V_{sig}$ to $VDD-V_{gs}-V_{sig}-A$.

(289) If the reference signal line **307** is not wired, and the capacitive elements **331** and **332** have their respective one ends kept at the low level, the potentials of the nodes **353** and **354** remain at $VDD-V_{gs}$ and $VDD-V_{gs}-V_{sig}$ even after the sampling period elapses. In this case, when the potentials (particularly, $VDD-V_{gs}$) of these nodes are high, there is a possibility that leakage current occurs at the pn junction.

(290) Therefore, the vertical scanning circuit **211** lowers the reference voltage V_{ref} when the sampling period elapses. It is therefore possible to lower the potentials of the nodes **353** and **354** to suppress the occurrence of leakage current.

(291) FIG. **35** is a timing chart depicting an example of a read operation of the pixel **301** in the sixth embodiment of the present technology. At timing $T10$ at the start of the reading of the n-th row, the vertical scanning circuit **211** sets the post-stage selection signal $selb$ of the n-th row to the high level. Furthermore, at timing $T11$ in the read period, the vertical scanning circuit **211** sets the selection signals Φ_r and Φ_s of the n-th row to the high level. Then, at timing $T12$ at the end of the reading, the vertical scanning circuit **211** returns the selection signals Φ_r and Φ_s and the post-stage

selection signal selb of the n-th row to the low level.

(292) Furthermore, if the reference voltage V_{ref} remains at the low level during the read period (period from timing **T10** to timing **T12**), the potentials of the nodes **353** and **354** decrease, and the potentials v_{slp} and v_{sld} that are read through the vertical signal lines **308** and **309** also decrease. In this case, there is a possibility that the operating point and range of the post-stage circuit cannot be sufficiently secured. Therefore, the vertical scanning circuit **211** returns the reference voltage V_{ref} to the high level during the read period.

(293) A difference between the potentials v_{slp} and v_{sld} becomes $\Delta 1$ during a period from timing **T10** to timing **T11**, and the difference between the potentials v_{slp} and v_{sld} becomes $\Delta 2$ during a period from timing **T11** to timing **T12**. The post-stage circuit (such as the column signal processing circuit **260**) calculates a difference between $\Delta 1$ and $\Delta 2$ as a net signal level V_{sig} .

(294) In the sixth embodiment, as illustrated in the drawing, since the control timing of the reference voltage V_{ref} at the time of the reading is different for each row, it is necessary to wire the reference signal line **307** for each row.

(295) As described above, according to the sixth embodiment of the present technology, since the vertical scanning circuit **211** lowers the potential of the high-impedance node by means of the control of the reference voltage V_{ref} , it is possible to eliminate the need of the pre-stage selection transistor **317**.

7. Seventh Embodiment

(296) In the first embodiment described above, the potentials of the high-impedance nodes **353** and **354** are lowered by means of the control of the pre-stage selection transistor **317**, but the potentials of these nodes can also be lowered by means of control of the voltage of the reference signal line. The solid-state imaging element **200** of the seventh embodiment is different from that of the first embodiment in that the voltage of the reference signal line is controlled.

(297) FIG. **36** is a circuit diagram depicting a configuration example of the pixel **301** in the seventh embodiment of the present technology. The pixel **301** of the seventh embodiment is different from that of the first embodiment in that the pre-stage selection transistor **317** is not arranged, and a selection transistor **359** is arranged instead of the selection transistors **351** and **352**.

(298) A connection node between the pre-stage amplification transistor **315** and the current source transistor **316** is the pre-stage node **330**. The selection transistor **359** opens and closes a path between the pre-stage node **330** and the node **353** in accordance with a selection signal Φ .

(299) The capacitive element **331** is inserted between the node **353** and the reference signal line **307**, and the capacitive element **332** is inserted between the node **353** and the node **354**. The reference signal line **307** is wired in the horizontal direction for each row. Furthermore, the post-stage reset transistor **361** initializes the potential of the node **354** with the power supply voltage V_{DD} .

(300) The nodes **353** and **354** are in a high-impedance state during hold. A gray semicircle in the drawing indicates a node that becomes high impedance during hold. The higher the potentials of these nodes **353** and **354**, the more likely that leakage current will occur at a pn junction between these nodes and the semiconductor substrate.

(301) Therefore, in order to suppress the occurrence of leakage current, the vertical scanning circuit **211** lowers the reference voltage V_{ref} from the high level to the low level when the reset level and the signal level are held. In response to the decrease in the reference voltage V_{ref} , the potentials of the nodes **353** and **354** also shift to the lower level. It is therefore possible to suppress the occurrence of leakage current.

(302) FIG. **37** is a timing chart depicting an example of a global shutter operation in the seventh embodiment of the present technology.

(303) The vertical scanning circuit **211** supplies the high-level FD reset signal rst and the high-level transfer signal trg to all the rows over a period from timing **T0** to timing **T1** after the pulse period elapses. Therefore, the exposure simultaneously starts in all the rows. At timing **T2** immediately

before the end of the exposure period, the vertical scanning circuit **211** supplies the high-level FD reset signal rst to all the rows over the pulse period.

(304) Furthermore, the vertical scanning circuit **211** supplies the high-level post-stage reset signal rstb to all the rows over a period from timing T2 to timing T3. The vertical scanning circuit **211** supplies the high-level transfer signal trg to all the rows over the pulse period from timing T4 of the end of the exposure.

(305) Furthermore, the vertical scanning circuit **211** supplies the high-level selection signal Φ to all the rows during a period from timing T2 to timing T5 after timing T4.

(306) By the above-described control, the potentials of the nodes **354** and **353** shift from VDD and VDD-Vgs to VDD-Vsig and VDD-Vgs-Vsig, respectively, at timing T3.

(307) Furthermore, the vertical scanning circuit **211** changes the reference voltage Vref of all the rows from the low level to the high level at timing T2. Then, the vertical scanning circuit **211** changes the reference voltage Vref of all the rows from the high level to the low level at timing T6 after timing T5. A difference between the high level and the low level of the reference voltage Vref is denoted as A.

(308) As described above, the vertical scanning circuit **211** sets the reference voltage Vref to the high level during the signal sampling period (period from timing T2 to timing T6), and shifts the reference voltage Vref to the low level when the sampling period elapses. By this control, immediately after timing T6, the potentials of the nodes **354** and **353** decrease from VDD-Vsig and VDD-Vgs-Vsig to VDD-Vsig-A and VDD-Vgs-Vsig-A, respectively.

(309) If the reference signal line **307** is not wired, and the capacitive element **331** has one end kept at the low level, the potentials of the nodes **354** and **353** remain at VDD-Vsig and VDD-Vgs-Vsig even after the sampling period elapses. In this case, when the potentials (particularly, VDD-Vgs) of these nodes are high, there is a possibility that leakage current occurs at the pn junction.

(310) Therefore, the vertical scanning circuit **211** lowers the reference voltage Vref when the sampling period elapses. It is therefore possible to lower the potentials of the nodes **354** and **353** to suppress the occurrence of leakage current.

(311) FIG. **38** is a timing chart depicting an example of a read operation of the pixel **301** in the seventh embodiment of the present technology. At timing T10 at the start of the reading of the n-th row, the vertical scanning circuit **211** sets the post-stage selection signal selb of the n-th row to the high level. Furthermore, the vertical scanning circuit **211** supplies the high-level post-stage reset signal rstb to the n-th row over the pulse period from timing T11 in the read period. Furthermore, the vertical scanning circuit **211** supplies the high-level selection signal **4** to the n-th row over a certain period from timing T11. Then, at timing T12 at the end of the reading, the vertical scanning circuit **211** returns the post-stage selection signal selb of the n-th row to the low level.

(312) Furthermore, if the reference voltage Vref remains at the low level during the read period (period from timing T10 to timing T12), the potentials of the nodes **353** and **354** decrease, and the potential of the vertical signal line **309** also decreases. In this case, there is a possibility that the operating point and range of the post-stage circuit cannot be sufficiently secured. Therefore, the vertical scanning circuit **211** returns the reference voltage Vref to the high level during the read period.

(313) At timing T11, the potential of the vertical signal line shifts from Vd to Vp. The post-stage circuit (such as the column signal processing circuit **260**) calculates a difference between Vd and Vp as a net signal level.

(314) As described above, according to the seventh embodiment of the present technology, since the vertical scanning circuit **211** lowers the potential of the high-impedance node by means of the control of the reference voltage Vref, it is possible to eliminate the need of the pre-stage selection transistor **317**.

8. Eighth Embodiment

(315) In the first embodiment described above, the potentials of the high-impedance nodes **353** and

354 are lowered by means of the control of the pre-stage selection transistor **317**, but the potentials of these nodes can also be lowered by means of control of the voltage of the reference signal line. The solid-state imaging element **200** of the eighth embodiment is different from that of the first embodiment in that the voltage of the reference signal line is controlled.

(316) FIG. **39** is a circuit diagram depicting a configuration example of the pixel **301** in the eighth embodiment of the present technology. The pixel **301** of the eighth embodiment is different from that of the first embodiment in that the pre-stage selection transistor **317** is not arranged.

(317) Furthermore, in the eighth embodiment, the post-stage circuit **370** is connected to the connection node between the pre-stage amplification transistor **315** and the current source transistor **316**. The selection transistor **351** opens and closes a path between the connection node and one end of the capacitive element **331**, and the selection transistor **352** opens and closes a path between the connection node and one end of the capacitive element **332**. The capacitive elements **331** and **332** have their respective other ends commonly connected to the reference signal line **307**. The reference signal line **307** is wired in the horizontal direction for each row.

(318) In the circuit configuration in the drawing, the node **353** between the selection transistor **351** and the capacitive element **331**, and the node **354** between the selection transistor **352** and the capacitive element **332** are in a high-impedance state during hold. A gray semicircle in the drawing indicates a node that becomes high impedance during hold. The higher the potentials of these nodes **353** and **354**, the more likely that leakage current will occur at a pn junction between these nodes and the semiconductor substrate.

(319) Therefore, in order to suppress the occurrence of leakage current, the vertical scanning circuit **211** lowers the reference voltage V_{ref} from the high level to the low level when the reset level and the signal level are held. In response to the decrease in the reference voltage V_{ref} , the potentials of the nodes **353** and **354** also shift to the lower level. It is therefore possible to suppress the occurrence of leakage current.

(320) The global shutter operation of the eighth embodiment is similar to the operation of the sixth embodiment illustrated in FIG. **34**.

(321) FIG. **40** is a timing chart depicting an example of a read operation of the pixel **301** in the eighth embodiment of the present technology. At timing **T10** at the start of the reading of the n-th row, the vertical scanning circuit **211** sets the selection signal Φ_r and the post-stage selection signal $selb$ of the n-th row to the high level. Furthermore, at timing **T11** in the read period, the vertical scanning circuit **211** sets the selection signal Φ_r of the n-th row to the low level and sets the selection signal Φ_s of the row to the high level. At timing **T12** at the end of the reading of the n-th row, the vertical scanning circuit **211** returns the selection signal Φ_s and the post-stage selection signal $selb$ of the n-th row to the low level.

(322) Furthermore, if the reference voltage V_{ref} remains at the low level during the read period (period from timing **T10** to timing **T12**), the potentials of the nodes **353** and **354** decrease, and the potentials v_{slp} and v_{sld} that are read through the vertical signal lines **308** and **309** also decrease. In this case, there is a possibility that the operating point and range of the post-stage circuit cannot be sufficiently secured. Therefore, the vertical scanning circuit **211** returns the reference voltage V_{ref} to the high level during the read period.

(323) As described above, according to the eighth embodiment of the present technology, since the vertical scanning circuit **211** lowers the potential of the high-impedance node by means of the control of the reference voltage V_{ref} , it is possible to eliminate the need of the pre-stage selection transistor **317**.

9. Application Example to Mobile Body

(324) The technology according to an embodiment of the present disclosure (the present technology) is applicable to various products. For example, the technology according to an embodiment of the present disclosure may be implemented as a device mounted on any type of mobile body such as an automobile, an electric vehicle, a hybrid electric vehicle, a motorcycle, a

bicycle, a personal mobility, an airplane, a drone, a ship, or a robot.

(325) FIG. **41** is a block diagram depicting an example of schematic configuration of a vehicle control system as an example of a mobile body control system to which the technology according to an embodiment of the present disclosure can be applied.

(326) The vehicle control system **12000** includes a plurality of electronic control units connected to each other via a communication network **12001**. In the example depicted in FIG. **29**, the vehicle control system **12000** includes a driving system control unit **12010**, a body system control unit **12020**, an outside-vehicle information detecting unit **12030**, an in-vehicle information detecting unit **12040**, and an integrated control unit **12050**. Furthermore, a microcomputer **12051**, a sound/image output section **12052**, and a vehicle-mounted network interface (I/F) **12053** are illustrated as functional components of the integrated control unit **12050**.

(327) The driving system control unit **12010** controls the operation of devices related to the driving system of the vehicle in accordance with various kinds of programs. For example, the driving system control unit **12010** functions as a control device for a driving force generating device for generating the driving force of the vehicle, such as an internal combustion engine, a driving motor, or the like, a driving force transmitting mechanism for transmitting the driving force to wheels, a steering mechanism for adjusting the steering angle of the vehicle, a braking device for generating the braking force of the vehicle, and the like.

(328) The body system control unit **12020** controls the operation of various kinds of devices provided to a vehicle body in accordance with various kinds of programs. For example, the body system control unit **12020** functions as a control device for a keyless entry system, a smart key system, a power window device, or various kinds of lamps such as a headlamp, a backup lamp, a brake lamp, a turn signal, a fog lamp, or the like. In this case, radio waves transmitted from a mobile device as an alternative to a key or signals of various kinds of switches can be input to the body system control unit **12020**. The body system control unit **12020** receives these input radio waves or signals, and controls a door lock device, the power window device, the lamps, or the like of the vehicle.

(329) The outside-vehicle information detecting unit **12030** detects information about the outside of the vehicle including the vehicle control system **12000**. For example, the outside-vehicle information detecting unit **12030** is connected with an imaging section **12031**. The outside-vehicle information detecting unit **12030** makes the imaging section **12031** image an image of the outside of the vehicle, and receives the imaged image. On the basis of the received image, the outside-vehicle information detecting unit **12030** may perform processing of detecting an object such as a human, a vehicle, an obstacle, a sign, a character on a road surface, or the like, or processing of detecting a distance thereto.

(330) The imaging section **12031** is an optical sensor that receives light, and which outputs an electric signal corresponding to a received light amount of the light. The imaging section **12031** can output the electric signal as an image, or can output the electric signal as information about a measured distance. In addition, the light received by the imaging section **12031** may be visible light, or may be invisible light such as infrared rays or the like.

(331) The in-vehicle information detecting unit **12040** detects information about the inside of the vehicle. The in-vehicle information detecting unit **12040** is, for example, connected with a driver state detecting section **12041** that detects the state of a driver. The driver state detecting section **12041**, for example, includes a camera that images the driver. On the basis of detection information input from the driver state detecting section **12041**, the in-vehicle information detecting unit **12040** may calculate a degree of fatigue of the driver or a degree of concentration of the driver, or may determine whether the driver is dozing.

(332) The microcomputer **12051** can calculate a control target value for the driving force generating device, the steering mechanism, or the braking device on the basis of the information about the inside or outside of the vehicle which information is obtained by the outside-vehicle

information detecting unit **12030** or the in-vehicle information detecting unit **12040**, and output a control command to the driving system control unit **12010**. For example, the microcomputer **12051** can perform cooperative control intended to implement functions of an advanced driver assistance system (ADAS) which functions include collision avoidance or shock mitigation for the vehicle, following driving based on a following distance, vehicle speed maintaining driving, a warning of collision of the vehicle, a warning of deviation of the vehicle from a lane, or the like.

(333) In addition, the microcomputer **12051** can perform cooperative control intended for automated driving, which makes the vehicle to travel automatically without depending on the operation of the driver, or the like, by controlling the driving force generating device, the steering mechanism, the braking device, or the like on the basis of the information about the outside or inside of the vehicle which information is obtained by the outside-vehicle information detecting unit **12030** or the in-vehicle information detecting unit **12040**.

(334) Furthermore, the microcomputer **12051** can output a control command to the body system control unit **12020** on the basis of the information about the outside of the vehicle, which is obtained by the outside-vehicle information detecting unit **12030**. For example, the microcomputer **12051** can perform cooperative control intended to prevent a glare by controlling the headlamp so as to change from a high beam to a low beam, for example, in accordance with the position of a preceding vehicle or an oncoming vehicle detected by the outside-vehicle information detecting unit **12030**.

(335) The sound/image output section **12052** transmits an output signal of at least one of a sound and an image to an output device capable of visually or auditorily notifying information to an occupant of the vehicle or the outside of the vehicle. In the example of FIG. **41**, an audio speaker **12061**, a display section **12062**, and an instrument panel **12063** are illustrated as the output device. The display section **12062** may, for example, include at least one of an on-board display and a head-up display.

(336) FIG. **42** is a diagram depicting an example of the installation position of the imaging section **12031**.

(337) In FIG. **42**, the imaging section **12031** includes imaging sections **12101**, **12102**, **12103**, **12104**, and **12105**.

(338) The imaging sections **12101**, **12102**, **12103**, **12104**, and **12105** are, for example, provided at positions on a front nose, sideview mirrors, a rear bumper, and a back door of the vehicle **12100**, and on an upper portion of a windshield within the interior of the vehicle. The imaging section **12101** provided to the front nose and the imaging section **12105** provided to the upper portion of the windshield within the interior of the vehicle obtain mainly an image of the front of the vehicle **12100**. The imaging sections **12102** and **12103** provided to the sideview mirrors obtain mainly an image of the sides of the vehicle **12100**. The imaging section **12104** provided to the rear bumper or the back door obtains mainly an image of the rear of the vehicle **12100**. The imaging section **12105** provided to the upper portion of the windshield within the interior of the vehicle is used mainly to detect a preceding vehicle, a pedestrian, an obstacle, a signal, a traffic sign, a lane, or the like.

(339) Incidentally, FIG. **42** depicts an example of photographing ranges of the imaging sections **12101** to **12104**. An imaging range **12111** represents the imaging range of the imaging section **12101** provided to the front nose. Imaging ranges **12112** and **12113** respectively represent the imaging ranges of the imaging sections **12102** and **12103** provided to the sideview mirrors. An imaging range **12114** represents the imaging range of the imaging section **12104** provided to the rear bumper or the back door. A bird's-eye image of the vehicle **12100** as viewed from above is obtained by superimposing image data imaged by the imaging sections **12101** to **12104**, for example.

(340) At least one of the imaging sections **12101** to **12104** may have a function of obtaining distance information. For example, at least one of the imaging sections **12101** to **12104** may be a stereo camera constituted of a plurality of imaging elements, or may be an imaging element having

pixels for phase difference detection.

(341) For example, the microcomputer **12051** can determine a distance to each three-dimensional object within the imaging ranges **12111** to **12114** and a temporal change in the distance (relative speed with respect to the vehicle **12100**) on the basis of the distance information obtained from the imaging sections **12101** to **12104**, and thereby extract, as a preceding vehicle, a nearest three-dimensional object in particular that is present on a traveling path of the vehicle **12100** and which travels in substantially the same direction as the vehicle **12100** at a predetermined speed (for example, equal to or more than 0 km/hour). Further, the microcomputer **12051** can set a following distance to be maintained in front of a preceding vehicle in advance, and perform automatic brake control (including following stop control), automatic acceleration control (including following start control), or the like. It is thus possible to perform cooperative control intended for automated driving that makes the vehicle travel automatically without depending on the operation of the driver or the like.

(342) For example, the microcomputer **12051** can classify three-dimensional object data on three-dimensional objects into three-dimensional object data of a two-wheeled vehicle, a standard-sized vehicle, a large-sized vehicle, a pedestrian, a utility pole, and other three-dimensional objects on the basis of the distance information obtained from the imaging sections **12101** to **12104**, extract the classified three-dimensional object data, and use the extracted three-dimensional object data for automatic avoidance of an obstacle. For example, the microcomputer **12051** identifies obstacles around the vehicle **12100** as obstacles that the driver of the vehicle **12100** can recognize visually and obstacles that are difficult for the driver of the vehicle **12100** to recognize visually. Then, the microcomputer **12051** determines a collision risk indicating a risk of collision with each obstacle. In a situation in which the collision risk is equal to or higher than a set value and there is thus a possibility of collision, the microcomputer **12051** outputs a warning to the driver via the audio speaker **12061** or the display section **12062**, and performs forced deceleration or avoidance steering via the driving system control unit **12010**. The microcomputer **12051** can thereby assist in driving to avoid collision.

(343) At least one of the imaging sections **12101** to **12104** may be an infrared camera that detects infrared rays. The microcomputer **12051** can, for example, recognize a pedestrian by determining whether or not there is a pedestrian in imaged images of the imaging sections **12101** to **12104**. Such recognition of a pedestrian is, for example, performed by a procedure of extracting characteristic points in the imaged images of the imaging sections **12101** to **12104** as infrared cameras and a procedure of determining whether or not it is the pedestrian by performing pattern matching processing on a series of characteristic points representing the contour of the object. When the microcomputer **12051** determines that there is a pedestrian in the imaged images of the imaging sections **12101** to **12104**, and thus recognizes the pedestrian, the sound/image output section **12052** controls the display section **12062** so that a square contour line for emphasis is displayed so as to be superimposed on the recognized pedestrian. The sound/image output section **12052** may also control the display section **12062** so that an icon or the like representing the pedestrian is displayed at a desired position.

(344) An example of the vehicle control system to which the technology according to an embodiment of the present disclosure can be applied has been described above. The technology according to an embodiment of the present disclosure can be applied to the imaging section **12031** among the configurations described above. Specifically, for example, the imaging device **100** in FIG. **1** can be applied to the imaging section **12031**. By applying the technology according to an embodiment of the present disclosure to the imaging section **12031**, noise can be reduced, and a more easily viewable captured image can be obtained, so that driver's fatigue can be reduced.

(345) Note that, the above embodiments show examples for embodying the present technology, and matters in the embodiments and matters specifying the invention in claims have correspondence relationships. Similarly, the matters specifying the invention in the claims and matters having the

same names in the embodiments of the present technology have correspondence relationships. However, the present technology is not limited to the embodiments and can be embodied by making various modifications to the embodiments without departing from the gist thereof.

(346) Note that effects described in the present description are merely examples and are not limited, and other effects may be provided.

(347) Note that the present technology may also have a following configuration.

(348) (1) A solid-state imaging element including: a predetermined number of capacitive elements; a pre-stage circuit that generates a predetermined reset level and a signal level corresponding to an exposure amount and causes each of the capacitive elements to hold a corresponding one of the reset level and the signal level; a selection circuit in which a selection transistor that opens and closes a path between one end of each of the capacitive elements and a predetermined node is arranged; a post-stage circuit that sequentially reads the reset level and the signal level via the node; and a vertical scanning circuit that performs control to lower a potential of the one end when the reset level and the signal level are held.

(349) (2) The solid-state imaging element described in (1), in which the node is a post-stage node that is a connection point between the selection circuit and the post-stage circuit, the capacitive elements include first and second capacitive elements, the selection circuit includes a first selection transistor that opens and closes a path between one end of the first capacitive element and the post-stage node, and a second selection transistor that opens and closes a path between one end of the second capacitive element and the post-stage node, the first and second capacitive elements having their respective another ends commonly connected to a predetermined pre-stage node, the pre-stage circuit includes a pre-stage selection transistor that outputs each of the reset level and the signal level to the pre-stage node in accordance with a predetermined pre-stage selection signal input to a gate, and the vertical scanning circuit lowers a voltage of the pre-stage selection signal when the reset level and the signal level are held.

(350) (3) The individual imaging element described in (1), in which the node is a pre-stage node that is a connection point between the pre-stage circuit and the selection circuit, the predetermined number of capacitive elements include first and second capacitive elements, the selection circuit includes a first selection transistor that opens and closes a path between one end of the first capacitive element and the pre-stage node, and a second selection transistor that opens and closes a path between one end of the second capacitive element and the pre-stage node, and the vertical scanning circuit lowers a reference voltage of a signal line to which their respective another ends of the first and second capacitive elements are commonly connected when the reset level and the signal level are held.

(351) (4) The solid-state imaging element described in (1), in which the node is a pre-stage node that is a connection point between the pre-stage circuit and the selection transistor, the predetermined number of capacitive elements include a first capacitive element inserted between the selection transistor and a predetermined signal line and a second capacitive element inserted between the selection transistor and the post-stage circuit, and the vertical scanning circuit lowers a reference voltage of the signal line when the reset level and the signal level are held.

(352) (5) The solid-state imaging element described in (1), in which the node is a connection node between the pre-stage circuit and the post-stage circuit, the predetermined number of capacitive elements include first and second capacitive elements, the selection circuit includes a first selection transistor that opens and closes a path between one end of the first capacitive element and the connection node, and a second selection transistor that opens and closes a path between one end of the second capacitive element and the connection node, and the vertical scanning circuit lowers a reference voltage of a signal line to which their respective another ends of the first and second capacitive elements are commonly connected when the reset level and the signal level are held.

(353) (6) The solid-state imaging element described in (1), further including a post-stage reset transistor, in which the node is a post-stage node that is a connection point between the selection

circuit and the post-stage circuit, the pre-stage circuit is arranged in a pre-stage circuit block that generates each of the reset level and a plurality of the signal levels corresponding to the exposure amount and causes each of the capacitive elements to hold a corresponding one of the reset level and the plurality of signal levels, the selection circuit is arranged in a selection unit that sequentially performs control to connect a capacitive element in which the reset level is held among the predetermined number of capacitive elements to a predetermined post-stage node, control to disconnect the predetermined number of capacitive elements from the post-stage node, and control to connect a capacitive element in which one of the plurality of signal levels is held among the predetermined number of capacitive elements to the post-stage node, and the post-stage reset transistor initializes a level of the post-stage node when the predetermined number of capacitive elements are disconnected from the post-stage node.

(354) (7) The solid-state imaging element described in (6), in which the predetermined number of capacitive elements include first and second capacitive elements and third and fourth capacitive elements, the pre-stage circuit block includes a first pre-stage circuit that sequentially generates a first reset level and a first signal level and causes the first and second capacitive elements to hold the first reset level and the first signal level, and a second pre-stage circuit that sequentially generates a second reset level and a second signal level and causes the third and fourth capacitive elements to hold the second reset level and the second signal level, and the selection unit includes a first selection circuit that connects one of the first and second capacitive elements to the post-stage node, and a second selection circuit that connects one of the third and fourth capacitive elements to the post-stage node.

(355) (8) The solid-state imaging element described in (7), in which the first pre-stage circuit includes a first photoelectric conversion element, a first pre-stage transfer transistor that transfers charges from the first photoelectric conversion element to a first floating diffusion layer, a first reset transistor that initializes the first floating diffusion layer, and a first pre-stage amplification transistor that amplifies a voltage of the first floating diffusion layer, and the second pre-stage circuit includes a second photoelectric conversion element, a second pre-stage transfer transistor that transfers charges from the second photoelectric conversion element to a second floating diffusion layer, a second reset transistor that initializes the second floating diffusion layer, and a second pre-stage amplification transistor that amplifies a voltage of the second floating diffusion layer.

(356) (9) The solid-state imaging element described in (8), in which the first pre-stage circuit further includes a first current source transistor connected to a first pre-stage node, the second pre-stage circuit further includes a second current source transistor connected to a second pre-stage node, the first pre-stage amplification transistor amplifies the voltage of the first floating diffusion layer, and outputs the amplified voltage to the first pre-stage node, the second pre-stage amplification transistor amplifies the voltage of the second floating diffusion layer, and outputs the amplified voltage to the second pre-stage node, the first and second capacitive elements have their respective one ends commonly connected to the first pre-stage node, and have their respective another ends connected to the first selection circuit, and the third and fourth capacitive elements have their respective one ends commonly connected to the second pre-stage node, and have their respective another ends connected to the second selection circuit.

(357) (10) The solid-state imaging element described in (8) or (9), in which at predetermined exposure start timing, the first and second pre-stage transfer transistors transfer the charges to the first and second floating diffusion layers, and the first and second reset transistors initialize the first and second floating diffusion layers and the first and second photoelectric conversion elements, and at predetermined exposure end timing, the first and second pre-stage transfer transistors transfer the charges to the first and second floating diffusion layers.

(358) (11) The solid-state imaging element described in any one of (8) to (10), in which the selection unit sequentially performs control to connect one of the first and second capacitive

elements to the post-stage node, control to connect the other of the first and second capacitive elements to the post-stage node, control to connect one of the third and fourth capacitive elements to the post-stage node, and control to connect the other of the third and fourth capacitive elements to the post-stage node.

(359) (12) The solid-state imaging element described in any one of (8) to (11), in which in a predetermined addition mode, the selection unit sequentially performs control to connect both one of the first and second capacitive elements and one of the third and fourth capacitive elements to the post-stage node and control to connect both the other of the first and second capacitive elements and the other of the third and fourth capacitive elements to the post-stage node.

(360) (13) The solid-state imaging element described in (8), in which the first pre-stage circuit further includes a first pre-stage selection transistor that outputs a voltage amplified by the first pre-stage amplification transistor to a predetermined pre-stage node in accordance with a predetermined first selection signal, the second pre-stage circuit further includes a second pre-stage selection transistor that outputs a voltage amplified by the second pre-stage amplification transistor to the pre-stage node in accordance with a predetermined second selection signal, and a current source transistor connected to the pre-stage node, the first and second capacitive elements have their respective one ends commonly connected to the pre-stage node, and have their respective another ends connected to the first selection circuit, and the third and fourth capacitive elements have their respective one ends commonly connected to the pre-stage node, and have their respective another ends connected to the second selection circuit.

(361) (14) The solid-state imaging element described in (13), in which the first and second pre-stage selection transistors sequentially shift to a closed state immediately before a predetermined exposure end timing and after the exposure end timing, the first reset transistor initializes the first floating diffusion layer in a case where the first pre-stage selection transistor is in the closed state, the second reset transistor initializes the second floating diffusion layer in a case where the second pre-stage selection transistor is in the closed state, the first and second pre-stage selection transistors sequentially shift to the closed state immediately after the exposure end timing, and the first and second pre-stage transfer transistors transfer the charges at the predetermined exposure end timing.

(362) (15) The solid-state imaging element described in (6), further including a short-circuit transistor that opens and closes a path between a first post-stage node and a second post-stage node in which the predetermined number of capacitors include first, second, third, fourth, fifth, sixth, seventh, and eighth capacitive elements, and the selection unit includes a first selection circuit that connects one of the first and second capacitive elements to the first post-stage node, a second selection circuit that connects one of the third and fourth capacitive elements to the first post-stage node, a third selection circuit that connects one of the fifth and sixth capacitive elements to the second post-stage node, and a fourth selection circuit that connects one of the seventh and eighth capacitive elements to the second post-stage node.

(363) (16) The solid-state imaging element described in (15), in which in a predetermined non-addition mode, the short-circuit transistor is in an open state, and in the non-addition mode, the selection unit performs, in a predetermined order, control to sequentially connect each of the first and second capacitive elements to the first post-stage node, control to sequentially connect each of the third and fourth capacitive elements to the first post-stage node, control to sequentially connect each of the fifth and sixth capacitive elements to the second post-stage node, and control to sequentially connect each of the seventh and eighth capacitive elements to the second post-stage node.

(364) (17) The solid-state imaging element described in (15) or (16), in which in a predetermined addition mode, the short-circuit transistor is in a closed state, and in the addition mode, the selection unit sequentially performs control to connect one of the fifth and sixth capacitive elements and one of the seventh and eighth capacitive elements to the second post-stage node while

connecting one of the first and second capacitive elements and one of the third and fourth capacitive elements to the first post-stage node, and control to connect the other of the fifth and sixth capacitive elements and the other of the seventh and eighth capacitive elements to the second post-stage node while connecting the other of the first and second capacitive elements and the other of the third and fourth capacitive elements to the first post-stage node.

(365) (18) The solid-state imaging element described in (6), in which the predetermined number of capacitive elements include first and second capacitive elements and a third capacitor, the pre-stage circuit block includes a first photoelectric conversion element, a first pre-stage transfer transistor that transfers charges from the first photoelectric conversion element to a predetermined floating diffusion layer, a second photoelectric conversion element, a second pre-stage transfer transistor that transfers charges from the second photoelectric conversion element to a predetermined floating diffusion layer, a reset transistor that initializes the floating diffusion layer, and a pre-stage amplification transistor that amplifies a voltage of the floating diffusion layer and outputs the amplified voltage to a predetermined pre-stage node, and the first and second capacitive elements and the third capacitive element have their respective one ends commonly connected to the pre-stage node, and have their respective another ends connected to the selection unit.

(366) (19) The solid-state imaging element described in (18), in which at predetermined exposure start timing, the first and second pre-stage transfer transistors transfer the charges to the floating diffusion layer, and the reset transistor initializes the floating diffusion layer and the first and second photoelectric conversion elements, and at predetermined exposure end timing, the first and second pre-stage transfer transistors sequentially transfer the charges to the first and second floating diffusion layers.

(367) (20) The solid-state imaging element described in (18) or (19), in which the selection unit sequentially performs control to connect one of the first and second capacitive elements to the post-stage node, control to connect the other of the first and second capacitive elements to the post-stage node, and control to connect the third capacitive element to the post-stage node.

REFERENCE SIGNS LIST

(368) **100** Imaging device **110** Imaging lens **120** Recording unit **130** Imaging control unit **200** Solid-state imaging element **201** Pixel chip **202** Circuit chip **203** Upper pixel chip **204** Lower pixel chip **211** Vertical scanning circuit **212** Timing control circuit **213** DAC **220** Pixel array unit **221** Upper pixel array unit **222** Lower pixel array unit **250** Load MOS circuit block **251, 373, 383** Load MOS transistor **260** Column signal processing circuit **261** ADC **262** Digital signal processing unit **300** Pixel block **301 to 304** Pixel **305** Pre-stage circuit block **310, 320, 410, 420** Pre-stage circuit **311, 321, 411, 421, 511 to 513** Photoelectric conversion element **312, 322, 412, 422, 514 to 516** Transfer transistor **313, 323, 413, 423** FD reset transistor **314, 324, 414, 424** FD **315, 325, 415, 425** Pre-stage amplification transistor **316, 326, 416, 426** Current source transistor **317, 327, 417, 427** Pre-stage selection transistor **331, 332, 336, 337, 431, 432, 436, 437, 531 to 533** Capacitive element **340** Selection unit **350, 355, 450, 455** Selection circuit **351, 352, 356, 357, 359, 451, 452, 456, 457, 551 to 553** Selection transistor **361, 461** Post-stage reset transistor **370, 380, 470** Post-stage circuit **371, 381, 471** Post-stage amplification transistor **372, 382, 472** Post-stage selection transistor **480** Short-circuit transistor **501** Semiconductor substrate **502, 504** n.sup.+ region **503** Gate electrode **12031** Imaging section

Claims

1. A solid-state imaging element comprising: a predetermined number of capacitive elements; a pre-stage circuit that generates a predetermined reset level and a signal level corresponding to an exposure amount and causes each of the capacitive elements to hold a corresponding one of the reset level and the signal level; a selection circuit in which a selection transistor that opens and closes a path between one end of each of the capacitive elements and a predetermined node is

arranged; a post-stage circuit that sequentially reads the reset level and the signal level via the node; and a vertical scanning circuit that performs control to lower a potential of the one end when the reset level and the signal level are held.

2. The solid-state imaging element according to claim 1, wherein the node is a post-stage node that is a connection point between the selection circuit and the post-stage circuit, the capacitive elements include first and second capacitive elements, the selection circuit includes a first selection transistor that opens and closes a path between one end of the first capacitive element and the post-stage node, and a second selection transistor that opens and closes a path between one end of the second capacitive element and the post-stage node, the first and second capacitive elements having their respective another ends commonly connected to a predetermined pre-stage node, the pre-stage circuit includes a pre-stage selection transistor that outputs each of the reset level and the signal level to the pre-stage node in accordance with a predetermined pre-stage selection signal input to a gate, and the vertical scanning circuit lowers a voltage of the pre-stage selection signal when the reset level and the signal level are held.

3. The individual imaging element according to claim 1, wherein the node is a pre-stage node that is a connection point between the pre-stage circuit and the selection circuit, the predetermined number of capacitive elements include first and second capacitive elements, the selection circuit includes a first selection transistor that opens and closes a path between one end of the first capacitive element and the pre-stage node, and a second selection transistor that opens and closes a path between one end of the second capacitive element and the pre-stage node, and the vertical scanning circuit lowers a reference voltage of a signal line to which their respective another ends of the first and second capacitive elements are commonly connected when the reset level and the signal level are held.

4. The solid-state imaging element according to claim 1, wherein the node is a pre-stage node that is a connection point between the pre-stage circuit and the selection transistor, the predetermined number of capacitive elements include a first capacitive element inserted between the selection transistor and a predetermined signal line and a second capacitive element inserted between the selection transistor and the post-stage circuit, and the vertical scanning circuit lowers a reference voltage of the signal line when the reset level and the signal level are held.

5. The solid-state imaging element according to claim 1, wherein the node is a connection node between the pre-stage circuit and the post-stage circuit, the predetermined number of capacitive elements include first and second capacitive elements, the selection circuit includes a first selection transistor that opens and closes a path between one end of the first capacitive element and the connection node, and a second selection transistor that opens and closes a path between one end of the second capacitive element and the connection node, and the vertical scanning circuit lowers a reference voltage of a signal line to which their respective another ends of the first and second capacitive elements are commonly connected when the reset level and the signal level are held.

6. The solid-state imaging element according to claim 1, further comprising a post-stage reset transistor, wherein the node is a post-stage node that is a connection point between the selection circuit and the post-stage circuit, the pre-stage circuit is arranged in a pre-stage circuit block that generates each of the reset level and a plurality of the signal levels corresponding to the exposure amount and causes each of the capacitive elements to hold a corresponding one of the reset level and the plurality of signal levels, the selection circuit is arranged in a selection unit that sequentially performs control to connect a capacitive element in which the reset level is held among the predetermined number of capacitive elements to a predetermined post-stage node, control to disconnect the predetermined number of capacitive elements from the post-stage node, and control to connect a capacitive element in which one of the plurality of signal levels is held among the predetermined number of capacitive elements to the post-stage node, and the post-stage reset transistor initializes a level of the post-stage node when the predetermined number of capacitive elements are disconnected from the post-stage node.

7. The solid-state imaging element according to claim 6, wherein the predetermined number of capacitive elements include first and second capacitive elements and third and fourth capacitive elements, the pre-stage circuit block includes a first pre-stage circuit that sequentially generates a first reset level and a first signal level and causes the first and second capacitive elements to hold the first reset level and the first signal level, and a second pre-stage circuit that sequentially generates a second reset level and a second signal level and causes the third and fourth capacitive elements to hold the second reset level and the second signal level, and the selection unit includes a first selection circuit that connects one of the first and second capacitive elements to the post-stage node, and a second selection circuit that connects one of the third and fourth capacitive elements to the post-stage node.

8. The solid-state imaging element according to claim 7, wherein the first pre-stage circuit includes a first photoelectric conversion element, a first pre-stage transfer transistor that transfers charges from the first photoelectric conversion element to a first floating diffusion layer, a first reset transistor that initializes the first floating diffusion layer, and a first pre-stage amplification transistor that amplifies a voltage of the first floating diffusion layer, and the second pre-stage circuit includes a second photoelectric conversion element, a second pre-stage transfer transistor that transfers charges from the second photoelectric conversion element to a second floating diffusion layer, a second reset transistor that initializes the second floating diffusion layer, and a second pre-stage amplification transistor that amplifies a voltage of the second floating diffusion layer.

9. The solid-state imaging element according to claim 8, wherein the first pre-stage circuit further includes a first current source transistor connected to a first pre-stage node, the second pre-stage circuit further includes a second current source transistor connected to a second pre-stage node, the first pre-stage amplification transistor amplifies the voltage of the first floating diffusion layer, and outputs the amplified voltage to the first pre-stage node, the second pre-stage amplification transistor amplifies the voltage of the second floating diffusion layer, and outputs the amplified voltage to the second pre-stage node, the first and second capacitive elements have their respective one ends commonly connected to the first pre-stage node, and have their respective another ends connected to the first selection circuit, and the third and fourth capacitive elements have their respective one ends commonly connected to the second pre-stage node, and have their respective another ends connected to the second selection circuit.

10. The solid-state imaging element according to claim 8, wherein at predetermined exposure start timing, the first and second pre-stage transfer transistors transfer the charges to the first and second floating diffusion layers, and the first and second reset transistors initialize the first and second floating diffusion layers and the first and second photoelectric conversion elements, and at predetermined exposure end timing, the first and second pre-stage transfer transistors transfer the charges to the first and second floating diffusion layers.

11. The solid-state imaging element according to claim 8, wherein the selection unit sequentially performs control to connect one of the first and second capacitive elements to the post-stage node, control to connect the other of the first and second capacitive elements to the post-stage node, control to connect one of the third and fourth capacitive elements to the post-stage node, and control to connect the other of the third and fourth capacitive elements to the post-stage node.

12. The solid-state imaging element according to claim 8, wherein in a predetermined addition mode, the selection unit sequentially performs control to connect both one of the first and second capacitive elements and one of the third and fourth capacitive elements to the post-stage node and control to connect both the other of the first and second capacitive elements and the other of the third and fourth capacitive elements to the post-stage node.

13. The solid-state imaging element according to claim 8, wherein the first pre-stage circuit further includes a first pre-stage selection transistor that outputs a voltage amplified by the first pre-stage amplification transistor to a predetermined pre-stage node in accordance with a predetermined first

selection signal, the second pre-stage circuit further includes a second pre-stage selection transistor that outputs a voltage amplified by the second pre-stage amplification transistor to the pre-stage node in accordance with a predetermined second selection signal, and a current source transistor connected to the pre-stage node, the first and second capacitive elements have their respective one ends commonly connected to the pre-stage node, and have their respective another ends connected to the first selection circuit, and the third and fourth capacitive elements have their respective one ends commonly connected to the pre-stage node, and have their respective another ends connected to the second selection circuit.

14. The solid-state imaging element according to claim 13, wherein the first and second pre-stage selection transistors sequentially shift to a closed state immediately before a predetermined exposure end timing and after the exposure end timing, the first reset transistor initializes the first floating diffusion layer in a case where the first pre-stage selection transistor is in the closed state, the second reset transistor initializes the second floating diffusion layer in a case where the second pre-stage selection transistor is in the closed state, the first and second pre-stage selection transistors sequentially shift to the closed state immediately after the exposure end timing, and the first and second pre-stage transfer transistors transfer the charges at the predetermined exposure end timing.

15. The solid-state imaging element according to claim 6, further comprising a short-circuit transistor that opens and closes a path between a first post-stage node and a second post-stage node, wherein the predetermined number of capacitors include first, second, third, fourth, fifth, sixth, seventh, and eighth capacitive elements, and the selection unit includes a first selection circuit that connects one of the first and second capacitive elements to the first post-stage node, a second selection circuit that connects one of the third and fourth capacitive elements to the first post-stage node, a third selection circuit that connects one of the fifth and sixth capacitive elements to the second post-stage node, and a fourth selection circuit that connects one of the seventh and eighth capacitive elements to the second post-stage node.

16. The solid-state imaging element according to claim 15, wherein in a predetermined non-addition mode, the short-circuit transistor is in an open state, and in the non-addition mode, the selection unit performs, in a predetermined order, control to sequentially connect each of the first and second capacitive elements to the first post-stage node, control to sequentially connect each of the third and fourth capacitive elements to the first post-stage node, control to sequentially connect each of the fifth and sixth capacitive elements to the second post-stage node, and control to sequentially connect each of the seventh and eighth capacitive elements to the second post-stage node.

17. The solid-state imaging element according to claim 15, wherein in a predetermined addition mode, the short-circuit transistor is in a closed state, and in the addition mode, the selection unit sequentially performs control to connect one of the fifth and sixth capacitive elements and one of the seventh and eighth capacitive elements to the second post-stage node while connecting one of the first and second capacitive elements and one of the third and fourth capacitive elements to the first post-stage node, and control to connect the other of the fifth and sixth capacitive elements and the other of the seventh and eighth capacitive elements to the second post-stage node while connecting the other of the first and second capacitive elements and the other of the third and fourth capacitive elements to the first post-stage node.

18. The solid-state imaging element according to claim 6, wherein the predetermined number of capacitive elements include first and second capacitive elements and a third capacitor, the pre-stage circuit block includes a first photoelectric conversion element, a first pre-stage transfer transistor that transfers charges from the first photoelectric conversion element to a predetermined floating diffusion layer, a second photoelectric conversion element, a second pre-stage transfer transistor that transfers charges from the second photoelectric conversion element to a predetermined floating diffusion layer, a reset transistor that initializes the floating diffusion layer, and a pre-stage

amplification transistor that amplifies a voltage of the floating diffusion layer and outputs the amplified voltage to a predetermined pre-stage node, and the first and second capacitive elements and the third capacitive element have their respective one ends commonly connected to the pre-stage node, and have their respective another ends connected to the selection unit.

19. The solid-state imaging element according to claim 18, wherein at predetermined exposure start timing, the first and second pre-stage transfer transistors transfer the charges to the floating diffusion layer, and the reset transistor initializes the floating diffusion layer and the first and second photoelectric conversion elements, and at predetermined exposure end timing, the first and second pre-stage transfer transistors sequentially transfer the charges to the first and second floating diffusion layers.

20. The solid-state imaging element according to claim 18, wherein the selection unit sequentially performs control to connect one of the first and second capacitive elements to the post-stage node, control to connect the other of the first and second capacitive elements to the post-stage node, and control to connect the third capacitive element to the post-stage node.
