

US Patent & Trademark Office

Patent Public Search | Text View

United States Patent Application Publication

20250286281

Kind Code

A1

Publication Date

September 11, 2025

Inventor(s)

JARGALSAIKHAN; Nyambayar et al.

LOW-BAND RADIATOR AND MULTI-BROADBAND ANTENNA COMPRISING SAME

Abstract

A low-band radiator comprises: a radiation substrate; a first dipole radiation portion formed from a conductor line on one surface of the radiation substrate and comprising two first loop arms each having the length extending in a predetermined first direction and formed in a loop shape having one end open; a second dipole radiation portion formed from a conductor line on one surface of the radiation surface, comprising two second loop arms each having the length extending in a predetermined second direction and formed in a loop shape having one end open, and disposed so as to intersect the first dipole radiation portion; and a balun portion coupled to the other surface of the radiation substrate and applying power feeding signals, respectively corresponding to the first and second loop arms, to two open ends of the loops.

A low-band radiator comprises: a radiation substrate; a first dipole radiation portion formed from a conductor line on one surface of the radiation substrate and comprising two first loop arms each having the length extending in a predetermined first direction and formed in a loop shape having one end open; a second dipole radiation portion formed from a conductor line on one surface of the radiation surface, comprising two second loop arms each having the length extending in a predetermined second direction and formed in a loop shape having one end open, and disposed so as to intersect the first dipole radiation portion; and a balun portion coupled to the other surface of the radiation substrate and applying power feeding signals, respectively corresponding to the first and second loop arms, to two open ends of the loops.

Inventors: JARGALSAIKHAN; Nyambayar (Incheon, KR), KIM; Ho-Yong (Incheon, KR), PARK; Jeong Geun (Daejeon, KR), PARK; Kwang Woo (Siheung-si, Gyeonggi-do, KR)

Applicant: ACE TECHNOLOGIES CORPORATION (Incheon, KR)

Family ID: 83722517

Appl. No.: 18/555794

**Filed (or PCT
Filed):** April 12, 2022

Foreign Application Priority Data

KR

10-2021-0050265

Apr. 19, 2021

Publication Classification

Int. Cl.: **H01Q9/28** (20060101); **H01Q5/49** (20150101); **H01Q7/00** (20060101); **H01Q21/26** (20060101)

U.S. Cl.:

CPC **H01Q9/285** (20130101); **H01Q5/49** (20150115); **H01Q7/00** (20130101); **H01Q21/26** (20130101);

Background/Summary**TECHINICAL FIELD**

[0001] The present disclosure relates to a low-band radiator and a multi-broadband antenna comprising the same, and more particularly, to a low-band radiator that minimizes the impact on other band radiators and can be manufactured in a compact size, and a multi-broadband antenna comprising the same.

DESCRIPTION OF THE RELATED ART

[0002] Due to the demand for various wireless communication services and the demand for high-speed, high-capacity data communication, wireless communication systems such as base stations are required to cover multiple frequency bands and have broadband characteristics. However, it is very inefficient from a cost and system operation perspective to cover multiple bands by equipping the base station with a plurality of antennas that only cover a single band for this purpose.

Accordingly, there is an increasing demand for a multi-broadband antenna that can simultaneously satisfy multiple bands and broadband by arranging a plurality of radiators of different types covering different frequency bands together in a single housing (radome).

[0003] However, one of the major difficulties in developing multi-broadband antennas is that the width of the antenna radome is limited by the influence of external environments such as wind pressure. In detail, as a plurality of radiators of different types are arranged overlapped to cover different bands within a limited and narrow space, interference between radiators cannot be avoided. In particular, the problem that a low-band radiator placed close to a high-band radiator interferes with the high-band radiator and severely distorts the radiation pattern of the high-band radiator is a major difficulty that is inevitably encountered during development.

[0004] One proposed solution to this problem is to miniaturize the physical size of the low-band radiator, minimize the overlap area with the high-band radiator, and improve the isolation between the low-band radiator and the high-band radiator.

DISCLOSURE OF INVENTION**Technical Problem**

[0005] An object of the present disclosure is to provide a low-band radiator that can be manufactured in a small size, and a multi-broadband antenna comprising the same.

[0006] Another object of the present disclosure is to provide a low-band radiator that has improved isolation from a high-band radiator and can minimize the influence on the radiation pattern of the

high-band radiator, and a multi-broadband antenna comprising the same.

Solution to Problem

[0007] A low-band radiator according to an embodiment of the present disclosure, conceived to achieve the objectives above, comprises: a radiation substrate; a first dipole radiation portion formed from a conductor line on one surface of the radiation substrate and comprising two first loop arms each having the length extending in a predetermined first direction and formed in a loop shape having one end open; a second dipole radiation portion formed from a conductor line on one surface of the radiation substrate, comprising two second loop arms each having the length extending in a predetermined second direction and formed in a loop shape having one end open, and disposed so as to intersect the first dipole radiation portion; and a balun portion coupled to the other surface of the radiation substrate and applying power feeding signals, respectively corresponding to the first and second loop arms, to two open ends of the loops.

[0008] Each of the first loop arms and the second loop arms may have at least one meander line formed in the inner direction of the loop at a predetermined position of the loop-shaped conductor line.

[0009] The low-band radiator may further include a parasitic patch formed on the other surface of the radiation substrate at a position that overlaps a predetermined meander line among at least one meander line of each of the first loop arms and the second loop arms.

[0010] Each of the first loop arms and the second loop arms may further have at least one stub formed in an inner direction of the loop at a predetermined position of the loop-shaped conductor line.

[0011] The radiation substrate may be formed in a shape corresponding to the outer shapes of the two first loop arms and the two second loop arms of the first and second dipole radiation portions.

[0012] The radiation substrate may have a smaller size than the first and second dipole radiation portions, and each of one first loop arm of the two first loop arms and one second loop arm of the two second loop arms may be formed in the form of a loop with the other side cut at a side end of the radiation substrate, and further include a bending line that connects both ends of the cut loop to each other with a predetermined length to maintain the loop structure of the loop arm, wherein the bending line may be bent toward the other surface of the radiation substrate at the side end of the radiation substrate.

[0013] The balun portion may include four pairs of feed pads that receive power feeding signals for each of the two first loop arms and each of the two second loop arms and feed the power feeding signals to the corresponding loop arms, and two feed pads from each of the four pairs of feed pads may feed the same power feeding signals to both open ends of the corresponding loop arm.

[0014] The balun portion may include: a first dipole feeding portion including two first feeding portions arranged in parallel with each other and each having an upper end coupled to the radiation substrate to apply power feeding signals respectively corresponding to the two first loop arms and a first coupling bar connected between the two first feeding portions and transmitting power feeding signals applied to one of the two first feeding portions to the remaining first feeding portion; and a second dipole feeding portion including two second feeding portions arranged in parallel with each other and each having an upper end coupled to the radiation substrate to apply power feeding signals respectively corresponding to the two second loop arms and a second coupling bar connected between the two second feeding portions and transmitting power feeding signals applied to one of the two second feeding portions to the remaining second feeding portion.

[0015] A first – feeding portion among the two first feeding portions may include: a first – feed substrate whose upper end penetrates the radiation substrate and is coupled at a position corresponding to a first – loop arm of the two first loop arms; a first – feed line formed on the lower side of one surface of the first – feed substrate in the direction of the first – loop arm and impedance matching and transmitting a first power feeding signal applied to the first coupling bar connected through the feed substrate; a first – ground plane formed on the other surface of the first

– feed substrate so as not to be electrically connected to the first coupling bar penetrating the first – feed substrate; and a pair of first – feed pads formed on an upper side of one surface of the first – feed substrate and spaced apart from the first – feed line and coupled to the first-ground plane, electrically connected to both ends of the open loop of the first – loop arm, respectively, to – feed the first power feeding signal to the first – loop arm.

[0016] A first + feeding portion among the two first feeding portions may include: a first + feed substrate whose upper end penetrates the radiation substrate and is coupled at a position corresponding to a first + loop arm of the two first loop arms; a first + feed line formed on the lower side of one surface of the first + feed substrate in the direction of the first + loop arm and impedance matching the first power feeding signal transmitted through the first coupling bar; a first + ground plane formed on the other surface of the first + feed substrate so as not to be electrically connected to the first coupling bar penetrating the first + feed substrate; and a pair of first + feed pads formed on an upper side of one surface of the first + feed substrate and spaced apart from the first + feed line and coupled to the first + ground plane, electrically connected to both ends of the open loop of the first + loop arm, respectively, to + feed the first power feeding signal to the first + loop arm.

[0017] A second – feeding portion among the two second feeding portions may include: a second – feed substrate whose upper end penetrates the radiation substrate and is coupled at a position corresponding to a second – loop arm of the two second loop arms; a second – feed line formed on the lower side of one surface of the second – feed substrate in the direction of the second – loop arm and impedance matching and transmitting a second power feeding signal applied to the second coupling bar connected through the feed substrate; a second – ground plane formed on the other surface of the second – feed substrate so as not to be electrically connected to the second coupling bar penetrating the second – feed substrate; and a pair of second – feed pads formed on an upper side of one surface of the second – feed substrate and spaced apart from the second – feed line and coupled to the second – ground plane, electrically connected to both ends of the open loop of the second – loop arm, respectively, to – feed the second power feeding signal to the second – loop arm.

[0018] A second + feeding portion among the two second feeding portions may include: a second + feed substrate whose upper end penetrates the radiation substrate and is coupled at a position corresponding to a second + loop arm of the two second loop arms; a second + feed line formed on the lower side of one surface of the second + feed substrate in the direction of the second + loop arm and impedance matching the second power feeding signal transmitted through the second coupling bar; a second + ground plane formed on the other surface of the second + feed substrate so as not to be electrically connected to the second coupling bar penetrating the second + feed substrate; and a pair of second + feed pads formed on an upper side of one surface of the second + feed substrate and spaced apart from the second + feed line and coupled to the second + ground plane, electrically connected to both ends of the open loop of the second + loop arm, respectively, to + feed the second power feeding signal to the second + loop arm.

[0019] A multi-broadband antenna according to another embodiment of the present disclosure, conceived to achieve the objectives above, comprises: a reflector; a plurality of high-band radiators arranged in the direction of one surface of the reflector; and a plurality of low-band radiators arranged to be spaced apart from the high-band radiators at a predetermined interval in the direction of one surface of the reflector, wherein each of the plurality of low-band radiators comprises: a radiation substrate; a first dipole radiation portion formed from a conductor line on one surface of the radiation substrate and comprising two first loop arms each having the length extending in a predetermined first direction and formed in a loop shape with a partially open structure; a second dipole radiation portion formed from a conductor line on one surface of the radiation substrate, comprising two second loop arms each having the length extending in a predetermined second direction and formed in a loop shape with a partially open structure, and

disposed so as to intersect the first dipole radiation portion; and a balun portion coupled between the reflector and the other surface of the radiation substrate, supporting the radiation substrate, and applying power feeding signals, corresponding to each of the first and second loop arms, to two open ends of the loops.

Advantageous Effects

[0020] Accordingly, the low-band radiator and the multi-broadband antenna comprising the same according to an embodiment of the present disclosure have improved isolation between the low-band radiator and the high-band radiator, can minimize the influence of the low-band radiator on the radiation pattern of the high-band radiator, and can be manufactured in a compact size.

Description

BRIEF DESCRIPTION OF THE DRAWINGS

[0021] FIG. 1 shows a top view of a multi-broadband antenna according to an embodiment of the present disclosure.

[0022] FIG. 2 shows a perspective view of a low-band radiator according to an embodiment of the present disclosure.

[0023] FIGS. 3 and 4 show top and bottom views of the radiation portion of FIG. 2.

[0024] FIG. 5 is a diagram for explaining the detailed structure of the first loop arm of FIG. 3.

[0025] FIGS. 6 and 7 show a perspective view and a top view of the balun portion of FIG. 2.

[0026] FIGS. 8 and 9 are diagrams for explaining the combined structure of the radiation portion and the balun portion.

DETAILED DESCRIPTION OF THE INVENTION

[0027] In order to fully understand the present disclosure, operational advantages of the present disclosure, and objects achieved by implementing the present disclosure, reference should be made to the accompanying drawings illustrating preferred embodiments of the present disclosure and to the contents described in the accompanying drawings.

[0028] Hereinafter, the present disclosure will be described in detail by describing preferred embodiments of the present disclosure with reference to accompanying drawings. However, the present disclosure can be implemented in various different forms and is not limited to the embodiments described herein. For a clearer understanding of the present disclosure, parts that are not of great relevance to the present disclosure have been omitted from the drawings, and like reference numerals in the drawings are used to represent like elements throughout the specification.

[0029] Throughout the specification, reference to a part “including” or “comprising” an element does not preclude the existence of one or more other elements and can mean other elements are further included, unless there is specific mention to the contrary. Also, terms such as “unit”, “device”, “module”, “block”, and the like described in the specification refer to units for processing at least one function or operation, which may be implemented by hardware, software, or a combination of hardware and software.

[0030] FIG. 1 shows a top view of a multi-broadband antenna according to an embodiment of the present disclosure.

[0031] Referring to FIG. 1, the multi-broadband antenna according to the illustrated exemplary embodiment comprises a reflector **10**, a plurality of high-band radiators **21** and **22** for radiating relatively high-band RF signals to realize multi-broadband, and a plurality of low-band radiators **30** for radiating relatively low-band RF signals.

[0032] The plurality of high-band radiators **21** and **22** and the plurality of low-band radiators **30** may be arranged to be spaced apart from one surface of the reflector **10** by a different predetermined distance. In this case, the plurality of low-band radiators **30** may be arranged to be spaced further apart from the reflector **10** than the plurality of high-band radiators **21** and **22**. That

is, the plurality of low-band radiators **30** may be arranged at a greater distance from the reflector **10** than the plurality of high-band radiators **21** and **22**.

[0033] In addition, the plurality of high-band radiators **21** and **22** and the plurality of low-band radiators **30** may be arranged according to a predetermined pattern. Here, as an example, it is shown that eight high-band radiators **21** and **22** are arranged in a 2×4 array and two low-band radiators are arranged in a 1×2 array, however, the number and arrangement pattern of the high-band radiators **21** and **22** and low-band radiators **30** may be changed in various ways.

[0034] In addition, as the plurality of high-band radiators **21** and **22** and the plurality of low-band radiators **30** are arranged to be spaced apart from the reflector **10** at different heights, the plurality of high-band radiators **21** and **22** and the plurality of low-band radiators **30** may be arranged so that some areas overlap with each other in the vertical direction of the reflector **10**.

[0035] Here, in the case of the high-band radiators **22** having an area overlapping with the arrangement area of the low-band radiators **30** among the plurality of high-band radiators **21** and **22**, they may be formed to be smaller than the remaining high-band radiators **21** so that the size of the overlapping area is small. That is, the plurality of high-band radiators **21** and **22** may have different sizes. This is to reduce the influence of the low-band radiators **30** disposed at a position having the overlapping area on the radiation pattern of the high-band radiators **22**, but is not essential.

[0036] Meanwhile, it will be described assuming that, in the multi-broadband antenna of the present disclosure, both the high-band radiators and the low-band radiators are dual polarized dipole radiators that radiate dual polarization of +45 degrees and −45 degrees. Accordingly, each of the plurality of high-band radiators **21** and **22** may be configured so that four radiation patches are formed to extend perpendicularly to each other to radiate dual polarized waves. However, this is just an example, and the structure of the plurality of high-band radiators **21** and **22** may be changed in various ways depending on required characteristics.

[0037] The plurality of low-band radiators **30** are spaced a greater distance from the reflector **10** than the high-band radiators **21** and **22**, disposed in the radiation direction of the high-band radiators **21**, and formed to be relatively large in size compared to the high-band radiators **21** and **22** so that they can radiate low-band RF signals. Therefore, the low-band radiators **30** may become a physical obstacle to the radiation pattern of the high-band radiator **21** and **22**, and as a result, the radiation pattern of the high-band radiators is influenced by the shape and structure of the low-band radiators **30**.

[0038] Although, as described above, the influence on the radiation pattern can be partially reduced by reducing the overlapping area with the low-band radiators **30** by forming some high-band radiators **22** to be smaller than other high-band radiators **21**, it is realistically very difficult to remove the overlapping area while maintaining the required characteristics of the high-band radiators **21** and **22** and the low-band radiators **30**, due to limitations in the size of the antenna.

[0039] Accordingly, in the present disclosure, in order to reduce the influence of the low-band radiators **30** on the radiation pattern of the high-band radiators **21** and **22** in a limited space, the low-band radiators **30** include a plurality of loop arms in which a conductive line forms a loop rather than a radiation patch having a planar structure. That is, the low-band radiator **30** is configured to include a loop arm with a linear structure rather than a radiation patch with a planar structure, thereby greatly reducing the area influencing the radiation pattern of the high-band radiators **21** and **22**, and thus the high-band radiators **21** and **22** can maintain its radiation characteristics as much as possible.

[0040] In addition, in this embodiment, the low-band radiators **30** are configured to further have a meander line or stub on the loop arm, so that the length resonance component due to miniaturization can be compensated, thereby reducing the size of the low-band radiators **30**.

[0041] Hereinafter, the detailed structure of the low-band radiator will be described with reference to the drawings.

[0042] FIG. 2 shows a perspective view of a low-band radiator according to an embodiment of the present disclosure, FIGS. 3 and 4 show top and bottom views of the radiation portion of FIG. 2, and FIG. 5 is a diagram for explaining the detailed structure of the first loop arm of FIG. 3. In addition, FIGS. 6 and 7 show a perspective view and a top view of the balun portion of FIG. 2, and FIGS. 8 and 9 are diagrams for explaining the combined structure of the radiation portion and the balun portion.

[0043] Referring to FIGS. 2 to 9, the low-band radiator **30** according to this embodiment may be largely composed of a radiation portion **1** and a balun portion **2**, and the radiation portion **1** may include a radiation substrate **100** and four loop arms **210**, **220**, **230**, and **240**, which are radiation patterns formed on one surface of the radiation substrate **100**.

[0044] In the present disclosure, each of the four loop arms **210**, **220**, **230**, and **240** is formed as a loop-shaped conductive line whose length is extended in a predetermined direction on one surface of the radiation substrate. Each of the four loop arms **210**, **220**, **230**, and **240** may be formed as a loop of a predetermined shape, and here, as an example, it is shown as being formed in the form of a hexagonal loop whose length is extended in the first and second directions. Among the four loop arms **210**, **220**, **230**, and **240**, two first loop arms **210** and **230** arranged in line with their lengths extended in the same first direction constitute a first dipole radiation portion, and two second loop arms **220** and **240** arranged in line with their length extended in the second direction constitute a second dipole radiation portion arranged to intersect the first dipole radiation portion. That is, the first dipole radiation portion and the second dipole radiation portion may be arranged to intersect each other to have an X-shaped pattern.

[0045] Meanwhile, each of the four loop arms **210**, **220**, **230**, and **240** may have a structure in which one side is partially open in the direction where the first dipole radiation portion and the second dipole radiation portion intersect. Here, the same power feeding signals are fed to both open ends of the loop. As an example, among the two first loop arms **210** and **230** of the first dipole radiation portion, the first – loop arm **210** may receive – power at both open ends, and the first + loop arm **230** may receive + power at both open ends, thereby radiating RF signals of +45 degree polarization among dual polarizations, and among the two second loop arms **220** and **240** of the second dipole radiation portion, the second – loop arm **220** may receive – power at both open ends, and the second + loop arm **240** may receive + power at both open ends, thereby radiating RF signals of –45 degree polarization among dual polarizations.

[0046] As such, in the present disclosure, each of the first and second dipole radiation portions of the radiation portion **1** is provided with two loop arms **210** and **230**; or **220** and **240** formed of thin conductive lines instead of a radiation patch having a conductive plate structure, so that the influence on the radiation pattern of the RF signals radiated from the high-band radiators **21** and **22** can be significantly reduced. In particular, even though the low-band radiators **30** are placed in the radiation direction of the high-band radiators **21** and **22**, the RF signals radiated from the high-band radiators **21** and **22** can also penetrate and radiate inside the loops of the loop arms **210**, **220**, **230**, and **240**, so that the radiation pattern of the high-band radiators **21** and **22** can be maintained as much as possible.

[0047] The radiation substrate **100** is a dielectric substrate supported by a balun portion **2** coupled to a predetermined position on the other surface, spaced apart from the reflector **10** by a predetermined distance, and arranged in parallel with the reflector **10**. In this embodiment, the radiation substrate **100** may be formed in an X shape corresponding to the pattern formed by the four loop arms **210**, **220**, **230**, and **240** of the first and second dipole radiation portions arranged to intersect each other. That is, the radiation substrate **100** may be formed in a shape corresponding to the outer shape of the four loop arms **210**, **220**, **230**, and **240**.

[0048] The radiation substrate **100** may be formed in a square shape like the substrates of the high-band radiators **21** and **22**, but in this embodiment, the radiation substrate **100** may be formed in a pattern extending in an X shape from the center according to the formation pattern of the four loop

arms **210**, **220**, **230**, and **240**, thereby reducing the size of the low-band radiators. That is, the radiation substrate **100** may include four substrate arms **110**, **120**, **130**, and **140** respectively corresponding to the four loop arms **210**, **220**, **230**, and **240**. Here, the four substrate arms **110**, **120**, **130**, and **140** each have a shape corresponding to the outer shape of the corresponding loop arm among the four loop arms **210**, **220**, **230**, and **240**.

[0049] In each of the four substrate arms **110**, **120**, **130**, and **140**, a balun coupling slot **111**, **121**, **131**, and **141** is formed at both ends of one side open in the loop of the loop arm **210**, **220**, **230**, and **240**, so that the upper end of the balun portion **2** can be inserted through.

[0050] When one end of the balun portion **2** is inserted through the radiation substrate **100**, the feed pads **520** and **530** of the balun portion **2** are respectively connected to both ends of the open sides of the corresponding loop arms **210**, **220**, **230**, and **240**, and apply the corresponding power feeding signals to each loop arm. Here, each loop arm **210**, **220**, **230**, and **240** of the balun portion **2** is provided with two corresponding feed pads **520** and **530**, so that power feeding signals can be individually fed to both ends of the open loops of the four loop arms **210**, **220**, **230**, and **240**. That is, the balun portion **2** is provided with pairs of feed pads **520** and **530** that feed power feeding signals to each of the four loop arms **210**, **220**, **230**, and **240**. Each pair of the feed pads **520** and **530** feeds the same power feeding signals to both ends of the open loop of the corresponding loop arm **210**, **220**, **230**, and **240**.

[0051] In this embodiment, at least one meander line **211** or **221**; and **212**, **222**, **232**, or **242**, or at least one stub **213**, **223**, **233**, or **243**; and **214**, **224**, **234**, or **244** may be further formed on each of the four loop arms **210**, **220**, **230**, and **240**. As described above, multi-broadband antennas are frequently limited in physical size, and this physical size limitation is an even greater constraint on the low-band radiator **30**, which has a relatively larger size than the high-band radiators **21** and **22**. Therefore, in order to manufacture a multi-broadband antenna in a limited space, it is important to reduce the physical size of the low-band radiator **30**.

[0052] In order to reduce the physical size of the low-band radiator **30**, the size occupied by the four loop arms **210**, **220**, **230**, and **240** must be reduced. Accordingly, in the present disclosure, at least one meander line **211** or **221**; and **212**, **222**, **232**, or **242** may be formed on each of the four loop arms **210**, **220**, **230**, and **240** so that each of the four loop arms **210**, **220**, **230**, and **240** has a length capable of resonating with RF signals of a required frequency within a limited size. That is, at least one meander line **211** or **221**; and **212**, **222**, **232**, or **242** can increase the length of the loop-shaped conductor line of each of the four loop arms **210**, **220**, **230**, and **240** so that each loop arm **210**, **220**, **230**, and **240** can have the required length. In this case, the meander lines **211** or **221**; and **212**, **222**, **232**, or **242** are formed in the inner direction of the loop on each of the four loop arms **210**, **220**, **230**, and **240** to prevent the size of the low-band radiators from increasing.

[0053] Here, as an example, it was assumed that one first meander line **211** or **221** is formed on the other side of the loop arm **210**, **220**, **230**, or **240** with one side open, and one second meander line **212**, **222**, **232**, or **242** is formed on each of the two lines between one side and the other side of the loop, so that three meander lines **211** or **221**; and **212**, **222**, **232**, or **242** are formed on each of the four loop arms **210**, **220**, **230**, and **240**. However, the number or length of meander lines formed on each loop arm **210**, **220**, **230**, or **240** may be set in various ways.

[0054] The at least one stub **213**, **223**, **233**, or **243**; and **214**, **224**, **234**, or **244** formed on each of the four loop arms **210**, **220**, **230**, and **240** is provided for broadband matching of the meander lines **211** or **221**; and **212**, **222**, **232**, or **242** having narrow-band characteristics. That is, as described above, to have a length that can resonate with RF signals of a required frequency within a limited size, the meander lines formed on each of the four loop arms **210**, **220**, **230**, and **240** have narrow-band characteristics, and in order to make the loop arms **210**, **220**, **230**, and **240** broadband on which these meander lines **242** are formed, they are matched using stubs **213**, **223**, **233**, or **243**; and **214**, **224**, **234**, or **244**.

[0055] The at least one stub **213**, **223**, **233**, or **243**; and **214**, **224**, **234**, or **244** is also formed in the

inner direction of the loop on each of the four loop arms **210**, **220**, **230**, and **240** to prevent the size of the low-band radiators from increasing, and the number and size of the stubs may be adjusted in various ways. Here, as an example, it is assumed that a first stub **213**, **223**, **233**, or **243** is formed between the first meander line **211** or **221** and the two second meander lines **212**, **222**, **232**, or **242**, respectively, and a second stub **214**, **224**, **234**, or **244** is formed between each of the two second meander lines **212**, **222**, **232**, or **242** and the open one end, but the present disclosure is not limited thereto.

[0056] Meanwhile, at positions corresponding to each of the four loop arms **210**, **220**, **230**, and **240** on the other surface of the radiation substrate **100**, parasitic patches **251** to **254** may be further formed to improve isolation from the high-band radiators **21** and **22**. As described above, RF signals radiated from the high-band radiators may be induced in the low-band radiators and re-radiated to the high-band radiators, thereby affecting the radiation pattern of the high-band radiators. This problem can be solved by improving the isolation between the high-band radiators **21** and **22** and the low-band radiators **30**. Accordingly, in the present disclosure, the parasitic patches **251** to **254** are further formed on the other surface of the radiation substrate **100**. Here, for example, two parasitic patches **251** to **254** may be formed on each of the four substrate arms **110**, **120**, **130**, and **140**, and in particular, may be formed on the other surface at the position where the meander lines (here, as an example, the second meander lines **212**, **222**, **232**, and **242**) of the corresponding four loop arms **210**, **220**, **230**, and **240** are formed.

[0057] Referring to FIG. 5, when the operating frequency bands of the low-band radiator **30** and the high-band radiator **21** and **22** according to this embodiment are 0.694 GHz to 0.96 GHz and 1.427 GHz to 2.7 GHz, respectively, the axial length (L.sub.arm) for each loop arm of the low-band radiator is approximately 0.185λ to 0.256λ . The total length of the low-band radiator is $0.427\lambda \pm 0.06\lambda$, which is about 16% smaller than the size of the existing half-wave low-band element.

[0058] In some cases, due to size limitations of the multi-broadband antenna, the radiation substrate **100** cannot have a size corresponding to the first and second dipole radiation portions. As described above, the two loop arms **210** and **230**; or **220** and **240** of each of the first and second dipole radiation portions must be arranged in line in the same direction, but the size of the multi-broadband antenna may be limited to be smaller than the length of the two loop arms **210** and **230**; or **220** and **240** arranged in line. Nevertheless, there is a limit to the size of the loop arms **210**, **220**, **230**, and **240** that can be reduced by forming more meander lines or stubs.

[0059] In this case, as shown in FIGS. 2 to 4, among the four substrate arms **110**, **120**, **130**, and **140** of the radiation substrate **100**, two substrate arms **130** and **140** cannot be formed to have a length corresponding to the loop arm. In addition, when the two substrate arms **130** and **140** are not formed to have the required length for the corresponding loop arms **230** and **240**, the loop arms **230** and **240** formed on one surface of the corresponding substrate arms **130** and **140** also do not maintain an intact loop structure, and are formed in the form of a loop in which the other side in the opposite direction to the open one side is cut at the side ends of the substrate arms **130** and **140**. That is, a loop is not formed, and as a result, the first and second dipole radiation portions cannot radiate RF signals normally.

[0060] Accordingly, the low-band radiator **30** of the present disclosure may further include bending lines **810** and **820** that are implemented as conductors with a predetermined length and are connected to both ends of the other side of the cut loop of the loop arms **230** and **240**, allowing the connected loop arms **230** and **240** to maintain the loop structure. That is, when the size of the substrate arms **110**, **120**, **130**, and **140** of the radiation substrate **100** is smaller than the size of the corresponding loop arms **210**, **220**, **230**, and **240** due to physical size limitations, the bending lines **810** and **820** are connected to the corresponding loop arms **210**, **220**, **230**, and **240**, respectively, so that a loop structure larger than the substrate arms **110**, **120**, **130**, and **140** can be maintained. Here, if the bending lines **810** and **820** are formed to extend directly in the expansion direction of the

loop arms **210**, **220**, **230**, and **240**, the size of the multi-broadband antenna cannot be miniaturized. Therefore, the bending lines **810** and **820** are bent at the side ends of the substrate arms **130** and **140** in the direction of the other surface of the radiation substrate, that is, toward the reflector, so that the bending lines **810** and **820** do not affect the size of the multi-broadband antenna.

[0061] Meanwhile, the balun portion **2** is coupled between the radiation portion **1** and the reflector **10**, functions as a support to ensure that the radiation portion **1** is placed at a predetermined height on one surface of the reflector **10**, and performs a power feeding function of applying power feeding signals to the radiation portion **1**.

[0062] The balun portion **2** is vertically coupled to the reflector **10** and the radiation portion **1** arranged in parallel with each other, and supports the radiation portion **1** so that the radiation portion **1** is arranged in parallel and spaced apart from each of the reflector **10** and the high-band radiators **21** and **22** by a predetermined distance. In addition, the balun portion **2** may include a first dipole feeding portion that applies +45 degree power feeding signals to the first dipole radiation portion and a second dipole feeding portion that applies -45 degree power feeding signals to the second dipole radiation portion.

[0063] The first dipole feeding portion - feeds +45 power feeding signals to both open ends of the first - loop arm **210** of the first dipole radiation portion, and + feeds +45 power feeding signals to both open ends of the first + loop arm **230**. The second dipole feeding portion - feeds -45 power feeding signals to both open ends of the second - loop arm **220** of the second dipole radiation portion, and + feeds -45 power feeding signals to both open ends of the second + loop arm **240**.

[0064] The first dipole feeding portion includes a first - feeding portion and a first + feeding portion arranged in parallel with each other and each having an upper end coupled through the balun coupling slot **111** and **131** of two substrate arms **110** and **130** corresponding to the first - loop arm **210** and the first + loop arm **230** among the four substrate arms **110**, **120**, **130**, and **140** of the radiation substrate **100**, and applying power feeding signals, respectively corresponding to the two first loop arms **210** and **230**, and a first coupling bar **610** connected between the first - feeding portion and the first + feeding portion and transmitting + power feeding signals applied to the first - feeding portion to the first + feeding portion.

[0065] Among the two first feeding portions, the first - feeding portion, coupled to the substrate arm **110** on which the first - loop arm **210** is formed and + feeding +45 degree power feeding signals, includes a first - feed substrate **310**, a first - feed line (not shown), a first - ground plane **710**, and a pair of first - feed pads (not shown).

[0066] The first - feed substrate **310** has an upper end coupled through the balun insertion slot **111** formed in the substrate arm **110**. Here, the first - feed substrate **310** may be formed with a protrusion **311** whose upper part protrudes so as to limit the depth of insertion into the balun insertion slot **111**. The first - feed line is formed on the lower side of one surface of the first - feed substrate **310** in the direction of the first - loop arm **210**. The first - feed line has one end to which power feeding signals are applied, and the other end connected to the first coupling bar **610**, formed in a predetermined pattern, and impedance matching and transmitting the applied power feeding signals to the first coupling bar **610**. The first - ground plane **710** is formed on the other surface of the first - feed substrate **310**, but is not electrically connected to the first coupling bar **610** penetrating the first - feed substrate **310**. Here, when the first - feeding portion receives power feeding signals through, as an example, a cable, the first - feed line may be connected to the inner conductor of the cable to receive power feeding signals, and the first - ground plane **710** may be connected to the outer conductor of the cable. In addition, the pair of first - feed pads is formed on the upper side of one surface of the first - feed substrate **310**, spaced apart from the first - feed line and the first coupling bar **610**, and is coupled to the first - ground plane **710**, to feed - power feeding signals to the first - loop arm **210**.

[0067] Here, since the pair of first - feed pads consists of two separate pads electrically connected to both ends of the open loop of the first - loop arm **210**, respectively, +45 degree power feeding

signals can be fed independently to both ends of the open loop of the first – loop arm **210**.

[0068] As described above, – feeding through the coupling between the first – ground plane **710** and the pair of first – feed pads (not shown) is to improve the isolation between the first – loop arm **210** and the adjacent loop arms **220** and **240** and to improve the cross polarization ratio. That is, the reason why the first – feeding portion feeds power feeding signals applied to the first – feed line to both ends of the open loop of the first – loop arm **210** through coupling between the first – ground plane **710** and the pair of first – feed pads (not shown) is to improve the isolation between the first – loop arm **210** and the adjacent loop arms **220** and **240** and to improve the cross polarization ratio. [0069] In addition, the first + feeding portion is coupled to the substrate arm **130** on which the first + loop arm **230** is formed, + feeds +45 degree power feeding signals, and includes a first + feed substrate **330**, a first + feed line **430**, a first + ground plane (not shown), and a pair of first + feed pads **530**.

[0070] The first + feed substrate **330** has an upper end coupled through the balun insertion slot **131** formed in the substrate arm **130**. Here, a protrusion **311** may also be formed on the first + feed substrate **330**. In addition, the first + feed line **430** is formed on the lower side of one surface of the first + feed substrate **330** in the direction of the first + loop arm **230**. The first + feed line **430** is formed in a predetermined pattern, and has one end connected to the first coupling bar **610**, to impedance match the power feeding signals applied through the first coupling bar **610**. The first + ground plane (not shown) is formed on the other surface of the first + feed substrate **330**, that is, to face the first – ground plane **710**, but is not electrically connected to the first coupling bar **610** penetrating the first + feed substrate **330**. In addition, the pair of first + feed pads **530** is formed on the upper side of one surface of the first + feed substrate **310**, spaced apart from the first + feed line **430** and the first coupling bar **610**, and is coupled with the first + ground plane, to + feed +45 degree power feeding signals to the first + loop arm **230**. Since the pair of first + feed pads **530** also consists of two separate pads electrically connected to both ends of the open loop of the first + loop arm **230**, respectively, +45 degree power feeding signals can be + fed independently to both ends of the open loop of the first + loop arm **230**.

[0071] The second dipole feeding portion also includes a second – feeding portion and a second + feeding portion arranged in parallel with each other and each having an upper end coupled through the balun coupling slot **121** and **141** of two substrate arms **120** and **140** corresponding to the second – loop arm **220** and the second + loop arm **240** among the four substrate arms **110**, **120**, **130**, and **140** of the radiation substrate **100**, and applying power feeding signals, respectively corresponding to the two second loop arms **220** and **240**, and a second coupling bar **620** connected between the second – feeding portion and the second + feeding portion and transmitting power feeding signals applied to the second – feeding portion to the second + feeding portion.

[0072] Here, the configuration of each of the second – feeding portion and the second + feeding portion is similar to that of the first – feeding portion and the first + feeding portion, and thus, are not described in detail herein.

[0073] As shown in FIG. **6**, the first – feeding portion and the first + feeding portion, the second – feeding portion and the second + feeding portion, which are arranged in parallel to each other, may be joined at their side ends in a vertical direction so that the balun portion **2** has the shape of a square pillar.

[0074] Feeding power feeding signals to both ends of the open loop of the corresponding loop arm **210**, **220**, **230**, and **240** through coupling between the ground plane and each of the corresponding pair of feed pads is to improve the isolation between the loop arms **210**, **220**, **230**, and **240** and the adjacent loop arms and to improve the cross polarization ratio.

[0075] In the first + feeding portion, the second – feeding portion, and the second + feeding portion as well, feeding power feeding signals to both ends of the open loop of the corresponding loop arm **220**, **230**, and **240** through coupling between the ground plane and each of the corresponding pair of feed pads is to improve the isolation between the loop arms **220**, **230**, and **240** and the adjacent

loop arms and to improve the cross polarization ratio.

[0076] As a result, the low-band radiator and the multi-broadband antenna comprising the same according to this embodiment can not only reduce the influence on the radiation pattern of the high-band radiators by applying loop arms instead of radiation patches, but also significantly reduce the size by additionally forming meander lines and stubs. In addition, the isolation from high-band radiators can be improved by adding parasitic patches, and, even in sizes where a loop arm cannot be formed, the loop structure can be maintained by using a bending line, allowing for further miniaturization. Additionally, a pair of feed pads of the balun portion receives power feeding signals through a coupling method and feeds the corresponding loop arm, thereby improving the isolation between the loop arms and improving the cross polarization ratio.

[0077] While the present disclosure is described with reference to embodiments illustrated in the drawings, these are provided as examples only, and the person having ordinary skill in the art would understand that many variations and other equivalent embodiments can be derived from the embodiments described herein.

[0078] Therefore, the true technical scope of the present disclosure is to be defined by the technical spirit set forth in the appended scope of claims.

Claims

1. A low-band radiator, comprising: a radiation substrate; a first dipole radiation portion formed from a conductor line on one surface of the radiation substrate and comprising two first loop arms each having the length extending in a predetermined first direction and formed in a loop shape having one end open; a second dipole radiation portion formed from a conductor line on one surface of the radiation substrate, comprising two second loop arms each having the length extending in a predetermined second direction and formed in a loop shape having one end open, and disposed so as to intersect the first dipole radiation portion; and a balun portion coupled to the other surface of the radiation substrate and applying power feeding signals, respectively corresponding to the first and second loop arms, to two open ends of the loops.
2. The low-band radiator according to claim 1, wherein each of the first loop arms and the second loop arms has at least one meander line formed in the inner direction of the loop at a predetermined position of the loop-shaped conductor line.
3. The low-band radiator according to claim 2, wherein the low-band radiator further includes a parasitic patch formed on the other surface of the radiation substrate at a position that overlaps a predetermined meander line among at least one meander line of each of the first loop arms and the second loop arms.
4. The low-band radiator according to claim 1, wherein each of the first loop arms and the second loop arms further has at least one stub formed in an inner direction of the loop at a predetermined position of the loop-shaped conductor line.
5. The low-band radiator according to claim 1, wherein the radiation substrate is formed in a shape corresponding to the outer shapes of the two first loop arms and the two second loop arms of the first and second dipole radiation portions.
6. The low-band radiator according to claim 1, wherein the radiation substrate has a smaller size than the first and second dipole radiation portions, and each of one first loop arm of the two first loop arms and one second loop arm of the two second loop arms is formed in the form of a loop with the other side cut at a side end of the radiation substrate, and further includes a bending line that connects both ends of the cut loop to each other with a predetermined length to maintain the loop structure of the loop arm, wherein the bending line is bent toward the other surface of the radiation substrate at the side end of the radiation substrate.
7. The low-band radiator according to claim 1, wherein the balun portion includes four pairs of feed pads that receive power feeding signals for each of the two first loop arms and each of the two

second loop arms and feed the power feeding signals to the corresponding loop arms, and two feed pads from each of the four pairs of feed pads feed the same power feeding signals to both open ends of the corresponding loop arm.

8. The low-band radiator according to claim 1, wherein the balun portion includes: a first dipole feeding portion including two first feeding portions arranged in parallel with each other and each having an upper end coupled to the radiation substrate to apply power feeding signals respectively corresponding to the two first loop arms and a first coupling bar connected between the two first feeding portions and transmitting power feeding signals applied to one of the two first feeding portions to the remaining first feeding portion; and a second dipole feeding portion including two second feeding portions arranged in parallel with each other and each having an upper end coupled to the radiation substrate to apply power feeding signals respectively corresponding to the two second loop arms and a second coupling bar connected between the two second feeding portions and transmitting power feeding signals applied to one of the two second feeding portions to the remaining second feeding portion.

9. The low-band radiator according to claim 8, wherein a first – feeding portion among the two first feeding portions includes: a first – feed substrate whose upper end penetrates the radiation substrate and is coupled at a position corresponding to a first – loop arm of the two first loop arms; a first – feed line formed on the lower side of one surface of the first – feed substrate in the direction of the first – loop arm and impedance matching and transmitting a first power feeding signal applied to the first coupling bar connected through the feed substrate; a first – ground plane formed on the other surface of the first – feed substrate so as not to be electrically connected to the first coupling bar penetrating the first – feed substrate; and a pair of first – feed pads formed on an upper side of one surface of the first – feed substrate and spaced apart from the first – feed line and coupled to the first – ground plane, electrically connected to both ends of the open loop of the first – loop arm, respectively, to – feed the first power feeding signal to the first – loop arm, and wherein a first + feeding portion among the two first feeding portions includes: a first + feed substrate whose upper end penetrates the radiation substrate and is coupled at a position corresponding to a first + loop arm of the two first loop arms; a first + feed line formed on the lower side of one surface of the first + feed substrate in the direction of the first + loop arm and impedance matching the first power feeding signal transmitted through the first coupling bar; a first + ground plane formed on the other surface of the first + feed substrate so as not to be electrically connected to the first coupling bar penetrating the first + feed substrate; and a pair of first + feed pads formed on an upper side of one surface of the first + feed substrate and spaced apart from the first + feed line and coupled to the first + ground plane, electrically connected to both ends of the open loop of the first + loop arm, respectively, to + feed the first power feeding signal to the first + loop arm.

10. The low-band radiator according to claim 8, wherein a second – feeding portion among the two second feeding portions includes: a second – feed substrate whose upper end penetrates the radiation substrate and is coupled at a position corresponding to a second – loop arm of the two second loop arms; a second – feed line formed on the lower side of one surface of the second – feed substrate in the direction of the second – loop arm and impedance matching and transmitting a second power feeding signal applied to the second coupling bar connected through the feed substrate; a second – ground plane formed on the other surface of the second – feed substrate so as not to be electrically connected to the second coupling bar penetrating the second – feed substrate; and a pair of second – feed pads formed on an upper side of one surface of the second – feed substrate and spaced apart from the second – feed line and coupled to the second – ground plane, electrically connected to both ends of the open loop of the second – loop arm, respectively, to – feed the second power feeding signal to the second – loop arm, and wherein a second + feeding portion among the two second feeding portions includes: a second + feed substrate whose upper end penetrates the radiation substrate and is coupled at a position corresponding to a second + loop

arm of the two second loop arms; a second + feed line formed on the lower side of one surface of the second + feed substrate in the direction of the second + loop arm and impedance matching the second power feeding signal transmitted through the second coupling bar; a second + ground plane formed on the other surface of the second + feed substrate so as not to be electrically connected to the second coupling bar penetrating the second + feed substrate; and a pair of second + feed pads formed on an upper side of one surface of the second + feed substrate and spaced apart from the second + feed line and coupled to the second + ground plane, electrically connected to both ends of the open loop of the second + loop arm, respectively, to + feed the second power feeding signal to the second + loop arm.

11. A multi-broadband antenna, comprising: a reflector; a plurality of high-band radiators arranged in the direction of one surface of the reflector; and a plurality of low-band radiators arranged to be spaced apart from the high-band radiators at a predetermined interval in the direction of one surface of the reflector, wherein each of the plurality of low-band radiators comprises: a radiation substrate; a first dipole radiation portion formed from a conductor line on one surface of the radiation substrate and comprising two first loop arms each having the length extending in a predetermined first direction and formed in a loop shape with a partially open structure; a second dipole radiation portion formed from a conductor line on one surface of the radiation substrate, comprising two second loop arms each having the length extending in a predetermined second direction and formed in a loop shape with a partially open structure, and disposed so as to intersect the first dipole radiation portion; and a balun portion coupled between the reflector and the other surface of the radiation substrate, supporting the radiation substrate, and applying power feeding signals, corresponding to each of the first and second loop arms, to two open ends of the loops.

12. The multi-broadband antenna according to claim 11, wherein each of the first loop arms and the second loop arms has at least one meander line formed in the inner direction of the loop at a predetermined position of the loop-shaped conductor line.

13. The multi-broadband antenna according to claim 12, wherein the low-band radiator further includes a parasitic patch formed on the other surface of the radiation substrate at a position that overlaps a predetermined meander line among at least one meander line of each of the first loop arms and the second loop arms.

14. The multi-broadband antenna according to claim 11, wherein each of the first loop arms and the second loop arms further has at least one stub formed in an inner direction of the loop at a predetermined position of the loop-shaped conductor line.

15. The multi-broadband antenna according to claim 11, wherein the radiation substrate is formed in a shape corresponding to the outer shapes of the two first loop arms and the two second loop arms of the first and second dipole radiation portions.

16. The multi-broadband antenna according to claim 11, wherein the radiation substrate has a smaller size than the first and second dipole radiation portions, and each of one first loop arm of the two first loop arms and one second loop arm of the two second loop arms is formed in the form of a loop with the other side cut at a side end of the radiation substrate, and further includes a bending line that connects both ends of the cut loop to each other with a predetermined length to maintain the loop structure of the loop arm, wherein the bending line is bent toward the other surface of the radiation substrate at the side end of the radiation substrate.

17. The multi-broadband antenna according to claim 11, wherein the balun portion includes four pairs of feed pads that receive power feeding signals for each of the two first loop arms and each of the two second loop arms and feed the power feeding signals to the corresponding loop arms, and two feed pads from each of the four pairs of feed pads feed the same power feeding signals to both open ends of the corresponding loop arm.

18. The multi-broadband antenna according to claim 11, wherein the balun portion includes: a first dipole feeding portion including two first feeding portions arranged in parallel with each other and each having an upper end coupled to the radiation substrate and a lower end coupled to the

reflector, to apply power feeding signals respectively corresponding to the two first loop arms and a first coupling bar connected between the two first feeding portions and transmitting power feeding signals applied to one of the two first feeding portions to the remaining first feeding portion; and a second dipole feeding portion including two second feeding portions arranged in parallel with each other and each having an upper end coupled to the radiation substrate and a lower end coupled to the reflector, to apply power feeding signals respectively corresponding to the two second loop arms and a second coupling bar connected between the two second feeding portions and transmitting power feeding signals applied to one of the two second feeding portions to the remaining second feeding portion.
