

US Patent & Trademark Office

Patent Public Search | Text View

United States Patent	12400728
Kind Code	B2
Date of Patent	August 26, 2025
Inventor(s)	Ayyapureddi; Sujeet

Apparatuses, systems, and methods for storing error information and providing recommendations based on same

Abstract

Per-row recent and/or baseline error information for word lines may be stored along the word lines in some examples. In some examples, baseline error information may be stored in a fuse array. In some examples, the baseline error information may be loaded from the fuse array to a memory array. In some examples, based on the recent and/or baseline error information, the memory device may provide a post-package repair recommendation.

Inventors:	Ayyapureddi; Sujeet (Boise, ID)
Applicant:	Micron Technology, Inc. (Boise, ID)
Family ID:	1000008780952
Assignee:	Micron Technology, Inc. (Boise, ID)
Appl. No.:	18/598832
Filed:	March 07, 2024

Prior Publication Data

Document Identifier	Publication Date
US 20240312553 A1	Sep. 19, 2024

Related U.S. Application Data

us-provisional-application US 63490056 20230314

Publication Classification

Int. Cl.: G11C29/00 (20060101); G11C29/52 (20060101)

U.S. Cl.:

CPC **G11C29/52** (20130101);

Field of Classification Search

CPC: G06F (11/106); G06F (11/0727); G06F (11/073); G06F (11/1048)

References Cited

U.S. PATENT DOCUMENTS

Patent No.	Issued Date	Patentee Name	U.S. Cl.	CPC
7676728	12/2009	Resnick	714/764	G06F 11/106
8687421	12/2013	Avila	365/185.11	G11C 16/26
8949685	12/2014	Joseph	714/763	G06F 11/1028
9037928	12/2014	Kleveland	714/710	G11C 29/44
9087614	12/2014	Son	N/A	G06F 11/1048
9786386	12/2016	Strauss	N/A	G11C 29/50004
9823964	12/2016	Reed	N/A	G06F 3/0688
10824365	12/2019	Jung	N/A	G06F 13/16
2018/0342299	12/2017	Yamada et al.	N/A	N/A
2021/0064462	12/2020	Eun et al.	N/A	N/A
2024/0312547	12/2023	Ayyapureddi	N/A	N/A
2024/0312550	12/2023	Ayyapureddi	N/A	N/A

FOREIGN PATENT DOCUMENTS

Patent No.	Application Date	Country	CPC
118658501	12/2023	CN	N/A

OTHER PUBLICATIONS

U.S. Appl. No. 18/598,899 titled “Apparatuses, Systems, and Methods for Storing Error Information and Providing Recommendations Based on Same”, filed Mar. 7, 2024; pp. all pages of application as filed. cited by applicant

U.S. Appl. No. 18/598,937 titled “Apparatuses, Systems, and Methods for Storing Error Information and Providing Recommendations Based on Same”, filed Mar. 7, 2024; pp. all pages of application as filed. cited by applicant

Primary Examiner: Abraham; Esaw T

Attorney, Agent or Firm: Dorsey & Whitney LLP

Background/Summary

CROSS REFERENCE TO RELATED APPLICATION(S) (1) This application claims the benefit under 35 U.S.C. § 119 of the earlier filing date of U.S. Provisional Application Ser. No. 63/490,056 filed Mar. 14, 2023, the entire contents of which are hereby incorporated by reference in their entirety for any purpose.

BACKGROUND

(1) This disclosure relates generally to semiconductor devices, such as semiconductor memory devices. The semiconductor memory device may include a number of memory cells which are used to store information. The stored information may be encoded as binary data, and each memory cell may store a single bit of the information. Information may decay or change in the memory cells due to a variety of different errors, which may lead to one or more bits of incorrect information (e.g., bits with different states than the bit which was originally written) being read out from the memory device.

(2) There may be many applications where it is useful to ensure a high fidelity of information read out from the memory. Memory devices may include error correction circuits, which may be used to determine if the information read out of the memory cells contains any errors compared to the data written into the memory cells, and may correct discovered errors. The memory device may periodically use the error correction circuits to repair errors in information stored within the memory array by scanning every memory cell of the memory array. However, present systems provide limited information on error correction and information on when repairs should be performed on memory devices.

Description

BRIEF DESCRIPTION OF THE DRAWINGS

(1) FIG. 1 is a block diagram of a semiconductor device according to some embodiments of the present disclosure.

(2) FIG. 2 is a block diagram of a memory system according to some embodiments of the present disclosure.

(3) FIG. 3 is a block diagram of a row of a memory array according to embodiments of the present disclosure.

(4) FIG. 4 is a block diagram of a memory according to some embodiments of the present disclosure.

(5) FIG. 5 shows an example grammar for programming the fuse array according to embodiments of the present disclosure.

(6) FIG. 6 shows an example programming of a fuse array according to embodiments of the present disclosure.

(7) FIG. 7 is a flow chart of a method according to embodiments of the present disclosure.

(8) FIG. 8 is a flow chart of a method according to embodiments of the present disclosure.

(9) FIG. 9 is a flow chart of a method according to embodiments of the present disclosure.

(10) FIG. 10 is a flow chart of a method according to embodiments of the present disclosure.

DETAILED DESCRIPTION

(11) The following description of certain embodiments is merely exemplary in nature and is in no way intended to limit the scope of the disclosure or its applications or uses. In the following detailed description of embodiments of the present systems and methods, reference is made to the accompanying drawings which form a part hereof, and which are shown by way of illustration specific embodiments in which the described systems and methods may be practiced. These embodiments are described in sufficient detail to enable those skilled in the art to practice presently disclosed systems and methods, and it is to be understood that other embodiments may be utilized and that structural and logical changes may be made without departing from the spirit and scope of the disclosure. Moreover, for the purpose of clarity, detailed descriptions of certain features will not be discussed when they would be apparent to those with skill in the art so as not to obscure the description of embodiments of the disclosure. The following detailed description is therefore not to be taken in a limiting sense, and the scope of the disclosure is defined only by the appended claims.

(12) A memory device may include a memory array which has a number of memory cells, each located (e.g., disposed) at the intersection of a word line (row) and digit line (bit line, column). The memory array may be subdivided into banks, each of which includes a number of rows and a number of columns (the number of rows and number of columns need not be equal to one another). The columns may generally be organized into column planes, each of which includes a number of sets of individual columns all activated by a column select signal (CS). Each bank may include some number X column planes. A column plane may receive some number N of column select (CS) signals, each of which may activate some number M of individual digit lines. As used herein, a column select set or CS set may generally refer to a set of digit lines which are activated by a given value of the CS signal within a column plane. The column select signal may be represented by (all or a portion of) a column address (CA). Responsive to a column select signal, data may be provided from corresponding locations from the column planes. The data from the column planes associated with the column select signal may be referred to as a cache line and/or a prefetch.

(13) During a read or write operation, a row may be activated, and data may be read from, or written to, the memory cells along the activated row. Each row may include memory cells which store a number of bits of data and a number of bits of parity information (e.g., data bits and parity bits), which may be used to correct up to a certain number of errors in the data bits. For example, a row may include one or more code words, each of which includes M data bits and K parity bits, which may be used to correct up to one of the M data bits or one of the K parity bits. During a write operation the parity bits may be generated by an error correction code (ECC) circuit based on the data written to the memory cells of the row. During a read operation the ECC circuit may use the parity bits to determine if the read data bits are correct, and may correct any errors which are found in the data as it is being provided off the memory device (e.g., to a controller). In some applications, the K parity bits (e.g., ECC information) for each row may be stored in memory cells along the same columns of the array. That is, certain column planes may be designated for the M data bits and other column planes may be designated for the K parity bits.

(14) The ECC circuit may identify errors in read data and correct the read data before it is provided to data terminals of the memory device. However, the error may remain in the code word stored in the memory array. The device may perform error check and scrub (ECS) operations to remedy this. In an ECS operation, the address of each code word of the memory array may be accessed one at a time. The code word from the current address is read out, an error, if present, is corrected by the ECC circuit, and then the corrected code word is written back to the memory array. The memory performs an ECS cycle by performing ECS operations on each code word of the memory by working through a sequence of every code word address.

(15) During an ECS cycle, the memory may collect information about the number of code words which contained an error. For example, the memory may report a total number of code words with errors and/or the address of the row which contains the most code word errors. However, more transparency into the number and location of errors in the memory array is desired, particularly in automotive and other fields where errors may lead to safety issues.

(16) Typically, the parity bits may provide enough information to correct one error in the code word. If the code word includes two errors, a “collision” may occur. In some instances, the two errors may cause the ECC circuit to flip a bit during correction, which may introduce a third error in the code word. Some errors in the code word are transient. That is, the error was introduced by a temporary condition in the memory array (e.g., transient electromagnetic disturbance, temperature fluctuation, etc.) and/or a flaky bit. For transient errors, the next time the code word is written to the memory cell, it may not include an error. However, some errors in the code word are persistent. That is, the error is due to a defect in the memory device (e.g., defective memory cell, short in a conductive line coupled to a memory cell, etc.).

(17) Memory arrays may be tested after fabrication prior to shipping to customers or end users to find defective rows and columns—that is, rows and columns with unacceptable numbers of errors.

The unacceptable number may be based on a pre-determined threshold number of errors in a row and/or column. For example, each row may include sixty-four column selects, each associated with a code word for a total of sixty-four code words. If a row is found to have four or more code words with errors, the row may be flagged as defective. The threshold number of errors may be based, at least in part, on a risk of collisions occurring based on the number of detected errors. Defective rows and columns may be replaced by redundant rows and columns in the memory array. The addresses for the defective rows and columns may be remapped to the redundant rows and columns. The remapping information may be stored in a fuse array of the memory device.

(18) After the memory device has left the factory, the memory array may be damaged and/or degrade over time, leading to more defective rows and/or columns. These additional defective rows and/or columns may be remapped to additional redundant rows and columns, respectively, by using post-package repair (PPR) functionality of the memory device. However, once all of the available redundant rows and/or columns have been used, no more defective rows or columns can be repaired.

(19) The ECC circuit of a memory device may manage errors, such as parity checks during access operations and/or during ECS operations to avoid prematurely “using up” the available redundant rows and columns. However, some rows and/or columns may develop enough errors that the risk of a collision becomes unacceptably high. In these cases, a PPR operation may be appropriate to replace the defective row and/or column. Some users may not know when a PPR operation is advisable and may remap rows or bit lines with errors that may be reliably managed by the ECC circuit. Accordingly, providing advice from the memory device as to when to perform a PPR operation may be desirable.

(20) The present disclosure is directed to apparatuses, systems and methods for storing per-row error information (e.g., ECC and/or ECS information) in a memory device and to provide PPR recommendations. In some examples, error information may include a number of code words with errors in a row (e.g., a pRECS value). In some examples, error information may include addresses of bits with errors or addresses of code words with errors. In some embodiments, only error information for rows that have errors may be included in the baseline information. The error information may include “baseline” information and “recent” information. Baseline information may include error information of the memory array collected after fabrication (e.g., pRECS values found during testing) but prior to being provided to a user (e.g., customer of a memory device company or end user). Recent information may include error information (e.g., ECS information) from a number of most recent ECS cycles, error information from a number of most recent hours or days, etc.

(21) Error information may be stored in various locations of a memory device. In some embodiments, baseline information may be stored in a fuse array of the memory device and recent information may be stored in a memory array. In some embodiments, recent information may be stored in the memory array, and some or all of the baseline information stored in the fuse array may be loaded into the memory array. In some embodiments, error information may be stored in regions of the memory array for metadata. In some embodiments, error information may be stored in regions of the memory array “leftover” after regions are assigned to metadata (e.g., “extra” bits in column planes assigned to store metadata).

(22) In some embodiments, the memory device may compare the recent information to the baseline information. If the comparison indicates a word line or a bit line has become defective (e.g., the recent information indicates an increase in the number of code words with errors compared to the baseline information), the memory device may issue a recommendation to perform a PPR operation.

(23) FIG. 1 is a block diagram of a semiconductor device according an embodiment of the disclosure. The semiconductor device **100** may be a semiconductor memory device, such as a DRAM device integrated on a single semiconductor chip.

(24) The semiconductor device **100** includes a memory array **118**. The memory array **118** is shown as including a plurality of memory banks. In the embodiment of FIG. **1**, the memory array **118** is shown as including eight memory banks BANK0-BANK7. More or fewer banks may be included in the memory array **118** of other embodiments. Each memory bank includes a plurality of word lines WL, a plurality of bit lines BL, and a plurality of memory cells MC arranged at intersections of the plurality of word lines WL and the plurality of bit line BL. The selection of the word line WL is performed by a row decoder **108** and the selection of the bit lines BL is performed by a column decoder **110**. In the embodiment of FIG. **1**, the row decoder **108** includes a respective row decoder for each memory bank and the column decoder **110** includes a respective column decoder for each memory bank. The bit lines BL are coupled to a respective sense amplifier (SAMP). Read data from the bit line BL is amplified by the sense amplifier SAMP, and transferred to read/write amplifiers **120** over complementary local data lines (LIOT/B), transfer gate (TG), and complementary main data lines (MIOT/B) which are coupled to an error correction code (ECC) control circuit **120**. Conversely, write data outputted from the ECC control circuit **120** is transferred to the sense amplifier SAMP over the complementary main data lines MIOT/B, the transfer gate TG, and the complementary local data lines LIOT/B, and written in the memory cell MC coupled to the bit line BL.

(25) The semiconductor device **100** may employ a plurality of external terminals that include command and address (C/A) terminals coupled to a command and address bus to receive commands and addresses, and a CS signal, clock terminals to receive clocks CK and/ $\overline{\text{CK}}$, data terminals DQ to provide data, and power supply terminals to receive power supply potentials VDD, VSS, VDDQ, and VSSQ.

(26) The clock terminals are supplied with external clocks CK and/ $\overline{\text{CK}}$ that are provided to an input circuit **112**. The external clocks may be complementary. The input circuit **112** generates an internal clock ICLK based on the CK and/ $\overline{\text{CK}}$ clocks. The ICLK clock is provided to the command decoder **106** and to an internal clock generator **114**. The internal clock generator **114** provides various internal clocks LCLK based on the ICLK clock. The LCLK clocks may be used for timing operation of various internal circuits. The internal data clocks LCLK are provided to the input/output circuit **122** to time operation of circuits included in the input/output circuit **122**, for example, to data receivers to time the receipt of write data.

(27) The C/A terminals may be supplied with memory addresses. In some embodiments, the memory addresses may be provided by a controller, such as controller **101**. The memory addresses supplied to the C/A terminals are transferred, via a command/address input circuit **102**, to an address decoder **104**. The address decoder **104** receives the address and supplies a decoded row address XADD to the row decoder **108** and supplies a decoded column address YADD to the column decoder **110**. The address decoder **104** may also supply a decoded bank address BADD, which may indicate the bank of the memory array **118** containing the decoded row address XADD and column address YADD. The C/A terminals may be supplied with commands. In some embodiments, the memory addresses may be provided by the controller **101**. Examples of commands include timing commands for controlling the timing of various operations, access commands for accessing the memory, such as read commands for performing read operations and write commands for performing write operations, as well as other commands and operations. The access commands may be associated with one or more row address XADD, column address YADD, and bank address BADD to indicate the memory cell(s) to be accessed.

(28) The commands may be provided as internal command signals to a command decoder **106** via the command/address input circuit **102**. The command decoder **106** includes circuits to decode the internal command signals to generate various internal signals and commands for performing operations. For example, the command decoder **106** may provide a row command signal to select a word line and a column command signal to select a bit line.

(29) The device **100** may receive an access command which is a read command. When a read

command is received, and a bank address, a row address and a column address are timely supplied with the read command, a code word including read data and read parity bits is read from memory cells in the memory array **118** corresponding to the row address and column address. The read command is received by the command decoder **106**, which provides internal commands so that read data from the memory array **118** is provided to the ECC control circuit **120**. The ECC control circuit **120** may use the parity bits in the code word to determine if the code word includes any errors, and if any errors are detected, may correct them to generate a corrected code word (e.g., by changing a state of the identified bit(s) which are in error). The corrected code word (without the parity bits) is output to outside the device **100** from the data terminals DQ via the input/output circuit **122**.

(30) The device **100** may receive an access command which is a write command. When the write command is received, and a bank address, a row address, and a column address are timely supplied as part of the write operation, and write data is supplied through the DQ terminals to the ECC control circuit **120**. The write data supplied to the data terminals DQ is written to a memory cells in the memory array **118** corresponding to the row address and column address. The write command is received by the command decoder **106**, which provides internal commands so that the write data is received by data receivers in the input/output circuit **122**. Write clocks may also be provided to the external clock terminals for timing the receipt of the write data by the data receivers of the input/output circuit **122**. The write data is supplied via the input/output circuit **122** to the ECC control circuit **120**. The ECC control circuit **120** may generate a number of parity bits based on the write data, and the write data and the parity bits may be provided as a code word to the memory array **118** to be written into the memory cells MC.

(31) The ECC control circuit **120** may be used to ensure the fidelity of the data read from a particular group of memory cells to the data written to that group of memory cells. The device **100** may include a number of different ECC control circuits **120**, each of which is responsible for a different portion of the memory cells MC of the memory array **118**. For example, there may be one or more ECC control circuits **120** for each bank of the memory array **118**.

(32) Each ECC control circuit **120** may receive a code word which includes a certain number of data bits and a certain number of parity bits (e.g., 128 data bits and 8 parity bits). The data bits may be provided from either from the IO circuit **122** or the memory array **118** depending on if it is a read or write operation, and the ECC control circuit **120** uses the parity bits (e.g., ECC information) to locate and correct potential errors in the code word. For example, as part of a write operation an ECC control circuit **120** may receive 128 bits of data from the IO circuit **122** and may generate 8 parity bits based on those 128 data bits to form a code word with 136 total bits. The code word may be written to the memory array **118**. In some embodiments, the data bits may be written to column planes configured to store the data and the eight bits of ECC information (e.g., parity bits) may be written to a column plane configured to store the ECC information. As part of an example read operation, the ECC control circuit **120** may receive a code word with 128 data bits and 8 parity bits from the memory cell array **118**. In some embodiments, the data bits may be retrieved from the data column planes and the ECC information may be retrieved from the ECC column plane. The ECC control circuit **120** may generate new parity bits from the 128 data bits, and then compare the new parity bits to the read parity bits in the code word to generate syndrome bits. The syndrome bits may be used to locate errors in the code word and the ECC control circuit **120** and may correct them if any are found before supplying the data bits to the IO circuit **122**. While various embodiments may be discussed with reference to ECC circuits which use code words where eight parity bits are used to find one error in 128 data bits, it should be understood that these are for explanatory purposes only, and that other numbers of data bits, error bits, and parity bits may be used in other example embodiments.

(33) During a read operation, the ECC control circuit **120** checks the code word and locates and corrects any errors before providing the corrected code word to the IO circuit **122**. Accordingly, if

there was an error, it may remain in the code word stored in the memory array **118** since the correction is made between the memory array **118** and the IO circuit **122**. The memory device **100** includes error check and scrub (ECS) circuit **130**, which is used to correct errors stored within the memory array **118**. Over the course of an ECS cycle, the ECS circuit **130** generates a sequence of addresses (e.g., a sequence of row addresses and a sequence of column addresses), which cover all the code words stored in the memory array **118**. For each address in the sequence, the ECS circuit **130** operates the address decoder **104** and command decoder **106** to perform a read operation on the memory cells of that address, and then instead of providing the corrected code word off the device **100** as in a normal read, the corrected code word is written back to the memory array **118**. In some embodiments, only a portion of the code word (e.g., only the data bits or only the data bit changed by the correction) may be written back to overwrite the previous code word. By cycling through a sequence of addresses which includes all code words, the ECS circuit **130** may perform an ECS cycle to repair the errors in the memory cells array **118**.

(34) The ECS circuit **130** may perform an ECS cycle based on a manual or auto mode. In a manual mode, the ECS circuit **130** may receive a command (e.g., a multi-purpose command or MPC) and may perform an ECS operation responsive to that command. In an auto mode, the ECS circuit **130** may use internal logic and timing to carry out ECS operation. For example, the ECS circuit **130** may perform ECS operations during refresh operations. The ECS circuit **130** may have a specified time over which to complete the sequence of addresses (e.g., to perform the ECS cycle). For example, the memory device **100** may specify 12, 24, or 48 hours to complete a sequence of ECS operations which includes all code words in the memory array **118**. The ECS circuit **130** may perform a read, correct, and write ECS operation on each address in the sequence such that the sequence is completed over the course of the specified period. Accordingly, the average timing between individual ECS operations may be specified by the total number of code words in the memory array **118** and the length of time in which the ECS cycle should be performed.

(35) The ECS circuit **130** collects information about the errors which are located. The device **100** may record per-row ECS information (e.g., per-row error information) when a per-row ECS mode is enabled. The per-row ECS mode may be enabled by a setting in the mode register **132**. For example, each row of the memory array **118** may include a number of code words. When the pRECS mode is enabled, the ECS circuit **130** may generate a count for each row which indicates how many code words on that row included an error during the most recent ECS cycle. For example, the ECS circuit **130** may include a per-row ECS register. During the ECS cycle, the ECS circuit **130** may generate a row address, and then perform an ECS operation on each code word of that row address (e.g., by generating column addresses in sequence) before moving on to a next row. During that process, if an error is detected and a pRECS mode is enabled, the value in the per-row ECS register may be updated (e.g., incremented). Once all the code words along the current row are checked (e.g., when the column address wraps back around to an initial value), the value in the per-row ECS register may be stored, and the per-row ECS register reset to an initial value (e.g., 0).

(36) In some embodiments, there may be multiple per-row ECS registers, such as a per-row ECS register for each bank. Multiple per-row ECS registers may be used because ECS operations may be dispersed between different banks (e.g., an ECS operation in a first bank may be followed by an ECS operation in a second bank before a second ECS operation in the first bank occurs). Accordingly, each per-row ECS register may track a number of errors along a current row for each bank.

(37) In some embodiments, the ECS circuit **130** may store the per-row ECS information on the row associated with that per-row ECS information. For example, a set of memory cells along the row may be set aside to be used as storage for per-row ECS information. In some embodiments, which memory cells are set aside may be a setting of the mode register **132**. For example, a column select (CS) signal value may specify the bit lines which intersect the set aside memory cells along each

row, and that value of the CS signal may be stored in the mode register **132**. In some embodiments, the bit lines may be located in column planes and/or associated with column selects in column planes configured to store metadata. Other methods of designating memory cells along the rows to store the per-row ECS information may be used in other examples.

(38) In some embodiments, the per-row ECS information stored in the memory array for each row may include recent error information. The recent error information may include the error information (e.g., the number of errors and/or number of code words with errors) from the most recent ECS cycle as well as the error information from a certain number of previous ECS cycles (e.g., the most recent five ECS cycles, all of the ECS cycles performed within the last three days). Thus, in some embodiments, each row may store multiple per-row ECS information values (e.g., multiple values indicating the number of code words with errors).

(39) Optionally, the device **100** may also generate overall ECS information such as overall readouts. In some embodiments, such overall ECS information may be provided to the mode register **132**. For example, overall ECS information may include a total number of errors corrected in a portion of the device **100**, a row with a maximum number of errors, and/or a number of errors in the row with the maximum number of errors. Examples of overall ECS information are described in U.S. patent application Ser. No. 17/730,396 filed on Apr. 27, 2022, which is incorporated herein by reference for any purpose.

(40) In some embodiments, the device **100** may store baseline error information. For example, the baseline error information may include per-row error information, such as the number of code words with errors, a number of bits with errors, and/or other error information. The baseline error information may have been acquired during testing of the device **100**, which may have occurred prior to shipping the device **100** from the manufacturer and/or prior to shipping the device **100** to an end user. In some embodiments, the baseline error information may be stored in a fuse array **134**. The fuse array **134** may include multiple fuses or antifuses that can be set to store the baseline information. While shown as a separate component in FIG. **1**, in other embodiments, the fuse array **134** may be included in another component of device **100**. For example, the fuse array **134** may be included in the mode register **132** and/or a global redundancy management circuit (not shown). In some embodiments, the fuse array **134** may include additional information such as values to be written to the mode register **132** and/or mapping information for redundant rows (e.g., redundant rows used to replace “regular” word lines after a PPR operation).

(41) In some embodiments, the baseline information may be copied from the fuse array **134** and stored in the memory array **118**. In some embodiments, the fuse array **134** may be encoded with a number of errors in a row, a number of code words with errors in a row, and the row address. In some embodiments, the fuse array **134** may be encoded with additional information to facilitate writing the error information to the correct rows of the memory array **118**. In some embodiments, the copying of the baseline information to the memory array **118** may be facilitated by a state machine implemented, at least in part, by a command decoder. In some embodiments, the state machine may be included in each bank (not shown). In some embodiments, the command decoder **106** may decode the content of the fuse array **134** to extract the error information and addresses to be written to the memory array **118**. In some embodiments, the command decoder **106** may include a command decoder **136** (“array codec”) specific for decoding the fuse array **134**. In some embodiments, the array codec **136** may be a separate component from the command decoder **106**. In some embodiments, the baseline information may include per-row information and the baseline information may be stored in memory cells along the applicable row. The baseline information may be stored in a portion of at least one column plane configured to store metadata. However, in other embodiments, the baseline information may be stored in other regions of the memory array (e.g., a column plane including redundant columns, column plane dedicated to per-row ECS data). In some embodiments, the baseline information may be copied from the fuse array **134** to the memory array **118** during power-up of the device **100**.

(42) In some embodiments, the controller **101** may read the ECS data and/or baseline information from the memory array **118**. In some embodiments, the ECS data and/or baseline data stored in the memory array **118** and/or fuse array **134** may not be accessible to the controller **101**. In some embodiments, certain ECS data, such as the overall ECS data that is provided to the mode register **132** may be accessible to the controller **101**. In some applications, restricting access to per-row ECS information and/or other error information may reduce the risk of weaknesses in the device **100** from being exploited. In some embodiments, the level of access the controller **101** has to the error information may be set by programming a fuse array of the mode register **132**.

(43) In some embodiments, the ECS circuit **130** may analyze error information and make a post-package repair (PPR) recommendation. That is, the ECS circuit **130** may provide a signal to indicate that a row should be remapped to a redundant row to repair the row. In some embodiments, the ECS circuit **130** may analyze the per-row ECS information and/or the baseline information to make the PPR recommendations. For example, if the most recent ECS information indicates a number of code words with errors or a total number of errors along a row is equal to or greater than a threshold value, the ECS circuit **130** may provide a signal indicating the row should be repaired. In another example, if an increase in errors between a number of errors in a most recent count and a previous count is equal to or greater than a threshold value, the ECS circuit **130** may recommend PPR for the row. In a further example, if an increase in errors between a number of errors in a most recent count and a count from the baseline information is equal to or greater than a threshold value, the ECS circuit **130** may recommend PPR for the row. Other analysis of the recent and baseline error information are also possible. For example, if an average number of errors in the recent error information is greater than the baseline information, the ECS circuit **130** may recommend PPR for the row. In another example, if each error count for a row of a consecutive number of recent ECS cycles are each greater than the error count of the previous ECS cycle, the ECS circuit **130** may recommend PPR for the row. In some embodiments, the technique and/or threshold values used by the ECS circuit **130** to determine whether a PPR is recommended may be programmed into the device **100**, for example, by programming the mode register **132**.

(44) In some embodiments, the ECS circuit **130** may provide the PPR recommendation by providing the row address of the row to be repaired to a register of the mode register **132**. The controller **101** may periodically check the mode register **132** for PPR recommendations. In some embodiments, the ECS circuit **130** and/or the mode register **132** may provide an active alert signal to an external pin that notifies the controller **101** that the mode register **132** should be checked for a PPR recommendation. In some embodiments, such as the one shown in FIG. 1, the external pin may be a dedicated alert pin. In other embodiments, the external pin may be a multi-purpose pin or a sideband bus. In some embodiments, the ECS circuit **130** may provide the recommendation as soon as it determines a row should be repaired. In other embodiments, the ECS circuit **130** may provide a recommendation or multiple recommendations after the ECS cycle has been completed.

(45) The controller **101** may issue a mode register read command (either periodically or responsive to an active signal on an external pin) to the device **100**. In some embodiments the mode register read command may indicate a register within the mode register **132** that stores the PPR recommendation. The PPR recommendation provided from the mode register **132** to the controller **101** may include a row address of the row (or row addresses of rows) that the ECS circuit **130** has determined should be repaired. In some embodiments, the controller **101** may issue a PPR command to the device **100** to cause the device **100** to perform a PPR operation to repair the row indicated by the row address.

(46) The device **100** may also receive commands causing it to carry out one or more refresh operations as part of a self-refresh mode. In some embodiments, the self-refresh mode command may be externally issued to the memory device **100**. In some embodiments, the self-refresh mode command may be periodically generated by a component of the device. In some embodiments, when an external signal indicates a self-refresh entry command, the refresh signal AREF may also

be activated. The refresh signal AREF may be a pulse signal which is activated when the command decoder **106** receives a signal which indicates entry to the self-refresh mode. The refresh signal AREF may be activated once immediately after command input, and thereafter may be cyclically activated at desired internal timing. The refresh signal AREF may be used to control the timing of refresh operations during the self-refresh mode. Thus, refresh operations may continue automatically. A self-refresh exit command may cause the automatic activation of the refresh signal AREF to stop and return to an IDLE state. The refresh signal AREF is supplied to the refresh control circuit **116**. The refresh control circuit **116** supplies a refresh row address RXADD to the row decoder **108**, which may refresh one or more wordlines WL indicated by the refresh row address RXADD.

(47) The power supply terminals are supplied with power supply potentials VDD and VSS. The power supply potentials VDD and VSS are supplied to an internal voltage generator circuit **124**. The internal voltage generator circuit **124** generates various internal potentials VPP, VOD, VARY, VPERI, and the like based on the power supply potentials VDD and VSS supplied to the power supply terminals. The internal potential VPP is mainly used in the row decoder **108**, the internal potentials VOD and VARY are mainly used in the sense amplifiers SAMP included in the memory array **118**, and the internal potential VPERI is used in many peripheral circuit blocks.

(48) The power supply terminals are also supplied with power supply potentials VDDQ and VSSQ. The power supply potentials VDDQ and VSSQ are supplied to the input/output circuit **122**. The power supply potentials VDDQ and VSSQ supplied to the power supply terminals may be the same potentials as the power supply potentials VDD and VSS supplied to the power supply terminals in an embodiment of the disclosure. The power supply potentials VDDQ and VSSQ supplied to the power supply terminals may be different potentials from the power supply potentials VDD and VSS supplied to the power supply terminals in another embodiment of the disclosure. The power supply potentials VDDQ and VSSQ supplied to the power supply terminals are used for the input/output circuit **122** so that power supply noise generated by the input/output circuit **122** does not propagate to the other circuit blocks.

(49) FIG. **2** is a block diagram of a memory system according to some embodiments of the present disclosure. The system **200** includes a controller **202** and a memory **204**. The memory **204** may be included in device **100** in some embodiments. In some embodiments, the controller **202** may be included in controller **101**. The memory system **200** illustrates a memory which generates and store per-row ECS information and an example controller which may be used to retrieve the per-row ECS information (if such permission is granted).

(50) The memory **204** includes an ECS circuit **214** which manages ECS operations. In some embodiments, the ECS circuit **214** may be included in ECS circuit **130**. The ECS circuit **214** includes an address generator **220** which over the course of an ECS cycle generates addresses for each code word in the memory array **210**. In some embodiments, the memory array **210** may be included in memory array **118**. For example, the ECS circuit **214** may provide a row and column address (an ECS address), and then update (e.g., increment) the column address, and continue until all column addresses along the row have been provided (e.g., the column address wraps back to an initial value), the ECS circuit **214** may then update (e.g., increment) the row address and repeat the process. The ECS circuit may continue generating ECS addresses until addresses associated with all code words have been provided over the course of an ECS cycle. The current ECS address may be provided to row and column decoders **212**, along with commands (such as read-modify-write commands, not shown) such that for each address, the code word associated with the current address is read out to the ECC circuit **216**, corrected (if necessary), and the corrected code word written back to the location specified by the current address. The ECS address may then be updated. The ECC circuit **216** may be included in ECC circuit **120** in some embodiments.

(51) The ECC circuit **216** may provide an error detected signal ErrDet to the ECS circuit **214**. The signal ErrDet may be active each time the ECC circuit **216** detects an error in the code word read

from the memory array **210** as part of an ECS operation. The ECS circuit **214** includes a per-row ECS (pRECS) register **222**. When a pRECS mode is enabled, the pRECS register **222** may change (e.g., increment) a stored count value each time the ErrDet signal is active, and reset to an initial value (e.g., 0) each time the address generator **220** indicates that a column address has wrapped back to a new value (e.g., each time a final column address along a row has been provided). For example, after the final column address has been generated, the address generator **220** may provide a column wrap signal Col_Wrap, and update the row address to a new value. Responsive to the signal Col_Wrap, the pRECS register **222** may write its current value to memory cells of the memory array **210** and reset the stored count value (e.g., to 0). For example, the count value in the pRECS register **222** may be written to memory cells along the current row (e.g., before the row address is updated responsive to Col_Wrap). In this manner, the pRECS value for each row may represent a number of code words along that row which contained an error (e.g., a number of times ErrDet was active for each value of the row address portion of the ECS address). In some embodiments, each row may store multiple pRECS values, where each pRECS value is a value from a different ECS cycle. In some embodiments, the pRECS values are from sequential ECS cycles. In some embodiments, there may be a pRECS register **222** for each bank, and each bank may separately generate row and column addresses for ECS operations.

(52) The memory array **210** may be organized in rows and columns. Each row may be specified by a row address (e.g., XADD) which specifies a word line. For example, the address generator **220** may generate a first row address XADD, and responsive to that, the row decoder **212** may activate a first word line (e.g., WL.sub.0) of the memory array **210**. The columns along the activated row are accessed by a column address, which is decoded to activated column select signals CS. While each column select signal is shown with a single bit line, each CS signal may activate multiple individual bit lines. For example, a given CS signal may activate 8 bit lines in each of 17 column planes of the memory array, for a total of 136 active bit lines, and 136 bits (128 data bits and 8 parity bits). In some embodiments, additional bit lines may be activated, such as when the memory array **210** is enabled to store metadata that is protected by the ECC circuit **216** (e.g., 128 data bits, 1-8 metadata bits, and 8 parity bits). Accordingly, the address generator **220** may generate a row address, then as part of a first ECS operation provide a first column select signal, then as part of a second ECS operation provide a second column select signal and so forth.

(53) In some embodiments, the per-row ECS information may be saved in the memory array **210**. In some embodiments, the per-row ECS information may be saved in memory cells along the row which the per-row ECS information is associated with. For example, one or more values of the column select signal (and their corresponding memory cells) may be set aside for storing per-row ECS information. The mode register **218** may be used to designate a value pRECS-CS, a value (or values) of the CS signal set aside for per-row ECS information. However, in some embodiments, one or more of the CS signals may be shared between per-row ECS information and metadata. For example, as noted, each CS signal may active eight bit lines per column plane. However, not all eight bits in all of the column planes may be needed based on the amount of metadata desired. Thus, the unused or “leftover” bits associated with the CS signals for metadata may be used for storing per-row ECS information. Thus, some of the CS signals may be the same (e.g., shared) between the bit lines associated with metadata and the bit lines associated with error information.

(54) When the address generator **220** is generating ECS addresses, the address in pRECS-CS may be skipped, since it does not contain a code word with correctable data. For example, if pRECS-CS designates a column select value CS.sub.M, then the address generator **220** may set a row address and provide column addresses CS.sub.0 to CS.sub.M-1, but not provide CS.sub.M. However, in other embodiments, columns including the pRECS values and/or baseline information stored in the rows may also be included in one or more code words and checked for errors. The address generator **220** may then provide the signal Col_Wrap when the column address is updated as it may return to a value of CS.sub.0. Responsive to the signal Col_Wrap, the ECS circuit **214** may provide

the value of the pRECS register **222** as data along with the row address and the column address which activates the value in the pRECS-CS (e.g., CS.sub.M) and a write command to write the value in the pRECS register **222** to the memory cells accessed by the value in the pRECS-CS register.

(55) In some embodiments, the mode register **218** may be included in mode register **132**. The mode register **218** may store various values which are related to the ECS operation. For example, the present disclosure describes an EC register and an EpRC register, although different, more, or fewer registers are possible in other examples. Each register may store various values associated with a respective counter in the ECS circuit **214**. For example, the EC register may represent a number of code words with errors which were detected in the previous ECS cycle. The EC register may represent a raw count value, or may represent a range in which the count value falls. For example, a first value of the EC register may represent that the count is below the threshold, a second value of the EC register may represent that the count is between the threshold and a first count value, a third value of the EC register may represent that the count is between the first count value and a second count value etc. The EpRC register may store both a count value and a row address associated with the row which contained the most code word errors.

(56) The mode register **218** includes a per-row ECS enable register pRECS-En. The register pRECS-En stores a value which indicates if the pRECS mode is enabled for the memory **204**. If the pRECS-En register stores an inactive pRECS-En value, then the pRECS mode may be disabled, and the memory **204** may not collect pRECS information. For example, the pRECS register **222** may not respond to the ErrDet signal. In some embodiments, even the pRECS register **222** contains an inactive value, other ECS information, such as EC and EpRC may still be collected. In some embodiments, different ECS information as well as the ECS functionality may be separately enabled by one or more respective registers (not shown) of the mode register **218**. In some embodiments, a controller **202** may set a value in the pRECS-En register to determine if pRECS information is collected or not. In some embodiments, the value of pRECS-En may be a memory **204** setting (e.g., programmed in a fuse array **224**) which may have a value which is independent of the controller **202**.

(57) The mode register **218** may also include a pRECS address register, pRECS-CS, which specifies which memory cells are used to store the per-row ECS information. For example, the pRECS-CS register may store a value of the CS signal which specifies memory cells which have been designated for use for storing pRECS. Other information used for designating memory cells may be used in other example embodiments. In some embodiments, the pRECS-CS may store a value which is programmed in the fuse array **224**. For example, the pRECS-CS value may be programmed into the fuse array **224** and then loaded into the pRECS-CS register of the mode register **218**. In this way, once programmed the pRECS address may be programmed into the memory **204** in a manner which is a permanent setting of the memory **204**. In some embodiments, the fuse array **224** may store additional information, such as baseline error information and/or may include multiple fuse arrays.

(58) The per-row error information may further include baseline information. For example, the baseline information may include pRECS values from an initial ECS cycle during testing of the memory **204** (e.g., by the manufacturer). In some embodiments, the baseline pRECS values may be stored in a similar manner to the recent pRECS values (e.g., from the most recent ECS cycles performed by the memory **204**). For example, the baseline information may be stored in memory cells along each row associated with CS values associated with pRECS data and/or the baseline information may be stored in “leftover” memory cells of metadata regions. In some embodiments, the baseline information may have been copied to the memory array **210** from a fuse array (e.g., fuse array **134** and/or fuse array **224**). Alternatively, in some embodiments, the baseline information may remain in the fuse array and retrieved from the fuse array by the ECS circuit **214**.

(59) The ECS circuit **214** may include a PPR recommendation circuit **226** which may analyze error

information and make a PPR recommendation. The PPR recommendation circuit **226** may provide a signal to indicate that a row should be remapped to a redundant row to repair the row. In some embodiments, PPR recommendation circuit **226** may analyze the pRECS values and/or the baseline information to make the PPR recommendations. The pRECS values for the recent and/or baseline error information may be received directly from the memory array **210** and/or the pRECS register **222**. In some embodiments, the pRECS values for the baseline error information may be received from a fuse array.

(60) The PPR recommendation circuit **226** may provide the PPR recommendation by providing the row address of the row to be repaired to a register PPR-ADD of the mode register **218**. The address may be received from the address generator **220** in some embodiments. The controller **202** may periodically check the PPR-ADD register for PPR recommendation(s). In some embodiments, the PPR recommendation circuit **226** and/or the mode register **218** may provide an active alert signal to an external pin that notifies the controller **202** that the PPR-ADD should be checked for a PPR recommendation. In some embodiments, the PPR recommendation circuit **226** may provide the recommendation as soon as it determines a row should be repaired. For example, it may analyze data associated with each row as it becomes available from the pRECS register **222** during the ECS operation. In other embodiments, the PPR recommendation circuit **226** may provide a recommendation or multiple recommendations after the ECS cycle has been completed. In some embodiments, the PPR recommendation circuit **226** may provide recommendations as soon as it determines a row should be repaired, but the alert signal may not be activated until the end of the ECS operation. In some embodiments, the register PPR-ADD may store multiple row addresses. This may reduce the risk that a row address associated with a PPR recommendation will be overwritten by a new recommendation before being retrieved by the controller **202**.

(61) The PPR recommendation circuit **226** may determine a row should be repaired by any suitable technique. For example, in some embodiments, a PPR recommendation may be made when a number of code words with errors or a total number of errors along a row is equal to or greater than a threshold value or if an increase in errors between a number of errors in a most recent count and a previous count is equal to or greater than a threshold value. In another example, if an increase in errors between a number of errors in a most recent count and a count from the baseline information is equal to or greater than a threshold value, a PPR recommendation may be made. Other analysis of the recent and baseline error information including the pRECS values are also possible. For example, if an average number of errors in the recent error information is greater than the baseline information or if each error count for a row of a consecutive number of recent ECS cycles are each greater than the error count of the previous ECS cycle, a PPR recommendation may be made. In some embodiments, the technique and/or threshold values used by the PPR recommendation circuit **226** to determine when to make a PPR recommendation may be programmed into the mode register **218** and/or fuses **224**.

(62) The controller **202** may issue a mode register read command (either periodically or responsive to an active signal on an external pin) to the memory **204** in order to read the register PPR-ADD. In some embodiments, the controller **202** may issue a PPR command to the memory **204** to perform a PPR operation to repair the row indicated by the row address(es) read from the register PPR-ADD.

(63) In some embodiments, the controller **202** may read the recent and/or baseline ECS information from the memory **204**. In some embodiments, the recent and/or baseline ECS information may not be accessible to the controller **202**. In some embodiments, certain ECS data, such as the overall ECS data such as EC and EpRC stored in mode register **218** may be accessible to the controller **202**. Further, in some embodiments, such as when pRECS-En is enabled, write commands to memory cells corresponding to the per-row ECS data (recent and/or baseline) may be inhibited. This may prevent unintentional overwriting of the ECS data.

(64) FIG. 3 is a block diagram of a row of a memory array according to embodiments of the present disclosure. The row **300** may be included in a memory array, such as memory array **118** and/or

memory array **210**. In some embodiments, row **300** may be included in a bank of a memory array. Row **300** may include multiple memory cells for storing data. A portion of the memory cells may store user data (e.g., data provided by a controller or other external device) as indicated by block **302**. Other memory cells may store other types of data such as metadata as indicated by block **304** and error information indicated by block **306** for the row. Some memory cells may include recent error information and some memory cells may include baseline error information. In the example shown in FIG. **3**, the memory cells may store multiple values ECS_0, ECS_1, ECS_2, ECS_3 related to recent error information (e.g., pRECS values from different ECS cycles) as indicated by blocks **308**, **310**, **312**, and **314**. In some embodiments, each value may be six bits, and each block **308**, **310**, **312**, and **314** includes six memory cells. However, other numbers of bits (e.g., four, eight) may be used depending on what error information is stored for the row. While four values are shown in FIG. **3**, in other embodiments, more or fewer values corresponding to recent error information may be included in the row **300**. The baseline error information indicated by block **316** may include a pRECS value from an ECS cycle and/or other error detection operation performed. (65) In some embodiments, different column select signals (CS) may be associated with the different blocks of memory cells (e.g., different CS assigned to data block **302** and metadata block **304**). However, in some embodiments, the same column select signals may be assigned to different blocks. For example, the same CS may be assigned to metadata block **304** and error information block **306**, but different column planes may store the metadata block **304** and error information block **306**. That is, the columns planes storing the metadata and the column planes storing the error information may be mutually exclusive.

(66) It is noted that the blocks representing memory cells and their contents shown in row **300** are for explanatory purposes only, and the sizes of the blocks do not necessarily accurately represent the relative number of memory cells in each block. Further, the locations of the different types of data in the row **300** are not limited to the arrangement shown in FIG. **3**.

(67) FIG. **4** is a block diagram of a memory according to some embodiments of the present disclosure. The memory **404** may be included in device **100** and/or memory **204** in some embodiments. The memory **404** generates and store per-row ECS information including recent information and baseline information. Further, the memory **404** may store baseline information in a fuse array and load the baseline information into the memory array **410**. In some embodiments, the memory array **410** may be included in memory array **118** and/or memory array **210**.

(68) The memory **404** includes a fuse array **524** which may store the baseline error information for the memory array **410** on a per-row basis. In some embodiments, the fuse array maybe included in fuse array **134** and/or fuse array **224**. In some embodiments, the per-row baseline information may be stored in the fuse array **424** as a key-value pair. The key-value pair may encode the row address and the number of code words with errors (e.g., the pRECS value). Typically, during testing, memory arrays, such as memory array **410**, have few rows that include errors (e.g., defective memory cells). For example, less than 0.1% of rows may have errors for some memory types. Thus, in some embodiments, the fuse array **424** may only include baseline error information (e.g., the key-value pair) for rows with errors instead of all rows where most of the rows would be associated with a pRECS value of zero (e.g., no errors in the row). In some embodiments, the fuse array **424** may be included in a fuse array used for writing to unused redundant rows.

(69) The memory **404** may include a fuse array command decoder **414** for decoding the baseline information stored in the fuse array **424**. In some embodiments, the fuse array command decoder **414** may be included in command decoder **106** and/or array command decoder **136**. The fuse array command decoder **414** may decode the key-value pairs as well as breaks in information related to rows with no baseline errors, banks, and the start and end of the baseline information in the fuse array **424**. The fuse array command decoder **414** may send the decoded key-value pair (e.g., the address and the baseline pRECS value or other error count information) to a state machine **416**. In some embodiments, each bank of the memory array **410** have a separate state machine **416**, and the

fuse array command decoder **414** may provide the decoded baseline information to the appropriate bank.

(70) The state machine **416** may multiplex the row address into the row latches of the row decoder of the row and column decoders **412** and the baseline pRECS value to the appropriate main I/O lines for writing baseline pRECS value to the row associated with the row address. The state machine **416** may generate an activation signal ACT associated with the row address and a write signal associated with the baseline pRECS value. In some embodiments, writing the baseline information to the row may also trigger an ECC operation performed by an ECC circuit **418**. In some embodiments, the ECC circuit **418** may be included in ECC circuit **120** and/or ECC circuit **216**. The ECC circuit **418** may generate parity bits associated with the baseline pRECS value. Both the baseline pRECS value and the parity bits may be written to the array **410**. For rows not included in the fuse array **424**, the fuse array command decoder **414** and/or state machine **416** may cause a baseline pRECS value of zero to be written to the row.

(71) In some embodiments, the loading of the baseline information stored in the fuse array **424** to the memory array **410** may be initiated during power up/initializing of the memory **404**. In some embodiments, the loading of the baseline information may be triggered by enabling per-row ECS data storage (e.g., by programming an appropriate value in a mode register).

(72) FIG. 5 shows an example grammar for programming the fuse array according to embodiments of the present disclosure. The grammar shown in FIG. 5 may be used to program a fuse array to store pre-row baseline error information, such as fuse array **424** and/or fuse array **134**. Seventeen bits may be associated with the row address and four bits may be associated with the number of code words with errors (e.g., pRECS value). However, in other embodiments, other numbers of bits may be used to store the row address and/or pRECS. For example, six bits may be used to store a pRECS value. The number of bits used to store the pRECS value may be based, at least in part, on a number of code words in each word. In some embodiments, the number of bits used to store the pRECS value may be based, at least in part, on a threshold value for the number of code words with errors tolerated for a row. For example, while a row may include sixty-four code words (which would require six bits to store a pRECS value), if a threshold value for repairing the row is lower than sixty-four, fewer bits may be used to store the pRECS value because the row may be replaced prior to reaching an error in every single code word.

(73) In some embodiments, such as the one shown in FIG. 5, row addresses may also be used to encode commands. When only baseline error information is stored for rows with a non-zero value of pRECS, any row address stored in the fuse array associated with a zero value may be understood by a decoder (e.g., decoder **414** and/or **136**) to be a command or other information rather than a row address. In the example shown in FIG. 5, row addresses corresponding to row 34 associated with a zero pRECS value indicates a start command that causes the decoder to start decoding the data from the fuse array. Row address 35 with a zero pRECS value indicates the start of baseline information associated with a bank. Row addresses 0-32 associated with zero pRECS values may be used to encode the bank addresses. Row address 36 with a zero pRECS value indicates the end baseline information associated with the bank. Finally, row address 37 with a zero pRECS value indicates the end of the baseline information in the fuse array. The remaining addresses associated with non-zero pRECS values indicate the rows for the current bank and their associated pRECS values.

(74) The fuse array may further store baseline error information for redundant rows. In some embodiments, this baseline information may also be loaded into the memory array. In the example shown in FIG. 5, Row address 38 with a zero pRECS value indicates the start of baseline information associated with the redundant rows and row address 39 with a zero pRECS value indicates the end baseline information associated with the redundant rows. The redundant rows may be referred to as PPR rows because they are mapped via execution of a PPR operation. The remaining addresses associated with non-zero pRECS values indicate the redundant rows and their

associated pRECS values.

(75) The addresses used for commands and the commands associated with said addresses are provided merely as examples. Other addresses may be used and/or the addresses may be associated with different commands in other embodiments. Further, additional or fewer commands may be encoded in other embodiments.

(76) FIG. 6 shows an example programming of a fuse array according to embodiments of the present disclosure. The example programming of the fuse array shown in FIG. 6 uses the example grammar shown in FIG. 5. As shown in the first line, an initial row address and pRECS value may be 34 and 0, respectively, to indicate to a command decoder (e.g., fuse array command decoder 414 and/or array command decoder 136) to begin an operation for loading baseline error information (e.g., pRECS values) from the fuse array to a memory array. Following the start command is a start bank command indicated by a row address of 35 and a pRECS value of 0. This indicates the start of baseline error information for a new bank. The bank address is provided after the start bank command. In the example shown in FIG. 6, the address is for BANK 0. Note that pRECS value is still zero for the bank address, thus allowing the decoder to interpret the address as a bank address rather than a row address.

(77) Following the bank address, row addresses and pRECS values are provided for rows in BANK0 that have code words with errors. The first row address is row 34 and has a pRECS value of 4. Note that row address 34 will not be confused for the start command because the pRECS value is a non-zero value. The next row in BANK0 with errors is the row corresponding to row 78, which has a pRECS value of seven. In the example shown in FIG. 6, only two rows in BANK0 had errors in their code words when the baseline error information was collected. However, more or fewer rows may have baseline error information in other examples. The command decoder may cause pRECS values of zeros to be written to memory cells assigned to the baseline error information for the remaining rows of BANK0.

(78) After the last row with baseline error information for BANK 0 has been provided from the fuse array, a stop bank command is provided with row address 36 and a pRECS value of 0. A new start bank command and a new bank address, BANK 6 in this example, are provided, followed by row addresses and pRECS values for rows in BANK 6. In the example shown, only two banks have rows with non-zero pRECS values. More or fewer banks may have baseline error information in other examples. Once the baseline error information has been provided from all of the banks, a final stop bank command is provided, and the stop command is issued by providing a row address of 37 with a pRECS value of zero. This indicates that all of the baseline information for the memory array has been provided, and loading of the baseline information into the array is complete.

(79) Optionally, baseline information for redundant rows may also be encoded in the fuse array. In the example shown in FIG. 6, another start command is issued followed by a start PPR command indicated by row address 38 with a pRECS value of 0. This informs the command decoder to decode the address differently as these addresses will be from redundant rows of a memory array rather than the “main” rows of the memory array. Similar to the “normal” operation, a start bank command and a bank address is issued (BANK 0 in this example). Redundant row addresses (e.g., PPR addresses) and associated pRECS values are then provided for the bank. In the example shown in FIG. 6, row address 12 and a pRECS value of 7 are provided. After all of the information for the rows of the bank are provided, a stop bank command is issued. While the example shown in FIG. 6 only includes one bank, in other examples, more or fewer banks may include baseline error information for redundant rows. Once all of the PPR baseline error information has been provided, a stop PPR command is issued by providing row address 39 with a pRECS value of zero. Finally, a stop command is issued to indicate all of the baseline information has been provided to the memory array.

(80) FIG. 7 is a flow chart of a method according to embodiments of the present disclosure. In

some embodiments, the method **700** shown in FIG. **7** may be performed in whole or in part by a memory device, such as device **100**, memory **204**, and/or memory **404**.

(81) At block **702**, “analyzing a value indicating a number of code words of a word line with errors of a memory array of a memory device” may be performed. In some embodiments, analyzing the value may include comparing the value to a threshold value. In some embodiments, analyzing the value may include comparing the value to baseline error information. In some embodiments, the baseline error information indicates a number of code words of the word line with errors during a test operation. In some embodiments, analyzing the value may include comparing the value to a plurality of values. In some embodiments, the plurality of values indicate numbers of code words of the word line with errors during previous error correction and scrub operations.

(82) At block **704**, based on the analyzing, “issuing a post-package repair (PPR) recommendation” may be performed. In some embodiments, the PPR recommendation comprises a row address corresponding to the word line to be repaired. In some embodiments, the PPR recommendation is issued when the value is equal to or greater than the threshold value. In some embodiments, the PPR recommendation is issued when the value is greater than the baseline error information. In some embodiments, the PPR recommendation is issued when the value is greater than a most recent one of the plurality of values or is greater than an average of the plurality of values.

(83) At block **706**, “storing the row address in a register of the memory device” may be performed. In some embodiments, the register may be stored in a mode register.

(84) Optionally method **700** may include block **708** where “providing an active alert signal to an external pin of the memory device” is performed.

(85) FIG. **8** is a flow chart of a method according to embodiments of the present disclosure. In some embodiments, the method **800** shown in FIG. **8** may be performed in whole or in part by a controller, such as controller **101** and/or controller **202**.

(86) At block **802**, “issuing, from a controller to a memory device, a mode register read command” may be performed. In some embodiments, the controller issues the mode register read command periodically. Optionally, method **800** further includes “receiving an active alert signal from the memory device” as indicated by block **801**. In some of these embodiments, the mode register read command is issued responsive to receiving the active alert signal.

(87) At block **804**, “receiving, from the memory device, a post package repair (PPR) recommendation” may be performed. In some embodiments, the PPR recommendation may include a row address stored in the mode register.

(88) At block **806**, “issuing, from the controller to the memory device, a PPR command” may be performed. The PPR command may cause a word line associated with the row address to be remapped to a redundant row of the memory device.

(89) Optionally method **800** may further include receiving per-row error information from the memory device and/or receiving per-row baseline error information from the memory device.

(90) FIG. **9** is a flow chart of a method according to embodiments of the present disclosure. In some embodiments, the method **900** shown in FIG. **9** may be performed in whole or in part by a memory device, such as device **100**, memory **204**, and/or memory **404**.

(91) At block **902**, “performing a first error correction and scrub operation on a memory array” may be performed.

(92) At block **904**, “determining a number of code words with errors for individual ones of a plurality of word lines of the memory array” may be performed.

(93) At block **906**, “writing a first plurality of values indicating the number of code words with errors for individual ones of the plurality of word lines to corresponding ones of the plurality of word lines” may be performed.

(94) At block **908**, “performing a second error correction and scrub operation on the memory array” may be performed.

(95) At block **910** “determining the number of code words with errors for individual ones of the

plurality of word lines of the memory array” may be performed.

(96) At block **912**, “writing a second plurality of values indicating the number of code words with errors for individual ones of the plurality of word lines to corresponding ones of the plurality of word lines” may be performed. The first plurality of values and the second plurality of values may be written to different memory cells of the plurality of word lines.

(97) In some embodiments, method **900** may further include “writing data to at least one of the plurality of word lines” as indicated by block **914**. The data may be written to different memory cells of the plurality of word lines than the first plurality of values and the second plurality of values.

(98) In some embodiments, method **900** may further include “writing metadata to at least one of the plurality of word lines” as indicated by block **916**. The metadata may be written to different memory cells of the plurality of word lines than the first plurality of values and the second plurality of values. In some embodiments, the metadata is written to a plurality of memory cells associated with a same column select as memory cells storing the first plurality of values, the second plurality of values, or both. In some embodiments, at least some of the metadata is written to a different column plane than a column plane including the first plurality of values, the second plurality of values, or both.

(99) In some embodiments, method **900** may further include “writing baseline error information to individual ones of the plurality of word lines” as indicated by block **918**. The baseline error information may be written to different memory cells of the plurality of word lines than memory cells storing the first plurality of values and the second plurality of values. In some embodiments, performing a testing operation on the memory array to acquire the baseline error information may be performed, and the baseline error information comprises the number of code words with errors for individual ones of the plurality of word lines of the memory array. In some embodiments, the testing operation is performed prior to the first error correction and scrub operation.

(100) FIG. **10** is a flow chart of a method according to embodiments of the present disclosure. In some embodiments, the method **1000** shown in FIG. **10** may be performed in whole or in part by a memory device, such as device **100**, memory **204**, and/or memory **404**.

(101) At block **1002** “reading data from a fuse array of a memory device” may be performed. In some embodiments, the data may be read from the fuse array by a command decoder.

(102) At block **1004**, “decoding a command, a bank address, a row address, and a value from the data with a command decoder” may be performed. In some embodiments, the value indicates a number of code words including errors of a row associated with the row address. In some embodiments, the command is encoded in the fuse array as a second row address and a second value equal to zero. In some embodiments, the command comprises a start command, a start bank command, a stop command, or a stop bank command. In some embodiments, the bank address is encoded as an address and a second value equal to zero. In some embodiments, the row address indicates a redundant row. In some embodiments, the command comprises a start redundant row command or a stop redundant row command.

(103) At block **1006**, “providing, from the command decoder, the row address and the value to a bank indicated by the bank address” may be performed.

(104) At block **1008**, “causing the value to be written to the row associated with the row address” may be performed. In some embodiments, the row address and the value are provided to a state machine associated with the bank, and the state machine causes the value to be written to the row associated with the row address.

(105) Optionally, in some embodiments, prior to block **1002** “powering up the memory device prior to the reading of the data from the fuse array” may be performed as indicated by block **1001**.

(106) The systems, methods, and apparatuses disclosed herein may allow for storage of both recent and baseline error information, particularly per-row error information in the memory, for example, in the memory array and/or a fuse array. The systems, methods, and apparatuses disclosed herein

may allow for analysis of word lines to detect degradation (e.g., increase in a number of code words with errors) of word lines. The systems, methods, and apparatuses disclosed herein may allow for the memory to provide recommendations (e.g., to a controller) as to when a word line should be repaired (e.g., remapped to a redundant word line). The techniques disclosed herein may provide for more robust error management as well as reducing over-use of the PPR command replacing word lines that do not require repair. This may delay or eliminate “running out” of redundant rows available to repair defective word lines.

(107) Of course, it is to be appreciated that any one of the examples, embodiments or processes described herein may be combined with one or more other examples, embodiments and/or processes or be separated and/or performed amongst separate devices or device portions in accordance with the present systems, devices and methods.

(108) Finally, the above-discussion is intended to be merely illustrative of the present system and should not be construed as limiting the appended claims to any particular embodiment or group of embodiments. Thus, while the present system has been described in particular detail with reference to exemplary embodiments, it should also be appreciated that numerous modifications and alternative embodiments may be devised by those having ordinary skill in the art without departing from the broader and intended spirit and scope of the present system as set forth in the claims that follow. Accordingly, the specification and drawings are to be regarded in an illustrative manner and are not intended to limit the scope of the appended claims.

Claims

1. An apparatus comprising: a memory array comprising a plurality of word lines, a plurality of bit lines configured to receive a plurality of column select signals, and a plurality of memory cells disposed at intersections of the plurality of word lines and the plurality of bit lines, wherein: a first portion of the plurality of memory cells disposed along each of the plurality of word lines is configured to store data, a second portion of the plurality of memory cells disposed along each of the plurality of word lines is configured to store metadata, and a third portion of the plurality of memory cells disposed along each of the plurality of word lines is configured to store error information, wherein a first portion of the plurality of bit lines associated with the second portion of the plurality of memory cells and a second portion of the plurality of bit lines associated with the third portion of the plurality of memory cells are associated with a same column select signal of the plurality of column select signals.
2. The apparatus of claim 1, wherein the error information comprises a plurality of values.
3. The apparatus of claim 2, wherein each of the plurality of values indicates a number of code words containing an error for a corresponding one of the plurality of word lines.
4. The apparatus of claim 3, wherein each of the plurality of values was acquired from a different error correction and scrub cycle of the memory array.
5. The apparatus of claim 2, wherein the error information comprises recent error and scrub cycle information and baseline error and scrub cycle information.
6. The apparatus of claim 5, further comprising a fuse array configured to provide the baseline error and scrub cycle information to the memory array.
7. The apparatus of claim 1, wherein the plurality of bit lines are organized into a plurality of column planes, wherein a first portion of the plurality of column planes store metadata and a second portion of the plurality of column planes store the error information.
8. The apparatus of claim 7, wherein the first portion and the second portion are mutually exclusive.
9. The apparatus of claim 7, wherein each of the plurality of values comprises four bits.
10. The apparatus of claim 7, wherein each of the plurality of values comprises six bits.
11. The apparatus of claim 1, further comprising an error and scrub cycle circuit configured to

determine a number of code words with errors in a word line of the plurality of word lines and write the number to the third portion of the plurality of memory cells for the word line.

12. The apparatus of claim 1, wherein each of the plurality of word lines comprises sixty-four code words.
