

US Patent & Trademark Office

Patent Public Search | Text View

United States Patent Application Publication

20250276599

Kind Code

A1

Publication Date

September 04, 2025

Inventor(s)

WANG; Yichang

CHARGING APPARATUS AND CHARGING SYSTEM

Abstract

A charging apparatus includes a plurality of first alternating current power supply lines, a plurality of first circuit groups, a first direct current bus, a first switch circuit located on each first alternating current power supply line, and a phase sequence detection circuit connected to each first alternating current power supply line. Rectifier circuits in all the first circuit groups are connected to charging circuits in all the first circuit groups via the first direct current bus. In addition, the phase sequence detection circuit is used to detect whether phase sequences of the plurality of first alternating current power supply lines are consistent. When the phase sequences are consistent, all first switch circuits are connected, or when the phase sequences are inconsistent, all first switch circuits are disconnected.

Inventors: WANG; Yichang (Lagos, NG)

Applicant: Huawei Digital Power Technologies Co., Ltd. (Shenzhen, CN)

Family ID: 84941725

Assignee: Huawei Digital Power Technologies Co., Ltd. (Shenzhen, CN)

Appl. No.: 19/170210

Filed: April 04, 2025

Foreign Application Priority Data

CN 202211222187.0

Oct. 08, 2022

Related U.S. Application Data

parent WO continuation PCT/CN2023/101774 20230621 PENDING child US 19170210

Publication Classification

Int. Cl.: B60L53/62 (20190101); **B60L53/51** (20190101); **H02J7/04** (20060101)

U.S. Cl.:

CPC B60L53/62 (20190201); **H02J7/04** (20130101); **B60L53/51** (20190201); **H02J2207/20** (20200101); **H02J2207/30** (20200101); **H02J2300/24** (20200101); **H02J2310/48** (20200101)

Background/Summary

CROSS-REFERENCE TO RELATED APPLICATIONS [0001] This application is a continuation of International Application No. PCT/CN2023/101774, filed on Jun. 21, 2023, which claims priority to Chinese Patent Application No. 202211222187.0, filed on Oct. 8, 2022. The disclosures of the aforementioned applications are hereby incorporated by reference in their entireties.

TECHNICAL FIELD

[0002] The embodiments relate to the field of electronic technologies, and to a charging apparatus and a charging system.

BACKGROUND

[0003] With the rapid popularization of new energy vehicles, electric vehicle charging devices used as auxiliary facilities also develop rapidly. Currently, there are two forms of charging devices: an integrated charging pile and a split-type charging pile. The split-type charging pile includes a split-type charging cabinet (also referred to as a split-type charging power unit) and a charging dispenser. The split-type charging cabinet is configured to: centralize a plurality of charging modules, and dynamically allocate, via a power allocation unit, the charging modules based on a charging power actually required by an electric vehicle. The charging dispenser is configured to perform information exchange, energy transmission, metering and billing, and the like with the electric vehicle, and includes a housing, a human machine interface, a charging control unit, a metering and billing unit, and the like.

[0004] With the rapid growth of charging power requirements of the electric vehicles, powers of split-type charging cabinets in the current market are increasing, which are developed from early 240 kW power of a power unit to current up to 1 MW of a power unit. A larger charging power makes fast charging possible for the new energy vehicles. However, for alternating current input power supply, after a total power of a charging device becomes increasingly large, one alternating current power supply line usually cannot meet a power supply requirement of an entire cabinet due to limitation of a through-current capability, and a plurality of alternating current power supply circuits are usually required to supply power. A plurality of alternating current power supply lines **01** may be outputs from a plurality of different transformers **02** shown in FIG. 1 (in FIG. 1, two transformers **02** and two alternating current power supply lines **01** are used as an example for illustration), or may be outputs from different circuit breakers (not shown in FIG. 2) of a same transformer **02** shown in FIG. 2 (in FIG. 2, a single transformer **02** and two alternating current power supply lines **01** are used as an example for illustration).

SUMMARY

[0005] The embodiments provide a charging apparatus and a charging system. For a charging apparatus having a plurality of alternating current power supply lines, device damage caused by an incorrect cable connection can be avoided.

[0006] According to a first aspect, an embodiment provides a charging apparatus. The charging apparatus includes a plurality of first alternating current power supply lines, a plurality of first circuit groups, a first direct current bus connected to all of the plurality of first circuit groups, a first

switch circuit located between an input end and an output end of each of the plurality of first alternating current power supply lines, and a phase sequence detection circuit connected to each of the plurality of first alternating current power supply lines. The plurality of first alternating current power supply lines are connected to the plurality of first circuit groups in a one-to-one correspondence. In other words, each of the plurality of first alternating current power supply lines is separately correspondingly connected to one first circuit group, and each of the plurality of first circuit groups is separately correspondingly connected to one first alternating current power supply line. Each first circuit group includes a plurality of rectifier circuits and a plurality of charging circuits, and an input end of each of the plurality of rectifier circuits is connected to the output end of the corresponding first alternating current power supply line, to receive three-phase alternating current voltages provided by the first alternating current power supply line. An output end of each of the plurality of rectifier circuits is connected to the first direct current bus, and an input end of each of the plurality of charging circuits is connected to the first direct current bus. In other words, output ends of the plurality of rectifier circuits are all connected in parallel to the first direct current bus, and input ends of the plurality of charging circuits are all connected in parallel to the first direct current bus. Each first switch circuit is configured to: connect, when the first switch circuit is connected, the first alternating current power supply line to a power supply circuit of the corresponding first circuit group; and disconnect, when the first switch circuit is disconnected, the first alternating current power supply line from the power supply circuit of the corresponding first circuit group. The phase sequence detection circuit is connected between the input end of each first alternating current power supply line and the first switch circuit, and the phase sequence detection circuit is configured to check whether voltage phase sequences on same phase wires of the plurality of first alternating current power supply lines are consistent. If the voltage phase sequences on the same phase wires of the plurality of first alternating current power supply lines are all consistent, all first switch circuits are controlled to be connected; or if the voltage phase sequences on the same phase wires of the plurality of first alternating current power supply lines are inconsistent, all first switch circuits are controlled to be disconnected.

[0007] According to the charging apparatus of the embodiments, rectifier circuits in all the first circuit groups are all connected to charging circuits in all the first circuit groups via the first direct current bus. The first direct current bus is designed in a pooling manner, so that a photovoltaic device and an energy storage device can be superimposed on the first direct current bus. In addition, a method for superposing the photovoltaic device and the energy storage device is simple, cost-effective, and efficient. In addition, the phase sequence detection circuit is used to detect whether phase sequences of the plurality of first alternating current power supply lines are consistent. When the phase sequences are consistent, all the first switch circuits are connected, or when the phase sequences are inconsistent, all the first switch circuits are disconnected, so that device damage caused by an incorrect cable connection can be avoided.

[0008] During specific implementation, a quantity of the first alternating current power supply lines and a quantity of the first circuit groups are not limited. There may be two first alternating current power supply lines and two first circuit groups, three first alternating current power supply lines and three first circuit groups, or more first alternating current power supply lines and more first circuit groups. In the accompanying drawings, the two first alternating current power supply lines and the two first circuit groups are used as an example for schematic description.

[0009] During specific implementation, the input end of the first alternating current power supply line is configured to connect to a power supply, to receive the three-phase alternating current voltages provided by the power supply. The three-phase alternating current voltages refer to three voltages that have a same frequency, an equal electric potential amplitude, and a phase difference of 120 degrees between each other. In the embodiments, the first alternating current power supply line includes at least three phase wires: a first phase wire, a second phase wire, and a third phase wire. Each phase wire is configured to receive a corresponding one-phase alternating current

voltage. During specific implementation, the first alternating current power supply line can be in a three-phase five-wire system. In other words, in addition to the three phase wires, the first alternating current power supply line further includes a neutral wire (also referred to as a neutral cable) and a ground cable (also referred to as a protection ground cable). When the first switch circuit is connected, the first alternating current power supply line provides the received three-phase alternating current voltages for the corresponding first circuit group.

[0010] In the embodiments, a phase sequence is a sequence of three-phase alternating currents, and is determined based on a phase difference. For example, A, B, and C are used to represent the three-phase alternating currents respectively. A phase-A alternating current is 120 degrees ahead of a phase-B alternating current, the phase-B alternating current is 120 degrees ahead of a phase-C alternating current, and the phase-C alternating current is 120 degrees ahead of the phase-A alternating current. The phase sequences of the plurality of first alternating current power supply lines being the same means that in the plurality of first alternating current power supply lines, a phase difference between the first phase wire and the second phase wire is the same, a phase difference between the second phase wire and the third phase wire is the same, and a phase difference between the third phase wire and the first phase wire is the same. For example, phase-A alternating currents are on all first phase wires of the plurality of first alternating current power supply lines, phase-B alternating currents are on all second phase wires of the plurality of first alternating current power supply lines, and phase-C alternating currents are on all third phase wires of the plurality of first alternating current power supply lines.

[0011] During specific implementation, the plurality of rectifier circuits and the plurality of charging circuits in each first circuit group are disposed in a split manner. The split disposition herein is relative to integral disposition, and means that the plurality of rectifier circuits and the plurality of charging circuits are physically independent of each other. For example, the plurality of rectifier circuits are also disposed in the split manner, and the plurality of charging circuits are also disposed in the split manner.

[0012] The input end of each of the plurality of rectifier circuits is connected to the output end of the corresponding first alternating current power supply line, to receive the three-phase alternating current voltages provided by the first alternating current power supply line. The output end of each of the plurality of rectifier circuits is connected to the first direct current bus, and the input end of each of the plurality of charging circuits is connected to the first direct current bus. In other words, the output ends of the plurality of rectifier circuits are all connected in parallel to the first direct current bus, and the input ends of the plurality of charging circuits are all connected in parallel to the first direct current bus. The first direct current bus can include a positive bus and a negative bus. Each rectifier circuit is configured to convert the three-phase alternating current voltages provided by the first alternating current power supply line into a direct current voltage that matches the first direct current bus. For example, the three-phase alternating current voltages are three-phase alternating current voltages of 380 V, the direct current voltage that matches the first direct current bus is a direct current voltage of 820 V, and the rectifier circuit may convert the three-phase alternating current voltages of 380 V into the direct current voltage of 820 V. Each charging circuit is configured to: convert the direct current voltage on the first direct current bus into a target direct current voltage having a specified current and a specified voltage, and output the target direct current voltage. For example, the charging circuit converts the direct current voltage of 820 V into a voltage and a current that are required by an electric vehicle, to stably charge the electric vehicle. In the embodiments, direct current voltages output by all the rectifier circuits are pooled via the first direct current bus and then enter each charging circuit.

[0013] A quantity of rectifier circuits in the embodiments may be configured based on a power of the three-phase alternating current voltages on the first alternating current power supply line. For example, the power of the three-phase alternating current voltages is 720 kW, a conversion power of each rectifier circuit is 120 kW, and six rectifier circuits may be configured.

[0014] A quantity of charging circuits is not limited. The quantity of charging circuits may be the same as the quantity of rectifier circuits, or may be different from the quantity of rectifier circuits. For example, the quantity of charging circuits is greater than or equal to the quantity of rectifier circuits.

[0015] In some examples, the rectifier circuit may include an AC-DC conversion circuit, and no transformer is disposed in the AC-DC conversion circuit, so that high efficiency and low loss of the rectifier circuit can be ensured. The charging circuit may include a DC-DC conversion circuit, and a transformer is disposed in the DC-DC conversion circuit, so that charging safety can be ensured.

[0016] For example, the first switch circuit may include three switches, and one switch is disposed on each phase wire. Further, during specific implementation, the first switch circuit may further include switches disposed on the neutral wire and/or the ground cable. This is not limited herein. In some embodiments, the switches may not be disposed for the neutral wire and the ground cable.

[0017] In some examples, the switch in the first switch circuit may be a common switch, for example, a circuit breaker, a relay, or a contactor, in an electric power system. This is not limited herein.

[0018] For example, the phase sequence detection circuit is further configured to: if the voltage phase sequences on the same phase wires of the plurality of first alternating current power supply lines are inconsistent, initiate a reminder message indicating that phase sequences of three-phase alternating current voltages on the plurality of first alternating current power supply lines are inconsistent, to prompt an incorrect cable connection.

[0019] In a possible design or implementation, the phase sequence detection circuit may include a comparator circuit, a control circuit, and a plurality of voltage collection circuits corresponding to the plurality of first alternating current power supply lines.

[0020] In a implementation, each first alternating current power supply line corresponds to one voltage collection circuit, each voltage collection circuit is connected to two phase wires of the corresponding first alternating current power supply line, the two phase wires that are connected to different voltage collection circuits and that are of first alternating current power supply lines are the same, and each voltage collection circuit is configured to collect a voltage signal between the two phase wires. During specific implementation, the two phase wires connected to the voltage collection circuit may be any two of the first phase wire, the second phase wire, and the third phase wire. However, for example, once the voltage collection circuit determines the two connected phase wires, two phase wires connected to another voltage collection circuit are two phase wires with a phase sequence same as the two connected phase wires in the corresponding first alternating current power supply line.

[0021] In another implementation, each first alternating current power supply line corresponds to two voltage collection circuits, the two voltage collection circuits are both connected to the neutral wire and one phase wire of the corresponding first alternating current power supply line, and each voltage collection circuit is configured to collect a voltage signal between the phase wire and the neutral wire N. The two voltage collection circuits connected to the same first alternating current power supply line are connected to different phase wires of the first alternating current power supply line, and the two phase wires that are connected to the two voltage collection circuits connected to different first alternating current power supply lines and that are of the first alternating current power supply lines are the same.

[0022] In embodiments, after the voltage collection circuit sends the collected voltage signal to the comparator circuit, the comparator circuit determines, based on the voltage signal collected by each voltage collection circuit, whether waveforms of voltage signals corresponding to the same phase wires of the plurality of first alternating current power supply lines are consistent; and if the waveforms of the voltage signals corresponding to the same phase wires of the plurality of first alternating current power supply lines are consistent, sends first control information to the control circuit, or if the waveforms of the voltage signals corresponding to the same phase wires of the

plurality of first alternating current power supply lines are inconsistent, sends second control information to the control circuit. The control circuit controls, after receiving the first control information sent by the comparator circuit, the first switch circuit to be connected, or controls, after receiving the second control information, the first switch circuit to be disconnected.

[0023] During specific implementation, when each first alternating current power supply line corresponds to the two voltage collection circuits, for the two voltage collection circuits of different first alternating current power supply lines, the comparator circuit compares the voltage signals collected by the voltage collection circuits that are connected to different first alternating current power supply lines and that are connected to the same phase wires. For example, the comparator circuit compares voltage signals collected by the voltage collection circuits separately connected to first phase wires in different first alternating current power supply lines, and compares voltage signals collected by the voltage collection circuits separately connected to second phase wires in different first alternating current power supply lines. If two groups of comparison results are both that voltage waveforms are consistent, it is considered that the waveforms of the voltage signals corresponding to the same phase wires in the plurality of first alternating current power supply lines are all consistent. If waveforms of at least one of two groups of comparison results are inconsistent, it is considered that phase sequences of the voltage signals corresponding to the same phase wires in the plurality of first alternating current power supply lines are inconsistent.

[0024] Further, for ease of comparison, each voltage collection circuit may further convert the collected voltage signal into a digital signal, and send the digital signal to the comparator circuit. The comparator circuit may compare, based on the received digital signal sent by each voltage collection circuit, whether digital signals sent by different voltage collection circuits that are connected to the same phase wires of the plurality of first alternating current power supply lines are consistent; and if the digital signals sent by different voltage collection circuits that are connected to the same phase wires of the plurality of first alternating current power supply lines are consistent, send the first control information to the control circuit; or if the digital signals sent by different voltage collection circuits that are connected to the same phase wires of the plurality of first alternating current power supply lines are inconsistent, send the second control information to the control circuit.

[0025] In the embodiments, that two digital signals are consistent means that the two digital signals have a same value at any moment.

[0026] A specific structure of the voltage collection circuit is not limited. For example, the voltage collection circuit may include a first resistor, a second resistor, a third resistor, a fourth resistor, a fifth resistor, a first diode, a first transistor, and an optical coupler. The first resistor is connected in series between a first input end of the voltage collection circuit and a negative electrode of the first diode. The second resistor is connected in series between a second input end of the voltage collection circuit and a positive electrode of the first diode. The negative electrode of the diode is further connected to a positive electrode of a photodiode in the optical coupler, and the positive electrode of the first diode is connected to a negative input end of the photodiode in the optical coupler. A collector of a transistor in the optical coupler is connected to a first reference voltage end, and an emitter of the transistor in the optical coupler is connected to a first end of the third resistor. A base of the first transistor is connected to a second end of the third resistor, a collector of the first transistor is connected to a first end of the fourth resistor and an output end of the voltage collection circuit, and an emitter of the first transistor is connected to a second reference voltage end. A second end of the fourth resistor is connected to the first reference voltage end. A first end of the fifth resistor is connected to the base of the first transistor, and a second end of the fifth resistor is connected to the emitter of the first transistor. A voltage at the second reference voltage end is greater than a voltage at the first reference voltage end. Further, during specific implementation, the voltage at the second reference voltage end may alternatively be less than the voltage at the first reference voltage end. This is not limited herein.

[0027] An example in which the voltage at the second reference voltage end is greater than the voltage at the first reference voltage end is used. A working principle of the voltage collection circuit is as follows: A voltage signal between the first input end and the second input end of the voltage collection circuit is a sine wave signal, a positive half-cycle signal of the sine wave signal may drive the photodiode in the optical coupler to emit light, and the transistor in the optical coupler a photocurrent to control the first transistor to output a high potential voltage. A negative half-cycle signal of the sine wave signal can pass through only the first diode to drive the photodiode in the optical coupler not to emit light, and the first transistor to output a low potential voltage to convert the sine wave signal into a digital signal.

[0028] In the embodiments, the control circuit may be a general-purpose central processing unit (CPU), a general-purpose processor, a digital signal processor (DSP), an application-specific integrated circuit (ASIC), a field programmable gate array (FPGA) or another programmable logic device, a transistor logic device, a hardware component, or any combination thereof. The processor may implement or execute various example logical blocks, modules, and circuits described with reference to content in the embodiments. Alternatively, the control circuit may be a combination implementing a computing function, for example, a combination of one or more microprocessors, or a combination of a DSP and a microprocessor.

[0029] In some examples, the charging apparatus may further include a first photovoltaic device connected to the first direct current bus. The first photovoltaic device may convert light energy into electric energy and provide the electric energy for the first direct current bus. In this way, not only an electric capacity of the charging apparatus can be increased, but also the electric energy provided by the first photovoltaic device can be preferentially used in the daytime. Alternatively, it is considered that electricity prices are different in different time periods, for example, electricity prices in the daytime are far higher than electricity prices in the nighttime. The charging apparatus may further include a first energy storage device connected to the first direct current bus, the first energy storage device may store electric energy when the electricity prices are low, and when the electricity prices are high, the electric energy stored in the first energy storage device is preferentially used.

[0030] For example, the first direct current bus of the charging apparatus is connected to the first photovoltaic device and the first energy storage device. The first energy storage device may not only store electric energy of a power grid, but also store the electric energy of the first photovoltaic device.

[0031] A specific implementation of the first photovoltaic device is not limited, and may be any manner that can implement a photovoltaic function.

[0032] A specific implementation of the first energy storage device is not limited, and may be any manner that can implement a storage function.

[0033] For example, the charging apparatus may further include a plurality of charging ports and a switch matrix. The switch matrix is connected to each charging circuit and the plurality of charging ports. The switch matrix is configured to: perform group scheduling on the direct current voltage output by each charging circuit, and correspondingly output scheduled direct current voltages to at least two charging ports.

[0034] In some examples, the charging apparatus may further include at least one second photovoltaic device and/or at least one second energy storage device, and at least one second direct current bus is connected to the second photovoltaic device and/or the second energy storage device. The second photovoltaic device may convert light energy into electric energy and provide the electric energy for the second direct current bus. In this way, not only the electric capacity of the charging apparatus can be increased, but also the electric energy provided by the second photovoltaic device can be preferentially used in the daytime. It is considered that the electricity prices are different in different time periods, for example, the electricity prices in the daytime are far higher than the electricity prices in the nighttime. The second energy storage device may store

electric energy when the electricity prices are low, and when the electricity prices are high, the electric energy stored in the second energy storage device is preferentially used. The second energy storage device may not only store the electric energy of the power grid, but also store the electric energy of the second photovoltaic device.

[0035] A specific implementation of the second photovoltaic device is not limited, and may be any manner that can implement the photovoltaic function.

[0036] A specific implementation of the second energy storage device is not limited, and may be any manner that can implement the storage function.

[0037] For example, the charging apparatus may further include a second switch circuit located on at least one second alternating current power supply line. Each second switch circuit is configured to: connect, when the second switch circuit is connected, the second alternating current power supply line to a power supply circuit of a corresponding second circuit group; and disconnect, when the second switch circuit is disconnected, the second alternating current power supply line from the power supply circuit of the corresponding second circuit group. In this way, after an input end of the second alternating current power supply line is connected to the power supply, the second switch circuit may be used to control a charging system to be powered on/off.

[0038] For example, the second switch circuit may include three switches, and one switch is disposed on each phase wire. Further, during specific implementation, the second switch circuit may further include switches disposed on the neutral wire and/or the ground cable. This is not limited herein. In some embodiments, the switches may not be disposed for the neutral wire and the ground cable.

[0039] For example, the switch in the second switch circuit may be a common switch, for example, a circuit breaker, a relay, or a contactor, in an electric power system. This is not limited herein.

[0040] According to a second aspect, an embodiment further provides another charging apparatus. The charging apparatus may include a plurality of second alternating current power supply lines, a plurality of second circuit groups, and a plurality of second direct current buses. The plurality of second alternating current power supply lines are connected to the plurality of second circuit groups in a one-to-one correspondence. In other words, each of the plurality of second alternating current power supply lines is separately correspondingly connected to one second circuit group, and each of the plurality of second circuit groups is separately correspondingly connected to one second alternating current power supply line. The plurality of second circuit groups are connected to the plurality of second direct current buses in a one-to-one correspondence. In other words, each of the plurality of second circuit groups is separately correspondingly connected to one second direct current bus, and each of the plurality of second direct current buses is separately correspondingly connected to one second circuit group. Each second circuit group includes a plurality of rectifier circuits and a plurality of charging circuits. During specific implementation, an input end of the second alternating current power supply line is configured to connect to a power supply, to receive three-phase alternating current voltages provided by the power supply. An input end of each of the plurality of rectifier circuits in the second circuit group is connected to an output end of the corresponding second alternating current power supply line, to receive the three-phase alternating current voltages provided by the second alternating current power supply line. An output end of each rectifier circuit in the second circuit group is connected to the corresponding second direct current bus, and an input end of each charging circuit in the second circuit group is connected to the corresponding second direct current bus. In other words, output ends of the plurality of rectifier circuits in the same second circuit group are all connected in parallel to the corresponding second direct current bus, and input ends of the plurality of charging circuits in the same second circuit group are all connected in parallel to the corresponding second direct current bus. In the embodiments, all direct current voltages output by all the rectifier circuits in the same second circuit group enter each charging circuit in the second circuit group after the direct current voltages are pooled via the corresponding second direct current bus. In the embodiments, different

second alternating current power supply lines are connected to different second direct current buses. Therefore, different second alternating current power supply lines are isolated from each other, and a circulating current is not formed even if the lines are incorrectly connected.

[0041] During specific implementation, a quantity of the second alternating current power supply lines and a quantity of the second circuit groups are not limited. There may be two second alternating current power supply lines and two second circuit groups, three second alternating current power supply lines and three second circuit groups, or more second alternating current power supply lines and more second circuit groups. In the accompanying drawings, the two second alternating current power supply lines and the two second circuit groups are used as an example for schematic description.

[0042] The plurality of rectifier circuits and the plurality of charging circuits in each second circuit group are disposed in a split manner. The split disposition herein is relative to integral disposition, and means that the plurality of rectifier circuits and the plurality of charging circuits are physically independent of each other. For example, the plurality of rectifier circuits are also disposed in the split manner, and the plurality of charging circuits are also disposed in the split manner.

[0043] The second direct current bus can include a positive bus and a negative bus. Each rectifier circuit is configured to convert the three-phase alternating current voltages provided by the second alternating current power supply line into a direct current voltage that matches the second direct current bus. For example, the three-phase alternating current voltages are three-phase alternating current voltages of 380 V, the direct current voltage that matches the second direct current bus is a direct current voltage of 820 V, and the rectifier circuit may convert the three-phase alternating current voltages of 380 V into the direct current voltage of 820 V. Each charging circuit is configured to: convert the direct current voltage on the corresponding second direct current bus into a target direct current voltage having a specified current and a specified voltage, and output the target direct current voltage. For example, the charging circuit converts the direct current voltage of 820 V into a voltage and a current that are required by an electric vehicle, to stably charge the electric vehicle.

[0044] A quantity of rectifier circuits in the embodiments may be set based on a power of the three-phase alternating current voltages on the second alternating current power supply line. For example, the power of the three-phase alternating current voltages is 720 kW, a conversion power of each rectifier circuit is 120 kW, and six rectifier circuits may be set.

[0045] A quantity of charging circuits is not limited. The quantity of charging circuits may be the same as the quantity of rectifier circuits, or may be different from the quantity of rectifier circuits. For example, the quantity of charging circuits is greater than or equal to the quantity of rectifier circuits.

[0046] For example, the rectifier circuit may include an AC-DC conversion circuit, and the charging circuit may include a DC-DC conversion circuit.

[0047] For example, the charging apparatus may further include at least one second photovoltaic device and/or at least one second energy storage device, and at least one second direct current bus is connected to the second photovoltaic device and/or the second energy storage device. The second photovoltaic device may convert light energy into electric energy and provide the electric energy for the second direct current bus. In this way, not only an electric capacity of the charging apparatus can be increased, but also the electric energy provided by the second photovoltaic device can be preferentially used in the daytime. It is considered that electricity prices are different in different time periods, for example, electricity prices in the daytime are far higher than electricity prices in the nighttime. The second energy storage device may store electric energy when the electricity prices are low, and when the electricity prices are high, the electric energy stored in the second energy storage device is preferentially used. The second energy storage device may not only store electric energy of a power grid, but also store the electric energy of the second photovoltaic device.

[0048] A specific implementation of the second photovoltaic device is not limited, and may be any

manner that can implement a photovoltaic function.

[0049] A specific implementation of the second energy storage device is not limited, and may be any manner that can implement a storage function.

[0050] For example, the charging apparatus may further include a plurality of charging ports and a switch matrix. The switch matrix is connected to each charging circuit and the plurality of charging ports. The switch matrix is configured to: perform group scheduling on the direct current voltage output by each charging circuit, and correspondingly output scheduled direct current voltages to at least two charging ports.

[0051] For example, the charging apparatus may further include a second switch circuit located on at least one second alternating current power supply line. Each second switch circuit is configured to: connect, when the second switch circuit is connected, the second alternating current power supply line to a power supply circuit of the corresponding second circuit group; and disconnect, when the second switch circuit is disconnected, the second alternating current power supply line from the power supply circuit of the corresponding second circuit group. In this way, after the input end of the second alternating current power supply line is connected to the power supply, the second switch circuit may be used to control a charging system to be powered on/off.

[0052] For example, the second switch circuit may include three switches, and one switch is disposed on each phase wire. Further, during specific implementation, the second switch circuit may further include switches disposed on a neutral wire and/or a ground cable. This is not limited herein. In some embodiments, the switches may not be disposed for the neutral wire and the ground cable.

[0053] For example, the switch in the second switch circuit may be a common switch, for example, a circuit breaker, a relay, or a contactor, in an electric power system. This is not limited herein.

[0054] According to a third aspect, an embodiment further provides a charging system. The charging system may include a charging apparatus and at least one charging dispenser connected to the charging apparatus. The charging apparatus may be the charging apparatus according to various implementations of the first aspect or the second aspect. Each of the at least one charging dispenser is separately configured to connect to an electric vehicle, and the charging apparatus may charge, via each charging dispenser, the electric vehicle connected to the charging dispenser. Each charging dispenser is connected to at least one charging circuit in the charging apparatus. In an embodiment, the charging apparatus further includes a charging port, and the charging apparatus may be connected to the charging dispenser via the charging port. When the charging apparatus is connected to a power supply, if there is an incorrect cable connection, a case in which the charging apparatus has a plurality of first alternating current power supply lines may be detected via a phase sequence detection circuit. In a case in which the charging apparatus has a plurality of second alternating current power supply lines, the plurality of second alternating current power supply lines are isolated from each other. Therefore, a circulating current does not occur even if the lines are incorrectly connected. In a case in which the charging apparatus has the first alternating current power supply line and the second alternating current power supply line, the first alternating current power supply line and the second alternating current power supply line are isolated from each other. Therefore, a circulating current does not occur even if the lines are incorrectly connected.

[0055] A quantity of charging dispensers is not limited, and may be set based on a quantity of charging ports. In some embodiments, one charging port corresponds to one charging dispenser. The charging port of the charging apparatus is connected to the corresponding charging dispenser. When the electric vehicle needs to be charged, the electric vehicle is connected to the charging dispenser.

[0056] For example, the charging dispenser may include a housing, a human machine interface, a charging control unit, a metering and billing unit, and the like. The charging dispenser is configured to perform information exchange, energy transmission, metering and billing, and the like with the electric vehicle.

[0057] For example, the charging system may further include at least one electric vehicle connected to the at least one charging dispenser, so that the charging apparatus charges the electric vehicle via the charging dispenser.

[0058] For effects that can be achieved in the third aspect, refer at least to the descriptions of effects that can be achieved in any possible design or implementation of the first aspect and the second aspect. Details are not described herein again.

Description

BRIEF DESCRIPTION OF DRAWINGS

[0059] FIG. 1 is a diagram of a scenario in which two transformers supply power;

[0060] FIG. 2 is a diagram of a scenario in which one transformer supplies power;

[0061] FIG. 3 is a schematic of a structure of a split-type charging cabinet in an integrated module architecture;

[0062] FIG. 4 is a schematic of a structure of a split-type charging cabinet in a split-type module architecture;

[0063] FIG. 5 is a schematic of a structure of a charging apparatus according to an embodiment;

[0064] FIG. 6 is a schematic flowchart of performing phase sequence detection by a phase sequence detection circuit according to an embodiment;

[0065] FIG. 7 is a schematic of a structure of a charging apparatus according to another embodiment;

[0066] FIG. 8 is a schematic of a structure of a charging apparatus according to another embodiment;

[0067] FIG. 9 is a schematic of a structure of a charging apparatus according to another embodiment;

[0068] FIG. 10 is a schematic of a structure of a charging apparatus according to another embodiment;

[0069] FIG. 11 is a schematic of a structure of a charging apparatus according to another embodiment;

[0070] FIG. 12 is a schematic of a structure of a charging apparatus according to another embodiment;

[0071] FIG. 13 is a schematic of a structure of a voltage collection circuit according to an embodiment;

[0072] FIG. 14 is a diagram of an input waveform and an output waveform of the voltage collection circuit shown in FIG. 13;

[0073] FIG. 15 is a schematic of a structure of a charging apparatus according to another embodiment;

[0074] FIG. 16 is a schematic of a structure of a charging apparatus according to another embodiment;

[0075] FIG. 17 is a schematic of a structure of a charging apparatus according to another embodiment;

[0076] FIG. 18 is a schematic of a structure of a charging apparatus according to another embodiment of this application; and

[0077] FIG. 19 is a diagram of a structure of a charging system according to an embodiment.

DETAILED DESCRIPTION OF EMBODIMENTS

[0078] To make the objectives, solutions, and advantages clearer, the following further describes the embodiments in detail with reference to the accompanying drawings. A specific operation method in a method embodiment may also be applied to an apparatus embodiment or a system embodiment. It should be noted that in descriptions of the embodiments, “at least one” means one

or more, and “a plurality of” means two or more. In view of this, in embodiments, “a plurality of” may also be understood as “at least two”. In addition, it should be understood that, in the descriptions of the embodiments, terms such as “first” and “second” are merely used for distinguishing and description, cannot be understood as an indication or implication of relative importance, and cannot be understood as an indication or implication of a sequence.

[0079] It should be noted that, “connection” in embodiments refers to an electrical connection, and a connection between two electrical elements may be a direct or indirect connection between the two electrical elements. For example, a connection between A and B may be a direct connection between A and B, or may be an indirect connection between A and B via one or more other electrical elements. For example, that A is connected to B may also be that A is directly connected to C, C is directly connected to B, A and B are connected via C.

[0080] With the rapid growth of charging power requirements of the electric vehicles, powers of split-type charging cabinets in the current market are increasing, which are developed from early 240 kW power of a power unit to current up to 1 MW power of a power unit. However, for alternating current input power supply, after a total power of a charging device becomes increasingly large, one alternating current power supply line, in some situations, cannot meet power supply of an entire cabinet due to limitation of a through-current capability, and a plurality of alternating current power supply lines can be required to supply power. A plurality of alternating current power supply lines **01** may be outputs from a plurality of different transformers **02** shown in FIG. 1 (in FIG. 1, two transformers **02** and two alternating current power supply lines **01** are used as an example for illustration), or may be outputs from different circuit breakers (not shown in FIG. 2) of a same transformer **02** shown in FIG. 2 (in FIG. 2, a single transformer **02** and two alternating current power supply lines **01** are used as an example for illustration).

[0081] A current split-type charging cabinet can be in an integrated module architecture. As shown in FIG. 3, a split-type charging cabinet **001** includes a plurality of integrated modules **03**, and each integrated module **03** includes an AC-DC conversion circuit **031** and a DC-DC conversion circuit **032**. The AC-DC conversion circuit **031** is configured to convert an alternating current output by the alternating current power supply line **01** into a direct current. The DC-DC conversion circuit **032** is configured to: adjust, to a target charging voltage, the direct current obtained through conversion by the AC-DC conversion circuit **031**, and allocate the target charging voltage to different charging ports **05** via a switch (not shown in the figure) in a switch matrix **04**. As a charging power gradually increases, superimposing a photovoltaic device and an energy storage device in a charging device has become a future development trend. Currently, there are two solutions for superimposing the photovoltaic device and the energy storage device. In a first solution shown in FIG. 3, a photovoltaic device **06** and an energy storage device **07** are superimposed on a cable between the switch matrix **04** and each charging port **05**. In a second solution, the photovoltaic device **06** and the energy storage device **07** are disposed before an input end of the switch matrix **04**, and a switch matrix needs to be additionally added to switch, to the original switch matrix **04**, voltages output by the photovoltaic device **06** and the energy storage device **07**. Therefore, when a charging device in the integrated module architecture is used, a solution for superposing the photovoltaic device and the energy storage device is complex, and has high costs and low efficiency.

[0082] A related technology proposes a split-type charging cabinet in a split-type module architecture, where the split-type module architecture is also referred to as a direct current bus architecture. As shown in FIG. 4, the split-type charging cabinet **001** includes a plurality of AC-DC conversion circuits **031** and a plurality of DC-DC conversion circuits **032** that are disposed in a split manner, and output ends of all the AC-DC conversion circuits **031** and input ends of all the DC-DC conversion circuits **032** are connected to each other via a direct current bus **08**. The photovoltaic device **06** and the energy storage device **07** are directly superimposed on the direct current bus **08**. The solution for superposing the photovoltaic device and the energy storage device

is simple and efficient, and has low costs; and therefore, attracts increasingly more attention in the industry.

[0083] However, in the direct current bus architecture, because there is no transformer between the direct current bus and the alternating current power supply line, the direct current bus is a non-isolated direct current bus. In this case, phase sequences of three-phase alternating current voltages on the plurality of alternating current power supply lines need to be completely consistent to avoid a circulating current. However, during device installation, commissioning, and construction, phase sequences of cable connections of the plurality of alternating current power supply lines cannot be completely the same due to non-standard operations. As a result, the system is burnt or the like.

[0084] In view of this, an embodiment provides a charging apparatus **100**. The charging apparatus **100** can avoid device damage caused by an incorrect cable connection. To make the objectives, solutions, and advantages clearer, the following further describes the embodiments in detail with reference to the accompanying drawings.

[0085] FIG. 5 is a schematic of a structure of the charging apparatus **100** according to an embodiment. The charging apparatus **100** includes a plurality of first alternating current power supply lines **110**, a plurality of first circuit groups **120**, a first direct current bus **130** connected to all of the plurality of first circuit groups **120**, a first switch circuit **140** located between an input end and an output end of each of the plurality of first alternating current power supply lines **110**, and a phase sequence detection circuit **150** connected to each of the plurality of first alternating current power supply lines **110**.

[0086] The plurality of first alternating current power supply lines **110** are connected to the plurality of first circuit groups **120** in a one-to-one correspondence. In other words, each of the plurality of first alternating current power supply lines **110** is separately correspondingly connected to one first circuit group **120**, and each of the plurality of first circuit groups **120** is separately correspondingly connected to one first alternating current power supply line **110**. During specific implementation, a quantity of the first alternating current power supply lines **110** and a quantity of the first circuit groups **120** are not limited. There may be two first alternating current power supply lines **110** and two first circuit groups **120**, three first alternating current power supply lines **110** and three first circuit groups **120**, or more first alternating current power supply lines **110** and more first circuit groups **120**. In the accompanying drawings, the two first alternating current power supply lines **110** and the two first circuit groups **120** are used as an example for schematic description.

[0087] During specific implementation, the input end of the first alternating current power supply line **110** is configured to connect to a power supply (not shown in the figure), to receive three-phase alternating current voltages provided by the power supply. The power supply is configured to provide the three-phase alternating current voltages for the charging apparatus **100**, for example, may be a power grid. The three-phase alternating current voltages refer to three voltages that have a same frequency, an equal electric potential amplitude, and a phase difference of 120 degrees between each other. In the embodiments, the first alternating current power supply line **110** includes at least three phase wires: a first phase wire L1, a second phase wire L2, and a third phase wire L3. Each phase wire is configured to receive a corresponding one-phase alternating current voltage. During specific implementation, the first alternating current power supply line **110** can be in a three-phase five-wire system. In other words, in addition to the three phase wires L1 to L3, the first alternating current power supply line **110** further includes a neutral wire (also referred to as a neutral cable) and a ground cable (also referred to as a protection ground cable). When the first switch circuit **140** is connected, the first alternating current power supply line **110** provides the received three-phase alternating current voltages for the corresponding first circuit group **120**.

[0088] Each first circuit group **120** includes a plurality of rectifier circuits **121** and a plurality of charging circuits **122**, and the plurality of rectifier circuits **121** and the plurality of charging circuits **122** may be disposed in a split manner. The split disposition herein is relative to integral disposition, and means that the plurality of rectifier circuits **121** and the plurality of charging

circuits **122** are physically independent of each other. For example, the plurality of rectifier circuits **121** are also disposed in the split manner, and the plurality of charging circuits **122** are also disposed in the split manner.

[0089] The input end of each of the plurality of rectifier circuits **121** is connected to the output end of the corresponding first alternating current power supply line **110**, to receive the three-phase alternating current voltages provided by the first alternating current power supply line **110**. The output end of each of the plurality of rectifier circuits **121** is connected to the first direct current bus **130**, and the input end of each of the plurality of charging circuits **122** is connected to the first direct current bus **130**. In other words, output ends of the plurality of rectifier circuits **121** are all connected in parallel to the first direct current bus **130**, and input ends of the plurality of charging circuits **122** are all connected in parallel to the first direct current bus **130**. Refer to FIG. 5. The first direct current bus **130** can include a positive bus and a negative bus. Each rectifier circuit **121** is configured to convert the three-phase alternating current voltages provided by the first alternating current power supply line **110** into a direct current voltage that matches the first direct current bus **130**. For example, the three-phase alternating current voltages are three-phase alternating current voltages of 380 V, the direct current voltage that matches the first direct current bus **130** is a direct current voltage of 820 V, and the rectifier circuit **121** may convert the three-phase alternating current voltages of 380 V into the direct current voltage of 820 V. Each charging circuit **122** is configured to: convert the direct current voltage on the first direct current bus **130** into a target direct current voltage having a specified current and a specified voltage, and output the target direct current voltage. For example, the charging circuit **122** converts the direct current voltage of 820 V into a voltage and a current that are required by an electric vehicle, to stably charge the electric vehicle. In the embodiments, direct current voltages output by all the rectifier circuits **121** are pooled via the first direct current bus **130** and then enter each charging circuit **122**.

[0090] A quantity of rectifier circuits **121** in the embodiments may be configured based on a power of the three-phase alternating current voltages on the first alternating current power supply line **110**. For example, the power of the three-phase alternating current voltages is 720 kW, a conversion power of each rectifier circuit **121** is 120 kW, and six rectifier circuits **121** may be configured.

[0091] A quantity of charging circuits **122** is not limited. The quantity of charging circuits **122** may be the same as the quantity of rectifier circuits **121**, or may be different from the quantity of rectifier circuits **121**. For example, the quantity of charging circuits **122** is greater than or equal to the quantity of rectifier circuits **121**.

[0092] For example, the rectifier circuit **121** may include an alternating current-direct current AC-DC conversion circuit, and no transformer is disposed in the AC-DC conversion circuit, so that high efficiency and low loss of the rectifier circuit **121** can be ensured. The charging circuit **122** may include a direct current-direct current DC-DC conversion circuit, and a transformer is disposed in the DC-DC conversion circuit, so that charging safety can be ensured.

[0093] Each first switch circuit **140** is configured to: connect, when the first switch circuit **140** is connected, the first alternating current power supply line **110** to a power supply circuit of the corresponding first circuit group **120**; and disconnect, when the first switch circuit **140** is disconnected, the first alternating current power supply line **110** from the power supply circuit of the corresponding first circuit group **120**. For example, the first switch circuit **140** may include three switches **141**, and one switch **141** is disposed on each phase wire. Further, during specific implementation, the first switch circuit **140** may further include a switch disposed on the neutral wire and/or the ground cable. This is not limited herein. In some embodiments, the switches may not be disposed for the neutral wire and the ground cable.

[0094] For example, the switch **141** in the first switch circuit **140** may be a common switch, for example, a circuit breaker, a relay, or a contactor, in an electric power system. This is not limited herein.

[0095] During specific implementation, there may be no transformer in the rectifier circuit **121**.

Therefore, there is no transformer between the first direct current bus and the input end of each first alternating current power supply line **110**. Therefore, the first direct current bus is a non-isolated direct current bus. To prevent device damage caused by inconsistent phase sequences of alternating current power supply lines, still refer to FIG. 5. The phase sequence detection circuit **150** is connected between the input end of each first alternating current power supply line **110** and the first switch circuit **140**. As shown in FIG. 6, the phase sequence detection circuit **150** is configured to perform the following steps. [0096] **S101**: Check whether voltage phase sequences on same phase wires of the plurality of first alternating current power supply lines **110** are consistent.

[0097] If the voltage phase sequences on the same phase wires of the plurality of first alternating current power supply lines **110** are consistent, step **S102** is performed. If the voltage phase sequences on the same phase wires of the plurality of first alternating current power supply lines **110** are inconsistent, step **S103** is performed. [0098] **S102**: Control all first switch circuits **140** to be connected. [0099] **S103**: Control all first switch circuits **140** to be disconnected.

[0100] According to the charging apparatus **100** of the embodiments, the rectifier circuits **121** in all the first circuit groups **120** are all connected to the charging circuits **122** in all the first circuit groups **120** via the first direct current bus **130**. The first direct current bus **130** is designed in a pooling manner, so that a photovoltaic device and an energy storage device can be superimposed on the first direct current bus **130**. In addition, a method for superposing the photovoltaic device and the energy storage device is simple, cost-effective, and efficient. In addition, the phase sequence detection circuit **150** is used to detect whether phase sequences of the plurality of first alternating current power supply lines **110** are consistent. When the phase sequences are consistent, all the first switch circuits **140** are connected, or when the phase sequences are inconsistent, all the first switch circuits **140** are disconnected, so that device damage caused by an incorrect cable connection can be avoided.

[0101] In the embodiments, a phase sequence is a sequence of three-phase alternating currents, and is determined based on a phase difference. For example, A, B, and C are used to represent the three-phase alternating currents respectively. A phase-A alternating current is 120 degrees ahead of a phase-B alternating current, the phase-B alternating current is 120 degrees ahead of a phase-C alternating current, and the phase-C alternating current is 120 degrees ahead of the phase-A alternating current. The phase sequences of the plurality of first alternating current power supply lines **110** being the same means that in the plurality of first alternating current power supply lines **110**, a phase difference between the first phase wire L1 and the second phase wire L2 is the same, a phase difference between the second phase wire L2 and the third phase wire L3 is the same, and a phase difference between the third phase wire L3 and the first phase wire L1 is the same. For example, phase-A alternating currents are on all first phase wires L1 of the plurality of first alternating current power supply lines **110**, phase-B alternating currents are on all second phase wires L2 of the plurality of first alternating current power supply lines **110**, and phase-C alternating currents are on all third phase wires L3 of the plurality of first alternating current power supply lines **110**.

[0102] For example, the phase sequence detection circuit **150** is further configured to: if the voltage phase sequences on the same phase wires of the plurality of first alternating current power supply lines **110** are inconsistent, initiate a reminder message indicating that phase sequences of three-phase alternating current voltages on the plurality of first alternating current power supply lines **110** are inconsistent, to prompt an incorrect cable connection.

[0103] For example, FIG. 7 to FIG. 12 are schematics of structures of charging apparatuses **100** according to different embodiments. The phase sequence detection circuit **150** may include a comparator circuit **152**, a control circuit **153**, and a plurality of voltage collection circuits **151** corresponding to the plurality of first alternating current power supply lines **110**.

[0104] In an implementation, refer to FIG. 7 to FIG. 9. Each first alternating current power supply line **110** corresponds to one voltage collection circuit **151**, each voltage collection circuit **151** is

connected to two phase wires of the corresponding first alternating current power supply line **110**, the two phase wires that are connected to different voltage collection circuits **151** and that are of first alternating current power supply lines **110** are the same, and each voltage collection circuit **151** is configured to collect a voltage signal between the two phase wires. During specific implementation, the two phase wires connected to the voltage collection circuit may be any two of the first phase wire **L1**, the second phase wire **L2**, and the third phase wire **L3**. However, in an example, once the voltage collection circuit **151** determines the two connected phase wires, two phase wires connected to another voltage collection circuit **151** are two phase wires with a phase sequence same as the two connected phase wires in the corresponding first alternating current power supply line **110**. For example, as shown in FIG. 7, two voltage collection circuits **151** are separately connected to first phase wires **L1** and second phase wires **L2** of two first alternating current power supply lines **110**. For example, as shown in FIG. 8, two voltage collection circuits **151** are separately connected to first phase wires **L1** and third phase wires **L3** of two first alternating current power supply lines **110**. For example, as shown in FIG. 9, two voltage collection circuits **151** are separately connected to second phase wires **L2** and third phase wires **L3** of two first alternating current power supply lines **110**.

[0105] In another implementation, refer to FIG. 10 to FIG. 12. Each first alternating current power supply line **110** corresponds to two voltage collection circuits **151**, the two voltage collection circuits **151** are both connected to a neutral wire **N** and one phase wire of the corresponding first alternating current power supply line **110**, and each voltage collection circuit **151** is configured to collect a voltage signal between the phase wire and the neutral wire **N**. The two voltage collection circuits **151** connected to the same first alternating current power supply line **110** are connected to different phase wires of the first alternating current power supply line **110**, and the two phase wires that are connected to the two voltage collection circuits **151** connected to different first alternating current power supply lines **110** and that are of the first alternating current power supply lines **110** are the same. For example, in FIG. 10, in the two voltage collection circuits **151** corresponding to each first alternating current power supply line **110**, one voltage collection circuit **151** is connected to the neutral wire **N** and the first phase wire **L1**, and the other voltage collection circuit **151** is connected to the neutral wire **N** and the second phase wire **L2**. For example, in FIG. 11, in the two voltage collection circuits **151** corresponding to each first alternating current power supply line **110**, one voltage collection circuit **151** is connected to the neutral wire **N** and the second phase wire **L2**, and the other voltage collection circuit **151** is connected to the neutral wire **N** and the third phase wire **L3**. For example, in FIG. 12, in the two voltage collection circuits **151** corresponding to each first alternating current power supply line **110**, one voltage collection circuit **151** is connected to the neutral wire **N** and the first phase wire **L1**, and the other voltage collection circuit **151** is connected to the neutral wire **N** and the third phase wire **L3**.

[0106] In embodiments, after the voltage collection circuit **151** sends the collected voltage signal to the comparator circuit **152**, the comparator circuit **152** determines, based on the voltage signal collected by each voltage collection circuit **151**, whether waveforms of voltage signals corresponding to the same phase wires of the plurality of first alternating current power supply lines **110** are consistent; and if the waveforms of the voltage signals corresponding to the same phase wires of the plurality of first alternating current power supply lines **110** are consistent, sends first control information to the control circuit **153**, or if the waveforms of the voltage signals corresponding to the same phase wires of the plurality of first alternating current power supply lines **110** are inconsistent, sends second control information to the control circuit **153**. The control circuit **153** controls, after receiving the first control information sent by the comparator circuit **152**, the first switch circuit **140** to be connected, or controls, after receiving the second control information, the first switch circuit **140** to be disconnected.

[0107] During specific implementation, when each first alternating current power supply line **110** corresponds to the two voltage collection circuits **151**, for the two voltage collection circuits **151** of

different first alternating current power supply lines **110**, the comparator circuit **152** compares the voltage signals collected by the voltage collection circuits **151** that are connected to different first alternating current power supply lines **110** and that are connected to the same phase wires. For example, in FIG. **10**, the comparator circuit **152** compares voltage signals collected by the voltage collection circuits **151** separately connected to first phase wires L1 in different first alternating current power supply lines **110**, and compares voltage signals collected by the voltage collection circuits **151** separately connected to second phase wires L2 in different first alternating current power supply lines **110**. If two groups of comparison results are both that voltage waveforms are consistent, it is considered that the waveforms of the voltage signals corresponding to the same phase wires in the plurality of first alternating current power supply lines **110** are all consistent. If waveforms of at least one of two groups of comparison results are inconsistent, it is considered that phase sequences of the voltage signals corresponding to the same phase wires in the plurality of first alternating current power supply lines **110** are inconsistent.

[0108] Further, for ease of comparison, each voltage collection circuit **151** may further convert the collected voltage signal into a digital signal, and send the digital signal to the comparator circuit **152**. The comparator circuit **152** may compare, based on the received digital signal sent by each voltage collection circuit **151**, whether digital signals sent by different voltage collection circuits **151** that are connected to the same phase wires of the plurality of first alternating current power supply lines **110** are consistent; and if the digital signals sent by different voltage collection circuits **151** that are connected to the same phase wires of the plurality of first alternating current power supply lines **110** are consistent, send the first control information to the control circuit **153**; or if the digital signals sent by different voltage collection circuits **151** that are connected to the same phase wires of the plurality of first alternating current power supply lines **110** are inconsistent, send the second control information to the control circuit **153**.

[0109] In the embodiments, that two digital signals are consistent means that the two digital signals have a same value at any moment.

[0110] A specific structure of the voltage collection circuit **151** is not limited. For example, a zero-crossing sampling circuit shown in FIG. **13** may be used. As shown in FIG. **13**, the voltage collection circuit **151** may include a first resistor R1, a second resistor R2, a third resistor R3, a fourth resistor R4, a fifth resistor R5, a first diode D1, a first transistor Q1, and an optical coupler U1. The first resistor R1 is connected in series between a first input end Sin1 of the voltage collection circuit **151** and a negative electrode of the first diode D1. The second resistor R2 is connected in series between a second input end Sin2 of the voltage collection circuit **151** and a positive electrode of the first diode D1. The negative electrode of the diode is further connected to a positive electrode of a photodiode in the optical coupler U1, and the positive electrode of the first diode D1 is connected to a negative input end of the photodiode in the optical coupler U1. A collector of a transistor in the optical coupler U1 is connected to a first reference voltage end V1, and an emitter of the transistor in the optical coupler U1 is connected to a first end of the third resistor R3. A base of the first transistor Q1 is connected to a second end of the third resistor R3, a collector of the first transistor Q1 is connected to a first end of the fourth resistor R4 and an output end Sout of the voltage collection circuit **151**, and an emitter of the first transistor Q1 is connected to a second reference voltage end V2. A second end of the fourth resistor R4 is connected to the first reference voltage end V1. A first end of the fifth resistor R5 is connected to the base of the first transistor Q1, and a second end of the fifth resistor R5 is connected to the emitter of the first transistor Q1. A voltage at the second reference voltage end V2 may be greater than a voltage at the first reference voltage end V1. Further, during specific implementation, the voltage at the second reference voltage end V2 may alternatively be less than the voltage at the first reference voltage end V1. This is not limited herein.

[0111] During specific implementation, the output end of the voltage collection circuit **151** is connected to the comparator circuit **152**. When the voltage collection circuit **151** shown in FIG. **13**

is used in charging apparatuses **100** shown in FIG. 7 to FIG. 9, the first input end Sin1 and the second input end Sin2 of the voltage collection circuit **151** are respectively connected to two phase wires. Phase wires connected to first input ends Sin1 of different voltage collection circuits **151** are the same, and phase wires connected to second input ends Sin2 of different voltage collection circuits **151** are the same. When the voltage collection circuit **151** shown in FIG. 13 is used in charging apparatuses **100** shown in FIG. 10 to FIG. 12, the first input end Sin1 and the second input end Sin2 of the voltage collection circuit **151** are respectively connected to a phase wire and the neutral wire N. First input ends Sin1 of different voltage collection circuits **151** are all connected to the neutral wire N, and second input ends Sin2 of different voltage collection circuits **151** are connected to the same phase wire. Alternatively, second input ends Sin2 of different voltage collection circuits **151** are all connected to the neutral wire N, and phase wires connected to first input ends Sin1 of different voltage collection circuits **151** are the same.

[0112] An example in which the voltage at the second reference voltage end V2 is greater than the voltage at the first reference voltage end V1 is used. A working principle of the voltage collection circuit **151** shown in FIG. 13 is as follows: A voltage signal between the first input end Sin1 and the second input end Sin2 of the voltage collection circuit **151** is a sine wave signal shown in FIG. 14, a positive half-cycle signal of the sine wave signal may drive the photodiode in the optical coupler U1 to emit light, and the transistor in the optical coupler U1 outputs a photocurrent to control the first transistor Q1 to output a high potential voltage. A negative half-cycle signal of the sine wave signal can pass through only the first diode D1 to drive the photodiode in the optical coupler U1 not to emit light, and the first transistor Q1 to output a low potential voltage to convert a voltage signal of a sine wave into a digital signal shown in FIG. 14.

[0113] In the embodiments, the control circuit **153** may be a general-purpose central processing unit (CPU), a general-purpose processor, a digital signal processor (DSP), an application-specific integrated circuit (ASIC), a field programmable gate array (FPGA) or another programmable logic device, a transistor logic device, a hardware component, or any combination thereof. The processor may implement or execute various example logical blocks, modules, and circuits described with reference to content in the embodiments. Alternatively, the control circuit **153** may be a combination implementing a computing function, for example, a combination of one or more microprocessors, or a combination of a DSP and a microprocessor.

[0114] FIG. 15 is a schematic of a structure of the charging apparatus **100** according to another embodiment. The charging apparatus **100** may further include a first photovoltaic device **160** connected to the first direct current bus **130**. The first photovoltaic device **160** may convert light energy into electric energy and provide the electric energy for the first direct current bus **130**. In this way, not only an electric capacity of the charging apparatus **100** can be increased, but also the electric energy provided by the first photovoltaic device **160** can be preferentially used in the daytime. Alternatively, it is considered that electricity prices are different in different time periods, for example, electricity prices in the daytime are far higher than electricity prices in the nighttime. The charging apparatus **100** may further include a first energy storage device **170** connected to the first direct current bus **130**, the first energy storage device **170** may store electric energy when the electricity prices are low, and when the electricity prices are high, the electric energy stored in the first energy storage device **170** is preferentially used.

[0115] For example, as shown in FIG. 15, the first direct current bus **130** of the charging apparatus **100** is connected to the first photovoltaic device **160** and the first energy storage device **170**. The first energy storage device **170** may not only store electric energy of a power grid, but also store the electric energy of the first photovoltaic device **160**.

[0116] A specific implementation of the first photovoltaic device **160** is not limited, and may be any manner that can implement a photovoltaic function.

[0117] A specific implementation of the first energy storage device **170** is not limited, and may be any manner that can implement a storage function.

[0118] Still refer to FIG. 15. The charging apparatus **100** may further include a plurality of charging ports **180** and a switch matrix **190** connected between each charging circuit **122** and the plurality of charging ports **180**. The switch matrix **190** is configured to: perform group scheduling on a direct current voltage output by each charging circuit **122**, and correspondingly output scheduled direct current voltages to at least two charging ports **180**.

[0119] To avoid a circulating current, an embodiment further provides the charging apparatus **100**. Refer to FIG. 16. The charging apparatus **100** includes a plurality of second alternating current power supply lines **210**, a plurality of second circuit groups **220**, and a plurality of second direct current buses **230**. The plurality of second alternating current power supply lines **210** are connected to the plurality of second circuit groups **220** in a one-to-one correspondence. In other words, each of the plurality of second alternating current power supply lines **210** is separately correspondingly connected to one second circuit group **220**, and each of the plurality of second circuit groups **220** is separately correspondingly connected to one second alternating current power supply line **210**. The plurality of second circuit groups **220** are connected to the plurality of second direct current buses **230** in a one-to-one correspondence. In other words, each of the plurality of second circuit groups **220** is separately correspondingly connected to one second direct current bus **230**, and each of the plurality of second direct current buses **230** is separately correspondingly connected to one second circuit group **220**.

[0120] During specific implementation, a quantity of the second alternating current power supply lines **210** and a quantity of the second circuit groups **220** are not limited. There may be two second alternating current power supply lines **210** and two second circuit groups **220**, three second alternating current power supply lines **210** and three second circuit groups **220**, or more second alternating current power supply lines **210** and more second circuit groups **220**. In the accompanying drawings, the two second alternating current power supply lines **210** and the two second circuit groups **220** are used as an example for schematic description.

[0121] Each second circuit group **220** includes a plurality of rectifier circuits **221** and a plurality of charging circuits **222**, and the plurality of rectifier circuits **221** and the plurality of charging circuits **222** may be disposed in a split manner. The split disposition herein is relative to integral disposition, and means that the plurality of rectifier circuits **221** and the plurality of charging circuits **222** are physically independent of each other. For example, the plurality of rectifier circuits **221** are also disposed in the split manner, and the plurality of charging circuits **222** are also disposed in the split manner.

[0122] During specific implementation, an input end of the second alternating current power supply line **210** is configured to connect to a power supply (not shown in the figure), to receive three-phase alternating current voltages provided by the power supply. An input end of each of the plurality of rectifier circuits **221** in the second circuit group **220** is connected to an output end of the corresponding second alternating current power supply line **210**, to receive the three-phase alternating current voltages provided by the second alternating current power supply line **210**. An output end of each rectifier circuit **221** in the second circuit group **220** is connected to the corresponding second direct current bus **230**, and an input end of each charging circuit **222** in the second circuit group **220** is connected to the corresponding second direct current bus **230**. In other words, output ends of the plurality of rectifier circuits **221** in the same second circuit group **220** are all connected in parallel to the corresponding second direct current bus **230**, and input ends of the plurality of charging circuits **222** in the same second circuit group **220** are all connected in parallel to the corresponding second direct current bus **230**. Refer to FIG. 16. The second direct current bus **230** can include a positive bus and a negative bus. Each rectifier circuit **221** is configured to convert the three-phase alternating current voltages provided by the second alternating current power supply line **210** into a direct current voltage that matches the second direct current bus **230**. For example, the three-phase alternating current voltages are three-phase alternating current voltages of 380 V, the direct current voltage that matches the second direct current bus **230** is a

direct current voltage of 820 V, and the rectifier circuit **221** may convert the three-phase alternating current voltages of 380 V into the direct current voltage of 820 V. Each charging circuit **222** is configured to: convert the direct current voltage on the corresponding second direct current bus **230** into a target direct current voltage having a specified current and a specified voltage, and output the target direct current voltage. For example, the charging circuit **222** converts the direct current voltage of 820 V into a voltage and a current that are required by an electric vehicle, to stably charge the electric vehicle. In the embodiments, all direct current voltages output by all the rectifier circuits **221** in the same second circuit group **220** enter each charging circuit **222** in the second circuit group **220** after the direct current voltages are pooled via the corresponding second direct current bus **230**. In the embodiments, different second alternating current power supply lines **230** are connected to different second direct current buses **210**. Therefore, different second alternating current power supply lines **210** are isolated from each other, and a circulating current is not formed even if the lines are incorrectly connected.

[0123] A quantity of rectifier circuits **221** in the embodiments may be set based on a power of the three-phase alternating current voltages on the second alternating current power supply line **210**. For example, the power of the three-phase alternating current voltages is 720 kW, a conversion power of each rectifier circuit **221** is 120 kW, and six rectifier circuits **221** may be set.

[0124] A quantity of charging circuits **222** is not limited. The quantity of charging circuits **222** may be the same as the quantity of rectifier circuits **221**, or may be different from the quantity of rectifier circuits **221**. For example, the quantity of charging circuits **222** is greater than or equal to the quantity of rectifier circuits **221**.

[0125] For example, the rectifier circuit **221** may include an AC-DC conversion circuit, and the charging circuit **222** may include a DC-DC conversion circuit.

[0126] FIG. **17** is a schematic of a structure of the charging apparatus **100** according to another embodiment. The charging apparatus **100** may further include at least one second photovoltaic device **250** and/or at least one second energy storage device **260**, and at least one second direct current bus **230** is connected to the second photovoltaic device **250** and/or the second energy storage device **260**. The second photovoltaic device **250** may convert light energy into electric energy and provide the electric energy for the second direct current bus **230**. In this way, not only an electric capacity of the charging apparatus **100** can be increased, but also the electric energy provided by the second photovoltaic device **160** can be, for example preferentially, used in the daytime, as it may be considered that electricity prices are different in different time periods. For example, electricity prices in the daytime are far higher than electricity prices in the nighttime. The second energy storage device **260** may store electric energy when the electricity prices are low, and when the electricity prices are high, the electric energy stored in the second energy storage device **260** is preferentially used. The second energy storage device **260** may not only store electric energy of a power grid, but also store the electric energy of the second photovoltaic device **250**.

[0127] A specific implementation of the second photovoltaic device **250** is not limited, and may be any manner that can implement a photovoltaic function.

[0128] A specific implementation of the second energy storage device **260** is not limited, and may be any manner that can implement a storage function.

[0129] Still refer to FIG. **16** and FIG. **17**. The charging apparatus **100** may further include the plurality of charging ports **180** and the switch matrix **190** connected between an output end of each charging circuit **122** and the plurality of charging ports **180**. The switch matrix **190** is configured to: perform group scheduling on the direct current voltage output by each charging circuit **122**, and correspondingly output the scheduled direct current voltages to the at least two charging ports **180**.

[0130] Still refer to FIG. **17**. The charging apparatus **100** may further include a second switch circuit **240** located on at least one second alternating current power supply line **210**. Each second switch circuit **240** is configured to: connect, when the second switch circuit **240** is connected, the second alternating current power supply line **210** to a power supply circuit of the corresponding

second circuit group **220**; and disconnect, when the second switch circuit **240** is disconnected, the second alternating current power supply line **210** from the power supply circuit of the corresponding first circuit group **120**. In this way, after the input end of the second alternating current power supply line **210** is connected to the power supply, the second switch circuit **240** may be used to control a charging system to be powered on/off.

[0131] For example, the second switch circuit **240** may include three switches **241**, and one switch **241** is disposed on each phase wire. Further, during specific implementation, the second switch circuit **240** may further include switches disposed on a neutral wire N and/or a ground cable. This is not limited herein. In some embodiments, the switches may not be disposed for the neutral wire N and the ground cable.

[0132] For example, the switch **241** in the second switch circuit **240** may be a common switch, for example, a circuit breaker, a relay, or a contactor, in an electric power system. This is not limited herein.

[0133] Correspondingly, an embodiment further provides the charging apparatus **100**. Refer to FIG. **18**. The charging apparatus **100** includes the plurality of first alternating current power supply lines **110**, the plurality of first circuit groups **120**, the first direct current bus **130** connected to all of the plurality of first circuit groups **120**, the first switch circuit **140** located between the input end and the output end of each of the plurality of first alternating current power supply lines **110**, the phase sequence detection circuit **150** connected to each of the plurality of first alternating current power supply lines **110**, the at least one second alternating current power supply line **210**, at least one second circuit group **220**, and the at least one second direct current bus **230**.

[0134] The plurality of first alternating current power supply lines **110** are connected to the plurality of first circuit groups **120** in a one-to-one correspondence. Each first circuit group **120** includes the plurality of rectifier circuits **121** and the plurality of charging circuits **122**. The input end of each of the plurality of rectifier circuits **121** is connected to the output end of the corresponding first alternating current power supply line **110**, and the output end of each of the plurality of rectifier circuits **121** is connected to the first direct current bus **130**. The input end of each of the plurality of charging circuits **122** is connected to the first direct current bus **130**. Each first alternating current power supply line **110** is configured to: receive three-phase alternating current voltages, and provide the received three-phase alternating current voltages for the corresponding first circuit group **120** when the first switch circuit **140** is connected. Each first switch circuit **140** is configured to: connect, when the first switch circuit **140** is connected, the first alternating current power supply line **110** to the power supply circuit of the corresponding first circuit group **120**, and disconnect, when the first switch circuit **140** is disconnected, the first alternating current power supply line **110** from the power supply circuit of the corresponding first circuit group **120**.

[0135] The phase sequence detection circuit **150** is connected between the input end of each first alternating current power supply line **110** and the first switch circuit **140**, and the phase sequence detection circuit **150** is configured to check whether voltage phase sequences on same phase wires of different first alternating current power supply lines **110** are consistent. If the voltage phase sequences on the same phase wires of different first alternating current power supply lines **110** are all consistent, all first switch circuits **140** are controlled to be connected; or if the voltage phase sequences on the same phase wires of different first alternating current power supply lines **110** are inconsistent, all first switch circuits **140** are controlled to be disconnected.

[0136] The at least one second alternating current power supply line **210** is connected to the at least one second circuit group **220** in a one-to-one correspondence, and the at least one second circuit group **220** is connected to the at least one second direct current bus **230** in a one-to-one correspondence. Each of the at least one second circuit group **220** includes the plurality of rectifier circuits **221** and the plurality of charging circuits **222**, the input end of each of the plurality of rectifier circuits **221** is connected to the corresponding second alternating current power supply line

210, and the output end of each of the plurality of rectifier circuits **221** is connected to the corresponding second direct current bus **230**. The input end of each of the plurality of charging circuits **222** is connected to the corresponding second direct current bus **230**.

[0137] In this embodiment, for different first alternating current power supply lines **110**, a circulating current can be avoided via the phase sequence detection circuit **150**. The first alternating current power supply line **110** and the second alternating current power supply line **210** are isolated from each other, and different second alternating current power supply lines **210** are also isolated from each other. Therefore, a circulating current does not occur even if the lines are incorrectly connected.

[0138] In some examples, still refer to FIG. **18**. The charging apparatus **100** may further include the first photovoltaic device **160** and/or the first energy storage device **170** connected to the first direct current bus **130**.

[0139] In some examples, still refer to FIG. **18**. The charging apparatus **100** may further include the at least one second photovoltaic device **250** and/or the at least one second energy storage device **260**, and the at least one second direct current bus **230** is connected to the second photovoltaic device **250** and/or the second energy storage device **260**.

[0140] Still refer to FIG. **18**. The charging apparatus **100** may further include the second switch circuit **240** located on the at least one second alternating current power supply line **210**. Each second switch circuit **240** is configured to: connect, when the second switch circuit **240** is connected, the second alternating current power supply line **210** to the power supply circuit of the corresponding second circuit group **220**; and disconnect, when the second switch circuit **240** is disconnected, the second alternating current power supply line **210** from the power supply circuit of the corresponding first circuit group **120**.

[0141] For example, still refer to FIG. **18**. The charging apparatus **100** may further include the plurality of charging ports **180** and the switch matrix **190** connected between the output end of each charging circuit **122** and the plurality of charging ports **180**. The switch matrix **190** is configured to: perform group scheduling on the direct current voltage output by each charging circuit **122**, and correspondingly output the scheduled direct current voltages to the at least two charging ports **180**.

[0142] During specific implementation, for setting of each circuit in this embodiment, refer to setting of each circuit in the foregoing embodiments in FIG. **5** to FIG. **17**. Details are not described herein again.

[0143] It should be noted that “first” and “second” in the embodiments are merely used to distinguish between different circuits, and are not intended to limit the circuits. For example, the first alternating current power supply line and the second alternating current power supply line indicate that the first alternating current power supply line is an alternating current power supply line different from the second alternating current power supply line.

[0144] FIG. **19** is a diagram of a structure of a charging system **10** according to an embodiment. The charging system **10** provided in this embodiment may include any one of the foregoing charging apparatuses **100** provided in embodiments and at least one charging dispenser **300** connected to the charging apparatus **100**. Each of the at least one charging dispenser **300** is separately configured to connect to an electric vehicle **200**, and the charging apparatus **100** may charge, via each charging dispenser **300**, the electric vehicle **200** connected to the charging dispenser **300**. During specific implementation, each charging dispenser **300** is connected to at least one charging circuit in the charging apparatus. In an embodiment, the charging apparatus **100** further includes the charging port **180**, and the charging apparatus **100** may be connected to the charging dispenser via the charging port **180**. When the charging apparatus **100** in the charging system **10** is connected to a power supply **20**, if there is an incorrect cable connection, a case in which the charging apparatus **100** has the plurality of first alternating current power supply lines **110** may be detected via the phase sequence detection circuit **150**. In a case in which the charging apparatus **100** has the plurality of second alternating current power supply lines **210**, the plurality

of second alternating current power supply lines **210** are isolated from each other. Therefore, a circulating current does not occur even if the lines are incorrectly connected. In a case in which the charging apparatus **100** has the first alternating current power supply line **110** and the second alternating current power supply line **210**, the first alternating current power supply line **110** and the second alternating current power supply line **210** are isolated from each other. Therefore, a circulating current does not occur even if the lines are incorrectly connected.

[0145] A quantity of charging dispensers **300** is not limited, and may be set based on a quantity of charging ports. In some embodiments, one charging port corresponds to one charging dispenser **300**. The charging port of the charging apparatus **100** is connected to the corresponding charging dispenser **300**. When the electric vehicle **200** needs to be charged, the electric vehicle **200** is connected to the charging dispenser **300**.

[0146] For example, the charging dispenser **300** mainly includes a housing, a human machine interface, a charging control unit, a metering and billing unit, and the like. The charging dispenser **300** is configured to perform information exchange, energy transmission, metering and billing, and the like with the electric vehicle **200**.

[0147] For example, still refer to FIG. **19**. The charging system **10** may further include at least one electric vehicle **200** connected to the at least one charging dispenser **300**, so that the charging apparatus **100** charges the electric vehicle **200** via the charging dispenser **300**.

[0148] It is clear that a person skilled in the art can make various modifications and variations to the embodiments without departing from their scope. The embodiments are intended to cover these modifications and their variations.

Claims

1. A charging apparatus, comprising: a plurality of first alternating current power supply lines, a plurality of first circuit groups, a first direct current bus connected to all of the plurality of first circuit groups, a first switch circuit located between an input end and an output end of each of the plurality of first alternating current power supply lines, and a phase sequence detection circuit connected to each of the plurality of first alternating current power supply lines, wherein the plurality of first alternating current power supply lines is connected to the plurality of first circuit groups in a one-to-one correspondence; each first circuit group comprises a plurality of rectifier circuits and a plurality of charging circuits, an input end of each of the plurality of rectifier circuits is connected to the output end of the corresponding first alternating current power supply line, an output end of each of the plurality of rectifier circuits is connected to the first direct current bus, and an input end of each of the plurality of charging circuits is connected to the first direct current bus; each first alternating current power supply line is configured to receive three-phase alternating current voltages; the phase sequence detection circuit is connected between the input end of each first alternating current power supply line and the first switch circuit, and the phase sequence detection circuit is configured to check whether voltage phase sequences on same phase wires of the plurality of first alternating current power supply lines are consistent; and when the voltage phase sequences on the same phase wires of the plurality of first alternating current power supply lines are all consistent, all first switch circuits are controlled to be connected; or when the voltage phase sequences on the same phase wires of the plurality of first alternating current power supply lines are inconsistent, all first switch circuits are controlled to be disconnected.

2. The charging apparatus according to claim 1, wherein the phase sequence detection circuit is further configured to: when the voltage phase sequences on the same phase wires of the plurality of first alternating current power supply lines are inconsistent, initiate a reminder message indicating that phase sequences of three-phase alternating current voltages on the plurality of first alternating current power supply lines are inconsistent.

3. The charging apparatus according to claim 1, wherein the phase sequence detection circuit

comprises: a comparator circuit, a control circuit, and a plurality of voltage collection circuits corresponding to the plurality of first alternating current power supply lines; each first alternating current power supply line corresponds to one voltage collection circuit, each voltage collection circuit is connected to two phase wires of the corresponding first alternating current power supply line, the two phase wires that are connected to the plurality of voltage collection circuits and that are of the first alternating current power supply lines are the same, and each voltage collection circuit is configured to collect a voltage signal between the two phase wires; or each first alternating current power supply line corresponds to two voltage collection circuits, the two voltage collection circuits are both connected to a neutral wire and one phase wire of the corresponding first alternating current power supply line, the two voltage collection circuits are connected to different phase wires of the first alternating current power supply line, the two phase wires that are connected to the two voltage collection circuits connected to different first alternating current power supply lines and that are of the first alternating current power supply lines are the same, and each voltage collection circuit is configured to collect a voltage signal between the phase wire and the neutral wire; the comparator circuit is configured to: determine, based on the voltage signal collected by each voltage collection circuit, whether waveforms of voltage signals corresponding to the same phase wires of the plurality of first alternating current power supply lines are consistent; and when the waveforms of the voltage signals corresponding to the same phase wires of the plurality of first alternating current power supply lines are consistent, send first control information to the control circuit, or when the waveforms of the voltage signals corresponding to the same phase wires of the plurality of first alternating current power supply lines are inconsistent, send second control information to the control circuit; and the control circuit is configured to: control, after receiving the first control information sent by the comparator circuit, the first switch circuit to be connected, or control, after receiving the second control information, the first switch circuit to be disconnected.

4. The charging apparatus according to claim 3, wherein each voltage collection circuit is further configured to: convert the collected voltage signal into a digital signal, and send the digital signal to the comparator circuit; and the comparator circuit is configured to: receive the digital signal sent by each voltage collection circuit, and compare whether digital signals sent by different voltage collection circuits that are connected to the same phase wires of the plurality of first alternating current power supply lines are consistent; and when the digital signals sent by different voltage collection circuits that are connected to the same phase wires of the plurality of first alternating current power supply lines are consistent, send the first control information to the control circuit; or when the digital signals sent by different voltage collection circuits that are connected to the same phase wires of the plurality of first alternating current power supply lines are inconsistent, send the second control information to the control circuit.

5. The charging apparatus according to claim 4, wherein the voltage collection circuit comprises: a first resistor, a second resistor, a third resistor, a fourth resistor, a fifth resistor, a first diode, a first transistor, and an optical coupler, wherein the first resistor is connected in series between a first input end of the voltage collection circuit and a negative electrode of the first diode; the second resistor is connected in series between a second input end of the voltage collection circuit and a positive electrode of the first diode; the negative electrode of the diode is further connected to a positive electrode of a photodiode in the optical coupler, and the positive electrode of the first diode is connected to a negative input end of the photodiode in the optical coupler; a collector of a transistor in the optical coupler is connected to a first reference voltage end, and an emitter of the transistor in the optical coupler is connected to a first end of the third resistor; a base of the first transistor is connected to a second end of the third resistor, a collector of the first transistor is connected to a first end of the fourth resistor and an output end of the voltage collection circuit, and an emitter of the first transistor is connected to a second reference voltage end; a second end of the fourth resistor is connected to the first reference voltage end; and a first end of the fifth resistor is

connected to the base of the first transistor, and a second end of the fifth resistor is connected to the emitter of the first transistor.

6. The charging apparatus according to claim 1, further comprising: a first photovoltaic device and/or a first energy storage device that are/is connected to the first direct current bus.

7. The charging apparatus according to claim 1, wherein each first switch circuit is configured to: connect, when the first switch circuit is connected, the first alternating current power supply line to a power supply circuit of the corresponding first circuit group; and disconnect, when the first switch circuit is disconnected, the first alternating current power supply line from the power supply circuit of the corresponding first circuit group; each rectifier circuit in the first circuit group is configured to convert the three-phase alternating current voltages provided by the first alternating current power supply line into a direct current voltage that matches the first direct current bus; and each charging circuit in the plurality of first circuit groups is configured to: convert the direct current voltage on the first direct current bus into a target direct current voltage having a specified current and a specified voltage, and output the target direct current voltage.

8. The charging apparatus according to claim 7, wherein the rectifier circuit comprises an AC-DC conversion circuit, and the charging circuit comprises a DC-DC conversion circuit.

9. The charging apparatus according to claim 1, wherein the charging apparatus further comprises at least one second alternating current power supply line, at least one second circuit group connected to the at least one second alternating current power supply line in a one-to-one correspondence, and at least one second direct current bus connected to the at least one second circuit group in a one-to-one correspondence; each of the at least one second circuit group comprises a plurality of rectifier circuits and a plurality of charging circuits; an input end of each rectifier circuit in each second circuit group is connected to the corresponding second alternating current power supply line, and an output end of each rectifier circuit is connected to the corresponding second direct current bus; and an input end of each charging circuit in each second circuit group is connected to the corresponding second direct current bus.

10. The charging apparatus according to claim 9, further comprising: at least one second photovoltaic device and/or at least one second energy storage device; and the at least one second direct current bus is connected to the second photovoltaic device and/or the second energy storage device.

11. The charging apparatus according to claim 9, wherein each second alternating current power supply line is configured to: receive the three-phase alternating current voltages, and provide the received three-phase alternating current voltages for each rectifier circuit in the corresponding second circuit group; each rectifier circuit in the second circuit group is configured to convert the three-phase alternating current voltages provided by the second alternating current power supply line into a direct current voltage that matches the second direct current bus; and each charging circuit in the second circuit group is configured to: convert the direct current voltage on the second direct current bus into a target direct current voltage having a specified current and a specified voltage, and output the target direct current voltage.

12. The charging apparatus according to claim 9, further comprising: a second switch circuit located on the at least one second alternating current power supply line; and each second switch circuit is configured to: connect, when the second switch circuit is connected, the second alternating current power supply line to a power supply circuit of the corresponding second circuit group; and disconnect, when the second switch circuit is disconnected, the second alternating current power supply line from the power supply circuit of the corresponding second circuit group.

13. The charging apparatus according to claim 1, further comprising: a plurality of charging ports and a switch matrix connected between each charging circuit and the plurality of charging ports; and the switch matrix is configured to: perform group scheduling on the direct current voltage output by each charging circuit, and correspondingly output scheduled direct current voltages to at least two charging ports.

14. A charging apparatus, comprising a plurality of alternating current power supply lines, a plurality of circuit groups that is connected to the plurality of alternating current power supply lines in a one-to-one correspondence, and a plurality of direct current buses that is connected to the plurality of circuit groups in a one-to-one correspondence, wherein each of the plurality of circuit groups comprises a plurality of rectifier circuits and a plurality of charging circuits; an input end of each of the plurality of rectifier circuits is connected to the corresponding alternating current power supply line, and an output end of each of the plurality of rectifier circuits is connected to the corresponding direct current bus; and an input end of each of the plurality of charging circuits is connected to the corresponding direct current bus.

15. The charging apparatus according to claim 14, further is comprising: at least one photovoltaic device and/or at least one energy storage device; and at least one direct current bus is connected to the photovoltaic device and/or the energy storage device.

16. The charging apparatus according to claim 14, further comprising: a plurality of charging ports and a switch matrix connected between each charging circuit and the plurality of charging ports; and the switch matrix is configured to enable each charging port to correspond to output ends of at least two charging circuits.

17. The charging apparatus according to claim 14, wherein each alternating current power supply line is configured to: receive three-phase alternating current voltages, and provide the received three-phase alternating current voltages for each rectifier circuit in the corresponding circuit group; each rectifier circuit in the circuit group is configured to convert the three-phase alternating current voltages provided by the alternating current power supply line into a direct current voltage that matches the direct current bus; and each charging circuit in the circuit group is configured to: convert the direct current voltage on the direct current bus into a target direct current voltage having a specified current and a specified voltage, and output the target direct current voltage.

18. The charging apparatus according to claim 14, further comprising: a switch circuit located on at least one alternating current power supply line; and each switch circuit is configured to: connect, when the switch circuit is connected, the alternating current power supply line to a power supply circuit of the corresponding circuit group; and disconnect, when the switch circuit is disconnected, the alternating current power supply line from the power supply circuit of the corresponding circuit group.

19. A charging system; comprising: a charging apparatus; and a plurality of charging dispensers connected to the charging apparatus, wherein each charging dispenser of the plurality of charging dispensers is separately configured to connect to an electric vehicle, and the charging apparatus is configured to charge, via each charging dispenser, the electric vehicle connected to the charging dispenser; and the charging apparatus comprises: a plurality of first alternating current power supply lines, a plurality of first circuit groups, a first direct current bus connected to all of the plurality of first circuit groups, a first switch circuit located between an input end and an output end of each of the plurality of first alternating current power supply lines, and a phase sequence detection circuit connected to each of the plurality of first alternating current power supply lines, wherein the plurality of first alternating current power supply lines is connected to the plurality of first circuit groups in a one-to-one correspondence; each first circuit group comprises: a plurality of rectifier circuits and a plurality of charging circuits, an input end of each of the plurality of rectifier circuits is connected to the output end of the corresponding first alternating current power supply line, an output end of each of the plurality of rectifier circuits is connected to the first direct current bus, and an input end of each of the plurality of charging circuits is connected to the first direct current bus; each first alternating current power supply line is configured to receive three-phase alternating current voltages; the phase sequence detection circuit is connected between the input end of each first alternating current power supply line and the first switch circuit, and the phase sequence detection circuit is configured to check whether voltage phase sequences on same phase wires of the plurality of first alternating current power supply lines are consistent; and when the

voltage phase sequences on the same phase wires of the plurality of first alternating current power supply lines are all consistent, all first switch circuits are controlled to be connected; or when the voltage phase sequences on the same phase wires of the plurality of first alternating current power supply lines are inconsistent, all first switch circuits are controlled to be disconnected, wherein each charging dispenser is connected to at least one charging circuit; or the charging apparatus comprises: a plurality of alternating current power supply lines, a plurality of circuit groups that is connected to the plurality of alternating current power supply lines in a one-to-one correspondence, and a plurality of direct current buses that is connected to the plurality of circuit groups in a one-to-one correspondence, wherein each of the plurality of circuit groups comprises: a plurality of rectifier circuits and a plurality of charging circuits; an input end of each of the plurality of rectifier circuits is connected to the corresponding alternating current power supply line, and an output end of each of the plurality of rectifier circuits is connected to the corresponding direct current bus; and an input end of each of the plurality of charging circuits is connected to the corresponding direct current bus, wherein each charging dispenser is connected to at least one charging circuit.

20. The charging system according to claim 19, further comprising: at least one electric vehicle connected to the at least one charging dispenser.
