

US Patent & Trademark Office

Patent Public Search | Text View

United States Patent	12413266
Kind Code	B2
Date of Patent	September 09, 2025
Inventor(s)	Abdelmonem; Amr et al.

Method and system for mitigating interference in the near field

Abstract

Aspects of the subject disclosure may include, for example, receiving, via an antenna, a communication signal generated by a communication device, and detecting interference in the communication signal, wherein the interference is generated by one or more interference sources, wherein the interference is detected by monitoring a near field region of the antenna, an intermediate field region of the antenna, a far field region of the antenna, or any combinations thereof, wherein the monitoring excludes monitoring only the far field region of the antenna. Other embodiments are disclosed.

Inventors: Abdelmonem; Amr (Northbrook, IL), Goodman; Igor (Buffalo Grove, IL), Tacconi; Pablo (Arlington, TX)

Applicant: ISCO International, LLC (Schaumburg, IL)

Family ID: 80353817

Assignee: ISCO International, LLC (Schaumburg, IL)

Appl. No.: 18/736707

Filed: June 07, 2024

Prior Publication Data

Document Identifier	Publication Date
US 20240322862 A1	Sep. 26, 2024

Related U.S. Application Data

continuation parent-doc US 17407258 20210820 US 12047127 child-doc US 18736707
us-provisional-application US 63231037 20210809
us-provisional-application US 63071896 20200828

Publication Classification

Int. Cl.: **H04B1/10** (20060101); **H01Q1/52** (20060101); **H01Q3/04** (20060101); **H01Q3/36** (20060101); **H01Q21/24** (20060101); **H04B1/04** (20060101); **H04B1/12** (20060101); **H04B5/00** (20240101); **H04B5/72** (20240101); **H04B7/00** (20060101); **H04B7/0413** (20170101); **H04B7/08** (20060101); **H04B7/10** (20170101); **H04B7/155** (20060101); **H04B17/18** (20150101); **H04B17/336** (20150101); **H04B17/345** (20150101); **H04B17/382** (20150101); **H04J11/00** (20060101); **H04L5/14** (20060101); **H04L25/03** (20060101); **H04W24/08** (20090101); **H04W72/541** (20230101); H04B17/10 (20150101)

U.S. Cl.:

CPC **H04B5/72** (20240101); **H01Q1/523** (20130101); **H01Q3/36** (20130101); **H01Q21/245** (20130101); **H04B1/0475** (20130101); **H04B1/10** (20130101); **H04B1/12** (20130101); **H04B7/002** (20130101); **H04B7/0413** (20130101); **H04B7/084** (20130101); **H04B7/10** (20130101); **H04B7/15557** (20130101); **H04B7/15571** (20130101); **H04B17/18** (20150115); **H04B17/336** (20150115); **H04B17/345** (20150115); **H04B17/382** (20150115); **H04J11/0023** (20130101); **H04L5/14** (20130101); **H04L25/03821** (20130101); **H04W24/08** (20130101); **H04W72/541** (20230101); H04B17/102 (20150115)

Field of Classification Search

USPC: None

References Cited

U.S. PATENT DOCUMENTS

Patent No.	Issued Date	Patentee Name	U.S. Cl.	CPC
2605413	12/1951	Alvarez	N/A	N/A
2978702	12/1960	Pakan	N/A	N/A
3093824	12/1962	Ammerman	N/A	N/A
3656166	12/1971	Klopach et al.	N/A	N/A
3718935	12/1972	Ranghelli et al.	N/A	N/A
3827051	12/1973	Foldes	N/A	N/A
4222017	12/1979	Foldes	N/A	N/A
4434426	12/1983	Gaglione et al.	N/A	N/A
4723321	12/1987	Saleh	N/A	N/A
4839663	12/1988	Kurtz	N/A	N/A
5001492	12/1990	Shapiro et al.	N/A	N/A
5015053	12/1990	Johnson	N/A	N/A
5068667	12/1990	Mizoguchi	N/A	N/A
5592177	12/1996	Barrett	N/A	N/A
5929820	12/1998	Caulfield et al.	N/A	N/A
5940044	12/1998	Smith	N/A	N/A
6072439	12/1999	Ippolito et al.	N/A	N/A
6111542	12/1999	Day et al.	N/A	N/A
6201801	12/2000	Dent	N/A	N/A

6310585	12/2000	Marino	N/A	N/A
6380903	12/2001	Hayes et al.	N/A	N/A
6621465	12/2002	Teillet et al.	N/A	N/A
6631277	12/2002	Berg et al.	N/A	N/A
6703974	12/2003	White et al.	N/A	N/A
6704557	12/2003	Krishnamurthy et al.	N/A	N/A
6717555	12/2003	Teillet et al.	N/A	N/A
6801160	12/2003	Henderson et al.	N/A	N/A
6801790	12/2003	Rudrapatna	N/A	N/A
6960650	12/2004	Pulst et al.	N/A	N/A
6998908	12/2005	Sternowski	N/A	N/A
7023398	12/2005	Gottl et al.	N/A	N/A
7123194	12/2005	Park et al.	N/A	N/A
7196674	12/2006	Timofeev et al.	N/A	N/A
7346134	12/2007	Smith	N/A	N/A
7365695	12/2007	Thomas et al.	N/A	N/A
7729431	12/2009	Gebara	375/259	H04B 1/126
7733288	12/2009	Williams	N/A	N/A
7773967	12/2009	Smith	N/A	N/A
8023984	12/2010	Jin et al.	N/A	N/A
8072384	12/2010	Morrow	N/A	N/A
8134511	12/2011	Koh et al.	N/A	N/A
8238318	12/2011	Negus	N/A	N/A
8289218	12/2011	Payne	N/A	N/A
8903324	12/2013	Bradley	N/A	N/A
8923381	12/2013	Rilling	375/147	H04L 27/38
8934457	12/2014	Kapoor	370/465	H04B 7/086
8954023	12/2014	Hillstrom et al.	N/A	N/A
8976072	12/2014	Lenormand et al.	N/A	N/A
9136932	12/2014	Asplund et al.	N/A	N/A
9219508	12/2014	Veysoglu et al.	N/A	N/A
9252865	12/2015	Rilling	N/A	H04B 1/1081
9271185	12/2015	Abdelmonem	N/A	H04W 64/00
9313680	12/2015	Galeev et al.	N/A	N/A
9461681	12/2015	Kato	N/A	H04B 7/08
9472852	12/2015	Oshea et al.	N/A	N/A
9496904	12/2015	Cyzs et al.	N/A	N/A
9504404	12/2015	Panguloori et al.	N/A	N/A
9531482	12/2015	Sobczak et al.	N/A	N/A
9548775	12/2016	Smith	N/A	N/A
9571176	12/2016	Desclos et al.	N/A	N/A
9590313	12/2016	Jan et al.	N/A	N/A
9654158	12/2016	Dafesh	N/A	H04B 1/7107
9712259	12/2016	Sobczak et al.	N/A	N/A
9716541	12/2016	Sanderovich et al.	N/A	N/A
9762297	12/2016	Lee et al.	N/A	N/A
9800355	12/2016	Lee et al.	N/A	N/A

9806413	12/2016	Chukka et al.	N/A	N/A
9847571	12/2016	Bit-Babik et al.	N/A	N/A
9887467	12/2017	Aryanfar	N/A	N/A
9887716	12/2017	Alavi	N/A	H04B 1/123
9887717	12/2017	Cyzs	N/A	H04W 72/0453
9923598	12/2017	Dafesh	N/A	H04B 1/1027
9929886	12/2017	Amadjikpe et al.	N/A	N/A
9941959	12/2017	Heath et al.	N/A	N/A
9960500	12/2017	Song et al.	N/A	N/A
9972918	12/2017	Lin et al.	N/A	N/A
9986512	12/2017	Abdelmonem	N/A	H04L 5/0073
9998158	12/2017	Smith	N/A	N/A
10027036	12/2017	Schmidt et al.	N/A	N/A
10056675	12/2017	Dybdal	N/A	N/A
10116048	12/2017	Mielke et al.	N/A	N/A
10234514	12/2018	Leese de Escobar	N/A	G01R 33/0354
10237765	12/2018	Bradley	N/A	N/A
10454185	12/2018	Moran et al.	N/A	N/A
10468781	12/2018	Paulsen et al.	N/A	N/A
10530033	12/2019	Moriguchi	N/A	N/A
10530440	12/2019	Bisiules et al.	N/A	N/A
10581163	12/2019	Schmutzler et al.	N/A	N/A
10608859	12/2019	Matitsine et al.	N/A	N/A
10652835	12/2019	Tacconi et al.	N/A	N/A
10727885	12/2019	Smith	N/A	N/A
10777894	12/2019	McMichael	N/A	N/A
10862518	12/2019	Labadie et al.	N/A	N/A
10868350	12/2019	Oppenlaender et al.	N/A	N/A
10868609	12/2019	Kossin et al.	N/A	N/A
10892559	12/2020	Farzaneh et al.	N/A	N/A
10924141	12/2020	Cyzs et al.	N/A	N/A
10958312	12/2020	Pollman et al.	N/A	N/A
10971815	12/2020	West et al.	N/A	N/A
11025472	12/2020	Matitsine et al.	N/A	N/A
11038549	12/2020	Harley et al.	N/A	N/A
11121816	12/2020	Wang et al.	N/A	N/A
11145971	12/2020	Cripe	N/A	N/A
11158956	12/2020	Le	N/A	N/A
11177582	12/2020	Seo	N/A	N/A
11239886	12/2021	Pollman et al.	N/A	N/A
11265032	12/2021	Smith	N/A	N/A
11289799	12/2021	Everest et al.	N/A	N/A
11296429	12/2021	Biancotto et al.	N/A	N/A
11316258	12/2021	Junttila	N/A	N/A
11329387	12/2021	Da Silveira et al.	N/A	N/A
11336028	12/2021	Shen et al.	N/A	N/A

11342668	12/2021	Chen et al.	N/A	N/A
11349530	12/2021	Frenger et al.	N/A	N/A
11349581	12/2021	Dybdal et al.	N/A	N/A
11360396	12/2021	Bauerschmidt et al.	N/A	N/A
11363678	12/2021	Rosenschild et al.	N/A	N/A
11411323	12/2021	Wu et al.	N/A	N/A
11437701	12/2021	Rai et al.	N/A	N/A
11451274	12/2021	El-Keyi et al.	N/A	N/A
11509071	12/2021	Abdelmonem et al.	N/A	N/A
11509072	12/2021	Abdelmonem et al.	N/A	N/A
11515652	12/2021	Abdelmonem et al.	N/A	N/A
11539146	12/2021	Chieh et al.	N/A	N/A
11594821	12/2022	Abdelmonem et al.	N/A	N/A
11600920	12/2022	Udagave	N/A	N/A
11626667	12/2022	Abdelmonem et al.	N/A	N/A
11670847	12/2022	Abdelmonem et al.	N/A	N/A
11705940	12/2022	Abdelmonem et al.	N/A	N/A
11811127	12/2022	Lysejko	N/A	H01Q 3/10
11837793	12/2022	Bhattacharya et al.	N/A	N/A
11838039	12/2022	Smith	N/A	N/A
11881909	12/2023	Abdelmonem et al.	N/A	N/A
11949489	12/2023	Abdelmonem	N/A	N/A
11956027	12/2023	Abdelmonem et al.	N/A	N/A
11985692	12/2023	Abdelmonem	N/A	N/A
12047127	12/2023	Abdelmonem et al.	N/A	N/A
12057895	12/2023	Abdelmonem et al.	N/A	N/A
12219522	12/2024	Tacconi	N/A	N/A
2002/0193071	12/2001	Waltho	N/A	N/A
2003/0162566	12/2002	Shapira et al.	N/A	N/A
2004/0082335	12/2003	Hirayama et al.	N/A	N/A
2004/0106436	12/2003	Ochi et al.	N/A	N/A
2004/0263421	12/2003	Schaffner et al.	N/A	N/A
2005/0226353	12/2004	Gebara et al.	N/A	N/A
2005/0239403	12/2004	Karabinis	N/A	N/A
2006/0014491	12/2005	Cleveland et al.	N/A	N/A
2006/0202906	12/2005	Okubo et al.	N/A	N/A
2007/0020224	12/2006	Vetter et al.	N/A	N/A
2007/0046558	12/2006	Tillery	N/A	N/A
2007/0060059	12/2006	Kim et al.	N/A	N/A
2007/0080868	12/2006	Hwang et al.	N/A	N/A
2007/0205955	12/2006	Korisch et al.	N/A	N/A
2007/0280369	12/2006	Reynolds	N/A	N/A
2008/0062062	12/2007	Borau et al.	N/A	N/A
2008/0150799	12/2007	Hemmi et al.	N/A	N/A
2008/0253308	12/2007	Ward et al.	N/A	N/A
2008/0280571	12/2007	Rofougaran et al.	N/A	N/A
2009/0040127	12/2008	Williams	N/A	N/A
2009/0189820	12/2008	Saito et al.	N/A	N/A
2009/0224995	12/2008	Puente et al.	N/A	N/A
2010/0304680	12/2009	Kuffner et al.	N/A	N/A

2010/0311353	12/2009	Rabinovich et al.	N/A	N/A
2011/0057849	12/2010	Naym et al.	N/A	N/A
2011/0059694	12/2010	Audic	N/A	N/A
2011/0069633	12/2010	Schmidt et al.	N/A	N/A
2011/0096812	12/2010	Hahm	375/E1.032	H04B 1/7107
2011/0116569	12/2010	Vaughan et al.	N/A	N/A
2011/0134001	12/2010	Sakata et al.	N/A	N/A
2011/0150118	12/2010	Asplund et al.	N/A	N/A
2011/0158081	12/2010	Wang	370/201	H03F 1/304
2011/0171922	12/2010	Kim et al.	N/A	N/A
2012/0009964	12/2011	Gormley et al.	N/A	N/A
2012/0063529	12/2011	Choi et al.	N/A	N/A
2012/0108178	12/2011	Lee et al.	N/A	N/A
2012/0188137	12/2011	Lalezari	N/A	N/A
2012/0229232	12/2011	Mahon et al.	N/A	N/A
2013/0044650	12/2012	Barker et al.	N/A	N/A
2013/0157601	12/2012	O'Keeffee et al.	N/A	N/A
2013/0237272	12/2012	Prasad	N/A	N/A
2013/0331039	12/2012	Hillstrom et al.	N/A	N/A
2014/0022125	12/2013	Zhu et al.	N/A	N/A
2014/0035698	12/2013	Schadler et al.	N/A	N/A
2014/0035792	12/2013	Schadler et al.	N/A	N/A
2014/0097987	12/2013	Worl et al.	N/A	N/A
2014/0191924	12/2013	Payne et al.	N/A	N/A
2014/0236546	12/2013	Payne	N/A	N/A
2014/0274094	12/2013	Abdelmonem et al.	N/A	N/A
2015/0015372	12/2014	Hara et al.	N/A	N/A
2015/0091755	12/2014	Chawgo	N/A	N/A
2015/0092621	12/2014	Jalloul et al.	N/A	N/A
2015/0108210	12/2014	Zhou	N/A	N/A
2015/0116153	12/2014	Chen et al.	N/A	N/A
2015/0156642	12/2014	Sobczak et al.	N/A	N/A
2015/0162658	12/2014	Bowers et al.	N/A	N/A
2015/0195001	12/2014	Barker et al.	N/A	N/A
2015/0200709	12/2014	Negus et al.	N/A	N/A
2015/0264584	12/2014	Dayanandan et al.	N/A	N/A
2015/0340875	12/2014	Prasad	N/A	N/A
2015/0351103	12/2014	Kim et al.	N/A	N/A
2016/0020514	12/2015	Elsaadani et al.	N/A	N/A
2016/0036505	12/2015	George et al.	N/A	N/A
2016/0087348	12/2015	Ko et al.	N/A	N/A
2016/0088572	12/2015	Bl et al.	N/A	N/A
2016/0105255	12/2015	Henry et al.	N/A	N/A
2016/0112111	12/2015	Bull	N/A	N/A
2016/0126633	12/2015	Keller et al.	N/A	N/A
2016/0142229	12/2015	Bevan et al.	N/A	N/A
2016/0233944	12/2015	Viswanathan	N/A	N/A
2016/0254595	12/2015	Sobczak et al.	N/A	N/A
2016/0276725	12/2015	Barnickel et al.	N/A	N/A

2016/0366605	12/2015	Tsui et al.	N/A	N/A
2016/0380690	12/2015	Jidhage	N/A	N/A
2017/0063410	12/2016	Cyzs	N/A	H04W 72/0453
2017/0077612	12/2016	Aryanfar	N/A	N/A
2017/0077616	12/2016	Corum et al.	N/A	N/A
2017/0085398	12/2016	Liu	N/A	N/A
2017/0093048	12/2016	Chen et al.	N/A	N/A
2017/0156119	12/2016	Neves et al.	N/A	N/A
2017/0171868	12/2016	Reis et al.	N/A	N/A
2017/0194704	12/2016	Chawgo et al.	N/A	N/A
2017/0237484	12/2016	Heath et al.	N/A	N/A
2017/0245162	12/2016	Beck et al.	N/A	N/A
2017/0250765	12/2016	Hasarchi et al.	N/A	N/A
2017/0294996	12/2016	Lee et al.	N/A	N/A
2017/0353929	12/2016	Tacconi et al.	N/A	N/A
2018/0034164	12/2017	Jang et al.	N/A	N/A
2018/0041270	12/2017	Buer et al.	N/A	N/A
2018/0083368	12/2017	Teillet et al.	N/A	N/A
2018/0167148	12/2017	Vannucci et al.	N/A	N/A
2018/0176802	12/2017	Rosenhouse et al.	N/A	N/A
2018/0219636	12/2017	Gale et al.	N/A	N/A
2019/0007078	12/2018	Tsui et al.	N/A	N/A
2019/0052294	12/2018	Abdelmonem	N/A	N/A
2019/0052381	12/2018	Abdelmonem	N/A	N/A
2019/0058534	12/2018	Anderson	N/A	N/A
2019/0074864	12/2018	Henry et al.	N/A	N/A
2019/0074865	12/2018	Henry et al.	N/A	N/A
2019/0103309	12/2018	Lin	N/A	N/A
2019/0103909	12/2018	Bengtsson et al.	N/A	N/A
2019/0165822	12/2018	Chen	N/A	N/A
2019/0212699	12/2018	Waldern et al.	N/A	N/A
2019/0222329	12/2018	Abdelmonem	N/A	N/A
2019/0252801	12/2018	Mahanfar et al.	N/A	N/A
2019/0273315	12/2018	Hu et al.	N/A	N/A
2019/0273326	12/2018	Sanford et al.	N/A	N/A
2019/0326986	12/2018	Heath et al.	N/A	N/A
2019/0334636	12/2018	Li et al.	N/A	N/A
2019/0372237	12/2018	Yman et al.	N/A	N/A
2019/0386759	12/2018	Singh et al.	N/A	N/A
2019/0393598	12/2018	Logothetis et al.	N/A	N/A
2020/0052388	12/2019	Jang et al.	N/A	N/A
2020/0136247	12/2019	Al et al.	N/A	N/A
2020/0145032	12/2019	Ayala et al.	N/A	N/A
2020/0185825	12/2019	Palud	N/A	N/A
2020/0187213	12/2019	Yun et al.	N/A	N/A
2020/0236630	12/2019	Tacconi et al.	N/A	N/A
2020/0288418	12/2019	Åström et al.	N/A	N/A
2020/0321697	12/2019	Zimmerman et al.	N/A	N/A
2020/0373663	12/2019	Xu	N/A	N/A

2021/0028829	12/2020	Rios	N/A	N/A
2021/0098896	12/2020	Wang et al.	N/A	N/A
2021/0127284	12/2020	Abdelmonem et al.	N/A	N/A
2021/0175622	12/2020	Jing et al.	N/A	N/A
2021/0185692	12/2020	Stephenne et al.	N/A	N/A
2021/0203422	12/2020	Gale et al.	N/A	N/A
2021/0226315	12/2020	Liu	N/A	N/A
2021/0227400	12/2020	Jia	N/A	N/A
2021/0297141	12/2020	Schafer et al.	N/A	N/A
2021/0320413	12/2020	Wu et al.	N/A	N/A
2021/0344122	12/2020	Kaistha et al.	N/A	N/A
2021/0359406	12/2020	Yang et al.	N/A	N/A
2022/0006167	12/2021	P	N/A	N/A
2022/0037753	12/2021	Tang et al.	N/A	N/A
2022/0043104	12/2021	El Assaad	N/A	N/A
2022/0069463	12/2021	Abdelmonem et al.	N/A	N/A
2022/0069853	12/2021	Abdelmonem et al.	N/A	N/A
2022/0069855	12/2021	Abdelmonem et al.	N/A	N/A
2022/0069865	12/2021	Abdelmonem et al.	N/A	N/A
2022/0069897	12/2021	Abdelmonem et al.	N/A	N/A
2022/0069898	12/2021	Abdelmonem et al.	N/A	N/A
2022/0069927	12/2021	Abdelmonem et al.	N/A	N/A
2022/0109977	12/2021	Zander et al.	N/A	N/A
2022/0123821	12/2021	Sakhnini et al.	N/A	N/A
2022/0131269	12/2021	Choi et al.	N/A	N/A
2022/0149921	12/2021	Nilsson et al.	N/A	N/A
2022/0200139	12/2021	Ryu et al.	N/A	N/A
2022/0209428	12/2021	Raghavan et al.	N/A	N/A
2022/0279520	12/2021	Tsui et al.	N/A	N/A
2022/0279535	12/2021	Tsui	N/A	N/A
2022/0311477	12/2021	Sun et al.	N/A	N/A
2022/0320756	12/2021	Hassan et al.	N/A	N/A
2022/0321241	12/2021	Bennett et al.	N/A	N/A
2022/0322321	12/2021	Dai et al.	N/A	N/A
2022/0352942	12/2021	Kalantari et al.	N/A	N/A
2022/0365224	12/2021	Rose et al.	N/A	N/A
2023/0081201	12/2022	Fleischer et al.	N/A	N/A
2023/0179252	12/2022	Ellgardt et al.	N/A	N/A
2023/0198141	12/2022	Chien et al.	N/A	N/A
2023/0318174	12/2022	Abdelmonem et al.	N/A	N/A
2023/0318175	12/2022	Abdelmonem et al.	N/A	N/A
2023/0318197	12/2022	Abdelmonem et al.	N/A	N/A
2023/0318198	12/2022	Abdelmonem et al.	N/A	N/A
2023/0327708	12/2022	Abdelmonem	N/A	N/A
2023/0387605	12/2022	Abdelmonem et al.	N/A	N/A
2023/0387606	12/2022	Abdelmonem et al.	N/A	N/A
2023/0387608	12/2022	Abdelmonem et al.	N/A	N/A
2024/0014883	12/2023	Schmidt et al.	N/A	N/A
2024/0047891	12/2023	Abdelmonem et al.	N/A	N/A
2024/0055777	12/2023	Abdelmonem et al.	N/A	N/A

2024/0113443	12/2023	Abdelmonem et al.	N/A	N/A
2024/0113745	12/2023	Abdelmonem et al.	N/A	N/A
2024/0129016	12/2023	Abdelmonem	N/A	N/A
2024/0129945	12/2023	Abdelmonem	N/A	N/A
2024/0137103	12/2023	Abdelmonem	N/A	N/A
2024/0137104	12/2023	Abdelmonem	N/A	N/A
2024/0178926	12/2023	Zaki et al.	N/A	N/A
2024/0195059	12/2023	Abdelmonem et al.	N/A	N/A
2024/0204857	12/2023	Abdelmonem	N/A	N/A
2024/0214032	12/2023	Abdelmonem et al.	N/A	N/A
2024/0214054	12/2023	Abdelmonem	N/A	N/A
2024/0267110	12/2023	Abdelmonem	N/A	N/A

FOREIGN PATENT DOCUMENTS

Patent No.	Application Date	Country	CPC
1864302	12/2005	CN	N/A
101291166	12/2007	CN	N/A
202523820	12/2011	CN	N/A
108631055	12/2017	CN	N/A
209910515	12/2019	CN	N/A
209963261	12/2019	CN	N/A
112103653	12/2019	CN	N/A
213637748	12/2020	CN	N/A
113451764	12/2020	CN	N/A
113922101	12/2021	CN	N/A
2009072037	12/2008	WO	N/A
2009120237	12/2008	WO	N/A
2020064914	12/2019	WO	N/A

OTHER PUBLICATIONS

Extended European Search Report for EP21862418.7 mailed Nov. 27, 24, 18 pp. cited by applicant
 “International Preliminary Report on Patentability”, Appln. No. PCT/US2023/023403, Dec. 5, 2024, 5 pages. cited by applicant
 “International Preliminary Report on Patentability received for PCT Application Serial No. PCT/US2023/023405”, 4 Pages, Nov. 7, 2024. cited by applicant
 “Notification Concerning Transmittal of International Preliminary Report On Patentability (Chapter I of the Patent Cooperation Treaty)”, PCT, From the International Bureau, 6 pages, 2024. cited by applicant
 International Search Report & Written Opinion for PCT/2023/076690 mailed Nov. 17, 23, 4 pp. cited by applicant
 International Search Report and Written Opinion for PCT/US2023/076674, mailed Nov. 17, 2023, 3 pp. cited by applicant
 Amendment Under Article 34 / Response to Written Opinion for PCT/US23/15540 filed Jan. 26, 2024., 11 pp. cited by applicant
 International Search Report & Written Opinion for PCT/US2023/015540 mailed Jun. 14, 2023, 15 pp. cited by applicant
 Amendment Under Article 34/Response to Written Opinion for PCT/US2021/046881 filed Jun. 16, 2022, 16 pages. cited by applicant
 Amendment Under Article 34 / Response to Written Opinion filed for PCT/US2021/046807 on Jun.

15, 22, 19 pages. cited by applicant
PCT/US2021/046804, Amendment under Article 34 and response to Written Opinion, filed May 31, 2022, 19 pages. cited by applicant
PCT/US2021/046804, International Preliminary Report on Patentability, mailed Sep. 13, 2022, 31 pages. cited by applicant
“Amendment Under Article 34 / Response to Written Opinion”, for application No. PCT/US2021/046806, Feb. 8, 2022, 8 pages. cited by applicant
“Amendment Under Article 34 / Response to Written Opinion”, PCT/US2023/015534, Jan. 26, 2024, 7 pages. cited by applicant
“Examination Report for India Application No. 202347019825”, Sep. 12, 2023, 7 Pages. cited by applicant
“International Preliminary Report”, for Application PCT/US2021/046805, Mar. 9, 2023, 9 pgs. cited by applicant
“International Preliminary Report on Patentability”, For Application PCT/US2021/046807, Aug. 20, 2021, 28 Pages. cited by applicant
“International Preliminary Report on Patentability”, for Application No. PCT/US2021/46881, Feb. 17, 2023, 25. cited by applicant
“International Preliminary Report On Patentability”, PCT/US2021/046872, May 4, 2022, 12 pgs. cited by applicant
“International Search Report and Written Opinion”, for Application No. PCT/US2021/046875, Nov. 23, 2021, 10 pages. cited by applicant
“International Search Report and Written Opinion”, for Application No. PCT/US2021/046872, Nov. 23, 2021, 13 pages. cited by applicant
“International Search Report and Written Opinion”, for Application No. PCT/US2021/46805, Nov. 8, 2021, 15 pages. cited by applicant
“International Search Report and Written Opinion”, for Application No. PCT/US2021/46881, Dec. 3, 2021, 12 pages. cited by applicant
“International Search Report and Written Opinion”, for Application No. PCT/US2021/046804, Dec. 3, 2021, 14 pages. cited by applicant
“International Search Report and Written Opinion”, For Application No. PCT/US2021/046807, Dec. 3, 2021, 15 pages. cited by applicant
“International Search Report and Written Opinion”, PCT/US2023/015534, Apr. 19, 2023, 7 pages. cited by applicant
“International Search Report and Written Opinion”, for Application No. PCT/US2021/046806, Nov. 8, 2021, 9 pages. cited by applicant
“International Search Report and Written Opinion”, Appln. No. PCT/US2023/023403, Sep. 15, 2023, 10 pages. cited by applicant
“International Search Report and Written Opinion for Application No. PCT/US2023/076650”, Nov. 16, 2023, 7 pages. cited by applicant
“International Search Report and Written Opinion for PCT/US2023/023402”, Sep. 15, 2023, 11 Pages. cited by applicant
“International Search Report and Written Opinion for PCT/US2023/023405”, Sep. 18, 2023, 10 Pages. cited by applicant
“Notification of Transmittal of International Preliminary Report On PA Tentability”, PCT/US2021/046875, May 2, 2022, 16 pages. cited by applicant
“Notification of Transmittal of International Preliminary Report on Patentability”, PCT/US2021/046806 mailed May 4, 2022, May 4, 2022, 16 pages. cited by applicant
“Notification of Transmittal of the International Search Report and the Written OPLAI'ION”, PCT/US2023/076696, ISR/WO Mailed Jan. 25, 24, Jan. 25, 2024, 7 pgs. cited by applicant
“PCT/US2021/046872—Article 34 Amendment”, Feb. 10, 2022, 8 pgs. cited by applicant

“PCT/US2021/046875—Article 34 Amendments”, Apr. 13, 2022, 8 pgs. cited by applicant
“PCT/US2023/015538”, International Search Report, Mailed Apr. 17, 2023, Apr. 17, 2023, 6 pgs. cited by applicant
Clenet, M. , et al., “Laminated Waveguide as Radiating Element for Array Applications”, IEEE Transactions on Antennas and Propagation, vol. 54, No. 5, pp. 1481-1487, May 2006. (Year: 2006). cited by applicant
PCT/US2023/076674, International Preliminary Report On Patentability, mailed Oct. 28, 2024, 20 pages. cited by applicant
International Preliminary Report on Patentability for PCT/US2023/015540 Mailed Jun. 12, 2024, 22 pp. cited by applicant
PCT/US2023/076674, Amendment Under Article 34, filed Aug. 13, 2024, 10 pages. cited by applicant
PCT/US2023/076650, Amendment Under Article 34, Filed Jul. 24, 2024, 12 pages. cited by applicant
Extended European Search Report for EP 21862420.3, mailed Oct. 1, 2024, 10 pp. cited by applicant
“European Search Report for 21862430.2”, Oct. 1, 2024, 9 Pages. cited by applicant
“PCT/US2023/015538 International Preliminary Report On Patentability”, Oct. 10, 2024, 5 pages. cited by applicant
International Preliminary Report on Patentability for PCT/US2023/076650 mailed Mar. 4, 2025. cited by applicant
“International Search Report and Written Opinion for PCT/US2024/061922”, Mar. 3, 2025, 13 pages. cited by applicant
“International Search Report and Written Opinion received for PCT Application Serial No. PCT/US2024/061929”, Mar. 6, 2025, 11 Pages. cited by applicant
“PCT/US2024/060650 International Search Report”, Mailed Jan. 23, 2025, Mar. 20, 2025, 7 pages. cited by applicant
“PCT/US2024/060676 International Search Report”, Mailed Jan. 23, 2025, Jan. 23, 2025, 6 pages. cited by applicant
Cai, et al., “Passive Intermodulation Measurement: Challenges and Solutions”, Engineering 14 181-191, 2022, 11 pages. cited by applicant
Smacchia, et al., “Advanced Compact Setups for Passive Intermodulation Measurements of Satellite Hardware”, IEEE, Feb. 2018, retrieved on [Feb. 18, 2025]. Retrieved from the internet <URL: <https://ieeexplore.ieee.org/abstract/document/8241799>> entire document. cited by applicant

Primary Examiner: Tran; Tuan A

Attorney, Agent or Firm: Guntin & Gust, PLC

Background/Summary

CROSS-REFERENCE TO RELATED APPLICATIONS (1) This application is a continuation of U.S. patent application Ser. No. 17/407,258 filed Aug. 20, 2021, which claims the benefit of and priority to U.S. Provisional Ser. No. 63/071,896, filed Aug. 28, 2020, and U.S. Provisional Ser. No. 63/231,037, filed Aug. 9, 2021. The contents of each of the foregoing applications are hereby incorporated by reference into this application as if set forth herein in full.

FIELD OF THE DISCLOSURE

(1) The subject disclosure relates to detecting interference and/or passive intermodulation (PIM) in a communications system, and performing action(s), such as polarization adjusting and/or phase shifting/delaying, that result in mitigation/cancellation of the interference and/or PIM.

BACKGROUND

(2) The deployment of fifth generation (5G) networks has made component requirements for cellular systems more stringent and sophisticated. In addition to capacity, throughput, latency, speed, and power consumption requirements, there is a need for multiple wireless services, bands, and networks to coexist and operate without impacting one another. Antennas are a key component in all wireless networks whether they are on the base station side or the handset side. Antenna designs have evolved over the past twenty years to meet the increasingly complex requirements of cellular standards. For example, almost all antennas now have multiple functions that create conflicting antenna design requirements. This antenna design evolution needs to continue to meet the growing demands of 5G networks as well as future demands of higher generation networks.

Description

BRIEF DESCRIPTION OF THE DRAWINGS

(1) Reference will now be made to the accompanying drawings, which are not necessarily drawn to scale, and wherein:

(2) FIG. 1A is a block diagram illustrating an exemplary, non-limiting embodiment of a communications network in accordance with various aspects described herein.

(3) FIG. 1B depicts an exemplary, non-limiting embodiment of a communications system functioning within, or operatively overlaid upon, the communications network of FIG. 1A in accordance with various aspects described herein.

(4) FIG. 2A is a block diagram illustrating an example, non-limiting embodiment of a system functioning within, or operatively overlaid upon, the communications network of FIG. 1A and/or the communications system of FIG. 1B in accordance with various aspects described herein.

(5) FIG. 2B depicts example null patterns for interference sources in accordance with various aspects described herein.

(6) FIG. 2C is a block diagram illustrating an example, non-limiting embodiment of a communications system having an antenna with monitoring port(s) for interference/PIM detection, and functioning within, or operatively overlaid upon, the communications network of FIG. 1A and/or the communications system of FIG. 1B in accordance with various aspects described herein.

(7) FIG. 2D is a block diagram illustrating example, non-limiting embodiments of two communications systems, including a first communications system having a single antenna, and a second communications system having two antennas, where each of the communications systems may be functioning within, or operatively overlaid upon, the communications network of FIG. 1A and/or the communications system of FIG. 1B in accordance with various aspects described herein.

(8) FIG. 2E is a block diagram illustrating an example, non-limiting embodiment of a communications system that includes the single antenna of FIG. 2D and that functions within, or is operatively overlaid upon, the communications network of FIG. 1A and/or the communications system of FIG. 1B in accordance with various aspects described herein.

(9) FIG. 2F is a block diagram illustrating an example, non-limiting embodiment of a communications system having an antenna and functioning within, or operatively overlaid upon, the communications network of FIG. 1A and/or the communications system of FIG. 1B in accordance with various aspects described herein.

(10) FIG. 2G is a block diagram illustrating an example, non-limiting embodiment of an antenna functioning within, or operatively overlaid upon, the communications network of FIG. 1A and/or

the communications system of FIG. 1B in accordance with various aspects described herein.

(11) FIG. 2H depicts example radiation patterns of various single column antennas in accordance with various aspects described herein.

(12) FIG. 2J depicts example radiation patterns of an antenna with two columns of radiating elements and an antenna with two rows of radiating elements in accordance with various aspects described herein.

(13) FIG. 2K depicts an example fixed twin beam pattern in accordance with various aspects described herein.

(14) FIG. 2L depicts an example radiation pattern of a first antenna array and an example radiation pattern of a second antenna array in accordance with various aspects described herein.

(15) FIG. 2M is a block diagram illustrating an example, non-limiting embodiment of polarization adjusting and associated equations in accordance with various aspects described herein.

(16) FIG. 2N is a block diagram illustrating an example, non-limiting embodiment of a communications system having multiple antennas each with monitoring port(s) for interference/PIM detection, where the system functions within, or is operatively overlaid upon, the communications network of FIG. 1A and/or the communications system of FIG. 1B in accordance with various aspects described herein.

(17) FIG. 2P is a block diagram illustrating an example time frame in a time-division duplexing (TDD) communications system in accordance with various aspects described herein.

(18) FIG. 2Q is a block diagram illustrating an example frequency-division duplexing (FDD) communications system in accordance with various aspects described herein.

(19) FIGS. 2R-2X each depicts an illustrative embodiment of a method in accordance with various aspects described herein.

(20) FIG. 3A depicts an exemplary, non-limiting embodiment of a system in accordance with various aspects described herein.

(21) FIG. 3B depicts an exemplary, non-limiting embodiment of a system for detecting PIM interferences in uplink signals of a base station in accordance with various aspects described herein.

(22) FIG. 3C depicts an exemplary, non-limiting embodiment of a communications system including a virtualized interference mitigation network in accordance with various aspects described herein.

(23) FIG. 3D depicts an illustrative non-limiting embodiment of a method for performing virtual interference mitigation in accordance with various aspects described herein.

(24) FIG. 4 is a block diagram of an example, non-limiting embodiment of a computing environment in accordance with various aspects described herein.

(25) FIG. 5 is a block diagram of an example, non-limiting embodiment of a mobile network platform in accordance with various aspects described herein.

(26) FIG. 6 is a block diagram of an example, non-limiting embodiment of a communication device in accordance with various aspects described herein.

DETAILED DESCRIPTION

(27) Early antennas were mostly single-input, single-output (SISO), but currently, the majority are multiple-input, multiple-output (MIMO). MIMO is a key antenna technology for wireless communications in which multiple antennas are used at both the source (transmitter) and the destination (receiver), where the antennas at each end of the communication circuit are combined to enhance data speed. In MIMO, each spatial stream is transmitted from a different radio/antenna in the same frequency channel as the transmitter. The receiver receives each stream on each of its identical radios/antennas, and reconstructs the original streams.

(28) The first MIMO specifications appeared in 3rd Generation Partnership Project (3GPP) standards at the tail end of the 3G Universal Mobile Telecommunications System (UMTS) era, but it was of limited use as it was not built into the design from the beginning. It was only with the

introduction of Long-Term Evolution (LTE) in 2008 that MIMO started to be mainstream. The goal of MIMO is to increase data rates by sending multiple data streams at the same time in the same frequency, known as spatial multiplexing. In a single antenna system, one cannot send multiple streams of data, but with MIMO, the signals transmitted from each antenna take different paths to the receivers. By applying the right mix of each data stream to each transmit antenna, the signals received at each receiving antenna only “see” one of the original data streams. In effect, MIMO systems use a combination of multiple antennas and multiple signal paths to gain knowledge of the communications channel. By using the spatial dimension of a communications link, MIMO systems can achieve significantly higher data rates than traditional SISO channels.

(29) In a communication system, a main objective for a communication channel is to increase signal to interference plus noise ratio (SINR). Let's take a 2×2 MIMO case as an example. For the same total transmitted power, the signal power has to be shared between the two transmitters, reducing SINR by 3 dB. This implies that MIMO gains over SISO is achieved when the SINR of the channel gets higher than is necessary to support the maximum SISO data rate. Such high SINR conditions occur when the user is near the cell center, or when interference from adjacent cells is low. When practical field deployments are taken into account, in a typical urban macro environment, it is estimated that 2×2 MIMO only provides approximately 20% gain over SISO. The 2×2 MIMO configuration can be increased by adding more antennas at each end of the link. In the original 3GPP Release 8 LTE standard in 2008, $2 \times$ and $4 \times$ operation was specified, and 8×8 was added later in Release 10. As the number of antennas increases, it becomes less likely that the channel will support orthogonal transmission paths. These orthogonal paths are known as Eigenmodes.

(30) For user equipment (UEs, such as smartphones, etc.), it can be difficult to support higher order MIMO due to the space limitations for the required number of receive antennas. For example, it took eight years after Release 8 specified $4 \times$ single-user (Su)-MIMO for UEs with four receivers to start appearing on the market. And to take full advantage of that, networks would have to upgrade their base stations with 4 transmit (Tx)/receive (Rx) antennas.

(31) There are alternative forms of MIMO, including Su-MIMO, where multiple streams of data can be transmitted to one user to increase peak data rates, and multi-user (Mu)-MIMO, where the same number of streams can be transmitted towards multiple users, each getting one or more streams. Mu-MIMO has the effect of increasing cell capacity, but not increasing peak data rates to any one user over the SISO case.

(32) Physically, an antenna can include radiating elements (or antenna elements (AEs)) arranged in interconnected columns and sharing the same radio frequency (RF) connector. Most low frequency bands (e.g., 600 megahertz (MHz) up to 2.5 gigahertz (GHz)) antennas in the marketplace today are multi-band (two or more bands), with each band having its own remote electronic/electrical tilt for separate optimization capability. The radiating elements can also be combined into an antenna array capable of creating multiple, steerable beams by utilizing a beamforming feed network (e.g., a butler matrix feed). Antennas for high frequency bands or millimeter (mm) waves are usually integrated with the receiver.

(33) An antenna's radiation has a pattern (power distribution) in the horizontal direction (an azimuth direction) and a pattern in the vertical direction usually referred to as the elevation. Antennas comprise a number of radiating elements, which may each be an orthogonally-polarized element pair, such as a dipole (e.g., a crossed-dipole) with certain properties and a particular structure. Radiating elements can be arranged in columns, and antennas that have multiple columns can form arrays. While each radiation array may have its own radiation pattern, the RF effect of the entire array can depend on the spacing, phase shifts, and amplitude variations between its radiating elements. Together, these three variables can be used to describe the array factor pattern.

Multiplying the array factor pattern and the element pattern can yield the overall radiation pattern of the array antenna and define the far field.

(34) There are various types of radiating antenna elements, such as those with wire and aperture elements that include dipole and monopole elements. Aperture elements can also include slot elements. Some designs incorporate combinations of both types and can also be built over printed circuit boards (PCBs) or micro strip patches. Each antenna element has a radiation pattern, usually referred to as an element pattern, whose characteristics are determined by the overall design of the element. Some or all of the principles, embodiments, and/or aspects described herein can apply equally to the various types of antennas.

(35) A dipole radiating element transmits electromagnetic waves that result in radiation around it. Near the dipole antenna, the radiated energy is oscillating as it is flowing outwards. At any instant of time, the magnetic field is “behind” the electric field by half of a period (or half of the wavelength). The near field is composed of two regions: the reactive near field and the radiating near field (also called the Fresnel zone or region). In the far-field region (also called the Fraunhofer zone or region), the field components are transverse to the radial direction of the antenna. The far-field E (electric) and H (magnetic) strength decrease by inverse law $1/r$, where r is the distance from the antenna. Embodiments described herein define and account for a new region between/overlapping the Fresnel region and the Fraunhofer region, namely an “intermediate” (or intermediate-field) region.

(36) The subject disclosure describes, among other things, illustrative embodiments of an interference/PIM cancellation system (or block) that is capable of detecting interference/PIM in RF networks and/or mitigating (or cancelling) the interference/PIM. As the majority of interference/PIM generally exists in an intermediate (or intermediate-field) region (described in more detail below) that overlaps the near-field and far-field regions, in exemplary embodiments, the interference/PIM cancellation system is capable of cancelling interference/PIM not based on (e.g., not based at all on or not based only on) nulling of far-field energy, but rather by effecting polarization adjusting and/or phase adjusting (e.g., via electronic or physical adjustments of signals and/or component(s) of an antenna system) based on the detected impact of the interference/PIM in the intermediate region. In exemplary embodiments, the interference/PIM cancellation system may be configured to account (e.g., detect, cancel, or otherwise compensate) for the presence of interference/PIM in some or all of the far-field region, the intermediate region, and the near-field region.

(37) In various embodiments, polarization adjusting and/or phase adjusting (or shifting/delaying) may include performing one or more (e.g., mechanical) adjustments to one or more components included in, or associated with, an antenna system. In exemplary embodiments, the interference/PIM cancellation system may include, or be included in, an adjusting mechanism or system, which may be configured to perform polarization adjusting and/or phase shifting/delaying electronically, mechanically, electromechanically, and/or the like. The one or more components may include radiating elements (which may, e.g., include crossed-dipole antenna elements, MIMO-type antenna elements, and/or other types of radiating elements) of the antenna system, or more generally, any structural portion of radiating elements, such as, for example, feed port(s), ground/base plane(s), and/or the like.

(38) As one example, one or more embodiments of the interference/PIM cancellation system may be configured to control physical movements of one or more radiating elements of one or more antennas based on the detected interference/PIM.

(39) In embodiments where the interference/PIM cancellation system controls physical movements of radiating elements, the interference/PIM cancellation system can do so by causing radiating elements to be physically rotated (e.g., without adjusting or moving an antenna housing). This can include, for example, causing radiating elements in a first column of radiating elements to be rotated by a certain amount in a certain direction (e.g., from a default polarization configuration, such as $+45/-45$ degrees, to a different polarization configuration, such as a $+30/-60$ degree orientation or the like) and either keeping radiating elements in a second column of radiating

elements unchanged or causing radiating elements in the second column to be rotated by a certain amount in a certain direction, which may provide a polarization adjusting (e.g., mixing) effect where signals are projected in a different set of axes. This may result in one column receiving the interference/PIM and the other column receiving little to none of the interference/PIM, thereby enabling mitigation or cancellation of the interference/PIM (e.g., via selective signal/antenna extraction/usage).

(40) In one or more embodiments, the interference/PIM cancellation system may control the physical movements of radiating elements by additionally, or alternatively, causing the radiating elements to be shifted along a radial axis of the antenna (e.g., without adjusting or moving an antenna housing). This can include, for example, causing radiating elements in a first column of radiating elements to be shifted or displaced by a certain amount in a first direction along the radial axis, and either leaving radiating elements in a second column of radiating elements unmoved or causing radiating elements in the second column to be shifted or displaced by a certain amount in a second direction opposite the first direction, which may result in phase shifts or delays between signals associated with the radiating elements in the first column and signals associated with the radiating elements in the second column. This may similarly result in one column receiving the interference/PIM and the other column receiving little to none of the interference/PIM, thereby enabling mitigation or cancellation of the interference/PIM (e.g., via selective signal/antenna extraction/usage).

(41) In some embodiments, the interference/PIM cancellation system may be integrated in a radio (e.g., a remote radio head (RRH) or remote radio unit (RRU)), and may be configured to effect some or all of the polarization adjusting functionality and/or phase shifting/delaying functionality described herein. In certain embodiments, the interference/PIM cancellation system may be integrated in an antenna system (e.g., as part of smart antenna functionality), and may be configured to effect some or all of the polarization adjusting functionality and/or phase shifting/delaying functionality described herein independently of a radio (e.g., a remote radio head (RRH) or remote radio unit (RRU)) and/or based on commands from the radio.

(42) In various embodiments, the interference/PIM cancellation system may be configured to effect the polarization adjusting and/or phase shifting/delaying by additionally, or alternatively, performing (e.g., electronic) processing on (or adjustments to) signals associated with radiating elements. In such embodiments, the interference/PIM cancellation system may perform signal processing operations that define polarizations/projections or radiation patterns for signals associated with the various radiating elements, which may provide the aforementioned polarization adjusting (e.g., mixing) effect where signals may be projected in a different set of axes. This may similarly result in some radiating elements receiving the interference/PIM and other radiating elements receiving little to none of the interference/PIM, thereby enabling mitigation or cancellation of the interference/PIM (e.g., via selective signal/antenna extraction/usage). In certain embodiments, the processing may be implemented in cases where the antennas are integrated with a radio (e.g., an RRH or an RRU). For example, as described herein, such processing may be implemented in MIMO antennas, where the radio has access to each radiating element in each column/row of the antenna via a respective controller/transceiver.

(43) In various embodiments, the interference/PIM cancellation system may additionally, or alternatively, include, or be implemented, in one or more RF devices (e.g., RF circuits or the like) configured to perform polarization adjusting and/or phase shifting/delaying by altering/combining, in the RF domain, phase(s) and/or amplitudes of signals to be transmitted and/or signals that are received. The polarization adjusting and/or phase shifting/delaying can be based on the level(s)/characteristic(s) of determined PIM combination(s) that need to be addressed.

(44) In certain exemplary embodiments described herein, the polarization adjusting and/or phase shifting/delaying can be additionally, or alternatively, provided by configuring or adapting one or more properties of certain radiating elements of an antenna (e.g., without adjusting or moving an

antenna housing). In one or more embodiments, different shapes (or combination(s) of shapes), dimensions, electrical/magnetic properties, or a combination thereof may be selected or defined for radiating elements of a first set (or column) of radiating elements of an antenna relative to radiating elements of a second set (or column) of radiating elements of the antenna. As an example, the structure of each of a selected set of radiating elements of an antenna system may be altered (e.g., shifted, folded, bypassed, and/or the like). As another example, the structure of each of a selected set of radiating elements of an antenna system may be substituted with a different structure. By virtue of the difference in properties between the first and second columns of radiating elements (which can, for example, provide a polarization adjusting and/or phase shifting/delaying effect), the amount of interference/PIM that is received, or whether interference/PIM is received at all, may be selectively controlled. For example, this may similarly result in some radiating elements receiving the interference/PIM and other radiating elements receiving little to none of the interference/PIM, thereby enabling mitigation or cancellation of the interference/PIM (e.g., via selective signal/antenna extraction/usage).

(45) As also described herein, one or more embodiments of the interference/PIM cancellation system may include monitoring elements that are distinct from the main radiating elements of an antenna, and that are configured to detect interference/PIM in the far-field region, the intermediate region, and/or the near-field region. In some implementations, the main radiating elements of an antenna may additionally, or alternatively, be configured to detect interference/PIM in one or more of these regions.

(46) In various embodiments, the interference/PIM cancellation system may include hardware and/or software components (which may, for example, be integrated in the antenna or located externally to the antenna) configured to effect polarization adjusting and/or phase shifting/delaying by performing signal conditioning of uplink signals in a manner that (partially or fully) cancels interference/PIM therefrom.

(47) It is to be appreciated and understood that various embodiments described herein may address interference/PIM in the near-field or intermediate-field regions, and may have minimal to no impact to downlink signals in the far-field region (e.g., in a portion of the far-field region that excludes the intermediate-field region).

(48) It is also to be appreciated and understood that the various embodiments that provide polarization adjusting and/or phase shifting/delaying (for example, by performing adjustments for component(s) associated with an antenna system, such as radiating elements, structural portions of radiating elements, etc., by processing of signals associated with radiating elements, by defining of different (e.g., structural) properties for different sets of radiating elements of antenna(s), etc.) and/or signal conditioning to cancel detected interference/PIM may be combined in any manner and used together in any way (e.g., physical rotation of radiating elements and processing of signals associated with radiating elements may be performed together; physical shifting of radiating elements, signal conditioning, and defining of different structural properties for different sets of radiating elements may be performed together; etc.).

(49) In some implementations, in the various embodiments in which adjustments are made for component(s) associated with an antenna system (e.g., adjustments for structural portion(s) of radiating elements, physical rotation/shifting of radiating elements, etc.) and/or processing of signals associated with radiating elements is performed, some or all of these adjustments and/or signal processing may be performed automatically—e.g., by one or more smart detection/cancellation devices/systems/algorithms based on the detected interference/PIM.

(50) In other implementations, in the various embodiments in which adjustments are made for component(s) associated with an antenna system (e.g., adjustments for structural portion(s) of radiating elements, physical rotation/shifting of radiating elements, etc.) and/or processing of signals associated with radiating elements is performed, some or all of these adjustments and/or signal processing may be performed manually—e.g., by one or more operators or administrators in

light of the detected interference/PIM. In such implementations, one or more preset conditions or settings (e.g., relating to particular adjustments, such as rotation angles, shifting displacement values, polarizations/projections, etc.) may be available for user selection, and may, when selected, cause the appropriate polarization adjustments and/or phase shifts/delays to be effected accordingly.

(51) Based on an analysis of known or likely interference/PIM levels, characteristics, and/or combinations, proper selection of polarization adjusting parameters/values, phase shifts/delays, and/or the like may be determined and utilized to manipulate antenna systems. By providing polarization adjusting and/or phase shifting/delaying (e.g., via adjustments to structural portion(s) of radiating elements of the antenna system, physical rotation/shifting of radiating elements of the antenna system, processing of signals associated with radiating elements, and/or defining of different (e.g., structural) properties for different sets of radiating elements), as described herein, downlink signals can be manipulated or otherwise influenced in a way that minimizes or reduces the amount of interference/PIM that is received in the uplink, which can improve overall uplink performance and coverage. Radiating elements, and more generally, an antenna system may, therefore, be designed, configured, and/or controlled in order to optimize (or improve) the near-field and far-field regions for interference/PIM reduction. The principle of orthogonality between the different modes of transmission can also be taken into account, where interference/PIM source(s) minimally interact with transmissions, thereby reducing the level of interference/PIM detected/received by a communications system.

(52) While the distinction between field components is clear mathematically, the fields overlap (e.g., the demarcation of the spatial field regions may be subjective), and thus there may be substantial far-field and near-field radiative components in the closest-in near-field reactive region. In various implementations, alternative methodologies or approaches may be employed, including approaches that focus on minimizing reflected energy based on the summation of the near field, the intermediate field, and the far field. This can be achieved, for example, by simulating an antenna's near field and optimizing (or improving) its properties.

(53) In exemplary embodiments, various techniques described herein, including methods for polarization adjusting and/or phase shifting/delaying and the like, can be exploited in time-division duplex (TDD) systems and/or frequency-division duplex (FDD) systems to relax, loosen, or otherwise decrease the number of system implementation requirements, such as those relating to guard times/bands in TDD and frequency separation in FDD.

(54) Various techniques described herein for manipulating/altering/adjusting signal transmission/reception and/or component(s) of an antenna system (e.g., radiating elements, structural portion(s) of radiating elements, etc.) may be applied to the uplink and/or downlink in a TDD communications system in order to reduce or eliminate the guard band. In exemplary embodiments, the polarization of the uplink can be adjusted relative to the polarization of the downlink, or vice versa, such that the uplink polarization and the downlink polarization are different from one another. For instance, in cases where one or more MIMO antennas that provide parallel transmissions are employed in a TDD system, polarization adjusting may be applied for some or all of the radiating elements utilized during downlink operations such that the polarization thereof is in a first polarization, and may be similarly applied for some or all of the radiating elements utilized during uplink operations such that the polarization thereof is in a different (e.g., orthogonal) polarization. Doing so creates an additional dimension of separation that permits a smaller guard band to be used, which can provide improved network speeds. In extreme cases, guard bands can even be eliminated, where downlink and uplink transmissions may overlap or coexist without interference by virtue of the use of different, orthogonal polarizations.

(55) Various techniques described herein for manipulating/altering/adjusting signal transmission/reception and/or component(s) of an antenna system (e.g., radiating elements, structural portion(s) of radiating elements, etc.) may also be applied to the uplink in a TDD

communications system in order to address any direct interference with FDD system signals and/or any PIM generated by mixing of FDD system signals. In exemplary embodiments, polarization adjusting can be employed in the TDD system to separate the TDD uplink from FDD system signals. Here, the TDD uplink may be deployed in particular polarization(s) that enable the TDD uplink to avoid receiving signals from the FDD systems and/or any PIM generated by mixing of FDD system signals.

(56) Various techniques described herein for manipulating/altering/adjusting signal transmission/reception and/or component(s) of an antenna system (e.g., radiating elements, structural portion(s) or radiating elements, etc.) may also be applied to the uplink and/or downlink in an FDD communications system in order to reduce or eliminate the need for duplexers (e.g., by relaxing or loosening duplexer requirements). In exemplary embodiments, for example, polarization adjusting, can be employed in an FDD system (e.g., as an additional way) to separate the downlink and uplink frequencies. Here, the downlink and the uplink may be deployed in different (e.g., orthogonal) polarizations. That is, for example, the polarization of the uplink can be adjusted relative to the polarization of the downlink, or vice versa, such that the uplink polarization and the downlink polarization are different from one another. Doing so creates an additional dimension of separation that permits the use of fewer or less sophisticated duplexers (e.g., duplexers with fewer stages), since signal gain (in dB) that might otherwise be offered through the use of more duplexer stages can instead be provided via polarization adjusting. This can advantageously enable massive MIMO implementations in FDD. In extreme cases, duplexers can even be eliminated altogether by virtue of the use of different, orthogonal polarizations.

(57) One or more aspects of the subject disclosure include a method. The method can comprise receiving, via an antenna, a communication signal generated by a communication device. Further, the method can include detecting interference in the communication signal, wherein the interference is generated by one or more interference sources, wherein the interference is detected by monitoring a near field region of the antenna, an intermediate field region of the antenna, a far field region of the antenna, or any combinations thereof, wherein the monitoring excludes monitoring only the far field region of the antenna.

(58) One or more aspects of the subject disclosure include a device, comprising a circuit coupled to an antenna and facilitating operations. The operations can include receiving, via the antenna, a signal generated by a communication device. Further, the operations can include detecting interference in the signal, wherein the interference is generated by one or more sources, wherein the interference is detected by monitoring a near field region of the antenna, an intermediate field of the antenna, a far field region of the antenna, or any combinations thereof, wherein the monitoring excludes monitoring only the far field region of the antenna.

(59) One or more aspects of the subject disclosure include a non-transitory machine-readable medium, comprising executable instructions that, when executed by a processing system including a processor, facilitate performance of operations. The operations can include receiving, via an antenna, a communication signal generated by a communication device. Further, the operations can include detecting interference in the communication signal, wherein the interference is generated by one or more interference sources, wherein the interference is detected by monitoring a near field region of the antenna, an intermediate field region of the antenna, or both with or without monitoring a far field region of the antenna.

(60) Other embodiments are described in the subject disclosure.

(61) Referring now to FIG. 1A, a block diagram is shown illustrating an example, non-limiting embodiment of a system **100** in accordance with various aspects described herein. For example, system **100** can facilitate, in whole or in part, detection of interference/PIM in a communications system and performing of action(s), such as polarization adjusting and/or phase shifting/delaying, as described herein, that result in mitigation/cancellation of the interference/PIM. In particular, a communications network **125** is presented for providing broadband access **110** to a plurality of data

terminals **114** via access terminal **112**, wireless access **120** to a plurality of mobile devices **124** and vehicle **126** via base station or access point **122**, voice access **130** to a plurality of telephony devices **134**, via switching device **132** and/or media access **140** to a plurality of audio/video display devices **144** via media terminal **142**. In addition, communications network **125** is coupled to one or more content sources **175** of audio, video, graphics, text and/or other media. While broadband access **110**, wireless access **120**, voice access **130** and media access **140** are shown separately, one or more of these forms of access can be combined to provide multiple access services to a single client device (e.g., mobile devices **124** can receive media content via media terminal **142**, data terminal **114** can be provided voice access via switching device **132**, and so on).

(62) The communications network **125** includes a plurality of network elements (NE) **150**, **152**, **154**, **156**, etc. for facilitating the broadband access **110**, wireless access **120**, voice access **130**, media access **140** and/or the distribution of content from content sources **175**. The communications network **125** can include a circuit switched or packet switched network, a voice over Internet protocol (VoIP) network, Internet protocol (IP) network, a cable network, a passive or active optical network, a 4G, 5G, or higher generation wireless access network, WIMAX network, UltraWideband network, personal area network or other wireless access network, a broadcast satellite network and/or other communications network.

(63) In various embodiments, the access terminal **112** can include a digital subscriber line access multiplexer (DSLAM), cable modem termination system (CMTS), optical line terminal (OLT) and/or other access terminal. The data terminals **114** can include personal computers, laptop computers, netbook computers, tablets or other computing devices along with digital subscriber line (DSL) modems, data over coax service interface specification (DOCSIS) modems or other cable modems, a wireless modem such as a 4G, 5G, or higher generation modem, an optical modem and/or other access devices.

(64) In various embodiments, the base station or access point **122** can include a 4G, 5G, or higher generation base station, an access point that operates via an 802.11 standard such as 802.11n, 802.11ac or other wireless access terminal. The mobile devices **124** can include mobile phones, e-readers, tablets, phablets, wireless modems, and/or other mobile computing devices.

(65) In various embodiments, the switching device **132** can include a private branch exchange or central office switch, a media services gateway, VoIP gateway or other gateway device and/or other switching device. The telephony devices **134** can include traditional telephones (with or without a terminal adapter), VoIP telephones and/or other telephony devices.

(66) In various embodiments, the media terminal **142** can include a cable head-end or other TV head-end, a satellite receiver, gateway or other media terminal **142**. The display devices **144** can include televisions with or without a set top box, personal computers and/or other display devices.

(67) In various embodiments, the content sources **175** include broadcast television and radio sources, video on demand platforms and streaming video and audio services platforms, one or more content data networks, data servers, web servers and other content servers, and/or other sources of media.

(68) In various embodiments, the communications network **125** can include wired, optical and/or wireless links and the network elements **150**, **152**, **154**, **156**, etc. can include service switching points, signal transfer points, service control points, network gateways, media distribution hubs, servers, firewalls, routers, edge devices, switches and other network nodes for routing and controlling communications traffic over wired, optical and wireless links as part of the Internet and other public networks as well as one or more private networks, for managing subscriber access, for billing and network management and for supporting other network functions.

(69) FIG. 1B depicts an exemplary, non-limiting embodiment of a telecommunication communications system **180** functioning within, or operatively overlaid upon, the communications network **100** of FIG. 1A in accordance with various aspects described herein. For example, system **180** can facilitate, in whole or in part, detection of interference/PIM in a communications system

and performing of action(s), such as polarization adjusting and/or phase shifting/delaying, as described herein, that result in mitigation/cancellation of the interference/PIM. As shown in FIG. 1B, the telecommunication system **180** may include mobile units **182**, **183A**, **183B**, **183C**, and **183D**, a number of base stations, two of which are shown in FIG. 1B at reference numerals **184** and **186**, and a switching station **188** to which each of the base stations **184**, **186** may be interfaced. The base stations **184**, **186** and the switching station **188** may be collectively referred to as network infrastructure.

(70) During operation, the mobile units **182**, **183A**, **183B**, **183C**, and **183D** exchange voice, data or other information with one of the base stations **184**, **186**, each of which is connected to a conventional land line communication network. For instance, information, such as voice information, transferred from the mobile unit **182** to one of the base stations **184**, **186** is coupled from the base station to the communication network to thereby connect the mobile unit **182** with, for example, a land line telephone so that the land line telephone may receive the voice information. Conversely, information, such as voice information may be transferred from a land line communication network to one of the base stations **184**, **186**, which in turn transfers the information to the mobile unit **182**.

(71) The mobile units **182**, **183A**, **183B**, **183C**, and **183D** and the base stations **184**, **186** may exchange information in either narrow band or wide band format. For the purposes of this description, it is assumed that the mobile unit **182** is a narrowband unit and that the mobile units **183A**, **183B**, **183C**, and **183D** are wideband units. Additionally, it is assumed that the base station **184** is a narrowband base station that communicates with the mobile unit **182** and that the base station **186** is a wideband digital base station that communicates with the mobile units **183A**, **183B**, **183C**, and **183D**.

(72) Narrow band format communication takes place using, for example, narrowband 200 kilohertz (KHz) channels. The Global system for mobile phone systems (GSM) is one example of a narrow band communication system in which the mobile unit **182** communicates with the base station **184** using narrowband channels. Alternatively, the mobile units **183A**, **183B**, **183C**, and **183D** communicate with the base station **186** using a form of digital communications such as, for example, 3GPP Long Term Evolution (LTE), code-division multiple access (CDMA), Universal Mobile Telecommunications System (UMTS), or other next generation wireless access technologies. LTE, for instance, is a wireless broadband communication standard that covers many different frequency bands depending on the geographical region. The terms narrowband and wideband referred to above can be replaced with sub-bands, concatenated bands, bands between carrier frequencies (carrier aggregation), and so on, without departing from the scope of the subject disclosure.

(73) The switching station **188** is generally responsible for coordinating the activities of the base stations **184**, **186** to ensure that the mobile units **182**, **183A**, **183B**, **183C**, and **183D** are constantly in communication with the base station **184**, **186** or with some other base stations that are geographically dispersed. For example, the switching station **188** may coordinate communication handoffs of the mobile unit **182** between the base station **184** and another base station as the mobile unit **182** roams between geographical areas that are covered by the two base stations.

(74) In various circumstances, the telecommunication system **180**, and more particularly, one or more of the base stations **184**, **186** can be undesirably subjected to interference. Interference can represent emissions within band (narrowband or wideband), out-of-band interferers, interference sources outside cellular (e.g., TV stations, commercial radio or public safety radio), interference signals from other carriers (inter-carrier interference), interference signals from UEs operating in adjacent base stations, PIM, and so on. Interference can represent any foreign signal that can affect communications between communication devices (e.g., a UE served by a particular base station).

(75) FIG. 2A is a block diagram illustrating an example, non-limiting embodiment of a system **200** functioning within, or operatively overlaid upon, the communications network **100** of FIG. 1A

and/or the communications system **180** of FIG. **1B** in accordance with various aspects described herein. As depicted, the system **200** can include an antenna (or antenna system) **201**. In various embodiments, the antenna **201** may include multiple radiating elements. In one or more embodiments, the antenna **201** may include multiple columns and/or rows of radiating elements, forming an antenna array. In certain embodiments, the antenna **201** may include multiple arrays or panels. As shown in FIG. **2A**, the antenna **201** can be associated with various spatial regions, including a reactive near-field region **200c**, a radiating near-field region **200d**, a far-field region **200f**, and an intermediate region **200i**. One or more UEs/users **200u** may be located in the far-field region **200f**. The intermediate region **200i** may include a zone that overlaps a portion of the radiating near-field region **200d** and a portion of the far-field region **200f**.

(76) In various antenna deployments, antennas (or more particularly, the uplink) may be subject to interference and/or PIM—e.g., a PIM source **200p**. PIM interference may be due to nonlinearities external to antennas that, when subjected to electromagnetic waves emitted by antenna elements in the downlink frequency band, generate reflections at frequencies in the uplink frequency band. PIM interference may also be due to antenna(s) of a base station transmitting and receiving in downlink and uplink frequency bands that are close to one another, or due to different antennas of different base stations transmitting in frequency bands that are close to one another. In these cases, intermodulation of signals transmitted in different (but sufficiently close) frequencies can result in passive signals falling into an uplink frequency band. In any case, interference/PIM decreases uplink sensitivity and thus negatively impacts uplink coverage, reliability, performance, and data speeds.

(77) As depicted in FIG. **2A**, the antenna **201** can be disposed or deployed on a structure, such as a building rooftop. It is to be appreciated and understood that the antenna **201** can be deployed in any suitable manner. As one example, the antenna **201** may be mounted on one or more towers where few or no objects may be located nearby (e.g., an unobstructed antenna on a tower), and thus a far-field representation may be adequate. As another example, multiple antennas **201** may be located within close proximity to one another (e.g., within a threshold distance from one another), where the antennas **201** may or may not have overlapping degrees of coverage, and thus the near-field region may have an impact on antenna performance. As yet another example, one or more antennas **201** may be deployed on building rooftop(s) in densely-populated areas (e.g., towns or cities). In this example, the antennas **201** may be located within close proximity to one another and may have overlapping degrees of coverage and/or be obstructed by nearby external objects, such that the near-field and intermediate field regions may have an impact on antenna performance.

(78) The far field (e.g., the far-field region **200f**) may be defined by a distance $r \gg 2L \cdot \sup{2/(\lambda)}$, where L is the length of the antenna and λ is the wavelength of a transmitted signal. Antenna specifications are generally based on the far-field region. In the far-field region, the electric and magnetic fields are perpendicular to each other, the ratio of E/H is the free space propagation, and the antenna pattern is not a function of the distance r . The near field, and more particularly the reactive near-field (e.g., the reactive near-field region **200c**), can be defined by $r < \lambda/2\pi$. In the radiating near-field region (or the Fresnel region) (e.g., the radiating near-field region **200d**), for $\lambda/2\pi < r < 2L \cdot \sup{2/(\lambda)}$, the radiated power density is greater than the reactive power density and $1/r \cdot \sup{3}$ is very small, but the $1/r$ and $1/r \cdot \sup{2}$ terms are still dominant. For the intermediate region (e.g., the intermediate region **200i**), where $r > 2L \cdot \sup{2/(\lambda)}$, the term $1/r$ is larger than the other terms but not yet dominant. In all of the regions other than the far-field region, the electric and magnetic fields are not perpendicular. Various exemplary embodiments described herein account for the transition region—i.e., the intermediate region-between/overlapping the near-field and far-field regions, which can be represented differently, mathematically.

(79) The electric and magnetic field equations for a dipole, such as a dipole antenna element of the antenna **201** (e.g., in a case where the antenna **201** includes dipole elements) may include:

$$(80) \quad E_r = \frac{IoL\cos}{2} \frac{e^{j[t-\frac{r}{c}]}}{o} \left(\frac{1}{cr^2} + \frac{1}{j} \frac{1}{r^3} \right); \quad (EQ1) \quad E = \frac{IoL\sin}{4} \frac{e^{j[t-\frac{r}{c}]}}{o} \left(\frac{j}{c^2 r} + \frac{1}{cr^2} + \frac{1}{j} \frac{1}{r^3} \right); \quad (EQ2)$$

$$E = 0; \quad (EQ3) \quad H = \frac{IoL\sin}{4} \frac{e^{j[t-\frac{r}{c}]}}{o} \left(\frac{j}{cr} + \frac{1}{r^2} \right); \quad (EQ4) \quad \text{and} \quad H_r = 0 \quad (EQ5) \quad H_\theta = 0, \text{ where}$$

$E_{\text{sub.r}}$ and $H_{\text{sub.r}}$ are the radial electric and magnetic fields components, where $E_{\text{sub.}\phi}$ and $H_{\text{sub.}\phi}$ are the azimuth electric and magnetic fields components, and where $E_{\text{sub.}\theta}$ and $H_{\text{sub.}\theta}$ are the polar electric and magnetic components.

Here, $I_{\text{sub.0}}$ is the peak value of the current flowing in the radiating element (e.g., dipole), $\epsilon_{\text{sub.0}}$ is the permittivity or dielectric constant of free space, $\omega = 2\pi f$, where f is the frequency, c is the speed of light, L is the length of the dipole, and r is the distance from the dipole.

(81) For the intermediate region, when $r > L_{\text{sup.2}}/(\lambda)$, the second and the third terms in $E_{\text{sub.}\theta}$ become zero, and the second term in $H_{\text{sub.}\phi}$ becomes zero, resulting in the following equations:

$$(82) \quad E_r \cong \frac{IoL\cos}{2} \frac{e^{j[t-\frac{r}{c}]}}{o cr^2}; \quad (EQ6) \quad E \cong \frac{j}{4} \frac{IoL\sin}{o} \frac{e^{j[t-\frac{r}{c}]}}{c^2 r}; \quad (EQ7) \quad \text{and}$$

$$H \cong \frac{j}{4} \frac{IoL\sin}{o cr} \frac{e^{j[t-\frac{r}{c}]}}{c}. \quad (EQ8)$$

(83) For the far-field region, when $r \gg L_{\text{sup.2}}/(\lambda)$, $E_{\text{sub.r}}$ becomes zero, the second and third terms in $E_{\text{sub.}\theta}$ become zero, and the second term in $H_{\text{sub.}\phi}$ becomes zero, resulting in the following equations:

$$(84) \quad E \cong \frac{j}{4} \frac{IoL\sin}{o c^2 r} \frac{e^{j[t-\frac{r}{c}]}}{c}; \quad (EQ9) \quad \text{and} \quad H \cong \frac{j}{4} \frac{IoL\sin}{o cr} \frac{e^{j[t-\frac{r}{c}]}}{c}. \quad (EQ10)$$

(85) Antennas are typically designed based on the desired behavior in the far-field region i.e., in accordance with certain design goals relating to beamwidth, half-power bandwidth, directivity, and back lobe radiation. Antennas are also designed not to generate PIM. Smart antennas are configured to minimize interference, generally by identifying the direction of the interference and creating nulls in that direction to avoid reception and transmission. For example, FIG. 2B depicts example null patterns **202** for interference sources in accordance with various aspects described herein. In certain embodiments, the antenna **201** may be operated using nulling techniques in which the energy reflected from the far-field is detected and used for optimization decisions. In such embodiments, the performance of the antenna(s) may thus be optimized (or improved) based on (e.g., based only on) the far field and not on the near field or the intermediate field.

(86) Because the majority of interference/PIM is usually in the intermediate region, it can be advantageous to adapt/adjust antenna configurations and/or perform signal processing that enables such interference/PIM to be accounted for (i.e., detected, cancelled, or otherwise compensated for). Take, for example, a typical signal, which may be a sum of desired uplink signal(s) and undesired signal(s). A desired signal may be a signal originating from an end user device that is typically in the far field of an antenna. PIM, on the other hand, may be generated from a combination of far-field, intermediate-field, and/or near-field interfering signals, a substantial portion of which may originate from the intermediate-field region of the antenna. Thus, in a case where the far-field region for a 700 MHz, 2 meter (m) long antenna starts at about 19m (e.g., about 120 feet) from the antenna, and the radiating near field starts at about 2.8m (e.g., about 10 feet) from the antenna, most of the interference/PIM signals originate from sources located in the radiating near field or the intermediate region (e.g., 10 to 120 feet from the antenna). In exemplary embodiments, therefore, the antenna **201** may be configured to perform optimization based on near-field, intermediate-field, and/or far-field regions rather than the far-field region alone. In various embodiments, the antenna **201** may be capable of cancelling or mitigating interference/PIM as described herein.

(87) FIG. 2C is a block diagram illustrating an example, non-limiting embodiment of a communications system **203** having an antenna **201a** with monitoring port(s) for interference/PIM detection, and functioning within, or operatively overlaid upon, the communications network **100** of FIG. 1A and/or the communications system **180** of FIG. 1B in accordance with various aspects described herein. The communications system **203** may include a radio **203r** (e.g., a remote radio

head or unit) and an interference/PIM detection control device **203d**. Although not shown in FIG. 2C, in one or more embodiments, the radio **203r** may be communicatively coupled to the interference/PIM detection control device **203d**. In various embodiments, the antenna **201a** may be the same as, may be similar to, or may otherwise correspond to the antenna **201** of FIG. 2A. As shown in FIG. 2C, the antenna **201a** may include multiple columns of (e.g., main) radiating elements **203g** and one or more columns of monitoring antenna elements **203m**, which may be referred to herein as “patches.” It will be appreciated and understood that the term patch, as used herein, may not imply and/or may not be limited to patch antennas—that is, patches described herein can be constructed from any suitable antenna design, including but not limited to patch antennas, and can represent one or more antennas that form a patch. In various embodiments, the monitoring elements **203m** may be included in, incorporated into, or otherwise built into, the antenna **201a**, and may be configured to detect interference/PIM signals originating from the intermediate-field region. The monitoring elements **203m** may be configured to maximize the reception of such signals from the intermediate-field region, and minimize the reception of signals from the far-field region of the antenna **201a**.

(88) The antenna **201a** and/or the main radiating elements **203g** therein may be any shape or combination of shapes with any suitable dimensions, polarizations, etc. The antenna **201a** may also include any suitable number of columns and rows of radiating elements **203g**. The monitoring elements **203m** may also be any shape or combination of shapes with any suitable dimensions, polarizations, etc., and can be configured based on interference/PIM cancellation needs. The monitoring elements **203m** can be disposed amongst the radiating element **203g** in any suitable manner, such as between various columns of the radiating elements **203g**, between radiating elements of the same column of radiating elements **203g**, and/or the like.

(89) As shown in FIG. 2C, the antenna **201a** may include, for the main radiating elements **203g**, one or more outputs **203t** on the antenna **201a**'s housing that can be communicatively coupled (e.g., via analog/RF line(s)) to the radio **203r**. The antenna **201a** may also include, as monitoring port(s) for the monitoring elements **203m**, one or more outputs **203u** on the housing that can be communicatively coupled (e.g., via analog/RF line(s) or other line(s) suitable to carry data from the monitoring elements **203m**) to the interference/PIM detection control device **203d**. In various embodiments, the interference/PIM detection control device **203d** may, through the use of digital signal processing, analyze and/or examine the interference/PIM signals received from the monitoring elements **203m**, and determine appropriate cancellation measures/decisions. Although FIG. 2C shows the interference/PIM detection control device **203d** as being an external device, in certain embodiments, the interference/PIM detection control device **203d** (e.g., some or all of the functionality thereof) may instead be included, or integrated, in the antenna **201a** or the radio **203r**.

(90) In various embodiments, and as shown in FIG. 2C, the antenna **201a** may (e.g., optionally) include an interference/PIM cancellation block **203c** integrated therein. The interference/PIM cancellation block **203c** may be configured to provide mitigation or cancellation of undesired interference/PIM signals, such as by performing signal conditioning on signals received by the radiating elements **203g**. In some embodiments, the output of the monitoring elements **203m** can be utilized within the antenna (e.g., by the interference/PIM cancellation block **203c**) to address the interference/PIM. In these embodiments, the interference/PIM cancellation block **203c** may include some or all of the functionalities of the interference/PIM detection control device **203d** (and/or other related cancellation devices) for detecting interference/PIM in the output of the monitoring elements **203m** and/or for determining and applying cancellation measures. Alternatively, the interference/PIM cancellation block **203c** may (e.g., after the output of the monitoring elements **203m** is provided to the interference/PIM detection control device **203d** for analysis) obtain data/command(s) from the interference/PIM detection control device **203d** with regard to interference/PIM mitigation or cancellation, and effect the mitigation/cancellation based on the data/command(s).

(91) In certain embodiments, the output of the monitoring elements **203m** can additionally, or alternatively, be routed externally to one or more other ports (e.g., on the antenna **201a**'s housing) coupled to one or more other systems/devices to obtain additional benefits, such as determining additional cancellation measures, obtaining insight into characteristics/location of the PIM source, performing additional signal analyses and data collection, and/or the like.

(92) Cancellation measures may include dynamic modification of antenna parameters, control of multiple antennas as a cluster, and/or informing other cancellation devices in the RF or digital path (including, for example, a Common Public Radio Interface (CPRI) or enhanced CPRI (eCPRI)) of the interference/PIM conditions, which may enable such other cancellation devices to cancel with greater efficiency and accuracy. Crest Factor Reduction (CFR) algorithms are focused on reducing the dynamic range of a power amplifier without sacrificing too much error vector magnitude (EVM). CFR can help the amplifier operate more efficiently. In one or more embodiments, one or more CFR algorithms can be used—e.g., within a radio or remote radio head—for interference/PIM cancellation. In certain embodiments, the parameters/control of the CFR algorithm(s) can be coupled with (e.g., provided to) the interference/PIM cancellation block **203c** and/or the interference/PIM detection control device **203d** for use in determining/applying cancellation measures. Alternatively, the CFR algorithm(s) can be coupled with (e.g., provided to) other interference/PIM cancellation devices disposed in the RF or digital path to achieve increased cancellation performance.

(93) It is to be appreciated and understood that the interference/PIM cancellation block **203c** may be a high-level representative block that provides one or more functions of various embodiments described herein, including, for example, embodiments that enable mitigation/cancellation of interference/PIM by causing adjustment(s) to be made to one or more component(s) of an antenna system (such as adjustments to structural portions of radiating elements, physical rotation/shifting of radiating elements, and/or the like) and/or by processing signals associated with radiating elements.

(94) In various embodiments, the antenna **201a** may include different sets of main radiating elements. For example, the antenna **201a** may include a first set of radiating elements configured to operate in a first frequency band, and a second set of radiating elements configured to operate in a second frequency band (see, for example, FIG. 2G, where an antenna may include a first set of radiating elements **207g**, **207h** configured to operate in one frequency band, and a second set of radiating elements **207g'**, **207h'** configured to operate in a different frequency band). In certain embodiments, some or all of the monitoring elements **203m** may be incorporated in the second set of radiating elements and configured for interference/PIM detection in the second frequency band.

(95) In various embodiments, some or all of the first set of radiating elements and/or the second set of radiating elements may be configured for interference/PIM detection in the first/second frequency bands. In these embodiments, the monitoring elements **203m** (and thus the outputs **203t**) may or may not be included or needed. In implementations where the monitoring elements **203m** and outputs **203u** are not included or needed, the detected interference/PIM signals may be routed via the outputs **203t**; alternatively, the detected interference/PIM signals may nevertheless be routed via the outputs **203t**, but the outputs **203t** may be communicatively coupled to the first/second set of main radiating elements (rather than to the monitoring elements **203m**).

(96) FIG. 2D is a block diagram **204** illustrating example, non-limiting embodiments of two communications systems, including a first communications system **204v** having a single antenna **201b**, and a second communications system **204w** having two antennas **201b'** and **201b''**, where each of the communications systems **204v** and **204w** may be functioning within, or operatively overlaid upon, the communications network **100** of FIG. 1A and/or the communications system **180** of FIG. 1B in accordance with various aspects described herein. As shown in FIG. 2D, the antenna **201b** of the first communications system **204v** may include a column **204m** of radiating elements **204g** communicatively coupled to an RRU **204i** (for a certain frequency band, such as Band 1), and

a column **204n** of radiating elements **204h** communicatively coupled to an RRU **204k** (for a certain frequency band, such as Band 2). As also depicted, the antenna **201b'** of the second communications system **204w** may include a column **204m'** of radiating elements **204g'** communicatively coupled to an RRU **204i'** (for a certain frequency band, such as Band 1), and the antenna **201b''** of the second communications system **204w** may include a column **204n'** of radiating elements **204h'** communicatively coupled to an RRU **204k'** (for a certain frequency band, such as Band 2). In various embodiments, one or more of the antennas **201b**, **201b'**, **201b''** may be the same as, may be similar to, or may otherwise correspond to the antenna system **201** of FIG. 2A.

(97) In some embodiments, in the first communications system **204v**, the antenna **201b** may include multiple columns of radiating elements (e.g., multiple columns **204m** and/or multiple columns **204n**) and/or there may be additional antennas **201b** communicatively coupled to the RRUs **204i**, **204k** or to additional RRUs. Additionally, in some embodiments, in the second communications system **204w**, the antenna **201b'** may include multiple columns of radiating elements (e.g., multiple columns **204m'**), the antenna **201b''** may include multiple columns of radiating elements (e.g., multiple columns **204n'**), and/or there may be additional antennas **201b'** and/or **201b''** communicatively coupled to the RRUs **204i'**, **204k'** or to additional RRUs. Furthermore, while the radiating elements **204g**, **204h**, **204g'**, and **204h'** are shown as crossed-dipole elements, it is to be appreciated and understood that each of the antennas **201b**, **201b'**, and **201b''** may additionally, or alternatively, include one or more other types of elements.

(98) In either of the first communications system **204v** and the second communications system **204w**, mixing of Band 1 and Band 2 downlink signals (DL1 and DL2, respectively) can result in interference/PIM. For example, PIM can produce energy in (e.g., that “lands” in) either the Band 1 uplink channel (UL1) or the Band 2 uplink channel (UL2), causing interference. In exemplary embodiments, various radiating elements of the first and second communications systems **204v** and **204w** may be capable of being physically rotated. In various embodiments, for example, the radiating elements **204h** of column **204n** of the antenna **201b** may be configured to physically rotate (**204z**) (e.g., about a radial axis of the antenna **201b**, shown as the X-axis) and/or the radiating elements **204g** of column **204m** of the antenna **201b** may be configured to physical rotate (e.g., about the X-axis). Similarly, in various embodiments, the radiating elements **204h'** of column **204n'** of the antenna **201b''** may be configured to physically rotate (**204z'**) (e.g., about the X-axis) and/or the radiating elements **204g'** of column **204m'** of the antenna **201b'** may be configured to physically rotate (e.g., about the X-axis). Physical rotation of orthogonal dipoles in one column relative to orthogonal dipoles in another column can be equivalent to, or result in, polarization adjusting (e.g., mixing), where signals are projected in a different set of axes, which can impact the near-field (and/or intermediate-field) signal strength in (e.g., each of) the orthogonal dipole transmitting/receiving antennas, thereby enabling interference/PIM mitigation or cancellation.

(99) In the first communications system **204v**, the RRUs **204i** and **204k** and the antennas (i.e., columns of radiating elements) may be 2Tx and 2Rx. Both bands (Bands 1 and 2) may be transmitted using separate crossed-dipole columns **204m** and **204n** within a single antenna **201b**, where the separate RRUs **204i** and **204k** share the antenna **201b**, where Band 1 is associated with two ports of the antenna **201b** and with the first column **204m** of crossed-dipole elements **204g**, and where Band 2 is associated with another two ports of the antenna **201b** and with the second column **204n** of crossed-dipole elements **204h**. Here, by rotating the crossed-dipole elements associated with Band 1 (e.g., some or all of the radiating elements **204g** in the column **204m**), the crossed-dipole elements associated with Band 2 (e.g., some or all of the radiating elements **204h** in the column **204n**), or both (e.g., some or all of the radiating elements **204g** in the column **204m** and some or all of the radiating elements **204h** in the column **204n**), the receipt/detection of PIM by the antenna **201b** (or by the first communications system **204v** overall) can be altered. Similarly, in the second communications system **204w**, separate 2Tx and 2Rx RRUs **204i'** and **204k'** and antennas (i.e., antennas **201b'** and **201b''**) may be employed. Here, by rotating the crossed-dipole elements

associated with Band 1 (e.g., some or all of the radiating elements **204g'** in the column **204m'** of the antenna **201b'**), the crossed-dipole elements associated with Band 2 (e.g., some or all of the radiating elements **204h'** in the column **204n'** of the antenna **201b''**), or both (e.g., some or all of the radiating elements **204g'** in the column **204m'** of the antenna **201b'** and some or all of the radiating elements **204h'** in the column **204n'** of the antenna **201b''**), the receipt/detection of PIM by the antennas **201b'** and/or **201b''** (or by the second communications system **204w** overall) can be altered.

(100) In exemplary embodiments, an interference/PIM cancellation block (an interference/PIM cancellation block **204c** of FIG. 2E, which may be the same as, may be similar to, or may correspond to the interference/PIM cancellation block **203c** of FIG. 2C) may be configured to provide rotational control of the radiating elements of the first and/or second communications systems **204v** and **204w**. In various embodiments, the choice of which column of radiating elements to rotate and/or the rotational amount or angle can be based on determined interference/PIM levels or characteristics, which may be detected by monitoring elements (e.g., the monitoring elements **203m** of FIG. 2C and/or an interference/PIM detection control device similar to the interference/PIM detection control device **203d**) or may be known to exist or determined to likely exist (e.g., in accordance with historical and/or measurement data). Based on such interference/PIM information, the interference/PIM cancellation block may cause various radiating elements (or column(s) of radiating elements) to rotate accordingly. For example, in the first communications system **204v**, the interference/PIM cancellation block may cause (e.g., each of) the radiating elements **204h** in the column **204n** of the antenna **201b** to rotate from a default polarization (e.g., of +45/-45 degrees) to a different polarization (e.g., of +30/-60 degrees or another orthogonal combination), while the radiating elements **204g** in the column **204m** may remain in the default polarization (e.g., of +45/-45 degrees). In any case, antenna configurations with a variety of differently polarized columns of radiating elements (e.g., a mix of vertically-polarized radiating elements and cross-polarized radiating elements; or columns of radiating elements with different orthogonal polarization combinations) can, therefore, be obtained.

(101) Appropriate rotation of select radiating elements (or columns of radiating elements) may result in, for example, one or more columns of radiating elements receiving or detecting some or all of the interference/PIM and one or more other columns of radiating elements receiving or detecting little to none of the interference/PIM, with minimal to no impact to the far field pattern. In exemplary cases, therefore, interference/PIM may be eliminated (zeroed out) or near eliminated with respect to a first column of orthogonal dipoles, and a second column of orthogonal dipoles may receive/detect some or all of the interference/PIM, thus enabling a receiving system to select the signal from the first column of orthogonal dipoles (the "clean" signal) for use. Here, while diversity may be lost (e.g., about 3 dB), interference/PIM cancelation of 15+ dB can be achieved, resulting in a net 12+ dB benefit. Configuring the communications systems such that certain column(s) of radiating elements are essentially interference/PIM free can also enable selective use thereof for certain types of traffic (e.g., high priority traffic or the like).

(102) It is to be appreciated and understood that the interference/PIM cancellation block may be configured to cause rotation of radiating elements in any suitable manner. In exemplary embodiments, for example, an antenna (e.g., the antennas **201b**, **201b'**, and/or **201b''**) may include one or more motor assemblies (e.g., a shaft and linear motor or other gear and rod mechanism, such as the motor(s) **207w** and/or **207y** and shaft(s) **207x** and/or **207z** shown in diagram **207** of FIG. 2G) communicatively coupled to radiating elements and configured to control rotary motion thereof (e.g., to fractions of a degree in accuracy and with minimal to no overshoot, or the like). In some embodiments, each column of radiating elements may be (e.g., independently) controllable by a respective motor assembly. In one or more embodiments, the interference/PIM cancellation block may be configured to cause radiating elements to rotate via remote electronic/electrical tilt.

(103) FIG. 2E is a block diagram illustrating an example, non-limiting embodiment of a

communications system **205** that includes the single antenna **201b** of FIG. 2D and that functions within, or is operatively overlaid upon, the communications network **100** of FIG. 1A and/or the communications system **180** of FIG. 1B in accordance with various aspects described herein. As shown in FIG. 2E, the antenna **201b** may (e.g., similar to the antenna **201a** of FIG. 2C) include an interference/PIM cancellation block (e.g., an interface/PIM cancellation block **204c**), and may be communicatively coupled to a radio (e.g., a radio **204r**) via outputs (e.g., outputs **204t**) and to an interference/PIM detection control device (e.g., an interference/PIM detection control device **204d**) via other outputs (e.g., outputs **204u**). Here, and as described above with respect to FIG. 2D, either or both of the column **204m** of radiating elements **204g** and the column **204n** of radiating elements **204h** may be rotatably controllable by the interference/PIM cancellation block **204c** based on detected levels/characteristics of interference/PIM.

(104) FIG. 2F is a block diagram illustrating an example, non-limiting embodiment of a communications system **206** having an antenna **201c**, and functioning within, or operatively overlaid upon, the communications network **100** of FIG. 1A and/or the communications system **180** of FIG. 1B in accordance with various aspects described herein. As shown in FIG. 2F, the antenna **201c** may include a column **206m** of radiating elements **206g** communicatively coupled to a dual band RRU **206j**, and a column **206n** of radiating elements **206h** communicatively coupled to the dual band RRU **206j**. In various embodiments, the antenna **201c** may be the same as, may be similar to, or may otherwise correspond to the antenna system **201** of FIG. 2A. The dual band RRU **206j** and dual band antennas (i.e., columns of radiating elements) may be 4Tx and 4Rx. While FIG. 2F shows a single RRU and a single antenna, it is to be appreciated and understood that, in alternate embodiments, separate RRUs and separate antennas may be employed for Band 1 and Band 2.

(105) In exemplary embodiments, the crossed-dipole elements (e.g., one or more of the radiating elements **206g** of the column **206m**) associated with one band, such as Band 1, may be linearly shiftable (**206s**) along the X-axis and/or the crossed-dipole elements (e.g., one or more of the radiating elements **206h** of the column **206n**) associated with the other band, such as Band 2, may be linearly shiftable (**206s'**) along the X-axis. Shifting one column of radiating elements relative to the other column of radiating elements can alter the reception/detection of PIM by the antenna **201c** (or by the communications system **206** overall). In particular, when a distance $d_{sub.1}$ between the column **206m** and the PIM source **200p** is equal to a distance $d_{sub.2}$ between the column **206n** and the PIM source **200p**, the downlink carriers may sum constructively. In contrast, if the difference between the distances $d_{sub.1}$ and $d_{sub.2}$ is half of the wavelength, the downlink carriers may sum destructively, reducing or eliminating the PIM.

(106) In exemplary embodiments, an interference/PIM cancellation block (not shown in FIG. 2F, but that may be the same as, may be similar to, or may correspond to the interference/PIM cancellation block **203c** of FIG. 2C and/or the interference/PIM cancellation block **204c** of FIG. 2E) may be configured to control physical shifting (**206s**, **206s'**) of radiating elements of the antenna **201c**. In various embodiments, the choice of which column of radiating elements to shift and/or the displacement amount and direction of shifting can be based on determined interference/PIM levels or characteristics, which may be detected by monitoring elements (e.g., the monitoring elements **203m** of FIG. 2C and/or an interference/PIM detection control device similar to the interference/PIM detection control device **203d**) or may be known to exist or determined to likely exist (e.g., in accordance with historical and/or measurement data). Based on such interference/PIM information, the interference/PIM cancellation block may cause various radiating elements (or column(s) of radiating elements) to displace along the X-axis accordingly. For example, the interference/PIM cancellation block may cause (e.g., each of) the radiating elements **206h** of the column **206n** of the antenna **201c** to shift in the X-direction by a certain amount, and may cause (e.g., each of) the radiating elements **206g** of the column **206m** of the antenna **201c** to shift in the opposite direction by a certain amount, and/or the like.

(107) Appropriate (e.g., linear) displacement of select radiating elements (or columns of radiating elements) may result in, for example, one or more columns of radiating elements receiving or detecting some or all of the interference/PIM and one or more other columns of radiating elements receiving or detecting little to none of the interference/PIM, with minimal to no impact to the far field pattern. Similar to the embodiments described above with respect to FIGS. 2D and 2E, for example, in exemplary cases, interference/PIM may be eliminated (zeroed out) or near eliminated with respect to a first column of orthogonal dipoles, and a second column of orthogonal dipoles may receive/detect some or all of the interference/PIM, thus enabling a receiving system to select the signal from the first column of orthogonal dipoles (the “clean” signal) for use.

(108) It is to be appreciated and understood that the interference/PIM cancellation block may be configured to cause shifting of radiating elements in any suitable manner. In exemplary embodiments, for example, an antenna (e.g., the antenna **201c**) may include one or more motor assemblies communicatively coupled to radiating elements and configured to control motion thereof along the radial axis of the antenna. In some embodiments, each column of radiating elements may be (e.g., independently) controllable by a respective motor assembly.

(109) In some embodiments, physical rotation/shifting of monitoring elements, such as the monitoring elements **203m** of FIG. 2C, may also be effected in order to adjust interference/PIM detection parameters of those elements.

(110) Some antennas include columns of 2, 4, and (sometimes) 8 radiating elements. As the number of radiating elements increases, the beam width in the elevation pattern decreases. In other words, adding more radiating elements in the same column of an antenna can permit narrower beamwidths in the elevation direction. An antenna may generally have less than 10 degrees in the elevation plane. In some instances, and in various embodiments described herein, a single column antenna may have a radiation pattern in the azimuth plane of about 65 to 90 degrees of half-power beamwidth. FIG. 2H depicts example radiation patterns **208a**, **208b**, and **208c** of various single column antennas (e.g., a 2-radiating element antenna, a 4-radiating element antenna, and an 8-radiating element antenna, respectively) in accordance with various aspects described herein. In some embodiments, one or more of the single column antennas shown in FIG. 2H may be the same as, may be similar to, or may otherwise correspond to the antenna **201** of FIG. 2A.

(111) In certain instances, an antenna may include multiple columns or rows of radiating elements, where each of the radiating elements may be connected to a respective transceiver. In such instances, longitudinal or azimuth beamforming scenarios may depend on the phase and amplitude of the signal at the input of the antenna. FIG. 2J depicts example radiation patterns **210a** and **210b** of an antenna with two columns of radiating elements and an antenna with two rows of radiating elements, respectively, in accordance with various aspects described herein. In some embodiments, one or more of the antennas shown in FIG. 2J may be the same as, may be similar to, or may otherwise correspond to the antenna **201** of FIG. 2A.

(112) Beamforming enables the creation of sophisticated radiation patterns with increased signal strength or sensitivity in a certain direction and/or reduced interference to and from another direction. The quantity of radiating elements in the beamforming array may affect the complexity of the beamforming patterns. For example, an antenna array consisting of eight elements may allow for a higher degree of pattern shaping as compared to a four-element array.

(113) Different amplitude and phase values may result in beamforming. In various embodiments, a matrix network can create fixed beam forming. In certain embodiments, the antenna **201** of FIG. 2A, for example, may include one or more fixed twin beam antennas. A fixed beam antenna can provide pre-set alignment of the main beams while providing optimal overlap, which has multiple applications in cell splitting. FIG. 2K depicts an example fixed twin beam radiation pattern **211** in accordance with various aspects described herein. Implementation of antenna configurations in which multiple (e.g., twin) beams or the like are provided/utilized are described herein. The antenna configurations of FIGS. 2D and 2F, for example, may enable port monitoring and beam

switching to selectively identify/capture “clean” and/or interference/PIM signals.

(114) For an M-element equally-spaced linear array that uses variable amplitude element excitations and phase scanning, the array factor can be represented by:

$$(115) \quad AF(\theta) = \sum_{m=0}^{M-1} A_m e^{jm(\frac{d \cos(\theta) + \phi_m}{c})}, \quad (\text{EQ11})$$

where

$$(116) \quad \phi_m = \tau d \cos(\theta_0), \quad \tau = 2/f,$$

f is the frequency, and d is the spacing between the radiating elements.

(117) In exemplary embodiments, one or more properties of certain radiating elements of an antenna may be configured or adapted to effect polarization adjusting and/or phase shifting/delaying, and thereby achieve interference/PIM mitigation or cancellation. In one or more embodiments, different shapes, dimensions, electrical/magnetic properties, or a combination thereof may be selected or defined for radiating elements of a first column of radiating elements of an antenna relative to radiating elements of a second column of radiating elements of the antenna. By virtue of the difference in properties between the first and second columns of radiating elements, the amount of interference/PIM that is received, or whether interference/PIM is received at all, may be selectively controlled. Take, for example, an 8-radiating element antenna. Designing or adapting half (4) of the 8 radiating elements in one configuration and the other four in a different configuration can provide a degree of freedom for optimizing (or improving) near-field and intermediate-field regions. In other words, with 4 radiating elements of each kind, the far field may “appear” similar to a case where all 8 radiating elements are identical, but the near-field and intermediate-field regions of the “mix” of 4 radiating elements of one configuration and 4 radiating elements of another configuration may “appear” differently, thereby enabling mitigation/cancellation of interference/PIM in the near-field and/or intermediate-field regions without impacting the far field. Processing requirements may include the need to update amplitude and phase beam weight values (e.g., on the order of 1 millisecond (ms)). Additionally, complex algorithms (which may be implemented in the radio, a baseband processing unit, and/or a third-party device) may be utilized to support pattern synthesis.

(118) In various embodiments, the interference/PIM cancellation block may be configured to cause one or more properties, such as a structure, of one or more radiating elements to be changed or altered, in any suitable manner. In exemplary embodiments, for example, one or more motor assemblies may be communicatively coupled to radiating element(s) (or one or more structural portions thereof) and/or other structural component(s), and configured to control motion of such radiating element(s) and/or structural portion(s)/component(s) such that an overall structure of the radiating element(s) or each of the radiating element(s) is altered. In some embodiments, each column of radiating element(s) and/or associated structural portion(s)/component(s) may be (e.g., independently) controllable by a respective motor assembly.

(119) Therefore, in a general case, having radiating elements in a first column of an antenna with structures/properties that are different from the structures/properties of radiating elements in a second column of the antenna, can provide signal phase manipulation, enabling generation of different (e.g., left/right) radiation patterns, such as two or more lobes.

(120) For an M-element not equally spaced linear array that uses variable amplitude element excitations and phase scanning, the array factor can be represented by:

$$(121) \quad AF(\theta) = \sum_{m=0}^{M-1} A_m e^{jm(\frac{d \cos(\theta) + \phi_m}{c})}. \quad (\text{EQ12})$$

(122) Here, in exemplary embodiments, each radiating element may be made to be slightly different (e.g., in structure or other property) from its neighboring radiating element and/or the radiating elements may be arranged in an interleaved 2 equally spaced array pattern or other suitable pattern, such that different or desired near-field properties are obtained. Optimizing the configuration of radiating elements in this way can enable PIM reduction without impacting the far

field.

(123) In various embodiments, beamforming by phase shifting can be achieved using ferrite phase shifters at RF or intermediate frequency (IF). In certain embodiments, phase shifting can be additionally, or alternatively, implemented via digital signal processing at baseband.

(124) In this way, whether antenna embodiments described herein passively or actively (e.g., based on feedback from an integrated or external device, such as the interference/PIM detection control device **203d** of FIG. 2C, the interference/PIM detection control device **204d** of FIG. 2E, or other detection device(s)) treat legitimate signals (e.g., free, or near-free, of interference/PIM) differently from non-legitimate signals, interference/PIM can be reduced or cancelled (e.g., via selective signal/antenna extraction/usage, such as via selection of radiating elements of the antenna).

(125) In some embodiments, altering of one or more properties of monitoring element(s), such as the monitoring elements **203m** of FIG. 2C, may also be effected in order to adjust interference/PIM detection parameters of those elements.

(126) The Antenna Interface Standards Group (AISG) defines and maintains standards for controlling/monitoring the interface between a base station and various equipment at a tower top, such as antennas with remote electrical tilt, amplifiers, RRHs, etc. Various versions of base communication standards have been released, including version 3 (AISG v3.0). AISG v3.0 provides for device control ports connectable to different base station controllers, as well as controller mapping of RF system interconnections of devices connected to a central bus. AISG v3.0 specifies the interface between a base station and antenna line devices (ALDs), which may be manageable units (e.g., subunits, such as remote electrical tilt, top-mounted amplifiers, antenna sensors, etc.) associated with base station antenna systems, and describes the common behavior of ALDs with AISG interfaces. An ALD may have one or more AISG interfaces controllable by a base station.

(127) In exemplary embodiments, the AISG interface can be leveraged to facilitate overall control of interference monitoring/detection, and/or polarization adjusting and/or phase shifting/delaying (such as via physical movement/alteration of radiating elements (or structural portions) thereof and/or via electronic-based adjustments). An AISG interface may be included in an antenna (e.g., antenna **201b** or the like, as shown in FIG. 2E by reference numeral **205i**; although AISG interface(s) may be included in other antenna embodiments, such as the antenna **201** of FIG. 2A, the antenna **201a** of FIG. 2C, the antenna **201c** of FIG. 2F, etc.), and may be communicatively coupled to an interference/PIM cancellation block (e.g., the interference/PIM cancellation block **204c** or the like) and/or an interference/PIM detection control device (e.g., the interference/PIM detection control device **204d** or the like). The AISG interface may be incorporated in an antenna in any suitable manner—e.g., the AISG interface may be implemented in an interference/PIM cancellation block; the AISG interface may be separate from, but integrated with, an interference/PIM cancellation block; the AISG interface may include an interference/PIM cancellation block; or the like. In exemplary embodiments, the AISG interface may be controllable (e.g., by the interference/PIM cancellation block) to cause the physical movements (e.g., rotation, shifting, etc.) of radiating elements and/or changes or alterations to properties/structures of radiating elements described herein. In some embodiments, for example, the AISG interface may be coupled to one or more motors or the like for effecting such movements/alterations, and may provide appropriate signal(s) thereto based on data/commands from the interference/PIM cancellation block. In this way, one or more standard interfaces, such as AISG interface(s), can be employed to facilitate polarization adjusting and/or phase shifting/delaying to mitigate/cancel interference/PIM in a communication system.

(128) Smart antenna system technology relates to intelligent antennas, phased arrays, Spatial Division Multi Access (SDMA), spatial processing, digital beamforming, adaptive antenna systems, and others. Smart antenna systems are customarily categorized as either switched beam with a finite number of fixed, predefined patterns or combining strategies (sectors) or as adaptive

arrays with an infinite number of patterns (scenario-based) that are adjusted in real-time. The dual purpose of a smart antenna system is to augment the signal quality of the radio-based system through more focused transmission of radio signals, while enhancing capacity through increased frequency reuse. In exemplary embodiments, the newly-identified intermediate-field region can be leveraged to optimize (or improve) antenna performance.

(129) Active Antenna Systems (AAS) use flexible cell splits (e.g., vertical or horizontal) and/or beamforming to provide increased system flexibility and performance. An AAS base station uses multiple transceivers on an antenna array to produce a radiation pattern that can be dynamically adjusted. Spatial selectivity in both the transmit and receive directions is important. For example, compared to fixed beam antennas, an AAS may experience different spatial selectivity since it does not achieve full spatial selectivity until after digital baseband processing of the multiple elements in the array.

(130) With recent advances in active antenna technology, it is possible to deploy base stations with a large number of antenna elements to enhance cell capacity and coverage. Antenna elements can be deployed in two-dimensional (2D) arrays, providing horizontal (azimuth) as well as vertical beamforming. In urban environments, with high rise buildings, this can improve indoor coverage and increase capacity. Wireless networks with base stations having a large number of antenna elements are known as massive MIMO, or Elevation Beamforming/Full Dimension (EB/FD) MIMO systems. Beamforming can rely on some or all of the techniques described herein to further optimize (or improve) performance.

(131) For a 2D array of M by N elements not equally spaced and that uses variable amplitude element excitations and phase scanning, the array factor can be represented by:

$$(132) \quad AF(\theta) = \prod_{m=0}^{M-1} \prod_{n=0}^{N-1} A_{mn} e^{jm(\frac{r \cdot \text{Math} \cdot r_{mn} + \dots}{c})}, \quad (\text{EQ13}) \quad \text{where}$$

$$\hat{r} \cdot \text{Math} \cdot r_{mn} = d \sin(\theta) \cos(\phi) + d \sin(\theta) \sin(\phi) + d \cos(\theta).$$

FIG. 2L depicts an example radiation pattern **212a** of a first antenna array **212c** (i.e., an 8×8 array) and an example radiation pattern **212b** of a second antenna array **212d** (e.g., a 16×16 array) in accordance with various aspects described herein. In various embodiments, one or more of the antenna arrays **212c** and **212d** may correspond to the antenna **201** of FIG. 2A.

(133) Examples of fixed beam techniques include butler matrix, Blass matrix and Wullenweber array. Adaptive beam forming methods include the block adaptive method and the sample-by-sample method. Block implementation of the adaptive beamformer uses a block of data to estimate the adaptive beamforming weight vector, and is known as sample matrix inversion (SMI). The sample-by-sample method updates the adaptive beamforming weight vector with each sample. Sample-by-sample methods include the least mean square (LMS) algorithm, the constant modulus algorithm (CMA), the least square CMA, and the recursive least square (RLS) algorithm. In various embodiments, some or all of these methods/algorithms may be adapted and utilized. For example, some or all of these methods/algorithms may be modified to account for variations in antenna array elements.

(134) FD-MIMO systems are distinct from the MIMO systems of LTE and LTE-Advanced standards in that a large number of antennas is employed at the eNodeB (eNB). As the number of eNB antennas M by N increases, cross-correlation of two random channel realizations becomes zero such that inter-user interference in the downlink can be controlled via a simple linear precoder. Such a benefit can be realized, however, only when perfect channel state information (CSI) is available at the eNB. While CSI acquisition in TDD systems is relatively simple due to the channel reciprocity, such is not the case for FDD systems, where the time variation and frequency response of the channel are measured via downlink reference signals (RS) and returned to the eNB after the quantization. Identifying potential issues of CSI acquisition and developing the proper solutions are, therefore, important for successful commercialization of FD-MIMO systems. Interference/PIM minimization or cancellation, as described herein, can have a direct impact thereto that be exploited

using non-symmetrical elements.

(135) FD-MIMO systems also employ active antennas with 2D planar arrays. In active antenna-based systems, gain and phase are controlled by the active components, such as a power amplifier (PA) and a low noise amplifier (LNA) attached to each antenna element. In a 2D-structured antenna array, the radio wave can be controlled on both the vertical (elevation) and horizontal (azimuth) directions such that control of the transmit beam in three-dimensional (3D) space is possible. This type of wave control mechanism is also referred to as 3D beamforming. 2D AAS can accommodate a large number of antennas without increasing deployment space.

(136) In smart antenna beamforming, when 64 linear antenna arrays, for example, are deployed in a horizontal direction, under the assumption that the antenna spacing is half of the wavelength ($\lambda/2$) and the system is using an LTE carrier frequency (e.g., 2 GHz), horizontal spacing of 3 m may be required. Due to the limited space on a rooftop or mast, such a spacing requirement might be burdensome for most cell sites. In contrast, when antennas are arranged in a square array, relatively small spacing is needed for a 2D antenna array (e.g., 1.0 m $\times$ 0.5 m with a dual-polarized 8 $\times$ 8 antenna array). Embodiments for interference/PIM minimization or cancellation, described herein, can enable further reductions in the sizes of such arrays.

(137) Smart antenna systems (which can leverage the SDMA method) employ adaptive algorithm(s) that enable signal extraction. While an antenna by itself is capable of converting electrical signals into electromagnetic waves or vice versa, the adaptive algorithm(s) provide the intelligence of a smart antenna system. An adaptive algorithm can be designed to account for challenges that prevent an antenna from combining bands. Embodiments for interference/PIM minimization or cancellation, described herein, can enable further enhancements to adaptive algorithm(s).

(138) In exemplary embodiments, an interference/PIM cancellation system may be configured to effect polarization adjusting and/or phase shifting/delaying by performing processing (e.g., mathematically) on (or adjustments to) signals associated with (e.g., to be transmitted by) various radiating elements, based on detected interference/PIM. In various embodiments, methods employed by a MIMO 2D array antenna for beamforming and nulling (of interference at certain points in space), for example, can be modified or otherwise replaced with advanced algorithm(s) configured to effect rotation of certain group(s) of radiating elements of the antenna. Whereas embodiments described above with respect to FIGS. 2D and 2E involve physical rotation of radiating elements to effect polarization adjusting, here, “electronic” rotation can be employed to create polarization selective nulling patterns. Changing the polarization of certain radiating elements' transmissions and receptions, while maintaining orthogonality, can reduce/eliminate interference/PIM (e.g., in the near-field or intermediate-field regions), with minimal to no effect to downlink signal patterns at user equipment (UEs) (e.g., in the far field). In various embodiments, the polarization of signals to be transmitted and the polarization of received signals may be different from one another.

(139) FIG. 2M is a block diagram illustrating an example, non-limiting embodiment **213** of polarization adjusting and associated equations in accordance with various aspects described herein. As shown in FIG. 2M, the polarization of signals transmitted by an orthogonally-polarized pair of elements, such as a crossed-dipole antenna **213u**, **213v**, may be changed. Here, suppose signals s.sub.1(t) and s.sub.2(t) are transmitted by the +45 degree dipole **213u** and the -45 degree dipole **213v**, respectively—that is, where signal s.sub.1(t) may be transmitted with a +45 degree polarization and signal s.sub.2(t) may be transmitted with a -45 degree polarization. In a case where (e.g., based on a desire to mitigate or cancel interference/PIM, such as likely PIM combinations) there is a need to “rotate” or modify the polarization of the signal s.sub.1(t) to 90 degrees (e.g., horizontal) and the polarization of the signal s.sub.2(t) to 0 degrees (e.g., vertical), equations 213p can be applied to derive new signals s.sub.1'(t) and s.sub.2'(t). As shown, the new signals can be computed by mixing (e.g., gain mixing) the original signals s.sub.1(t) and s.sub.2(t),

which is equivalent to a “rotation” of the crossed-dipole antenna by an angle **213w** (here, for example, 45 degrees in the counter-clockwise direction). In this way, when signals **s.sub.1'(t)** and **s.sub.2'(t)** are transmitted from the +45 dipole and the -45 dipole, it is equivalent to transmitting **s.sub.1(t)** and **s.sub.2(t)** from dipoles oriented at 90 degrees and 0 degrees. Selection of certain polarizations and/or radiation patterns can be viewed as a projection of signals in different axes. (140) It is to be appreciated and understood that the weights in polarization adjusting are real values (rather than complex values), and operate by “mathematically” rotating receive antenna dipoles to match the polarization of a desired signal. It is also to be appreciated that selection of radiating elements (e.g., which columns of radiating elements) for which polarization adjusting is to be applied may be based on the level(s)/characteristic(s) of determined PIM combination(s) that need to be addressed. Additionally, polarization adjusting can be effected for transmit only, for receive only, or for both transmit and receive. In cases where polarization adjusting is effected for both transmit and receive, in one or more embodiments, the polarizations selected for the transmit and the receive may be the same, similar, or different and/or the polarization adjusting may be performed in the same manner, in a similar manner, or differently for the transmit and the receive. In one or more embodiments, a radio, such as an RRH or RRU (which may have individual access to each radiating element of the antenna), may be configured to perform the electronic/mathematic rotation. For example, a MIMO 2D array antenna may be integrated with the radio. In some respects, this may be advantageous over implementations where a radio is not integrated with the antenna(s), such as where one vendor supplies the radio and a different vendor supplies the antenna(s), which may be the case in some or all of the systems described above with respect to FIGS. 2D, 2E, and 2F, and which may require a concerted effort between the vendors to arrive at the desired technical implementation.

(141) It is further to be appreciated and understood that, since beamforming scanning generally occurs in the azimuth plane and beam narrowing generally occurs in the elevation plane, algorithms that rely on the near field and the intermediate-field may result in tighter relations between azimuth and elevation antenna performance.

(142) In various embodiments, the interference/PIM cancellation system may additionally, or alternatively, include, or be implemented, in one or more RF devices (e.g., RF circuits or the like) configured to perform polarization adjusting and/or phase shifting/delaying by altering/combining, in the RF domain, phase(s) and/or amplitudes of signals to be transmitted and/or signals that are received. The polarization adjusting and/or phase shifting/delaying can be based on the level(s)/characteristic(s) of determined PIM combination(s) that need to be addressed.

(143) FIG. 2N is a block diagram illustrating an example, non-limiting embodiment of a communications system **214**, in which multiple antennas **201d**, **201d'**, **201d''**, and **201d'''** (each with monitoring port(s) for interference/PIM detection) are deployed, functioning within, or operatively overlaid upon, the communications network **100** of FIG. 1A and/or the communications system **180** of FIG. 1B in accordance with various aspects described herein. In one or more embodiments, the multiple antennas **201d**, **201d'**, **201d''**, and **201d'''** (e.g., as a combination) may correspond to the antenna **201** of FIG. 2A. In various embodiments, one or more of the antennas **201d**, **201d'**, **201d''**, and **201d'''** may be similar to one or more of the antenna **201a** of FIG. 2C and the antenna **201b** of FIG. 2E. For example, in certain embodiments, one or more of the antennas **201d**, **201d'**, **201d''**, and **201d'''** may include multiple columns of (e.g., main) radiating elements and (e.g., optionally) one or more columns of monitoring antenna elements (e.g., similar to the monitoring elements **203m** of FIG. 2C).

(144) As shown in FIG. 2N, the communications system **214** may include a radio **214r** (e.g., a remote radio head or unit), an interference/PIM detection control device **214d**, a baseband-based interference/PIM canceller **214b**, and an RF-based interference/PIM canceller **214f**. As depicted, one or more of the antennas **201d**, **201d'**, **201d''**, and **201d'''** may include a first set of output(s) communicatively coupled to the radio **214r** via the RF-based interference/PIM canceller **214f**, and

a second set of output(s) interconnected with one another and communicatively coupled to the interference/PIM detection control device **214d**. Here, for example, the antennas **201d**, **201d'**, **201d''**, and **201d'''** may be configured to “share” a PIM detection module.

(145) Exemplary embodiments of the communications system **214** may operate in multiple bands (e.g., two or more frequency bands). In various embodiments, signals in a certain frequency (or range of frequencies) may be transmitted in certain polarization(s) and other signals in another frequency (or range of frequencies) may be transmitted in different polarization(s), where the signals at different frequencies may interact (or mix) with one another when various techniques described herein are implemented. This can involve, for example, polarization adjusting and/or phase shifting/delaying, where one or more component(s) of the antennas **201d**, **201d'**, **201d''**, and **201d'''**, such as radiating elements, structural portions of radiating elements (e.g., feed port(s), ground plane(s), and/or the like), etc. are adjusted and/or signals associated with radiating elements are manipulated/processed. For instance, adjustment(s) can be performed via physical/electronic rotation/shifting of the radiating elements (or signals associated therewith) in certain columns of one or more of the antennas **201d**, **201d'**, **201d''**, and **201d'''** and/or between antennas that operate/react together, resulting in interference/PIM being picked up by some radiating elements of the communications system **214** and not by other radiating elements of the communications system **214**. Polarization adjusting and/or phase shifting/delaying can be generally applied or can be applied for the particular frequencies (or ranges of frequencies) that interact with one another. In various embodiments, the interference/PIM detection control device **214d** may detect interference/PIM (e.g., received by the radiating elements and/or by any monitoring elements included in the antennas) over lines **214y**, and may provide data/controls via lines **214z** to the RF-based interference/PIM canceller **214f** and/or the baseband-based interference/PIM canceller **214b** to enable such polarization adjusting and/or phase shifting/delaying by the RF-based interference/PIM canceller **214f** and/or the baseband-based interference/PIM canceller **214b**. For example, the RF-based interference/PIM canceller **214f** and/or the baseband-based interference/PIM canceller **214b** may provide feedback that effects polarization adjusting and/or phase shifting/delaying for select radiating elements of select antennas—e.g., for the uplink and/or the downlink. In certain embodiments, the feedback (which may, for example, be based on, or include, information from collected near-field, intermediate-field, and/or far field energy) may cause radiating elements/antennas to be remotely tilted (e.g., down or up) and/or emit beams in certain directions, such as the azimuth direction, etc. In one or more embodiments, one or more of the antennas **201d**, **201d'**, **201d''**, and **201d'''** may be configured to adjust signal transmission and reception based on instructions/communications with cancellation systems/devices included in, or associated with, the radio **214r**, the baseband processing unit, as well as other system(s) positioned on a CPRI link, an eCPRI link, and/or the like.

(146) In various embodiments, and as shown in FIG. 2N, some or all of the antennas **201d**, **201d'**, **201d''**, and **201d'''** may (e.g., optionally) include an interference/PIM cancellation block (e.g., interference/PIM cancellation blocks **214c**, **214c'**, **214c''**, and **214c'''**) integrated therein and configured to provide mitigation or cancellation of undesired interference/PIM signals. In some of these embodiments, the interference/PIM detection control device **214d** may provide data/controls to one of more of these interference/PIM cancellation blocks (e.g., similar to that described above with respect to FIG. 2C) to facilitate activation of certain interference/PIM mitigation/cancellation measures (e.g., polarization adjusting and/or phase shifting/delaying via electronic/RF processing of signals associated with radiating elements, controlling of physical movements of radiating elements and/or structural portions thereof, such as by physically rotating radiating elements, shifting radiating elements, etc., as described herein). In one or more embodiments, an interference/PIM cancellation block may include some or all of the functionalities of the RF-based interference/PIM canceller **214f** and/or the baseband-based interference/PIM canceller **214b**, in which case one or more of the RF-based interference/PIM canceller **214f** and/or the baseband-

based interference/PIM canceller **214b** may or may not be included or needed. In certain embodiments, an interference/PIM cancellation block may include some or all of the functionalities of the interference/PIM detection control device **214d**, in which case the interference/PIM detection control device **214d** may or may not be included or needed. In some embodiments, the interference/PIM detection control device **214d** may be integrated in the baseband unit, the radio **214r**, and/or one or more of the antennas **201d**, **201d'**, **201d''**, and **201d'''**.

(147) In this way, even in multi-antenna communications systems (where pre-coding is used to map modulation symbols onto the different antennas to achieve the best possible data reception at the receiver, and where the type of pre-coding may depend on the multi-antenna technique employed as well as on the numbers of layers/antenna ports), various embodiments described herein relating to polarization adjusting and/or phase shifting/delaying can be applied to improve overall system performance and coverage.

(148) Certain implementations are provided herein using Coordinated Multi-Point (CoMP) transmission/reception. This method is considered by 3GPP as a tool to improve coverage, cell-edge throughput, and/or spectral efficiency. Depending on the location of a UE, the UE may be able to receive signals from multiple cell sites and the UE's transmissions may be received at multiple cell sites regardless of the system load. If the transmissions from the multiple cell sites are coordinated for the downlink, the performance can be significantly increased. This coordination can be simple, as in the techniques that focus on interference or PIM avoidance, or more complex, as in the case where the same data is transmitted from multiple cell sites. In exemplary embodiments, for the uplink, various polarization adjusting-based and/or phase shifting/delaying-based interference/PIM cancellation techniques described herein (e.g., with an emphasis on the near field and the intermediate field) can be employed to take advantage of reception at multiple cell sites so as to significantly improve the link performance.

(149) Certain implementations enhance the requirement reference points at which core RF requirements are specified based on the 3GPP. The two main approaches used today include defining the requirements at the boundary of the transceiver and defining the requirements at the far field of the antenna. Exemplary embodiments enable incorporation of additional requirements at the intermediate field and the near field of the antenna as well. Downlink MIMO Rel-12 features two CSI enhancements: 4Tx Precoding Matrix Index (PMI) feedback codebook enhancement and aperiodic feedback Physical Uplink Shared Channel (PUSCH) mode **3-2**. The CSI enhancements enable the eNB to complete delivery of data packets earlier than with legacy CSI feedback, thus improving spectral efficiency. The Rel-12 4Tx codebook enhancement mainly targets cross-polarized antennas and, thus, reuse of the 8Tx dual codebook structure. In addition to the enhanced codebook, a new aperiodic CSI feedback PUSCH mode **3-2** is introduced in Rel-12 with increased CSI accuracy, since it provides both sub-band Channel Quality Indication (CQI) and sub-band performance management (PM). The addition of PIM and interference parameters (e.g., relating to various embodiments described herein, such as those that implement polarization adjusting and/or phase shifting/delaying) can further enhance the codebook.

(150) Dynamic spectrum sharing (DSS) is a technique where LTE spectrum allocation is dynamically shared between 5G and LTE users. Depending on the load and traffic demand from both technologies, the base station dynamically changes the spectrum allocation to use more of the spectrum for 5G or LTE. As a result, the split between LTE and 5G New Radio (NR) in the spectrum changes over time. DSS is especially appealing to operators given that its rollout is possible through a software upgrade on existing base station hardware. The 3GPP only provides guidance on how to configure systems to enable efficient spectrum sharing for standalone (SA) and non-standalone (NSA) deployments. In exemplary embodiments, antenna(s) can be controlled to optimize for both 4G/LTE and 5G services by reducing PIM and interference generated from the 4G/LTE and 5G requirements so as to enable smooth/seamless DSS operation.

(151) In TDD, time, rather than frequency, is used to separate the transmission and reception of

signals, and thus a single frequency is assigned to a UE for both the uplink and the downlink. In TDD, two time slots—one for the uplink and one for the downlink may be assigned to each UE, with a short data burst in each direction. FIG. 2P is a block diagram illustrating an example time frame **216** in a TDD communications system in accordance with various aspects described herein. In various embodiments, one or more of the antennas described herein (e.g., the antenna **201** of FIG. 2A, the antenna **201a** of FIG. 2C, the antenna **201b** of FIG. 2E, etc.) can be employed in the TDD communications system and operated in a frequency F1. As depicted in FIG. 2P, the TDD time frame **216** may include a time slot **216a** for downlink operations, a time slot **216b** for uplink operations, a time slot **216c** for downlink operations, and so on. A guard time/band **216t** between transmit and receive streams may generally be needed in TDD. Time split between the forward and reverse channels is sufficiently small that the transmission and reception appear to be simultaneous and continuous to users. The guard time in TDD is intended as a time allowance for round-trip propagation delay. This time interval may need to be sufficiently long in order to prevent the transmit and receive signals from clashing. TDD is thus generally employed where the distance between the transmitter and receiver is generally small; otherwise, the channel efficiency may drop and the time guard may need to be rather long.

(152) Since TDD typically permits a higher number of time slots in favor of one direction of transmission over the other (e.g., usually in favor of the downlink), various techniques described herein for polarization adjusting may be applied to the uplink and/or downlink in a TDD communications system in order to reduce or eliminate the guard band. In exemplary embodiments, for example, techniques described above with respect to FIGS. 2C, 2E, 2F, 2M, etc. can be employed in a TDD system (e.g., as an additional way) to separate the downlink and the uplink. Here, the downlink and the uplink may be deployed in different (e.g., orthogonal) polarizations, P1 and P2, respectively. In exemplary embodiments, the polarization of the uplink can be adjusted relative to the polarization of the downlink, or vice versa, such that the uplink polarization P1 and the downlink polarization P2 are different from one another.

(153) For instance, in cases where one or more MIMO antennas that provide parallel transmissions are employed in a TDD system, polarization adjusting may be applied for some or all of the radiating elements utilized during downlink operations such that the polarization thereof is in the polarization P1, and may be similarly applied for some or all of the radiating elements utilized during uplink operations such that the polarization thereof is in the polarization P2. Doing so creates an additional dimension of separation that permits a smaller guard band to be used, which can provide improved network speeds. In extreme cases, guard bands can even be eliminated, where downlink and uplink transmissions may overlap or coexist without interference by virtue of the use of different, orthogonal polarizations P1 and P2.

(154) TDD systems may be deployed in frequency bands that are about 2.5 GHz and higher in order to address guard band delay constraints. However, a TDD system may coexist, or otherwise have overlapping operative ranges, with FDD systems (e.g., in other regions, such as nearby countries) at the same frequency, which can result in direct interference. In other cases, such FDD systems may operate at lower frequencies, but signals from those FDD systems can mix and generate PIM in the TDD band(s), which can negatively impact the uplink in the TDD system. In exemplary embodiments, various techniques described herein for polarization adjusting may be applied to the uplink in a TDD communications system in order to address any direct interference with FDD system signals and/or any PIM generated by mixing of FDD system signals. In exemplary embodiments, techniques described above with regard to processing of signals or adjustment(s) for component(s) of an antenna system (e.g., as described above with respect to FIGS. 2C, 2E, 2M, etc.) can be employed in the TDD system to separate the TDD uplink from FDD system signals. Here, the TDD uplink may be deployed in particular polarization(s) that enable the TDD uplink to avoid receiving signals from the FDD systems and/or any PIM generated by mixing of FDD system signals.

(155) FDD operates the uplink and the downlink in two different frequencies (e.g., frequency $F_{sub.a}$ in the uplink and $F_{sub.b}$ in the downlink), which enables simultaneous transmit and receive. Generally, physical duplexers may be employed on both the transmit and receive of an FDD-based antenna system to ensure that residual frequency transmissions in the uplink do not overlap or leak into the downlink, and vice versa. Because massive MIMO involves antennas with numerous radiating elements, it can be challenging to implement massive MIMO in FDD since it would require a large number of duplexers to be employed on both the transmit and receive (e.g., a duplexer on the transmit and a duplexer on the receive for each radiating element of the antenna). As duplexers generally include multiple stages, where frequency separation is a function of the number of stages, incorporation and management of all of these devices for optimal frequency separation can be challenging.

(156) Various techniques described herein for polarization adjusting may be applied to the uplink and/or the downlink in an FDD communications system in order to reduce or eliminate the need for duplexers (e.g., by relaxing or loosening duplexer requirements). FIG. 2Q is a block diagram illustrating an example FDD communications system **217** in accordance with various aspects described herein. In exemplary embodiments, techniques described above with respect to polarization adjusting, such as those involving processing of signals or adjustment(s) for component(s) of an antenna system (e.g., as described above with respect to FIGS. 2C, 2E, 2M, etc.) can be employed in the FDD communications system **217** (e.g., as an additional way) to separate the uplink and downlink frequencies $F_{sub.a}$ and $F_{sub.b}$. Here, the uplink and the downlink may be deployed in different (e.g., orthogonal) polarizations, $P_{sub.a}$ and $P_{sub.b}$, respectively. Doing so creates an additional dimension of separation that permits the use of fewer or less sophisticated duplexers (e.g., duplexers with fewer stages), since signal gain (in dB) that might otherwise be offered through the use of more duplexer stages can instead be provided via polarization adjusting. This can advantageously enable massive MIMO implementations in FDD. In extreme cases, duplexers can even be eliminated altogether by virtue of the use of different, orthogonal polarizations $P_{sub.a}$ and $P_{sub.b}$.

(157) Based on parameters of detected interference/PIM and/or based on condition(s) relating to TDD/FDD communications, there may be optimal or desired directions or polarizations for receiving communications (the uplink) and transmitting communications (the downlink). In various embodiments, polarization adjusting can be effected by performing one or more techniques described herein, such as by physically rotating or electronically rotating one or both elements of an orthogonally-polarized element pair and/or by altering one or more structural properties of an orthogonally-polarized element pair, such that an uplink polarization is different from (e.g., is orthogonal to) a downlink polarization.

(158) In a case where physical rotation is employed, for a given orthogonally-polarized element pair, one element of the orthogonally-polarized element pair may need to be utilized for the uplink and the other element of the orthogonally-polarized element pair may need to be utilized for the downlink. Referring to FIG. 2M merely as an example, dipole element **213u** can be operated in the uplink (or, alternatively, the downlink) and dipole element **213v** can be operated in the downlink (or, alternatively, the uplink). Here, polarization adjusting can involve causing dipole element **213u** to physically rotate by a certain angle in a certain direction, causing dipole element **213v** to physically rotate by a certain angle in a certain direction, or both, which can result in the uplink and downlink polarizations being different from one another. Where crossed-dipole radiating element **213u**, **213v** is included as one of the radiating elements of an antenna, such as, for example, the antenna **201b** of FIG. 2E or the like, polarization adjusting via physical rotation can, for one or more columns of radiating elements, be effected such that one or more dipole elements (e.g., each dipole element) in one of the orientations (e.g., the dipole elements oriented in -45 degrees) is rotated by a certain angle in a certain direction, one or more dipole elements (e.g., each dipole element) in another physical orientation (e.g., the dipole elements oriented in $+45$ degrees) is

rotated by a certain angle in a certain direction, or both.

(159) In a case where rotation of radiating elements is applied electronically, for a given orthogonally-polarized element pair, each element of the orthogonally-polarized element pair may be operated in both the uplink and the downlink. Referring to FIG. 2M merely as an example, dipole element **213u** can be operated in both the uplink and the downlink, and dipole element **213v** can be operated in both the uplink and the downlink. Here, polarization adjusting can involve gain mixing (e.g., similar to that described above with respect to FIG. 2M) that results in the uplink polarization and the downlink polarization for a particular dipole element being different from (e.g., orthogonal to) one another. This can be achieved, for example: by determining and applying/feeding a signal for an uplink of dipole element **213u** (e.g., a signal $s_{\text{sub.1}}'(t)$ -uplink) based on some angle, such as angle **213w**; by determining and applying/feeding a signal for a downlink of dipole element **213u** (e.g., a signal $s_{\text{sub.1}}'(t)$ -downlink) based on a different angle or a 0 degree angle; by determining and applying/feeding a signal for an uplink of dipole element **213v** (e.g., a signal $s_{\text{sub.2}}'(t)$ -uplink) based on some angle; by determining and applying/feeding a signal for a downlink of dipole element **213v** (e.g., a signal $s_{\text{sub.2}}'(t)$ -downlink) based on a different angle or a 0 degree angle; or the like. In other words, any combination of zero and non-zero angles can be applied amongst the uplinks and downlinks for a given orthogonally-polarized element pair to arrive at uplink/downlink polarization differentiation. Where crossed-dipole radiating element **213u**, **213v** is included as one of the radiating elements of an antenna (e.g., a MIMO antenna), such as, for example, the antenna **201b** of FIG. 2E or the like, polarization adjusting via electronic-based rotation can, for one or more columns of radiating elements, be effected in a similar manner such that uplink and downlink polarizations are different.

(160) It is to be appreciated and understood that different configurations can be employed to provide physical rotation and/or electronic rotation of radiating elements and/or altering of one or more structural properties of radiating elements. As an example, in various embodiments, an antenna system may include one port for elements of a set (e.g., a column) of orthogonally-polarized element pairs oriented in a first manner (e.g., dipole elements oriented in -45 degrees), another port for elements of the set (e.g., column) of orthogonally-polarized element pairs oriented in a second manner (e.g., dipole elements oriented in $+45$ degrees), and similar ports for one or more other columns of orthogonally-polarized element pairs (if any). In this example, polarization adjusting (such as, for example, to achieve different uplink and downlink polarizations) can be effected electronically by determining and applying/feeding a respective signal (including, for example, respective uplink and downlink signals) to each of the ports.

(161) As another example, in various embodiments, an antenna system may include an individual port for each element of an orthogonally-polarized element pair (e.g., 16 ports for 8 orthogonally-polarized element pairs). In this example, polarization adjusting (such as, for example, to achieve different uplink and downlink polarizations) can be effected electronically by determining and applying/feeding a respective signal (including, for example, respective uplink and downlink signals), via a respective port, for each element of the orthogonally-polarized element pairs (e.g., 32 uplink/downlink signals for 16 elements of 8 orthogonally-polarized element pairs).

(162) It is to be appreciated and understood that polarization adjusting via electronic rotation can be effected or controlled by a BBU, a radio, or a system integrated in an antenna. In one or more embodiments, an antenna may include a respective device or circuitry for each orthogonally-polarized element pair or for each element of each orthogonally-polarized element pair. The device or circuitry may include, for example, polarization shifter component(s) or device(s) (e.g., analog polarization rotator(s)) operatively coupled to each orthogonally-polarized element pair or to each element of each orthogonally-polarized element pair. In various embodiments, the respective device or circuitry may obtain signals (e.g., $s_{\text{sub.1}}(t)$, $s_{\text{sub.1}}'(t)$, $s_{\text{sub.2}}(t)$, or the like, etc.) determined or generated by a BBU, a radio, or other system, and may apply/feed such signals to the respective orthogonally-polarized element pairs or to the respective elements of the orthogonally-

polarized element pairs. In this way, appropriate angle(s) of rotation (if applicable) can be applied for select orthogonally-polarized element pairs or select elements of orthogonally-polarized element pairs, such that even elements that are physically oriented in the same manner (e.g., physically oriented at -45 degrees) can be selectively electronically polarized at different angles as desired.

(163) In various embodiments, an antenna may include a respective device or circuitry and/or associated motor or set of motors for each orthogonally-polarized element pair or for each element of each orthogonally-polarized element pair, which enables polarization adjusting via physical rotation(s).

(164) In one or more embodiments, one or more AISG interfaces or control lines can be leveraged to provide command(s) relating to polarization adjusting, where the commands can, for example, be embedded in a control port (e.g., operating at a different frequency from signal frequencies) and used by the above-described circuitry or devices to apply/feed appropriate signals to respective orthogonally-polarized element pairs or to respective elements of the orthogonally-polarized element pairs or to cause physical rotation of respective orthogonally-polarized element pairs or respective elements of the orthogonally-polarized element pairs.

(165) As described above with respect to FIG. 2F, phase shifting/delaying can be implemented via physical displacement of radiating element(s). In one or more embodiments, and similar to embodiments relating to physical rotation of radiating elements, an antenna may include a respective device or circuitry and/or associated motor or set of motors for each orthogonally-polarized element pair or for each element of each orthogonally-polarized element pair, which enables polarization adjusting via physical displacement/shifting of radiating elements. It is to be appreciated and understood that phase shifting/delaying can be additionally, or alternatively, effected electronically. For example, in various embodiments, an antenna may include a respective phase shift/delay device or circuitry, for each orthogonally-polarized element pair or for each element of each orthogonally-polarized element pair, that enables introduction of phase delays for signals associated with select elements or element pairs.

(166) In certain embodiments, phase adjusting can be employed in a communications system, such as a TDD or FDD communications system, to arrive at a difference between the uplink and the downlink (e.g., similar to polarization differences provided via polarization adjusting). In these embodiments, phase shifts/delays can be provided electronically or physically in antenna configurations and manner(s) similar to those described above with respect to electronic/physical rotation of orthogonally-polarized element pairs or individual elements of orthogonally-polarized element pairs. As with embodiments involving polarization adjusting via physical rotation, in a case where phase adjusting is implemented via physical displacement of radiating elements, for a given orthogonally-polarized element pair in which a difference between the uplink and the downlink is desired, one element of the orthogonally-polarized element pair may need to be utilized for the uplink and the other element of the orthogonally-polarized element pair may need to be utilized for the downlink. Further, as with embodiments involving polarization adjusting via electronic rotation of radiating elements, in a case where phase adjusting is implemented electronically, for a given an orthogonally-polarized element pair, each element of the orthogonally-polarized element pair may be operated in both the uplink and the downlink.

(167) It is to be appreciated and understood that the quantity and arrangement of communications systems, antennas, UEs, radiating elements, monitoring elements, outputs, radios, interference/PIM cancellation systems, interference/PIM detection control devices, AISG interfaces, motors, RF baseband interference/PIM cancellers, and/or baseband-based interference/PIM cancellers shown in FIGS. 2A, 2C, 2D, 2E, 2F, 2G, 2M, 2N, 2P, and/or 2Q are provided as an example. In practice, there may be additional communications systems, antennas, UEs, radiating elements, monitoring elements, outputs, radios, interference/PIM cancellation systems, interference/PIM detection control devices, AISG interfaces, motors, RF baseband interference/PIM cancellers, and/or

baseband-based interference/PIM cancellers than those shown in FIGS. 2A, 2C, 2D, 2E, 2F, 2G, 2M, 2N, 2P, and/or 2Q. For example, various embodiments may include more or fewer communications systems, antennas, UEs, radiating elements, monitoring elements, outputs, radios, interference/PIM cancellation systems, interference/PIM detection control devices, AISG interfaces, motors, RF baseband interference/PIM cancellers, and/or baseband-based interference/PIM cancellers. Furthermore, two or more communications systems, antennas, UEs, radiating elements, monitoring elements, outputs, radios, interference/PIM cancellation systems, interference/PIM detection control devices, AISG interfaces, motors, RF baseband interference/PIM cancellers, or baseband-based interference/PIM cancellers shown in FIGS. 2A, 2C, 2D, 2E, 2F, 2G, 2M, 2N, 2P, and/or 2Q may be implemented within a single communications system, antenna, UE, radiating element, monitoring element, output, radio, interference/PIM cancellation system, interference/PIM detection control device, AISG interface, motor, RF baseband interference/PIM canceller, or baseband-based interference/PIM canceller shown in FIGS. 2A, 2C, 2D, 2E, 2F, 2G, 2M, 2N, 2P, and/or 2Q or a single communications system, antenna, UE, radiating element, monitoring element, output, radio, interference/PIM cancellation system, interference/PIM detection control device, AISG interface, motor, RF baseband interference/PIM canceller, or baseband-based interference/PIM canceller shown in FIGS. 2A, 2C, 2D, 2E, 2F, 2G, 2M, 2N, 2P, and/or 2Q may be implemented as multiple, distributed communications systems, antennas, UEs, radiating elements, monitoring elements, outputs, radios, interference/PIM cancellation systems, interference/PIM detection control devices, AISG interfaces, motors, RF baseband interference/PIM cancellers, or baseband-based interference/PIM cancellers.

Additionally, or alternatively, a set of communications systems, antennas, UEs, radiating elements, monitoring elements, outputs, radios, interference/PIM cancellation systems, interference/PIM detection control devices, AISG interfaces, motors, RF baseband interference/PIM cancellers, and/or baseband-based interference/PIM cancellers (e.g., one or more communications systems, antennas, UEs, radiating elements, monitoring elements, outputs, radios, interference/PIM cancellation systems, interference/PIM detection control devices, AISG interfaces, motors, RF baseband interference/PIM cancellers, and/or baseband-based interference/PIM cancellers) may perform one or more functions described as being performed by another set of communications systems, antennas, UEs, radiating elements, monitoring elements, outputs, radios, interference/PIM cancellation systems, interference/PIM detection control devices, AISG interfaces, motors, RF baseband interference/PIM cancellers, and/or baseband-based interference/PIM cancellers.

(168) FIG. 2R depicts an illustrative embodiment of a method **220** in accordance with various aspects described herein. In some embodiments, one or more process blocks of FIG. 2R can be performed by an interference/PIM cancellation system, such as one or more of the interference/PIM cancellation systems described herein. In certain embodiments, one or more process blocks of FIG. 2R may be performed by another device or a group of devices separate from or including the interference/PIM cancellation system, such as a radio (e.g., an RRH), a baseband unit (BBU), an antenna or antenna system, an interference/PIM detection control device, and/or an AISG interface.

(169) At **222**, the method can include receiving, via an antenna, a communication signal generated by a communication device. For example, step **222** can be performed in a manner similar to that described elsewhere herein.

(170) At **224**, the method can include detecting interference in the communication signal, wherein the interference is generated by one or more interference sources, wherein the interference is detected by monitoring a near field region of the antenna, an intermediate field region of the antenna, a far field region of the antenna, or any combinations thereof, wherein the monitoring excludes monitoring only the far field region of the antenna. For example, step **224** can be performed in a manner similar to that described elsewhere herein.

(171) In some implementations of these embodiments, the intermediate field region comprises a region that spans a portion of the near field region of the antenna and a portion of the far field

region of the antenna.

(172) In some implementations of these embodiments, the method further comprises identifying an antenna resource for mitigating the interference, and performing by the antenna resource conditioning on the communication signal to reduce the interference.

(173) In some implementations of these embodiments, the antenna comprises a plurality of radiating elements, wherein the antenna is configured to operate the plurality of radiating elements in bands that mix and interfere together. In some implementations of these embodiments, the interference detected includes mixing and interference of the bands, wherein the interference detected comprises passive intermodulation (PIM) interference.

(174) In some implementations of these embodiments, the interference comprises inter-cell interference.

(175) In some implementations of these embodiments, the interference is generated from dynamic spectrum sharing between transmitters.

(176) In some implementations of these embodiments, the interference comprises leakage interference generated by another base station.

(177) In some implementations of these embodiments, a polarization of the interference enables detection of the interference. In some implementations of these embodiments, the polarization of the interference is detectable separately from other signals received by the antenna.

(178) In some implementations of these embodiments, the antenna is integrated with a remote radio head.

(179) In some implementations of these embodiments, the antenna operates in a communication system utilizing time division multiple access.

(180) In some implementations of these embodiments, the antenna operates in a communication system utilizing frequency division multiple access.

(181) In some implementations of these embodiments, a signaling protocol used by one or more transmitters unassociated with the antenna comprises an orthogonal frequency-division multiple access protocol. In some implementations of these embodiments, the interference is further detected by detecting the signaling protocol used by the one or more transmitters.

(182) While for purposes of simplicity of explanation, the respective processes are shown and described as a series of blocks in FIG. 2R, it is to be understood and appreciated that the claimed subject matter is not limited by the order of the blocks, as some blocks may occur in different orders and/or concurrently with other blocks from what is depicted and described herein. Moreover, not all illustrated blocks may be required to implement the methods described herein.

(183) In various embodiments, a device comprises a circuit coupled to an antenna. The circuit facilitates operations, including receiving, via the antenna, a signal generated by a communication device, and detecting interference in the signal, wherein the interference is generated by one or more sources, wherein the interference is detected by monitoring a near field region of the antenna, an intermediate field of the antenna, a far field region of the antenna, or any combinations thereof, wherein the monitoring excludes monitoring only the far field region of the antenna.

(184) In some implementations of these embodiments, the operations further include identifying a resource for mitigating the interference.

(185) In some implementations of these embodiments, the circuit is configured to detect a polarization of the interference.

(186) In various embodiments, a non-transitory machine-readable medium comprises executable instructions that, when executed by a processing system including a processor, facilitate performance of operations. The operations comprise receiving, via an antenna, a communication signal generated by a communication device, and detecting interference in the communication signal, wherein the interference is generated by one or more interference sources, wherein the interference is detected by monitoring a near field region of the antenna, an intermediate field region of the antenna, or both with or without monitoring a far field region of the antenna.

(187) In some implementations of these embodiments, the operations further comprise controlling, by a remote radio unit, the antenna to perform one or more actions for mitigating or cancelling the interference.

(188) FIG. 2S depicts an illustrative embodiment of a method **230** in accordance with various aspects described herein. In some embodiments, one or more process blocks of FIG. 2S can be performed by an interference/PIM cancellation system, such as one or more of the interference/PIM cancellation systems described herein. In certain embodiments, one or more process blocks of FIG. 2S may be performed by another device or a group of devices separate from or including the interference/PIM cancellation system, such as a radio (e.g., an RRH), a baseband unit (BBU), an antenna or antenna system, an interference/PIM detection control device, and/or an AISG interface. In one or more embodiments, the method can include operations. For example, a device may comprise a processing system including a processor and associated with a communications system, and a memory that stores executable instructions that, when executed by the processing system, facilitate performance of such operations.

(189) At **232**, the method can include obtaining data regarding passive intermodulation (PIM) detected in a received communication signal. For example, step **232** can be performed in a manner similar to that described elsewhere herein.

(190) At **234**, the method can include performing polarization adjusting for a communications system such that an impact of the PIM on the communications system is minimized. For example, step **234** can be performed in a manner similar to that described elsewhere herein.

(191) In some implementations of these embodiments, the PIM originates in a near field region of an antenna system of the communications system or an intermediate field region of the antenna system that spans a portion of the near field region and a portion of a far field region of the antenna system.

(192) In some implementations of these embodiments, the performing the polarization adjusting results in no impact to a far field region of an antenna system of the communications system, as compared to a case where the polarization adjusting is not performed.

(193) In some implementations of these embodiments, the performing the polarization adjusting comprises rotating one or more radiating elements of an antenna system of the communications system.

(194) In some implementations of these embodiments, the performing the polarization adjusting comprises performing electronic adjustments for one or more radiating elements of an antenna system of the communications system.

(195) While for purposes of simplicity of explanation, the respective processes are shown and described as a series of blocks in FIG. 2S, it is to be understood and appreciated that the claimed subject matter is not limited by the order of the blocks, as some blocks may occur in different orders and/or concurrently with other blocks from what is depicted and described herein. Moreover, not all illustrated blocks may be required to implement the methods described herein.

(196) In various embodiments, a method comprises obtaining data regarding passive intermodulation (PIM) originating from one or more interference sources, and mitigating, by an adjusting mechanism associated with a communications system, the PIM by performing polarization adjusting for the communications system.

(197) In some implementations of these embodiments, the PIM originates in a near field region of an antenna system of the communications system or an intermediate field region of the antenna system that spans a portion of the near field region and a portion of a far field region of the antenna system.

(198) In some implementations of these embodiments, the performing the polarization adjusting results in no impact to a far field region of an antenna system of the communications system, as compared to a case where the polarization adjusting is not performed.

(199) In some implementations of these embodiments, the performing the polarization adjusting

comprises rotating one or more radiating elements of an antenna system of the communications system.

(200) In some implementations of these embodiments, the performing the polarization adjusting comprises performing electronic adjustments for one or more radiating elements of an antenna system of the communications system.

(201) In some implementations of these embodiments, the performing the polarization adjusting involves one or more adjustments for one or more orthogonally-polarized element pairs of an antenna system of the communications system.

(202) In some implementations of these embodiments, the communications system comprises a multiple-input-multiple-output (MIMO) antenna.

(203) In some implementations of these embodiments, the polarization adjusting is performed by a remote radio unit.

(204) In some implementations of these embodiments, the polarization adjusting involves controlling one or more motors.

(205) In some implementations of these embodiments, the obtaining is performed by a processing system including a processor, wherein the adjusting mechanism is included in or comprises the processing system.

(206) In various embodiments, a non-transitory machine-readable medium comprises executable instructions that, when executed by a processing system including a processor and associated with a communications system, facilitate performance of operations. The operations comprise receiving data regarding interference present in a received communication signal, and performing polarization adjusting for the communications system such that the interference is mitigated.

(207) In some implementations of these embodiments, the interference originates in a near field region of an antenna system of the communications system or an intermediate field region of the antenna system that spans a portion of the near field region and a portion of a far field region of the antenna system.

(208) In some implementations of these embodiments, the performing the polarization adjusting results in no impact to a far field region of an antenna system of the communications system, as compared to a case where the polarization adjusting is not performed.

(209) In some implementations of these embodiments, the performing the polarization adjusting involves one or more adjustments for one or more orthogonally-polarized element pairs of an antenna system of the communications system.

(210) In some implementations of these embodiments, the communications system comprises a multiple-input-multiple-output (MIMO) antenna.

(211) FIG. 2T depicts an illustrative embodiment of a method **240** in accordance with various aspects described herein. In some embodiments, one or more process blocks of FIG. 2T can be performed by an interference/PIM cancellation system, such as one or more of the interference/PIM cancellation systems described herein. In certain embodiments, one or more process blocks of FIG. 2T may be performed by another device or a group of devices separate from or including the interference/PIM cancellation system, such as a radio (e.g., an RRH), a baseband unit (BBU), an antenna or antenna system, an interference/PIM detection control device, and/or an AISG interface. In one or more embodiments, the method can include operations. For example, a device may comprise a processing system including a processor and associated with an antenna system, and a memory that stores executable instructions that, when executed by the processing system, facilitate performance of such operations.

(212) At **242**, the method can include obtaining data regarding interference detected in a received communication signal. For example, step **242** can be performed in a manner similar to that described elsewhere herein.

(213) At **244**, the method can include performing polarization adjusting by rotating one or more radiating elements of an antenna system such that an impact of the interference on the antenna

system is minimized. For example, step 244 can be performed in a manner similar to that described elsewhere herein.

(214) In some implementations of these embodiments, the interference originates in a near field region of the antenna system or an intermediate field region of the antenna system that spans a portion of the near field region and a portion of a far field region of the antenna system.

(215) In some implementations of these embodiments, the performing the polarization adjusting results in no impact to a far field region of the antenna system, as compared to a case where the polarization adjusting is not performed.

(216) In some implementations of these embodiments, the interference comprises passive intermodulation (PIM).

(217) In some implementations of these embodiments, the polarization adjusting comprises rotating a subset of the radiating elements of the antenna system.

(218) While for purposes of simplicity of explanation, the respective processes are shown and described as a series of blocks in FIG. 2T, it is to be understood and appreciated that the claimed subject matter is not limited by the order of the blocks, as some blocks may occur in different orders and/or concurrently with other blocks from what is depicted and described herein. Moreover, not all illustrated blocks may be required to implement the methods described herein.

(219) In various embodiments, a method comprises obtaining data regarding interference originating from one or more interference sources, and mitigating, by an adjusting mechanism associated with an antenna system, the interference by performing polarization adjusting via rotation of radiating elements of the antenna system.

(220) In some implementations of these embodiments, the interference originates in a near field region of the antenna system or an intermediate field region of the antenna system that spans a portion of the near field region and a portion of a far field region of the antenna system.

(221) In some implementations of these embodiments, the performing the polarization adjusting results in no impact to a far field region of the antenna system, as compared to a case where the polarization adjusting is not performed.

(222) In some implementations of these embodiments, the interference comprises passive intermodulation (PIM).

(223) In some implementations of these embodiments, the radiating elements comprise orthogonally-polarized element pairs.

(224) In some implementations of these embodiments, the antenna system comprises a plurality of antennas, wherein the radiating elements are included in one antenna of the plurality of antennas.

(225) In some implementations of these embodiments, the antenna system comprises a single antenna having a plurality of radiating elements, wherein the radiating elements comprise a subset of the plurality of radiating elements.

(226) In some implementations of these embodiments, the polarization adjusting comprises rotating a first set of radiating elements by a first angle of rotation and a second set of radiating elements by a second angle of rotation.

(227) In some implementations of these embodiments, the polarization adjusting is performed by a remote radio unit.

(228) In some implementations of these embodiments, the polarization adjusting involves controlling one or more motors.

(229) In some implementations of these embodiments, the polarization adjusting is performed via one or more Antenna Interface Standards Group (AISG)-based interfaces.

(230) In some implementations of these embodiments, the obtaining is performed by a processing system including a processor, wherein the adjusting mechanism is included in or comprises the processing system.

(231) In various embodiments, a non-transitory machine-readable medium comprises executable instructions that, when executed by a processing system including a processor and associated with

an antenna system, facilitate performance of operations. The operations comprise receiving data regarding interference present in a received communication signal, and performing polarization adjusting by causing one or more radiating elements of the antenna system to be rotated such that the interference is mitigated.

(232) In some implementations of these embodiments, the performing the polarization adjusting results in no impact to a far field region of the antenna system, as compared to a case where the polarization adjusting is not performed.

(233) In some implementations of these embodiments, the polarization adjusting comprises rotating a subset of the radiating elements of the antenna system.

(234) FIG. 2U depicts an illustrative embodiment of a method **250** in accordance with various aspects described herein. In some embodiments, one or more process blocks of FIG. 2U can be performed by an interference/PIM cancellation system, such as one or more of the interference/PIM cancellation systems described herein. In certain embodiments, one or more process blocks of FIG. 2U may be performed by another device or a group of devices separate from or including the interference/PIM cancellation system, such as a radio (e.g., an RRH), a baseband unit (BBU), an antenna or antenna system, an interference/PIM detection control device, and/or an AISG interface. In one or more embodiments, the method can include operations. For example, a device may comprise a processing system including a processor and associated with an antenna system, and a memory that stores executable instructions that, when executed by the processing system, facilitate performance of such operations.

(235) At **252**, the method can include obtaining data regarding interference detected in a received communication signal. For example, step **252** can be performed in a manner similar to that described elsewhere herein.

(236) At **254**, the method can include performing phase adjusting for one or more radiating elements of an antenna system such that an impact of the interference on the antenna system is minimized. For example, step **254** can be performed in a manner similar to that described elsewhere herein.

(237) In some implementations of these embodiments, the interference originates in a near field region of the antenna system or an intermediate field region of the antenna system that spans a portion of the near field region and a portion of a far field region of the antenna system.

(238) In some implementations of these embodiments, the performing the phase adjusting results in no impact to a far field region of the antenna system, as compared to a case where the phase adjusting is not performed.

(239) In some implementations of these embodiments, the performing the phase adjusting comprises physically displacing the one or more radiating elements along an axis of the antenna system.

(240) In some implementations of these embodiments, the performing the phase adjusting comprises electronically applying a phase shift or delay to one or more signals associated with the one or more radiating elements.

(241) While for purposes of simplicity of explanation, the respective processes are shown and described as a series of blocks in FIG. 2U, it is to be understood and appreciated that the claimed subject matter is not limited by the order of the blocks, as some blocks may occur in different orders and/or concurrently with other blocks from what is depicted and described herein. Moreover, not all illustrated blocks may be required to implement the methods described herein.

(242) In various embodiments, a method comprises obtaining data regarding interference originating from one or more interference sources, and mitigating, by an adjusting mechanism associated with an antenna system, the interference by performing phase adjusting of radiating elements of the antenna system.

(243) In some implementations of these embodiments, the interference originates in a near field region of the antenna system or an intermediate field region of the antenna system that spans a

portion of the near field region and a portion of a far field region of the antenna system.

(244) In some implementations of these embodiments, the performing the phase adjusting results in no impact to a far field region of the antenna system, as compared to a case where the phase adjusting is not performed.

(245) In some implementations of these embodiments, the interference comprises passive intermodulation (PIM).

(246) In some implementations of these embodiments, the radiating elements comprise orthogonally-polarized element pairs.

(247) In some implementations of these embodiments, the antenna system comprises a plurality of antennas, wherein the radiating elements are included in one antenna of the plurality of antennas.

(248) In some implementations of these embodiments, the antenna system comprises a single antenna having a plurality of radiating elements, wherein the radiating elements comprise a subset of the plurality of radiating elements.

(249) In some implementations of these embodiments, the performing the phase adjusting comprises physically displacing a subset of the radiating elements along an axis of the antenna system.

(250) In some implementations of these embodiments, the performing the phase adjusting comprises electronically applying a phase shift or delay to one or more signals associated with a subset of the radiating elements of the antenna system.

(251) In some implementations of these embodiments, the performing the phase adjusting comprises displacing a first set of radiating elements by a first amount in a first direction and a second set of radiating elements by a second amount in a second direction opposite the first direction.

(252) In some implementations of these embodiments, the phase adjusting is performed by a remote radio unit, by controlling one or more motors, or a combination thereof.

(253) In some implementations of these embodiments, the phase adjusting is performed via one or more Antenna Interface Standards Group (AISG)-based interfaces.

(254) In some implementations of these embodiments, the obtaining is performed by a processing system including a processor, wherein the adjusting mechanism is included in or comprises the processing system.

(255) In various embodiments, a non-transitory machine-readable medium comprises executable instructions that, when executed by a processing system including a processor and associated with an antenna system, facilitate performance of operations. The operations comprise receiving data regarding interference present in a received communication signal, and performing phase adjusting by causing one or more radiating elements of the antenna system to be displaced along an axis of the antenna system such that the interference is mitigated.

(256) In some implementations of these embodiments, the performing the phase adjusting results in no impact to a far field region of the antenna system, as compared to a case where the phase adjusting is not performed.

(257) FIG. 2V depicts an illustrative embodiment of a method **260** in accordance with various aspects described herein. In some embodiments, one or more process blocks of FIG. 2V can be performed by an interference/PIM cancellation system, such as one or more of the interference/PIM cancellation systems described herein. In certain embodiments, one or more process blocks of FIG. 2V may be performed by another device or a group of devices separate from or including the interference/PIM cancellation system, such as a radio (e.g., an RRH), a baseband unit (BBU), an antenna or antenna system, an interference/PIM detection control device, and/or an AISG interface. In one or more embodiments, the method can include operations. For example, a device may comprise a processing system associated with a time-division duplexing (TDD) communications system and including a processor, and a memory that stores executable instructions that, when executed by the processing system, facilitate performance of such operations.

(258) At **262**, the method can include performing polarization adjusting for an uplink of a TDD communications system. For example, step **262** can be performed in a manner similar to that described elsewhere herein.

(259) At **264**, the method can include performing polarization adjusting for a downlink of the TDD communications system, wherein a first polarization of the uplink and a second polarization of the downlink are different. For example, step **264** can be performed in a manner similar to that described elsewhere herein.

(260) In some implementations of these embodiments, the first polarization is orthogonal to the second polarization.

(261) In some implementations of these embodiments, the TDD communications system comprises a multiple-input-multiple-output (MIMO) antenna.

(262) In some implementations of these embodiments, the TDD communications system comprises an antenna system having a plurality of orthogonally-polarized element pairs.

(263) In some implementations of these embodiments, the TDD communications system comprises an antenna system having a plurality of radiating elements, wherein the performing the polarization adjusting for the uplink or the performing the polarization adjusting for the downlink comprises causing a subset of the plurality of radiating elements to rotate.

(264) While for purposes of simplicity of explanation, the respective processes are shown and described as a series of blocks in FIG. 2V, it is to be understood and appreciated that the claimed subject matter is not limited by the order of the blocks, as some blocks may occur in different orders and/or concurrently with other blocks from what is depicted and described herein. Moreover, not all illustrated blocks may be required to implement the methods described herein.

(265) In various embodiments, a non-transitory machine-readable medium comprises executable instructions that, when executed by a processing system associated with a frequency-division duplexing (FDD) communications system and including a processor, facilitate performance of operations. The operations comprise performing polarization adjusting for an uplink of the FDD communications system, and performing polarization adjusting for a downlink of the FDD communications system, wherein a first polarization of the uplink and a second polarization of the downlink are different.

(266) In some implementations of these embodiments, the first polarization is orthogonal to the second polarization.

(267) In some implementations of these embodiments, the FDD communications system employs massive multiple-input-multiple-output (MIMO).

(268) In some implementations of these embodiments, the FDD communications system comprises an antenna system having a plurality of orthogonally-polarized element pairs.

(269) In some implementations of these embodiments, the FDD communications system comprises an antenna system having a plurality of radiating elements, wherein the performing the polarization adjusting for the uplink or the performing the polarization adjusting for the downlink comprises causing a subset of the plurality of radiating elements to become physically adjusted, electronically adjusted, or both physically and electronically adjusted.

(270) In various embodiments, a method comprises performing, by an adjusting mechanism associated with a communications system, polarization adjusting for an uplink of the communications system, and performing, by the adjusting mechanism, polarization adjusting for a downlink of the communications system, wherein a first polarization of the uplink and a second polarization of the downlink are different.

(271) In some implementations of these embodiments, the first polarization is orthogonal to the second polarization.

(272) In some implementations of these embodiments, the communications system comprises a TDD communications system.

(273) In some implementations of these embodiments, the communications system comprises an

FDD communications system. In some implementations of these embodiments, the FDD communications system employs massive multiple-input-multiple-output (MIMO).

(274) In some implementations of these embodiments, the communications system comprises an antenna system having a plurality of orthogonally-polarized element pairs.

(275) In some implementations of these embodiments, the first polarization being different from the second polarization enables uplink transmissions and downlink transmissions to overlap with one another.

(276) In some implementations of these embodiments, the performing the polarization adjusting for the uplink or the performing the polarization adjusting for the downlink enables the uplink to avoid detecting interference generated by multiple frequency-division duplexing (FDD) communications systems

(277) In some implementations of these embodiments, the performing the polarization adjusting for the uplink comprises adjusting a polarization associated with at least one radiating element of a plurality of radiating elements of an antenna.

(278) In some implementations of these embodiments, the performing the polarization adjusting for the downlink comprises adjusting a polarization associated with at least one radiating element of a plurality of radiating elements of an antenna.

(279) FIG. 2W depicts an illustrative embodiment of a method **270** in accordance with various aspects described herein. In some embodiments, one or more process blocks of FIG. 2W can be performed by an interference/PIM cancellation system, such as one or more of the interference/PIM cancellation systems described herein. In certain embodiments, one or more process blocks of FIG. 2W may be performed by another device or a group of devices separate from or including the interference/PIM cancellation system, such as a radio (e.g., an RRH), a baseband unit (BBU), an antenna or antenna system, an interference/PIM detection control device, and/or an AISG interface.

(280) At **272**, the method can include identifying one or more radiating elements of an antenna system that are to be adjusted based on interference determined to affect an operation of the antenna system. For example, step **272** can be performed in a manner similar to that described elsewhere herein.

(281) At **274**, the method can include altering one or more properties of the one or more radiating elements to effect polarization adjusting such that an impact of the interference on the antenna system is minimized. For example, step **274** can be performed in a manner similar to that described elsewhere herein.

(282) In some implementations of these embodiments, the interference originates in a near field region of the antenna system or an intermediate field region of the antenna system that spans a portion of the near field region and a portion of a far field region of the antenna system.

(283) In some implementations of these embodiments, the polarization adjusting results in no impact to a far field region of the antenna system, as compared to a case where the polarization adjusting is not performed.

(284) In some implementations of these embodiments, the interference comprises passive intermodulation (PIM).

(285) In some implementations of these embodiments, the one or more properties relate to physical shape.

(286) In some implementations of these embodiments, the one or more properties relate to physical dimensions.

(287) In some implementations of these embodiments, the one or more properties relate to electrical properties, magnetic properties, or a combination thereof.

(288) In some implementations of these embodiments, the one or more radiating elements comprise a subset of the radiating elements of the antenna system.

(289) In some implementations of these embodiments, the antenna system is associated with a frequency-division duplexing (FDD) communications system or a time-division duplexing (TDD)

communications system.

(290) In some implementations of these embodiments, the antenna system comprises a plurality of antennas, wherein the one or more radiating elements are included in one antenna of the plurality of antennas.

(291) In some implementations of these embodiments, the antenna system comprises a single antenna having a plurality of radiating elements, wherein the one or more radiating elements comprise a subset of the plurality of radiating elements.

(292) In some implementations of these embodiments, the antenna system comprises a plurality of radiating elements that includes the one or more radiating elements and other radiating elements, wherein the other radiating elements have one or more other properties.

(293) While for purposes of simplicity of explanation, the respective processes are shown and described as a series of blocks in FIG. 2W, it is to be understood and appreciated that the claimed subject matter is not limited by the order of the blocks, as some blocks may occur in different orders and/or concurrently with other blocks from what is depicted and described herein. Moreover, not all illustrated blocks may be required to implement the methods described herein.

(294) In various embodiments, a device comprises a processing system including a processor and associated with an antenna system having a plurality of radiating elements, and a memory that stores executable instructions that, when executed by the processing system, facilitate performance of operations. The operations comprise operating the antenna system in a communications system, and mitigating interference via polarization adjusting, wherein the polarization adjusting is provided based on one or more of the plurality of radiating elements of the antenna system being adapted to exhibit one or more properties.

(295) In some implementations of these embodiments, the polarization adjusting results in no impact to a far field region of the antenna system, as compared to a case where the polarization adjusting is not provided.

(296) In some implementations of these embodiments, the one or more properties relate to physical shape, physical dimensions, or a combination thereof.

(297) In some implementations of these embodiments, the one or more properties relate to electrical properties, magnetic properties, or a combination thereof.

(298) In some implementations of these embodiments, the polarization adjusting is provided via one or more Antenna Interface Standards Group (AISG)-based interfaces.

(299) In various embodiments, an antenna system comprises a first subset of radiating elements configured in a first manner, and a second subset of radiating elements configured in a second manner, wherein the first manner is different from the second manner, resulting in polarization adjusting that enables an impact of interference on the antenna system to be minimized when the antenna system is operated.

(300) In some implementations of these embodiments, the interference comprises passive intermodulation (PIM).

(301) In some implementations of these embodiments, the first manner is different from the second manner with respect to physical shape, physical dimensions, electromagnetic properties, or any combination thereof.

(302) FIG. 2X depicts an illustrative embodiment of a method **280** in accordance with various aspects described herein. In some embodiments, one or more process blocks of FIG. 2X can be performed by an interference/PIM cancellation system, such as one or more of the interference/PIM cancellation systems described herein. In certain embodiments, one or more process blocks of FIG. 2X may be performed by another device or a group of devices separate from or including the interference/PIM cancellation system, such as a radio (e.g., an RRH), a baseband unit (BBU), an antenna or antenna system, an interference/PIM detection control device, and/or an AISG interface. In one or more embodiments, the method can include operations. For example, a device may comprise a processing system including a processor and associated with an antenna system having

orthogonally-polarized element pairs, and a memory that stores executable instructions that, when executed by the processing system, facilitate performance of such operations.

(303) At **282**, the method can include obtaining data regarding interference detected in a received communication signal. For example, step **282** can be performed in a manner similar to that described elsewhere herein.

(304) At **284**, the method can include performing polarization adjusting for one or more orthogonally-polarized element pairs such that an impact of the interference on an antenna system is minimized. For example, step **284** can be performed in a manner similar to that described elsewhere herein.

(305) In some implementations of these embodiments, the interference originates in a near field region of the antenna system or an intermediate field region of the antenna system that spans a portion of the near field region and a portion of a far field region of the antenna system.

(306) In some implementations of these embodiments, the performing the polarization adjusting results in no impact to a far field region of the antenna system, as compared to a case where the polarization adjusting is not performed.

(307) In some implementations of these embodiments, the interference comprises passive intermodulation (PIM).

(308) In some implementations of these embodiments, the antenna system comprises a multiple-input-multiple-output (MIMO) antenna.

(309) In some implementations of these embodiments, the polarization adjusting is performed by a radio device integrated with the antenna system.

(310) While for purposes of simplicity of explanation, the respective processes are shown and described as a series of blocks in FIG. 2X, it is to be understood and appreciated that the claimed subject matter is not limited by the order of the blocks, as some blocks may occur in different orders and/or concurrently with other blocks from what is depicted and described herein. Moreover, not all illustrated blocks may be required to implement the methods described herein.

(311) In various embodiments, a method comprises obtaining data regarding interference originating from one or more interference sources, and mitigating, by an adjusting mechanism associated with an antenna system that comprises orthogonally-polarized element pairs, the interference by performing polarization adjusting for the orthogonally-polarized element pairs.

(312) In some implementations of these embodiments, the interference originates in a near field region of the antenna system or an intermediate field region of the antenna system that spans a portion of the near field region and a portion of a far field region of the antenna system.

(313) In some implementations of these embodiments, the performing the polarization adjusting results in no impact to a far field region of the antenna system, as compared to a case where the polarization adjusting is not performed.

(314) In some implementations of these embodiments, the interference comprises passive intermodulation (PIM).

(315) In some implementations of these embodiments, the polarization adjusting is performed for both an uplink of the antenna system and a downlink of the antenna system.

(316) In some implementations of these embodiments, the polarization adjusting is different for an uplink of the antenna system and a downlink of the antenna system.

(317) In some implementations of these embodiments, the polarization adjusting is performed for an uplink of the antenna system but not a downlink of the antenna system.

(318) In some implementations of these embodiments, the polarization adjusting is performed for a downlink of the antenna system but not an uplink of the antenna system.

(319) In some implementations of these embodiments, the polarization adjusting comprises mixing of signals associated with the orthogonally-polarized element pairs, wherein the orthogonally-polarized element pairs comprise crossed-dipole elements.

(320) In some implementations of these embodiments, the obtaining is performed by a processing

system including a processor, wherein the adjusting mechanism is included in or comprises the processing system.

(321) In various embodiments, a non-transitory machine-readable medium comprises executable instructions that, when executed by a processing system including a processor and associated with an antenna system comprising orthogonally-polarized element pairs, facilitate performance of operations. The operations comprise receiving data regarding interference present in a received communication signal, and performing polarization adjusting for one or more of the orthogonally-polarized element pairs such that the interference is mitigated.

(322) In some implementations of these embodiments, the interference originates in a near field region of the antenna system or an intermediate field region of the antenna system that spans a portion of the near field region and a portion of a far field region of the antenna system.

(323) In some implementations of these embodiments, the performing the polarization adjusting results in no impact to a far field region of the antenna system, as compared to a case where the polarization adjusting is not performed.

(324) In some implementations of these embodiments, the antenna system comprises a multiple-input-multiple-output (MIMO) antenna.

(325) FIG. 3A depicts an exemplary, non-limiting embodiment of a system **300** in accordance with various aspects described herein. In various embodiments, the system **300** may be functioning within, or operatively overlaid upon, the communications network **100** of FIG. 1A and/or the communications system **180** of FIG. 1B. For example, portion(s) of system **300** can facilitate, in whole or in part, detection of interference/PIM in a communications system and performing of action(s), such as polarization adjusting and/or phase shifting/delaying, as described herein, that result in mitigation/cancellation of the interference/PIM. As illustrated in FIG. 3A, a baseband processor unit (BBU) **310** comprises a plurality of baseband processors and interfaces or connectors for connection to a remote radio unit (RRU) **320** through a plurality of fiber optic cables **330**. BBU **310** processes downlink data signals for transmission to mobile or stationary UEs (not illustrated) and uplink data signals received from mobile or stationary UEs. BBU **310** integrates multiple lines of common public radio interface (CPRI) antenna carrier data in full duplex at high speed over the fiber optic cables **330**.

(326) RRU **320** transmits and receives radio frequency (RF) signals from one or more antennas **340** through RF coaxial cables **350**. RRU **320** contains circuitry to convert the baseband digital signals received from BBU **310** to RF signals, and vice-versa.

(327) Optionally, inserted between BBU **310** and RRU **320** is a conditioner **360**. In an embodiment, conditioner **360** can be configured to output signals based on a predefined protocol such as a Gigabit Ethernet output, an open base station architecture initiative (OBSAI) protocol, or CPRI protocol, among others. Conditioner **360** can comprise an adaptive filter configured to execute signal processing algorithm(s). Conditioner **360** can receive digital signals, known as antenna carriers (denoted by A_xC), from BBU **310** and RRU **320** via fiber optic cables **330**. Each antenna carrier carries In-Phase and Quadrature (I/Q) data for one RF signal at one antenna element. In an embodiment illustrated in FIG. 3A, a 2×2 MIMO antenna **341** comprises two uplink antenna carriers on the uplink fiber and two downlink antenna carriers on the downlink fiber. I/Q data samples are interleaved and placed in a basic frame of the antenna carrier. Samples from multiple antennas are contained in each basic frame. The uplink information can include one or more system information blocks (SIBs) as defined by a protocol, such as, for example, an LTE protocol. The SIBs can include a physical resource block (PRB). From a PRB, the system can obtain uplink information, which can include among other things, an indication of how many communication devices will be transmitting wireless signals in uplink paths assigned by one or more base stations, power level(s) that will be used by each of the communication devices during uplink wireless communications, the resource blocks that are assigned to each communication device, and other useful parametric information utilized by each communication device when communicating via an

uplink path.

(328) In certain embodiments, the PRB can also be used by the system of the subject disclosure to create a signal profile. The signal profile can be, for example, an energy profile and/or a spectral profile, which can be determined from parametric information provided in the PRB (e.g., power level, resource blocks being used, radio access technology being used, etc.). The signal profile can be used to determine whether the wireless signal received is a standard signal (e.g., LTE signal), and if not standard, whether the wireless signal received causes signal interference. Accordingly, the signal profile can be used by the system of the subject disclosure to perform time domain and/or frequency domain analysis of measurements, which, in turn, can result in the detection of signal interferers.

(329) The system of the subject disclosure can be adapted to perform, according to the uplink information, measurements on wireless signals transmitted by the communication devices via the uplink paths assigned to the communication devices. The wireless signals can be received via antennas (which, in some embodiments, may be configured as MIMO antennas). These antennas can be coupled to the system of the subject disclosure for performing measurements, processing and conditioning the signals received from the antennas according to such measurements, and for providing the conditioned signals to one or more base station processors. The measurements can be based on a sampling of analog signals supplied by an antenna receiving uplink wireless signals transmitted by the communication devices. In other embodiments, the measurements can be associated with measurements derived from digital signals supplied by one or more radio access networks (RANs) coupled to one or more corresponding antennas of a base station.

(330) Optional conditioner **360** can provide support for 2×2 and 4×4 MIMO antenna configurations (or other MIMO configurations), diversity antenna configurations, and a variety of CPRI interfaces. In an embodiment, conditioner **360** supports up to 200 MHz carriers and all CPRI rates. In an embodiment, conditioner **360** interfaces with 3 to 12 CPRI fiber pairs providing coverage for multiple bands in, for example, a three sector site. Conditioner **360** can be located anywhere within fiber optic range of BBU **310** or RRU **320**, e.g., off tower, or even off site (e.g., a central office remote from the RRU **320**).

(331) Conditioner **360** comprises a plurality of CPRI interface cards **365**. In an embodiment, each CPRI interface card **365** supports a CPRI link comprising up to 4 antenna carriers at, for example, 5, 10, and 20 MHz bandwidths. Each CPRI link comprises either one or more frequency bands. Multiple CPRI links can comprise multiple frequency bands. Each CPRI link can further comprise signals associated with MIMO or diversity antenna configurations, and can comprise one or more sectors. For example, in one embodiment, the conditioner **360** can provide capacity for up to twelve RRUs, 48 antenna carriers, and 12 sectors. In other embodiments, the conditioner **360** can provide capacity for more or fewer RRUs, more or fewer antenna carriers, and more or fewer sectors.

(332) Each CPRI interface card **365** can examine SIBs obtained from one or more downlink fibers to determine parameters of the uplink path signals received over the uplink fiber. In an embodiment, the CPRI interface card **365** can take SINR measurements of each uplink path according to information in the SIBs obtained from the one or more downlink fibers, and determine whether one or more SINR measurements fall below a threshold. In some embodiments, the CPRI interface card **365** can take corrective action to improve one or more SINR measurements falling below the threshold, such as moving an uplink path affected by interference to an available uplink path in the same sector, or in different sectors, as set forth in more detail below. In an embodiment, the CPRI interface card **365** can compare signals from different sectors to determine an approach for taking corrective action.

(333) It will be appreciated that the threshold noted above can represent a minimally expected SINR measurement. It will be appreciated that the threshold compared against one or more SINR measurements can be a predetermined threshold. In other embodiments, the threshold can be determined empirically from measurements taken in a controlled setting to identify a desirable

SINR measurement. In yet other embodiments, the threshold can be determined according to a running average of power levels within a resource block or among groupings of resource blocks. Other techniques for determining a threshold that is compared to a SINR measurement can be used. Similarly, correlation techniques can be used to identify circumstances that warrant corrective action of certain SINR measurements.

(334) It is to be appreciated and understood that some or all of the aspects of detection of interference/PIM and/or polarization adjusting and/or phase shifting/delaying, described herein, can be performed in, or by, one or more of the antennas **340**, one or more of the RRUs **320**, one or more of the BBUs **310**, and/or the optional conditioner **360**.

(335) FIG. **3B** depicts an exemplary, non-limiting embodiment of a system for detecting passive intermodulation (PIM) interferences in uplink signals of a base station in accordance with various aspects described herein. In various embodiments, this system may be functioning within, or operatively overlaid upon, the communications network **100** of FIG. **1A** and/or the communications system **180** of FIG. **1B**. For example, portion(s) of this system can facilitate, in whole or in part, detection of interference/PIM in a communications system and performing of action(s), such as polarization adjusting and/or phase shifting/delaying, as described herein, that result in mitigation/cancellation of the interference/PIM.

(336) As illustrated in FIG. **3B**, inserted between BBUs (not illustrated) and RRUs **370A** is a PIM detector **370**, which non-intrusively receives and supplies signals through a plurality of fiber optic cables **370B**, which comprise multiple lines of CPRI antenna carrier data in full duplex at high speed over the fiber optic cables **370B**. The PIM detector **370** can be installed remotely from the base station. RRUs **370A** transmit and receive radio frequency (RF) signals from one or more antennas **370C** through RF coaxial cables **370D**, denoted as “paths.”

(337) PIM detector **370** illustrated in FIG. **3B** measures the presence of PIM in one band and in one or multiple paths of an uplink based on detection algorithms applied to the measured signals. PIM detector **370** can rank the source of PIM due to a junction, cables or components, or an antenna. PIM detector **370** can quantify the PIM interference level, from low, moderate, to severe.

(338) Knowing that a transmission signal on the same line is strong, if the line is duplexed, can indicate a PIM issue, and generally is an internal problem to the base station. Based on the level of PIM measured and correlation to received signal strength indicator (RSSI), a determination of the magnitude of the problem will be evaluated. For example, if the level of PIM on Path **1** and on Path **2** are correlated, then it is more likely an external PIM is present. If there is no correlation, it is likely an internal PIM is present due to a particular component of the base station. By assessing a signature of the PIM, PIM detector **370** can detect whether the source of interference is due to an LTE band signal, or due to other cellular technologies, or even non-cellular sources. As shown in FIG. **3B**, if PIM is measured and is available on multiple bands that share the same cables and antenna, it is likely that a particular component or cable of a base station is the source of PIM.

(339) Correlation with time can also be detected if PIM interference happens during a particular time when the system is heavily used and the PIM level can be correlated to another transmitter.

(340) In an embodiment, a sequence of steps in a method are performed in which transmitters are turned on at different high power levels during a maintenance window and in certain combination(s) so that the PIM detector can determine if the PIM happens at certain target bands and under certain conditions. As illustrated in FIG. **3B**, a cellular network carrier supplies 8 RF bands or services to a base station comprising four antennas **370C** in the mobile network. Each band/service may comprise 2 paths, or possibly 4 paths. As illustrated in FIG. **3B**, four antennas **370C** comprise the 8 bands/services supplied by the carrier, over a total of 24 paths, two paths for the low frequency band, and four paths for the high frequency band on each antenna.

(341) In the method, PIM detector **370** builds an array of 24 RSSI measurements, one RSSI measurement for each path, while transmission occurs on one path, preferably under a simulated high traffic condition. Such high traffic condition can be simulated with the help of an Air interface

load generator (AILG) or an Orthogonal channel noise simulator (OCNS) that creates signals at different frequencies, so that the level of PIM can be detected and determined. Another array of 24 RSSI measurements is built by PIM detector **370** while transmission occurs only on the second path, and so forth. Each transmission path is used to create a row in a 24×24 matrix $M_{sub.i}$ of RSSI measurements formed by the various transmissions:

$$(342) \ 24[24] = M_i,$$

where i denotes the power level.

(343) Next, PIM detector **370** changes the power level of the transmissions, thereby forming a series of matrices. By comparing the RSSI in each matrix to the next one, PIM detector **370** can determine whether the transmissions are creating leakage, or possibly internal PIM from a particular transmission path. If increasing power with M_i has an impact on the RSSI reading, then the interference is PIM, and internal PIM in particular. If the change in RSSI when power is doubled is 2 dBc, then the interference can be characterized as a 3rd order PIM. If the increase is $\approx 3-8$ dBc, then the interference can be characterized as 5th order PIM. If increasing power with M_i does not have an impact on the RSSI reading, then the interference is external.

(344) In an embodiment, different combinations of bands and/or paths that can be impacted by PIM arise from multiple transmissions. From such combinations of bands and/or paths, PIM detector **370** can be configured to determine if the PIM is caused by an internal component of a base station or an external component that is not part of the base station (e.g., an external metallic object that reflects a signal transmission from the base station). PIM detector **370** can measure interference based on the detection algorithms in multiple bands and/or multiple paths based on the multiple transmissions. For example, consider that, if only two transmitters are transmitting in two bands out of the eight bands, there would be $(8!/6!/2!)$ combinations, or 28 possible dual band transmission cases for the base station illustrated in FIG. 3B. If three transmitters out of the eight bands were transmitting at the same time to cause the PIM, there would be $(8!/5!/3!)$ combinations, or 56 possible tri-band transmission cases for the base station of FIG. 3B. If four transmitters out of the eight bands were transmitting at the same time to cause the PIM, there would be $(8!/4!/4!)$ combinations, or 70 possible quad-band transmission cases for the base station of FIG. 3B. If all 154 possible transmission combinations $(28+56+70)$ are considered, then a matrix MC_i can be formed by measuring the RSSI in each of the 24 paths:

$$(345) \ 154[24] = MC_i,$$

where i denotes the power level.

(346) By comparing the RSSI levels under different power levels and conditions, PIM detector **370** can determine whether there is a certain combination that creates PIM interference, whether the interference is a function of certain frequency bands, or whether the interference is a function of certain antenna proximity issues. By repeating the test transmissions at other sectors, further diagnosis can be performed.

(347) Once PIM interference has been detected, corrective actions may include, for example, applying one or more polarization adjusting and/or phase shifting/delaying techniques described herein; resolving issues related to variability among sectors; or looking at MC_i and evaluating the increase in RSSI at different levels to determine what order level PIM (3rd, 5th, etc.) is causing the interference. Additionally, the impact on performance under different loading conditions can be considered. For example, the delta increase in RSSI can be correlated to a certain power level, and as a result, the offending transmission should be reduced. Another case is when the optimum level of transmission is determined for a particular traffic condition on one of the 8 transmitters. This process may be repeated for each band.

(348) In an embodiment, interference detection may be extended in several ways: the matrices of a particular sector may be correlated with that of another sector in the same site, and as a result, determine if there are issues in particular with antenna isolation, or more of a systemic issue; the matrix element of a particular sector can be correlated to determine the integrity of the RF

environment and the quality of RF signals; or detection algorithms can determine the LTE quality. In an embodiment, the matrices of a particular site can be correlated with those of a neighboring site (taking into consideration that the other site may have a different antenna configuration or isolation but the same frequency bands). In this case, the information can help increase the confidence level in determining if the PIM is internal or external, and if it's external, what bands are targeted. The information can help detect if the PIM or interference is coming from another competitive carrier or is self-inflicted due to the multiple bands in operation. (For example, peak and quiet time tends to be the same for all carriers and therefore maintenance window testing can rule out or confirm the source.)

(349) In another embodiment, RSSI elements in the matrices could be replaced with spectral pictures in which the information can be segmented further into an array of frequencies. This will give further insight and provide information on the mixing combinations and determine if there are leakages instead of PIM. Also, any correlation with power levels can be used to determine the order of the PIM. In an embodiment, the system can be automated to perform carrier testing at maintenance window, which will provide a wealth of information on the quality of the network.

(350) FIG. 3C illustrates a block diagram depicting an example, non-limiting embodiment of a communication system **385** including a virtualized interference mitigation network in accordance with various aspects described herein. In various embodiments, the communications system **385** may be functioning within, or operatively overlaid upon, the communications network **100** of FIG. 1A and/or the communications system **180** of FIG. 1B.

(351) As depicted in FIG. 3C, a virtualized interference mitigation network is presented that can be used to implement some or all of the methods for interference mitigation described herein. For example, portion(s) of this network can facilitate, in whole or in part, detection of interference/PIM in a communications system and performing of action(s), such as polarization adjusting and/or phase shifting/delaying, as described herein, that result in mitigation/cancellation of the interference/PIM. In one or more embodiments, communication system **385** may be configured to provide conditioning of uplink signals. Communication system **385** can include remote radio units (RRU) **320** and one or more antennas **340**. The RRUs **320** can transmit and receive radio frequency (RF) signals to and from the one or more antennas **340** through RF coaxial cables **350**. The RRUs **320** can include circuitry to convert the baseband digital signals to RF signals, and vice-versa. In one embodiment, the RRUs **320** can be coupled to fiber optic cables **330**. In one embodiment, the fiber optic cables **330** can carry digital data to and from the RRUs. In one embodiment, a common public radio interface (CPRI) protocol can be used to carry digital data to and from the RRUs **320** via full duplex at high speed over the fiber optic cables **330**.

(352) The digital data, also known as antenna carriers (denoted by AxC), can originate from the RRUs **320** or from virtual BBUs **385A**. In one embodiment, each antenna carrier can include I/Q data for an RF signal associated with an antenna element. I/Q data can describe an instantaneous state of an RF signal by providing magnitude and phase angle information based on sinusoidal modeling of the RF signal. If an RF signal is used for modulating a voice/data signal on a carrier wave, then I/Q data can effectively convey information about the data being carried. In addition, I/Q data can be provided in a Cartesian coordinate system (X, Y), where X =amplitude and Y =phase angle. In an embodiment illustrated in FIG. 3C, a 2×2 MIMO antenna **341** can include two uplink antenna carriers on the uplink fiber and two downlink antenna carriers on the downlink fiber. I/Q data samples can be interleaved and placed in a basic frame of the antenna carrier. Samples from multiple antennas are contained in each basic frame.

(353) In one or more embodiments, the communication system **385** can include virtualized interference mitigation, where functions for interference detection, mitigation (e.g., via polarization adjusting and/or phase shifting/delaying as described herein), and baseband communications serving uplink and downlink paths can be implemented via a cloud networking architecture **386**. In particular, a cloud networking architecture **386** is shown that can leverage cloud technologies and

supports innovation and scalability. The cloud networking architecture **386** for virtualized interference mitigation can include a transport layer **387** and/or one or more virtualized network function clouds **385D**. The cloud networking architecture **386** can also include one or more cloud computing environments **385E**. In various embodiments, this cloud networking architecture **386** can be implemented via an open architecture that leverages application programming interfaces (APIs), which can seamlessly scale to meet evolving customer requirements including traffic growth, diversity of traffic types, and diversity of performance and reliability expectations.

(354) In one or more embodiments, the cloud networking architecture **386** can employ virtualized network function clouds **385D** to perform some or all of the functions of interference detection and mitigation (e.g., via polarization adjusting and/or phase shifting/delaying) described herein. The virtualized network function clouds **385D** can include virtual network functions (VFN) or virtual network elements (VFE) to perform some or all of the functions for interference detection and mitigation (e.g., via polarization adjusting and/or phase shifting/delaying) as described herein. For example, the virtualized network function clouds **385D** can provide a substrate of networking capability, often called Network Function Virtualization Infrastructure (NFVI) or simply infrastructure that is capable of being directed with software and Software Defined Networking (SDN) protocols. In one embodiment, the virtualized network function clouds **385D** can include one or more a SDN Controllers **385C** that can direct, control, and/or modify the operation of the virtualized network function clouds **385D** and of the VFE and/or VFE that are instantiated in the virtualized network function clouds **385D**. The virtualized network function clouds **385D** can support Network Function Virtualization (NFV).

(355) As an example, an interference mitigation function, such as an interference/PIM cancellation block (e.g., the interference/PIM cancellation block **203c** of FIG. 2C or the like), an interference/PIM detection control device (e.g., interference/PIM detection control device **203d** of FIG. 2C or the like), an adaptive front-end module, and/or the like can be implemented via a VNE composed of NFV software modules, merchant silicon, and/or associated controllers. The interference mitigation function can be in the form of a Virtual Interference Mitigation Service that is instantiated into the virtualized network function cloud **385D** by the SDN Controller **385C**. Various interference mitigation functions can be instantiated in the virtualized network function clouds **385D**, such as, but not limited to, systems and/or methods for signal processing, interference detection, adaptive threshold determination, interference/PIM mitigation (e.g., via polarization adjusting and/or phase shifting/delaying, as described herein), network adaptation and optimization, and/or link analysis, optimization, and/or management. Other interference mitigation functions can be instantiated in the virtualized network function clouds **385D**, such as, but not limited to, systems and/or methods for adapting inter-cell interference thresholds based on thermal noise, conditioning uplink signals, and general interference diagnosis and testing.

(356) In one or more embodiments, software can be written so that increasing workload on the virtualized network function clouds **385D** consumes incremental resources from a common resource pool, and moreover so that it's elastic: so the resources are only consumed when needed. In a similar fashion, virtual interference mitigation servers **385B**, virtual BBUs **385A**, and other network elements, such as other routers, switches, edge caches, and middle-boxes, can be instantiated from a common resource pool as directed by a SDN Controller **385C**. Such sharing of infrastructure across a broad set of uses makes planning and growing infrastructure easier to manage.

(357) In an embodiment, the cloud networking architecture **386** can include a transport layer **387**. The transport layer **387** can include fiber, cable, wired and/or wireless transport elements, network elements and interfaces to transmit digital signals to and from the RRUs **320** to the virtualized network function clouds **385D**. In one example, fiber optic cable **330** can transmit digital signals between the RRUs **320** and the virtualized network function cloud **385D**, and the transport layer **387** simply be a continuation of the fiber optic cable and/or include repeating and/or buffering

functions. In one example, the transport layer **387** can translate the digital signals between the fiber optic cable **330** and other transport media, such as wired or wireless connections. In one embodiment, a network element, such as a virtual BBU **385A**, may need to be positioned at a specific location. For example, a bank of virtual BBUs **385A** may be physically co-located to take advantage of common infrastructure. To optimally link digital signals between a client RRU **320** and a virtual BBU **385A** that is in a remote location, the transport layer **387** may convert between a communication media, such as a fiber optic link to the RRU **320**, and a long-haul media, such as the Internet or a cellular system. In one embodiment, a network element, such as a BBU, may include physical layer adapters that cannot be abstracted or virtualized, or that might require special DSP code and analog front-ends (AFEs), such that the network element cannot be completely virtualized. In this case, all or part of the network element may be included in the transport layer **387**.

(358) The virtualized network function clouds **385D** can interface with the transport layer **387** to provide virtual network elements, such as virtual interference mitigation servers **385B** and virtual BBUs **385A**, that provide specific NFVs. In particular, the virtualized network function cloud **385D** can leverage cloud operations, applications, and architectures to support communication loading and required interference mitigation. For example, virtual interference mitigation servers **385B** and virtual BBUs **385A** can employ network function software that provides either a one-for-one mapping of non-networked versions of these functions or, alternately, combines versions of these functions that are designed and/or optimized for cloud computing. For example, virtual interference mitigation servers **385B** and virtual BBUs **385A**, or other ancillary network devices, may be able to process digital data signals without generating large amounts of network traffic. As such, their workload can be distributed across a number of servers within and/or between each virtualized network function cloud **385D**. Each of the virtual interference mitigation servers **385B** and virtual BBUs **385A** can add its portion of capability to the whole, so that the cloud networking architecture **386** exhibits an overall elastic function with higher availability than a strictly monolithic version. These virtual interference mitigation servers **385B** and virtual BBUs **385A** can be instantiated and managed by a SDN Controller **385C** using an orchestration approach similar to those used in cloud compute services.

(359) In one or more embodiments, the virtualized network function clouds **385D** can further interface with other cloud computing environments **385E** via application programming interfaces (API) that can expose functional capabilities of the virtual interference mitigation servers **385B** and virtual BBUs **385A** to provide flexible and expanded capabilities to the virtualized network function cloud **385D**. In particular, interference mitigation workloads may have applications distributed across the virtualized network function clouds **385D** and the cloud computing environment **385E** (at third-party vendors). The SDN Controller **385C** may orchestrate workloads supported entirely in NFV infrastructure from these third-party locations.

(360) In one or more embodiments, a virtual interference mitigation server **385B** at a virtualized network function cloud **385D** can be configured to receive digital signals from RRUs **320** operating at a communications site, such as at a cellular tower. The virtual interference mitigation server **385B** can rely on the digital nature of the digital signals (converted from the RF domain prior to transmission on the fiber optic cables **330**), the transport layer **387**, and the virtualized network function cloud **385D** to facilitate remote processing of digital signals representing RF signals received at the RRUs **320**. In one embodiment, the virtual interference mitigation server **385B** can perform measurements on these digital signals for detecting interference on RF signals, and can initiate mitigation for detected interference.

(361) In one or more embodiments, the virtual interference mitigation server **385B** can perform measurements on digital data that it receives via the transport layer **387**. The virtual interference mitigation server **385B** can include interfaces capable of interfacing with the digital signals in a protocol, such as the common public radio interface (CPRI) protocol. In one embodiment, the

virtual interference mitigation server **385B** can include one or more protocol-capable interface cards. In one embodiment, the virtual interference mitigation server **385B** can implement protocol compatibility via hardware, software, or a combination of hardware and software. In one embodiment, each virtual interference mitigation server **385B** can support one or more data links (CPRI-capable links). Each data link can include one or more frequency bands. Multiple data links can include multiple frequency bands. Each data link can further include signals associated with multiple-input and multiple-output (MIMO) antennas **341** or diversity antenna configurations. Each data link can support one or more sectors. For example, a virtual interference mitigation server **385B** can provide capacity for banks of RRUs **320**, antenna carriers, and sectors at multiple cell locations.

(362) In one or more embodiments, the virtual interference mitigation server **385B** can examine system information blocks (SIBs) to determine parameters of the uplink path signals received over the transport layer **387**. In an embodiment, the virtual interference mitigation server **385B** can obtain SINR measurements of uplink paths according to digital signal information from SIBs. The virtual interference mitigation server **385B** can determine whether one or more SINR measurements fall below a threshold and, in turn, can take corrective action to improve one or more SINR measurements that fall below the threshold. For example, the virtual interference mitigation server **385B** can determine a corrective action, whereby an uplink path that is affected by interference is moved to an available uplink path in the same sector, or in different sectors. In an embodiment, the virtual interference mitigation server **385B** can compare signals from different sectors to determine an approach for taking corrective action.

(363) In one or more embodiments, the virtual interference mitigation server **385B** can (e.g., optionally) include a conditioner function. The condition function can include an adaptive filter, and/or can execute signal processing algorithm(s). The conditioner of the virtual interference mitigation server **385B** can receive digital signals from the transport layer **387**, where these digital signals represent RF signals that are received at the RRU **320**. The conditioner of the virtual interference mitigation server **385B** can provide support for 2×2 and 4×4 MIMO antenna configurations (or other MIMO configurations), diversity antenna configurations, and a variety of CPRI interfaces. In one embodiment, the conditioner can be co-located at the virtual interference mitigation server **385B**. In other embodiments, the conditioner can be located anywhere, including at the virtual BBU **385A**, the RRU **320**, the transport layer **387**, and/or at a second virtualized network function cloud **385D** or a cloud computing environment **385E**.

(364) In one or more embodiments, the virtual BBU **385A** provides digital communications to the RRU **320**. In one embodiment, a virtual BBU **385A** that is directing a RRU **320** can be located in the same virtualized network function cloud **385D** as a virtual interference mitigation server **385B** that is performing interference measurements on digital signals from this same RRU **320**. In this way, a SDN Controller **385C** at the virtualized network function cloud **385D** can coordinate instantiation, configuration, and, if needed, decommissioning of the virtual BBU **385A** and the virtual interference mitigation server **385B**. In one embodiment, the virtual BBU **385A** and the virtual interference mitigation server **385B** can be instantiated into different virtualized network function clouds **385D**. In this situation, multiple SDN Controllers **385C** and virtualized network function clouds **385D** may be involved in managing these VNE.

(365) FIG. 3D depicts an illustrative non-limiting embodiment of a method **388** for performing virtual interference mitigation. Method **388** can be combined or adapted in whole or in part with other embodiments of the subject disclosure including other methods described herein. Beginning with step **388A**, a virtual interference mitigation server **385B** of the subject disclosure can be adapted to obtain digital data representing RF signals of uplink paths associated with RRUs **320** in communication with communication devices (e.g., mobile phones, tablets, stationary communication devices, etc.) that transmit wireless signals on the uplink paths. Uplink instructions are generally sent to communication devices via downlink wireless signals to enable the

communication devices to engage in uplink wireless communications. In other embodiments, the virtual interference mitigation server **385B** can obtain uplink information based on information provided by a transport layer **387**. The uplink instructions can include SIBs from which the system performing method **388** can obtain uplink information, including an indication of how many communication devices will be transmitting wireless signals in uplink paths assigned by one or more base stations, power level(s) that will be used by each of the communication devices during uplink wireless communications, the resource blocks that are assigned to each communication device, and other useful parametric information utilized by each communication device when communicating via an uplink path.

(366) In one or more embodiments, at step **388B**, the virtual interference mitigation server **385B** of the subject disclosure can be adapted to perform measurements of the digital signals of the uplink paths assigned to the communication devices. Wireless signals from the communication devices can be received via antennas **340**. These antennas **340** can be coupled to RRUs **320**, which can generate the digital signals representing the RF signals that have been received. In one or more embodiments, the virtual interference mitigation server **385B** can perform measurements, processing, and/or conditioning of the digital signals received from the transport layer **387**.

(367) At step **388C**, the virtual interference mitigation server **385B** can be adapted to detect signal interference in one or more of the measurements performed at step **388B** based on such measurements that compare unfavorably to one or more thresholds. As noted earlier, the uplink information can include, but is not limited to, the number of communication devices that will be transmitting in uplink paths, the power level(s) used by each communication devices while transmitting during one or more assigned resource blocks, the resource blocks that have been assigned to each communication device, and other useful parametric information utilized by each communication device when communicating via an uplink path.

(368) The number of communication devices transmitting wireless signals on uplink paths can be used to determine a density of spectral energy expected in certain resource blocks and at certain time slots. With prior knowledge of the transmission characteristics used by each communication device, the system can be adapted to determine a threshold per resource block based on an expected power level for each corresponding resource block, an overall threshold based on an expected average power level across groups of resource blocks, a timing of the use of the resource blocks by the communication devices, or combinations thereof. A threshold can be determined statically, or dynamically as a running average of power levels. In an embodiment, the measurements performed at step **388B** can be based on SINR (or other) measurements. At step **388C**, the system of the subject disclosure can be further adapted to identify one or more affected uplink paths based on one or more measurements that compare unfavorably to the one or more thresholds of step **388B**.

(369) Responsive to identifying the affected paths and thereby detecting signal interference in such paths based on the threshold(s), the virtual interference mitigation server **385B** of the subject disclosure can be adapted to take corrective actions in step **388D** to improve the measurements of the affected paths. The affected uplink path can be affected by interference signals as described in the subject disclosure. The corrective action can include without limitation, singly or in combination, locating unused uplink paths that are not affected by the interference, suppressing one or more interference signals on the affected uplink paths, adjusting the number of communication device allowed to transmit wireless signals on the affected uplink paths, and/or by performing other mitigation techniques (e.g., polarization adjusting and/or phase shifting/delaying techniques) described in the subject disclosure.

(370) At step **388E**, the virtual interference mitigation server **385B** can be adapted to provide updated digital data to one or more virtual BBU **385A** to implement a corrective action. The virtual interference mitigation server **385B** of the subject disclosure can instruct one or more virtual BBUs **385A** to effect one or more polarization adjusting and/or phase shifting/delaying techniques described herein. Additionally, or alternatively, the virtual interference mitigation server **385B** can

instruct one or more virtual BBUs **385A** to move transmissions to one or more uplink paths different from the one or more affected uplink paths, instruct one or more of the plurality of communication devices to move to one or more uplink paths to uplink paths located in different sectors, or to move affected uplink paths to different uplink paths of a different base station, or any combinations thereof. The different uplink paths moved to can be unused, and thus, available uplink paths. In an embodiment, the virtual interference mitigation server **385B** of the subject disclosure can check the noise and/or interference level of the available uplink paths to ensure that better communications can be provided as a result of moving from the affected uplink paths.

(371) The foregoing embodiments can be adapted for other applications as well. For example, the uplink information can be used by the system of the subject disclosure to determine PRB utilization, which can be reported to a base station processor. Based on interference detection and mitigation across one or more resource blocks, the system of the subject disclosure can be further adapted to provide recommendations and/or direct a base station processor to modify SIBs to improve PRB utilization in one or more uplink paths.

(372) While for purposes of simplicity of explanation, the respective processes are shown and described as a series of blocks in FIG. **3D**, respectively, it is to be understood and appreciated that the claimed subject matter is not limited by the order of the blocks, as some blocks can occur in different orders and/or concurrently with other blocks from what is depicted and described herein. Moreover, not all illustrated blocks may be required to implement the methods described herein.

(373) Turning now to FIG. **4**, there is illustrated a block diagram of a computing environment in accordance with various aspects described herein. In order to provide additional context for various embodiments of the embodiments described herein, FIG. **4** and the following discussion are intended to provide a brief, general description of a suitable computing environment **400** in which the various embodiments of the subject disclosure can be implemented. In particular, computing environment **400** can be used in the implementation of network elements **150**, **152**, **154**, **156**, access terminal **112**, base station or access point **122**, switching device **132**, media terminal **142**, and/or one or more devices/components/systems of FIGS. **3A-3C**, etc. Each of these devices can be implemented via computer-executable instructions that can run on one or more computers, and/or in combination with other program modules and/or as a combination of hardware and software. For example, computing environment **400** can facilitate, in whole or in part, detection of interference/PIM in a communications system and performing of action(s), such as polarization adjusting and/or phase shifting/delaying, as described herein, that result in mitigation/cancellation of the interference/PIM.

(374) Generally, program modules comprise routines, programs, components, data structures, etc., that perform particular tasks or implement particular abstract data types. Moreover, those skilled in the art will appreciate that the methods can be practiced with other computer system configurations, comprising single-processor or multiprocessor computer systems, minicomputers, mainframe computers, as well as personal computers, hand-held computing devices, microprocessor-based or programmable consumer electronics, and the like, each of which can be operatively coupled to one or more associated devices.

(375) As used herein, a processing circuit includes one or more processors as well as other application specific circuits such as an application specific integrated circuit, digital logic circuit, state machine, programmable gate array or other circuit that processes input signals or data and that produces output signals or data in response thereto. It should be noted that while any functions and features described herein in association with the operation of a processor could likewise be performed by a processing circuit.

(376) The illustrated embodiments of the embodiments herein can be also practiced in distributed computing environments where certain tasks are performed by remote processing devices that are linked through a communications network. In a distributed computing environment, program modules can be located in both local and remote memory storage devices.

(377) Computing devices typically comprise a variety of media, which can comprise computer-readable storage media and/or communications media, which two terms are used herein differently from one another as follows. Computer-readable storage media can be any available storage media that can be accessed by the computer and comprises both volatile and nonvolatile media, removable and non-removable media. By way of example, and not limitation, computer-readable storage media can be implemented in connection with any method or technology for storage of information such as computer-readable instructions, program modules, structured data or unstructured data.

(378) Computer-readable storage media can comprise, but are not limited to, random access memory (RAM), read only memory (ROM), electrically erasable programmable read only memory (EEPROM), flash memory or other memory technology, compact disk read only memory (CD-ROM), digital versatile disk (DVD) or other optical disk storage, magnetic cassettes, magnetic tape, magnetic disk storage or other magnetic storage devices or other tangible and/or non-transitory media which can be used to store desired information. In this regard, the terms “tangible” or “non-transitory” herein as applied to storage, memory or computer-readable media, are to be understood to exclude only propagating transitory signals per se as modifiers and do not relinquish rights to all standard storage, memory or computer-readable media that are not only propagating transitory signals per se.

(379) Computer-readable storage media can be accessed by one or more local or remote computing devices, e.g., via access requests, queries or other data retrieval protocols, for a variety of operations with respect to the information stored by the medium.

(380) Communications media typically embody computer-readable instructions, data structures, program modules or other structured or unstructured data in a data signal such as a modulated data signal, e.g., a carrier wave or other transport mechanism, and comprises any information delivery or transport media. The term “modulated data signal” or signals refers to a signal that has one or more of its characteristics set or changed in such a manner as to encode information in one or more signals. By way of example, and not limitation, communication media comprise wired media, such as a wired network or direct-wired connection, and wireless media such as acoustic, RF, infrared and other wireless media.

(381) With reference again to FIG. 4, the example environment can comprise a computer **402**, the computer **402** comprising a processing unit **404**, a system memory **406** and a system bus **408**. The system bus **408** couples system components including, but not limited to, the system memory **406** to the processing unit **404**. The processing unit **404** can be any of various commercially available processors. Dual microprocessors and other multiprocessor architectures can also be employed as the processing unit **404**.

(382) The system bus **408** can be any of several types of bus structure that can further interconnect to a memory bus (with or without a memory controller), a peripheral bus, and a local bus using any of a variety of commercially available bus architectures. The system memory **406** comprises ROM **410** and RAM **412**. A basic input/output system (BIOS) can be stored in a non-volatile memory such as ROM, erasable programmable read only memory (EPROM), EEPROM, which BIOS contains the basic routines that help to transfer information between elements within the computer **402**, such as during startup. The RAM **412** can also comprise a high-speed RAM such as static RAM for caching data.

(383) The computer **402** further comprises an internal hard disk drive (HDD) **414** (e.g., EIDE, SATA), which internal HDD **414** can also be configured for external use in a suitable chassis (not shown), a magnetic floppy disk drive (FDD) **416**, (e.g., to read from or write to a removable diskette **418**) and an optical disk drive **420**, (e.g., reading a CD-ROM disk **422** or, to read from or write to other high capacity optical media such as the DVD). The HDD **414**, magnetic FDD **416** and optical disk drive **420** can be connected to the system bus **408** by a hard disk drive interface **424**, a magnetic disk drive interface **426** and an optical drive interface **428**, respectively. The hard

disk drive interface **424** for external drive implementations comprises at least one or both of Universal Serial Bus (USB) and Institute of Electrical and Electronics Engineers (IEEE) 1394 interface technologies. Other external drive connection technologies are within contemplation of the embodiments described herein.

(384) The drives and their associated computer-readable storage media provide non-volatile storage of data, data structures, computer-executable instructions, and so forth. For the computer **402**, the drives and storage media accommodate the storage of any data in a suitable digital format.

Although the description of computer-readable storage media above refers to a hard disk drive (HDD), a removable magnetic diskette, and a removable optical media such as a CD or DVD, it should be appreciated by those skilled in the art that other types of storage media which are readable by a computer, such as zip drives, magnetic cassettes, flash memory cards, cartridges, and the like, can also be used in the example operating environment, and further, that any such storage media can contain computer-executable instructions for performing the methods described herein.

(385) A number of program modules can be stored in the drives and RAM **412**, comprising an operating system **430**, one or more application programs **432**, other program modules **434** and program data **436**. All or portions of the operating system, applications, modules, and/or data can also be cached in the RAM **412**. The systems and methods described herein can be implemented utilizing various commercially available operating systems or combinations of operating systems.

(386) A user can enter commands and information into the computer **402** through one or more wired/wireless input devices, e.g., a keyboard **438** and a pointing device, such as a mouse **440**. Other input devices (not shown) can comprise a microphone, an infrared (IR) remote control, a joystick, a game pad, a stylus pen, touch screen or the like. These and other input devices are often connected to the processing unit **404** through an input device interface **442** that can be coupled to the system bus **408**, but can be connected by other interfaces, such as a parallel port, an IEEE 1394 serial port, a game port, a universal serial bus (USB) port, an IR interface, etc.

(387) A monitor **444** or other type of display device can be also connected to the system bus **408** via an interface, such as a video adapter **446**. It will also be appreciated that in alternative embodiments, a monitor **444** can also be any display device (e.g., another computer having a display, a smart phone, a tablet computer, etc.) for receiving display information associated with computer **402** via any communication means, including via the Internet and cloud-based networks. In addition to the monitor **444**, a computer typically comprises other peripheral output devices (not shown), such as speakers, printers, etc.

(388) The computer **402** can operate in a networked environment using logical connections via wired and/or wireless communications to one or more remote computers, such as a remote computer(s) **448**. The remote computer(s) **448** can be a workstation, a server computer, a router, a personal computer, portable computer, microprocessor-based entertainment appliance, a peer device or other common network node, and typically comprises many or all of the elements described relative to the computer **402**, although, for purposes of brevity, only a remote memory/storage device **450** is illustrated. The logical connections depicted comprise wired/wireless connectivity to a local area network (LAN) **452** and/or larger networks, e.g., a wide area network (WAN) **454**. Such LAN and WAN networking environments are commonplace in offices and companies, and facilitate enterprise-wide computer networks, such as intranets, all of which can connect to a global communications network, e.g., the Internet.

(389) When used in a LAN networking environment, the computer **402** can be connected to the LAN **452** through a wired and/or wireless communications network interface or adapter **456**. The adapter **456** can facilitate wired or wireless communication to the LAN **452**, which can also comprise a wireless AP disposed thereon for communicating with the adapter **456**.

(390) When used in a WAN networking environment, the computer **402** can comprise a modem **458** or can be connected to a communications server on the WAN **454** or has other means for establishing communications over the WAN **454**, such as by way of the Internet. The modem **458**,

which can be internal or external and a wired or wireless device, can be connected to the system bus **408** via the input device interface **442**. In a networked environment, program modules depicted relative to the computer **402** or portions thereof, can be stored in the remote memory/storage device **450**. It will be appreciated that the network connections shown are example and other means of establishing a communications link between the computers can be used.

(391) The computer **402** can be operable to communicate with any wireless devices or entities operatively disposed in wireless communication, e.g., a printer, scanner, desktop and/or portable computer, portable data assistant, communications satellite, any piece of equipment or location associated with a wirelessly detectable tag (e.g., a kiosk, news stand, restroom), and telephone. This can comprise Wireless Fidelity (Wi-Fi) and BLUETOOTH® wireless technologies. Thus, the communication can be a predefined structure as with a conventional network or simply an ad hoc communication between at least two devices.

(392) Wi-Fi can allow connection to the Internet from a couch at home, a bed in a hotel room or a conference room at work, without wires. Wi-Fi is a wireless technology similar to that used in a cell phone that enables such devices, e.g., computers, to send and receive data indoors and out; anywhere within the range of a base station. Wi-Fi networks use radio technologies called IEEE 802.11 (a, b, g, n, ac, ag, etc.) to provide secure, reliable, fast wireless connectivity. A Wi-Fi network can be used to connect computers to each other, to the Internet, and to wired networks (which can use IEEE 802.3 or Ethernet). Wi-Fi networks operate in the unlicensed 2.4 and 5 GHz radio bands for example or with products that contain both bands (dual band), so the networks can provide real-world performance similar to the basic 10BaseT wired Ethernet networks used in many offices.

(393) Turning now to FIG. 5, an embodiment **500** of a mobile network platform **510** is shown that is an example of network elements **150**, **152**, **154**, **156**, and/or one or more devices/components/systems of FIGS. 3A-3C, etc. For example, platform **510** can facilitate, in whole or in part, detection of interference/PIM in a communications system and performing of action(s), such as polarization adjusting and/or phase shifting/delaying, as described herein, that result in mitigation/cancellation of the interference/PIM. In one or more embodiments, the mobile network platform **510** can generate and receive signals transmitted and received by base stations or access points such as base station or access point **122**. Generally, mobile network platform **510** can comprise components, e.g., nodes, gateways, interfaces, servers, or disparate platforms, that facilitate both packet-switched (PS) (e.g., internet protocol (IP), frame relay, asynchronous transfer mode (ATM)) and circuit-switched (CS) traffic (e.g., voice and data), as well as control generation for networked wireless telecommunication. As a non-limiting example, mobile network platform **510** can be included in telecommunications carrier networks, and can be considered carrier-side components as discussed elsewhere herein. Mobile network platform **510** comprises CS gateway node(s) **512** which can interface CS traffic received from legacy networks like telephony network(s) **540** (e.g., public switched telephone network (PSTN), or public land mobile network (PLMN)) or a signaling system #7 (SS7) network **560**. CS gateway node(s) **512** can authorize and authenticate traffic (e.g., voice) arising from such networks. Additionally, CS gateway node(s) **512** can access mobility, or roaming, data generated through SS7 network **560**; for instance, mobility data stored in a visited location register (VLR), which can reside in memory **530**. Moreover, CS gateway node(s) **512** interfaces CS-based traffic and signaling and PS gateway node(s) **518**. As an example, in a 3GPP UMTS network, CS gateway node(s) **512** can be realized at least in part in gateway GPRS support node(s) (GGSN). It should be appreciated that functionality and specific operation of CS gateway node(s) **512**, PS gateway node(s) **518**, and serving node(s) **516**, is provided and dictated by radio technology(ies) utilized by mobile network platform **510** for telecommunication over a radio access network **520** with other devices, such as a radiotelephone **575**.

(394) In addition to receiving and processing CS-switched traffic and signaling, PS gateway

node(s) **518** can authorize and authenticate PS-based data sessions with served mobile devices. Data sessions can comprise traffic, or content(s), exchanged with networks external to the mobile network platform **510**, like wide area network(s) (WANs) **550**, enterprise network(s) **570**, and service network(s) **580**, which can be embodied in local area network(s) (LANs), can also be interfaced with mobile network platform **510** through PS gateway node(s) **518**. It is to be noted that WANs **550** and enterprise network(s) **570** can embody, at least in part, a service network(s) like IP multimedia subsystem (IMS). Based on radio technology layer(s) available in technology resource(s) or radio access network **520**, PS gateway node(s) **518** can generate packet data protocol contexts when a data session is established; other data structures that facilitate routing of packetized data also can be generated. To that end, in an aspect, PS gateway node(s) **518** can comprise a tunnel interface (e.g., tunnel termination gateway (TTG) in 3GPP UMTS network(s) (not shown)) which can facilitate packetized communication with disparate wireless network(s), such as Wi-Fi networks.

(395) In embodiment **500**, mobile network platform **510** also comprises serving node(s) **516** that, based upon available radio technology layer(s) within technology resource(s) in the radio access network **520**, convey the various packetized flows of data streams received through PS gateway node(s) **518**. It is to be noted that for technology resource(s) that rely primarily on CS communication, server node(s) can deliver traffic without reliance on PS gateway node(s) **518**; for example, server node(s) can embody at least in part a mobile switching center. As an example, in a 3GPP UMTS network, serving node(s) **516** can be embodied in serving GPRS support node(s) (SGSN).

(396) For radio technologies that exploit packetized communication, server(s) **514** in mobile network platform **510** can execute numerous applications that can generate multiple disparate packetized data streams or flows, and manage (e.g., schedule, queue, format . . .) such flows. Such application(s) can comprise add-on features to standard services (for example, provisioning, billing, customer support . . .) provided by mobile network platform **510**. Data streams (e.g., content(s) that are part of a voice call or data session) can be conveyed to PS gateway node(s) **518** for authorization/authentication and initiation of a data session, and to serving node(s) **516** for communication thereafter. In addition to application server, server(s) **514** can comprise utility server(s), a utility server can comprise a provisioning server, an operations and maintenance server, a security server that can implement at least in part a certificate authority and firewalls as well as other security mechanisms, and the like. In an aspect, security server(s) secure communication served through mobile network platform **510** to ensure network's operation and data integrity in addition to authorization and authentication procedures that CS gateway node(s) **512** and PS gateway node(s) **518** can enact. Moreover, provisioning server(s) can provision services from external network(s) like networks operated by a disparate service provider; for instance, WAN **550** or Global Positioning System (GPS) network(s) (not shown). Provisioning server(s) can also provision coverage through networks associated to mobile network platform **510** (e.g., deployed and operated by the same service provider), such as distributed antenna networks that enhance wireless service coverage by providing more network coverage.

(397) It is to be noted that server(s) **514** can comprise one or more processors configured to confer at least in part the functionality of mobile network platform **510**. To that end, the one or more processor can execute code instructions stored in memory **530**, for example. It is to be appreciated that server(s) **514** can comprise a content manager, which operates in substantially the same manner as described hereinbefore.

(398) In example embodiment **500**, memory **530** can store information related to operation of mobile network platform **510**. Other operational information can comprise provisioning information of mobile devices served through mobile network platform **510**, subscriber databases; application intelligence, pricing schemes, e.g., promotional rates, flat-rate programs, couponing campaigns; technical specification(s) consistent with telecommunication protocols for operation of

disparate radio, or wireless, technology layers; and so forth. Memory **530** can also store information from at least one of telephony network(s) **540**, WAN **550**, SS7 network **560**, or enterprise network(s) **570**. In an aspect, memory **530** can be, for example, accessed as part of a data store component or as a remotely connected memory store.

(399) In order to provide a context for the various aspects of the disclosed subject matter, FIG. 5, and the following discussion, are intended to provide a brief, general description of a suitable environment in which the various aspects of the disclosed subject matter can be implemented.

While the subject matter has been described above in the general context of computer-executable instructions of a computer program that runs on a computer and/or computers, those skilled in the art will recognize that the disclosed subject matter also can be implemented in combination with other program modules. Generally, program modules comprise routines, programs, components, data structures, etc. that perform particular tasks and/or implement particular abstract data types.

(400) Turning now to FIG. 6, an illustrative embodiment of a communication device **600** is shown. The communication device **600** can serve as an illustrative embodiment of various devices and/or components described herein, such as base stations, RRHs, antenna systems, and/or the like; data terminals **114**, mobile devices **124**, vehicle **126**, display devices **144**, or other client devices for communication via communications network **125**; etc. For example, computing device **600** can facilitate, in whole or in part, detection of interference/PIM in a communications system and performing of action(s), such as polarization adjusting and/or phase shifting/delaying, as described herein, that result in mitigation/cancellation of the interference/PIM.

(401) The communication device **600** can comprise a wireline and/or wireless transceiver **602** (herein transceiver **602**), a user interface (UI) **604**, a power supply **614**, a location receiver **616**, a motion sensor **618**, an orientation sensor **620**, and a controller **606** for managing operations thereof. The transceiver **602** can support short-range or long-range wireless access technologies such as Bluetooth®, ZigBee®, WiFi, DECT, or cellular communication technologies, just to mention a few (Bluetooth® and ZigBee® are trademarks registered by the Bluetooth® Special Interest Group and the ZigBee® Alliance, respectively). Cellular technologies can include, for example, CDMA-1X, UMTS/HSDPA, GSM/GPRS, TDMA/EDGE, EV/DO, WiMAX, SDR, LTE, as well as other next generation wireless communication technologies as they arise. The transceiver **602** can also be adapted to support circuit-switched wireline access technologies (such as PSTN), packet-switched wireline access technologies (such as TCP/IP, VoIP, etc.), and combinations thereof.

(402) The UI **604** can include a depressible or touch-sensitive keypad **608** with a navigation mechanism such as a roller ball, a joystick, a mouse, or a navigation disk for manipulating operations of the communication device **600**. The keypad **608** can be an integral part of a housing assembly of the communication device **600** or an independent device operably coupled thereto by a tethered wireline interface (such as a USB cable) or a wireless interface supporting for example Bluetooth®. The keypad **608** can represent a numeric keypad commonly used by phones, and/or a QWERTY keypad with alphanumeric keys. The UI **604** can further include a display **610** such as monochrome or color LCD (Liquid Crystal Display), OLED (Organic Light Emitting Diode) or other suitable display technology for conveying images to an end user of the communication device **600**. In an embodiment where the display **610** is touch-sensitive, a portion or all of the keypad **608** can be presented by way of the display **610** with navigation features.

(403) The display **610** can use touch screen technology to also serve as a user interface for detecting user input. As a touch screen display, the communication device **600** can be adapted to present a user interface having graphical user interface (GUI) elements that can be selected by a user with a touch of a finger. The display **610** can be equipped with capacitive, resistive or other forms of sensing technology to detect how much surface area of a user's finger has been placed on a portion of the touch screen display. This sensing information can be used to control the manipulation of the GUI elements or other functions of the user interface. The display **610** can be an integral part of the housing assembly of the communication device **600** or an independent device

communicatively coupled thereto by a tethered wireline interface (such as a cable) or a wireless interface.

(404) The UI **604** can also include an audio system **612** that utilizes audio technology for conveying low volume audio (such as audio heard in proximity of a human ear) and high volume audio (such as speakerphone for hands free operation). The audio system **612** can further include a microphone for receiving audible signals of an end user. The audio system **612** can also be used for voice recognition applications. The UI **604** can further include an image sensor **613** such as a charged coupled device (CCD) camera for capturing still or moving images.

(405) The power supply **614** can utilize common power management technologies such as replaceable and rechargeable batteries, supply regulation technologies, and/or charging system technologies for supplying energy to the components of the communication device **600** to facilitate long-range or short-range portable communications. Alternatively, or in combination, the charging system can utilize external power sources such as DC power supplied over a physical interface such as a USB port or other suitable tethering technologies.

(406) The location receiver **616** can utilize location technology such as a global positioning system (GPS) receiver capable of assisted GPS for identifying a location of the communication device **600** based on signals generated by a constellation of GPS satellites, which can be used for facilitating location services such as navigation. The motion sensor **618** can utilize motion sensing technology such as an accelerometer, a gyroscope, or other suitable motion sensing technology to detect motion of the communication device **600** in three-dimensional space. The orientation sensor **620** can utilize orientation sensing technology such as a magnetometer to detect the orientation of the communication device **600** (north, south, west, and east, as well as combined orientations in degrees, minutes, or other suitable orientation metrics).

(407) The communication device **600** can use the transceiver **602** to also determine a proximity to a cellular, WiFi, Bluetooth®, or other wireless access points by sensing techniques such as utilizing a received signal strength indicator (RSSI) and/or signal time of arrival (TOA) or time of flight (TOF) measurements. The controller **606** can utilize computing technologies such as a microprocessor, a digital signal processor (DSP), programmable gate arrays, application specific integrated circuits, and/or a video processor with associated storage memory such as Flash, ROM, RAM, SRAM, DRAM or other storage technologies for executing computer instructions, controlling, and processing data supplied by the aforementioned components of the communication device **600**.

(408) Other components not shown in FIG. **6** can be used in one or more embodiments of the subject disclosure. For instance, the communication device **600** can include a slot for adding or removing an identity module such as a Subscriber Identity Module (SIM) card or Universal Integrated Circuit Card (UICC). SIM or UICC cards can be used for identifying subscriber services, executing programs, storing subscriber data, and so on.

(409) The terms “first,” “second,” “third,” and so forth, which may be used in the claims, unless otherwise clear by context, is for clarity only and doesn't otherwise indicate or imply any order in time. For instance, “a first determination,” “a second determination,” and “a third determination,” does not indicate or imply that the first determination is to be made before the second determination, or vice versa, etc.

(410) In the subject specification, terms such as “store,” “storage,” “data store,” data storage,” “database,” and substantially any other information storage component relevant to operation and functionality of a component, refer to “memory components,” or entities embodied in a “memory” or components comprising the memory. It will be appreciated that the memory components described herein can be either volatile memory or nonvolatile memory, or can comprise both volatile and nonvolatile memory, by way of illustration, and not limitation, volatile memory, non-volatile memory, disk storage, and memory storage. Further, non-volatile memory can be included in read only memory (ROM), programmable ROM (PROM), electrically programmable ROM

(EPROM), electrically erasable ROM (EEPROM), or flash memory. Volatile memory can comprise random access memory (RAM), which acts as external cache memory. By way of illustration and not limitation, RAM is available in many forms such as synchronous RAM (SRAM), dynamic RAM (DRAM), synchronous DRAM (SDRAM), double data rate SDRAM (DDR SDRAM), enhanced SDRAM (ESDRAM), Synchlink DRAM (SLDRAM), and direct Rambus RAM (DRRAM). Additionally, the disclosed memory components of systems or methods herein are intended to comprise, without being limited to comprising, these and any other suitable types of memory.

(411) Moreover, it will be noted that the disclosed subject matter can be practiced with other computer system configurations, comprising single-processor or multiprocessor computer systems, mini-computing devices, mainframe computers, as well as personal computers, hand-held computing devices (e.g., PDA, phone, smartphone, watch, tablet computers, netbook computers, etc.), microprocessor-based or programmable consumer or industrial electronics, and the like. The illustrated aspects can also be practiced in distributed computing environments where tasks are performed by remote processing devices that are linked through a communications network; however, some if not all aspects of the subject disclosure can be practiced on stand-alone computers. In a distributed computing environment, program modules can be located in both local and remote memory storage devices.

(412) Some of the embodiments described herein can also employ artificial intelligence (AI) to facilitate automating one or more features described herein. One or more embodiments can employ various AI-based schemes for carrying out various embodiments thereof. Moreover, a classifier can be employed. A classifier is a function that maps an input attribute vector, $x=(x_1, x_2, x_3, x_4, \dots, x_n)$, to a confidence that the input belongs to a class, that is, $f(x)=\text{confidence}(\text{class})$. Such classification can employ a probabilistic and/or statistical-based analysis (e.g., factoring into the analysis utilities and costs) to determine or infer an action that a user desires to be automatically performed. A support vector machine (SVM) is an example of a classifier that can be employed. The SVM operates by finding a hypersurface in the space of possible inputs, which the hypersurface attempts to split the triggering criteria from the non-triggering events. Intuitively, this makes the classification correct for testing data that is near, but not identical to, training data. Other directed and undirected model classification approaches comprise, e.g., naïve Bayes, Bayesian networks, decision trees, neural networks, fuzzy logic models, and probabilistic classification models providing different patterns of independence. Classification as used herein also is inclusive of statistical regression that is utilized to develop models of priority.

(413) As will be readily appreciated, one or more of the embodiments can employ classifiers that are explicitly trained (e.g., via a generic training data) as well as implicitly trained (e.g., via observing UE behavior, operator preferences, historical information, receiving extrinsic information). For example, SVMs can be configured via a learning or training phase within a classifier constructor and feature selection module. Thus, the classifier(s) can be used to automatically learn and perform a number of functions, including but not limited to determining according to predetermined criteria which of the acquired cell sites will benefit a maximum number of subscribers and/or which of the acquired cell sites will add minimum value to the existing communications network coverage, etc.

(414) As used in some contexts in this application, in some embodiments, the terms “component,” “system” and the like are intended to refer to, or comprise, a computer-related entity or an entity related to an operational apparatus with one or more specific functionalities, wherein the entity can be either hardware, a combination of hardware and software, software, or software in execution. As an example, a component may be, but is not limited to being, a process running on a processor, a processor, an object, an executable, a thread of execution, computer-executable instructions, a program, and/or a computer. By way of illustration and not limitation, both an application running on a server and the server can be a component. One or more components may reside within a

process and/or thread of execution and a component may be localized on one computer and/or distributed between two or more computers. In addition, these components can execute from various computer readable media having various data structures stored thereon. The components may communicate via local and/or remote processes such as in accordance with a signal having one or more data packets (e.g., data from one component interacting with another component in a local system, distributed system, and/or across a network such as the Internet with other systems via the signal). As another example, a component can be an apparatus with specific functionality provided by mechanical parts operated by electric or electronic circuitry, which is operated by a software or firmware application executed by a processor, wherein the processor can be internal or external to the apparatus and executes at least a part of the software or firmware application. As yet another example, a component can be an apparatus that provides specific functionality through electronic components without mechanical parts, the electronic components can comprise a processor therein to execute software or firmware that confers at least in part the functionality of the electronic components. While various components have been illustrated as separate components, it will be appreciated that multiple components can be implemented as a single component, or a single component can be implemented as multiple components, without departing from example embodiments.

(415) Further, the various embodiments can be implemented as a method, apparatus or article of manufacture using standard programming and/or engineering techniques to produce software, firmware, hardware or any combination thereof to control a computer to implement the disclosed subject matter. The term “article of manufacture” as used herein is intended to encompass a computer program accessible from any computer-readable device or computer-readable storage/communications media. For example, computer readable storage media can include, but are not limited to, magnetic storage devices (e.g., hard disk, floppy disk, magnetic strips), optical disks (e.g., compact disk (CD), digital versatile disk (DVD)), smart cards, and flash memory devices (e.g., card, stick, key drive). Of course, those skilled in the art will recognize many modifications can be made to this configuration without departing from the scope or spirit of the various embodiments.

(416) In addition, the words “example” and “exemplary” are used herein to mean serving as an instance or illustration. Any embodiment or design described herein as “example” or “exemplary” is not necessarily to be construed as preferred or advantageous over other embodiments or designs. Rather, use of the word example or exemplary is intended to present concepts in a concrete fashion. As used in this application, the term “or” is intended to mean an inclusive “or” rather than an exclusive “or”. That is, unless specified otherwise or clear from context, “X employs A or B” is intended to mean any of the natural inclusive permutations. That is, if X employs A; X employs B; or X employs both A and B, then “X employs A or B” is satisfied under any of the foregoing instances. In addition, the articles “a” and “an” as used in this application and the appended claims should generally be construed to mean “one or more” unless specified otherwise or clear from context to be directed to a singular form.

(417) Moreover, terms such as “user equipment,” “mobile station,” “mobile,” subscriber station,” “access terminal,” “terminal,” “handset,” “mobile device” (and/or terms representing similar terminology) can refer to a wireless device utilized by a subscriber or user of a wireless communication service to receive or convey data, control, voice, video, sound, gaming or substantially any data-stream or signaling-stream. The foregoing terms are utilized interchangeably herein and with reference to the related drawings.

(418) Furthermore, the terms “user,” “subscriber,” “customer,” “consumer” and the like are employed interchangeably throughout, unless context warrants particular distinctions among the terms. It should be appreciated that such terms can refer to human entities or automated components supported through artificial intelligence (e.g., a capacity to make inference based, at least, on complex mathematical formalisms), which can provide simulated vision, sound

recognition and so forth.

(419) As employed herein, the term “processor” can refer to substantially any computing processing unit or device comprising, but not limited to comprising, single-core processors; single-processors with software multithread execution capability; multi-core processors; multi-core processors with software multithread execution capability; multi-core processors with hardware multithread technology; parallel platforms; and parallel platforms with distributed shared memory. Additionally, a processor can refer to an integrated circuit, an application specific integrated circuit (ASIC), a digital signal processor (DSP), a field programmable gate array (FPGA), a programmable logic controller (PLC), a complex programmable logic device (CPLD), a discrete gate or transistor logic, discrete hardware components or any combination thereof designed to perform the functions described herein. Processors can exploit nano-scale architectures such as, but not limited to, molecular and quantum-dot based transistors, switches and gates, in order to optimize space usage or enhance performance of user equipment. A processor can also be implemented as a combination of computing processing units.

(420) What has been described above includes mere examples of various embodiments. It is, of course, not possible to describe every conceivable combination of components or methodologies for purposes of describing these examples, but one of ordinary skill in the art can recognize that many further combinations and permutations of the present embodiments are possible. Accordingly, the embodiments disclosed and/or claimed herein are intended to embrace all such alterations, modifications and variations that fall within the spirit and scope of the appended claims. Furthermore, to the extent that the term “includes” is used in either the detailed description or the claims, such term is intended to be inclusive in a manner similar to the term “comprising” as “comprising” is interpreted when employed as a transitional word in a claim.

(421) In addition, a flow diagram may include a “start” and/or “continue” indication. The “start” and “continue” indications reflect that the steps presented can optionally be incorporated in or otherwise used in conjunction with other routines. In this context, “start” indicates the beginning of the first step presented and may be preceded by other activities not specifically shown. Further, the “continue” indication reflects that the steps presented may be performed multiple times and/or may be succeeded by other activities not specifically shown. Further, while a flow diagram indicates a particular ordering of steps, other orderings are likewise possible provided that the principles of causality are maintained.

(422) As may also be used herein, the term(s) “operably coupled to”, “coupled to”, and/or “coupling” includes direct coupling between items and/or indirect coupling between items via one or more intervening items. Such items and intervening items include, but are not limited to, junctions, communication paths, components, circuit elements, circuits, functional blocks, and/or devices. As an example of indirect coupling, a signal conveyed from a first item to a second item may be modified by one or more intervening items by modifying the form, nature or format of information in a signal, while one or more elements of the information in the signal are nevertheless conveyed in a manner than can be recognized by the second item. In a further example of indirect coupling, an action in a first item can cause a reaction on the second item, as a result of actions and/or reactions in one or more intervening items.

(423) Although specific embodiments have been illustrated and described herein, it should be appreciated that any arrangement which achieves the same or similar purpose may be substituted for the embodiments described or shown by the subject disclosure. The subject disclosure is intended to cover any and all adaptations or variations of various embodiments. Combinations of the above embodiments, and other embodiments not specifically described herein, can be used in the subject disclosure. For instance, one or more features from one or more embodiments can be combined with one or more features of one or more other embodiments. In one or more embodiments, features that are positively recited can also be negatively recited and excluded from the embodiment with or without replacement by another structural and/or functional feature. The

steps or functions described with respect to the embodiments of the subject disclosure can be performed in any order. The steps or functions described with respect to the embodiments of the subject disclosure can be performed alone or in combination with other steps or functions of the subject disclosure, as well as from other embodiments or from other steps that have not been described in the subject disclosure. Further, more than or less than all of the features described with respect to an embodiment can also be utilized.

(424) The foregoing embodiments can be combined in whole or in part with the embodiments described in U.S. Pat. No. 10,284,313 (issued on May 7, 2019). For instance, embodiments of the aforementioned U.S. patent can be combined in whole or in part with embodiments of the subject disclosure. For example, one or more features and/or embodiments described in the aforementioned U.S. patent can be used in conjunction with (or as a substitute for) one or more features and/or embodiments described herein, and vice versa. Accordingly, all sections of the aforementioned U.S. patent are incorporated herein by reference in their entirety.

Claims

1. A method, comprising: detecting interference in a communication signal received by an antenna system that includes a first set of radiating elements associated with a first band and a second set of radiating elements associated with a second band, wherein the interference is generated by one or more interference sources, and wherein the interference is detected by monitoring a near field region of the antenna system, an intermediate field region of the antenna system, a far field region of the antenna system, or any combinations thereof; and based on the detecting, performing polarization adjusting for the first set of radiating elements, by a first adjustment amount and for the second set of radiating elements by a second adjustment amount different from the first adjustment amount.
2. The method of claim 1, wherein the intermediate field region comprises a region that spans a portion of the near field region of the antenna system and a portion of the far field region of the antenna system.
3. The method of claim 1, further comprising: identifying an antenna resource for mitigating the interference; and performing, by the antenna resource, conditioning on the communication signal to reduce the interference.
4. The method of claim 1, wherein the first and second bands mix and interfere together.
5. The method of claim 4, wherein the interference detected includes mixing and interference of the first and second bands, and wherein the interference detected comprises passive intermodulation (PIM) interference.
6. The method of claim 1, wherein the interference comprises inter-cell interference.
7. The method of claim 1, wherein the interference is generated from dynamic spectrum sharing between transmitters.
8. The method of claim 1, wherein the interference comprises leakage interference generated by another base station.
9. The method of claim 1, wherein a polarization of the interference enables detection of the interference.
10. The method of claim 9, wherein the polarization of the interference is detectable separately from other signals received by the antenna system.
11. The method of claim 1, wherein the antenna system is integrated with a remote radio head.
12. The method of claim 1, wherein the antenna system operates in a communication system utilizing time division multiple access.
13. The method of claim 1, wherein the antenna system operates in a communication system utilizing frequency division multiple access.
14. The method of claim 1, wherein a signaling protocol used by one or more transmitters

unassociated with the antenna system comprises an orthogonal frequency-division multiple access protocol.

15. The method of claim 14, wherein the interference is further detected by detecting the signaling protocol used by the one or more transmitters.

16. A device, comprising: a circuit coupled to an antenna system that includes a first set of radiating elements associated with a first band and a second set of radiating elements associated with a second band, the circuit facilitating operations including: detecting interference in a signal received via the antenna system, wherein the interference is generated by one or more sources, and wherein the interference is detected by monitoring an intermediate field region of the antenna system that spans a portion of a near field region of the antenna system and a portion of a far field region of the antenna system; and based on the detecting, causing polarization adjusting to be performed for the first set of radiating elements, by a first adjustment amount and for the second set of radiating elements by a second adjustment amount different from the first adjustment amount.

17. The device of claim 16, wherein the operations further include identifying a resource for mitigating the interference.

18. The device of claim 16, wherein the circuit is configured to detect a polarization of the interference.

19. A non-transitory machine-readable medium, comprising executable instructions that, when executed by a processing system including a processor, facilitate performance of operations, the operations comprising: detecting interference in a communication signal received by an antenna system that includes a first set of radiating elements associated with a first band and a second set of radiating elements associated with a second band, wherein the interference is detected by monitoring an intermediate field region of the antenna system that spans a portion of a near field region of the antenna system and a portion of a far field region of the antenna system; and based on the detecting, performing polarization adjusting for the first set of radiating elements, by a first adjustment amount and for the second set of radiating elements by a second adjustment amount different from the first adjustment amount.

20. The non-transitory machine-readable medium of claim 19, wherein the operations further comprise controlling, by a remote radio unit, the antenna system to perform one or more actions for mitigating or cancelling the interference.
