



US012406199B2

(12) **United States Patent**
Morel et al.

(10) **Patent No.:** **US 12,406,199 B2**
(45) **Date of Patent:** **Sep. 2, 2025**

(54) **QUANTUM DEVICE**

(56) **References Cited**

(71) Applicant: **COMMISSARIAT A L'ENERGIE
ATOMIQUE ET AUX ENERGIES
ALTERNATIVES**, Paris (FR)

U.S. PATENT DOCUMENTS

2019/0392352 A1 12/2019 Lampert et al.
2022/0188687 A1 * 6/2022 Morel G06N 10/40
2023/0093578 A1 * 3/2023 Ruskuc G06N 10/40
716/100
2023/0229952 A1 * 7/2023 Pakkiam G06N 10/70
716/100

(72) Inventors: **Adrien Morel**, Grenoble (FR); **Franck
Badets**, Grenoble (FR)

(73) Assignee: **COMMISSARIAT A L'ENERGIE
ATOMIQUE ET AUX ENERGIES
ALTERNATIVES**, Paris (FR)

FOREIGN PATENT DOCUMENTS

FR 3 089 724 A1 6/2020

(*) Notice: Subject to any disclaimer, the term of this
patent is extended or adjusted under 35
U.S.C. 154(b) by 581 days.

OTHER PUBLICATIONS

Vandersypen, et al., "Interfacing spin qubits in quantum dots and
donors—hot, dense and coherent", Arxiv.Org, Dec. 2016.
Bonteau, "A current controlled CMOS current amplifier", 2017 5th
International Symposium on Electrical and Electronics Engineering
(ISEEE), 2017.

(21) Appl. No.: **17/901,623**

(22) Filed: **Sep. 1, 2022**

(Continued)

Primary Examiner — Brian Ngo

(74) *Attorney, Agent, or Firm* — BakerHostetler

(65) **Prior Publication Data**

US 2023/0080817 A1 Mar. 16, 2023

(30) **Foreign Application Priority Data**

Sep. 16, 2021 (FR) 2109709

(51) **Int. Cl.**
G06N 10/40 (2022.01)


(52) **U.S. Cl.**
CPC **G06N 10/40** (2022.01)

(58) **Field of Classification Search**
USPC 716/100
See application file for complete search history.

(57) **ABSTRACT**

A quantum device includes multiple spin qubits, multiple
electrometers, each being capacitively coupled to one of the
spin qubits, multiple injection-locked oscillators, each being
coupled to one of the electrometers and designed to transmit
an excitation signal to the electrometer to which it is
coupled, each excitation signal having a different frequency,
an amplification circuit comprising at least one amplifier,
wherein the device comprises a feedback loop coupling the
output of the amplification circuit to an input of each
injection-locked oscillator and through which an injection
signal flows, each injection-locked oscillator being designed
to receive the injection signal and, as a function of the
injection signal, maintain or decrease its excitation signal.

15 Claims, 10 Drawing Sheets



(56)

References Cited

OTHER PUBLICATIONS

Guevel, et al., “19.2 A 110mK 295μW 28nm FDSOI CMOS Quantum Integrated Circuit with a 2.8GHz Excitation and hA Current Sensing of an On-Chip Double Quantum Dot”, 2020 IEEE International Solid-State Circuits Conference—(ISSCC), 2020.
Yoon, “LC-tank CMOS Voltage-Controlled Oscillators using High Quality Inductors Embedded in Advanced Packaging Technologies”, Georgia Institute of Technology, 2004.
Reilley, et al., “Fast single-charge sensing a RF quantum point contact”, Applied Physics Letters 91, 162101, 2007.

* cited by examiner




Fig. 1




Fig. 2




Fig. 3




Fig. 4




Fig. 5




Fig. 6




Fig. 7








Fig. 8








Fig. 13




Fig. 14

1

QUANTUM DEVICE

CROSS-REFERENCE TO RELATED
APPLICATION

This application claims priority to foreign French patent application No. FR 2109709, filed on Sep. 16, 2021, the disclosure of which is incorporated by reference in its entirety.

FIELD OF THE INVENTION

The invention relates to a quantum device. The field of the invention is that of quantum devices, and more particularly that of processing quantum information.

BACKGROUND

A quantum system is based on the use of a quantum state with multiple levels. In a number of fields, such as in electronics, quantum systems may comprise more than two levels, which is similar to conventional electronics where N values may be used, where N is greater than 2. A quantum system comprising various levels may be described by considering only its two first energy levels. In particular, quantum computing is based on the use of a quantum state with two measurable levels as an information vector, called a qubit or quantum bit, and the laws of quantum mechanics (superposition, entanglement, measurement) to run algorithms. A quantum device, or computer, allows the quantum state of these qubits to be manipulated, in particular for the purpose of performing operations. Unlike a conventional electronic or computing machine (operating with two voltage levels corresponding to binary states of 0 and 1), a quantum device is more akin to an analogue machine, in that the quantum state of the qubits can take an infinite number of values.

A system using an electron or a quasiparticle with spin $\frac{1}{2}$ may be used to embody a qubit, known as a spin qubit, the two levels corresponding to the two possible spin orientations. Spin qubits may be formed in a semiconductor, advantageously silicon. Semiconductor technologies are being studied with a view to producing spin qubits because of their high potential for integration, just like conventional electronics. Electrons or holes are individually confined in quantum wells kept at cryogenic temperatures (below 1 kelvin (K)) in a cryostat and produced within electrostatically defined nano-sized confinement structures which, in the case of silicon, have an architecture similar to that of MOSFETs. These confinement structures correspond to quantum dots. A quantum dot behaves like a potential well confining one or more elementary charges (electrons or holes) in a semiconductor region.

A spin qubit is read by using another quantum dot, called a read quantum dot, which is coupled to that of the spin qubit to be read. These two quantum dots form two potential wells separated by a potential barrier. Each of the two quantum dots comprises an electrostatic control gate arranged on a first semiconductor region in which the potential wells of the quantum dots are formed. The potential wells are arranged between second semiconductor regions forming charge carrier reservoirs, referred to as the source and drain by analogy with MOSFET technology. A quasiparticle may be a hole or an electron. The spin of the quasiparticle in the quantum dot of the qubit to be read is used as a "reference spin" while the spin of the quasiparticle in the read quantum dot is measured after being manipulated.

2

There are various methods for reading spin qubits. The first consists in measuring the capacitance between two quantum dots, which is representative of their relative states. The second consists in measuring the conductance of an electrometer, this conductance being representative of the state of the qubit close to the electrometer. See Vandersypen 2016 in this regard.

The first method for reading spin qubits consists in measuring the capacitance between the quantum dot of the qubit to be read and the read quantum dot, which corresponds to a representation of their relative states. For this, a reflectometry device is generally used. A high-frequency signal (e.g. between 100 MHz and a few GHz) is sent to the gate of the read quantum dot from test instruments arranged at room temperature outside the cryostat that contains the quantum dots. The signal is reflected and then demodulated. An inductance is placed at the end of the line at the location of the qubit in order to create an LC resonator consisting of this inductance, of a parasitic capacitance and of the quantum capacitance C_q formed by the qubit. When the value of C_q varies, the phase and amplitude of the reflected signal vary, which may be detected by the measurement instruments arranged at room temperature. It is thus possible to know the relative spin state (parallel or antiparallel) of the electron in the read quantum dot according to the spin state of the electron in the quantum dot of the qubit to be read.

With this first reading method, it is necessary either to have a number of wires equal to the number of qubits to be excited running from the cryostat, which becomes impossible when the number of qubits is large, for example more than 1000, or to send multiple signals at various frequencies through the same wire and to differentiate between these frequencies using the LC resonators arranged at cryogenic temperature. In this latter solution, it is therefore necessary for the resonant frequency of the LC resonator associated with each qubit to be calibrated and different for each resonator. There is thus a trade-off between the frequency spacing between each qubit (defined by the quality factor of the LC resonators since the higher the quality factor, the greater the number of qubits addressed by a single row), the area taken up by the inductances (the smaller the inductance, the lower its quality factor) and the time taken for the readout (inversely proportional to the quality factor of the LC resonator).

Additionally, with this first reading method, the use of magnetic cores to facilitate the integration of the inductances is limited by the strong static magnetic field required to reveal the quasiparticles' spins which saturates the cores' magnetic permeabilities. Air-core inductors do not have this problem, but they occupy a much larger area, limiting their widespread use inside the cryostat.

Inter-inductance coupling may also present new problems when measuring qubits simultaneously using a number of these inductances excited by the reflectometry signals.

The second method consists in measuring the conductance of an electrometer coupled to the quantum dot of the qubit to be read, this conductance being representative of the state of the qubit. Specifically, by virtue of the Zeeman effect (splitting an atom's energy level into multiple distinct energy sublevels in the presence of an external magnetic field), when the spin of the quasiparticle is oriented upwards, it is necessarily in the "high" energy state (which state will be referred to hereinafter as H). Conversely, if the spin of the quasiparticle is oriented downwards, the quasiparticle is in the "low" energy state (which state will be referred to hereinafter as L). By placing the energy level of the reservoir close to a quantum dot between H and L, the quasiparticle

will tend to escape from the quantum dot when it is in the H state and remain in the quantum dot when it is in the L state (Pauli blockade). It is thus possible to convert the spin of the quasiparticle into charge information (quasiparticle present or not present in the quantum dot), this conversion commonly being called spin-to-charge conversion. This charge information may be read by an electrometer such as a single-electron transistor (SET) or a quantum point contact (QPC), the conductance of which varies as a function of its electrostatic environment. For further information on QPCs reference may be made to Reilley 2007.

With this second method, variation in the spin of the quasiparticle is converted into a variation in the charge of the quantum dot (by way of Pauli blockade) which leads to a variation in the conductance of the electrometer, which results in a variation in the current flowing in the electrometer. This current may then be amplified using a transimpedance amplifier (TIA). Typically, this readout is used with a TIA arranged at room temperature connected to an electrometer. It is therefore not possible to use this solution to address a large number of qubits, for example a whole array of qubits, because it would be necessary either to have a number of wires at least equal to the number of qubits addressed running from the cryostat, which requires far too much space, or to arrange all of the TIAs in the cryostat, which is not possible in view of the cooling capacities of current cryostats (1 W maximum for operation at 4 K, or 1 mW for operation at 100 mK). In addition, the readout speed of such a solution is limited by the capacitance of the wires (between 100 and 300 pF) to be charged upstream of the TIAs arranged at room temperature. The bandwidth of such a system would struggle to exceed 10 kHz.

SUMMARY OF THE INVENTION

One object of the invention is to overcome at least one of the aforementioned drawbacks.

A further object of the invention is a quantum device designed to minimize the number of wires per spin qubit.

Another object of the invention is to provide a quantum device that consumes less power.

Yet another object of the invention is to provide a more compact quantum device.

At least one of the aforementioned objects is achieved by a quantum device comprising:

- multiple spin qubits, each comprising at least one quantum dot,
- multiple electrometers, each being capacitively coupled to a potential well of the at least one quantum dot of at least one of the spin qubits, and
- multiple injection-locked oscillators, each being coupled to at least one electrode of one of the electrometers and designed to transmit an oscillating signal called an excitation signal, to at least one input electrode of the electrometer to which it is coupled, each excitation signal having a different frequency,

characterized in that it also comprises

- an amplification circuit comprising at least one amplifier, said amplification circuit being coupled to the output of each electrometer and comprising an output,

and in that said device comprises a feedback loop coupling the output of said amplification circuit to an input of each injection-locked oscillator and through which an electrical signal, called an injection signal, flows, comprising components at the frequencies of said excitation signals, each injection-locked oscillator being designed to receive the injection signal and, as a function of said injection signal,

keep its excitation signal in a first operating state or decrease its excitation signal to a second operating state.

According to these features, the device according to the invention allows a plurality of spin qubits to be read using a single amplification circuit which may comprise just one amplifier, N electrometers and N injection-locked oscillators, where N is greater than 1. As such, the device according to the invention allows a plurality of spin qubits to be read while limiting the number of wires per spin qubit.

Additionally, according to the invention, the output of the amplification circuit is connected to an input of the N injection-locked oscillators which allows the injection signal to be injected into the injection-locked oscillators which are used to excite the electrometers. According to the invention, each injection-locked oscillator receives as input an injection signal comprising all of the components of the excitation signals of the device according to the invention and transmits a single excitation signal as output. In particular and for each injection-locked oscillator, the presence of an injection signal at the resonant frequency, preferably with a suitable phase (generally in phase opposition) drastically reduces the amplitude of the oscillation of the injection signal transmitted by the injection oscillator, whereas an injection signal at a different frequency has no effect on the operation of the injection oscillator in question. Each injection-locked oscillator thus has two alternative operating states: the first state in which the excitation signal oscillates according to an initial state, and the second state in which the injection signal is decreased. The device according to the invention thus allows the number of electronic components used to be decreased. Thus, in the device according to the invention, power consumption and the space taken up by the electronic components are optimized, providing a compact device that consumes less power than the devices known from the prior art.

One subject of the invention is a quantum device comprising:

- multiple spin qubits, each comprising at least one quantum dot,
- multiple electrometers, each being capacitively coupled to a potential well of the at least one quantum dot of at least one of the spin qubits, and
- multiple injection-locked oscillators, each being coupled to at least one electrode of one of the electrometers and designed to transmit an oscillating signal, called an excitation signal, to at least one input electrode of the electrometer to which it is coupled, each excitation signal having a different frequency,

an amplification circuit comprising at least one amplifier, said amplification circuit being coupled to the output of each electrometer and comprising an output, characterized in that said device comprises a feedback loop coupling the output of said amplification circuit to an input of each injection-locked oscillator and through which an electrical signal, called an injection signal, flows, comprising components at the frequencies of said excitation signals, each injection-locked oscillator being designed to receive the injection signal and, as a function of said injection signal, keep its excitation signal in a first operating state or decrease its excitation signal to a second operating state.

Another subject of the invention is a method for reading multiple spin qubits, each comprising a quantum dot, said method using multiple electrometers, each being capacitively coupled to a potential well of the at least one quantum dot of at least one of the spin qubits, multiple injection-locked oscillators, each being coupled to at least one elec-

5

trode of one of the electrometers, an amplification circuit, said amplification circuit being coupled to the output of each electrometer and comprising at least one amplifier and an output, said method comprising:

each of the injection-locked oscillators transmitting an oscillating signal, called an excitation signal, to at least one input electrode of the electrometer to which it is coupled, each excitation signal having a different frequency, characterized in that said method further comprises:

injecting a signal, called an injection signal, into each injection-locked oscillator via a feedback loop coupling the output of said amplification circuit to the input of each injection-locked oscillator, the injection signal comprising components at the frequencies of said excitation signals and, for each injection-locked oscillator, decreasing or maintaining the excitation signal resulting from said injection signal.

BRIEF DESCRIPTION OF THE DRAWINGS

The invention will be better understood and other advantages will become apparent from reading the following description given by way of non-limiting example and with reference to the appended figures, in which:

FIG. 1 schematically shows a first example of a device according to the invention;

FIG. 2 schematically shows the first example of the device according to the invention when all of the spin qubits are in a low state;

FIG. 3 schematically shows the first example of the device according to the invention when one of the spin qubits is in the high state;

FIG. 4 schematically shows the first example of the device according to the invention when the measurement means associated with the spin qubit in the high state is in a second operating state;

FIG. 5 schematically shows a first example of the device according to the invention when three spin qubits are in the high state;

FIG. 6 schematically shows the first example of the device according to the invention when the measurement means associated with the spin qubits in the high state are in a second operating state;

FIG. 7 schematically shows a second example of a device according to the invention;

FIG. 8 is one example of measurement means used in a device according to the invention;

FIG. 9 is one example of an amplification circuit used in a device according to the invention;

FIG. 10 is another example of measurement means used in a device according to the invention;

FIG. 11 is one example of an injection-locked oscillator used in a device according to the invention;

FIG. 12 schematically shows a third example of a device according to the invention;

FIG. 13 schematically shows a fourth example of a device according to the invention; and

FIG. 14 schematically shows a first example of a method according to the invention.

DETAILED DESCRIPTION

FIG. 1 schematically shows a first example of a device 100. The device 100 is a quantum device 100 and comprises: multiple spin qubits 102, each comprising at least one quantum dot,

6

multiple electrometers 104, each being capacitively coupled to a potential well of the at least one quantum dot of at least one of the spin qubits 102, and

multiple injection-locked oscillators 106, each being coupled to at least one electrode of one of the electrometers 104 and designed to transmit an oscillating signal 122, called an excitation signal 122, to at least one input electrode of the electrometer 104 to which it is coupled, each excitation signal 122 having a different frequency,

an amplification circuit 108 comprising at least one amplifier 110, said amplification circuit 108 being coupled to the output of each electrometer 104 and comprising an output 112.

In this example, the device comprises in particular:

four spin qubits, each numbered 102₁, 102₂, 102₃, 102₄, four electrometers, respectively called first electrometer 104₁, second electrometer 104₂, third electrometer 104₃ and fourth electrometer 104₄, and

four injection-locked oscillators 106, respectively called first injection-locked oscillator 106₁, second injection-locked oscillator 106₂, third injection-locked oscillator 106₃, and fourth injection-locked oscillator 106₄.

Of course, in other variants of device 100, the device 100 may comprise more or fewer of these components. For example, the device 100 may comprise between 2 and 10000 qubits.

The device 100 further comprises a feedback loop 114 coupling the output 112 of the amplification circuit 108 to an input 116 of each injection-locked oscillator 106 through which an electrical signal flows, called an injection signal 120 also denoted I_{108} . The injection signal 120 comprises components at the frequencies of said excitation signals 122. In the device 100, each injection-locked oscillator 106 is arranged to receive the injection signal 120 and, as a function of said injection signal 120, keep its excitation signal 122 in a first operating state or decrease its excitation signal 122 to a second operating state. In the example illustrated in FIG. 1, the injection signal 120 relates to a current. In other variants, the injection signal may be a voltage. For further information on injection-locked oscillators, reference may be made to Yoon 2004 or to FR 3 089 724.

In the device 100 illustrated in FIG. 1, the amplification circuit 108 comprises just one amplifier 110. In the embodiment illustrated in FIG. 1, the amplifier may be a transimpedance amplifier, also denoted TIA, or the amplification circuit 108 is designed to perform current amplification.

In a non-limiting manner, the spin qubits of the device 100 may be spin qubits produced in a semiconductor layer, for example silicon or germanium. The charges of which the spin is to be read may correspond to electrons or to holes.

In addition, according to this exemplary embodiment, the electrometers 104 of the device 100 may comprise, and preferably be, single-electron transistors (SETs). In this case, each electrometer 104 of the device 100 may comprise a gate, a source and a drain. By way of example, the drain and gate of each electrometer 104 may form the input electrodes of the electrometers 104 while the sources of the electrometers 104 form the output electrodes of the electrometers 104. The sources of the electrometers 104 may be electrically connected to one another. Of course, in other embodiments which are not illustrated, the electrometers 104 may comprise or be quantum point contacts (QPCs).

In this example, each injection-locked oscillator 106 may be coupled to the gate of the corresponding electrometer 104. Thus, each excitation signal 122 is applied to that gate

of the electrometer **104**. In another variant, each injection-locked oscillator **106** may be coupled to the drain of the corresponding electrometer **104**. The excitation signal sent to the drain of the electrometer may be more linear than a signal sent to the gate of the electrometer. Measurement precision may therefore be improved.

When the electrometers **104** are QPCs, the excitation signals **122** are applied by injection-locked oscillators **106** to the input electrode of each of the QPC-type electrometers **104**, which may be the electrode to which a DC bias voltage is delivered.

In FIG. **1**, the excitation signals **122** may each be sinusoidal signals all having different frequencies. The excitation signal **122** may relate to a current. In the example illustrated in FIG. **1**, each injection-locked oscillator **106** produces an excitation signal **122** comprising at least one frequency and amplitude. The frequency of the excitation signal **122** is specific to each injection-locked oscillator **106** and the amplitude of the excitation signal **122** is dependent on the state of the spin qubit.

By way of example, the signal output from each injection-locked oscillator **106** may be denoted:

$$I_{106_i} = A_i \sin(2\pi f_i t)$$

where the subscript *i* corresponds to the number of the injection-locked oscillator **106** and f_i corresponds to the frequency of the i^{th} injection-locked oscillator **106**, and A_i is the amplitude of the corresponding excitation signal **122**. In this example, the amplitude A_i output from each electrometer **104** is dependent on the state of the spin qubit facing the corresponding electrometer **104**. In a non-limiting manner, the excitation signal **122**₁ delivered by the first injection-locked oscillator **106**₁ may have a frequency f_1 equal to 10 MHz, the excitation signal **122**₂ delivered by the second injection-locked oscillator **106**₂ may have a frequency f_2 equal to 11 MHz, the excitation signal **122**₃ delivered by the third injection-locked oscillator **106**₃ may have a frequency f_3 equal to 13 MHz and the excitation signal **122**₄ delivered by the fourth injection-locked oscillator **106**₄ may have a frequency f_4 equal to 14 MHz. Thus, in FIG. **1**, all of the excitation signals **122** comprise different frequencies. In addition, these frequencies are spaced far enough apart to avoid errors due to false alarms and/or non-detections. Typically the spacing between the frequencies may be of the order of 1 MHz, and more generally between 100 kHz and 10 MHz.

In the device **100**, all of the signals output from the electrometers **104** are combined into a signal at the input of the amplification circuit **108**. The signal at the input of the amplification circuit **108** is, according to Kirchhoff's first law, dependent on all of the signals from the various electrometers **104**.

By way of example, the signal at the input of the amplification circuit **108** is expressed as

$$I_{e,108} = \sum_{i=1}^N I_{106_i} = \sum_{i=1}^N A_i \sin(2\pi f_i t)$$

where *N* corresponds to the total number of electrometers **104** in the device **100** (in the case of FIG. **1**, *N* is equal to 4), and the subscript *e* refers to the input of the amplification circuit **108**. Thus, the signal at the input of the amplification circuit **108** is dependent on all of the excitation signals **122**. The signal at the input of the amplification circuit **108** thus contains all of the components of all of the excitation signals

122 of the device **100**. As such, the signal at the input of the amplification circuit **108** contains the information on the state of each spin qubit. In the example illustrated in FIG. **1**, the signal at the input of the amplification circuit **108** is a spectrum that comprises a line associated with each excitation signal **122**. Each line of the spectrum of the signal at the input of the amplification circuit **108** has an amplitude that is dependent on the corresponding spin state.

By way of example, the device **100** further comprises a cryostat including a chamber configured to be kept at a temperature lower than or equal to 4 kelvin (K) and in which at least the spin qubits, the electrometers **104**, the injection-locked oscillators **106**, and the amplification circuit **108** and, if required, bias circuits are arranged.

In the case of the device according to the invention, the information on the spin of each spin qubit is obtained by studying the excitation signal **122** output from each injection-locked oscillator **106**. The injection signal **120** entering each injection-locked oscillator **106** carries information which is demultiplexed inside the locked oscillators **106** used for the initial excitation. Thus, the device **100** is based on the use of *N* electrometers **104**, *N* injection-locked oscillators **106** and an amplification circuit **108** comprising, in the example illustrated, a single amplifier **110**, used for reading *N* spin qubits, where *N* is an integer greater than 1. Such an arrangement also avoids the use of a multitude of demultiplexing chains which may be used to retrieve the information on the spin of each spin qubit (e.g. *N* demultiplexing chains) and which may be made up of multiple components such as analogue-to-digital converters and/or mixers, and/or integrators, and/or comparators. As such, the device according to the invention is less bulky and not using one or more demultiplexing chains makes it possible to limit the power consumption of each component and thus limit the power consumption of the device according to the invention.

FIG. **2** schematically shows the device **100** when all of the spin qubits of the device **100** are in the low state.

In the device **100**, the conductance associated with each electrometer **104** varies as a function of the state of the spin qubit with which the electrometer **104** is coupled. By way of example, when the spin qubit is in the low state, the conductance of an electrometer **104** may be of the order of tens of nS (nanosiemens), corresponding to a current of the order of nA (nanoamperes), whereas the conductance of an electrometer **104**, when the spin qubit is in the low state, may be of the order of tens of pS (pico Siemens), corresponding to a current of the order of pA (picoamperes). The signal output from each electrometer is dependent on the state of the spin qubit.

By way of example, the excitation signal **122** flowing through an electrometer **104** may be of the order of pA if an electron in the quantum dot of the spin qubit has its spin oriented downwards, and of the order of nA if the electron in the quantum dot of the spin qubit has its spin oriented upwards.

The spin qubits illustrated in FIG. **1** are all in the low state. As such, the amplitudes associated with each spin qubit are of the order of picoamperes (pA) and therefore small with respect to the state of spin qubits in the high state which may be of the order of nA. Thus, the signal at the input of the amplification circuit **108** is of the order of pA.

The amplification circuit **108** is designed to amplify the signal at its input. In the example illustrated in FIG. **2**, the amplification circuit is designed to perform negative amplification. Such a feature allows the operation of the second operating state of the injection-locked oscillators to be

implemented in a simple manner. Thus, the injection signal **120** is proportional to the signal at the input of the amplifier circuit **108** and is phase-shifted by approximately 180° relative to the signal at the input of the amplifier circuit **108**. In this example, the injection signal **120** is a spectrum that comprises a line associated with each excitation signal **122**. Each line of the spectrum of the injection signal **120** has an amplitude that is dependent on the corresponding spin state. Thus, using a spectrum provides a simple representation suitable for processing of the injection signal by the injection-locked oscillators **106**. In particular, this may limit errors due to false alarms and/or absence of detection. The device **100** is therefore more accurate.

The injection signal **120** output from the amplification circuit **108** traverses the feedback loop **114** in order to be injected into the various injection-locked oscillators **106** of the device **100**. The signal injected into each injection-locked oscillator **106** is thus proportional to the injection signal **120**.

FIG. 3 schematically shows the device **100** when one of the spin qubits of the device **100** transitions to the high state.

In the case of FIG. 3, the spin qubit numbered 1 is in the high state. By way of example, the signal output from the first electrometer **104**₁ is of the order of nA and therefore higher than the signals output from the other electrometers **104**₂, **104**₃, **104**₄ which are of the order of pA. Thus, in the signal at the input of the first amplification circuit **108**, the first line at frequency f_1 comprises an amplitude that is greater than the lines at frequencies f_2 , f_3 and f_4 . The same goes for the injection signal **120** output from the amplification circuit **108**.

In the example of FIG. 3, the signal reinjected into each injection-locked oscillator **106** contains all of the components of the injection signal **120**. In this example, the amplitude of the injection signal **120** of the line at frequency f_1 is higher than or equal to a threshold. The first injection-locked oscillator **106**₁ switches to the second operating state. The excitation signal **122**₁ output from the first injection-locked oscillator **106**₁ operating in the second operating state is lower than the excitation signal **122**₁ from the first injection-locked oscillator **106**₁ operating in the first operating state. The threshold that causes the oscillator **106**₁ to switch from its first to its second operating state depends on the topology of the oscillator, on its biasing point, and on whether it operates with voltage or current injection. For example, in the case of current injection, the threshold may be between 0.1 times and 1 times the oscillator biasing current.

Conversely, the amplitudes of the injection signal **120** at the lines at respective frequencies f_2 , f_3 et f_4 are lower than the thresholds defined using the excitation signal **122** transmitted by the second, third and fourth injection-locked oscillators **106**₂, **106**₃, **106**₄ when they are in their first operating state. As such, the second, third and fourth injection-locked oscillators **106**₂, **106**₃ et **106**₄ stay in their first operating states. Their associated excitation signals **122** are therefore maintained; they are not decreased. Although the injection signal **120** comprises lines at the various frequencies f_1 , f_2 , f_3 et f_4 , the injection signal **120** at frequency f_1 does not intervene in the operation of the second, third and fourth excitation means **106**₂, **106**₃, **106**₄.

These features promote the “filtering” behaviour of the injection-locked oscillators of the device according to the invention, which allows either the “initial” excitation signal, i.e. the excitation signal initially transmitted by each injection-locked oscillator, to be maintained, or the transmission of the excitation signal to be decreased or even halted.

FIG. 4 schematically shows the device **100** when the first injection-locked oscillator **106**₁ is operating in its second operating state. The signal transmitted by the oscillator is a voltage signal, the gate impedance of the electrometer being practically infinite.

FIG. 5 schematically shows the device **100** when three spin qubits of the device **100** are in the high state.

In the example illustrated in FIG. 5, the first, third and fourth spin qubits are in the high state. For example, the conductance associated with the second electrometer **104**₂ is of the order of ten nS whereas those of the first, third and fourth electrometers **104**₁, **104**₃, **104**₄ are of the order of ten pS.

In this example, the signal output from the second electrometer **104**₂ may be ignored. The signal at the input of the amplification circuit **108** may thus be simplified and expressed according to the following formula:

$$I_{e,108} = \sum_{i=1}^4 I_{106_i} \approx A_1 \sin(2\pi f_1 t) + A_3 \sin(2\pi f_3 t) + A_4 \sin(2\pi f_4 t)$$

The injection signal **120** output from the amplification circuit **108** may thus be expressed as follows:

$$I_{108} \approx -AA_1 \sin(2\pi f_1 t) - AA_3 \sin(2\pi f_3 t) - AA_4 \sin(2\pi f_4 t)$$

where A corresponds to the amplification factor of the amplification circuit **108**.

In this example, the injection signal **120** contains the frequency components corresponding to the electrometers **104** for which the associated qubit is in the high state. In this example, the signal reinjected into the first, third and fourth injection-locked oscillators **106**₁, **106**₃, **106**₄ is proportional to the injection signal **120** and thus comprises lines with amplitudes of the same order of magnitude. The first, third and fourth injection-locked oscillators **106**₁, **106**₃, **106**₄ will thus switch to their second operating state, which brings about a substantial decrease in the excitation signal **122** output from these injection-locked oscillators **106**₁, **106**₃, **106**₄. Conversely, the signal injected into the second injection-locked oscillator **106**₂ does not contain any, or hardly any, component at the frequency f_2 . As such, the second injection-locked oscillator **106**₂ stays in its first operating state. The excitation signal from the second injection-locked oscillator **106**₂ is thus maintained, i.e. it is not decreased. As such, the excitation signal **122**₂ from the second injection-locked oscillator **106**₂ oscillates at the same amplitude.

FIG. 6 schematically shows the behaviour of the first, third and fourth injection-locked oscillators **106**₁, **106**₃, **106**₄ of the device **100** after three spin qubits of the device **100** have transitioned to the high state.

In this example, the first, third and fourth excitation means **106**₁, **106**₃, **106**₄ have switched to the second operating mode.

FIG. 7 is a second example of a device **700** according to the invention.

The device **700** illustrated in FIG. 7 comprises all of the elements of the device **100**. Thus, only the differences will be described.

The device **700** further comprises multiple measurement means **702**, respectively numbered **702**₁, **702**₂, **702**₃ et **702**₄, each being coupled with an injection-locked oscillator **106**. Each measurement means **702** is designed to detect the operating state of the injection-locked oscillator **106** to which it is coupled and, depending on the detected state, to transmit a signal, called a measurement signal, relating to a

11

spin state. Thus, studying the injection signal **122** transmitted by each injection-locked oscillator **106** provides information on the state of the corresponding spin qubit. As such, in the device according to the invention, the spin qubits may be read directly by analysing the excitation signals **122**, thereby allowing the compactness, and low power consumption, of the device according to the invention to be improved even further. In addition, this makes its implementation simpler because the processing of the information is made easier.

By way of non-limiting example, each measurement means **702** comprises an analogue comparator **704** connected by its input to the output of one of the injection-locked oscillators **106** and coupled by its output to a digital processing means **706**. The analogue comparator **704** is designed to detect the operating mode of the injection-locked oscillator **106**, i.e. the first operating state or the second operating state of the injection-locked oscillator **106** to which it is connected. For example, each analogue comparator **704** continuously records the excitation signal **122** from the corresponding injection-locked oscillator **106** and transmits a signal that varies according to the excitation signal **122**. In the example illustrated in FIG. 7, the negative input of the analogue comparator **704** is set to a potential and the positive input of the analogue comparator **704** is set to the output of the corresponding injection-locked oscillator **106**.

For a given measurement means **702**, when the oscillator **106** is operating in its first operating state, for example when no significant decrease in the excitation signal **122** is registered by the analogue comparator **704**, then the output of the excitation signal **122** from the injection-locked oscillator **106** successively rises above and then falls below the potential of the negative input of the analogue comparator **704**. The output of the analogue comparator **704** may thus be a square-wave signal with a frequency equal to that of the injection-locked oscillator **106**.

When the injection-locked oscillator **106** is operating in its second operating state, for example when a significant decrease in the excitation signal **122** is recorded by the comparator **704**, then the excitation signal **122** never goes above or below the potential of the negative input of the analogue comparator **704**. The signal output by the analogue comparator **704** is thus a constant signal.

The signal transmitted by the analogue comparator **704** is transmitted to the digital processing means **706** which will output a digital signal with two possible states, 0 or 1, representing the spin state of the corresponding spin qubit. By way of example, the state 0 may represent a low spin state while the state 1 may represent a high spin state.

Alternatively, the circuit illustrated in FIG. 7 may comprise multiple bias circuits **118** (schematic illustration), each being coupled to an electrometer **104** and arranged to apply a DC bias voltage to said electrometer **104** which is designed so that each electrometer **104** produces a Coulomb blockade. In this example, the DC bias voltage may be applied to the input electrode of each electrometer **104**, for example to the drain and gate of each electrometer. In this example, all of the electrometers **104** are biased with DC bias voltages of the same value. The bias circuits **118** may also be implemented on the device **100**.

Preferably, the electrometers **104** are biased so as to obtain a substantial difference in conductance within the electrometers **104** depending on the spin orientation of the charges in the spin qubits, which will result in output signals of different amplitudes depending on the spin orientation of the charges. For example, the current flowing through an

12

electrometer **104** may be of the order of pA if an electron in the quantum dot of the spin qubit has its spin oriented downwards, and of the order of nA if the electron in the quantum dot of the spin qubit has its spin oriented upwards.

FIG. 8 illustrates a second example of measurement means **702** that may be implemented in the device **100** or **700**. This example focuses on the measurement means associated with the first injection-locked oscillator **106₁**. Of course, the measurement means **702** illustrated in FIG. 2 may be coupled to any injection-locked oscillator **106** of the device **100** or **700** according to the invention. The measurement means **702** associated with each injection-locked oscillator **106** may be similar or different.

In this example, the signal **122₁** is transmitted by the first injection-locked oscillator **106₁**. The measurement means **702** comprises a first comparator **802** and a second comparator **804**, an OR gate **806**, a current source system **808** and a capacitor **810**. The measurement means illustrated in FIG. 8 also comprises two latch devices, respectively denoted **812** and **814**, known as a "D latch" system. The measurement means illustrated in FIG. 8 also comprises a delay line **816** and a CMOS switch **818**. The second comparator **804** is designed to output a signal that alternately comprises two states, a low state 0 and a high state 1. The current source **808** is arranged to supply the capacitor **810** with DC.

When the first injection-locked oscillator **106₁** is in its first operating state, i.e. when the injection signal **122₁** is maintained, then the first comparator **802** transmits an oscillating signal as its output. At each rising or falling edge of this signal, the flip-flops **812** (for rising edges) and **814** (for falling edges) close the switch **818** for a time determined by the delay line **816** (the OR gate **806** allows the driver signals from the latches to be combined). The voltage across the terminals of the capacitor therefore cannot increase, and the output of the comparator **804** remains at a low level. If, however, the first injection-locked oscillator **106₁** is in its second operating state, the amplitude of the injection signal **122₁** has a lower value, which does not allow the first comparator **802** to switch. The output of the switch **810** therefore remains at a low level, and the switch **818** remains in its open state. Under these conditions, the voltage across the terminals of the capacitor **810** increases linearly until causing the output of the comparator **804** to switch to its high level.

FIG. 9 illustrates one example of an amplification circuit **108** that may be implemented in the device **100** or the device **700**.

In the example illustrated in FIG. 9, the amplification circuit **108** may comprise an amplifier **902** comprising a resistive feedback **904**. The amplification circuit **108** illustrated in FIG. 9 is a transimpedance amplifier. The resistive feedback **904** is designed to convert the signal at the input of the amplification circuit **108** into an injection signal **120** relating to a voltage. In the case illustrated in FIG. 9, the gain of the amplification circuit **108** is proportional to the resistance present in the resistive feedback **904**. By way of non-limiting example, the gain of the amplification circuit **108** illustrated in FIG. 9 is of the order of MΩ. The amplification circuit **108** may comprise a bandwidth between 10-30 MΩ, a gain of 10 MΩ, an input noise of the order of 10 fA/sqrt(Hz) and a consumption of the order of a hundred microwatts. In the device **100** or **700**, the bandwidth of the amplification circuit **108** is chosen so that all of the frequencies of all of the excitation signals **122** are within this bandwidth.

13

Of course, other arrangements may be implemented in the device according to the invention, such as those described in L. Le. Guevel 2020.

FIG. 10 illustrates another example of an amplification circuit 108 that may be implemented in the device 100 or the device 700.

The amplification circuit illustrated in FIG. 100 is designed to perform current amplification. Thus, in this example, the injection signal 122 relates to a current. In this case, the feedback loop 114 of the device 100 or 700 is connected to a current input port of each injection-locked oscillator 106.

The amplification circuit 108 illustrated in FIG. 10 is produced with the features described in document Bonteanu 2017.

FIG. 11 illustrates one example of an injection-locked oscillator 106. The injection-locked oscillator 106 illustrated in FIG. 6 is, by way of example, the first injection-locked oscillator 106₁. The injection-locked oscillator 106₁ illustrated in FIG. 11 comprises an LC-type architecture, referred to as a cross-coupled differential topology with an NMOS pair and a tail-current at the source. The injection-locked oscillator comprises a resonant circuit 1100 known as a tank LC. The resonant circuit comprises two inductances 1102 and 1104, a capacitor 1106, two transistors CMOS 1111 and 1112 and a current source 1114 for generating a bias current 1190. The gate of the transistor 1111 is connected to the drain of the transistor 1112 and vice versa, and the drains of both transistors are connected to the resonant circuit 1100. In this type of architecture, the excitation signal 122 transmitted by the injection-locked oscillator 106 thus exhibits damping due to energy losses in the inductances 1102 et 110 and the capacitor 1106. To compensate for this damping, the NMOS transistors 1111 and 1112 and the current source 1114 act as a “negative resistance” which allows energy to be injected into the injection-locked oscillator 106₁ and keep it in an undamped oscillating state. The energy injected by the transistors 1111 and 1112 and the current source 1114 compensate for the resistive losses in the resonant circuit 1100.

The excitation signal 122₁ transmitted by the injection-locked oscillator 106₁ illustrated in FIG. 11 comprises a frequency that is expressed according to the formula:

$$f_i = \frac{1}{2\pi} \sqrt{\frac{1}{LC}}$$

where L corresponds to the total inductance of the resonant circuit 1100 and C is the total capacitance of the resonant circuit 1100. Such an arrangement promotes the oscillation frequency specific to each injection-locked oscillator 106 and makes adjusting this frequency simpler.

Thus, according to this arrangement, the excitation signal 122 illustrated in FIG. 11 comprises a natural oscillation frequency f_i .

The oscillation frequency of the injection-locked oscillator 106₁ may be adjusted capacitively. This facilitates adapting and/or modifying the frequency of each excitation signal 122 whether for choosing its value or for potentially modifying this value. In addition, the oscillation frequency of the injection signal 122₁ transmitted by the injection-locked oscillator 106₁ is dependent on the total capacitance of the resonant circuit 1100 and the total inductance of the resonant circuit 1100. Thus, the oscillation frequency f_i may easily be adjusted and/or modified by modifying the total inductance

14

and/or the total capacitance of the resonant circuit 1100. The oscillation frequency of each injection-locked oscillator 106 may be adjusted capacitively. For example, the first injection-locked oscillator 106₁ may comprise a total capacitance equal to $C_1 = C_{ref}$ (typically between 10 fF (femtofarads) and 1 pF (picofarads) depending the desired oscillation frequency), the second injection-locked oscillator 106₂ may comprise a total capacitance equal to $C_2 = 2^2 C_{ref} = 4C_{ref}$, the third injection-locked oscillator 106₃ may comprise a total capacitance equal to $C_3 = 2^3 C_{ref} = 8C_{ref}$ and the fourth injection-locked oscillator 106₄ may comprise a total capacitance equal to $C_4 = 2^4 C_{ref} = 16 C_{ref}$. The value of the total capacitance of each injection-locked oscillator 106 may be programmable. For example, the device 100 or 700 may comprise a plurality of switches coupled to a memory which is designed to adjust the total capacitance of each injection-locked oscillator 106. Thus, the capacitance of each injection-locked oscillator 106 may be adjusted more precisely.

The injection-locked oscillator 106₁ illustrated in FIG. 11 comprises an input port 1108 which may be a current input port or a voltage input port. In case where the port 1108 is a voltage input port, an output voltage from the amplifier 110 drives the current source I_{108} with a certain transconductance gain. If, however, the port 1108 is a current input port, an output current from the amplifier 110 is copied (with, where applicable, a gain) by the current source I_{108} . Thus, the injection signal may be a voltage or a current, thereby providing an injection-locked oscillator that is easy to implement in the device according to the invention. In the case of using the current input port, the injection-locked oscillator 106₁ in this example may be coupled to the amplification circuit 108 illustrated in FIG. 10. In the case where the injection signal 120 relates to a voltage, for example when the amplification circuit 108 contains a resistive feedback as illustrated in FIG. 9, the amplification circuit 108 may be coupled with a transconductance amplification stage, for example, a MOS transistor designed to convert an input voltage on the gate of the MOS transistor into a drain-source current.

In the example illustrated, when the injection signal 120 (here relating to a current) does not contain any line at the frequency of the injection-locked oscillator 106₁, the injection signal 120 has no effect on the dynamic range of the injection-locked oscillator 106₁. As such, the excitation signal 122₁ transmitted by the injection-locked oscillator 106₁ is not modified. This is because the injection signal 120 is filtered by the LC resonant circuit.

The simplified transfer function linking the output voltage of the injection-locked oscillator 106₁ to the injection signal 120 may be expressed according to the following formula:

$$|H| = \left| \frac{V_{106}}{I_{108}} \right| = \left| \frac{j \frac{L}{2} \omega}{1 - \left(\frac{w_0}{w} \right)^2} \right| = \left| \frac{L}{2} \omega \frac{\frac{w^2}{w_0}}{1 - \left(\frac{w}{w_0} \right)^2} \right|$$

where I_{108} corresponds to the injection signal 120 relating to a current and V_{106} corresponds to the output voltage of the injection-locked oscillator 106₁. Thus, in the example illustrated, the transfer function is minimal for $w = w_0$. As explained above with reference to FIG. 9, when the amplitude of the injection signal 120, at the corresponding line, is lower than a threshold, the injection-locked oscillator 106₁

15

operates in its first operating state. The excitation signal **122₁** from the injection-locked oscillator **106₁** is not modified.

When the amplitude of the injection signal **120**, at the corresponding line, is higher than or equal to the threshold, the injection-locked oscillator **106₁** switches to its second operating state. The excitation signal **122₁** decreases. Specifically, in the example illustrated in FIG. 11, the transfer function increases and therefore the effect of the injection signal **120** on the dynamic range of the injection-locked oscillator **106₁** illustrated by the preceding equation is no longer negligible. The injection signal **122₁** opposes the operation of the injection-locked oscillator **106₁**. The excitation signal **122₁** transmitted by the injection-locked oscillator **106₁** operating in its first operating state has an amplitude that is typically at least 10 times greater than that of the excitation signal **122** transmitted by the injection-locked oscillator **106₁** operating in its second operating state. By way of example, the amplitude of the excitation signal **122₁** transmitted by the injection-locked oscillator **106₁** when it is operating in its first operating state may be of the order of a few hundreds of mV whereas when it is in its second operating state, the signal transmitted by the injection-locked oscillator **106₁** may be of the order of a few tens of mV. The excitation signal **122₁** transmitted by the injection-locked oscillator **106₁** operating in its second operating state has an amplitude that is dependent on the injection signal **120** and on the bias current of the injection-locked oscillator **106₁** when it is in its first operating state. This allows the value of the decrease in the injection-locked oscillators operating in their second operating state to be adjusted. As such, the decrease in the injection signal may be small, and so the excitation signal may continue to excite the corresponding electrometer. Conversely, the decrease may be large, which may result in the transmission of an excitation signal that does not excite the corresponding electrometer, and may also result in the injection-locked oscillator stopping.

Of course, the arrangement of the injection-locked oscillator **106₁** is not limited to this example. Other arrangements of the injection-locked oscillator **106** are applicable to the operation of the injection-locked oscillators **106** used in the device according to the invention. For example, the injection-locked oscillator **106₁** may comprise an LC structure such as an NMOS pair and tail current at the drain, a PMOS pair and tail current at the source, or a PMOS pair and tail current at the drain, or more complex LC architectures such as, for example, CMOS core cross-coupled differential topologies.

In the devices **100** or **700**, the injection-locked oscillators **106** may all be the same, for example they may all have the arrangement described in FIG. 11, or they may comprise a different arrangement from one oscillator to another.

FIG. 12 is another example of a quantum device **1200** according to the invention.

In the device illustrated in FIG. 12, the spin qubits are arranged in a spin qubit array **1202** comprising *n* rows in a first direction **1204** and *m* columns in a second direction **1206**.

In the device **1200**, the electrometers **104** are arranged in the form of an array (not illustrated) positioned facing the spin qubit array **1202** so that the at least one quantum dot of each spin qubit is capacitively coupled to a quantum dot of one of the electrometers **104**.

In the example illustrated in FIG. 12, the array of spin qubits comprises *n* rows and *m* columns where *n* et *m* are integers greater than or equal to 1 and may be equal or

16

different. The array of electrometers **104** is arranged above or below the array of spin qubits **1202** such that the quantum dot of each of the spin qubits is capacitively coupled to a quantum dot of one of the electrometers **104** located close by, above or below, the quantum dot of each of the spin qubits. In this example, the array of electrometers comprises *n* rows and *m* columns.

The parameters *n* and *m* may take values that are typically between 10 and 1000. By way of example, the values of *n* and *m* may be 100.

The array of spin qubits **1202** and the array of electrometers may be produced in a superposed manner via the implementation of a 3D integration method.

In the example illustrated in FIG. 12, the device **1200** in this embodiment comprises *n* excitation means **106** arranged in the first direction. Each injection-locked oscillator **106** is coupled to all of the electrometers **104** coupled to spin qubits positioned on one and the same row of the spin qubit array **1202**. All of the electrometers **104** arranged on one and the same row of the array of spin qubits **1202** are coupled to one and the same injection-locked oscillator **106** so that one and the same excitation signal **122** is applied to at least one input electrode of the electrometers **104** present on one and the same row of the array of electrometers.

In the device **1200**, the amplification circuit **108** also comprises *m* amplifiers **110** arranged in the second direction. Each amplifier **110** is coupled to all of the electrometers **104** coupled to spin qubits positioned on one and the same column of the spin qubit array **1202**, the output of each amplifier **110** being coupled to the input of the injection-locked oscillator **106**. In this way, all of the output signals delivered by the electrometers on one and the same column of the array of electrometers are summed before being sent to the corresponding amplifier **110**.

Thus, each column of the array of spin qubits **1202** (coupled to the electrometers) associated with an injection-locked oscillator **106** and an amplifier **110** of the amplification circuit corresponds to the device **100**. The operation of the device **1200** is therefore similar to that of the device **100**.

The device **1200** also comprises *m* switches arranged in the second direction and positioned upstream or, preferably, downstream of the amplification circuit **108**. Each switch is arranged so as to alternately connect all of the electrometers **104** coupled to spin qubits positioned on one and the same column of the spin qubit array **1202** to the corresponding amplifier **110** or to the corresponding injection-locked oscillator **106**.

The device **1200** may also comprise bias circuits coupled to each electrometer **104**.

In addition, the device **1200** also comprises measurement means **1208** coupled to the output of each injection-locked oscillator **106**.

FIG. 13 is another example of a quantum device **1300** according to the invention. The device **1300** comprises all of the elements of the device **1200**. Only the differences with respect to FIG. 12 will be described.

The amplification circuit **108** comprises just one amplifier **110**. The device **1300** further comprises *m* switches (not illustrated) arranged in the second direction, each switch being arranged so as to alternately connect all of the electrometers **104** coupled to spin qubits positioned on one and the same column of the spin qubit array **1202** to the amplifier **110**.

According to the variants of the devices **1200** and **1300**, the device may read an array of spin qubits that may comprise several thousand spin qubits. The device's power

consumption is decreased and its compactness is increased in comparison with a device that does not participate in the readout of an array of spin qubits. The switches of these devices are arranged to perform a sequential readout of the array of spin qubits **1202**. In particular, the readout is performed column by column of the array of spin qubits **1202**.

The variant described according to device **1300** may be favoured because it does not require the use of an amplifier in the amplification circuit for the whole array of spin qubits. As such, this version requires fewer electronic components (fewer amplifiers in this case), which improves compactness and decreases power consumption.

According to variants of the devices **1200** and **1300**, the array of electrometers **104** comprises fewer electrometers than spin qubits in the array of spin qubits **1202**. In this case, the devices **1200** and **1300** may comprise a processing unit designed to retrieve, by triangulation, the state of each spin qubit from a signal transmitted by each electrometer **104**. The processing unit may comprise a computer and/or a processor and/or a computing module.

FIG. **14** schematically shows a first example of a method **1400** according to the invention. The method **1400** is a method for reading multiple spin qubits **102**, each comprising a quantum dot. The method **1400** is designed to implement any of the devices **100**, **700**, **1200** and **1300**.

The method **1400** illustrated in FIG. **14** uses the electrometers **104**, each being capacitively coupled to a potential well of the at least one quantum dot of at least one of the spin qubits **102**, the injection-locked oscillators **106**, each being coupled to at least one electrode of one of the electrometers **104**, the amplification circuit **108**, said amplification circuit **108** being coupled to the output of each electrometer **104** and comprising at least one amplifier **110** and an output **112**, said method comprising:

each of the injection-locked oscillators **106** transmitting **1402** the excitation signal **122** to at least one input electrode of the electrometer **104** to which it is coupled, each excitation signal **122** having a different frequency, characterized in that said method **1400** further comprises:

injecting **1406** the injection signal **120** into each injection-locked oscillator **106** via a feedback loop **114** coupling the output **112** of said amplification circuit **108** to the input of each injection-locked oscillator **106**, the injection signal **120** comprising components at the frequencies of said excitation signals **122** and, for each injection-locked oscillator **106**, decreasing **1408** or maintaining **1410** the excitation signal **122** as a function of said injection signal.

The method according to the invention provides a solution for reading multiple spin qubits that is straightforward to implement and designed so as to use the fewest possible electronic components. As such, the method affords advantages that are similar to those of the device according to invention, in particular in limiting the power consumption of the components implementing the method according to the invention.

LIST OF CITED DOCUMENTS

Vandersypen 2016: "Interfacing spin qubits in quantum dots and donors—hot, dense and coherent", ARXIV.ORG, 18 Dec. 2016, DOI: 10.1038/S41534-0038-Y
Bonteanu 2017: "A current controlled CMOS current amplifier", G. Bonteanu, DOI: 10.1109/ISEEE.2017.8170668

L. Le. Guevel 2020: L. Le. Guevel et al., "19.2 A 110 mK 295 μ W 28 nm FDSOI CMOS Quantum Integrated Circuit with a 2.8 GHz Excitation and nA Current Sensing of an On-Chip Double Quantum Dot," 2020 *IEEE International Solid-State Circuits Conference—(ISSCC)*, San Francisco, CA, USA, 2020, pp. 306-308, DOI: 10.1109/ISSCC19947.2020.9063090.

Yoon 2004: Sangwoong Yoon, "LC-tank CMOS Voltage-Controlled Oscillators using High Quality Inductors Embedded in Advanced Packaging Technologies", Georgia Institute of Technology 2004

Reilley 2007: "Fast single-charge sensing a RF quantum point contact" D. J Reilley et al., APPLIED PHYSICS LETTERS 91, 162101, 2007

The invention claimed is:

1. A quantum device comprising:

multiple spin qubits, each comprising at least one quantum dot,

multiple electrometers, each being capacitively coupled to a potential well of the at least one quantum dot of at least one of the spin qubits, and

multiple injection-locked oscillators, each being coupled to at least one electrode of one of the electrometers and designed to transmit an oscillating signal, called an excitation signal, to at least one input electrode of the electrometer to which it is coupled, each excitation signal having a different frequency,

further comprising:

an amplification circuit comprising at least one amplifier, said amplification circuit being coupled to the output of each electrometer and comprising an output,

and in that said device comprises a feedback loop coupling the output of said amplification circuit to an input of each injection-locked oscillator and through which an electrical signal, called an injection signal, flows, comprising components at the frequencies of said excitation signals, each injection-locked oscillator being designed to receive the injection signal and, as a function of said injection signal, keep its excitation signal in a first operating state or decrease its excitation signal to a second operating state.

2. The device according to claim 1, wherein the injection signal has a spectrum comprising a line associated with each excitation signal, each line of said spectrum having an amplitude that is dependent on a state of the spin qubit.

3. The device according to claim 2, wherein each injection-locked oscillator is designed to:

operate in its first operating state when the amplitude of the injection signal, at the corresponding line, is lower than a threshold, and

operate in its second operating state when the amplitude of the injection signal, at the corresponding line, is higher than or equal to said threshold.

4. The device according to claim 1, wherein, for each injection-locked oscillator, the excitation signal transmitted in the first operating state is at least 10 times greater than the excitation signal transmitted in the second operating state.

5. The device according to claim 1, comprising multiple measurement means, each being coupled to an injection-locked oscillator, each measurement means being designed to detect the operating state of said injection-locked oscillator and, depending on the detected state, to transmit a signal, called a measurement signal, relating to a spin state.

6. The device according to claim 1, wherein the amplification circuit is designed to negatively amplify a signal output by the electrometers.

19

7. The device according to claim 1, wherein the amplification circuit is designed to perform current amplification or, when the at least one amplifier of the amplification circuit comprises at least one transimpedance amplifier, designed to convert an input signal into a voltage at the output of said amplification circuit. 5

8. The device according to claim 1, wherein each electrometer comprises a drain, and a gate, injection-locked oscillators being coupled to the drain or to the gate.

9. The device according to claim 1, wherein each electrometer comprises a quantum point contact or a single-electron transistor. 10

10. The device according to claim 1, comprising multiple bias circuits, each being coupled to an electrometer and arranged to apply a DC bias voltage to said electrometer which is designed so that each electrometer produces a Coulomb blockade. 15

11. The device according to claim 1, wherein:

the spin qubits are arranged in a spin qubit array comprising n rows in a first direction and m columns in a second direction, and 20

the electrometers are arranged in the form of an array positioned facing the spin qubit array so that the at least one quantum dot of one of the electrometers is capacitively coupled to at least one quantum dot of at least one spin qubit. 25

12. The device according to claim 11, wherein the amplification circuit comprises:

m amplifiers arranged in the second direction, each amplifier being coupled to all of the electrometers coupled to spin qubits positioned on one and the same column of the spin qubit array, the output of each amplifier being coupled to the input of the injection-locked oscillator, said device further comprising: 30

n excitation means arranged in the first direction, each injection-locked oscillator being coupled to all of the electrometers coupled to spin qubits positioned on one and the same row of the spin qubit array, 35

m switches arranged in the second direction and positioned upstream or downstream of the amplification circuit, each switch being arranged so as to alternately connect all of the electrometers coupled to spin qubits positioned on one and the same column of the spin qubit array to the corresponding amplifier or to the corresponding injection-locked oscillator. 40

20

13. The device according to claim 11, comprising:

n excitation means arranged in the first direction, each injection-locked oscillator being coupled to all of the electrometers coupled to spin qubits positioned on one and the same row of the spin qubit array, the amplification circuit comprising a single amplifier, said device further comprising:

m switches arranged in the second direction, each switch being arranged so as to alternately connect all of the electrometers coupled to spin qubits positioned on one and the same column of the spin qubit array to the amplifier, the output of the amplifier being coupled to each injection-locked oscillator.

14. The device according to claim 12, wherein each spin qubit alternately comprises two states, a high state and a low state, when a quantum dot of one of the electrometers is coupled to at least one quantum dot of at least two spin qubits, said device further comprising a processing unit configured to retrieve, by triangulation, the state of each spin qubit from a signal transmitted by each electrometer, said signal being dependent on the state of the spin qubit.

15. A method for reading multiple spin qubits, each comprising a quantum dot, said method using multiple electrometers, each being capacitively coupled to a potential well of the at least one quantum dot of at least one of the spin qubits, multiple injection-locked oscillators, each being coupled to at least one electrode of one of the electrometers, an amplification circuit, said amplification circuit being coupled to the output of each electrometer and comprising at least one amplifier and an output, said method comprising: 30

each of the injection-locked oscillators transmitting an oscillating signal, called an excitation signal, to at least one input electrode of the electrometer to which it is coupled, each excitation signal having a different frequency, wherein said method further comprises:

injecting a signal, called an injection signal, into each injection-locked oscillator via a feedback loop coupling the output of said amplification circuit to the input of each injection-locked oscillator, the injection signal comprising components at the frequencies of said excitation signals and, for each injection-locked oscillator, decreasing or maintaining the excitation signal resulting from said injection signal. 40

* * * * *