

US Patent & Trademark Office

Patent Public Search | Text View

United States Patent	12407274
Kind Code	B2
Date of Patent	September 02, 2025
Inventor(s)	Khalid; Muhammad et al.

Inverter topology circuit

Abstract

An inverter topology circuit that includes a direct current source; a first capacitor; a second capacitor, and a number of switches (a first switch, a second switch, a third switch, a fourth switch, a fifth switch, a sixth switch, a seventh switch, an eighth switch, a ninth switch, a tenth switch, and an eleventh switch). A first side of the first switch and a first side of the third switch are connected to a first side of the direct current source. A first side of the second switch and a first side of the fourth switch are connected to a second side of the direct current source. The first capacitor and the second capacitor are connected in series and are connected in parallel with the direct current source.

Inventors: Khalid; Muhammad (Dhahran, SA), Ali; Mohammad (Dhahran, SA)

Applicant: KING FAHD UNIVERSITY OF PETROLEUM AND MINERALS (Dhahran, SA)

Family ID: 92896137

Assignee: KING FAHD UNIVERSITY OF PETROLEUM AND MINERALS (Dhahran, SA)

Appl. No.: 18/191934

Filed: March 29, 2023

Prior Publication Data

Document Identifier	Publication Date
US 20240333176 A1	Oct. 03, 2024

Publication Classification

Int. Cl.: H02M7/5387 (20070101); H02M7/483 (20070101)

U.S. Cl.:

CPC **H02M7/53871** (20130101); **H02M7/4833** (20210501);

Field of Classification Search

CPC: H02M (7/487); H02M (7/53871); H02M (7/4833); H02M (1/32); H02M (1/36)

References Cited

U.S. PATENT DOCUMENTS

Patent No.	Issued Date	Patentee Name	U.S. Cl.	CPC
10965221	12/2020	Bassi	N/A	H02M 7/483
11196354	12/2020	Rawa	N/A	H02M 7/487
2021/0194382	12/2020	Bassi	N/A	H02M 1/0012
2022/0069736	12/2021	Bassi	N/A	H02M 7/4837

FOREIGN PATENT DOCUMENTS

Patent No.	Application Date	Country	CPC
110829867	12/2019	CN	N/A
115051585	12/2021	CN	N/A
202011029808	12/2019	IN	N/A
202011029808	12/2019	IN	N/A
WO-2020047677	12/2019	WO	H02M 1/0095

OTHER PUBLICATIONS

Translation CN-110829867-A (Year: 2020). cited by examiner

Drawings and claims IN 202011029808 (Year: 2020). cited by examiner

Thirteen-Level UXE-Type Inverter With 12-Band Hysteresis Current Control Employing PSO Based PI Controller, Deepak et al. IEEE Access (p. 29890-29902) vol. 11, 2023 (Year: 2023). cited by examiner

Islam et al. ; A Switched Capacitor-Based 13-null inverter With Reduced Switch Count. cited by applicant

Ali et al. ; A Modified Less-Switch-Count Switched-Capacitor Multilevel Inverter for Solar PV-Applications ; IEEE 2022 ; 6 Pages. cited by applicant

Sathik et al. ; Cross Connected Compact Switched-Capacitor Multilevel Inverter (C3-SCMLI) Topology with Reduced Switch Count ; IEEE Transactions on Circuits and Systems II: Express Briefs ; Apr. 29, 2020 ; 5 Pages. cited by applicant

Siddique et al. ; Single-Phase 9L Switched-Capacitor Boost Multilevel Inverter (9L-SC-BMLI) Topology ; IEEE Transactions on Industry ; Sep. 28, 2022 ; 8 Pages. cited by applicant

Primary Examiner: Tran; Thienvu V

Assistant Examiner: Torres; Yahveh Comas

Background/Summary

STATEMENT OF PRIOR DISCLOSURE BY AN INVENTOR

(1) Aspects of the present disclosure are described in *A Modified Less-Switch-Count Switched-Capacitor Multilevel Inverter for Solar PV-Applications*, M. Ali and M. Khalid, 2022 5th International Conference on Power Electronics and their Applications (ICPEA), Hail, Saudi Arabia, incorporated herein by reference.

BACKGROUND

Technical Field

(2) The present disclosure is directed to an inverter topology circuit.

Description of Related Art

(3) The “background” description provided herein is for the purpose of generally presenting the context of the disclosure. Work of the presently named inventors, to the extent it is described in this background section, as well as aspects of the description which may not otherwise qualify as prior art at the time of filing, are neither expressly nor impliedly admitted as prior art against the present invention.

(4) With global population growth, energy demand is increasing to meet the population's various needs. Renewable energy sources (RESs), such as solar energy, fuel cells, and wind energy, are preferable to non-renewable energy sources (fossil fuels) and have become the mainstream of development. The solar energy is converted into electrical energy using a photovoltaic (PV) system. PV systems are modular, easy to install, and excess energy generated can be sent to a utility grid. In the PV system, several power electronic inverter devices, such as Direct Current (DC)-Alternating Current (AC) converters, AC-DC converters, and dual-converters are required to enhance the energy produced for effective and efficient use of PV systems.

(5) The performance and application of the PV system may depend on the performance of power electronic inverter devices. A conventional two-level inverter has defects of high harmonic content, low efficiency, and the like. With the rapid development of power electronic technology, multi-level inverters have been introduced. The multi-level inverters can generate different output voltage waveforms combining different input DC voltage sources. In multi-level inverters, increasing the number of output voltage levels improves the output voltage quality and decreases the total harmonic distortion (THD) of the output voltage waveform causing the output voltage to appear like a sinusoidal waveform. Conventional multi-level inverters include diode-clamped, capacitor-clamped, and H-bridge cascaded inverters. Both the diode-clamped multi-level inverter and the capacitor-clamped multi-level inverter have the problem that a capacitor voltage needs to be added with a voltage balancing circuit. The H-bridge cascaded multi-level inverter needs a plurality of independent direct-current power supplies. To increase the number of output voltage levels in multi-level inverters, a number of utilized power electronic components and DC sources have been increased which is not always cost-effective and is a disadvantage for these inverters.

(6) To overcome the aforementioned issues with the multi-level inverters, switched capacitor multi-level inverters have been introduced. The switched capacitor multi-level inverters generate a large number of output voltage levels with a small number of DC voltage input sources. Moreover, the switched capacitor multi-level inverter topologies can increase the maximum output voltage without requiring a boosting stage. However, the switched capacitor-based inverter requires high voltage rating switches, which limits its application for medium voltage applications.

(7) The conventional multi-level inverter employs a neutral point clamped (NPC) and a cascaded H-Bridge (CHB) topology. The NPC requires many electrical components. For instance, for an 11-

level implementation, 14 IGBTs (insulated gate bipolar transistors), 12 diodes, and 10 capacitors are required. Also, 5 neutral points require perfect balancing, which leads to significant efforts. For an 11-level operation, 5 DC sources of equal magnitude and 20 IGBTs are required. These components and configurations have led to a complex inverter topology which is costly and less efficient.

(8) Accordingly, it is one object of the present disclosure to provide an inverter topology circuit that reduces potential stress on switching elements and optimizes the circuit's design to achieve high voltage gain by employing fewer components.

SUMMARY

(9) In an exemplary embodiment, an inverter topology circuit is disclosed. The circuit includes a direct current source; a first capacitor; a second capacitor, and a number of switches (a first switch, a second switch, a third switch, a fourth switch, a fifth switch, a sixth switch, a seventh switch, an eighth switch, a ninth switch, a tenth switch, and an eleventh switch). A first side of the first switch and a first side of the third switch are connected to a first side of the direct current source, while a first side of the second switch and a first side of the fourth switch are connected to a second side of the direct current source. A first side of the fifth switch and a first side of the seventh switch are connected to a second side of the third switch, while a first side of the sixth switch and a first side of the eighth switch are connected to a second side of the fourth switch. A first side of the ninth switch, a second side of the sixth switch, and a second side of the seventh switch are connected to a first side of the first capacitor. A first side of the tenth switch, a second side of the first capacitor are connected to a first side of the second capacitor. A first side of the eleventh switch, a second side of the fifth switch, and a second side of the eighth switch are connected to a second side of the second capacitor. The first capacitor and the second capacitor are connected in series and are connected in parallel with the direct current source.

(10) In another exemplary embodiment, a method for controlling the charging and discharging of a first capacitor and a second capacitor in an inverter is disclosed. The method includes determining a DC link voltage V_{dc} of the inverter. The method includes determining a state of an inverter by a nearest-level control (NLC). The method includes determining a direction of current flow. The method includes determining a magnitude of an auxiliary DC link voltage. The method includes determining a threshold of the auxiliary DC link voltage. In response to the state level being $+V_{sub.dc}/2$, the current flow being positive, and the magnitude of the auxiliary DC link voltage being higher than the threshold, charging the first capacitor and the second capacitor. In response to the state level being $+V_{sub.dc}/2$, the current flow being positive, and the magnitude of the auxiliary DC link voltage being lower than the threshold, discharging the first capacitor and the second capacitor. In response to the state level being $+V_{sub.dc}/2$, the current flow being negative, and the magnitude of the auxiliary DC link voltage being higher than the threshold, charging the first capacitor and the second capacitor. In response to the state level being $+V_{sub.dc}/2$, the current flow being negative, and the magnitude of the auxiliary DC link voltage being lower than the threshold, discharging the first capacitor and the second capacitor. In response to the state level being $-V_{sub.dc}/2$, the current flow being positive, and the magnitude of the auxiliary DC link voltage being higher than the threshold, charging the first capacitor and the second capacitor. In response to the state level being $-V_{sub.dc}/2$, the current flow being positive, and the magnitude of the auxiliary DC link voltage being lower than the threshold, discharging the first capacitor and the second capacitor. In response to the state level being $-V_{sub.dc}/2$, the current flow being negative, and the magnitude of the auxiliary DC link voltage being higher than the threshold, charging the first capacitor and the second capacitor. In response to the state level being $-V_{sub.dc}/2$, the current flow being negative, and the magnitude of the auxiliary DC link voltage being lower than the threshold, discharging the first capacitor and the second capacitor.

(11) The foregoing general description of the illustrative embodiments and the following detailed

description thereof are merely exemplary aspects of the teachings of this disclosure, and are not restrictive.

Description

BRIEF DESCRIPTION OF THE DRAWINGS

- (1) A more complete appreciation of this disclosure and many of the attendant advantages thereof will be readily obtained as the same becomes better understood by reference to the following detailed description when considered in connection with the accompanying drawings, wherein:
- (2) FIG. 1 illustrates a schematic diagram of an inverter topology circuit, according to aspects of the present disclosure;
- (3) FIG. 2A illustrates a first state of the inverter topology circuit at 0 V.sub.dc, according to aspects of the present disclosure;
- (4) FIG. 2B illustrates a second state of the inverter topology circuit at 0 V, according to aspects of the present disclosure;
- (5) FIG. 2C illustrates a third state of the inverter topology circuit at 0.25 V.sub.dc, according to aspects of the present disclosure;
- (6) FIG. 2D illustrates a fourth state of the inverter topology circuit at 0.5 V.sub.dc, according to aspects of the present disclosure;
- (7) FIG. 2E illustrates a fifth state of the inverter topology circuit at 0.5 V.sub.dc, according to aspects of the present disclosure;
- (8) FIG. 2F illustrates a sixth state of the inverter topology circuit at 0.75 V.sub.dc, according to aspects of the present disclosure;
- (9) FIG. 2G illustrates a seventh state of the inverter topology circuit at V.sub.dc, according to aspects of the present disclosure;
- (10) FIG. 2H illustrates an eighth state of the inverter topology circuit at 1.25 V.sub.dc, according to aspects of the present disclosure;
- (11) FIG. 2I illustrates a ninth state of the inverter topology circuit at -0.25 V.sub.dc, according to aspects of the present disclosure;
- (12) FIG. 2J illustrates a tenth state of the inverter topology circuit at -0.5 V.sub.dc, according to aspects of the present disclosure;
- (13) FIG. 2K illustrates an eleventh state of the inverter topology circuit at -0.5 V.sub.dc, according to aspects of the present disclosure;
- (14) FIG. 2L illustrates a twelfth state of the inverter topology circuit at -0.75 V.sub.dc, according to aspects of the present disclosure;
- (15) FIG. 2M illustrates a thirteenth state of the inverter topology circuit at -V.sub.dc, according to aspects of the present disclosure;
- (16) FIG. 2N illustrates a fourteenth state of the inverter topology circuit at -1.25 V.sub.dc, according to aspects of the present disclosure;
- (17) FIG. 3 illustrates a method for controlling the charging and discharging of a first capacitor and a second capacitor in an inverter, according to aspects of the present disclosure;
- (18) FIG. 4A illustrates a graph of output voltage, load current, and capacitor voltages of the inverter topology circuit with a resistive load (R-load), according to aspects of the present disclosure;
- (19) FIG. 4B illustrates a graph of output voltage, load current, and capacitor voltages of the inverter topology circuit with an RL-load, according to aspects of the present disclosure;
- (20) FIG. 4C illustrates a graph of output voltage, load current, and capacitor voltages of the inverter topology circuit with load change, according to aspects of the present disclosure;
- (21) FIG. 4D illustrates a graph of output voltage, load current, and capacitor voltages of the

inverter topology circuit with modulation index change, according to aspects of the present disclosure;

(22) FIG. 5A illustrates capacitor currents in a conventional inverter, according to aspects of the present disclosure;

(23) FIG. 5B illustrates capacitor currents in the inverter topology circuit, according to aspects of the present disclosure;

(24) FIG. 6A illustrates current behavior through switches/diodes in the conventional inverter, according to aspects of the present disclosure;

(25) FIG. 6B illustrates current behavior through switches/diodes in the inverter topology circuit, according to aspects of the present disclosure;

(26) FIG. 7A illustrates a junction temperature of the switches/diodes in the conventional inverter, according to aspects of the present disclosure;

(27) FIG. 7B illustrates a junction temperature of the switches/diodes in the inverter topology circuit, according to aspects of the present disclosure;

(28) FIG. 8A illustrates a blocking voltage across the switches/diodes in the conventional inverter, according to aspects of the present disclosure;

(29) FIG. 8B illustrates a blocking voltage across the switches/diodes in the inverter topology circuit, according to aspects of the present disclosure;

(30) FIG. 9A illustrates a graph of source current behavior in the conventional inverter, according to aspects of the present disclosure; and

(31) FIG. 9B illustrates a graph of source current behavior in the inverter topology circuit, according to aspects of the present disclosure.

DETAILED DESCRIPTION

(32) In the drawings, like reference numerals designate identical or corresponding parts throughout the several views. Further, as used herein, the words “a,” “an” and the like generally carry a meaning of “one or more,” unless stated otherwise.

(33) Furthermore, the terms “approximately,” “approximate,” “about,” and similar terms generally refer to ranges that include the identified value within a margin of 20%, 10%, or preferably 5%, and any values therebetween.

(34) Aspects of this disclosure are directed to an inverter for a solar PV application that employs a lower switch count. The disclosed inverter reduces the capacitors' inrush currents, resulting in increased capacitor life and reduced switch current stress. Additionally, the inverter is configured to provide an eleven (11)-level output, leading to better harmonic performance and omission or reduction of output filter size. The inverter is configured to be operated as a microinverter or string inverter in adverse temperature conditions for solar PV applications.

(35) FIG. 1 illustrates a circuit diagram of an inverter topology circuit, according to aspects of the present disclosure (hereinafter interchangeably referred to as “circuit **100**”). As shown in FIG. 1, the circuit **100** includes a direct current source **102**, a first capacitor (C.sub.1) **104**, a second capacitor (C.sub.2) **106**, a plurality of switches (S.sub.1-S.sub.11), and a load **108**. For example, the plurality of switches (S.sub.1-S.sub.11) includes eleven (11) switches i.e., a first switch S.sub.1, a second switch S.sub.2, a third switch S.sub.3, a fourth switch S.sub.4, a fifth switch S.sub.5, a sixth switch S.sub.6, a seventh switch S.sub.7, an eighth switch S.sub.8, a ninth switch S.sub.9, a tenth switch S.sub.10, and an eleventh switch S.sub.11.

(36) The direct current source **102** is configured to provide a direct current to the circuit **100**. The direct current source **102** includes, but is not limited to, a plurality of photovoltaic panel arrays, a plurality of wind power turbines, a photovoltaic cell, a photovoltaic cell panel or a wind energy battery, a plurality of wave generators, and such naturally available resources. In an example, the direct current source **102** may include a plurality of direct current sources connected in parallel. In an aspect, a first side of the direct current source **102** is a positive pole, and a second side of the direct current source **102** is a negative pole.

(37) In the circuit **100**, the plurality of switches (S.sub.1-S.sub.11) may include at least any one of an insulated gate bipolar transistor (IGBT), a metal-oxide-semiconductor field-effect transistor (MOSFET), a silicon-controlled rectifier (SCR), or a gate turn-off thyristor (GTO). For example, the switches are insulated gate bipolar transistors (IGBTs).

(38) As shown in FIG. 1, a first side of the first switch S.sub.1 and a first side of the third switch S.sub.3 are connected to the first side of the direct current source **102**. A first side of the second switch S.sub.2 and a first side of the fourth switch S.sub.4 are connected to the second side of the direct current source **102**. A first side of the fifth switch S.sub.5 and a first side of the seventh switch S.sub.7 are connected to a second side of the third switch S.sub.3. A first side of the sixth switch S.sub.6 and a first side of the eighth switch S.sub.8 are connected to a second side of the fourth switch S.sub.4.

(39) Further, a first side of the ninth switch S.sub.9, a second side of the sixth switch S.sub.6, and a second side of the seventh switch S.sub.7 are connected to a first side of the first capacitor **104**. A first side of the tenth switch S.sub.10 and a second side of the first capacitor **104** are connected to a first side of the second capacitor **106**. In an aspect, the tenth switch S.sub.10 is formed with two insulated gate bipolar transistors (IGBTs) with the emitters connected in series, as shown in FIG. 1.

(40) As shown in FIG. 1, a first side of the eleventh switch S.sub.11, a second side of the fifth switch S.sub.5, and a second side of the eighth switch S.sub.8 are connected to a second side of the second capacitor **106**.

(41) In an operative aspect, the first side of the first switch S.sub.1, the third switch S.sub.3, the fifth switch S.sub.5, the eighth switch S.sub.8, and the ninth switch S.sub.9 are collectors of the switches. In an aspect, the second side of the first switch S.sub.1, the third switch S.sub.3, the fifth switch S.sub.5, the eighth switch S.sub.8, and the ninth switch S.sub.9 are emitters of the corresponding switches.

(42) In an aspect, the second side of the second switch S.sub.2, the fourth switch S.sub.4, the sixth switch S.sub.6, the seventh switch S.sub.7, and the eleventh switch S.sub.11 are collectors of the switches. In an aspect, the first side of the second switch S.sub.2, the fourth switch S.sub.4, the sixth switch S.sub.6, the seventh switch S.sub.7, and the eleventh switch S.sub.11 are emitters of the corresponding switches.

(43) The first capacitor **104**, and the second capacitor **106** are connected in series. Further, the first capacitor **104** and the second capacitor **106** are connected in parallel with the direct current source **102**. In an example, the first capacitor **104** and the second capacitor **106** have a capacitor inrush current of less than 5 amperes at a max capacitance of 1700 μ F and an input voltage to the circuit of 100 V.

(44) In an example, the first side of the first capacitor **104** is an anode and the first side of the second capacitor **106** is an anode.

(45) In another example, the second side of the first capacitor **104** is a cathode and the second side of the second capacitor **106** is a cathode.

(46) In an aspect, the circuit **100** is coupled to a storage device and the load **108**. For example, the load **108** may be a DC load or an AC load. In an example, the DC load is selected from a group consisting of a battery, an electric vehicle, a pump, a compressor, a heater, a cathodic protection device, a DC to DC converter, and an electrolyzer. In one example, the AC load is selected from a group consisting of a pump, a compressor, a heater, and a transformer.

(47) The circuit **100** is configured to produce a boosted output voltage of 1.25. The circuit **100** utilizes 12 IGBTs. For example, the rating of the plurality of switches (S.sub.1-S.sub.11) is shown along with the switches as shown in FIG. 1. As the capacitor inrush current is reduced by a large factor, the durability of the circuit **100** increases, especially in high-temperature operations.

(48) FIG. 2A-FIG. 2N illustrate various operational states of the circuit **100** (also refers as an inverter **100**), according to aspects of the present disclosure.

(49) FIG. 2A illustrates a first state of the inverter **100** at 0 V.sub.dc (state 1 as shown in Table 1),

where the switches S.sub.1, S.sub.3, S.sub.5, and S.sub.11 are ON and switches S.sub.2, S.sub.4, S.sub.6, S.sub.7, S.sub.8, S.sub.9, and S.sub.10, are OFF. FIG. 2B illustrates a second state of the inverter **100** at 0 V (state 2 as shown in Table 1), where the switches S.sub.2, S.sub.4, S.sub.6, and S.sub.9 are ON and switches S.sub.1, S.sub.3, S.sub.5, S.sub.7, S.sub.8, S.sub.10, and S.sub.11, are OFF.

(50) FIG. 2C illustrates a third state of the inverter **100** at 0.25 V.sub.dc (state 3 as shown in Table 1), where the switches S.sub.1, S.sub.3, S.sub.7, and S.sub.10 are ON and switches S.sub.2, S.sub.4, S.sub.5, S.sub.6, S.sub.8, S.sub.9, and S.sub.11, are OFF. FIG. 2D illustrates a fourth state of the inverter **100** at 0.5 V.sub.dc (state 4 as shown in Table 1), where the switches S.sub.1, S.sub.3, S.sub.7, and S.sub.11 are ON and switches S.sub.2, S.sub.4, S.sub.5, S.sub.6, S.sub.8, S.sub.9, and S.sub.10, are OFF.

(51) FIG. 2E illustrates a fifth state of the inverter **100** at 0.5 V.sub.dc (state 5 as shown in Table 1), where the switches S.sub.1, S.sub.4, S.sub.8, and S.sub.9 are ON and switches S.sub.2, S.sub.3, S.sub.5, S.sub.6, S.sub.7, S.sub.10, and S.sub.11, are OFF. FIG. 2F illustrates a sixth state of the inverter **100** at 0.75 V.sub.dc (which is state 6 as shown in Table 1), where the switches S.sub.1, S.sub.4, S.sub.8, and S.sub.10 are ON and switches S.sub.2, S.sub.3, S.sub.5, S.sub.6, S.sub.7, S.sub.9, and S.sub.11, are OFF.

(52) FIG. 2G illustrates a seventh state of the inverter **100** at V.sub.dc (state 7 as shown in Table 1), where the switches S.sub.1, S.sub.4, S.sub.8, and S.sub.11 are ON and switches S.sub.2, S.sub.3, S.sub.5, S.sub.6, S.sub.7, S.sub.9, and S.sub.10, are OFF. FIG. 2H illustrates an eighth state of the inverter **100** at 1.25 V.sub.dc (state 8 as shown in Table 1), where the switches S.sub.1, S.sub.4, S.sub.6, and S.sub.10 are ON and switches S.sub.2, S.sub.3, S.sub.5, S.sub.7, S.sub.8, S.sub.9, and S.sub.11, are OFF.

(53) FIG. 2I illustrates a ninth state of the inverter **100** at -0.25 V.sub.dc (state 9 as shown in Table 1), where the switches S.sub.2, S.sub.4, S.sub.8, and S.sub.10 are ON and switches S.sub.1, S.sub.3, S.sub.5, S.sub.6, S.sub.7, S.sub.9, and S.sub.11, are OFF. FIG. 2J illustrates a tenth state of the inverter **100** at -0.5 V.sub.dc (state 10 as shown in Table 1), where the switches S.sub.2, S.sub.4, S.sub.8, and S.sub.9 are ON and switches S.sub.1, S.sub.3, S.sub.5, S.sub.6, S.sub.7, S.sub.10, and S.sub.11, are OFF.

(54) FIG. 2K illustrates an eleventh state of the inverter **100** at -0.5 V.sub.dc (state 11 as shown in Table 1), where the switches S.sub.2, S.sub.3, S.sub.7, and S.sub.11 are ON and switches S.sub.1, S.sub.4, S.sub.5, S.sub.6, S.sub.8, S.sub.9, and S.sub.10, are OFF. FIG. 2L illustrates a twelfth state of the inverter **100** at -0.75 V.sub.dc (state 12 as shown in Table 1), where the switches S.sub.2, S.sub.3, S.sub.7, and S.sub.10 are ON and switches S.sub.1, S.sub.4, S.sub.5, S.sub.6, S.sub.8, S.sub.9, and S.sub.11, are OFF.

(55) FIG. 2M illustrates a thirteenth state of the inverter **100** at -V.sub.dc (state 13 as shown in Table 1), where the switches S.sub.2, S.sub.3, S.sub.7, and S.sub.9 are ON and switches S.sub.1, S.sub.4, S.sub.5, S.sub.6, S.sub.8, S.sub.10, and S.sub.11, are OFF. FIG. 2N illustrates a fourteenth state of the inverter **100** at -1.25 V.sub.dc (state 14 as shown in Table 1), where the switches S.sub.2, S.sub.3, S.sub.5, and S.sub.10 are ON and switches S.sub.1, S.sub.4, S.sub.6, S.sub.7, S.sub.8, S.sub.9, and S.sub.11, are OFF.

(56) Table 1 represents the switching states of the circuit **100** (inverter **100**) given as below.

(57) TABLE-US-00001 TABLE 1 Switching states of the inverter 100. State

S.sub.1	S.sub.3	S.sub.5	S.sub.6	S.sub.7	S.sub.8	S.sub.9	S.sub.10	S.sub.11	I.sub.o	C.sub.1	C.sub.2	V.sub.o
1	1	1	1	0	0	0	0	1	+	—	—	0
2	0	0	0	1	0	0	1	0	+	—	—	0
3	1	1	0	0	1	0	0	1	0	+	D	—
4	1	1	1	0	1	0	0	0	1	+	D	D
5	1	0	0	0	0	1	1	0	0	+	C	C
6	1	0	0	0	0	1	0	1	0	+	—	C
7	1	0	0	0	0	1	0	0	1	+	—	—
8	1	0	0	1	0	0	0	1	0	+	D	—
9	0	0	0	0	0	1	0	1	0	+	—	C
10	0	0	0	0	0	1	1	0	0	+	C	C
11	0	1	0	0	1	0	0	0	1	+	D	D
12	0	1	0	0	1	0	0	1	0	+	D	—
13	0	1	0	0	1	0	1	0	0	+	—	—
14	0	1	1	0	0	0	0	1	0	+	—	C

1'. 1 0 0 1 0 0 0 1 0 - C - 5

V.sub.dc/4 2'. 1 0 0 0 0 1 0 0 1 — — — V.sub.dc 3'. 1 0 0 0 0 1 0 1 0 — — — D 3 V.sub.dc/4 4'. 1 0 0 0 0 1 1 0 0 — D D V.sub.dc/2 5'. 1 1 0 0 1 0 0 0 1 — C C V.sub.dc/2 6'. 1 1 0 0 1 0 0 1 0 — C — V.sub.dc/4 7'. 1 1 1 0 0 0 0 0 1 — — — 0 8'. 0 0 0 1 0 0 1 0 0 — — — 0 9'. 0 0 0 0 0 1 0 1 0 — — D — V.sub.dc/4 10'. 0 0 0 0 0 1 1 0 0 — D D — V.sub.dc/2 11'. 0 1 0 0 1 0 0 0 1 — C C — V.sub.dc/2 12'. 0 1 0 0 1 0 0 1 0 — C — — 3 V.sub.dc/4.sup. 13'. 0 1 0 0 1 0 1 0 0 — — — — V.sub.dc 14'. 0 1 1 0 0 0 0 1 0 — — D — 5 V.sub.dc/4.sup.

1. The $\pm 0.25 V_{sub.dc}$ states:

(58) At $0.25 V_{sub.dc}$, C.sub.1 discharges with positive current, and charges with negative current (as shown in FIG. 2C). At $-0.25 V_{sub.dc}$, as shown in Table 1 and FIG. 2I. C.sub.2 discharges with positive current and charges with negative current, respectively. The charge on C.sub.2 at $0.25 V_{sub.dc}$ and C.sub.1 at $-0.25 V_{sub.dc}$ is remain unaltered.

(59) 2. The $\pm 0.5 V_{sub.dc}$ States:

(60) At $0.5 V_{sub.dc}$ level, the inverter **100** has several redundant states. There are four configurations as shown by conditions in FIG. 2D, FIG. 2E, FIG. 2J, and FIG. 2K.

(61) 3. The $\pm 0.75 V_{sub.dc}$ States:

(62) For states $\pm 0.75 V_{sub.dc}$, a circuit path for the positive and negative cycle, respectively, is shown in FIG. 2F and FIG. 2L. For $0.75 V_{sub.dc}$ circuit condition, C.sub.2 is affected according to the direction of the current, and for $-0.75 V_{sub.dc}$ condition, C.sub.1 charges or discharges.

(63) 4. The $\pm V_{sub.dc}$ States:

(64) In these conditions, the capacitor's charge remains unaffected by any direction of flow of current. This is shown in FIG. 2G and FIG. 2M for positive and negative cycle, respectively.

(65) 5. The $\pm 1.25 V_{sub.dc}$ States:

(66) For $1.25 V_{sub.dc}$, as shown in FIG. 2H, with positive current, C.sub.1 will discharge, and vice-versa. The capacitor C.sub.2 charges and discharges for the state $-1.25 V_{sub.dc}$, as shown in FIG. 2N.

(67) FIG. 3 illustrates a method **300** for controlling the charging and discharging of the first capacitor **204** and the second capacitor **206** in the inverter **100**, according to aspects of the present disclosure. In an aspect, FIG. 3 illustrates state selection using the redundant states (according to Table-1).

(68) Step **302** includes determining a state of the inverter **100** by a nearest-level control (NLC) technique. The NLC technique is a technique used in modular multilevel converters (MMCs) with a large number of submodules (SMs). In the present disclosure, the circuit **100** (inverter **100**) is configured to determine the state of the inverter **100** by using the NLC technique. Step **302** further includes determining a DC link voltage $V_{sub.dc}$ of the inverter **100**. Step **302** further includes determining a direction of current flow and determining a magnitude of an auxiliary DC link voltage. The inverter **100** also determines a threshold of the auxiliary DC link voltage ($\Delta V_{sub.C}$). For example, the threshold of the auxiliary DC link voltage is 50V.

(69) The controllable charging and discharging of the capacitors can be performed according to the magnitude of the auxiliary DC-link voltage and the direction of the flow of current.

(70) Step **304** includes determining if the determined state is $+V_{sub.dc}/2$ or $-V_{sub.dc}/2$.

(71) Step **306** includes, if the determined state is $+V_{sub.dc}/2$, determining whether the current is positive ($I_{sub.0} \geq 0$) or not. If the determined current is positive ($I_{sub.0} \geq 0$), the method **300** will go to step **308**. If the determined current is negative ($I_{sub.0} \leq 0$), the method **300** will go to step **310**.

(72) Step **308** includes determining if the auxiliary DC link voltage is lower than the threshold ($\Delta V_{sub.C} \geq 0$) or not.

(73) In response to the state level being $+V_{sub.dc}/2$, the current flow being positive ($I_{sub.0} \geq 0$), and the magnitude of the auxiliary DC link voltage being higher than the threshold ($\Delta V_{sub.C} \geq 0$), step **308** further includes charging the first capacitor **104** and the second capacitor **106**. For example, if the current is positive ($I_{sub.0} \geq 0$) and the auxiliary DC-link voltage is above 50 V, then state 5 (as shown in table 1) will be chosen to charge the capacitors, as shown in FIG. 3.

(74) In response to the state level being $+V_{\text{sub.dc}}/2$, the current flow being positive ($I_{\text{sub.0}} \geq 0$), and the magnitude of the auxiliary DC link voltage being lower than the threshold ($\Delta V_{\text{sub.C}} < 0$), step **308** further includes discharging the first capacitor **104** and the second capacitor **106**. If the value of the auxiliary DC-link voltage is below 50 V, then the circuit **100** will select state 4 (as shown in table 1) to discharge the capacitors through the load **208**, as shown in FIG. 3.

(75) Step **310**, if the determined current is negative ($I_{\text{sub.0}} < 0$), includes determining if the auxiliary DC link voltage is lower than the threshold or not ($\Delta V_{\text{sub.C}} \geq 0$).

(76) In response to the state level being $+V_{\text{sub.dc}}/2$, the current flow being negative ($I_{\text{sub.0}} < 0$), and the magnitude of the auxiliary DC link voltage being lower than the threshold ($\Delta V_{\text{sub.C}} < 0$), step **310** further includes discharging the first capacitor **104** and the second capacitor **106**. If the determined current is negative ($I_{\text{sub.0}} < 0$) and the auxiliary DC-link voltage is below 50 V, then state 4' (as shown in table 1) will be chosen to discharge the capacitors.

(77) In response to the state level being $+V_{\text{sub.dc}}/2$, the current flow being negative ($I_{\text{sub.0}} < 0$), and the magnitude of the auxiliary DC link voltage being higher than the threshold ($\Delta V_{\text{sub.C}} \geq 0$), step **310** further includes charging the first capacitor **104** and the second capacitor **106**. If the value of the magnitude of the auxiliary DC link voltage is above 50 V, then the circuit **100** will select state 5' (as shown in table 1) to charge the capacitors through the load **108**.

(78) If the determined state has a different value from the $V_{\text{sub.dc}}/2$ or $-V_{\text{sub.dc}}/2$, then step **312** will be performed. The states shown in FIG. 2A, FIG. 2B, FIG. 2C, FIG. 2F, FIG. 2G, FIG. 2H, FIG. 2I, FIG. 2L, FIG. 2M and FIG. 2N are normal states, and the charging and discharging of the capacitors cannot be controlled in these states. However, in states $\pm V_{\text{sub.dc}}/2$, there are redundant states available.

(79) Step **314**, if the determined state is $-V_{\text{sub.dc}}/2$, determining whether the current is positive or not. If the determined current is positive ($I_{\text{sub.0}} \geq 0$), the method **300** will go to step **316**. If the determined current is negative ($I_{\text{sub.0}} < 0$), the method **300** will go to step **318**.

(80) Step **316** includes determining if the auxiliary DC link voltage is lower than the threshold or not ($\Delta V_{\text{sub.C}} < 0$).

(81) In response to the state level being $-V_{\text{sub.dc}}/2$, the current flow being positive ($I_{\text{sub.0}} \geq 0$), and the magnitude of the auxiliary DC link voltage being lower than the threshold ($\Delta V_{\text{sub.C}} < 0$), step **316** further includes discharging the first capacitor **104** and the second capacitor **106**. For example, if the current is positive and the auxiliary DC-link voltage is below 50 V, then the state 11 (as shown in table 1) will be chosen to discharge the capacitors, as shown in FIG. 3.

(82) In response to the state level being $-V_{\text{sub.dc}}/2$, the current flow being positive ($I_{\text{sub.0}} \geq 0$), and the magnitude of the auxiliary DC link voltage being higher than the threshold ($\Delta V_{\text{sub.C}} \geq 0$), step **316** further includes charging the first capacitor **104** and the second capacitor **106**. For example, if the current is positive ($I_{\text{sub.0}} \geq 0$) and the auxiliary DC-link voltage is above 50 V, then the state 10 (as shown in table 1) will be chosen to charge the capacitors, as shown in FIG. 3.

(83) Step **318**, if the determined state is $-V_{\text{sub.dc}}/2$ and the determined current is negative ($I_{\text{sub.0}} < 0$), includes determining if the auxiliary DC link voltage is lower than the threshold or not ($\Delta V_{\text{sub.C}} < 0$).

(84) In response to the state level being $-V_{\text{sub.dc}}/2$, the current flow being negative ($I_{\text{sub.0}} < 0$), and the magnitude of the auxiliary DC link voltage being lower than the threshold, step **318** further includes discharging the first capacitor **104** and the second capacitor **106**. For example, if the current is negative and the auxiliary DC-link voltage is below 50 V, then the state 10' (as shown in table 1) will be chosen to discharge the capacitor, as shown in FIG. 3.

(85) In response to the state level being $-V_{\text{sub.dc}}/2$, the current flow being negative ($I_{\text{sub.0}} < 0$), and the magnitude of the auxiliary DC link voltage being higher than the threshold, step **318** further includes charging the first capacitor **104** and the second capacitor **106**. For example, if the current is negative and the auxiliary DC-link voltage is above 50 V, then the state 11' (as shown in table 1) will be chosen to charge the capacitor, as shown in FIG. 3.

(86) As compared to a conventional inverter, the present circuit **100** uses IGBTs to replace the two diodes. The present circuit **100** is configured to achieve an enhanced performance by using the redundant states of the inverter. The present circuit **100** is configured to reduce large capacitor inrush currents and switch/diode current stresses.

Examples and Experiments

(87) The following examples are provided to illustrate further and to facilitate the understanding of the present disclosure.

(88) During the first experiment, the present circuit **100** was analyzed and it was observed that the circuit **100** was able to produce an eleven (11) level output corresponding to nine (9) levels synthesized by the conventional inverter, resulting in better output waveforms. The results of the first experiment have been verified and are shown in FIG. 4A-FIG. 4D. In an aspect, due to a greater number of levels in the output, the magnitude of the total harmonic distortion (THD) is lower, leading to a smaller filter requirement.

(89) FIG. 4A illustrates a graph **400** of output voltage, load current, and capacitor voltages of the circuit **100** with a resistive load (R-load). In an example, the R-load is 50Ω . Signal **402** indicates the voltage (VC.sub.1) across the first capacitor C.sub.1 over time. Signal **404** indicates the voltage (VC.sub.2) across the second capacitor C.sub.2 over time. Signal **406** indicates the output voltage (V.sub.o) of the circuit **100**. Signal **408** indicates the input current (I.sub.o) of the circuit **100**.

(90) FIG. 4B illustrates a graph **420** of output voltage, load current, and capacitor voltages of the circuit with RL-load. In an example, the RL-load is 50Ω , 50 mH. Signal **422** indicates the voltage (VC.sub.1) across the first capacitor C.sub.1 over the time. Signal **424** indicates the voltage (VC.sub.2) across the second capacitor C.sub.2 over the time. Signal **426** indicates the output voltage (V.sub.o) of the circuit **100**. Signal **428** indicates the input current (I.sub.o) of the circuit **100**.

(91) FIG. 4C illustrates a graph **440** of output voltage, load current and capacitor voltages of the circuit **100** with load change. In an example, the load change from 50Ω , 50 mH to 25Ω , 50 mH. Signal **442** indicates the voltage (VC.sub.1) across the first capacitor C.sub.1 over time. Signal **444** indicates the voltage (VC.sub.2) across the second capacitor C.sub.2 over time. Signal **446** indicates the output voltage (V.sub.o) of the circuit **100**. Signal **448** indicates the input current (I.sub.o) of the circuit **100**.

(92) FIG. 4D illustrates a graph **460** of output voltage, load current and capacitor voltages of the circuit with modulation index change. A modulation index is defined as the ratio of a fundamental component amplitude of the inverter output voltage to one-half of the available DC bus voltage. Signal **462** indicates the voltage (VC.sub.1) across the first capacitor C.sub.1 over the time. Signal **464** indicates the voltage (VC.sub.2) across the second capacitor C.sub.2 over the time. Signal **466** indicates the output voltage (V.sub.o) of the circuit **100**. Signal **468** indicates the input current (I.sub.o) of the circuit **100**.

(93) During the second experiment, the present circuit **100** was analyzed and compared with the conventional inverter. FIG. 5A illustrates capacitor currents (IC.sub.1 and IC.sub.2) in the conventional inverter. Signal **500** illustrates current (IC.sub.1) in the first capacitor C.sub.1 in the conventional inverter. Signal **510** illustrates current (IC.sub.2) in the second capacitor C.sub.2 in the conventional inverter.

(94) FIG. 5B illustrates capacitor currents (IC.sub.1 and IC.sub.2) in the circuit **100**. Signal **520** illustrates current (IC.sub.1) in the first capacitor C.sub.1 in the circuit **100**. Signal **540** illustrates current (IC.sub.2) in the second capacitor C.sub.2 in the circuit **100**.

(95) From experimentation, it was demonstrated that the circuit **100** exhibits 20 times decrease in the capacitor inrush currents. Inrush currents lead to heating of the capacitors through their equivalent series resistance (ESR), leading to early evaporation of the electrolyte and its early cessation. Thus, the circuit **100** provides a more reliable capacitor operation. The comparison of capacitor inrush currents of both capacitors is shown in FIG. 5A-FIG. 5B.

(96) FIG. 6A illustrates current behavior through the switches/diodes in the conventional inverter. Signal **600** illustrates the first switch current $I_{\text{sub.s1}}$ and the second switch current $I_{\text{sub.s2}}$ in the conventional inverter. Signal **602** illustrates the third switch current $I_{\text{sub.s3}}$ and the fourth switch current $I_{\text{sub.s4}}$ in the conventional inverter. Signal **604** illustrates the fifth switch current $I_{\text{sub.s5}}$ and the sixth switch current $I_{\text{sub.s6}}$ in the conventional inverter. Signal **606** illustrates the seventh diode current $I_{\text{sub.d7}}$ and the eighth diode current $I_{\text{sub.d8}}$ in the conventional inverter. Signal **608** illustrates the ninth switch current $I_{\text{sub.s9}}$ and the eleventh switch current $I_{\text{sub.s11}}$ in the conventional inverter. Signal **610** illustrates a first component of the tenth switch current $I_{\text{sub.s10_1}}$ and a second component of the tenth switch current $I_{\text{sub.s10_2}}$ in the conventional inverter.

(97) FIG. 6B illustrates current behavior through the switches in the circuit **100**. Signal **650** illustrates the first switch current $I_{\text{sub.s1}}$ and the second switch current $I_{\text{sub.s2}}$ in the circuit **100**. Signal **652** illustrates the third switch current $I_{\text{sub.s3}}$ and the fourth switch current $I_{\text{sub.s4}}$ in the circuit **100**. Signal **654** illustrates the fifth switch current $I_{\text{sub.s5}}$ and the sixth switch current $I_{\text{sub.s6}}$ in the circuit **100**. Signal **656** illustrates the seventh switch current $I_{\text{sub.s7}}$ and the eighth switch current $I_{\text{sub.s8}}$ in the circuit **100**. Signal **658** illustrates the ninth switch current $I_{\text{sub.s9}}$ and the eleventh switch current $I_{\text{sub.s11}}$ in the circuit **100**. Signal **660** illustrates a first component of the tenth switch current $I_{\text{sub.s10_1}}$ and a second component of the tenth switch current $I_{\text{sub.s10_2}}$ in the circuit **100**.

(98) The inrush current due to capacitors affects the switches and the diodes of the inverter. In circuit **100**, the current through the switches coming in series with the capacitor falls by 20 times as seen in FIG. 6A-FIG. 6B.

(99) FIG. 7A illustrates the junction temperature of the switches/diodes in the conventional inverter. Signal **702** illustrates the junction temperature of the first switch $S_{\text{sub.1}}$ in the conventional inverter. Signal **704** illustrates the junction temperature of the third switch $S_{\text{sub.3}}$ in the conventional inverter. Signal **706** illustrates the junction temperature of the fifth switch $S_{\text{sub.5}}$ in the conventional inverter. Signal **708** illustrates the junction temperature of the first diode $D_{\text{sub.1}}$ in the conventional inverter. Signal **710** illustrates the junction temperature of the seventh switch $S_{\text{sub.7}}$ in the conventional inverter. Signal **712** illustrates the junction temperature of a first component of the eighth switch $S_{\text{sub.8_1}}$ in the conventional inverter.

(100) FIG. 7B illustrates the junction temperature of the switches/diodes in the circuit **100**. Signal **752** illustrates the junction temperature of the first switch $S_{\text{sub.1}}$ in the circuit **100**. Signal **754** illustrates the junction temperature of the third switch $S_{\text{sub.3}}$ in the circuit **100**. Signal **756** illustrates the junction temperature of the fifth switch $S_{\text{sub.5}}$ in the circuit **100**. Signal **758** illustrates the junction temperature of the seventh switch $S_{\text{sub.7}}$ in the circuit **100**. Signal **760** illustrates the junction temperature of the ninth switch $S_{\text{sub.9}}$ in the circuit **100**. Signal **762** illustrates the junction temperature of the first component of the tenth switch $S_{\text{sub.10_1}}$ in the circuit **100**.

(101) In the present circuit **100**, the switches have low junction temperatures such that the switches can be used for long-duration operation than the conventional inverter. It also ensures that the present circuit **100** performs better in high-temperature conditions than the conventional inverter. The results are shown in FIG. 7A-FIG. 7B.

(102) FIG. 8A illustrates blocking voltage across the switches/diodes in the conventional inverter. Signal **800** illustrates the first switch voltage $V_{\text{sub.s1}}$ and the second switch voltage $V_{\text{sub.s2}}$ in the conventional inverter. Signal **802** illustrates the third switch voltage $V_{\text{sub.s3}}$ and the fourth switch voltage $V_{\text{sub.s4}}$ in the conventional inverter. Signal **804** illustrates the fifth switch voltage $V_{\text{sub.s5}}$ and the sixth switch voltage $V_{\text{sub.s6}}$ in the conventional inverter. Signal **806** illustrates the seventh diode voltage $V_{\text{sub.d7}}$ and the eighth diode voltage $V_{\text{sub.d8}}$ in the conventional inverter. Signal **808** illustrates the ninth switch voltage $V_{\text{sub.s9}}$ and the eleventh switch voltage $V_{\text{sub.s11}}$ in the conventional inverter. Signal **810** illustrates a first component of the tenth switch voltage

V.sub.s10_1 and a second component of the tenth switch voltage V.sub.s10_2 in the conventional inverter.

(103) FIG. 8B illustrates blocking voltage across the switches/diodes in the circuit 100. Signal 850 illustrates the first switch voltage V.sub.s1 and the second switch voltage V.sub.s2 in the circuit 100. Signal 852 illustrates the third switch voltage V.sub.s3 and the fourth switch voltage V.sub.s4 in the circuit 100. Signal 854 illustrates the fifth switch voltage V.sub.s5 and the sixth switch voltage V.sub.s6 in the circuit 100. Signal 856 illustrates the seventh switch voltage V.sub.s7 and the eighth switch voltage V.sub.s8 in the circuit 100. Signal 858 illustrates the ninth switch voltage V.sub.s9 and the eleventh switch voltage V.sub.s11 in the circuit 100. Signal 860 illustrates a first component of the tenth switch voltage V.sub.s10_1 and a second component of the tenth switch voltage V.sub.s10_2 in the circuit 100. In the present circuit 100, although the maximum voltage is blocked by the switch. In an aspect, the maximum voltage is equal to DC source voltage. In an example, some of the switches exhibit lower voltage as shown in FIG. 8A-FIG. 8B.

(104) FIG. 9A illustrates a graph 900 of source current in the conventional inverter. Signal 902 illustrates output current (V.sub.o) in the conventional inverter. FIG. 9B illustrates a graph 950 of source current in the circuit 100. Signal 952 illustrates output current (V.sub.o) in the circuit 100. The low capacitor inrush current leads to low current stress on the source compared to the conventional inverter, as shown in FIG. 9A-FIG. 9B.

(105) In the present circuit 100, the circuit currents are stable and contribute to the reliable operation of the inverter (circuit 100) than the conventional inverter, especially in high-temperature conditions. Using fewer components to produce 11-levels and a reliable performance is a resilient solution for single-phase Solar PV applications to be implemented in high-temperature zones.

(106) Obviously, numerous modifications and variations of the present disclosure are possible in light of the above teachings. It is therefore to be understood that within the scope of the appended claims, the invention may be practiced otherwise than as specifically described herein.

Claims

1. An inverter topology circuit, comprising: a direct current source; a first capacitor; a second capacitor; a first switch, a second switch, a third switch, and a fourth switch, wherein: a first side of the first switch and a first side of the third switch are connected to a first side of the direct current source, while a first side of the second switch and a first side of the fourth switch are connected to a second side of the direct current source; a fifth switch, a sixth switch, a seventh switch, and an eighth switch, wherein: a first side of the fifth switch and a first side of the seventh switch are connected to a second side of the third switch, while a first side of the sixth switch and a first side of the eighth switch are connected to a second side of the fourth switch; a ninth switch, wherein: a first side of the ninth switch, a second side of the sixth switch, and a second side of the seventh switch are connected to a first side of the first capacitor; a tenth switch, wherein: a first side of the tenth switch, a second side of the first capacitor are connected to a first side of the second capacitor; an eleventh switch, wherein: a first side of the eleventh switch, a second side of the fifth switch, and a second side of the eighth switch are connected to a second side of the second capacitor; and the first capacitor and the second capacitor are connected in series and are connected in parallel with the direct current source.

2. The circuit of claim 1, wherein the switches are insulated gate bipolar transistors (IGBTs).

3. The circuit of claim 2, wherein the tenth switch is formed with two IGBTs with the emitters connected in series.

4. The circuit of claim 1, wherein the first capacitor and the second capacitor have a capacitor inrush current of less than 5 amperes at a max capacitance of 1700 μ F and an input voltage to the circuit of 100 V.

5. The circuit of claim 1, wherein the first side of the direct current source is the positive pole, and

the second side of the direct current source is the negative pole.

6. The circuit of claim 1, wherein the first side of the first switch, the third switch, the fifth switch, the eighth switch, the ninth switch, and the second side of the second switch, the fourth switch, the sixth switch, the seventh switch, the eleventh switch are collectors of the switches.

7. The circuit of claim 1, wherein the second side of the first switch, the third switch, the fifth switch, the eighth switch, the ninth switch, and the first side of the second switch, the fourth switch, the sixth switch, the seventh switch, the eleventh switch are emitters of the switches.

8. The circuit of claim 1, wherein the first side of the first capacitor and the second capacitor are anodes of the capacitors.

9. The circuit of claim 1, wherein the second side of the first capacitor and the second capacitor are cathodes of the capacitors.

10. A method for controlling the charging and discharging of a first capacitor and a second capacitor in an inverter, comprising: determining a DC link voltage $V_{sub.dc}$ of the inverter; determining a state of an inverter by a nearest-level control (NLC); determining a direction of current flow; determining a magnitude of an auxiliary DC link voltage; determining a threshold of the auxiliary DC link voltage; in response to the state level being $+V_{sub.dc}/2$, the current flow being positive, and the magnitude of the auxiliary DC link voltage being higher than the threshold, charging the first capacitor and the second capacitor; in response to the state level being $+V_{sub.dc}/2$, the current flow being positive, and the magnitude of the auxiliary DC link voltage being lower than the threshold, discharging the first capacitor and the second capacitor; in response to the state level being $+V_{sub.dc}/2$, the current flow being negative, and the magnitude of the auxiliary DC link voltage being higher than the threshold, charging the first capacitor and the second capacitor; in response to the state level being $+V_{sub.dc}/2$, the current flow being negative, and the magnitude of the auxiliary DC link voltage being lower than the threshold, discharging the first capacitor and the second capacitor; in response to the state level being $-V_{sub.dc}/2$, the current flow being positive, and the magnitude of the auxiliary DC link voltage being higher than the threshold, charging the first capacitor and the second capacitor; in response to the state level being $-V_{sub.dc}/2$, the current flow being positive, and the magnitude of the auxiliary DC link voltage being lower than the threshold, discharging the first capacitor and the second capacitor; in response to the state level being $-V_{sub.dc}/2$, the current flow being negative, and the magnitude of the auxiliary DC link voltage being higher than the threshold, charging the first capacitor and the second capacitor; and in response to the state level being $-V_{sub.dc}/2$, the current flow being negative, and the magnitude of the auxiliary DC link voltage being lower than the threshold, discharging the first capacitor and the second capacitor, wherein the inverter further includes: a direct current source; a first switch, a second switch, a third switch, and a fourth switch, wherein: a first side of the first switch and a first side of the third switch are connected to a first side of the direct current source, while a first side of the second switch and a first side of the fourth switch are connected to a second side of the direct current source; a fifth switch, a sixth switch, a seventh switch and an eighth switch, wherein: a first side of the fifth switch and a first side of the seventh switch are connected to a second side of the third switch, while a first side of the sixth switch and a first side of the eighth switch are connected to a second side of the fourth switch; a ninth switch, wherein: a first side of the ninth switch, a second side of the sixth switch, and a second side of the seventh switch are connected to a first side of the first capacitor; a tenth switch, wherein: a first side of the tenth switch, a second side of the first capacitor are connected to a first side of the second capacitor; an eleventh switch, wherein: a first side of the eleventh switch, a second side of the fifth switch, and a second side of the eighth switch are connected to a second side of the second capacitor; and the first capacitor and the second capacitor are connected in series and are connected in parallel with the direct current source.

11. The method of claim 10, wherein the threshold of the auxiliary DC link voltage is 50V.

12. The method of claim 10, wherein the switches are insulated gate bipolar transistors (IGBTs).

13. The method of claim 12, wherein the tenth switch includes two IGBTs with the emitters connected in series.
 14. The method of claim 10, wherein the first capacitor and the second capacitor have a capacitor inrush current of less than 5 amperes at a max capacitance of 1700 μ F and an input voltage to the circuit of 100 V.
 15. The method of claim 10, wherein the first side of the direct current source is the positive pole, and the second side of the direct current source is the negative pole.
 16. The method of claim 10, wherein the first side of the first switch, the third switch, the fifth switch, the eighth switch, the ninth switch, and the second side of the second switch, the fourth switch, the sixth switch, the seventh switch, the eleventh switch are collectors of the switches.
 17. The method of claim 10, wherein the second side of the first switch, the third switch, the fifth switch, the eighth switch, the ninth switch, and the first side of the second switch, the fourth switch, the sixth switch, the seventh switch, the eleventh switch are emitters of the switches.
 18. The method of claim 10, wherein the first side of the first capacitor and the second capacitor are anodes of the capacitors.
 19. The method of claim 10, wherein the second side of the first capacitor and the second capacitor are cathodes of the capacitors.
-