

US Patent & Trademark Office

Patent Public Search | Text View

United States Patent Application Publication

20250281766

Kind Code

A1

Publication Date

September 11, 2025

Inventor(s)

WANG; TING-WEI et al.

CARDIAC STIMULATION DEVICE

Abstract

The cardiac stimulation device includes a sensing module and a stimulation module. The sensing module is configured to measure at least one cardiac state of a subject. The stimulation module is coupled to the sensing module. The stimulation module includes a stimulation emitting coil, a stimulation control circuit and a stimulation receiver. The stimulation control circuit is coupled to the stimulation emitting coil. The stimulation control circuit is configured to drive the stimulation emitting coil to emit a stimulation electromagnetic signal based on the at least one cardiac state. The stimulation receiver includes a stimulation receiving coil and a stimulation electrode. The stimulation receiving coil is configured to receive the stimulation electromagnetic signal to generate a stimulation voltage provided to the stimulation electrode. The stimulation electrode is arranged at a cardiac stimulation area of the subject. The stimulation voltage is provided to the cardiac stimulation area through the stimulation electrode.

Inventors: WANG; TING-WEI (Hsinchu City, TW), LYU; EN-ZHU (Hsinchu City, TW)

Applicant: NATIONAL TSING HUA UNIVERSITY (Hsinchu City, TW)

Family ID: 1000008319807

Assignee: NATIONAL TSING HUA UNIVERSITY (Hsinchu City, TW)

Appl. No.: 18/971980

Filed: December 06, 2024

Foreign Application Priority Data

TW

113108122

Mar. 06, 2024

Publication Classification

Int. Cl.: A61N1/40 (20060101); A61N1/365 (20060101)

Background/Summary

FIELD OF THE INVENTION

[0001] The present invention relates to a cardiac stimulation device; in particular, a cardiac stimulation device which is configured to stimulate the heart with voltage through an electromagnetic induction.

BACKGROUND OF THE INVENTION

[0002] For patients suffer from abnormal heart rhythm, cardiac stimulation devices for regulating heart rhythm can effectively manage and regulate the patient's heart rhythm. In general, conventional cardiac stimulation devices provide auxiliary stimulation to patients' heart by monitoring their cardiac state in real-time. For example, if detected an abnormal cardiac state such as arrhythmia, bradycardia, or atrial fibrillation, the cardiac stimulation device will immediately provide electrical stimulation to the patient's heart. The cardiac stimulation device provides a preventive effect on atrial fibrillation caused by partial bradycardia, and reduces the frequency or duration for happening symptoms. Therefore, the cardiac stimulation device improves the quality of life of patients and avoiding the risk of related heart diseases or fatal heart disease attacks.

[0003] However, the conventional cardiac stimulation devices require a persistent and uninterrupted power supply to ensure a long-term continuous operation. When the cardiac stimulation device fails to operate stably for a long time, it will greatly affect the patient's life. Although a long-lasting battery set and/or a low-power configuration will extend the durability of the cardiac stimulation devices, the cardiac stimulation device can only operate stably for about ten years at most, and the battery installed inside the cardiac stimulation device still need to be replaced to extend the service time before the expiration date. In terms of battery replacement, patients must take the risk for the secondary surgery to replace the battery, which not only increases the risk of infection, but also has incalculable effects on the patient's physical and mental health during or after the secondary surgery. In addition, multiple surgeries will also increase the medical expenses that patients need to bear.

[0004] In addition, the conventional cardiac stimulation devices still face many hardware challenges that need to be overcome or optimized. For example, the built-in battery may result in a larger volume, and the structural rigidity or additional weight of the conventional cardiac stimulation device may cause discomfort to the subject.

[0005] Accordingly, there are still issues for improving in the field, such as battery life and hardware, that need to be overcome and resolved in the cardiac stimulation devices applied for regulating heart rhythm.

SUMMARY OF THE INVENTION

[0006] Therefore, the present invention provides a cardiac stimulation device to effectively solve the problems encountered in the conventional cardiac stimulation devices.

[0007] One of the objects of the present invention is to provide a cardiac stimulation device that does not require battery replacement, which reducing the inconvenience of the secondary surgery for battery replacement.

[0008] One of the objects of the present invention is to provide a cardiac stimulation device providing a better wearing experience and less hardware limitations to patients than the conventional cardiac stimulation device.

[0009] The present invention provides a cardiac stimulation device. The cardiac stimulation device

includes a sensing module and a stimulation module. The sensing module is configured to measure at least one cardiac state of a subject. The stimulation module is coupled to the sensing module. The stimulation module includes a stimulation emitting coil, a stimulation control circuit and a stimulation receiver. The stimulation control circuit is coupled to the stimulation emitting coil. Wherein the stimulation control circuit is configured to drive the stimulation emitting coil to emit a stimulation electromagnetic signal based on the at least one cardiac state. The stimulation receiver includes a stimulation receiving coil and a stimulation electrode. Wherein the stimulation receiving coil is configured to receive the stimulation electromagnetic signal to generate a stimulation voltage provided to the stimulation electrode. Wherein the stimulation electrode is arranged at a cardiac stimulation area of the subject. And wherein the stimulation voltage is provided to the cardiac stimulation area through the stimulation electrode.

[0010] In an embodiment, the sensing module further includes a sensing emitting coil and a sensing electrode, wherein the sensing receiving coil is coupled to the sensing electrode, and configured to receive the sensing electromagnetic signal and generate the feedback electromagnetic signal.

Wherein the sensing electrode is arranged at a cardiac sensing area of the subject. And wherein the sensing electrode is configured to adjust at least one electrical parameter of the sensing receiving coil for generating the feedback electromagnetic signal based on the at least one cardiac state.

[0011] In an embodiment, the sensing electrode includes a first electrode and a second electrode; and wherein a gap is formed between the first electrode and the second electrode, and the gap is varied by the at least one cardiac state.

[0012] In an embodiment, the first electrode and the second electrode form an interdigital electrode.

[0013] In an embodiment, the sensing control circuit includes a frequency adjustment unit coupled to the sensing emitting coil; and wherein frequency adjustment unit is configured to adjust a frequency of the sensing electromagnetic signal.

[0014] In an embodiment, the frequency adjustment unit includes a capacitor array configured to adjust an impedance of the sensing emitting coil.

[0015] In an embodiment, the sensing module further includes a shielding component at least arranged at a first side of the sensing emitting coil. Wherein the shielding component at least shields a portion of the sensing electromagnetic signal emitted toward to a first direction.

[0016] In an embodiment, the stimulation control circuit includes a discharge controller, a discharge controller configured to provide a control signal based on the at least one cardiac state, a storage capacitor configured to storage a driving voltage, and a switch configured to receive the control signal and enable transmitting the driving voltage to the stimulation emitting coil based on the control signal.

[0017] In an embodiment, the stimulation control circuit further includes a boost circuit configured to receive a supply voltage and boost the supplied power to the driving voltage.

[0018] In an embodiment, the cardiac stimulation device further includes a control module configured to receive the at least one cardiac state and provide a control signal to the stimulation module. Wherein the stimulation module is configured to emit the stimulation electromagnetic signal based on the control signal

[0019] In summary, the cardiac stimulation device of the present invention has a stimulation module. The stimulation module provides stimulation electromagnetic signal from outside to the subject's body to generate a stimulation voltage through the stimulation receiving coil by receiving the stimulation electromagnetic signal. The stimulation voltage is provided by a stimulation electrode and used to stimulate a specific cardiac area of the subject by connecting the stimulation electrode to the stimulation receiving coil and fixing the stimulation electrode at the specific cardiac area. The stimulation module of the cardiac stimulation device provides the function of cardiac regulation. In addition, the cardiac stimulation device of the present invention measures the cardiac state through the sensing module and wirelessly and remotely deliver the stimulation

voltage required for cardiac stimulation and regulation through the stimulation module. Accordingly, the cardiac stimulation device achieves an implantable cardiac stimulation in the patient's body without installing any batteries.

Description

BRIEF DESCRIPTION OF THE DRAWINGS

[0020] The accompanying drawings are presented to aid in the description of various aspects of the disclosure and are provided solely for illustration of the aspects. To simplify the drawings and highlight the contents to be presented in the drawings, the well-known structures or elements in the drawings may be drawn in a simple schematic manner or presented in an omitted manner. For example, the number of elements may be singular or plural. These drawings are provided only to explain these aspects and not to limit thereof.

[0021] FIG. 1 is a schematic diagram of the cardiac stimulation device according to an embodiment of the present invention.

[0022] FIGS. 2A to 2B are block diagrams of the stimulation module according to an embodiment of the present invention.

[0023] FIG. 3 is a schematic diagram of a cardiac stimulation device with a control module according to an embodiment of the present invention.

[0024] FIG. 4 is a schematic diagram of a sensing module using eddy current induction according to one embodiment of the present invention.

[0025] FIG. 5 is a schematic diagram of a sensing receiving coil and a sensing electrode according to an embodiment of the present invention.

[0026] FIGS. 6A and 6B are schematic diagrams of different settings of the sensing electrodes according to an embodiment of the present invention.

DETAILED DESCRIPTION OF THE PREFERRED EMBODIMENTS

[0027] Even though the terms such as “first”, “second”, and “third” may be used to describe an element, a part, a region, a layer, and/or a portion in the present specification, these elements, parts, regions, layers and/or portions are not limited by such terms. Such terms are used to differentiate an element, a part, a region, a layer, and/or a portion from another element, part, region, layer, and/or portion. Therefore, in the following discussions, a first element, portion, region, or portion may be called a second element, portion, region, layer, or portion, and do not depart from the teaching of the present disclosure. The terms “comprise,” “include”, or “have” used in the present specification are open-ended terms and mean to “include”, but not limited to

[0028] As used herein, the term “coupled to” in the various tenses of the verb “couple” may mean that element A is directly connected to element B or that other elements may be connected between elements A and B (i.e., that element A is indirectly connected with element B).

[0029] The terms “approximate” or “essentially” used in the present specification include the value itself and the average values within the acceptable range of deviation of the specific values confirmed by a person having ordinary skill in the current art, considering the specific measurement discussed and the number of errors related to such measurement (that is, the limitation of the measurement system). For example, “about” may mean within one or more standard deviations of the value itself or +30%, +20%, +10%, +5%. In addition, “about”, “approximate”, or “essentially” used in the present specification may select a more acceptable range of deviation or standard deviation based on optical property, etching property, or other properties. One cannot apply one standard deviation to all properties.

[0030] The present invention provides a cardiac stimulation device. The cardiac stimulation device includes a sensing module configured to measure at least one cardiac state of a subject, and a stimulation module coupled to the sensing module. The stimulation module includes a stimulation

emitting coil, a stimulation control circuit coupled to the stimulation emitting coil, and a stimulation receiver having a stimulation receiving coil and a stimulation electrode. The stimulation module provides the stimulation electromagnetic signal from the outside of the subject's body. The stimulation receiving coil receives the stimulation electromagnetic signal, and converts the stimulation electromagnetic signal to a stimulation power by magneto-electric effect. The stimulation power is delivered by the stimulation electrode arranged at the subject's heart to stimulate a specific cardiac area of the subject's heart and regulate the cardiac state. The stimulation power used for stimulating is wirelessly delivered to the specific cardiac area through the stimulation module for cardiac stimulation. Therefore, the cardiac stimulation device achieves implantable cardiac stimulation in subject's body without the need to install any batteries inside the subject's body.

[0031] Specifically, referring to FIG. 1, which illustrates that a cardiac stimulation device **100** includes a sensing module **110** configured to measure at least one cardiac state (CS) of a subject, and a stimulation module **120** coupled to the sensing module **110**. The stimulation module **120** includes a stimulation emitting coil **121**, a stimulation control circuit **122** coupled to the stimulation emitting coil **121**, and a stimulation receiver **123** having a stimulation receiving coil **1231** and a stimulation electrode **1232**. The stimulation control circuit **122** is configured to drive the stimulation emitting coil **121** to emit a stimulation electromagnetic signal (MS1) based on the at least one cardiac state (CS). The stimulation receiving coil **1231** receives the stimulation electromagnetic signal (MS1) and generates a stimulation voltage (SV) provided to the stimulation electrode **1232**. The stimulation electrode **1232** is arranged at a cardiac stimulation area (SA) of the subject. The stimulation voltage (SV) is provided to the cardiac stimulation area (SA) through the stimulation electrode **1232**.

[0032] The stimulation module **120** is configured to stimulate the heart of the subject by using electromagnetic induction. The stimulation module **120** may be divided into two main parts. One of the two main parts includes the stimulation emitting coil **121** arranged outside the subject's body (such as skin surface) and the stimulation control circuit **122** coupled to the stimulation emitting coil **121**, and the other includes the stimulation receiver **123** arranged on the subject or implanted in the subject. The stimulation control circuit **122** provides a stimulation electrical signal (ES1) (preferably a pulse electrical signal) to the stimulation emitting coil **121**. The stimulation emitting coil **121** converts the stimulation electrical signal (ES1) into a stimulation electromagnetic signal (EMS1) based on the electromagnetic effect and provides the stimulation electromagnetic signal (EMS1) to the stimulation receiving coil **1231** of the stimulation receiver **123**. The stimulation receiving coil **1231** converts the stimulation electromagnetic signal (EMS1) into the stimulation voltage (SV) based on the magneto-electric effect and provides the stimulation voltage (SV) to the stimulation electrode **1232**.

[0033] The stimulation control circuit **122** is coupled to the sensing module **110** and receives signals represented as the at least one cardiac state (CS) measured by the sensing module **110**. The cardiac state (CS) referred to in the present invention is, for example, the cardiac operating state observed by measuring cardiac electrical signals, atrial or ventricular blood flow signals, pulse signals, or other cardiac state (CS) indicators through the sensing module **110**. When the at least one cardiac state (CS) of the subject reaches the level where the heart rhythm needs to be adjusted or regulated, the stimulation control circuit **122** will output the stimulation electrical signal (ES1) for subsequent cardiac stimulation. After stimulation, the subject's cardiac state (CS) is continuously observed by the sensing module **110**, and the stimulation control circuit **122** will evaluate whether to continue the next stimulation or complete the stimulation according to the observed cardiac state (CS).

[0034] The stimulation control circuit **122** can be composed by any means that provides the stimulation electrical signal (ES1). In an embodiment, the stimulation control circuit **122** is preferably configured to provide pulse electrical signals. In the embodiment, referring to FIG. 2A,

the stimulation control circuit **122** includes a discharge controller **1221**, a storage capacitor **1222** and a switch **1223**. The discharge controller **1221** is configured to provide a control signal based on the at least one cardiac state (CS). The storage capacitor **1222** is configured to store the driving voltage (Vc). The switch **1223** is configured to receive the control signal and transmit the driving voltage (Vc) to the stimulation emitting coil **121** based on the control signal. When the discharge controller **1221** (e.g. microcontroller) determined that the subject's heart requiring to be stimulated based on the current cardiac state (CS), the discharge controller **1221** will provide a stimulation instruction (SI) to the switch **1223** (e.g. transistor switch, or switch). After the switch **1223** is turned on, a conductive path is formed among the storage capacitor **1222** and the stimulation emitting coil **121**. The driving voltage (Vc) stored in the storage capacitor **1222** can be provided to the stimulation emitting coil **121**. The driving voltage (Vc) generates an RLC transient response on the stimulation emitting coil **121** to generate the stimulation electromagnetic signal (MS1). The current relationship between the storage capacitor **1222** and the stimulation emitting coil **121** during discharge can be expressed by the following formula:

$$[00001] I(t) = \frac{V_c}{L} e^{-t} \sin t$$

From the above formula, it can be known that the value of current I(t) is proportional to the driving voltage (Vc) and inversely proportional to the inductance value (L) of the stimulation emitting coil **121**. Therefore, the current I(t) can be adjusted by adjusting the driving voltage (Vc), the inductance value (L) of the stimulation emitting coil **121**, or the opening time of the switch **1223** to adjust the stimulation electromagnetic signal (EMS1) output by the stimulation emitting coil **121**. [0035] In an embodiment, referring to FIG. 2B, the stimulation control circuit **122** further includes a boost circuit **1224**. The boost circuit **1224** is configured to receive a supply voltage and boost the supply voltage to the driving voltage (Vc). For example, the boost circuit **1224** can boost the supply voltage (PV) (e.g. 5V) supplied by an external power supply circuit. The boosted voltage (i.e. the driving voltage (Vc)) is stored by the storage capacitor **1222**. In this way, the driving voltage (Vc) stored in the storage capacitor **1222** can be regulated or amplified by the boost circuit **1224**, and lower supply voltages (such as the voltage provided by the discharge controller **1221**) can also be used without the need for additional power supply. It should be noted that FIG. 2B illustrates only an example implementation means for the power supply of the boost circuit **1224** provided by the discharge controller **1221**, the present invention is not limited to the example shown in FIG. 2B. In other words, the boost circuit **1224** can also derive power from other voltage sources.

[0036] In an embodiment, referring to FIG. 3, the cardiac stimulation device **100** further includes a control module **130**. The control module **130** is configured to receive the at least one cardiac state (CS) and provide a control signal to the stimulation module **120**. The stimulation module **120** emits the stimulation electromagnetic signal (EMS1) based on the control signal. Specifically, the control module **130** is an independent component coupled to the stimulation module **120** and the sensing module **110**. Hence, the control module **130** may be computing capable components such as microprocessors, FPGAs, smartphones, tablets, etc. It should be noted that the control module **130** shown in FIG. 3 is not mutually exclusive with the embodiments shown in FIG. 2A or FIG. 2B. For example, the control module **130** may be configured to provide the stimulation instruction (SI) to the discharge controller **1221** and control the switch **1223** through the discharge controller **1221**. On the other hand, the control module **130** can also be configured to directly provide the stimulation instruction (SI) required by the switch **1223** to the switch **1223**. Hence, the control module **130** directly controls the conductive path among the switch **1223** and the stimulation emitting coil **121**. In addition, the control module **130** may be configured to provide the stimulation instruction (SI) to the stimulation module **120** based on the cardiac state (CS) provided by the sensing module **110**. The control module **130** can be served as an intermediate medium between the sensing module **110** and the stimulation module **120**. The control module **130** can be selected based on the computational complexity of the cardiac state (CS) to avoid mismatches caused by different

signal types or computational requirements between the sensing module **110** and the stimulation module **120**.

[0037] In an embodiment, the discharge controller **1221** or the control module **130** can be configured to adjust the activation frequency or duty cycle of the switch **1223** or the duration of a stimulation based on the current cardiac state (CS) of the subject or the feedback cardiac state (CS) after the stimulation. On the other hand, in an embodiment, the discharge controller **1221** or the control module **130** can also be configured to adjust the driving voltage (V_c) stored in the storage capacitor **1222**. With the discharge controller **1221** or the control module **130**, the cardiac stimulation device **100** can provide stimulation electromagnetic signals with different intensities, frequencies, or emitting modes, and achieve a proper or best stimulation effect for different subjects or different cardiovascular states.

[0038] The present invention is not limited to the formation of the stimulation emitting coil **121** and/or the stimulation receiving coil **1231**. The stimulation emitting coil **121** and/or the stimulation receiving coil **1231** can be formed on a substrate (preferably a flexible substrate) through a conductor line(s) formed as a radiation path to emit the electromagnetic signals. In a further embodiment, the stimulation emitting coil **121** and/or the stimulation receiving coil **1231** can be formed as a single turn coil, a multi-turn coil, a spiral coil, a concentric circle coil, or any other means for radiating by enameled wires or conductors with or without the substrate. Moreover, the stimulation emitting coil **121** and the stimulation receiving coil **1231** are not limited to having the same coil parameters. For example, different turns can be selected to adjust the ratio of the stimulation electrical signal (ES₁) to the stimulation voltage (SV), but not limited to this.

[0039] The present invention does not limit the arranging location of the stimulation receiving coil **1231**. The stimulation receiving coil **1231** can be arranged on the skin, subcutaneously, on outside of the heart, or any locations suitable for receiving the stimulation electromagnetic signal (MS₁). For example, the arranging location of the stimulation receiving coil **1231** may refer to the arranging location for implantable defibrillators (ICD) in conventional technology to arrange at the subcutaneous position of the left anterior chest. The stimulation receiving coil **1231** is coupled to the stimulation electrode **1232** through a conductor line(s). Therefore, the stimulation electrode **1232** can be arranged on the cardiac stimulation area (SA) away or closed to the stimulation receiving coil **1231**. The cardiac stimulation area (SA) can be any position of the subject's heart that can be stimulated, such as the arranging location for a conventional electrode setup of implantable defibrillators. With the stimulation electrode **1232**, the cardiac stimulation device **100** can provide an electrical stimulation for the subject's heart and effectively control the rhythm or the ventricular rate of the subject's heart.

[0040] The pairing between the stimulation electrode **1232** and the stimulation receiving coil **1231** of the present invention is not limited to one-to-one. For example, a stimulation receiving coil **1231** may correspond to multiple stimulation electrodes **1232**. Thus, the multiple stimulation electrodes **1232** can stimulate multiple position of the subject's heart simultaneously or in sequence. On the other hand, a plurality of the stimulation receiving coils **1231** can correspond to multiple stimulation electrodes **1232**, so that each stimulation position can be independently provided with a specific stimulation voltage (SV). In addition, the stimulation emitting coil **121** corresponding to the stimulation receiving coil **1231** can also be configured in a one-to-one, many to one, or many to many. Through the above configuration, the selectivity of setting the stimulation position and stimulation electromagnetic signal (EMS₁) can be improved. The stimulation emitting coil **121** can also limit the divergence of the stimulation electromagnetic signal (MS₁) through a shielding component. For example, a shielding component can be set around the stimulation emitting coil **121** to block the stimulation electromagnetic signal (MS₁) and reduce the risk of affecting other circuit components, medical devices, or other stimulation emitting coils **121** (if there are multiple stimulation emitting coils).

[0041] In summary, the stimulation receiving coil **1231** is configured to receive the stimulation

electromagnetic signal (EMS1) from the stimulation emitting coil **121** to generate the stimulation voltage (SV). The stimulation electrode **1232** is configured to provide the stimulation voltage (SV) to the cardiac stimulation area (SA) of the subject's heart. The stimulation receiving coil **1231** and the stimulation electrode **1232** arranged on/in the subject are both composed by passive components operating without power supply. The generation of stimulation voltage (SV) is achieved through an external stimulation electromagnetic signal (EMS1), and the requirement of the battery or the power supply is limited to the stimulation module **120** and/or the sensing module **110** arranged outside the subject. Therefore, the subject is free to the need to replace the power supply or the battery for the stimulation receiving coil **1231** and the stimulation electrode **1232**. It can effectively reduce the discomfort and risk of subject for replacing batteries inside the subject's body.

[0042] It should be noted that the sensing module **110** is not limited to the sensing mechanism. For example, the sensing module **110** may be configured to measure the at least one cardiac state (CS) of the subject by using principles such as acoustics, optics, electricity, or magnetism. In a specific embodiment, the sensing module **110** is configured to measure the at least one cardiac state (CS) through eddy current induction. Specifically, referring to FIG. 4, the sensing module **110** includes a sensing emitting coil **111** and a sensing control circuit **112** coupled to the sensing emitting coil **111**. The sensing control circuit **112** is configured to drive the sensing emitting coil **111** to emit a sensing electromagnetic signal (EMS2) to the heart position of the subject, and receive a sensing signal, generated by a feedback electromagnetic signal (EMS3) from the heart position, from the sensing emitting coil **111**. Wherein the feedback electromagnetic signal (EMS3) is induced by the sensing electromagnetic signal (EMS2) at the heart position. The sensing control circuit **112** is further configured to calculate and determine the at least one cardiac state (CS) based on the sensing signal.

[0043] In the embodiment, the sensing emitting coil **111** can be any radiator that can emit electromagnetic waves. The present invention does not limit the structure, shape, or material for the sensing emitting coil **111**. The sensing control circuit **112** is configured to provide an AC signal to the sensing emitting coil **111** to cause the sensing emitting coil **111** to emit the sensing electromagnetic signal (EMS2). When the sensing electromagnetic signal (EMS2) is transmitted to the heart of the subject, the ionic liquids (such as blood inside the heart) can be considered as a planar conductor. When the planar conductor received the sensing electromagnetic signal (EMS2), the planar conductor will be induced and generate eddy currents. The generation of eddy current will generate the feedback electromagnetic signal (EMS3) at the planar conductor and feedback to the sensing emitting coil **111**. Thus, the sensing emitting coil **111** receives the feedback electromagnetic signal (EMS3) and generates the sensing signal. It should be noted that the present invention is not limited to the form or type of the sensing signal. For example, the feedback electromagnetic signal (EMS3) causes a change in the measured inductance value of the sensing emitting coil **111**, the measured inductance value can be considered as a sensing signal by measuring the change in inductance value of the sensing emitting coil **111**. On the other hand, the frequency or amplitude of the feedback electromagnetic signal (EMS3), or the frequency or phase change between the sensing electromagnetic signal (EMS2) and the feedback electromagnetic signal (EMS3) can also be considered as a sensing signal. The sensing signal can be analyzed by the sensing module **110** to obtain the at least one cardiac state (CS).

[0044] The at least one cardiac state (CS) of the present invention can be a heart rhythm or a ventricular tachycardia. Specifically, when the heart is pumping, the volume of blood in the atria or ventricles is changed with the contraction or relaxation of the heart. The volume change of blood in the atrium or ventricle will cause changes in the impedance, area, or other parameters of the planar conductor for inducing the eddy current. Therefore, different sensing signals can be used to determine the subject's heart rate, ventricular tachycardia, or other related cardiac states.

[0045] With the sensing module **110** measuring the cardiac state (CS) by using eddy current

induction, it is possible to measure the cardiac state (CS) in a non-contact and a non-invasive manner. Hence, the sensing module **110** can be arranged outside the subject's body through means such as wearing. Comparing to a conventional implanted sensing mechanism, the sensing module **110** is less restricted by replacement or supplement of power required for sensing the cardiac state (CS). Therefore, the subject does not need to replace the power supply for sensing module **110**. It can effectively reduce the discomfort and risk for subject to replace batteries.

[0046] In the embodiment of the sensing module **110** with the eddy current induction, the sensitivity of the eddy current to cardiac state (CS) can be further optimized by setting a sensing receiving coil corresponding to the induction transmitting coil. Specifically, referring to FIG. 5, the sensing module **110** further includes a sensing receiving coil **113** and a sensing electrode **114**. The sensing receiving coil **113** is coupled to the sensing electrode **114** and configured to receive the sensing electromagnetic signal (EMS2) to generate the feedback electromagnetic signal (EMS3). Wherein the sensing electrode **114** is arranged at a cardiac sensing area of the subject, and is configured to adjust at least one electrical parameter of the sensing receiving coil **113** for generating the feedback electromagnetic signal (EMS3) according to the at least one cardiac state (CS).

[0047] The sensing receiving coil **113** is considered as a component for generating mutual inductance to replace the ionic liquid as blood. When the sensing receiving coil **113** received the sensing electromagnetic signal (EMS2) from the sensing emitting coil **111**, the sensing receiving coil **113** generates the corresponding feedback electromagnetic signal (EMS3). The sensing receiving coil **113** ensures the consistency of a location of the signal source, a frequency of the signal, and other parameters of the feedback electromagnetic signal (EMS3), thereby improving the sensing sensitivity or facilitating or simplifying the subsequent signal processing.

[0048] The sensing electrode **114** is arranged to be attached on the cardiac sensing areas that reflect heartbeats, such as the heart or near the heart. When the heart beats, the sensing electrode **114** will sense the heartbeat and accordingly change the electrical parameters such as impedance, capacitance, or inductance of the sensing electrode **114**. Due to the sensing electrode **114** is electrically coupled to the sensing receiving coil **113**, when the electrical parameters of the sensing electrode **114** changed due to the cardiac state (CS) (such as heart beats), the equivalent circuits of the sensing electrode **114** and the sensing receiving coil **113** will also change accordingly. The change will modulate the feedback electromagnetic signal (EMS3) generated in response to the sensing electromagnetic signal (EMS2). The modulated level (such as frequency or amplitude) of the feedback electromagnetic signal (EMS3) can be used to determine the cardiac state (CS) of the subject.

[0049] In an embodiment, referring to FIG. 6A, the sensing electrode **114** includes a first electrode **1141** and a second electrode **1142**. The gap (d) between the first electrode **1141** and the second electrode **1142** is varied with the at least one cardiac state (CS). The gap (d) between the first electrode **1141** and the second electrode **1142** will change due to heartbeats, which will alter the capacitance value of the sensing electrode **114** or the dielectric value between first electrode **1141** and the second electrode **1142**. The first electrodes **1141** and the second electrodes **1142** effectively reflect the cardiac state (CS). In a further example of the embodiment, referring to FIG. 6B, the first electrode **1141** and the second electrode **1142** are preferably formed as an interdigital electrode. The interdigital electrode may be referred to a comb-like structure or a finger-like structure arranged alternately with each other formed by the first electrode **1141** and second electrode **1142**. By setting the interdigital electrode, the capacitance characteristics of the sensing electrode **114** can be further enhanced, and it can be more sensitive to the cardiac state (CS) such as heartbeats. It should be noted that the present invention is not limited to the formation of interdigital electrode, and any prior art form of interdigital electrode can be applied to the sensing electrode **114** of the present invention.

[0050] It should be noted that the sensing mechanism of the sensing electrode **114** is not limited to

changes in gap distance. In an example, the sensing mechanism of the sensing electrode **114** can be measuring the electrical parameters changed by sensing the electrical signal of the cardiac state (CS). Specifically, the electrical signals of the cardiac state (CS) include nerve conduction signals, cardiac muscle discharge signals, or sinoatrial electrical signals. By using the sensing electrode **114** and the sensing receiving coil **113**, the sensitivity of the eddy current measurement to the cardiac state (CS) can be improved, and the signal-to-noise ratio can be enhanced. For the sensing electrode **114** and the sensing receiving coil **113** installed inside the subject, an active power source is not required. The sensing electrode **114** and the sensing receiving coil **113** are passively changing the electrical parameters by the cardiac state (CS) and passively induced by the sensing electromagnetic signal (EMS2). The changed electrical parameters will be measured by the sensing module **110** arranged outside the subject's body. There is no need to burden the subject with the risk of replacing the sensing electrode **114** and the sensing receiving coil **113** or the battery for the sensing electrode **114** and the sensing receiving coil **113**.

[0051] The corresponding number of the sensing electrode **114** of the sensing module **110** and the sensing receiving coil **113** in the embodiment is not limited to one-to-one. For example, one sensing receiving coil **113** may be correspond to multiple sensing electrodes **114**. This allows for simultaneous measurement of the cardiac state (CS) for multiple positions of heart. On the other hand, multiple sensing receiving coils **113** may be correspond to multiple sensing electrodes **114**, so that each sensing position can be independently measured. In addition, the sensing emitting coil **111** corresponding to the sensing receiving coil **113** can also be configured as one-to-one, many to one, or many to many with the sensing receiving coil **113**. Through the above configuration, the selectivity for setting the sensing position and for the sensing electromagnetic signal (EMS2) can be improved. The divergence of sensing electromagnetic signal (EMS2) emitted by the sensing emitting coil **111** can be limited by a shielding component. For example, the shielding component can be set around the sensing emitting coil **111** to block the sensing electromagnetic signal (EMS2) and reduce the risk of affecting other circuit components, medical devices, or other sensing emitting coils **111** (if there are multiple sensing emitting coils **111**).

[0052] For different subjects, the skin thickness, heart depth, and placement of the receiving coil may lead to differences efficiency in a cardiac stimulation or a cardiac state (CS) measurement. Therefore, the sensing module **110** or the stimulation module **120** can be configured to provide sensing electromagnetic signal (EMS2) or stimulation electromagnetic signal (EMS1) with different signal parameters (e.g. frequency) for different subjects. For example, the sensing module **110** or the stimulation module **120** may be configured to obtain the optimal response parameter settings based on the sensing electromagnetic signal (EMS2) or the stimulation electromagnetic signal (EMS1) with different signal parameters. In the configuration, for example, the electrical parameters of the sensing emitting coil **111** or the stimulation emitting coil **121** can be adjusted by adjustable passive components (such as capacitors), so that when the sensing emitting coil **111** or the stimulation emitting coil **121** received the an electrical signal for emitting, the sensing emitting coil **111** or the stimulation emitting coil **121** with different electrical parameters will emit different signal parameters of the stimulation electromagnetic signal (EMS1) or the sensing electromagnetic signal (EMS2). The adjustable passive components can be selected by a switch **1223** in an array manner, but are not limited to. On the other hand, the signal parameters of the electrical signal provided to the stimulation emitting coil **121** or the sensing emitting coil **111** can also be directly modulated to provide different signal parameters of the sensing electromagnetic signal (EMS2) or the stimulation electromagnetic signal (EMS1). By providing optimal response parameter settings, the measurements or the stimulation can be effectively taken to a target depth or a target location. It reduces the risk of sensing or stimulation failure or subject harm caused by excessive or insufficient energy.

[0053] In an embodiment, the sensing receiving coil **113** or the stimulation receiving coil **1231** of the present invention can be sealed with a sealing material because the sensing receiving coil **113** or

the stimulation receiving coil **1231** does not require battery replacement and can be activated by the magneto-electric effect. The material selection limitation is less for the sealed sensing receiving coil **113** or stimulation receiving coil **1231**. Therefore, the materials for the sensing receiving coil **113** or the stimulation receiving coil **1231** are widely selected. The sealing material may select from high biocompatibility (such as PDMS) and arranged outside layer of the sealed sensing receiving coil **113** or stimulation receiving coil **1231** for sealing. The electrical safety and biocompatibility of the sensing receiving coil **113** or the stimulation receiving coil **1231** can be improved through the sealing materials. Furthermore, the sealing materials avoids adverse reactions such as rejection in subject's body after implantation of the sensing receiving coil **113** or the stimulation receiving coil **1231**.

[0054] In summary, the cardiac stimulation device **100** of the present invention includes the stimulation module **120**. The stimulation module **120** stimulates a specific area(s) of the subject's heart by providing the stimulation electromagnetic signal (EMS1) from outside the patient's body. The stimulation electromagnetic signal (EMS1) causes the stimulation receiving coil **1231** to generate the stimulation voltage (SV). The stimulation electrode **1232** arranged at the subject's heart provides the stimulation voltage (SV) to the subject's heart to achieve the function of the cardiac regulation, the cardiac stimulation device **100** of the present invention further includes the sensing module **110**. The sensing module **110** can be configured to measure the cardiac state (CS) based on eddy current induction. Accordingly, the cardiac stimulation device **100** of the present invention provides a non-contact measurement and a non-contact stimulation can be achieved. In addition, the stimulation receiving coil **1231** or the sensing receiving coil **113** installed in the patient's body does not require battery. Therefore, it is possible to achieve implantable cardiac stimulation and state measurement without installing any batteries in the patient's body.

[0055] The foregoing disclosure is merely preferred embodiments of the present invention and is not intended to limit the claims of the present invention. Any equivalent technical variation of the description and drawings of the present invention of the present shall be within the scope of the claims of the present invention.

Claims

1. A cardiac stimulation device, comprising: a sensing module configured to measure at least one cardiac state of a subject; and a stimulation module coupled to the sensing module, including: a stimulation emitting coil; a stimulation control circuit coupled to the stimulation emitting coil; wherein the stimulation control circuit is configured to drive the stimulation emitting coil to emit a stimulation electromagnetic signal based on the at least one cardiac state; and a stimulation receiver including a stimulation receiving coil and a stimulation electrode; wherein the stimulation receiving coil is configured to receive the stimulation electromagnetic signal to generate a stimulation voltage provided to the stimulation electrode; wherein the stimulation electrode is arranged at a cardiac stimulation area of the subject; and wherein the stimulation voltage is provided to the cardiac stimulation area through the stimulation electrode.
2. The cardiac stimulation device of claim 1, wherein the sensing module includes: a sensing emitting coil; and a sensing control circuit coupled to the sensing emitting coil; wherein the sensing control circuit is configured to drive the sensing emitting coil to emit a sensing electromagnetic signal to the subject's cardiac position, and receive a first inductive signal induced by a feedback electromagnetic signal; and wherein the sensing control circuit is further configured to determine the at least one cardiac state based on the first inductive signal.
3. The cardiac stimulation device of claim 2, wherein the sensing module further includes: a sensing receiving coil; and a sensing electrode; wherein the sensing receiving coil is coupled to the sensing electrode, and configured to receive the sensing electromagnetic signal and generate the feedback electromagnetic signal; wherein the sensing electrode is arranged at a cardiac sensing area

- of the subject; and wherein the sensing electrode is configured to adjust at least one electrical parameter of the sensing receiving coil for generating the feedback electromagnetic signal based on the at least one cardiac state.
- 4.** The cardiac stimulation device of claim 3, wherein the sensing electrode includes a first electrode and a second electrode; and wherein a gap is formed between the first electrode and the second electrode, and the gap is varied by the at least one cardiac state.
- 5.** The cardiac stimulation device of claim 4, wherein the first electrode and the second electrode form an interdigital electrode.
- 6.** The cardiac stimulation device of claim 2, wherein the sensing control circuit includes a frequency adjustment unit coupled to the sensing emitting coil; and wherein frequency adjustment unit is configured to adjust a frequency of the sensing electromagnetic signal.
- 7.** The cardiac stimulation device of claim 6, wherein the frequency adjustment unit includes a capacitor array configured to adjust an impedance of the sensing emitting coil.
- 8.** The cardiac stimulation device of claim 2, wherein the sensing module further includes: a shielding component at least arranged at a first side of the sensing emitting coil; wherein the shielding component at least shields a portion of the sensing electromagnetic signal emitted toward to a first direction.
- 9.** The cardiac stimulation device of claim 1, wherein the stimulation control circuit includes: a discharge controller configured to provide a control signal based on the at least one cardiac state; a storage capacitor configured to storage a driving voltage; and a switch configured to receive the control signal and enable transmitting the driving voltage to the stimulation emitting coil based on the control signal.
- 10.** The cardiac stimulation device of claim 9, wherein the stimulation control circuit further includes: a boost circuit configured to receive a supply voltage and boost the supplied power to the driving voltage.
- 11.** The cardiac stimulation device of claim 1, further including: a control module configured to receive the at least one cardiac state and provide a control signal to the stimulation module; wherein the stimulation module is configured to emit the stimulation electromagnetic signal based on the control signal.
-