

US Patent & Trademark Office

Patent Public Search | Text View

United States Patent Application Publication	20250284959
Kind Code	A1
Publication Date	September 11, 2025
Inventor(s)	Chamberland; Christopher et al.

THERMODYNAMIC COMPUTING MEAN-FIELD FORWARDS AND BACKWARDS PROPAGATION

Abstract

A thermodynamic computing system is implemented using one or more thermodynamic chips that implement a plurality of energy based models (EBMs). Each EBM comprises oscillators, wherein the oscillators represent neuron and synapse values of an engineered energy potential. The synapse values may be updated or trained via mean-field forwards and backwards propagation. During the forwards propagation, the energy potentials of the EBMs are not perturbed, and gradient terms are obtained. During the backwards propagation, the energy potentials of the EBMs are perturbed, and additional gradient terms are obtained. The gradient terms may be combined with the additional gradient terms to determine updated synapse values.

Inventors:	Chamberland; Christopher (Austin, TX), Verdon-Akzam; Guillaume (San Fransisco, CA)
Applicant:	Extropic Corp. (Austin, TX)
Family ID:	96949118
Assignee:	Extropic Corp. (Austin, TX)
Appl. No.:	18/977690
Filed:	December 11, 2024

Related U.S. Application Data

us-provisional-application US 63562576 20240307

Publication Classification

Int. Cl.:	G06N3/084 (20230101); G06N3/045 (20230101)
U.S. Cl.:	
CPC	G06N3/084 (20130101); G06N3/045 (20230101);

Background/Summary

BACKGROUND Related Application [0001] This application claims benefit of priority to U.S. Provisional Application Ser. No. 63/562,576, entitled “MEAN-FIELD FORWARDS AND BACKWARDS PROPAGATION TECHNIQUES FOR NEURAL NETWORK INFERENCE AND LEARNING USING THERMODYNAMIC COMPUTING,” filed Mar. 7, 2024, and which is incorporated herein by reference in its entirety.

Description of Related Art

[0002] Various algorithms, such as machine learning algorithms, often use statistical probabilities to make decisions or to model systems. Some such learning algorithms may use Bayesian statistics, or may use other statistical models that have a theoretical basis in natural phenomena. Also, machine learning algorithms themselves may be implemented using Bayesian statistics, or may use other statistical models that have a theoretical basis in natural phenomena.

[0003] Generating such statistical probabilities may involve performing complex calculations which may require both time and energy to perform, thus increasing a latency of execution of the algorithm and/or negatively impacting energy efficiency. In some scenarios, calculation of such statistical probabilities using classical computing devices may result in non-trivial increases in execution time of algorithms and/or energy usage to execute such algorithms.

[0004] As an alternative, algorithms may be performed using thermodynamic computers. However, communication between multiple algorithms implemented on a thermodynamic computing device and/or communications between thermodynamic computing devices may require converting information into a classical computing device form, thus reducing at least some of the benefits of a thermodynamic computer implementation.

Description

BRIEF DESCRIPTION OF THE DRAWINGS

[0005] FIG. 1A is a high-level diagram illustrating a thermodynamic system of one or more thermodynamic chips that are configured to implement energy based models (EBM) and relay gadgets, wherein the thermodynamic system is configured to determine gradients used to update synapse oscillators of the EBMs, according to some embodiments.

[0006] FIG. 1B is a high-level diagram illustrating oscillators of energy based models (EBMs) that represent neurons and synapse values that may be perturbed by the thermodynamic system, according to some embodiments.

[0007] FIG. 2 is a high-level diagram illustrating a plurality of EBMs that collectively represent a neural network, wherein output oscillators and relay oscillators are measured by a classical computing device to calculate gradient terms during a forwards pass, according to some embodiments.

[0008] FIG. 3 is a high-level diagram illustrating a plurality of energy based models (EBMs) that may be used to determine gradient terms used to update synapses, wherein synapses of respective energy potentials of the EBMs are dynamical degrees of freedom, according to some embodiments.

[0009] FIG. 4A is a high-level diagram illustrating a plurality of energy based models (EBMs) that may be used to determine gradient terms during a forwards pass used to update synapses, wherein gradient terms are obtained on a plurality of relay oscillators thus requiring fewer measurements, according to some embodiments.

[0010] FIG. 4B is a high-level diagram illustrating a plurality of energy based models (EBMs) that may be used to determine gradient terms during a backwards pass used to update synapses, wherein gradient terms are obtained on a plurality of relay oscillators thus requiring fewer measurements, according to some embodiments.

[0011] FIG. 5 is a high-level diagram illustrating gradient terms, that may be used to update synapse values, obtained using relay oscillators in an analogue way, according to some embodiments.

[0012] FIG. 6 is high-level diagram illustrating a process of determining weights and biases to be used in an energy-based model (EBM), wherein the weights and biases are determined using measurement values for synapse oscillators, according to some embodiments.

[0013] FIG. 7 is high-level diagram illustrating a process of determining weights and biases to be used in an energy-based model (EBM), wherein the weights and biases are computed using a classical computing device, according to some embodiments.

[0014] FIG. 8 is a diagram illustrating hardware components that may be used to implement oscillators of energy-based models (EBMs), as well as two different example hardware configurations of a relay oscillator that have a time-dependent mass or a time-dependent frequency, respectively, according to some embodiments.

[0015] FIG. 9 is a diagram providing additional details regarding a hardware configuration used to implement a relay oscillator with a time-dependent frequency, according to some embodiments.

[0016] FIG. 10 is a diagram providing additional details regarding a hardware configuration used to implement a relay oscillator with a time-dependent mass, according to some embodiments.

[0017] FIG. 11 is a high-level diagram illustrating an output oscillator, an input oscillator, and a relay gadget, wherein the relay gadget comprises a group of relay oscillators and is configured to relay thermodynamic information between the output oscillator and the input oscillator and includes bias oscillators, according to some embodiments.

[0018] FIG. 12 is a high-level diagram illustrating a spatial analogue relay gadget, wherein respective ones of relay oscillators of a group of relay oscillators are configured to store respective sample values of an output oscillator, according to some embodiments.

[0019] FIG. 13 is a high-level diagram illustrating a temporal analogue relay gadget, wherein a group of relay oscillators comprises a single relay oscillator, according to some embodiments.

[0020] FIG. 14 is a high-level diagram illustrating a series analogue relay gadget, wherein a group of relay oscillators comprises a plurality of relay oscillators arranged in series, according to some embodiments.

[0021] FIG. 15A illustrates example couplings between visible neurons of an energy-based model (EBM), according to some embodiments.

[0022] FIG. 15B illustrates example couplings between visible neurons and non-visible neurons (e.g., hidden neurons) of an energy-based model (EBM), according to some embodiments.

[0023] FIG. 16 is a high-level diagram illustrating oscillators included in a substrate of the thermodynamic chip and mapping of the oscillators to logical neurons of the thermodynamic chip, according to some embodiments.

[0024] FIG. 17 is an additional high-level diagram illustrating oscillators included in a substrate of the thermodynamic chip mapped to logical neurons, weights, and biases of a given neuro-thermodynamic computing system, according to some embodiments.

[0025] FIG. 18 is a high-level flowchart illustrating the process of implementing energy based models and determining gradients that may be used to update synapse oscillators representing synapse values, according to some embodiments.

[0026] FIG. 19 is a block diagram illustrating an example computer system that may be used in at least some embodiments.

[0027] While embodiments are described herein by way of example for several embodiments and illustrative drawings, those skilled in the art will recognize that embodiments are not limited to the embodiments or drawings described. It should be understood, that the drawings and detailed description thereto are not intended to limit embodiments to the particular form disclosed, but on the contrary, the intention is to cover all modifications, equivalents and alternatives falling within the spirit and scope as defined by the appended claims. The headings used herein are for organizational purposes only and are not meant to be used to limit the scope of the description or the claims. As used throughout this application, the word “may” is used in a permissive sense (i.e., meaning having the potential to), rather than the mandatory sense (i.e., meaning must). Similarly, the words “include,” “including,” and “includes” mean including, but not limited to. When used in the claims, the term “or” is used as an inclusive or and not as an exclusive or. For example, the phrase “at least one of x, y, or z” means any one of x, y, and z, as well as any combination thereof.

DETAILED DESCRIPTION

[0028] The present disclosure relates to methods, systems, and/or apparatuses for a thermodynamic system comprising one or more thermodynamic chips used to implement a plurality of energy based models (EBMs) configured to thermodynamically evolve. The thermodynamic system may be configured to implement a neural network by using oscillators of the EBMs. Some oscillators of the respective EBMs may be neuron oscillators representing neuron values, and other respective oscillators of the respective EBMs are synapse oscillators representing synapse values. In some embodiments, the synapse oscillators, when coupled with the neuron oscillators, establish an engineered potential that is configured to be perturbed. In some embodiments, one or more relay gadgets, each comprising one or more oscillators (relay oscillators) may be configured to relay thermodynamic information between the EBMs as the EBMs thermodynamically evolve in a forward pass and a backward pass. In some embodiments, respective EBMs may represent respective layers of a neural network. The forwards and backwards passes may be used to determine gradients used for training the EBMs. For example, gradient terms (forwards gradient terms) of a given EBM are determined during the forwards pass, wherein the engineered energy function is not perturbed in the forward pass. Furthermore, as an example, gradient terms (backwards gradient terms) of the given EBM are determined during the backwards pass, wherein the engineered energy function is perturbed in the backward pass.

[0029] In some embodiments, a classical computing device may be used to measure thermodynamic information of one or more synapse oscillators of a given EBM, compute the forwards or backwards gradient terms of a given EBM based on the measurements of the synapse oscillators, and determine updated synapse values based on the forwards or backwards gradient terms. In other embodiments, additional relay oscillators configured to couple and uncouple with other oscillators may be used to determine the forwards or backwards gradient terms based on respective relay oscillators evolving thermodynamically and may be used to update synapse values based on the forwards or backwards gradient terms based on respective relay oscillators evolving thermodynamically.

[0030] In some embodiments, a thermodynamic system may be used to implement a neural network. The thermodynamic system may take input data and output inference data. For example, oscillators of an energy based model (EBM) such as described herein may take the input data and evolve thermodynamically to generate inferences based on the input data. The thermodynamic system may be configured to train itself and to minimize a loss function when using labeled training data. Training may comprise determining gradients of a loss function such as a first derivative and second derivative (e.g., Hessian) of the loss function with respect to synapse values and updating synapse oscillators representing the synapse values. In this

way, a thermodynamic training scheme may be implemented using the model. In some embodiments, a thermodynamic system may use measurements of output oscillators and/or relay oscillators to determine gradient terms used to update synapse values (e.g., synapse values such as weights and biases). In some embodiments, a thermodynamic system may use measurements of input oscillators and synapse oscillators to determine the gradient terms. Furthermore, in some other embodiments, gradient terms may be determined using a plurality of additional relay oscillators.

[0031] In some embodiments, a forwards pass may comprise determining gradients wherein energy potentials of respective EBMs are not perturbed. The energy potentials of respective EBMs are based on synapse values such as weights and biases of neuron oscillators. The energy potential may be tuned throughout a training process to improve metrics such as a loss function, wherein inference results that more closely match labeled training data result in less loss. In some embodiments, a backwards pass may comprise determining gradients wherein the energy potentials of respective EBMs are perturbed. The gradient of the unperturbed potential and the gradient of the perturbed potential may be combined to determine how to update synapse parameters of the thermodynamic system. The thermodynamic system may perturb the energy potential of respective EBMs by adjusting input or output oscillators by a small amount. For example, each neuron of a given EBM block may have an energy potential that is perturbed. Such a perturbed energy potential may be obtained by turning on additional coupling terms, wherein the coupling terms may be mediated via relay oscillators. Thus, by way of example, a gradient terms may be stored in the position degrees of freedom of relay oscillators, wherein such relay oscillators are coupled to output oscillators. Perturbing the energy potentials during a backwards pass allows for gradients of the loss function to be measured directly. Therefore, fewer computations on external classical computing devices may be needed. The perturbed potential may be linear in the outputs of the given EBM block.

[0032] Several schemes for performing mean-field forwards and backwards propagation may be implemented, wherein each layer of a deep neural network may be implemented using an energy based model (EBM). In some embodiments, relay oscillators may be coupled to an output of an EBM during the forward pass. The relay oscillators may be used to store the thermal equilibrium expectation value of the output of an EBM, which may then be used as input to a next EBM layer. Relay oscillators may also be used to store gradients during the forwards pass. The potential energy function of an EBM may be chosen such that the thermal equilibrium expectation value of the output may be similar to a result obtained in a layer of a corresponding deep neural network. Several schemes may be used to perform mean-field backwards propagation. In some embodiments, mean-field corresponds to using a computed expectation value to compute derivatives of a loss function with respect to parameters (e.g., synapses such as weights and biases) of each EBM.

[0033] In some embodiments, thermal equilibrium expectation values may be stored in one or more relay oscillators and used as inputs to the next EBM block. Gradients of a loss function may be computed by using sample values to compute expectation values. In some embodiments, finite difference methods may be applied to compute a desired gradient. In some embodiments, a small perturbation to the potential energy function during the backwards pass may result in being able to measure the gradients of the loss function directly. This may allow for fewer computations on an external classical processing device than otherwise. Furthermore, the perturbed potential may be chosen in order to obtain desired gradients. The gradients may be used to update synapse oscillators representing synapse parameters (e.g., synapses such as weights and biases) of the EBM during training of the EBM.

Mean-Field Forwards Propagation

[0034] In some embodiments, both analog and digital methods for performing forward propagation in deep learning models may be implemented with energy based models. For example, the protocols described herein may make use of relay oscillator methods.

[0035] For example, consider an l 'th layer of a deep learning network with input $x_{\text{sub}.l}$ and output $y_{\text{sub}.l}$. The probability of a given output $y_{\text{sub}.l}$ may be given by,

$$[00001] p(y_l | \text{Math. } x_l, \dots) = \frac{e^{-\mathcal{E}_l(y_l | \text{Math. } x_l)}}{Z(x_l, \dots)}, \quad (\text{equation1})$$

where $\mathcal{E}_{\text{sub}.l}$ may be a potential energy function of the l 'th block with parameters $\theta_{\text{sub}.l}$ (e.g., synapses such as weights and biases). The energy function $\mathcal{E}_{\text{sub}.l}$ may be chosen such that the thermal equilibrium expectation value, i.e.,

$$[00002] \text{Math. } y_l | \text{Math. } = \int dy_l y_l \frac{e^{-\mathcal{E}_l(y_l | \text{Math. } x_l)}}{Z(x_l, \dots)}, \quad (\text{equation2})$$

may be equal to the desired output of a deep learning model. That is, in expectation value, the EBM model with energy function $\mathcal{E}_{\text{sub}.l}$ performs computation such as block l of a desired neural network. The nodes $x_{\text{sub}.l}$ and $y_{\text{sub}.l}$ may be harmonic oscillators which encode the values of the inputs and outputs to the EBM with energy function $\mathcal{E}_{\text{sub}.l}$. In what follows, $\phi_{\text{sub}.x.\text{sub}.j}$ may denote the position degrees of freedom for the oscillators which encode the value $x_{\text{sub}.j}$ as input to the EBM block with potential $\mathcal{E}_{\text{sub}.j}$. Similarly, the outputs $y_{\text{sub}.j}$ may be encoded in the position degrees of freedom of the oscillators $\phi_{\text{sub}.y.\text{sub}.j}$. Lastly, the position degrees of freedom of the relay oscillators coupled to $\phi_{\text{sub}.y.\text{sub}.j}$ may be labelled as $\phi_{\text{sub}.r.\text{sub}.j}$.

Obtaining Expectation Values Using Relay Oscillators

[0036] In some embodiments, a coupling Hamiltonian may describe the dynamics of a relay oscillator. For example, for some hyperparameters for the coupling pulses, and at thermal equilibrium, an expectation value  may be transferred to a state of the relay oscillator $\phi_{\text{sub}.r.\text{sub}.l}$. The Hamiltonian may be given by,


[00003]

$$H_{\text{rel}}^{(j,l)} = \frac{(\dot{\phi}_{r_l}^{(j)})^2}{2m_{r_l}^{(j)}} + \frac{(\dot{\phi}_{y_l}^{(j)})^2}{2m_{y_l}^{(j)}} + \frac{1}{2}m_{r_l}^{(j)}(\phi_{r_l}^{(j)}(t) - \phi_{r_l}^{(j)}(t_1^{(A)}))^2 + \mathcal{E}_l(\phi_{y_l}^{(j)} | \text{Math. } x_l, \dots) + A(t)(\phi_{r_l}^{(j)} - \phi_{y_l}^{(j)})^2 + X(t)\phi_{r_l}^{(j)}\phi_{x_{l+1}}^{(j)} + B(t)\phi_{b_l}^{(j)}\phi_{r_l}^{(j)}, \quad (\text{equation3})$$

where $\phi_{\text{sub}.b.\text{sub}.l.\text{sup}.(j)}$ are bias oscillators which are coupled to the relay oscillators. For example, the dynamics of a system for the $j.\text{sup}.th$ oscillator of the $l.\text{sup}.th$ layer with relay oscillators may be governed by a Hamiltonian that includes: kinetic energy terms of the relay oscillator and output oscillator, a potential of the relay oscillator, the potential of the $l.\text{sup}.th$ layer of the EBM given input oscillators and synapse parameters (e.g., synapses such as weights and biases), a time dependent coupling between the relay oscillator and the output oscillators, time dependent coupling between the relay oscillator and the input oscillator of the next EBM layer, and a time dependent coupling between an optional bias oscillator and the relay oscillator. The time-dependent coupling pulses $\lambda_{\text{sub}.A}(t)$, $\lambda_{\text{sub}.X}(t)$ and $\lambda_{\text{sub}.B}(t)$ may take the form,

[00004](respectively equations 4, 5, and 6)

$$A(t) = A((k_A(t - t_1^{(A)})) - (k_A(t - t_2^{(A)}))) \quad X(t) = X((k_X(t - t_1^{(X)})) + \frac{(X)}{0}) \quad B(t) = B((k_B(t - t_1^{(B)})) + \frac{(B)}{0}),$$

where $\sigma(x)$ may be the sigmoid function. Appropriate choices of the hyperparameters in equations 3-6 can ensure that after $\phi_{\text{sub}.r.\text{sub}.l.\text{sup}.(l)}$ may be decoupled from $\phi_{\text{sub}.y.\text{sub}.l.\text{sup}.(j)}$, samples taken of $\phi_{\text{sub}.r.\text{sub}.l.\text{sup}.(j)}$ may approximately be given by  $\phi_{\text{sub}.y.\text{sub}.l.\text{sup}.(j)}$ . The hyperparameters can also be chosen such that the coupling between the relay oscillator and $\phi_{\text{sub}.x.\text{sub}.l+1.\text{sup}.(j)}$ imparts  $\phi_{\text{sub}.y.\text{sub}.l.\text{sup}.(j)}$  to $\phi_{\text{sub}.x.\text{sub}.l+1.\text{sup}.(j)}$. The product of mass time frequency of $\phi_{\text{sub}.x.\text{sub}.l+1.\text{sup}.(j)}$ may be increased such that it remains clamped at  $\phi_{\text{sub}.y.\text{sub}.l.\text{sup}.(j)}$ . Therefore, the input to the EBM block with potential energy $\mathcal{E}_{\text{sub}.l+1}$ may be given by the computed value of the l 'th layer of a deep neural network. In other embodiments, (e.g., in a fully digital implementation instead of analogue), the coupling between $\phi_{\text{sub}.r.\text{sub}.l.\text{sup}.(j)}$ and $\phi_{\text{sub}.x.\text{sub}.l+1.\text{sup}.(j)}$ may be removed altogether and the position $\phi_{\text{sub}.r.\text{sub}.l.\text{sup}.(j)}$ may be measured. The measured value may still correspond to approximately  $\phi_{\text{sub}.y.\text{sub}.l.\text{sup}.(j)}$ . Then the oscillator $\phi_{\text{sub}.x.\text{sub}.l+1.\text{sup}.(j)}$ may be clamped using a clamping potential of the form $\lambda_{\text{sub}.c}(\phi_{\text{sub}.x.\text{sub}.l+1.\text{sup}.(j)} - \text{custom-character} \phi_{\text{sub}.y.\text{sub}.l.\text{sup}.(j)} \text{custom-character})_{\text{sup}.2}$ for some large value of $\lambda_{\text{sub}.c}$.

[0037] FIG. 1A is a high-level diagram illustrating a thermodynamic system of one or more thermodynamic chips comprising energy based models (EBM) and relay gadgets, wherein the thermodynamic system is configured to determine gradients used to update synapse oscillators of EBMs,

according to some embodiments.

[0038] In some embodiments, thermodynamic chip(s) **100** comprise energy based models (EBMs) **102a-b** and relay gadgets **106a-b**. Relay gadgets **106a-b** may comprise relay oscillators **108a** used to relay thermodynamic information, such as expectation values, of neuron oscillators **104a** to neuron oscillators of **104b**. Synapse oscillators of oscillators **104a** and **104b** may be used to process thermodynamic information, wherein oscillators **104a** and **104b** evolve thermodynamically according to an energy potential (e.g., according to Langevin dynamics). Synapse oscillators and neuron oscillators of oscillators **104a** of EBM **102a** may be coupled together to establish an energy potential. The thermodynamic system represented in FIG. 1 may be used to determine gradients, wherein the gradient terms may be used to update synapse oscillators of EBMs. In a forwards pass, wherein engineered energy potentials of the EBMs are not perturbed, the system may determine forward gradients **110**. In a backwards pass, the engineered energy potential of the EBMs are perturbed to determine backward gradients **112**. Gradients may be useful to determine how to update parameters such as described herein. FIG. 1 shows a segment of a chain of EBMs **102a-b** and relay gadgets **106a-b**. A plurality of EBMs may be used to represent respective layers of a neural network.

Performing Forwards Propagation Using Relay Oscillator Expectation Values

[0039] In some embodiments, to ensure that the input of EBM **102b** (e.g., the input neuron oscillators of the l'th EBM block, wherein the EBM block corresponds to the l'th layer of a deep neural network) may be clamped to .sub.y.sub.l-1.sup.(j) , which corresponds to the output of EBM **102a** of the l-1 layer of a deep neural network. Consequently, forward propagation can be implemented by performing a protocol using relay oscillators of a relay gadget for each EBM block, where each EBM block has a potential energy chosen such that the thermal equilibrium expectation value of the output has the same value as the output that would be obtained by directly computing the given layer of a deep neural network on a classical computing device (e.g., GPU/FPGA chip).

Computing the Gradients for Mean-Field Backpropagation

[0040] In some embodiments, a final layer of a deep neural network may be used to compute a loss function. The loss function may be any suitable loss function, for example, such as the mean squared error (MSE) loss function given by

$$\begin{aligned} \text{[00005]} \quad MSE &= \frac{1}{2N} \sum_{i=1}^N (\text{Math. } (y_i^{(t)} - \text{Math. } y_i^{(K)} \text{ Math. })^2 \\ &= \frac{1}{N} \sum_{i=1}^N L_i, \end{aligned} \quad \begin{aligned} &\text{(equation7) where } L_i = \frac{1}{2} (y_i^{(t)} - \text{Math. } y_i^{(K)} \text{ Math. })^2, \text{ (equation8)} \\ &\end{aligned}$$

wherein a network with a total of K layers may be used. In equation 7, N may be the total number of training samples, y.sub.i.sup.(t) may be the ground truth and .sub.i.sup.(K)  may be the EBM models prediction (which may be emulating a deep neural network). In order to implement back propagation, gradient terms of the form

$$\text{[00006]} \quad \frac{\partial L_i}{\partial \theta_j}, \quad \text{(equation9)}$$

may be computed (e.g., determine backwards gradients **112**), where $\theta_{\text{sub.l.sup.(j)}}$ may be the j'th parameter (e.g., synapses of oscillators **104a** or **104b** such as weights and biases) of $\epsilon_{\text{sub.l}}$. Using the chain rule, equation 9 may be written as

$$\text{[00007]} \quad \frac{\partial L_i}{\partial \theta_j} = \frac{\partial L_i}{\partial \text{Math. } y_l^{(j)} \text{ Math. }} \cdot \frac{\partial \text{Math. } y_l^{(j)} \text{ Math. }}{\partial \theta_j}. \quad \text{(equation10)}$$

Later it is shown that

$$\text{[00008]} \quad \frac{\partial \text{Math. } y_l^{(j)} \text{ Math. }}{\partial \theta_j}$$

may be given by

$$\text{[00009]} \quad \frac{\partial \text{Math. } y_l^{(j)} \text{ Math. }}{\partial \theta_j} = -\text{Cov}(y_l^{(j)}, \frac{\partial \mathcal{E}_l(y_l \text{ Math. } x_l)}{\partial \theta_j}) \cdot \text{Furthermore } \frac{\partial L_i}{\partial \text{Math. } y_l^{(j)} \text{ Math. }}, \quad \text{(equation11)}$$

in the final layer K of the neural network, may be written as

$$\text{[00010]} \quad \frac{\partial L_i}{\partial \text{Math. } y_K^{(1)} \text{ Math. }} = -(y_i^{(t)} - \text{Math. } y_K^{(1)} \text{ Math. }). \quad \text{(equation12)}$$

For the hidden layers, it may be written

$$\text{[00011]} \quad \frac{\partial L_i}{\partial \text{Math. } y_l^{(j)} \text{ Math. }} = \text{Math. } \frac{\partial L_i}{\partial \text{Math. } y_{l+1}^{(s)} \text{ Math. }} \cdot \frac{\partial \text{Math. } y_{l+1}^{(s)} \text{ Math. }}{\partial \text{Math. } y_l^{(j)} \text{ Math. }}, \quad \text{(equation13)}$$

where the set .sub.j.sup.(l) includes all indices for which the output nodes y.sub.l+1.sup.(s) are coupled to x.sub.l.sup.(j)=.sub.l.sup.(j) . Furthermore, it may be shown that

$$\text{[00012]} \quad \frac{\partial \text{Math. } y_{l+1}^{(s)} \text{ Math. }}{\partial \text{Math. } y_l^{(j)} \text{ Math. }} = -\text{Cov}(y_{l+1}^{(s)}, \frac{\partial \mathcal{E}_{l+1}(y_{l+1} \text{ Math. } y_l \text{ Math. })}{\partial \text{Math. } y_l^{(j)} \text{ Math. }}) \cdot \frac{\partial \mathcal{E}_{l+1}(y_{l+1} \text{ Math. } y_l \text{ Math. })}{\partial y_{l+1} \text{ Math. } y_l \text{ Math. }}, \quad \text{(equation14)}$$

where the input x.sub.l+1 to the EBM block in layer l+1 may be given by .sub.l  given the dynamics of the relay oscillators.

[0041] FIG. 1B is a high-level diagram illustrating oscillators of energy based models (EBMs) that represent neurons and synapse values that may be perturbed by the thermodynamic system, according to some embodiments.

[0042] In some embodiments, energy based model **102a** comprises oscillators that represent neurons **110**, and synapses (e.g., weights **114**, **116** and biases **112**). The example configuration shown in FIG. 1B illustrates that a neuron oscillator **110** may be coupled with bias synapse oscillators **112** and weights synapse oscillators **114** and **116**. The synapse oscillators **112**, **114**, and **116** may be used, when coupled to neuron oscillator **110**, to establish an energy potential such as energy potential **206a**. Various arrangements of neuron oscillators and synapse oscillators may be used to establish various engineered energy potential based on the type of EBM being used. Furthermore, synapse oscillators such as **112**, **114**, and **116** may be updated based on gradient terms such as described herein. The hardware components of oscillators is described in later figures.

[0043] FIG. 2 is a high-level diagram illustrating a plurality of EBMs that collectively represent a neural network, wherein output oscillators and relay oscillators are measured by a classical computing device to calculate gradient terms during a forwards pass, according to some embodiments.

[0044] In some embodiments, during a forwards pass, energy potential **206a-d** may comprise synapse values implemented in hardware (e.g., synapse values are not dynamical degrees of freedom). In such an embodiment, classical computing device **212** may measure a position or momentum degrees of freedom of output oscillators **208a** an N number of times **250** during a forwards pass **202**. Furthermore, classical computing device **212** may measure **252** position or momentum degrees of freedom of relay oscillators **108a**. Similarly, output oscillators of each EBM may be measured N times (e.g., **254**, **258**, **262**). By way of example, relay oscillators **108a** may be used to relay thermodynamic information such as expectation values from output oscillator **208a** to input oscillator **204b**.

Implementation of Covariance Calculation Wherein Synapse Parameters are Not Dynamical Degrees of Freedom

[0045] In some embodiments, covariances may be calculated. For example, the terms in equations 11, 12, and 14 can be computed using an architecture that comprises measuring output oscillators **208a-d** and relay oscillators **108a-c** and storing measured values in a classical computing device **212**. In some embodiments, the measured values may be used as samples for backwards propagation later which may be used to

the expectation values in the covariance calculations, wherein the calculations may be computed on a classical post-processing device **212** such as an FPGA/ASIC chip.

[0046] For example, a forward pass **202** of a deep learning network is shown in FIG. 2, with the final layer (e.g., EBM **102d**) computing a loss function (e.g., MSE loss). In some embodiments, at each output of a given EBM (e.g., output **208a** of EBM **102a**), and prior to coupling the output to the relay oscillator, an N number of measurements or samples (e.g., **250**, **254**, **258** or **262**) of the position degree of freedom of the oscillators encoding the output may be performed. For example, at layer l, a number of measurements **250** (e.g., N samples) of $\phi_{\text{sub.y}} \mathbf{208a}$ after the oscillators reach thermal equilibrium may be performed. Such measurements may be used to compute a portion of the terms in equations 11 and 14 since they may be used as samples for computing some of the expectation values. After the relay oscillators (e.g., **108a-c**) are coupled to the output oscillators of an EBM block, the position degrees of freedom of the relay oscillators may be measured. In some embodiments, for the l'th EBM block **102a**, measuring $\phi_{\text{sub.r.sub.l}} \mathbf{108a}$ would result in an approximate value for $\langle \text{custom-character.y.sub.l} \rangle_{\text{custom-character}}$ with the appropriate couplings, and time-dependent mass or frequencies. Now starting with

$$[00013] \frac{\partial \langle \text{Math.y}_l^{(j)} \rangle_{\text{Math.}}}{\partial \langle \phi \rangle},$$

expanding the covariance term in equation 11 may result in

$$[00014] \frac{\partial \langle \text{Math.y}_l^{(j)} \rangle_{\text{Math.}}}{\partial \langle \phi \rangle} = - \langle \text{Math.y}_l^{(j)} \rangle \frac{\partial \langle \text{Math.y}_l \rangle_{\text{Math.}}}{\partial \langle \phi \rangle} + \langle \text{Math.y}_l^{(j)} \rangle_{\text{Math.}} \frac{\partial \langle \text{Math.y}_l \rangle_{\text{Math.}}}{\partial \langle \phi \rangle} \quad (\text{equation15})$$

In some embodiments, the term $\langle \text{custom-character.y.sub.l.sub.(j)} \rangle_{\text{custom-character}}$ may be obtained directly from the relay oscillator measurements during the forward pass **202**. In other embodiments using an architecture where synapse values are chosen to be dynamical degrees of freedom, the term

$$[00015] \langle \text{Math.y}_l \rangle_{\text{Math.}} \frac{\partial \langle \text{Math.y}_l \rangle_{\text{Math.}}}{\partial \langle \phi \rangle} \quad p(y_l | x_l)$$

(such as shown later) may be computed by measuring the position or momentum of the parameters (e.g., synapses such as weights and biases) directly, wherein the gradient may be reconstructed. In some embodiments where synapse values are not chosen to be dynamical degrees of freedom, the gradient may be computed on a classic post-processing device **212** using all of the N measurement outcomes of the position degrees of freedom of the output EBM in layer l to approximate the expectation value. In such an embodiment, it may be written,

$$[00016] \langle \text{Math.y}_l \rangle_{\text{Math.}} \frac{\partial \langle \text{Math.y}_l \rangle_{\text{Math.}}}{\partial \langle \phi \rangle} \approx \frac{1}{N} \sum_{s=1}^N \langle \text{Math.y}_{l,s} \rangle_{\text{Math.}} \frac{\partial \langle \text{Math.y}_{l,s} \rangle_{\text{Math.}}}{\partial \langle \phi \rangle}, \quad (\text{equation16})$$

where $y_{\text{sub.l},s}$ may be the sample $s \in 1, \dots, N$ of the output nodes $y_{\text{sub.l}}$, which may be sampled from the probability distribution $p(y_{\text{sub.l}} | \theta_{\text{sub.l.x.sub.l}})$. Similarly, such samples may be used to approximate the expectation value of the term

$$[00017] \langle \text{Math.y}_l^{(j)} \rangle_{\text{Math.}} \frac{\partial \langle \text{Math.y}_l^{(j)} \rangle_{\text{Math.}}}{\partial \langle \phi \rangle} \quad p(y_l | x_l)$$

using a similar formulation as in equation 16.

[0047] Furthermore, from equation 14

[00018] (equation17).

$$\frac{\partial \langle \text{Math.y}_{l+1}^{(s)} \rangle_{\text{Math.}}}{\partial \langle \text{Math.y}_l^{(j)} \rangle_{\text{Math.}}} = - \langle \text{Math.y}_{l+1}^{(s)} \rangle \frac{\partial \langle \text{Math.y}_{l+1} \rangle_{\text{Math.}}}{\partial \langle \text{Math.y}_l^{(j)} \rangle_{\text{Math.}}} + \langle \text{Math.y}_{l+1}^{(s)} \rangle_{\text{Math.}} \frac{\partial \langle \text{Math.y}_{l+1} \rangle_{\text{Math.}}}{\partial \langle \text{Math.y}_l^{(j)} \rangle_{\text{Math.}}} \quad p(y_{l+1} | y_l, \text{Math.y}_l)$$

Similarly to equation 15, the N measured samples of the output **208b** of the block l+1 (e.g., EBM **102b**) obtained during the forward pass may be used to compute an approximation of the first term on the right-hand side of equation 15, as well as the term

$$[00019] \langle \text{Math.y}_{l+1} \rangle_{\text{Math.}} \frac{\partial \langle \text{Math.y}_{l+1} \rangle_{\text{Math.}}}{\partial \langle \text{Math.y}_l^{(j)} \rangle_{\text{Math.}}} \quad p(y_{l+1} | y_l, \text{Math.y}_l)$$

Architecture for Finite Difference Methods, Wherein Synapse Parameters are Dynamical Degrees of Freedom

[0048] FIG. 3 is a high-level diagram illustrating a plurality of energy based models (EBMs) that may be used to determine gradient terms used to update synapses, wherein synapses of respective energy potentials of the EBMs are dynamical degrees of freedom, according to some embodiments.

[0049] In some embodiments, parameters (e.g., synapses such as weights and biases) of energy potential **206a-d** may be dynamical degrees of freedom. For example, gradients of the loss function in equation 9 may be obtained by performing a series of measurements **362** of the parameters (e.g., synapses such as weights and biases) of energy potential **206d** and measurements of output neurons (e.g., output oscillator **304**). In such an embodiment, the architecture comprises parameters θ (e.g., synapses such as weights and biases) of energy potentials **206a-c** that are dynamical degrees of freedom. By setting the product of mass times frequency squared of the parameters (e.g., synapses) to be large relative to the input neurons **204a-c** and output neurons **208a-c** of a given EBM block, respectively EBMs **102a-c**, the timescale of the dynamics of the parameters of the energy potentials **206a-c** may be much slower than those of the neurons **204a-c** and **208a-c**. For example, changes in the expectation values of the output neurons **208a-c**, given small changes in the parameters θ , may be measured.

[0050] For example, the Langevin equation of motion for the θ parameter oscillators (e.g., representing synapse values such as weights and biases) of energy potential **206a-c** may be written as

$$[00020] \frac{d \phi^{(t)}}{dt} = - \langle \phi \rangle - \frac{\partial H_{\text{tot}}}{\partial \phi} \Big|_t + \sqrt{2m_l} k_B T \frac{dW_t}{dt}, \quad (\text{equation18})$$

where $\pi_{\text{sub.}\theta_{\text{sub.l.sub.(j)}}}$ may be understood to be the momentum of the degree of freedom of the j'th oscillator in layer l, and $\phi_{\text{sub.}\theta_{\text{sub.l.sub.(j)}}}$ may be its conjugate position degree of freedom. The parameter γ may represent friction, $m_{\text{sub.l}}$ may be the mass of the parameters for the EBM in layer l, and $W_{\text{sub.t}}$ may be a Wiener process. Similarly, variables may be used for each layer (e.g., layers l, l+1, l+2, etc.), wherein layer l may represent a given layer. Integrating equation 18, wherein the momentum dependence of the Hamiltonian in equation 18 only arises through its kinetic term, the following may result

$$[00021] \langle \phi \rangle(t) - \langle \phi \rangle(0) + \int_0^t \langle \phi \rangle(\tau) d\tau = - \int_0^t \langle \text{Math.y}_l \rangle_{\text{Math.}} \frac{\partial \langle \text{Math.y}_l \rangle_{\text{Math.}}}{\partial \langle \phi \rangle} \Big|_i \text{Math.} \quad d\tau + \sqrt{2m_l} k_B T \int_0^t dW \quad p(y_l | x_l)$$

As can be seen from equation 19, by performing measurements of the momentum degrees of freedom of the oscillators (synapse oscillators) for some time t, averaged gradients of the energy function may be computed. The time interval and system parameters may be chosen to minimize variance in the measurement due to the noise term. In some embodiments, such as in what follows, since gradients of the form

$$[00022] \frac{\partial L_j}{\partial \langle \text{Math.y}_l^{(j)} \rangle_{\text{Math.}}}, \frac{\partial \langle \text{Math.y}_l^{(j)} \rangle_{\text{Math.}}}{\partial \langle \phi \rangle} \text{ and } \frac{\partial \langle \text{Math.y}_{l+1}^{(s)} \rangle_{\text{Math.}}}{\partial \langle \text{Math.y}_l^{(j)} \rangle_{\text{Math.}}}$$

may be computed (see equations 10 and 13), changes in expectation values of the form $\langle \text{custom-character.y.sub.l.sub.(j)} \rangle_{\text{custom-character}}$ (e.g., expectation value of output relay oscillators **208a**) given changes in the parameters θ (e.g., synapses such as weights and biases) of energy potential **206a** during a back propagation step (e.g., backward pass **302**) may be measured.

[0051] In some embodiments, a protocol for the output layer K (e.g., EBM **102d**) is described herein. The gradient of a loss function with respect to

the parameters of the output layer EBM **102d** (e.g., synapses such as weights and biases) may be given by

$$[00023] \frac{\partial L}{\partial \theta_K^{(1)}} = -(\mathbf{y} - \text{Math. } \mathbf{y}_K^{(1)} \cdot \text{Math. } \frac{\partial \text{Math. } \mathbf{y}_K^{(1)} \cdot \text{Math.}}{\partial \theta_K^{(1)}}), \quad (\text{equation20})$$

where for simplicity the indices i in L have been omitted. If changes in the position degrees of freedom of the parameters $\theta_{\text{sub.K.sup.}(j)}$ (e.g., synapses such as weights and biases) of energy potential **206d** are measured while simultaneously measuring the updated  custom-character $y_{\text{sub.K.sup.}(1)}$  custom-character (e.g., expectation value of output oscillator **304**) of the output neurons,

$$[00024] \frac{\partial \text{Math. } \mathbf{y}_K^{(1)} \cdot \text{Math.}}{\partial \theta_K^{(1)}}$$

may be computed as

$$[00025] \frac{\partial \text{Math. } \mathbf{y}_K^{(1)} \cdot \text{Math.}}{\partial \theta_K^{(1)}} \approx \frac{\text{Math. } \mathbf{y}_K^{(1)} \cdot \text{Math. } (t + \delta t) - \text{Math. } \mathbf{y}_K^{(1)} \cdot \text{Math. } (t)}{\theta_K^{(1)}(t + \delta t) - \theta_K^{(1)}(t)},$$

(equation 21) which may be a good approximation for small time intervals of size δt if  custom-character $y_{\text{sub.K.sup.}(1)}$  custom-character behaves linearly. Furthermore, measurements for varying time intervals may be performed to confirm the linear behavior of  custom-character $y_{\text{sub.K.sup.}(1)}$  custom-character, wherein an appropriate size for δt may be chosen. In some embodiments, the protocol for the output layer EBM **102d** may be summarized as follows:

[0052] At time t , the thermodynamic system may initialize the parameters $\theta_{\text{sub.K.sup.}(j)}$ (e.g., synapses such as weights and biases) of energy potential **206d** to the values they had during a forward pass **300**.

[0053] The thermodynamic system may allow the parameters $\theta_{\text{sub.K.sup.}(j)}$ to evolve for time δt , and perform at least one measurement of $\theta_{\text{sub.K.sup.}(j)}$ and  custom-character $y_{\text{sub.K.sup.}(1)}$  custom-character in such a time interval.

[0054] The thermodynamic system may use equation 24 to approximate the gradient

$$[00026] \frac{\partial \text{Math. } \mathbf{y}_K^{(1)} \cdot \text{Math.}}{\partial \theta_K^{(1)}}$$

on an external classical computing device **212** (e.g., FPGA/ASIC chip).

[0055] The thermodynamic system may compute

$$[00027] \frac{\partial L}{\partial \theta_K^{(1)}}$$

using equation 20.

[0056] Note that the value  custom-character $y_{\text{sub.K.sup.}(1)}$  custom-character(t) **304** may be already known by the thermodynamic system as it may be measured during the forward pass **300**.

[0057] In some embodiments, a protocol for the hidden layers (e.g., EBMs **102a-c**) is described herein. For the hidden layers EBMs **102a-c**, gradient terms may be written

$$[00028] \frac{\partial L}{\partial \theta_l^{(n)}} = \text{Math. } \frac{\partial L}{\partial \text{Math. } \mathbf{y}_l^{(n)} \cdot \text{Math.}} \cdot \frac{\partial \text{Math. } \mathbf{y}_l^{(n)} \cdot \text{Math.}}{\partial \theta_l^{(n)}}, \quad (\text{equation22}) \text{ and } \frac{\partial L}{\partial \text{Math. } \mathbf{y}_l^{(s)} \cdot \text{Math.}} = \text{Math. } \frac{\partial L}{\partial \text{Math. } \mathbf{y}_{l+1}^{(s)} \cdot \text{Math.}} \cdot \frac{\partial \text{Math. } \mathbf{y}_{l+1}^{(s)} \cdot \text{Math.}}{\partial \text{Math. } \mathbf{y}_l^{(s)} \cdot \text{Math.}},$$

(equation 23). In the l 'th layer,  custom-character $y_{\text{sub.l.sup.}(j)}$  custom-character (e.g., expectation value of output oscillator **208a**) may be determined given small changes in $\theta_{\text{sub.l.sup.}(j)}$ (e.g., synapse values of energy potential **206a**) and use an approximation such as

$$[00029] \frac{\partial \text{Math. } \mathbf{y}_l^{(j)} \cdot \text{Math.}}{\partial \theta_l^{(j)}} \approx \frac{\text{Math. } \mathbf{y}_l^{(j)} \cdot \text{Math. } (t + \delta t) - \text{Math. } \mathbf{y}_l^{(j)} \cdot \text{Math. } (t)}{\theta_l^{(j)}(t + \delta t) - \theta_l^{(j)}(t)},$$

(equation 24). In some embodiments, equation 23 may be used, wherein the previously computed values

$$[00030] \frac{\partial L}{\partial \text{Math. } \mathbf{y}_{l+1}^{(s)} \cdot \text{Math.}}$$

in addition to changes in  custom-character $y_{\text{sub.l+1.sup.}(s)}$  custom-character (e.g., output oscillators **208b**) given changes in  custom-character $y_{\text{sub.l.sup.}(j)}$  custom-character (e.g., output oscillators **208a**) are used, wherein the values are computed by the thermodynamic system. For example, when the parameters $\theta_{\text{sub.l.sup.}(j)}$ (e.g., synapses such as weights and biases) of energy potential **206a** result in a change in  custom-character $y_{\text{sub.l.sup.}(j)}$  custom-character (e.g., output oscillators **208a**), the new input for EBM **102b** may be used to compute the change in  custom-character $y_{\text{sub.l+1.sup.}(s)}$  custom-character (e.g., output oscillators **208b**), wherein output of output oscillators **208a** may be relayed via relay oscillators **108a** to input oscillators **204b**. Consequently, this allows the gradient

$$[00031] \frac{\partial \text{Math. } \mathbf{y}_{l+1}^{(s)} \cdot \text{Math.}}{\partial \text{Math. } \mathbf{y}_l^{(j)} \cdot \text{Math.}}$$

to be approximated by the thermodynamic system.

Architecture for Perturbed Mean Field Back Propagation, Wherein Synapse Parameters are Dynamical Degrees of Freedom

[0058] In some embodiments, mean field backwards propagation may be performed using a device that comprises synapses that are dynamical degrees of freedom. In some embodiments, mean field backwards propagation (e.g., backwards pass **302**) comprises adding a small perturbation to the original potential energy function **206a-d** of a given EBM block **102a-d**. In some embodiments, throughout both the forwards pass **300** (wherein gradient terms are found without perturbing the potentials of energy potentials **206a-d**) and backwards pass **302** (wherein gradient terms are found with a perturbed potential of energy potentials **206a-d**), the parameters θ (e.g., synapses such as weights and biases) of energy potentials **206a-d** are dynamical degrees of freedom following Langevin dynamics as in equation 18.

[0059] In some embodiments during the forward pass **300**, at each EBM block, momentum measurements of the parameters (e.g., synapses) of energy potentials **206a-d** may be used, to obtain the gradient terms of the form

$$[00032] \mathbb{E} \left[\frac{\partial \mathcal{E}_i(\mathbf{y}_i | \mathbf{x}_i)}{\partial \theta_i} \right]_{p_i(\mathbf{y}_i | \mathbf{x}_i)}, \quad (\text{equation25}).$$

Furthermore, the expectation value may be taken over the distribution

$$[00033] p_i(\mathbf{y}_i | \mathbf{x}_i) = \frac{e^{-\text{Math. } \mathbf{y}_i \cdot \text{Math. } (\mathbf{x}_i)}}{Z}, \quad (\text{equation } 26)$$

Such gradients may be recorded on an external classical computing device **212** such as an FPGA/ASIC chip. Furthermore, for each EBM block **102a-c**, the average state of an output oscillator **208a-c** may be measured after the state of the output oscillator is transferred to respective relay oscillators **108a-b**. For instance, for an EBM block **102a** in layer l ,  custom-character $y_{\text{sub.l.sup.}(j)}$  custom-character (e.g., expectation value of output oscillator **208a**) may be measured and stored.

[0060] In some embodiments, during a forwards pass **300**, in addition to measuring the gradients in equation 25 using an architecture with parameters (e.g., synapses of energy potential **206b**) that are dynamical degrees of freedom, gradients of the form

$$[00034] \mathbb{E} \left[\frac{\partial \text{Math. } \mathbf{y}_{l+1}^{(s)} \cdot \text{Math. } \mathbf{y}_l^{(j)} \cdot \text{Math.}}{\partial \text{Math. } \mathbf{y}_l^{(j)} \cdot \text{Math.}} \right]_{p_{l+1}(\mathbf{y}_{l+1}^{(s)} | \text{Math. } \mathbf{y}_l \cdot \text{Math.})}, \quad (\text{Equation } 27)$$

may be measured for each EBM block (e.g., EBM **102b-c**). In order to obtain such gradients, a similar architecture to the one used for measuring gradients of the parameters θ (e.g., synapses such as weights and biases) may be used. For example, consider an EBM block **102b** in layer $l+1$. After being coupled with the relay oscillator **108a**, the input oscillator $x_{\text{sub.l+1}}^{(j)}$ **204b** may be clamped to the state  custom-character $y_{\text{sub.l.sup.}(j)}$  custom-character (e.g., expectation value of output oscillator **208a**). By tuning the product of mass time frequency squared of the input oscillators **204b**, which encode the state  custom-character $y_{\text{sub.l.sup.}(j)}$  custom-character, such oscillators (e.g. input $x_{\text{sub.l+1}}^{(j)}$ **204b**) may undergo Langevin

dynamics with parameter degrees of freedom sharing a much slower time scale relative to the output oscillators **208b** which encode the state $y_{\text{sub}.l+1}$. By measuring the momentum degrees of freedom of the output oscillators **208a** encoding the state $y_{\text{sub}.l}$ (prior to their evolution), such momentum measurements can then be used to reconstruct the gradient in equation 27.

[0061] For example, a protocol for a forwards pass may be given as follows:

[0062] A thermodynamic system may do the following for each layer $l \in \{1, 2, \dots, K\}$: Clamp the input oscillators to the EBM block in layer l to the output of a previous layer $x_{\text{sub}.l} = y_{\text{sub}.l-1}$ (custom-character), tune the product of mass times frequency squared of the oscillators encoding the parameter degrees of freedom $\theta_{\text{sub}.l}$ such that they evolve on a much slower time scale relative to the output oscillators of the given EBM layer encoding the state $y_{\text{sub}.l}$. Perform multiple momentum measurements (or position measurements) of the parameter degrees of freedom (e.g., synapse values such as weights and biases). Compute the gradients

$$[00035] E \left[\frac{\partial \text{Math.}_{\text{sub}.l} (y_l | x_l)}{\partial \theta_{\text{sub}.l}^{(j)}} \right]_{p_{\text{sub}.l} (y_l | x_l)}$$

on an external classical post-processing device such as an FPGA/ASIC chip using the momentum (or position) measurements, wherein the index j runs over all parameters for the EBM block in layer l . Re-initialize the parameters to $\theta_{\text{sub}.l}$ (e.g., their values prior to the evolution). With the input oscillators initialized to the output of a previous layer $x_{\text{sub}.l} = y_{\text{sub}.l-1}$ (custom-character), tune the product of mass times frequency squared of the input oscillators of the given layer such that they evolve on a much slower time scale relative to the output oscillators of the given layer encoding the state $y_{\text{sub}.l}$. Perform multiple momentum (or position) measurements of the input oscillators. On the FPGA/ASIC chip, use such measurements to compute the gradients

$$[00036] E \left[\frac{\partial \text{Math.}_{\text{sub}.l} (y_l | \text{Math.}_{\text{sub}.l-1} \text{Math.}_{\text{sub}.l-1})}{\partial \text{Math.}_{\text{sub}.l-1} \theta_{\text{sub}.l-1}^{(j)}} \right]_{p_{\text{sub}.l} (y_l | \text{Math.}_{\text{sub}.l-1} \text{Math.}_{\text{sub}.l-1})}$$

The index j runs over all input neurons to the EBM block in layer l . Store all measured gradients such that they can be used during the backwards propagation step (e.g., backwards pass **302**).

[0063] In some embodiments during the backwards pass **302**, the protocol may start with the final output layer K (e.g., EBM **102d**). For example, for all layers, the goal may be to compute

$$\frac{\partial L}{\partial \theta_{\text{sub}.l}^{(j)}} = \text{Math.}_{\text{sub}.l} \frac{\partial L}{\partial \text{Math.}_{\text{sub}.l} y_l^{(n)} \text{Math.}_{\text{sub}.l}} \frac{\partial \text{Math.}_{\text{sub}.l} y_l^{(n)} \text{Math.}_{\text{sub}.l}}{\partial \theta_{\text{sub}.l}^{(j)}}, \text{ with } \quad (\text{equation } 28)$$

$$[00037] \frac{\partial L}{\partial \text{Math.}_{\text{sub}.l} y_l^{(j)} \text{Math.}_{\text{sub}.l}} = \text{Math.}_{\text{sub}.l} \frac{\partial L}{\partial \text{Math.}_{\text{sub}.l} y_{l+1}^{(s)} \text{Math.}_{\text{sub}.l}} \frac{\partial \text{Math.}_{\text{sub}.l} y_{l+1}^{(s)} \text{Math.}_{\text{sub}.l}}{\partial \text{Math.}_{\text{sub}.l} y_l^{(j)} \text{Math.}_{\text{sub}.l}}, \text{ and } \quad (\text{equation } 29)$$

$$L = \frac{1}{2} (y - \text{Math.}_{\text{sub}.K} y_K \text{Math.}_{\text{sub}.K})^2, \quad (\text{equation } 30)$$

where y may be an element of the training data set. Now for layer K , consider the perturbed potential given by

$$[00038] \text{Math.}_{\text{sub}.K}^{(B)} (y_K | x_K) = \text{Math.}_{\text{sub}.K} (y_K | x_K) + V(y_K), \quad (\text{equation } 31)$$

where $\epsilon \ll 1$ and $V(y_{\text{sub}.K})$ may be a potential that only depends on the output of the EBM block in layer K and the superscript (B) indicates the potential for the backwards pass. Measuring the momentum of the parameters, the gradient

$$[00039] E \left[\frac{\partial \text{Math.}_{\text{sub}.K}^{(B)} (y_K | x_K)}{\partial \theta_{\text{sub}.K}^{(j)}} \right] = \int dy_K \frac{\partial \text{Math.}_{\text{sub}.K} (y_K | x_K)}{\partial \theta_{\text{sub}.K}^{(j)}} \frac{e^{-\text{Math.}_{\text{sub}.K} (y_K | x_K) - \text{Math.}_{\text{sub}.K} V(y_K)}}{Z^{(B)}} \equiv I_1, \quad (\text{equation } 32)$$

may be obtained where

$$[00040] Z^{(B)} = \int dy_K e^{-\text{Math.}_{\text{sub}.K} (y_K | x_K) - \text{Math.}_{\text{sub}.K} V(y_K)}, \quad (\text{equation } 33)$$

and wherein $V(y_{\text{sub}.K})$ may be independent of $\theta_{\text{sub}.K}$. Now since $\epsilon \ll 1$, a Taylor expansion may be used for the exponential in equations 32 and 33 and may be written as

$$[00041] e^{-\text{Math.}_{\text{sub}.K} (y_K | x_K) - V(y_K)} = e^{-\text{Math.}_{\text{sub}.K} (y_K | x_K)} (1 - V(y_K) + \frac{1}{2} V(y_K)^2), \quad (\text{equation } 34)$$

In what follows, a partition function may be defined as

$$[00042] Z \equiv \int dy_K e^{-\text{Math.}_{\text{sub}.K} (y_K | x_K)}, \quad (\text{equation } 35)$$

Inserting equation 34 into equation 32 may result in

$$[00043] I_1^{(K,j)} = \int dy_K \frac{\partial \text{Math.}_{\text{sub}.K} (y_K | x_K)}{\partial \theta_{\text{sub}.K}^{(j)}} \left[\frac{e^{-\text{Math.}_{\text{sub}.K} (y_K | x_K)}}{Z} \left(\frac{1 - V(y_K) + \frac{1}{2} V(y_K)^2}{1 - \text{Math.}_{\text{sub}.K} \frac{V(y_K) e^{-\text{Math.}_{\text{sub}.K} (y_K | x_K)}}{Z} + \frac{1}{2} V(y_K)^2 \right) \right], \quad (\text{equation } 36)$$

Note that using

$$[00044] \int dy_K \frac{V(y_K) e^{-\text{Math.}_{\text{sub}.K} (y_K | x_K)}}{Z} = \text{Math.}_{\text{sub}.K} V(y_K) \text{Math.}_{\text{sub}.K}, \quad (\text{equation } 37)$$

where it may be understood that the expectation value may be taken with respect to the distribution in equation 26, and using

$$[00045] \frac{1}{1 - \text{Math.}_{\text{sub}.K} V(y_K) \text{Math.}_{\text{sub}.K} + \frac{1}{2} V(y_K)^2} = 1 + \text{Math.}_{\text{sub}.K} V(y_K) \text{Math.}_{\text{sub}.K} + \frac{1}{2} V(y_K)^2, \quad (\text{equation } 38)$$

equation 36 may be written as

$$\begin{aligned} I_1^{(K,j)} &= \int dy_K \frac{\partial \text{Math.}_{\text{sub}.K} (y_K | x_K)}{\partial \theta_{\text{sub}.K}^{(j)}} \\ &\quad \left[\frac{e^{-\text{Math.}_{\text{sub}.K} (y_K | x_K)}}{Z} (1 + \text{Math.}_{\text{sub}.K} V(y_K) \text{Math.}_{\text{sub}.K} - V(y_K) + \frac{1}{2} V(y_K)^2) \right] \\ &= \text{Math.}_{\text{sub}.K} \frac{\partial \text{Math.}_{\text{sub}.K} (y_K | x_K)}{\partial \theta_{\text{sub}.K}^{(j)}} \text{Math.}_{\text{sub}.K} + \text{Math.}_{\text{sub}.K} \frac{\partial \text{Math.}_{\text{sub}.K} (y_K | x_K)}{\partial \theta_{\text{sub}.K}^{(j)}} \text{Math.}_{\text{sub}.K} \text{Math.}_{\text{sub}.K} V(y_K) \text{Math.}_{\text{sub}.K} - \\ &\quad \text{Math.}_{\text{sub}.K} \frac{\partial \text{Math.}_{\text{sub}.K} (y_K | x_K)}{\partial \theta_{\text{sub}.K}^{(j)}} V(y_K) \text{Math.}_{\text{sub}.K} + \frac{1}{2} V(y_K)^2 \\ &= \text{Math.}_{\text{sub}.K} \frac{\partial \text{Math.}_{\text{sub}.K} (y_K | x_K)}{\partial \theta_{\text{sub}.K}^{(j)}} \text{Math.}_{\text{sub}.K} - \text{Cov}(V(y_K), \frac{\partial \text{Math.}_{\text{sub}.K} (y_K | x_K)}{\partial \theta_{\text{sub}.K}^{(j)}}) + \\ &\quad \frac{1}{2} V(y_K)^2. \end{aligned} \quad (\text{equation } 39)$$

From equation 61 below, the following may be used

$$[00047] \frac{\partial \text{Math.}_{\text{sub}.K} \text{Math.}_{\text{sub}.K}}{\partial \theta_{\text{sub}.K}^{(j)}} = -\text{Cov}(y_K, \frac{\partial \text{Math.}_{\text{sub}.K} (y_K | x_K)}{\partial \theta_{\text{sub}.K}^{(j)}}), \quad (\text{equation } 40)$$

Note that the goal may be to compute

[00077] $\text{Cov}(X, Y) = \text{Math. } XY \text{ Math.} - \text{Math. } X \text{ Math. } Y \text{ Math.},$ (equation62)

Therefore, the term

$$[00078] \frac{\partial \text{Math. } y_l \text{ Math.}}{\partial \phi}$$

can be obtained by computing the covariance between the output of the EBM in layer l and the gradient of the corresponding potential energy with respect to the parameters.

[0068] Next, computing the term

$$[00079] \frac{\partial L}{\partial \text{Math. } y_l^{(j)} \text{ Math.}}$$

is discussed (where without loss of generality the index i is removed) by starting with the final layer, and then consider the hidden layers of the deep neural network. For the final layer, using equation 8 may result in

$$[00080] \frac{\partial L}{\partial \text{Math. } y_K^{(j)} \text{ Math.}} = -(\mathbf{y}^{(t)} - \text{Math. } y_K^{(1)} \text{ Math.}), \quad (\text{equation63})$$

where the index (j) may be set to (1) since the final layer of the model may have a single output. For the hidden layer, the chain rule may be used to write

$$[00081] \frac{\partial L}{\partial y_l^{(j)} \text{ Math.}} = \text{Math.} \frac{\partial L}{\partial y_{l+1}^{(s)} \text{ Math.}} \frac{\partial \text{Math. } y_{l+1}^{(s)} \text{ Math.}}{\partial \text{Math. } y_l^{(j)} \text{ Math.}}, \quad (\text{equation64})$$

where the set $\text{custom-character.sub.j.sup.(l)}$ includes all indices for which the output nodes $y_{l+1}^{(s)}$ are coupled to

$$[00082] x_l^{(j)} = \text{Math. } y_l^{(j)} \text{ Math.}$$

The second term on the right-hand side of equation 65 may be computed as follows. First write out the derivative of the expectation value explicitly as

$$[00083] \frac{\partial \text{Math. } y_{l+1}^{(s)} \text{ Math.}}{\partial \text{Math. } y_l^{(j)} \text{ Math.}} = \int d\mathbf{y}^{(s)} y_{l+1}^{(s)} \frac{\partial}{\partial \text{Math. } y_l^{(j)} \text{ Math.}} \frac{e^{-\phi_{l+1}(\mathbf{y}_{l+1} \text{ Math. } y_l \text{ Math.})}}{Z(\text{Math. } y_l \text{ Math.}, \dots)}, \quad (\text{equation65})$$

It may be noted that the input to the EBM block in layer l+1 may be $x_{l+1} = \text{custom-character.sub.l} \text{ custom-character}$ since the relay oscillator imparts its state to x_{l+1} . As such, x_{l+1} may be replaced with $\text{custom-character.sub.l} \text{ custom-character}$ in equation 65. Now, computing the derivative in equation 65, may result in

$$[00084] \frac{\partial}{\partial \text{Math. } y_l^{(j)} \text{ Math.}} \frac{e^{-\phi_{l+1}(\mathbf{y}_{l+1} \text{ Math. } y_l \text{ Math.})}}{Z(\text{Math. } y_l \text{ Math.}, \dots)} = -p(y_{l+1} \text{ Math. } y_l \text{ Math.}, \dots) \left(\frac{\partial \phi_{l+1}(\mathbf{y}_{l+1} \text{ Math. } y_l \text{ Math.})}{\partial \text{Math. } y_l^{(j)} \text{ Math.}} - \text{Math.} \frac{\partial \phi_{l+1}(\mathbf{y}_{l+1} \text{ Math. } y_l \text{ Math.})}{\partial \text{Math. } y_l^{(j)} \text{ Math.}} \right) \text{Math.}$$

Inserting equation 66 into equation 65, may result in

$$[00085] \frac{\partial \text{Math. } y_{l+1}^{(s)} \text{ Math.}}{\partial \text{Math. } y_l^{(j)} \text{ Math.}} = -\text{Cov}(y_{l+1}^{(s)}, \frac{\partial \phi_{l+1}(\mathbf{y}_{l+1} \text{ Math. } y_l \text{ Math.})}{\partial \text{Math. } y_l^{(j)} \text{ Math.}}), \quad (\text{equation67})$$

where a method is used that is similar to the method that went into deriving equation 61.

Training Deep EBMs Using Mean-Field Forwards and Backwards Propagation and Additional Relay Oscillators

[0069] FIG. 4A is a high-level diagram illustrating a plurality of energy based models (EBMs) that may be used to determine gradient terms during a forwards pass used to update synapses, wherein gradient terms are obtained on a plurality of relay oscillators thus requiring fewer measurements, according to some embodiments.

[0070] In some embodiments, training a deep energy based model (EBM) may be performed using a mean-field forwards (e.g., forwards pass **400**) and backwards propagation (e.g., backwards pass **450**) method. For example, the expectation value of the output of a given EBM block (e.g., EBM **102a**) may be used as an input to the next block (EBM **102b**). The parameters (e.g., synapses such as weights and biases) of energy potentials **206a-d** are trained by computing gradients of a loss function similar to what is done in deep neural networks. Gradients of the energy function in each EBM block **102a-d** may be stored in the position degrees of freedom of one or more relay oscillators **406a-d** using a mean-field relay oscillator protocol during both the forwards (**400**) and backwards (**450**) pass. However, during the backwards pass **450**, a perturbation to the energy potential **206a-d** in each EBM block **102a-d** may be turned on. The perturbed potential may be achieved through a linear coupling between relay oscillators that encode the relevant gradients and output neurons of the EBM blocks. By applying the chain rule, the gradients may be stored in relay oscillators and can be used to compute gradients of loss function with respect to the parameters (e.g., synapses such as weights and biases) of each EBM block. Such gradients may be then used to train the EBM parameters. An example illustration of the overall forwards and backwards architecture for training parameters of a deep EBM using a mean-field approach is shown in FIGS. 4A and 4B, with example details in their implementation described below.

Mean-Field Forwards Propagation Using Additional Relay Oscillators

[0071] In some embodiments, operations are performed during a forwards pass **402**. Gradients obtained during the forwards pass **402** may be used to compute gradients of a loss function with respect to parameters $\theta = (\theta_{\text{sub.1}}, \theta_{\text{sub.2}}, \dots, \theta_{\text{sub.K}})$ (e.g., synapses such as weights and biases) of each EBM block **102a-d** part of the larger deep EBM. It may be assumed that a deep EBM may be composed of $K \geq 1$ EBM blocks, with the EBM for block $1 \leq l \leq K$ having parameters $\theta_{\text{sub.l}}$ for energy potentials **206a-d**.

[0072] In some embodiments, position degrees of freedom of input oscillators for a deep EBM network may be clamped to the values x . It may be assumed that the EBM in the first block has a conditional energy function given by $\epsilon_{\text{sub.}\theta_{\text{sub.1}}}(\mathbf{y}_{\text{sub.1}}|x)$ (e.g., energy potential **206a-d**) with output oscillators encoding the values $y_{\text{sub.1}}$. The mean-field relay oscillator scheme, wherein the position degrees of freedoms of the intermediate relay oscillators labelled as $r_{\text{sub.1}}$, may be used to clamp the position degree of freedom of the final output relay oscillators to $x_{\text{sub.1}} = \text{custom-character.sub.1} \text{ custom-character}$ (e.g., see **420** of FIG. 4A). The output of EBM **102a** may be used as input to the next EBM block **102b** with potential energy $\epsilon_{\text{sub.}\theta_{\text{sub.2}}}(\mathbf{y}_{\text{sub.2}}|x_{\text{sub.1}})$.

[0073] In some embodiments, consider the l'th EBM block with $1 \leq l \leq K$. Suppose the output $y_{\text{sub.l}}$ is of size $M \geq 1$ (i.e. there may be M output oscillators encoding the vector $y_{\text{sub.l}}$). In addition to the relay oscillators which may be used to encode the expectation value of the output $y_{\text{sub.l}}$ into $x_{\text{sub.l}} = \text{custom-character.sub.l} \text{ custom-character}$, additional relay oscillators may be used for each EBM block to store the gradient terms of the form

$$[00086] \mathbb{E} \left[\frac{\partial \epsilon_l(\mathbf{y}_l \text{ Math. } x_{l-1})}{\partial \text{Math. } y_{l-1}^{(j)} \text{ Math.}} \right]_{y_l \sim p_l(\mathbf{y}_l \text{ Math. } x_{l-1})}, \quad (\text{equation68})$$

(e.g., unperturbed gradients of inputs **408a**) where the probability distribution may be

$$[00087] p_l(\mathbf{y}_l | x_{l-1}) = e^{-\epsilon_l(\mathbf{y}_l | x_{l-1})} / Z.$$

For example, M final output relay oscillators may be used to store the gradients given by equation 68 for each index $1 \leq j \leq M$. Note that the coupling term $\Sigma_{\text{sub.t}=1}^{\text{sup.N}} \lambda_{\text{sub.t}} \text{sup.(2)} [\phi_{\text{sub.r.sub.t}} - \alpha_{\text{sub.1}} \partial_{\text{sub.}\theta_{\text{sub.l}} \text{sub.(j)}} \epsilon_{\text{sub.}\theta_{\text{sub.l}}}(\mathbf{y}_{\text{sub.l}} | \text{custom-character.sub.l-1} \text{ custom-character})]_{\text{sup.2}}$ in equation 106 may be replaced with

$$[00088] \text{Math.} \frac{N}{t=1} \frac{(2)}{t} \left[r_t - \frac{1}{\alpha_{\text{sub.1}}} \frac{\partial \epsilon_l(\mathbf{y}_l \text{ Math. } x_{l-1})}{\partial \text{Math. } y_{l-1}^{(j)} \text{ Math.}} \right]^2,$$

where $\alpha_{\text{sub.1}}$ may be a constant to ensure that the gradients, when multiplied by $\alpha_{\text{sub.1}}$, may have units of position since the gradient term is coupled to the position degree of freedom of the relay oscillator. The latter relay oscillators may also be used during the backwards pass as is

described.

[0074] In some embodiments, the l'th EBM block may have M' parameters (i.e. $\theta_{\text{sub.l}}$ may be a vector of size M'). In addition to using a mean-field relay oscillator protocol to encode the gradients in equation 68, another batch of relay oscillators may be used to obtain gradients of the form

$$[00089] \mathbb{E}\left[\frac{\partial \mathcal{E}_{\text{sub.l}}(\mathbf{y}_l, \text{Math. } \mathbf{x}_{l-1})}{\partial \boldsymbol{\theta}}\right]_{\mathbf{y}_l \sim p_{\text{sub.l}}(\mathbf{y}_l, \text{Math. } \mathbf{x}_{l-1})}, \quad (\text{equation69})$$

(e.g., unperturbed gradients of synapses **410a**). Storing the gradients of equation 69 into the position degrees of freedom of M' final output relay oscillators can be achieved by following a mean-field relay oscillator protocol. For gradients of the form of equation 69, the coupling may have the form

$$[00090] \text{Math. } \mathbf{r}_{t=1}^{M'} = \frac{(3)}{2} \left[r_t - \frac{\partial \mathcal{E}_{\text{sub.l}}(\mathbf{y}_l, \text{Math. } \mathbf{x}_{l-1})}{\partial \boldsymbol{\theta}} \right]^2,$$

for some constant $\alpha_{\text{sub.2}}$.

[0075] In some embodiments, it may be assumed that the output of the K'th EBM block is a scalar and can be labeled as $y_{\text{sub.K}}$. A mean-field relay oscillator protocol may be used to store the expectation value custom-character in the state of a relay oscillator.

Mean-Field Backwards Propagation Using Additional Relay Oscillators

[0076] FIG. 4B is a high-level diagram illustrating a plurality of energy based models (EBMs) that may be used to determine gradient terms during a backwards pass used to update synapses, wherein gradient terms are obtained on a plurality of relay oscillators thus requiring fewer measurements, according to some embodiments.

[0077] In some embodiments of a deep neural network, the parameters (e.g., synapses such as weights and biases) of energy potentials **206a-d** may be trained by defining a loss function and computing gradients of the loss function with respect to the model parameters using the chain rule. In some embodiments with a deep EBM architecture, where each block of the network may be presented by an EBM, the expectation value of the output of a given block may be used as input to the next block. In some embodiments, the loss function may be used to train the model parameters.

[0078] For example, a mean squared error (MSE) loss function may be used and may be represented by

$$[00091] \text{MSE} = \frac{1}{2N} \sum_{i=1}^N (\mathbf{y}_i^{(t)} - \text{Math. } \mathbf{y}_K^{(i)} \cdot \text{Math. })^2 \quad (\text{equation70}) \quad \text{where } L_i = \frac{1}{2} (\mathbf{y}_i^{(c)} - \{\mathbf{y}_K^{(i)}\}_J)^2, \quad (\text{equation71})$$

$$= \frac{1}{N} \cdot \text{Math. } L_i,$$

In equation 70, N may be the total number of training examples. The output oscillator custom-character.sub.K.sup.(i) custom-character **404** represents the expectation value of the output of the K'th EBM block for the i'th training example, and $y_{\text{sub.i}}^{\text{sup.(t)}}$ as the ground truth. In some embodiments, it may be desired to compute terms of the form

$$[00092] \frac{\partial L_i}{\partial \boldsymbol{\theta}}, \quad (\text{equation72})$$

for all $1 \leq K$ and where $\theta_{\text{sub.l}}^{\text{sup.(j)}}$ may be the j'th parameter (e.g., synapses such as weights and biases) of $\epsilon_{\text{sub.l}}$. Using the chain rule, equation 72 may be written as

$$[00093] \frac{\partial L_i}{\partial \boldsymbol{\theta}} = \frac{\partial L_i}{\partial \text{Math. } \mathbf{y}_l^{(j)} \cdot \text{Math. }} \cdot \frac{\partial \text{Math. } \mathbf{y}_l^{(j)} \cdot \text{Math. }}{\partial \boldsymbol{\theta}}, \quad (\text{equation73})$$

Without loss of generality, the index i in L.sub.i may be omitted and it may be written as L. In some embodiments, the term

$$[00094] \frac{\partial \text{Math. } \mathbf{y}_l^{(j)} \cdot \text{Math. }}{\partial \boldsymbol{\theta}}$$

may be given by

$$[00095] \frac{\partial \text{Math. } \mathbf{y}_l^{(j)} \cdot \text{Math. }}{\partial \boldsymbol{\theta}} = -\text{Cov}(\mathbf{y}_l^{(j)}, \frac{\partial (\mathbf{y}_l | \mathbf{x}_{l-1})}{\partial \boldsymbol{\theta}})_{p(\mathbf{y}_l | \mathbf{x}_{l-1})}, \quad (\text{equation74})$$

where $\text{Cov}(X, Y) = \text{Math. } XY \cdot \text{Math. } - \text{Math. } X \cdot \text{Math. } \cdot \text{Math. } Y \cdot \text{Math. }$

may be the covariance of two random variables X and Y. The final layer K may be written as

$$[00096] \frac{\partial L}{\partial \text{Math. } \mathbf{y}_K \cdot \text{Math. }} = -(\mathbf{y}^{(t)} - \text{Math. } \mathbf{y}_K \cdot \text{Math. }), \quad (\text{equation75}).$$

The hidden layers may be written as

$$[00097] \frac{\partial L}{\partial \text{Math. } \mathbf{y}_l^{(j)} \cdot \text{Math. }} = \text{Math. } \frac{\partial L}{\partial \text{Math. } \mathbf{y}_{l+1}^{(s)} \cdot \text{Math. }} \cdot \frac{\partial \text{Math. } \mathbf{y}_{l+1}^{(s)} \cdot \text{Math. }}{\partial \text{Math. } \mathbf{y}_l^{(j)} \cdot \text{Math. }}, \quad (\text{equation76})$$

where the set custom-character.sub.j.sup.(l) includes all indices for which the output nodes $y_{\text{sub.l+1}}^{\text{sup.(s)}}$ are coupled to $x_{\text{sub.l}}^{\text{sup.(j)}}$ =

custom-character.sub.l.sup.(j) custom-character. In some embodiments, the following may be used

$$[00098] \frac{\partial \text{Math. } \mathbf{y}_{l+1}^{(s)} \cdot \text{Math. }}{\partial \text{Math. } \mathbf{y}_l^{(j)} \cdot \text{Math. }} = -\text{Cov}(\mathbf{y}_{l+1}^{(s)}, \frac{\partial \mathcal{E}_{\text{sub.l+1}}(\mathbf{y}_{l+1}, \text{Math. } \mathbf{y}_l, \text{Math. })}{\partial \text{Math. } \mathbf{y}_l^{(j)} \cdot \text{Math. }})_{p_{\text{sub.l+1}}(\mathbf{y}_{l+1}, \text{Math. } \mathbf{y}_l, \text{Math. })}, \quad (\text{equation77})$$

wherein the input $x_{\text{sub.l+1}}$ to the EBM block in layer l+1 may be given by custom-character.sub.l custom-character given the dynamics of the relay oscillators.

[0079] In some embodiments, a mean-field relay oscillator protocol can be used to obtain the gradients in equations 74 and 77. For example, a step during a backwards pass may be to use a perturbed energy potential **206a-d** given by

$$[00099] \tilde{\mathcal{V}}_l^{(B)}(\mathbf{y}_l, \text{Math. } \mathbf{x}_{l-1}) = \mathcal{V}_l(\mathbf{y}_l, \text{Math. } \mathbf{x}_{l-1}) + \epsilon V(\mathbf{y}_l), \quad (\text{equation78}) \quad \text{for } 1 \leq l \leq K \text{ and } \epsilon \ll 1.$$

For example, during the backwards pass, a potential $V(y_{\text{sub.l}})$ is added by turning on ϵ to a small but non-zero value. An example of an appropriate choice of the potential $V(y_{\text{sub.l}})$ is given below. The (B) superscript is added in $\{\tilde{\text{over } (\epsilon)}\}_{\text{sub.}\theta_{\text{sub.l}}^{\text{sup.(B)}}(y_{\text{sub.l}} | x_{\text{sub.l-1}})}$ to indicate the modified energy potential used during the backwards pass. By way of example, the usefulness of using a perturbed potential given in equation 78 during the backwards pass is as follows. Start with the case where $l=K$. As during the forwards pass, a mean-field relay oscillator scheme may be used to encode the gradient

$$[00100] \mathbb{E}\left[\frac{\partial \tilde{\mathcal{V}}_K^{(B)}(\mathbf{y}_K, \text{Math. } \mathbf{x}_{K-1})}{\partial \boldsymbol{\theta}}\right] = \int d\mathbf{y}_K \frac{\partial \tilde{\mathcal{V}}_K^{(B)}(\mathbf{y}_K | \mathbf{x}_{K-1})}{\partial \boldsymbol{\theta}} \frac{e^{-\beta(\mathcal{V}_K(\mathbf{y}_K | \mathbf{x}_{K-1}) - \epsilon V(\mathbf{y}_K))}}{Z^{(B)}} \equiv I_1^{(K,j)}, \quad (\text{equation79})$$

into the position degrees of freedom of output relay oscillators **414d**. In equation 79 the following term is used

$$[00101] Z^{(B)} = \int d\mathbf{y}_K e^{-\beta(\mathcal{V}_K | \mathbf{x}_{K-1}) - \epsilon V(\mathbf{y}_K)}, \quad (\text{equation80}).$$

Since $\epsilon \ll 1$, a Taylor expansion may be used for the exponential in equations 79 and 80 and only leading order terms in ϵ may be kept. Doing so may result in

$$[00102] I_1^{(K,j)} = \text{Math. } \frac{\partial \mathcal{V}_K(\mathbf{y}_K | \mathbf{x}_{K-1})}{\partial \boldsymbol{\theta}} \cdot \text{Math. } - \epsilon \text{Cov}(V(\mathbf{y}_K), \frac{\partial \mathcal{V}_K(\mathbf{y}_K | \mathbf{x}_{K-1})}{\partial \boldsymbol{\theta}}) + \quad (\text{equation81}).$$

Similar to equation 61 the following may be computed

$$[00103] \frac{\partial \text{.Math. } y_K \text{.Math.}}{\partial \text{.Math. } y_K} = -\text{Cov}(y_K, \frac{\partial \text{.Math. } x_{K-1}}{\partial \text{.Math. } y_K}), \quad (\text{equation82}).$$

In some embodiments, the goal may be to compute

$$[00104] \frac{\partial L}{\partial \text{.Math. } y_K} = \frac{\partial L}{\partial \text{.Math. } y_K} \frac{\partial \text{.Math. } y_K \text{.Math.}}{\partial \text{.Math. } y_K} = g_K \frac{\partial \text{.Math. } y_K \text{.Math.}}{\partial \text{.Math. } y_K}, \quad (\text{equation83})$$

where the following definition may be used

$$[00105] g_K \equiv \frac{\partial L}{\partial \text{.Math. } y_K \text{.Math.}}, \quad (\text{equation84}).$$


Note that since K is the final layer, the following may result

$$[00106] g_K = \frac{\partial L}{\partial \text{.Math. } y_K \text{.Math.}} = -(\text{y} - \text{.Math. } y_K \text{.Math.}), \quad (\text{equation85})$$

where .sub.K may be encoded in the final output relay oscillator **404**. As such, the perturbed potential energy function may be chosen to be given by

$$[00107] V(y_K) = g_K y_K. \quad (\text{equation86})$$

Such a potential term can be achieved by coupling the final output relay oscillator **404** whose position degree of freedom may be static at

.sub.K with the oscillator encoding the output oscillator y.sub.K. Inserting equation 86 into equation 81 and rearranging terms, may result in

$$[00108] I_1^{(K,j)} - \text{.Math.} \frac{\partial \text{.Math. } x_K \text{.Math.}}{\partial \text{.Math. } y_K} \text{.Math.} = -\epsilon g_K \text{Cov}(y_K, \frac{\partial \text{.Math. } x_K \text{.Math.}}{\partial \text{.Math. } y_K}) + \quad (\text{equation87}).$$

$$= g_K \frac{\partial \text{.Math. } y_K \text{.Math.}}{\partial \text{.Math. } y_K} = \frac{\partial L}{\partial \text{.Math. } y_K},$$

Let {tilde over (φ)}.sub.r.sub.1.sup.(K,j) be relay oscillators **410d** whose position degree of freedom may be static at

$$[00109] \text{.Math.} \frac{\partial \text{.Math. } x_K \text{.Math.}}{\partial \text{.Math. } y_K} \text{.Math.}$$

(e.g., the forwards gradients of synapses) and let {tilde over (φ)}.sub.r.sub.2.sup.(K,j) be relay oscillators **414d** whose position degree of freedom may be static at I.sub.1.sup.(K,j) (e.g., the backwards gradients of synapses). A third set of relay oscillators storing gradients of the loss function (relay oscillators **418d**) may be added and labelled as {tilde over (φ)}.sub.r.sub.3.sup.(K,j) with mass m.sub.f and frequency ω.sub.f which may be coupled to relay oscillator {tilde over (φ)}.sub.r.sub.1.sup.(K,j) **410d** and relay oscillator {tilde over (φ)}.sub.r.sub.2.sup.(K,j) **414d** (wherein {tilde over (φ)}.sub.r.sub.1.sup.(K,j) **410d** and {tilde over (φ)}.sub.r.sub.2.sup.(K,j) **414d** may be both treated as static) as in equation 108. However, the coupling term may be given by the three-body coupling λ.sub.3(t){tilde over (φ)}.sub.r.sub.3.sup.(K,j){tilde over (φ)}.sub.r.sub.2.sup.(K,j){tilde over (φ)}.sub.r.sub.1.sup.(K,j). Following a relay oscillator protocol such as described herein and using the result in equation 87, the position degree of freedom {tilde over (φ)}.sub.r.sub.3.sup.(K,j) of relay oscillator **418d** may be static at the value

$$[00110] \frac{\partial L}{\partial \text{.Math. } y_K}$$

if the coupling λ.sub.3 is set as follows,

$$[00111] \lambda_3 = -\frac{m_f \omega_f^2}{\epsilon}.$$

Alternatively, a coupling of the form λ.sub.3(t){tilde over (φ)}.sub.r.sub.3.sup.(K,j)−c.sub.1({tilde over (φ)}.sub.r.sub.2.sup.(K,j)−{tilde over (φ)}.sub.r.sub.1.sup.(K,j))}.sup.2 for some constant c.sub.1 may be used. For example, it may be chosen that c.sub.1=1/ε and λ.sub.3>>m.sub.fω.sub.f.sup.2/2.

[0080] In some embodiments, layers l<K may be considered. Recall that

$$[00112] \frac{\partial L}{\partial \text{.Math. } y_l} = \text{.Math.} \frac{\partial L}{\partial \text{.Math. } y_l^{(n)} \text{.Math.}} \frac{\partial \text{.Math. } y_l^{(n)} \text{.Math.}}{\partial \text{.Math. } y_l}, \quad (\text{equation88}) \text{ with}$$

$$\frac{\partial L}{\partial \text{.Math. } y_l^{(n)} \text{.Math.}} = \text{.Math.} \frac{\partial L}{\partial \text{.Math. } y_{l+1}^{(s)} \text{.Math.}} \frac{\partial \text{.Math. } y_{l+1}^{(s)} \text{.Math.}}{\partial \text{.Math. } y_l^{(n)} \text{.Math.}}, \quad (\text{equation89}).$$

In equation 89, the term

$$[00113] \frac{\partial L}{\partial \text{.Math. } y_{l+1}^{(s)} \text{.Math.}}$$

may be meant to be pre-computed in the previous layer (i.e. when considering the EBM block in layer l,

$$[00114] \frac{\partial L}{\partial \text{.Math. } y_{l+1}^{(s)} \text{.Math.}}$$

should have already been computed in layer l+1). Such a term may arise from the perturbation potential. In equation 89, calculation of the term

$$[00115] \frac{\partial \text{.Math. } y_{l+1}^{(s)} \text{.Math.}}{\partial \text{.Math. } y_l^{(n)} \text{.Math.}}$$

may be needed. In some embodiments, it may be shown that

$$[00116] \text{.Math.} \frac{\partial L}{\partial \text{.Math. } y_{l+1}^{(s)} \text{.Math.}} \frac{\partial \text{.Math. } y_{l+1}^{(s)} \text{.Math.}}{\partial \text{.Math. } y_l^{(n)} \text{.Math.}} = - \text{.Math.} \frac{\partial L}{\partial \text{.Math. } y_{l+1}^{(s)} \text{.Math.}} \text{Cov}(y_{l+1}^{(s)}, \frac{\partial \text{.Math. } y_{l+1} \text{.Math.}}{\partial \text{.Math. } y_l^{(n)} \text{.Math.}}), \quad (\text{equation90})$$

(see equation 67). Note that the covariance term in 90 vanishes if the index s does not belong to the set .sub.j.sup.(l). As such, equation 90 may be simplified by summing over all output indices for the EBM block in layer l+1 (the reason for doing so may become clearer below). The following may result

$$[00117] \text{.Math.} \frac{\partial L}{\partial \text{.Math. } y_{l+1}^{(s)} \text{.Math.}} \frac{\partial \text{.Math. } y_{l+1}^{(s)} \text{.Math.}}{\partial \text{.Math. } y_l^{(n)} \text{.Math.}} = - \frac{\partial L}{\partial \text{.Math. } y_{l+1} \text{.Math.}} \text{.Math.} \text{Cov}(y_{l+1}, \frac{\partial \text{.Math. } y_{l+1} \text{.Math.}}{\partial \text{.Math. } y_l^{(n)} \text{.Math.}}), \quad (\text{equation91}).$$

Now given the perturbed potential in equation 78 for l<K, a mean field relay oscillator scheme may be used, such as may be done during the forwards pass, to encode the gradient

$$[00118] \mathbb{E}[\frac{\partial \text{.Math. } x_{l+1} \text{.Math.}}{\partial \text{.Math. } y_l^{(n)} \text{.Math.}}] = \int dy_{l+1} \frac{\partial \text{.Math. } x_{l+1} \text{.Math.}}{\partial \text{.Math. } y_l^{(n)} \text{.Math.}} e^{-\frac{V(y_{l+1})}{Z^{(B)}}} \equiv I_2^{(l+1,j)}, \quad (\text{equation92})$$

(e.g., backwards gradients of inputs) in the position degree of freedom of output relay oscillators **412a-d**. Taylor expanding and keeping terms to leading order in ε, may result in

$$[00119] I_2^{(l+1,j)} = \text{.Math.} \frac{\partial \text{.Math. } x_{l+1} \text{.Math.}}{\partial \text{.Math. } y_l^{(n)} \text{.Math.}} \text{.Math.} - \text{Cov}(V(y_{l+1}), \frac{\partial \text{.Math. } x_{l+1} \text{.Math.}}{\partial \text{.Math. } y_l^{(n)} \text{.Math.}}) + \quad (\text{equation93}).$$

(9) Use a mean-field relay oscillator protocol to encode the gradient

$$[00133] E\left[\frac{\partial \tilde{V}_K^{(B)}}{\partial \text{Math. } y_{K-1}^{(B)}} \cdot \text{Math. } x_K\right] \equiv I_2^{(K,j)}$$

into the position degree of freedom of the relay oscillator $\phi.\text{sub.r.sub.2.sup.}(K,j)$ **412d**. (10) Couple a third batch of relay oscillators $\phi.\text{sub.r.sub.3.sup.}(K,j)$ **416d** (for each j) with masses $m.\text{sub.f}$ and frequencies $\omega.\text{sub.f}$ to $\phi.\text{sub.r.sub.2.sup.}(K,j)$ **412d** and $\phi.\text{sub.r.sub.1.sup.}(K,j)$ **408d** as in equation 108 with $\phi.\text{sub.r.sub.2.sup.}(K,j)$ and $\phi.\text{sub.r.sub.1.sup.}(K,j)$ treated as static) and using the coupling $\lambda.\text{sub.3}(t)(\phi.\text{sub.r.sub.3.sup.}(K,j) - c.\text{sub.1}(\phi.\text{sub.r.sub.2.sup.}(K,j) - \phi.\text{sub.r.sub.1.sup.}(K,j)))$.sup.2) and set $c.\text{sub.1}=1/\epsilon$ and choose

$$[00134] \quad 3 \gg \frac{1}{2} m_f \frac{2}{f}.$$

Tune the product $m.\text{sub.f} \omega.\text{sub.f}$.sup.2 such that the position degree of freedom of $\phi.\text{sub.r.sub.3.sup.}(K,j)$ **416d** remains static at

$$[00135] \frac{\partial L}{\partial \text{Math. } y_{K-1}^{(B)}} \cdot \text{Math.}$$

(11) Measure the position degree of freedom of the relay oscillators $\{\tilde{\phi}\}.\text{sub.r.sub.3.sup.}(K,j)$ **410d** for each index j and send the measurement results to an external classical post-processing device. (12) End the segment of the if statement where $l=K$ is true. (13) Else where the segment of the if statement where $l=K$ is false, the following may be performed. (14) Set the perturbed potential energy $V(y.\text{sub.l})=g.\text{sub.l}.\text{Math. } y.\text{sub.l}$ by linearly coupling the relay oscillators $\phi.\text{sub.r.sub.3.sup.}(l+1,j)$ **416a-b** (computed in the previous layer) to $y.\text{sub.l.sup.}(j)$ (for each index j). (15) Repeat the steps (6)-(11) but with the index K replaced with l (e.g., relay oscillators **406a-b**). The index j in step (7), (8) and (11) runs over all parameters (e.g., synapses such as weights and biases) for the EBM block in layer l . The index j in steps (9) and (10) runs over all input neurons to the EBM block in layer l .

[0084] In some embodiments, all the gradients

$$[00136] \frac{\partial L}{\partial y}$$

may be encoded in the position degrees of freedom of relay oscillators $\{\tilde{\phi}\}.\text{sub.3.sup.}(l,j)$ **418a-d**, and the system can measure the position of these relay oscillators to perform the final θ parameter (e.g., synapses such as weights and biases) updates on an external classical post-processing device.

Using Relay Oscillators to Obtain Gradients and Perform Natural Gradient Descent in a Fully Analogue Way

[0085] FIG. 5 is a high-level diagram illustrating gradient terms, that may be used to update synapse values, are obtained using relay oscillators in an analogue way, according to some embodiments.

[0086] In some embodiments, relay oscillators (ROs) **406a-d** can be used in such a way that their position degree of freedom reaches equilibrium at the space-averaged value of the gradient of the energy function of a given EBM. Such a protocol may be used to train deep EBMs using a mean-field forwards and backwards propagation protocol. In some embodiments, Natural Gradient Descent (NGD) can be implemented in a fully analogue fashion using a mean-field relay oscillator protocol.

Natural Gradient Descent

[0087] In some embodiments, parameters of an EBM (e.g., synapses such as weights **504** and biases **506**) can be trained following an NGD protocol. The Bogoliubov-Kubo-Mori (BKM) metric meets desirable asymptotic optimality criteria. The BKM metric for energy based models may be defined as

$$[00137] \quad \text{BKM}(\cdot)_{j,k} = \int (\partial_j p(x)) (\partial_k \log p(x)) dx, \quad (\text{equation97}) \text{ where } p(x) = \exp(-\langle x \rangle) / Z(\cdot).$$

Using this definition of $p.\text{sub.}\theta(x)$, both terms in equation 97 may be calculated. The first term results in

$$[00138] \quad \partial_j p(x) = (\mathbb{E}_{z \sim p(z)} [\partial_j (z)] - \partial_j (x)) p(x), \quad (\text{equation98})$$

and the second term may be given by

$$[00139] \quad \partial_k \log p(x) = (-\partial_k (x) + \mathbb{E}_{y \sim p(y)} [\partial_k (y)]), \quad (\text{equation99}).$$

Putting equations 98 and 99 into equation 97, results in

$$[00140] \quad (\text{equation100}). \quad \text{BKM}(\cdot)_{j,k} = \mathbb{E}_{x \sim p(x)} [\partial_j (x) \partial_k (x)] - \mathbb{E}_{x \sim p(x)} [\partial_j (x)] \mathbb{E}_{y \sim p(y)} [\partial_k (y)].$$

Given the BKM metric in equation 100, the parameters (e.g., synapses such as weights **504** and biases **506**) may be updated as

$$[00141] \quad (\text{equation101}) \quad t_{+1} = t + \frac{1}{t} \left((t) (-\nabla_t p(t) - N \left(\frac{1}{N} \text{Math. } \nabla_t (t, x_{t_i}) - \mathbb{E}_{x \sim p(x)} [\nabla_t (t, x)] \right) \right)$$

where $\lambda.\text{sub.t}$ may be the learning rate and $\text{custom-character.sup.}+(\cdot)$ may be the Moore-Penrose pseudo-inverse of the information matrix $\text{custom-character}(\theta)$. A special choice for the information matrix may be to set $\text{custom-character}(\theta) = \text{custom-character.sup.}.\text{BKM}(\theta)$.

Mean-Field Relay Oscillators for Computing Gradients

[0088] In some embodiments, terms of the form

$$[00142] \quad \mathbb{E}_{(x,z) \sim p(x,z)} [\partial_j (x,z) \partial_k (x,z)] \quad (\text{equation102}) \text{ and}$$

$$\mathbb{E}_{(x,z) \sim p(x,z)} [\partial_j (x,z)] \mathbb{E}_{(x,z) \sim p(x,z)} [\partial_k (x,z)], \quad (\text{equation103})$$

which may be required in equation 100, can be stored in the position degree of freedom of relay oscillators (Ros) **406a-d**. Terms of the form $\text{custom-character.sub.}(x,z) p.\text{sub.}\theta.\text{sub.}(x,z) [\partial.\text{sub.}\theta.\text{sub.}j.\text{sub.}\theta(x,z)]$ may also be needed when performing mean-field forwards and backwards propagation. The following are example steps of a process as described herein.

[0089] Step 1: An EBM block with energy function $e.\text{sub.}\theta(x,z)$ is considered. Relay oscillators such as **510** which may be coupled to the neurons **504** of a given EBM, may be used such that the final output relay oscillators **512a-c** position degree of freedom corresponds to a trajectory given by the expectation value of the desired gradient. For example, a spatial relay oscillator scheme may be used. Other examples of relay oscillator schemes include a temporal (wherein a relay oscillator is repetitively used to obtain multiple gradients) or a sequence (wherein a chain of relay oscillators have increasingly large product of mass and frequency squared) based protocols. The following potential energy function may be considered for a spatial relay oscillator scheme

[00143] (equation104)

$$V_{\text{BKM}}^{(1)} = \frac{1}{2} m_r(t) \dot{r}(t)^2 \frac{N}{\text{Math. } r_j} + \frac{1}{2} m_r(t) \ddot{r}(t)^2 \frac{2}{r_{N+1}} + (x,z) + \frac{N}{\text{Math. } t} \frac{(1)}{r_t - 1} \partial_j (x,z) \partial_k (x,z) + r_{N+1}(t) \frac{N}{\text{Math. } (r_{N+1} - r_j)}$$

Following a mean-field relay oscillator protocol, the coupling term $\Sigma.\text{sub.t}=1.\text{sup.} N \lambda.\text{sub.t}.\text{sup.}(1)$

$[\phi.\text{sub.r.sub.t} - \alpha.\text{sub.1} \partial.\text{sub.}\theta.\text{sub.}j.\text{sub.}\theta(x,z) \partial.\text{sub.}\theta.\text{sub.}k.\text{sub.}\theta(x,z)]$.sup.2 in equation 104 may result in the following expectation value for the position degree of freedom $\phi.\text{sub.r.sub.}N+1$ of the final output relay oscillator **512a-c**

$$[00144] \quad (\text{equation105}) \quad \begin{aligned} \text{Math. } r_{N+1} \cdot \text{Math. } &\approx \frac{r_{N+1}}{N r_{N+1} + \frac{1}{2} m_r(t) \ddot{r}(t)^2} \frac{N}{\text{Math. } j=1} \partial_j (x_i, z_i) \partial_k (x_i, z_i) \\ &\approx \frac{1}{N} \frac{N}{\text{Math. } j=1} \partial_j (x_i, z_i) \partial_k (x_i, z_i) \\ &\approx \frac{1}{N} \mathbb{E}_{(x,z) \sim p(x,z)} [\partial_j (x,z) \partial_k (x,z)], \end{aligned}$$

where in going to the second line the condition

$\phi_{\text{sub},\delta}$ and the oscillators $\phi_{\text{sub},r,\text{sup}}(u)$ and $\phi_{\text{sub},r,\text{sub},f}$ which may be treated as static at their equilibrium values may be described by

$$[00155] \quad V = \frac{(u)}{r} T + B_{r_f} T, \quad (\text{equation112})$$

Note that in computing the equilibrium dynamics of $\phi_{\text{sub},\delta}$, given the above conditions, the following two replacements are used, $\phi_{\text{sub},r,\text{sup}}(u)$ and $B_{\text{sub},r,\text{sub},f}$. To compute $\phi_{\text{sub},\delta}$, the expectation value may be represented by

$$[00156] \quad \text{Math.} = \frac{\int d e^{-V}}{\int d e^{-V}}, \quad (\text{equation113})$$

To evaluate the integral in equation 113, the potential $V_{\text{sub},\delta}$ may be such that $e^{-\beta V_{\text{sub},\delta}}/Z$ (where $Z = \int d\phi_{\text{sub},\delta} e^{-\beta V_{\text{sub},\delta}}$) may be a Gaussian distribution when using the expectation values for $\phi_{\text{sub},r,\text{sup}}(u)$ and $B_{\text{sub},r,\text{sub},f}$. A Gaussian distribution for a random variable x of length N has probability distribution given by

$$[00157] \quad P(x) = \frac{1}{(2\pi)^{N/2} \text{Math.} \text{Math.}^{1/2}} \exp -\frac{1}{2} (x - \mu)^T \text{Math.}^{-1} (x - \mu) \quad (\text{equation114})$$

with mean μ and covariance matrix Σ . Expanding the exponent in equation 114 and matching it to $-\beta V_{\text{sub},\delta}$ (with the expectation values used for $\phi_{\text{sub},r,\text{sup}}(u)$ and $B_{\text{sub},r,\text{sub},f}$), may result in (ignoring constant terms as they don't affect the statistics)

$$[00158] \quad \text{Math.} = \frac{1}{2} \text{Math.} B_{r_f}^{-1} \text{Math.}, \\ = -\frac{1}{2} \text{Math.} B_{r_f}^{-1} \text{Math.} \frac{(u)}{r} \text{Math.}, \quad (\text{repectively equations 115 and 116})$$

Consequently, from equation 116,

$$[00159] \quad \text{Math.} \approx -\frac{1}{2} \text{Math.} B_{r_f}^{-1} \text{Math.} \frac{(u)}{r} \text{Math.}, \quad (\text{equation117})$$

where the approximation label arises since expectation values for $\phi_{\text{sub},r,\text{sup}}(u)$ and $B_{\text{sub},r,\text{sub},f}$ are used. From the equilibrium values of $B_{\text{sub},r,\text{sub},f}$ and $\phi_{\text{sub},r,\text{sup}}(u)$, equation 117 corresponds to the second term on the right-hand side of equation 5. Furthermore the variance may be represented by

$$[00160] \quad \text{Var}(\quad) = \frac{1}{2} \text{Math.} B_{r_f}^{-1} \text{Math.}, \quad (\text{equation118})$$

The non-zero variance given in equation 118 may correspond to a noisy NGD gradient update if the position degree of freedom of the $\phi_{\text{sub},\delta}$ relay oscillators are used to update the parameters θ (e.g., synapses such as weights and biases). To complete the NGD protocol, the parameters θ (e.g., synapses such as weights and biases) may be updated.

[0095] In some embodiments, the parameters (e.g., synapses such as weights and biases) may be dynamical degrees with position degrees of freedom $\phi_{\text{sub},\theta}$ and product $m_{\text{sub},\theta} \omega_{\text{sub},\theta} \supset 2$ that may be much larger than those of the neurons used in the energy function $\epsilon_{\text{sub},\theta}(x,z)$. In this way, the parameters θ can be treated as static up until this point. In some embodiments, a coupling between $\phi_{\text{sub},\theta}$ and $\phi_{\text{sub},\delta}$ may be turned on quickly, and the correct parameter update rule of equation 101 (in expectation value) may be obtained, although the variance in $\phi_{\text{sub},\delta}$ may add some noise to the parameter updates. More specifically, the following potential may be used

$$[00161] \quad V_{\text{param}}(\quad, \quad) = \frac{1}{2} m \quad (t) \quad (t)^2 \sum_{j=1}^M \text{Math.} (\quad_j - \quad_0^j)^2 + \quad (t) \sum_{j=1}^M \quad_j + \frac{1}{2} m_{(b)} \quad (b, \quad)^2 \sum_{j=1}^M \text{Math.} (\quad_{b_j} - \quad_{b_j}) + \quad (b, \quad) \quad (t) \sum_{j=1}^M \text{Math.} \quad_{b_j} + V \quad (\text{equation 119})$$

where $V_{\text{sub},\delta}$ may be given in equation 112 and $\theta_{\text{sub},0}$ may be the initial values chosen for the parameters θ (and $\theta_{\text{sub},0,\text{sup}}(j)$ may be the j 'th component of the vector $\theta_{\text{sub},0}$). Bias oscillators $\phi_{\text{sub},b,\text{sub},j,\text{sup}}(\theta)$ may be used in some embodiments, but in other embodiments bias oscillators may be treated as optional. The coupling $\lambda_{\text{sub},\theta}(t)$ in equation 119 may be turned on after $\phi_{\text{sub},\delta}$ reaches thermal equilibrium, and then turned off after $\phi_{\text{sub},\theta}$ reach their new equilibrium values. Note that the coupling $\lambda_{\text{sub},(b,\theta)}(t)$ for the bias oscillators may be used in the same manner as if $\phi_{\text{sub},\theta}$ were treated as relay oscillators.

[0096] In some embodiments, from equation 119, when the coupling $\lambda_{\text{sub},\theta}(t)$ is turned on and reaches its maximum value (say $\lambda_{\text{sub},\theta}$), an expectation value of the synapse oscillators may be

$$[00162] \quad \text{Math.} = \frac{\int d \quad d \quad e^{-V_{\text{param}}(\quad, \quad)}}{\int d \quad d \quad e^{-V_{\text{param}}(\quad, \quad)}} \quad (\text{equation120}) \\ \approx \quad_0 - \text{Math.} B_{r_f}^{-1} \text{Math.} \frac{(u)}{r} \text{Math.},$$

where the approximation from going from the first to the second line arises since expectation values $B_{\text{sub},r,\text{sub},f,\text{sup}}-1$ and $\phi_{\text{sub},r,\text{sup}}(u)$ are used. In such an embodiment, the condition $\lambda_{\text{sub},\theta} = -2\eta m_{\text{sub},\theta} \omega_{\text{sub},\theta} \supset 2$ as well as the condition

$$[00163] \quad 2^2 m^2 \ll \max \text{Math.} B_{r_f} \text{Math.}, \quad (\text{equation121})$$

are used which can be achieved for small η . The term $\alpha_{\text{sub},4\eta}/\alpha_{\text{sub},1}$ may correspond to the learning rate $1/\lambda_{\text{sub},t}$ in equation 101.

[0097] In some embodiments, the above process may be repeated each time $\phi_{\text{sub},\delta}$ reaches a new equilibrium value when the parameters change due to the coupling in equation 119.

[0098] FIG. 6 is high-level diagram illustrating a process of determining weights and biases to be used in an energy-based model (EBM), wherein the weights and biases are determined using measurement values for synapse oscillators, according to some embodiments.

[0099] As shown in FIG. 6, in a first evolution, visible neurons of an energy-based model implemented on a thermodynamic chip 602 may be clamped to input data. For example, multiple mini-batches of input data may be clamped to visible neurons for multiple evolutions used to generate a first set of measurements used to compute a positive phase term. For example, the measurements may be used by classical computing device 604 to compute the positive phase term.

[0100] Also, in a second (or other subsequent) evolution, the visible neurons may remain unclamped, such that the visible neuron oscillators are free to evolve along with the synapse oscillators during the second (or other subsequent) evolution. Measurements may also be taken and used by the classical computing device 604 to compute a negative phase term.

[0101] Additionally, the positive and negative phase terms computed based on the first and second sets of measurements (e.g., clamped measurements and un-clamped measurements) may be used to calculate updated weights and biases.

[0102] This process may be repeated, with the determined updated weights and biases used as initial weights and biases for a subsequent iteration. In some embodiments, inferences generated using the updated weights and biases may be compared to training data to determine if the energy-based model has been sufficiently trained. If so, the model may transition into a mode of performing inferences using the learned weights and biases. If not sufficiently trained, the process may continue with additional iterations of determining updated weights and biases.

[0103] FIG. 7 is high-level diagram illustrating a process of determining weights and biases to be used in an energy-based model (EBM), wherein the weights and biases are computed using a classical computing device, according to some embodiments.

[0104] In some embodiments, updated weights and bias values may be computed iteratively by classical computing device 704 based on inference measurements from thermodynamic chip 702. For example, inference values may be compared to training data values, and new weights and biases

may be iteratively computed using the inference values closely corresponding to the training data. As can be seen in FIG. 7, in some embodiments the synapse oscillator may be omitted as degrees of freedom of the energy-based model. For example, when a classical computing device is used to iteratively determine the weight and bias values.

[0105] FIG. 8 is a diagram illustrating hardware components that may be used to implement oscillators of energy-based models (EBMs), as well as two different example hardware configurations of a relay oscillator that have a time-dependent mass or a time-dependent frequency, respectively, according to some embodiments.

[0106] In some embodiments, each of the oscillators of the first energy-based model **102a** and the second energy-based model **102b**, may be implemented using superconducting circuit elements, such as shown in FIG. 8. These superconducting circuit elements may be used to implement oscillators that are mapped to visible or hidden neurons of the first or second energy-based model (e.g., **208a** and **204b**). Also, such oscillators may be mapped to synapses (e.g. weights or biases) of the first or second energy-based model. FIGS. **16-17** provide additional details regarding the mappings and hardware configurations used to implement example energy-based models. Also, as shown in FIG. 8 superconducting circuit elements may be used to implement the bias oscillator **806**.

[0107] However, slightly different superconducting circuits may be used to implement the relay oscillator. In some embodiments a relay gadget **106a** or **106b** may comprise a plurality of relay oscillators such as **108a**, wherein an expectation value of output oscillator **208a** may be relayed to input oscillator **204b**. For example, circuit **802** shows an example implementation circuit for the relay oscillator **108a**, wherein the circuit **802** implements a time-dependent frequency that can be controlled by controller **808**. As another alternative, circuit **804** shows an example implementation circuit for the relay oscillator **108a**, wherein the circuit **804** implements a time-dependent mass that can be controlled by controller **808**.

[0108] In some embodiments, the relay gadget does not include a bias oscillator **806**.

[0109] FIG. 9 is a diagram providing additional details regarding a hardware configuration used to implement a relay oscillator with a time-dependent frequency, according to some embodiments.

[0110] In some embodiments, a superconducting quantum interference device (SQUID) can be used in a circuit used to implement a relay oscillator with time-dependent frequency along with a controllable current line that induces a flux in the circuit. For example, time-dependent frequency circuit **802** includes rf-SQUID **902** and current line **904** that induces flux **912**. Note the added flux **912** causes adjustments to the circuit flux **918** and current **914**. The rf-SQUID **902** and current inducing flux **904** can be treated as a flux-tunable inductor, wherein changing the inductance of a LC-resonator changes the frequency of the time-dependent frequency circuit **802**. In order to make the frequency time-dependent, a time dependent flux bias may be applied to a SQUID terminated resonator, such as shown in FIG. 9. In some embodiments, time-dependent frequency circuit **902** also includes Josephson junction **920** which is grounded **922**. In some embodiments, the Josephson junction **920** and inductor **916** (along with controllable inductor **918**) may form a part of relay oscillator **108a-c**. Note that in some embodiments relay oscillator **108a-c** further includes a capacitor in parallel with the inductance and Josephson junction. However, for simplification purposes, the capacitor is not shown in FIG. 9.

[0111] In some embodiments, a value of the relay oscillator **108a-c** may be read via readout **906**. For example, a position degree of freedom of the relay oscillator **108a-c** may be readout via readout **906**. In some embodiments, readout **906** includes a resonator **908** which may have a length corresponding to $\frac{1}{4}$ the wavelength of the signal being readout from the relay oscillator **108a-c**. Also, readout **906** may include feedline **910**.

[0112] Note that inducing the flux in the time-dependent frequency circuit **802** via the current line **904** and resulting induced flux **912** allows for the Josephson inductance **918** to be tuned. This inductance is in series with the resonator inductance **916** so it simply adds to the L term of the LC oscillator. In the time-dependent frequency circuit **802** shown in FIG. 9 there is a voltage antinode at the capacitor below the resonator **906** and a voltage node as the SQUID end, which is grounded.

[0113] In some embodiments, the following function may be used for the time-dependent frequency:

$$[00164] \quad r(t) = \frac{r^{(n)}}{f} (k_r(t - t_r)) + r$$

[0114] When a time-dependent frequency is used, the equation of motion for the average position of the relay oscillator **108a-c** becomes:

$$[00165] m_r \frac{d^2 x}{dt^2} + m_r \frac{d x}{dt} = -(-2 A(t)(y - r) + B(t)(b - r) + X(t)(x - r) + m_r \frac{2}{r}(t - r) + \sqrt{2m_r(t)k_B} T \frac{dW_r^{(r)}}{dt}) \text{ Or } \\ m_r \frac{d^2 x}{dt^2} + m \frac{d x}{dt} = -(-2 A(t)(y - r) - 2 B(t)(r - b) + 2 X(t)(x - r) + m_r \frac{2}{r}(t - r) + \sqrt{2m_r(t)k_B} T \frac{dW_r^{(r)}}{dt})$$

[0115] Note that since frequency is a function of capacitance and inductance, e.g.

$$[00166] \left(f = \frac{1}{\sqrt{LC}} \right),$$

by adjusting the inductance (L), the frequency of the circuit can be controlled. For example, as discussed above, a SQUID can be treated as a flux-tunable inductor, and by changing the inductance of the flux-tunable inductor, the inductance of an LC resonator can be changed, which also changes the LC resonator's frequency. For example, a time dependent flux bias can be applied to a SQUID terminated resonator.

[0116] FIG. 10 is a diagram providing additional details regarding a hardware configuration used to implement a relay oscillator with a time-dependent mass, according to some embodiments.

[0117] A mass of an oscillator, is given by $m = \phi \cdot \text{sub.0} \cdot \text{sup.2C}$, where C is the capacitance of the circuit used to implement the oscillator and $\phi \cdot \text{sub.0} = h/2e$ is the reduced magnetic flux of the circuit used to implement the oscillator, e.g. a constant. Also, e is the elementary charge and h is Planck's constant. In some embodiments, a Cooper-pair box, such as Cooper-pair box **1002**, may be used to change the capacitance of the circuit. This allows the oscillator mass to change as a function of time, in response to control signals from controller **1008**. The gate voltage modulates the charge transfer through the small junction in the Cooper-pair box, thus leading to a gate-dependent capacitance.

[0118] FIG. 11 is a high-level diagram illustrating an output oscillator, an input oscillator, and a relay gadget, wherein the relay gadget comprises a group of relay oscillators and is configured to relay thermodynamic information between the output oscillator and the input oscillator and includes bias oscillators, according to some embodiments.

[0119] In some embodiments, thermodynamic information is relayed from a first energy-based model (EBM) **1100** to a second energy-based model (EBM) **1102** via relay gadget **1104** (e.g., **106a** or **106b**). The thermodynamic information of EBM **1100** is outputted via output oscillator **1106** and inputted into input oscillator **1108** via relay gadget **1104**. The thermodynamic information may include, for example, samples of thermodynamic equilibrium of output oscillator **1106**, or the expectation value of the output oscillator **1106**. The expectation value is at least derivable based on samples values of the output oscillator **1106**. Output oscillator **1106** may be governed by a potential wherein the potential follows a single-well potential, double-well potential, multi-well potential, or any generic potential that may be engineered. The output oscillator **1106** may also be coupled to other oscillators belonging to EBM **1100**.

[0120] In some embodiments, an expectation value of one or more degrees of freedom of output oscillator **1106** may be influenced by a potential of output oscillator **1106** as well as couplings between output oscillator **1106** and one or more oscillators belonging to first energy-based model **1100**. Potentials governing the dynamics of the output oscillator **1106** may have multiple wells. With generic arbitrary potentials (e.g. multiple wells) and coupling between output oscillator **1106** and one or more oscillators belonging to first energy-based model **1100**, the position degrees of freedom of the output oscillators can hop between wells. As described herein, a relay gadget provides a solution to approximate an expectation value of the output oscillator. Furthermore, utilizing the expectation value allows for forwards and backwards propagation. For example, using an approximated expectation value in forwards and backwards propagation may provide better results than using a sample value, as the expectation value better represents the state of the oscillator whose degree of freedom value is being relayed to a second oscillator.

[0121] Relay gadget **1104** comprises a group of relay oscillators **1110** and an additional relay oscillator **1112**. The group of relay oscillators **1110** comprises one or more relay oscillators arranged with respective bias oscillators (e.g., relay oscillator **1116** arranged with bias oscillator **1118**). As

described later, relay oscillators in oscillator group **1110** may be configured and coupled in various ways (e.g. temporally and spatially) to transfer thermodynamic information. The additional relay oscillator **1112** is connected to bias oscillator **1120**. As discussed later, the additional relay oscillator **1112** may be configured and coupled in various ways to transfer thermodynamic information. For example, the group of relay oscillators **1110** transfers thermodynamic information to additional relay oscillator **1112** via coupling **1124**. Coupling **1124** may be controlled by on-chip classical controller **1114**.

[0122] Output oscillator **1106** is coupled to the one or more relay oscillators of the group of relay oscillators **1110** via on-chip classical controller **1114**. On-chip classical controller **1114** may send a pulse or a group of pulses to cause couplings between oscillators (e.g., coupling between output oscillator **1106** and relay oscillator **1116**) or relay oscillators like **1116** and a bias oscillator like **1118** via **1130**. Coupling is represented by coupling **1122**, **1124**, **1126** and oscillators may be coupled or not coupled. When coupling is on, parameters of respective coupled oscillators affect the other oscillator it is coupled to. Couplings between oscillators within the group of relay oscillators **1110** are not expressly shown in FIG. **11** to emphasize that the coupling may take different configurations (e.g. temporal or spatial configurations as detailed below). Nevertheless, on-chip classical controller **1114** may cause a first set of one or more pulses to be emitted through controller connection **1128**, wherein the first set of pulses couples one or more relay oscillators of the group of relay oscillators **1110** to the output oscillator **1106** (e.g., turn on coupling **1122**). The on-chip classical controller **1114** is further configured to cause a second set of one or more pulses to be emitted through **1132**, wherein the second set of pulses couples one or more relay oscillators of the group of relay oscillators **1110** to the additional relay oscillator **1112** (e.g., turn on coupling **1124**). The on-chip classical controller **1114** is further configured to cause a third set of one or more pulses (for example, set of pulses **1138**) to be emitted, wherein the third set of pulses **1138** couples the additional relay oscillator **1112** to the input oscillator **1108** (e.g., turn on coupling **1126**).

[0123] In some embodiments, an additional relay oscillator **1112** takes on an expectation value of an output oscillator **1106** based at least in part on a coupling or couplings between a group of relay oscillators **1110**, wherein respective relay oscillators of group **1110** comprise respective sample values of the output oscillator **1106**. The additional relay oscillator **1112** may take on the expectation value of output oscillator **1106** based at least on respective sample values taken on by respective relay oscillators. Furthermore, additional relay oscillator **1112** may transfer the taken on expectation value to input oscillator **1108** via controller **1114** causing coupling **1126** to turn on.

[0124] In some embodiments, bias oscillators such as bias oscillator **1118** may be used, for example, to stabilize relay oscillators of the relay gadget. In some embodiments, relay gadget **1104** may be implemented without bias oscillators such as **1118**.

[0125] FIG. **12** is a high-level diagram illustrating a spatial analogue relay gadget, wherein respective ones of relay oscillators of a group of relay oscillators are configured to store respective sample values of an output oscillator, according to some embodiments.

[0126] In some embodiments, controller **1114** sends a first set of one or more pulses wherein the first set of pulses causes output oscillator **1106** of first energy-based model (EBM) **1100** to be coupled to at least one or more relay oscillators $\{\phi_{\text{sub.r.sub.1}}, \phi_{\text{sub.r.sub.2}}, \dots \phi_{\text{sub.r.sub.N}}\}$, in the group of relay oscillators **1210**. The group of relay oscillators **1210** comprises a plurality of relay oscillators, wherein respective relay oscillators $\{\phi_{\text{sub.r.sub.1}}, \phi_{\text{sub.r.sub.2}}, \dots \phi_{\text{sub.r.sub.N}}\}$, are configured to store a sample of the output oscillator **1106** based at least in part on respective couplings between the respective ones of the relay oscillators (e.g., **1116**) of the group of relay oscillators **1210** and the output oscillator **1106**. The on-chip classical controller **1114** is further configured to cause another set of one or more pulses to be emitted, wherein the other set of pulses turns off the respective couplings between the output oscillator **1106** and the respective ones of the relay oscillator of the group of relay oscillators **1210** at different times. This may allow different samples of the output oscillator **1106** to be stored on the respective ones of the relay oscillators $\{\phi_{\text{sub.r.sub.1}}, \phi_{\text{sub.r.sub.2}}, \dots \phi_{\text{sub.r.sub.N}}\}$.

[0127] On-chip classical controller **1114** may be further configured to cause a second set of one or more pulses to be emitted, wherein the second set of pulses turns on the coupling between respective ones of the relay oscillators with sample values of the output oscillator **106** to an additional relay oscillator **1212**. The coupling is configured to transfer an approximation of the expectation value of output oscillator **1106** based at least in part on the sample values stored on respective relay oscillators in the first group of relay oscillators **1210**. Once the additional relay oscillator **1212** is tuned to the expectation value of output oscillator **1106**, controller **1114** may cause a set of one or more pulses that may cause the additional relay oscillator to be coupled to input oscillator **1108**. In some embodiments, bias oscillators such as bias oscillator **1118** may be used, for example, to stabilize relay oscillators of the relay gadget. In some embodiments, relay gadget **1104** may be implemented without bias oscillators such as **1118**.

[0128] FIG. **13** is a high-level diagram illustrating a temporal analogue relay gadget, wherein a group of relay oscillators comprises a single relay oscillator, according to some embodiments.

[0129] In some embodiments, the group of relay oscillators **1110** comprises a single relay oscillator **1316**. The single relay oscillator **1316** is configured to store a sample of the output oscillator **1106** based at least in part on the coupling between the single relay oscillator **1316** and the output oscillator **1106**. The coupling between output oscillator **1106** and single relay oscillator **1316** is caused by a first set of one or more pulses emitted from on-chip classical controller **1114**. The on-chip classical controller **1114** is configured to cause a second set of one or more pulses to be emitted, wherein the second set of pulses causes the single relay oscillator **1316** to be coupled to additional relay oscillator **1312**. The sequence of emitting the first set of pulses and then emitting the second set of pulses may be repeated numerous times. Each instance the sequence of the sequential sets of pulses is emitted, the position of additional relay oscillator **1312** is incrementally adjusted. Each adjustment may converge the additional relay oscillator **1312** to the expectation value of output oscillator **1106**.

[0130] In some embodiments, bias oscillators such as bias oscillator **1118** may be used to stabilize relay oscillators of the relay gadget. In some embodiments, relay gadget **1104** may be implemented without bias oscillators such as **1118**.

[0131] FIG. **14** is a high-level diagram illustrating a series analogue relay gadget, wherein a group of relay oscillators comprises a plurality of relay oscillators arranged in series, according to some embodiments.

[0132] FIG. **14** shows a drawing of a series analogue relay gadget **1404** such as shown in some embodiments. The group of relay oscillators **1110** comprises a plurality of relay oscillators $\{\phi_{\text{sub.r.sub.1}}, \phi_{\text{sub.r.sub.2}}, \dots\}$ (e.g. relay oscillator **1416A**, **1416B**, **1416C**) arranged one after another in series. Each relay oscillator has a product of mass and frequency squared. The first relay oscillator **1416A**, $\phi_{\text{sub.r.sub.1}}$, has the smallest product of mass and frequency squared. The next relay oscillator **1416B**, $\phi_{\text{sub.r.sub.2}}$, has a product of mass and frequency squared larger than the previous relay oscillator **1416A**, $\phi_{\text{sub.r.sub.1}}$. This trend of increasing the product of mass and frequency squared continues for each subsequent relay oscillator in the group of relay oscillators **1110**. As last in the chain of relay oscillators, the additional relay oscillator **1412** has the largest product of mass and frequency squared. The couplings between relay oscillators and the coupling between the output oscillator **1106** and the first relay oscillator **1416A**, $\phi_{\text{sub.r.sub.1}}$, may be turned on at the same time and allowed to evolve thermodynamically according to Langevin dynamics. Once coupling is initiated, each successive relay oscillator takes continuous samples of the previous oscillator it is coupled to. Furthermore, each successive relay oscillator may be a closer approximation of the expectation value of the output oscillator **1106**. In this manner, additional relay oscillator **1412** approximates an expectation value of input oscillator **1106**. At this point, coupling between the additional relay oscillator **1412** and input oscillator **1108** may be turned on and the thermodynamic information may be transferred to input oscillator **1108**. The number of relay oscillators and the timing of coupling may be chosen beforehand and optimized for a desired precision or accuracy of the expectation value of the output relay oscillator.

[0133] In some embodiments, bias oscillators such as bias oscillator **1118** may be used to stabilize relay oscillators of the relay gadget. In some embodiments, relay gadget **1104** may be implemented without bias oscillators such as **1118**.

[0134] FIG. **15A** illustrates example couplings between visible neurons of an energy-based model (EBM), according to some embodiments.

[0135] In some embodiments, input neurons and output neurons of an energy-based model, such as visible neurons **1502** and visible neurons **1504**, may be directly linked via connected edges **1506**. As shown in FIG. **15A**, a given visible neuron **1502** of the five shown in the figure is connected,

via edges **1506**, to each of the respective three visible neurons **1504**. A person having ordinary skill in the art should understand that FIG. **15A** is meant to represent example embodiments of a graph architecture implemented using a thermodynamic chip that may be applied and that specific numbers of visible neurons **1502** and/or visible neurons **1504** shown in the figure are not meant to be restrictive. Additional configurations combining more/less visible neurons **1502** and/or visible neurons **1504** are also encompassed by the discussion herein. In addition, recall that neurons are logical representations of physical oscillators, such that, when describing neurons in FIGS. **15A** and **15B**, it should be understood that neurons and edges are implemented using oscillators and couplings.

[0136] FIG. **15B** illustrates example couplings between visible neurons and non-visible neurons (e.g., hidden neurons) of an energy-based model (EBM), according to some embodiments.

[0137] In some embodiments, FIG. **15B** may resemble additional example embodiments of an energy-based model architecture implemented using a thermodynamic chip. As shown in the figure, additional non-visible neurons **1508** may be used, which are respectively coupled, via edges **1506**, to both visible neurons **1502** and to visible neurons **1504**. Note that while the non-visible neurons are “not visible” from the perspective of inputs and outputs, the non-visible neurons may each correspond to a given oscillator. In addition, it may be noted that, in some embodiments that make use of non-visible neurons, no direct connections, via edges **1506**, may be implemented between visible neurons **1502** and visible neurons **1504**, but rather connections are routed firstly via non-visible neurons **1508**, as shown in FIG. **15B**. Couplings between visible and non-visible neurons may be additionally referred to herein as “layers” of a given energy-based model architecture that is implemented using a thermodynamic chip, according to some embodiments.

[0138] FIG. **16** is a high-level diagram illustrating oscillators included in a substrate of the thermodynamic chip and mapping of the oscillators to logical neurons of the thermodynamic chip, according to some embodiments.

[0139] In some embodiments, a substrate **1602** may be included in a thermodynamic chip, such as any one of the thermodynamic chips described above. Oscillators **1604** of substrate **1602** may be mapped in a logical representation **1652** to neurons **1654**, as well as weights and biases (shown in FIG. **17**). In some embodiments, oscillators **1604** may include oscillators with potentials ranging from a single well potential to a dual-well potential and may be mapped to visible neurons, weights, and biases.

[0140] In some embodiments, Josephson junctions and/or superconducting quantum interference devices (SQUIDS) may be used to implement and/or excite/control the oscillators **1604**. In some embodiments, the oscillators **1604** may be implemented using superconducting flux elements (e.g., qubits). In some embodiments, the superconducting flux elements may physically be instantiated using a superconducting circuit built out of coupled nodes comprising capacitive, inductive, and Josephson junction elements, connected in series or parallel, such as shown in FIG. **16** for oscillator **1604**. However, in some embodiments, generally speaking various non-linear flux loops may be used to implement the oscillators **1604**, such as those having single-well potential, double-well potential, or various other potentials, such as a potential somewhere between a single-well potential and a double-well potential.

[0141] FIG. **17** is an additional high-level diagram illustrating oscillators included in a substrate of the thermodynamic chip mapped to logical neurons, weights, and biases of a given neuro-thermodynamic computing system, according to some embodiments.

[0142] While weights and biases are not shown in FIG. **16** for ease of illustration, respective ones of the visible neurons **1654** of FIG. **16** may each have an associated bias, and edges connecting the neurons **1654** may have associated weights. For example, FIG. **15** illustrates an arrangement of five visible neurons along with associated weights and biases. Each of the weights and biases may be mapped to oscillators in the thermodynamic chip, as well as the visible (and non-visible) neurons being mapped to oscillators in the thermodynamic chip. For example, FIG. **17** shows a portion of a thermodynamic chip, wherein weights and biases associated with a given neuron **1754** are shown. For example, bias **1756** may be a bias value for visible neuron **1754** and weights **1758** and **1760** may be weights for edges formed between visible neuron **1754** and other visible neurons of the thermodynamic chip. As shown in FIG. **17**, each of the chip elements (visible neuron **1754**, bias **1756**, weight **1758**, and weight **1760**) may be mapped to separate ones of oscillators **1704**. This may allow the visible neurons (and/or hidden neurons), weights, and biases to have independent degrees of freedom within a given thermodynamic chip that can separately evolve.

[0143] In some embodiments, oscillators associated with weights and biases, such as bias **1756** and weights **1758** and **1760**, may be allowed to evolve during a training phase and may be held nearly constant during an inference phase. For example, in some embodiments, larger “masses” may be used for the weights and biases such that the weights and biases evolve more slowly than the visible neurons. This may have the effect of holding the weight values and the bias values nearly constant during an evolution phase used for generating inference values.

[0144] FIG. **18** is a high-level flowchart illustrating the process of implementing energy based models and determining gradients that may be used to update synapse oscillators representing synapse values, according to some embodiments.

[0145] At block **1802**, one or more engineered energy potentials such as **206a-d** are implemented on one or more oscillators of one or more energy based models (EBMs) **102a-d**. Respective oscillators of the respective EBMs are neuron oscillators (e.g., **204a-d** and **208a-d**) representing neuron values. Other respective oscillators of the respective EBMs are synapse oscillators (e.g., bias oscillator **112**, and weight oscillators **114**, **116**) representing synapse values.

[0146] At block **1804**, the system determines gradient terms (forwards gradient terms) of a given EBM during a forwards pass **110**, wherein the engineered energy potential is not perturbed in the forwards pass.

[0147] At block **1806**, respective engineered energy potentials are perturbed by the system based on adjusting the one or more oscillators of the EBM, wherein the adjusting causes a small energy potential to be added to the respective engineered energy functions

[0148] At block **1808**, the system determines gradient terms (backwards gradient terms) of a given EBM during a backwards pass **112**, wherein the engineered energy potential is perturbed in the backwards pass.

[0149] In some embodiments, synapses may not be dynamical degrees of freedom. In such an embodiment, the method may further include the following. Measuring thermodynamic information of one or more synapse oscillators of a given EBM. Storing measured thermodynamic information on one or more classical computing devices. computing the forwards or backwards gradient terms of a given EBMs based on the measurements of the one or more oscillators. Determining update synapse values based on the forwards or backwards gradient terms.

[0150] In some embodiments, synapses may be dynamical degrees of freedom. Such an embodiment may include methods such as the following. Determining the forwards or backwards gradient terms based on evolving respective oscillators thermodynamically. Storing the determined forwards or backwards gradient terms on one or more relay oscillators. Updating the synapse values based on the forwards or backwards gradient terms.

Illustrative Computer System

[0151] FIG. **19** is a block diagram illustrating an example computer system that may be used in at least some embodiments. In some embodiments, the computing system shown in FIG. **19** may be used, at least in part, to implement any of the techniques described above in FIGS. **1-18**.

Furthermore, computer system **1900** may be configured to interact and/or interface with neuro-thermodynamic computing device **1980**, according to some embodiments.

[0152] In the illustrated embodiment, computer system **1900** includes one or more processors **1910** coupled to a system memory **1920** (which may comprise both non-volatile and volatile memory modules) via an input/output (I/O) interface **1930**. Computer system **1900** further includes a network interface **1940** coupled to I/O interface **1930**. Classical computing functions may be performed on a classical computer system, such as computing computer system **1900**.

[0153] Additionally, computer system **1900** includes computing device **1970** coupled to thermodynamic chip **1980**. In some embodiments, computing device **1970** may be a field programmable gate array (FPGA), application specific integrated circuit (ASIC) or other suitable processing unit. In some embodiments, computing device **1970** may be a similar computing device as described in FIGS. **1-18**, such as classical computing

devices used to control a thermodynamic chip. In some embodiments, computing device **1980** may be a similar neuro thermodynamic computing device as described in FIGS. **1-18**, such as neuro thermodynamic computing devices implemented using thermodynamic chips.

[0154] In various embodiments, computer system **1900** may be a uniprocessor system including one processor **1910**, or a multiprocessor system including several processors **1910** (e.g., two, four, eight, or another suitable number). Processors **1910** may be any suitable processors capable of executing instructions. For example, in various embodiments, processors **1910** may be general-purpose or embedded processors implementing any of a variety of instruction set architectures (ISAs), such as the x86, PowerPC, SPARC, or MIPS ISAs, or any other suitable ISA. In multiprocessor systems, each of processors **1910** may commonly, but not necessarily, implement the same ISA. In some implementations, graphics processing units (GPUs) may be used instead of, or in addition to, conventional processors.

[0155] System memory **1920** may be configured to store instructions and data accessible by processor(s) **1910**. In at least some embodiments, the system memory **1920** may comprise both volatile and non-volatile portions; in other embodiments, only volatile memory may be used. In various embodiments, the volatile portion of system memory **1920** may be implemented using any suitable memory technology, such as static random-access memory (SRAM), synchronous dynamic RAM or any other type of memory. For the non-volatile portion of system memory (which may comprise one or more NVDIMMs, for example), in some embodiments flash-based memory devices, including NAND-flash devices, may be used. In at least some embodiments, the non-volatile portion of the system memory may include a power source, such as a supercapacitor or other power storage device (e.g., a battery). In various embodiments, memristor based resistive random-access memory (ReRAM), three-dimensional NAND technologies, Ferroelectric RAM, magneto resistive RAM (MRAM), or any of various types of phase change memory (PCM) may be used at least for the non-volatile portion of system memory. In the illustrated embodiment, program instructions and data implementing one or more desired functions, such as those methods, techniques, and data described above, are shown stored within system memory **1920** as code **1925** and data **1926**.

[0156] In some embodiments, I/O interface **1930** may be configured to coordinate I/O traffic between processor **1910**, system memory **1920**, computing device **1970**, and any peripheral devices in the computer system, including network interface **1940** or other peripheral interfaces such as various types of persistent and/or volatile storage devices. In some embodiments, I/O interface **1930** may perform any necessary protocol, timing or other data transformations to convert data signals from one component (e.g., system memory **1920**) into a format suitable for use by another component (e.g., processor **1910**). In some embodiments, I/O interface **1930** may include support for devices attached through various types of peripheral buses, such as a variant of the Peripheral Component Interconnect (PCI) bus standard or the Universal Serial Bus (USB) standard, for example. In some embodiments, the function of I/O interface **1930** may be split into two or more separate components, such as a north bridge and a south bridge, for example. Also, in some embodiments some or all of the functionality of I/O interface **1930**, such as an interface to system memory **1920**, may be incorporated directly into processor **1910**.

[0157] Network interface **1940** may be configured to allow data to be exchanged between computing device **1900** and other devices **1960** attached to a network or networks **1950**, such as other computer systems or devices. In various embodiments, network interface **1940** may support communication via any suitable wired or wireless general data networks, such as types of Ethernet network, for example. Additionally, network interface **1940** may support communication via telecommunications/telephony networks such as analog voice networks or digital fiber communications networks, via storage area networks such as Fibre Channel SANs, or via any other suitable type of network and/or protocol.

[0158] In some embodiments, system memory **1920** may represent one embodiment of a computer-accessible medium configured to store at least a subset of program instructions and data used for implementing the methods and apparatus discussed in the context of FIG. **1** through FIG. **18**. However, in other embodiments, program instructions and/or data may be received, sent or stored upon different types of computer-accessible media. Generally speaking, a computer-accessible medium may include non-transitory storage media or memory media such as magnetic or optical media, e.g., disk or DVD/CD coupled to computer system **1900** via I/O interface **1930**. A non-transitory computer-accessible storage medium may also include any volatile or non-volatile media such as RAM (e.g., SDRAM, DDR SDRAM, RDRAM, SRAM, etc.), ROM, etc., that may be included in some embodiments of computer system **1900** as system memory **1920** or another type of memory. In some embodiments, a plurality of non-transitory computer-readable storage media may collectively store program instructions that when executed on or across one or more processors implement at least a subset of the methods and techniques described above. A computer-accessible medium may further include transmission media or signals such as electrical, electromagnetic, or digital signals, conveyed via a communication medium such as a network and/or a wireless link, such as may be implemented via network interface **1940**. Portions or all of multiple computing devices such as that illustrated in FIG. **19** may be used to implement the described functionality in various embodiments; for example, software components running on a variety of different devices and servers may collaborate to provide the functionality. In some embodiments, portions of the described functionality may be implemented using storage devices, network devices, or special-purpose computer systems, in addition to or instead of being implemented using general-purpose computer systems. The term “computer system”, as used herein, refers to at least all these types of devices, and is not limited to these types of devices.

CONCLUSION

[0159] Various embodiments may further include receiving, sending or storing instructions and/or data implemented in accordance with the foregoing description upon a computer-accessible medium. Generally speaking, a computer-accessible medium may include storage media or memory media such as magnetic or optical media, e.g., disk or DVD/CD-ROM, volatile or non-volatile media such as RAM (e.g., SDRAM, DDR, RDRAM, SRAM, etc.), ROM, etc., as well as transmission media or signals such as electrical, electromagnetic, or digital signals, conveyed via a communication medium such as network and/or a wireless link.

[0160] The various methods as illustrated in the Figures above and the Appendix below and described herein represent exemplary embodiments of methods. The methods may be implemented in software, hardware, or a combination thereof. The order of method may be changed, and various elements may be added, reordered, combined, omitted, modified, etc.

[0161] It will also be understood that, although the terms first, second, etc., may be used herein to describe various elements, these elements should not be limited by these terms. These terms are only used to distinguish one element from another. For example, a first contact could be termed a second contact, and, similarly, a second contact could be termed a first contact, without departing from the scope of the present invention. The first contact and the second contact are both contacts, but they are not the same contact.

[0162] Various modifications and changes may be made as would be obvious to a person skilled in the art having the benefit of this disclosure. It is intended to embrace all such modifications and changes and, accordingly, the above description and the Appendix below is to be regarded in an illustrative rather than a restrictive sense.

Claims

1. A system comprising: one or more thermodynamic chips, wherein oscillators of the one or more thermodynamic chips are configured to implement: a plurality of energy based models (EBMs) configured to thermodynamically evolve, wherein: respective oscillators of the respective EBMs are mapped to be neuron oscillators representing neuron values; and other respective oscillators of the respective EBMs are mapped to be synapse oscillators representing synapse values, wherein: the synapse oscillators when coupled with the neuron oscillators establish an engineered potential that is configured to be perturbed; and one or more relay gadgets, each comprising one or more of the oscillators (relay oscillators) configured to relay thermodynamic information between the EBMs as the EBMs thermodynamically evolve in a forward pass and a backward pass; and wherein: one or more forwards gradient terms of a given EBM are determined during the forwards pass, wherein the engineered energy potential is not perturbed in the forward pass; one or more backwards gradient terms of the given EBM are determined during the backwards pass, wherein the

engineered energy potential is perturbed in the backward pass.

2. The system of claim 1 further comprising one or more classical computing devices configured to: measure thermodynamic information of one or more of the synapse oscillators of a given one of the EBM; compute the forwards or backwards gradient terms of the given EBM based on the measurements of the synapse oscillators; and determine updated synapse values based on the forwards or backwards gradient terms.

3. The system of claim 1, wherein the one or more thermodynamic chips further comprise additional relay oscillators configured to: couple and uncouple with one or more of the synapse oscillators of a given one of the EBM; be used to determine the forwards or backwards gradient terms based on respective relay oscillators evolving thermodynamically; and store updated synapse values determined based on the forwards or backwards gradient terms, wherein the forwards or backwards gradient terms are determined based on respective relay oscillators of the EBM evolving thermodynamically.

4. The system of claim 1, wherein: a neural network is implemented via respective EBM of the plurality of EBM; and the respective EBM represent respective layers of the neural network.

5. The system of claim 4, wherein: one or more neuron oscillators of a given EBM are configured to be clamped to thermodynamic information of one or more neuron oscillators of another one of the EBM.

6. The system of claim 1, wherein: the forwards gradient terms are determined based on changes in the engineered energy potential given a change in one or more oscillators of the EBM; and the backwards gradient terms are determined based on how the perturbed engineered energy potential changes given a change in one or more oscillators of the EBM.

7. The system of claim 6, wherein: updated synapse values are determined based on the forwards or backwards gradient terms.

8. The system of claim 1, wherein: a difference between the forwards gradient terms and respective backwards gradient terms are determined; and an updated synapse value is determined based on the difference between the forwards and backwards gradient terms.

9. A method, comprising: implementing one or more engineered energy potentials using one or more oscillators of one or more energy based models (EBMs), wherein: respective oscillators of the respective EBM are neuron oscillators representing neuron values; and other respective oscillators of the respective EBM are synapse oscillators representing synapse values, wherein: the synapse oscillators when coupled with the neuron oscillators establish an engineered potential that is configured to be perturbed; and determining gradient terms (forwards gradient terms) of a given EBM during a forwards pass, wherein the engineered energy potential is not perturbed in the forward pass; perturbing respective engineered energy potentials based on adjusting the one or more oscillators of the EBM, wherein the adjusting causes a small energy potential to be added to the respective engineered energy potentials; and determining gradient terms (backwards gradient terms) of the given EBM are determined during a backwards pass, wherein the engineered energy potential is perturbed in the backward pass.

10. The method of claim 9 further comprising: measuring thermodynamic information of one or more synapse oscillators of a given EBM; storing measured thermodynamic information on one or more classical computing devices.

11. The method of claim 10 further comprising: computing the forwards or backwards gradient terms of a given one of the EBM based on the measurements of the one or more oscillators; and determining updated synapse values based on the forwards or backwards gradient terms.

12. The method of claim 9 further comprising: determining the forwards or backwards gradient terms based on evolving respective oscillators thermodynamically; and storing the determined forwards or backwards gradient terms on one or more relay oscillators.

13. The method of claim 12 further comprising: updating the synapse values based on the forwards or backwards gradient terms.

14. The method of claim 9, further comprising: implementing a neural network via respective EBM of a plurality of EBM, wherein the respective EBM represent respective layers of the neural network.

15. The method of claim 14, further comprising: clamping one or more visible oscillators of a given EBM to thermodynamic information of one or more visible oscillators of another EBM.

16. The method of claim 9, wherein: the forwards gradient terms are based on how the engineered energy potential changes given a change in one or more oscillators of the EBM; and the backwards gradient terms are based on how the perturbed engineered energy potential changes given a change in one or more oscillators of the EBM.

17. The method of claim 16, wherein: the forwards or backwards gradient terms are used to update synapse values of the EBM.

18. The method of claim 9, further comprising: determining a difference between the forwards gradient terms and respective backwards gradient terms; and determining updated synapse value based on the difference between the forwards and backwards gradient terms.

19. One or more non-transitory, computer-readable, storage media storing program instruction, that when executed on or across one or more processors, cause the one or more processors to: cause one or more engineered energy potentials to be implemented using one or more oscillators of one or more energy based models (EBMs), wherein the one or more oscillators of each EBM comprises visible oscillators and synapse oscillators; calculate a forwards gradient term of an engineered energy potential of the EBM that is not perturbed based on measurements of one or more oscillators; calculate a backwards gradient term of an engineered energy potential of the EBM that is not perturbed based on measurements of one or more oscillators; and cause the synapse oscillators of respective EBM to be updated.

20. The one or more non-transitory, computer-readable, storage media of claim 19 that when executed on or across one or more processors, further cause the one or more processors to: calculate a difference between the forwards gradient terms and the backwards gradient terms.
