

US Patent & Trademark Office

Patent Public Search | Text View

United States Patent	12412420
Kind Code	B2
Date of Patent	September 09, 2025
Inventor(s)	Thomas; Tigi

Apparatus, systems, and methods for microphone gain control for electronic user devices

Abstract

Apparatus, systems, and methods for microphone gain control for electronic user devices are disclosed. An example apparatus includes at least one memory, instructions in the apparatus, and processor circuitry to execute the instructions to determine a proximity of a user to a user device based on an image generated via one or more cameras associated with the user device, determine an amount of gain to be applied to an audio signal generated by a microphone associated with the user device based on the proximity of the user, and cause an amplifier of the user device to apply the gain to the audio signal.

Inventors:	Thomas; Tigi (Bangalore, IN)
Applicant:	Intel Corporation (Santa Clara, CA)
Family ID:	78005532
Assignee:	Intel Corporation (Santa Clara, CA)
Appl. No.:	17/358894
Filed:	June 25, 2021

Prior Publication Data

Document Identifier	Publication Date
US 20210318850 A1	Oct. 14, 2021

Publication Classification

Int. Cl.: G06V40/16 (20220101); G06F3/00 (20060101); G06F3/01 (20060101); G10L21/0356 (20130101)

U.S. Cl.:

CPC **G06V40/168** (20220101); **G06F3/005** (20130101); **G06F3/013** (20130101);
G10L21/0356 (20130101);

Field of Classification Search

USPC: None

References Cited

U.S. PATENT DOCUMENTS

Patent No.	Issued Date	Patentee Name	U.S. Cl.	CPC
4811404	12/1988	Vilmur	704/226	G10L 21/0208
6363344	12/2001	Higuchi	704/226	G10L 21/0208
6593956	12/2002	Potts	N/A	N/A
8681203	12/2013	Yin et al.	N/A	N/A
9197974	12/2014	Clark	N/A	H04R 29/004
9298974	12/2015	Kuo	N/A	N/A
10027883	12/2017	Kuo	N/A	H04N 23/63
10027888	12/2017	Mackraz	N/A	G06V 10/25
10440324	12/2018	Lichtenberg	N/A	N/A
10819950	12/2019	Lichtenberg et al.	N/A	N/A
10820795	12/2019	Weise	N/A	G06V 20/64
11252374	12/2021	Lichtenberg et al.	N/A	N/A
2003/0035001	12/2002	Van Geest	N/A	N/A
2008/0002948	12/2007	Murata	N/A	N/A
2008/0136895	12/2007	Mareachen	N/A	N/A
2008/0260131	12/2007	Akesson	N/A	N/A
2008/0279425	12/2007	Tang	382/118	G06V 40/16
2009/0015658	12/2008	Enstad	N/A	N/A
2010/0123785	12/2009	Chen	N/A	N/A
2011/0161074	12/2010	Pance et al.	N/A	N/A
2011/0316996	12/2010	Abe	N/A	N/A
2012/0150333	12/2011	De Luca	N/A	N/A
2012/0183161	12/2011	Agevik	N/A	N/A
2013/0156209	12/2012	Visser	381/66	H04M 9/082
2013/0202130	12/2012	Zurek	381/94.3	H04M 1/605
2014/0169627	12/2013	Gupta	382/103	G06V 20/588
2014/0337016	12/2013	Herbig	704/201	G10L 25/27
2014/0341547	12/2013	Shenoy	N/A	N/A
2015/0131803	12/2014	Weksler et al.	N/A	N/A
2015/0264299	12/2014	Leech	348/78	H04N 7/0117
2015/0296319	12/2014	Shenoy	381/303	H04R 3/005
2016/0073054	12/2015	Balasaygun et al.	N/A	N/A
2016/0195856	12/2015	Spero	700/90	G05B 15/02
2017/0127035	12/2016	Kon et al.	N/A	N/A
2017/0186441	12/2016	Wenus	N/A	N/A
2017/0201825	12/2016	Whyte	N/A	N/A
2018/0084365	12/2017	Ugur	N/A	N/A
2018/0144746	12/2017	Mishra et al.	N/A	N/A

2018/0310114	12/2017	Eronen	N/A	N/A
2019/0172462	12/2018	Mishra	N/A	N/A
2019/0313014	12/2018	Welbourne	N/A	G06V 40/70
2019/0394606	12/2018	Tammi	N/A	N/A
2020/0028884	12/2019	Childers et al.	N/A	N/A
2020/0110572	12/2019	Lenke et al.	N/A	N/A
2020/0137489	12/2019	Sheaffer	N/A	N/A
2020/0145617	12/2019	Zavesky et al.	N/A	N/A
2020/0184987	12/2019	Kupryjanow et al.	N/A	N/A
2020/0314483	12/2019	Rakshit et al.	N/A	N/A
2020/0393159	12/2019	Takayanagi	N/A	N/A
2021/0092517	12/2020	Kulkarni et al.	N/A	N/A
2021/0116983	12/2020	Hallberg et al.	N/A	N/A
2021/0321212	12/2020	Li	N/A	N/A
2022/0059071	12/2021	Pearce et al.	N/A	N/A
2022/0060525	12/2021	Chavez et al.	N/A	N/A
2022/0159403	12/2021	Sporer	N/A	N/A
2022/0239848	12/2021	Swierk et al.	N/A	N/A
2022/0295012	12/2021	Swierk et al.	N/A	N/A
2022/0319063	12/2021	Mizobuchi et al.	N/A	N/A
2023/0103060	12/2022	Chaudhuri	N/A	N/A

FOREIGN PATENT DOCUMENTS

Patent No.	Application Date	Country	CPC
111754990	12/2019	CN	N/A
2011123757	12/2010	WO	N/A
2022067293	12/2021	WO	N/A

OTHER PUBLICATIONS

Feng et al., “Face Detection, Bounding Box Aggregation and Pose Estimation for Robust Facial Landmark Localisation in the Wild,” 2017 IEEE Conference on Computer Vision and Pattern Recognition Workshops (CVPRW), 2017, pp. 160-169, 10 pages. cited by applicant

United States Patent and Trademark Office, “Final Office Action,” issued in connection with U.S. Appl. No. 17/483,552, dated Feb. 13, 2025, 12 pages. cited by applicant

European Patent Office, “Communication pursuant to Article 94(3) EPC,” issued in connection with European Patent Application No. 22191774.3, Mar. 10, 2025, 7 pages. cited by applicant

“A Method and Apparatus for Smart Auto-Mute of Conference Participants,” IP.com Prior Art Database Technical Disclosure, May 1, 2014, 12 pages. cited by applicant

European Patent Office, “European Search Report,” issued in connection with European patent application No. 22191774.3, Feb. 20, 2023, 8 pages. cited by applicant

United States Patent and Trademark Office, “Non-Final Office Action,” issued in connection with U.S. Appl. No. 17/483,552, dated Oct. 25, 2024, 9 pages. cited by applicant

Warusfel, “Listen HRTF Database,” dated Sep. 6, 2002, updated May 25, 2003, retrieved from <http://recherche.ircam.fr/equipes/salles/listen/>, 1 page. cited by applicant

United States Patent and Trademark Office, “Non-Final Office Action,” issued in connection with U.S. Appl. No. 17/475,235, dated Oct. 30, 2024, 15 pages. cited by applicant

United States Patent and Trademark Office, “Final Office Action,” issued in connection with U.S. Appl. No. 17/475,235, dated Feb. 11, 2025, 19 pages. cited by applicant

United States Patent and Trademark Office, “Notice of Allowance and Fee(s) Due,” issued in connection with U.S. Appl. No. 17/483,552, dated Jul. 1, 2025, 9 pages. cited by applicant

Background/Summary

FIELD OF THE DISCLOSURE

(1) This disclosure relates generally to electronic user devices and, more particularly, to apparatus, systems, and methods for microphone gain control for electronic user devices.

BACKGROUND

(2) An electronic user device such as a laptop includes one or more microphones to capture audio such as a voice of a user of the device. The microphone(s) can be used during a video call in which an image of the user is captured via camera(s) of the electronic user device in addition to the audio captured by the microphone(s).

Description

BRIEF DESCRIPTION OF THE DRAWINGS

- (1) FIG. 1 illustrates an example user device constructed in accordance with teachings of this disclosure and, in particular, illustrates a first interaction between a user and a microphone of the user device.
- (2) FIG. 2 illustrates the example user device of FIG. 1 and, in particular, illustrates a second interaction between the user and a microphone of the user device.
- (3) FIG. 3 illustrates an example system constructed in accordance with teachings of this disclosure and including a user device, user proximity detection circuitry for detecting user proximity relative to the device, and microphone gain control circuitry for controlling microphone gain in response to the user proximity detection in accordance with teachings of this disclosure.
- (4) FIG. 4 is a block diagram of example implementation of the user proximity detection circuitry of FIG. 3 and an example implementation of the microphone gain control circuitry of FIG. 3.
- (5) FIG. 5 is a block diagram of neural network generation circuitry for training neural network(s) to generate neural network model(s) for use by the example user proximity detection circuitry of FIGS. 3 and/or 4 during analysis of video frames in accordance with teachings of this disclosure.
- (6) FIG. 6 includes examples images of a user and corresponding facial landmarks identified in the images.
- (7) FIG. 7 is a flowchart representative of example machine readable instructions and/or operations that may be executed and/or instantiated by example processor circuitry to train a neural network to identify faces in image data.
- (8) FIG. 8 is a flowchart representative of example machine readable instructions and/or operations that may be executed and/or instantiated by example processor circuitry to train a neural network to identify facial landmarks in image data.
- (9) FIG. 9 is a flowchart representative of example machine readable instructions and/or operations that may be executed and/or instantiated by example processor circuitry to implement the user proximity detection circuitry of FIGS. 3 and/or 4.
- (10) FIG. 10 is a flowchart representative of example machine readable instructions and/or operations that may be executed and/or instantiated by example processor circuitry to implement the microphone gain control circuitry of FIGS. 3 and/or 4.
- (11) FIG. 11 is a block diagram of an example processor platform including processor circuitry

structured to execute and/or instantiate the example machine readable instructions of FIG. 9 to implement the user proximity detection circuitry of FIGS. 3 and/or 4.

(12) FIG. 12 is a block diagram of an example implementation of the processor circuitry of FIG. 11.

(13) FIG. 13 is a block diagram of another example implementation of the processor circuitry of FIG. 11.

(14) FIG. 14 is a block diagram of an example processor platform including processor circuitry structured to execute and/or instantiate the example machine readable instructions of FIG. 10 to implement the microphone gain control circuitry of FIGS. 3 and/or 4.

(15) FIG. 15 is a block diagram of an example implementation of the processor circuitry of FIG. 14.

(16) FIG. 16 is a block diagram of another example implementation of the processor circuitry of FIG. 14.

(17) FIG. 17 is a block diagram of an example processor platform including processor circuitry structured to execute and/or instantiate the example machine readable instructions of FIG. 6 to implement the example first neural network generation circuitry of FIG. 5.

(18) FIG. 18 is a block diagram of an example processor platform including processor circuitry structured to execute and/or instantiate the example machine readable instructions of FIG. 7 to implement the example second neural network generation circuitry of FIG. 5.

(19) FIG. 19 is a block diagram of an example software distribution platform (e.g., one or more servers) to distribute software (e.g., software corresponding to the example machine readable instructions of FIGS. 9 and/or 10) to client devices associated with end users and/or consumers (e.g., for license, sale, and/or use), retailers (e.g., for sale, re-sale, license, and/or sub-license), and/or original equipment manufacturers (OEMs) (e.g., for inclusion in products to be distributed to, for example, retailers and/or to other end users such as direct buy customers).

(20) The figures are not to scale. In general, the same reference numbers will be used throughout the drawing(s) and accompanying written description to refer to the same or like parts.

(21) Unless specifically stated otherwise, descriptors such as “first,” “second,” “third,” etc. are used herein without imputing or otherwise indicating any meaning of priority, physical order, arrangement in a list, and/or ordering in any way, but are merely used as labels and/or arbitrary names to distinguish elements for ease of understanding the disclosed examples. In some examples, the descriptor “first” may be used to refer to an element in the detailed description, while the same element may be referred to in a claim with a different descriptor such as “second” or “third.” In such instances, it should be understood that such descriptors are used merely for identifying those elements distinctly that might, for example, otherwise share a same name.

(22) As used herein, the phrase “in communication,” including variations thereof, encompasses direct communication and/or indirect communication through one or more intermediary components, and does not require direct physical (e.g., wired) communication and/or constant communication, but rather additionally includes selective communication at periodic intervals, scheduled intervals, aperiodic intervals, and/or one-time events. As used herein, “processor circuitry” is defined to include (i) one or more special purpose electrical circuits structured to perform specific operation(s) and including one or more semiconductor-based logic devices (e.g., electrical hardware implemented by one or more transistors), and/or (ii) one or more general purpose semiconductor-based electrical circuits programmed with instructions to perform specific operations and including one or more semiconductor-based logic devices (e.g., electrical hardware implemented by one or more transistors). Examples of processor circuitry include programmed microprocessors, Field Programmable Gate Arrays (FPGAs) that may instantiate instructions, Central Processor Units (CPUs), Graphics Processor Units (GPUs), Digital Signal Processors (DSPs), XPU, or microcontrollers and integrated circuits such as Application Specific Integrated Circuits (ASICs). For example, an XPU may be implemented by a heterogeneous computing

system including multiple types of processor circuitry (e.g., one or more FPGAs, one or more CPUs, one or more GPUs, one or more DSPs, etc., and/or a combination thereof) and application programming interface(s) (API(s)) that may assign computing task(s) to whichever one(s) of the multiple types of the processing circuitry is/are best suited to execute the computing task(s).

DETAILED DESCRIPTION

(23) An electronic user device such as a laptop, tablet, or smartphone includes one or more microphones (e.g., a built-in microphone array) to capture sound such as speech by a user of the device and/or sounds in an environment in which the device is located. The microphones convert the sound into electrical signal(s) for processing by processor circuitry of the user device. The user device may include user applications such as a video conferencing application installed thereon. During a video conference, the microphone(s) of the device capture voice-generated sound (e.g., speech) of the user while one or more camera(s) of the electronic user device capture image(s) (e.g., video) of the user.

(24) In some instances, an audio signal level output by the microphone(s) of the user device and representing the user's voice during a video conference is subject to fluctuation as the user (i.e., speaker) changes position with respect to the user device and, thus, the microphone(s). For instance, as the user moves toward the microphone(s), the signal level output by the microphone(s) increases. As the user moves away from the microphone(s), the signal level output by the microphone(s) decreases. The fluctuating signal level of the captured sound can affect characteristics of the voice audio transmitted to and output by user devices associated with other participants of the video conference. For instance, when the speaker is close to the microphone(s), the voice audio of the speaker transmitted to the other user device(s) can be associated with higher volume than when the speaker is farther away from the microphone(s).

(25) In some cases, the electrical signal(s) output by the microphone(s) are amplified before processing by the processor circuitry of the user device. An amplifier applies a gain to the microphone signal to increase the signal level. Gain is a measurement of an ability of an amplifier to increase an amplitude of a signal from an input port to an output port (e.g., by adding energy to the signal). The amplifier applies gain to an input signal to increase an amplitude of the signal at the output of the amplifier. Microphone gain is the gain applied by the amplifier to microphone signal(s) to increase the amplitude of the signal(s). As a result of the increased gain, a loudness of a voice captured in the microphone signal(s) can be increased.

(26) Some known electronic user devices include microphone gain control systems to adjust microphone gain in view of fluctuations in microphone input signal(s). For instance, automatic gain control (AGC) uses signal level-based analysis to dynamically increase or decrease the gain applied to a signal in view of a microphone output signal level range threshold. For instance, an AGC system may detect an input signal level below a threshold output level range and instruct the amplifier to apply a gain based on the threshold. However, AGC control systems do not discriminate input signals based on audio type. Therefore, the AGC system may adjust the gain on the input signal without discriminating between, for instance, frequency differences between background noise and a speaker's voice during a video conference. For example, an AGC system may detect a low amplitude input audio signal that corresponds to a background noise such as a footsteps or noise generated by an air conditioning unit. Because this input signal level is below the threshold output signal level range, the AGC may instruct the amplifier to increase the gain to applied to the audio signal, which can distort the voice audio that is also captured in the audio signal and transmitted to the user device(s) of the other video conference attendee(s).

(27) Disclosed herein are example apparatus, systems, and methods that provide for dynamic microphone gain control based on a proximity of a user (i.e., a speaker) to a camera associated with the user device. In examples disclosed herein, image data is generated by a video camera associated with the device (e.g., a built-in video camera, a separate camera that is an accessory to the user device) during, for instance, a video conference. Also, during the video conference, audio data from

the user is captured via microphone(s) associated with the device (e.g., a built-in microphone array). Examples disclosed herein include user proximity detection circuitry to analyze the image data to detect a proximity of the user relative to the camera. Although examples disclosed herein are discussed in connection with video data, other types of image data (e.g., still image data) could be used.

(28) Examples disclosed herein include microphone gain control circuitry to determine an amount of gain by which the audio signal output by the microphone(s) should be adjusted based on the proximity of the user to the camera. In examples disclosed herein, the microphone gain control circuitry instructs an amplifier to apply the gain of the microphone audio signal to provide a signal in which an audio output level of the user's voice is independent of the position of the user relative to the camera. As a result, fluctuations in the volume level of the speaker's voice as perceived by other participants in the video conference due to changes in the distance of the speaker from the device are reduced or substantially eliminated.

(29) Examples disclosed herein determine user proximity based on detection of landmarks in the image data generated by the camera(s) of the device. Some examples disclosed herein detect a user's face in the image data and identify landmarks with respect to the user's face via image recognition analysis. The facial landmarks can include, for example, a location of the user's two eyes. Some examples disclosed herein determine a distance between corresponding points identified at the user's right and left eyes. For instance, a first point located at an edge of a user's right eye proximate to the user's nose and a second, opposite point at an edge of the user's left eye proximate the user's nose can be identified in the image data. A distance between the first point and the second point is used to determine (e.g., estimate) a size (e.g., width) of the user's nose bridge in pixels. The size of the user's nose bridge as detected from the image data can serve as an indicator of a proximity of the user to the camera. The nose bridge can be selected as a proxy for determining user distance from the camera because a width of the nose bridge may have less variance across demographics (e.g., genders, nationalities) than other facial features; however, other facial features could alternatively be used to determine user proximity.

(30) In some examples, the image data can include multiple individuals. In such examples, one of the individuals may be identified as or predicted to be the speaker based on, for example, an analysis of sizes of bounding boxes associated with each user during image analysis.

(31) Examples disclosed herein correlate the amount of gain to be applied to the audio signal with the proximity of the face the user (i.e., the speaker) to the camera. In some examples disclosed herein, the gain applied to a voice band of the audio signal generated by the microphone(s) is increased when the proximity of the user to the camera is determined to be greater than a threshold distance from the camera. Conversely, a gain applied to the voice band of the microphone audio signal is decreased when the proximity of the user to the camera is less than a threshold distance from the camera. The proximity-based adjustments to the gain provide for a substantially consistent voice level output in the audio signal data that is transmitted to other user devices (e.g., devices associated with other participants of a video conference). Examples disclosed herein provide for user proximity detection using image data collected during video calls rather than using separate proximity sensors that would increase computing resources. Thus, examples disclosed herein provide for efficient use of computer resources to adjust microphone gain based on user proximity.

(32) FIG. 1 illustrates an example user device **100** constructed in accordance with teachings of this disclosure for applying dynamic microphone gain control based on user proximity sensing. In the example of FIG. 1, the user device **100** is a laptop. However, the user device **100** can include other types personal computing (PC) devices such as a desktop, an electronic tablet, a hybrid or convertible PC, etc. In some examples, the user device **100** includes a mobile device such as a smartphone.

(33) The example user device **100** includes one or more microphones **102**. The microphones **102** provide means for detecting sounds in the environment in which the user device **100** is located. In

some examples, the user device **100** includes two or more microphones defining a microphone array. The microphone(s) **102** can be carried by the user device **100** on, for example, one or more sides of a lid of the device **100**. In other examples, the microphone(s) **102** are an accessory removably coupled to one or portions of the user device **100**.

(34) The example user device **100** of FIG. 1 includes a display screen **108** to present graphical content to a user **106** of the user device **100**. The example user device **100** of FIG. 1 includes one or more camera(s) **104**. The camera(s) **104** provide means for generating image data. In the example of FIG. 1, the user device **100** includes a user-facing camera **104** positioned proximate to the display screen **108** of the user device **100** such that when a user **106** faces the display screen **108**, the user is within a field of view of the camera **104**. The camera(s) **104** of the user device **100** can include a video camera. Although in the example of FIG. 1, the camera **104** is integrated with (e.g., built-into) a housing of the user device **100**, in other examples, the camera(s) **104** are removably coupled to one or portions of the user device **100**. For example, a camera **104** (e.g., a webcam) can be coupled to the user device **100** (e.g., to a lid of a laptop, to a monitor of a desktop).

(35) In the example of FIG. 1, the microphone(s) **102** can be used to output audio signal(s) in response to sound (e.g., speech) captured from the user **106** (the terms “user” and “subject” are used interchangeably herein and both refer to a human being). Also, the camera(s) **104** of the user device **100** can generate image data including at least a portion of the user **106** such as a face of the user **106**. In some examples, the microphone(s) **102** and the camera(s) **104** are used by a teleconference application (e.g., a video conference application) installed on the user device **100** such that sound and image data associated with the user **106** are captured by the microphone(s) **102** and the camera(s) **104**, respectively, and processed by the user device **100** for transmission to user device(s) associated with other participant(s) of the teleconference.

(36) In the example of FIG. 1, an amplitude of audio signal output by the microphone(s) **102** in response to sound captured from the user **106** can vary based on a position of the user **106** relative to the microphone(s) **102** of the user device **100** even if the user **106** is making the same sound at the same volume level. In examples disclosed herein, image data generated by the camera(s) **104** associated with the user device **100** can be used to determine a distance of the user **106** from the camera(s) **104** and, thus, the microphone(s) **102** of the user device **100**. For instance, in the example of FIG. 1, the user **106** is in a first position in which the user **106** is a first distance $X_{sub.1}$ from the camera(s) **104** of the user device **100**. As a result, the audio signal(s) generated by the microphone(s) **102** that captures a voice of the user **106** when the user **106** is speaking while in the first position of FIG. 1 are associated with a first audio signal level.

(37) In FIG. 2, the user **106** is positioned a second distance $X_{sub.2}$ from the camera(s) **104** of the user device **100**. The second distance $X_{sub.2}$ of the user **106** from the camera(s) **104** shown in FIG. 2 is greater than the first distance $X_{sub.1}$ of the user **106** from the camera(s) **104** shown in FIG. 1. Put another way, the user **106** is farther from the camera(s) **104** in FIG. 2 than in FIG. 1 and, thus, farther from the user device **100** including the microphone(s) **102** in FIG. 2 than in FIG. 1. As a result, the audio signal(s) generated by the microphone(s) **102** that capture the voice of the user **106** when the user **106** is speaking while in the second position of FIG. 2 are associated with a second audio signal level. For example, an amplitude of the audio corresponding to the voice of the user **106** when the user **106** is in the second position of FIG. 2 may be less than the amplitude of the audio corresponding to the voice of the user **106** when the user is in the first position of FIG. 1 even if the user is making the exact same sound at the exact same volume due to the increased distance of the user **106** from the microphone(s) **102**.

(38) FIG. 3 illustrates an example system **300** constructed in accordance with teachings of this disclosure for controlling microphone gain in response to user proximity to a user device associated with the microphone(s). The example system **300** of FIG. 3 includes a user device **301** (e.g., the user device **100** of FIG. 1). As discussed in connection with FIG. 1, the user device **301** can be a personal computing device such as a laptop, a desktop computer, an electronic tablet, a smartphone,

etc.

(39) The example user device **301** includes the display screen **108**. In some examples, the display screen **108** is a touch screen that enables a user (e.g., the user **106** of FIG. **1**) to interact with data presented on the display screen **108** by touching the display screen **108** with a stylus and/or one or more fingers or a hand of the user. Additionally or alternatively, the user can interact with data presented on the display screen **108** via user input device(s) **302** such as the microphone(s) **102**, a keyboard, a mouse, touch pad, etc. The example user device **301** includes one or more output device(s) **304** such as speaker(s) **306** to provide audible outputs to the user of the user device **301**.

(40) The example user device **301** of FIG. **3** includes processor circuitry **310**. The processor circuitry **310** of the example user device **301** is a semiconductor-based hardware logic device. The hardware processor circuitry **310** may implement a central processing unit (CPU) of the user device **301**, may include any number of cores, and may be implemented, for example, by a processing commercially available from Intel® Corporation. The processor circuitry **310** executes machine readable instructions (e.g., software) including, for example, user application(s) **312** such as a video conferencing application **314** installed on the user device **301**. The user application(s) **312** are stored in one or more storage devices **316** such as non-volatile memory (e.g., flash memory). The example user device **301** of FIG. **3** includes a power source **318** such as a battery and/or transformer and AC/DC converter to provide power to the processor circuitry **310** and/or other components of the user device **301** communicatively coupled via a bus **320**.

(41) The example user device **301** of FIG. **3** includes the camera(s) **104**. The example user device **301** of FIG. **3** includes a video encoder **308** to process image data output by the camera(s) **104**. As disclosed in connection with FIGS. **1** and **2**, the camera(s) **104** generate image data including at least a portion of one or more users (e.g., the user **106**) of the user device **301**. Also, the microphone(s) **102** output audio signal(s) including the voice(s) of the user(s) while interacting with the video conferencing application **314**. The example user device **301** includes an analog-to-digital (A/D) converter **305** to convert analog signals from the microphone(s) **102** to digital signal(s).

(42) In the example of FIG. **3**, image data generated by the camera(s) **104** of the user device **301** (e.g., during use of the video conferencing application **314**) and processed by the video encoder **308** is passed to user proximity detection circuitry **322** to determine a position of a user (e.g., the user **106**) relative to the camera(s) **104** of the user device **301**. The example user proximity detection circuitry **322** analyzes the image data to detect the face(s) of user(s) captured in the image data. The image data including the face(s) is analyzed by the example user proximity detection circuitry **322** to identify a speaker based on bounding box analysis and to estimate a size of certain features of the face of the speaker in the image in pixels, such as size (e.g., width) of the speaker's nose bridge. Based on the size of the facial features, the example user proximity detection circuitry **322** estimates a distance of the speaker to the camera(s) **104** of the user device **301**. The estimated or predicted user proximity value is used to control an amount of gain control applied to the audio signal capturing the speaker's voice.

(43) In the example of FIG. **3**, the user proximity detection circuitry **322** is implemented by executable instructions executed on the processor circuitry **310** of the user device **301**. However, in other examples, the user proximity detection circuitry **322** is implemented by processor circuitry **324** of another user device **326** (e.g., a smartphone, an edge device, a wearable device, etc.) in communication with the user device **301** (e.g., via wired or wireless communication protocols), and/or by a cloud-based device **328** (e.g., one or more server(s), processor(s), and/or virtual machine(s)). In other examples, the user proximity detection circuitry **322** is implemented by dedicated circuitry located on the user device **301** and/or the user device **326**. These components may be implemented in software, hardware, or in any combination of two or more of software, firmware, and/or hardware.

(44) In the example of FIG. **3**, the user proximity estimation determined by the user proximity

detection circuitry **322** is passed to microphone gain control circuitry **330**. In the example of FIG. **3**, the microphone gain control circuitry **330** determines an amount of gain by which the audio signal(s) output by the microphone(s) **102** (e.g., during use of the video conferencing application **314**) should be adjusted based on the user proximity estimation. The microphone gain control circuitry **330** generates instructions that cause an amplifier **332** of the user device **301** to adjust the gain of the audio signal(s) generated by the microphones(s) **102**. The amplifier **332** provides means for amplifying the audio signal(s) by, for instance, applying gain to the audio signal(s). The example microphone gain control circuitry **330** of FIG. **1** analyzes the audio data output by the microphone(s) **102** to estimate a noise level (e.g., ambient noise level) in the audio data. The microphone gain control circuitry **330** compares a voice band signal level in the audio data to the noise level to determine a signal-to-noise ratio of the audio signal(s) output by the microphone(s) **102**. In the example of FIG. **3**, if the signal-to-noise ratio is below a threshold, the microphone gain control circuitry **330** refrains from causing the amplifier **332** to adjust the gain of the audio signal(s) to prevent amplification of ambient noise.

(45) The example microphone gain control circuitry **330** of FIG. **3** can perform other types of audio signal processing and/or analysis. For instance, the microphone gain control circuitry **330** of FIG. **3** can include a filter to filter the audio data (e.g., apply a low pass filter) to remove components of the audio data outside of a voice band (e.g., a range of audio frequencies in the audio signal that is associated with speech). In such examples, the gain adjustment(s) are applied to the filtered audio data signal(s). Thus, as a result of the processing of the audio signals by the microphone gain control circuitry **330**, the amplifier **332** adjusts the gain of the voice band in the signal data based on user proximity and in view of variables such as a signal-to-noise ratio of the audio data.

(46) In the example of FIG. **3**, the microphone gain control circuitry **330** is implemented by executable instructions executed on the processor circuitry **310** of the user device **301**. However, in other examples, microphone gain control circuitry **330** is implemented by the processor circuitry **324** of the other user device **326** and/or by the cloud-based device(s) **328** (e.g., one or more server(s), processor(s), and/or virtual machine(s)). In other examples, the user proximity detection circuitry **322** is implemented by dedicated circuitry located on the user device **301** and/or the user device **326**. These components may be implemented in software, hardware, or in any combination of two or more of software, firmware, and/or hardware.

(47) In some examples, the amplifier **332** is implemented by the processor circuitry **310**. In other examples, the amplifier **332** is implemented by dedicated circuitry.

(48) In the example of FIG. **3**, the audio data including the adjusted gain as determined by the microphone gain control circuitry **330** and applied by the amplifier **332** is transmitted to one or more video conferencing output device(s) **334** (e.g., laptops, smartphones, etc. associated with other participants of the video conference). The audio data may be transmitted to the video conferencing output device(s) **334** via one or more protocol(s) (e.g., voice-over-internet protocol(s)) associated with the video conferencing application **314**. As a result of the user-proximity based gain control provided by the microphone gain control circuitry **330**, fluctuations in the audio level of the voice of the speaker (e.g., the user **106**) output at the video conferencing output device(s) **334** (e.g., by speaker(s) of the video conferencing output device(s) **334**) due to changes in the distance of the speaker relative to the user device **301** are reduced or substantially eliminated.

(49) FIG. **4** is a block diagram of an example implementation of the user proximity detection circuitry **322** and the microphone gain control circuitry **330** of FIG. **3**. As mentioned above, the user proximity detection circuitry **322** is structured to identify (e.g., predict, estimate, recognize) a proximity of a speaker (e.g., the user **106** of FIG. **1**) relative to the camera(s) **104** of the user device **301**. In the example of FIG. **4**, the user proximity detection circuitry **322** is implemented by one or more of the processor circuitry **310** of the user device **301**, the processor circuitry **324** of the second user device **326**, and/or cloud-based device(s) **328** (e.g., server(s), processors(s), and/or virtual

machine(s) in the cloud **328** of FIG. **1** executing instructions). In some examples, some of the user proximity analysis is implemented by the user proximity detection circuitry **322** via a cloud-computing environment and one or more other parts of the analysis is implemented by the processor circuitry **310** of the user device **301** and/or the processor circuitry **324** of the user device **326** such as a wearable device. In some examples, the user proximity detection circuitry **322** is implemented by special purpose circuitry.

(50) As also mentioned above, the microphone gain control circuitry **330** is structured to control gain applied to audio signal(s) capturing a voice of the speaker and output by the microphone(s) **102** of the user device **301**. In the example of FIG. **4**, the microphone gain control circuitry **330** is implemented by one or more of the processor circuitry **310** of the user device **301**, the processor circuitry **324** of the second user device **326**, and/or cloud-based device(s) **328** (e.g., server(s), processors(s), and/or virtual machine(s) in the cloud **328** of FIG. **1** executing instructions). In some examples, some of the gain control analysis is implemented by the microphone gain control circuitry **330** via a cloud-computing environment and one or more other parts of the analysis is implemented by the processor circuitry **310** of the user device **301** and/or the processor circuitry **324** of the user device **326** such as a wearable device. In some examples, the microphone gain control circuitry **330** is implemented by special purpose circuitry

(51) During a video conference using the user device **301** (e.g., during operation of the video conferencing application **314**), the camera(s) **104** (e.g., video camera(s)) of the user device **100** of FIG. **1** generate image data in the form of a video stream or feed signal **402** (e.g., output by the video encoder **308** of FIG. **3**). In the example of FIG. **4**, the video stream signal **402** is provided to the user proximity detection circuitry **322** for analysis with respect to proximity of the user (i.e., the speaker) relative to the camera(s) **104**. Also, during a video conference, the microphone(s) **102** of the user device **100** generate an audio stream signal **404** based on sound captured from the user of the user device **301** and/or the environment in which the user device **301** is located. As disclosed herein, the audio stream signal **404** is sampled and the samples are provided to the microphone gain control circuitry **330** for gain control.

(52) In some examples, the video stream signal **402** is captured at a high resolution (e.g., 1280×720 pixels) and a high frame rate (e.g., 30 frames per second (FPS)) based on, for example, settings associated with the video conferencing application **314** and/or the video encoder **308** of FIG. **3**. The example user proximity detection circuitry **322** of FIG. **4** includes video preprocessing circuitry **406**. In the example of FIG. **4**, the video preprocessing circuitry **406** down samples the video stream signal **402** output by the camera(s) **104**. For example, the video preprocessing circuitry **406** reduces a sampling rate of the video stream signal **402** from, for instance, 30 FPS to 3 FPS. In some examples, the video preprocessing circuitry **406** samples the video stream signal **402** at a rate of 1-5 FPS. The video preprocessing circuitry **406** generates processed video frame(s) **405** as a result of the down sampling. In some examples, the video preprocessing circuitry **406** reduces or reshapes a resolution of the processed video frame(s) **405**. For example, the video preprocessing circuitry **406** can decrease a resolution of the processed video frame(s) **405** (e.g., from 1280×720 pixels to 300×300 pixels). The down-sampling and/or resolution reduction performed by the video preprocessing circuitry **406** reduces consumption of computing resources during the user proximity analysis without sacrificing accuracy in detection of the proximity of the user to the camera(s) **104**.

(53) The example user proximity detection circuitry **322** includes face detection circuitry **408**. In the example of FIG. **4**, the face detection circuitry **408** detects face(s) (i.e., human face(s)) in the video frames **405**. In the example of FIG. **4**, the face detection circuitry **408** executes one or more neural network model(s) to detect face(s) in the respective video frame(s) **405**. In particular, the example face detection circuitry **408** of FIG. **4** executes one or more face detection model(s) **414** to identify face(s) in the video frame(s) **405** and to output bounding boxes at the predicted location(s) of the face(s) in the video frame image data **405**. As disclosed in connection with FIG. **5**, the face detection model(s) **414** are generated as a result of neural network training.

(54) In the example of FIG. 4, the face detection model(s) **414** are stored in a database **412**. In some examples, the user proximity detection circuitry **322** includes the database **412**. In other examples, the database **412** is located external to the user proximity detection circuitry **322** in a location accessible to the user proximity detection circuitry **322** as shown in FIG. 4.

(55) As a result of the execution of the face detection model(s) **414**, the face detection circuitry **408** detects or identifies faces in the respective video frame(s) **405** and locates the face(s) by creating a bounding box around each predicted face. In the example of FIG. 4, the outputs of the face detection model(s) **414** include corresponding confidence level(s) associated with the predicted face(s). In the example of FIG. 4, an area of a bounding box generated as a result of execution of the face detection model(s) **414** is substantially proportional to a size of the face detected in the video frame **405** and a proximity of the face to the camera(s) **104** of the user device **100**.

(56) The example user proximity detection circuitry **322** of FIG. 4 includes a face filter **410**. The face filter **410** filters the bounding boxes associated with detected face(s) in the respective video frame(s) **405** based on the confidence level(s) assigned to the prediction(s) and a face detection threshold. The face detection threshold can define a confidence level or probability likelihood that a bounding box is associated with a human face captured in the image data. For example, the face detection threshold can define a minimum confidence level of 80% with respect to detecting face(s). The face detection threshold can be defined by user input(s) and stored in the database **412**. In the example of FIG. 4, the face filter **410** compares the respective confidence level(s) associated with the bounding box(es) generated as a result of execution of the face detection model(s) **414** for the video frame(s) **405** to the face detection threshold. Based on the comparison, the face filter **410** identifies the bounding box(es) that satisfy the threshold and, thus, are likely to represent face(s) in the video frame(s) **405**. In some examples, the face filter **410** removes the bounding box(es) in a video frame **405** that do not satisfy the face detection threshold from further analysis. In some examples, the face filter **410** identifies video frame(s) **405** that include bounding box(es) that satisfy the face detection threshold and removes (e.g., deletes) the video frame(s) **405** that do not include any bounding boxes that satisfy the threshold from further analysis.

(57) In some examples, the face filter **410** identifies more than one bounding box in a video frame **405** that satisfies the face detection threshold. Thus, in such examples, more than one face is detected in the video frame **405**. In these examples, the face filter **410** selects the bounding box with the largest area for further analysis. Put another way, when multiple bounding boxes in a video frame **405** satisfy the face detection threshold, the face filter **410** selects the bounding box with the largest area as most likely representative of a user who is speaking while interacting with the user device **100** (e.g., a primary speaker during the video conference) based on the size of the bounding box associated with the user's face relative to other faces in the image data. For instance, a face of a user who is closest to the camera(s) **104** and centered relative to the field of view of the camera(s) **104** may be associated with the largest bounding box in the video frame **405**, thereby indicating that the user is most likely the speaker during the video conference because of his or her position relative to the camera(s) **104**. The video frame(s) **405** including bounding box(es) that satisfy the face detection threshold are stored in the database **412** as filtered video frame(s) **415**.

(58) The example user proximity detection circuitry **322** of FIG. 4 includes face landmark detection circuitry **416**. The example face landmark detection circuitry **416** detects face landmark(s) **418** in a face associated with a bounding box (e.g., the bounding box having the largest area) in a filtered video frame **415**. The face landmarks **418** include key points on a face corresponding to features of the face (e.g., tip of a nose, inner corner of an eye) as detected in the image data (e.g., pixel data). In the example of FIG. 4, the face landmarks **418** identified by the face landmark detection circuitry **416** are used to determine attributes of a face of the user (i.e., the speaker), such as a size of the user's nose bridge, or a portion of the nose extending between the user's eyes.

(59) In the example of FIG. 4, the face landmark detection circuitry **416** executes neural network model(s) to detect the face landmarks **418** in the video frame(s) **405**. In particular, the example face

landmark detection circuitry **416** of FIG. **4** executes landmark detection model(s) **420** stored in the database **412** to identify the face landmarks **418** in the video frame(s) **405**. As disclosed in connection with FIG. **5**, the landmark detection model(s) **420** are generated as a result of neural network training. As a result of the execution of the landmark detection model(s) **420**, the face landmark detection circuitry **416** detects or identifies the face landmarks **418** in the respective video frame(s) **405**. The landmark detection model(s) **420** can be generated to enable the face landmark detection circuitry **416** to detect particular face landmarks, such as a corner of the user's respective eyes proximate to the user's nose. Each face landmark **418** identified in a video frame **405** can be represented by a two-dimensional coordinate indicating the location of pixel in the video frame **405** representative of a key point on a face.

(60) The example face landmark detection circuitry **416** of FIG. **4** also determines a distance (e.g., number of pixels) between the extracted face landmarks **418**. The face landmark detection circuitry **416** can select two face landmarks **418** to determine a distance between the two the face landmarks **418**. The face landmark detection circuitry **416** determines the two-dimensional distance between the two face landmarks **418** using the two-dimensional coordinates of the pixels associated with the respective locations of the face landmarks **418**. In some examples, the face landmark detection circuitry **416** rounds the distance between the two face landmarks **418** to the nearest integer representing a number of pixels between the two points at which the landmarks **418** are located. In other examples, the face landmark detection circuitry **416** outputs a non-integer distance of pixels between the two face landmark points. As disclosed herein, the distance P between the two face landmarks **418** as determined by the face landmark detection circuitry **416** is used by the user proximity detection circuitry **322** to determine a distance between the face of the user (i.e., speaker) and the camera(s) **104**.

(61) The example user proximity detection circuitry **322** of FIG. **4** includes proximity estimating circuitry **422**. The example proximity estimating circuitry **422** determines a proximity of the user associated with the facial landmarks **418** identified by the face landmark detection circuitry **416** relative to the camera(s) **104** associated with the user device **100**. In the example of FIG. **4**, the facial landmarks **418** identified by the face landmark detection circuitry **416** are used to estimate or determine a distance of the user from the camera(s) **104**. For example, the face landmark detection circuitry **416** can identify the coordinates of pixels corresponding to the corners of the user's eyes proximate to the user's nose and calculate the distance P in pixels between the eye points to estimate a width of a nose bridge of the user. The proximity estimating circuitry **422** retrieves a reference value W that defines a known width of a human nose bridge from anthropomorphic reference data **424** stored in the database **412**. The anthropomorphic reference data **424** can be defined by user input(s) include known measurements (e.g., widths) for facial features such as the nose bridge. The anthropomorphic reference data **424** can include facial feature measurement(s) based on, for example, average data collected for individuals based on gender, demographics, age, etc. Although in examples disclosed herein refer to using a width of the nose bridge in the proximity determination, other facial feature measurements (e.g., a forehead width) can be used.

(62) The example proximity estimating circuitry **422** determines D , the distance between the face of the user (e.g., a user whose face is associated with the largest bounding box, the user **106** of FIG. **1**, etc.) and the camera(s) **104**, using Equation 1, below, wherein W is the reference facial feature measurement (e.g., a known nose bridge width), F is the focal length of the camera(s) **104** (stored as camera reference data **417** in the database **412** and defined by user input(s) for the camera(s) **104**), and P is the measured distance between the landmarks **418** in pixels that represent a facial feature measurement for the user in the image data (e.g., a measured nose bridge width). Equation 1 can be based on triangular similarity.

(63)
$$D = \frac{(W \times F)}{P} \quad (\text{Equation } 1)$$

(64) The distance D between the user and the camera(s) **104** represents the proximity of the user to

the camera(s) **104**. In the example of FIG. **4**, the distance D of the user from the camera(s) **104** and the measured distance P between the face landmarks (e.g., representing a size of the user's nose bridge in pixels) have an inverse relationship. In particular, the smaller the distance between the user and camera(s) **104**, the larger the size of the user's nose bridge as determined by the face landmark detection circuitry **416** based on the face landmarks **418** identified in the video frame(s) **405**. As the distance between the user and the camera(s) **104** increases, a size of the nose bridge of the user as determined from the pixel image data decreases. For example, when the user is a distance of 30 centimeters (cm) from the camera(s) **104**, the face landmark detection circuitry **416** may estimate the width of the user's nose bridge to be 83 pixels. As another example, when the user is a distance of 180 cm from the camera(s) **104**, the face landmark detection circuitry **416** may estimate the width of the user's nose bridge size to be 18 pixels.

(65) In the example of FIG. **4**, the proximity estimating circuitry **422** determines the distance D of the user identified in the image data from the camera(s) **104** for each video frame **405** output by the video preprocessing circuitry **406**. The proximity estimating circuitry **422** can generate a curve based on the proximity values D. In some examples, the proximity values can vary between the video frames **405** extracted from the video stream **402**, which can indicate that the user has moved relative to the camera(s) **104**. However, in some examples, the change in distance between the user and the camera(s) **104** is an anomaly due to, for example, a quick head movement of the user that is captured in the video frame(s) **405**. For example, the proximity estimating circuitry **422** may determine a first distance D.sub.1 between the user and the camera(s) **104** for a first video frame **405**, a second distance D.sub.2 for a second video frame **405**, and a third distance D.sub.3 for a third video frame **405**, where the second distance D.sub.2 is greater than the first distance D.sub.1 and the third distance D.sub.3. Such variations in the user proximity measurement between the video frames may represent an anomaly in the user proximity calculation as a result of, for instance, a quick head movement of the user, rather than reflecting actual changes in the distance of the user from the camera(s) **104**, which can result in undesired effects when the user proximity values are used for audio gain control. In the example of FIG. **4**, the proximity estimating circuitry **422** provides for smoothing of the proximity values to reduce and/or eliminate anomalies in the user proximity values between video frame(s) (e.g., adjacent video frames).

(66) In the example of FIG. **4**, the proximity estimating circuitry **422** performs a smoothing operation using Equations 2 and 3, below.

$$\mu[0]=x[0] \quad (\text{Equation 2})$$

$$\mu[n]=\alpha x[n]+(1-\alpha)\mu[n-1] \quad (\text{Equation 3})$$

(67) In the above Equations 2 and 3, $\mu[n]$ represents a smoothed proximity value at a time step n and $x[n]$ represents an actual proximity value at a time step n, where $n=0$ represents the initial time step. A filtering parameter α is a tunable parameter that may be adjusted between 0 and 1. For instance, the filter parameter can be assigned a value of $\alpha=0.2$ to generate smooth proximity value curve.

(68) Thus, the example user proximity detection circuitry **322** of FIG. **4** determines estimated, smoothed user proximity value(s) based on the video stream signal **402** output by the camera(s) **104**. In the example of FIG. **4**, the microphone gain control circuitry **330** analyzes the audio stream signal **404** to control gain applied to the audio stream signal **404**. In particular, the microphone gain control circuitry **330** adjusts an amount of gain applied to the audio stream signal **404** based on analysis of the audio stream signal **404** and the user proximity estimation determined by the user proximity detection circuitry **322**.

(69) In the example of FIG. **4**, the A/D converter **305** of the user device **100** samples the audio stream signal **404** and generates digital audio samples **407**. The example microphone gain control circuitry **330** of FIG. **4** includes a digital low-pass voice filter **426**. The example low-pass voice filter **426** provides filters the audio samples **407** to reduce effects of ambient noise in the environment in which the user device **100** is located and captured by the microphone(s) **102**. The

low-pass voice filter **426** can include, for example, a digital infinite impulse response (IIR) elliptic filter. In the example of FIG. **4**, the low-pass voice filter **426** filters the audio samples **407** to remove noise that falls outside of a frequency range associated with a voice band of human speech. In some examples, the voice band is defined as frequencies of less than 6 kHz. The voice band frequencies can be defined by user input(s). As a result of the filtering, the low pass voice filter **426** outputs filtered audio samples **409** associated with a frequency band range from 0 to 6 kHz corresponding to the voice band.

(70) The example microphone gain control circuitry **330** of FIG. **4** includes noise estimating circuitry **428**. The example noise estimating circuitry **428** determines a level of ambient noise level in the audio samples **407**. In particular, the noise estimating circuitry **428** analyzes the audio samples **407** to identify the audio sample(s) **407** that do not include frequencies associated with the voice band. The noise estimating circuitry **428** estimates the ambient noise level based on frequencies in the audio sample(s) **407** that do not include the voice band frequencies.

(71) The example microphone gain control circuitry **330** of FIG. **4** includes a calculator **429**. In the example of FIG. **4**, the calculator **429** calculates a signal-to-noise ratio (SNR) based on (a) the filtered audio sample(s) **409** indicative of voice data and (b) the ambient noise level identified by the noise estimating circuitry **428**. In the example of FIG. **4**, the calculator **429** determines the SNR using Equation 4, below, where RMS.sub.signal is a root mean square of the filtered audio samples **409** including voice data and RMS.sub.noise is a root mean square of the audio samples **407** identified by the noise estimating circuitry **428** as not including voice activity.

(72)
$$\text{SNR} = 10 \log\left(\frac{\text{RMS}_{\text{signal}}^2}{\text{RMS}_{\text{noise}}^2}\right) \quad (\text{Equation } 4)$$

(73) The example microphone gain control circuitry **330** of FIG. **4** includes gain determining circuitry **430**. The example gain determining circuitry **430** determines an amount of gain to apply to the voice band of the filtered audio sample(s) **409**. The example gain determining circuitry **430** compares the SNR calculated by the calculator **429** to a SNR threshold level stored as SNR rule(s) **431**. The SNR threshold level defines a SNR value that should be satisfied or exceeded to cause the amplifier **332** to apply gain to the voice band of the filtered audio sample(s) **409**. For instance, in some examples, the audio samples **407** extracted from the audio stream signal **404** have a low SNR (e.g., less than 40 dB). In these examples, the audio samples **407** correspond to audio with a relatively high level of ambient noise. In such examples, the gain determining circuitry **430** determines, based on the SNR rule(s) **431**, that the gain of the filtered audio sample(s) **409** should not be adjusted because applying the gain would increase the loudness of the ambient noise in the audio signal. In some such examples, the gain determining circuitry **430** determines, based on the SNR rule(s) **431**, that a default gain value should be applied that does not (e.g., excessively) increase the loudness of the ambient noise in the audio.

(74) In other examples, the audio samples **407** have a high SNR (e.g., greater than 40 dB) corresponding to a low level of ambient noise in the audio data. In these examples, the gain determining circuitry **430** determines, based on the SNR rule(s) **431**, that the amplifier **332** should apply the gain to the filtered audio sample(s) **409** to adjust the volume level of the voice because of the low level of ambient noise. In the example of FIG. **4**, the gain determining circuitry **430** instructs the amplifier **332** to apply a gain to the respective filtered audio samples **409** if the SNR associated with those filtered audio samples **409** is above the SNR threshold (e.g., the SNR is greater than 40 dB) based on the SNR rule(s) **431**.

(75) The SNR rules **431** can be defined by user input(s) and stored in a database **432**. In some examples, the microphone gain control circuitry **330** includes the database **432**. In other examples, the database **432** is located external to the microphone gain control circuitry **330** in a location accessible to the microphone gain control circuitry **330** as shown in FIG. **4**. In some examples, the database **412**, **432** are the same database.

(76) In the example of FIG. **4**, if the SNR threshold is satisfied, the gain determining circuitry **430**

determines an amount of gain to be applied to the filtered audio sample(s) **409** based on the proximity of the user to the camera(s) **104** as determined by the proximity estimating circuitry **422** of the user proximity detection circuitry **322**. In the example of FIG. **4**, the proximity estimating circuitry **422** communicates the user proximity value(s) to the gain determining circuitry **430**. The gain determining circuitry **430** determines the gain to be applied in view of the user proximity value(s) based on proximity-gain mapping rule(s) **434**.

(77) The proximity-gain mapping rule(s) **434** include reference data or mapping(s) (e.g., table(s)) that associate user proximity values with respect to a distance of user(s) from user device(s) (including accessories such as camera(s)) to gain values to be applied to audio signal(s) captured by microphone(s) associated with the device(s). In particular, the proximity-gain mapping rule(s) **434** define relationships between user proximities to device(s) and gain to enable a substantially uniform loudness of voice to be output despite differences in user proximity relative to the device(s). The proximity-gain mapping rule(s) **434** can be defined based on user input(s) and stored in the database **432**. In some examples, the proximity-gain mapping rule(s) **434** are defined based on, for example, characteristics of the user device **100** (e.g., device type, signal processing hardware), characteristics of the microphone(s) **102**, etc.

(78) For example, the proximity-gain mapping rule(s) **434** can indicate if a distance between a user and a device is 40 cm, a gain value of 2 dB should be applied to the audio signal. As another example, the proximity-gain mapping rule(s) **434** can indicate that if the distance between the user and the device is 60 cm, a gain value of 6 dB should be applied to the audio signal. Thus, the proximity-gain mapping rule(s) **434** define that the amount of gain applied to the audio signal should increase as the distance between a user and the device and, thus, a microphone associated with the device, increases to enable the substantially uniform loudness of voice to be output despite the increased distance of the user from the microphone. In some examples, the proximity-gain mapping rule(s) **434** include a rule that if a distance between a user and a device is below a certain value, no gain should be applied to the audio signal to prevent unnecessary amplification of the voice band when the user is in close proximity to the device. The proximity-gain mapping rule(s) **434** can include a rule defining a maximum amount of gain to be applied such that if a distance between a user and a device is greater than a certain value, any further increase in distance of the user from the device does not result in any further increase in gain to avoid amplifying ambient noise rather than voice.

(79) The gain determining circuitry **430** uses the proximity-gain mapping rule(s) **434** to determine a gain value (i.e., an amount of gain) to be applied to a filtered audio sample **409** in view of a proximity of a user to the camera(s) **104** as determined by the proximity estimating circuitry **422**. In some examples, the gain determining circuitry **430** can perform interpolation (e.g., linear interpolation) to determine the gain value for the proximity value based on the proximity-gain mapping rule(s) **434** (e.g., the proximity gain mapping rule(s) **434** do not include the exact user proximity measurement). In some examples, the gain determining circuitry **430** applies an amplification factor to determine the gain value, where a value of the amplification factor as defined by the proximity-gain mapping rule(s) **434** increases with increased distance of the user from the camera(s) **104**.

(80) In the example of FIG. **4**, the analysis of the video stream signal **402** by the user proximity detection circuitry **322** and the analysis of the audio samples **407** by the microphone gain control circuitry **330** occur substantially in real-time (e.g., in a near instantaneous manner (e.g., ± 1 second) recognizing there may be real-world delays for computing time, transmission, etc.) as the video data and the audio data are generated. Thus, the proximity value determined by the proximity estimating circuitry **422** corresponds in time to the filtered audio samples **409** passed to the gain determining circuitry **430** for gain control by the low-pass filter **426**.

(81) The example microphone gain control circuitry **330** of FIG. **4** includes gain control circuitry **435**. The gain control circuitry **435** generates instructions that are transmitted to the amplifier **332**

to cause the amplifier **332** apply the gain determined by the gain determining circuitry **430**. In some examples, the amplifier **332** applies the gain to generate an amplified audio signal $y[n]$ using Equation 5, below, where $x[n]$ is the filtered audio sample **409** including the voice band output by the low-pass voice filter **426** and $g[n]$ is the gain as determined by the gain determining circuitry **430** based on the proximity-gain mapping rule(s) **434**.

$$y[n] = \text{Saturation}(g[n] * x[n]) \quad (\text{Equation 5})$$

(82) Amplified audio sample(s) **433** output by the amplifier **332** are transmitted to audio and video (A/V) time synchronization circuitry **436** of the user device **301**. The A/V time synchronization circuitry **436** also receives the video stream signal **402** output by the video encoder **308** of FIG. 3. The A/V time synchronization circuitry **436** performs time synchronization of the amplified audio sample(s) **433** and the video stream signal **402**. For example, the amplified audio sample(s) **433** and the video stream signal **402** can include time stamp data corresponding to a time at which the audio or video was captured. The A/V time synchronization circuitry **436** matches the time stamp(s) of the amplified audio sample(s) **433** to the time stamp(s) of the video stream signal **402** to create a time synchronized audio and video stream. The A/V time synchronization circuitry **436** outputs data including synchronized video data and amplified audio data for transmission to the video conference output device(s) **334** (e.g., based on communication protocols associated with, for instance, the video conferencing application **314**). In the example of FIG. 4, the A/V time synchronization circuitry **436** can be implemented by the processor circuitry **310** of the user device **301** of FIG. 3, the processor circuitry **324** of the second user device **326**, and/or cloud-based device(s) **328** (e.g., server(s), processors(s), and/or virtual machine(s) in the cloud **328** of FIG. 3).

(83) During a video conference (e.g., during operation of the video conferencing application **314**), the camera(s) **104** of the user device **301** generate the video stream signal **402** over time and the microphone(s) **102** generate the audio stream signal **404** over time. The user proximity detection circuitry **322** analyzes new video data in the video stream signal **402** to determine if there have been any changes with respect to the proximity of the user (i.e., the speaker) to the camera(s). Also, the microphone gain control circuitry **330** analyzes new audio data in the audio stream signal **404** over time. The microphone gain control circuitry **330** of FIGS. 3 and/or 4 dynamically responds to changes in user proximity to the camera(s) **104** by instructing the amplifier **332** to adjust gain in view of the proximity measurements received from the proximity estimating circuitry **422** over time. As a result, the example system **300** of FIGS. 3 and/or 4 provides for substantially consistent loudness of the voice output despite changes in user proximity to the camera(s) **104** and, by proxy, the microphone(s) **102**.

(84) The example user proximity detection circuitry **322** of FIGS. 3 and/or 4 also dynamically responds to changes in positions of two or more users, which can indicate a change in the primary speaker. For example, the face filter **410** analyzes the bounding boxes output by the face detection circuitry **408** for the respective video frames **405** over time. As the user move relative to the camera(s) **104** the size of the bounding box(es) and/or the confidence level(s) associated with the bounding box(es) may change. Thus, face selected by the face filter **410** for further analysis can change based on changes in the bounding box analysis. For example, a first user may be identified by the face filter **410** as associated with the largest bounding box in a first video frame. As such, the face landmark detection performed by the face landmark detection circuitry **416** and the proximity estimation performed by the proximity estimating circuitry **422** is based on image data for the first user in the first video frame. However, a second user may be identified by the face filter **410** as associated with the largest bounding box in a second video frame occurring after the first video frame. In such examples, the face landmark detection performed by the face landmark detection circuitry **416** and the proximity estimation performed by the proximity estimating circuitry **422** is based on image data for the second user in the second video frame. The gain determining circuitry **430** determines the gain to be applied based on the distance measurements about by the proximity estimating circuitry **422** for the particular user identified by the face filter

410. Thus, the example system **300** of FIG. **3** and/or **4** accounts for changes in user positions for two or more users, which can indicate changes in speaking roles, by continuously measuring user proximity and adjusting gain.

(85) In some examples, the face detection circuitry **408** may not be able to detect any faces in the video frame **405** because of, for instance, low lighting the environment in which the user device **301** is located during the video conference. In such examples, the user proximity detection circuitry **322** refrains from outputting user proximity measurements. Instead, the microphone gain control circuitry **330** can instruct the amplifier **332** to apply a default gain value to the filtered audio sample(s) based on the SNR rule(s) **431** and/or the proximity-gain mapping rule(s) **434**.

(86) In other examples, the camera(s) **104** may be turned off during the video conference and, thus, the video stream signal **402** is not generated. Instead, the microphone gain control circuitry **330** can instruct the amplifier **332** to apply a default gain value to the filtered audio sample(s) based on the SNR rule(s) **431** and/or the proximity-gain mapping rule(s) **434**.

(87) FIG. **5** is a block diagram of an example implementation of one or more computing systems for generating the neural network model(s) **414**, **420** used by the example user proximity detection circuitry **322** of FIGS. **3** and/or **4** to identify faces in the video frame(s) **405** and to identify facial landmarks in the face selected for further analysis by the face filter **410** of FIG. **4**.

(88) As disclosed in connection with FIG. **4**, the face detection circuitry **408** analyzes the video frame(s) **405** to identify face(s) in the image data associated with the video frame(s) **405**. In examples disclosed herein, machine learning is used to improve efficiency of the face detection circuitry **408** in detecting human faces in the video frames **405**.

(89) Artificial intelligence (AI), including machine learning (ML), deep learning (DL), and/or other artificial machine-driven logic, enables machines (e.g., computers, logic circuits, etc.) to use a model to process input data to generate an output based on patterns and/or associations previously learned by the model via a training process. For instance, the model may be trained with data to recognize patterns and/or associations and follow such patterns and/or associations when processing input data such that other input(s) result in output(s) consistent with the recognized patterns and/or associations.

(90) Many different types of machine learning models and/or machine learning architectures exist. In examples disclosed herein, a neural network model such as a VGGNet based Face Detection and Face Point detection neural network is used. In general, machine learning models/architectures that are suitable to use in the example approaches disclosed herein will be CNN based neural networks (e.g., CNN-based VGGNet neural networks). However, other types of machine learning models could additionally or alternatively be used.

(91) In general, implementing a ML/AI system involves two phases, a learning/training phase and an inference phase. In the learning/training phase, a training algorithm is used to train a model to operate in accordance with patterns and/or associations based on, for example, training data. In general, the model includes internal parameters that guide how input data is transformed into output data, such as through a series of nodes and connections within the model to transform input data into output data. Additionally, hyperparameters are used as part of the training process to control how the learning is performed (e.g., a learning rate, a number of layers to be used in the machine learning model, etc.). Hyperparameters are defined to be training parameters that are determined prior to initiating the training process.

(92) Different types of training may be performed based on the type of ML/AI model and/or the expected output. For example, supervised training uses inputs and corresponding expected (e.g., labeled) outputs to select parameters (e.g., by iterating over combinations of select parameters) for the ML/AI model that reduce model error. As used herein, labelling refers to an expected output of the machine learning model (e.g., a classification, an expected output value, etc.). Alternatively, unsupervised training (e.g., used in deep learning, a subset of machine learning, etc.) involves inferring patterns from inputs to select parameters for the ML/AI model (e.g., without the benefit of

expected (e.g., labeled) outputs).

(93) In some examples disclosed herein, ML/AI models are trained using stochastic gradient descent. However, any other training algorithm may additionally or alternatively be used. In examples disclosed herein, training is performed until a targeted accuracy level is reached (e.g., >95%). Training is performed using hyperparameters that control how the learning is performed (e.g., a learning rate, a number of layers to be used in the machine learning model, etc.). In other examples, pre-trained model(s) are used. In some examples re-training may be performed. Such re-training may be performed in response to, for example, poor face detection due to, for instance, low ambient lighting.

(94) Training is performed using training data. In examples disclosed herein, the training data originates from previously collected image data of users including user faces, previously generated bounding boxes, image data including particular facial features such as eyes, nose, etc. Because supervised training is used, the training data is labeled. In some examples, the training data is pre-processed to provide for light balancing in the image data, image rotation, etc.

(95) Once training is complete, the model is deployed for use as an executable construct that processes an input and provides an output based on the network of nodes and connections defined in the model. The model(s) are stored at one or more databases (e.g., the database **412** of FIG. **4**). The model may then be executed by the face detection circuitry **408** and the face landmark detection circuitry **416** of the example user proximity detection circuitry **322** of FIG. **4**.

(96) Once trained, the deployed model may be operated in an inference phase to process data. In the inference phase, data to be analyzed (e.g., live data) is input to the model, and the model executes to create an output. This inference phase can be thought of as the AI “thinking” to generate the output based on what it learned from the training (e.g., by executing the model to apply the learned patterns and/or associations to the live data). In some examples, input data undergoes pre-processing before being used as an input to the machine learning model. Moreover, in some examples, the output data may undergo post-processing after it is generated by the AI model to transform the output into a useful result (e.g., a display of data, an instruction to be executed by a machine, etc.).

(97) In some examples, output of the deployed model may be captured and provided as feedback. By analyzing the feedback, an accuracy of the deployed model can be determined. If the feedback indicates that the accuracy of the deployed model is less than a threshold or other criterion, training of an updated model can be triggered using the feedback and an updated training data set, hyperparameters, etc., to generate an updated, deployed model.

(98) Referring to FIG. **5**, the example system **300** includes first neural network generation circuitry **504** to train a neural network to detect human faces in image data. The example first neural network generation circuitry **504** includes first neural network processing circuitry **506**. In examples disclosed herein, the first neural network processing circuitry **506** implements a first neural network.

(99) The example first neural network generation circuitry **504** of FIG. **5** includes first neural network trainer circuitry **508**. The example first neural network trainer circuitry **508** of FIG. **5** performs training of the neural network implemented by the first neural network processing circuitry **506**.

(100) The example first neural network generation circuitry **504** of FIG. **5** includes a first training control circuitry **510**. The example training control circuitry **510** instructs the first neural network trainer circuitry **508** to perform training of the neural network based on first training data **512**. In the example of FIG. **5**, the first training data **512** used by the first neural network trainer circuitry **508** to train the neural network is stored in a database **514**.

(101) In the example of FIG. **5**, the first training data **512** can include previously generated image data including human faces. The previously generated image data can be collected by the camera(s) **104** associated with the user device(s) **100**, **301** and/or different user devices. In some examples,

previously generated video frame(s) **405** extracted from the video stream signal **402** by the video preprocessing circuitry **406** are used the first training data **512**.

(102) The first neural network trainer circuitry **508** trains the neural network implemented by the neural network processing circuitry **506** using the training data **512** to detect human faces in image data. One or more face detection model(s) **414** are generated as a result of the neural network training. The face detection model(s) **414** are stored in the database **412**. In other examples, the face detection model(s) **414** can be stored in a different database. The databases **412**, **514** may be the same storage device or different storage devices.

(103) The face detection circuitry **408** of the example user proximity detection circuitry **322** of FIG. **4** executes the face detection model(s) **414**. In particular, the face detection circuitry **408** executes the face detection model(s) **414** for each video frame **405**. As a result of the execution of the face detection model(s) **414**, the face detection circuitry **408** outputs bounding box(es) **502** corresponding to detected face(s) in the respective video frames **405** and respective confidence level(s) associated with the bounding box(es). The predicted bounding boxes **502** are stored in the database **412**. In some examples, the predicted bounding box(es) **502**, the video frames **405**, and/or the filtered video frame(s) **415** identified by the face filter **410** are used as the training data **512** to refine the face detection model(s) **414**.

(104) The example user proximity detection circuitry **322** of FIGS. **4** and **5** executes a second neural network to detect facial landmarks that serve as reference points for determining user proximity. The example system **300** includes second neural network generation circuitry **518** to train a neural network to detect facial landmark(s) (e.g., eyes, nose, forehead) in image data of a human face. The example second neural network generation circuitry **518** includes second neural network processing circuitry **522**. In examples disclosed herein, the second neural network processing circuitry **522** implements a second neural network.

(105) The example second neural network generation circuitry **518** of FIG. **5** includes a second neural network trainer circuitry **520**. The example second neural network trainer circuitry **520** of FIG. **5** performs training of the neural network implemented by the second neural network processing circuitry **522**.

(106) The example second neural network generation circuitry **518** of FIG. **5** includes second training control circuitry **524**. The example training control circuitry **524** instructs the second neural network trainer circuitry **520** to perform training of the neural network based on second training data **526**. In the example of FIG. **5**, the second training data **526** used by the second neural network trainer circuitry **520** to train the neural network is stored in a database **528**.

(107) In the example of FIG. **5**, the second training data **526** can include image data of human faces, including image data of particular features of a face, such as eyes, nose, mouth, forehead, etc. The previously generated image data can be collected by the camera(s) **104** associated with the user device(s) **100**, **301** and/or different user devices. In some examples, previously generated video frame(s) **405** extracted from the video stream signal **402** by the video preprocessing circuitry **406** are used as the second training data **526**.

(108) The second neural network trainer circuitry **520** trains the neural network implemented by the neural network processing circuitry **522** using the training data **526** to detect landmarks associated with the faces in the image data. One or more landmark detection model(s) **420** are generated as a result of the neural network training. The landmark detection model(s) **420** are stored in the database **412**. In other examples, the landmark detection model(s) **420** can be stored in a different database. The databases **412**, **528** may be the same storage device or different storage devices.

(109) The face landmark detection circuitry **416** of the example user proximity detection circuitry **322** of FIG. **4** executes the landmark detection model(s) **420**. In particular, the face landmark detection circuitry **416** executes the landmark detection model(s) **420** for each filtered video frame **415** identified by the face filter **410** as including a bounding box satisfying the face detection threshold. As a result of the execution of the landmark detection model(s) **420**, the face landmark

detection circuitry **416** outputs the predicted face landmarks **418** including pixel coordinates of the facial landmarks identified in the image data. The predicted facial landmarks **418** are stored in the database **412**. In some examples, the predicted facial landmarks **418** are used as the training data **526** to refine the landmark detection model(s) **420**.

(110) In some examples, the user proximity detection circuitry **322** includes means for extracting video frame(s) from a video stream. For example, the means for extracting may be implemented by the video preprocessing circuitry **406**. In some examples, the video preprocessing circuitry **406** may be implemented by machine executable instructions such as that implemented by at least block **903** of FIG. **9** executed by processor circuitry, which may be implemented by the example processor circuitry **1112** of FIG. **11**, the example processor circuitry **1200** of FIG. **12**, and/or the example Field Programmable Gate Array (FPGA) circuitry **1300** of FIG. **13**. In other examples, the video preprocessing circuitry **406** is implemented by other hardware logic circuitry, hardware implemented state machines, and/or any other combination of hardware, software, and/or firmware. For example, the video preprocessing circuitry **406** may be implemented by at least one or more hardware circuits (e.g., processor circuitry, discrete and/or integrated analog and/or digital circuitry, an FPGA, an Application Specific Integrated Circuit (ASIC), a comparator, an operational-amplifier (op-amp), a logic circuit, etc.) structured to perform the corresponding operation without executing software or firmware, but other structures are likewise appropriate.

(111) In some examples, the user proximity detection circuitry **322** includes means for detecting a face. For example, the face detecting means may be implemented by the face detection circuitry **408**. In some examples, the face detection circuitry **408** may be implemented by machine executable instructions such as that implemented by at least blocks **904**, **906**, **908** of FIG. **9** executed by processor circuitry, which may be implemented by the example processor circuitry **1112** of FIG. **11**, the example processor circuitry **1200** of FIG. **12**, and/or the example Field Programmable Gate Array (FPGA) circuitry **1300** of FIG. **13**. In other examples, the face detection circuitry **408** is implemented by other hardware logic circuitry, hardware implemented state machines, and/or any other combination of hardware, software, and/or firmware. For example, the face detection circuitry **408** may be implemented by at least one or more hardware circuits (e.g., processor circuitry, discrete and/or integrated analog and/or digital circuitry, an FPGA, an Application Specific Integrated Circuit (ASIC), a comparator, an operational-amplifier (op-amp), a logic circuit, etc.) structured to perform the corresponding operation without executing software or firmware, but other structures are likewise appropriate.

(112) In some examples, the user proximity detection circuitry **322** includes means for filtering faces identified in image data. For example, the face filtering means may be implemented by the face filter **410**. In some examples, the face filter **410** may be implemented by machine executable instructions such as that implemented by at least blocks **910**, **912** of FIG. **9** executed by processor circuitry, which may be implemented by the example processor circuitry **1112** of FIG. **11**, the example processor circuitry **1200** of FIG. **12**, and/or the example Field Programmable Gate Array (FPGA) circuitry **1300** of FIG. **13**. In other examples, the face filter **410** is implemented by other hardware logic circuitry, hardware implemented state machines, and/or any other combination of hardware, software, and/or firmware. For example, the face filter **410** may be implemented by at least one or more hardware circuits (e.g., processor circuitry, discrete and/or integrated analog and/or digital circuitry, an FPGA, an Application Specific Integrated Circuit (ASIC), a comparator, an operational-amplifier (op-amp), a logic circuit, etc.) structured to perform the corresponding operation without executing software or firmware, but other structures are likewise appropriate.

(113) In some examples, the user proximity detection circuitry **322** includes means for identifying facial landmarks. For example, the facial landmark identifying means may be implemented by the face landmark detection circuitry **416**. In some examples, the face landmark detection circuitry **416** may be implemented by machine executable instructions such as that implemented by at least block **914** of FIG. **9** executed by processor circuitry, which may be implemented by the example

processor circuitry **1112** of FIG. **11**, the example processor circuitry **1200** of FIG. **12**, and/or the example Field Programmable Gate Array (FPGA) circuitry **1300** of FIG. **13**. In other examples, the face landmark detection circuitry **416** is implemented by other hardware logic circuitry, hardware implemented state machines, and/or any other combination of hardware, software, and/or firmware. For example, the face landmark detection circuitry **416** may be implemented by at least one or more hardware circuits (e.g., processor circuitry, discrete and/or integrated analog and/or digital circuitry, an FPGA, an Application Specific Integrated Circuit (ASIC), a comparator, an operational-amplifier (op-amp), a logic circuit, etc.) structured to perform the corresponding operation without executing software or firmware, but other structures are likewise appropriate.

(114) In some examples, the user proximity detection circuitry **322** includes means for determining a proximity of a user. For example, the means for determining proximity may be implemented by the proximity estimating circuitry **422**. In some examples, the face landmark detection circuitry **416** may be implemented by machine executable instructions such as that implemented by at least blocks **916**, **918** of FIG. **9** executed by processor circuitry, which may be implemented by the example processor circuitry **1112** of FIG. **11**, the example processor circuitry **1200** of FIG. **12**, and/or the example Field Programmable Gate Array (FPGA) circuitry **1300** of FIG. **13**. In other examples, the proximity estimating circuitry **422** is implemented by other hardware logic circuitry, hardware implemented state machines, and/or any other combination of hardware, software, and/or firmware. For example, the proximity estimating circuitry **422** may be implemented by at least one or more hardware circuits (e.g., processor circuitry, discrete and/or integrated analog and/or digital circuitry, an FPGA, an Application Specific Integrated Circuit (ASIC), a comparator, an operational-amplifier (op-amp), a logic circuit, etc.) structured to perform the corresponding operation without executing software or firmware, but other structures are likewise appropriate.

(115) In some examples, the microphone gain control circuitry **330** includes means for filtering audio data. For example, the audio filtering means may be implemented by the low-pass voice filter **426**. In some examples, the low-pass voice filter **426** may be implemented by machine executable instructions such as that implemented by at least block **1004** of FIG. **10** executed by processor circuitry, which may be implemented by the example processor circuitry **1412** of FIG. **14**, the example processor circuitry **1500** of FIG. **15**, and/or the example Field Programmable Gate Array (FPGA) circuitry **1600** of FIG. **16**. In other examples, the low-pass voice filter **426** is implemented by other hardware logic circuitry, hardware implemented state machines, and/or any other combination of hardware, software, and/or firmware. For example, the low-pass voice filter **426** may be implemented by at least one or more hardware circuits (e.g., processor circuitry, discrete and/or integrated analog and/or digital circuitry, an FPGA, an Application Specific Integrated Circuit (ASIC), a comparator, an operational-amplifier (op-amp), a logic circuit, etc.) structured to perform the corresponding operation without executing software or firmware, but other structures are likewise appropriate.

(116) In some examples, the microphone gain control circuitry **330** includes means for estimating noise. For example, the noise estimating means may be implemented by the noise estimating circuitry **428**. In some examples, the noise estimating circuitry **428** may be implemented by machine executable instructions such as that implemented by at least block **1006** of FIG. **10** executed by processor circuitry, which may be implemented by the example processor circuitry **1412** of FIG. **14**, the example processor circuitry **1500** of FIG. **15**, and/or the example Field Programmable Gate Array (FPGA) circuitry **1600** of FIG. **16**. In other examples, the noise estimating circuitry **428** is implemented by other hardware logic circuitry, hardware implemented state machines, and/or any other combination of hardware, software, and/or firmware. For example, the noise estimating circuitry **428** may be implemented by at least one or more hardware circuits (e.g., processor circuitry, discrete and/or integrated analog and/or digital circuitry, an FPGA, an Application Specific Integrated Circuit (ASIC), a comparator, an operational-amplifier (op-amp), a logic circuit, etc.) structured to perform the corresponding operation without executing software or

firmware, but other structures are likewise appropriate.

(117) In some examples, the microphone gain control circuitry **330** includes means for calculating a signal-to-noise-ratio. For example, the means for calculating may be implemented by the calculator **429**. In some examples, the calculator **429** may be implemented by machine executable instructions such as that implemented by at least block **1008** of FIG. **10** executed by processor circuitry, which may be implemented by the example processor circuitry **1412** of FIG. **14**, the example processor circuitry **1500** of FIG. **15**, and/or the example Field Programmable Gate Array (FPGA) circuitry **1600** of FIG. **16**. In other examples, the calculator **429** is implemented by other hardware logic circuitry, hardware implemented state machines, and/or any other combination of hardware, software, and/or firmware. For example, the calculator **429** may be implemented by at least one or more hardware circuits (e.g., processor circuitry, discrete and/or integrated analog and/or digital circuitry, an FPGA, an Application Specific Integrated Circuit (ASIC), a comparator, an operational-amplifier (op-amp), a logic circuit, etc.) structured to perform the corresponding operation without executing software or firmware, but other structures are likewise appropriate.

(118) In some examples, the microphone gain control circuitry **330** includes means for determining gain. For example, the gain determining means may be implemented by the gain determining circuitry **430**. In some examples, the gain determining circuitry **430** may be implemented by machine executable instructions such as that implemented by at least blocks **1010**, **1012**, **1014**, **1016**, **1018** of FIG. **10** executed by processor circuitry, which may be implemented by the example processor circuitry **1412** of FIG. **14**, the example processor circuitry **1500** of FIG. **15**, and/or the example Field Programmable Gate Array (FPGA) circuitry **1600** of FIG. **16**. In other examples, the gain determining circuitry **430** is implemented by other hardware logic circuitry, hardware implemented state machines, and/or any other combination of hardware, software, and/or firmware. For example, the gain determining circuitry **430** may be implemented by at least one or more hardware circuits (e.g., processor circuitry, discrete and/or integrated analog and/or digital circuitry, an FPGA, an Application Specific Integrated Circuit (ASIC), a comparator, an operational-amplifier (op-amp), a logic circuit, etc.) structured to perform the corresponding operation without executing software or firmware, but other structures are likewise appropriate.

(119) While an example manner of implementing the user proximity detection circuitry **322** of FIG. **3** is illustrated in FIG. **4**, one or more of the elements, processes, and/or devices illustrated in FIG. **4** may be combined, divided, re-arranged, omitted, eliminated, and/or implemented in any other way. Further, the example video preprocessing circuitry **406**, the example face detection circuitry **408**, the example face filter **410**, the example face landmark detection circuitry **416**, the example proximity estimating circuitry **422**, and/or, more generally, the example user proximity detection circuitry **322** may be implemented by hardware, software, firmware, and/or any combination of hardware, software, and/or firmware. Thus, for example, any of the example video preprocessing circuitry **406**, the example face detection circuitry **408**, the example face filter **410**, the example face landmark detection circuitry **416**, the example proximity estimating circuitry **422**, and/or, more generally, the example user proximity detection circuitry **322** could be implemented by processor circuitry, analog circuit(s), digital circuit(s), logic circuit(s), programmable processor(s), programmable microcontroller(s), graphics processing unit(s) (GPU(s)), digital signal processor(s) (DSP(s)), application specific integrated circuit(s) (ASIC(s)), programmable logic device(s) (PLD(s)), and/or field programmable logic device(s) (FPLD(s)) such as Field Programmable Gate Arrays (FPGAs). When reading any of the apparatus or system claims of this patent to cover a purely software and/or firmware implementation, at least one of the example video preprocessing circuitry **406**, the example face detection circuitry **408**, the example face filter **410**, the example face landmark detection circuitry **416**, and/or the example proximity estimating circuitry **422** is/are hereby expressly defined to include a non-transitory computer readable storage device or storage disk such as a memory, a digital versatile disk (DVD), a compact disk (CD), a Blu-ray disk, etc., including the software and/or firmware. Further still, the example user proximity detection circuitry

322 may include one or more elements, processes, and/or devices in addition to, or instead of, those illustrated in FIG. 4, and/or may include more than one of any or all of the illustrated elements, processes, and devices.

(120) While an example manner of implementing microphone gain control circuitry **330** of FIG. 3 is illustrated in FIG. 4, one or more of the elements, processes, and/or devices illustrated in FIG. 4 may be combined, divided, re-arranged, omitted, eliminated, and/or implemented in any other way. Further, the example low pass voice filter **426**, the example noise estimating circuitry **428**, the example calculator **429**, the example gain determining circuitry **430**, the example gain control circuitry **435**, and/or, more generally, the example microphone gain control circuitry **330** may be implemented by hardware, software, firmware, and/or any combination of hardware, software, and/or firmware. Thus, for example, any of the example low pass voice filter **426**, the example noise estimating circuitry **428**, the example calculator **429**, the example gain determining circuitry **430**, the example gain control circuitry **435** and/or, more generally, the example microphone gain control circuitry **330** could be implemented by processor circuitry, analog circuit(s), digital circuit(s), logic circuit(s), programmable processor(s), programmable microcontroller(s), graphics processing unit(s) (GPU(s)), digital signal processor(s) (DSP(s)), application specific integrated circuit(s) (ASIC(s)), programmable logic device(s) (PLD(s)), and/or field programmable logic device(s) (FPLD(s)) such as Field Programmable Gate Arrays (FPGAs). When reading any of the apparatus or system claims of this patent to cover a purely software and/or firmware implementation, at least one of the example low pass voice filter **426**, the example noise estimating circuitry **428**, the example calculator **429**, the example gain determining circuitry **430**, and/or the example gain control circuitry **435** is/are hereby expressly defined to include a non-transitory computer readable storage device or storage disk such as a memory, a digital versatile disk (DVD), a compact disk (CD), a Blu-ray disk, etc., including the software and/or firmware. Further still, the example microphone gain control circuitry **330** may include one or more elements, processes, and/or devices in addition to, or instead of, those illustrated in FIG. 4, and/or may include more than one of any or all of the illustrated elements, processes, and devices.

(121) While an example manner of implementing the first neural network generation circuitry **504** is illustrated in FIG. 5, one or more of the elements, processes, and/or devices illustrated in FIG. 5 may be combined, divided, re-arranged, omitted, eliminated, and/or implemented in any other way. Further, the example training control circuitry **510**, the example trainer circuitry **508**, the example neural network processing circuitry **506**, and/or, more generally, the example first neural network generation circuitry **504** may be implemented by hardware, software, firmware, and/or any combination of hardware, software, and/or firmware. Thus, for example, any of the example training control circuitry **510**, the example trainer circuitry **508**, the example neural network processing circuitry **506**, and/or, more generally, the example first neural network generation circuitry **504** could be implemented by processor circuitry, analog circuit(s), digital circuit(s), logic circuit(s), programmable processor(s), programmable microcontroller(s), graphics processing unit(s) (GPU(s)), digital signal processor(s) (DSP(s)), application specific integrated circuit(s) (ASIC(s)), programmable logic device(s) (PLD(s)), and/or field programmable logic device(s) (FPLD(s)) such as Field Programmable Gate Arrays (FPGAs). When reading any of the apparatus or system claims of this patent to cover a purely software and/or firmware implementation, at least one of the example training control circuitry **510**, the example trainer circuitry **508**, and/or the example neural network processing circuitry **506** is/are hereby expressly defined to include a non-transitory computer readable storage device or storage disk such as a memory, a digital versatile disk (DVD), a compact disk (CD), a Blu-ray disk, etc., including the software and/or firmware. Further still, the example first neural network generation circuitry **504** may include one or more elements, processes, and/or devices in addition to, or instead of, those illustrated in FIG. 5, and/or may include more than one of any or all of the illustrated elements, processes, and devices.

(122) While an example manner of implementing the second neural network generation circuitry

518 is illustrated in FIG. 5, one or more of the elements, processes, and/or devices illustrated in FIG. 5 may be combined, divided, re-arranged, omitted, eliminated, and/or implemented in any other way. Further, the example training control circuitry **524**, the example trainer circuitry **520**, the example neural network processing circuitry **522**, and/or, more generally, the example second neural network generation circuitry **518** may be implemented by hardware, software, firmware, and/or any combination of hardware, software, and/or firmware. Thus, for example, any of the example training control circuitry **524**, the example trainer circuitry **520**, the example neural network processing circuitry **522**, and/or, more generally, the example second neural network generation circuitry **518** could be implemented by processor circuitry, analog circuit(s), digital circuit(s), logic circuit(s), programmable processor(s), programmable microcontroller(s), graphics processing unit(s) (GPU(s)), digital signal processor(s) (DSP(s)), application specific integrated circuit(s) (ASIC(s)), programmable logic device(s) (PLD(s)), and/or field programmable logic device(s) (FPLD(s)) such as Field Programmable Gate Arrays (FPGAs). When reading any of the apparatus or system claims of this patent to cover a purely software and/or firmware implementation, at least one of the example training control circuitry **524**, the example trainer circuitry **520**, and/or the example neural network processing circuitry **522** is/are hereby expressly defined to include a non-transitory computer readable storage device or storage disk such as a memory, a digital versatile disk (DVD), a compact disk (CD), a Blu-ray disk, etc., including the software and/or firmware. Further still, the example second neural network generation circuitry **518** may include one or more elements, processes, and/or devices in addition to, or instead of, those illustrated in FIG. 5, and/or may include more than one of any or all of the illustrated elements, processes, and devices.

(123) FIG. 6 includes examples images of a user **600** (e.g., the user **106** of FIG. 1) and corresponding facial landmarks associated with the user **600** and identified in the images by the face landmark detection circuitry **416** of the example user proximity detection circuitry **322** of FIG. 4. In particular, FIG. 6 illustrates a first image **602** of the user **600**, a second image **604** of the user **600**, and a third image **606** of the user **600**. The images **602**, **604**, **606** can be captured by the camera(s) **104** of the user device(s) **100**, **301** of FIGS. 1 and/or 3.

(124) In FIG. 6, the first image **602** captures the user **106** at a first distance from the camera(s) **104** (e.g., distance $X_{sub.1}$ in FIG. 1). A first face landmark **608** and a second facial landmark **610** (e.g., the face landmarks **418**) are identified in the first image **602** by the face landmark detection circuitry **416** of the example user proximity detection circuitry **322** of FIG. 4 (e.g., as a result of execution of the landmark detection model(s) **420**). In the example of FIG. 6, the face landmarks **608**, **610** represent inner eye points of the respective eyes of the user **600**, or eye points proximate to a nose of the user **600**. The first face landmark **608** includes a first pixel coordinate location corresponding to the location of the first face landmark **608** and the second face landmark **610** includes a second pixel coordinate location corresponding to the location of the second face landmark **610**. The proximity estimating circuitry **422** of the example user proximity detection circuitry **322** of FIG. 4 determines a first distance $P_{sub.1}$ in pixels between the first face landmark **608** and the second face landmark **610** (e.g., the inner eye points) based on the associated pixel coordinate values to estimate a width of a nose bridge **612** of the user **600**.

(125) In FIG. 6, the second image **604** captures the user **106** at a second distance from the camera(s) **104** greater than the first distance associated with the first image **602** (e.g., distance $X_{sub.2}$ in FIG. 1). The face landmark detection circuitry **416** identifies the first and second face landmarks **608**, **610** in the second image **604**. The proximity estimating circuitry **422** determines a second distance $P_{sub.2}$ in pixels between the first face landmark **608** and the second face landmark **610** (e.g., the inner eye points) based on the associated pixel coordinate values in the second image **604** to estimate a width of a nose bridge **612** of the user **600**. In the example of FIG. 6, the estimated width of the nose bridge **612** of the user **600** as represented by the second distance $P_{sub.2}$ of the second image **604** is less than the width of the nose bridge **612** as represented by the

first distance P.sub.1 determined using the first image **602**. Thus, as a result of the increased distance between the user **600** and the camera(s) **104** in the second image **604**, the estimated width of the nose bridge **612** of the user **612** is less in the second image **604** than the first image **602**.

(126) The third image **606** of FIG. **6** captures the user **106** at a third distance from the camera(s) **104** greater than the first distance associated with the first image **602** and the second distance associated with the second image **604**. The face landmark detection circuitry **416** identifies the first and second face landmarks **608**, **610** in the third image **606**. The proximity estimating circuitry **422** determines a third distance P.sub.3 in pixels between the first face landmark **608** and the second face landmark **610** (e.g., the inner eye points) based on the associated pixel coordinate values in the third image **606** to estimate a width of a nose bridge **612** of the user **600**. In the example of FIG. **6**, the estimated width of the nose bridge **612** of the user **600** as represented by the distance P.sub.3 of the third image **606** is less than the widths of the nose bridge **612** as represented by the first distance P.sub.1 determined using the first image **602** and the second distance P.sub.2 determined using the second image **604**. Thus, as a result of the increased distance between the user **600** and the camera(s) **104** in the third image **604**, the estimated width of the nose bridge **612** of the user **600** is less in the third image **606** than the first image **600** and the second image **604**. As disclosed in connection with FIGS. **3-5**, the width of the nose bridge **612** (or other facial landmarks) is used by the proximity estimating circuitry **422** to determine a distance of the user **600** from the camera(s) **104**. The resulting distance calculated by the proximity estimating circuitry **422** is used by the microphone gain control circuitry **330** of FIG. **3** to control audio gain.

(127) A flowchart representative of example hardware logic circuitry, machine readable instructions, hardware implemented state machines, and/or any combination thereof for implementing the first neural network generation circuitry **504** of FIG. **5** is shown in FIG. **7**. A flowchart representative of example hardware logic circuitry, machine readable instructions, hardware implemented state machines, and/or any combination thereof for implementing the second neural network generation circuitry **518** of FIG. **5** is shown in FIG. **8**. A flowchart representative of example hardware logic circuitry, machine readable instructions, hardware implemented state machines, and/or any combination thereof for implementing the user proximity detection circuitry **322** of FIGS. **3** and/or **4** is shown in FIG. **9**. A flowchart representative of example hardware logic circuitry, machine readable instructions, hardware implemented state machines, and/or any combination thereof for implementing the microphone gain control circuitry **330** of FIGS. **3** and/or **4** is shown in FIG. **10**. The machine readable instructions may be one or more executable programs or portion(s) of an executable program for execution by processor circuitry, such as the processor circuitry **1112**, **1412**, **1712**, **1812** shown in the example processor platform(s) **1100**, **1400**, **1700**, **1800** discussed below in connection with FIGS. **11**, **14**, **17**, and **18**. The program(s) may be embodied in software stored on one or more non-transitory computer readable storage media such as a CD, a floppy disk, a hard disk drive (HDD), a DVD, a Blu-ray disk, a volatile memory (e.g., Random Access Memory (RAM) of any type, etc.), or a non-volatile memory (e.g., FLASH memory, an HDD, etc.) associated with processor circuitry located in one or more hardware devices, but the entire program(s) and/or parts thereof could alternatively be executed by one or more hardware devices other than the processor circuitry and/or embodied in firmware or dedicated hardware. The machine readable instructions may be distributed across multiple hardware devices and/or executed by two or more hardware devices (e.g., a server and a client hardware device). For example, the client hardware device may be implemented by an endpoint client hardware device (e.g., a hardware device associated with a user) or an intermediate client hardware device (e.g., a radio access network (RAN) gateway that may facilitate communication between a server and an endpoint client hardware device). Similarly, the non-transitory computer readable storage media may include one or more mediums located in one or more hardware devices. Further, although the example program(s) are described with reference to the flowcharts illustrated in FIGS. **7-10**, many other methods of implementing the example user

proximity detection circuitry **322**, the example microphone gain control circuitry **330**, the example first neural network generation circuitry **504**, and/or the example second neural network generation circuitry **518** may alternatively be used. For example, the order of execution of the blocks may be changed, and/or some of the blocks described may be changed, eliminated, or combined. Additionally or alternatively, any or all of the blocks may be implemented by one or more hardware circuits (e.g., processor circuitry, discrete and/or integrated analog and/or digital circuitry, an FPGA, an ASIC, a comparator, an operational-amplifier (op-amp), a logic circuit, etc.) structured to perform the corresponding operation without executing software or firmware. The processor circuitry may be distributed in different network locations and/or local to one or more hardware devices (e.g., a single-core processor (e.g., a single core central processor unit (CPU)), a multi-core processor (e.g., a multi-core CPU), etc.) in a single machine, multiple processors distributed across multiple servers of a server rack, multiple processors distributed across one or more server racks, a CPU and/or a FPGA located in the same package (e.g., the same integrated circuit (IC) package or in two or more separate housings, etc.).

(128) The machine readable instructions described herein may be stored in one or more of a compressed format, an encrypted format, a fragmented format, a compiled format, an executable format, a packaged format, etc. Machine readable instructions as described herein may be stored as data or a data structure (e.g., as portions of instructions, code, representations of code, etc.) that may be utilized to create, manufacture, and/or produce machine executable instructions. For example, the machine readable instructions may be fragmented and stored on one or more storage devices and/or computing devices (e.g., servers) located at the same or different locations of a network or collection of networks (e.g., in the cloud, in edge devices, etc.). The machine readable instructions may require one or more of installation, modification, adaptation, updating, combining, supplementing, configuring, decryption, decompression, unpacking, distribution, reassignment, compilation, etc., in order to make them directly readable, interpretable, and/or executable by a computing device and/or other machine. For example, the machine readable instructions may be stored in multiple parts, which are individually compressed, encrypted, and/or stored on separate computing devices, wherein the parts when decrypted, decompressed, and/or combined form a set of machine executable instructions that implement one or more operations that may together form a program such as that described herein.

(129) In another example, the machine readable instructions may be stored in a state in which they may be read by processor circuitry, but require addition of a library (e.g., a dynamic link library (DLL)), a software development kit (SDK), an application programming interface (API), etc., in order to execute the machine readable instructions on a particular computing device or other device. In another example, the machine readable instructions may need to be configured (e.g., settings stored, data input, network addresses recorded, etc.) before the machine readable instructions and/or the corresponding program(s) can be executed in whole or in part. Thus, machine readable media, as used herein, may include machine readable instructions and/or program(s) regardless of the particular format or state of the machine readable instructions and/or program(s) when stored or otherwise at rest or in transit.

(130) The machine readable instructions described herein can be represented by any past, present, or future instruction language, scripting language, programming language, etc. For example, the machine readable instructions may be represented using any of the following languages: C, C++, Java, C#, Perl, Python, JavaScript, HyperText Markup Language (HTML), Structured Query Language (SQL), Swift, etc.

(131) As mentioned above, the example operations of FIGS. **7-10** may be implemented using executable instructions (e.g., computer and/or machine readable instructions) stored on one or more non-transitory computer and/or machine readable media such as optical storage devices, magnetic storage devices, an HDD, a flash memory, a read-only memory (ROM), a CD, a DVD, a cache, a RAM of any type, a register, and/or any other storage device or storage disk in which information

is stored for any duration (e.g., for extended time periods, permanently, for brief instances, for temporarily buffering, and/or for caching of the information). As used herein, the terms non-transitory computer readable medium and non-transitory computer readable storage medium is expressly defined to include any type of computer readable storage device and/or storage disk and to exclude propagating signals and to exclude transmission media.

(132) “Including” and “comprising” (and all forms and tenses thereof) are used herein to be open ended terms. Thus, whenever a claim employs any form of “include” or “comprise” (e.g., comprises, includes, comprising, including, having, etc.) as a preamble or within a claim recitation of any kind, it is to be understood that additional elements, terms, etc., may be present without falling outside the scope of the corresponding claim or recitation. As used herein, when the phrase “at least” is used as the transition term in, for example, a preamble of a claim, it is open-ended in the same manner as the term “comprising” and “including” are open ended. The term “and/or” when used, for example, in a form such as A, B, and/or C refers to any combination or subset of A, B, C such as (1) A alone, (2) B alone, (3) C alone, (4) A with B, (5) A with C, (6) B with C, or (7) A with B and with C. As used herein in the context of describing structures, components, items, objects and/or things, the phrase “at least one of A and B” is intended to refer to implementations including any of (1) at least one A, (2) at least one B, or (3) at least one A and at least one B. Similarly, as used herein in the context of describing structures, components, items, objects and/or things, the phrase “at least one of A or B” is intended to refer to implementations including any of (1) at least one A, (2) at least one B, or (3) at least one A and at least one B. As used herein in the context of describing the performance or execution of processes, instructions, actions, activities and/or steps, the phrase “at least one of A and B” is intended to refer to implementations including any of (1) at least one A, (2) at least one B, or (3) at least one A and at least one B. Similarly, as used herein in the context of describing the performance or execution of processes, instructions, actions, activities and/or steps, the phrase “at least one of A or B” is intended to refer to implementations including any of (1) at least one A, (2) at least one B, or (3) at least one A and at least one B.

(133) As used herein, singular references (e.g., “a”, “an”, “first”, “second”, etc.) do not exclude a plurality. The term “a” or “an” object, as used herein, refers to one or more of that object. The terms “a” (or “an”), “one or more”, and “at least one” are used interchangeably herein.

Furthermore, although individually listed, a plurality of means, elements or method actions may be implemented by, e.g., the same entity or object. Additionally, although individual features may be included in different examples or claims, these may possibly be combined, and the inclusion in different examples or claims does not imply that a combination of features is not feasible and/or advantageous.

(134) FIG. 7 is a flowchart representative of example machine readable instructions and/or example operations **700** that may be executed and/or instantiated by processor circuitry to train a neural network to identify human faces in image data. The example instructions **700** of FIG. 7, when executed by the first neural network generation circuitry **504** of FIG. 5, result in a neural network and/or a model thereof (e.g., the face detection model(s) **414**), that can be distributed to other computing systems, such as the face detection circuitry **408** of the example user proximity detection circuitry **322** of FIG. 4.

(135) The machine readable instructions and/or operations **700** of FIG. 7 begin at block **702**, at which the training control circuitry **510** of the example first neural network generation circuitry **504** accesses image data including human faces. The image data can include the video frame(s) **405**, the filtered video frame(s) **415**, and/or the predicted bounding box(es) stored in the database **412** associated with the user proximity detection circuitry **322** as part of feedback training.

(136) At block **704**, the training control circuitry **510** labels the data with respect to human faces in the image data and/or facial features (e.g., nose, mouth, eyes). At block **706**, the example training control circuitry **510** generates the training data **512** based on the labeled image data.

(137) At block **708**, the example training control circuitry **510** instructs the neural network trainer circuitry **508** to perform training of the neural network processing circuitry **506** using the training data **512**. In the example of FIG. 7, the training is based on supervised learning. As a result of the training, the face detection model(s) **414** are generated at block **710**. Based on the face detection model(s) **414**, the neural network is trained to identify human faces in image data and to generate bounding boxes for the respective faces with associated confidence levels for detection of the faces. The face detection model(s) **414** can be stored in the database **412** for access by the face detection circuitry **408** of the example user proximity detection circuitry **322** of FIG. 4. The example instructions **700** of FIG. 7 end when no additional training (e.g., retraining) is to be performed (blocks **712**, **714**).

(138) FIG. 8 is a flowchart representative of example machine readable instructions and/or example operations **800** that may be executed and/or instantiated by processor circuitry to train a neural network to identify facial landmarks in image data. The example instructions **800** of FIG. 8, when executed by the second neural network generation circuitry **518** of FIG. 5, result in a neural network and/or a model thereof (e.g., the landmark detection model(s) **420**), that can be distributed to other computing systems, such as the face landmark detection circuitry **416** of the example user proximity detection circuitry **322** of FIG. 4.

(139) The machine readable instructions and/or operations **800** of FIG. 8 begin at block **802**, at which the training control circuitry **524** of the example second neural network generation circuitry **518** accesses image data including human faces. The image data can include the video frame(s) **405**, the filtered video frame(s) **415**, and/or the predicted face landmark(s) **418** stored in the database **412** associated with the user proximity detection circuitry **322** as part of feedback training.

(140) At block **804**, the training control circuitry **510** labels the data with respect to facial landmark(s) (e.g., an inner corner of a user's eye proximate to the user's nose) associated with human faces in the image data. For example, the training control circuitry **510** labels the pixels (e.g., pixel coordinates) in the image data associated with the facial landmark(s). At block **806**, the example training control circuitry **510** generates the training data **526** based on the labeled image data.

(141) At block **808**, the example training control circuitry **524** instructs the neural network trainer circuitry **520** to perform training of the neural network processing circuitry **522** using the training data **526**. In the example of FIG. 8, the training is based on supervised learning. As a result of the training, the landmark detection model(s) **420** are generated at block **810**. Based on the landmark detection model(s) **420**, the neural network is trained to identify facial landmark(s) associated with a human face in image data and to output pixel coordinates of the location of the facial landmark(s). The landmark detection model(s) **420** can be stored in the database **412** for access by the face landmark detection circuitry **416** of the example user proximity detection circuitry **322** of FIG. 4. The example instructions **800** of FIG. 8 end when no additional training (e.g., retraining) is to be performed (blocks **812**, **814**).

(142) FIG. 9 is a flowchart representative of example machine readable instructions and/or example operations **900** that may be executed and/or instantiated by processor circuitry to determine a proximity of a user (e.g., the user **106**) relative to cameras (e.g., the camera(s) **104**) of a user device (e.g., the user device **100**, **301** of FIGS. 1, 3). The machine readable instructions and/or operations **900** of FIG. 9 begin at block **902**, at which the user proximity detection circuitry **322** receives the video stream signal **402** generated by the camera(s) **104**. At block **903**, the video preprocessing circuitry **406** of the example user proximity detection circuitry **322** processes the video stream signal **402**. For example, the video preprocessing circuitry **406** can reduce a sampling rate (e.g., downsample) the video stream signal **402** to a lower frame rate and/or reshape the video stream signal **402** to a lower resolution to generate the video frames **405**.

(143) At block **904**, the face detection circuitry **408** of the user proximity detection circuitry **322** executes the face detection model(s) **414** to detect face(s) in one of the video frames **405**. At block

906, if the face detection circuitry **408** does not detect any face(s) in the video frame because of, for example, low ambient light, the instructions of FIG. **9** continue to block **920** to determine if additional video stream signal data has been received.

(144) If the face detection circuitry **408** identifies face(s) in the video frame, then at block **908**, the face detection circuitry **408** generates bounding box(es) including associated confidence level(s) for the prediction of the face(s) in the video frame detected as a result of the neural network analysis. An area of the bounding box can be proportional to the size of the face in the image data and, thus, a proximity of the user to the camera(s) **104**.

(145) At block **910**, the face filter **410** of the user proximity detection circuitry **322** analyzes the confidence level(s) associated with the bounding box(es) to identify face(s) that satisfy a confidence level threshold for prediction of a human face. In examples in which more than one face is identified that satisfies the confidence level threshold, the face filter **410** analyzes the size of the bounding boxes associated with the faces to select the face associated with the bounding box having the largest area for further analysis. The face filter **410** output a filtered video frame including the face selected for further analysis (e.g., a face associated with a primary speaker).

(146) If, at block **912**, none of the face(s) identified in the video frame satisfy the confidence threshold, the instructions of FIG. **9** continue to block **920** to determine if additional video stream signal data has been received.

(147) At block **914**, the face landmark detection circuitry **416** of the user proximity detection circuitry **322** executes the landmark detection model(s) **420** to identify face landmark(s) in the face identified in filtered video frame. The face landmark(s) can include, for example, a corner or point of each of the user's eyes proximate to the user's nose. As a result of execution of the landmark detection model(s) **420**, the face landmark detection circuitry **416** outputs pixel coordinate data including the locations of the face landmark(s) in pixels. The face landmark detection circuitry **416** can determine a distance between two face landmarks. For example, the face landmark detection circuitry **416** can determine a distance in pixels between two eye points, which can represent a width of the user's nose bridge in the image data.

(148) At block **916**, the proximity estimating circuitry **422** of the user proximity detection circuitry **322** determines the user proximity relative to the camera(s) **104** associated with the user device **100**, **301** based on the coordinate data associated with the face landmark(s). For example, the proximity estimating circuitry **422** solves a triangular similarity equation to determine a distance of the user from the camera(s) **104** based on the measured distance between the face landmarks identified by the face landmark detection circuitry **416** (e.g., a distance between two eye points), known facial feature reference data (e.g., the anthropomorphic reference data **424**, including, for example, reference nose bridge widths), and camera reference data **417** (e.g., focal length). At block **918**, the proximity estimating circuitry **422** outputs the user proximity measurement(s) for use in microphone gain control by the microphone gain control circuitry **330** of FIGS. **3** and **4**. The example instructions **900** of FIG. **9** end at blocks **920**, **922** when no additional video stream signal data is received.

(149) FIG. **10** is a flowchart representative of example machine readable instructions and/or example operations **1000** that may be executed and/or instantiated by processor circuitry to determine control an amount of gain applied to sound captured by microphone(s) (e.g., the microphone(s) **102**) based on a proximity of a user to camera(s) (e.g., the camera(s) **104**) associated with a user device (e.g., the user device **100**, **301**). The machine readable instructions and/or operations **1000** of FIG. **10** begin at block **1002**, at which the microphone gain control circuitry **330** receives audio sample(s) **407** including sound captured by the microphone(s).

(150) At block **1004**, the low-pass voice filter **426** of the microphone gain control circuitry **330** filters the audio sample(s) **407** to remove ambient noise data. For example, the low-pass voice filter **426** can apply a filter to permit frequencies in the audio sample(s) **407** associated with a voice band (e.g., frequencies of less than 6 kHz) to pass. As a result, the low-pass filter **426** outputs filtered

audio sample(s) **409**.

(151) At block **1006**, the noise estimating circuitry **428** of the microphone gain control circuitry **330** estimates an ambient noise level of the audio sample(s) by analyzing the audio samples **407** that do not include voice band activity.

(152) At block **1008**, the calculator **429** of the microphone gain control circuitry **330** calculates the signal-to-noise ratio (SNR) based on the filtered audio samples **409** including the voice band frequencies and the ambient noise level of the audio samples **407** identified by the noise estimating circuitry **428**.

(153) At block **1010**, the gain determining circuitry **430** of the example microphone gain control circuitry **330** compares the SNR calculated by the calculator **429** to an SNR threshold defined by the SNR rule(s) **431**. At block **1012**, if the gain determining circuitry **430** determines that the SNR calculated by the calculator **429** does not satisfy the SNR threshold (e.g., is below the SNR threshold, thereby indicating a high level of ambient noise in the environment), then the gain determining circuitry **430** determines that the amplifier should refrain applying gain to the voice band of the filtered audio sample(s) **409** and/or to apply a default gain value based on the proximity-gain mapping rule(s) **434**. Thus, the gain determining circuitry **430** prevents ambient noise from being unduly amplified.

(154) At block **1014**, if the gain determining circuitry **430** determines that SNR calculated by the calculator **429** satisfies the SNR threshold, the gain determining circuitry **430** accesses the user proximity measurement(s) generated by the proximity estimating circuitry **422** of the user proximity detection circuitry **322** (e.g., at block **916** of FIG. **9**). As disclosed herein, the user proximity measurement(s) indicate a distance of the user (i.e., the primary speaker in a video conference) from the camera(s) **104** associated with the user device **100**, **301**. If the gain determining circuitry **430** determines that the user proximity measurement(s) have not been generated, the instructions of FIG. **10** proceed to block **1012** to apply default gain rule(s). For example, if the face detection circuitry **408** of the user proximity detection circuitry **322** is unable to identify face(s) in the video frame(s) **405** because of low ambient lighting (e.g., block **906** of FIG. **9**), then the gain determining circuitry **430** determine that a default gain should be applied to the voice band of the audio data and/or that the amplifier **332** should refrain from applying gain based on the proximity-gain mapping rule(s) **434**.

(155) If the user proximity measurement(s) are available, then at block **1016**, the gain determining circuitry **430** determines an amount of gain to be applied to the voice band of the filtered audio sample(s) **409** based on the proximity-gain mapping rule(s) **434**. The proximity-gain mapping rule(s) **434** can include mappings of user proximity measurements to gain values to be applied. In some examples, the proximity-gain mapping rule(s) **434** define a minimum proximity measurement for which gain is to be applied (e.g., so as not unnecessarily amplify the voice band when the user is proximate to the camera(s) **104**). In some examples, the proximity-gain mapping rule(s) **434** define a maximum amount of gain to be applied such that further increases in a distance of the user from the camera(s) **104** does not result in increased gain values (e.g., to avoid amplifying ambient noise).

(156) At block **1018**, the gain control circuitry **435** transmits instructions to the amplifier **332** of the user device **100**, **301** regarding the amount of gain to be applied to the voice band. In some examples, the instructions cause the amplifier **332** to output amplified audio sample(s) **433** based on the instructions. The example instructions **1000** of FIG. **10** end at blocks **1020**, **1022** when no additional audio sample(s) are received.

(157) FIG. **11** is a block diagram of an example processor platform **1100** structured to execute and/or instantiate the machine readable instructions and/or operations of FIG. **9** to implement the user proximity detection circuitry **322** of FIGS. **3** and/or **4**. The processor platform **1100** can be, for example, a server, a personal computer, a workstation, a self-learning machine (e.g., a neural network), a mobile device (e.g., a cell phone, a smart phone, a tablet such as an iPad™), a personal

digital assistant (PDA), an Internet appliance, or any other type of computing device.

(158) The processor platform **1100** of the illustrated example includes processor circuitry **1112**. The processor circuitry **1112** of the illustrated example is hardware. For example, the processor circuitry **1112** can be implemented by one or more integrated circuits, logic circuits, FPGAs microprocessors, CPUs, GPUs, DSPs, and/or microcontrollers from any desired family or manufacturer. The processor circuitry **1112** may be implemented by one or more semiconductor based (e.g., silicon based) devices. In this example, the processor circuitry **1112** implements the example video preprocessing circuitry **406**, the example face detection circuitry **408**, the example face filter **410**, the example face landmark detection circuitry **416**, and the example proximity estimating circuitry **422**.

(159) The processor circuitry **1112** of the illustrated example includes a local memory **1113** (e.g., a cache, registers, etc.). The processor circuitry **1112** of the illustrated example is in communication with a main memory including a volatile memory **1114** and a non-volatile memory **1116** by a bus **1118**. The volatile memory **1114** may be implemented by Synchronous Dynamic Random Access Memory (SDRAM), Dynamic Random Access Memory (DRAM), RAMBUS® Dynamic Random Access Memory (RDRAM®), and/or any other type of RAM device. The non-volatile memory **1116** may be implemented by flash memory and/or any other desired type of memory device. Access to the main memory **1114**, **1116** of the illustrated example is controlled by a memory controller **1117**.

(160) The processor platform **1100** of the illustrated example also includes interface circuitry **1120**. The interface circuitry **1120** may be implemented by hardware in accordance with any type of interface standard, such as an Ethernet interface, a universal serial bus (USB) interface, a Bluetooth® interface, a near field communication (NFC) interface, a PCI interface, and/or a PCIe interface.

(161) In the illustrated example, one or more input devices **1122** are connected to the interface circuitry **1120**. The input device(s) **1122** permit(s) a user to enter data and/or commands into the processor circuitry **1112**. The input device(s) **1122** can be implemented by, for example, an audio sensor, a microphone, a camera (still or video), a keyboard, a button, a mouse, a touchscreen, a track-pad, a trackball, an isopoint device, and/or a voice recognition system.

(162) One or more output devices **1124** are also connected to the interface circuitry **1120** of the illustrated example. The output devices **1124** can be implemented, for example, by display devices (e.g., a light emitting diode (LED), an organic light emitting diode (OLED), a liquid crystal display (LCD), a cathode ray tube (CRT) display, an in-place switching (IPS) display, a touchscreen, etc.), a tactile output device, a printer, and/or speaker. The interface circuitry **1120** of the illustrated example, thus, typically includes a graphics driver card, a graphics driver chip, and/or graphics processor circuitry such as a GPU.

(163) The interface circuitry **1120** of the illustrated example also includes a communication device such as a transmitter, a receiver, a transceiver, a modem, a residential gateway, a wireless access point, and/or a network interface to facilitate exchange of data with external machines (e.g., computing devices of any kind) by a network **1126**. The communication can be by, for example, an Ethernet connection, a digital subscriber line (DSL) connection, a telephone line connection, a coaxial cable system, a satellite system, a line-of-site wireless system, a cellular telephone system, an optical connection, etc.

(164) The processor platform **1100** of the illustrated example also includes one or more mass storage devices **1128** to store software and/or data. Examples of such mass storage devices **1128** include magnetic storage devices, optical storage devices, floppy disk drives, HDDs, CDs, Blu-ray disk drives, redundant array of independent disks (RAID) systems, solid state storage devices such as flash memory devices, and DVD drives.

(165) The machine executable instructions **1132**, which may be implemented by the machine readable instructions of FIG. 9, may be stored in the mass storage device **1128**, in the volatile

memory **1114**, in the non-volatile memory **1116**, and/or on a removable non-transitory computer readable storage medium such as a CD or DVD.

(166) FIG. **12** is a block diagram of an example implementation of the processor circuitry **1112** of FIG. **11**. In this example, the processor circuitry **1112** of FIG. **11** is implemented by a microprocessor **1200**. For example, the microprocessor **1200** may implement multi-core hardware circuitry such as a CPU, a DSP, a GPU, an XPU, etc. Although it may include any number of example cores **1202** (e.g., **1** core), the microprocessor **1200** of this example is a multi-core semiconductor device including **N** cores. The cores **1202** of the microprocessor **1200** may operate independently or may cooperate to execute machine readable instructions. For example, machine code corresponding to a firmware program, an embedded software program, or a software program may be executed by one of the cores **1202** or may be executed by multiple ones of the cores **1202** at the same or different times. In some examples, the machine code corresponding to the firmware program, the embedded software program, or the software program is split into threads and executed in parallel by two or more of the cores **1202**. The software program may correspond to a portion or all of the machine readable instructions and/or operations represented by the flowchart of FIG. **9**.

(167) The cores **1202** may communicate by an example bus **1204**. In some examples, the bus **1204** may implement a communication bus to effectuate communication associated with one(s) of the cores **1202**. For example, the bus **1204** may implement at least one of an Inter-Integrated Circuit (I2C) bus, a Serial Peripheral Interface (SPI) bus, a PCI bus, or a PCIe bus. Additionally or alternatively, the bus **1204** may implement any other type of computing or electrical bus. The cores **1202** may obtain data, instructions, and/or signals from one or more external devices by example interface circuitry **1206**. The cores **1202** may output data, instructions, and/or signals to the one or more external devices by the interface circuitry **1206**. Although the cores **1202** of this example include example local memory **1220** (e.g., Level 1 (L1) cache that may be split into an L1 data cache and an L1 instruction cache), the microprocessor **1200** also includes example shared memory **1210** that may be shared by the cores (e.g., Level 2 (L2_cache)) for high-speed access to data and/or instructions. Data and/or instructions may be transferred (e.g., shared) by writing to and/or reading from the shared memory **1210**. The local memory **1220** of each of the cores **1202** and the shared memory **1210** may be part of a hierarchy of storage devices including multiple levels of cache memory and the main memory (e.g., the main memory **1114**, **1116** of FIG. **11**). Typically, higher levels of memory in the hierarchy exhibit lower access time and have smaller storage capacity than lower levels of memory. Changes in the various levels of the cache hierarchy are managed (e.g., coordinated) by a cache coherency policy.

(168) Each core **1202** may be referred to as a CPU, DSP, GPU, etc., or any other type of hardware circuitry. Each core **1202** includes control unit circuitry **1214**, arithmetic and logic (AL) circuitry (sometimes referred to as an ALU) **1216**, a plurality of registers **1218**, the L1 cache **1220**, and an example bus **1222**. Other structures may be present. For example, each core **1202** may include vector unit circuitry, single instruction multiple data (SIMD) unit circuitry, load/store unit (LSU) circuitry, branch/jump unit circuitry, floating-point unit (FPU) circuitry, etc. The control unit circuitry **1214** includes semiconductor-based circuits structured to control (e.g., coordinate) data movement within the corresponding core **1202**. The AL circuitry **1216** includes semiconductor-based circuits structured to perform one or more mathematic and/or logic operations on the data within the corresponding core **1202**. The AL circuitry **1216** of some examples performs integer based operations. In other examples, the AL circuitry **1216** also performs floating point operations. In yet other examples, the AL circuitry **1216** may include first AL circuitry that performs integer based operations and second AL circuitry that performs floating point operations. In some examples, the AL circuitry **1216** may be referred to as an Arithmetic Logic Unit (ALU). The registers **1218** are semiconductor-based structures to store data and/or instructions such as results of one or more of the operations performed by the AL circuitry **1216** of the corresponding core

1202. For example, the registers **1218** may include vector register(s), SIMD register(s), general purpose register(s), flag register(s), segment register(s), machine specific register(s), instruction pointer register(s), control register(s), debug register(s), memory management register(s), machine check register(s), etc. The registers **1218** may be arranged in a bank as shown in FIG. **12**. Alternatively, the registers **1218** may be organized in any other arrangement, format, or structure including distributed throughout the core **1202** to shorten access time. The bus **1220** may implement at least one of an I2C bus, a SPI bus, a PCI bus, or a PCIe bus

(169) Each core **1202** and/or, more generally, the microprocessor **1200** may include additional and/or alternate structures to those shown and described above. For example, one or more clock circuits, one or more power supplies, one or more power gates, one or more cache home agents (CHAs), one or more converged/common mesh stops (CMSs), one or more shifters (e.g., barrel shifter(s)) and/or other circuitry may be present. The microprocessor **1200** is a semiconductor device fabricated to include many transistors interconnected to implement the structures described above in one or more integrated circuits (ICs) contained in one or more packages. The processor circuitry may include and/or cooperate with one or more accelerators. In some examples, accelerators are implemented by logic circuitry to perform certain tasks more quickly and/or efficiently than can be done by a general purpose processor. Examples of accelerators include ASICs and FPGAs such as those discussed herein. A GPU or other programmable device can also be an accelerator. Accelerators may be on-board the processor circuitry, in the same chip package as the processor circuitry and/or in one or more separate packages from the processor circuitry. (170) FIG. **13** is a block diagram of another example implementation of the processor circuitry **1112** of FIG. **11**. In this example, the processor circuitry **1112** is implemented by FPGA circuitry **1300**. The FPGA circuitry **1300** can be used, for example, to perform operations that could otherwise be performed by the example microprocessor **1200** of FIG. **12** executing corresponding machine readable instructions. However, once configured, the FPGA circuitry **1300** instantiates the machine readable instructions in hardware and, thus, can often execute the operations faster than they could be performed by a general purpose microprocessor executing the corresponding software.

(171) More specifically, in contrast to the microprocessor **1200** of FIG. **12** described above (which is a general purpose device that may be programmed to execute some or all of the machine readable instructions represented by the flowchart of FIG. **9** but whose interconnections and logic circuitry are fixed once fabricated), the FPGA circuitry **1300** of the example of FIG. **13** includes interconnections and logic circuitry that may be configured and/or interconnected in different ways after fabrication to instantiate, for example, some or all of the machine readable instructions represented by the flowchart of FIG. **9**. In particular, the FPGA **1300** may be thought of as an array of logic gates, interconnections, and switches. The switches can be programmed to change how the logic gates are interconnected by the interconnections, effectively forming one or more dedicated logic circuits (unless and until the FPGA circuitry **1300** is reprogrammed). The configured logic circuits enable the logic gates to cooperate in different ways to perform different operations on data received by input circuitry. Those operations may correspond to some or all of the software represented by the flowchart of FIG. **9**. As such, the FPGA circuitry **1300** may be structured to effectively instantiate some or all of the machine readable instructions of the flowchart of FIG. **9** as dedicated logic circuits to perform the operations corresponding to those software instructions in a dedicated manner analogous to an ASIC. Therefore, the FPGA circuitry **1300** may perform the operations corresponding to the some or all of the machine readable instructions of FIG. **9** faster than the general purpose microprocessor can execute the same.

(172) In the example of FIG. **13**, the FPGA circuitry **1300** is structured to be programmed (and/or reprogrammed one or more times) by an end user by a hardware description language (HDL) such as Verilog. The FPGA circuitry **1300** of FIG. **13**, includes example input/output (I/O) circuitry **1302** to obtain and/or output data to/from example configuration circuitry **1304** and/or external hardware

(e.g., external hardware circuitry) **1306**. For example, the configuration circuitry **1304** may implement interface circuitry that may obtain machine readable instructions to configure the FPGA circuitry **1300**, or portion(s) thereof. In some such examples, the configuration circuitry **1304** may obtain the machine readable instructions from a user, a machine (e.g., hardware circuitry (e.g., programmed or dedicated circuitry) that may implement an Artificial Intelligence/Machine Learning (AI/ML) model to generate the instructions), etc. In some examples, the external hardware **1306** may implement the microprocessor **1200** of FIG. **12**. The FPGA circuitry **1300** also includes an array of example logic gate circuitry **1308**, a plurality of example configurable interconnections **1310**, and example storage circuitry **1312**. The logic gate circuitry **1308** and interconnections **1310** are configurable to instantiate one or more operations that may correspond to at least some of the machine readable instructions of FIG. **9** and/or other desired operations. The logic gate circuitry **1308** shown in FIG. **13** is fabricated in groups or blocks. Each block includes semiconductor-based electrical structures that may be configured into logic circuits. In some examples, the electrical structures include logic gates (e.g., And gates, Or gates, Nor gates, etc.) that provide basic building blocks for logic circuits. Electrically controllable switches (e.g., transistors) are present within each of the logic gate circuitry **1308** to enable configuration of the electrical structures and/or the logic gates to form circuits to perform desired operations. The logic gate circuitry **1308** may include other electrical structures such as look-up tables (LUTs), registers (e.g., flip-flops or latches), multiplexers, etc.

(173) The interconnections **1310** of the illustrated example are conductive pathways, traces, vias, or the like that may include electrically controllable switches (e.g., transistors) whose state can be changed by programming (e.g., using an HDL instruction language) to activate or deactivate one or more connections between one or more of the logic gate circuitry **1308** to program desired logic circuits.

(174) The storage circuitry **1312** of the illustrated example is structured to store result(s) of the one or more of the operations performed by corresponding logic gates. The storage circuitry **1312** may be implemented by registers or the like. In the illustrated example, the storage circuitry **1312** is distributed amongst the logic gate circuitry **1308** to facilitate access and increase execution speed.

(175) The example FPGA circuitry **1300** of FIG. **13** also includes example Dedicated Operations Circuitry **1314**. In this example, the Dedicated Operations Circuitry **1314** includes special purpose circuitry **1316** that may be invoked to implement commonly used functions to avoid the need to program those functions in the field. Examples of such special purpose circuitry **1316** include memory (e.g., DRAM) controller circuitry, PCIe controller circuitry, clock circuitry, transceiver circuitry, memory, and multiplier-accumulator circuitry. Other types of special purpose circuitry may be present. In some examples, the FPGA circuitry **1300** may also include example general purpose programmable circuitry **1318** such as an example CPU **1320** and/or an example DSP **1322**. Other general purpose programmable circuitry **1318** may additionally or alternatively be present such as a GPU, an XPU, etc., that can be programmed to perform other operations.

(176) Although FIGS. **12** and **13** illustrate two example implementations of the processor circuitry **1112** of FIG. **11**, many other approaches are contemplated. For example, as mentioned above, modern FPGA circuitry may include an on-board CPU, such as one or more of the example CPU **1320** of FIG. **13**. Therefore, the processor circuitry **1112** of FIG. **11** may additionally be implemented by combining the example microprocessor **1200** of FIG. **12** and the example FPGA circuitry **1300** of FIG. **13**. In some such hybrid examples, a first portion of the machine readable instructions represented by the flowchart of FIG. **9** may be executed by one or more of the cores **1202** of FIG. **12** and a second portion of the machine readable instructions represented by the flowchart of FIG. **9** may be executed by the FPGA circuitry **1300** of FIG. **13**.

(177) In some examples, the processor circuitry **1112** of FIG. **11** may be in one or more packages. For example, the processor circuitry **1200** of FIG. **12** and/or the FPGA circuitry **1300** of FIG. **13** may be in one or more packages. In some examples, an XPU may be implemented by the processor

circuitry **1112** of FIG. **11**, which may be in one or more packages. For example, the XPU may include a CPU in one package, a DSP in another package, a GPU in yet another package, and an FPGA in still yet another package.

(178) FIG. **14** is a block diagram of an example processor platform **1400** structured to execute and/or instantiate the machine readable instructions and/or operations of FIG. **10** to implement the microphone gain control circuitry **330** of FIGS. **3** and/or **4**. The processor platform **1400** can be, for example, a server, a personal computer, a workstation, a self-learning machine (e.g., a neural network), a mobile device (e.g., a cell phone, a smart phone, a tablet such as an iPad™), a personal digital assistant (PDA), an Internet appliance, or any other type of computing device.

(179) The processor platform **1400** of the illustrated example includes processor circuitry **1412**. The processor circuitry **1412** of the illustrated example is hardware. For example, the processor circuitry **1412** can be implemented by one or more integrated circuits, logic circuits, FPGAs microprocessors, CPUs, GPUs, DSPs, and/or microcontrollers from any desired family or manufacturer. The processor circuitry **1412** may be implemented by one or more semiconductor based (e.g., silicon based) devices. In this example, the processor circuitry **1412** implements the example low-pass voice filter **426**, the example noise estimating circuitry **428**, the example calculator **429**, the example gain determining circuitry **430**, and the example gain control circuitry **435**.

(180) The processor circuitry **1412** of the illustrated example includes a local memory **1413** (e.g., a cache, registers, etc.). The processor circuitry **1412** of the illustrated example is in communication with a main memory including a volatile memory **1414** and a non-volatile memory **1416** by a bus **1418**. The volatile memory **1414** may be implemented by Synchronous Dynamic Random Access Memory (SDRAM), Dynamic Random Access Memory (DRAM), RAMBUS® Dynamic Random Access Memory (RDRAM®), and/or any other type of RAM device. The non-volatile memory **1416** may be implemented by flash memory and/or any other desired type of memory device. Access to the main memory **1414**, **1416** of the illustrated example is controlled by a memory controller **1417**.

(181) The processor platform **1400** of the illustrated example also includes interface circuitry **1420**. The interface circuitry **1420** may be implemented by hardware in accordance with any type of interface standard, such as an Ethernet interface, a universal serial bus (USB) interface, a Bluetooth® interface, a near field communication (NFC) interface, a PCI interface, and/or a PCIe interface.

(182) In the illustrated example, one or more input devices **1422** are connected to the interface circuitry **1420**. The input device(s) **1422** permit(s) a user to enter data and/or commands into the processor circuitry **1412**. The input device(s) **1422** can be implemented by, for example, an audio sensor, a microphone, a camera (still or video), a keyboard, a button, a mouse, a touchscreen, a track-pad, a trackball, an isopoint device, and/or a voice recognition system.

(183) One or more output devices **1424** are also connected to the interface circuitry **1420** of the illustrated example. The output devices **1424** can be implemented, for example, by display devices (e.g., a light emitting diode (LED), an organic light emitting diode (OLED), a liquid crystal display (LCD), a cathode ray tube (CRT) display, an in-place switching (IPS) display, a touchscreen, etc.), a tactile output device, a printer, and/or speaker. The interface circuitry **1420** of the illustrated example, thus, typically includes a graphics driver card, a graphics driver chip, and/or graphics processor circuitry such as a GPU.

(184) The interface circuitry **1420** of the illustrated example also includes a communication device such as a transmitter, a receiver, a transceiver, a modem, a residential gateway, a wireless access point, and/or a network interface to facilitate exchange of data with external machines (e.g., computing devices of any kind) by a network **1426**. The communication can be by, for example, an Ethernet connection, a digital subscriber line (DSL) connection, a telephone line connection, a coaxial cable system, a satellite system, a line-of-site wireless system, a cellular telephone system,

an optical connection, etc.

(185) The processor platform **1400** of the illustrated example also includes one or more mass storage devices **1428** to store software and/or data. Examples of such mass storage devices **1428** include magnetic storage devices, optical storage devices, floppy disk drives, HDDs, CDs, Blu-ray disk drives, redundant array of independent disks (RAID) systems, solid state storage devices such as flash memory devices, and DVD drives.

(186) The machine executable instructions **1432**, which may be implemented by the machine readable instructions of FIG. **10**, may be stored in the mass storage device **1428**, in the volatile memory **1414**, in the non-volatile memory **1416**, and/or on a removable non-transitory computer readable storage medium such as a CD or DVD.

(187) FIG. **15** is a block diagram of an example implementation of the processor circuitry **1412** of FIG. **14**. In this example, the processor circuitry **1412** of FIG. **14** is implemented by a microprocessor **1500**. For example, the microprocessor **1200** may implement multi-core hardware circuitry such as a CPU, a DSP, a GPU, an XPU, etc. Although it may include any number of example cores **1502** (e.g., **1** core), the microprocessor **1500** of this example is a multi-core semiconductor device including **N** cores. The cores **1502** of the microprocessor **1500** may operate independently or may cooperate to execute machine readable instructions. For example, machine code corresponding to a firmware program, an embedded software program, or a software program may be executed by one of the cores **1502** or may be executed by multiple ones of the cores **1502** at the same or different times. In some examples, the machine code corresponding to the firmware program, the embedded software program, or the software program is split into threads and executed in parallel by two or more of the cores **1502**. The software program may correspond to a portion or all of the machine readable instructions and/or operations represented by the flowchart of FIG. **10**.

(188) The cores **1502** may communicate by an example bus **1504**. In some examples, the bus **1504** may implement a communication bus to effectuate communication associated with one(s) of the cores **1502**. For example, the bus **1504** may implement at least one of an Inter-Integrated Circuit (I2C) bus, a Serial Peripheral Interface (SPI) bus, a PCI bus, or a PCIe bus. Additionally or alternatively, the bus **1504** may implement any other type of computing or electrical bus. The cores **1502** may obtain data, instructions, and/or signals from one or more external devices by example interface circuitry **1506**. The cores **1502** may output data, instructions, and/or signals to the one or more external devices by the interface circuitry **1506**. Although the cores **1502** of this example include example local memory **1520** (e.g., Level 1 (L1) cache that may be split into an L1 data cache and an L1 instruction cache), the microprocessor **1500** also includes example shared memory **1510** that may be shared by the cores (e.g., Level 2 (L2_cache)) for high-speed access to data and/or instructions. Data and/or instructions may be transferred (e.g., shared) by writing to and/or reading from the shared memory **1510**. The local memory **1520** of each of the cores **1502** and the shared memory **1510** may be part of a hierarchy of storage devices including multiple levels of cache memory and the main memory (e.g., the main memory **1414**, **1416** of FIG. **14**). Typically, higher levels of memory in the hierarchy exhibit lower access time and have smaller storage capacity than lower levels of memory. Changes in the various levels of the cache hierarchy are managed (e.g., coordinated) by a cache coherency policy.

(189) Each core **1502** may be referred to as a CPU, DSP, GPU, etc., or any other type of hardware circuitry. Each core **1502** includes control unit circuitry **1514**, arithmetic and logic (AL) circuitry (sometimes referred to as an ALU) **1516**, a plurality of registers **1218**, the L1 cache **1520**, and an example bus **1522**. Other structures may be present. For example, each core **1502** may include vector unit circuitry, single instruction multiple data (SIMD) unit circuitry, load/store unit (LSU) circuitry, branch/jump unit circuitry, floating-point unit (FPU) circuitry, etc. The control unit circuitry **1514** includes semiconductor-based circuits structured to control (e.g., coordinate) data movement within the corresponding core **1502**. The AL circuitry **1516** includes semiconductor-

based circuits structured to perform one or more mathematical and/or logic operations on the data within the corresponding core **1502**. The AL circuitry **1516** of some examples performs integer based operations. In other examples, the AL circuitry **1516** also performs floating point operations. In yet other examples, the AL circuitry **1516** may include first AL circuitry that performs integer based operations and second AL circuitry that performs floating point operations. In some examples, the AL circuitry **1516** may be referred to as an Arithmetic Logic Unit (ALU). The registers **1518** are semiconductor-based structures to store data and/or instructions such as results of one or more of the operations performed by the AL circuitry **1516** of the corresponding core **1502**. For example, the registers **1518** may include vector register(s), SIMD register(s), general purpose register(s), flag register(s), segment register(s), machine specific register(s), instruction pointer register(s), control register(s), debug register(s), memory management register(s), machine check register(s), etc. The registers **1518** may be arranged in a bank as shown in FIG. **15**. Alternatively, the registers **1518** may be organized in any other arrangement, format, or structure including distributed throughout the core **1502** to shorten access time. The bus **1520** may implement at least one of an I2C bus, a SPI bus, a PCI bus, or a PCIe bus

(190) Each core **1502** and/or, more generally, the microprocessor **1500** may include additional and/or alternate structures to those shown and described above. For example, one or more clock circuits, one or more power supplies, one or more power gates, one or more cache home agents (CHAs), one or more converged/common mesh stops (CMSs), one or more shifters (e.g., barrel shifter(s)) and/or other circuitry may be present. The microprocessor **1500** is a semiconductor device fabricated to include many transistors interconnected to implement the structures described above in one or more integrated circuits (ICs) contained in one or more packages. The processor circuitry may include and/or cooperate with one or more accelerators. In some examples, accelerators are implemented by logic circuitry to perform certain tasks more quickly and/or efficiently than can be done by a general purpose processor. Examples of accelerators include ASICs and FPGAs such as those discussed herein. A GPU or other programmable device can also be an accelerator. Accelerators may be on-board the processor circuitry, in the same chip package as the processor circuitry and/or in one or more separate packages from the processor circuitry.

(191) FIG. **16** is a block diagram of another example implementation of the processor circuitry **1412** of FIG. **14**. In this example, the processor circuitry **1412** is implemented by FPGA circuitry **1600**. The FPGA circuitry **1600** can be used, for example, to perform operations that could otherwise be performed by the example microprocessor **1500** of FIG. **15** executing corresponding machine readable instructions. However, once configured, the FPGA circuitry **1600** instantiates the machine readable instructions in hardware and, thus, can often execute the operations faster than they could be performed by a general purpose microprocessor executing the corresponding software.

(192) More specifically, in contrast to the microprocessor **1500** of FIG. **15** described above (which is a general purpose device that may be programmed to execute some or all of the machine readable instructions represented by the flowchart of FIG. **10** but whose interconnections and logic circuitry are fixed once fabricated), the FPGA circuitry **1600** of the example of FIG. **16** includes interconnections and logic circuitry that may be configured and/or interconnected in different ways after fabrication to instantiate, for example, some or all of the machine readable instructions represented by the flowchart of FIG. **10**. In particular, the FPGA **1600** may be thought of as an array of logic gates, interconnections, and switches. The switches can be programmed to change how the logic gates are interconnected by the interconnections, effectively forming one or more dedicated logic circuits (unless and until the FPGA circuitry **1600** is reprogrammed). The configured logic circuits enable the logic gates to cooperate in different ways to perform different operations on data received by input circuitry. Those operations may correspond to some or all of the software represented by the flowchart of FIG. **10**. As such, the FPGA circuitry **1600** may be structured to effectively instantiate some or all of the machine readable instructions of the

flowchart of FIG. 10 as dedicated logic circuits to perform the operations corresponding to those software instructions in a dedicated manner analogous to an ASIC. Therefore, the FPGA circuitry **1600** may perform the operations corresponding to the some or all of the machine readable instructions of FIG. 10 faster than the general purpose microprocessor can execute the same.

(193) In the example of FIG. 16, the FPGA circuitry **1600** is structured to be programmed (and/or reprogrammed one or more times) by an end user by a hardware description language (HDL) such as Verilog. The FPGA circuitry **1600** of FIG. 16, includes example input/output (I/O) circuitry **1602** to obtain and/or output data to/from example configuration circuitry **1604** and/or external hardware (e.g., external hardware circuitry) **1606**. For example, the configuration circuitry **1604** may implement interface circuitry that may obtain machine readable instructions to configure the FPGA circuitry **1600**, or portion(s) thereof. In some such examples, the configuration circuitry **1604** may obtain the machine readable instructions from a user, a machine (e.g., hardware circuitry (e.g., programmed or dedicated circuitry) that may implement an Artificial Intelligence/Machine Learning (AI/ML) model to generate the instructions), etc. In some examples, the external hardware **1606** may implement the microprocessor **1500** of FIG. 15. The FPGA circuitry **1600** also includes an array of example logic gate circuitry **1608**, a plurality of example configurable interconnections **1610**, and example storage circuitry **1612**. The logic gate circuitry **1608** and interconnections **1610** are configurable to instantiate one or more operations that may correspond to at least some of the machine readable instructions of FIG. 10 and/or other desired operations. The logic gate circuitry **1608** shown in FIG. 16 is fabricated in groups or blocks. Each block includes semiconductor-based electrical structures that may be configured into logic circuits. In some examples, the electrical structures include logic gates (e.g., And gates, Or gates, Nor gates, etc.) that provide basic building blocks for logic circuits. Electrically controllable switches (e.g., transistors) are present within each of the logic gate circuitry **1608** to enable configuration of the electrical structures and/or the logic gates to form circuits to perform desired operations. The logic gate circuitry **1608** may include other electrical structures such as look-up tables (LUTs), registers (e.g., flip-flops or latches), multiplexers, etc.

(194) The interconnections **1610** of the illustrated example are conductive pathways, traces, vias, or the like that may include electrically controllable switches (e.g., transistors) whose state can be changed by programming (e.g., using an HDL instruction language) to activate or deactivate one or more connections between one or more of the logic gate circuitry **1608** to program desired logic circuits.

(195) The storage circuitry **1612** of the illustrated example is structured to store result(s) of the one or more of the operations performed by corresponding logic gates. The storage circuitry **1612** may be implemented by registers or the like. In the illustrated example, the storage circuitry **1612** is distributed amongst the logic gate circuitry **1608** to facilitate access and increase execution speed.

(196) The example FPGA circuitry **1600** of FIG. 16 also includes example Dedicated Operations Circuitry **1614**. In this example, the Dedicated Operations Circuitry **1614** includes special purpose circuitry **1616** that may be invoked to implement commonly used functions to avoid the need to program those functions in the field. Examples of such special purpose circuitry **1616** include memory (e.g., DRAM) controller circuitry, PCIe controller circuitry, clock circuitry, transceiver circuitry, memory, and multiplier-accumulator circuitry. Other types of special purpose circuitry may be present. In some examples, the FPGA circuitry **1600** may also include example general purpose programmable circuitry **1618** such as an example CPU **1620** and/or an example DSP **1622**. Other general purpose programmable circuitry **1618** may additionally or alternatively be present such as a GPU, an XPU, etc., that can be programmed to perform other operations.

(197) Although FIGS. 15 and 16 illustrate two example implementations of the processor circuitry **1412** of FIG. 14, many other approaches are contemplated. For example, as mentioned above, modern FPGA circuitry may include an on-board CPU, such as one or more of the example CPU **1620** of FIG. 16. Therefore, the processor circuitry **1412** of FIG. 14 may additionally be

implemented by combining the example microprocessor **1500** of FIG. **15** and the example FPGA circuitry **1600** of FIG. **16**. In some such hybrid examples, a first portion of the machine readable instructions represented by the flowchart of FIG. **10** may be executed by one or more of the cores **1502** of FIG. **15** and a second portion of the machine readable instructions represented by the flowchart of FIG. **10** may be executed by the FPGA circuitry **1600** of FIG. **16**.

(198) In some examples, the processor circuitry **1412** of FIG. **14** may be in one or more packages. For example, the processor circuitry **1500** of FIG. **15** and/or the FPGA circuitry **1600** of FIG. **16** may be in one or more packages. In some examples, an XPU may be implemented by the processor circuitry **1412** of FIG. **14**, which may be in one or more packages. For example, the XPU may include a CPU in one package, a DSP in another package, a GPU in yet another package, and an FPGA in still yet another package.

(199) FIG. **17** is a block diagram of an example processor platform **1700** structured to execute and/or instantiate the machine readable instructions and/or operations of FIG. **7** to implement the first neural network generation circuitry **504** of FIG. **5**. The processor platform **1700** can be, for example, a self-learning machine (e.g., a neural network) or any other type of computing device.

(200) The processor platform **1700** of the illustrated example includes processor circuitry **1712**. The processor circuitry **1712** of the illustrated example is hardware. For example, the processor circuitry **1712** can be implemented by one or more integrated circuits, logic circuits, FPGAs microprocessors, CPUs, GPUs, DSPs, and/or microcontrollers from any desired family or manufacturer. The processor circuitry **1712** may be implemented by one or more semiconductor based (e.g., silicon based) devices. In this example, the processor circuitry **1712** implements the example trainer circuitry **508**, the example training control circuitry **510**, and the example neural network processing circuitry **506**.

(201) The processor circuitry **1712** of the illustrated example includes a local memory **1713** (e.g., a cache, registers, etc.). The processor circuitry **1712** of the illustrated example is in communication with a main memory including a volatile memory **1714** and a non-volatile memory **1716** by a bus **1718**. The volatile memory **1714** may be implemented by Synchronous Dynamic Random Access Memory (SDRAM), Dynamic Random Access Memory (DRAM), RAMBUS® Dynamic Random Access Memory (RDRAM®), and/or any other type of RAM device. The non-volatile memory **1716** may be implemented by flash memory and/or any other desired type of memory device. Access to the main memory **1714**, **1716** of the illustrated example is controlled by a memory controller **1717**.

(202) The processor platform **1700** of the illustrated example also includes interface circuitry **1720**. The interface circuitry **1720** may be implemented by hardware in accordance with any type of interface standard, such as an Ethernet interface, a universal serial bus (USB) interface, a Bluetooth® interface, a near field communication (NFC) interface, a PCI interface, and/or a PCIe interface.

(203) In the illustrated example, one or more input devices **1722** are connected to the interface circuitry **1720**. The input device(s) **1722** permit(s) a user to enter data and/or commands into the processor circuitry **1712**. The input device(s) **1722** can be implemented by, for example, an audio sensor, a microphone, a camera (still or video), a keyboard, a button, a mouse, a touchscreen, a track-pad, a trackball, an isopoint device, and/or a voice recognition system.

(204) One or more output devices **1724** are also connected to the interface circuitry **1720** of the illustrated example. The output devices **1724** can be implemented, for example, by display devices (e.g., a light emitting diode (LED), an organic light emitting diode (OLED), a liquid crystal display (LCD), a cathode ray tube (CRT) display, an in-place switching (IPS) display, a touchscreen, etc.), a tactile output device, a printer, and/or speaker. The interface circuitry **1720** of the illustrated example, thus, typically includes a graphics driver card, a graphics driver chip, and/or graphics processor circuitry such as a GPU.

(205) The interface circuitry **1720** of the illustrated example also includes a communication device

such as a transmitter, a receiver, a transceiver, a modem, a residential gateway, a wireless access point, and/or a network interface to facilitate exchange of data with external machines (e.g., computing devices of any kind) by a network **1726**. The communication can be by, for example, an Ethernet connection, a digital subscriber line (DSL) connection, a telephone line connection, a coaxial cable system, a satellite system, a line-of-site wireless system, a cellular telephone system, an optical connection, etc.

(206) The processor platform **1700** of the illustrated example also includes one or more mass storage devices **1728** to store software and/or data. Examples of such mass storage devices **1728** include magnetic storage devices, optical storage devices, floppy disk drives, HDDs, CDs, Blu-ray disk drives, redundant array of independent disks (RAID) systems, solid state storage devices such as flash memory devices, and DVD drives.

(207) The machine executable instructions **1732**, which may be implemented by the machine readable instructions of FIG. 7, may be stored in the mass storage device **1728**, in the volatile memory **1714**, in the non-volatile memory **1716**, and/or on a removable non-transitory computer readable storage medium such as a CD or DVD.

(208) FIG. **18** is a block diagram of an example processor platform **1800** structured to execute and/or instantiate the machine readable instructions and/or operations of FIG. 8 to implement the second neural network generation circuitry **518** of FIG. 5. The processor platform **1800** can be, for example, a self-learning machine (e.g., a neural network) or any other type of computing device.

(209) The processor platform **1800** of the illustrated example includes processor circuitry **1812**. The processor circuitry **1812** of the illustrated example is hardware. For example, the processor circuitry **1812** can be implemented by one or more integrated circuits, logic circuits, FPGAs microprocessors, CPUs, GPUs, DSPs, and/or microcontrollers from any desired family or manufacturer. The processor circuitry **1812** may be implemented by one or more semiconductor based (e.g., silicon based) devices. In this example, the processor circuitry **1812** implements the example trainer circuitry **520**, the example training control circuitry **524**, and the example neural network processing circuitry **522**.

(210) The processor circuitry **1812** of the illustrated example includes a local memory **1813** (e.g., a cache, registers, etc.). The processor circuitry **1812** of the illustrated example is in communication with a main memory including a volatile memory **1814** and a non-volatile memory **1816** by a bus **1818**. The volatile memory **1814** may be implemented by Synchronous Dynamic Random Access Memory (SDRAM), Dynamic Random Access Memory (DRAM), RAMBUS® Dynamic Random Access Memory (RDRAM®), and/or any other type of RAM device. The non-volatile memory **1816** may be implemented by flash memory and/or any other desired type of memory device. Access to the main memory **1814**, **1816** of the illustrated example is controlled by a memory controller **1817**.

(211) The processor platform **1700** of the illustrated example also includes interface circuitry **1820**. The interface circuitry **1820** may be implemented by hardware in accordance with any type of interface standard, such as an Ethernet interface, a universal serial bus (USB) interface, a Bluetooth® interface, a near field communication (NFC) interface, a PCI interface, and/or a PCIe interface.

(212) In the illustrated example, one or more input devices **1822** are connected to the interface circuitry **1820**. The input device(s) **1822** permit(s) a user to enter data and/or commands into the processor circuitry **1812**. The input device(s) **1822** can be implemented by, for example, an audio sensor, a microphone, a camera (still or video), a keyboard, a button, a mouse, a touchscreen, a track-pad, a trackball, an isopoint device, and/or a voice recognition system.

(213) One or more output devices **1824** are also connected to the interface circuitry **1820** of the illustrated example. The output devices **1824** can be implemented, for example, by display devices (e.g., a light emitting diode (LED), an organic light emitting diode (OLED), a liquid crystal display (LCD), a cathode ray tube (CRT) display, an in-place switching (IPS) display, a touchscreen, etc.),

a tactile output device, a printer, and/or speaker. The interface circuitry **1820** of the illustrated example, thus, typically includes a graphics driver card, a graphics driver chip, and/or graphics processor circuitry such as a GPU.

(214) The interface circuitry **1820** of the illustrated example also includes a communication device such as a transmitter, a receiver, a transceiver, a modem, a residential gateway, a wireless access point, and/or a network interface to facilitate exchange of data with external machines (e.g., computing devices of any kind) by a network **1826**. The communication can be by, for example, an Ethernet connection, a digital subscriber line (DSL) connection, a telephone line connection, a coaxial cable system, a satellite system, a line-of-site wireless system, a cellular telephone system, an optical connection, etc.

(215) The processor platform **1800** of the illustrated example also includes one or more mass storage devices **1828** to store software and/or data. Examples of such mass storage devices **1828** include magnetic storage devices, optical storage devices, floppy disk drives, HDDs, CDs, Blu-ray disk drives, redundant array of independent disks (RAID) systems, solid state storage devices such as flash memory devices, and DVD drives.

(216) The machine executable instructions **1832**, which may be implemented by the machine readable instructions of FIG. **8**, may be stored in the mass storage device **1828**, in the volatile memory **1814**, in the non-volatile memory **1816**, and/or on a removable non-transitory computer readable storage medium such as a CD or DVD.

(217) A block diagram illustrating an example software distribution platform **1905** to distribute software such as the example machine readable instructions **1132** of FIG. **11** and/or the example machine readable instructions **1432** of FIG. **14** to hardware devices owned and/or operated by third parties is illustrated in FIG. **19**. The example software distribution platform **1905** may be implemented by any computer server, data facility, cloud service, etc., capable of storing and transmitting software to other computing devices. The third parties may be customers of the entity owning and/or operating the software distribution platform **1905**. For example, the entity that owns and/or operates the software distribution platform **1905** may be a developer, a seller, and/or a licensor of software such as the example machine readable instructions **1132** of FIG. **11** and/or the example machine readable instructions **1432** of FIG. **14**. The third parties may be consumers, users, retailers, OEMs, etc., who purchase and/or license the software for use and/or re-sale and/or sub-licensing. In the illustrated example, the software distribution platform **1905** includes one or more servers and one or more storage devices. The storage devices store the machine readable instructions **1132**, **1432** which may correspond to the example machine readable instructions **900**, **1000** of FIGS. **9** and **10**, as described above. The one or more servers of the example software distribution platform **1905** are in communication with a network **1910**, which may correspond to any one or more of the Internet and/or any of the example networks **1126**, **1426** described above. In some examples, the one or more servers are responsive to requests to transmit the software to a requesting party as part of a commercial transaction. Payment for the delivery, sale, and/or license of the software may be handled by the one or more servers of the software distribution platform and/or by a third party payment entity. The servers enable purchasers and/or licensors to download the machine readable instructions **1132**, **1432** from the software distribution platform **1905**. For example, the software, which may correspond to the example machine readable instructions **1132** of FIG. **11**, may be downloaded to the example processor platform **1100**, which is to execute the machine readable instructions **1132** to implement the user proximity detection circuitry **322**. As another example, the software, which may correspond to the example machine readable instructions **1432** of FIG. **14**, may be downloaded to the example processor platform **1400**, which is to execute the machine readable instructions **1432** to implement the microphone gain control circuitry **330**. In some examples, one or more servers of the software distribution platform **1905** periodically offer, transmit, and/or force updates to the software (e.g., the example machine readable instructions **1132** of FIG. **11**, the example machine readable instructions **1432** of FIG. **14**)

to ensure improvements, patches, updates, etc., are distributed and applied to the software at the end user devices.

(218) From the foregoing, it will be appreciated that example systems, methods, apparatus, and articles of manufacture have been disclosed that provide for dynamic adjustments of gain applied to audio captured by microphone(s) associated with a user device based on proximity of a user to the user device. In examples disclosed herein, camera(s) associated with the user output image (e.g., video) data including the user during, for example, a video conference. Examples disclosed herein use facial recognition analysis to identify face(s) in the image data, to select a face as associated with a primary speaker when more than one face is identified, and to identify facial landmarks (e.g., points associated with each of the user's eyes). In examples disclosed herein, the locations of the facial landmarks are used to predict a distance of the user from the camera(s), which serves as a proxy for the distance of the user from the user device. Examples disclosed herein determine an amount of gain to be applied to a voice band of the audio signal based on the predicted user proximity measurements. Examples disclosed herein detect changes in user proximity to the device and dynamically adjust the gain in response to the changes to cause output of audio that provides for substantially consistent volume of the user's voice despite variations in user distance from the device.

(219) Disclosed systems, methods, apparatus, and articles of manufacture improve the efficiency of using a computing device by using image data generated as part of a video conference to determine user proximity to the user device and control audio gain based on the user proximity, rather than using a separate proximity sensors or other hardware. Disclosed systems, methods, apparatus, and articles of manufacture are accordingly directed to one or more improvement(s) in the operation of a machine such as a computer or other electronic and/or mechanical device.

(220) Example apparatus, systems, and methods for microphone gain control for electronic user devices are disclosed herein. Further examples and combinations thereof include the following:

(221) Example 1 includes an apparatus including at least one memory; instructions in the apparatus; and processor circuitry to execute the instructions to determine a proximity of a user to a user device based on an image generated via one or more cameras associated with the user device; determine an amount of gain to be applied to an audio signal generated by a microphone associated with the user device based on the proximity of the user; and cause an amplifier of the user device to apply the gain to the audio signal.

(222) Example 2 includes the apparatus of example 1, wherein the processor circuitry is to detect a face of the user in the image; identify a facial landmark associated with the face in the image; and determine the proximity of the user based on the facial landmark.

(223) Example 3 includes the apparatus of examples 1 or 2, wherein the facial landmark includes a first facial landmark and a second facial landmark and the processor circuitry is to determine a distance between the first facial landmark and the second facial landmark based on first pixel coordinate data associated with the first facial landmark and second pixel coordinate data associated with the second facial landmark and determine the proximity of the user based on the distance between the first facial landmark and the second facial landmark.

(224) Example 4 includes the apparatus of any of examples 1-3, wherein the first facial landmark includes an eye point associated with a first eye of the user and the second facial landmark includes an eye point associated with the second facial landmark.

(225) Example 5 includes the apparatus of any of examples 1-4, wherein the face is a first face, the user is a first user, and the processor circuitry is to detect a second face in the image, the second face associated with a second user; generate a first bounding box for the first face and a second bounding box for the second face; perform a comparison of an area of the first bounding box to an area of the second bounding box; and select the first face for determining the proximity based on the comparison.

(226) Example 6 includes the apparatus of any of examples 1-5, wherein the processor circuitry is

to detect a third face in the image, the third face associated with a third user; generate a third bounding box for the third face; assign a first confidence level to the first bounding box, a second confidence level to the second bounding box, and a third confidence level to the third bounding box; and refrain from selecting the third face for determining the proximity based on the third confidence level.

(227) Example 7 includes the apparatus of any of examples 1-6, wherein the processor circuitry is to determine a signal-to-noise ratio of the audio signal; perform a comparison of the signal-to-noise ratio to a threshold; and determine the amount of gain to be applied to the audio signal based on the comparison.

(228) Example 8 includes the apparatus of any of examples 1-7, wherein the processor circuitry is to cause the amplifier to apply the gain to a voice band of the audio signal.

(229) Example 9 includes the apparatus of any of examples 1-8, wherein the image includes a video frame.

(230) Example 10 includes the apparatus of any of examples 1-9, wherein the processor circuitry is to reduce a sampling rate of a video signal and extract the video frame from the video signal having the reduced sampling rate.

(231) Example 11 includes an apparatus including means for detecting a face of a user in a video frame, the video frame associated with a video stream to be generated by a camera, the camera associated with a user device; means for identifying facial landmarks in the face; means for determining a proximity of the user relative to the camera based on the facial landmarks; means for determining a gain to be applied to an audio signal based on the proximity, the audio signal to be generated by a microphone associated with the user; and means for controlling to cause an amplifier of the user device to apply the gain to the audio signal.

(232) Example 12 includes the apparatus of example 11, wherein facial landmarks include a first facial landmark and a second facial landmark, the facial landmark identifying means is to determine a distance between the first facial landmark and the second facial landmark, the proximity determining means to determine the proximity based on the distance.

(233) Example 13 includes the apparatus of examples 11 or 12, further including means for extracting the video frame from the video stream.

(234) Example 14 includes the apparatus of any of examples 11-13, wherein the extracting means is to reduce a sampling rate of the video stream.

(235) Example 15 includes the apparatus of any of examples 11-14, wherein the face detecting means is to generate bounding box in response to detecting the face.

(236) Example 16 includes the apparatus of any of examples 11-15, further including means for filtering the audio signal, the filtering means to remove ambient noise from the audio signal, the gain determining means to cause the amplifier to apply the gain to a voice band of the audio signal.

(237) Example 17 includes the apparatus of any of examples 11-16, further including means for calculating a signal-to-noise ratio of the audio signal, the gain determining means to determine the gain to be applied based on the signal-to-noise ratio.

(238) Example 18 includes at least one non-transitory computer readable storage medium comprising instructions that, when executed, cause processor circuitry to at least determine a proximity of a user to a user device based on an image generated via one or more cameras; determine an amount of gain to be applied to an audio signal generated by a microphone associated with the user device based on the proximity of the user; and cause an amplifier of the user device to apply the gain to the audio signal.

(239) Example 19 includes the at least one non-transitory computer readable storage medium of example 18, wherein the instructions, when executed, cause the processor circuitry to: detect a face of the user in the image; identify a facial landmark associated with the face in the image; and determine the proximity of the user based on the facial landmark.

(240) Example 20 includes the at least one non-transitory computer readable storage medium of

examples 18 or 19, wherein the facial landmark includes a first facial landmark and a second facial landmark and the instructions, when executed, cause the processor circuitry to determine a distance between the first facial landmark and the second facial landmark based on first pixel coordinate data associated with the first facial landmark and second pixel coordinate data associated with the second facial landmark; and determine the proximity of the user based on the distance between the first facial landmark and the second facial landmark.

(241) Example 21 includes the at least one non-transitory computer readable storage medium of any of examples 18-20, wherein the first facial landmark includes an eye point associated with a first eye of the user and the second facial landmark includes an eye point associated with the second facial landmark.

(242) Example 22 includes the at least one non-transitory computer readable storage medium of any of examples 18-21, wherein the face is a first face, the user is a first user, and the instructions, when executed, cause the processor circuitry to detect a second face in the image, the second face associated with a second user; generate a first bounding box for the first face and a second bounding box for the second face; perform a comparison of an area of the first bounding box to an area of the second bounding box; and select the first face for determining the proximity based on the comparison.

(243) Example 23 includes the at least one non-transitory computer readable storage medium of any of examples 18-22, wherein the instructions, when executed, cause the processor circuitry to detect a third face in the image, the third face associated with a third user; generate a third bounding box for the third face; assign a first confidence level to the first bounding box, a second confidence level to the second bounding box, and a third confidence level to the third bounding box; and refrain from selecting the third face for determining the proximity based on the third confidence level.

(244) Example 24 includes the at least one non-transitory computer readable storage medium of any of examples 18-23, wherein the instructions, when executed, cause the processor circuitry to determine a signal-to-noise ratio of the audio signal; perform a comparison of the signal-to-noise ratio to a threshold; and determine the amount of gain to be applied to the audio signal based on the comparison.

(245) Example 25 includes the at least one non-transitory computer readable storage medium of any of examples 18-24, wherein the instructions, when executed, cause the processor circuitry to cause the amplifier to apply the gain to a voice band of the audio signal.

(246) Example 26 includes the at least one non-transitory computer readable storage medium of any of examples 18-25, wherein the image includes a video frame.

(247) Example 27 includes an electronic user device including means for generating an audio signal; means for amplifying the audio signal; means for generating an image; and means for processing to determine a proximity of a user relative to the image generating means based on the image; determine an amount of gain to be applied to the audio signal based on the proximity of the user; and cause the amplifying means to apply the gain to the audio signal.

(248) Example 28 includes the electronic user device of example 27, wherein the processing means is to detect a face of the user in the image; identify a first facial landmark and a second facial landmark associated with the face in the image; and determine the proximity of the user based on the first facial landmark and the second facial landmark.

(249) Example 29 includes the electronic user device of examples 27 or 28, wherein the processing means is to determine a distance between the first facial landmark and the second facial landmark based on first pixel coordinate data associated with the first facial landmark and second pixel coordinate data associated with the second facial landmark; and determine the proximity of the user based on the distance between the first facial landmark and the second facial landmark.

(250) Example 30 includes the electronic user device of any of examples 27-29, wherein the processing means is to determine a signal-to-noise ratio of the audio signal; perform a comparison

of the signal-to-noise ratio to a threshold; and determine the amount of gain to be applied to the audio signal based on the comparison.

(251) Example 31 includes the electronic user device of any of examples 27-30, wherein the face is a first face, the user is a first user, and the processing means is to detect a second face in the image, the second face associated with a second user; generate a first bounding box for the first face and a second bounding box for the second face; perform a comparison of an area of the first bounding box to an area of the second bounding box; and select the first face for determining the proximity based on the comparison.

(252) Example 32 includes the electronic user device of any of examples 27-31, wherein the image generating means includes a video camera.

(253) Example 33 includes a method including determining, by executing instructions with processor circuitry, a proximity of a user to a user device based on an image generated via one or more cameras associated with the user device; determining, by executing instructions with the processor circuitry, an amount of gain to be applied to an audio signal generated by a microphone associated with the user device based on the proximity of the user; and causing, by executing instructions with the processor circuitry, an amplifier of the user device to apply the gain to the audio signal.

(254) Example 34 includes the method of example 33, further including detecting a face of the user in the image; identifying a facial landmark associated with the face in the image; and determining the proximity of the user based on the facial landmark.

(255) Example 35 includes the method of examples 33 or 34, wherein the facial landmark includes a first facial landmark and a second facial landmark and further including determining a distance between the first facial landmark and the second facial landmark based on first pixel coordinate data associated with the first facial landmark and second pixel coordinate data associated with the second facial landmark; and determining the proximity of the user based on the distance between the first facial landmark and the second facial landmark.

(256) Example 36 includes the method of any of examples 33-35, wherein the first facial landmark includes an eye point associated with a first eye of the user and the second facial landmark includes an eye point associated with the second facial landmark.

(257) Example 37 includes the method of any of examples 33-36, wherein the face is a first face, the user is a first use, and further including detecting a second face in the image, the second face associated with a second user; generating a first bounding box for the first face and a second bounding box for the second face; performing a comparison of an area of the first bounding box to an area of the second bounding box; and selecting the first face for determining the proximity based on the comparison.

(258) Example 38 includes the method of any of examples 33-37, further including detecting a third face in the image, the third face associated with a third user; generating a third bounding box for the third face; assigning a first confidence level to the first bounding box, a second confidence level to the second bounding box, and a third confidence level to the third bounding box; and refraining from selecting the third face for determining the proximity based on the third confidence level.

(259) Example 39 includes the method of any of examples 33-38, further including determining a signal-to-noise ratio of the audio signal; performing a comparison of the signal-to-noise ratio to a threshold; and determining the amount of gain to be applied to the audio signal based on the comparison.

(260) Example 40 includes the method of any of examples 33-39, further including causing the amplifier to apply the gain to a voice band of the audio signal.

(261) Example 41 includes the method of any of examples 33-40, wherein the image includes a video frame.

(262) Example 42 includes an electronic device including interface circuitry to access an input

image; and processor circuitry including one or more of at least one of a central processing unit, a graphic processing unit or a digital signal processor, the at least one of the central processing unit, the graphic processing unit or the digital signal processor having control circuitry to control data movement within the processor circuitry, arithmetic and logic circuitry to perform one or more first operations corresponding to instructions, and one or more registers to store a result of the one or more first operations, the instructions in the apparatus; a Field Programmable Gate Array (FPGA), the FPGA including logic gate circuitry, a plurality of configurable interconnections, and storage circuitry, the logic gate circuitry and interconnections to perform one or more second operations, the storage circuitry to store a result of the one or more second operations; or Application Specific Integrate Circuitry (ASIC) including logic gate circuitry to perform one or more third operations; the processor circuitry to perform at least one of the first operations, the second operations, or the third operations to instantiate user proximity detection circuitry to determine a proximity of a user to the electronic device based on the input image; gain determining circuitry to determine an amount of gain to be applied to an audio signal generated by a microphone associated with the user device based on the proximity of the user; and gain control circuitry to cause an amplifier of the user device to apply the gain to the audio signal.

(263) Example 43 includes the electronic device of example 42, wherein the processor circuitry is to perform at least one of the first operations, the second operations, or the third operations to instantiate face detection circuitry to detect a face of the user in the input image; and face landmark detection circuitry to identify a facial landmark associated with the face in the input image.

(264) Example 44 includes the electronic device of examples 42 or 43, wherein the processor circuitry is to perform at least one of the first operations, the second operations, or the third operations to instantiate the user proximity circuitry to determine the proximity of the user based on the facial landmark.

(265) Example 45 includes the electronic user device of any of examples 42-44, wherein the processor circuitry is to perform at least one of the first operations, the second operations, or the third operations to instantiate the user proximity circuitry to determine a distance between the first facial landmark and the second facial landmark based on first pixel coordinate data associated with the first facial landmark and second pixel coordinate data associated with the second facial landmark; and determine the proximity of the user based on the distance between the first facial landmark and the second facial landmark.

(266) Example 46 includes the electronic user device of any of examples 42-45, wherein the processor circuitry is to perform at least one of the first operations, the second operations, or the third operations to instantiate the gain determining circuitry to determine the amount of gain to apply to a voice band of the audio signal.

(267) Example 47 includes the electronic user device of any of examples 42-46, wherein the input image includes a video frame wherein the processor circuitry is to perform at least one of the first operations, the second operations, or the third operations to instantiate video preprocessing circuitry to reduce a sampling rate of a video signal and extract the video frame from the video signal having the reduced sampling rate.

(268) Although certain example methods, apparatus and articles of manufacture have been disclosed herein, the scope of coverage of this patent is not limited thereto. On the contrary, this patent covers all methods, apparatus and articles of manufacture fairly falling within the scope of the claims of this patent.

(269) The following claims are hereby incorporated into this Detailed Description by this reference, with each claim standing on its own as a separate embodiment of the present disclosure.

Claims

1. An apparatus comprising: at least one memory; machine-readable instructions; and at least one processor circuit to execute the machine-readable instructions to: determine a first proximity value representing a first distance of a user to a user device based on a first image generated via one or more cameras associated with the user device, the first image corresponding to a first time; determine a second proximity value representing a second distance of the user to the user device based on a second image generated via the one or more cameras, the second image corresponding to a second time after the first time; apply a first filtering parameter to the second proximity value to generate a weighted second proximity value; apply a second filtering parameter to the first proximity value to generate a weighted first proximity value, a value of the second filtering parameter adjusted based on the first filtering parameter; determine a filtered proximity value corresponding to the second time based on (a) the weighted first proximity value and (b) the weighted second proximity value; determine an amount of gain to be applied to an audio signal generated by a microphone associated with the user device based on the filtered proximity value; and cause an amplifier of the user device to apply the gain to the audio signal.
2. The apparatus of claim 1, wherein one or more of the at least one processor circuit is to: detect a face of the user in the first image; identify a facial landmark associated with the face in the first image; and determine the first proximity value based on the facial landmark.
3. The apparatus of claim 2, wherein the facial landmark includes a first facial landmark and a second facial landmark and one or more of the at least one processor circuit is to: determine a distance between the first facial landmark and the second facial landmark based on first pixel coordinate data associated with the first facial landmark and second pixel coordinate data associated with the second facial landmark; and determine the first proximity value based on the distance between the first facial landmark and the second facial landmark.
4. The apparatus of claim 3, wherein the first facial landmark includes a first eye point associated with a first eye of the user and the second facial landmark includes a second eye point associated with the second facial landmark.
5. The apparatus of claim 2, wherein the face is a first face, the user is a first user, and one or more of the at least one processor circuit is to: detect a second face in the first image, the second face associated with a second user; generate a first bounding box for the first face and a second bounding box for the second face; perform a comparison of a first area of the first bounding box to a second area of the second bounding box; and select the first face for determining the first proximity value based on the comparison.
6. The apparatus of claim 5, wherein one or more of the at least one processor circuit is to: detect a third face in the first image, the third face associated with a third user; generate a third bounding box for the third face; assign a first confidence level to the first bounding box, a second confidence level to the second bounding box, and a third confidence level to the third bounding box; and refrain from selecting the third face for determining the first proximity value based on the third confidence level.
7. The apparatus of claim 1, wherein one or more of the at least one processor circuit is to: determine a signal-to-noise ratio of the audio signal; perform a comparison of the signal-to-noise ratio to a threshold; and determine the amount of the gain to be applied to the audio signal based on the comparison.
8. The apparatus of claim 1, wherein one or more of the at least one processor circuit is to cause the amplifier to apply the gain to a voice band of the audio signal.
9. The apparatus of claim 8, wherein one or more of the at least one processor circuit is to: filter the audio signal to (a) permit first frequencies associated with the voice band and (b) remove second frequencies associated with ambient noise; and cause the amplifier to apply the gain to the filtered audio signal.
10. An apparatus comprising: means for detecting a face of a user in a first video frame

corresponding to a first time and in a second video frame corresponding to a second time after the first time, the first video frame and the second video frame associated with a video stream generated by a camera, the camera associated with a user device; means for identifying first facial landmarks in the face in the first video frame and second facial landmarks in the face in the second video frame; means for determining proximity to: determine a first proximity value representing a first distance of the user relative to the camera based on the first facial landmarks; determine a second proximity value representing a second distance of the user relative to the camera based on the second facial landmarks; apply a first filtering parameter to the second proximity value to generate a weighted second proximity value; apply a second filtering parameter to the first proximity value to generate a weighted first proximity value, a value of the second filtering parameter adjusted based on the first filtering parameter; and determine a filtered proximity value corresponding to the second time based on (a) the weighted first proximity value and (b) the weighted second proximity value; means for determining a gain to be applied to an audio signal based on the filtered proximity value, the audio signal to be generated by a microphone associated with the user; means for filtering the audio signal to (a) permit first frequencies associated with a voice band and (b) remove second frequencies associated with ambient noise; and means for controlling to cause an amplifier of the user device to apply the gain to the filtered audio signal.

11. The apparatus of claim 10, wherein the first facial landmarks include a third facial landmark and a fourth facial landmark, the facial landmark identifying means is to determine a distance between the third facial landmark and the fourth facial landmark, the proximity determining means to determine the first proximity value based on the distance.

12. The apparatus of claim 10, wherein the face detecting means is to generate a bounding box in response to detecting the face.

13. The apparatus of claim 10, further including means for calculating a signal-to-noise ratio of the audio signal, the gain determining means to determine the gain to be applied based on the signal-to-noise ratio.

14. At least one non-transitory computer readable storage medium comprising machine-readable instructions to cause at least one processor circuit to at least: determine a first proximity value representing a first distance of a user to a user device based on a first image generated via one or more cameras, the first image associated with a first time; determine a second proximity value representing a second distance of the user to the user device based on a second image generated via the one or more cameras, the second image associated with a second time, the second time after the first time; apply a first filtering parameter to the second proximity value to generate a weighted second proximity value; apply a second filtering parameter to the first proximity value to generate a weighted first proximity value, a value of the second filtering parameter adjusted based on the first filtering parameter; determine a filtered proximity value corresponding to the second time based on the weighted first proximity value and the weighted second proximity value; determine an amount of gain to be applied to an audio signal generated by a microphone associated with the user device based on the filtered proximity value; filter the audio signal to (a) permit first frequencies associated with a voice band and (b) remove second frequencies associated with ambient noise; and cause an amplifier of the user device to apply the gain to the filtered audio signal.

15. The at least one non-transitory computer readable storage medium of claim 14, wherein the machine-readable instructions are to cause one or more of the at least one processor circuit to: detect a face of the user in the first image; identify a facial landmark associated with the face in the first image; and determine the first proximity value of the user based on the facial landmark.

16. The at least one non-transitory computer readable storage medium of claim 15, wherein the facial landmark includes a first facial landmark and a second facial landmark and the machine-readable instructions are to cause one or more of the at least one processor circuit to: determine a distance between the first facial landmark and the second facial landmark based on first pixel coordinate data associated with the first facial landmark and second pixel coordinate data

associated with the second facial landmark; and determine the first proximity value of the user based on the distance between the first facial landmark and the second facial landmark.

17. The at least one non-transitory computer readable storage medium of claim 16, wherein the first facial landmark includes a first eye point associated with a first eye of the user and the second facial landmark includes a second eye point associated with the second facial landmark.

18. The at least one non-transitory computer readable storage medium of claim 15, wherein the face is a first face, the user is a first user, and the machine-readable instructions are to cause one or more of the at least one processor circuit to: detect a second face in the first image, the second face associated with a second user; generate a first bounding box for the first face and a second bounding box for the second face; perform a comparison of a first area of the first bounding box to a second area of the second bounding box; and select the first face for determining the first proximity value based on the comparison.

19. The at least one non-transitory computer readable storage medium of claim 18, wherein the machine-readable instructions are to cause one or more of the at least one processor circuit to: detect a third face in the first image, the third face associated with a third user; generate a third bounding box for the third face; assign a first confidence level to the first bounding box, a second confidence level to the second bounding box, and a third confidence level to the third bounding box; and refrain from selecting the third face for determining the first proximity value based on the third confidence level.

20. The at least one non-transitory computer readable storage medium of claim 14, wherein the machine-readable instructions are to cause one or more of the at least one processor circuit to: determine a signal-to-noise ratio of the audio signal; perform a comparison of the signal-to-noise ratio to a threshold; and determine the amount of the gain to be applied to the filtered audio signal based on the comparison.
