

# US Patent & Trademark Office

## Patent Public Search | Text View

United States Patent  
Kind Code  
Date of Patent  
Inventor(s)

12413253  
B2  
September 09, 2025  
Shen; Zhi et al.

### Bridge combiners and multiplexers

#### Abstract

In some embodiments, an architecture can include a first group of filters each configured to support a band such that a first frequency range covers the respective bands, and a second group of one or more filters each configured to support a band such that a second frequency range covers the respective one or more bands. Each filter of the first group can be configured to provide an impedance at or near a short circuit impedance for a signal in each band of the second group, and each filter of the second group can be configured to provide an impedance at or near a short circuit impedance for a signal in each band of the first group. The filters of the first and second groups can be implemented as one or more multiplexers. The architecture can further include a coupling circuit having a common node and configured to couple the common node to the one or more multiplexers through a first path and a second path. The coupling circuit can be further configured such that the impedance provided by each filter of the first group for the signal in each band of the second group results in the signal being sufficiently excluded from the first path, and such that the impedance provided by each filter of the second group for the signal in each band of the first group results in the signal being sufficiently excluded from the second path.

**Inventors:** Shen; Zhi (Aliso Viejo, CA), Chen; Li (Irvine, CA), Domino; William J. (Yorba Linda, CA), Wloczynski; Stephane Richard Marie (Irvine, CA), Zhang; Xiao (Irvine, CA)

**Applicant:** SKYWORKS SOLUTIONS, INC. (Irvine, CA)

**Family ID:** 77920938

**Assignee:** Skyworks Solutions, Inc. (Irvine, CA)

**Appl. No.:** 18/111872

**Filed:** February 20, 2023

#### Prior Publication Data

**Document Identifier**  
US 20240007133 A1

**Publication Date**  
Jan. 04, 2024

## Related U.S. Application Data

continuation parent-doc US 17222823 20210405 US 11588506 child-doc US 18111872  
us-provisional-application US 63005421 20200405  
us-provisional-application US 63005424 20200405  
us-provisional-application US 63005425 20200405  
us-provisional-application US 63005426 20200405  
us-provisional-application US 63005427 20200405

---

## Publication Classification

**Int. Cl.:** **H04B1/00** (20060101); **H03H1/00** (20060101); **H03H3/08** (20060101); **H03H7/46** (20060101); **H04B1/18** (20060101); **H04B1/40** (20150101); **H04W72/23** (20230101)

**U.S. Cl.:**

**CPC** **H04B1/006** (20130101); **H03H1/0007** (20130101); **H03H3/08** (20130101); **H03H7/46** (20130101); **H04B1/0078** (20130101); **H04B1/18** (20130101); **H04B1/40** (20130101); **H04W72/23** (20230101); H03H2001/0014 (20130101); H03H2001/0092 (20130101)

## Field of Classification Search

**CPC:** H04B (1/006); H04B (1/0078); H04B (1/18); H04B (1/40); H04W (72/23); H04H (1/0007); H04H (3/08); H04H (7/46); H03H (1/0007); H03H (3/08); H03H (7/46)

---

## References Cited

### U.S. PATENT DOCUMENTS

| Patent No.   | Issued Date | Patentee Name     | U.S. Cl. | CPC       |
|--------------|-------------|-------------------|----------|-----------|
| 2015/0295596 | 12/2014     | Wluczysiak et al. | N/A      | N/A       |
| 2016/0065255 | 12/2015     | Domino            | N/A      | N/A       |
| 2019/0268027 | 12/2018     | Wluczysiak        | N/A      | H04L 5/08 |

### FOREIGN PATENT DOCUMENTS

| Patent No.      | Application Date | Country | CPC |
|-----------------|------------------|---------|-----|
| 10-2015-0118052 | 12/2014          | KR      | N/A |
| 10-2017-0048434 | 12/2016          | KR      | N/A |

---

*Primary Examiner:* Abelson; Ronald B

*Attorney, Agent or Firm:* Chang & Hale LLP

---

## Background/Summary

CROSS-REFERENCE TO RELATED APPLICATION(S) (1) This application is a continuation of U.S. application Ser. No. 17/222,823 filed Apr. 5, 2021, entitled ARCHITECTURES HAVING BRIDGE COMBINERS AND MULTIPLEXERS, which claims priority to U.S. Provisional

Application Nos. 63/005,424 filed Apr. 5, 2020, entitled ARCHITECTURES HAVING BRIDGE COMBINERS AND MULTIPLEXERS, 63/005,425 filed Apr. 5, 2020, entitled BRIDGE COMBINERS, PHASE SHIFTERS AND/OR RESONATORS FOR WIRELESS APPLICATIONS, 63/005,426 filed Apr. 5, 2020, entitled SWITCHING CIRCUITS FOR BRIDGE COMBINERS, 63/005,427 filed Apr. 5, 2020, entitled CIRCUITS, DEVICES AND METHODS RELATED TO HALF-BRIDGE COMBINERS, and 63/005,421 filed Apr. 5, 2020, entitled BRIDGE COMBINERS AND FILTERS FOR RADIO-FREQUENCY APPLICATIONS, the disclosure of each of which is hereby expressly incorporated by reference herein in its entirety.

## BACKGROUND

### Field

(1) The present disclosure relates to bridge combiners and related circuits for radio-frequency (RF) applications.

### Description of the Related Art

(2) In radio-frequency (RF) applications, a signal having a plurality of frequency components can be routed from a common path to separate paths. In reverse, a plurality of signals can be routed from respective paths to a common path. Either or both of such functionalities allow, for example, carrier aggregation of a plurality of RF signals.

## SUMMARY

(3) In accordance with some implementations, the present disclosure relates to a radio-frequency architecture that includes a first group of filters each configured to support a band such that a first frequency range covers the respective bands, and a second group of one or more filters each configured to support a band such that a second frequency range covers the respective one or more bands. Each filter of the first group is configured to provide an impedance at or near a short circuit impedance for a signal in each band of the second group, and each filter of the second group is configured to provide an impedance at or near a short circuit impedance for a signal in each band of the first group. The filters of the first and second groups are implemented as one or more multiplexers. The radio-frequency architecture further includes a coupling circuit having a common node and configured to couple the common node to the one or more multiplexers through a first path and a second path. The coupling circuit is further configured such that the impedance provided by each filter of the first group for the signal in each band of the second group results in the signal being sufficiently excluded from the first path, and such that the impedance provided by each filter of the second group for the signal in each band of the first group results in the signal being sufficiently excluded from the second path.

(4) In some embodiments, the one or more multiplexers can include a multiplexer that includes the first group of filters but not the second group of one or more filters. In some embodiments, the one or more multiplexers can include a multiplexer that includes the first group of filters and the second group of one or more filters.

(5) In some embodiments, the first path can present a first impedance  $Z_1$  to the coupling circuit, and the second path can present a second impedance  $Z_2$  to the coupling circuit, such that complex part of  $Z_1$  is a conjugate of complex part of  $Z_2$ .

(6) In some implementations, the present disclosure relates to a packaged module that includes a packaging substrate configured to receive a plurality of components, and a radio-frequency circuit implemented on the packaging substrate. The radio-frequency circuit includes a first group of filters each configured to support a band such that a first frequency range covers the respective bands, and a second group of one or more filters each configured to support a band such that a second frequency range covers the respective one or more bands. Each filter of the first group is configured to provide an impedance at or near a short circuit impedance for a signal in each band of the second group, and each filter of the second group is configured to provide an impedance at or near a short circuit impedance for a signal in each band of the first group. The filters of the first and

second groups are implemented as one or more multiplexers. The radio-frequency circuit further includes a coupling circuit having a common node and configured to couple the common node to the one or more multiplexers through a first path and a second path. The coupling circuit is further configured such that the impedance provided by each filter of the first group for the signal in each band of the second group results in the signal being sufficiently excluded from the first path, and such that the impedance provided by each filter of the second group for the signal in each band of the first group results in the signal being sufficiently excluded from the second path.

(7) In some implementations, the present disclosure relates to a wireless device that includes one or more antennas, and a front-end module in communication with the one or more antennas. The front-end module includes a radio-frequency circuit having a first group of filters each configured to support a band such that a first frequency range covers the respective bands, and a second group of one or more filters each configured to support a band such that a second frequency range covers the respective one or more bands. Each filter of the first group is configured to provide an impedance at or near a short circuit impedance for a signal in each band of the second group, and each filter of the second group configured to provide an impedance at or near a short circuit impedance for a signal in each band of the first group. The filters of the first and second groups are implemented as one or more multiplexers. The radio-frequency circuit further includes a coupling circuit having a common node and configured to couple the common node to the one or more multiplexers through a first path and a second path. The coupling circuit is further configured such that the impedance provided by each filter of the first group for the signal in each band of the second group results in the signal being sufficiently excluded from the first path, and such that the impedance provided by each filter of the second group for the signal in each band of the first group results in the signal being sufficiently excluded from the second path. The wireless device further includes a receiver in communication with the front-end module and configured to process one or more signals associated with the first and second group.

(8) For purposes of summarizing the disclosure, certain aspects, advantages and novel features of the inventions have been described herein. It is to be understood that not necessarily all such advantages may be achieved in accordance with any particular embodiment of the invention. Thus, the invention may be embodied or carried out in a manner that achieves or optimizes one advantage or group of advantages as taught herein without necessarily achieving other advantages as may be taught or suggested herein.

---

## Description

### BRIEF DESCRIPTION OF THE DRAWINGS

(1) FIG. 1 depicts an architecture that can be implemented utilizing a coupling circuit having one or more features as described herein.

(2) FIG. 2 shows a normalized Smith chart that provides a visual representation of an impedance.

(3) FIGS. 3A and 3B depict the example impedances of FIG. 1 on the normalized Smith chart of FIG. 2.

(4) FIG. 4 shows an architecture that can be implemented similar to the example of FIG. 1, where a first group of filters includes three filters for supporting three bands, and a second group of filters includes two filters for supporting two bands.

(5) FIG. 5 shows an architecture where a first group of filters includes two filters for supporting two bands, and a second group of filters includes one filter for supporting one band.

(6) FIG. 6 shows that in some embodiments, a filter in a first group of filter(s) and a filter in a second group of filter(s) can be configured such that first and second impedances provided for first and second paths of a coupling circuit have complex parts that are conjugates, or approximately conjugates, of each other.

(7) FIG. 7 shows an architecture that can be implemented similar to the examples of FIGS. 4 and 5, and with one or more phase shifters.

(8) FIG. 8 shows an architecture that utilizes a plurality of coupling circuits with a plurality of groups of filters, where at least one group includes a plurality of filters for supporting different bands.

(9) FIG. 9 shows an example of an architecture where a common signal node of a coupling circuit is coupled to an antenna, and first and second paths from the coupling circuit are coupled to one or more multiplexers.

(10) FIG. 10 shows another example of an architecture where a common signal node of a coupling circuit is coupled to an antenna, and first and second paths from the coupling circuit are coupled to one or more multiplexers.

(11) FIG. 11 shows yet another example of an architecture where a common signal node of a coupling circuit is coupled to an antenna, and first and second paths from the coupling circuit are coupled to one or more multiplexers.

(12) FIG. 12 shows an architecture that can be a more specific example of the architecture of FIG. 9.

(13) FIG. 13 shows an architecture that can be another more specific example of the architecture of FIG. 9.

(14) FIG. 14 shows an architecture that can be a more specific example of the architecture of FIG. 10.

(15) FIG. 15 shows an architecture that can be another more specific example of the architecture of FIG. 10.

(16) FIG. 16 shows that in some embodiments, an architecture having one or more features as described herein can include a coupling circuit that includes two LC circuits that couple an input node to ground.

(17) FIG. 17A shows that in some embodiments, an architecture having one or more features as described herein can include a coupling circuit having a resonator.

(18) FIG. 17B shows that in some embodiments, the resonator of the coupling circuit of FIG. 17A can include an acoustic resonator.

(19) FIGS. 18A and 18B show that in some embodiments, an architecture having one or more features as described herein can include a coupling circuit having a half bridge configuration.

(20) FIG. 19A shows an example architecture that includes the half-bridge coupling circuit of FIG. 18A.

(21) FIG. 19B shows an example architecture that includes the half-bridge coupling circuit of FIG. 18B.

(22) FIG. 20 shows an architecture that is a more specific example of the architecture of FIG. 4, utilizing the coupling circuit of FIG. 16.

(23) FIG. 21 shows scans of impedances for the example architecture of FIG. 20.

(24) FIG. 22 shows an example of how phase shifting functionality can be utilized in an architecture that includes a coupling circuit as described herein.

(25) FIG. 23 shows another example of how phase shifting functionality can be utilized in an architecture that includes a coupling circuit as described herein.

(26) FIG. 24 shows an architecture that can be a more specific example of the architecture of FIG. 8, where a plurality of coupling circuits can be utilized.

(27) FIG. 25 show an architecture that can be a more specific example of the architectures of FIGS. 9 and 12.

(28) FIG. 26 show an architecture that can be a more specific example of the architectures of FIGS. 9 and 13.

(29) FIG. 27 shows an architecture having switching functionalities described herein in reference to FIGS. 11, 13 and 14.

(30) FIG. **28** shows an example architecture that includes switching functionalities to allow a plurality of coupling circuits to share a common antenna, and also to share a common group of filters.

(31) FIG. **29** shows an architecture that can be a more specific example of the architecture of FIG. **19A**.

(32) FIG. **30** shows an example architecture that utilizes a number of features described herein.

(33) FIG. **31** shows that in some embodiments, a radio-frequency (RF) module can include one or more features as described herein.

(34) FIG. **32** depicts an example wireless device having one or more advantageous features described herein.

#### DETAILED DESCRIPTION OF SOME EMBODIMENTS

(35) The headings provided herein, if any, are for convenience only and do not necessarily affect the scope or meaning of the claimed invention.

(36) Among others, PCT Publication No. WO2016/033427 (International Application No. PCT/US2015/047378 titled DOMINO CIRCUIT AND RELATED ARCHITECTURES AND METHODS FOR CARRIER AGGREGATION) discloses circuits, architectures and methods related to coupling circuits that can be utilized for carrier aggregation operations. For the purpose of description, such a coupling circuit can also be referred to as a bridge circuit, a Domino circuit, or a Domino bridge circuit.

(37) FIG. **1** depicts an architecture **700** that can be implemented utilizing a coupling circuit **100** having one or more features as described herein. In some embodiments, such a coupling circuit can include one or more of the examples disclosed in the above-mentioned PCT Publication No. WO2016/033427.

(38) In the example architecture **700** of FIG. **1**, the coupling circuit **100** is shown to couple a common signal node **102** to a first signal processing component **701** (Band A component such as Band A filter) and a second signal processing component **702** (Band B component such as Band B filter). Configured in the foregoing manner, impedance  $Z_{in1}$  presented to the coupling circuit **100** can be equal to (or approximately equal to) a load impedance (e.g., 50 Ohm) of the Band A filter for a Band A signal, and be equal to (or approximately equal to) zero for a Band B signal. Similarly, impedance  $Z_{in2}$  presented to the coupling circuit **100** can be equal to (or approximately equal to) a load impedance (e.g., 50 Ohm) of the Band B filter for the Band B signal, and be equal to (or approximately equal to) zero for the Band A signal.

(39) As disclosed in PCT Publication No. WO2016/033427, the coupling circuit **100** can be configured to couple the foregoing first and second signal paths associated with the Band A and Band B filters, such that the approximately zero impedance presented by the first signal path (with Band A filter) to the signal in the second frequency band (Band B signal) results in the signal in the second frequency band (Band B signal) being substantially excluded from the first signal path, and such that the approximately zero impedance presented by the second signal path (with Band B filter) to the signal in the first frequency band (Band A signal) results in the signal in the first frequency band (Band A signal) being substantially excluded from the second signal path.

(40) In the example of FIG. **1**, as well as some of the other examples described herein, impedances presented by respective filters are depicted in the context of a flow of signal(s) from a common signal node (**102** in FIG. **1**) to either or both of first and second signal paths associated with first (Band A) and second (Band B) filters. However, and as disclosed in PCT Publication No. WO2016/033427, it will be understood that one or more features of the present disclosure can also be implemented in a configuration where a flow of signal(s) is in reverse relative to the foregoing configuration.

(41) FIG. **2** shows a normalized Smith chart **710** that provides a visual representation of an impedance  $Z=R+jX$ , where  $R$  is resistance and  $X$  is reactance. It is noted that for a pure capacitance, reactance  $X$  is equal to  $X_{sub.C}=-1/\omega C$  where  $\omega=2\pi f$ , and for a pure inductance,

reactance  $X$  is equal to  $X_{\text{sub.L}} = \omega L$ . Thus for a pure resistance,  $Z = R$ ; for a pure capacitance,  $Z = jX_{\text{sub.C}} = -j/\omega C$ , and for a pure inductance,  $Z = jX_{\text{sub.L}} = j\omega L$ . It is also noted that an impedance in the region above the horizontal line of the Smith chart **710** has a positive imaginary value and represents an inductive impedance, and an impedance in the region below the horizontal line of the Smith chart **710** has a negative imaginary value and represents a capacitive impedance.

(42) Referring to FIG. 2, the foregoing horizontal line segment is shown to bisect the outermost circle, with the left end of the horizontal line segment representing a short circuit ( $Z=0$ ) state, and the right end of the horizontal line segment representing an open circuit ( $Z=\infty$ ) state. The mid-point of the horizontal line segment (and thus the center of the outermost circle) represents a matched impedance state. Such a matched impedance state has a value of  $Z=1$  in the normalized representation. In an un-normalized representation, such a matched impedance state can have a value of, for example,  $Z=50$  ohms.

(43) In the normalized Smith chart of FIG. 2, solid-line circles are constant-resistance circles **712** at example normalized values. For example, the outermost circle referenced above has a constant-resistance value of 0, and the successively smaller circles have constant-resistance values of 0.2, 0.5, 1, 2, 3, 4, 5 and 10. All of such constant-resistance circles share their right-most points at the right end of the above-referenced horizontal line segment (open circuit state).

(44) In the normalized Smith chart **710** of FIG. 2, dash-line arcs are constant-reactance arcs **714** at example normalized values. For example, the above-referenced horizontal line segment (an arc of an infinite-radius circle) has a constant-reactance value of 0, and the successively smaller-radius-circle arcs have constant-reactance values of 0.2, 0.5, 1, 2, 3, 4, 5 and 10. Such constant-reactance arcs can be provided above and below the horizontal line segment. For the arcs above the horizontal line segment, the arcs share their lower-most points at the right end of the horizontal line segment (open circuit state). For the arcs below the horizontal line segment, the arcs share their upper-most points at the right end of the horizontal line segment (open circuit state).

(45) FIGS. 3A and 3B depict the example impedances  $Z_{\text{in1}}$  and  $Z_{\text{in2}}$  of FIG. 1, respectively, on the normalized Smith chart of FIG. 2. More particularly, FIG. 3A shows  $Z_{\text{in1}}$  having an impedance region at or about the matched impedance state ( $Z=1+j0$ ) that includes impedance values associated with a frequency range of the first frequency band (Band A), and an impedance region at or about the short circuit state ( $Z=0+j0$ ) that includes impedance values associated with a frequency range of the second frequency band (Band B). Similarly, FIG. 3B shows  $Z_{\text{in2}}$  having an impedance region at or about the matched impedance state ( $Z=1+j0$ ) that includes impedance values associated with the frequency range of the second frequency band (Band B), and an impedance region at or about the short circuit state ( $Z=0+j0$ ) that includes impedance values associated with the frequency range of the first frequency band (Band A).

(46) Referring to the example of FIGS. 1 and 3, it is noted that the impedance states for  $Z_{\text{in1}}$  and  $Z_{\text{in2}}$  of FIGS. 3A and 3B can be considered to be ideal impedance states. However, in some embodiments, the Band A filter of the example of FIG. 1 can be a part of a group having a plurality of filters for supporting a plurality of respective bands, with the filters of the group being connectable to the first of two paths (e.g., the upper path associated with  $Z_{\text{in1}}$ ) associated with the coupling circuit **100**. Similarly, the Band B filter of the example of FIG. 1 can be a part of a group having a plurality of filters for supporting a plurality of respective bands, with the filters of the group being connectable to the second of two paths (e.g., the lower path associated with  $Z_{\text{in2}}$ ) associated with the coupling circuit **100**.

(47) For example, FIG. 4 shows an architecture **720** that can be implemented similar to the example of FIG. 1, but where a first group of filters **721** includes three filters for supporting three bands (Band 1A, Band 1B, Band 1C), and a second group of filters **722** includes two filters for supporting two bands (Band 2A, Band 2B). In such an architecture, a coupling circuit **100** is shown to couple a common signal node **102** to the first group of filters **721** and the second group of filters **722**. Configured in the foregoing manner, impedance values for  $Z_{\text{in1}}$  are presented to the coupling

circuit **100** for a signal in the band corresponding to a selected one of the filters of the first group of filters **721** and for a signal in the band corresponding to a selected one of the filters of the second group of filters **722**. Similarly, impedance values for  $Z_{in2}$  are presented to the coupling circuit **100** for a signal in the band corresponding to the selected one of the filters of the second group of filters **722** and for a signal in the band corresponding to the selected one of the filters of the first group of filters **721**.

(48) In the example of FIG. 4, the first group of filters **721** is described as having three filters, and the second group of filters **722** is described as having two filters. It will be understood that each of the first and second groups of filters can also be implemented with different numbers of filters.

(49) In the example of FIG. 4, each of the first and second groups of filters **721**, **722** is described as having a plurality of filters. It will be understood that in some embodiments, one group can include a plurality of filters, and the other group can include a single filter.

(50) For example, FIG. 5 shows an architecture **720** where a first group of filters **721** includes two filters for supporting two bands (Band 1A, Band 1B), and a second group of filters **722** includes one filter for supporting one band (Band 2). In such an architecture, a coupling circuit **100** is shown to couple a common signal node **102** to the first group of filters **721** and the single filter of the second group **722**. Configured in the foregoing manner, impedance values for  $Z_{in1}$  are presented to the coupling circuit **100** for a signal in the band corresponding to a selected one of the filters of the first group of filters **721** and for a signal in the band corresponding to the single filter of the second group **722**. Similarly, impedance values for  $Z_{in2}$  are presented to the coupling circuit **100** for a signal in the band corresponding to the single filter of the second group **722** and for a signal in the band corresponding to the selected one of the filters of the first group of filters **721**.

(51) In the examples of FIGS. 4 and 5, a selected filter in the first group **721** and a selected filter in the second group **722** can be configured so as to provide ideal impedance states, similar to the example of FIGS. 1 and 3. However, with such a configuration where two selected filters are optimized, performance can suffer significantly when using other (non-selected) filter(s) of the first and second groups **721**, **722**.

(52) It is noted that in many applications, and especially when a group of filters involve a wide frequency range, it is impossible or difficult to achieve ideal impedance states (ideal matched impedance state and/or ideal short circuit state) for all of the filters in the group. However, in some embodiments, even if impedances  $Z_{in1}$  and  $Z_{in2}$  are not in ideal impedance states, desired or acceptable performance can be achieved if real parts of the complex impedances  $Z_{in1}$  and  $Z_{in2}$  are sufficiently close to the respective real parts of the ideal impedance states and imaginary parts of the complex impedances  $Z_{in1}$  and  $Z_{in2}$  are configured appropriately as described herein.

(53) In some embodiments, each filter in a first group of filter(s) and a second group of filter(s) can be configured such that first and second impedances provided for first and second paths of a coupling circuit have complex parts that are conjugates, or approximately conjugates, of each other. More particularly, the first impedance provided for the first path of the coupling circuit can be expressed as  $Z_{sub.1} = R_{sub.1} + jX$ , and the second impedance provided for the second path of the coupling circuit can be expressed as  $Z_{sub.2} = R_{sub.2} - jX$ , where  $-jX$  is a conjugate of  $+jX$  of  $Z_{sub.1}$ .

(54) FIG. 6 shows the foregoing complex portion-conjugated impedances in terms of the first and second impedances  $Z_{in1}$  and  $Z_{in2}$  corresponding to the example architecture **720** of FIG. 4. In the example of FIG. 4, the three filters (Band 1A, Band 1B, Band 1C) of the first group **721** can have frequency bands  $F1A < F1B < F1C$ , respectively, and the two filters (Band 2A, Band 2B) of the second group **722** can have frequency bands  $F2A < F2B$ , respectively, such that  $F1A < F1B < F1C < F2A < F2B$ .

(55) With the foregoing configurations of the filters of the first and second groups **721**, **722**, FIG. 6 depicts Smith charts for the impedances  $Z_{in1}$  and  $Z_{in1}$  of FIG. 4.

(56) Referring to FIG. 6, impedances  $Z_{in1}$  for signals in the three bands (Band 1A, Band 1B, Band



1C) of the first group **721** are shown to be in regions at or close to the matched impedance value (e.g.,  $Z=1$  in normalized Smith chart), and impedances  $Z_{in1}$  for signals in the two bands (Band **2A**, Band **2B**) of the second group **722** are shown to be in regions at or close to the short circuit value (e.g.,  $Z=0$  in normalized Smith chart). Similarly, impedances  $Z_{in2}$  for signals in the two bands (Band **2A**, Band **2B**) of the second group **722** are shown to be in regions at or close to the matched impedance value, and impedances  $Z_{in2}$  for signals in the three bands (Band **1A**, Band **1B**, Band **1C**) of the first group **721** are shown to be in regions at or close to the short circuit value.

(57) In the example of FIG. **6**, each filter is shown to provide  $Z_{in1}$  and  $Z_{in2}$  values having respective ones of real parts associated with matched impedance state ( $Z \approx 1$ ) and short circuit state ( $Z \approx 0$ ), and complex parts that are conjugates of each other. More particularly, for Band **1A**,  $Z_{in1} = R_{sub.1} + jX_{sub.1}$  (with  $R_{sub.1} \approx 1$  and  $X_{sub.1} \neq 0$ ), and  $Z_{in2} = R'_{sub.1} - jX_{sub.1}$  (with  $R'_{sub.1} \approx 0$  and  $X_{sub.1} \neq 0$ ), with  $+jX_{sub.1}$  and  $-jX_{sub.1}$  of  $Z_{in1}$  and  $Z_{in2}$  being conjugates of each other, as depicted by arrow **724a**. For Band **1B**,  $Z_{in1} = R_{sub.2} + jX_{sub.2}$  (with  $R_{sub.2} \approx 1$  and  $X_{sub.2} \approx 0$ ), and  $Z_{in2} = R'_{sub.2} - jX_{sub.2}$  (with  $R'_{sub.2} \approx 0$  and  $X_{sub.2} \approx 0$ ), with  $+jX_{sub.2}$  and  $-jX_{sub.2}$  of  $Z_{in1}$  and  $Z_{in2}$  being conjugates of each other, as depicted by arrow **724b**. For Band **1C**,  $Z_{in1} = R_{sub.3} - jX_{sub.3}$  (with  $R_{sub.3} \approx 1$  and  $X_{sub.3} \neq 0$ ), and  $Z_{in2} = R'_{sub.3} + jX_{sub.3}$  (with  $R'_{sub.3} \approx 0$  and  $X_{sub.3} \neq 0$ ), with  $-jX_{sub.3}$  and  $+jX_{sub.3}$  of  $Z_{in1}$  and  $Z_{in2}$  being conjugates of each other, as depicted by arrow **724c**.

(58) Similarly, for Band **2A**,  $Z_{in2} = R_{sub.4} + jX_{sub.4}$  (with  $R_{sub.4} \approx 1$  and  $X_{sub.4} \neq 0$ ), and  $Z_{in1} = R'_{sub.4} - jX_{sub.4}$  (with  $R'_{sub.4} \approx 0$  and  $X_{sub.4} \neq 0$ ), with  $+jX_{sub.4}$  and  $-jX_{sub.4}$  of  $Z_{in2}$  and  $Z_{in1}$  being conjugates of each other, as depicted by arrow **724d**. For Band **2A**,  $Z_{in2} = R_{sub.5} - jX_{sub.5}$  (with  $R_{sub.5} \approx 1$  and  $X_{sub.5} \neq 0$ ), and  $Z_{in1} = R'_{sub.5} + jX_{sub.5}$  (with  $R'_{sub.5} \approx 0$  and  $X_{sub.5} \neq 0$ ), with  $-jX_{sub.5}$  and  $+jX_{sub.5}$  of  $Z_{in2}$  and  $Z_{in1}$  being conjugates of each other, as depicted by arrow **724e**.

(59) It is noted that in the foregoing examples of  $Z_{in1}$  and  $Z_{in2}$  for the five bands of FIG. **6**, if  $Z_{in1}$  for a given band is capacitive (i.e., impedance is in a region below the horizontal line of the Smith chart), then  $Z_{in2}$  for the same band is inductive (i.e., impedance is in a region above the horizontal line of the Smith chart). Similarly, if  $Z_{in1}$  for a given band is inductive, then  $Z_{in2}$  for the same band is capacitive.

(60) In the example of FIGS. **4** and **6**, suppose that each filter of a given group (e.g., the first group **721**) is configured to provide the foregoing  $Z_{in1}$  and  $Z_{in2}$  impedances for the first and second paths of the coupling circuit **100**. In some embodiments, the architecture **720** can be configured such that some or all of capacitive and inductive impedances of  $Z_{in1}$  and  $Z_{in2}$  are rotated toward desirable location(s) on a Smith chart. For example, a capacitive or inductive impedance close to a short circuit state can be rotated towards such a short circuit state so as to provide an impedance equal to, or approximately equal to, the short circuit impedance. In another example, a capacitive or inductive impedance close to a matched impedance state can be rotated towards such a matched impedance state so as to provide an impedance equal to, or approximately equal to, the matched impedance.

(61) In some embodiments, the foregoing rotation of  $Z_{in1}$  and  $Z_{in2}$  impedances for the given group of filters can be implemented by, for example, configuring of another group (e.g., the second group **722**), introduction of one or more phase shifting components, or some combination thereof. Examples of such phase shifting components are described herein in greater detail.

(62) FIGS. **7-15** show examples of architectures that can be implemented utilizing one or more features described in reference to the examples of FIGS. **4-6**.

(63) For example, FIG. **7** shows an architecture **730** that can be implemented similar to the examples of FIGS. **4** and **6**, where a first group of filters **721** includes a plurality of filters, and a second group of filters **722** includes a plurality of filters. FIG. **7** shows that in some embodiments, the architecture **730** can further include a first phase shifter **103** implemented between the coupling circuit **100** and the first group of filters **721**, and a second phase shifter **105** implemented between

the coupling circuit **100** and the second group of filters **722**. Additional examples related to the architecture **730** of FIG. **7** are described herein in greater detail.

(64) In another example, FIG. **8** shows an architecture **732** that utilizes a plurality of coupling circuits **100a**, **100b** with a plurality of groups of filters, where at least one group includes a plurality of filters for supporting different bands. In the example of FIG. **8**, a first coupling circuit **100a** is shown to couple a common signal node **102** to first and second paths, with the first path including a group of one or more filters **723**, and the second path including a common signal node for a second coupling circuit **100b**. The second coupling circuit **100b** is shown to couple its common signal node to its first and second paths, with the first path including a group of one or more filters **722**, and the second path including a group of one or more filters **721**.

(65) In the example of FIG. **8**, phase shifters **103a**, **103b** are shown to be provided along the first and second paths associated with the first coupling circuit **100a**. Similarly, phase shifters **103c**, **103d** are shown to be provided along the first and second paths associated with the second coupling circuit **100b**. It will be understood that in some embodiments, some or all of such paths associated with the coupling circuits **100a**, **100b** can be implemented without phase shifter(s). Additional examples related to the architecture **732** of FIG. **8** are described herein in greater detail.

(66) In yet more examples, FIGS. **9-11** show architectures where a common signal node **102** of a coupling circuit **100** is coupled to an antenna, and first and second paths from the coupling circuit **100** are coupled to one or more multiplexers **701**. For the purpose of description, such one or more multiplexers (**701**) can include one or more groups of filters, where at least one of such group(s) includes a plurality of different band filters. It will be understood that while each path from a respective coupling circuit is shown to include a phase shifter, such a path may or may not include a phase shifter.

(67) In the example of FIG. **9**, an architecture **734** can include a switching circuit **107** implemented along a path between the coupling circuit **100** and the multiplexer(s) **701**. FIGS. **12** and **13** show more specific examples of such an architecture.

(68) In the example of FIG. **10**, an architecture **736** can include a switching circuit **109** implemented between the coupling circuit **100** and one or more antennas. FIGS. **14** and **15** show more specific examples of such an architecture.

(69) In the example of FIG. **11**, an architecture **738** can include a switching circuit **107** implemented along a path between the coupling circuit **100** and the multiplexer(s) **701**, as well as a switching circuit **109** implemented between the coupling circuit **100** and one or more antennas. Additional examples of such an architecture are described herein.

(70) FIG. **12** shows an architecture **734** that can be a more specific example of the architecture **734** of FIG. **9**. In the example of FIG. **12**, a switch **107** can be implemented between a coupling circuit **100** and a group of filters **722**, so as to allow selection of a filter among the filters within the same group **722**. For example, suppose that the group of filters **722** includes Band 2A and Band 2B filters. The switch **107** can be configured to allow the coupling circuit **100** to be coupled to either of such two filters.

(71) FIG. **13** shows an architecture **734** that can be another more specific example of the architecture **734** of FIG. **9**. In the example of FIG. **13**, a switch **107** can be implemented between a coupling circuit **100** and a plurality of groups of filters **722**, so as to allow selection of a group among the groups. For example, suppose that the architecture **734** includes three groups of filters **721**, **722**, **723**. The switch **107** can be configured to, for example, allow the coupling circuit **100** to be coupled to the group **721** or the group **722**. It will be understood that the group **723** can also be switchably coupled to the coupling circuit **100** in a similar manner.

(72) In some embodiments, the architecture **734** of FIG. **13** can include one or more switching function blocks to allow switchable selection of a filter within a given group. Similarly, in some embodiments, the architecture **734** of FIG. **12** can include one or more switching function blocks to allow switchable selection of a group among a plurality of groups. It will be understood that in

some embodiments, such filter-group selection and filter-selection (within a given group) functionalities can be achieved by an appropriately configured switching network. Examples related to such a switching network are described herein in greater detail.

(73) FIG. 14 shows an architecture 736 that can be a more specific example of the architecture 736 of FIG. 10. In the example of FIG. 14, a switch 109 can be implemented between a coupling circuit 100 and a plurality of antennas (e.g., ANT1, ANT2), so as to allow selection of an antenna to be coupled to a common signal node of the coupling circuit 100. In the example of FIG. 14, first and second paths from the coupling circuit 100 can be coupled to one or more multiplexers 701 as described herein.

(74) FIG. 15 shows an architecture 736 that can be another more specific example of the architecture 736 of FIG. 10. In the example of FIG. 15, a switch 109 can be implemented between a common antenna (ANT) and a plurality of coupling circuits (e.g., 100a, 100b). Such a configuration can allow the common antenna (ANT) to be coupled to the common signal node of either of the coupling circuits 100a, 100b. In the example of FIG. 15, each of first and second paths from each coupling circuit (100a or 100b) can be coupled to a filter, a multiplexer, another coupling circuit, a switch, etc., including the various examples described herein.

(75) FIGS. 16-18 show various examples of coupling circuits 100 that can be utilized in the various architectures as described herein. FIG. 16 shows that in some embodiments, an architecture having one or more features as described herein can include a coupling circuit 100 disclosed in PCT Publication No. WO2016/033427. More particularly, the coupling circuit 100 can include two LC circuits that couple an input node 102 to ground. The first LC circuit can include a first inductance L1 (on the input side) in series with a first capacitance C1 (on the ground side). The second LC circuit can include a second capacitance C2 (on the input side) in series with a second inductance L2 (on the ground side). A node between L1 and C1 is shown to be coupled to a first path, and a node between C2 and L2 is shown to be coupled to a second path.

(76) FIG. 17A shows that in some embodiments, an architecture having one or more features as described herein can include a coupling circuit 100 having a resonator 111. In some embodiments, such a resonator can replace a capacitance or an inductance in the coupling circuit 100 of FIG. 16. For example, the coupling circuit 100 of FIG. 17A is shown to include a resonator 111 that replaces the capacitance C2 of the coupling circuit 100 of FIG. 16. It will be understood that each of the other elements L1, C1, L2 of the coupling circuit 100 of FIG. 17A may or may not have the same value as the corresponding counterpart element (L1, C1 or L2) of the coupling circuit 100 of FIG. 16.

(77) FIG. 17B shows that in some embodiments, the resonator 111 of the coupling circuit 100 of FIG. 17A can include an acoustic resonator such as a bulk acoustic wave (BAW) resonator, any other BAW-based resonator, a surface acoustic wave (SAW) resonator (e.g., a temperature-compensated SAW (TC-SAW) resonator, a leaky SAW (LSAW) resonator, a longitudinal LSAW (LLSAW) resonator, a trapped SAW resonator), any acoustic resonator with sub-2  $\mu\text{m}$  piezoelectric layer on interface of supporting substrate, or some combination thereof. An example of an architecture having such a resonator in a coupling circuit is described herein in greater detail.

(78) FIGS. 18A and 18B show that in some embodiments, an architecture having one or more features as described herein can include a coupling circuit 100 having a half bridge configuration. As disclosed in PCT Publication No. WO2016/033427, the coupling circuit 100 of FIG. 18A can be configured to provide a 3-pole low-pass filter functionality for the path coupled to the node between L1 and C1. Examples related to an architecture having such a half-bridge coupling circuit are described herein in greater detail.

(79) Similarly, the coupling circuit 100 of FIG. 18B can be configured to provide a 3-pole high-pass filter functionality for the path coupled to the node between C2 and L2. Examples related to an architecture having such a half-bridge coupling circuit are described herein in greater detail.

(80) FIG. 19A shows an example architecture 740 that includes the half-bridge coupling circuit 100

of FIG. 18A. In the example of FIG. 19A, the coupling circuit 100 couples a common signal node 102 to a first group of filters 701 through a node between L1 and C1. The common signal node 102 is also shown to be directly coupled to a second group of filters 702.

(81) In the example of FIG. 19A, a phase shifter 103 is shown to be provided between the coupling circuit 100 and the first group of filters 701. In some embodiments, such a phase shifter can be configured to accommodate or compensate for a phase shift associated with a filter within the first group 701.

(82) FIG. 19B shows an example architecture 742 that includes the half-bridge coupling circuit 100 of FIG. 18B. In the example of FIG. 19B, the coupling circuit 100 couples a common signal node 102 to a second group of filters 702 through a node between C2 and L2. The common signal node 102 is also shown to be directly coupled to a first group of filters 701.

(83) In the example of FIG. 19A, a phase shifter 103 is shown to be provided between the coupling circuit 100 and the second group of filters 702. In some embodiments, such a phase shifter can be configured to accommodate or compensate for a phase shift associated with a filter within the second group 702.

(84) FIG. 20 shows an architecture 720 that is a more specific example of the architecture 720 of FIG. 4, utilizing the coupling circuit 100 of FIG. 16. In the example of FIG. 20, a first group of filters 721 is shown to include three low frequency band duplexers, each having respective transmit (Tx) and receive (Rx) filters, for three bands F1, F2, F3. Thus, the first group of filters 721 includes three Rx filters for F1\_Rx, F2\_Rx, F3\_Rx bands, and three Tx filters for F1\_Tx, F2\_Tx, F3\_Tx bands. Similarly, a second group of filters 722 is shown to include two high frequency band duplexers, each having respective transmit (Tx) and receive (Rx) filters, for two bands F4, F5. Thus, the second group of filters 722 includes two Rx filters for F4\_Rx, F5\_Rx bands, and two Tx filters for F4\_Tx, F5\_Tx bands. For the purpose of description of the example of FIG. 20, it will be assumed that the frequency bands F1, F2, F3, F4, F5 have successively higher frequency values (e.g., middle-frequency value in a given band), such that  $F1 < F2 < F3 < F4 < F5$ .

(85) In the example of FIG. 20, the coupling circuit 100 is shown to include a common signal node 102 that is between an inductance L1 and a capacitance C2. The common signal node 102 is shown to be coupled to an antenna 760. A first node between the inductance L1 and a capacitance C1 is shown to be coupled to the first group of filters 721, so as to be presented with a first impedance Zin1. A second node between the capacitance C2 and an inductance L2 is shown to be coupled to the second group of filters 722, so as to be presented with a second impedance Zin2. A node between the capacitance C1 and the inductance L2 is shown to be coupled to a ground.

(86) Referring to the example of FIG. 20, suppose that a receive operation involves a signal being received through the antenna 760, and a selected Rx filter in each of the first and second groups 721, 722 is coupled to the coupling circuit 100 for carrier aggregation. In such an example context, each of such selected filters can be configured such that impedances Zin1 and Zin2 associated with the coupling circuit 100 are as described herein in reference to FIGS. 4 and 6. Accordingly, FIG. 21 shows scans of Zin1 and Zin2 impedances for the example architecture 720 of FIG. 20, showing various complex part-conjugate nature of Zin1 and Zin2 for each band.

(87) FIGS. 22 and 23 show examples of how phase shifting functionality can be utilized in architectures that include a coupling circuit as described herein. For example, FIG. 22 shows an architecture 730 that is similar to the architecture 720 of FIG. 20, but in which one or more phase shifters can be utilized to better isolate a group of bands from one or more other groups of bands.

(88) In the example of FIG. 22, a first group of filters 721 is shown to include three low frequency band duplexers, and a second group of filters 722 is shown to include two high frequency band duplexers, similar to the example of FIG. 20. For such groups of filters (e.g., low frequency band filters for bands F1, F2, F3, and high frequency band filter for bands F4, F5), impedances Zin1 and Zin2 can be similar to the example of FIGS. 20 and 21.

(89) In the example of FIG. 22, a first phase shifter 103 can be implemented between the coupling

circuit **100** and the first group of filters **721**, and a second phase shifter **105** can be implemented between the coupling circuit **100** and the second group of filters **722**. Such first and second phase shifters can be configured to provide improved isolation between a third group of filters (e.g., mid frequency bands) and each of the first and second groups **721**, **722**. For example, the phase shifter **103** can provide a shift in phase, such that an impedance  $Z_{in3}$  after the phase shifter **103** is approximately an open circuit impedance for a mid frequency band signal, and a capacitive impedance for a high frequency band signal. The phase shifter **105** can provide a shift in phase, such that an impedance  $Z_{in4}$  after the phase shifter **105** is approximately an open circuit impedance for the mid frequency band signal, and an inductive impedance for a low frequency band signal. It is noted that the foregoing phase shifting configuration minimizes or reduces mutual loading between the mid frequency band and the high frequency band.

(90) In another example, FIG. **23** shows an architecture **730** that is similar to the architecture **730** of FIG. **22**, but in which phase shifting functionality can be implemented to be band-specific for at least some of the bands supported by first and second groups of filters **721**, **722**. In some embodiments, phase shifting elements **770** such as transmission lines, L/C components and/or resonators can be configured for band-specific implementations. In some embodiments, such band-specific phase shifting functionality can result in improved performance of the coupling circuit **100**.

(91) For example, for the first group of filters **721** in the architecture **730** of FIG. **23**, an inductance element and a transmission line can be configured and implemented for the Tx and Rx filters of the first band (F1), transmission lines can be configured and implemented for both of the Tx and Rx filters of the second band (F1), and a transmission line and an inductance element can be configured and implemented for the Tx and Rx filters of the third band (F3).

(92) For the second group of filters **722** in the architecture **730** of FIG. **23**, an inductance element and a transmission line can be configured and implemented for the Tx and Rx filters of the first band (F4), and a transmission line and a resonator can be configured and implemented for the Tx and Rx filters of the second band (F5).

(93) FIG. **23** also shows that in some embodiments, a phase shifting element, such as a resonator, can be implemented as a part of a coupling circuit. For example, the coupling circuit **100** is shown to include a resonator **111** implemented to replace a capacitance (e.g.,  $C1$  in FIG. **22**). In some embodiments, the resonator **111** of the coupling circuit **100** and the resonator associated with the band-specific phase shifting elements **770** can be configured to function operatively to provide improved functionality of the coupling circuit.

(94) In some embodiments, each of the foregoing resonators can be implemented as, for example, an acoustic resonator such as a bulk acoustic wave (BAW) resonator or a surface acoustic wave (SAW) resonator (e.g., a temperature-compensated (TC) SAW resonator).

(95) FIG. **24** shows an architecture **732** that can be a more specific example of the architecture **732** of FIG. **8**, where a plurality of coupling circuits can be utilized. In the example of FIG. **24**, a first group of filters **721** is shown to include one low frequency band duplexer, a second group of filters **722** is shown to include two mid frequency band duplexers, and a third group of filters **723** is shown to include two high frequency band duplexers.

(96) Referring to FIG. **24**, the architecture **732** is shown to include a first coupling circuit **100a** having a common signal node **102** coupled to an antenna **760**, a first path coupled to a common signal node (between  $L3$  and  $C4$ ) of a second coupling circuit **100b** (from a node between  $L1$  and  $C1$ ), and a second path coupled to the third group of filters **723** (from a node between  $C2$  and  $L2$ ). The second coupling circuit **100b** is shown to have its first path coupled to the first group of filters **721** (from a node between  $L3$  and  $C3$ ) and its second path coupled to the second group of filters **722** (from a node between  $C4$  and  $L4$ ).

(97) Configured in the foregoing manner, an impedance of  $Z_{in3}$  is presented in the first path of the first coupling circuit **100a**, and an impedance of  $Z_{in4}$  is presented in the second path of the first coupling circuit **100a**. Similarly, an impedance of  $Z_{in1}$  is presented in the first path of the second

coupling circuit **100b**, and an impedance of  $Z_{in2}$  is presented in the second path of the second coupling circuit **100b**.

(98) In the example of FIG. 24, a group of filters associated with the first path of the first coupling circuit **100a** can be considered to include the filters of the low frequency bands (**721**) and the filters of the mid frequency bands (**722**). Accordingly, the impedance  $Z_{in3}$  can have a value that is at or close to a load-matched impedance for low and mid frequency bands, and a value that is at or close to a short circuit state for high frequency bands. The impedance  $Z_{in4}$  can have a value that is at or close to a load-matched impedance for high frequency bands, and a value that is at or close to a short circuit state for low and mid frequency bands.

(99) Also in the example of FIG. 24, the second coupling circuit **100b** is shown to support the low frequency band filters **721** and the mid frequency band filters **722** through its first and second paths. Accordingly, the impedance  $Z_{in1}$  can have a value that is at or close to a load-matched impedance for low frequency bands, and a value that is at or close to a short circuit state for mid frequency bands. The impedance  $Z_{in2}$  can have a value that is at or close to a load-matched impedance for mid frequency bands, and a value that is at or close to a short circuit state for low frequency bands.

(100) In the example of FIG. 24, a phase shifter is shown to be provided for each path of each coupling circuit. More particularly, phase shifters **103b**, **103a** are shown to be provided for the first and second paths of the first coupling circuit **100a**, and phase shifters **103d**, **103c** are shown to be provided for the first and second paths of the second coupling circuit **100b**. In some embodiments, such phase shifters can be selected to provide one or more desirable functionalities as described herein. It will be understood that in some embodiments, an architecture similar to the example of FIG. 24 may include none of such phase shifters, some of such phase shifters, or all of such phase shifters.

(101) FIGS. 25-28 show examples of architectures having one or more switching functionalities described herein in reference to FIGS. 9-15. For example, FIG. 25 show an architecture **734** that can be a more specific example of the architectures **734** of FIGS. 9 and 12. In the example of FIG. 25, a coupling circuit **100** is shown to couple a common signal node **102** to a first group of filters **721** having three low frequency band duplexers (**F1**, **F2**, **F3**) through a first path, and to a second group of filters **722** having two high frequency band duplexers (**F4**, **F5**) through a second path. Such a second path is shown to include a switch **780** configured to allow selection of a high frequency band (**F4** or **F5**) among the bands of the second group **722**.

(102) In another example, FIG. 26 show an architecture **734** that can be a more specific example of the architectures **734** of FIGS. 9 and 13. In the example of FIG. 26, a coupling circuit **100** is shown to couple a common signal node **102** to a first group of filters **721** (having two low frequency band duplexers) or a second group of filters **722** (having two low frequency band duplexers), through a first path, and to a third group of filters **723** (having a high frequency band duplexer) through a second path. The first path is shown to include a switch **782** configured to allow selection of the first group of filters **721** or the second group of filters **722**.

(103) In yet another example, FIG. 27 shows an architecture **738** having switching functionalities described herein in reference to FIGS. 11, 13 and 14. In the example of FIG. 27, a first group of low frequency band filters **721a** is shown to include two low frequency band duplexers, and a second group of low frequency band filters **721b** is shown to include two low frequency band duplexers. A first group of high frequency band filters **722a** is shown to include a high frequency band duplexer, and a second group of high frequency band filters **722b** is shown to include a high frequency band duplexer. Accordingly, such groups of filters can be grouped into a first group having low frequency band duplexers (**721a** and **721b**) coupled to a coupling circuit **100** through a first path, and a second group having high frequency band duplexers (**722a** and **722b**) coupled to the coupling circuit **100** through a second path.

(104) In the example of FIG. 27, a switching network **786** is shown to be implemented to provide

switching functionalities between the coupling circuit **100** and the foregoing first and second groups of filters. More particularly, switches **S1** and **S2** of the switching network **786** can be operated to provide coupling of the first group of low frequency band filters **721a** or the second group of low frequency band filters **721b** to the coupling circuit **100** (through the first path). Similarly, switches **S3** and **S4** of the switching network **786** can be operated to provide coupling of the first group of high frequency band filters **722a** or the second group of high frequency band filters **722b** to the coupling circuit **100** (through the second path).

(105) In the example of FIG. **27**, a switching network **788** is shown to be implemented to allow a common signal node **102** of the coupling circuit **100** to be coupled to a first antenna **760a** or to a second antenna **760b**. For example, a switch **S11** can be closed and a switch **S12** can be opened to couple the common signal node **102** to the first antenna **760a**. Similarly, the switch **S11** can be opened and the switch **S12** can be closed to couple the common signal node **102** to the second antenna **760b**.

(106) Referring to the example of FIG. **27**, it will be understood that the foregoing switching networks **786** and **788** can be implemented in a number of ways. In some embodiments, the switching networks **786** and **788** can be part of a switching circuit indicated as **784**, and such a switching circuit can be implemented on, for example, a die or a module.

(107) FIG. **28** shows an example architecture **738** that includes switching functionalities to allow a plurality of coupling circuits **100a**, **100b** to share a common antenna **760**, and also to share a common group of filters **722**. Suppose that an architecture design includes carrier aggregation capability between low frequency bands and high frequency bands. If such low frequency bands span sufficiently wide range in frequency, it may be desirable to split the low frequency bands into two sub-groups of low frequency bands, and pair each sub-group with a group of the high frequency bands utilizing a respective coupling circuit.

(108) Accordingly, in the example of FIG. **28**, the common group of filters **722** can include one or more high frequency bands. The first sub-group of low frequency filters can be **721a**, and the second sub-group of low frequency filters can be **721b**. Configured in the foregoing manner, the first sub-group of filters **721a** and the common group of filters **722** can be coupled to a common signal node **102a** of the first coupling circuit **100a** having appropriate values of **L1**, **C1**, **C2**, **L2** selected to accommodate such groups of filters. Similarly, the second sub-group of filters **721b** and the common group of filters **722** can be coupled to a common signal node **102b** of the second coupling circuit **100b** having appropriate values of **L3**, **C3**, **C4**, **L4** selected to accommodate such groups of filters. In some embodiments, phase shifters **103a**, **105a**, **103b**, **105b** can be provided as shown and configured to provide desirable shifts in phases for improved performance.

(109) Referring to the example of FIG. **28**, a low-band/high-band carrier aggregation can involve the first sub-group **721a** or the second sub-group **721b**. Accordingly, if the first sub-group **721a** is being utilized, a switch **790** can allow the second path of the first coupling circuit **100a** to be connected to the common group of filters **722**, and the second path of the second coupling circuit **100b** to be disconnected from the common group of filters **722**. Similarly, if the second sub-group **721b** is being utilized, the switch **790** can allow the second path of the first coupling circuit **100a** to be disconnected from the common group of filters **722**, and the second path of the second coupling circuit **100b** to be connected to the common group of filters **722**.

(110) In the example of FIG. **28**, the architecture **738** is shown to utilize a common antenna **760**. Accordingly, if the first coupling circuit **100a** is being utilized, its common signal node **102a** can be coupled to the antenna **760** by a switch **792**, and a common signal node **102b** of the second coupling circuit **100b** can be uncoupled from the antenna **760** by the switch **792**. Similarly, if the second coupling circuit **100b** is being utilized, its common signal node **102b** can be coupled to the antenna **760** by the switch **792**, and a common signal node **102a** of the first coupling circuit **100a** can be uncoupled from the antenna **760** by the switch **792**.

(111) FIG. **29** shows an architecture **740** that can be a more specific example of the architecture

**740** of FIG. **19A**. In the example of FIG. **29**, the architecture **740** is shown to include a first group of filters **721** having three mid frequency band duplexers and a second group of filters **722** having two high frequency band duplexers. A half-bridge coupling circuit **100** is shown to have its common signal node **102** coupled to an antenna **760**. A node between **L1** and **C1** of the coupling circuit **100** is shown to be coupled to the first group of filters **721** through a phase shifter **103**. The second group of filters **722** is shown to be coupled to the common signal node **102**.

(112) Configured in the foregoing manner, impedance  $Z_{in1}$  is presented by the first path to the first group of filters **721**, impedance  $Z_{in2}$  is presented by the second path to the second group of filters **722**, and impedance  $Z_{in3}$  is presented to the common signal node **102** by the inductance **L1**.

Accordingly, at a mid band frequency (for one of the mid frequency bands of the group **721**), each of  $Z_{in1}$  and  $Z_{in3}$  has a value at or close to a matched load impedance, and  $Z_{in2}$  has an open circuit value. At a high band frequency (for one of the high frequency bands of the group **722**),  $Z_{in2}$  has a value at or close to a matched load impedance,  $Z_{in1}$  has a short circuit value, and  $Z_{in3}$  has an open circuit value.

(113) FIG. **30** shows an example architecture **800** that utilizes a number of features described herein. In the example of FIG. **30**, two coupling circuits **100a**, **100b** are shown to provide couplings between a common antenna **760** and respective groups of filters. More particularly, the first coupling circuit **100a** is shown to provide coupling between the antenna **760** and groups of filters **721a**, **722**; and the second coupling circuit **100b** is shown to provide coupling between the antenna **760** and groups of filters **721b**, **722**.

(114) Referring to FIG. **30**, the group of filters **721a** is shown to include a number of mid frequency band filters including duplexers for **B3Tx/B3Rx** and **B1Tx/B1Rx** bands, and a **B32Rx** band filter. The group of filters **721b** is shown to include a number of mid frequency band filters including duplexers for **B66Tx/B66Rx** and **B25Tx/B25Rx** bands. The group of filters **722** is shown to include a number of high frequency band filters including a duplexers for **B7Tx/B7Rx** and **B30Tx/B30Rx** bands, and filters **B40TRx** and **B41TRx** configured to support Tx and Rx operations in respective bands. Accordingly, the foregoing grouping of filters utilizes at least some of the features of the example of FIG. **28**, where a plurality of coupling circuits can be utilized to accommodate splitting of a group of filters (low frequency band filters in FIG. **28**, and mid frequency band filters in FIG. **30**) into sub-groups of filters.

(115) Accordingly, in the example of FIG. **30**, the first coupling circuit **100a** can include inductances **LMB**, **LHB** and capacitances **CMB**, **CHB** as shown to support the foregoing mid frequency band and high frequency band filters. Similarly, the second coupling circuit **100b** can include inductances **LMB**, **LHB** and capacitances **CMB**, **CHB** as shown to support the foregoing mid frequency band and high frequency band filters. It will be understood that each of **LMB**, **LHB**, **CMB**, **CHB** of the first coupling circuit **100a** may or may not have the same value as respective one of **LMB**, **LHB**, **CMB**, **CHB** of the second coupling circuit **100b**.

(116) In the example of FIG. **30**, the architecture **800** is configured to allow at least some of the filters of the group **722** to be shared between the first and second coupling circuits **100a**, **100b**. More particularly, a switch **802** can allow the **B7Tx/B7Rx** duplexer and the **B41TRx** filter to be coupled to the second path of the first coupling circuit **100a**, or to the second path of the second coupling circuit **100b**.

(117) In the example of FIG. **30**, a switching circuit **804** (e.g., implemented as an antenna switching module (ASM)) can be configured to allow coupling of the antenna **760** to the first coupling circuit **100a** or to the second coupling circuit **100b**. More particularly, the common signal node **102a** of the first coupling circuit **100a** can be coupled to the antenna **760** by an appropriate operation of the switching circuit **804**. Similarly, the common signal node **102b** of the second coupling circuit **100b** can be coupled to the antenna **760** by an appropriate operation of the switching circuit **804**.

(118) In the example of FIG. **30**, the architecture **800** can include one or more circuits that do not utilize a coupling circuit. For example, a group of filters **806** can include time-domain duplexing



(TDD) filters such as mid frequency bands **B34** and **B39**. Such a group of filters is shown to be coupled to the antenna **760** through the switching circuit **804** without a coupling circuit. In some embodiments, some or all of such TDD bands can be individually, together with each other, with another FDD (frequency-domain duplexing) band (such as one or more filters of the group **722**), or some combination thereof, utilizing the antenna **760**.

(119) In some embodiments, the architecture **800** of FIG. **30** can include phase shifting elements such as transmission lines, L/C components and/or resonators configured to provide desirable functionalities, including functionalities associated with either or both of the first and second coupling circuits **100a**, **100b**.

(120) FIG. **31** shows that in some embodiments, one or more features as described herein can be implemented in a radio-frequency (RF) module **300** (e.g., a front-end module or an LNA module). The module **300** can include a packaging substrate **302** such as a laminate substrate. Such a module can include one or more LNAs **308**. At least one of such LNAs can be configured to operate in a CA mode as described herein.

(121) The module **300** can further include a carrier aggregation (CA) circuit **100** having one or more features as described herein. Such a CA circuit can be configured to provide CA functionality for the LNA **308** through a diplexer/filter assembly **306**. Transmission lines **304** can be configured to, for example, provide desired phase shifts in various signal paths, including those associated with inputs and output(s) of the diplexer/filter assembly **306**. Although not shown, the module **300** can further include grounding switches for the CA circuit **100** to facilitate CA and non-CA operations as described herein.

(122) In some implementations, an architecture, device and/or circuit having one or more features described herein can be included in an RF device such as a wireless device. Such an architecture, device and/or circuit can be implemented directly in the wireless device, in one or more modular forms as described herein, or in some combination thereof. In some embodiments, such a wireless device can include, for example, a cellular phone, a smart-phone, a hand-held wireless device with or without phone functionality, a wireless tablet, a wireless router, a wireless access point, a wireless base station, etc. Although described in the context of wireless devices, it will be understood that one or more features of the present disclosure can also be implemented in other RF systems such as base stations.

(123) FIG. **32** depicts an example wireless device **500** having one or more advantageous features described herein. In some embodiments, such advantageous features can be implemented in a front-end (FE) or LNA module **300** as described herein. Such a module can include a CA circuit **100** having one or more features as described herein. In some embodiments, such module can include more or less components than as indicated by the dashed box.

(124) PAs in a PA module **512** can receive their respective RF signals from a transceiver **510** that can be configured and operated to generate RF signals to be amplified and transmitted, and to process received signals. The transceiver **510** is shown to interact with a baseband sub-system **508** that is configured to provide conversion between data and/or voice signals suitable for a user and RF signals suitable for the transceiver **510**. The transceiver **510** is also shown to be connected to a power management component **506** that is configured to manage power for the operation of the wireless device **500**. Such power management can also control operations of the baseband sub-system **508** and other components of the wireless device **500**.

(125) The baseband sub-system **508** is shown to be connected to a user interface **502** to facilitate various input and output of voice and/or data provided to and received from the user. The baseband sub-system **508** can also be connected to a memory **504** that is configured to store data and/or instructions to facilitate the operation of the wireless device, and/or to provide storage of information for the user.

(126) In the example wireless device **500**, the module **300** can include one or more carrier aggregation-capable signal paths configured to provide one or more functionalities as described

herein. In some embodiments, at least some of the signals received through a diversity antenna 530 can be routed to one or more low-noise amplifiers (LNAs) 308 through such carrier aggregation-capable signal path(s). Amplified signals from the LNAs 308 are shown to be routed to the transceiver 510.

(127) A number of other wireless device configurations can utilize one or more features described herein. For example, a wireless device does not need to be a multi-band device. In another example, a wireless device can include additional antennas such as diversity antenna, and additional connectivity features such as Wi-Fi, Bluetooth, and GPS.

(128) One or more features of the present disclosure can be implemented with various cellular frequency bands as described herein. Examples of such bands are listed in Table 1. It will be understood that at least some of the bands can be divided into sub-bands. It will also be understood that one or more features of the present disclosure can be implemented with frequency ranges that do not have designations such as the examples of Table 1.

(129) TABLE-US-00001

| TABLE 1 | Tx Frequency Range (MHz) | Rx Frequency Range (MHz) | Band Mode (MHz)                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                          |
|---------|--------------------------|--------------------------|------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------|
| B1      | FDD 1,920-1,980          | 2,110-2,170              | B2 FDD 1,850-1,910 1,930-1,990 B3 FDD 1,710-1,785 1,805-1,880 B4 FDD 1,710-1,755 2,110-2,155 B5 FDD 824-849 869-894 B6 FDD 830-840 875-885 B7 FDD 2,500-2,570 2,620-2,690 B8 FDD 880-915 925-960 B9 FDD 1,749.9-1,784.9 1,844.9-1,879.9 B10 FDD 1,710-1,770 2,110-2,170 B11 FDD 1,427.9-1,447.9 1,475.9-1,495.9 B12 FDD 699-716 729-746 B13 FDD 777-787 746-756 B14 FDD 788-798 758-768 B15 FDD 1,900-1,920 2,600-2,620 B16 FDD 2,010-2,025 2,585-2,600 B17 FDD 704-716 734-746 B18 FDD 815-830 860-875 B19 FDD 830-845 875-890 B20 FDD 832-862 791- 821 B21 FDD 1,447.9-1,462.9 1,495.9-1,510.9 B22 FDD 3,410-3,490 3,510-3,590 B23 FDD 2,000-2,020 2,180-2,200 B24 FDD 1,626.5-1,660.5 1,525-1,559 B25 FDD 1,850-1,915 1,930-1,995 B26 FDD 814-849 859-894 B27 FDD 807-824 852-869 B28 FDD 703-748 758-803 B29 FDD N/A 716-728 B30 FDD 2,305-2,315 2,350-2,360 B31 FDD 452.5-457.5 462.5-467.5 B33 TDD 1,900-1,920 1,900-1,920 B34 TDD 2,010-2,025 2,010-2,025 B35 TDD 1,850-1,910 1,850-1,910 B36 TDD 1,930-1,990 1,930-1,990 B37 TDD 1,910-1,930 1,910-1,930 B38 TDD 2,570-2,620 2,570-2,620 B39 TDD 1,880-1,920 1,880-1,920 B40 TDD 2,300-2,400 2,300-2,400 B41 TDD 2,496-2,690 2,496-2,690 B42 TDD 3,400-3,600 3,400-3,600 B43 TDD 3,600-3,800 3,600-3,800 B44 TDD 703-803 703-803 |

(130) It is noted that while various examples are described herein in the context of carrier aggregation of two or three bands, one or more features of the present disclosure can also be implemented in configurations involving carrier aggregation of different numbers of bands.

(131) Unless the context clearly requires otherwise, throughout the description and the claims, the words “comprise,” “comprising,” and the like are to be construed in an inclusive sense, as opposed to an exclusive or exhaustive sense; that is to say, in the sense of “including, but not limited to.” The word “coupled”, as generally used herein, refers to two or more elements that may be either directly connected, or connected by way of one or more intermediate elements. Additionally, the words “herein,” “above,” “below,” and words of similar import, when used in this application, shall refer to this application as a whole and not to any particular portions of this application. Where the context permits, words in the above Detailed Description using the singular or plural number may also include the plural or singular number respectively. The word “or” in reference to a list of two or more items, that word covers all of the following interpretations of the word: any of the items in the list, all of the items in the list, and any combination of the items in the list.

(132) The above detailed description of embodiments of the invention is not intended to be exhaustive or to limit the invention to the precise form disclosed above. While specific embodiments of, and examples for, the invention are described above for illustrative purposes, various equivalent modifications are possible within the scope of the invention, as those skilled in the relevant art will recognize. For example, while processes or blocks are presented in a given order, alternative embodiments may perform routines having steps, or employ systems having blocks, in a different order, and some processes or blocks may be deleted, moved, added,

subdivided, combined, and/or modified. Each of these processes or blocks may be implemented in a variety of different ways. Also, while processes or blocks are at times shown as being performed in series, these processes or blocks may instead be performed in parallel, or may be performed at different times.

(133) The teachings of the invention provided herein can be applied to other systems, not necessarily the system described above. The elements and acts of the various embodiments described above can be combined to provide further embodiments.

(134) While some embodiments of the inventions have been described, these embodiments have been presented by way of example only, and are not intended to limit the scope of the disclosure. Indeed, the novel methods and systems described herein may be embodied in a variety of other forms; furthermore, various omissions, substitutions and changes in the form of the methods and systems described herein may be made without departing from the spirit of the disclosure. The accompanying claims and their equivalents are intended to cover such forms or modifications as would fall within the scope and spirit of the disclosure.

## Claims

1. A radio-frequency architecture comprising: a first group of one or more filters each configured to support a respective band, and a second group of one or more filters each configured to support a respective band, each filter of the first group configured to provide an impedance at or near a short circuit impedance for a signal in each band of the second group, each filter of the second group configured to provide an impedance at or near a short circuit impedance for a signal in each band of the first group; and a coupling circuit including a common node and configured to couple the common node to the one or more filters of the first group and the one or more filters of the second group through a first path and a second path, respectively, the coupling circuit further configured such that the impedance provided by each filter of the first group for the signal in each band of the second group results in the signal being sufficiently excluded from the first path, and such that the impedance provided by each filter of the second group for the signal in each band of the first group results in the signal being sufficiently excluded from the second path.

2. A packaged module comprising: a packaging substrate configured to receive a plurality of components; and a radio-frequency circuit implemented on the packaging substrate and including a first group of one or more filters each configured to support a respective band, and a second group of one or more filters each configured to support a respective band, each filter of the first group configured to provide an impedance at or near a short circuit impedance for a signal in each band of the second group, each filter of the second group configured to provide an impedance at or near a short circuit impedance for a signal in each band of the first group, the radio-frequency circuit further including a coupling circuit including a common node and configured to couple the common node to the one or more filters of the first group and the one or more filters of the second group through a first path and a second path, respectively, the coupling circuit further configured such that the impedance provided by each filter of the first group for the signal in each band of the second group results in the signal being sufficiently excluded from the first path, and such that the impedance provided by each filter of the second group for the signal in each band of the first group results in the signal being sufficiently excluded from the second path.

3. A wireless device comprising: one or more antennas; a front-end module in communication with the one or more antennas and including a radio-frequency circuit that includes a first group of one or more filters each configured to support a respective band, and a second group of one or more filters each configured to support a respective band, each filter of the first group configured to provide an impedance at or near a short circuit impedance for a signal in each band of the second group, each filter of the second group configured to provide an impedance at or near a short circuit impedance for a signal in each band of the first group, the radio-frequency circuit further including

a coupling circuit including a common node and configured to couple the common node to the one or more filters of the first group and the one or more filters of the second group through a first path and a second path, respectively, the coupling circuit further configured such that the impedance provided by each filter of the first group for the signal in each band of the second group results in the signal being sufficiently excluded from the first path, and such that the impedance provided by each filter of the second group for the signal in each band of the first group results in the signal being sufficiently excluded from the second path; and a receiver in communication with the front-end module and configured to process one or more signals associated with the first and second group.

---