

US Patent & Trademark Office

Patent Public Search | Text View

United States Patent Application Publication

20250286267

Kind Code

A1

Publication Date

September 11, 2025

Inventor(s)

Liao; Wen-Shiang

ANTENNA APPARATUS AND METHOD

Abstract

A package structure includes a first die, an insulating material around the first die, a first antenna extending through the insulating material, wherein the first antenna includes a first conductive plate extending through the insulating material and a plurality of first conductive pillars extending through the insulating material, wherein the first conductive plate is disposed between the plurality of first conductive pillars and the first die, and a first high-k block embedded in the insulating material, wherein the first high-k block is disposed between the first conductive plate and the plurality of first conductive pillars, and wherein the first high-k block comprises a material having a dielectric constant that is different than a dielectric constant of the insulating material.

Inventors: Liao; Wen-Shiang (Toufen Township, TW)

Applicant: Taiwan Semiconductor Manufacturing Co., Ltd. (Hsinchu, TW)

Family ID: 1000008618210

Appl. No.: 19/211998

Filed: May 19, 2025

Related U.S. Application Data

parent US continuation 17864765 20220714 parent-grant-document US 12334625 child US 19211998

Publication Classification

Int. Cl.: H01Q1/22 (20060101); H01L21/56 (20060101); H01L23/00 (20060101); H01L23/31 (20060101); H01L23/498 (20060101)

U.S. Cl.:

Background/Summary

CROSS-REFERENCE TO RELATED APPLICATIONS [0001] This application is a continuation of U.S. application Ser. No. 17/864,765, filed on Jul. 14, 2022, which application is hereby incorporated herein by reference.

BACKGROUND

[0002] In modern semiconductor devices and systems, integration and miniaturization of components have progressed at an increasingly rapid pace. In wireless applications, one of the growing challenges encountered by the integration process is the disposition of radio frequency devices or antennas. Conventional antennas associated with integrated circuits are usually designed with limited performance and capability due to the competing objective of size reduction. Thus, an improved integrated antenna structure is desired.

Description

BRIEF DESCRIPTION OF THE DRAWINGS

[0003] Aspects of the present disclosure are best understood from the following detailed description when read with the accompanying figures. It is noted that, in accordance with the standard practice in the industry, various features are not drawn to scale. In fact, the dimensions of the various features may be arbitrarily increased or reduced for clarity of discussion.

[0004] FIG. 1 illustrates a cross-sectional view of an integrated circuit die in accordance with some embodiments.

[0005] FIGS. 2 through 14B illustrate cross-sectional views and a top-down view of intermediate steps during a process for forming a package component in accordance with some embodiments.

[0006] FIGS. 15 illustrates a top-down view of the package component in accordance with other embodiments.

[0007] FIGS. 16 illustrates a top-down view of the package component in accordance with other embodiments.

[0008] FIG. 17 illustrates a schematic diagram of a simulation result for different insulating materials, in accordance with some embodiments.

DETAILED DESCRIPTION

[0009] The following disclosure provides many different embodiments, or examples, for implementing different features of the invention. Specific examples of components and arrangements are described below to simplify the present disclosure. These are, of course, merely examples and are not intended to be limiting. For example, the formation of a first feature over or on a second feature in the description that follows may include embodiments in which the first and second features are formed in direct contact, and may also include embodiments in which additional features may be formed between the first and second features, such that the first and second features may not be in direct contact. In addition, the present disclosure may repeat reference numerals and/or letters in the various examples. This repetition is for the purpose of simplicity and clarity and does not in itself dictate a relationship between the various embodiments and/or configurations discussed.

[0010] Further, spatially relative terms, such as “beneath,” “below,” “lower,” “above,” “upper” and the like, may be used herein for ease of description to describe one element or feature's relationship to another element(s) or feature(s) as illustrated in the figures. The spatially relative terms are intended to encompass different orientations of the device in use or operation in addition to the orientation depicted in the figures. The apparatus may be otherwise oriented (rotated **90** degrees or at other orientations) and the spatially relative descriptors used herein may likewise be interpreted accordingly.

[0011] Various embodiments provide methods applied to forming an integrated circuit package comprising vertical Through Insulator Via (TIV) plates and TIV gratings. A high-k block is embedded in the insulator between each TIV plate and a respective TIV grating to form an antenna oscillation cavity. Each high-k block is comprised of a material that has a dielectric constant that is equal to or greater than 3.9, and the dielectric constant of each high-k block is different from dielectric constants of the other high-k blocks. In addition, a spacing between each TIV plate and its respective TIV grating may be varied. Advantageous features of one or more embodiments disclosed herein may allow for high-frequency lateral Radio Frequency (RF) transmission suitable for 5G & 6G high-frequency (e.g., 28, 38, 77, and 120 GHz) RF transceivers, as well as portable, wearable, IoT (internet of things) and smart phone products. In addition, forming antenna oscillation cavities comprising various high-k blocks, wherein each high-k block comprises a material having a different dielectric constant from materials of the other high-k blocks allows for the transmission and receiving of up to at least eight different RF bands with different frequency ranges. For example, a higher weighted average dielectric constant of the combined high-k block and insulator between a TIV plate and its respective TIV grating will allow for the transmission and receiving of a higher RF band. The high-k block being disposed between each TIV plate and its respective TDV grating allows for a reduced size of each antenna oscillation cavity, resulting in a reduction in the size of the integrated circuit package and making it more compact. Further, because the formation process of the TIV plates and the TIV gratings is compatible with current processes, manufacturing costs are reduced and efficiency is increased.

[0012] FIG. **1** illustrates a cross-sectional view of an integrated circuit die **50** in accordance with some embodiments. The integrated circuit die **50** will be packaged in subsequent processing to form an integrated circuit package. The integrated circuit die **50** may be a logic die (e.g., central processing unit (CPU), graphics processing unit (GPU), system-on-a-chip (SoC), application processor (AP), microcontroller, etc.), a memory die (e.g., dynamic random access memory (DRAM) die, static random access memory (SRAM) die, etc.), a power management die (e.g., power management integrated circuit (PMIC) die), a radio frequency (RF) die, baseband transceiver die, a sensor die, a micro-electro-mechanical-system (MEMS) die, a signal processing die (e.g., digital signal processing (DSP) die), a front-end die (e.g., analog front-end (AFE) dies), a high-performance computing (HPC) die, an artificial intelligence (AI) die, an automotive die, the like, or combinations thereof.

[0013] The integrated circuit die **50** may be formed in a wafer, which may include different device regions that are singulated in subsequent steps to form a plurality of integrated circuit dies. The integrated circuit die **50** may be processed according to applicable manufacturing processes to form integrated circuits. For example, the integrated circuit die **50** includes a semiconductor substrate **52**, such as silicon, doped or undoped, or an active layer of a semiconductor-on-insulator (SOI) substrate. The semiconductor substrate **52** may include other semiconductor materials, such as germanium; a compound semiconductor including silicon carbide, gallium arsenic, gallium phosphide, indium phosphide, indium arsenide, and/or indium antimonide; an alloy semiconductor including SiGe, GaAsP, AlInAs, AlGaAs, GaInAs, GaInP, and/or GaInAsP; or combinations thereof. Other substrates, such as multi-layered or gradient substrates, may also be used. The semiconductor substrate **52** has an active surface (e.g., the surface facing upwards in FIG. **1**), sometimes called a front side, and an inactive surface (e.g., the surface facing downwards in FIG.

1), sometimes called a back side.

[0014] Devices (represented by a transistor) **54** may be formed at the front surface of the semiconductor substrate **52**. The devices **54** may be active devices (e.g., transistors, diodes, etc.), capacitors, resistors, etc. An inter-layer dielectric (ILD) **56** is over the front surface of the semiconductor substrate **52**. The ILD **56** surrounds and may cover the devices **54**. The ILD **56** may include one or more dielectric layers formed of materials such as Phospho-Silicate Glass (PSG), Boro-Silicate Glass (BSG), Boron-Doped Phospho-Silicate Glass (BPSG), undoped Silicate Glass (USG), or the like.

[0015] Conductive plugs **58** extend through the ILD **56** to electrically and physically couple the devices **54**. For example, when the devices **54** are transistors, the conductive plugs **58** may couple the gates and source/drain regions of the transistors. The conductive plugs **58** may be formed of tungsten, cobalt, nickel, copper, silver, gold, aluminum, the like, or combinations thereof. An interconnect structure **60** is over the ILD **56** and conductive plugs **58**. The interconnect structure **60** interconnects the devices **54** to form an integrated circuit. The interconnect structure **60** may be formed by, for example, metallization patterns in dielectric layers on the ILD **56**. The metallization patterns include metal lines and vias formed in one or more low-k dielectric layers. The metallization patterns of the interconnect structure **60** are electrically coupled to the devices **54** by the conductive plugs **58**.

[0016] The integrated circuit die **50** further includes pads **62**, such as aluminum pads, to which external connections are made. The pads **62** are on the active side of the integrated circuit die **50**, such as in and/or on the interconnect structure **60**. One or more passivation films **64** are on the integrated circuit die **50**, such as on portions of the interconnect structure **60** and pads **62**. Openings extend through the passivation films **64** to the pads **62**. Die connectors **66**, such as conductive pillars (for example, formed of a metal such as copper), extend through the openings in the passivation films **64** and are physically and electrically coupled to respective ones of the pads **62**. The die connectors **66** may be formed by, for example, plating, or the like. The die connectors **66** electrically couple the respective integrated circuits of the integrated circuit die **50**.

[0017] Optionally, solder regions (e.g., solder balls or solder bumps) may be disposed on the pads **62**. The solder balls may be used to perform chip probe (CP) testing on the integrated circuit die **50**. CP testing may be performed on the integrated circuit die **50** to ascertain whether the integrated circuit die **50** is a known good die (KGD). Thus, only integrated circuit dies **50**, which are KGDs, undergo subsequent processing and are packaged, and dies, which fail the CP testing, are not packaged. After testing, the solder regions may be removed in subsequent processing steps.

[0018] A dielectric layer **68** may (or may not) be on the active side of the integrated circuit die **50**, such as on the passivation films **64** and the die connectors **66**. The dielectric layer **68** laterally encapsulates the die connectors **66**, and the dielectric layer **68** is laterally coterminous with the integrated circuit die **50**. Initially, the dielectric layer **68** may bury the die connectors **66**, such that the topmost surface of the dielectric layer **68** is above the topmost surfaces of the die connectors **66**. In some embodiments where solder regions are disposed on the die connectors **66**, the dielectric layer **68** may bury the solder regions as well. Alternatively, the solder regions may be removed prior to forming the dielectric layer **68**.

[0019] The dielectric layer **68** may be a polymer such as polybenzoxazole (PBO), polyimide, benzocyclobutene (BCB), or the like; a nitride such as silicon nitride or the like; an oxide such as silicon oxide, PSG, BSG, BPSG, or the like; the like, or a combination thereof. The dielectric layer **68** may be formed, for example, by spin coating, lamination, chemical vapor deposition (CVD), or the like. In some embodiments, the die connectors **66** are exposed through the dielectric layer **68** during formation of the integrated circuit die **50**. In some embodiments, the die connectors **66** remain buried and are exposed during a subsequent process for packaging the integrated circuit die **50**. Exposing the die connectors **66** may remove any solder regions that may be present on the die connectors **66**.

[0020] FIGS. 2 through 14B illustrate cross-sectional views and top-down views of intermediate steps during a process for forming a first package component **100**, in accordance with some embodiments. A first package region **100A** and a second package region **100B** are illustrated, and one or more of the integrated circuit dies **50** are packaged to form an integrated circuit package in each of the package regions **100A** and **100B**. The integrated circuit packages may also be referred to as integrated fan-out (InFO) packages.

[0021] In FIG. 2, a carrier substrate **102** is provided, and a release layer **104** is formed on the carrier substrate **102**. The carrier substrate **102** may be a glass carrier substrate, a ceramic carrier substrate, or the like. The carrier substrate **102** may be a wafer, such that multiple packages can be formed on the carrier substrate **102** simultaneously.

[0022] The release layer **104** may be formed of a polymer-based material, which may be removed along with the carrier substrate **102** from the overlying structures that will be formed in subsequent steps. In some embodiments, the release layer **104** is an epoxy-based thermal-release material, which loses its adhesive property when heated, such as a light-to-heat-conversion (LTHC) release coating. In other embodiments, the release layer **104** may be an ultra-violet (UV) glue, which loses its adhesive property when exposed to UV lights. The release layer **104** may be dispensed as a liquid and cured, may be a laminate film laminated onto the carrier substrate **102**, or may be the like. The top surface of the release layer **104** may be leveled and may have a high degree of planarity.

[0023] Still referring to FIG. 2, a dielectric layer **106** is formed on the release layer **104**. The dielectric layer **106** may be, for example, a layer of polymer material such as, e.g., polybenzoxazole (PBO), polyimide (PI), benzocyclobutene (BCB), or other polymer material that is electrically insulating. The dielectric layer **106** may be formed using a process such as lamination, coating, (e.g., spin-coating), chemical vapor deposition (CVD), or the like. In some embodiments, the dielectric layer **106** may comprise a glass, a spin-on glass (SOG), a ceramic, low temperature co-fired ceramic (LTCC), silicon oxide, silicon nitride, silicon carbide, silicon oxynitride, or the like. In an embodiment, the dielectric layer **106** may have a thickness **T1** that is in a range from 5 μm to 50 μm .

[0024] In FIG. 3, a mask layer **112** is formed over the structure shown in FIG. 2, such as over the dielectric layer **106**. The mask layer **112** may be a dry-film photoresist, or the like, and may be formed using a lamination process. In an embodiment, the mask layer **112** may be formed to have a thickness that is in a range from 120 μm to 300 μm . The mask layer **112** may be patterned using acceptable development and exposure techniques to form first openings (or through holes) **114** and second openings **115** in which to subsequently form vias that are electrically conductive (which may also be called through-insulator-vias TIVs), according to some embodiments. These vias comprise the subsequently formed TIV gratings **120** (shown in FIG. 5) and TIV plates **121** (shown in FIG. 5). The first openings **114** and the second openings **115** may expose top surfaces of the dielectric layer **106**.

[0025] In FIG. 4, a seed layer **116** is formed on the mask layer **112** and in the first openings **114** and the second openings **115** of the mask layer **112**, such as on bottom surfaces and sidewalls of the first openings **114**, and bottom surfaces and sidewalls of the second openings **115**. The metal seed layer **116** may comprise, for example, a Ti/Cu bilayer, a copper layer, or other suitable metal layer, and may be deposited using a PVD process, or the like. Any suitable thickness may be used for the seed layer **116**. For example, in some embodiments, the seed layer **116** may comprise at least 1000 Å of titanium and at least 5000 Å of copper. In other embodiments, the seed layer **116** may comprise other combinations of metals and thicknesses. A conductive material **118** is formed on the seed layer **116** and in the first openings **114** and the second openings **115**, in order to fill in the first openings **114** and the second openings **115**. The conductive material **118** may be a copper layer or other suitable metal formed by an electrochemical plating (ECP) process, or the like. During the ECP process, the conductive material **118** is deposited both laterally on the sidewalls of the first

openings **114** and the second openings **115**, as well as vertically on bottom surfaces of the first openings **114** and the second openings **115**.

[0026] In FIG. 5, a planarization step, such as a chemical mechanical polish (CMP), or the like, may be performed to remove portions of the seed layer **116** and excess portions of the conductive material **118** which are over the mask layer **112**. The remaining conductive material **118** and the seed layer **116** in the first openings **114** form the TIV gratings **120**. The remaining conductive material **118** and the seed layer **116** in the second openings **115** form the TIV plates **121**.

Accordingly, after the planarization step, top surfaces of the conductive material **118**, the seed layer **116**, and the mask layer **112** are level. In an embodiment, each of the TIV gratings **120** may have a width **W1** that is in a range from 50 μm to 1000 μm . In an embodiment, each of the TIV plates **121** may have a width **W2** that may be in a range from 50 μm to 1000 μm . In an embodiment, the width **W2** of the TIV plates **121** may be larger than the width **W1** of the TIV gratings **120**.

[0027] In FIG. 6, after the planarization step, the mask layer **112** may be removed using a suitable removal process such as ashing or chemical stripping.

[0028] In FIGS. 7A through 7E, a plurality of high-k blocks **126** and a plurality of integrated circuit dies **50** are bonded to a top surface of the dielectric layer **106** using, for example, a pick and place process, a carrier bonding process, or the like. An example carrier bonding process is illustrated in FIGS. 7A through 7E, but other pick and place processes are also possible for placing the plurality of high-k blocks **126** and the plurality of integrated circuit dies **50**. In FIG. 7A, a carrier substrate **80** is shown. The carrier substrate **80** may comprise silicon-based materials, such as a silicon substrate (e.g., a silicon wafer), a glass material, silicon oxide, or other materials, such as aluminum oxide, the like, or a combination. The carrier substrate **80** may comprise a transparent material such as glass, or the like. An adhesive layer **82** is formed on the carrier substrate **80** to facilitate a subsequent debonding of the carrier substrate **80** from the first package component **100**. The adhesive layer **82** may comprise a polymer-based material, which may be removed along with the carrier substrate **80** from the first package component **100**. In some embodiments, the adhesive layer **82** may comprise an epoxy-based thermal-release material, which loses its adhesive property when heated, such as a Light-to-Heat-Conversion (LTHC) release coating. In some embodiments, the adhesive layer **82** may comprise an ultra-violet (UV) glue, which loses its adhesive property when exposed to UV light. After the adhesive layer **82** is formed, a suitable curing process may be performed to harden the adhesive material **82**.

[0029] In FIG. 7B, a mask layer (e.g., a photoresist) is formed over the adhesive layer **82**. The mask layer is patterned using suitable development and exposure techniques to form openings in the mask layer that expose top surfaces of the adhesive layer **82**. A suitable etching process (e.g., an anisotropic etching process) is then performed to partially etch exposed portions of the adhesive layer **82** using the mask layer as an etching mask. As a result, the adhesive layer **82** may comprise regions with different thicknesses, and the thicknesses can be controlled by varying the parameters of the etching process. After the etching process is performed on the adhesive layer **82**, the mask layer may then be removed using an acceptable ashing or stripping process. Although FIG. 7B illustrates an adhesive layer **82** with two different thicknesses, one or more photolithography and etching processes may be used to pattern an adhesive layer **82** with any number of different thicknesses.

[0030] In FIG. 7C, the plurality of high-k blocks **126** and the plurality of integrated circuit dies **50** are attached to a top surface of the adhesive layer **82** using, for example, a pick and place process, or the like. The plurality of integrated circuit dies **50** are attached to the adhesive layer **82** such that the dielectric layer **68** of each of the plurality of integrated circuit dies **50** faces the adhesive layer **82**. The plurality of high-k blocks **126** may be disposed on regions of the adhesive layer **82** that have larger heights than the regions of the adhesive layer **82** on which the plurality of integrated circuit dies **50** are disposed on. As a result, topmost surfaces of the plurality of high-k blocks **126** and topmost surfaces of the plurality of integrated circuit dies **50** are level. The plurality of

integrated circuit dies **50** and the plurality of high-k blocks **126** may also comprise a die attach films (DAF) **124** that are disposed on top surfaces of the plurality of integrated circuit dies **50** and the plurality of high-k blocks **126**. The DAF **124** may comprise a polymer material. In FIG. 7D, the carrier substrate **80** and the first package component **100** are then transported to a bond chamber where the carrier substrate **80** is oriented to align the plurality of high-k blocks **126** and the plurality of integrated circuit dies **50** with the TIV gratings **120** and the TIV plates **121**, such that the plurality of high-k blocks **126** and the plurality of integrated circuit dies **50** face the dielectric layer **106**. The plurality of high-k blocks **126** and the plurality of integrated circuit dies **50** are pressed against the dielectric layer **106** to couple the plurality of high-k blocks **126** and the plurality of integrated circuit dies **50** to the dielectric layer **106** using the die attach films (DAFs) **124**. A first anneal process is then performed in the bond chamber to initiate bonding of the DAF films **124** with the dielectric layer **106**. As a result, the plurality of high-k blocks **126** and the plurality of integrated circuit dies **50** are adhered to the dielectric layer **106**. The first anneal may be performed at a temperature in a range from 150° C. to 350° C. and for a duration of time that is in a range from 0.5 hours to 4 hours.

[0031] In FIG. 7E, a de-bonding of the carrier substrate **80** is then performed to detach (or “de-bond”) the carrier substrate **80** from the plurality of high-k blocks **126** and the plurality of integrated circuit dies **50**. In accordance with some embodiments, the de-bonding includes projecting a light such as a laser light or an UV light on the adhesive layer **82** so that the adhesive layer **82** decomposes under the heat of the light. The carrier substrate **80** can then be mechanically removed leaving the plurality of high-k blocks **126** and the plurality of integrated circuit dies **50** bonded to the dielectric layer **106**. After the removal of the carrier, a second anneal may be performed at a temperature in a range from 150° C. to 350° C. and for a duration of time that is in a range from 0.5 hours to 4 hours. The second anneal strengthens the bonding between the plurality of high-k blocks **126** and the dielectric layer **106**. The second anneal also strengthens the bonding between the plurality of integrated circuit dies **50** and the dielectric layer **106**. In other embodiments, the second anneal may be performed before the removal of the carrier. Although FIGS. 7A through 7E illustrate that the plurality of high-k blocks **126** and the plurality of integrated circuit dies **50** are bonded to the top surface of the dielectric layer **106** simultaneously using the carrier substrate **80**, the plurality of integrated circuit dies **50** may be bonded to the top surface of the dielectric layer **106** either prior to or after the plurality of high-k blocks **126** are bonded to the top surface of the dielectric layer **106**. In such a case, the bonding of the plurality of integrated circuit dies **50** to the top surface of the dielectric layer **106** may be performed with a first carrier substrate, and the bonding of the plurality of high-k blocks **126** to the top surface of the dielectric layer **106** may be performed with a second carrier substrate different from the first carrier substrate.

[0032] In an embodiment, each of the plurality of high-k blocks **126** may be disposed between a TIV grating **120** and respective TIV plate **121**.

[0033] Each of the plurality of high-k blocks **126** may comprise a width W_3 that is in a range from 10 μm to 100 μm . Each of the plurality of high-k blocks **126** comprises a material having a dielectric constant value that is equal to or greater than 3.9. In an embodiment, each of the plurality of high-k blocks **126** comprises a material having a dielectric constant value of up to 20,000. In an embodiment, each of the plurality of high-k blocks **126** may comprise a different material from materials of the other high-k blocks of the plurality of high-k blocks **126**. Further, each of the plurality of high-k blocks **126** may comprise a material having a dielectric constant that is different from the dielectric constants of materials of the other high-k blocks of the plurality of high-k blocks **126**. The plurality of high-k blocks **126** may comprise SiO_2 , Si_3N_4 , Al_2O_3 , Y_2O_3 , TiO_2 , HfO_2 , ZrO_2 , PbZrTiO_3 , BaTiO_3 , BaSrTiO_3 , SrTiO_3 , or the like. In an embodiment, one or more of the plurality of high-k blocks **126** may have a cube shape having a length, a width, and a height all being equal to each other. In an embodiment, one or more of the plurality of high-k blocks **126** may have a cuboid shape, wherein

at least one of a length, a width, or a height is not equal to the other dimensions of the cuboid.

[0034] In FIG. 8, an electrically insulating molding material (or molding compound) **128** is formed over the structure shown in FIG. 7E, such as on top surfaces and sidewalls of the TIV gratings **120**, top surfaces and sidewalls of the TIV plates **121**, top surfaces and sidewalls of the plurality of the high-k blocks **126**, top surfaces and sidewalls of the plurality of integrated circuit dies **50**, sidewalls of the die attach film (DAF) **124**, and top surfaces of the dielectric layer **106**. The molding material **128** can comprise a dielectric material, such as silicon-based material, an epoxy molding compound that includes silica, or the like, that provides electrical isolation between each of the TIV gratings **120** and other structures of the first package component **100**. The molding material **128** also provides electrical isolation between each of the TIV plates **121** and other structures of the first package component **100**. A dielectric constant of the molding material **128** may be in the range from 50 to 5000 μm . The dielectric constant of the molding material **128** may be different from dielectric constants of the materials of the plurality of the high-k blocks **126**. The dielectric constant of the molding material **128** may be smaller than the dielectric constants of the materials of the plurality of the high-k blocks **126**. The molding material **128** may be formed using any suitable process, such as, spin-coating, a deposition process, an injection process, or the like. When the molding material **128** is formed using a spin-coating process, a curing process is also performed at a temperature in a range from 150° C. to 210° C., in order to harden the molding material **128**. Excess portions of the molding material **128** may then be planarized by grinding and CMP to remove a portion of the molding material **128** and expose top surfaces of the TIV gratings **120** and the TIV plates. During the planarization, a portion of the dielectric layer **68** of each of the plurality of integrated circuit dies **50** may also be removed so as to expose top surfaces of the die connectors **66**. As illustrated in FIG. 8, the planarization may result in the top surfaces of the TIV gratings **120**, the TIV plates **121**, and the die connectors **66** being level with a top surface of the molding material **128**. In an embodiment, after the planarization, a height H1 of each of the TIV gratings **120** may be in a range from 120 μm to 300 μm . In an embodiment, after the planarization, a height of the TIV plates **121** may be equal to the height H1. In an embodiment, a height of the molding material **128** may be equal to the height H1. In an embodiment, after the planarization, a thickness T2 of the molding material **128** above a top surface of each of the plurality of the high-k blocks **126** is in a range from 0 μm to 100 μm .

[0035] Referring further to FIG. 8, the molding material **128** disposed between a first sidewall of one of the plurality of the high-k blocks **126** and a nearest sidewall of an adjacent TIV grating **120** that faces the first sidewall may have a width W4 that is in a range from 0.1 μm to 100 μm . In addition, the molding material **128** disposed between a second sidewall of the one of the plurality of the high-k blocks **126** and a nearest sidewall of an adjacent TIV plate **121** that faces the second sidewall may have the width W4. A high-k block **126** and molding material **128** disposed between a TIV grating **120** and a respective TIV plate **121** will fill the space between each TIV grating **120** and respective TIV plate **121** (e.g., with insulating materials of the molding material **128** and the high-k block **126**), forming an antenna oscillation cavity structure between the TIV grating **120** and the respective TIV plate **121**. The combined insulating materials of the molding material **128** and the high-k block **126** between the TIV grating **120** and the respective TIV plate **121** may have a weighted average dielectric constant value that is dependent on the width W4 of the molding material **128** and the width W3 of the high-k block **126**. By varying the width W3 of the high-k block **126** and the width W4 of the molding material **128**, the weighted average dielectric constant value of the combined insulating materials between the TIV grating **120** and the respective TIV plate **121** can be tuned. For example, using a high-k block **126** with a larger width W3 and also having a reduced width W4 of the molding material **128** will result in a higher weighted average dielectric constant value of the combined insulating materials between the TIV grating **120** and the respective TIV plate **121**. Further, using a high-k block **126** with a smaller width W3 and also having an increased width W4 of the molding material **128** will result in a smaller weighted

average dielectric constant value of the combined insulating materials between the TIV grating **120** and the respective TIV plate **121**. A higher average dielectric constant value of the combined insulating materials between the TIV grating **120** and the respective TIV plate **121** will allow for the transmission and receiving of a higher RF band. Additionally, a smaller average dielectric constant value of the combined insulating materials between the TIV grating **120** and the respective TIV plate **121** will allow for the transmission and receiving of a lower RF band.

[0036] In FIGS. **9** through **13**, exemplary processing will now be described for providing additional redistribution layers of a front-side redistribution structure **149**, conductive connectors **150** to provide for input/output (I/O) to die circuitry, and conductive connectors **152** that allow for the grounding of the TIV gratings **120**.

[0037] FIG. **9** illustrates the formation of a redistribution layer (RDL) **130** (which also maybe referred to as a metallization pattern) which is part of the front-side redistribution structure **149** shown subsequently in FIG. **13**. To form the RDL **130**, a seed layer is first formed on top surfaces of the molding material **128**, top surfaces of the TIV gratings **120**, top surfaces of the TIV plates **121**, and top surfaces of the plurality of integrated circuit dies **50**. The metal seed layer may comprise, for example, a Ti/Cu bilayer, a copper layer, or other suitable metal layer, and may be deposited using a PVD process (e.g., sputtering) or the like. Any suitable thickness may be used for the seed layer. For example, in some embodiments, the seed layer may comprise at least 1000 Å of titanium and at least 5000 Å of copper. In other embodiments, the seed layer may comprise other combinations of metals and thicknesses. A conductive material layer is then deposited on the seed layer. The conductive material layer may be copper, or the like, that is deposited using a plating process, for example, electroplating, electroless plating, immersion plating, or the like. The seed layer and the conductive material layer may be then be patterned using acceptable photolithography and etching techniques to remove portions of the seed layer and conductive material layer. The remaining portions of the seed layer and overlying conductive material layer form the RDL **130**, the RDL **130** being in physical and electrical contact with the die connectors **66** and the TIV gratings **120**.

[0038] Referring further to FIG. **9**, after the formation of the RDL **130**, a dielectric layer **132** is formed over the RDL **130**, the molding material **128**, the TIV gratings **120**, the TIV plates **121**, and the plurality of integrated circuit dies **50**. The dielectric layer **132** is formed such that the RDL **130** is embedded in the dielectric layer **132**. The dielectric layer **132** may be, for example, a layer of polymer material such as, e.g., polybenzoxazole (PBO), polyimide (PI), benzocyclobutene (BCB), or other polymer material that is electrically insulating. The dielectric layer **132** may be formed using a process such as lamination, coating, (e.g., spin-coating), chemical vapor deposition (CVD), or the like. In an embodiment, the dielectric layer **106** and the dielectric layer **132** may comprise different materials.

[0039] In FIG. **10**, a first mask layer (e.g., a photoresist) may be formed over the dielectric layer **132** and subsequently patterned to expose top surfaces of the dielectric layer **132**. A suitable etching process is then performed using the first mask layer as an etching mask to form openings in the dielectric layer **132** that expose top surfaces of the RDL **130** and the TIV plates **121**. A first seed layer (not shown in FIG. **10**) that may comprise a bilayer of Ti/Cu, a copper layer, or other suitable metal layer, may be deposited in the openings in the dielectric layer **132**, such as on sidewalls of the openings and on the exposed top surfaces of the RDL **130** and the TIV plates **121**. A first conductive material may then be deposited in the openings using a plating process, such as electroplating or electroless plating, in order to fill the openings. The first conductive material may comprise copper, titanium, or the like. The first mask layer may then be removed using an acceptable ashing or stripping process.

[0040] After the removal of the first mask layer, a planarization step, such as a chemical mechanical polish (CMP), may be performed to remove excess portions of the first seed layer and the first conductive material that are over top surfaces of the dielectric layer **132**. The remaining

first seed layer and the first conductive material in the openings forms the vias **134** (which may be referred to as through insulator vias or TIVs). Accordingly, top surfaces of the dielectric layer **132** are level with top surfaces of the vias **134**.

[0041] In FIG. **11**, a second mask layer (e.g., a photoresist) may then be formed over the dielectric layer **132** and the vias **134**. The second mask layer may be patterned to form openings that expose top surfaces of the vias **134**. A second seed layer is formed in the openings in the second mask layer. The second seed layer may comprise, for example, a Ti/Cu bilayer, a copper layer, or other suitable metal layer, and may be deposited using a PVD process (e.g., sputtering) or the like. A second conductive material may then be deposited on the second seed layer using a plating process, such as electroplating or electroless plating. The second conductive material may comprise copper, titanium, or the like. The second mask layer may then be removed using an acceptable ashing or stripping process. The second seed layer and the overlying second conductive material form a redistribution layer (RDL) **138** (sometimes referred to as a metallization pattern). The RDL **138** includes feed lines **136** that electrically connect each TIV plate **121** to a die connector **66** of one of the plurality of integrated circuit dies **50**. The RDL **138** also includes ground lines **140** that are electrically connected to each TIV grating **120**.

[0042] Referring further to FIG. **11**, a dielectric layer **135** is formed over the dielectric layer **132** and the RDL **138**, such that the RDL **138** is embedded in the dielectric layer **135**. The dielectric layer **135** may be formed using a similar process and similar materials as those described above in FIG. **9** for the formation of the dielectric layer **132**. After the formation of the dielectric layer **135**, vias **142** are then formed in the dielectric layer **135** using similar processes and similar materials as those described above in FIG. **10** for the formation of the vias **134**. The vias **142** are electrically connected to the TIV gratings **120** and the plurality of integrated circuit dies **50**.

[0043] In FIG. **12**, a redistribution layer (RDL) **144** (sometimes referred to as a metallization pattern) is formed over the dielectric layer **135** and the vias **142**. The RDL **144** is formed using similar processes and similar materials as those described above in FIG. **11** for the formation of the RDL **138**. After the formation of the RDL **144**, a dielectric layer **146** is formed over the dielectric layer **135** and the RDL **144**, such that the RDL **144** is embedded in the dielectric layer **146**. The dielectric layer **146** may be formed using a similar process and similar materials as those described above in FIG. **9** for the formation of the dielectric layer **132**. The front-side redistribution structure **149** is shown as an example having three layers of metallization patterns. More or fewer dielectric layers and metallization patterns may be formed in the front-side redistribution structure **149**. If fewer dielectric layers and metallization patterns are to be formed, steps and process discussed above may be omitted. If more dielectric layers and metallization patterns are to be formed, steps and processes discussed above may be repeated.

[0044] In FIG. **13**, the dielectric layer **146** is patterned using acceptable photolithography and etching techniques to form openings in the dielectric layer **146** that expose top surfaces of the RDL **144**. A conductive metal such as copper, titanium, or the like, is deposited over the dielectric layer **146** and in the openings in the dielectric layer **146** using for example, sputtering, evaporation, PECVD, or the like. Suitable photolithographic masking and etching process are then used to remove portions of the conductive metal, and the remaining portions of the conductive metal form the underbump metal (UBM) pads **148**. Conductive connectors **150** and conductive connectors **152** are formed on the UBM pads **148**. The conductive connectors **150** and the conductive connectors **152** may be solder balls, metal pillars, metal vias, or the like. The conductive connectors **150** and the conductive connectors **152** may include a conductive material such as solder, or the like. In some embodiments, the conductive connectors **150** and the conductive connectors **152** are formed by initially forming a layer of solder through evaporation, electroplating, printing, solder transfer, ball placement, or the like. Once a layer of solder has been formed on the structure, a reflow may be performed in order to shape the material into the desired bump shapes. Each conductive connector **150** is used to provide electrical input/output (I/O) to circuitry of a respective one of the

plurality of integrated circuit dies **50**. Each conductive connector **152** is electrically connected to a respective TIV grating **120**, and allows for the grounding of the respective TIV grating **120**.

[0045] In FIG. **14A**, a carrier substrate de-bonding is performed to detach (or “de-bond”) the carrier substrate **102** from the dielectric layer **106**. In accordance with some embodiments, the de-bonding includes projecting a light such as a laser light or an UV light on the release layer **104** so that the release layer **104** decomposes under the heat of the light and the carrier substrate **102** can be removed. The dielectric layer **106** provides protection at the bottom side of the first package component **100**. After the carrier substrate **102** is de-bonded from the back-side redistribution structure **105**, a singulation process is then performed by sawing along scribe line regions, e.g., between the first package region **100A** and the second package region **100B**. The sawing singulates the first package region **100A** from the second package region **100B**. The resulting, singulated device stack is from one of the first package region **100A** or the second package region **100B**.

[0046] Further referring to FIG. **14A**, each TIV grating **120** and its adjacent respective TIV plate **121** may be referred to as an antenna **40**. A patch antenna is a microstrip antenna comprising a flat rectangular sheet or “patch” of metal, usually mounted over a larger sheet of metal called a ground plane. In the embodiment described herein, each of the TIV plates **121** function as a “patch antenna” and the adjacent respective TIV grating **120** functions as the corresponding ground plane for the TIV plate **121**. The TIV plate **121** and its respective TIV grating **120** form the antenna **40**. Molding material **128** and a high-k block **126** fills the space between each TIV plate **121** and its respective TIV grating **120**, forming an antenna oscillation cavity structure between the TIV plate **121** and the respective TIV grating **120**, such as between a first sidewall of the TIV grating **120** and a second sidewall of the respective TIV plate **121** that faces the first sidewall. The TIV gratings **120** are electrically grounded when the first package component **100** is installed into its intended application environment. For example, in some embodiments, each of the TIV gratings **120** is electrically connected to conductive connectors **152** using a ground line **140**. The TIV gratings **120** may comprise a conductive mesh, or a set of electrically connected vertical posts or pillars (e.g., having a shape that is rectangular, square, circular, or the like, when seen in a top-down view) that are parallel to each other. The molding material **128** may separate adjacent ones of the TIV gratings **120**. In an embodiment, the TIV gratings **120** may be formed as a solid metal planar structure or any other suitable structure. In an embodiment, the TIV plates **121** may comprise conductive plates. Each of the TIV plates **121** may be electrically connected to one of the plurality of integrated circuit dies **50** by a corresponding feed line **136**. In other embodiments, each TIV grating **120** and its respective TIV plate **121** may be electrically coupled to each other.

[0047] FIG. **14B** illustrates a top-down view of a cross-section of the first package component **100** along a line A-A shown in FIG. **14A**. The first package component **100** may comprise an integrated circuit die **50** having one antenna **40** adjacent to each sidewall of the integrated circuit die **50**, such that the first package component **100** comprises four antennas **40**. In other embodiments, the first package component **100** may have a greater or smaller number of antennas **40**. The TIV plate **121** (e.g., the patch antenna) of each antenna **40** is electrically connected to the integrated circuit die **50** by an antenna feed line **136**. An antenna oscillation cavity is formed between each TIV plate **121** and TIV grating **120** of an antenna **40**. The TIV grating **120** functions as a ground plane for the antenna **40**. Each antenna **40** of the first package component **100** comprises a vertical TIV plate **121** and respective vertical TIV grating **120** to form an antenna oscillation cavity in between the vertical TIV plate **121** and its respective vertical TIV grating **120**. In this way, a major surface of the vertical TIV plate **121** (e.g., the conductive plate) is disposed in a plane that is perpendicular to a major surface of the carrier substrate **102**. The major surface of the vertical TIV plate **121** (e.g., the conductive plate) is also disposed in a plane that is parallel to a sidewall of the integrated circuit die **50**. In addition, a major surface of the TIV grating **120** (e.g., a major surface of each conductive pillar) is disposed in a plane that is perpendicular to a major surface of the carrier substrate **102**. The major surface of the TIV grating **120** (e.g., a major surface of each conductive pillar) is also

disposed in a plane that is parallel to the sidewall of the integrated circuit die **50**. The antenna **40** is a directional antenna which allows it to transmit or receive power in specific directions. Because of the vertical orientations of the TIV plate **121** and TIV grating **120** of each antenna **40**, each antenna **40** is able to transmit or receive 5G & 6G high-frequency radiation in a lateral direction that is parallel to a major surface of the carrier substrate **102**.

[0048] In an embodiment, the first package component **100** may comprise a first antenna **40A** adjacent to a first sidewall of the integrated circuit die **50**, wherein a spacing **S1** between a sidewall of a TIV grating **120** and a sidewall of a respective TIV plate **121** that faces the sidewall of the TIV grating **120** may be in a range from 0.1 μm to 10,000 μm . The first antenna **40A** also comprises molding material **128** disposed between the sidewall of the TIV grating **120** and the sidewall of the respective TIV plate **121**, with no high-k block **126** being present between the sidewall of the TIV grating **120** and the sidewall of the respective TIV plate **121**. In this way, an entirety of a space between the sidewall of the TIV grating **120** and the sidewall of the respective TIV plate **121** that faces the sidewall of the TIV grating **120** is filled with the molding material **128**. As a result, the dielectric constant value of the insulating material of the antenna oscillation cavity structure between the TIV grating **120** and the respective TIV plate **121** is equal to the dielectric constant value of the molding material **128**, the dielectric constant value of the molding material **128** being in a range from 2.0 to 200. The first antenna **40A** having the spacing **S1** in the range from 1 μm to 10,000 μm between the sidewall of the TIV grating **120** and the sidewall of the respective TIV plate **121** that faces the sidewall of the TIV grating **120**, and having the molding material **128** with a dielectric constant value in the range from 2.0 to 200 between the sidewall of the TIV grating **120** and the sidewall of the respective TIV plate **121** will allow the first antenna **40A** to transmit and receive a RF band in a range from 700 MHz to 800 Mhz.

[0049] The first package component **100** may comprise a second antenna **40B** adjacent to a second sidewall of the integrated circuit die **50**, wherein a spacing **S2** between a sidewall of a TIV grating **120** and a sidewall of a respective TIV plate **121** that faces the sidewall of the TIV grating **120** may be in a range from 0.1 μm to 500 μm . The second antenna **40B** also comprises molding material **128** and a high-k block **126A** disposed between the sidewall of the TIV grating **120** and the sidewall of the respective TIV plate **121**, wherein a dielectric constant value of a material of the high-k block **126A** is in a range from 3.9 to 20,000. As a result, the dielectric constant value of the combined insulating material (e.g. of the molding material **128** and the high-k block **126A**) of the antenna oscillation cavity structure between the TIV grating **120** and the respective TIV plate **121** is equal to a weighted average dielectric constant value of the molding material **128** and the high-k block **126A**. The second antenna **40B** having the spacing **S2** in the range from 1 μm to 10,000 μm between the sidewall of the TIV grating **120** and the sidewall of the respective TIV plate **121** that faces the sidewall of the TIV grating **120**, and having the high-k block **126A** with a dielectric constant value in the range from 3.9 to 20,000 between the sidewall of the TIV grating **120** and the sidewall of the respective TIV plate **121** will allow the second antenna **40B** to transmit and receive a RF band in a range from 7 GHz to 8 GHz.

[0050] The first package component **100** may comprise a third antenna **40C** adjacent to a third sidewall of the integrated circuit die **50**, wherein a spacing **S3** between a sidewall of a TIV grating **120** and a sidewall of a respective TIV plate **121** that faces the sidewall of the TIV grating **120** may be in a range from 0.1 μm to 10,000 μm . The third antenna **40C** also comprises molding material **128** and a high-k block **126B** disposed between the sidewall of the TIV grating **120** and the sidewall of the respective TIV plate **121**, wherein a dielectric constant value of a material of the high-k block **126B** is in a range from 3.9 to 30,000. As a result, the dielectric constant value of the combined insulating material (e.g. of the molding material **128** and the high-k block **126B**) of the antenna oscillation cavity structure between the TIV grating **120** and the respective TIV plate **121** is equal to a weighted average dielectric constant value of the molding material **128** and the high-k block **126B**. The third antenna **40C** having the spacing **S3** in the range from 1.0 μm to 100,000 μm

between the sidewall of the TIV grating **120** and the sidewall of the respective TIV plate **121** that faces the sidewall of the TIV grating **120**, and having the high-k block **126B** with a dielectric constant value in the range from 3.9 to 40,000 between the sidewall of the TIV grating **120** and the sidewall of the respective TIV plate **121** will allow the third antenna **40C** to transmit and receive a RF band in a range from 14 GHz to 16 GHz.

[0051] The first package component **100** may comprise a fourth antenna **40D** adjacent to a fourth sidewall of the integrated circuit die **50**, wherein a spacing **S4** between a sidewall of a TIV grating **120** and a sidewall of a respective TIV plate **121** that faces the sidewall of the TIV grating **120** may be in a range from 0.1 μm to 10,00 μm . The fourth antenna **40D** also comprises molding material **128** and a high-k block **126C** disposed between the sidewall of the TIV grating **120** and the sidewall of the respective TIV plate **121**, wherein a dielectric constant value of a material of the high-k block **126C** is in a range from 3.9 to 50,000. As a result, the dielectric constant value of the combined insulating material (e.g. of the molding material **128** and the high-k block **126C**) of the antenna oscillation cavity structure between the TIV grating **120** and the respective TIV plate **121** is equal to a weighted average dielectric constant value of the molding material **128** and the high-k block **126C**. The fourth antenna **40D** having the spacing **S4** in the range from 1.0 μm to 100,000 μm between the sidewall of the TIV grating **120** and the sidewall of the respective TIV plate **121** that faces the sidewall of the TIV grating **120**, and having the high-k block **126C** with a dielectric constant value in the range from 3.9 to 60,000 between the sidewall of the TIV grating **120** and the sidewall of the respective TIV plate **121** will allow the fourth antenna **40D** to transmit and receive a RF band in a range from 28 GHz to 32 GHz. In an embodiment, each of the high-k block **126A**, the high-k block **126B**, and the high-k block **126C** may comprise the width **W3** in a direction that is parallel to a direction moving from the TIV grating **120** to the TIV plate **121** of the respective second antenna **40B**, third antenna **40C**, or fourth antenna **40D**. In addition, each of the high-k block **126A**, the high-k block **126B**, and the high-k block **126C** may comprise the width **W4** in a direction that is perpendicular to a direction moving from the TIV grating **120** to the TIV plate **121** of the respective second antenna **40B**, third antenna **40C**, or fourth antenna **40D**. In an embodiment, the width **W4** is in a range from 100 μm to 500,000 μm . Although four antennas **40** have been illustrated in FIG. **14B**, fewer or more antennas **40** can be incorporated in the first package component **100**. In addition, a larger number of antennas **40** can be incorporated in the first package component **100**, wherein each antenna **40** is able to transmit and receive a different RF band with a different frequency range. This is done by using different high-k blocks **126** comprising different dielectric constant values that are disposed in the antenna oscillation cavity structure between a sidewall of the TIV grating **120** and a sidewall of the respective TIV plate **121** of each antenna **40**, as well as varying a spacing between the sidewall of the TIV grating **120** and the sidewall of the respective TIV plate **121** of each antenna **40**. For example, the first package component **100** may comprise at least 8 antennas **40**, wherein each antenna **40** is able to transmit and receive a different RF band with a different frequency range. In another example, the first package component **100** may comprise more than 20 antennas **40**, wherein each antenna **40** is able to transmit and receive a different RF band with a different frequency range.

[0052] Advantages can be achieved as a result of the formation of the first package component **100** comprising the TIV plates **121** and TIV gratings **120**. One of the high-k blocks **126A-C** is embedded in the molding material **128** between each TIV plate **121** and a respective TIV grating **120** to form an antenna oscillation cavity of each of the second antenna **40B**, third antenna **40C**, and fourth antenna **40D**. Each of the high-k blocks **126A-C** is comprised of a material that is different from materials of the other high-k blocks, and the different materials of the high-k blocks **126A-C** have dielectric constants that are equal to or greater than 3.9. The dielectric constant of a material of each high-k block **126A-C** is different from dielectric constants of materials of the other high-k blocks **126A-C**. In addition, the spacing **S1**, the spacing **S2**, the spacing **S3**, and the spacing **S4** may be varied between the TIV plate **121** and the respective TIV grating **120** of the first antenna

40A, the second antenna **40B**, the third antenna **40C**, and the fourth antenna **40D**, respectively. These advantages may include allow for high-frequency lateral Radio Frequency (RF) transmission suitable for 5G & 6G high-frequency (e.g., 28, 38, 77, and 120 GHz) RF transceivers, as well as portable, wearable, IoT (internet of things) and smart phone products. In addition, forming antenna oscillation cavities comprising the various high-k blocks **126A-C**, wherein each of the high-k blocks **126A-C** comprises a material having a different dielectric constant from materials of the other high-k blocks **126A-C** allows for the transmission and receiving of up to four different RF bands with different frequency ranges. The high-k blocks **126A-C** being disposed between each TIV plate **121** and its respective TIV grating **120** allows for a reduced size of each antenna oscillation cavity, resulting in a reduction in the size of the first package component **100** and making it more compact. Further, because the formation process of the TIV plates **121** and the TIV gratings **120** is compatible with current processes, manufacturing costs are reduced and efficiency is increased.

[0053] FIG. **15** illustrates the first package component **100** in accordance with some other embodiments. FIG. **15** illustrates a top-down view of a cross-section of the first package component **100** along the line A-A shown in FIG. **14A**. Unless specified otherwise, like reference numerals in this embodiment (and subsequently discussed embodiments) represent like components in the embodiment shown in FIGS. **1** through **14B** formed by like processes. Accordingly, the process steps and applicable materials may not be repeated herein. The first package component **100** may comprise an integrated circuit die **50** having eight antennas **40** adjacent to sidewalls of the integrated circuit die **50**. The eight antennas **40** are disposed around a perimeter of the integrated circuit die **50**. In other embodiments, the first package component **100** may have a greater or smaller number of antennas **40**. The TIV plate **121** (e.g., the patch antenna) of each antenna **40** is electrically connected to the integrated circuit die **50** by an antenna feed line **136**. An antenna oscillation cavity is formed between each TIV plate **121** and TIV grating **120** of an antenna **40**. In an embodiment, the eight antennas **40** comprise a first antenna **40E**, a second antenna **40F**, a third antenna **40G**, a fourth antenna **40H**, a fifth antenna **40I**, a sixth antenna **40J**, a seventh antenna **40K**, and an eighth antenna **40L**. In an embodiment, the fourth antenna **40H** and the fifth antenna **40I** may be disposed such that a direction moving from the TIV plate **121** to the TIV grating **120** of each of the fourth antenna **40H** and the fifth antenna **40I** is parallel to a first direction (e.g., the x-direction). The first antenna **40E** may be disposed such that a direction moving from the TIV plate **121** to the TIV grating **120** of the first antenna **40E** is parallel to a second direction (e.g., the y-direction). The second antenna **40F** and the third antenna **40G** may be disposed such that a direction moving from the TIV plate **121** to the TIV grating **120** of each of the second antenna **40F** and the third antenna **40G** is parallel to a third direction (e.g., the negative x-direction). The sixth antenna **40J**, the seventh antenna **40K**, and the eighth antenna **40L** may be disposed such that a direction moving from the TIV plate **121** to the TIV grating **120** of each of the sixth antenna **40J**, the seventh antenna **40K**, and the eighth antenna **40L** is parallel to a fourth direction (e.g., the negative y-direction).

[0054] In an embodiment, the first antenna **40E** may comprise a spacing **S5** between a sidewall of a TIV grating **120** and a sidewall of a respective TIV plate **121** that faces the sidewall of the TIV grating **120**, wherein the spacing **S5** may be in a range from 0.1 μm to 100,000 μm . The first antenna **40E** also comprises molding material **128** disposed between the sidewall of the TIV grating **120** and the sidewall of the respective TIV plate **121**, with no high-k block **126** being present between the sidewall of the TIV grating **120** and the sidewall of the respective TIV plate **121**. In this way, an entirety of a space between the sidewall of the TIV grating **120** and the sidewall of the respective TIV plate **121** that faces the sidewall of the TIV grating **120** is filled with the molding material **128**. As a result, the dielectric constant value of the insulating material of the antenna oscillation cavity structure between the TIV grating **120** and the respective TIV plate **121** is equal to the dielectric constant value of the molding material **128**, the dielectric constant value of the

molding material **128** being in a range from 2.0 to 40,000. The first antenna **40E** having the spacing **S5** in the range from 0.1 μm to 100,000 μm between the sidewall of the TIV grating **120** and the sidewall of the respective TIV plate **121** that faces the sidewall of the TIV grating **120**, and having the molding material **128** with a dielectric constant value in the range from 2.0 to 200 between the sidewall of the TIV grating **120** and the sidewall of the respective TIV plate **121** will allow the first antenna **40E** to transmit and receive a RF band in a range from 700 MHz to 800 Mhz.

[0055] The second antenna **40F** may comprise a spacing **S6** between a sidewall of a TIV grating **120** and a sidewall of a respective TIV plate **121** that faces the sidewall of the TIV grating **120**, wherein the spacing **S6** may be in a range from 0.1 μm to 100,000 μm . The second antenna **40F** also comprises molding material **128** and a high-k block **126D** disposed between the sidewall of the TIV grating **120** and the sidewall of the respective TIV plate **121**, wherein a dielectric constant value of a material of the high-k block **126D** is in a range from 2.0 to 10,000. As a result, the dielectric constant value of the combined insulating material (e.g. of the molding material **128** and the high-k block **126D**) of the antenna oscillation cavity structure between the TIV grating **120** and the respective TIV plate **121** is equal to a weighted average dielectric constant value of the molding material **128** and the high-k block **126D**. The second antenna **40F** having the spacing **S6** in the range from 0.1 μm to 100,000 μm between the sidewall of the TIV grating **120** and the sidewall of the respective TIV plate **121** that faces the sidewall of the TIV grating **120**, and having the high-k block **126D** with a dielectric constant value in the range from 2.0 to 10,000 between the sidewall of the TIV grating **120** and the sidewall of the respective TIV plate **121** will allow the second antenna **40F** to transmit and receive a RF band in a range from 7 GHz to 8 GHz.

[0056] The third antenna **40G** may comprise a spacing **S7** between a sidewall of a TIV grating **120** and a sidewall of a respective TIV plate **121** that faces the sidewall of the TIV grating **120**, wherein the spacing **S7** may be in a range from 0.1 μm to 200,000 μm . The third antenna **40G** also comprises molding material **128** and a high-k block **126E** disposed between the sidewall of the TIV grating **120** and the sidewall of the respective TIV plate **121**, wherein a dielectric constant value of a material of the high-k block **126E** is in a range from 2.0 to 20,000. As a result, the dielectric constant value of the combined insulating material (e.g. of the molding material **128** and the high-k block **126E**) of the antenna oscillation cavity structure between the TIV grating **120** and the respective TIV plate **121** is equal to a weighted average dielectric constant value of the molding material **128** and the high-k block **126E**. The third antenna **40G** having the spacing **S7** in the range from 0.1 μm to 200,000 μm between the sidewall of the TIV grating **120** and the sidewall of the respective TIV plate **121** that faces the sidewall of the TIV grating **120**, and having the high-k block **126E** with a dielectric constant value in the range from 2.0 to 20,000 between the sidewall of the TIV grating **120** and the sidewall of the respective TIV plate **121** will allow the third antenna **40G** to transmit and receive a RF band in a range from 14 GHz to 16 GHz.

[0057] The fourth antenna **40H** may comprise a spacing **S8** between a sidewall of a TIV grating **120** and a sidewall of a respective TIV plate **121** that faces the sidewall of the TIV grating **120**, wherein the spacing **S8** may be in a range from 0.1 μm to 300,000 μm . The fourth antenna **40H** also comprises molding material **128** and a high-k block **126F** disposed between the sidewall of the TIV grating **120** and the sidewall of the respective TIV plate **121**, wherein a dielectric constant value of a material of the high-k block **126F** is in a range from 2.0 to 30,000. As a result, the dielectric constant value of the combined insulating material (e.g. of the molding material **128** and the high-k block **126F**) of the antenna oscillation cavity structure between the TIV grating **120** and the respective TIV plate **121** is equal to a weighted average dielectric constant value of the molding material **128** and the high-k block **126F**. The fourth antenna **40H** having the spacing **S8** in the range from 0.1 μm to 400,000 μm between the sidewall of the TIV grating **120** and the sidewall of the respective TIV plate **121** that faces the sidewall of the TIV grating **120**, and having the high-k block **126F** with a dielectric constant value in the range from 2.0 to 30,000 between the sidewall of the TIV grating **120** and the sidewall of the respective TIV plate **121** will allow the fourth antenna

40H to transmit and receive a RF band in a range from 28 GHz to 32 GHz.

[0058] The fifth antenna **40I** may comprise a spacing **S9** between a sidewall of a TIV grating **120** and a sidewall of a respective TIV plate **121** that faces the sidewall of the TIV grating **120**, wherein the spacing **S9** may be in a range from 0.1 μm to 500,000 μm . The fifth antenna **40I** also comprises molding material **128** and a high-k block **126G** disposed between the sidewall of the TIV grating **120** and the sidewall of the respective TIV plate **121**, wherein a dielectric constant value of a material of the high-k block **126G** is in a range from 2.0 to 40,000. As a result, the dielectric constant value of the combined insulating material (e.g. of the molding material **128** and the high-k block **126G**) of the antenna oscillation cavity structure between the TIV grating **120** and the respective TIV plate **121** is equal to a weighted average dielectric constant value of the molding material **128** and the high-k block **126G**. The fifth antenna **40I** having the spacing **S9** in the range from 0.1 μm to 600,000 μm between the sidewall of the TIV grating **120** and the side wall of the respective TIV plate **121** that faces the sidewall of the TIV grating **120**, and having the high-k block **126G** with a dielectric constant value in the range from 2.0 to 40,000 between the sidewall of the TIV grating **120** and the sidewall of the respective TIV plate **121** will allow the fifth antenna **40I** to transmit and receive a RF band in a range from 56 GHz to 64 GHz.

[0059] The sixth antenna **40J** may comprise a spacing **S10** between a sidewall of a TIV grating **120** and a sidewall of a respective TIV plate **121** that faces the sidewall of the TIV grating **120**, wherein the spacing **S10** may be in a range from 0.1 μm to 700,000 μm . The sixth antenna **40J** also comprises molding material **128** and a high-k block **126H** disposed between the sidewall of the TIV grating **120** and the sidewall of the respective TIV plate **121**, wherein a dielectric constant value of a material of the high-k block **126H** is in a range from 2.0 to 50,000. As a result, the dielectric constant value of the combined insulating material (e.g. of the molding material **128** and the high-k block **126H**) of the antenna oscillation cavity structure between the TIV grating **120** and the respective TIV plate **121** is equal to a weighted average dielectric constant value of the molding material **128** and the high-k block **126H**. The sixth antenna **40J** having the spacing **S10** in the range from 0.1 μm to 700,000 μm between the sidewall of the TIV grating **120** and the sidewall of the respective TIV plate **121** that faces the sidewall of the TIV grating **120**, and having the high-k block **126H** with a dielectric constant value in the range from 2.0 to 60,000 between the sidewall of the TIV grating **120** and the sidewall of the respective TIV plate **121** will allow the sixth antenna **40J** to transmit and receive a RF band in a range from 112 GHz to 128 GHz.

[0060] The seventh antenna **40K** may comprise a spacing **S11** between a sidewall of a TIV grating **120** and a sidewall of a respective TIV plate **121** that faces the sidewall of the TIV grating **120**, wherein the spacing **S11** may be in a range from 0.1 μm to 800,000 μm . The seventh antenna **40K** also comprises molding material **128** and a high-k block **126I** disposed between the sidewall of the TIV grating **120** and the sidewall of the respective TIV plate **121**, wherein a dielectric constant value of a material of the high-k block **126I** is in a range from 2.0 to 70,000. As a result, the dielectric constant value of the combined insulating material (e.g. of the molding material **128** and the high-k block **126I**) of the antenna oscillation cavity structure between the TIV grating **120** and the respective TIV plate **121** is equal to a weighted average dielectric constant value of the molding material **128** and the high-k block **126I**. The seventh antenna **40K** having the spacing **S11** in the range from 0.1 μm to 900,000 μm between the sidewall of the TIV grating **120** and the sidewall of the respective TIV plate **121** that faces the sidewall of the TIV grating **120**, and having the high-k block **126I** with a dielectric constant value in the range from 2.0 to 80,000 between the sidewall of the TIV grating **120** and the sidewall of the respective TIV plate **121** will allow the seventh antenna **40K** to transmit and receive a RF band in a range from 224 GHz to 256 GHz.

[0061] The eighth antenna **40L** may comprise a spacing **S12** between a sidewall of a TIV grating **120** and a sidewall of a respective TIV plate **121** that faces the sidewall of the TIV grating **120**, wherein the spacing **S12** may be in a range from 0.1 μm to 1000,000 μm . The eighth antenna **40L** also comprises molding material **128** and a high-k block **126J** disposed between the sidewall of the

TIV grating **120** and the sidewall of the respective TIV plate **121**, wherein a dielectric constant value of a material of the high-k block **126J** is in a range from 2.0 to 90,000. As a result, the dielectric constant value of the combined insulating material (e.g. of the molding material **128** and the high-k block **126J**) of the antenna oscillation cavity structure between the TIV grating **120** and the respective TIV plate **121** is equal to a weighted average dielectric constant value of the molding material **128** and the high-k block **126J**. The eighth antenna **40L** having the spacing **S12** in the range from 0.1 μm to 1100,000 μm between the sidewall of the TIV grating **120** and the sidewall of the respective TIV plate **121** that faces the sidewall of the TIV grating **120**, and having the high-k block **126J** with a dielectric constant value in the range from 2.0 to 100,000 between the sidewall of the TIV grating **120** and the sidewall of the respective TIV plate **121** will allow the eighth antenna **40L** to transmit and receive a RF band in a range from 448 GHz to 512 GHz. Although eight antennas **40** have been illustrated in FIG. **15**, fewer or more antennas **40** can be incorporated in the first package component **100**. In addition, a larger number of antennas **40** can be incorporated in the first package component **100**, wherein each antenna **40** is able to transmit and receive a different RF band with a different frequency range. This is done by using different high-k blocks **126** comprising different dielectric constant values that are disposed in the antenna oscillation cavity structure between a sidewall of the TIV grating **120** and a sidewall of the respective TIV plate **121** of each antenna **40**, as well as varying a spacing between the sidewall of the TIV grating **120** and the sidewall of the respective TIV plate **121** of each antenna **40**. In an embodiment, each of the high-k block **126D**, the high-k block **126E**, the high-k block **126F**, the high-k block **126G**, the high-k block **126H**, the high-k block **126I**, and the high-k block **126J** may comprise the width **W3** in a direction that is parallel to a direction moving from the TIV grating **120** to the TIV plate **121** of the respective second antenna **40F**, third antenna **40G**, fourth antenna **40H**, fifth antenna **40I**, sixth antenna **40J**, seventh antenna **40K** or eighth antenna **40L**. In addition, each of high-k block **126D**, the high-k block **126E**, the high-k block **126F**, the high-k block **126G**, the high-k block **126H**, the high-k block **126I**, and the high-k block **126J** may comprise the width **W4** in a direction that is perpendicular to a direction moving from the TIV grating **120** to the TIV plate **121** of the respective second antenna **40F**, third antenna **40G**, fourth antenna **40H**, fifth antenna **40I**, sixth antenna **40J**, seventh antenna **40K** or eighth antenna **40L**.

[0062] Advantages can be achieved as a result of the formation of the first package component **100** comprising the TIV plates **121** and TIV gratings **120**. One of the high-k blocks **126D-J** is embedded in the molding material **128** between each TIV plate **121** and a respective TIV grating **120** to form an antenna oscillation cavity of each of the second antenna **40F**, third antenna **40G**, fourth antenna **40H**, fifth antenna **40I**, sixth antenna **40J**, seventh antenna **40K** and eighth antenna **40L**. Each of the high-k blocks **126D-J** is comprised of a material that is different from materials of the other high-k blocks **126D-J**, and the different materials of the high-k blocks **126D-J** have dielectric constants that are equal to or greater than 3.9. The dielectric constant of a material of each high-k block **126D-J** is different from dielectric constants of materials of the other high-k blocks **126D-J**. In addition, the spacings **S5** through **S12** may be varied between the TIV plate **121** and the respective TIV grating **120** of the first antenna **40E** through the eighth antenna **40L**, respectively. These advantages may include allow for high-frequency lateral Radio Frequency (RF) transmission suitable for 5G & 6G high-frequency (e.g., 28, 38, 77, and 120 GHz) RF transceivers, as well as portable, wearable, IoT (internet of things) and smart phone products. In addition, forming antenna oscillation cavities comprising the various high-k blocks **126D-J**, wherein each of the high-k blocks **126D-J** comprises a material having a different dielectric constant from materials of the other high-k blocks **126D-J** allows for the transmission and receiving of up to eight different RF bands with different frequency ranges. The high-k blocks **126D-J** being disposed between each TIV plate **121** and its respective TIV grating **120** allows for a reduced size of each antenna oscillation cavity, resulting in a reduction in the size of the first package component **100** and making it more compact. Further, because the formation process of the TIV plates **121** and the TIV gratings **120** is

compatible with current processes, manufacturing costs are reduced and efficiency is increased. [0063] FIG. 16 illustrates the first package component 100 in accordance with some other embodiments. FIG. 16 illustrates a top-down view of a cross-section of the first package component 100 along the line A-A shown in FIG. 14A. Unless specified otherwise, like reference numerals in this embodiment (and subsequently discussed embodiments) represent like components in the embodiment shown in FIGS. 1 through 15 formed by like processes. Accordingly, the process steps and applicable materials may not be repeated herein. The first package component 100 may comprise an integrated circuit die 50 having eight antennas 40 adjacent to sidewalls of the integrated circuit die 50. The eight antennas 40 are disposed around a perimeter of the integrated circuit die 50. In other embodiments, the first package component 100 may have a greater or smaller number of antennas 40. In an embodiment, the eight antennas 40 comprise the first antenna 40E, the second antenna 40F, the third antenna 40G, the fourth antenna 40H, the fifth antenna 40I, the sixth antenna 40J, the seventh antenna 40K, and the eighth antenna 40L that were described earlier in FIG. 15. In an embodiment, the sixth antenna 40J, the seventh antenna 40K and the eighth antenna 40L may be disposed such that a direction moving from the TIV plate 121 to the TIV grating 120 of each of the sixth antenna 40J, the seventh antenna 40K and the eighth antenna 40L is parallel to a first direction (e.g., the x-direction). The first antenna 40E may be disposed such that a direction moving from the TIV plate 121 to the TIV grating 120 of the first antenna 40E is parallel to a second direction (e.g., the y-direction). The third antenna 40G, the fourth antenna 40H, and the fifth antenna 40I may be disposed such that a direction moving from the TIV plate 121 to the TIV grating 120 of each of the third antenna 40G, the fourth antenna 40H, and the fifth antenna 40I is parallel to a third direction (e.g., the negative x-direction). The second antenna 40F may be disposed such that a direction moving from the TIV plate 121 to the TIV grating 120 of the second antenna 40F is parallel to a fourth direction (e.g., the negative y-direction). Although eight antennas 40 have been illustrated in FIG. 16, fewer or more antennas 40 can be incorporated in the first package component 100. In addition, a larger number of antennas 40 can be incorporated in the first package component 100, wherein each antenna 40 is able to transmit and receive a different RF band with a different frequency range. This is done by using different high-k blocks 126 comprising different dielectric constant values that are disposed in the antenna oscillation cavity structure between a sidewall of the TIV grating 120 and a sidewall of the respective TIV plate 121 of each antenna 40, as well as varying a spacing between the sidewall of the TIV grating 120 and the sidewall of the respective TIV plate 121 of each antenna 40.

[0064] In FIG. 17, a schematic diagram of a simulation result for different insulating materials is shown, in accordance with some embodiments. The antenna configuration for the simulation is similar to the structure shown in FIG. 14A with the resonance frequency set at about 77 GHz. Two different insulating film materials are simulated and the performances of their S-parameters S11 (generic representation of a signal return loss) are compared. Referring to FIG. 17, a line 370 and a line 372 represent the simulation results for the materials with dielectric constants of around 3.0 and 83, respectively. As shown in FIG. 17, the first material with a dielectric constant of 3.0 exhibits a return loss in a range from -10 dB to 0 dB with a local minimum at around 75-88 GHz. In contrast, the second dielectric material with a dielectric constant of 83 exhibits a signal loss in a range from -62 dB to -23 dB. Specifically, the second dielectric material provides a sharper frequency selectivity gain at a valley around 76 GHz.

[0065] In accordance with an embodiment, a package structure includes a first die; an insulating material around the first die; a first antenna extending through the insulating material, where the first antenna includes a first conductive plate extending through the insulating material; and a plurality of first conductive pillars extending through the insulating material, where the first conductive plate is disposed between the plurality of first conductive pillars and the first die; and a first high-k block embedded in the insulating material, where the first high-k block is disposed between the first conductive plate and the plurality of first conductive pillars, and where the first

high-k block includes a material having a dielectric constant that is different than a dielectric constant of the insulating material. In an embodiment, the dielectric constant of the material of the first high-k block is higher than the dielectric constant of the insulating material. In an embodiment, the insulating material separates adjacent ones of the plurality of first conductive pillars. In an embodiment, a major surface of the first conductive plate and a major surface of each first conductive pillar of the plurality of first conductive pillars is disposed in a plane that is parallel to a first sidewall of the first die. In an embodiment, the package structure further includes a second antenna extending through the insulating material, where the second antenna includes a second conductive plate extending through the insulating material; a plurality of second conductive pillars extending through the insulating material, where the second conductive plate is disposed between the plurality of second conductive pillars and the first die; and a second high-k block embedded in the insulating material, where the second high-k block is disposed between the second conductive plate and the plurality of second conductive pillars. In an embodiment, the first antenna is adjacent to a first sidewall of the first die, and the second antenna is adjacent to a second sidewall of the first die. In an embodiment, the dielectric constant of the material of the first high-k block is higher than the dielectric constant of the insulating material, and where a dielectric constant of a material of the second high-k block is higher than the dielectric constant of the material of the first high-k block. In an embodiment, the first high-k block and the second high-k block include SiO₂, Si₃N₄, Al₂O₃, Y₂O₃, TiO₂, HfO₂, ZrO₂, PbZrTiO₃, BaTiO₃, BaSrTiO₃, or SrTiO₃.

[0066] In accordance with an embodiment, a package includes a first polymer layer; an insulating material over the first polymer layer; a die embedded in the insulating material; a first antenna including a first portion extending through the insulating material to a first feed line that electrically connects the die and the first portion of the first antenna; and a second portion extending through the insulating material, the second portion of the first antenna including a plurality of conductive pillars, where the first antenna has a first spacing between a first sidewall of the first portion and a second sidewall of the second portion that faces the first sidewall of the first portion; and a second antenna including a third portion extending through the insulating material to a second feed line that electrically connects the die and the third portion of the second antenna; and a fourth portion extending through the insulating material, the fourth portion of the second antenna including a plurality of conductive pillars, where the second antenna has a second spacing between a third sidewall of the third portion and a fourth sidewall of the fourth portion that faces the third sidewall of the first portion, where the first spacing is different from the second spacing. In an embodiment, the package further includes a first redistribution structure over the die and the insulating material; a first conductive connector electrically connected to the die through the first redistribution structure; and second conductive connectors electrically connected to the second portion of the first antenna and the fourth portion of the second antenna through the first redistribution structure. In an embodiment, the package further includes a first cuboid disposed between the first portion of the first antenna and the second portion of the first antenna; and a second cuboid disposed between the third portion of the second antenna and the fourth portion of the second antenna. In an embodiment, the first cuboid includes a first material with a first dielectric constant, where the second cuboid includes a second material with a second dielectric constant, and where the first dielectric constant and the second dielectric constant are different. In an embodiment, the first cuboid and the second cuboid include SiO₂, Si₃N₄, Al₂O₃, Y₂O₃, TiO₂, HfO₂, ZrO₂, PbZrTiO₃, BaTiO₃, BaSrTiO₃, or SrTiO₃. In an embodiment, the package further includes a third antenna including a fifth portion extending through the insulating material to a third feed line that electrically connects the die and the fifth portion of the third antenna; and a sixth portion extending through the insulating material, the sixth portion of the third antenna including a plurality of conductive pillars, where the third antenna has a third spacing between a fifth sidewall of the fifth

portion and a sixth sidewall of the sixth portion that faces the fifth sidewall of the fifth portion, where the third spacing is different from the second spacing and the first spacing. In an embodiment, an entirety of a space between the fifth portion and the sixth portion of the third antenna is filled with the insulating material.

[0067] In accordance with an embodiment, a method of forming a package includes forming a first polymer layer over a substrate; forming a plurality of first conductive pillars and a first conductive plate on the first polymer layer; attaching a die to the first polymer layer, where the first conductive plate is disposed between the plurality of first conductive pillars and the die; attaching a high-k block to the first polymer layer, where the high-k block is disposed between the plurality of first conductive pillars and the first conductive plate; forming a molding material over the first polymer layer, where the molding material surrounds the die, the high-k block, the plurality of first conductive pillars and the first conductive plate, where a dielectric constant of a material of the high-k block is different from a dielectric constant of the molding material. In an embodiment, the method further includes forming a first redistribution structure over the die, the high-k block, the molding material, the plurality of first conductive pillars and the first conductive plate, where a first feed line in the first redistribution structure electrically connects the die to the first conductive plate. In an embodiment, the dielectric constant of the material of the high-k block is higher than the dielectric constant of the molding material. In an embodiment, the dielectric constant of the material of the high-k block is equal to or greater than 3.9. In an embodiment, attaching the die to the first polymer layer and attaching the high-k block to the first polymer layer is performed at the same time.

[0068] The foregoing outlines features of several embodiments so that those skilled in the art may better understand the aspects of the present disclosure. Those skilled in the art should appreciate that they may readily use the present disclosure as a basis for designing or modifying other processes and structures for carrying out the same purposes and/or achieving the same advantages of the embodiments introduced herein. Those skilled in the art should also realize that such equivalent constructions do not depart from the spirit and scope of the present disclosure, and that they may make various changes, substitutions, and alterations herein without departing from the spirit and scope of the present disclosure.

Claims

1. A package structure comprising: a first die; an insulating material around the first die; a first antenna extending through the insulating material and disposed adjacent to a first sidewall of the first die, wherein the first antenna comprises: a first conductive plate extending through the insulating material; and a plurality of first conductive pillars extending through the insulating material; a second antenna extending through the insulating material and disposed adjacent to a second sidewall of the first die, wherein the second antenna comprises: a second conductive plate extending through the insulating material; and a plurality of second conductive pillars extending through the insulating material; a first high-k block embedded in the insulating material and disposed between the first conductive plate and the plurality of first conductive pillars; and a second high-k block embedded in the insulating material and disposed between the second conductive plate and the plurality of second conductive pillars.
2. The package structure of claim 1, wherein the first high-k block and the second high-k block comprise SiO₂, Si₃N₄, Al₂O₃, Y₂O₃, TiO₂, HfO₂, ZrO₂, PbZrTiO₃, BaTiO₃, BaSrTiO₃, or SrTiO₃.
3. The package structure of claim 1, wherein the dielectric constant of a material of the first high-k block and the dielectric constant of a material of the second high-k block is higher than the dielectric constant of the insulating material.
4. The package structure of claim 3, wherein the dielectric constant of the material of the first high-

k block is higher than the dielectric constant of the material of the second high-k block.

5. The package structure of claim 1, wherein the first sidewall of the first die and the second sidewall of the first die are parallel to each other.

6. The package structure of claim 5, further comprising: a third antenna extending through the insulating material and disposed adjacent to a third sidewall of the first die, wherein the third antenna comprises: a third conductive plate extending through the insulating material; and a plurality of third conductive pillars extending through the insulating material; and a third high-k block embedded in the insulating material and disposed between the third conductive plate and the plurality of third conductive pillars.

7. The package structure of claim 6, wherein the dielectric constant of a material of the third high-k block is higher than the dielectric constant of a material of the first high-k block.

8. The package structure of claim 6, wherein the third sidewall of the first die is perpendicular to the first sidewall of the first die and the second sidewall of the first die.

9. A package comprising: an insulating material over a polymer layer; a first die embedded in the insulating material; a first antenna disposed adjacent a first sidewall of the first die, the first antenna comprising: a first portion extending through the insulating material; and a second portion extending through the insulating material, the second portion of the first antenna comprising a plurality of conductive pillars, wherein the first portion of the first antenna is disposed between the second portion of the first antenna and the first sidewall of the first die; and a second antenna disposed adjacent a second sidewall of the first die, the second antenna comprising: a third portion extending through the insulating material; and a fourth portion extending through the insulating material, the fourth portion of the second antenna comprising a plurality of conductive pillars, wherein the third portion of the second antenna is disposed between the fourth portion of the second antenna and the second sidewall of the first die.

10. The package of claim 9, wherein the first sidewall of the first die and the second sidewall of the first die are parallel to each other.

11. The package of claim 9, wherein the first sidewall of the first die and the second sidewall of the first die are perpendicular to each other.

12. The package of claim 9, further comprising: a first high-k block disposed between the first portion of the first antenna and the second portion of the first antenna; and a second high-k block disposed between the third portion of the second antenna and the fourth portion of the second antenna.

13. The package of claim 12, wherein a material of the first high-k block, a material of the second high-k block, and a material of the insulating material are different from each other.

14. The package of claim 13, wherein the material of the first high-k block and the material of the second high-k block comprise SiO₂, Si₃N₄, Al₂O₃, Y₂O₃, TiO₂, HfO₂, ZrO₂, PbZrTiO₃, BaTiO₃, BaSrTiO₃, or SrTiO₃.

15. The package of claim 9, further comprising: a first redistribution structure over the first die and the insulating material; a first conductive connector electrically connected to the first die through the first redistribution structure; and second conductive connectors electrically connected to the second portion of the first antenna and the fourth portion of the second antenna through the first redistribution structure.

16. A method of forming a package, the method comprising: forming a first dielectric layer over a substrate; forming a plurality of first conductive pillars and a first conductive plate on the first dielectric layer; forming a plurality of second conductive pillars and a second conductive plate on the first dielectric layer; attaching a die to the first dielectric layer, wherein the die is disposed between the first conductive plate and the second conductive plate; attaching a first high-k block to the first dielectric layer, wherein the first high-k block is disposed between the plurality of first conductive pillars and the first conductive plate; and attaching a second high-k block to the first dielectric layer, wherein the second high-k block is disposed between the plurality of second

conductive pillars and the second conductive plate, wherein the dielectric constant of a material of the first high-k block is different from the dielectric constant of a material of the second high-k block.

17. The method of claim 16, wherein the material of the first high-k block and the material of the second high-k block comprise SiO.sub.2, Si.sub.3N.sub.4, Al.sub.2O.sub.3, Y.sub.2O.sub.3, TiO.sub.2, HfO.sub.2, ZrO.sub.2, PbZrTiO.sub.3, BaTiO.sub.3, BaSrTiO.sub.3, or SrTiO.sub.3.

18. The method of claim 16, further comprising: forming a molding material over the first dielectric layer, wherein the molding material surrounds the die, the first high-k block, the second high-k block, the plurality of first conductive pillars, the first conductive plate, the plurality of second conductive pillars, and the second conductive plate.

19. The method of claim 18, wherein the dielectric constant of the material of the first high-k block and the dielectric constant of the material of the second high-k block are different from the dielectric constant of the molding material.

20. The method of claim 18, further comprising: forming a first redistribution structure over the die, the first high-k block, the second high-k block, the molding material, the plurality of first conductive pillars, the first conductive plate, the plurality of second conductive pillars, and the second conductive plate, wherein a first feed line in the first redistribution structure electrically connects the die to the first conductive plate, and wherein a second feed line in the first redistribution structure electrically connects the die to the second conductive plate.
