

US Patent & Trademark Office

Patent Public Search | Text View

United States Patent	12401554
Kind Code	B2
Date of Patent	August 26, 2025
Inventor(s)	Briseno-Vidrios; Carlos Jesus et al.

Demodulator for an isolation communication channel for dual communication

Abstract

An integrated circuit includes a demodulator to demodulate a signal simultaneously transmitted over an isolation communication channel and obtain gate information and configuration information. The demodulator includes a gate demodulation path and a configuration demodulation path. The received signal oscillates at a first frequency to represent a first state, oscillates at different frequencies to represent a second state, oscillates at a third frequency (or third and fourth frequencies), which are lower than the first frequency, to represent a third state, and the received signal is steady state to represent a fourth state. The gate demodulation path detects the first and second states. The configuration demodulation path includes first and second sub-demodulation paths. An envelope detector in the first sub-demodulation path detects the second state and the second sub-demodulation path detects the third state. The configuration demodulation paths uses an output of the gate demodulation path.

Inventors: Briseno-Vidrios; Carlos Jesus (Austin, TX), May; Michael R. (Austin, TX), De Bakker; Patrick (Hollis, NH)

Applicant: Skyworks Solutions, Inc. (Irvine, CA)

Family ID: 1000008778985

Assignee: Skyworks Solutions, Inc. (Irvine, CA)

Appl. No.: 18/655034

Filed: May 03, 2024

Prior Publication Data

Document Identifier	Publication Date
US 20240291699 A1	Aug. 29, 2024

Related U.S. Application Data

Publication Classification

Int. Cl.: H04L27/06 (20060101); H03K17/56 (20060101); H03M1/38 (20060101)

U.S. Cl.:

CPC H04L27/06 (20130101); H03K17/56 (20130101); H03M1/38 (20130101)

Field of Classification Search

CPC: H04L (27/06); H03M (1/38); H03K (17/56)

References Cited

U.S. PATENT DOCUMENTS

Patent No.	Issued Date	Patentee Name	U.S. Cl.	CPC
6100717	12/1999	May	N/A	N/A
6611553	12/2002	Scott et al.	N/A	N/A
7701731	12/2009	Dhuyvetter et al.	N/A	N/A
7864546	12/2010	Dhuyvetter et al.	N/A	N/A
8064872	12/2010	Dupuis	N/A	N/A
8462003	12/2012	Ng et al.	N/A	N/A
8847503	12/2013	Chang et al.	N/A	N/A
9000675	12/2014	Chang et al.	N/A	N/A
9584147	12/2016	Glibbery et al.	N/A	N/A
9608623	12/2016	Kandah et al.	N/A	N/A
9812989	12/2016	Dupuis	N/A	N/A
9966837	12/2017	Seaton	N/A	N/A
10097166	12/2017	Ludicky	N/A	N/A
10097338	12/2017	Ng	N/A	N/A
10651752	12/2019	Liu et al.	N/A	N/A
11050369	12/2020	Schneider	N/A	N/A
11121892	12/2020	Pinto et al.	N/A	N/A
11418179	12/2021	Ding	N/A	N/A
11539559	12/2021	Briseno-Vidrios et al.	N/A	N/A
11575305	12/2022	May et al.	N/A	N/A
11888658	12/2023	Briseno-Vidrios et al.	N/A	N/A
11962233	12/2023	May et al.	N/A	N/A
12034577	12/2023	Briseno-Vidrios et al.	N/A	N/A
12218576	12/2024	May et al.	N/A	N/A
2003/0040289	12/2002	Collin et al.	N/A	N/A
2003/0215020	12/2002	Dong et al.	N/A	N/A

2005/0036247	12/2004	Liu	N/A	N/A
2006/0008075	12/2005	Scott et al.	N/A	N/A
2006/0291589	12/2005	Eliezer et al.	N/A	N/A
2007/0242780	12/2006	May et al.	N/A	N/A
2008/0025450	12/2007	Alfano et al.	N/A	N/A
2008/0192509	12/2007	Dhuyvetter et al.	N/A	N/A
2008/0218258	12/2007	Crawley	330/10	H03F 3/45183
2009/0017773	12/2008	Dupuis et al.	N/A	N/A
2009/0147545	12/2008	Melanson	N/A	N/A
2009/0206817	12/2008	Ng et al.	N/A	N/A
2009/0212759	12/2008	Melanson	N/A	N/A
2009/0213914	12/2008	Dong et al.	N/A	N/A
2009/0243765	12/2008	Blanke et al.	N/A	N/A
2010/0052826	12/2009	Callahan et al.	N/A	N/A
2010/0118918	12/2009	Dupuis	N/A	N/A
2013/0009674	12/2012	Reese et al.	N/A	N/A
2013/0099817	12/2012	Haigh	N/A	N/A
2013/0264961	12/2012	Chang et al.	N/A	N/A
2013/0278438	12/2012	Mueck	N/A	N/A
2013/0279611	12/2012	Mueck et al.	N/A	N/A
2014/0049297	12/2013	Nagai et al.	N/A	N/A
2014/0169038	12/2013	Kamath et al.	N/A	N/A
2014/0328427	12/2013	Chang et al.	N/A	N/A
2015/0171901	12/2014	Dupuis et al.	N/A	N/A
2015/0180228	12/2014	Mills et al.	N/A	N/A
2015/0234415	12/2014	Sicard et al.	N/A	N/A
2016/0056829	12/2015	Glibbery et al.	N/A	N/A
2017/0033603	12/2016	Peter et al.	N/A	N/A
2018/0013419	12/2017	Imanishi et al.	N/A	N/A
2018/0062678	12/2017	Ragonese et al.	N/A	N/A
2018/0109256	12/2017	Burton et al.	N/A	N/A
2019/0215920	12/2018	Clauberg et al.	N/A	N/A
2019/0222107	12/2018	Morokuma et al.	N/A	N/A
2019/0222126	12/2018	Parisi et al.	N/A	N/A
2019/0229603	12/2018	Dubois et al.	N/A	N/A
2019/0267985	12/2018	Li et al.	N/A	N/A
2019/0348355	12/2018	May et al.	N/A	N/A
2019/0355506	12/2018	Fei et al.	N/A	N/A
2019/0386651	12/2018	Ying et al.	N/A	N/A
2020/0076416	12/2019	Bang et al.	N/A	N/A
2020/0266718	12/2019	Liu et al.	N/A	N/A
2021/0036662	12/2020	Al-Shyouch	N/A	N/A
2021/0250021	12/2020	Bang et al.	N/A	N/A
2022/0014016	12/2021	Jin	N/A	N/A
2022/0115941	12/2021	May et al.	N/A	N/A
2022/0116249	12/2021	Briseno-Vidrios et al.	N/A	N/A
2022/0116250	12/2021	Briseno-Vidrios et al.	N/A	N/A

2022/0311433	12/2021	Miatton et al.	N/A	N/A
2022/0385258	12/2021	Zhan et al.	N/A	N/A
2023/0117387	12/2022	Morici et al.	N/A	N/A
2023/0208688	12/2022	Briseno-Vidrios et al.	N/A	N/A
2023/0216717	12/2022	Bendotti et al.	N/A	N/A
2023/0387782	12/2022	May et al.	N/A	N/A
2024/0113924	12/2023	Briseno-Vidrios et al.	N/A	N/A
2024/0348146	12/2023	May et al.	N/A	N/A

FOREIGN PATENT DOCUMENTS

Patent No.	Application Date	Country	CPC
2014-207668	12/2013	JP	N/A
WO 2022/076682	12/2021	WO	N/A

OTHER PUBLICATIONS

Analog Devices, “Single Gate, Adjustable Slew Rate, Isolated Gate Driver, 3 A Short-Circuit (<3 Q),” ADuM4122 Data Sheet, downloaded from <https://www.analog.com/en/search.html?q=adum4122>, Jun. 16, 2020, 18 pages. cited by applicant

Frank, et al., “Real-Time Adjustable Gate Current Control IC Solves DV/DT Problems in Electric Drives,” PCIM Europe, May 20-24, 2014, Infineon Technologies AG Germany, ISPN 978-3-8007-3603-4, pp. 98-104. cited by applicant

Infineon, EiceDRIVER™ High Voltage Gate Driver IC With Reinforced Isolation, Final Data Sheet Revision 2.1, Oct. 22, 2018, 34 pages. cited by applicant

Silicon Labs, “AN1009: Driving MOSFET and IGBT Switches Using the Si828x,” Rev. 0.1, downloaded from <https://www.silabs.com/.../AN1009-driving-mosfet-and-igbt-switches-using-the-si828x> on Aug. 28, 2020, 22 pages. cited by applicant

International Search Report and Written Opinion, re Application No. PCT/US2021/053967, mailed Jan. 27, 2022. cited by applicant

International Preliminary Report on Patentability, re Application No. PCT/US2021/053967, mailed Mar. 28, 2023. cited by applicant

U.S. Appl. No. 17/991,495, filed Nov. 21, 2022. cited by applicant

Primary Examiner: Guarino; Rahel

Attorney, Agent or Firm: Knobbe, Martens, Olson & Bear, LLP

Background/Summary

CROSS-REFERENCE TO RELATED APPLICATION(S)

(1) Any and all applications for which a foreign or domestic priority claim is identified in the Application Data Sheet as filed with the present application are hereby incorporated by reference under 37 CFR 1.57, and should be considered a part of this specification.

(2) This application relates to the application entitled “Transmitter For Dual Communication Over An Isolation Channel,” application Ser. No. 17/066,244, filed Oct. 8, 2020; and this application relates to the patent application entitled “Interface For Passing Control Information Over An Isolation Channel,” application Ser. No. 17/066,251, filed Oct. 8, 2020, all of which applications were filed on the same day as the present application and all of which applications are incorporated

herein by reference.

BACKGROUND

Field of the Invention

(3) The invention relates to isolation technology and more particularly to communication across an isolation barrier.

Description of the Related Art

(4) Isolation communication channels are utilized in various applications where necessary to prevent current flow between isolated electric circuits by using an isolation barrier while still maintaining communication between the circuits. The isolation may be required for signal isolation, safety, or for other reasons. Communication between isolated circuits has typically involved a transmitter and receiver communicating over an isolation communication channel to provide, e.g., control information between the different voltage domains. The isolation communication channel may be implemented, e.g., using capacitive, inductive (transformers), or optical (opto-isolators) isolation techniques. In a typical isolation application, a control system provides one or more control signals for controlling a load system. During normal operation, a large DC or transient voltage difference may exist between the domain of the control system and the domain of the load system, thus requiring an isolation barrier between the control system and the load system. Isolation of the circuits in the separate voltage domains using an isolation barrier prevents damaging currents from flowing between the control system and the load system by a direct conduction path, while the isolation communication channel allows communication between the two systems.

(5) FIG. 1 illustrates a prior art system **100** that includes an isolated gate driver **101**. The gate driver **101** receives control information for driving a gate signal of a high-power transistor **102** that is electrically isolated from the control functionality providing the control information. In the exemplary system **100**, controller **103**, which may be a microprocessor, microcontroller, or other suitable processing device, operates in a first domain (i.e., a domain including VDD1 and VDD2). The controller **103** provides a gate signal to control a load system operating in a second domain i.e., a domain including VDD3 and VDD4. The isolation barrier electrically isolates the primary side including VDD1 (e.g., less than twenty volts) and VDD2 (e.g., less than twenty volts) and devices coupled thereto, from the secondary side including VDD3 (e.g., tens of volts) and VDD4 (e.g., hundreds of volts) and devices coupled thereto.

(6) The isolated gate driver **101** includes a transmitter circuit **106** and a receiver circuit **108**, which communicate over an isolation communication channel **109**. In the system **100**, controller **103** supplies gate information (GATE) to the transmitter circuit **106** in the first voltage domain. The transmitter circuit **106** transmits the gate information to the receiver circuit **108** in the second voltage domain. The receiver circuit **108** uses the gate information to generate a gate drive signal **120** to drive the high-power transistor **102** that is used to control a system load.

(7) While the isolated gate driver allows communication across the isolation barrier, improvements in such communication is desirable to provide more precise control over the system load.

SUMMARY OF EMBODIMENTS OF THE INVENTION

(8) Accordingly, in one embodiment a method includes receiving a signal transmitted across a single isolation communication channel as a received signal. The method further includes demodulating the received signal to determine respective values for gate information and configuration information contained in the received signal based on which of four states the received signal represents.

(9) In another embodiment, an apparatus includes one or more input terminals to receive a signal transmitted across an isolation communication channel. A demodulator circuit is coupled to the one or more input terminals to demodulate a received signal to obtain gate information and to obtain configuration information. Respective values of the gate information and the configuration information are determined according to which one of four states the demodulator circuit detects in

the received signal.

(10) In another embodiment an integrated circuit includes a demodulator to demodulate a signal received from an isolation communication channel to obtain gate information and configuration information simultaneously transmitted over the isolation communication channel. The demodulator includes a plurality of demodulation paths. The signal includes a first state in which the signal oscillates at a first frequency for a first bit time, a second state wherein the signal oscillates at different frequencies during a second bit time, a third state in which the signal oscillates at a third frequency lower than the first frequency during at least a portion of a third bit time, and a fourth state in which the signal is steady state for a fourth bit time. An envelope detector in one of the demodulation paths detects the second state.

Description

BRIEF DESCRIPTION OF THE DRAWINGS

- (1) The present invention may be better understood, and its numerous objects, features, and advantages made apparent to those skilled in the art by referencing the accompanying drawings.
- (2) FIG. 1 illustrates a prior art system with an isolated gate driver.
- (3) FIG. 2A illustrates a system with an isolated gate driver with two isolation communication channels to transmit gate and configuration information.
- (4) FIG. 2B illustrates an embodiment of an isolated gate driver that transmits two types of information across a single isolation communication channel.
- (5) FIG. 3 illustrates traditional on-off keying (OOK).
- (6) FIG. 4 illustrates an embodiment of a high level block diagram of a transmit side of an isolated gate driver.
- (7) FIG. 5 illustrates a serial word for transmission across an isolation communication channel that provide drive strength information.
- (8) FIG. 6 illustrates an embodiment of a configuration detect and map circuit.
- (9) FIG. 7 illustrates an embodiment of mapping configuration parameters to drive current strength.
- (10) FIG. 8 illustrates an embodiment of a modulation scheme that allows sending configuration information and gate information simultaneously.
- (11) FIG. 9 illustrates a high level diagram of a modified OOK modulator.
- (12) FIG. 10 illustrates a block diagram of an embodiment of a receive circuit.
- (13) FIG. 11 illustrates additional aspects of an embodiment of the demodulator portion of the receive circuit.
- (14) FIG. 12 illustrates waveforms showing operation of the demodulator portion.
- (15) FIG. 13 illustrates the fast and slow paths of the configuration demodulation according to an embodiment.
- (16) FIG. 14 illustrates additional details of an embodiment of the envelope detector.
- (17) FIG. 15 illustrates processing of the serial out data from the configuration demodulator.
- (18) FIG. 16 illustrates a sampling circuit to sample the data from the configuration demodulator.
- (19) FIG. 17 illustrates a timing diagram of the sampling circuit.
- (20) FIG. 18 illustrates an embodiment showing how the drive strength information is used to control the drive strength of transistors generating the gate signal.
- (21) FIG. 19 illustrates an embodiment showing how the drive strength information is used to generate a gate signal combined off-chip.
- (22) The use of the same reference symbols in different drawings indicates similar or identical items.

DETAILED DESCRIPTION

- (23) A typical CMOS digital isolation solution has a single communication channel **109** as shown

in FIG. 1. A second isolation communication channel would normally be required to dynamically transmit information other than gate information, such as status bits, configuration bits, etc., through the isolation barrier. The gate signal is a critical control function that cannot be delayed while configuration information is being sent. Accordingly, referring to FIG. 2A, in order to provide configuration information in addition to the gate information, e.g., dynamic drive strength information, the system **200** utilizes an isolated gate driver **201** with a separate isolation communication channel **210** to send the configuration information. Separate transmitter circuits **206A** and **206B** transmit the gate and configuration information, respectively, to receiver circuits **208A** and **208B** on the secondary side utilizing the two isolation communication channels **209** and **210**. The transmitter circuit **206A** transmits the gate information over the first isolation communication channel **209**. The transmitter circuit **206B** transmits the configuration information (information other than gate information), over the second communication channel **210**. The illustrated differential isolation communication channels **209** and **210** each transmit a positive (TX-P) signal and a negative signal (TX-N). The illustrated isolation communication channels **209** and **210** utilize capacitive isolation although other embodiments may utilize various approaches to isolation such as inductive coupling or optical coupling to communicatively couple the transmit circuits **206A** and **206B** and the receive circuits **208A** and **208B**. Thus, the physical implementation of the isolation communication channels may differ in different embodiments.

(24) The secondary side includes driver circuitry (e.g., included in receiver circuit **208A**), that generates gate signal **216** based on the GATE signal received from the primary side and provides the gate signal **216** to the gate of device **218**. In an example embodiment, the high-power device **218** controls power delivered to a load. Exemplary high-power devices include power metal-oxide-semiconductor field-effect transistors (MOSFETs), insulated-gate bipolar transistors (IGBTs), Gallium-Nitride (GaN) MOSFETs, Silicon-Carbide (SiC) power MOSFETs, and other suitable devices able to deliver high power signals.

(25) In embodiments there are two aspects of the gate signal **216** that are controlled. The receive circuit **208A** controls both whether the gate signal is on or off and also controls the drive strength of the gate signal **216** based on configuration information received from the receive circuit **208B**.

(26) Thus, as explained above, in one approach the second isolation communication channel carries configuration information. While providing a communication path for configuration information is beneficial, the second communication channel **210** consumes additional power and requires additional silicon area. In addition, package limitations can often prevent the inclusion of a second isolation communication channel. In order to overcome package limitations and the disadvantages due to additional power and area of a second isolation communication channel, while still providing dynamic configuration information, embodiments described herein send configuration information simultaneously with the main digital gate signal over a single isolation communication channel without affecting the main performance requirements of the main digital signal.

(27) Referring to FIG. 2B, in an exemplary embodiment, the system **220** includes an isolated gate driver **221** that includes a transmitter circuit **226** and a receiver circuit **227** communicatively coupled across an isolation barrier through use of isolation communication channel **228**. The system **220** includes a primary side integrated circuit (containing transmitter **226**) and a secondary side integrated circuit (containing receiver **227**) respectively disposed in first and second voltage domains. In embodiments, transmitter circuit **226** is formed on a first integrated circuit die and receiver circuit **227** is formed on a second integrated circuit die, both of which are attached to a lead frame and include terminals coupled to isolation channel **228** formed on the lead frame and packaged as a single device. In still other embodiments, transmitter circuit **226** and receiver circuit **227** include terminals coupled to the isolation communication channel **228**, all of which are formed on an integrated circuit die. In still other embodiments transmitter circuit **226** and receiver circuit **227** are integrated circuits included in a multi-chip module. In embodiments, terminals of the transmitter circuit and receiver circuit are coupled to external elements, e.g., transformers, discrete

resistors, and discrete capacitors within the multi-chip module or to terminals of the package of the multi-chip module, and to a package of controller **222**.

(28) In embodiments the transmitter circuit **226** and receiver circuit **227** utilize modified on-off keying (OOK) to allow the main digital signal to be sent simultaneously with configuration information over the single isolation communication channel **228**. Compared with a two channel implementation shown in FIG. 2A in which one channel is used for the main digital signal and the other channel is used for configuration information, embodiments described herein use a single isolation communication channel thereby consuming less power and utilizing less silicon die area. In an example, as described further herein, the single isolation communication channel **228** carries both gate information for gate signal **230** to drive transistor **232** and drive strength information for the gate signal **230**.

(29) FIG. 3 illustrates traditional on-off keying (OOK) modulation. OOK is a form of amplitude-shift keying modulation that represents digital data as the presence or absence of a high frequency signal on the communication channel. For example, when the GATE signal (e.g. to drive the gate of transistor **232** in FIG. 2B) is a logic “0”, the transmitter transmits a steady state signal (OV) at **301** on the differential isolation channel (TXP-TXN) where TXP is the positive transmitted signal and TXN is the negative transmitted signal for the differential pair. When the GATE signal is a “1”, the transmitter transmits a high frequency signal at **303** over the isolation communication channel, e.g., with a frequency of 500 MHz. Thus, the presence of the high frequency represents a binary one, while its absence represents a binary zero. However, traditional OOK can only send one piece of data at a time. In contrast, embodiments described herein transmit the main digital signal (e.g., the gate signal) along with configuration (or other) information over the single isolation communication channel. The main digital signal can be a logical one or a zero and at the same time the configuration information can also be a logical one or zero regardless of the logical value of the main digital signal.

(30) FIG. 4 illustrates a high level block diagram of an embodiment of the transmit side **400** of an isolated gate driver. In the illustrated embodiment, gate information **401** from controller **222** (FIG. 2B) provides the information used for the main digital signal—the gate signal. In addition, the transmit side receives configuration information on input terminals **403** and **405**. The configuration information may be provided in various forms, such as an analog voltage, a current, a digital voltage, or through resistance values of resistors coupled to the input terminals **403** and **405**. The transmitter circuit transmits the configuration information simultaneously with the gate information over a single isolation communication channel. The configuration detect and map circuit **407** receives the parameters (voltage, current, digital value, resistance) present on input terminals **403** and **405** and maps the parameters to a particular drive strength value. In an embodiment, the configuration detect and map logic is made aware of whether to map voltage values, current values, digital values, or resistance values to the drive strength. That may be accomplished through a one-time programmable memory (OTP) that is programmed with the type of parameters being supplied to the isolated gate driver. In an embodiment, the configuration detect and map logic maps the configuration information to a three bit value (P2, P1, P0) for configuration CONFIG1 and a three bit value (N2, N1, N0) for CONFIG2. In an embodiment, P2, P1, P0 controls the drive strength of the gate signal generated by PFETs when the gate signal is pulled up and N2, N1, N0 controls the drive strength of the gate signal generated NFETs when the gate signal is pulled down. The configuration detect and map circuit **307** supplies the three bit digital values to the parallel to serial logic circuit **409** that converts the parallel bits to a serial word. In an embodiment, the parallel to serial logic circuit **409** also adds a start bit, parity, and redundancy to the serial word, as shown in FIG. 5, for transmission across the isolation communication channel. For example, bit (P2) and its complement (P2) are transmitted over the isolation communication channel. Other embodiments add additional parity bits to provide for multi-bit error correction or for other error checking techniques. Each serial bit is transmitted on the isolation communication channel along with a

value of the GATE signal. A typical serial bit time is 1 or 2 us but other embodiments use a bit time of a different length. Logic **409** supplies the serial word to the transmit OOK modulation circuit **411**, which is described further herein. The transmit OOK modulator also receives the gate signal from input terminal **401**.

(31) FIGS. **6** and **7** illustrate additional details of the configuration detect and mapping circuit **401**. In an embodiment, the resistance values of resistors **601** and **603** coupled to input terminals **403** and **405** determine the drive current strength of the gate signals. The current from current sources **607** and **608** cause voltages across resistor **601** and variable resistor **609**, and comparator **610** receives the two voltages. The successive approximation register (SAR) **611** adjusts the variable resistor **609** until the comparator **610** indicates the voltages on its inputs are equal, e.g., when the comparator output changes polarity, thereby indicating that the SAR setting corresponds to the value of the external resistor **601**. Mapping logic **615** maps the final SAR value (or equivalent resistance value) to a three bit code indicating drive current strength as explained in more detail in the example of FIG. **7**. The configuration information on input terminal **405** is similarly determined using current sources **617** and **619**, variable resistor **621**, comparator **623**, and SAR **625**. SAR **625** is adjusted until the voltages at the inputs of comparator **623** are the same, thereby indicating the value of external resistor **603**.

(32) In another embodiment a voltage level is supplied on input terminals **403** and **405** to specify the configuration information rather than using resistors **601** and **603**. In such an embodiment, rather than connecting resistors, the controller **222** (see FIG. **2B**) supplies a voltage to the input terminals from, e.g., a digital to analog converter (DAC) in the controller. To operate in the “analog voltage” mode, the current source **607** is turned off and current source **608** supplies a known current to variable resistor **609**. The SAR **611** adjusts the variable resistance until the comparator **610** indicates the voltages at its inputs are equal. The voltage across the variable resistor **609** is supplied to the mapping logic or the SAR output (the variable resistance setting) is interpreted as an estimate of the voltage level seen at terminal **403**. The detection of the voltage on input terminal **405** is similarly accomplished. The current source **617** is turned off and current source **619** supplies a known current. SAR **625** adjusts the variable resistance **621** until the comparator **623** indicates the voltages at its inputs are equal. The voltage across the variable resistor **621** (or the SAR output) is supplied to the mapping logic **615**, which interprets the SAR setting as an estimate of the voltage seen at terminal **405**.

(33) In still another mode of operation, rather than resistors or analog voltages being applied to the input terminals receiving configuration information, a digital value is applied to the input terminals allowing the selection of two different values for the configuration information on each input terminal. In an embodiment of “digital” mode, the current source **607** is turned off and the current source **608** supplies a current to a fixed resistance value of the variable resistor **609** that causes a threshold voltage value to be supplied to the comparator. That threshold voltage distinguishes a logic 1 from a logic 0. The comparator output may be supplied directly to the mapping logic **615**. In other digital embodiments, a separate comparator is used to determine a logic 0 or 1. In still other embodiments, one or more of terminals **403** and **405** function as a serial input port and the configuration is supplied in a digital word allowing greater selection of configuration settings. The circuitry associated with input terminal **405** operates in digital mode in a similar manner to the operation of the circuits described with relation in input terminal **403**. Many other circuits can be used to determine voltages, resistance, current, capacitance, or other parameters values on terminal **403** and **405**. The circuits shown in FIG. **6** are examples and many other circuits can be used to receive and determine parameter values that would be apparent to those of skill in the art.

(34) FIG. **7** illustrates an embodiment of the mapping functionality, which maps resistance, analog voltage, or digital values to a particular configuration value. In an embodiment, the mode of operation (analog resistance, analog voltage, digital) is programmed into a one time programmable memory **625**, e.g., through an interface **627**. In other embodiments the mode of operation may be

programmed into the other kinds of memory in the transmitter integrated circuit, e.g., non-volatile memory (NVM). With reference to the embodiment of FIG. 7, in “analog resistance” mode **701**, resistance values map to configuration states S0-S7, represented by 3 bits. The three bits map to eight different drive current strengths shown as drive current strength percentages **705**. FIG. 7 shows that the various configuration states S0-S7 map to a particular percentage drive current strengths ranging from 8.75% to 100% of the maximum drive current. For example, a resistance near the value of 4.42 k Ω (state S2) maps to a 17.5% drive current strength. Thus, 17.5% of a maximum drive current strength is utilized to drive at least one value of the gate signal. The particular percentages are only examples and other embodiments may utilize different percentages of drive current strength and a different number of configuration bits. Note that the resistance values are illustrative and other resistance values may be used in other embodiments.

(35) The table in FIG. 7 also shows how in “analog voltage” mode voltage levels **703** on the input terminals map to the different configuration states. For example, a voltage level near 221 mV (state S2) maps to a drive current strength percentage of 17.5%. In voltage mode, a controller (e.g., controller **222** in FIG. 2B) supplies the voltage to the input terminal. While an analog voltage mode is shown, other embodiments use an analog current and map analog current values to the configuration states.

(36) In “digital mode” an external controller, e.g., controller **222** (FIG. 2B) drives the configuration terminals with digital signals and states S0 and S8 are mapped to arbitrary drive strength values shown as p/nfet_str_low and p/nfet_str_high. For example a digital “0” on pin **403** maps to p/nfet_str_low and a digital “1” on pin **403** maps to p/nfet_str_high, and a digital “0” on pin **405** maps to n/nfet_str_low and a digital “1” on pin **405** maps to n/nfet_str_high. PFET and NFET transistors (see, e.g., FIG. 18) are used to generate the gate drive signal. In an embodiment, the drive strength values for digital mode are programmed into OTP (or NVM). The particular mappings for resistance, voltage, and percentages may also be programmed into the memory (OTP, NVM, or other) used by the mapping logic **615**.

(37) In an embodiment, the configuration terminals also provide a disable feature to disable the transmitter. A bit in memory (OTP, NVM, or other) is set to indicate the disable feature is enabled. The disable feature disables the transmit signal path in the transmit circuit if the state S8 is received in either the analog (resistance or voltage) or digital mode. The disable feature may cause 0V to be coupled to the transmit signal path or otherwise disable transmissions. In analog voltage mode a voltage >850 mV maps to S8 and in analog resistance mode a high impedance (hiZ) value maps to S8. In digital mode a logical 1 indicates the S8 state and thus disable mode. With the disable feature enabled, the digital mode only provides a single drive current strength value in S0. With this disable feature, a single pin can be used the control both the drive strength and enable/disable function of the transmitter, thus allowing more features in a smaller pin count package.

(38) In an embodiment, an additional bit(s) in memory (OTP, NVM, or other) indicates use of a single pin (rather than two) to indicate signal strength. In an embodiment, the additional bit always indicates a particular input terminal is to be used, e.g., if the single pin bit is set, always use input terminal **403**. In other embodiments, additional bits may be used in single pin mode to indicate which input terminal is the “single pin.” Thus, in the single pin mode the drive strength information from only one of the configuration pins is used to generate both P2, P1, P0 and N2, N1, N0. With the single pin mapping to both P and N functions, drive strength control can be utilized in reduced pin count packages where only a single pin is available for strength control function. Embodiment may include capability to support any or all of the several modes of operation, including analog/digital, disable/not disable, and single pin/not single pin.

(39) Referring again to FIG. 6, once mapping is complete, the parallel data is converted to serial in logic **409** and a start bit, redundancy (to the extent desired) and parity is added for serial transmission across the isolation communication. The serial data is supplied to the OOK modulator **411**, which modulates the serial configuration data and the gate signal. FIGS. 8 and 9 illustrates

operation of the OOK modulator.

(40) FIG. 8 illustrates an embodiment of the modulation scheme that allows sending both configuration information and gate information simultaneously. To transmit configuration information having a value of CONFIG=0, with GATE=0, a constant voltage is sent as shown at **801**. For CONFIG=1 and GATE=0 the signal is modulated at a frequency of 64 MHz as shown at **802**. For CONFIG=0 and GATE=1, as shown at **803**, the signal is frequency modulated at the OOK frequency. In an embodiment the OOK frequency is 450 MHz. The OOK frequency should be high enough to readily distinguish from the lower frequency signal when CONFIG=1 and GATE=0. Finally, for GATE=1 and CONFIG=1, the signal is frequency modulated at two frequencies during the bit time with a first frequency shown at **805** and a second frequency shown at **807**. The frequencies are contained in envelope **809**. In an embodiment, the frequency shown at **807** is 450 MHz and the frequency shown in **805** is 550 MHz and the envelope **809** is an 8 MHz envelope. Thus, the modulator is responsive to the GATE signal to provide straight OOK modulation (a 0 or 450 MHz signal) with the CONFIG signal at 0 and provides an adjustment to the OOK signal with the CONFIG signal=1 (~64 MHz or 450/550 MHz). Note that the frequency deviation of the transmitted signal is substantially larger in response to changes in the GATE signal as compared to changes in the CONFIG signal. For example, changes in the GATE signal cause the modulation frequency to change from 0 to 450 MHz. In contrast, changes in the CONFIG signal, assuming the GATE signal is constant, cause the modulation frequency to change from 0 to 64 MHz or from 450 MHz to 550 MHz. This frequency separation helps ensure an accurate demodulation of the GATE signal.

(41) FIG. 9 illustrates an embodiment of the OOK modulator **411**. The modulated signal generated is based on the values of the CONFIG signal **901** and the GATE signal **903** to generate the signal shown in FIG. 8 that represents four states (two binary values for CONFIG and two binary values for GATE). The AND gate **905** receives the CONFIG signal **901** and the envelope signal **911**. Oscillator control logic **908** receives the output of AND gate **905** and controls whether oscillator **909** generates a 450 MHz signal or a 550 MHz signal. An output of 0 from AND gate **905** causes the oscillator **909** to generate a 450 MHz signal and an output of 1 causes the oscillator to generate a 550 MHz signal. The oscillator **909** may be implemented as a ring oscillator with different taps for different frequencies or different supply voltages or currents, an LC oscillator with adjustable capacitance, or any other suitable oscillator. With CONFIG=0, the oscillator **909** generates a 450 MHz signal and with CONFIG=1 the oscillator **909** generates the 450 MHz signal and the 550 MHz signal at a rate determined by the frequency of the envelope signal **911**. For example, with an 8 MHz envelope signal, the 450 MHz signal and the 550 MHz signals repeat at an 8 MHz rate as shown in FIG. 8. The divider circuit **915** divides the oscillator output signal by 8 or other appropriate divide value to readily distinguish the lower frequency signal from the 450/550 MHz signal. With CONFIG=0, AND gate **917** supplies a 0 to multiplexer **919**. Multiplexer **919** receives an input signal from the oscillator **909** and another input signal from AND gate **917**. The value of the GATE signal selects the input provided on the output of multiplexer **919**. With GATE=1, the multiplexer selects the oscillator output signal (450 MHz or 450/550 MHz) as the multiplexer output signal depending on the value of CONFIG. With GATE=0, the multiplexer selects the output of AND gate **917**, corresponding to the signals shown **801** or **802**. AND gate **917** supplies either a 0, with CONFIG=0 or the output of divider **915** with CONFIG=1. Note that in the embodiment of FIG. 9, with CONFIG=1, and GATE=0, the divider divides the oscillator output that varies according to the envelope signal. Thus, the divide by 8 signal is 450/8 MHz and 550/8 MHz with the envelope signal **911** determining the rate of change between the two frequencies. In other embodiments, the GATE signal is also supplied to control logic **908** and having GATE=0 and CONFIG=1 and the control logic **908** forces the oscillator output to be fixed at either 450 MHz or 550 MHz in that state and thus the frequency at **802** to be fixed at 56.25 MHz or 68.75 MHz. The 64 MHz signal represents a suitable frequency for that particular state with GATE=0 and

CONFIG=1 but the frequency can be higher, lower, or varying according to the particular embodiment. The signal from multiplexer **919** is then supplied to drivers **921** and **923** and transmitted over the isolation communication channel. The transmitted signal is then received by the receiver coupled to the isolation communication channel, and is sent to a demodulator to recover the GATE signal and the CONFIG signal. The GATE signal controls the transistor coupled to the receiver circuit and the CONFIG information is de-serialized to recover the configuration bits, which are then used, e.g., to control the drive strength of the GATE signal.

(42) The drive strength aspects of the modulator shown in FIG. **9** is easily disabled, e.g., by setting CONFIG **901** to 0, and then the OOK signal returns to a traditional OOK modulation with a 1 indicated by a 450 MHz signal and a 0 indicated by a steady state voltage such as 0V. In that way, in applications where no drive strength signal is provided, the modified OOK modulator can operate as a standard OOK modulator. In an embodiment, the configuration of this modified OOK modulator into a standard OOK modulator is implemented by OTP control in a similar way as described in other aspects of embodiments described herein.

(43) Another embodiment waits until GATE=1 to transmit configuration information. The OOK signal is frequency modulated to represent CONFIG=1 (or 0) as shown at **805** and **807** and the OOK signal is a fixed frequency as shown at **803** to represent a CONFIG=0 (or 1). That approach has the benefits of being simpler but limits the transition to only when the main signal (e.g., GATE) is one. Also, instead of frequency modulation, other embodiments pulse width modulate the OOK signal when GATE=1, but that approach becomes more difficult for high OOK frequencies in which the pulse width is small.

(44) Various other modulation schemes can be used. For example, four frequencies can be used to represent the four states represented by GATE and CONFIG. In some of these embodiments, the GATE signal changing causes a much larger frequency deviation at the output of the modulator than changes in the CONFIG signal. In this way, the integrity of the GATE signal could be maintained while only relatively small frequency changes caused by the CONFIG signal would only cause minor changes to the demodulation of the GATE signal. Alternatively, various patterns of 1s and 0s may be used during a bit time to represent different values.

(45) FIG. **10** illustrates a block diagram of portions of an embodiment of the receiver **227** shown in FIG. **2B**. The receiver receives a differential signal that was transmitted over the isolation communication channel and is received as the differential signals RXP and RXN. Those signals are amplified in one or more amplifiers **1001** and supplied to an OOK demodulator **1003** to demodulate gate information from the received differential signal and supply the gate signal **1005**. The gate signal and the received signal, after amplification, are supplied to a configuration demodulation path **1007** that extracts the configuration information from the received differential signal and supplies the configuration information to the clock recovery, deserializer, and error check circuit **1009**. The clock recovery, deserializer, and error check circuit **1009** converts the serial data stream received over the isolation communication channel to a parallel word of configuration information, e.g., 3 bits, to apply as drive strength signals to the driver control logic **1010**. Thus, the clock recovery, deserializer, and error check circuit **1009** recovers a clock signal to sample the serial out data **1012** from the configuration demodulation path **1007**, recreates P2, P1, P0 and N2, N1, and N0, checks the parity bits, redundancy bits, or otherwise performs the error checking to ensure the data is correct before updating the configuration setting of the driver control circuit **1010**. If errors are found, the drive strength values are not updated. Other configuration settings may also be controlled by the configuration information transmitted. For example, the configuration information can specify the type of error reporting desired, default values for drive strength, or turn on and off times for the high-power transistor. In the embodiment of FIG. **10** two output terminals **1020** and **1022** are used to supply the turn on and turn off signals for the gate signal, which are combined externally to drive the power transistor. The VOP pin **1020** provides the positive drive current to turn on the power transistor and the VON pin **1022** provides the sinking

current to turn off the power transistor. Other embodiments utilize a single output terminal for the gate signal. The strengths of the drive currents provided by the driver control logic **1010** are controlled by the configuration information.

(46) FIG. **11** illustrates additional details of an embodiment of the demodulator in the receive circuit. The demodulator includes a gate demodulation path **1101** and a configuration demodulation path **1102**. FIG. **12** illustrates example waveforms involved in the demodulation of the transmitted signal. In the example waveforms of FIG. **12** ISORX **1104**, the received signal after amplification, starts at a state representing CONFIG=1 and GATE=0 (oscillating at 64 MHz) and then changes to CONFIG=0 and GATE=1 (oscillating at 450 MHz). With reference to FIGS. **11** and **12**, the amplifier **1103** supplies an amplifier output ISORX **1104** to a filter **1105**. In an embodiment, filter **1105** is implemented as a bandpass filter with a center frequency around 500 MHz, and a bandwidth such that it can pass 450 MHz and 550 MHz, but will reject other frequencies such as 64 MHz, and those frequencies associated with noise in the system. The filter **1105** supplies a filter output **1106** as an input to a root mean square (RMS) detect circuit **1107**. The RMS detect circuit **1105** detects the energy in the received signal and supplies an RMS output signal **1108**. to comparator **1109** and comparator **1111**. The comparator **1109** compares the RMS detect output **1108** to a reference voltage REF1 shown in FIG. **12**. In FIG. **12**, the RMS output **1108** is below REF1 (when ISORX oscillates at 64 MHz) until **1201** at which time the RMS output signal **1108** goes above the voltage threshold REF1 indicating the RMS value corresponds to an oscillation value of at least 450 MHz. At that time the GATE signal **1110** goes from 0 to 1. Note that if the oscillation was 450/550 MHz (GATE=1, CONFIG=1), the GATE signal supplied by comparator **1109** would still be a 1 as the RMS detect output **1108** would still be above REF1. Thus, gate demodulation path **1101** functions as an OOK demodulator and looks for oscillations at or above a certain frequency (450 Mhz) and ignores oscillations below that frequency, thus ignoring the modifications to the OOK signal caused by CONFIG=1, when GATE=0, resulting in ISORX oscillating at approximately 64 MHz. When the RMS detect output rise above REF1, the GATE signal **1110** from the comparator **1109** goes to one and when the RMS detect output falls below REF1, the gate signal **1110** goes to 0.

(47) In one part of the configuration demodulation path, comparator **1111** compares the output **1108** of the RMS detect circuit **1107** to the voltage threshold REF0. As shown in FIG. **12** the compare results in an oscillating signal **1115** at 128 MHz when ISORX is oscillating at 64 MHz (GATE=0 and CONFIG=1). When ISORX is 0, the slow path signal is zero and when ISORX is 450 MHz or 450/550 MHz, the slow path signal **1115** is a “1”. The comparator **1111** supplies the slow path signal **1115** to the digital demodulation block **1118**, which includes sub-demodulation paths described further herein.

(48) The fast path signal **1117** of the configuration demodulation path comes from the output **1104** of the amplifier **1103** and the fast path signal is supplied (with the 8 MHz envelope present when GATE=1 and CONFIG=1 and without the envelope present when GATE=1 and CONFIG=0) to the digital demodulation block **1118**. Schmitt trigger **1120** converts the output of the amplifier **1103** (after a buffer circuit) to a digital value for the digital demodulation block **1118**. Note that some circuits in the gate demodulation path and the configuration demodulation path are shared.

(49) FIG. **13** illustrates additional details of sub-demodulation paths **1301** (slow path) and **1303** (fast path) of the configuration demodulation path and some common elements in the configuration demodulation path including the selector circuit **1305** and the counter **1307**. Selector circuit **1305** selects the fast path signal or the slow path signal according to the value of the GATE signal **1110**. If the GATE signal is “1”, implying the transmitted signal is at least 450 MHz, the selector circuit **1305** selects the fast path signal **1117**. If the GATE signal is “0”, implying the transmitted signal is ~ 64 MHz (varying between 56.25 MHz and 68.75 MHz in the embodiment illustrated in FIG. **9**), or lower in frequency, the selector circuit selects the slow path signal **1115**. The ripple counter **1307** counts the number of pulses from the fast path signal or slow path signal and supplies the count

value to the fast path sub-demodulation path **1303** and to the slow path sub-demodulation path. The counter **1307** is periodically reset by reset signal **1306**. The slow path sub-demodulation path **1301** receives the count value **1308** and compares the count value to integer values to see if the count value is within a frequency range bounded by the integer values M and N. If the count value is above a minimum value M and below a maximum value N, then the frequency of the slow path signal is within the frequency range (e.g., a frequency range including 128 MHz) and the output **1312** from AND gate **1310** goes to a “1”. If count value is below M, e.g., CONFIG=0 then AND gate **1310** supplies a “0” on output **1312**. If the count value is above N, indicating the slow path signal has a higher frequency than, e.g., ~128 MHz, then AND gate **1310** supplies a “0”.

(50) The fast path sub-demodulation path **1303** receives the count value at compare logic **1314** and selector circuit **1316**. The compare logic **1314** determines if the count value is greater than or equal to an integer P, thereby indicating the frequency of the transmitted signal (and the fast path signal) is above a predetermined frequency, e.g. 450 MHz. If the counter value **1308** is less than P, the selector circuit **1316** selects 0 and otherwise selects the count value. The envelope detector **1318** detects the presence of an envelope, e.g., the 8 MHz envelope shown in FIG. 8. In an embodiment the envelope detector **1318** implements a single frequency of a discrete Fourier transform (DFT) to find the energy at 8 MHz and detect the envelope. Thus, if the count value is changing between periodic resets based on a 450 MHz/550 MHz transmitted signal (GATE=1, CONFIG=1), the envelope is detected and the output of the envelope detector goes to “1”. If on the other hand, no envelope is detected, e.g., the transmitted signal is 450 MHz 1 (GATE=1, CONFIG=0) the output of the envelope detector is “0”. The output **1320** of the envelope detector is combined in OR gate **1322** with the output **1312** of AND gate **1310**. A filter, e.g., a finite impulse response (FIR) filter **1323** removes glitches from the output of OR gate **1320** and supplies a serial output **1324**. Additional filters, e.g., additional FIR filters, may be used in the fast sub-demodulation path and slow sub-demodulation path that are not shown for ease of illustration. The compare logic compares the count value from counter **1307** to M, N, and P in an embodiment using 4 samples per 8 MHz envelope (using a 32 MHz internal clock signal) in the fast path and a similar number of counts are obtained for the 128 MHz input to the slow path. In an embodiment, the comparison is made only for the selected path (active path) with the non-selected path output to OR gate **1322** being forced to zero. The idea is that only one of the slow and fast paths is active at any point in time.

(51) FIG. 14 illustrates additional details of the envelope detector **1318**. The DFT **1402** supplies a filter **1404**. The filter output is squared in **1406** and comparator **1408** compares the bin energy from **1406** to a reference value corresponding to the bin energy that would be present if the envelope were present at a minimum amplitude value. If the bin energy is greater than the reference, the envelope detector supplies a “1” and if the bin energy is not greater than the reference, the envelope detector supplies a “0”.

(52) Referring to FIG. 15, the serial output **1324** from the configuration demodulator is supplied to the clock recovery, deserializer, and error check circuit **1009** (see FIG. 10) that samples the serial output in sample circuit **1502**, recreates the configuration information including the start bit, P2, P1, P0, N2, N1, N0, and parity bits and any other redundancy bits in serial to parallel block **1504**. Once the transmitted word is recovered, the error check logic **1506** checks for errors, e.g., parity errors. If no errors are detected, the START bit, redundant bits, and parity bit(s) are removed and the recovered CONFIG values update the driver strength (or other configuration settings) in the drive control block.

(53) FIG. 16 illustrates an embodiment of sample logic **1502**. The sample clock signal is recovered from transitions of serial out and delayed to cause the sampling to occur in the middle of a serial out bit. A transition detector (1 to 0 or 0 to 1) can be used to generate a sampling pulse from sequential bits having a transition. The lack of transitions in sequential bits, e.g., sequential 1s or 0s, requires another way to determine a sample time. The delay block **1601** delays the serial output

and XOR gate **1603** compares the delayed serial output to the current serial output. If the bits are different, indicating a transition, the counter **1605** resets. Flip-flop **1607** receives the current serial out bit on its D input. The pulse logic **1609** pulses the clock of flip-flop **1607** when the counter equals 2. That places the pulse two clock cycles of counter **1605** after the transition. The counter's clock **1611** has a period such that two cycles of the counter will place the sample pulse near the middle of the serial out bit. If no transition is detected, the pulse logic **1609** also pulses when the count=5 to place the next pulse near the middle of the next serial out bit. In an embodiment, the serial word is framed as shown in FIG. 5, thus guaranteeing that at most two sequential bits are the same before a transition occurs. The counter is reset at the next transition. The output of the flip-flop **1607** is supplied to the error detection logic **1506**.

(54) FIG. 17 illustrates a timing diagram of the sample circuit **1502**. When the serial data out from filter **1323** (see FIG. 13) has an output sequence "1", "0", "1", the transitions (edges) at **1701** and **1703** drive the pulses **1702** and **1704** (on count=2 after the edge). However, when two sequential "1s" (or "0s") occur, the edge **1705** drives the first pulse **1706** and count=5 drives the second pulse **1708**. Due to the framing of the serial word an edge generated pulse should occur next after the count generated pulse **1708**. Once the transmitted signal is successfully received, the GATE information and CONFIG information is used by the driver control block.

(55) FIG. 18 illustrates how driver control block **1800** uses the drive strength signals. PFET control logic **1802** receives the configuration bits Drive Strength P (P2, P1, P0) and adjusts the current supplied by PFET(s) **1804**, where PFET **1804** is, e.g., 8 PFET transistors configured in parallel of the same or different sizes (width/length (W/L) ratios), that are used to adjust the current to achieve the percentage drive strength shown, e.g., in FIG. 7, and corresponding to the states S0 to S7 depending upon the setting. The PFET control logic **1802** includes (or is coupled to) NVM or other memory that specifies the drive strength percentages corresponding to the configuration bits, and whether arbitrary drive strengths have been provided, and if so, their drive strength values (for S0 and S8) for operation in digital mode and other necessary configuration information. The M configuration bits for the PFETs drive strength, e.g., 3 bits, map to the N signal lines, e.g., 8 signal lines, to control the drive strength current on output terminal **1806**, which is coupled to the gate of power transistor **1808**. Similarly, the NFET control block **1810** receives M configuration bits (Drive Strength N) to control the drive strength supplied by NFET(s) transistor(s) **1812**. The control block **1810** maps the M configuration bits to N control lines to adjust the current supplied by NFET(s) **1812**, where NFET **1812** is formed by, e.g., 8 NFET transistors in parallel of the same or different sizes, that are used to achieve the percentage drive strength shown, e.g., in FIG. 7 corresponding to S0 to S8. The PFET transistors **1802** and NFET transistors **1812** also receive at their respective gates a complementary version of the GATE signal (assuming GATE is active high).

(56) In an embodiment shown in FIG. 19, rather than supplying a single output **1806**, the driver control block **1900**, corresponding to driver control block **1010** in FIG. 10, separate output terminals **1902** and **1904** (see VOP and VON in FIG. 11) are supplied by the PFETs **1804** and NFETs **1812** and the output terminals are combined externally to drive a gate of an external transistor **1906**. The terminal **1902** provides positive drive current to turn on the external transistor, e.g., IGBT **1906**, while the terminal **1904** provides sinking current to turn off the external transistor **1906**. While not shown, a Miller clamp may be used in conjunction with the two terminals.

(57) Thus, a system with an isolation communication channel has been described that simultaneously communicates gate and configuration information across the isolation communication channel. A modulator in the transmitter encodes the information for dual communication and a demodulator decodes the transmitted information to achieve, e.g., dynamic variable drive strength control of an isolated gate driver. The description of the invention set forth herein is illustrative, and is not intended to limit the scope of the invention as set forth in the following claims. Other variations and modifications of the embodiments disclosed herein, may be

made based on the description set forth herein, without departing from the scope of the invention as set forth in the following claims.

Claims

1. A method comprising: receiving a signal transmitted across an isolation communication channel, the received signal oscillates at different frequencies to indicate gate information and different configuration states; and demodulating the received signal to determine the gate information contained in the received signal and detecting an envelope to determine the different configuration states contained in the received signal.
2. The method of claim 1 further comprising demodulating the received signal in a configuration demodulation path to determine the different configuration states.
3. The method of claim 2 further comprising demodulating the received signal as an on-off keying signal in the configuration demodulation path.
4. The method of claim 2 wherein an output of the configuration demodulation path is determined, at least in part, by an output of a gate demodulation path.
5. The method of claim 2 wherein the configuration demodulation path includes a first sub-demodulation path and a second sub-demodulation path.
6. The method of claim 5 wherein the configuration demodulation path includes an on-off keying demodulator in the first sub-demodulation path.
7. The method of claim 2 further comprising demodulating the received signal in a first sub-demodulation path of the configuration demodulation path to detect the envelope to determine the different configuration states, presence of the envelope indicating one of four states and indicating the received signal is changing at least between a first frequency and a second frequency at a third frequency.
8. The method of claim 7 further comprising demodulating the received signal in a second sub-demodulation path of the configuration demodulation path to determine a frequency associated with the received signal and determining the received signal to be in one of four states based on the frequency.
9. The method of claim 1 further comprising demodulating the received signal to determine gate information contained in the received signal.
10. The method of claim 9 further comprising demodulating the received signal in a configuration demodulation path to detect the configuration information based at least in part on the gate information.
11. An apparatus comprising: one or more input terminals to receive a signal transmitted across an isolation communication channel, the received signal oscillates at different frequencies to indicate gate information and different configuration states; and a demodulator circuit coupled to the one or more input terminals to demodulate the received signal to obtain the gate information contained in the received signal, the demodulator circuit including an envelope detector that determines the different configuration states contained in the received signal.
12. The apparatus of claim 11 wherein the demodulator circuit further comprises a configuration demodulation path that determines the different configuration states.
13. The apparatus of claim 12 wherein the demodulator circuit demodulates the received signal as an on-off keying signal in the configuration demodulation path.
14. The apparatus of claim 12 wherein an output of the configuration demodulation path is determined, at least in part, by an output of a gate demodulation path.
15. The apparatus of claim 12 wherein the configuration demodulation path includes a first sub-demodulation path and a second sub-demodulation path.
16. The apparatus of claim 15 wherein the configuration demodulation path includes an on-off keying demodulator in the first sub-demodulation path.

17. The apparatus of claim 12 further comprising in a first sub-demodulation path in the configuration demodulation path to detect an envelope to determine the different configuration states, presence of the envelope indicating one of four states and indicating the received signal is changing at least between a first frequency and a second frequency at a third frequency.
 18. The apparatus of claim 17 further wherein comprising a second sub-demodulation path of the configuration demodulation path to determine a frequency associated with the received signal and determining the received signal to be in one of four states based on the frequency.
 19. The apparatus of claim 11 wherein the demodulator circuit further demodulates the received signal to determine gate information contained in the received signal.
 20. The apparatus of claim 19 wherein the demodulator circuit further detects the different configuration states based at least on part on the gate information.
-