

US Patent & Trademark Office

Patent Public Search | Text View

United States Patent	12416834
Kind Code	B2
Date of Patent	September 16, 2025
Inventor(s)	Liu; Yanjun et al.

Electromagnetic wave control apparatus

Abstract

An electromagnetic wave control apparatus includes an upper electrode layer, a lower electrode layer, a liquid crystal layer, and a first metamaterial layer disposed between the upper electrode layer and the lower electrode layer. The first metamaterial layer includes a first array including alignment unit structures. A first surface of the alignment unit structure is a surface that is of the alignment unit structure and that faces away from the liquid crystal layer. A length-to-width ratio of the first surface of the alignment unit structure is greater than 1. A length of the first surface, a width of the first surface, and a spacing between two adjacent alignment unit structures range from 1 nm to 5000 nm.

Inventors: Liu; Yanjun (Shenzhen, CN), Guo; Rui (Shenzhen, CN), Li; Tenghao (Shenzhen, CN), Cen; Mengjia (Shenzhen, CN), Wang; Jiawei (Shenzhen, CN)

Applicant: HUAWEI TECHNOLOGIES CO., LTD. (Shenzhen, CN); Southern University of Science and Technology (Shenzhen, CN)

Family ID: 1000008820993

Assignee: Huawei Technologies Co., Ltd. (Shenzhen, CN); Southern University of Science and Technology (Shenzhen, CN)

Appl. No.: 18/492400

Filed: October 23, 2023

Prior Publication Data

Document Identifier	Publication Date
US 20240045272 A1	Feb. 08, 2024

Foreign Application Priority Data

CN	202110435765.8	Apr. 22, 2021
----	----------------	---------------

Related U.S. Application Data

continuation parent-doc WO PCT/CN2022/080166 20220310 PENDING child-doc US 18492400

Publication Classification

Int. Cl.: G02F1/1337 (20060101)

U.S. Cl.:

CPC G02F1/133707 (20130101); G02F1/133723 (20130101); G02F1/133738 (20210101); G02F1/133742 (20210101); G02F2202/30 (20130101); G02F2202/36 (20130101)

Field of Classification Search

USPC: None

References Cited

U.S. PATENT DOCUMENTS

Patent No.	Issued Date	Patentee Name	U.S. Cl.	CPC
10942398	12/2020	Calafiore	N/A	G03F 7/0002
2003/0002156	12/2002	Hobbs	349/198	G02F 1/133371
2006/0262250	12/2005	Hobbs	349/96	G02B 5/3058
2007/0121210	12/2006	Sato	359/569	G02F 1/133371
2016/0209680	12/2015	Chen et al.	N/A	N/A
2017/0199425	12/2016	Nam	N/A	G02F 1/23
2018/0143470	12/2017	Oh et al.	N/A	N/A

FOREIGN PATENT DOCUMENTS

Patent No.	Application Date	Country	CPC
1967324	12/2006	CN	N/A
104049424	12/2013	CN	N/A
108885365	12/2017	CN	N/A
110865475	12/2019	CN	N/A
112117390	12/2019	CN	H01L 27/3218
212647221	12/2020	CN	N/A
2010137386	12/2009	WO	N/A

Primary Examiner: Vu; Phu

Attorney, Agent or Firm: Leydig, Voit & Mayer, Ltd.

Background/Summary

CROSS-REFERENCE TO RELATED APPLICATIONS (1) This application is a continuation of International Application No. PCT/CN2022/080166, filed on Mar. 10, 2022, which claims priority

to Chinese Patent Application No. 202110435765.8, filed on Apr. 22, 2021. The disclosures of the aforementioned applications are hereby incorporated by reference in their entireties.

TECHNICAL FIELD

(1) The present disclosure relates to an electromagnetic wave control apparatus, and more specifically, to an electromagnetic wave control apparatus by using a liquid crystal layer.

BACKGROUND

(2) Liquid crystal materials are widely used in electromagnetic wave adjustment and control apparatuses. Under action of an external electric field, liquid crystal molecules are in a specific arrangement status due to anisotropic electrical properties. At the same time, the liquid crystal molecules represent different optical effect due to anisotropic optical properties of the liquid crystal molecules. These features of the liquid crystal molecules can be used for implementing flexible adjustment and control on an electromagnetic wave.

(3) In the adjustment and control apparatus based on the liquid crystal material, the liquid crystal molecules need to be aligned in advance, and then the liquid crystal molecules are adjusted and controlled by adding an external drive voltage, to control the electromagnetic wave. In an existing adjustment and control apparatus, to obtain complete 2π phase adjustment and control, a thick liquid crystal layer material is usually selected, which is unfavorable to miniaturization and integration of a device, and causes a large drive voltage required by the apparatus. In addition, in the existing apparatus, liquid crystal molecules are aligned by using a conventional friction alignment method, which has disadvantages such as large losses and difficult control of product uniformity. Factors such as a result of liquid crystal alignment and a thickness of a liquid crystal layer are critical to manufacturing a liquid crystal device having excellent photoelectric features. Therefore, this application provides a new electromagnetic wave control apparatus, to better implement adjustment and control on an electromagnetic wave while implementing alignment on liquid crystal molecules.

SUMMARY

(4) The present disclosure provides an electromagnetic wave control apparatus. A metamaterial structure is combined with a liquid crystal material, to enable the apparatus to have both a liquid crystal alignment capability and a phase adjustment and control capability.

(5) According to a first aspect, an electromagnetic wave control apparatus is provided. The electromagnetic wave control apparatus includes an upper electrode layer, a lower electrode layer, and a liquid crystal layer and a first metamaterial layer that are disposed between the upper electrode layer and the lower electrode layer. The first metamaterial layer includes a first array including alignment unit structures. A length-width ratio of a first surface of the alignment unit structure is greater than 1. The first surface is a surface that is of the unit structure and that faces away from the liquid crystal layer. A length of the first surface, a width of the first surface, and a spacing between two adjacent alignment unit structures range from 1 nm to 5000 nm.

(6) Therefore, in the electromagnetic wave control apparatus in this embodiment of this application, an array includes alignment unit structures that each have a length-width ratio greater than 1 and a sub-wavelength size, to enable an electromagnetic wave to accumulate a specific phase delay when liquid crystal molecules are aligned. This enhances phase adjustment and control of a reflected or transmitted electromagnetic wave. Accordingly, a thickness of the liquid crystal layer in the apparatus can be reduced, and performance of a liquid crystal device can be improved.

(7) With reference to the first aspect, in some implementations in the first aspect, the length of the first surface, the width of the first surface, and the spacing range from $\lambda/100$ to λ , where λ is a wavelength of the electromagnetic wave incident to the first metamaterial layer, and the wavelength of the electromagnetic wave ranges from 100 nm to 2000 nm.

(8) Therefore, in the electromagnetic wave control apparatus in this embodiment of this application, a size of the alignment unit structure is $\lambda/100$ to λ of a wavelength of the incident

electromagnetic wave, to enable the incident electromagnetic wave to accumulate a specific phase delay, and implement phase adjustment and control for electromagnetic waves with different wavelengths.

(9) With reference to the first aspect, in some implementations in the first aspect, the length-width ratio of the first surface is greater than or equal to 1.5.

(10) Therefore, for the electromagnetic wave control apparatus in this embodiment of this application, an array includes alignment unit structures that each have a length-width ratio greater than or equal to 1.5, to enable the liquid crystal molecules to be arranged in a major axis direction of the alignment unit structure. In this way, alignment effect on the liquid crystal molecules is better. At the same time, a larger length-width ratio of the alignment unit structure indicates better alignment effect of the apparatus on the liquid crystal molecules.

(11) With reference to the first aspect, in some implementations in the first aspect, the first metamaterial layer is located on a lower surface of the liquid crystal layer.

(12) With reference to the first aspect, in some implementations in the first aspect, the apparatus further includes: a second metamaterial layer. The second metamaterial layer is located on an upper surface of the liquid crystal layer. The second metamaterial layer includes a second array including the alignment unit structures.

(13) With reference to the first aspect, in some implementations in the first aspect, an alignment direction of the second array is perpendicular to an alignment direction of the first array.

(14) Therefore, for the electromagnetic wave control apparatus in this embodiment of this application, two metamaterial layers whose alignment directions are perpendicular are respectively disposed on the upper surface of the liquid crystal layer and the lower surface of the liquid crystal layer, to enable a polarization direction of a linearly polarized electromagnetic wave to be twisted by about 90° after the linearly polarized electromagnetic wave is transmitted by the apparatus. A special optical waveguide feature of the liquid crystal molecules in the apparatus may be used to manufacture a liquid crystal device with a better extinction ratio.

(15) With reference to the first aspect, in some implementations in the first aspect, an alignment direction of the second array is parallel to an alignment direction of the first array.

(16) With reference to the first aspect, in some implementations in the first aspect, the apparatus further includes: a polyimide (PI) frictional layer. The PI frictional layer is located on an upper surface of the liquid crystal layer. An alignment direction of the PI frictional layer is perpendicular to an alignment direction of the first array.

(17) Therefore, for the electromagnetic wave control apparatus in this embodiment of this application, the metamaterial layer and the PI frictional layer are respectively disposed on the upper surface of the liquid crystal layer and the lower surface of the liquid crystal layer, and an alignment direction of the metamaterial layer for the liquid crystal molecules and an alignment direction of the PI frictional layer for the liquid crystal molecules are perpendicular to each other, to enable the polarization direction of the linearly polarized electromagnetic wave to be twisted by about 90° after the linearly polarized electromagnetic wave is transmitted by the apparatus. The special optical waveguide feature of the liquid crystal molecules in the apparatus may be used to manufacture the liquid crystal device with the better extinction ratio.

(18) With reference to the first aspect, in some implementations in the first aspect, the apparatus further includes a third array including the alignment unit structures. An alignment direction of the third array is perpendicular to the alignment direction of the first array.

(19) Therefore, the electromagnetic wave control apparatus in this embodiment of this application, two arrays whose alignment directions are perpendicular can be reused, to implement alignment on the liquid crystal molecules in two different directions at a same metamaterial layer. In comparison with conventional friction alignment and optical alignment technologies, the alignment direction of the liquid crystal molecules can be flexibly controlled, and integration of the liquid crystal device can be implemented.

(20) With reference to the first aspect, in some implementations in the first aspect, the alignment unit structure is a rectangular column.

(21) Therefore, for the electromagnetic wave control apparatus in this embodiment of this application, an array includes rectangular column unit structures that each have a length-width ratio greater than or equal to 1, so that the apparatus is easy to prepare. In addition, a shape of the rectangular column unit structure is regular, so that the liquid crystal molecules may be neatly arranged on a surface of the metamaterial layer. This facilitates the alignment on the liquid crystal molecules and may improve working efficiency of the apparatus.

(22) With reference to the first aspect, in some implementations in the first aspect, the alignment unit structure is a wedge-shaped column.

(23) With reference to the first aspect, in some implementations in the first aspect, the alignment unit structure is a triangular prism. The first surface is a side surface of the triangular prism. A ratio of a height of the triangular prism to a side length of a bottom triangle is greater than 1.

(24) With reference to the first aspect, in some implementations in the first aspect, the alignment unit structure is an elliptical column. The first surface is a bottom surface of the elliptical column. A ratio of a major axis of the bottom surface of the elliptical column to a minor axis of the bottom surface of the elliptical column is greater than 1.

(25) With reference to the first aspect, in some implementations in the first aspect, the alignment unit structure is an ellipsoid. The first surface is a projection plane of the ellipsoid. A ratio of a major axis of the projection plane of the ellipsoid to a minor axis of the projection plane of the ellipsoid is greater than 1.

(26) Therefore, for the electromagnetic wave control apparatus in this embodiment of this application, a shape of the alignment unit structure is not limited. The alignment on the liquid crystal molecules may be implemented as long as the length-width ratio of the alignment unit structure on the projection plane is greater than 1, so that the array including the alignment unit structures is easier to prepare.

(27) With reference to the first aspect, in some implementations in the first aspect, a material of the alignment unit structure is metal.

(28) With reference to the first aspect, in some implementations in the first aspect, a material of the alignment unit structure is a dielectric material.

(29) With reference to the first aspect, in some implementations in the first aspect, the apparatus further includes a spacer layer. The metamaterial layer is disposed on a surface of the spacer layer.

(30) Therefore, for the electromagnetic wave control apparatus in this embodiment of this application, the metamaterial layer is disposed on the surface of the spacer layer, to improve efficiency of an alignment apparatus, so that the alignment apparatus is easier to prepare, and arrangement and the alignment on the liquid crystal molecules can be better implemented.

(31) With reference to the first aspect, in some implementations in the first aspect, a spatial light modulator is a transmissive spatial light modulator.

(32) With reference to the first aspect, in some implementations in the first aspect, the spatial light modulator is a reflective spatial light modulator.

(33) Therefore, for the apparatus provided in this application, a metamaterial is combined with the liquid crystal material, to construct an electromagnetic wave control apparatus that has both the liquid crystal alignment capability and the phase adjustment and control capability. Based on the foregoing apparatus, the alignment on the liquid crystal molecules may be implemented by using a simple metamaterial structure. This overcomes disadvantages such as large losses of conventional friction alignment and difficult control, and implements the flexible arrangement and the alignment on the liquid crystal molecules. In addition, the array includes the alignment unit structures that each have the sub-wavelength size, to enable the electromagnetic wave to accumulate the specific phase delay in a transmission process of the electromagnetic wave. This enhances the phase adjustment and control of the reflected or the transmitted electromagnetic wave. Accordingly, the

thickness of the liquid crystal layer in the apparatus can be reduced, the performance of the liquid crystal device can be improved, and the integration of the liquid crystal device can be improved.

Description

BRIEF DESCRIPTION OF DRAWINGS

- (1) FIG. 1 is a schematic diagram of an electromagnetic wave control apparatus applicable to an embodiment of this application;
- (2) FIG. 2 is a schematic diagram of some alignment unit structures applicable to an embodiment of this application;
- (3) FIG. 3 is a schematic diagram of an alignment unit structure applicable to an embodiment of this application;
- (4) FIG. 4 is a schematic diagram of an alignment unit structure applicable to an embodiment of this application;
- (5) FIG. 5 is a schematic diagram of an alignment unit structure applicable to an embodiment of this application;
- (6) FIG. 6 is a schematic diagram of a structure of an electromagnetic wave control apparatus applicable to an embodiment of this application;
- (7) FIG. 7 is a schematic diagram of a structure of an electromagnetic wave control apparatus applicable to an embodiment of this application;
- (8) FIG. 8 is an electron micrograph diagram of an alignment unit structure applicable to an embodiment of this application;
- (9) FIG. 9 is a diagram of liquid crystal alignment effect of an electromagnetic wave control apparatus under a polarization microscope applicable to an embodiment of this application;
- (10) FIG. 10 is a schematic diagram of a structure of a transmissive spatial light modulator applicable to an embodiment of this application;
- (11) FIG. 11 is a schematic diagram of an electromagnetic wave transmittance of a transmissive spatial light modulator applicable to an embodiment of this application;
- (12) FIG. 12 is a schematic diagram of phase adjustment and control performed by a transmissive spatial light modulator on an electromagnetic wave applicable to an embodiment of this application;
- (13) FIG. 13 is a schematic diagram of a structure of a reflective spatial light modulator applicable to an embodiment of this application; and
- (14) FIG. 14 is a schematic diagram of a reusable and adjustable metasurface structure applicable to an embodiment of this application.

DESCRIPTION OF EMBODIMENTS

- (15) In embodiments of this application, a metamaterial structure is combined with a liquid crystal material, to implement adjustment and control on an electromagnetic wave. As an artificial microstructure with a sub-wavelength size, the metamaterial structure can assist a liquid crystal device to implement flexible adjustment and control on the electromagnetic wave. At the same time, the liquid crystal device constructed by using a metamaterial helps promote miniaturization and integration of a product. In addition, a metamaterial layer may be integrated on a photonic chip by using a photolithography technology. This facilitates large-scale manufacturing and processing of a device.
- (16) Specifically, in embodiments of this application, nanounit structures with a specific length-width ratio are neatly arranged as one metamaterial layer, to form an alignment layer in a “groove” shape, so as to implement an alignment function on liquid crystal molecules. In addition, the nanounit structures arranged in sequence present a structure similar to an antenna array, and the metamaterial structure may control features such as polarization, a phase, an amplitude, and

dispersion of the electromagnetic wave based on a resonance feature of a nano-antenna array. Therefore, for the apparatus provided in this application, a metamaterial is combined with the liquid crystal material, to construct an electromagnetic wave control apparatus that has both a liquid crystal alignment capability and a phase adjustment and control capability.

(17) The following describes technical solutions of this application with reference to accompanying drawings. It is clear that the described embodiments are merely some but not all of embodiments of this application. All other embodiments obtained by a person of ordinary skill in the art based on embodiments of this application without creative efforts shall fall within the protection scope of this application.

(18) FIG. 1 is a schematic diagram of an electromagnetic wave control apparatus **100** applicable to an embodiment of this application. (a) in FIG. 1 is a cross sectional view of the apparatus **100** without a drive voltage. As shown in (a) in FIG. 1, the apparatus **100** includes: a lower electrode layer (including a substrate **101** and an electrode array **102** on a surface of the substrate **101**), and an upper electrode layer **107**. A liquid crystal layer **105** is between the upper electrode layer and the lower electrode layer, and includes liquid crystal molecules **106** and a metamaterial layer **104** including several unit structures. Optionally, the apparatus **100** may further include a spacer layer **103**, configured to optimize structural efficiency. The metamaterial layer **104** may be disposed on a surface of the spacer layer **103**. Alternatively, the apparatus **100** may not include the spacer layer **103**. This is not limited in this application.

(19) (c) in FIG. 1 shows a top view of the metamaterial layer **104** in (a) in FIG. 1. The metamaterial layer **104** includes an array including neatly arranged alignment unit structures. The apparatus **100** is described in FIG. 1 by using a rectangular column unit structure as an example. The rectangular column unit structure has a specific length-width ratio, so that the metamaterial layer **104** presents a micro “groove” structure. The liquid crystal molecules may lie down in a micro “groove” formed by the rectangular column unit structure. Therefore, in the liquid crystal layer **105**, liquid crystal molecules on a surface of an electrode are arranged in a major axis direction of the rectangular column unit structure. The liquid crystal molecules between upper and lower electrode layer tend to be arranged in parallel due to action of van der Waals force.

(20) Different voltages are applied between the upper electrode layer and the lower electrode layer, to enable the liquid crystal molecules in the apparatus **100** to rotate on a yz plane. A material of the electrode layer may be indium tin oxide (ITO), or may be another conductive material. This is not limited in this application.

(21) (b) in FIG. 1 is a cross sectional view of the apparatus **100** when a drive voltage is applied. (d) in FIG. 1 is a top view of the metamaterial layer **104** in (b) in FIG. 1. It can be seen from (b) in FIG. 1 and (d) in FIG. 1 that the liquid crystal molecules rotate on the yz plane perpendicular to the metamaterial layer by applying the driving voltage. When a voltage is applied enough, the liquid crystal molecules tend to be arranged parallel to a direction of an electric field under attraction of the electrostatic field, in other words, a major axis direction of the liquid crystal molecules is perpendicular to an xy plane. In this case, the liquid crystal molecules cannot adjust and control a polarization direction of an incident light beam.

(22) (a) in FIG. 2 is a schematic diagram of some alignment unit structures at the metamaterial layer **104**.

(23) Specifically, in (a) in FIG. 2, a length-width ratio of a first surface of each alignment unit structure **201** is greater than 1. The first surface is a surface that is of the unit structure **201** and that faces away from the liquid crystal layer. As shown in (a) in FIG. 2, the first surface of the alignment unit structure **201** may be a lower surface of the rectangular column. As shown in (a) in FIG. 2, several rectangular column unit structures **201** are arranged neatly. W indicates a width of the rectangular column unit structure, and L indicates a length of the rectangular column unit structure. The length-width ratio L/W of each rectangular column unit structure **201** needs to be greater than 1, to enable the metamaterial layer **104** to present a “groove” parallel to a y-axis

direction on the xy plane, so that liquid crystal molecules **202** are arranged in a “groove” direction. In this way, alignment on the liquid crystal molecules **202** is implemented. The rectangular column unit structure **201** needs to be of a sub-wavelength size with a geometric size less than an incident wavelength of a surface of the structure. If the length-width ratio L/W of the unit structure is large enough, a strip-shaped rectangular column **203** may be presented, as shown in (b) in FIG. 2.

(24) An array including alignment unit structures that each have a length-width ratio equal to 1 in an x-axis direction has a same period as the array including alignment unit structures that each have a length-width ratio equal to 1 in the y-axis direction. Therefore, isotropic optical properties are presented. However, in this embodiment of this application, the length-width ratio of the alignment unit structure **201** at the metamaterial layer **104** is greater than 1, and alignment unit structures are not symmetric. Therefore, the array including the alignment unit structures is anisotropic, to implement a function of alignment on liquid crystal molecules. To implement a better alignment result, the length-width ratio of the alignment unit structure **201** may be greater than or equal to 1.5. A larger length-width ratio of the alignment unit structure **201** indicates better alignment effect on the liquid crystal molecules.

(25) Therefore, for the electromagnetic wave control apparatus in this embodiment of this application, the array includes alignment unit structures that each have a length-width ratio greater than 1, to enable the liquid crystal molecules to be arranged in a major axis direction of the alignment unit structure. In this way, an objective of alignment on the liquid crystal molecules is achieved. The apparatus has simple structure and is easy to prepare, can better control arrangement of the liquid crystal molecules, and reduce wear at the alignment layer, to better implement the alignment on the liquid crystal molecules.

(26) Further, in the schematic diagram of the alignment unit structure in (a) in FIG. 2, a length L of the first surface of the alignment unit structure **201**, a width W of the first surface of the alignment unit structure **201**, and a spacing between two adjacent alignment unit structures **201** all range from 1 nm to 5000 nm. In this case, an electromagnetic wave reflected or transmitted by the metamaterial layer **104** obtains a specific phase delay.

(27) More specifically, the length L of the first surface, the width W of the first surface, and the spacing between two adjacent alignment unit structures **201** all range from $\lambda/100$ to λ , where λ is a wavelength of an electromagnetic wave incident to the apparatus. A wavelength range of the electromagnetic wave may range from 100 nm to 5000 nm. Further, a wavelength range of the electromagnetic wave may range from 100 nm to 2000 nm. It should be understood that for electromagnetic waves in different wavelength ranges, alignment unit structures of different sizes may be selected for the apparatus in this embodiment of this application. A size of the alignment unit structure needs to be related to a wavelength of the electromagnetic wave that needs to be adjusted and controlled. In addition to an electromagnetic wave ranging from 100 nm to 2000 nm, the apparatus provided in this embodiment of this application may be further configured to adjust and control an electromagnetic wave with another wavelength, for example, a terahertz band or a radio band. This is not limited in this application.

(28) It should be understood that the phase delay obtained by the electromagnetic wave reflected or transmitted by the metamaterial layer **104** may exist in the following cases: Because the array including the alignment unit structures **201** presents a structure similar to an antenna array, resonance occurs on an electromagnetic wave incident to a surface of the array. The electromagnetic wave incident to the apparatus is reflected or transmitted by the array including the alignment unit structures, to obtain a specific resonance phase. Alternatively, because the alignment unit structure **201** is a structure with the sub-wavelength size, there is a specific optical path difference between the electromagnetic wave reflected or transmitted by the metamaterial layer **104** and the incident electromagnetic wave, so that the reflected or transmitted electromagnetic wave obtains a transmission phase. Alternatively, because a size of the alignment unit structure **201** in the x-axis direction is different from a size of the alignment unit structure **201** in the y-axis direction,

and anisotropy exists in adjustment and control of a left-handed or right-handed polarized electromagnetic wave, the incident electromagnetic wave obtains a geometric phase.

(29) It should be understood that the phase delay obtained by the reflected or transmitted electromagnetic wave is related to factors such as a size of the alignment unit structure **201** and an equivalent refractive index of the liquid crystal layer. Due to the phase delay generated at the metamaterial layer **104**, phases accumulated in sending the electromagnetic wave by the apparatus **100** may be increased. On one hand, with a same thickness of a liquid crystal material, the phase delay generated by the metamaterial layer **104** enables the apparatus **100** to generate deep phase modulation. On the other hand, due to the phase delay accumulated at the metamaterial layer, a thinner liquid crystal material may be used, to implement 2π phase modulation for the electromagnetic wave. As a thickness of the material of the liquid crystal layer decreases, a drive voltage required for adjusting and controlling the electromagnetic wave may be reduced, so that heat generation between upper and lower electrodes may be reduced, and crosstalk between adjacent alignment unit structures may be reduced. This reduces a pixel size of the liquid crystal device, and improves device resolution.

(30) Therefore, in the electromagnetic wave control apparatus in this embodiment of this application, an array includes the alignment unit structures that each have a length-width ratio greater than 1 and the sub-wavelength size, to enable the electromagnetic wave to accumulate the specific phase delay on the basis of the alignment on the liquid crystal molecules. This can enhance phase adjustment and control of the reflected or transmitted electromagnetic wave. Accordingly, a thickness of the liquid crystal layer in the apparatus can be reduced, and performance of a liquid crystal device can be improved.

(31) It should be understood that, in addition to the rectangular column unit structure shown in FIG. 2, the alignment unit structure may alternatively be another geometric structure with a specific length-width ratio. In an optional implementation, the alignment unit structure may be a wedge-shaped column **301** shown in (a) in FIG. 3. A length-width ratio L/W of a first surface of each wedge-shaped column **301** also needs to be greater than 1. The first surface of the wedge-shaped column **301** is a surface that faces away from a liquid crystal layer. As shown in (a) in FIG. 3, the first surface may be a side surface of the wedge-shaped column **301**.

(32) The alignment unit structure may alternatively be a triangular prism **302** shown in (b) in FIG. 3. As shown in (b) in FIG. 3, a first surface of the triangular prism **302** is a surface that faces away from the liquid crystal layer. For example, the first surface may be any side surface of the triangular prism **302**. A ratio of a height of the triangular prism **302** to a side length of a bottom triangle of the triangular prism **302** is greater than 1.

(33) The alignment unit structure may alternatively be an elliptic cylinder **401** shown in FIG. 4. As shown in FIG. 4, a first surface of the elliptic cylinder **401** is a surface that faces away from a liquid crystal layer. For example, the first surface may be a bottom surface of the elliptic cylinder **401**. As shown in (b) in FIG. 4, a ratio L/W of a major axis of the bottom surface of the elliptic cylinder **401** to a minor axis of the bottom surface of the elliptic cylinder **401** is greater than 1.

(34) In addition to the several cases shown in FIG. 2 to FIG. 4, the alignment unit structure may alternatively be another structure in an irregular shape. When a length-width ratio of the alignment unit structure on a projection plane of the alignment unit structure is greater than 1, alignment may also be implemented on the liquid crystal molecules at a liquid crystal layer. For example, a unit structure at the metamaterial layer **104** may be an ellipsoid **501** shown in FIG. 5. As shown in (b) in FIG. 5, a first surface of the ellipsoid **501** may be a projection plane on a surface that is of the ellipsoid and that faces away from a liquid crystal layer. A ratio L/W of a major axis of the projection plane of the ellipsoid **501** to a minor axis of the projection plane of the ellipsoid **501** is greater than 1. In addition to the ellipsoid shown in FIG. 5, the alignment unit structure may alternatively be another structure in an irregular shape, for example, a spindle-shaped structure, a dumbbell-shaped structure, or a football-shaped structure. This is not limited in this application.

(35) It should be understood that a material of the alignment unit structure may be a low-loss dielectric material, for example, silicon dioxide (SiO_2), titanium dioxide (TiO_2), silicon nitride (SiN_x), aluminum oxide (Al_2O_3), silicon (Si), or the like. A material of the alignment unit structure may alternatively be a metal material, for example, gold (Au), silver (Ag), aluminum (Al), copper (Cu), or platinum (Pt). This is not limited in this application.

(36) The electromagnetic wave control apparatus in this embodiment of this application may alternatively use three arrangement manners shown in FIG. 6.

(37) A possible apparatus structure is shown in (a) in FIG. 6, and includes an upper electrode layer **601**, a lower electrode layer **602**, and a liquid crystal layer **603** and a first metamaterial layer **604** that are disposed between the upper electrode layer **601** and the lower electrode layer **602**. The metamaterial layer **604** may be located on a lower surface of the liquid crystal layer **603**, for example, disposed on a surface of the lower electrode layer **602**. It should be understood that the first metamaterial layer **604** includes a first array including alignment unit structures. The alignment unit structure may be any structure shown in FIG. 2 to FIG. 5.

(38) Another possible apparatus structure is shown in (b) in FIG. 6, and includes the upper electrode layer **601**, the lower electrode layer **602**, the liquid crystal layer **603**, the first metamaterial layer **604**, and a second metamaterial layer **605**. The first metamaterial layer **604** is located on the lower surface of the liquid crystal layer. The second metamaterial layer **605** is located on an upper surface of the liquid crystal layer, for example, the second metamaterial layer **605** is disposed on a surface of the upper electrode layer **601**.

(39) Another possible apparatus structure is shown in (c) in FIG. 6, and includes the upper electrode layer **601**, the lower electrode layer **602**, the liquid crystal layer **603**, the first metamaterial layer **604**, and a polyimide (PI) frictional layer **606**. The first metamaterial layer **604** is located on a lower surface of the liquid crystal layer. The PI frictional layer **606** is located on the upper surface of the liquid crystal layer **603**, for example, disposed on the surface of the upper electrode layer **601**. Optionally, in the apparatus shown in (c) in FIG. 6, the PI frictional layer **606** may alternatively be located on the lower surface of the liquid crystal layer **603**. The first metamaterial layer **604** may be located on the upper surface of the liquid crystal layer.

(40) It should be further noted that, in the electromagnetic wave control apparatus shown in (b) in FIG. 6, an alignment direction of the first metamaterial layer **604** and an alignment direction of the second metamaterial layer **605** may be parallel to each other. Optionally, there may alternatively be a specific included angle, for example, 45° , between the alignment direction of the metamaterial layer **605** and the alignment direction of the metamaterial layer **604**. Optionally, the alignment direction of the metamaterial layer **605** and the alignment direction of the metamaterial layer **604** may be perpendicular to each other. As shown in (a) in FIG. 7, the first metamaterial layer **604** disposed on the surface of the lower electrode layer includes the first array including alignment unit structures. The second metamaterial layer **605** disposed on the upper electrode layer includes a second array including alignment unit structures. An alignment direction of the first array is perpendicular to an alignment direction of the second array. Liquid crystal molecules between the upper electrode layer and the lower electrode layer tend to be arranged in parallel due to action of van der Waals force. However, because the alignment direction of the metamaterial layer **605** for the liquid crystal molecules is perpendicular to the alignment direction the metamaterial layer **604** for the liquid crystal molecules, an arrangement direction of liquid crystal molecules near the upper electrode is perpendicular to an arrangement direction of liquid crystal molecules near the lower electrode. In this case, the liquid crystal molecules are arranged in a direction of 0° (an included angle between the upper electrode layer and an x-axis direction) from the upper electrode layer, and are gradually and uniformly twisted to the lower electrode in a direction of -90° , for example, the liquid crystal molecules are twisted by 90° one by one clockwise. A layer of the liquid crystal molecules that are twisted in an arrangement manner shown in (a) in FIG. 7 has a property of an optical waveguide. When linearly polarized light in a polarization direction parallel to the x-axis

direction is propagated to the surface of the lower electrode layer through the liquid crystal layer, the polarization direction is rotated by 90° . (b) in FIG. 7 is a schematic diagram of arrangement of the liquid crystal molecules when a drive voltage is applied. In this case, the liquid crystal molecules tend to be arranged parallel to a direction of an electric field, that is, a major axis direction of the liquid crystal molecules is perpendicular to an xy plane. In this case, the liquid crystal molecules cannot adjust and control a polarization direction of an incident light beam.

(41) Therefore, for the electromagnetic wave control apparatus in this embodiment of this application, two metamaterial layers whose alignment directions are perpendicular are respectively disposed on the upper electrode layer and the lower electrode layer, so that a polarization direction of a linearly polarized electromagnetic wave is twisted by about 90° after the linearly polarized electromagnetic wave is transmitted by the apparatus. A special optical waveguide feature of the liquid crystal molecules in the apparatus may be used to manufacture a liquid crystal device with a better extinction ratio.

(42) Similar to the structure in (b) in FIG. 6, the alignment direction of the first metamaterial layer **604** may also be parallel or perpendicular to, or form a specific included angle with an alignment direction of the PI frictional layer **606** in (c) in FIG. 6. In addition, the liquid crystal molecules may implement an optical waveguide feature similar to the optical waveguide feature shown in (a) in FIG. 7, to further construct a liquid crystal device with a better extinction ratio.

(43) In addition to the several structures shown in FIG. 6, the alignment apparatus may alternatively use another similar arrangement manner. This is not limited in this application. For example, in (b) in FIG. 6, the first metamaterial layer **604** and the second metamaterial layer **605** may use different alignment unit structures.

(44) In an optional implementation, in the electromagnetic wave control apparatus in this embodiment of this application, the first metamaterial layer may alternatively include both the first array including alignment unit structures and a third array including alignment unit structures, and an alignment direction of the third array is perpendicular to the alignment direction of the first array. Two arrays whose alignment directions are perpendicular to each other are reused, to implement alignment on liquid crystal molecules in two directions at a same metamaterial layer.

(45) Similarly, the first metamaterial layer may further include a fourth array in another alignment direction. The first metamaterial layer may further include arrays in several alignment directions at the same time, and each array may use a different alignment unit structure. This is not limited in this embodiment of this application.

(46) Therefore, the electromagnetic wave control apparatus in this embodiment of this application, two arrays whose alignment directions are perpendicular can be reused, to implement alignment on the liquid crystal molecules in two different directions at a same metamaterial layer. In comparison with conventional friction alignment and optical alignment technologies, the alignment direction of the liquid crystal molecules can be flexibly controlled, and integration of the liquid crystal device can be implemented.

(47) The following uses the apparatus **100** in FIG. 1 as an example to describe an experimental result of the electromagnetic wave control apparatus in this embodiment of this application. A unit structure used in an experiment is a rectangular column structure and a material is gold. FIG. 8 is an electron microscopic diagram of a structure of a unit structure with a length-width ratio L/W of 1:1, 2:1, 3:1, 4:1, or 5:1. FIG. 9 shows an experiment result of alignment effect of unit structures with five length-width ratios on liquid crystal molecules. Two polarizers P1 and P2 are respectively placed on an upper surface of an upper cover plate **106** of the apparatus **100** and a lower surface of a substrate layer **101** of the apparatus **100**. The polarizer P1 on the upper cover plate **106** is in a polarization direction P. After natural light from a light source passes through the polarizer, only linearly polarized light parallel to the polarization direction P is left. Polarization direction of the polarizer P2 on the lower surface of the substrate layer **101** is A. Only linearly polarized light whose polarization direction is parallel to A can be totally transmitted by P2. Linearly polarized

light in another polarization direction may be partially transmitted by P2. Linearly polarized light whose polarization direction is perpendicular to A cannot be transmitted by P2. After the natural light from the light source passes through P1 and P2, if A is perpendicular to P, a light beam cannot be transmitted by P2, and P2 cannot transmit light. If A is parallel to P, a light beam may be transmitted by P2, and P2 totally transmits light. FIG. 9 is a diagram of alignment effect of the apparatus 100 on liquid crystal molecules when A is perpendicular to P and when A is parallel to P. Under a polarization microscope, alignment effect in a power-off state (OFF) is compared with alignment effect in a power-on state (ON).

(48) As shown in FIG. 9, when P is perpendicular to A, power is turned off, and weak light is transmitted by P2. This indicates that the liquid crystal molecules change a polarization direction of the light beam. When the power is turned on, the liquid crystal molecules are arranged in a direction of an electric field, a polarization direction of the light beam cannot be adjusted and controlled, and light-transmitting phenomenon disappears. A larger length-width ratio of a rectangular column indicates more obvious contrast of the light-transmitting phenomenon. The experiment result shows that an array including unit structures may implement alignment on the liquid crystal molecules. Similarly, when P is parallel to A, power is turned off, the light beam cannot be totally transmitted by P2, and an extinction phenomenon exists. This indicates that the liquid crystal molecules change a polarization direction of the light beam. When the power is turned on, the liquid crystal molecules are arranged in a direction of an electric field, the polarization direction of the light beam cannot be adjusted and controlled, and an extinction phenomenon disappears. A larger length-width ratio of a rectangular column indicates more obvious contrast of the extinction phenomenon. It is also shown that an array including unit structures may implement alignment on the liquid crystal molecules. In addition, the larger length-width ratio L/W of the unit structure indicates better alignment effect on the liquid crystal molecules. To implement a better alignment result, the length-width ratio L/W of the unit structure may be greater than or equal to 5.

(49) To further optimize an adjustment and control function of the apparatus 100 on an incident light beam, in the apparatus 100 shown in FIG. 1, a spacer layer 103 may be added to optimize device efficiency. A material of the spacer layer 103 may be a material with a low loss and a low refractive index, for example, SiO₂. Alternatively, the apparatus 100 may not include the spacer layer 103. This is not limited in this application.

(50) It should be understood that the electromagnetic wave control apparatus in this embodiment of this application may be used in a structure such as a projection display liquid crystal on silicon (LCOS) module and a wavelength-selective switch (WSS). Further, the electromagnetic wave control apparatus in this embodiment of this application may be a spatial light modulator (SLM), and may perform time or space conversion or modulation on a feature such as a phase, an amplitude, and an intensity of an optical wave under control of a control signal. The control signal may be an optical signal or an electrical signal. The spatial light modulator may alternatively include a plurality of independent units, and the independent units are spatially arranged in a one-dimensional or two-dimensional array. Each unit may independently receive the control of the control signal and change an optical property of each unit based on the signal, to modulate the incident light beam.

(51) FIG. 10 is a diagram of a structure of a transmissive spatial light modulator applicable to an embodiment of this application. As shown in (a) in FIG. 10, a spatial light modulator structure 1000 is a polarization-dependent phase transmissive spatial light modulator based on a metasurface, and includes an upper glass layer 1001 and a lower glass layer 1001. The upper glass layer 1001 and the lower glass layer 1001 each are plated with an ITO electrode, to form an external circuit 1002. A matrix control layer is disposed between the upper glass layer 1001 and the lower glass layer 1001, and includes a metamaterial layer and a liquid crystal layer. The metamaterial layer may include an alignment unit structure 1004 similar to the metamaterial layer 104 in (a) in FIG. 1.

Liquid crystal molecules **1003** at the liquid crystal layer are arranged in a major axis direction (namely, a y-axis direction) of the alignment unit structure **1004**. A spacer layer may alternatively be added between a lower electrode and the alignment unit structure **1004**, to improve efficiency of the structure.

(52) It should be understood that FIG. **10** merely shows a possible example of a transmissive spatial light modulator structure. The metamaterial layer may include any array including alignment unit structures in FIG. **2** to FIG. **5**. This is not limited in this application. In addition, the transmissive spatial light modulator structure **1000** may use any arrangement manner shown in FIG. **6**. This is not limited in this application.

(53) By changing an external applied voltage, the liquid crystal molecules **1003** in the spatial light modulator structure may rotate at different angles on a yz plane, to change an equivalent refractive index of the liquid crystal layer in various directions. Therefore, a spatial light modulator generates different electromagnetic responses to an incident light beam, to implement adjustment and control on the incident light beam.

(54) As shown in (a) in FIG. **10**, there is a spacing between lower electrodes. Therefore, the matrix control layer may be divided into a plurality of adjustment and control matrix units. Independent voltage control may be implemented between the adjustment and control matrix units. (b) in FIG. **10** is a schematic diagram of one adjustment and control matrix unit. Each adjustment and control matrix unit may include at least one rectangular nanopillar. (c) in FIG. **10** is atop view of three adjustment and control matrix units shown in (a) in FIG. **10**. Different voltages are applied to each adjustment and control matrix unit, to control the liquid crystal molecules **1003** to present different rotation angles. Therefore, different adjustment and control matrix units have different phase adjustment and control effect on incident light with a same wavelength. With a phase delay generated at the metamaterial layer, the spatial light modulator structure **1000** may implement phase adjustment and control on incident light and implement adjustment and control on an emergent angle of the incident light.

(55) In the spatial light modulator structure **1000**, a thickness of the matrix control layer between the upper and lower electrodes **1002** is 1.5 μm . A length of an electrode on each adjustment and control matrix unit in an x-axis direction is 690 nm, and a width in the y-axis direction is 345 nm. Each TiO₂ rectangular nanopillar is 250 nm high in a z-axis direction, 225 nm long in the y-axis direction, and 150 nm wide in the x-axis direction. The alignment unit structure **904** is a TiO₂ rectangular nanopillar. Each adjustment and control matrix unit includes two TiO₂ rectangular nanopillars.

(56) In (a) in FIG. **10**, a combination of three adjustment and control matrix units is respectively shown. In the three adjustment and control matrix units, included angles $\theta_{\text{sub.LC}}$ between the liquid crystal molecules and a y axis are 90°, 45° and 0° from left to right. Emergent light passing through the spatial light modulator is deflected to the right. The three adjustment and control matrix units with $\theta_{\text{sub.LC}}$ of 90°, 45°, and 0° may be considered as a periodic structure. In one periodic structure, a rotation angle of the liquid crystal molecules in adjacent adjustment and control matrix units changes violently, and a maximum deflection angle ϕ of the emergent light may be 11.7°. Similarly, if the rotation angles $\theta_{\text{sub.LC}}$ of the liquid crystal molecules are adjusted and controlled to be 0°, 45°, and 90° from left to right, the emergent light is deflected to the left, and a maximum deflection angle is -11.7°. Therefore, the structure can adjust and control a deflection angle of the emergent light in a range of $\pm 11.7^\circ$.

(57) It should be understood that materials related to the spatial light modulator structure **1000** are dielectric materials, and almost no incident light is absorbed in a range of 600 nm to 700 nm. A TiO₂ material used in the alignment unit structure **1004** may alternatively be replaced by another material with a high refractive index without ohmic losses, and a same function may be implemented provided that a geometric structure of the rectangular nanopillar is adjusted and the periodic structure of an adjustment and control matrix unit is adjusted and controlled.

(58) (a) in FIG. **11** is a distribution diagram of a component $E_{\text{sub.y}}$ of an electric field on an xz plane in a periodic structure including liquid crystal control units whose $\theta_{\text{sub.LC}}$ are 0° , 45° , and 90° from left to right. A dashed line in (a) in FIG. **11** is an equipotential line of electric field distribution, and a direction indicated by an arrow is a polarization direction of the emergent light after the emergent light passes through the liquid crystal layer. (b) in FIG. **11** is a diagram of transmittances corresponding to different diffraction orders of a spatial light modulator **900**. The incident light is a transverse electric wave (TE wave). When the incident light passes through the liquid crystal control units whose $\theta_{\text{sub.LC}}$ are 0° , 45° , and 90° , a transmittance of +1-order diffractive light of the incident light may reach 0.43, and is better than a transmittance of the phase transmissive spatial light modulator of another structure in the conventional technology.

(59) The rectangular nanopillar unit structure **1004** enables the liquid crystal molecules to have better alignment effect. When there is no voltage, the liquid crystal molecules are arranged in a major axis direction of a rectangular nanopillar, namely, a y -axis direction.

(60) (a) in FIG. **12** is a distribution diagram of a component $E_{\text{sub.y}}$ of an electric field on an xz plane in a periodic structure including liquid crystal control units whose $\theta_{\text{sub.LC}}$ are 90° , 45° , and 0° from left to right. (b) in FIG. **12** shows a phase change of incident light (TE wave) with different wavelengths when the incident light passes through the periodic structure. As shown in (b) in FIG. **12**, a dashed line in the figure indicates a phase change of emergent light when an incident wavelength is 634 nm. When $\theta_{\text{sub.LC}}=0^\circ$, liquid crystal molecules are arranged in a major axis direction of a rectangular nanopillar, and the phase change of the emergent light is the largest. Therefore, when the polarization direction of the incident light is in the major axis direction of the rectangular nanopillar, the spatial light modulator has good phase adjustment and control effect on the emergent light. When $\theta_{\text{sub.LC}}=90^\circ$, liquid crystal molecules are arranged in a direction perpendicular to a major axis direction of a rectangular nanopillar, for example, arranged in a z axis direction, and the phase change of the emergent light is small. Therefore, when the polarization direction of the incident light is perpendicular to the major axis direction of the rectangular nanopillar, the spatial light modulator has weak phase adjustment and control effect on the emergent light.

(61) Therefore, for the transmissive spatial light modulator in this embodiment of this application, the liquid crystal molecules are aligned based on the metamaterial layer that includes the alignment unit structure. In addition, a phase delay accumulated at the metamaterial layer may be used, to generate deep phase modulation in the spatial light modulator, or reduce the thickness of the liquid crystal layer. By changing an external applied voltage to control the rotation angle of the liquid crystal molecules, an emergent direction and a phase of a transmitted beam may be adjusted and controlled. Compared with another type of liquid crystal spatial light modulator, the transmissive spatial light modulator based on the metamaterial layer has a simple structure, is easier to prepare, and optimizes a structure of the liquid crystal spatial light modulator.

(62) FIG. **13** is a diagram of a structure of another reflective spatial light modulator applicable to an embodiment of this application. (a) in FIG. **13** is a side sectional view of the reflective spatial light modulator structure. As shown in (a) in FIG. **13**, a spatial light modulator structure **1300** is a polarization-dependent phase-reflective spatial light modulator based on a metamaterial layer, and includes an upper cover plate **1306**, a liquid crystal layer **1304**, liquid crystal molecules **1305**, a metamaterial layer **1303**, a spacer layer **1302**, and a liquid crystal on silicon (LCoS) drive backplane **1301**. The upper cover plate **1306** includes an electrode. The electrode may be a conductive layer made of a material such as ITO or zinc oxide (ZnO).

(63) It should be understood that FIG. **13** merely shows a possible example of the reflective spatial light modulator structure. The metamaterial layer may include an array including alignment unit structures in FIG. **2** to FIG. **5**. This is not limited in this application. In addition, the transmissive spatial light modulator structure **1300** may use any arrangement manner shown in FIG. **6**. This is not limited in this application.

(64) Similar to the structure of the spatial light modulator **1000** in FIG. **10**, the LCoS drive backplane may apply voltages of different sizes to the liquid crystal layer **1304**, so that the liquid crystal molecules are arranged at different rotation angles. Therefore, a response of the spatial light modulator structure to incident light with a same wavelength changes, to achieve a purpose of adjusting and controlling a phase of emergent light.

(65) (b) in FIG. **13** shows a partial top view of the metamaterial layer **1303** of the spatial light modulator structure **1300**. On the metamaterial layer **1303**, the unit structure is a neatly arranged rectangular column. In addition, a length-width ratio of the rectangular column is greater than 1, that is, the rectangular column is longer in a y-axis direction and shorter in an x-axis direction. The rectangular column unit structure forms a micro “groove” on a lower surface of the liquid crystal layer. Under joint action of van der Waals force, the liquid crystal molecules at the liquid crystal layer **1304** are arranged in a major axis direction of the rectangular column, that is, arranged in the y-axis direction. Therefore, the metamaterial layer **1303** may implement a liquid crystal alignment function in the spatial light modulator **1300**. When a drive voltage is applied, the major axis direction of the liquid crystal molecules rotates around an x-axis until the major axis direction of the liquid crystal molecules is perpendicular to an xy plane. Similar to the spatial light modulator **1000** in FIG. **10**, when a polarization direction of the incident light is in the major axis direction (namely, the y-axis direction) of the rectangular nanopillar, the spatial light modulator has good phase adjustment and control effect on the emergent light.

(66) Therefore, for the reflective spatial light modulator in this embodiment of this application, the liquid crystal molecules are aligned based on the metamaterial layer that includes the alignment unit structure. By changing an external applied voltage to control the rotation angle of the liquid crystal molecules, an emergent direction and a phase of a beam may be adjusted and controlled. In addition, deep phase modulation may be generated in the spatial light modulator by using a phase delay accumulated at the metamaterial layer or reducing a thickness of the liquid crystal layer. By changing the external applied voltage to control the rotation angle of the liquid crystal molecules, an emergent direction and a phase of a transmitted beam may be adjusted and controlled. Compared with another type of liquid crystal spatial light modulator, the transmissive spatial light modulator based on the metamaterial layer has a simple structure, is easier to prepare, and optimizes a structure of the liquid crystal spatial light modulator.

(67) FIG. **14** shows a reusable and adjustable metasurface structure **1400** applicable to an embodiment of this application. FIG. **14** is a partial top view of a metasurface. Arrays including two alignment unit structures **1401** whose alignment directions are perpendicular are respectively arranged at substrate layers on left and right sides. At a left substrate layer, a major axis direction of a rectangular column is parallel to an x-axis, and liquid crystal molecules are arranged in parallel in an x-axis direction. On a right substrate layer, the major axis direction of the rectangular column is parallel to a y-axis, and the liquid crystal molecules are arranged in parallel in a y-axis direction. Under action of the liquid crystal molecules in two alignment directions, a polarization direction of a light beam incident to the left side of the substrate layer is deflected in a direction parallel to the x-axis direction, and a polarization direction of a light beam incident to the right side of the substrate layer is deflected in a direction parallel to the y-axis direction. At the same time, the metasurface may also implement phase modulation of an incident light beam.

(68) Therefore, for the metasurface structure in this embodiment of this application, dual-polarization direction modulation may be implemented on a same chip, and phase modulation of a light beam can be further implemented. The metasurface structure cooperates with a polarization beam splitter, to reduce a polarization conversion element and implement better integration.

(69) The foregoing descriptions are merely specific implementations of this application, but are not intended to limit the protection scope of this application. Any variation or replacement readily figured out by a person skilled in the art within the technical scope disclosed in this application

shall fall within the protection scope of this application. Therefore, the protection scope of this application shall be subject to the protection scope of the claims.

Claims

1. An electromagnetic wave control apparatus, comprising: an upper electrode layer; a lower electrode layer; a liquid crystal layer; a first metamaterial layer located on a lower surface of the liquid crystal layer, the first metamaterial layer comprising a first array comprising first alignment unit structures and a third array comprising third alignment unit structures, wherein an alignment direction of the third array is perpendicular to the alignment direction of the first array; a polyimide frictional layer located on an upper surface of the liquid crystal layer, an alignment direction of the polyimide frictional layer being perpendicular to an alignment direction of the first array; a first voltage source configured to supply a first voltage to the first alignment unit structures; and a third voltage source configured to supply a third voltage to the third alignment unit structures, wherein the liquid crystal layer and the first metamaterial layer are disposed between the upper electrode layer and the lower electrode layer, and wherein the first voltage source and the third voltage source are configured to supply different voltages to the first alignment unit structure and to the third alignment unit structure.
2. The apparatus according to claim 1, wherein the length of the first surface, the width of the first surface, and the spacing are in a range of $\lambda/100$ to λ , wherein λ is a wavelength of an electromagnetic wave incident on the first metamaterial layer, and wherein λ is in a range of from 100 nm to 2000 nm.
3. An electromagnetic wave control apparatus, comprising: an upper electrode layer; a lower electrode layer; a liquid crystal layer; a first metamaterial layer located on a lower surface of the liquid crystal layer, the first metamaterial layer comprising a first array comprising first alignment unit structures and a third array comprising third alignment unit structures; a second metamaterial layer located on an upper surface of the liquid crystal layer, the second metamaterial layer comprising a second array comprising second alignment unit structures; a first voltage source configured to supply a first voltage to the first alignment unit structures; and a third voltage source configured to supply a third voltage to the third alignment unit structures, wherein the first alignment unit structures and the third alignment unit structures are configured to implement, at a single metamaterial layer, alignment on liquid crystal molecules in the liquid crystal layer in two different directions, wherein the liquid crystal layer and the first metamaterial layer are disposed between the upper electrode layer and the lower electrode layer, and wherein the first voltage source and the third voltage source are configured to supply different voltages to the first alignment unit structure and to the third alignment unit structure.
4. The apparatus according to claim 3, wherein an alignment direction of the second array is perpendicular to an alignment direction of the first array.
5. The apparatus according to claim 3, wherein an alignment direction of the second array is parallel to an alignment direction of the first array.
6. The apparatus according to claim 1, wherein the apparatus further comprises: a spacer layer, wherein the first metamaterial layer is disposed on a surface of the spacer layer.
7. The apparatus according to claim 1, wherein the alignment unit structure is a rectangular column.
8. The apparatus according to claim 1, wherein the alignment unit structure is a wedge-shaped column.
9. The apparatus according to claim 1, wherein the alignment unit structure is a triangular prism, the first surface is a side surface of the triangular prism, and a ratio of a height of the triangular prism to a side length of a bottom triangle is greater than 1.
10. The apparatus according to claim 1, wherein the alignment unit structure is an elliptical column, the first surface is a bottom surface of the elliptical column, and a ratio of a major axis of the

bottom surface of the elliptical column to a minor axis of the bottom surface of the elliptical column is greater than 1.

11. The apparatus according to claim 1, wherein the alignment unit structure is an ellipsoid, the first surface is a projection plane of the ellipsoid, and a ratio of a major axis of the projection plane of the ellipsoid to a minor axis of the projection plane of the ellipsoid is greater than 1.

12. The apparatus according to claim 1, wherein a material of the alignment unit structure is metal.

13. The apparatus according to claim 11, wherein a material of the alignment unit structure is a dielectric material.

14. The apparatus according to claim 13, wherein the apparatus is configured to control the electromagnetic wave reflected by the metamaterial layer.

15. The apparatus according to claim 13, wherein the apparatus is configured to control the electromagnetic wave transmitted by the metamaterial layer.

16. The apparatus according to claim 1, wherein the length-to-width ratio is greater than or equal to 5.

17. The apparatus according to claim 3, wherein the length-to-width ratio is greater than or equal to 5.

18. The apparatus according to claim 1, wherein a length-to-width ratio of a first surface of a respective alignment unit structure is greater than 1.5, the first surface being a surface that faces away from the liquid crystal layer, and wherein a length of the first surface, a width of the first surface, and a spacing between the respective alignment unit structure and an adjacent alignment unit structure are in a range of 1 nm to 5000 nm.

19. The apparatus according to claim 3, wherein a length-to-width ratio of a first surface of a respective alignment unit structure is greater than 1.5, the first surface being a surface that faces away from the liquid crystal layer.
