

US Patent & Trademark Office

Patent Public Search | Text View

United States Patent	12418195
Kind Code	B2
Date of Patent	September 16, 2025
Inventor(s)	DeJonge; Stuart W. et al.

Modular lighting panel

Abstract

Systems and methods described herein provide examples of an electrical panel (e.g., a modular electrical panel) that is configured to control a plurality of electrical loads. The electrical panel may include a control circuit, memory, a communication circuit, and an alternating current (AC) line feed and/or a direct current (DC) line feed. The electrical panel may also include a plurality of power supplies and a plurality of control modules, where more than one control module is associated with each of the plurality of power supplies. Each control module may be configured to receive DC power from the associated power supply and provide an output voltage to at least one electrical load. The electrical panel provides flexibility as to whether each stage of conversion, regulation, and/or control is performed at a control module located within the electrical panel or performed at an accessory module located at an electrical load.

Inventors: DeJonge; Stuart W. (Riegelsville, PA), Newman, Jr.; Robert C. (Emmaus, PA), Nuhfer; Matthew W. (Medford, MA), Pessina; Michael W. (Allentown, PA), Shearer; Thomas M. (Macungie, PA)

Applicant: Lutron Technology Company LLC (Coopersburg, PA)

Family ID: 1000008818712

Assignee: Lutron Technology Company LLC (Coopersburg, PA)

Appl. No.: 18/591174

Filed: February 29, 2024

Prior Publication Data

Document Identifier	Publication Date
US 20240204561 A1	Jun. 20, 2024

Related U.S. Application Data

continuation parent-doc US 18307924 20230427 US 11949281 child-doc US 18591174
continuation parent-doc US 17739479 20220509 US 11670957 20230606 child-doc US 18307924
continuation parent-doc US 17078947 20201023 US 11329502 20220510 child-doc US 17739479
continuation parent-doc US 16457962 20190629 US 10820394 20201027 child-doc US 17078947
division parent-doc US 15656437 20170721 US 10548202 20200128 child-doc US 16457962
us-provisional-application US 62365773 20160722

Publication Classification

Int. Cl.: **H05B47/18** (20200101); **H02J9/06** (20060101); **H05B33/02** (20060101); **H05B45/10** (20200101); **H05B45/38** (20200101); H05B45/3725 (20200101)

U.S. Cl.:

CPC **H02J9/061** (20130101); **H05B33/02** (20130101); **H05B45/10** (20200101); **H05B45/38** (20200101); **H05B47/18** (20200101); H05B45/3725 (20200101)

Field of Classification Search

CPC: H02J (9/061); H05B (47/18); H05B (45/38); H05B (45/10); H05B (33/02); H05B (45/3725)

References Cited

U.S. PATENT DOCUMENTS

Patent No.	Issued Date	Patentee Name	U.S. Cl.	CPC
5212478	12/1992	Moseley	N/A	N/A
5530322	12/1995	Ference et al.	N/A	N/A
5808417	12/1997	Ference et al.	N/A	N/A
6055163	12/1999	Wagner et al.	N/A	N/A
6188181	12/2000	Sinha et al.	N/A	N/A
6370039	12/2001	Telefus	N/A	N/A
7566987	12/2008	Black et al.	N/A	N/A
7675195	12/2009	Mierta	N/A	N/A
7741732	12/2009	Black et al.	N/A	N/A
7781919	12/2009	Black et al.	N/A	N/A
7880638	12/2010	Veskovic et al.	N/A	N/A
7936281	12/2010	Rigatti et al.	N/A	N/A
8247608	12/2011	Roques et al.	N/A	N/A
8492987	12/2012	Nuhfer et al.	N/A	N/A
8680787	12/2013	Veskovic et al.	N/A	N/A
8866401	12/2013	Shearer et al.	N/A	N/A
9113521	12/2014	Gredler et al.	N/A	N/A
9155144	12/2014	Mitterbacher	N/A	N/A
9232574	12/2015	Veskovic	N/A	N/A
9253829	12/2015	Veskovic	N/A	N/A
9565731	12/2016	DeJonge	N/A	N/A
9655180	12/2016	Stevens, Jr. et al.	N/A	N/A

10342100	12/2018	DeJonge et al.	N/A	N/A
10548202	12/2019	DeJonge et al.	N/A	N/A
10820394	12/2019	DeJonge et al.	N/A	N/A
11329502	12/2021	DeJonge et al.	N/A	N/A
11670957	12/2022	DeJonge et al.	N/A	N/A
11949281	12/2023	DeJonge	N/A	H05B 47/18
2008/0067954	12/2007	Black et al.	N/A	N/A
2008/0067959	12/2007	Black et al.	N/A	N/A
2008/0111491	12/2007	Spira et al.	N/A	N/A
2008/0136261	12/2007	Miarta	N/A	N/A
2008/0278297	12/2007	Steiner et al.	N/A	N/A
2009/0160627	12/2008	Godbole et al.	N/A	N/A
2009/0271642	12/2008	Cheng et al.	N/A	N/A
2011/0006603	12/2010	Robinson et al.	N/A	N/A
2011/0018464	12/2010	Lo et al.	N/A	N/A
2011/0074222	12/2010	Steiner et al.	N/A	N/A
2011/0309746	12/2010	Eckel et al.	N/A	N/A
2012/0139472	12/2011	Ishibashi	N/A	N/A
2012/0140363	12/2011	Jeppe et al.	N/A	N/A
2013/0030589	12/2012	Pessina et al.	N/A	N/A
2013/0063047	12/2012	Veskovic	N/A	N/A
2013/0151025	12/2012	Wendt et al.	N/A	N/A
2013/0181630	12/2012	Taipale et al.	N/A	N/A
2013/0214609	12/2012	Carmen et al.	N/A	N/A
2014/0001974	12/2013	Lu et al.	N/A	N/A
2014/0042933	12/2013	Livschitz et al.	N/A	N/A
2014/0152101	12/2013	Kusunose	N/A	N/A
2014/0265568	12/2013	Crafts et al.	N/A	N/A
2014/0265880	12/2013	Taipale et al.	N/A	N/A
2014/0334202	12/2013	Cameron	N/A	N/A
2014/0361699	12/2013	Sullivan et al.	N/A	N/A
2015/0349567	12/2014	Weightman et al.	N/A	N/A
2016/0036349	12/2015	Cooper et al.	N/A	N/A
2016/0172900	12/2015	Welch, Jr.	N/A	N/A
2016/0329849	12/2015	Nakajima et al.	N/A	N/A
2017/0111976	12/2016	Van Endert	N/A	N/A
2017/0123390	12/2016	Barco et al.	N/A	N/A
2017/0311400	12/2016	Newman, Jr. et al.	N/A	N/A
2018/0013292	12/2017	White et al.	N/A	N/A
2018/0027630	12/2017	DeJonge et al.	N/A	N/A
2018/0367026	12/2017	Rayner et al.	N/A	N/A

FOREIGN PATENT DOCUMENTS

Patent No.	Application Date	Country	CPC
3028692	12/2015	FR	N/A
2011055192	12/2010	WO	N/A
2016079400	12/2015	WO	N/A

OTHER PUBLICATIONS

Redwood System Installation Guide:, Redwood Version 2.1, Available at <www.redwoodsistemas.com>, Redwood Systems Smart Lights/Smart Buildings, Aug. 2012. cited by applicant
“Redwood Systems' Intelligent Lighting for Data Centers”, ANXTER, Redwood Systems Smart Lights/Smart Buildings, Sep. 2013. cited by applicant

Primary Examiner: Berhane; Adolf D

Background/Summary

CROSS-REFERENCE TO RELATED APPLICATIONS (1) This application is a continuation of U.S. patent application Ser. No. 18/307,924 filed Apr. 27, 2023; which is a continuation of U.S. patent application Ser. No. 17/739,479 filed May 9, 2022 (now U.S. Pat. No. 11,670,957 issued Jun. 6, 2023); which is a continuation of U.S. patent application Ser. No. 17/078,947, filed Oct. 23, 2020 (now U.S. Pat. No. 11,329,502, issued May 10, 2022); which is a continuation of U.S. patent application Ser. No. 16/457,962, filed Jun. 29, 2019 (now U.S. Pat. No. 10,820,394, issued Oct. 27, 2020); which is a divisional of U.S. patent application Ser. No. 15/656,437, filed Jul. 21, 2017 (now U.S. Pat. No. 10,548,202, issued Jan. 28, 2020); which claims the benefit of Provisional U.S. Patent Application No. 62/365,773, filed Jul. 22, 2016, the disclosures of which are incorporated herein by reference in their entireties.

BACKGROUND

(1) Light-emitting diode (LED) light sources (i.e., LED light engines) are often used in place of or as replacements for conventional incandescent, fluorescent, or halogen lamps, and the like. LED light sources may comprise a plurality of light-emitting diodes mounted on a single structure and provided in a suitable housing. LED light sources are typically more efficient and have longer operational lives as compared to incandescent, fluorescent, and halogen lamps. In order to illuminate properly, an LED driver control device (i.e., an LED driver) may be coupled to the LED light source for regulating the power supplied to the LED light source. The LED driver may regulate either the voltage provided to the LED light source, the current supplied to the LED light source, or both. Examples of LED drivers are described in greater detail in commonly-assigned U.S. Pat. No. 8,492,987, issued Jul. 23, 2010, and U.S. Patent Application Publication No. 2013/0063047, published Mar. 14, 2013, both entitled LOAD CONTROL DEVICE FOR A LIGHT-EMITTING DIODE LIGHT SOURCE, the entire disclosures of which are hereby incorporated by reference in their entirety.

(2) As the electrical infrastructure changes to accommodate renewable energy sources (e.g., wind power, photovoltaic solar power, fuel cells, etc.), it is likely that there will be a movement towards direct current (DC) power distribution as this is the native version of generation for many of these technologies. For example, photovoltaic solar arrays generate DC power and often this is directly stored in batteries. From there, power may be drawn directly from the battery bank as direct current (DC), or it may be inverted to alternating current for use by appliances. With this anticipated move to a DC power bank, it would be desirable to use power directly as DC power rather than convert it to AC power. Many AC electrical loads actually require DC power to function and traditionally require rectification to render the AC power useful to the electrical load. Many AC electrical loads also employ active power factor correction (PFC) so as to minimize production of unwanted harmonics on the AC mains. However, the rectification and active power factor correction operations introduce an efficiency loss.

(3) Finally, existing electrical panels (e.g., lighting panels) typically include only a minimum

amount of hardware for controlling the operation of the electrical load, with most, if not all, of the power conversion and load control functionality residing remote from the panel at the electrical load. For example, electrical panels typically provide AC mains voltage to attached electrical loads, and the electrical loads typically include the required processors, converters, and controls necessary to convert the received AC mains voltage into appropriate driving voltages for the electrical loads. For instance, typical light fixtures include not only the light emitting elements themselves, but also the hardware and software (e.g., LED driver, ballast, etc.) required to convert the received AC mains voltage into a driving voltage for the lighting load. This tends to result in expensive and bulky lighting fixtures.

SUMMARY

(4) Systems and methods described herein provide examples of a load control system that includes an electrical panel (e.g., a modular electrical panel), where the electrical panel is configured to control a plurality of electrical loads. The electrical panel may include a control circuit, memory, and a communication circuit. The electrical panel may include one or more of an alternating current (AC) line feed, a direct current (DC) line feed, or a battery bank feed. The AC line feed may be connected to an AC power source, while the DC line feed may be connected to a DC power source (e.g., one or more alternative energy devices, such as, but not limited to: a photovoltaic (PV) system, a wind turbine system, a hydroelectric system, etc.), and the battery bank feed may be connected to a bank of batteries. The electrical panel may be, for example, a lighting panel, and the plurality of electrical loads may include at least lighting loads (e.g., LED light engines). The electrical panel may be, for example, a shading panel, and the plurality of electrical loads may include at least motorized window treatments.

(5) The electrical panel may also include a plurality of power supplies and a plurality of control modules, where more than one control module may be associated with each of the plurality of power supplies. Each power supply may be configured to receive AC power and provide DC power, while one or more of the power supplies may also be configured to receive DC input and output a converted version of the received DC power. Each control module may be configured to receive DC power from an associated power supply and provide an output voltage to at least one electrical load. The control module may provide an output voltage that is regulated to provide power for operation and control of an associated electrical load, or the control module may provide an output voltage that is then received by an accessory module at the electrical load, where the accessory module performs the final stages of regulation and/or control for powering the electrical load. As such, the electrical panel provides flexibility as to whether each stage of conversion, regulation, and/or control is performed at a control module located within the electrical panel, or performed at an accessory module located at an electrical load.

(6) The electrical panel may be configured to provide DC power from the battery bank feed to at least one electrical load during an emergency situation, for example, thereby eliminating the need for local and/or dedicated batteries to be located at the electrical load for emergency power. The electrical panel may further comprise a grid-tie inverter, which may provide for an electrical connection from the DC line feed (e.g., and in turn a DC power source) to the AC line feed (e.g., and in turn an AC electrical grid). As such, the control circuit of the electrical panel may be configured to feed DC power to an electrical grid via the AC line feed. Further, the control circuit may be configured to determine whether to provide, to at least one power supply, AC power from the AC line feed or DC power from the DC line feed, for example, based on one or more factors described herein (e.g., time-of-day pricing of AC power from the electrical grid).

(7) One or more of the power supplies may be multi-feed power supplies. For example, one or more of the power supplies may be configured to operate an electrical load when receiving AC power from the AC line feed using an AC input on the power supply, and configured to operate the electrical load when receiving DC power from the DC line feed using a DC input on the power supply. Control modules may be configured to output different Classes of power (e.g., Low Voltage

Class 2, Low Voltage Class 1, High Voltage Class 1, etc.). For example, a first control module may be configured to output a first Class of power, and a second control module may be configured to output a second Class of power, the second Class being different from the first Class. Further, one or more of the power supplies may be configured to determine whether they are operating a Low Power Class 2 power supply, a Low Power Class 1 power supply, or a High Power Class 1 power supply, based on one or more of a measured current on a link to the electrical load, a measured voltage on a link to the electrical load, a measured power on a link to the electrical load, or feedback from the electrical load.

(8) One or more of the control modules may be configured to provide DC power and communications over a two-wire link to an electrical load. For example, a control module may be configured to provide communications by injecting a timing window within a DC voltage, the timing window being characterized by one of four offsets, where each offset corresponds to a different data transmission (e.g., “00”, “01”, “10”, or “11”).

Description

BRIEF DESCRIPTION OF THE DRAWINGS

(1) FIG. 1 is a simplified block diagram of an example load control system.

(2) FIG. 2 is a simplified block diagram of an example power supply and control module of the load control system of FIG. 1.

(3) FIG. 3 is a simplified block diagram of an example forward converter and current sense circuit of the control module of FIG. 2.

(4) FIG. 4 is an example of a timing diagram of a DC voltage generated by a control module of a lighting panel for communicating digital messages to an electrical load.

(5) FIG. 5 is an example flowchart of a classification detection procedure performed by an electrical panel.

(6) FIG. 6 is an example of a grid-tie inverter control procedure performed by an electrical panel

DETAILED DESCRIPTION

(7) FIG. 1 is a simplified block diagram of an example load control system **100**. The load control system **100** may comprise an electrical panel (e.g., a lighting panel **102**) and one or more electrical loads. The lighting panel **102** may include a panel control circuit **104** (e.g., a panel controller), memory **105**, a communication circuit **106**, a lighting panel power supply **107**, one or more power supplies (e.g., AC/DC power converters), and one or more control modules. The electrical loads may include one or more lighting loads, such as, but not limited to, LED light engines **150** and one or more motorized window treatments **160**. Accordingly, the lighting panel **102** may provide power and control for a plurality of different types of electrical loads.

(8) The lighting panel **102** may control the amount of power delivered to an electrical load, such as an LED light engine **150**, and thus the intensity of the light engine. An LED light engine **150** may include a single LED or a plurality of LEDs connected in series, in parallel, or in a suitable combination thereof, depending on the particular lighting system. An LED light engine **150** may comprise one or more organic light-emitting diodes (OLEDs). The LED light engine **150** may also include a resistor and/or low dropout regulator (LDR) that regulates/offsets the current through the LEDs.

(9) The motorized window treatments **160** may each comprise, for example, a cellular shade, a roller shade, a drapery, a Roman shade, a Venetian blind, a Persian blind, a pleated blind, a tensioned roller shade system, or other suitable motorized window covering. The motorized window treatments **160** may each comprise a motor drive unit (not shown) for adjusting the position of a covering material of the motorized window treatment **160**, for example, to control the amount of daylight entering the space. The motor drive unit of each motorized window treatment

160 may be configured to receive digital messages via wired or wireless signals and to control the amount of daylight entering the space in response to the received digital messages. The motorized window treatments **160** may each have an antenna mounted for receiving radio frequency (RF) signals. The motor drive unit of each motorized window treatment **160** may receive power from an external DC power supply.

(10) The lighting panel **102** may include input terminals for an AC line feed **132**, a DC line feed **134**, and/or a battery bank feed **133** providing power to the lighting panel **102**. For example, the lighting panel **102** may receive power from the AC line feed **132** that may provide a three-phase AC mains input voltage from an AC power source (not shown). The AC line feed **132** may receive the AC input voltage via a main breaker or directly from the grid. Alternatively, or additionally, the lighting panel **102** may receive power from the DC line feed **134** and/or the battery bank feed **133** that may provide a DC input voltage from a DC power source (not shown). For example, the DC power source may include one or more alternative energy devices, such as, but not limited to: a photovoltaic (PV) system, a wind turbine system, a hydroelectric system, etc. The DC power source may also include a battery bank. If the lighting panel **102** is connected to both an AC power source and a DC power source, the panel control circuit **104** may be configured to determine how much power to receive (i.e., draw) from the AC power supply, and how much power to receive from the DC power supply, based on one or more factors (e.g., variables), such as time-of-day pricing (e.g., of the AC power supply), availability of power from either supply, external conditions (e.g., environmental conditions, price index, time of day, etc.), and/or the like.

(11) The lighting panel **102** may include a portion or the entirety of each of a plurality of load control devices (e.g., where a load control device may include a combination of a power supply and a control module). In instances where the lighting panel **102** includes a portion of a load control device, the remaining portions may reside remote from the lighting panel **102** (e.g., at the electrical load). For example, the lighting panel **102** may include various parts or stages of an LED driver used to control an LED light engine. The lighting panel **102** may include one or more LED drivers in their entirety and/or one or more varying portions of other LED drivers. As such, the lighting panel **102** may be modular and include select stages of power conversion and control (e.g., dimming control) in the lighting panel **102** itself for each of a plurality of electrical loads and electrical load types. For example, expensive and/or complicated control techniques (e.g., power conversion techniques aimed at reducing switching loss) may be implemented in the lighting panel **102** to reduce the costs and/or complexity of the individual light fixtures (and in turn the entire light control system **100**). The lighting panel **102** may output DC power to at least some of the connected electrical loads, and as such, provide for DC power distribution (e.g., versus AC power distribution) from the panel to the loads. The example lighting panel **102** of FIG. 1 is just one of many configurations that may be taken by the lighting panel **102**.

(12) The lighting panel **102** may include one or more power supplies and one or more control modules. The power supplies may perform power conversion (e.g., from an AC input to a DC output) and/or power factor correction (PFC) to adjust the power factor towards a power factor of one. For example, the power supplies may each include an AC/DC converter and a PFC circuit. The AC/DC converter may be in the form of a rectifier circuit. Alternatively, the power supply may not include an AC/DC converter (e.g., a rectifier circuit), for example, if the power supply is connected to the DC line feed **134** and not the AC line feed **132**. The PFC circuit may include a boost converter, a buck converter, a buck-boost converter, a flyback converter, a linear regulator, or a combination of a switching regulator and a linear regulator. The boost converter of the power supply may receive a rectified voltage $V_{\text{sub.RECT}}$ and generate a boosted DC bus voltage $V_{\text{sub.BUS}}$ across a bus capacitor $C_{\text{sub.BUS}}$ (e.g., an electrolytic capacitor). The power supply may provide the DC bus voltage $V_{\text{sub.BUS}}$ to one or more control modules. The power supply and the control modules may also communicate with one another over the DC bus (e.g., in accordance with the communication protocol described with reference to FIG. 4). A power supply may include

a dedicated control circuit or be entirely controlled by the panel control circuit **104** of the lighting panel **102**.

(13) The lighting panel **102** may include a plurality of different power supplies that output a plurality of different power-limited DC bus voltages $V_{sub.BUS}$ (e.g., 100 W limited, 500 W limited, 750 W limited, 4,500 W limited, and/or the like). The power supplies may include their own control circuit (e.g., microprocessor, an application-specific integrated circuit (ASIC), or analog IC) and/or use the panel control circuit **104** of the lighting panel **102**. Further, the power supplies may include a radio-frequency interference (RFI) filter circuit that minimizes RF noise on the AC mains or the DC mains. The power supplies may also include snubbing circuits that reduce switching losses of the AC/DC converters, such as lossless snubbers. Further, when not in use, the power supplies may reside in a sleep state (e.g., when the power supply comprises its own control circuit) or a complete off state (e.g., when the power supply does not include its own control circuit and uses the panel control circuit **104** of the lighting panel **102**).

(14) The lighting panel **102** may, for example, include AC/DC power supplies, such as an AC/DC power supply **108**, an AC/DC power converter **110**, and/or an AC/DC power converter **112**. The AC/DC power supplies may receive AC line voltage from the AC line feed **132**. The AC/DC power supplies may output DC power (e.g., the DC bus voltage $V_{sub.BUS}$) to one or more control modules. Further, the AC/DC power supplies may receive one or more control signals from the panel control circuit **104** and/or from one or more input devices for controlling the operation and output voltages of the AC/DC power supplies (e.g., via internal control circuits of the power supplies). The AC/DC power supplies may also send command signals (e.g., wired or wireless control signals) to one or more control modules or electrical loads for controlling operational characteristics (e.g., pulse-width modulated (PWM) duty cycle, intensity, color, temperature, fade rate, etc.) of the control modules or the electrical loads. Further, the AC/DC power supplies may send feedback signals to the panel control circuit **104** relating to the operation of the power supplies themselves, and/or the control modules or the electrical loads.

(15) The power supplies may be rated for any electrical class, for example, Class 1 or Class 2 power supplies. For example, the AC/DC power supply **108** may be a Class 2 power supply that receives 100-277 VAC and outputs 24V/48V DC. Class 2 power supplies may, for example, be limited to 60V DC and 100 W. The AC/DC converters **110** may be a Low Voltage Class 1 power supply (e.g., limited to 15 A, 60V, and 750 W), while the AC/DC converter **112** may be a High Voltage Class 1 power supply (e.g., limited to 10 A, 450V, and 4,500 W). The AC/DC converter **110** may receive 100-277 VAC, perform power factor correction via a PFC circuit (e.g., a boost converter or flyback converter), and output 24V/48V DC. The power supplies of the lighting panel **102** are not limited to Class 1 and Class 2 power supplies, but may also be rated as other UL or IEC classifications as required by particular local regulations. Additionally, the lighting panel system **102** may provide power and control signals to motorized shading equipment, such as motorized window treatments **160**.

(16) The power supplies and/or the panel control circuit **104** of the lighting panel **102** may be configured to determine the rated class type of a power supply (e.g., Low Voltage Class 2, Low Voltage Class 1, High Voltage Class 1, etc.). The determination may be made, for example, based on the control modules and/or electrical loads that are connected to the power supply, and in turn, the desired operational characteristics of the power supply. For example, the power supply (e.g., or the panel control circuit **104**) may be configured to measure the amount of current, voltage, and/or power requested on the link, e.g., at the output terminals of the power supply, to determine its desired class type. Alternatively or additionally, a control module and/or electrical load (e.g., an accessory module located at the electrical load) may communicate (e.g., by transmitting a message) to the power supply and/or panel control circuit **104** indicating its power requirements, such as an amount of power needed, type of dimming required, etc. The power supply may then be configured (e.g., by the panel control circuit **104**) to control (e.g., limit) its output power accordingly (e.g.,

operate as a Low Voltage Class 2 power supply, a Low Voltage Class 1 power supply, a High Voltage Class 1 power supply, etc.). The power supply may also be configured to provide an alert and/or report back to the panel control circuit **104** upon determining its class type. Further, the panel control circuit **104** may be configured to adjust the class type of a power supply after installation. For example, a power supply may be initially configured to operate as a Class 1 power supply (e.g., a High Voltage Class 1 power supply), and later be configured (e.g., by the panel control circuit **104**) to operate as another class of power supply (e.g., as a Low Voltage Class 2 power supply provided that the proper compliance with the relevant standards exists).

(17) Although described with reference to AC/DC power supplies, the lighting panel **102** may include DC power converters that receive direct DC voltage from the DC line feed **134** and output 24V/48V DC, for example. Further, one or more of the power supplies may be configured to receive an AC input and a DC input, for example, such that the power supply is configured to operate in an AC mode when the input voltage is an AC voltage and in a DC mode when the input voltage is a DC voltage. An example of a power supply that is configured to operate in an AC mode and a DC mode is described herein.

(18) The lighting panel **102** may comprise a plurality of control modules for every power supply (e.g., the AC/DC power supply **108**, the AC/DC power converter **110**, and/or the AC/DC power converter **112**). The lighting panel **102** may also include physical and/or electrical circuit protection that may be located before the power supply, such as breakers **124**, and/or after the control module, such as breakers **126**. Additionally, output breakers may be configured as electronic breakers whose operating characteristics are adjusted via panel control circuit **104** or a separate control circuit. A plurality of different types of control modules may be connected to a single power supply, and each control module may be individually controllable (e.g., by the power supply and/or the panel control circuit **104**). Further, the power supply and/or the panel control circuit **104** may address each control module uniquely, for example, depending on the functions performed by that control module (e.g., color changing, emergency, zoning, etc.). Additionally, the control modules may communicate information back to the power supply and/or the panel control circuit **104**. For example, the control modules may receive approval from the power supply before fully powering on its electrical load (e.g., to prevent overloading the power supply or exceeding the regulatory requirement for the particular class installation).

(19) The lighting panel **102** comprises a plurality of types of control modules including, for example, control modules for driving LED light engines **150**, control modules for driving a motorized window treatment **160**, and control modules for providing digital communication to an electrical load. The control modules may receive DC power from a power supply and provide controlled power to the electrical load (e.g., power to a LED light engine **150**, power to a motorized window treatments **160**, power to an accessory module remote from the lighting panel **102**, and/or the like). A control module may output the proper power for operation and control of an electrical load, such as the driver module **114**, or the control module may operate in tandem with an accessory module located at the electrical load (e.g., an isolated low voltage converter **116** in combination with an accessory module **152**, or a fault detect and branch circuit **118** in combination with an accessory module **154**), such that the two in combination provide the proper power for operation and control of the electrical load. As such, the lighting panel **102** provides for a modular architecture that allows for select functionality to be performed within the lighting panel **102** and other functionality to be performed at the accessory module located at the electrical load.

(20) In addition to modularity, efficiency gains may be realized through use of the lighting panel **102**. For example, the control module in the lighting panel may output high voltage (e.g., 450V) to an electrical load, which may be more efficient than distribution at lower voltages (e.g., 277V). Further, in instances where the output of the control module in the lighting panel **102** is lower than typical line voltage (e.g., Class 2 scenarios, such as the output of the driver module **114**), the power loss at the electrical load may be reduced, the load may run cooler and in turn last longer, and the

electrical loads may not require as much hardware/software located at the load itself, resulting in the load being smaller and more lightweight. If the power supply receives DC input, the design of the power supply and/or control modules may be simplified (e.g., without PFC-related circuitry), and end-to-end efficiency may be enhanced. Moreover, having a centrally located lighting panel **102** within a facility makes maintenance and service easier.

(21) The control modules may output controlled DC power or controlled AC power, depending on the configuration. The control modules may control the output power in accordance with a received command signal from a control circuit (e.g., such as the panel control circuit **104**), a connected power supply, a wireless control signal received from an input device, and/or feedback from the electrical load (e.g., temperature, light output, power, color, etc.). The control modules may also provide feedback data to the power supply and/or the panel control circuit **104** of the lighting panel **102** (e.g., feedback data relating to the electrical load, the input power of the control module, intensity level of a connected light source, load failure conditions, sensor statuses, lumen levels, etc.). A control module may include a dedicated control circuit, or may be controlled by the panel control circuit **104** of the lighting panel **102** and/or a control circuit of the associated power supply.

(22) One example control module is the driver module **114**. The driver module **114** receives a DC bus voltage $V_{sub.BUS}$ from the AC/DC power supply **108**, and provides a regulated DC voltage (e.g., a PWM DC voltage, a constant voltage DC signal, or a DC level with an imposed communication signal etc.) to the LED light engine **150**. For example, the driver module **114** may include a load regulation circuit that receives the bus voltage $V_{sub.BUS}$ and controls the amount of power delivered to the LED light engine **150**, for example, to control the intensity of the LED light engine **150** between a low-end (i.e., minimum) intensity $L_{sub.LE}$ (e.g., approximately 0.1-5%) and a high-end (i.e., maximum) intensity $L_{sub.HE}$ (e.g., approximately 100%). The driver module **114** may also include additional circuitry, such as a current sense circuit and/or a voltage sense circuit. Since the driver module **114** provides a regulated voltage to the LED light engine **150**, the LED light engine **150** that is connected to the driver module **114** may include a minimum amount of hardware and/or software, thereby reducing the cost, size, and complexity of the fixture. For example, the LED light engine **150** may include (e.g., only include) a single LED or a plurality of LEDs, a resistor, and a low drop-out (LDO) regulator that regulates the current through the LEDs.

(23) In other examples, some or all of the functionality of the driver module **114** may be split between a control module located in the lighting panel **102** (e.g., the isolated low voltage converter **116**, the fault detect and branch circuit **118**, or the like) and an accessory module located at the electrical load (e.g., the accessory modules **152** and **154**). As such, the lighting panel **102** provides for a modular design where an electrical load (e.g., LED light engine **150**) may include a varying degree of regulation circuitry, while the remaining portions may reside within a control module located within the lighting panel **102** itself. Additionally, and although not illustrated, the lighting panel **102** may include a power supply and the electrical load may include the entirety of the control module (e.g., within the same housing/fixture). For example, the lighting panel may include the AC/DC power supply **108**, and the voltage driver module **114** may be implemented as an accessory module located at the LED light engine **150** (e.g., within the same housing/fixture).

(24) Further, such modularity of control modules allows for both Class 1 and Class 2 configurations of electrical loads. For example, together, the isolated low voltage converter **116** and the accessory module **152** may include all of the functionality of a LED driver module (e.g., the driver module **114**). The isolated low voltage converter **116** may, for example, include an isolated converter (e.g., a transformer) and a current sense circuit, and the accessory module **152** may include back end regulation at the LED light source **150**. As such, the isolated low voltage converter **116** may output voltage in accordance with Low Voltage Class 2 requirements. As another example, the fault detect and branch circuit **118** may include fault detection and regulation circuits, and the accessory module **154** may include the converter. In such a configuration, the fault detect and branch circuit **118** may output voltage in accordance with High Voltage Class 1

requirements (e.g., 450V). These are just two non-limiting examples of how a control module (e.g., the driver module **114**) may be split between a control module located within the lighting panel **102** and an accessory module located at the electrical load.

(25) The lighting panel **102** may also include one or more control modules for providing digital communication to an electrical load (e.g., communication modules). For example, the lighting panel **102** may include one or more device control modules **120** and/or accessory communication modules **122**. The device control module **120** may provide communication over a dedicated communication line to one or more electrical loads (e.g., motorized window treatments **160**) to control operational characteristics of the electrical load (e.g., raise, lower, zoning information, unique identifier, etc.). A sensor/keypad module **170** may receive wired or wireless digital signals from sensors and/or keypads, and the sensor/keypad module **170** may send digital commands to the device control module **120** (e.g., via the communication circuit **106**) to control the electrical loads. The accessory communication module **122** may provide communication over a dedicated communication line to one or more electrical loads (e.g., LED light engines **150**) to control operational characteristics of the electrical load (e.g., intensity, color, temperature, fade rate, zoning information, unique identifier, etc.). The accessory communication module **122** may receive digital commands via the communication circuit **106**.

(26) The lighting panel **102** (e.g., the panel control circuit **104**, a power supply, and/or a control module) may provide both data and power to an electrical load, such as an LED light engine **150** or accessory module **152,154**, using a single line (e.g., two wires). The electrical load may be uniquely addressed such that individualized control of and/or communication with the electrical load may be performed. For example, the lighting panel **102** may perform a form of power line communication (PLC) when providing DC power to the electrical load, and/or perform modulate a DC voltage to provide communication when powering an electrical load with DC power. An example form of DC power and communication that may be provided over two wires is provided in FIG. 4, which for example, may be used when the power supply is operating as a Class 2 power supply (e.g., AC/DC power supply **108** and the voltage driver module **114**). Alternately, the PLC communication over the DC power wires may use techniques such as current carrier signals or high frequency modulated signals to communicate digital information between the lighting loads and the communication circuit **104**.

(27) The lighting panel **102** may also include additional control modules and/or power supplies. For example, the lighting panel **102** may include a 0-10V dimming module **142** that provides 0-10V dimming commands to one or more line voltage electrical loads. The lighting panel **102** may also include a phase adaptive module **144** used to provide phase controlled AC voltage to one or more voltage loads (e.g., incandescent lamps or phase-dimmable LED lamps). Further, the lighting panel **102** may include a switching module **146** that may provide traditional on/off switching control for one or more electrical loads. Finally, the lighting panel **102** may include a shade power supply module **148** that may provide power and zoning to multiple motorized window treatments **160** (not illustrated).

(28) The panel control circuit **104** may be configured to control the operation of the power supplies and or control modules to selective provide power drawn from the AC line feed **132**, from the DC line feed **134**, and/or from the battery bank feed **133**. For example, the lighting panel **102** may include a switching circuit configured to switch between directing AC power or DC power to one or more power supplies, the power supplies themselves may receive both AC power and DC power and be configured to switch between the use of AC power or DC power, or the grid-tie inverter **135** may be configured to direct AC power or DC power to one or more power supplies, for example, based on one or more factors described herein. For example, in each instance, the control circuit **104** may control the switching between the use of AC power or DC power by the one or more power supplies. This allows the lighting panel **102** to selectively use power from a particular source based on a variety of conditions, such as, but not limited to, during AC mains power failure, during

times of peak demand reduction, when substantial alternate power is available from a PV array, etc. Additionally, this selective direction of power to the electrical loads may be used to accomplish the requirements of emergency power sourcing to particular lighting loads as required by certain national building codes. This system is advantageous in managing the source of emergency power in that it is configurable after the installation of the system rather than requiring fixture outfitting with emergency power during the design and installation phase of a project. In addition to controlling the switch between the use of AC power or DC power by a power supply, the control circuit **104** may control one or more characteristics of the electrical loads (e.g., the intensity level of an LED light engine **150**) based on whether a power supply is receiving AC power or DC power. For example, the control circuit **104** may lower the intensity (e.g., high-end intensity) of one or more lighting load when using DC power (e.g., only DC power).

(29) The panel control circuit **104** may be configured to control the operation of the power supplies and/or the control modules, for example, in response to a user command received via one or more input devices. For example, if a power supply and/or control module includes a dedicated control circuit, then the panel control circuit **104** may manage the operation of the control circuit of the power supply and/or the control module, and the control circuit of the power supply may control the internal operation of the power supply and/or associated control module(s) (e.g., and when configured, the control circuit of the control module may control the internal operation of the control module). If, however, the power supply does not include a dedicated control circuit, then the panel control circuit **104** may control the internal operation of the power supply and/or associated control module(s). The panel control circuit **104** may comprise, for example, a digital controller or any other suitable processing device, such as, for example, a microcontroller, a programmable logic device (PLD), a microprocessor, an application specific integrated circuit (ASIC), or a field-programmable gate array (FPGA).

(30) The panel control circuit **104** may comprise and/or be coupled to memory **105**. The memory **105** may include one or more components of volatile and/or non-volatile memory, in any combination. The memory **105** may store operational characteristics of the components of the lighting panel **102**. The lighting panel power supply **107** may generate a direct-current (DC) supply voltage V_{subCC} for powering the panel control circuit **104** and the other low-voltage circuitry of the lighting panel **102**. The lighting panel power supply **107** may be coupled to the AC line feed **132**, the DC line feed **134**, the battery bank feed **133**, and/or a power supply (e.g., AC/DC power supply **108**, **110**, **112**) via the electrical connections **109**. The panel control circuit **104** may be connected to and configured to control any combination of components (e.g., all components) of the lighting panel **102**.

(31) The communication circuit **106** of the lighting panel **102** may be coupled to a gateway device **138** and/or one or more data terminals **136**, which for example, may include a network link (e.g., Ethernet port), a digital communication link, a Digital Multiplex (DMX) link, etc. The communication circuit **106** may be configured to communicate via a wireless communication link, such as a radio-frequency (RF) communication link or an infrared (IR) communication link.

(32) The load control system **100** may comprise one or more input devices, such that the lighting panel **102** is configured to receive user inputs, transmit digital messages, and/or receive digital messages via the input devices. The digital messages may be transmitted via wired (e.g., through a wired communication link) or wireless signals (e.g., the RF signals). For example, the input devices may include one or more of an access point or hub **166**, a wireless sensor **162** (e.g., an occupancy/vacancy sensor, a daylight sensor, etc.), a wireless keypad **164** (e.g., a battery-powered handheld remote control device), a sensor/keypad module **170**, a wired sensor **172** (e.g., an occupancy/vacancy sensor, a daylight sensor, etc.), a visual display remote control device **174** (e.g., a dynamic keypad), a wireless mobile device **180**, a web interface **182**, a wall-mounted remote control device (not shown), etc. The access point or hub **166** may be configured to transmit and receive wired and wireless signals, and may include a network connection to the lighting panel **102**.

(e.g., the panel control circuit **104** and/or the communication circuit **106**) and may act as a standard protocol (e.g., Wi-Fi) access point and/or a proprietary protocol (e.g., the ClearConnect® protocol) access point for one or more input devices and/or electrical loads. The sensor/keypad module **170** may include a QS link to one or more wire devices, such as the wired sensor **172** and the visual display remote control device **174**, and may be configured to communicate wirelessly using a proprietary protocol (e.g., the ClearConnect® protocol).

(33) The digital messages may include information such as a command, a query, and/or identifying information. For example, the digital messages transmitted by the input device may include a unique identifier (e.g., a serial number) associated with the transmitting input device. The wireless signals carrying the digital messages may be transmitted at a certain communication frequency or frequency range f.sub.RF (e.g., approximately 434 MHz, 900 MHz, 2.4 GHz, or 5.6 GHz). The transmission may utilize a proprietary communication protocol, such as the ClearConnect® protocol, Wi-Fi, Bluetooth®, ZIGBEE, Z-WAVE, KNX-RF, ENOCEAN RADIO, and/or a different proprietary protocol.

(34) The input devices may be assigned to one or more components of the load control system **100** (e.g., the lighting panel **102**, the panel control circuit **104**, a power supply (e.g., AC/DC power supply **108**, an AC/DC power converter **110**, and/or an AC/DC power converter **112**), a control module (e.g., control module **114**, **116**, or **118**, communication module **120** or **122**), an accessory module (e.g., the accessory module **152** or **154**), and/or a motorized window treatment **160**) during a configuration procedure of the load control system **100**, such that the load control system, e.g., the lighting panel **102**, may be responsive to digital messages transmitted by the input devices. Examples of methods of associating control devices are described in greater detail in commonly-assigned U.S. Patent Application Publication No. 2008/0111491, published May 15, 2008, entitled RADIO-FREQUENCY LIGHTING CONTROL SYSTEM; U.S. Patent Application Publication No. 2013/0214609, published Aug. 22, 2013, entitled TWO-PART LOAD CONTROL SYSTEM MOUNTABLE TO A SINGLE ELECTRICAL WALLBOX; and U.S. patent application Ser. No. 13/830,237, filed Mar. 14, 2013, entitled COMMISSIONING LOAD CONTROL SYSTEMS; the entire disclosures of which are hereby incorporated by reference.

(35) The communication circuit **106** of the lighting panel **102** may be connected to the gateway device **138** (e.g., a bridge) and may be configured to enable communication with a network, such as a wireless network and/or wired local area network (LAN). The gateway device **138** may be connected to a router (not shown) via a wired digital communication link (e.g., an Ethernet communication link). The router may allow for communication with the network, e.g., for access to the Internet. The gateway device **138** may be wirelessly connected to the network, e.g., using Wi-Fi technology. The gateway device **138** may be configured to transmit the RF signals to one or more components of the lighting panel **102** and/or an accessory module for controlling the respective electrical loads in response to digital messages received from external devices via the network. The transmission may use a proprietary protocol described herein. The gateway device **138** may be configured to receive digital messages from the accessory modules of the load control system **100** (e.g., via the RF signals and/or using a proprietary protocol). The gateway device **138** may be configured to transmit digital messages via the network for providing data (e.g., status information) to external devices. The gateway device **138** may operate as a central controller for the lighting panel **102**, or may relay digital messages between the accessory modules of the load control system **100** and the network. For example, feedback and/or reports may be received (e.g., by the panel control circuit **104**) from the accessory modules of the load control system **100** and sent over the network (e.g., via the gateway device **138**) to a user.

(36) The lighting panel **102** may be in communication with a system administration (e.g., a system administrator server) via the gateway device **138**. For example, the panel control circuit **104** may be configured to provide a report relating to the operation and/or configuration of the lighting panel **102** and/or other components of the lighting control system **100** to the system administrator.

Further, the system administrator may be able to configure one or more components of the lighting panel **102** and/or other components of the lighting control system **100** from a remote location. A report may include one or more notification, alerts, or summaries relating to a failed component, a reconfigured component (e.g., change of rated class of a power supply), an additional load being connected to the lighting panel **102**, operation of the grid-tie inverter, a switch between AC-DC or vice versa, digital messages sent/received within the lighting system **100**, demands of the lighting system **100**, commissioning of components of the lighting system **100**, etc.

(37) The wireless mobile device **180** (e.g., a network device) may include a smart phone (e.g., an iPhone® smart phone, an Android® smart phone, or a Blackberry® smart phone), a personal computer, a laptop, a wireless-capable media device (e.g., MP3 player, gaming device, or television), a tablet device (e.g., an iPad® hand-held computing device), a Wi-Fi or wireless-communication-capable television, or any other suitable Internet-Protocol-enabled device. For example, the wireless mobile device **180** may be configured to transmit RF signals to the gateway device **138** via a Wi-Fi communication link, a Wi-MAX communications link, a Bluetooth® communications link, a near field communication (NFC) link, a cellular communications link, a television white space (TVWS) communication link, or any combination thereof. Examples of lighting systems operable to communicate with wireless mobile devices **180** on a network are described in greater detail in commonly-assigned U.S. Patent Application Publication No. 2013/0030589, published Jan. 31, 2013, entitled LOAD CONTROL DEVICE HAVING INTERNET CONNECTIVITY, the entire disclosure of which is hereby incorporated by reference.

(38) The lighting panel **102** may also include a combination grid-tie inverter/battery charger **135**. Alternatively, the lighting panel **102** may not include the grid-tie inverter/battery charger **135** (e.g., the load control system may include a grid-tie inverter external to the lighting panel), and may include a single DC line feed (e.g., the DC line feed **134**). With either configuration, a connection may be provided for tying the lighting panel **102** back to the AC power grid so that the lighting panel **102** may feed excess power back to the grid (e.g., via the AC line feed **132**). For example, the lighting panel **102** may use a portion of the DC power that is received from the DC power source (e.g., via the DC line feed **134** and/or via the battery bank feed **133**) for powering one or more electrical loads, and sell any remaining DC power back to the grid via the grid-tie inverter **135**. The panel control circuit **104** may determine how much DC power to use versus to sell back to the grid based on one or more factors (e.g., environmental conditions, price index of the AC power, time of day, etc.). Further, the panel control circuit **104** may decide to lower the power provided to one or more electrical loads (e.g., dim one or more LED light engines **150**) based on the amount of received DC power, potentially within a window of acceptance and/or based on one or more of the factors, such that the lighting panel **102** limits the amount of received AC power (e.g., potentially doesn't receive any AC power).

(39) The lighting panel **102** may be connected to an AC power supply via the AC line feed **132**, to a DC power supply via the DC line feed **134**, and to a battery bank via the battery bank feed **133**. The grid-tie inverter/battery charger **135** of the lighting panel **102** may be connected to a battery bank via the battery bank feed **133** and/or to a DC power source (e.g., an alternative energy source, such as a PV power supply) via the DC line feed **134**. The lighting panel **102** may provide power to any one or more of the electrical loads during any emergency situation (e.g., to power one or more LED light engines **150**) using energy stored in the battery bank. Therefore, the panel control circuit **104** may configure any of the connected electrical loads to operate as an emergency device (e.g., emergency lighting) during an emergency situation, for example, after installation and without having to connect dedicated batteries to a specific electrical load or to each electrical load. Further, the panel control circuit **104** may be configured to recharge the battery bank via the grid-tie inverter/battery charger **135** using the DC power source and/or the AC power source, for example, such that the battery bank does not need replenishment. Alternatively or additionally, the lighting panel **102** may use DC power received from the DC power supply and/or the battery bank directly

to power the electrical loads in emergency situations, for example, with the use of the battery bank or a site based generation facility.

(40) The load control system **100** may be configured (e.g., programmed) through a commissioning procedure. For example, the devices of the load control system **100** (e.g., the control modules of the lighting panel **102**, the accessory modules **152**, **154**, the input devices, etc.) may be associated with one another, for example, through a commissioning procedure. A combination of communication features may be used to create an intuitive and simple way to accomplish the commissioning aspects of an addressable lighting system. The mobile device **180** may be used to commission the load control system **100**. For example, the load control system **100** may include a plurality of lighting fixtures (e.g., the LED light engines **150** having accessory modules **152**, **154**), where each of the lighting fixtures are individually addressable, and as such, the load control system **100** may be installed and configured to the particular application with little regard (e.g., restriction) to the actual wiring structure utilized. The mobile device **180** may be used to perform zoning of fixtures after installation and without having to rewire the load control system **100**. For example, the lighting panel **102** may be configured to control (e.g., simultaneously control) a plurality of lighting fixtures that abut a row of windows in a building together to accomplish a daylight harvesting function, even though the lighting fixtures are not wired together. For instance, the lighting panel **102** may store and utilize a unique address to control the behavior of each lighting fixture. Further, the lighting panel **102** may store a database relating the particular behavior of each of the electrical loads in a space for a variety of control inputs. The lighting panel **102** may use the database to determine the relationships and commands for each power supply and control module (e.g., for zoning, daylight harvesting, etc.), and the lighting panel **102** may create the database during the commissioning process.

(41) The lighting panel **102** may perform commissioning in such a manner as to reduce the time and labor typically required to associate multiple electrical loads with one or more controls. For example, the electrical loads (e.g., the LED light fixtures **150**) may include a radio beacon (not shown), such as a Bluetooth beacon. Each radio beacon may include a radio transmitter and ultimately provides addressability for an electrical load. In addition, the accessory modules **152**, **154** may be configured to transmit a beacon signal. The radio beacon in the electrical load may broadcast a unique identifier of the radio beacon (e.g., serial number) via radio signals that may be received by the mobile device **180**. The electrical loads may include a wired or wireless connection back to the lighting panel **102**, for example, to a control module (e.g., the driver module **114**), communication module **122**, and/or communication circuit **106**. The lighting panel **102** may create a database relating to how to group electrical loads based on the received signal strength of the broadcast signal (e.g., and in turn, the proximity of the radio beacon to the mobile device **180**). The database may be created during the commissioning process and used to determine the behavior for a plurality of loads in a particular space. To create the database, the mobile device **180** may receive and determine a signal strength and unique identifier of a radio beacon. Using the receiving signal strength, the mobile device **180** may group or associated one or more electrical loads together for commissioning purposes in the database. After the association of electrical load and radio beacon is established and stored in the database of the lighting panel **102**, the lighting panel **102** may control a group of electrical loads together based on the identification information of each electrical load and/or associated control function, for example, via a wireless or a wired communication channel between lighting panel **102** and the electrical load. Examples of systems that perform commissioning and example commissioning procedures are described in greater detail in commonly-assigned U.S. Provisional Patent Application No. 62/279,409, filed Jan. 15, 2016, and U.S. Provisional Patent Application No. 62/326,466, filed Apr. 22, 2016, both entitled COMMISSIONING LOAD CONTROL SYSTEMS, the entire disclosures of which are hereby incorporated by reference.

(42) The lighting panel **102** may include additional power supplies (e.g., N+1 power supplies) of a

particular type, such as the AC/DC power supplies **108**, the AC/DC power converters **110**, and/or the AC/DC power converters **112**. Further, the lighting panel **102** may include additional control modules (e.g., N+1 control modules) of a particular type, such as the driver modules **114**, the isolated low voltage converters **116**, or the fault detect and branch circuits **118**. In such instances, the panel control circuit **104** of the lighting panel **102** may be configured to switch-in (e.g., automatically switch-in) a power supply or control module if a power supply or control module were to fail. For example, the panel control circuit **104** may be configured to detect that a power supply or control module has failed or was in danger of failing, and upon such a determination, the panel control circuit **104** may reroute the circuit through an additional power supply or control module so the failure does not cause an interruption of power (e.g., an extended disruption of power) to the electrical load. As such, the electrical load(s) receiving power from the failed power supply or control module would not lose power for an extended period or not lose power at all, depending on the detection time and/or the switch-in time for the additional power supply or control module. Further, the panel control circuit **104** may be configured to provide a notification, for example, to a system administrator, if a power supply or control module were to fail. Accordingly, the system administrator may replace the failed power supply or control module within the lighting panel **102** without having to take any electrical loads offline.

(43) FIG. 2 is a simplified block diagram of a system **200** including an example power supply **208** and an example control module **214** of the load control system of FIG. 1. The power supply **208** is an example of the power supply **108**, and the control module **214** is an example of the driver module **114**. Also illustrated in the system **200** is the panel control circuit **104** of the lighting panel **102** and power supply **107** of the lighting panel **102**, but the specific configuration of these components with respect to the power supply **208** and control module **214** is an example configuration. Further, it should be noted that the power supply **208** may also include memory and a communication circuit, and/or the power supply **208** may include a dedicated internal power supply instead of using the power supply of the lighting panel **107**.

(44) The power supply **208** and the control module **214** may be configured to control the amount of power delivered to an electrical load, such as, the LED light engine **150**, and thus the intensity of the electrical load. The LED light engine **150** is shown as a plurality of LEDs connected in series but may comprise a single LED or a plurality of LEDs connected in parallel or a suitable combination thereof, depending on the particular lighting system. The power supply **208** may comprise a first input terminal **212** (e.g., a hot terminal) and a second input terminal **216** (e.g., a neutral terminal) that are adapted to be coupled to a power source (not shown), e.g., via the AC line feed **132**, the DC line feed **134**, and/or the battery bank feed **133**. The first and second input terminals **212**, **216** may be configured to receive an input voltage $V_{sub.IN}$, e.g., an AC mains input voltage or a DC input voltage. The power supply **208** also includes a power supply control circuit **244**, however in some examples, the power supply control circuit **244** may be omitted and, for example, the power supply **208** may be controlled entirely by the panel control circuit **104** of the lighting panel **102**.

(45) The power supply **208** may comprise a radio-frequency (RFI) filter circuit **204**, a rectifier circuit **206**, a boost converter **202**, and/or a ripple detect circuit **218**. The RFI filter circuit **204** may minimize the noise provided on the AC mains. The rectifier circuit **204** may be a dynamic rectifier circuit configured to change its operation in response to whether an AC voltage or a DC voltage is present at the input terminals **212**, **216**. The rectifier circuit **206** may be configured to rectify the input voltage $V_{sub.IN}$ to generate a rectified voltage $V_{sub.RECT}$ when the input terminals are connected to an AC power source and an AC voltage is present at the input terminals **212**, **216**. The rectifier circuit **206** may be configured to pass through the input voltage $V_{sub.IN}$ (e.g., not rectify the input voltage $V_{sub.IN}$) when the input terminals are connected to a DC power source and a DC voltage is present at the input terminals **212**, **216** of the power supply **208**.

(46) The boost converter **202** may receive the rectified voltage $V_{sub.RECT}$ and generate a boosted

DC bus voltage V.sub.BUS across a bus capacitor C.sub.BUS (e.g., an electrolytic capacitor). The boost converter **202** may comprise any suitable power converter circuit for generating an appropriate bus voltage, such as, for example, a flyback converter, a single-ended primary-inductor converter (SEPIC), a Ćuk converter, or other suitable power converter circuit. The boost converter **202** may operate as a PFC circuit to adjust the power factor of the power supply **208** towards a power factor of one. The power supply **208** may comprise an input capacitor C.sub.IN (e.g., a film capacitor) coupled across the input of the boost converter **202**. Examples of boost converters are described in greater detail in commonly-assigned U.S. Pat. No. 8,492,987, issued Jul. 23, 2013, and U.S. Pat. No. 8,680,787, issued Mar. 25, 2014, both entitled LOAD CONTROL DEVICE FOR A LIGHT-EMITTING DIODE LIGHT SOURCE, the entire disclosures of which are hereby incorporated by reference.

(47) The control module **214** may comprise a load regulation circuit **230** and/or a current sense circuit **240**. The load regulation circuit **230** may receive the bus voltage V.sub.BUS and control the amount of power delivered to the LED light engine **150**, for example, to control the intensity of the LED light engine **150**. An example of the load regulation circuit **230** may be an isolated, half-bridge forward converter. An example of a forward converter is described in greater detail in commonly-assigned U.S. Pat. No. 9,253,829, issued Feb. 2, 2015, entitled LOAD CONTROL DEVICE FOR A LIGHT-EMITTING DIODE LIGHT SOURCE, the entire disclosure of which is hereby incorporated by reference. The load regulation circuit **230** may comprise, for example, a buck converter, a linear regulator, or any suitable LED drive circuit for adjusting the intensity of the LED light engine **150**.

(48) The power supply control circuit **244** may be configured to control the operation of the boost converter **202** of the power supply **208**. For example, the power supply control circuit **244** may generate a bus voltage control signal V.sub.BUS-CNTL, which may be provided to the boost converter **202** for adjusting the magnitude of the bus voltage V.sub.BUS towards a target bus voltage V.sub.BUS-TARGET. The power supply control circuit **244** may receive a bus voltage feedback control signal V.sub.BUS-FB from the boost converter **202**, which may indicate the magnitude of the bus voltage V.sub.BUS.

(49) The control module **214** may comprise a module control circuit **254**, which may generate drive control signals V.sub.DR1, V.sub.DR2. The drive control signals V.sub.DR1, V.sub.DR2 may be provided to the load regulation circuit **230** of the control module **214** for adjusting the magnitude of a load voltage V.sub.LOAD generated across the LED light engine **150** and the magnitude of a load current I.sub.LOAD conducted through the LED light engine **150**, for example, to control the intensity of the LED light engine **150** to a target intensity L.sub.TRGT. The module control circuit **254** may adjust an operating frequency f.sub.OP and/or a duty cycle D.sub.CINV (e.g., an on time T.sub.ON) of the drive control signals V.sub.DR1, V.sub.DR2 to adjust the magnitude of the load voltage V.sub.LOAD and/or the load current I.sub.LOAD. The module control circuit **254** may receive a load voltage feedback signal V.sub.V-LOAD generated by the load regulation circuit **230**. The load voltage feedback signal V.sub.V-LOAD may indicate the magnitude of the load voltage V.sub.LOAD. The power supply control circuit **244** of the power supply **208** may operate independently of the module control circuit **254** of the control module **214**. In addition, the power supply control circuit **244** may be configured to communicate with the module control circuit **254** to allow the power supply control circuit **244** and the module control circuit **254** to work together to control the operation of the system **200**.

(50) The current sense circuit **240** of the control module **214** may receive a sense voltage V.sub.SENSE generated by the load regulation circuit **230**. The sense voltage V.sub.SENSE may indicate the magnitude of the load current I.sub.LOAD. The current sense circuit **240** may receive a signal-chopper control signal V.sub.CHOP from the module control circuit **254**. The current sense circuit **240** may generate a load current feedback signal V.sub.I-LOAD, which may be a DC voltage indicating the average magnitude I.sub.AVE of the load current I.sub.LOAD. The module

control circuit **254** may receive the load current feedback signal V.sub.I-LOAD from the current sense circuit **240** and control the drive control signals V.sub.DR1, V.sub.DR2 accordingly. For example, the module control circuit **254** may control the drive control signals V.sub.DR1, V.sub.DR2 to adjust a magnitude of the load current I.sub.LOAD to a target load current I.sub.TRGT to thus control the intensity of the LED light engine **150** to the target intensity L.sub.TRGT (e.g., using a control loop). The module control circuit **254** may be configured to determine a load power P.sub.LOAD presently being consumed by the LED light engine **150** using the load voltage feedback signal V.sub.V-LOAD and the load current feedback signal V.sub.I-LOAD. The load current I.sub.LOAD may be the current that is conducted through the LED light engine **150**. The target load current I.sub.TRGT may be the current that the module control circuit **254** would ideally like to conduct through the LED light engine **150** (e.g., based at least on the load current feedback signal V.sub.I-LOAD).

(51) The power supply **208** may also comprise a ripple detect circuit **218**, which may receive the rectified voltage V.sub.RECT and may generate a ripple detect signal V.sub.RIP-DET that may indicate whether AC ripple is present or not on the rectified voltage V.sub.RECT (e.g., whether an AC voltage or a DC voltage, respectively is coupled to the input terminals **212**, **216**). The power supply control circuit **244** may receive the ripple detect signal V.sub.RIP-DET and may operate in an AC mode if an AC voltage is coupled to the input terminals **212**, **216** or a DC mode if a DC voltage is coupled to the input terminals **212**, **216**. The ripple detect circuit **218** may also be coupled to receive the input voltage V.sub.IN and/or the bus voltage V.sub.BUS.

(52) The power supply **208** may also comprise a controllable switching circuit **218** (e.g., including a MOSFET) electrically coupled in series with the bus capacitor C.sub.BUS for disconnecting the bus capacitor. When operating in the AC mode, the power supply control circuit **244** may enable the operation of the boost converter **202** of the power supply **208** to generate the bus voltage V.sub.BUS across the bus capacitor C.sub.BUS. The power supply control circuit **244** may render the controllable switching circuit **218** conductive and may control the magnitude of the bus voltage V.sub.BUS to a maximum magnitude V.sub.BUS-MAX (e.g., approximately 465 volts). The power supply control circuit **244** may also operate the boost converter **202** as a PFC circuit during the AC mode to adjust the power factor of the power supply **208** towards a power factor of one.

(53) When operating in the DC mode, the power supply control circuit **244** may be configured to disable the operation of the boost converter **202** to reduce the power loss in the power supply **208** due to the power loss in the boost converter when enabled. When disabled, the boost converter **202** may pass through the DC voltage from the input terminals **212**, **216** and the bus voltage V.sub.BUS may have a minimum magnitude V.sub.BUS-MIN (e.g., approximately 380 volts). When operating in the DC mode, the power supply control circuit **244** may be configured to enable the boost converter **202** during a startup routine of the power supply **208** and disable the boost converter **202** during normal operation. Further, the power supply control circuit **244** may render the controllable switching circuit **218** conductive to disconnect the bus capacitor C.sub.BUS in the DC mode since the bus capacitor may not be required when the DC voltage is present at the input terminals. Rather than disabling the boost converter **202** in the DC mode, the power supply control circuit **244** may also scale back the operation of the boost converter (e.g., reduce the target bus voltage V.sub.BUS-TARGET) in order to reduce the losses in the boost converter **202**.

(54) The control module **214** may also comprise a capacitor C.sub.FILM (e.g., a film capacitor) coupled across the input of the load regulation circuit **230** for supplying high-frequency current that may be required to circulate through the load regulation circuit. Since the bus capacitor C.sub.BUS may comprise one or more electrolytic capacitors, disconnecting the bus capacitor C.sub.BUS of the power supply **208** may increase the lifetime of the LED driver **100**. In addition, disconnecting the bus capacitor C.sub.BUS may reduce an inrush current conducted by the power supply **208** when power is applied to the input terminals **212**, **216**.

(55) The power supply control circuit **244** may also enable the operation of the boost converter **202**

in the DC mode when the power $P_{\text{sub.LOAD}}$ required by LED light engine **150** exceeds a threshold amount $P_{\text{sub.TH}}$ (e.g., approximately 80%). In addition, the power supply control circuit **244** may also be configured to control the target bus voltage $V_{\text{sub.BUS-TARGET}}$ as a function of the power $P_{\text{sub.LOAD}}$ required by LED light engine **150** (e.g., if the power supply control circuit **244** is configured to communicate with the module control circuit **245** to determine the power $P_{\text{sub.LOAD}}$ required by LED light engine **150**). The power supply control circuit **244** may be configured to adjust the target bus voltage $V_{\text{sub.BUS-TARGET}}$ linearly between the minimum magnitude $V_{\text{sub.BUS-MIN}}$ and the maximum magnitude $V_{\text{sub.BUS-MAX}}$ when the power $P_{\text{sub.LOAD}}$ required by LED light engine **150** is above the threshold amount $P_{\text{sub.TH}}$. The power supply control circuit **244** may be configured to control the target bus voltage $V_{\text{sub.BUS-TARGET}}$ using open loop control, for example, by using a lookup table to determine the target bus voltage $V_{\text{sub.BUS-TARGET}}$ in response to the target intensity $L_{\text{sub.TRGT}}$ and/or target load current $I_{\text{sub.TRGT}}$. The power supply control circuit **244** may also be configured to control the target bus voltage $V_{\text{sub.BUS-TARGET}}$ using closed loop control, for example, by using the load voltage feedback signal $V_{\text{sub.V-LOAD}}$ and the load current feedback signal $V_{\text{sub.I-LOAD}}$ to determine the power P required by LED light engine **150**. The power supply control circuit **244** could also be configured to learn the target intensity $L_{\text{sub.TRGT}}$ and/or target load current $I_{\text{sub.TRGT}}$ at which the power $P_{\text{sub.LOAD}}$ required by LED light engine **150** exceeds the threshold amount $P_{\text{sub.TH}}$ (e.g., during a startup routine).

(56) FIG. **3** is a simplified block diagram of an example load regulation circuit (e.g., a forward converter) and current sense circuit of an example control module **314**. The control module **314** may include a forward converter **330** and/or a current sense circuit **340**. The control module **314** may be an example of the control module **214**, the forward converter **330** may be an example of the load regulation circuit **230** of the control module **214**, and the current sense circuit **340** may be an example of the current sense circuit **240** of the control module **214**.

(57) The forward converter **330** may comprise a half-bridge inverter circuit having two field effect transistors (FETs) **Q310**, **Q312** for generating a high-frequency inverter voltage $V_{\text{sub.INV}}$ from the bus voltage $V_{\text{sub.BUS}}$. The FETs **Q310**, **Q312** may be rendered conductive and non-conductive in response to the drive control signals $V_{\text{sub.DR1}}$, $V_{\text{sub.DR2}}$. The drive control signals $V_{\text{sub.DR1}}$, $V_{\text{sub.DR2}}$ may be received from the module control circuit **254**. The drive control signals $V_{\text{sub.DR1}}$, $V_{\text{sub.DR2}}$ may be coupled to the gates of the respective FETs **Q310**, **Q312** via a gate drive circuit **318** (e.g., which may comprise part number L6382DTR, manufactured by ST Microelectronics). The module control circuit **254** may generate the inverter voltage $V_{\text{sub.INV}}$ at a constant operating frequency $f_{\text{sub.OP}}$ (e.g., approximately 60-65 kHz) and thus a constant operating period $T_{\text{sub.OP}}$. However, the operating frequency $f_{\text{sub.OP}}$ may be adjusted under certain operating conditions. For example, the operating frequency $f_{\text{sub.OP}}$ may be decreased near the high-end intensity $L_{\text{sub.HE}}$. The module control circuit **254** may be configured to adjust a duty cycle $DC_{\text{sub.INV}}$ of the inverter voltage $V_{\text{sub.INV}}$ to control the intensity of an LED light engine **150** towards the target intensity $L_{\text{sub.TRGT}}$. The module control circuit **254** may adjust the duty cycle $DC_{\text{sub.INV}}$ of the inverter voltage $V_{\text{sub.INV}}$ to adjust the magnitude (e.g., the average magnitude $I_{\text{sub.AVE}}$) of the load current $I_{\text{sub.LOAD}}$ towards the target load current $I_{\text{sub.TRGT}}$. The magnitude of the load current $I_{\text{sub.LOAD}}$ may vary between a maximum rated current $I_{\text{sub.MAX}}$ and a minimum rated current $I_{\text{sub.MIN}}$.

(58) The inverter voltage $V_{\text{sub.INV}}$ is coupled to the primary winding of a transformer **320** through a DC-blocking capacitor **C316** (e.g., which may have a capacitance of approximately 0.047 μF), such that a primary voltage $V_{\text{sub.PRI}}$ is generated across the primary winding. The transformer **320** may be characterized by a turns ratio $n_{\text{sub.TURNS}}$ (i.e., $N_{\text{sub.1}}/N_{\text{sub.2}}$), which may be approximately 115:29. A sense voltage $V_{\text{sub.SENSE}}$ may be generated across a sense resistor **R322**, which may be coupled in series with the primary winding of the transformer **320**. The FETs **Q310**, **Q312** and the primary winding of the transformer **320** may be characterized by

parasitic capacitances C.sub.P1, C.sub.P2, C.sub.P3, respectively. The secondary winding of the transformer **320** may generate a secondary voltage. The secondary voltage may be coupled to the AC terminals of a full-wave diode rectifier bridge **324** for rectifying the secondary voltage generated across the secondary winding. The positive DC terminal of the rectifier bridge **324** may be coupled to the LED light engine **150** through an output energy-storage inductor L**326** (e.g., which may have an inductance of approximately 10 mH), such that the load voltage V.sub.LOAD may be generated across an output capacitor C**328** (e.g., which may have a capacitance of approximately 3 μ F).

(59) The current sense circuit **340** may comprise an averaging circuit for producing the load current feedback signal V.sub.I-LOAD. The averaging circuit may comprise a low-pass filter comprising a capacitor C**342** (e.g., which may have a capacitance of approximately 0.066 μ F) and a resistor R**332** (e.g., which may have a resistance of approximately 3.32 k Ω). The low-pass filter may receive the sense voltage V.sub.SENSE via a resistor R**334** (e.g., which may have a resistance of approximately 1 k Ω). The current sense circuit **340** may comprise a transistor Q**336** coupled between the junction of the resistors R**332**, R**334** and circuit common. The gate of the transistor Q**336** may be coupled to circuit common through a resistor R**338** (e.g., which may have a resistance of approximately 22 k Ω). The gate of the transistor Q**336** may receive the signal-chopper control signal V.sub.CHOP from the module control circuit **254**. An example of the current sense circuit **340** may be described in greater detail in commonly-assigned U.S. patent application Ser. No. 13/834,153, filed Mar. 15, 2013, entitled FORWARD CONVERTER HAVING A PRIMARY-SIDE CURRENT SENSE CIRCUIT, the entire disclosure of which is hereby incorporated by reference.

(60) FIG. **4** is an example of a timing diagram of a DC voltage V.sub.DC generated by a control module of a lighting panel (e.g., the lighting panel **102**) for provide power and communicating digital messages to an electrical load. The timing diagram **400** illustrates an example data pattern of a transmitted digital message carried via the DC voltage V.sub.DC. The DC voltage V.sub.DC and the data pattern may be generated by a control module (e.g., the driver module **114**) of the lighting panel **102**. For example, the driver module **114** may be configured to pulse-width modulate (PWM) the DC voltage V.sub.DC to introduce a reference edge and a data edge into the DC voltage V.sub.DC. The time period between successive reference edges may be consistent and may define a communication time period. The communication time period may be static or adjustable based on the electrical load. Digital information (e.g., bits of the transmitted digital messages) may be encoded in the PWM duty cycle of the DC voltage V.sub.DC. For example, the bits of the transmitted digital messages may be encoded in the firing time of a data edge (e.g., a data edge time) of the driver module **114** as measured with respect to a firing time of a reference edge (e.g., a reference edge time). In other words, the bits of the transmitted digital messages may be encoded as a function of the firing times of the reference and data edges.

(61) The value of the digital data transmitted by the control module may be dependent upon an offset time period T.sub.OS (i.e., a difference) between the data edge and the previous reference edge. The control module may control the data edges to be at one of four times across the time window T.sub.WIN, thus resulting in one of four offset time periods T.sub.OS1, T.sub.OS2, T.sub.OS3, T.sub.OS4, from the previous reference edge, such that two bits may be transmitted each communication time period. To transmit bits "00", the control module may be configured operable to pulse width modulate the DC voltage V.sub.DC at the first possible data edge time, such that the first offset time period T.sub.OS1 exists between the reference edge and the data edge. For example, each of the possible data edge times may be an offset period difference Δ T.sub.OS apart. The control module may be configured to control the offset time period T.sub.OS between the reference edge and the data edge to the second offset time period T.sub.OS2 to transmit bits "01", to the third offset time period T.sub.OS3 to transmit bits "10", and the fourth offset time period T.sub.OS4 to transmit bits "11", for example, as shown in FIG. **4**.

(62) To decode the data, a control circuit (e.g., microprocessor) of each electrical load (e.g., LED light engine **150**, accessory module, etc.) may determine if the offset time period $T_{sub.OS}$ of each data pattern is approximately equal to one of the four offset time periods $T_{sub.OS1}$, $T_{sub.OS2}$, $T_{sub.OS3}$, $T_{sub.OS4}$ within a default tolerance $\Delta T_{sub.OS}$, which may be equal to, for example, approximately fifty microseconds. Alternatively, the number of data edges possible in the time window $T_{sub.WIN}$ could be greater than four (e.g., eight) in order to transmit more than two bits of data during each communication time period. The control modules of the lighting panel **102** may be configured to set the communication time period and number of data edges possible in each time window $T_{sub.WIN}$ such that, for example, the electrical load is operable across its entire range when receiving just a portion of the full DC voltage $V_{sub.DC}$ (e.g., the communication time period minus the entire time window).

(63) When the control module is not transmitting a digital message to the electrical load, the control module may provide a fully conductive DC voltage $V_{sub.DC}$. Accordingly, the DC voltage $V_{sub.DC}$ would not have at least one reference edge in each communication cycle when the control module is not transmitting a digital message to the electrical load. Alternatively, the control module may pulse width modulate the DC voltage $V_{sub.DC}$ at the first data edge (e.g., at $T_{sub.OS1}$), as if the control module was continuously transmitting bits “00.” Further, an accessory module may be configured to respond to the control module in a similar fashion. For example, a response time window $T_{sub.RWIN}$ may be used where, for example, the offset time period $T_{sub.OS}$ between a reference edge and a data edge in the response time window $T_{sub.RWIN}$ is used to determine the response communication performed by the accessory module. The response time window $T_{sub.RWIN}$ may be smaller in duration than the time window $T_{sub.WIN}$, for example, since less information may need to be transmitted from the accessory module to the control module in the lighting panel **102**. Alternatively, every other time window $T_{sub.WIN}$ may be used as the response time window $T_{sub.RWIN}$.

(64) The system utilizing the methods shown in FIG. 4 allows for reuse of existing building wiring to accommodate new lighting fixtures as only two wires are required between the lighting panel and lighting fixtures. For example, this legacy configuration of wiring may exist between traditional dimming panels and the traditional lighting loads, such as incandescent bulbs. As no new wires are required between the lighting panel location and the fixture location, this new system provides an opportunity for system upgrades without pulling new wires.

(65) FIG. 5 is an example flowchart of a power supply classification detection procedure **500** performed by an electrical panel, such as the lighting panel **102**. The electrical panel may detect (e.g., automatically detect) the rated class type of one or more power supplies of the electrical panel. For example, the rated class types may include, but are not limited to, Low Voltage Class 2, Low Voltage Class 1, and High Voltage Class 1. Although the detection procedure **500** is described with reference to the Low Voltage Class 2, the Low Voltage Class 1, and the High Voltage Class 1 class types, the detection procedure **500** may detect any combination or type of rated class types of power supplies. Further, it should be appreciated that a panel control circuit (e.g., the panel control circuit **104**) and/or one or more of the power supplies themselves may perform the detection procedure **500**.

(66) The electrical panel may set $N=0$ at **510**, where $N_{sub.MAX}$ is the total number of power supplies of the electrical panel (e.g., the total number of adjustable/configurable power supplies of the electrical panel). At **520**, the electrical panel may determine the rated class of the power supply N . The electrical panel may determine the rated class of the power supply, for example, based on the control modules and/or electrical loads that are connected to the power supply, and in turn, the desired operational characteristics of the power supply. For example, the power supply and/or the panel control circuit may be configured to measure the amount of current, voltage, and/or power requested on the link, e.g., at the output terminals of the power supply, to determine its desired class type. Alternatively or additionally, a control module and/or electrical load (e.g., an accessory

module located at the electrical load) may communicate (e.g., by transmitting a digital or analog message) to the power supply and/or panel control circuit indicating its power requirements, such as an amount of power needed, type of dimming required, etc.

(67) After determining the rated class of the power supply **N** at **520**, the electrical panel may configure the power supply **N** to operate according to the rated class at **530**. For example, the electrical panel may configure the power supply to control (e.g., limit) its output power accordingly (e.g., operate as a Low Voltage Class 2 power supply, a Low Voltage Class 1 power supply, a High Voltage Class 1 power supply, etc.). At **540**, the electrical panel may send a notification (e.g., an alert and/or report) of the rated class type of the power supply **N**. For example, the panel control circuit may send a notification of the rated class type of the power supply **N** to a network or system administration (e.g., via the gateway device **138**). Further, in instances where the detection procedure **500** is performed by the power supplies themselves, the power supply **N** may send a notification to the panel control circuit at **540** indicating its rated class type. Further, in instances where the detection procedure **500** is performed by the power supplies themselves, **510**, **550**, and **560** of the detection procedure **500** may be omitted.

(68) At **550**, the electrical panel may determine whether the $N = N_{\text{sub.MAX}}$. If the electrical panel determines that **N** is less than $N_{\text{sub.MAX}}$, then the electrical panel may increment **N** by 1 at **560**, and repeat **520-540** for a subsequent power supply. If the electrical panel determines that $N = N_{\text{sub.MAX}}$ at **550**, then the detection procedure **500** may exit. The electrical panel may perform the detection procedure **500** at start-up and/or periodically throughout operation. For example, the electrical panel may be configured to adjust the class type of a power supply after installation. For instance, the a particular power supply may be initially configured to operate as a Class 1 power supply (e.g., a High Voltage Class 1 power supply), and later be configured (e.g., by the panel control circuit **104**) to operate as another class of power supply (e.g., as a Low Voltage Class 2 power supply provided that the proper redundancy exists).

(69) As noted herein, an electrical panel, such as the lighting panel **102**, may be connected to one or more DC power sources via the DC line feed **134** and/or via the battery bank feed **133**. The DC power sources may include any combination of an alternative energy sources, such as a PV power supply, a wind turbine system, a hydroelectric system, a battery bank, etc. The electrical panel may include a grid-tie inverter (e.g., or, for example, the grid-tie inverter may be connected to the electrical panel but external to the electrical panel). The grid-tie inverter may be electrically connected between the DC line feed (e.g., and/or the battery bank feed) and the AC line feed **132**. The grid-tie inverter may be configured to receive DC power via the DC line feed, convert the DC power to AC power, and provide the AC power to the AC line feed (e.g., and ultimately to an external electrical grid). The electrical panel may sell a portion or all of the DC power received from one or more DC power sources back to the electrical grid, for example, after using a portion of the DC power for powering one or more electrical loads. The amount or percentage of DC power sold back to the electrical grid may be determined by the electrical panel using a grid-tie inverter control procedure.

(70) FIG. **6** is an example of a grid-tie inverter control procedure **600** performed by an electrical panel, such as the lighting panel **102**. The electrical panel (e.g., the panel control circuit **104**) may perform the grid-tie inverter control procedure **600** continuously or periodically, for example, at scheduled times of the day, whenever an electrical load is adjusted (e.g., turned on or off), and/or in response to an input from a system administrator. At **610**, the electrical panel may determine (e.g., measure) the amount of DC input power $P_{\text{sub.DC-IN}}$ that is received via the DC line feed **134** and/or via the battery bank feed **133** from the one or more DC power sources. At **620**, the electrical panel may determine the amount of power $P_{\text{sub.EL}}$ requested by the electrical loads of the electrical panel (e.g., the power supplies). The power requested by the electrical loads $P_{\text{sub.EL}}$ may vary continuously, for example, in response to other inputs into the load control system (e.g., the load control system **100**), such as via remote control devices, occupancy/vacancy sensors,

daylight sensors, etc.

(71) The electrical panel may then determine how much DC input power $P_{sub.DC-IN}$ to use versus to sell back to the electrical grid based on one or more factors. These factors may include, but are not limited to, the amount of DC input power $P_{sub.DC-IN}$, the amount of power $P_{sub.EL}$ requested by the electrical loads of the electrical panel, environmental conditions, such as weather, whether the electrical panel is receiving AC input power $P_{sub.AC}$ (e.g., whether there is an outage), a price index of AC input power $P_{sub.AC}$, the time of day, the day of the week, the month of the year, the location of the electrical panel, etc. For example, at **630** of the grid-tie inverter control procedure **600**, the electrical panel may determine the factors that are associated with the sale of AC power to the electrical grid. The factors may be static or may adjust, for example, based on settings received from a system administrator. The factors may also be weighted.

(72) At **640**, the electrical panel may determine to adjust (e.g., lower) the power $P_{sub.EL}$ provided to one or more electrical loads (e.g., dim one or more LED light engines **150**) based on the determined factors. The electrical panel may determine to lower the power $P_{sub.EL}$ provided to the electrical loads within a window of acceptance. For example, the electrical panel may determine to lower the power $P_{sub.EL}$ such that the electrical panel limits the amount of received AC input power $P_{sub.AC}$ (e.g., potentially doesn't receive any AC power). The electrical panel may determine to lower the power $P_{sub.EL}$, for example, in instances where the price index of AC input power $P_{sub.AC}$ exceeds a threshold, on particular days of the week and/or times of the day, where there is an outage and the electrical panel isn't receiving any AC input power $P_{sub.AC}$, and/or the like.

(73) At **650**, the electrical panel may determine whether to sell any DC input power $P_{sub.DC-IN}$ to back to the electrical grid. For example, if the electrical panel determines that the amount of power $P_{sub.EL}$ (e.g., the adjust $P_{sub.EL}$) is less than the amount of DC input power $P_{sub.DC-IN}$, then the electrical panel may sell any excess DC input power $P_{sub.DC-IN}$ back to the grid at **660**.

(74) If, for example, the electrical panel determines that the amount of power $P_{sub.EL}$ (e.g., the adjust $P_{sub.EL}$) is equal to or exceeds the amount of DC input power $P_{sub.DC-IN}$, then, at **670**, the electrical panel may determine to use all of the DC input power $P_{sub.DC-IN}$ to meet the request of the loads and, to the extent necessary, also use AC input power $P_{sub.AC}$. By using all of the DC input power $P_{sub.DC-IN}$, the electrical panel may avoid a double conversion (e.g., converting DC input power $P_{sub.DC-IN}$ to AC for sale, and converting AC input power $P_{sub.AC}$ to DC for use by the electrical loads). Further, even if the electrical panel determines that the amount of power $P_{sub.EL}$ (e.g., the adjust $P_{sub.EL}$) is equal to or exceeds the amount of DC input power $P_{sub.DC-IN}$, the electrical panel may still determine, based on the determined factors, to store all or a portion of the DC input power $P_{sub.DC-IN}$ in the battery banks via the battery bank feed **133**.

(75) Although described with reference to the LED light engines **150** and the motorized window treatments **160**, one or more embodiments described herein may be used with other electrical loads and load control devices. For example, one or more of the embodiments described herein may be performed by a variety of load control devices that are configured to control a variety of electrical load types, such as, for example, a screw-in luminaire including a dimmer circuit and an incandescent or halogen lamp; a screw-in luminaire including a ballast and a compact fluorescent lamp; a screw-in luminaire including an LED driver and an LED light source; a dimming circuit for controlling the intensity of an incandescent lamp, a halogen lamp, an electronic low-voltage lighting load, a magnetic low-voltage lighting load, or another type of lighting load; an electronic switch, controllable circuit breaker, or other switching device for turning electrical loads or appliances on and off; a plug-in load control device, controllable electrical receptacle, or controllable power strip for controlling one or more plug-in electrical loads (e.g., coffee pots, space heaters, other home appliances, and the like); a motor control unit for controlling a motor load (e.g., a ceiling fan or an exhaust fan); a drive unit for controlling a motorized window treatment or

a projection screen; motorized interior or exterior shutters; a thermostat for a heating and/or cooling system; a temperature control device for controlling a heating, ventilation, and air conditioning (HVAC) system; an air conditioner; a compressor; an electric baseboard heater controller; a controllable damper; a humidity control unit; a dehumidifier; a water heater; a pool pump; a refrigerator; a freezer; a television or computer monitor; a power supply; an audio system or amplifier; a generator; an electric charger, such as an electric vehicle charger; and an alternative energy controller (e.g., a solar, wind, or thermal energy controller). A lighting panel **102** may be coupled to and/or adapted to control multiple types of electrical loads in a load control system.

Claims

1. An electrical distribution panel controller, comprising: distribution panel control circuitry operatively coupled to an alternating current (AC) line feed to the electric distribution panel and operatively coupled to a direct current (DC) line feed to the electric distribution panel, the distribution panel control circuitry to: detect an interruption of the AC line feed to the electric distribution panel; and responsive to detection of the interruption of the AC line feed to the electric distribution panel, cause bridge inverter circuitry operatively coupled between the DC line feed and the AC line feed to transfer power from the DC line feed to the AC line feed.
2. The electrical distribution panel controller of claim 1 wherein the distribution panel control circuitry to further, responsive to detection of the interruption of the AC line feed to the electric distribution panel: identify emergency electric load devices operatively coupled to the AC line feed; and maintain AC line feed power to the identified emergency electric load devices.
3. The electrical distribution panel controller of claim 2, further comprising: memory circuitry operatively coupled to the distribution panel control circuitry; wherein to identify emergency electric load devices operatively coupled to the AC line feed, the distribution panel control circuitry to further: retrieve, from the memory circuitry, data representative of the emergency electric load devices.
4. The electrical distribution panel controller of claim 1, further comprising: communication interface circuitry operatively coupled to the distribution panel control circuitry; wherein the distribution panel control circuitry to further: transmit a signal that includes information indicative of the interruption of the AC line feed, responsive to detection of the interruption of the AC line feed.
5. The electrical distribution panel controller of claim 1 wherein the distribution panel control circuitry to further: receive at least one parameter from each of a plurality of DC power supplies disposed in the electrical distribution panel; for each of the plurality of DC power supplies: determine whether the at least one parameter falls outside an allowable range; and responsive to the determination that the at least one parameter falls outside an allowable range, cause a switchover to a different DC power supply disposed in the electrical distribution panel.
6. The electrical distribution panel controller of claim 1 wherein the distribution panel control circuitry to further: monitor DC line feed supply to the electrical distribution panel; monitor DC demand in the electrical distribution panel; and convert excess DC line feed supply to AC line feed via the bridge inverter circuitry.
7. An electrical distribution panel control method, comprising: detecting, by distribution panel control circuitry an interruption of the AC line feed to the electric distribution panel; wherein the distribution panel control circuitry operatively couples to an alternating current (AC) line feed to the electric distribution panel and operatively couples to a direct current (DC) line feed to the electric distribution panel; and causing, by the distribution panel control circuitry, bridge inverter circuitry operatively coupled between the DC line feed and the AC line feed to transfer power from the DC line feed to the AC line feed responsive to detection of the interruption of the AC line feed to the electric distribution panel.

8. The method of claim 7, further comprising: wherein the distribution panel control circuitry to further responsive to detection of the interruption of the AC line feed to the electric distribution panel: identifying, by the distribution panel control circuitry, one or more emergency electric load devices operatively coupled to the AC line feed; and maintaining, by the distribution panel control circuitry, AC line feed power to the identified one or more emergency electric load devices.
9. The method of claim 8 wherein identifying the one or more emergency electric load devices operatively coupled to the AC line feed further comprises: retrieving, by the distribution panel control circuitry, from operatively coupled memory circuitry, data representative of the emergency electric load devices.
10. The method of claim 7, further comprising: causing, by the distribution panel control circuitry, operatively coupled communication interface circuitry to transmit a signal that includes information indicative of the interruption of the AC line feed, responsive to detection of the interruption of the AC line feed.
11. The method of claim 7, further comprising: receiving, by the distribution panel control circuitry, at least one parameter from each of a plurality of DC power supplies disposed in the electrical distribution panel; and for each of the plurality of DC power supplies: determining, by the distribution panel control circuitry, whether the at least one parameter falls outside an allowable range; and causing, by the distribution panel control circuitry, a switchover to a different DC power supply disposed in the electrical distribution panel responsive to the determination that the at least one parameter falls outside an allowable range.
12. The method of claim 7, further comprising: receiving, by the distribution panel control circuitry, a first input indicative of the DC line feed supply to the electrical distribution panel; receiving, by the distribution panel control circuitry, a second input indicative of the DC demand in the electrical distribution panel; and converting, by the distribution panel control circuitry, excess DC line feed supply to AC line feed via the bridge inverter circuitry.
13. A non-transitory, machine-readable, storage device that includes instructions that, when executed by distribution panel control circuitry, causes the distribution panel control circuitry to: detect an interruption of the AC line feed to the electric distribution panel; wherein the distribution panel control circuitry operatively couples to an alternating current (AC) line feed to the electric distribution panel and operatively couples to a direct current (DC) line feed to the electric distribution panel; and cause bridge inverter circuitry operatively coupled between the DC line feed and the AC line feed to transfer power from the DC line feed to the AC line feed responsive to detection of the interruption of the AC line feed to the electric distribution panel.
14. The non-transitory, machine-readable, storage device of claim 13 wherein the instructions, when executed by the distribution panel control circuitry, further cause the distribution panel control circuitry to: responsive to detection of the interruption of the AC line feed to the electric distribution panel: identify one or more emergency electric load devices operatively coupled to the AC line feed; and maintain AC line feed power to the identified one or more emergency electric load devices.
15. The non-transitory, machine-readable, storage device of claim 14 wherein the instructions that cause the distribution panel control circuitry to identify the one or more emergency electric load devices operatively coupled to the AC line feed further cause the distribution panel control circuitry: retrieve from operatively coupled memory circuitry, data representative of the emergency electric load devices.
16. The non-transitory, machine-readable, storage device of claim 13 wherein the instructions, when executed by the distribution panel control circuitry, further cause the distribution panel control circuitry to: cause operatively coupled communication interface circuitry to transmit a signal that includes information indicative of the interruption of the AC line feed, responsive to detection of the interruption of the AC line feed.
17. The non-transitory, machine-readable, storage device of claim 13 wherein the instructions,

when executed by the distribution panel control circuitry, further cause the distribution panel control circuitry to: receive at least one parameter from each of a plurality of DC power supplies disposed in the electrical distribution panel; and for each of the plurality of DC power supplies: determine whether the at least one parameter falls outside an allowable range; and cause a switchover to a different DC power supply disposed in the electrical distribution panel responsive to the determination that the at least one parameter falls outside an allowable range.

18. The non-transitory, machine-readable, storage device of claim 13 wherein the instructions, when executed by the distribution panel control circuitry, further cause the distribution panel control circuitry to: receive a first input indicative of the DC line feed supply to the electrical distribution panel; receive a second input indicative of the DC demand in the electrical distribution panel; and convert excess DC line feed supply to AC line feed via the bridge inverter circuitry.
