

US Patent & Trademark Office

Patent Public Search | Text View

United States Patent	12399060
Kind Code	B2
Date of Patent	August 26, 2025
Inventor(s)	Ito; Kaoru et al.

Detection device with light directivity

Abstract

A detection device includes: a planar detection device including photodetection elements; point light sources provided correspondingly to the photodetection elements; a light directivity control element disposed between the point light sources and the photodetection elements; and a detection circuit electrically coupled to the photodetection elements. Each point light source corresponds to at least one of the photodetection elements. In a light amount setting mode, the point light sources are lit up at different light amounts; the photodetection elements output sensor values corresponding to the different light amounts; the sensor values that are detected are compared with a preset target sensor value; and light amounts for detection of the point light sources are set. In a detection mode, the point light sources are lit up at the set light amounts for detection; and the photodetection elements output sensor values corresponding to the light amounts for detection.

Inventors: Ito; Kaoru (Tokyo, JP), Fujisawa; Akihiko (Tokyo, JP), Abe; Daichi (Tokyo, JP)

Applicant: Magnolia White Corporation (Tokyo, JP)

Family ID: 1000008781967

Assignee: Magnolia White Corporation (Tokyo, JP)

Appl. No.: 18/603479

Filed: March 13, 2024

Prior Publication Data

Document Identifier	Publication Date
US 20240328855 A1	Oct. 03, 2024

Foreign Application Priority Data

JP	2023-049613	Mar. 27, 2023
----	-------------	---------------

Publication Classification

Int. Cl.: G01J1/44 (20060101); G01J1/08 (20060101); G01N15/0205 (20240101); G01N15/14 (20060101); G01N15/1434 (20240101)

U.S. Cl.:

CPC G01J1/44 (20130101); G01J1/08 (20130101); G01J2001/446 (20130101); G01J2001/448 (20130101); G01N15/0205 (20130101); G01N15/1434 (20130101); G01N15/147 (20130101); G01N2201/12746 (20130101)

Field of Classification Search

CPC: G01N (15/1459); G01N (15/0205); G01N (15/1433); G01N (21/6456); G01N (2021/6419); G01N (2021/6421); G01N (15/149); G01N (2015/0294); G01N (2015/1006); G01N (2015/1493); G01N (2015/1497); G01N (15/1429); G01N (15/147); G01N (15/1434); G01N (2021/6482); G01N (2201/12746); G01J (1/44); G01J (1/08); G01J (2001/446); G01J (2001/448)

References Cited

U.S. PATENT DOCUMENTS

Patent No.	Issued Date	Patentee Name	U.S. Cl.	CPC
4559452	12/1984	Igaki	356/637	G07D 7/162
11897750	12/2023	Checchinato	N/A	A47J 31/44
2022/0118136	12/2021	Church	N/A	A61M 1/3681

FOREIGN PATENT DOCUMENTS

Patent No.	Application Date	Country	CPC
H06-261737	12/1993	JP	N/A

Primary Examiner: Bennett; Jennifer D

Attorney, Agent or Firm: K&L Gates LLP

Background/Summary

CROSS-REFERENCE TO RELATED APPLICATION

(1) This application claims the benefit of priority from Japanese Patent Application No. 2023-049613 filed on Mar. 27, 2023, the entire contents of which are incorporated herein by reference.

BACKGROUND

1. Technical Field

(2) What is disclosed herein relates to a detection device.

2. Description of the Related Art

(3) Japanese Patent Application Laid-open Publication No. H06-261737 (JP-A-H06-261737) discloses a biosensor that includes a solid-state imaging device, a culture vessel held above an imaging surface of this solid-state imaging device, cells and a culture medium for growing the cells contained in this culture vessel, and a light-emitting element to emit light into the culture vessel. In

the biosensor of JP-A-H06-261737, the light emitted from the light-emitting element enters the solid-state imaging device through the culture medium and the cells (objects to be detected) in the culture vessel.

(4) In such a detection device, a light source is required to emit light at a light amount depending on characteristics of a detection element. The amount of light applied to the detection element varies depending on the types and conditions (thicknesses, turbidity, and so on) of the objects to be detected, the culture vessel, and the culture medium because the light is applied to the detection element through the objects to be detected, the culture vessel, and the culture medium. As a result, light at an amount different from that within a detection range of the detection element may be emitted, thereby reducing the detection accuracy.

(5) For the foregoing reasons, there is a need for a detection device capable of improving the detection accuracy.

SUMMARY

(6) According to an aspect, a detection device includes: a planar detection device including a plurality of photodetection elements arranged in a planar configuration; a plurality of point light sources provided correspondingly to the photodetection elements; a light directivity control element disposed between the point light sources and the photodetection elements; and a detection circuit electrically coupled to the photodetection elements. Each of the point light sources corresponds to at least one of the photodetection elements. In a light amount setting mode, the point light sources are controlled to be lit up at different light amounts; the photodetection elements are configured to output a plurality of sensor values corresponding to the different light amounts; the sensor values that are detected are compared with a preset target sensor value; and light amounts for detection of the point light sources are set. In a detection mode, the point light sources are controlled to be lit up at the set light amounts for detection; and the photodetection elements are configured to output sensor values corresponding to the light amounts for detection.

Description

BRIEF DESCRIPTION OF THE DRAWINGS

(1) FIG. 1 is a sectional view schematically illustrating a detection device according to an embodiment;

(2) FIG. 2 is a block diagram illustrating a configuration example of the detection device according to the embodiment;

(3) FIG. 3 is a block diagram illustrating a configuration example of a detection control circuit according to the embodiment;

(4) FIG. 4 is a circuit diagram illustrating a sensor pixel;

(5) FIG. 5 is a plan view schematically illustrating the sensor pixel according to the embodiment;

(6) FIG. 6 is a sectional view along VI-VI' of FIG. 5;

(7) FIG. 7 illustrates explanatory diagrams for schematically explaining a relation of objects to be detected, a placement substrate, and a culture medium with sensor values;

(8) FIG. 8 illustrates explanatory diagrams for schematically explaining the relation of the objects to be detected, the placement substrate, and the culture medium with the sensor values in a detection device according to a comparative example;

(9) FIG. 9 is a flowchart illustrating a light amount setting mode and a detection mode of the detection device according to the embodiment;

(10) FIG. 10 is an explanatory view schematically illustrating a lighting pattern for adjusting light amounts of a plurality of light-emitting elements of the detection device according to the embodiment;

(11) FIG. 11 is a plan view schematically illustrating an arrangement relation between a plurality of

photodiodes and the light-emitting elements;

(12) FIG. 12 is an explanatory graph for explaining relations of the light-emitting elements lit up at different light amounts with the sensor values of the photodiodes;

(13) FIG. 13 is an explanatory diagram for explaining the relations of the light-emitting elements lit up at different light amounts with the sensor values of the photodiodes of the detection device according to a first modification of the embodiment;

(14) FIG. 14 is an explanatory diagram for explaining the relations of the light-emitting elements lit up at different light amounts with the sensor values of the photodiodes of the detection device according to a second modification of the embodiment;

(15) FIG. 15 is a plan view schematically illustrating a configuration example of the light-emitting elements of the detection device according to a third modification of the embodiment;

(16) FIG. 16 is a timing waveform diagram for explaining an operation example of the detection device according to the third modification;

(17) FIG. 17 is an explanatory view schematically illustrating the lighting pattern for adjusting the light amounts of the light-emitting elements of the detection device according to a fourth modification of the embodiment; and

(18) FIG. 18 is an explanatory view schematically illustrating the lighting pattern for adjusting the light amounts of the light-emitting elements of the detection device according to a fifth modification of the embodiment.

DETAILED DESCRIPTION

(19) The following describes a mode (embodiment) for carrying out the present disclosure in detail with reference to the drawings. The present disclosure is not limited to the description of the embodiment given below. Components described below include those easily conceivable by those skilled in the art or those substantially identical thereto. In addition, the components described below can be combined as appropriate. What is disclosed herein is merely an example, and the present disclosure naturally encompasses appropriate modifications easily conceivable by those skilled in the art while maintaining the gist of the present disclosure. To further clarify the description, the drawings may schematically illustrate, for example, widths, thicknesses, and shapes of various parts as compared with actual aspects thereof. However, they are merely examples, and interpretation of the present disclosure is not limited thereto. The same component as that described with reference to an already mentioned drawing is denoted by the same reference numeral through the present disclosure and the drawings, and detailed description thereof may not be repeated where appropriate.

(20) In the present specification and claims, in expressing an aspect of disposing another structure on or above a certain structure, a case of simply expressing “on” includes both a case of disposing the other structure immediately on the certain structure so as to contact the certain structure and a case of disposing the other structure above the certain structure with still another structure interposed therebetween, unless otherwise specified.

Embodiment

(21) FIG. 1 is a sectional view schematically illustrating a detection device according to an embodiment. As illustrated in FIG. 1, a detection device 1 includes an optical sensor 10, an optical filter layer 50, a placement substrate 101 and a cover member 103 for placing objects to be detected 100, and a light source device 80. The optical filter layer 50, the placement substrate 101 and the cover member 103 (objects to be detected 100), and the light source device 80 are arranged in this order on the optical sensor 10.

(22) Each of the object to be detected 100 is a micro-object such as a bacterium. The detection device 1 is a biosensor that detects the micro-object such as the bacterium. The placement substrate 101 is a light-transmitting plate-like member formed of glass, for example. The objects to be detected 100 are placed together with a culture medium 102 on the placement substrate 101. The cover member 103 covering the objects to be detected 100 is provided on the upper side of the

placement substrate **101**. The placement substrate **101** and the cover member **103** are a Petri dish, for example. The objects to be detected **100** serving as detection targets are placed on the placement substrate **101** and placed between the optical sensor **10** and the light source device **80**. (23) The objects to be detected **100** are not limited to the bacteria and may be other micro-objects such as cells. The detection device **1** is not limited to a biosensor and may be configured as, for example, a fingerprint detection device that detects a fingerprint or a vein detection device that detects a vascular pattern of, for example, veins. In this case, the object to be detected **100** may be a living body such as a finger, a palm, or a wrist.

(24) The optical sensor **10** is a planar detection device that includes a plurality of photodiodes **30** (photodetection elements) arranged in a planar configuration. A detailed configuration of the optical sensor **10** will be described later with reference to FIG. 2 and FIGS. 5 and 6.

(25) The optical filter layer **50** is a light directivity control element disposed between a plurality of light-emitting elements **82** (light source device **80**) and the photodiodes **30** (optical sensor **10**). More specifically, the optical filter layer **50** is provided between the photodiodes **30** of the optical sensor **10** and the placement substrate **101**. The optical filter layer **50** is disposed so as to face the photodiodes **30** of the optical sensor **10**. The optical filter layer **50** is an optical element that transmits components of light L emitted from the light-emitting elements **82** that travel in a direction orthogonal to the optical sensor **10** toward the photodiodes **30**. The optical filter layer **50** is also called collimating apertures or a collimator.

(26) The light source device **80** includes a light source substrate **81** and the light-emitting elements **82**. The light-emitting elements **82** are point light sources provided correspondingly to the photodiodes **30** of the optical sensor **10**. The light-emitting elements **82** are provided on the light source substrate **81** and arranged so as to face the photodiodes **30** of the optical sensor **10**. The light-emitting elements **82** are each made of a light-emitting diode (LED), for example.

(27) The light L emitted from the light-emitting elements **82** passes through the placement substrate **101**, the culture medium **102**, the cover member **103**, and the optical filter layer **50**, and is transmitted toward the photodiodes **30** of the optical sensor **10**. The amounts of light received by the photodiodes **30** differ between areas overlapping the objects to be detected **100** and areas not overlapping the objects to be detected **100**. As a result, the optical sensor **10** can image the objects to be detected **100**.

(28) In the present embodiment, the light-emitting elements **82** serving as the point light sources are arranged at a predetermined pitch. As a result, compared with a case of providing a surface light source, the direction of the light L is restrained from varying, thus enabling better imaging. The arrangement pitch of the light-emitting elements **82** is set so as to reduce interference of the light L emitted from the adjacent light-emitting elements **82**. In addition, the optical sensor **10** is irradiated with the light L, of which the viewing angle is limited by the optical filter layer **50**. The arrangement pitch of the photodiodes **30** is set so as to ensure the light-receiving area of the optical sensor **10**.

(29) FIG. 2 is a block diagram illustrating a configuration example of the detection device according to the embodiment. As illustrated in FIG. 2, the detection device **1** further includes a host integrated circuit (IC) **70** that controls the optical sensor **10** and the light source device **80**. The optical sensor **10** includes an array substrate **2**, a plurality of sensor pixels **3** (photodiodes **30**) formed on the array substrate **2**, gate line drive circuits **15A** and **15B**, a signal line drive circuit **16A**, and a detection control circuit **11**.

(30) The array substrate **2** is formed using a substrate **21** as a base. Each of the sensor pixels **3** is configured with a corresponding one of the photodiodes **30**, a plurality of transistors, and various types of wiring. The array substrate **2** with the photodiodes **30** formed thereon is a drive circuit board for driving the sensor for each predetermined detection area, and is also called a backplane or an active matrix substrate.

(31) The substrate **21** has a detection area AA and a peripheral area GA. The detection area AA is

an area provided with the sensor pixels **3** (photodiodes **30**). The peripheral area **GA** is an area between the outer perimeter of the detection area **AA** and the outer edges of the substrate **21** and is an area not provided with the sensor pixels **3**. The gate line drive circuits **15A** and **15B**, the signal line drive circuit **16A**, and the detection control circuit **11** are provided in the peripheral area **GA**. (32) Each of the sensor pixels **3** is an optical sensor including the photodiode **30** as a sensor element. Each of the photodiodes **30** outputs an electrical signal corresponding to light emitted thereto. More specifically, the photodiode **30** is a positive-intrinsic-negative (PIN) photodiode or an organic photodiode (OPD) using an organic semiconductor. The sensor pixels **3** (photodiodes **30**) are arranged in a matrix having a row-column configuration in the detection area **AA**.

(33) The detection control circuit **11** is a circuit that supplies control signals **Sa**, **Sb**, and **Sc** to the gate line drive circuits **15A** and **15B**, and the signal line drive circuit **16A**, respectively, to control operations of these circuits. Specifically, the gate line drive circuits **15A** and **15B** output gate drive signals to sensor gate lines **GLS** (refer to FIG. **4**) based on the control signals **Sa** and **Sb**. The signal line drive circuit **16A** electrically couples a sensor signal line **SLS** selected based on the control signal **Sc** to the detection control circuit **11**. The detection control circuit **11** includes a signal processing circuit that performs signal processing of a detection signal **Vdet** from each of the photodiodes **30**.

(34) The photodiodes **30** included in the sensor pixels **3** perform detection in response to the gate drive signals supplied from the gate line drive circuits **15A** and **15B**. Each of the photodiodes **30** outputs the electrical signal corresponding to the light emitted thereto as the detection signal **Vdet** to the signal line drive circuit **16A**. The detection control circuit **11** (detection circuit) is electrically coupled to the photodiodes **30**. The detection control circuit **11** performs the signal processing of the detection signals **Vdet** from the photodiodes **30**, and outputs sensor values **So** based on the detection signals **Vdet** to the host IC **70**. This operation causes the detection device **1** to detect information on the object to be detected **100**.

(35) FIG. **3** is a block diagram illustrating a configuration example of the detection control circuit according to the embodiment. As illustrated in FIG. **3**, the detection control circuit **11** includes a detection signal amplitude adjustment circuit **41**, an analog-to-digital (A/D) conversion circuit **42**, a signal processing circuit **43**, and a detection timing control circuit **44**. In the detection control circuit **11**, the detection timing control circuit **44** performs control to cause the detection signal amplitude adjustment circuit **41**, the A/D conversion circuit **42**, and the signal processing circuit **43** to operate in synchronization with one another based on a control signal supplied from the host IC **70** (refer to FIG. **2**).

(36) The detection signal amplitude adjustment circuit **41** is a circuit that adjusts the amplitude of the detection signal **Vdet** output from the photodiode **30** and is configured with an amplifier, for example. The A/D conversion circuit **42** converts analog signals output from the detection signal amplitude adjustment circuit **41** into digital signals. The signal processing circuit **43** is a circuit that performs signal processing of the digital signals from the A/D conversion circuit **42** and transmits the sensor values **So** to the host IC **70**.

(37) Referring back to FIG. **2**, the light source device **80** includes the light source substrate **81**, the light-emitting elements **82** formed on the light source substrate **81**, gate line drive circuits **15C** and **15D**, a signal line drive circuit **16B**, and a light-emitting element control circuit **12**.

(38) The light-emitting elements **82** are arranged in a matrix having a row-column configuration in an area overlapping the detection area **AA** of the light source substrate **81**. The light source substrate **81** is a drive circuit board for driving each of the light-emitting elements **82** to be switched between on (in a lit-up state) and off (in a non-lit state).

(39) The light-emitting element control circuit **12** is a circuit that supplies control signals **Sd**, **Se**, and **Sf** to the gate line drive circuits **15C** and **15D**, and the signal line drive circuit **16B**, respectively, to control operations of these circuits. Specifically, the gate line drive circuits **15C** and **15D** output drive signals to gate lines (not illustrated) based on the control signals **Sd** and **Se**, and

thus select the light-emitting elements **82** in a given row. The signal line drive circuit **16B** supplies a light-emitting element control signal to a selected signal line (not illustrated) based on the control signal Sf. Thus, the light source device **80** can light up the different light-emitting elements **82** at different light amounts. The light source device **80** can also switch each of the light-emitting elements **82** between the lit-up state (on) and the non-lit state (off).

(40) The light source substrate **81** of the light source device **80** is what is called an active matrix substrate, but is not limited thereto. Any method may be used to control on and off the light-emitting elements **82**. For example, the light-emitting element control circuit **12** may individually control each of the light-emitting elements **82**.

(41) The host IC **70** controls the optical sensor **10** and the light source device **80** to execute a light amount setting mode to set light amounts of the light-emitting elements **82** for detection and a detection mode to detect the object to be detected **100**. In the light amount setting mode, the host IC **70** lights up the light-emitting elements **82** at different light amounts, and the photodiodes **30** output the sensor values So corresponding to the different light amounts. The host IC **70** then compares the detected sensor values So with a preset target sensor value So-t and sets the light amounts of the light-emitting elements **82** for detection. In the detection mode, the host IC **70** lights up the light-emitting elements **82** at the set light amounts for detection, and the photodiodes **30** output the sensor values So corresponding to the set light amounts for detection.

(42) The host IC **70** includes a sensor value storage circuit **71**, a sensor value calculation circuit **72**, a light amount setting circuit **73**, and a target value storage circuit **79** as control circuits for the optical sensor **10**. The sensor value storage circuit **71** stores therein the sensor values So output from the detection control circuit **11** of the optical sensor **10**. The sensor value calculation circuit **72** performs a predetermined calculation process on the sensor values So of the photodiodes **30**. For example, the sensor value calculation circuit **72** calculates the average value of the sensor values So from the photodiodes **30** corresponding to one of the light-emitting elements **82**.

(43) In the light amount setting mode, the light amount setting circuit **73** compares each of the sensor values So detected by the photodiodes **30** with the preset target sensor value So-t acquired from the target value storage circuit **79** and sets the light amounts of the light-emitting elements **82** for detection. The target value storage circuit **79** stores therein the preset target sensor value So-t. A method for setting the light amounts of the light-emitting elements **82** for detection by the light amount setting circuit **73** and the details of the target sensor value So-t stored in the target value storage circuit **79** will be described with reference to FIG. 7 and subsequent drawings.

(44) The host IC **70** includes a lighting pattern generation circuit **74** and a lighting pattern storage circuit **75** as control circuits for the light source device **80**. The lighting pattern storage circuit **75** stores therein information on a light amount of each of the light-emitting elements **82** in the light amount setting mode. The lighting pattern storage circuit **75** also stores therein the information on the light amount of each of the light-emitting elements **82** in the detection mode based on the information on the light amounts for detection acquired from the light amount setting circuit **73**. The lighting pattern storage circuit **75** stores therein an arrangement pattern of on (lit-up state) and off (non-lit state) of the light-emitting elements **82** as needed.

(45) The lighting pattern generation circuit **74** generates various control signals based on the information on the light amounts in the lighting pattern storage circuit **75**. The lighting pattern generation circuit **74** then outputs, to the light-emitting element control circuit **12**, the light-emitting element control signals including the information on the light amounts of the light-emitting elements **82** in each of the light amount setting mode and the detection mode.

(46) The host IC **70** further includes an image generation circuit **76**. In the detection mode, the image generation circuit **76** generates an image of the objects to be detected **100** based on the sensor values So output from the photodiodes **30**. The sensor values So used by the image generation circuit **76** are output from the photodiodes **30** correspondingly to the light amounts for detection set in the light amount setting mode.

(47) Although not illustrated, the host IC **70** includes a control circuit that synchronously controls the detection control circuit **11** and the light-emitting element control circuit **12**. That is, the switching of the light amounts of the light-emitting elements **82** of the light source device **80** and the detection of the photodiodes **30** of the optical sensor **10** are synchronously controlled based on a control signal from the host IC **70**. The optical sensor **10** includes the two gate line drive circuits **15A** and **15B**, but may include one gate line drive circuit. The light source device **80** includes the two gate line drive circuits **15C** and **15D**, but may include one gate line drive circuit.

(48) The following describes a configuration example of the optical sensor **10**. FIG. **4** is a circuit diagram illustrating the sensor pixel. As illustrated in FIG. **4**, the sensor pixel **3** includes the photodiode **30**, a capacitive element Ca, and a first transistor TrS. The first transistor TrS is provided correspondingly to the photodiode **30**. The first transistor TrS is formed of a thin-film transistor, and in this example, formed of an n-channel metal oxide semiconductor (MOS) thin-film transistor (TFT). The gate of the first transistor TrS is coupled to the sensor gate line GLS. The source of the first transistor TrS is coupled to the sensor signal line SLS. The drain of the first transistor TrS is coupled to the anode of the photodiode **30** and the capacitive element Ca.

(49) The cathode of the photodiode **30** is supplied with a power supply potential SVS from the detection control circuit **11**. The capacitive element Ca is supplied with a reference potential VR1 serving as an initial potential of the capacitive element Ca from the detection control circuit **11**.

(50) When the sensor pixel **3** is irradiated with light, a current corresponding to the amount of the light flows through the photodiode **30**. As a result, an electric charge is stored in the capacitive element Ca. After the first transistor TrS is turned on, a current corresponding to the electric charge stored in the capacitive element Ca flows through the sensor signal line SLS. The sensor signal line SLS is coupled to the detection control circuit **11** through the signal line drive circuit **16A**. Thus, the optical sensor **10** of the detection device **1** can detect a signal corresponding to the amount of the light received by the photodiode **30** for each of the sensor pixels **3**.

(51) The first transistor TrS is not limited to the n-type TFT, and may be configured as a p-type TFT. The pixel circuit of the sensor pixel **3** illustrated in FIG. **4** is merely exemplary. The sensor pixel **3** may be provided with a plurality of transistors corresponding to one photodiode **30**.

(52) The following describes a detailed configuration of the optical sensor **10**. FIG. **5** is a plan view schematically illustrating the sensor pixel according to the embodiment.

(53) In the following description, a first direction Dx is one direction in a plane parallel to the substrate **21** (refer to FIG. **6**). A second direction Dy is one direction in the plane parallel to the substrate **21** and is a direction orthogonal to the first direction Dx. The second direction Dy may non-orthogonally intersect the first direction Dx. A third direction Dz is a direction orthogonal to the first direction Dx and the second direction Dy and is a direction normal to the principle surface of the substrate **21**. The term “plan view” refers to a positional relation when viewed in a direction orthogonal to the substrate **21**.

(54) As illustrated in FIG. **5**, the sensor pixel **3** is an area surrounded by the sensor gate lines GLS and the sensor signal lines SLS. In the present embodiment, the sensor gate line GLS includes a first sensor gate line GLA and a second sensor gate line GLB. The first sensor gate line GLA is provided so as to overlap the second sensor gate line GLB. The first and the second sensor gate lines GLA and GLB are provided in different layers with insulating layers **22c** and **22d** interposed therebetween (refer to FIG. **6**). The first and the second sensor gate lines GLA and GLB are electrically coupled together at any point and are supplied with the gate drive signals having the same potential. At least one of the first gate line GLA and the second sensor gate line GLB is coupled to the gate line drive circuits **15A** and **15B**. In FIG. **5**, the first and the second sensor gate lines GLA and GLB have different widths but may have the same width.

(55) The photodiode **30** is provided in the area surrounded by the sensor gate lines GLS and the sensor signal lines SLS. An upper electrode **34** and a lower electrode **35** are provided for each of the photodiodes **30**. The photodiode **30** is a PIN photodiode, for example. The lower electrode **35**

is, for example, an anode electrode of the photodiode **30**. The upper electrode **34** is, for example, a cathode electrode of the photodiode **30**.

(56) The upper electrode **34** is coupled to a power supply signal line Lvs through coupling wiring **36**. The power supply signal line Lvs is wiring that supplies the power supply potential SVS to the photodiode **30**. In the present embodiment, the power supply signal line Lvs extends in the second direction Dy while overlapping the sensor signal line SLS. The sensor pixels **3** arranged in the second direction Dy are coupled to the power supply signal line Lvs that is shared by those sensor pixels **3**. Such a configuration can enlarge an opening for the sensor pixel **3**. The lower electrode **35**, the photodiode **30**, and the upper electrode **34** are substantially quadrilateral in plan view. However, the shapes of the lower electrode **35**, the photodiode **30**, and the upper electrode **34** are not limited thereto and can be changed as appropriate.

(57) The first transistor TrS is provided near an intersection between the sensor gate line GLS and the sensor signal line SLS. The first transistor TrS includes a semiconductor layer **61**, a source electrode **62**, a drain electrode **63**, a first gate electrode **64A**, and a second gate electrode **64B**.

(58) The semiconductor layer **61** is an oxide semiconductor. The semiconductor layer **61** is more preferably a transparent amorphous oxide semiconductor (TAOS) among various oxide semiconductors. Using an oxide semiconductor as the first transistor TrS can reduce a leakage current of the first transistor TrS. That is, the first transistor TrS can reduce the leakage current from a non-selected one of the sensor pixels **3**. Therefore, the optical sensor **10** can improve the signal-to-noise ratio (S/N). The semiconductor layer **61** is, however, not limited thereto, and may be formed of, for example, a microcrystalline oxide semiconductor, an amorphous oxide semiconductor, polysilicon, or low-temperature polycrystalline silicon (LTPS).

(59) The semiconductor layer **61** is provided along the first direction Dx and intersects the first and the second gate electrodes **64A** and **64B** in plan view. The first and the second gate electrodes **64A** and **64B** are provided so as to branch from the first and the second sensor gate lines GLA and GLB, respectively. In other words, portions of the first and the second sensor gate lines GLA and GLB that overlap the semiconductor layer **61** serve as the first and the second gate electrodes **64A** and **64B**. Aluminum (Al), copper (Cu), silver (Ag), molybdenum (Mo), or an alloy of these metals is used as the first and the second gate electrodes **64A** and **64B**. Channel regions are formed at portions of the semiconductor layer **61** that overlap the first and the second gate electrodes **64A** and **64B**.

(60) One end of the semiconductor layer **61** is coupled to the source electrode **62** through a contact hole H1. The other end of the semiconductor layer **61** is coupled to the drain electrode **63** through a contact hole H2. A portion of the sensor signal line SLS that overlaps the semiconductor layer **61** serves as the source electrode **62**. A portion of a third conductive layer **67** that overlaps the semiconductor layer **61** serves as the drain electrode **63**. The third conductive layer **67** is coupled to the lower electrode **35** through a contact hole H3. Such a configuration allows the first transistor TrS to switch between coupling and decoupling between the photodiode **30** and the sensor signal line SLS.

(61) The following describes a layer configuration of the optical sensor **10**. FIG. **6** is a sectional view along VI-VI' of FIG. **5**.

(62) In the description of the detection device **1** that includes the optical sensor **10**, a direction from the substrate **21** toward the photodiode **30** in a direction (third direction Dz) orthogonal to a surface of the substrate **21** is referred to as “upward” or “above”. A direction from the photodiode **30** toward the substrate **21** is referred to as “downward” or “below”.

(63) As illustrated in FIG. **6**, the substrate **21** is an insulating substrate and is made using, for example, a glass substrate of quartz, alkali-free glass, or the like. The first transistor TrS, various types of wiring (the sensor gate line GLS and the sensor signal line SLS), and insulating layers are provided to form the array substrate **2** on one surface side of the substrate **21**. The photodiodes **30** are arranged on the upper side of the array substrate **2**, that is, on the one surface side of the

substrate **21**. The substrate **21** may be a resin substrate or a resin film made of a resin such as polyimide.

(64) Insulating layers **22a** and **22b** are provided on the substrate **21**. Insulating layers **22a**, **22b**, **22c**, **22d**, **22e**, **22f**, and **22g** are inorganic insulating films and are formed of a silicon oxide (SiO₂) or a silicon nitride (SiN). Each of the inorganic insulating layers is not limited to a single layer and may be a multilayered film.

(65) The first gate electrode **64A** is provided above the insulating layer **22b**. The insulating layer **22c** is provided on the insulating layer **22b** so as to cover the first gate electrode **64A**. The semiconductor layer **61**, a first conductive layer **65**, and a second conductive layer **66** are provided on the insulating layer **22c**. The first conductive layer **65** is provided so as to cover an end of the semiconductor layer **61** coupled to the source electrode **62**. The second conductive layer **66** is provided so as to cover an end of the semiconductor layer **61** coupled to the drain electrode **63**.

(66) The insulating layer **22d** is provided on the insulating layer **22c** so as to cover the semiconductor layer **61**, the first conductive layer **65**, and the second conductive layer **66**. The second gate electrode **64B** is provided on the insulating layer **22d**. The semiconductor layer **61** is provided between the first gate electrode **64A** and the second gate electrode **64B** in the direction orthogonal to the substrate **21**. That is, the first transistor TrS has what is called a dual-gate structure. The first transistor TrS may, however, have a bottom-gate structure that is provided with the first gate electrode **64A** and not provided with the second gate electrode **64B**, or a top-gate structure that is not provided with the first gate electrode **64A** and provided with only the second gate electrode **64B**.

(67) The insulating layer **22e** is provided on the insulating layer **22d** so as to cover the second gate electrode **64B**. The source electrode **62** (sensor signal line SLS) and the drain electrode **63** (third conductive layer **67**) are provided on the insulating layer **22e**. In the present embodiment, the drain electrode **63** is the third conductive layer **67** provided above the semiconductor layer **61** with the insulating layers **22d** and **22e** interposed therebetween. The source electrode **62** is electrically coupled to the semiconductor layer **61** through the contact hole H1 and the first conductive layer **65**. The drain electrode **63** is electrically coupled to the semiconductor layer **61** through the contact hole H2 and the second conductive layer **66**.

(68) The third conductive layer **67** is provided in an area overlapping the photodiode **30** in plan view. The third conductive layer **67** is provided also on the upper side of the semiconductor layer **61** and the first and the second gate electrodes **64A** and **64B**. That is, the third conductive layer **67** is provided between the second gate electrode **64B** and the lower electrode **35** in the direction orthogonal to the substrate **21**. With this configuration, the third conductive layer **67** has a function as a protective layer that protects the first transistor TrS.

(69) The second conductive layer **66** extends so as to face the third conductive layer **67** in an area not overlapping the semiconductor layer **61**. A fourth conductive layer **68** is provided on the insulating layer **22d** in the area not overlapping the semiconductor layer **61**. The fourth conductive layer **68** is provided between the second conductive layer **66** and the third conductive layer **67**. This configuration generates capacitance between the second conductive layer **66** and the fourth conductive layer **68**, and capacitance between the third conductive layer **67** and the fourth conductive layer **68**. The capacitance generated by the second conductive layer **66**, the third conductive layer **67**, and the fourth conductive layer **68** serves as capacitance of the capacitive element Ca illustrated in FIG. 4.

(70) A first organic insulating layer **23a** is provided on the insulating layer **22e** so as to cover the source electrode **62** (sensor signal line SLS) and the drain electrode **63** (third conductive layer **67**). The first organic insulating layer **23a** is a planarizing layer that planarizes asperities formed by the first transistor TrS and various conductive layers.

(71) The following describes a sectional configuration of the photodiode **30**. The photodiode **30** is stacked on the first organic insulating layer **23a** of the array substrate **2** in the order of the lower

electrode **35**, the photodiode **30**, and the upper electrode **34**.

(72) The lower electrode **35** is provided on the first organic insulating layer **23a** and is electrically coupled to the third conductive layer **67** through the contact hole H3. The lower electrode **35** is the anode of the photodiode **30** and is an electrode for reading the detection signal Vdet. For example, a metal material such as molybdenum (Mo) or aluminum (Al) is used as the lower electrode **35**. The lower electrode **35** may alternatively be a multilayered film formed of a plurality of layers of these metal materials. The lower electrode **35** may be formed of a light-transmitting conductive material such as indium tin oxide (ITO) or indium zinc oxide (IZO).

(73) The photodiode **30** includes an i-type semiconductor layer **31**, an n-type semiconductor layer **32**, and a p-type semiconductor layer **33** as semiconductor layers. The i-type semiconductor layer **31**, the n-type semiconductor layer **32**, and the p-type semiconductor layer **33** are formed of amorphous silicon (a-Si), for example. In FIG. **6**, the p-type semiconductor layer **33**, the i-type semiconductor layer **31**, and the n-type semiconductor layer **32** are stacked in this order in the direction orthogonal to the surface of the substrate **21**. However, the photodiode **30** may have a reversed configuration. That is, the n-type semiconductor layer **32**, the i-type semiconductor layer **31**, and the p-type semiconductor layer **33** may be stacked in this order. Each of the semiconductor layers may be a photoelectric conversion element formed of an organic semiconductor.

(74) The a-Si of the n-type semiconductor layer **32** is doped with impurities to form an n⁺ region. The a-Si of the p-type semiconductor layer **33** is doped with impurities to form a p⁺ region. The i-type semiconductor layer **31** is, for example, a non-doped intrinsic semiconductor, and has lower conductivity than that of the n-type semiconductor layer **32** and the p-type semiconductor layer **33**.

(75) The upper electrode **34** is the cathode of the photodiode **30** and is an electrode for supplying the power supply potential SVS to the photoelectric conversion layers. The upper electrode **34** is, for example, a light-transmitting conductive layer of, for example, ITO, and a plurality of the upper electrodes **34** are provided for the respective photodiodes **30**.

(76) The insulating layers **22f** and **22g** are provided on the first organic insulating layer **23a**. The insulating layer **22f** covers the periphery of the upper electrode **34** and is provided with an opening in a position overlapping the upper electrode **34**. The coupling wiring **36** is coupled to a portion of the upper electrode **34** not provided with the insulating layer **22f**. The insulating layer **22g** is provided on the insulating layer **22f** so as to cover the upper electrode **34** and the coupling wiring **36**. A second organic insulating layer **23b** serving as a planarizing layer is provided on the insulating layer **22g**. If the photodiode **30** is made of organic semiconductors, an insulating layer **22h** may be further provided on the upper side thereof.

(77) The following describes one example of a detection method of the detection device **1** according to the present embodiment. FIG. **7** illustrates explanatory diagrams for schematically explaining a relation of the objects to be detected, the placement substrate, and the culture medium with the sensor values. FIG. **8** illustrates explanatory diagrams for schematically explaining the relation of the objects to be detected, the placement substrate, and the culture medium with the sensor values in a detection device according to a comparative example.

(78) A maximum sensor value So-max illustrated in FIGS. **7** and **8** is the sensor value So corresponding to the upper limit value of a detection range of the detection control circuit **11** (refer to FIG. **3**). A minimum sensor value So-min is the sensor value So corresponding to the lower limit value of the detection range of the detection control circuit **11**. The detection range of the detection control circuit **11** is a detection range in which an electric charge (sensor value So) output from the photodiode **30** are detectable.

(79) As illustrated in the left diagrams of FIG. **7**, in an initial state where no object to be detected **100** is present in the culture medium **102**, the light L emitted from the light-emitting elements **82** enters the photodiode **30** through the culture medium **102** and the placement substrate **101**. The photodiode **30** outputs a sensor value So-a corresponding to the amount of light emitted thereto. In the initial state, the sensor value So-a is between the minimum sensor value So-min and the

maximum sensor value So-max.

(80) As illustrated in the right diagrams of FIG. 7, after a predetermined time elapses from the initial state, the objects to be detected **100** (such as bacteria) have grown in the culture medium **102**. The amounts of light incident on the photodiodes **30** vary depending on the turbidity (light transmittance) of the culture medium **102** and/or the presence or absence of the objects to be detected **100**. The amounts of light incident on the photodiodes **30** are smaller in areas overlapping the objects to be detected **100** than in areas not overlapping the objects to be detected **100**. The photodiodes **30** corresponding to positions of the objects to be detected **100** output sensor values So-b, So-c, and So-d. The sensor values So-b, So-c, and So-d corresponding to the objects to be detected **100** are smaller than the sensor value So-a in the initial state and are between the minimum sensor value So-min and the maximum sensor value So-max.

(81) As illustrated in the left diagrams of FIG. 8, in the detection device according to the comparative example, the amounts of light L emitted from the light-emitting elements **82** are smaller than in the detection device according to the embodiment illustrated in FIG. 7. In this case, in the initial state, a sensor value So-e output from the photodiode **30** is between the minimum sensor value So-min and the maximum sensor value So-max and is smaller than the sensor value So-a illustrated in FIG. 7.

(82) As illustrated in the right diagrams of FIG. 8, in the detection device according to the comparative example, after a predetermined time elapses from the initial state, the amounts of light incident on the photodiodes **30** are smaller in areas overlapping the objects to be detected **100** than in areas not overlapping the objects to be detected **100**. The sensor values So from the photodiodes **30** in positions corresponding to the objects to be detected **100** are smaller than the lower limit value of the detection range of the detection control circuit **11**. As a result, a sensor value So-f that has been output from the photodiodes **30** in the positions corresponding to the objects to be detected **100** and has undergone the signal processing by the detection control circuit **11** is equal to the minimum sensor value So-min.

(83) Thus, even if the amounts of the light L emitted from the light-emitting elements **82** are within a detectable range in the initial state, the objects to be detected **100** may not be accurately detectable depending on the state of the objects to be detected **100**, the culture medium **102**, and the like. In other words, even if the state of the objects to be detected **100**, the culture medium **102**, and the like has changed, the amounts of the light L emitted from the light-emitting elements **82** need to be appropriately set so that the sensor values So-b, So-c, and So-d are between the minimum sensor value So-min and the maximum sensor value So-max, as illustrated in FIG. 7.

(84) The following describes the method for setting the amounts of the light L emitted from the light-emitting elements **82** in the detection mode to detect the objects to be detected **100** (hereinafter, referred to as “light amounts for detection”), with reference to FIGS. 9 to 14.

(85) FIG. 9 is a flowchart illustrating the light amount setting mode and the detection mode of the detection device according to the embodiment. As illustrated in FIG. 9, the detection device **1** according to the embodiment includes the light amount setting mode (from Step ST1 to Step ST5) and the detection mode (from Step ST6 to Step ST8).

(86) At the start of measurement of the optical sensor **10**, the host IC **70** executes the light amount setting mode in the initial state illustrated in FIG. 7. The host IC **70** supplies control signals to the light source device **80** to light up the light-emitting elements **82** in a lighting pattern for adjusting the light amounts (Step ST1).

(87) FIG. 10 is an explanatory view schematically illustrating the lighting pattern for adjusting the light amounts of the light-emitting elements of the detection device according to the embodiment. As illustrated in FIG. 10, the light-emitting elements **82** are arranged in a matrix having a row-column configuration on the light source substrate **81**. In the lighting pattern for adjusting the light amounts, the light-emitting elements **82** are lit up at different light amounts. The light amount of a light-emitting element **82-1** located at the upper left in FIG. 10 is smallest, and the light amount

increases in the order of light-emitting elements **82-1**, **82-2**, . . . , **82-6** arranged in the first row. The light amounts of light-emitting elements **82-7** to **82-12** arranged in the second row are larger than those of the light-emitting elements **82** in the first row. The light amounts of light-emitting elements **82-13** to **82-18** arranged in the third row are larger than those of the light-emitting elements **82** in the second row. Thus, the light amounts of the light-emitting elements **82** arranged in a matrix having a row-column configuration sequentially differ, and the light amount increases as a light-emitting element number of the light-emitting element **82** increases. The light-emitting element number is a number given to each light-emitting element **82** and ranges from 1 to n.

Among the light-emitting elements **82** in the last row, the light-emitting element **82-n** in the last row located at the lower right of FIG. **10** emits the largest amount of light.

(88) The lighting pattern for adjusting the light amounts of the light-emitting elements **82** is stored in advance in the lighting pattern storage circuit **75** (refer to FIG. **2**). The lighting pattern generation circuit **74** receives the information on the lighting pattern for adjusting the light amounts from the lighting pattern storage circuit **75**, generates the light-emitting element control signal corresponding to the light amount of each of the light-emitting elements **82**, and outputs the result to the light source device **80**.

(89) The number, the arrangement pitch, and the lighting pattern for adjusting the light amounts of the light-emitting elements **82** illustrated in FIG. **10** are merely exemplary and can be changed as appropriate.

(90) The host IC **70** then performs detection using the optical sensor **10** (Step ST2). Specifically, the light L from the light-emitting elements **82** lit up at the different light amounts enters the photodiodes **30** of the optical sensor **10** through the culture medium **102** in the initial state and the placement substrate **101**. The photodiodes **30** output the sensor values So corresponding to the different light amounts.

(91) FIG. **11** is a plan view schematically illustrating an arrangement relation between the photodiodes and the light-emitting elements. As illustrated in FIG. **11**, a plurality of the photodiodes **30** are provided in an area overlapping one of the light-emitting elements **82**. Photodiode groups **30G-1**, **30G-2**, **30G-7**, and **30G-8** are arranged for the light-emitting elements **82-1**, **82-2**, **82-7**, and **82-8**, respectively. In the example illustrated in FIG. **11**, a photodiode group **30G** including nine of the photodiodes **30** is disposed in an area overlapping one of the light-emitting elements **82**.

(92) FIG. **11** is merely exemplary. At least one of the photodiodes **30** only needs to be provided so as to overlap one of the light-emitting elements **82**. The number of the photodiodes **30** included in the photodiode group **30G** may be equal to or smaller than eight, or equal to or larger than 10.

(93) The host IC **70** then receives the sensor values So from the optical sensor **10** and calculates the average value of the sensor values So corresponding to each of the light-emitting elements **82** (Step ST3). In the example illustrated in FIG. **11**, the photodiode groups **30G-1**, **30G-2**, **30G-7**, and **30G-8** are arranged correspondingly to the light-emitting elements **82-1**, **82-2**, **82-7**, and **82-8**, respectively, that are lit up at the different light amounts. The sensor value calculation circuit **72** calculates the average value of the sensor values So for each of the photodiode groups **30G-1**, **30G-2**, **30G-7**, and **30G-8**, that is, for each of the light-emitting elements **82** lit up at the different light amounts. For example, the sensor value calculation circuit **72** calculates the average value of the sensor values So output from the nine photodiodes **30** in the photodiode group **30G-1**.

(94) Then, the light amount setting circuit **73** of the host IC **70** (refer to FIG. **2**) compares the calculated sensor values So with the target sensor value So-t. FIG. **12** is an explanatory graph for explaining relations of the light-emitting elements lit up at the different light amounts with the sensor values of the photodiodes. The sensor value So of each light-emitting element **82** in FIG. **12** is the average value of the sensor values So of the photodiodes **30** included in the photodiode group **30G** described above.

(95) The light amount setting circuit **73** (refer to FIG. **2**) receives the sensor values So of the light-

emitting elements **82** lit up at the different light amounts from the sensor value calculation circuit **72**. The light amount setting circuit **73** also receives the preset target sensor value $So-t$ from the target value storage circuit **79**. The light amount setting circuit **73** then compares the sensor values So of the light-emitting elements **82** lit up at the different light amounts with the target sensor value $So-t$ (Step ST4).

(96) The target sensor value $So-t$ is a value corresponding to the sensor value $So-a$ in the initial state illustrated in FIG. 7 and is set in advance within a range from 90% to 100% with respect to the maximum sensor value $So-max$. Setting the target sensor value $So-t$ to a value close to the maximum sensor value $So-max$ allows the sensor values $So-b$, $So-c$, and $So-d$ corresponding to the objects to be detected **100** to be maintained to a value equal to or larger than the minimum sensor value $So-min$ after the lapse of the predetermined time.

(97) As illustrated in FIG. 12, the sensor value So in the initial state increases as the light-emitting element number increases from the light-emitting element **82-1** to the light-emitting element **82-n**, that is, as the light amount of the light-emitting element **82** increases. In the example illustrated in FIG. 12, a sensor value $So-1$ of the photodiodes **30** corresponding to a light-emitting element **82-(n-4)** among the light-emitting elements **82** is closest to the target sensor value $So-t$. A sensor value $So-2$ of the photodiodes **30** corresponding to a light-emitting element **82-(n-3)** is second closest to the target sensor value $So-t$. A difference $\Delta So-1$ between the sensor value $So-1$ and the target sensor value $So-t$ is smaller than a difference $\Delta So-2$ between the sensor value $So-2$ and the target sensor value $So-t$.

(98) Referring back to FIG. 9, the light amount setting circuit **73** (refer to FIG. 2) selects the sensor value $So-1$ (first sensor value) closest to the target sensor value $So-t$ from among the sensor values So corresponding to the different light amounts. The light amount setting circuit **73** then sets the light amounts for detection to the light amount of the light-emitting element **82-(n-4)** corresponding to the sensor value $So-1$ (Step ST5). The set information on the light amounts for detection is stored in the lighting pattern storage circuit **75**.

(99) Then, the host IC **70** executes the detection mode based on the set light amounts for detection. In the detection mode, the light source device **80** lights up the light-emitting elements **82** at the set light amounts for detection (Step ST6). The lighting pattern generation circuit **74** receives the information on the light amounts for detection from the lighting pattern storage circuit **75**, generates, for the light-emitting elements **82**, the light-emitting element control signals corresponding to the light amounts for detection, and outputs the signals to the light source device **80**. Thus, in the detection mode, the light-emitting elements **82** are simultaneously lit up at the light amounts for detection.

(100) The optical sensor **10** performs the detection of the photodiodes **30** (Step ST7). The gate line drive circuit **15B** of the optical sensor **10** sequentially scans from a sensor gate line GLS-1 in the first row to a sensor gate line GLS-m in the last row based on control signals from the host IC **70**. Thus, the optical sensor **10** scans the photodiodes **30** in the entire detection area AA.

(101) The photodiodes **30** output the sensor values So corresponding to the light L at the set light amounts for detection. In more detail, the light L from the light-emitting elements **82** lit up at the light amounts for detection is applied to the culture medium **102** and the objects to be detected **100**. The light with amounts depending on the presence or absence of the objects to be detected **100** and/or the turbidity of the culture medium **102** enters the photodiodes **30**. As a result, the photodiodes **30** output the sensor values So that vary depending on the presence or absence of the objects to be detected **100** and/or the turbidity of the culture medium **102**.

(102) The image generation circuit **76** (refer to FIG. 2) generates the image based on the sensor values So from the photodiodes **30** (Step ST8).

(103) As described above, the detection device **1** of the present embodiment has the light amount setting mode and the detection mode. In the light amount setting mode, the light-emitting elements **82** are lit up at the different light amounts, and the photodiodes **30** output the sensor values So

corresponding to the different light amounts. The host IC **70** compares the detected sensor values S_o with the preset target sensor value S_{o-t} , and sets the light amounts of the light-emitting elements **82** for detection.

(104) Thus, the light amounts of the light-emitting elements **82** for detection are appropriately set so that the sensor value S_o in the initial state is close to the target sensor value S_{o-t} (from 90% to 100% of the maximum sensor value S_{o-max}). As a result, even if the state of the objects to be detected **100**, the culture medium **102**, and the like has changed over time, the sensor values S_o corresponding to the objects to be detected **100** (refer to the sensor values S_{o-b} , S_{o-c} , and S_{o-d} illustrated in FIG. 7) are between the minimum sensor value S_{o-min} and the maximum sensor value S_{o-max} . Therefore, the detection device **1** can improve the detection accuracy.

(105) First Modification

(106) FIG. **13** is an explanatory diagram for explaining the relations of the light-emitting elements lit up at the different light amounts with the sensor values of the photodiodes of the detection device according to a first modification of the embodiment. In the detection device **1** according to the first modification, the lighting pattern for adjusting the light amounts and the light amounts of the light-emitting elements **82** are the same as those in the example illustrated in FIG. **10**. In the first modification, however, the turbidity of the culture medium **102** in the initial state (refer to FIG. 7) is higher than that in the embodiment described above. In other words, in the first modification, smaller light amounts enter the photodiodes **30** through the culture medium **102** in the initial state.

(107) As illustrated in FIG. **13**, in the first modification, the sensor values S_o of the photodiodes **30** corresponding to the light-emitting elements **82** are smaller than those of the example illustrated in FIG. **12**. In the first modification, the sensor value S_{o-1} of the photodiodes **30** corresponding to a light-emitting element **82-(n-2)** is closest to the target sensor value S_{o-t} among the light-emitting elements **82**. The sensor value S_{o-2} of the photodiodes **30** corresponding to a light-emitting element **82-(n-1)** is second closest to the target sensor value S_{o-t} .

(108) In the first modification, the light amount setting circuit **73** sets the light amounts for detection to the light amount of the light-emitting element **82-(n-2)** corresponding to the sensor value S_{o-1} . The light amounts for detection set in the first modification are larger than the light amounts for detection set in the embodiment described above. In this manner, the detection device **1** according to the first modification can appropriately set the light amounts for detection in accordance with the state of the culture medium **102** and the like in the initial state.

(109) Second Modification

(110) FIG. **14** is an explanatory diagram for explaining the relations of the light-emitting elements lit up at the different light amounts with the sensor values of the photodiodes of the detection device according to a second modification of the embodiment. As illustrated in FIG. **14**, in the second modification, the sensor value S_{o-1} of the photodiodes **30** corresponding to the light-emitting element **82-(n-4)** and the sensor value S_{o-2} of the photodiodes **30** corresponding to the light-emitting element **82-(n-3)** are closest to the target sensor value S_{o-t} among the light-emitting elements **82**. The target sensor value S_{o-t} is a value between the sensor values S_{o-1} and S_{o-2} . The difference ΔS_{o-1} between the sensor value S_{o-1} and the target sensor value S_{o-t} is equal to the difference ΔS_{o-2} between the sensor value S_{o-2} and the target sensor value S_{o-t} .

(111) The light amount setting circuit **73** (refer to FIG. 2) selects the sensor value S_{o-1} (first sensor value) and the sensor value S_{o-2} (second sensor value) that are closest to the target sensor value S_{o-t} from among the sensor values S_o corresponding to the different light amounts. Then, in the case where the difference ΔS_{o-1} is equal to the difference ΔS_{o-2} , the light amount setting circuit **73** sets the light amounts for detection to the average value of the light amount of the light-emitting element **82-(n-4)** (first light amount) corresponding to the sensor value S_{o-1} and the light amount of the light-emitting element **82-(n-3)** (second light amount) corresponding to the sensor value S_{o-2} .

(112) In this manner, the detection device **1** according to the second modification may select the

two sensor values So-1 and So-2 that are closest to the target sensor value So-t, and set the light amounts for detection within a range from the first light amount corresponding to the sensor value So-1 to the second light amount corresponding to the sensor value So-2.

(113) Third Modification

(114) FIG. 15 is a plan view schematically illustrating a configuration example of the light-emitting elements of the detection device according to a third modification of the embodiment. As illustrated in FIG. 15, in a light source device 80A according to the third modification, the light-emitting elements 82 each include light-emitting elements 82-R, 82-G, and 82-B. The light-emitting element 82-R emits red light. The light-emitting element 82-G emits green light. The light-emitting element 82-B emits blue light. The light-emitting elements 82-R, 82-G, and 82-B are arranged so as to be lined up in this order. The arrangement of the light-emitting elements 82-R, 82-G, and 82-B is not limited to this arrangement, and can be changed as appropriate. The light-emitting elements 82 may have four or more colors.

(115) FIG. 16 is a timing waveform diagram for explaining an operation example of the detection device according to the third modification. As illustrated in FIG. 16, the detection device 1 executes the light amount setting mode described above in a light amount setting period T1. In a first period T11, the detection device 1 lights up the red light-emitting elements 82-R at different light amounts and sets the light amounts for detection of the red light-emitting elements 82-R based on the sensor values So corresponding to the red light and the target sensor value So-t. In the same way, in a second period T12, the detection device 1 lights up the green light-emitting elements 82-G at different light amounts and sets the light amounts for detection of the green light-emitting elements 82-G based on the sensor values So corresponding to the green light and the target sensor value So-t. In a third period T13, the detection device 1 lights up the blue light-emitting elements 82-B at different light amounts and sets the light amounts for detection of the blue light-emitting elements 82-B based on the sensor values So corresponding to the blue light and the target sensor value So-t.

(116) After the light amount setting period T1, the detection device 1 executes the detection mode described above in a detection period T2. In a fourth period T21, the detection device 1 lights up the red light-emitting elements 82-R at the set light amounts for detection, and the photodiodes 30 of the optical sensor 10 output sensor values So(R) corresponding to the light amounts for detection. The sensor values So(R) are sensor values corresponding to the red light.

(117) In the same way, in a fifth period T22, the detection device 1 lights up the green light-emitting elements 82-G at the set light amounts for detection, and the photodiodes 30 of the optical sensor 10 output sensor values So(G) corresponding to the light amounts for detection. The sensor values So(G) are sensor values corresponding to the green light. In a sixth period T23, the detection device 1 lights up the blue light-emitting elements 82-B at the set light amounts for detection, and the photodiodes 30 of the optical sensor 10 output sensor values So(B) corresponding to the light amounts for detection. The sensor values So(B) are sensor values corresponding to the blue light. The image generation circuit 76 (refer to FIG. 2) generates a color image based on the sensor values So(R), So(G), and So(B) from the photodiodes 30.

(118) Fourth Modification

(119) FIG. 17 is an explanatory view schematically illustrating the lighting pattern for adjusting the light amounts of the light-emitting elements of the detection device according to a fourth modification of the embodiment. With the lighting pattern for adjusting the light amounts illustrated in FIG. 10, the example has been described in which the light amounts of all the light-emitting elements 82 are made different. The lighting pattern for adjusting the light amounts is, however, not limited to this pattern, and can be changed as appropriate depending on the required detection accuracy, the resolution of the light amount, the number of the light-emitting elements 82, and the like.

(120) As illustrated in FIG. 17, in the fourth modification, the light source device 80 includes light-

emitting element groups **82G-1** and **82G-2** each including a plurality of the light-emitting elements **82**. In the light amount setting mode, the light source device **80** differentiates the light amounts of the light-emitting elements **82** in each of the light-emitting element groups **82G-1** and **82G-2**. The light-emitting element groups **82G-1** and **82G-2** are arranged adjacent to each other in the second direction Dy. Each of the light-emitting element groups **82G-1** and **82G-2** includes 18 light-emitting elements **82** in three rows and six columns.

(121) In the light-emitting element group **82G-1**, the light amount increases as the light-emitting element number increases from the light-emitting element **82-1** to the light-emitting element **82-18**. In the light-emitting element group **82G-2**, the light amount increases as the light-emitting element number increases from a light-emitting element **82-19** to the light-emitting element **82-n**.

(122) In the fourth modification, when the light amounts for detection are set, the difference in light amount between the adjacent light-emitting element numbers is larger than in FIG. **10**, but the light amounts for detection can be set for each of areas of the light-emitting element groups **82G-1** and **82G-2**.

(123) Fifth Modification

(124) FIG. **18** is an explanatory view schematically illustrating the lighting pattern for adjusting the light amounts of the light-emitting elements of the detection device according to a fifth modification of the embodiment. As illustrated in FIG. **18**, in the fifth modification, the light source device **80** includes light-emitting element groups **82G-1**, **82G-2**, **82G-3**, and **82G-4** each including a plurality of the light-emitting elements **82**. In the light amount setting mode, the light source device **80** differentiates the light amounts of the light-emitting elements **82** in each of the light-emitting element groups **82G-1**, **82G-2**, **82G-3**, and **82G-4**.

(125) The light-emitting element groups **82G-1** and **82G-2** are arranged adjacent to each other in the first direction Dx. The light-emitting element groups **82G-3** and **82G-4** are arranged adjacent to each other in the first direction Dx. The light-emitting element groups **82G-1** and **82G-3** are arranged adjacent to each other in the second direction Dy. The light-emitting element groups **82G-2** and **82G-4** are arranged adjacent to each other in the second direction Dy. Each of the light-emitting element groups **82G-1**, **82G-2**, **82G-3**, and **82G-4** includes 9 light-emitting elements **82** in three rows and three columns.

(126) In the fifth modification, the light amounts for detection can be set for each of areas of the light-emitting element groups **82G-1**, **82G-2**, **82G-3**, and **82G-4**.

(127) The number of the light-emitting element groups **82G** and the number of the light-emitting elements **82** included in each of the light-emitting element groups **82G** can be changed as appropriate. All the lighting patterns for adjusting the light amounts illustrated in FIGS. **10**, **17**, and **18** illustrate examples in which the light amount increases from the upper left toward the lower right. However, these examples are merely exemplary. The lighting pattern for adjusting the light amounts is not limited to these examples. In the lighting pattern for adjusting the light amounts, the pattern of different light amounts may be arranged in any way.

(128) While the preferred embodiment of the present disclosure has been described above, the present disclosure is not limited to the embodiment described above. The content disclosed in the embodiment is merely an example, and can be variously modified within the scope not departing from the gist of the present disclosure. Any modifications appropriately made within the scope not departing from the gist of the present disclosure also naturally belong to the technical scope of the present disclosure. At least one of various omissions, substitutions, and changes of the components can be made without departing from the gist of the embodiment and the modifications described above.

Claims

1. A detection device comprising: a planar detection device comprising a plurality of photodetection elements arranged in a planar configuration; a plurality of point light sources provided correspondingly to the photodetection elements; a light directivity control element disposed between the point light sources and the photodetection elements; and a detection circuit electrically coupled to the photodetection elements, wherein each of the point light sources corresponds to at least one of the photodetection elements, in a light amount setting mode: the point light sources are controlled to be lit up at different light amounts; the photodetection elements are configured to output a plurality of sensor values corresponding to the different light amounts; the sensor values that are detected are compared with a preset target sensor value; and light amounts for detection of the point light sources are set, in a detection mode: the point light sources are controlled to be lit up at the set light amounts for detection; and the photodetection elements are configured to output sensor values corresponding to the light amounts for detection, the light directivity control element, a light-transmitting placement substrate to place thereon a plurality of objects to be detected, and the point light sources are arranged sequentially on the planar detection device, in a vertical direction to the planar detection device, the light-transmitting placement substrate being in direct contact with the light directivity control element, and a distance between the light-transmitting placement substrate and the point light sources is greater than a distance between the light directivity control element and the light-transmitting placement substrate.
2. The detection device according to claim 1, wherein the photodetection elements are a plurality of photodiodes.
3. A detection device comprising: a planar detection device comprising a plurality of photodetection elements arranged in a planar configuration; a plurality of point light sources provided correspondingly to the photodetection elements; a light directivity control element disposed between the point light sources and the photodetection elements; and a detection circuit electrically coupled to the photodetection elements, a light amount setting circuit configured to set light amounts of the point light sources, wherein each of the point light sources corresponds to at least one of the photodetection elements, in a light amount setting mode: the point light sources are controlled to be lit up at different light amounts; the photodetection elements are configured to output a plurality of sensor values corresponding to the different light amounts; the sensor values that are detected are compared with a preset target sensor value; and light amounts for detection of the point light sources are set, in a detection mode: the point light sources are controlled to be lit up at the set light amounts for detection; and the photodetection elements are configured to output sensor values corresponding to the light amounts for detection, and the light amount setting circuit is configured to: select a first sensor value closest to the target sensor value from among the sensor values corresponding to the different light amount; and set the light amounts for detection of the point light sources to a light amount of the point light source corresponding to the first sensor value.
4. The detection device according to claim 3, wherein the light directivity control element, a light-transmitting placement substrate to place thereon a plurality of objects to be detected, and the point light sources are arranged sequentially on the planar detection device in a vertical direction to the planar detection device.
5. The detection device according to claim 3, wherein the photodetection elements are a plurality of photodiodes.
6. A detection device comprising: a planar detection device comprising a plurality of photodetection elements arranged in a planar configuration; a plurality of point light sources provided correspondingly to the photodetection elements; a light directivity control element disposed between the point light sources and the photodetection elements; and a detection circuit electrically coupled to the photodetection elements, a light amount setting circuit configured to set light amounts of the point light sources, wherein each of the point light sources corresponds to at

least one of the photodetection elements, in a light amount setting mode: the point light sources are controlled to be lit up at different light amounts; the photodetection elements are configured to output a plurality of sensor values corresponding to the different light amounts; the sensor values that are detected are compared with a preset target sensor value; and light amounts for detection of the point light sources are set, in a detection mode: the point light sources are controlled to be lit up at the set light amounts for detection; and the photodetection elements are configured to output sensor values corresponding to the light amounts for detection, and the light amount setting circuit is configured to: select a first sensor value and a second sensor value close to the target sensor value from among the sensor values corresponding to the different light amounts, the target sensor value being a value between the first sensor value and the second sensor value; and set, when a difference between the target sensor value and the first sensor value is equal to a difference between the target sensor value and the second sensor value, the light amounts for detection of the point light sources to an average value of a first light amount of the point light source corresponding to the first sensor value and a second light amount of the point light source corresponding to the second sensor value.

7. The detection device according to claim 6, wherein the photodetection elements are a plurality of photodiodes.

8. The detection device according to claim 6, wherein the light directivity control element, a light-transmitting placement substrate to place thereon a plurality of objects to be detected, and the point light sources are arranged sequentially on the planar detection device in a vertical direction to the planar detection device.

9. A detection device comprising: a planar detection device comprising a plurality of photodetection elements arranged in a planar configuration; a plurality of point light sources provided correspondingly to the photodetection elements; a light directivity control element disposed between the point light sources and the photodetection elements; and a detection circuit electrically coupled to the photodetection elements, wherein each of the point light sources corresponds to at least one of the photodetection elements, in a light amount setting mode: the point light sources are controlled to be lit up at different light amounts; the photodetection elements are configured to output a plurality of sensor values corresponding to the different light amounts; the sensor values that are detected are compared with a preset target sensor value; and light amounts for detection of the point light sources are set, in a detection mode: the point light sources are controlled to be lit up at the set light amounts for detection; and the photodetection elements are configured to output sensor values corresponding to the light amounts for detection, the detection circuit has a detection range in which the sensor values from the photodetection elements are detectable, and the target sensor value is set within a range from 90% to 100% with respect to an upper limit value of the detection range.

10. The detection device according to claim 9, wherein the photodetection elements are a plurality of photodiodes.

11. The detection device according to claim 9, wherein the light directivity control element, a light-transmitting placement substrate to place thereon a plurality of objects to be detected, and the point light sources are arranged sequentially on the planar detection device in a vertical direction to the planar detection device.

12. A detection device comprising: a planar detection device comprising a plurality of photodetection elements arranged in a planar configuration; a plurality of point light sources provided correspondingly to the photodetection elements; a light directivity control element disposed between the point light sources and the photodetection elements; and a detection circuit electrically coupled to the photodetection elements, wherein each of the point light sources corresponds to at least one of the photodetection elements, in a light amount setting mode: the point light sources are controlled to be lit up at different light amounts; the photodetection elements are configured to output a plurality of sensor values corresponding to the different light amounts; the

sensor values that are detected are compared with a preset target sensor value; and light amounts for detection of the point light sources are set, in a detection mode: the point light sources are controlled to be lit up at the set light amounts for detection; and the photodetection elements are configured to output sensor values corresponding to the light amounts for detection, the detection device further comprises a storage circuit to store therein the light amounts for detection set in the light amount setting mode, and the detection device is configured to: execute the light amount setting mode when the planar detection device starts measurement, and simultaneously light up the point light sources at the set light amounts for detection in the detection mode.

13. The detection device according to claim 12, wherein the photodetection elements are a plurality of photodiodes.

14. The detection device according to claim 12, wherein the light directivity control element, a light-transmitting placement substrate to place thereon a plurality of objects to be detected, and the point light sources are arranged sequentially on the planar detection device in a vertical direction to the planar detection device.
