

US Patent & Trademark Office

Patent Public Search | Text View

United States Patent	12401421
Kind Code	B2
Date of Patent	August 26, 2025
Inventor(s)	Xue; Yisheng et al.

Coaxial optical front end for optical wireless communication

Abstract

Methods, systems, and devices for wireless communications are described. A user equipment (UE) may receive, from a network entity via an optical wireless communication link, a first optical wireless signal using photodetectors positioned on a photodetector panel of the UE. The photodetector panel may include a hole around which the photodetectors are positioned and may be located a first distance from a curved optical device of the UE via which the first optical wireless signal is received. The UE may transmit, to the network entity via the optical wireless communication link, a second optical wireless signal using a light source of the UE that is located a second distance from the curved optical device via which the second optical wireless signal is transmitted. The second optical wireless signal may pass through the hole in the photodetector panel based on the second distance being greater than the first distance.

Inventors: Xue; Yisheng (San Diego, CA), Becze; Karoly (Escondido, CA), Zhang; Xiaoxia (San Diego, CA), Li; Junyi (Fairless Hills, PA), Soltani; Morteza (San Diego, CA), Sun; Jing (San Diego, CA), Liu; Sam (San Diego, CA)

Applicant: QUALCOMM Incorporated (San Diego, CA)

Family ID: 1000008781962

Assignee: QUALCOMM Incorporated (San Diego, CA)

Appl. No.: 18/339856

Filed: June 22, 2023

Prior Publication Data

Document Identifier	Publication Date
US 20240430007 A1	Dec. 26, 2024

Publication Classification

Int. Cl.: H04B10/112 (20130101); H04B10/40 (20130101)

U.S. Cl.:

CPC H04B10/112 (20130101); H04B10/40 (20130101);

Field of Classification Search

CPC: H04B (10/112); H04B (10/116); H04B (10/40)

USPC: 398/118

References Cited

U.S. PATENT DOCUMENTS

Patent No.	Issued Date	Patentee Name	U.S. Cl.	CPC
5465170	12/1994	Arimoto	N/A	N/A
2012/0248347	12/2011	Renna et al.	N/A	N/A
2017/0346556	12/2016	Tiecke	N/A	H04B 10/25
2018/0007247	12/2017	Aggarwal	N/A	H04B 10/116
2022/0140901	12/2021	Arulandu	398/118	H04B 10/11
2022/0345221	12/2021	Mitchell	N/A	H04B 10/1121

OTHER PUBLICATIONS

International Search Report and Written Opinion—PCT/US2024/029766—ISA/EPO—Sep. 12, 2024. cited by applicant

Primary Examiner: Singh; Dalzid E

Attorney, Agent or Firm: Holland & Hart LLP

Background/Summary

FIELD OF TECHNOLOGY

(1) The following relates to wireless communications, including a coaxial optical front end (OFE) for optical wireless communication (OWC).

BACKGROUND

(2) Wireless communications systems are widely deployed to provide various types of communication content such as voice, video, packet data, messaging, broadcast, and so on. These systems may be capable of supporting communication with multiple users by sharing the available system resources (e.g., time, frequency, and power). Examples of such multiple-access systems include fourth generation (4G) systems such as Long Term Evolution (LTE) systems, LTE-Advanced (LTE-A) systems, or LTE-A Pro systems, and fifth generation (5G) systems which may be referred to as New Radio (NR) systems. These systems may employ technologies such as code division multiple access (CDMA), time division multiple access (TDMA), frequency division multiple access (FDMA), orthogonal FDMA (OFDMA), or discrete Fourier transform spread orthogonal frequency division multiplexing (DFT-S-OFDM). A wireless multiple-access communications system may include one or more base stations, each supporting wireless

communication for communication devices, which may be known as user equipment (UE).

(3) In some examples, a UE may perform optical wireless communication (OWC) with a network entity.

SUMMARY

(4) The described techniques relate to improved methods, systems, devices, and apparatuses that support a coaxial optical front end (OFE) for optical wireless communications (OWC). For example, the described techniques provide for an OFE that includes one or more photodetectors and a light source positioned on a common axis. For example, the coaxial OFE may include an optical device (e.g., a lens or a mirror) operable to collimate and/or condense light, a photodetector panel on which the one or more photodetectors are positioned, and a light source. The light source may be located further from the optical device than the photodetector panel (e.g., behind the photodetector panel), and an optical wireless signal from the light source may be transmitted to the optical device via a hole in the photodetector panel to support uplink transmissions. As such, the coaxial OFE may support beam steering for both uplink and downlink transmissions. For example, a user equipment (UE) that implements the coaxial OFE may use beam steering to increase optical gain for optical wireless signals received or transmitted by the UE.

(5) A method for OWC by a UE is described. The method may include receiving, from a network entity via an OWC link, a first optical wireless signal using one or more photodetectors positioned on a photodetector panel of the UE, where the photodetector panel includes a hole around which the one or more photodetectors are positioned, and where the photodetector panel is located a first distance from a curved optical device of the UE via which the first optical wireless signal is received and transmitting, to the network entity via the OWC link, a second optical wireless signal using a light source of the UE that is located a second distance from the curved optical device via which the second optical wireless signal is transmitted, where the second optical wireless signal passes through the hole in the photodetector panel based on the second distance being greater than the first distance.

(6) A UE for OWC is described. The UE may include at least one processor, and at least one memory coupled with the at least one processor, with instructions stored in the at least one memory. The instructions may be executed by the at least one processor, individually or in any combination, to cause the UE to receive, from a network entity via an OWC link, a first optical wireless signal using one or more photodetectors positioned on a photodetector panel of the UE, where the photodetector panel includes a hole around which the one or more photodetectors are positioned, and where the photodetector panel is located a first distance from a curved optical device of the UE via which the first optical wireless signal is received and transmit, to the network entity via the OWC link, a second optical wireless signal using a light source of the UE that is located a second distance from the curved optical device via which the second optical wireless signal is transmitted, where the second optical wireless signal passes through the hole in the photodetector panel based on the second distance being greater than the first distance.

(7) Another UE for OWC is described. The UE may include means for receiving, from a network entity via an OWC link, a first optical wireless signal using one or more photodetectors positioned on a photodetector panel of the UE, where the photodetector panel includes a hole around which the one or more photodetectors are positioned, and where the photodetector panel is located a first distance from a curved optical device of the UE via which the first optical wireless signal is received and means for transmitting, to the network entity via the OWC link, a second optical wireless signal using a light source of the UE that is located a second distance from the curved optical device via which the second optical wireless signal is transmitted, where the second optical wireless signal passes through the hole in the photodetector panel based on the second distance being greater than the first distance.

(8) A non-transitory computer-readable medium storing code for OWC is described. The code may include instructions executable by at least one processor, individually or in any combination, to

receive, from a network entity via an OWC link, a first optical wireless signal using one or more photodetectors positioned on a photodetector panel of the UE, where the photodetector panel includes a hole around which the one or more photodetectors are positioned, and where the photodetector panel is located a first distance from a curved optical device of the UE via which the first optical wireless signal is received and transmit, to the network entity via the OWC link, a second optical wireless signal using a light source of the UE that is located a second distance from the curved optical device via which the second optical wireless signal is transmitted, where the second optical wireless signal passes through the hole in the photodetector panel based on the second distance being greater than the first distance.

(9) In some examples of the method. UEs, and non-transitory computer-readable medium described herein, transmitting the second optical wireless signal may include operations, features, means, or instructions for transmitting the second optical wireless signal via a first lens a third distance from the curved optical device and a second lens a fourth distance from the curved optical device, where the first lens collimates the second optical wireless signal from the light source to the second lens and the second lens condenses the second optical wireless signal through the hole of the photodetector panel.

(10) In some examples of the method, UEs, and non-transitory computer-readable medium described herein, the third distance may be less than the second distance and greater than the fourth distance, and the fourth distance may be greater than the first distance.

(11) In some examples of the method, UEs, and non-transitory computer-readable medium described herein, a fifth distance between the light source and the first lens corresponds to a focal length of the first lens.

(12) In some examples of the method, UEs, and non-transitory computer-readable medium described herein, a first ratio of focal length to aperture diameter of the first lens may be the same as a second ratio of focal length to aperture diameter of the curved optical device.

(13) In some examples of the method, UEs, and non-transitory computer-readable medium described herein, a first focal length of the first lens is the same as a second focal length of the second lens and less than a third focal length of the curved optical device.

(14) In some examples of the method, UEs, and non-transitory computer-readable medium described herein, receiving the first optical wireless signal may include operations, features, means, or instructions for receiving the first optical wireless signal using a set of multiple photodetectors of the one or more photodetectors and performing an equal gain combination operation on a set of multiple signals output by the set of multiple photodetectors.

(15) In some examples of the method, UEs, and non-transitory computer-readable medium described herein, the set of multiple photodetectors may be associated with a same radio frequency (RF) chain.

(16) In some examples of the method, UEs, and non-transitory computer-readable medium described herein, receiving the first optical wireless signal may include operations, features, means, or instructions for receiving the first optical wireless signal using a first subset of photodetectors of the one or more photodetectors and a second subset of photodetectors of the one or more photodetectors, performing a first equal gain combination operation on a first set of multiple signals output by the first subset of photodetectors, and performing a second equal gain combination operation on a second set of multiple signals output by the second subset of photodetectors.

(17) In some examples of the method, UEs, and non-transitory computer-readable medium described herein, the first subset of photodetectors may be associated with a first RF chain and the second subset of photodetectors may be associated with a second RF chain.

(18) In some examples of the method, UEs, and non-transitory computer-readable medium described herein, the first distance may be less than a focal length of the curved optical device.

(19) In some examples of the method, UEs, and non-transitory computer-readable medium

described herein, the one or more photodetectors includes a first set of photodetectors, the first set of photodetectors including two photodetectors aligned vertically with the hole and two photodetectors aligned horizontally with the hole.

(20) In some examples of the method, UEs, and non-transitory computer-readable medium described herein, the curved optical device may be a lens or a mirror.

(21) A UE for OWC is described. The UE may include a curved optical device, a photodetector panel located a first distance from the curved optical device and including one or more photodetectors and a hole around which the one or more photodetectors are positioned, a light source located a second distance from the curved optical device, at least one processor, and at least one memory coupled with the at least one processor, with instructions stored in the at least one memory. The instructions may be executed by the at least one processor, individually or in any combination, to cause the UE to establish an OWC link with a network entity and communicate, with the network entity via the OWC link, one or more optical wireless signals using at least one of the light source or the one or more photodetectors of the photodetector panel.

(22) In some examples of the UE, the instructions to communicate the one or more optical wireless signals are executable by the at least one processor, individually or in any combination, to cause the UE to transmit, using the light source, the one or more optical wireless signals through the hole of the photodetector panel via the curved optical device based on the second distance being greater than the first distance.

(23) In some examples of the UE, the UE may include a first lens a third distance from the curved optical device, where the third distance is less than the second distance and greater than the first distance, and a second lens a fourth distance from the curved optical device, where the fourth distance is greater than the first distance and less than the third distance.

(24) In some examples of the UE, the instructions to communicate the one or more optical wireless signals are executable by the at least one processor, individually or in any combination, to cause the UE to transmit, using the light source, the one or more optical wireless signals via the first lens, the second lens, and the curved optical device, where the first lens collimates the one or more optical wireless signals from the light source to the second lens and the second lens condenses the one or more optical wireless signals through the hole of the photodetector panel and to the curved optical device.

(25) In some examples of the UE, a fifth distance between the light source and the first lens corresponds to a focal length of the first lens.

(26) In some examples of the UE, the curved optical device, the photodetector panel, the first lens, the second lens, and the light source are aligned on a same axis.

(27) In some examples of the UE, a first ratio of focal length to aperture diameter of the first lens is the same as a second ratio of focal length to aperture diameter of the curved optical device.

(28) In some examples of the UE, a first focal length of the first lens is the same as a second focal length of the second lens and less than a third focal length of the curved optical device

(29) In some examples of the UE, a diameter of the curved optical device is greater than a diameter of the first lens and a diameter of the second lens.

(30) In some examples of the UE, the instructions to communicate the one or more optical wireless signals are executable by the at least one processor, individually or in any combination, to cause the UE to receive the one or more optical wireless signals using a set of multiple photodetectors of the one or more photodetectors and perform an equal gain combination operation on a set of multiple signals output by the set of multiple photodetectors.

(31) In some examples of the UE, the set of multiple photodetectors are associated with a same RF chain.

(32) In some examples of the UE, the instructions to communicate the one or more optical wireless signals are executable by the at least one processor, individually or in any combination, to cause the UE to receive the one or more optical wireless signals using a first subset of photodetectors of the

- one or more photodetectors and a second subset of photodetectors of the one or more photodetectors, perform a first equal gain combination operation on a first set of multiple signals output by the first subset of photodetectors, and perform a second equal gain combination operation on a second set of multiple signals output by the second subset of photodetectors.
- (33) In some examples of the UE, the first subset of photodetectors is associated with a first RF chain and the second subset of photodetectors is associated with a second RF chain.
- (34) In some examples of the UE, each photodetector of the first subset of photodetectors is a first size and each photodetector of the second subset of photodetectors is a second size, the second size being larger than the first size.
- (35) In some examples of the UE, the first distance is less than a focal length of the curved optical device.
- (36) In some examples of the UE, the one or more photodetectors comprises a first set of photodetectors positioned on the photodetector panel, the first set of photodetectors comprising two photodetectors aligned vertically with the hole and two photodetectors aligned horizontally with the hole.
- (37) In some examples of the UE, the curved optical device is a lens or a mirror.
-

Description

BRIEF DESCRIPTION OF THE DRAWINGS

- (1) FIG. 1 shows an example of a wireless communications system that supports a coaxial optical front end (OFE) for optical wireless communication (OWC) in accordance with one or more aspects of the present disclosure.
- (2) FIG. 2 shows an example of a wireless communications system that supports a coaxial OFE for OWC in accordance with one or more aspects of the present disclosure.
- (3) FIGS. 3 and 4 show examples of OFEs that support a coaxial OFE for OWC in accordance with one or more aspects of the present disclosure.
- (4) FIGS. 5A, 5B, 5C, and 5D show examples of photodetector panel configurations that support a coaxial OFE for OWC in accordance with one or more aspects of the present disclosure.
- (5) FIG. 6 shows an example of an OFE that supports a coaxial OFE for OWC in accordance with one or more aspects of the present disclosure.
- (6) FIG. 7 shows an example of a process flow that supports a coaxial OFE for OWC in accordance with one or more aspects of the present disclosure.
- (7) FIGS. 8 and 9 show block diagrams of devices that support a coaxial OFE for OWC in accordance with one or more aspects of the present disclosure.
- (8) FIG. 10 shows a block diagram of a communications manager that supports a coaxial OFE for OWC in accordance with one or more aspects of the present disclosure.
- (9) FIG. 11 shows a diagram of a system including a device that supports a coaxial OFE for OWC in accordance with one or more aspects of the present disclosure.
- (10) FIGS. 12 through 15 show flowcharts illustrating methods that support a coaxial OFE for OWC in accordance with one or more aspects of the present disclosure.

DETAILED DESCRIPTION

(11) Some wireless communications systems may support optical wireless communication (OWC). For instance, a first device, such as a user equipment (UE), may communicate with a second device, such as a network entity, via an OWC link. For example, the first device may transmit an optical wireless signal (e.g., a signal at a frequency within the range of 10.sup.13 to 10.sup.16 hertz (Hz), such as a signal in the infrared to ultraviolet spectrum) to the second device via a beam of light using a light source, and the second device may receive and measure the optical wireless signal using a photodetector, such as via a lens (e.g., a condenser lens), a mirror (e.g., a concave

mirror), or other curved optical device that focuses the optical signal towards (e.g., onto, near) the photodetector. A combination of one or more curved optical devices (such as lenses and/or mirrors) and one or more optical communication components (such as light sources and/or photodetectors) used to communicate an optical wireless signal may be referred to as an optical front end (OFE) of a device that supports OWC.

(12) In some examples, a UE may steer an uplink optical wireless signal via a lens that collimates a transmitted beam of light from a light source and may steer a downlink optical wireless signal via the lens that focuses (e.g., condenses) the downlink optical wireless signal towards a photodetector. An optimal position for both the light source and the photodetector relative to the lens in order to maximize optical gain may be the same, however, both the light source and photodetector cannot occupy the same space within the OFE. In some cases, the UE may use separate OFEs for uplink and downlink (e.g., positioning the OFEs in parallel) or may use a dichroic mirror that is used to reflect either signal from the light source or to the photodetector, such that the light source or the photodetector may be positioned off-axis relative to the lens. However, using separate OFEs or a dichroic mirror for uplink and downlink may be expensive to implement (e.g., due to the use of additional large lenses or the dichroic mirror) or may take up an excessive amount of space in a container of the OFE (e.g., lens tube).

(13) In accordance with examples described herein, a UE (e.g. or a network entity) may implement a coaxial OFE that supports beam steering for reception and transmission of optical wireless signals at the UE (or network entity). For example, the OFE may include a curved optical device (e.g., lens, mirror), a light source located a first distance from the curved optical device, and a photodetector panel located in between, and on a same axis with, the curved optical device and the light source. The photodetector panel may include one or more photodetectors and a central hole around which the one or more photodetectors are positioned. Accordingly, the UE may receive a downlink optical wireless signal via the curved optical device that directs (e.g., focuses, condenses) the downlink optical wireless signal toward the one or more photodetectors of the photodetector panel. The UE may transmit an uplink optical wireless signal using the light source, and the uplink wireless signal may pass through the hole in the photodetector panel to the curved optical device that collimates the uplink optical wireless signal for transmission. In some examples, the OFE may include a relay subsystem of lenses located between the light source and the photodetector panel. The subsystem of lenses may be used to collimate an optical wireless signal from the light source and subsequently condense the optical wireless signal toward the hole in the photodetector panel.

(14) By implementing the coaxial OFE, a UE (e.g., or a network entity) may support optical beam steering, increasing coverage of an OWC system, increasing a quality of OWC, and facilitating miniaturization of UEs that support OWC. For example, by positioning optical communication components on a same axis, the UE or the network entity may reduce a physical space that the OFE occupies while supporting both uplink and downlink beam steering. In some examples, the OFE may be contained in a lens tube, and the coaxial OFE may support reducing a size or a diameter of the lens tube, thus miniaturizing the UE and improving a form factor of the UE. In some examples, the coaxial OFE may enable a UE to perform beam steering in both the uplink and downlink transmission direction, and locations (e.g., distances) of optical communication components in the OFE relative to each other may be determined to increase (e.g., balance) optical gains for both receiving and transmitting optical wireless signals. Increasing optical gains associated with the optical wireless signals may support increased accuracy or efficiency of OWC between the UE and the network entity. In some implementations, the gain of a communicated optical wireless signal may increase as a result of the UE performing equal gain combination on the signal received via an array of photodetectors positioned on the photodetector panel. Such equal gain combination may support a reduced quantity of radio frequency (RF) chains used to support the photodetector panel (e.g., as compared to having a respective RF chain for each photodetector of the photodetector panel).

(15) Aspects of the disclosure are initially described in the context of wireless communications systems. Aspects of the disclosure are further described in the context of wireless communications systems, OFEs, photodetector panel configurations, and process flows. Aspects of the disclosure are further illustrated by and described with reference to apparatus diagrams, system diagrams, and flowcharts that relate to a coaxial OFE for OWC.

(16) FIG. 1 shows an example of a wireless communications system **100** that supports a coaxial OFE for OWC in accordance with one or more aspects of the present disclosure. The wireless communications system **100** may include one or more network entities **105**, one or more UEs **115**, and a core network **130**. In some examples, the wireless communications system **100** may be a Long Term Evolution (LTE) network, an LTE-Advanced (LTE-A) network, an LTE-A Pro network, a New Radio (NR) network, or a network operating in accordance with other systems and radio technologies, including future systems and radio technologies not explicitly mentioned herein.

(17) The network entities **105** may be dispersed throughout a geographic area to form the wireless communications system **100** and may include devices in different forms or having different capabilities. In various examples, a network entity **105** may be referred to as a network element, a mobility element, a radio access network (RAN) node, or network equipment, among other nomenclature. In some examples, network entities **105** and UEs **115** may wirelessly communicate via one or more communication links **125** (e.g., a radio frequency (RF) access link). For example, a network entity **105** may support a coverage area **110** (e.g., a geographic coverage area) over which the UEs **115** and the network entity **105** may establish one or more communication links **125**. The coverage area **110** may be an example of a geographic area over which a network entity **105** and a UE **115** may support the communication of signals according to one or more radio access technologies (RATs).

(18) The UEs **115** may be dispersed throughout a coverage area **110** of the wireless communications system **100**, and each UE **115** may be stationary, or mobile, or both at different times. The UEs **115** may be devices in different forms or having different capabilities. Some example UEs **115** are illustrated in FIG. 1. The UEs **115** described herein may be capable of supporting communications with various types of devices, such as other UEs **115** or network entities **105**, as shown in FIG. 1.

(19) As described herein, a node of the wireless communications system **100**, which may be referred to as a network node, or a wireless node, may be a network entity **105** (e.g., any network entity described herein), a UE **115** (e.g., any UE described herein), a network controller, an apparatus, a device, a computing system, one or more components, or another suitable processing entity configured to perform any of the techniques described herein. For example, a node may be a UE **115**. As another example, a node may be a network entity **105**. As another example, a first node may be configured to communicate with a second node or a third node. In one aspect of this example, the first node may be a UE **115**, the second node may be a network entity **105**, and the third node may be a UE **115**. In another aspect of this example, the first node may be a UE **115**, the second node may be a network entity **105**, and the third node may be a network entity **105**. In yet other aspects of this example, the first, second, and third nodes may be different relative to these examples. Similarly, reference to a UE **115**, network entity **105**, apparatus, device, computing system, or the like may include disclosure of the UE **115**, network entity **105**, apparatus, device, computing system, or the like being a node. For example, disclosure that a UE **115** is configured to receive information from a network entity **105** also discloses that a first node is configured to receive information from a second node.

(20) In some examples, network entities **105** may communicate with the core network **130**, or with one another, or both. For example, network entities **105** may communicate with the core network **130** via one or more backhaul communication links **120** (e.g., in accordance with an S1, N2, N3, or other interface protocol). In some examples, network entities **105** may communicate with one another via a backhaul communication link **120** (e.g., in accordance with an X2, Xn, or other

interface protocol) either directly (e.g., directly between network entities **105**) or indirectly (e.g., via a core network **130**). In some examples, network entities **105** may communicate with one another via a midhaul communication link **162** (e.g., in accordance with a midhaul interface protocol) or a fronthaul communication link **168** (e.g., in accordance with a fronthaul interface protocol), or any combination thereof. The backhaul communication links **120**, midhaul communication links **162**, or fronthaul communication links **168** may be or include one or more wired links (e.g., an electrical link, an optical fiber link), one or more wireless links (e.g., a radio link, a wireless optical link), among other examples or various combinations thereof. A UE **115** may communicate with the core network **130** via a communication link **155**.

(21) One or more of the network entities **105** described herein may include or may be referred to as a base station **140** (e.g., a base transceiver station, a radio base station, an NR base station, an access point, a radio transceiver, a NodeB, an eNodeB (eNB), a next-generation NodeB or a giga-NodeB (either of which may be referred to as a gNB), a 5G NB, a next-generation eNB (ng-eNB), a Home NodeB, a Home eNodeB, or other suitable terminology). In some examples, a network entity **105** (e.g., a base station **140**) may be implemented in an aggregated (e.g., monolithic, standalone) base station architecture, which may be configured to utilize a protocol stack that is physically or logically integrated within a single network entity **105** (e.g., a single RAN node, such as a base station **140**).

(22) In some examples, a network entity **105** may be implemented in a disaggregated architecture (e.g., a disaggregated base station architecture, a disaggregated RAN architecture), which may be configured to utilize a protocol stack that is physically or logically distributed among two or more network entities **105**, such as an integrated access backhaul (IAB) network, an open RAN (O-RAN) (e.g., a network configuration sponsored by the O-RAN Alliance), or a virtualized RAN (vRAN) (e.g., a cloud RAN (C-RAN)). For example, a network entity **105** may include one or more of a central unit (CU) **160**, a distributed unit (DU) **165**, a radio unit (RU) **170**, a RAN Intelligent Controller (RIC) **175** (e.g., a Near-Real Time RIC (Near-RT RIC), a Non-Real Time RIC (Non-RT RIC)), a Service Management and Orchestration (SMO) **180** system, or any combination thereof. An RU **170** may also be referred to as a radio head, a smart radio head, a remote radio head (RRH), a remote radio unit (RRU), or a transmission reception point (TRP). One or more components of the network entities **105** in a disaggregated RAN architecture may be co-located, or one or more components of the network entities **105** may be located in distributed locations (e.g., separate physical locations). In some examples, one or more network entities **105** of a disaggregated RAN architecture may be implemented as virtual units (e.g., a virtual CU (VCU), a virtual DU (VDU), a virtual RU (VRU)).

(23) The split of functionality between a CU **160**, a DU **165**, and an RU **170** is flexible and may support different functionalities depending on which functions (e.g., network layer functions, protocol layer functions, baseband functions, RF functions, and any combinations thereof) are performed at a CU **160**, a DU **165**, or an RU **170**. For example, a functional split of a protocol stack may be employed between a CU **160** and a DU **165** such that the CU **160** may support one or more layers of the protocol stack and the DU **165** may support one or more different layers of the protocol stack. In some examples, the CU **160** may host upper protocol layer (e.g., layer 3 (L3), layer 2 (L2)) functionality and signaling (e.g., Radio Resource Control (RRC), service data adaptation protocol (SDAP), Packet Data Convergence Protocol (PDCP)). The CU **160** may be connected to one or more DUs **165** or RUs **170**, and the one or more DUs **165** or RUs **170** may host lower protocol layers, such as layer 1 (L1) (e.g., physical (PHY) layer) or L2 (e.g., radio link control (RLC) layer, medium access control (MAC) layer) functionality and signaling, and may each be at least partially controlled by the CU **160**. Additionally, or alternatively, a functional split of the protocol stack may be employed between a DU **165** and an RU **170** such that the DU **165** may support one or more layers of the protocol stack and the RU **170** may support one or more different layers of the protocol stack. The DU **165** may support one or multiple different cells (e.g.,

via one or more RUs **170**). In some cases, a functional split between a CU **160** and a DU **165**, or between a DU **165** and an RU **170** may be within a protocol layer (e.g., some functions for a protocol layer may be performed by one of a CU **160**, a DU **165**, or an RU **170**, while other functions of the protocol layer are performed by a different one of the CU **160**, the DU **165**, or the RU **170**). A CU **160** may be functionally split further into CU control plane (CU-CP) and CU user plane (CU-UP) functions. A CU **160** may be connected to one or more DUs **165** via a midhaul communication link **162** (e.g., F1, F1-c, F1-u), and a DU **165** may be connected to one or more RUs **170** via a fronthaul communication link **168** (e.g., open fronthaul (FH) interface). In some examples, a midhaul communication link **162** or a fronthaul communication link **168** may be implemented in accordance with an interface (e.g., a channel) between layers of a protocol stack supported by respective network entities **105** that are in communication via such communication links.

(24) In wireless communications systems (e.g., wireless communications system **100**), infrastructure and spectral resources for radio access may support wireless backhaul link capabilities to supplement wired backhaul connections, providing an IAB network architecture (e.g., to a core network **130**). In some cases, in an IAB network, one or more network entities **105** (e.g., IAB nodes **104**) may be partially controlled by each other. One or more IAB nodes **104** may be referred to as a donor entity or an IAB donor. One or more DUs **165** or one or more RUs **170** may be partially controlled by one or more CUs **160** associated with a donor network entity **105** (e.g., a donor base station **140**). The one or more donor network entities **105** (e.g., IAB donors) may be in communication with one or more additional network entities **105** (e.g., IAB nodes **104**) via supported access and backhaul links (e.g., backhaul communication links **120**). IAB nodes **104** may include an IAB mobile termination (IAB-MT) controlled (e.g., scheduled) by DUs **165** of a coupled IAB donor. An IAB-MT may include an independent set of antennas for relay of communications with UEs **115**, or may share the same antennas (e.g., of an RU **170**) of an IAB node **104** used for access via the DU **165** of the IAB node **104** (e.g., referred to as virtual IAB-MT (vIAB-MT)). In some examples, the IAB nodes **104** may include DUs **165** that support communication links with additional entities (e.g., IAB nodes **104**, UEs **115**) within the relay chain or configuration of the access network (e.g., downstream). In such cases, one or more components of the disaggregated RAN architecture (e.g., one or more IAB nodes **104** or components of IAB nodes **104**) may be configured to operate according to the techniques described herein.

(25) In the case of the techniques described herein applied in the context of a disaggregated RAN architecture, one or more components of the disaggregated RAN architecture may be configured to support a coaxial OFE for OWC as described herein. For example, some operations described as being performed by a UE **115** or a network entity **105** (e.g., a base station **140**) may additionally, or alternatively, be performed by one or more components of the disaggregated RAN architecture (e.g., IAB nodes **104**, DUs **165**, CUs **160**, RUs **170**, RIC **175**, SMO **180**).

(26) A UE **115** may include or may be referred to as a mobile device, a wireless device, a remote device, a handheld device, or a subscriber device, or some other suitable terminology, where the “device” may also be referred to as a unit, a station, a terminal, or a client, among other examples. A UE **115** may also include or may be referred to as a personal electronic device such as a cellular phone, a personal digital assistant (PDA), a tablet computer, a laptop computer, or a personal computer. In some examples, a UE **115** may include or be referred to as a wireless local loop (WLL) station, an Internet of Things (IoT) device, an Internet of Everything (IoE) device, or a machine type communications (MTC) device, among other examples, which may be implemented in various objects such as appliances, or vehicles, meters, among other examples.

(27) The UEs **115** described herein may be able to communicate with various types of devices, such as other UEs **115** that may sometimes act as relays as well as the network entities **105** and the network equipment including macro eNBs or gNBs, small cell eNBs or gNBs, or relay base stations, among other examples, as shown in FIG. 1.

(28) The UEs **115** and the network entities **105** may wirelessly communicate with one another via one or more communication links **125** (e.g., an access link) using resources associated with one or more carriers. The term “carrier” may refer to a set of RF spectrum resources having a defined physical layer structure for supporting the communication links **125**. For example, a carrier used for a communication link **125** may include a portion of a RF spectrum band (e.g., a bandwidth part (BWP)) that is operated according to one or more physical layer channels for a given radio access technology (e.g., LTE, LTE-A, LTE-A Pro, NR). Each physical layer channel may carry acquisition signaling (e.g., synchronization signals, system information), control signaling that coordinates operation for the carrier, user data, or other signaling. The wireless communications system **100** may support communication with a UE **115** using carrier aggregation or multi-carrier operation. A UE **115** may be configured with multiple downlink component carriers and one or more uplink component carriers according to a carrier aggregation configuration. Carrier aggregation may be used with both frequency division duplexing (FDD) and time division duplexing (TDD) component carriers. Communication between a network entity **105** and other devices may refer to communication between the devices and any portion (e.g., entity, sub-entity) of a network entity **105**. For example, the terms “transmitting,” “receiving,” or “communicating,” when referring to a network entity **105**, may refer to any portion of a network entity **105** (e.g., a base station **140**, a CU **160**, a DU **165**, a RU **170**) of a RAN communicating with another device (e.g., directly or via one or more other network entities **105**).

(29) A carrier may be associated with a particular bandwidth of the RF spectrum and, in some examples, the carrier bandwidth may be referred to as a “system bandwidth” of the carrier or the wireless communications system **100**. For example, the carrier bandwidth may be one of a set of bandwidths for carriers of a particular radio access technology (e.g., 1.4, 3, 5, 10, 15, 20, 40, or 80 megahertz (MHz)). Devices of the wireless communications system **100** (e.g., the network entities **105**, the UEs **115**, or both) may have hardware configurations that support communications using a particular carrier bandwidth or may be configurable to support communications using one of a set of carrier bandwidths. In some examples, the wireless communications system **100** may include network entities **105** or UEs **115** that support concurrent communications using carriers associated with multiple carrier bandwidths. In some examples, each served UE **115** may be configured for operating using portions (e.g., a sub-band, a BWP) or all of a carrier bandwidth.

(30) Signal waveforms transmitted via a carrier may be made up of multiple subcarriers (e.g., using multi-carrier modulation (MCM) techniques such as orthogonal frequency division multiplexing (OFDM) or discrete Fourier transform spread OFDM (DFT-S-OFDM)). In a system employing MCM techniques, a resource element may refer to resources of one symbol period (e.g., a duration of one modulation symbol) and one subcarrier, in which case the symbol period and subcarrier spacing may be inversely related. The quantity of bits carried by each resource element may depend on the modulation scheme (e.g., the order of the modulation scheme, the coding rate of the modulation scheme, or both), such that a relatively higher quantity of resource elements (e.g., in a transmission duration) and a relatively higher order of a modulation scheme may correspond to a relatively higher rate of communication. A wireless communications resource may refer to a combination of an RF spectrum resource, a time resource, and a spatial resource (e.g., a spatial layer, a beam), and the use of multiple spatial resources may increase the data rate or data integrity for communications with a UE **115**.

(31) One or more numerologies for a carrier may be supported, and a numerology may include a subcarrier spacing (Δf) and a cyclic prefix. A carrier may be divided into one or more BWPs having the same or different numerologies. In some examples, a UE **115** may be configured with multiple BWPs. In some examples, a single BWP for a carrier may be active at a given time and communications for the UE **115** may be restricted to one or more active BWPs.

(32) The time intervals for the network entities **105** or the UEs **115** may be expressed in multiples of a basic time unit which may, for example, refer to a sampling period of

$T_{\text{sub}} = 1/(\Delta f_{\text{sub}} \cdot N_{\text{sub}} \cdot N_{\text{f}})$ seconds, for which Δf_{sub} may represent a supported subcarrier spacing, and $N_{\text{sub}} \cdot N_{\text{f}}$ may represent a supported discrete Fourier transform (DFT) size. Time intervals of a communications resource may be organized according to radio frames each having a specified duration (e.g., 10 milliseconds (ms)). Each radio frame may be identified by a system frame number (SFN) (e.g., ranging from 0 to 1023).

(33) Each frame may include multiple consecutively-numbered subframes or slots, and each subframe or slot may have the same duration. In some examples, a frame may be divided (e.g., in the time domain) into subframes, and each subframe may be further divided into a quantity of slots. Alternatively, each frame may include a variable quantity of slots, and the quantity of slots may depend on subcarrier spacing. Each slot may include a quantity of symbol periods (e.g., depending on the length of the cyclic prefix prepended to each symbol period). In some wireless communications systems **100**, a slot may further be divided into multiple mini-slots associated with one or more symbols. Excluding the cyclic prefix, each symbol period may be associated with one or more (e.g., $N_{\text{sub}} \cdot N_{\text{f}}$) sampling periods. The duration of a symbol period may depend on the subcarrier spacing or frequency band of operation.

(34) A subframe, a slot, a mini-slot, or a symbol may be the smallest scheduling unit (e.g., in the time domain) of the wireless communications system **100** and may be referred to as a transmission time interval (TTI). In some examples, the TTI duration (e.g., a quantity of symbol periods in a TTI) may be variable. Additionally, or alternatively, the smallest scheduling unit of the wireless communications system **100** may be dynamically selected (e.g., in bursts of shortened TTIs (sTTIs)).

(35) Physical channels may be multiplexed for communication using a carrier according to various techniques. A physical control channel and a physical data channel may be multiplexed for signaling via a downlink carrier, for example, using one or more of time division multiplexing (TDM) techniques, frequency division multiplexing (FDM) techniques, or hybrid TDM-FDM techniques. A control region (e.g., a control resource set (CORESET)) for a physical control channel may be defined by a set of symbol periods and may extend across the system bandwidth or a subset of the system bandwidth of the carrier. One or more control regions (e.g., CORESETs) may be configured for a set of the UEs **115**. For example, one or more of the UEs **115** may monitor or search control regions for control information according to one or more search space sets, and each search space set may include one or multiple control channel candidates in one or more aggregation levels arranged in a cascaded manner. An aggregation level for a control channel candidate may refer to an amount of control channel resources (e.g., control channel elements (CCEs)) associated with encoded information for a control information format having a given payload size. Search space sets may include common search space sets configured for sending control information to multiple UEs **115** and UE-specific search space sets for sending control information to a specific UE **115**.

(36) In some examples, a network entity **105** (e.g., a base station **140**, an RU **170**) may be movable and therefore provide communication coverage for a moving coverage area **110**. In some examples, different coverage areas **110** associated with different technologies may overlap, but the different coverage areas **110** may be supported by the same network entity **105**. In some other examples, the overlapping coverage areas **110** associated with different technologies may be supported by different network entities **105**. The wireless communications system **100** may include, for example, a heterogeneous network in which different types of the network entities **105** provide coverage for various coverage areas **110** using the same or different radio access technologies.

(37) Some UEs **115**, such as MTC or IoT devices, may be low cost or low complexity devices and may provide for automated communication between machines (e.g., via Machine-to-Machine (M2M) communication). M2M communication or MTC may refer to data communication technologies that allow devices to communicate with one another or a network entity **105** (e.g., a base station **140**) without human intervention. In some examples, M2M communication or MTC

may include communications from devices that integrate sensors or meters to measure or capture information and relay such information to a central server or application program that uses the information or presents the information to humans interacting with the application program. Some UEs **115** may be designed to collect information or enable automated behavior of machines or other devices. Examples of applications for MTC devices include smart metering, inventory monitoring, water level monitoring, equipment monitoring, healthcare monitoring, wildlife monitoring, weather and geological event monitoring, fleet management and tracking, remote security sensing, physical access control, and transaction-based business charging.

(38) The wireless communications system **100** may be configured to support ultra-reliable communications or low-latency communications, or various combinations thereof. For example, the wireless communications system **100** may be configured to support ultra-reliable low-latency communications (URLLC). The UEs **115** may be designed to support ultra-reliable, low-latency, or critical functions. Ultra-reliable communications may include private communication or group communication and may be supported by one or more services such as push-to-talk, video, or data. Support for ultra-reliable, low-latency functions may include prioritization of services, and such services may be used for public safety or general commercial applications. The terms ultra-reliable, low-latency, and ultra-reliable low-latency may be used interchangeably herein.

(39) In some examples, a UE **115** may be configured to support communicating directly with other UEs **115** via a device-to-device (D2D) communication link **135** (e.g., in accordance with a peer-to-peer (P2P), D2D, or sidelink protocol). In some examples, one or more UEs **115** of a group that are performing D2D communications may be within the coverage area **110** of a network entity **105** (e.g., a base station **140**, an RU **170**), which may support aspects of such D2D communications being configured by (e.g., scheduled by) the network entity **105**. In some examples, one or more UEs **115** of such a group may be outside the coverage area **110** of a network entity **105** or may be otherwise unable to or not configured to receive transmissions from a network entity **105**. In some examples, groups of the UEs **115** communicating via D2D communications may support a one-to-many (1:M) system in which each UE **115** transmits to each of the other UEs **115** in the group. In some examples, a network entity **105** may facilitate the scheduling of resources for D2D communications. In some other examples, D2D communications may be carried out between the UEs **115** without an involvement of a network entity **105**.

(40) The core network **130** may provide user authentication, access authorization, tracking, Internet Protocol (IP) connectivity, and other access, routing, or mobility functions. The core network **130** may be an evolved packet core (EPC) or 5G core (5GC), which may include at least one control plane entity that manages access and mobility (e.g., a mobility management entity (MME), an access and mobility management function (AMF)) and at least one user plane entity that routes packets or interconnects to external networks (e.g., a serving gateway (S-GW), a Packet Data Network (PDN) gateway (P-GW), or a user plane function (UPF)). The control plane entity may manage non-access stratum (NAS) functions such as mobility, authentication, and bearer management for the UEs **115** served by the network entities **105** (e.g., base stations **140**) associated with the core network **130**. User IP packets may be transferred through the user plane entity, which may provide IP address allocation as well as other functions. The user plane entity may be connected to IP services **150** for one or more network operators. The IP services **150** may include access to the Internet, Intranet(s), an IP Multimedia Subsystem (IMS), or a Packet-Switched Streaming Service.

(41) The wireless communications system **100** may operate using one or more frequency bands, which may be in the range of 300 megahertz (MHz) to 300 gigahertz (GHz). Generally, the region from 300 MHz to 3 GHz is known as the ultra-high frequency (UHF) region or decimeter band because the wavelengths range from approximately one decimeter to one meter in length. UHF waves may be blocked or redirected by buildings and environmental features, which may be referred to as clusters, but the waves may penetrate structures sufficiently for a macro cell to

provide service to the UEs **115** located indoors. Communications using UHF waves may be associated with smaller antennas and shorter ranges (e.g., less than 100 kilometers) compared to communications using the smaller frequencies and longer waves of the high frequency (HF) or very high frequency (VHF) portion of the spectrum below 300 MHz.

(42) The wireless communications system **100** may also operate using a super high frequency (SHF) region, which may be in the range of 3 GHz to 30 GHz, also known as the centimeter band, or using an extremely high frequency (EHF) region of the spectrum (e.g., from 30 GHz to 300 GHz), also known as the millimeter band. In some examples, the wireless communications system **100** may support millimeter wave (mmW) communications between the UEs **115** and the network entities **105** (e.g., base stations **140**, RUs **170**), and EHF antennas of the respective devices may be smaller and more closely spaced than UHF antennas. In some examples, such techniques may facilitate using antenna arrays within a device. The propagation of EHF transmissions, however, may be subject to even greater attenuation and shorter range than SHF or UHF transmissions. The techniques disclosed herein may be employed across transmissions that use one or more different frequency regions, and designated use of bands across these frequency regions may differ by country or regulating body.

(43) The wireless communications system **100** may utilize both licensed and unlicensed RF spectrum bands. For example, the wireless communications system **100** may employ License Assisted Access (LAA), LTE-Unlicensed (LTE-U) radio access technology, or NR technology using an unlicensed band such as the 5 GHz industrial, scientific, and medical (ISM) band. While operating using unlicensed RF spectrum bands, devices such as the network entities **105** and the UEs **115** may employ carrier sensing for collision detection and avoidance. In some examples, operations using unlicensed bands may be based on a carrier aggregation configuration in conjunction with component carriers operating using a licensed band (e.g., LAA). Operations using unlicensed spectrum may include downlink transmissions, uplink transmissions, P2P transmissions, or D2D transmissions, among other examples.

(44) A network entity **105** (e.g., a base station **140**, an RU **170**) or a UE **115** may be equipped with multiple antennas, which may be used to employ techniques such as transmit diversity, receive diversity, multiple-input multiple-output (MIMO) communications, or beamforming. The antennas of a network entity **105** or a UE **115** may be located within one or more antenna arrays or antenna panels, which may support MIMO operations or transmit or receive beamforming. For example, one or more base station antennas or antenna arrays may be co-located at an antenna assembly, such as an antenna tower. In some examples, antennas or antenna arrays associated with a network entity **105** may be located at diverse geographic locations. A network entity **105** may include an antenna array with a set of rows and columns of antenna ports that the network entity **105** may use to support beamforming of communications with a UE **115**. Likewise, a UE **115** may include one or more antenna arrays that may support various MIMO or beamforming operations. Additionally, or alternatively, an antenna panel may support RF beamforming for a signal transmitted via an antenna port.

(45) Beamforming, which may also be referred to as spatial filtering, directional transmission, or directional reception, is a signal processing technique that may be used at a transmitting device or a receiving device (e.g., a network entity **105**, a UE **115**) to shape (e.g., steer) an antenna beam (e.g., a transmit beam, a receive beam) along a spatial path between the transmitting device and the receiving device. Beamforming may be achieved by combining the signals communicated via antenna elements of an antenna array such that some signals propagating along particular orientations with respect to an antenna array experience constructive interference while others experience destructive interference. The adjustment of signals communicated via the antenna elements may include a transmitting device or a receiving device applying amplitude offsets, phase offsets, or both to signals carried via the antenna elements associated with the device. The adjustments associated with each of the antenna elements may be defined by a beamforming weight

set associated with a particular orientation (e.g., with respect to the antenna array of the transmitting device or receiving device, or with respect to some other orientation).

(46) A network entity **105** or a UE **115** may use beam sweeping techniques as part of beamforming operations. For example, a network entity **105** (e.g., a base station **140**, an RU **170**) may use multiple antennas or antenna arrays (e.g., antenna panels) to conduct beamforming operations for directional communications with a UE **115**. Some signals (e.g., synchronization signals, reference signals, beam selection signals, or other control signals) may be transmitted by a network entity **105** multiple times along different directions. For example, the network entity **105** may transmit a signal according to different beamforming weight sets associated with different directions of transmission. Transmissions along different beam directions may be used to identify (e.g., by a transmitting device, such as a network entity **105**, or by a receiving device, such as a UE **115**) a beam direction for later transmission or reception by the network entity **105**.

(47) Some signals, such as data signals associated with a particular receiving device, may be transmitted by transmitting device (e.g., a transmitting network entity **105**, a transmitting UE **115**) along a single beam direction (e.g., a direction associated with the receiving device, such as a receiving network entity **105** or a receiving UE **115**). In some examples, the beam direction associated with transmissions along a single beam direction may be determined based on a signal that was transmitted along one or more beam directions. For example, a UE **115** may receive one or more of the signals transmitted by the network entity **105** along different directions and may report to the network entity **105** an indication of the signal that the UE **115** received with a highest signal quality or an otherwise acceptable signal quality.

(48) In some examples, transmissions by a device (e.g., by a network entity **105** or a UE **115**) may be performed using multiple beam directions, and the device may use a combination of digital precoding or beamforming to generate a combined beam for transmission (e.g., from a network entity **105** to a UE **115**). The UE **115** may report feedback that indicates precoding weights for one or more beam directions, and the feedback may correspond to a configured set of beams across a system bandwidth or one or more sub-bands. The network entity **105** may transmit a reference signal (e.g., a cell-specific reference signal (CRS), a channel state information reference signal (CSI-RS)), which may be precoded or unprecoded. The UE **115** may provide feedback for beam selection, which may be a precoding matrix indicator (PMI) or codebook-based feedback (e.g., a multi-panel type codebook, a linear combination type codebook, a port selection type codebook). Although these techniques are described with reference to signals transmitted along one or more directions by a network entity **105** (e.g., a base station **140**, an RU **170**), a UE **115** may employ similar techniques for transmitting signals multiple times along different directions (e.g., for identifying a beam direction for subsequent transmission or reception by the UE **115**) or for transmitting a signal along a single direction (e.g., for transmitting data to a receiving device).

(49) A receiving device (e.g., a UE **115**) may perform reception operations in accordance with multiple receive configurations (e.g., directional listening) when receiving various signals from a transmitting device (e.g., a network entity **105**), such as synchronization signals, reference signals, beam selection signals, or other control signals. For example, a receiving device may perform reception in accordance with multiple receive directions by receiving via different antenna subarrays, by processing received signals according to different antenna subarrays, by receiving according to different receive beamforming weight sets (e.g., different directional listening weight sets) applied to signals received at multiple antenna elements of an antenna array, or by processing received signals according to different receive beamforming weight sets applied to signals received at multiple antenna elements of an antenna array, any of which may be referred to as “listening” according to different receive configurations or receive directions. In some examples, a receiving device may use a single receive configuration to receive along a single beam direction (e.g., when receiving a data signal). The single receive configuration may be aligned along a beam direction determined based on listening according to different receive configuration directions (e.g., a beam

direction determined to have a highest signal strength, highest signal-to-noise ratio (SNR), or otherwise acceptable signal quality based on listening according to multiple beam directions).

(50) In some wireless communications systems, a UE **115** may communicate with a network entity **105** via an optical wireless communication link. For example, the network entity **105** may communicate an optical wireless signal with the UE **115** via a beam of light, which may be received and measured using optical components of the UE **115** or network entity **105**. Optical components of the UE **115** or network entity **105** may be used to transmit or receive an optical wireless signal. Optical components may include, for example, one or more lenses (e.g., condenser lenses) or mirrors (e.g., concave mirrors, reflectors) that may focus the optical wireless signal towards one or more photodetectors. Additionally, or alternatively, the optical components may include one or more light sources and one or more lenses (such as same or different lenses) or mirrors that may collimate optical wireless signals emitted (for example, output) by the one or more light sources. A combination of optical components (e.g., a combination of one or more lenses, one or more mirrors, one or more photodetectors, one or more light sources) may be referred to as an OFE of the UE **115** or network entity **105**.

(51) In accordance with examples described herein, a UE **115** may support communicating optical wireless signals with a network entity **105** using a coaxial OFE. For example, a UE **115** may receive, from a network entity **105** via an optical wireless communication link, a first optical wireless signal using one or more photodetectors positioned on a photodetector panel of the UE **115**. The photodetector panel may include a hole around which the one or more photodetectors are positioned and may be located a first distance from a curved optical device (such as a lens or a mirror) of the UE **115** via which the first optical wireless signal is received. The UE **115** may transmit, to the network entity **105** via the optical wireless communication link, a second optical wireless signal using a light source of the UE **115** that is located a second distance from the curved optical device via which the second optical wireless signal is transmitted. The second optical wireless signal may pass through the hole in the photodetector panel based on the second distance being greater than the first distance. The OFE may include the curved optical device, the photodetector panel, and the light source, which may each be located along a same axis, and may thus be referred to as a coaxial OFE.

(52) FIG. 2 shows an example of a wireless communications system **200** that supports a coaxial OFE for OWC in accordance with one or more aspects of the present disclosure. In some examples, aspects of the wireless communications system **200** may implement or be implemented by aspects of the wireless communications system **100**. For example, the wireless communications system **200** may include a UE **115-a** and a network entity **105-a**, which may be examples of the corresponding devices as described herein, including with reference to FIG. 1.

(53) In some wireless communication systems, a UE **115-a** and a network entity **105-a** may communicate information via an optical RF band. For example, the UE **115-a** and the network entity **105-a** may communicate information in a frequency band of (approximately) 10.sup.13 to 10.sup.16 Hz, such as in the infrared to ultraviolet spectrum. Communications in this frequency band may be referred to as optical communications.

(54) In some examples, the UE **115-a** and the network entity **105-a** may support OWC. For example, the UE **115-a** and the network entity **105-a** may transmit optical wireless signals **210**, such as beams of light, via an optical wireless communication link **205**. The optical wireless communication link **205** may be an example of a communication link **125** via which optical wireless signals **210** may be communicated. In some examples, the network entity **105-a** and the UE **115-a** may communicate using optical beams **215** of varying widths. For example, the network entity **105-a** and the UE **115-a** may communicate using relatively wider beams, such as an optical beam **215-a** and an optical beam **215-b**, respectively. In some cases, the network entity **105-a** and the UE **115-a** may communicate using relatively narrower optical beams **215**, such as an optical beam **215-c** and an optical beam **215-d**, respectively.

(55) In some optical wireless communication systems, the network entity **105-a** may transmit an optical wireless signal **210** to the UE **115-a** by amplifying the optical wireless signal **210** using a power amplifier, emitting the optical wireless signal **210** using a light source **225**, such as a laser light source, and forming an optical beam **215** using a lens (e.g., a condenser lens, a collimating lens), such as a lens **230**, or a mirror. In some cases, the UE **115-a** may receive the optical wireless signal **210** by condensing the optical wireless signal **210** onto a photodetector **220** using a lens **230-a**. The photodetector **220** and the lens **230-a** (e.g., or mirror) may be components of a receive OFE of the UE **115-a**. The photodetector **220** may include an array of silicon photomultipliers (SiPM) which may increase a gain of the received optical wireless signal **210**.

(56) In some examples, the UE **115-a** may similarly transmit the optical wireless signal **210** and the network entity **105-a** may similarly receive the optical wireless signal **210**. For example, the UE **115-a** may transmit an optical wireless signal **210** to the network entity **105-a** by amplifying the optical wireless signal **210** using a power amplifier, emitting the optical wireless signal **210** using a light source **225**, and forming an optical beam **215** using a lens, such as a lens **230-b**, or a mirror (e.g., a reflector). The power amplifier, the light source **225**, and the lens **230-b** (e.g., or mirror) may be components of a transmit OFE of the UE **115-a**. The network entity **105-a** may receive the optical wireless signal **210** at an OFE (e.g., a receive OFE) of the network entity **105-a**, which may be similar to the receive OFE of the UE **115-a**.

(57) In some examples, a lens **230** may be an aspheric lens. A lens may include one or more convex lenses oriented together such that a boresight ray **235** entering a curved surface of the lens **230** may exit a flat surface of the lens **230** and focus to the photodetector **220**. Additionally, an off-axis ray **240** entering the flat surface of a lens **230** may exit the curved surface of the lens **230** and collimate to in a boresight direction of the lens **230**. In some examples, such focusing of a boresight ray **235** to a photodetector **220** and collimating an off-axis ray **240** from a light source **225** may be based on the photodetector **220** and the light source **225** being positioned at focal points of the respective lenses **230**.

(58) The process of condensing an optical wireless signal **210** (e.g., using the lens **230-a** or a mirror) may be referred to as receive beam steering. The receive beam steering gain of the optical wireless signal **210** (e.g., received in the boresight direction) detected by the photodetector **220** may be described by $10 \cdot \log_{10} A_{\text{sub.1}} / A_{\text{sub.2}}$, in which $A_{\text{sub.1}}$ is the area of the lens **230-a** and $A_{\text{sub.2}}$ is the area (e.g., sensitivity area) of the photodetector **220**. In some examples, the UE **115-a** may obtain a maximum optical gain for reception of the optical wireless signal **210** by placing the photodetector **220** at, or close to, the focal length **250** (e.g., focal distance) of the lens **230-a**.

(59) The UE **115-a** may perform transmit beam steering using a transmit OFE. In some cases, the UE **115-a** may have a transmit power less than that of the network entity **105-a** (e.g., by approximately 7 to 10 dB), and, in some cases, the network entity **105-a** receiving uplink optical wireless signals **210** from the UE **115-a** may not use mechanical beam steering techniques if serving multiple UEs **115**. In some examples, the UE **115-a** may obtain a maximum optical gain for transmission of the optical wireless signal **210** by placing the light source **225** at, or close to, the focal length **250** of the lens **230-b**, which the UE **115-a** may use as a collimating lens for transmit beams.

(60) In some examples, due to the UE **115-a** performing receive beam steering and transmit beam steering to maximize gain for receive and transmit beams, respectively, the receive OFE of the UE **115-a** and the transmit OFE of the UE **115-a** may compete for the same space. For example, the placement of the lens **230** relative to the light source **225** or relative to the photodetector **220** to support maximum optical gain may be the same, or approximately the same, for both the receive OFE and the transmit OFE. For instance, the placement of the photodetector **220** and of the light source **225** may both be at a focal length **250** of the lens **230** to produce the maximum optical gain for both reception and transmission of optical wireless signals **210**. However, the light source **225**

and the photodetector **220** may be independent physical components that cannot occupy the same physical space (e.g., of a lens tube that contains the OFE) at the focal length **250** of the lens **230**. (61) In some examples, rather than using a single lens **230** as part of a single OFE for both uplink and downlink communications, the UE **115-a** may use a receive OFE and a transmit OFE that are independent from each other. For example, the UE **115-a** may use a lens **230-a** for the receive OFE and a lens **230-b** for the transmit OFE, and the UE **115-a** may position the receive OFE and the transmit OFE in parallel (e.g., side-by-side, on different axes) based on the receive beams and the transmit beams having the same, or approximately the same, optical path for receive beam steering and transmit beam steering. However, putting the multiple lenses **230** in parallel may increase a size of an OFE (e.g., a lens tube) that contains the multiple lenses **230** (e.g., the transmit OFE and the receive OFE). For example, a diameter of the lens tube (e.g., a minimum diameter) may be limited by the parallel placement of the receive OFE and the transmit OFE.

(62) In some cases, the UE **115-a** may use a dichroic mirror and may use the same lens **230** for beam steering of both transmit beams and receive beams. Transmit and receive beams may be communicated via different wavelengths, and the dichroic mirror may reflect some wavelengths while transmitting other wavelengths. For example, the UE **115-a** may use the dichroic mirror to reflect wavelengths associated with transmit beams, while wavelengths associated with receive beams may pass through the dichroic mirror. However, the dichroic mirror may be expensive to manufacture or implement, and/or the use of the dichroic mirror for beam steering may depend on a relatively greater quantity of lenses at the UE **115-a** used in conjunction with the dichroic mirror. Further, placement of a light source **225** or photodetector **220** off-axis relative to a lens **230** and dichroic mirror in order to implement the dichroic mirror may increase a size of an OFE containing such components.

(63) In accordance with examples described herein, the UE **115-a** may implement a coaxial OFE to perform beam steering for both receive and transmit beams. For example, the UE **115-a** may position the light source **225** a distance away from a lens **230** and may position a photodetector panel in between, and on the same axis as, the lens **230** and the light source **225**. The photodetector panel may include one or more photodetectors **220**, for receiving optical wireless signals **210**, and a hole around which the one or more photodetectors **220** are positioned, through which the UE **115-a** transmits optical wireless signals **210** to the network entity **105-a** via the lens **230**.

(64) FIG. 3 shows an example of an OFE **300** that supports a coaxial OFE for OWC in accordance with one or more aspects of the present disclosure. In some examples, aspects of the OFE **300** may implement or be implemented by aspects of the wireless communications system **100** and/or the wireless communications system **200**. For example, the OFE **300** may be included in or implemented by a UE **115** and/or a network entity **105**, which may be examples of the corresponding devices as described herein, including with reference to FIGS. 1 and 2.

(65) The OFE **300** may include a photodetector panel **315** that includes a hole **325** and one or more photodetectors **320** (e.g., an array of photodetectors **320**). In some cases, the photodetector panel may be a printed circuit board (PCB) for receiving optical wireless signals (e.g., a receive PCB). In some examples, other circuitry may be included on the photodetector panel **315** to support reception of an optical wireless signal. In some examples, the hole **325** may be centrally located at the photodetector panel **315**, and the one or more photodetectors **320** may be positioned around the central hole **325**. In some examples, the hole **325** may be located elsewhere on the photodetector panel **315**. A UE **115** or a network entity **105** may use the one or more photodetectors **320** to receive optical wireless signals. The photodetector panel may be positioned a distance **330** (e.g., d.sub.RX) from a lens **310** of the OFE **300**, and the distance **330** may be determined to collect a maximum amount of power from received optical wireless signals (e.g., downlink optical wireless signals) in accordance with, for example, a focal length of the lens **310**, a configuration of the one or more photodetectors **320**, a size of the hole **325**, a position of a light source **305** of the OFE **300** within the OFE **300**, transmission characteristics associated with the light source **305** (e.g.,

directivity, power, frequency), among other factors.

(66) For example, the photodetector panel **315** may be positioned close to a focal point of the lens **310**. In some examples, the distance **330** may be less than the focal length of the lens **310** which may allow optical wireless signals to be received at the photodetectors **320** of the photodetector panel **315** rather than at the center of the photodetector panel **315**, where the hole **325** is positioned. The distance **330** may also be determined to reduce blockage of optical wireless signals (e.g., uplink optical wireless signals) that are transmitted by the light source **305**.

(67) The hole **325** of the photodetector panel **315** may enable the UE **115** to transmit uplink optical wireless signals from a light source **305** through the hole **325** to the lens **310**. The hole **325** may be various sizes, and in some cases may have a diameter of 0.1 mm, 1 mm, or 3 mm, among other diameters. Additionally, the hole **325** may have various shapes. For example, in the example of FIG. 3, the hole **325** is depicted as having a circular shape, however, other shapes (e.g., square, rectangular, diamond, oval, and the like) are possible. In some examples, the light source **305** may be positioned a distance **335** (e.g., d.sub.TX) from the lens **310**, and the distance **335** may be determined to achieve a maximum transmit optical gain (e.g., in view of a constraint that the light source **305** may not be positioned at the focal point of the lens **310**). For example, the light source **305** may be positioned at the distance **335** such that an image of the light source **305** (e.g., an image of a transmitted optical wireless signal) is at or close to the focal point of the lens **310** (e.g., as close to the focal point of the lens **310** as possible in view of the constraint that the light source **305** is not positioned at the focal point of the lens **310**). The hole **325** may be positioned such that the image of the light source **305** may pass through the hole **325** and to the lens **310** for transmission.

(68) In the example of FIG. 3, the photodetector panel **315** may include four photodetectors **320**: a photodetector **320-a**, a photodetector **320-b**, a photodetector **320-c**, and a photodetector **320-d**. In some examples, one or more of the photodetectors **320** may be an SiPM. In some examples, one or more of the photodetectors **320** may have a size of 1 mm by 1 mm. Various configurations of photodetectors **320** on the photodetector panel **315** are possible, for example, as described with reference to FIGS. 5A through 5D.

(69) A size of the hole **325** may balance various considerations. For example, optical wireless signals received at the photodetector panel **315** may undergo higher loss due at greater sizes of the hole **325** (e.g., if the hole **325** has a diameter of 3 mm). However, blockage of optical wireless signals transmitted by the light source **305** may be reduced at greater sizes of the hole **325**. In some examples, the UE **115** may use a photodetector with a smaller hole **325**, such as a hole with a 1 mm diameter. Using the hole **325** with the smaller diameter (e.g., 1 mm) may enable the photodetectors **320** to be positioned closer to an optical axis (e.g., a central axis for the lens **310** and/or the photodetector panel **315**). By being positioned closer to the optical axis, the photodetectors **320** may collect more power from optical wireless signals due to light condensing. The lens **310**, the photodetector panel **315**, and the light source **305** may be aligned (e.g., centrally aligned) with respect to the optical axis (e.g., a central axis of the lens **310**, such as along a boresight direction of the lens **310**).

(70) The lens **310** may serve as a common lens for both receive beams and transmit beams for beam steering of optical wireless signals. For example, the UE **115** may receive a downlink optical wireless signal from a network entity **105** via the lens **310** such that the lens **310** condenses light of the downlink optical wireless signal toward the photodetectors **320** of the photodetector panel **315**. The UE **115** may transmit an uplink optical wireless signal to the network entity **105** via the lens **310** such that light emitted (e.g., transmitted) from the light source **305** pass through the hole **325** of the photodetector panel **315** to reach the lens **310**. The lens **310** may collimate the light of the uplink optical wireless signal (e.g., light corresponding to the image of the light source **305**), and a network entity **105** may receive the uplink optical wireless signal.

(71) FIG. 4 shows an example of an OFE **400** that supports a coaxial OFE for OWC in accordance

with one or more aspects of the present disclosure. In some examples, aspects of the OFE **400** may implement or be implemented by aspects of the wireless communications system **100** and/or the wireless communications system **200**. For example, the OFE **400** may be included in or implemented by a UE **115** and/or a network entity **105**, which may be examples of the corresponding devices as described herein, including with reference to FIGS. **1** and **2**.

(72) The OFE **400** may include an optical relay sub-system including a lens **435** and a lens **440** to support transmission of uplink optical wireless signals. For example, the lens **435** and the lens **440** may be positioned in between a light source **405** of the OFE **400** and a photodetector panel **415** (e.g., a photodetector panel **315**) of the OFE **400** and may be used to form an image of the light source **405**. The image of the light source **405** may be formed between the lens **435** and the photodetector panel **415**, or the image may be formed at or around the hole in the photodetector panel **415**. For example, the image of the light source **405** may be formed at, or near, a focal point of a lens **410** of the OFE **400** (e.g., a lens **310**). The light of the image may pass through a hole (e.g., a hole **325**) in the photodetector panel **415** to reach the lens **410**. In some examples, a size (e.g., a diameter, such as an aperture diameter) of the lens **410** may be larger than a size (e.g., a diameter, such as an aperture diameter) of either of the lens **435** or the lens **440**. In some examples, the lens **435** and the lens **440** may be the same size (e.g., have a same diameter, such as a same aperture diameter) and/or may be of a same or similar lens type. In some examples, a focal length **450** (e.g., a focal distance) of the lens **435** may be the same as a focal length **455** of the lens **440**. In some examples, the focal lengths **450** and **455** may be different.

(73) In some cases, the focal length **450** and the focal length **455** may be the less than a focal length **445** of the lens **410**. In some examples, the lens **410** and the lens **435** (e.g., and the lens **440**) may be of a same or similar lens type or may share common optical characteristics or parameters. For example, the lens **410** and the lens **435** may have a same (e.g., or similar) f-number (e.g., f-stop). That is, a ratio of the focal length **450** to the diameter (e.g., aperture diameter) of the lens **435** may be the same as a ratio of the focal length **445** to the diameter (e.g., aperture diameter) of the lens **410**. In some examples, the focal length **450** may be less than the focal length **445**, for example, due to the lens **410** and the lens **435** having the same f-number and the diameter of the lens **410** being greater than the diameter of the lens **435**. In some examples, the lens **435** may have optical characteristics that are based on the focal length **445** or other optical parameters of the lens **410**, which may enable the lens **435** to maximize optical gain of transmitted optical wireless signals from the light source **405** via the lens **410**. Such optical characteristics of the lens **435** (e.g., or optical characteristics of the lens **440**) may support efficiently transmitting light from the light source **405** through the hole in the photodetector panel **415** and to the lens **410** with reduced loss, for example, relative to a coaxial OFE (e.g., an OFE **300**) that does not implement the relay sub-system of the lens **435** and the lens **440**.

(74) The OFE **400** may utilize the optical relay sub-system, as well as the light source **405**, the photodetector panel **415**, and the lens **410**, to perform beam steering for receive beams and transmit beams of optical wireless signals in accordance with a single, coaxial OFE. The light source **405**, the photodetector panel **415**, the lens **410**, the lens **435**, and the lens **440** may be aligned (e.g., aligned centrally) on a common axis. Receive beams and transmit beams for a UE **115** using the OFE **400** may pass through the same lens **410**. The lens **410** may condense receive (e.g., downlink) light toward one or more photodetectors of the photodetector panel **415**, and the lens **410** may collimate transmit (e.g., uplink) light that pass through a hole in the photodetector panel **415** and that are also transmitted via the lens **440** and the lens **435** before reaching the lens **410**. The transmitted light may be shaped by the optical relay sub-system which may form an image of the light source **405** around, or at, the hole in the photodetector panel **415** (e.g., at or near the focal length **445**).

(75) The photodetector panel **415** may be positioned a distance **425** from the lens **410**. The distance **425** may be determined to maximize condensing (e.g., beam steering) gain for downlink optical

wireless signals received at photodetectors of the photodetector panel **415**. In some examples, the distance **425** may be less than the focal length **445**. The light source **405** may be positioned a distance **430** from the lens **410**, which may allow for transmission of light beams via the optical relay sub-system and through the hole in the photodetector panel **415** before reaching the lens **410**. The distance **430** may be determined to maximize beam steering gain. For example, the image of the light source **405** may be formed at, or close to, the focal length **445** of the lens **410** based on the distance **430** (e.g., and distances of the lens **435** and the lens **440**). The image of the light source **405** may be formed or shaped at the focal length **445** of the lens to increase (e.g., maximize) the optical gain of uplink light beams transmitted by the light source **405**.

(76) FIGS. 5A, 5B, 5C, and 5D show examples of a photodetector panel configuration **500**, a photodetector panel configuration **520**, a photodetector panel configuration **525**, and a photodetector panel configuration **530**, respectively, that support a coaxial OFE for OWC in accordance with one or more aspects of the present disclosure. In some examples, aspects of the photodetector panel configuration **500**, the photodetector panel configuration **520**, the photodetector panel configuration **525**, and the photodetector panel configuration **530** may implement or be implemented by aspects of the wireless communications system **100** and/or the wireless communications system **200**. For example, the photodetector panel configuration **500**, the photodetector panel configuration **520**, the photodetector panel configuration **525**, and the photodetector panel configuration **530** may be included in or implemented by a UE **115** and/or a network entity **105**, which may be examples of the corresponding devices as described herein, including with reference to FIGS. 1 through 4. The photodetector panel configurations may be implemented by a photodetector panel of an OFE, such as a photodetector panel **315** or an OFE **300** or a photodetector panel **415** of an OFE **400**.

(77) Referring to FIG. 5A, the photodetector panel configuration **500** may include a photodetector panel **505-a** that includes a hole **515-a** and a set of four photodetectors **510** positioned around the hole **515-a**. In some examples, the photodetectors **510** may be SiPMs. A photodetector **510-a** and a photodetector **510-c** may be positioned above and below the hole **515-a**, respectively, and may be aligned vertically with the hole **515-a**. A photodetector **510-b** and a photodetector **510-d** may be positioned to the right of and to the left of the hole **515-a**, respectively, and may be aligned horizontally. In some examples, the hole **515-a** may have a diameter of 3 mm (e.g., or some other diameter) and the photodetectors **510** may have dimensions 1 mm by 1 mm (among other sized photodetectors **510**). In some examples, the hole **515-a** may have a circular shape. In some examples, the hole **515-a** may have another shape (e.g., with varying dimensions, such as varying widths and lengths).

(78) The UE **115** may measure an optical wireless signal using each of the multiple photodetectors **510** and may perform equal gain combination to combine the measurements (e.g., outputs) from each of the multiple photodetectors **510**. For example, the photodetectors **510** be positioned on the photodetector panel **505-a** such that each photodetector **510** may output a similar electrical signal, such as near enough to homogenous such that equal gain combination of the respectively output electrical signals may be performed. Thus, the UE **115** may measure a relatively higher total signal gain than a single photodetector **510**, which may result in an increased quality of communications. The UE **115** may perform equal gain combination (e.g., may process an output for equal gain combination) for the photodetector **510-a**, the photodetector **510-b**, the photodetector **510-c**, and the photodetector **510-d** using a single RF chain. For example, the UE **115** may receive one or more optical wireless signals using the photodetectors **510** and may perform an equal gain combination operation on multiple signals output by the photodetectors **510**. The photodetector **510-a**, the photodetector **510-b**, the photodetector **510-c**, and the photodetector **510-d** may be associated with (e.g., included in) the same RF chain. As such, an OFE that includes the photodetector panel **505-a** may include a reduced quantity of RF chains relative to if each photodetector **510** was associated with a respective RF chain. In some examples, each photodetector **510** may be associated with a

respective RF chain, and equal gain combination may not be performed in receiving an optical wireless signal.

(79) Referring to FIG. 5B, the photodetector panel configuration **520** may include a photodetector panel **505-b** that includes a hole **515-b**, a first set of photodetectors **510**, which may be associated with a first RF chain, and a second set of photodetectors **510**, which may be associated with a second RF chain. The hole **515-b** may be an example of the hole **515-a**. In some examples, the photodetectors **510** may be SiPMs. The photodetectors **510** of the first and second sets may each have the same dimensions, such as each having dimensions of 3 mm by 3 mm or of 1 mm by 1 mm (among other possible dimensions). The first set of photodetectors may include a photodetector **510-c**, a photodetector **510-f**, a photodetector **510-g**, and a photodetector **510-h** (e.g., photodetectors **510** aligned vertically and horizontally with respect to the hole **515-b**). The second set of photodetectors may include a photodetector **510-i**, a photodetector **510-j**, a photodetector **510-k**, and a photodetector **510-l** (e.g., photodetectors aligned diagonally with respect to the hole **515-b**).

(80) The UE **115** may perform equal gain combination (e.g., in the analog domain) for each of the first set of photodetectors **510** and the second set of photodetectors **510** using the first RF chain and the second RF chain, respectively. For example, the UE **115** may receive one or more optical wireless signals using the first set of photodetectors **510** and the second set of photodetectors **510**. The first set of photodetectors **510** may be positioned on the photodetector panel **505-b** such that each photodetector **510** may output a similar electrical signal with respect to other photodetectors **510** of the first set. Additionally, the second set of photodetectors may be positioned on the photodetector panel **505-b** such that each photodetector **510** may output a similar electrical signal with respect to other photodetectors **510** of the second set. Accordingly, the UE **115** may perform a first equal gain combination operation on a first set of signals output by the first set of photodetectors **510** and may perform a second equal gain combination operation on a second set of signals output by the second set of photodetectors **510**. Two RF chains may be sufficient for the UE **115** to process the output of the first and second equal gain combinations, which may reduce a quantity of RF chains associated with an OFE that includes the photodetector panel **505-b** relative to if each photodetector **510** was associated with a respective RF chain. In some examples, each photodetector **510** may be associated with a respective RF chain, and equal gain combination may not be performed in receiving an optical wireless signal.

(81) Referring to FIG. 5C, the photodetector panel configuration **525** may include a photodetector panel **505-c** that includes a hole **515-c** and a set of four photodetectors positioned around the hole **515-c**. In some examples, the hole **515-c** may be smaller in size (e.g., diameter) compared to the hole **515-a** or **515-b**. For example, the hole **515-c** may have a diameter of 1 mm. In some examples, because the hole **515-c** is smaller in size, a photodetector **510-m**, a photodetector **510-n**, a photodetector **510-o**, and a photodetector **510-p** of the set of photodetectors may be positioned to be off-center (e.g., off-center horizontally or vertically) with the hole **515-c**. In some examples, the photodetectors **510** may be 3 mm by 3 mm (e.g., photodetectors **510** larger than photodetectors **510** of the photodetector panel configurations **500** and **520**), and, in some cases, the photodetectors **510** may be SiPMs. The photodetector panel configuration **525** may be used by a UE **115** to position the photodetectors **510** closer to an optical axis of an OFE, which may support an increased optical gain (e.g., optical condensing gain, electronical combination gain) of received optical wireless signals compared to the photodetector panel configuration **500**.

(82) In some examples, the UE **115** may perform equal gain combination to combine the measurements (e.g., outputs) from each of the photodetectors **510** of the photodetector panel **505-c**. For example, the photodetectors **510** be positioned on the photodetector panel **505-c** such that each photodetector **510** may output a similar electrical signal to enable the UE **115** to perform equal gain combination for signals output by the photodetector **510-m**, the photodetector **510-n**, the photodetector **510-o**, and the photodetector **510-p** using a single (e.g., same) RF chain. As such, an

OFE that includes the photodetector panel **505-c** may include a reduced quantity of RF chains relative to if each photodetector **510** was associated with a respective RF chain. In some examples, each photodetector **510** may be associated with a respective RF chain, and equal gain combination may not be performed in receiving an optical wireless signal.

(83) Referring to FIG. 5D, the photodetector panel configuration **530** may include a photodetector panel **505-d** that includes a hole **515-d**, a first set of a first set of photodetectors **510**, which may be associated with a first RF chain, and a second set of photodetectors **510**, which may be associated with a second RF chain. In some cases, the hole **515-d** may be smaller than the hole **515-a** or **515-b** (e.g., may be the same size as the hole **515-c**). For example, the hole **515-d** may have a diameter of 1 mm. In some examples, the photodetectors **510** may be SiPMs, and photodetectors **510** of the first set may be smaller in size compared to the photodetectors **510** of the second set. For example, the first set of photodetectors **510** may each have dimensions of 1 mm by 1 mm, and the second set of photodetectors **510** may each have dimensions of 3 mm by 3 mm. The smaller sized photodetectors **510** of the first set may have better frequency response compared to the photodetectors **510** of the second set. The first set of photodetectors may include a photodetector **510-q**, a photodetector **510-r**, a photodetector **510-s**, and a photodetector **510-t** (e.g., photodetectors **510** aligned vertically and horizontally with respect to the hole **515-d**). The second set of photodetectors may include a photodetector **510-u**, a photodetector **510-v**, a photodetector **510-w**, and a photodetector **510-x** (e.g., photodetectors aligned diagonally with respect to the hole **515-d**).

(84) The UE **115** may perform equal gain combination for each of the first set of photodetectors **510** and the second set of photodetectors **510** using the first RF chain and the second RF chain, respectively. For example, the UE **115** may receive one or more optical wireless signals using the first set of photodetectors **510** and the second set of photodetectors **510**. The first set of photodetectors **510** may be positioned on the photodetector panel **505-d** such that each photodetector **510** may output a similar electrical signal with respect to other photodetectors **510** of the first set. Additionally, the second set of photodetectors may be positioned on the photodetector panel **505-d** such that each photodetector **510** may output a similar electrical signal with respect to other photodetectors **510** of the second set. Accordingly, the UE **115** may perform a first equal gain combination operation on a first set of signals output by the first set of photodetectors **510** and may perform a second equal gain combination operation on a second set of signals output by the second set of photodetectors **510**. Two RF chains may be sufficient for the UE **115** to process the output of the first and second equal gain combinations, which may reduce a quantity of RF chains associated with an OFE that includes the photodetector panel **505-b** relative to if each photodetector **510** was associated with a respective RF chain. In some examples, each photodetector **510** may be associated with a respective RF chain, and equal gain combination may not be performed in receiving an optical wireless signal.

(85) FIG. 6 shows an example of an OFE **600** that supports a coaxial OFE for OWC in accordance with one or more aspects of the present disclosure. In some examples, aspects of the OFE **600** may implement or be implemented by aspects of the wireless communications system **100** and/or the wireless communications system **200**. For example, the OFE **600** may be included in or implemented by a UE **115** and/or a network entity **105**, which may be examples of the corresponding devices as described herein, including with reference to FIGS. 1, 2, and 5A through 5D.

(86) In some examples, rather than using a common lens (e.g., a lens **310** or a lens **410** as described herein with reference to FIGS. 3 and 4, respectively) for beam steering of both receive and transmit beams of optical wireless signals, the OFE **600** may include a mirror **610** (e.g., a reflector). The mirror **610** may reflect light of an optical wireless signal (e.g., a downlink optical wireless signal for a network entity **105**) such that light beams that impact the mirror **610** may be directed toward photodetectors of a photodetector panel **615** (e.g., a photodetector panel **315**, **415**, or **505**), and a UE **115** may receive the optical wireless signal using the photodetectors.

(87) A light source **605** may be positioned at a greater distance from the mirror **610** compared to the photodetector panel **615**. Accordingly, the light source **605** may transmit an optical wireless signal (e.g., an uplink optical wireless signal) and light of the optical wireless signal may pass through a hole in the photodetector panel **615** to reach the mirror **610**. The mirror **610** may reflect and collimate the light, and the optical wireless signal may be received at a network entity **105**. In some examples, the OFE **600** may include a relay sub-system of lenses, as described with reference to FIG. 4. For example, the OFE **600** may include a lens **620** and a lens **625** via which the light source **605** may transmit the optical wireless signal to the mirror **610** and through the hole in the photodetector panel **615**. In other examples, the OFE **600** may include the light source **605**, the photodetector panel **615**, and the mirror **610** without the optical relay sub-system (e.g., without the lens **620** and the lens **625**).

(88) In some examples, the mirror **610** may support a larger aperture (e.g., a larger diameter) compared to a lens (e.g., the lens **410**). For example, the mirror **610** of the OFE **600** may have a larger diameter (e.g., aperture) compared with the lens **310** or the lens **410** as described herein with reference to FIGS. 3 and 4, respectively. Because the mirror **610** may have a larger aperture, the mirror **610** may direct a larger amount of light power from downlink optical wireless signals toward the photodetectors of the photodetector panel **615**, which may improve an optical gain of optical wireless signals that the UE **115** may receive at the photodetector panel **615**. Similarly, the mirror **610** may direct a larger amount of light power from uplink optical wireless signals transmitted by the light source **605** toward a network entity **105** that may receive the uplink optical wireless signal, which may improve an optical gain for optical wireless signals that the UE **115** transmits.

(89) FIG. 7 shows an example of a process flow **700** that supports a coaxial OFE for OWC in accordance with one or more aspects of the present disclosure. In some examples, aspects of the process flow **700** may implement or be implemented by aspects of the wireless communications system **100** and/or the wireless communications system **200**. For example, the process flow **700** may be implemented by a UE **115-b** and a network entity **105-b**, which may be examples of the corresponding devices as described herein with reference to FIGS. 1 and 2. In the following description of the process flow **700**, the operations between the network entity **105-b** and the UE **115-b** may be performed in a different order than the example order shown. Some operations may also be omitted from the process flow **700**, and other operations may be added to the process flow **700**. Further, although some operations or signaling may be shown to occur at different times for discussion purposes, these operations may actually occur at the same time.

(90) At **705**, the UE **115-b** may establish an optical wireless communication link with the network entity **105-b**. For example, the UE **115-b** may establish the optical wireless communication link with the network entity **105-b** using one or more optical communication components of the UE **115-b** and one or more optical devices (e.g., lenses, mirrors, reflectors) of the UE **115-b**. The optical communication components may be, for example, a photodetector, a photodetector panel, a light source, or any combination thereof.

(91) At **710**, the UE **115-b** may transmit a parameter message to the network entity **105-b** indicating one or more parameters associated with an OFE of the UE **115-b**. In some examples, the parameter message may indicate that the UE **115-b** supports (e.g., includes) a coaxial OFE for reception and transmission of optical wireless signals. In some examples, the parameter message may indicate one or more parameters of the coaxial OFE. For example, the parameter message may indicate a first distance between a curved optical device (e.g., lens, mirror, reflector) and a photodetector panel (e.g., receive PCB) that receives one or more optical wireless signals via the curved optical device. Additionally, or alternatively, the parameter message may indicate a second distance between the curved optical device and a light source that transmits one or more optical wireless signals via the curved optical device. In some examples, if the UE **115-b** implements an optical relay sub-system to support transmitting optical wireless signals, the parameter message may

indicate one or more parameters associated with the lenses of the optical relay sub-system (e.g., respective distances from the curved optical device). In some cases, the UE **115-b** may have a capability to modify the one or more of the distances (e.g., first and second distances), such as via one or more translation stages coupled with the curved optical device, the photodetector panel, the light source, and/or, and may indicate the capability to modify the distances to the network entity **105-b** (e.g., via the parameter message).

(92) In some cases, the UE **115-b** may perform measurements (e.g., calculations) to determine one or more of the distances with respect to an optical gain for receiving optical wireless signals (e.g., receive optical gain), an optical gain for transmitting optical wireless signals (e.g., transmit optical gain), or any combination thereof. The UE **115-b** may adjust the first distance and the second distance to maximize one of the receive optical gain or the transmit optical gain, or the UE **115-b** may adjust the first and second distances to balance both the receive optical gain and the transmit optical gain (e.g., according to some ratio of receive optical gain and transmit optical gain or according to one or more threshold values). In some examples, the parameter message may include the measurements performed by the UE **115-b**.

(93) At **715**, the UE **115-b** may receive, from the network entity **105-b** via the optical wireless communication link, a first optical wireless signal (e.g., downlink signal) using one or more photodetectors positioned on a photodetector panel of the UE **115-b**. The photodetector panel may include a hole around which the one or more photodetectors are positioned, and the photodetector panel may be located the first distance from the curved optical device of the UE **115-b** via which the first optical wireless signal is received.

(94) At **720**, the transmit, to the network entity **105-b** via the optical wireless communication link, a second optical wireless signal (e.g., uplink signal) using a light source of the UE **115-b** that is located the second distance from the curved optical device via which the second optical wireless signal is transmitted. The second optical wireless signal may pass through the hole in the photodetector panel based on the second distance being greater than the first distance.

(95) In some examples, the UE **115-b** may transmit the second optical wireless signal via a first lens a third distance from the curved optical device and a second lens a fourth distance from the curved optical device (e.g., lenses included in an optical relay sub-system between the light source and the photodetector panel). The first lens may collimate the second optical wireless signal from the light source to the second lens and the second lens may condense the second optical wireless signal through the hole of the photodetector panel. The third distance may be less than the second distance and greater than the fourth distance, and the fourth distance may be greater than the first distance. A fifth distance between the light source and the first lens may correspond to a first focal length of the first lens. In some examples, the first focal length of the first lens may be the same as a second focal length of the second lens. In some examples, a first ratio of the first focal length to a first diameter of an aperture of the first lens may be the same as a second ratio of a third focal length of the curved optical device to a second diameter of an aperture of the curved optical device.

(96) FIG. **8** shows a block diagram **800** of a device **805** that supports a coaxial OFE for OWC in accordance with one or more aspects of the present disclosure. The device **805** may be an example of aspects of a UE **115** as described herein. The device **805** may include a receiver **810**, a transmitter **815**, and a communications manager **820**. The device **805**, or one or more components of the device **805** (e.g., the receiver **810**, the transmitter **815**, and the communications manager **820**), may include at least one processor (not shown), which may be coupled with at least one memory, to, individually or collectively, support or enable the described techniques. Each of these components may be in communication with one another (e.g., via one or more buses).

(97) The receiver **810** may provide a means for receiving information such as packets, user data, control information, or any combination thereof associated with various information channels (e.g., control channels, data channels, information channels related to a coaxial OFE for OWC).

Information may be passed on to other components of the device **805**. The receiver **810** may utilize

a single antenna or a set of multiple antennas.

(98) The transmitter **815** may provide a means for transmitting signals generated by other components of the device **805**. For example, the transmitter **815** may transmit information such as packets, user data, control information, or any combination thereof associated with various information channels (e.g., control channels, data channels, information channels related to a coaxial OFE for OWC). In some examples, the transmitter **815** may be co-located with a receiver **810** in a transceiver module. The transmitter **815** may utilize a single antenna or a set of multiple antennas.

(99) The communications manager **820**, the receiver **810**, the transmitter **815**, or various combinations thereof or various components thereof may be examples of means for performing various aspects of a coaxial OFE for OWC as described herein. For example, the communications manager **820**, the receiver **810**, the transmitter **815**, or various combinations or components thereof may be capable of performing one or more of the functions described herein.

(100) In some examples, the communications manager **820**, the receiver **810**, the transmitter **815**, or various combinations or components thereof may be implemented in hardware (e.g., in communications management circuitry). The hardware may include at least one of a processor, a digital signal processor (DSP), a central processing unit (CPU), an application-specific integrated circuit (ASIC), a field-programmable gate array (FPGA) or other programmable logic device, a microcontroller, discrete gate or transistor logic, discrete hardware components, or any combination thereof configured as or otherwise supporting, individually or collectively, a means for performing the functions described in the present disclosure. In some examples, at least one processor and at least one memory coupled with the at least one processor may be configured to perform one or more of the functions described herein (e.g., by one or more processors, individually or collectively, executing instructions stored in the at least one memory).

(101) Additionally, or alternatively, the communications manager **820**, the receiver **810**, the transmitter **815**, or various combinations or components thereof may be implemented in code (e.g., as communications management software or firmware) executed by at least one processor. If implemented in code executed by at least one processor, the functions of the communications manager **820**, the receiver **810**, the transmitter **815**, or various combinations or components thereof may be performed by a general-purpose processor, a DSP, a CPU, an ASIC, an FPGA, a microcontroller, or any combination of these or other programmable logic devices (e.g., configured as or otherwise supporting, individually or collectively, a means for performing the functions described in the present disclosure).

(102) In some examples, the communications manager **820** may be configured to perform various operations (e.g., receiving, obtaining, monitoring, outputting, transmitting) using or otherwise in cooperation with the receiver **810**, the transmitter **815**, or both. For example, the communications manager **820** may receive information from the receiver **810**, send information to the transmitter **815**, or be integrated in combination with the receiver **810**, the transmitter **815**, or both to obtain information, output information, or perform various other operations as described herein.

(103) The communications manager **820** may support OWC at a UE in accordance with examples as disclosed herein. For example, the communications manager **820** is capable of, configured to, or operable to support a means for receiving, from a network entity via an OWC link, a first optical wireless signal using one or more photodetectors positioned on a photodetector panel of the UE, where the photodetector panel includes a hole around which the one or more photodetectors are positioned, and where the photodetector panel is located a first distance from a curved optical device of the UE via which the first optical wireless signal is received. The communications manager **820** is capable of, configured to, or operable to support a means for transmitting, to the network entity via the OWC link, a second optical wireless signal using a light source of the UE that is located a second distance from the curved optical device via which the second optical wireless signal is transmitted, where the second optical wireless signal passes through the hole in

the photodetector panel based on the second distance being greater than the first distance.

(104) By including or configuring the communications manager **820** in accordance with examples as described herein, the device **805** (e.g., at least one processor controlling or otherwise coupled with the receiver **810**, the transmitter **815**, the communications manager **820**, or any combination thereof) may support techniques for reduced power consumption by increasing efficiency of optical wireless signals. For example, the device **805** may support improved beam steering of optical wireless signals which may collect or direct a greater amount of power of the optical wireless signals received or transmitted by the UE or the network entity, enabling the UE or the network entity to reduce power or reduce processing associated with receiving or transmitting optical wireless signals with less waste.

(105) FIG. **9** shows a block diagram **900** of a device **905** that supports a coaxial OFE for OWC in accordance with one or more aspects of the present disclosure. The device **905** may be an example of aspects of a device **805** or a UE **115** as described herein. The device **905** may include a receiver **910**, a transmitter **915**, and a communications manager **920**. The device **905**, or one of more components of the device **905** (e.g., the receiver **910**, the transmitter **915**, and the communications manager **920**), may include at least one processor (not shown), which may be coupled with at least one memory, to support the described techniques. Each of these components may be in communication with one another (e.g., via one or more buses).

(106) The receiver **910** may provide a means for receiving information such as packets, user data, control information, or any combination thereof associated with various information channels (e.g., control channels, data channels, information channels related to a coaxial OFE for OWC). Information may be passed on to other components of the device **905**. The receiver **910** may utilize a single antenna or a set of multiple antennas.

(107) The transmitter **915** may provide a means for transmitting signals generated by other components of the device **905**. For example, the transmitter **915** may transmit information such as packets, user data, control information, or any combination thereof associated with various information channels (e.g., control channels, data channels, information channels related to a coaxial OFE for OWC). In some examples, the transmitter **915** may be co-located with a receiver **910** in a transceiver module. The transmitter **915** may utilize a single antenna or a set of multiple antennas.

(108) The device **905**, or various components thereof, may be an example of means for performing various aspects of a coaxial OFE for OWC as described herein. For example, the communications manager **920** may include a photodetector component **925** a light source component **930**, or any combination thereof. The communications manager **920** may be an example of aspects of a communications manager **820** as described herein. In some examples, the communications manager **920**, or various components thereof, may be configured to perform various operations (e.g., receiving, obtaining, monitoring, outputting, transmitting) using or otherwise in cooperation with the receiver **910**, the transmitter **915**, or both. For example, the communications manager **920** may receive information from the receiver **910**, send information to the transmitter **915**, or be integrated in combination with the receiver **910**, the transmitter **915**, or both to obtain information, output information, or perform various other operations as described herein.

(109) The communications manager **920** may support OWC at a UE in accordance with examples as disclosed herein. The photodetector component **925** is capable of, configured to, or operable to support a means for receiving, from a network entity via an OWC link, a first optical wireless signal using one or more photodetectors positioned on a photodetector panel of the UE, where the photodetector panel includes a hole around which the one or more photodetectors are positioned, and where the photodetector panel is located a first distance from a curved optical device of the UE via which the first optical wireless signal is received. The light source component **930** is capable of, configured to, or operable to support a means for transmitting, to the network entity via the OWC link, a second optical wireless signal using a light source of the UE that is located a second distance

from the curved optical device via which the second optical wireless signal is transmitted, where the second optical wireless signal passes through the hole in the photodetector panel based on the second distance being greater than the first distance.

(110) FIG. **10** shows a block diagram **1000** of a communications manager **1020** that supports a coaxial OFE for OWC in accordance with one or more aspects of the present disclosure. The communications manager **1020** may be an example of aspects of a communications manager **820**, a communications manager **920**, or both, as described herein. The communications manager **1020**, or various components thereof, may be an example of means for performing various aspects of a coaxial OFE for OWC as described herein. For example, the communications manager **1020** may include a photodetector component **1025**, a light source component **1030**, a relay component **1035**, an equal gain component **1040**, or any combination thereof. Each of these components, or components or subcomponents thereof (e.g., one or more processors, one or more memories), may communicate, directly or indirectly, with one another (e.g., via one or more buses).

(111) The communications manager **1020** may support OWC at a UE in accordance with examples as disclosed herein. The photodetector component **1025** is capable of, configured to, or operable to support a means for receiving, from a network entity via an OWC link, a first optical wireless signal using one or more photodetectors positioned on a photodetector panel of the UE, where the photodetector panel includes a hole around which the one or more photodetectors are positioned, and where the photodetector panel is located a first distance from a curved optical device of the UE via which the first optical wireless signal is received. The light source component **1030** is capable of, configured to, or operable to support a means for transmitting, to the network entity via the OWC link, a second optical wireless signal using a light source of the UE that is located a second distance from the curved optical device via which the second optical wireless signal is transmitted, where the second optical wireless signal passes through the hole in the photodetector panel based on the second distance being greater than the first distance.

(112) In some examples, to support transmitting the second optical wireless signal, the relay component **1035** is capable of, configured to, or operable to support a means for transmitting the second optical wireless signal via a first lens a third distance from the curved optical device and a second lens a fourth distance from the curved optical device, where the first lens collimates the second optical wireless signal from the light source to the second lens and the second lens condenses the second optical wireless signal through the hole of the photodetector panel.

(113) In some examples, the third distance is less than the second distance and greater than the fourth distance, and the fourth distance is greater than the first distance.

(114) In some examples, a fifth distance between the light source and the first lens corresponds to a focal length of the first lens.

(115) In some examples, a first ratio of focal length to aperture diameter of the first lens is the same as a second ratio of focal length to aperture diameter of the curved optical device.

(116) In some examples, a first focal length of the first lens may be the same as a second focal length of the second lens. In some examples, the first focal length may be less than a third focal length of the curved optical device.

(117) In some examples, to support receiving the first optical wireless signal, the photodetector component **1025** is capable of, configured to, or operable to support a means for receiving the first optical wireless signal using a set of multiple photodetectors of the one or more photodetectors. In some examples, to support receiving the first optical wireless signal, the equal gain component **1040** is capable of, configured to, or operable to support a means for performing an equal gain combination operation on a set of multiple signals output by the set of multiple photodetectors.

(118) In some examples, the set of multiple photodetectors are associated with a same RF chain.

(119) In some examples, to support receiving the first optical wireless signal, the photodetector component **1025** is capable of, configured to, or operable to support a means for receiving the first optical wireless signal using a first subset of photodetectors of the one or more photodetectors and

a second subset of photodetectors of the one or more photodetectors. In some examples, to support receiving the first optical wireless signal, the equal gain component **1040** is capable of, configured to, or operable to support a means for performing a first equal gain combination operation on a first set of multiple signals output by the first subset of photodetectors. In some examples, to support receiving the first optical wireless signal, the equal gain component **1040** is capable of, configured to, or operable to support a means for performing a second equal gain combination operation on a second set of multiple signals output by the second subset of photodetectors.

(120) In some examples, the first subset of photodetectors is associated with a first RF chain and the second subset of photodetectors is associated with a second RF chain.

(121) In some examples, each photodetector of the first subset of photodetectors is a first size and each photodetector of the second subset of photodetectors is a second size, the second size being larger than the first size.

(122) In some examples, the first distance is less than a focal length of the curved optical device.

(123) In some examples, the one or more photodetectors includes a first set of photodetectors, the first set of photodetectors including two photodetectors aligned vertically with the hole and two photodetectors aligned horizontally with the hole.

(124) In some examples, the curved optical device is a lens or a mirror.

(125) FIG. **11** shows a diagram of a system **1100** including a device **1105** that supports a coaxial OFE for OWC in accordance with one or more aspects of the present disclosure. The device **1105** may be an example of or include the components of a device **805**, a device **905**, or a UE **115** as described herein. The device **1105** may communicate (e.g., wirelessly) with one or more network entities **105**, one or more UEs **115**, or any combination thereof. The device **1105** may include components for bi-directional voice and data communications including components for transmitting and receiving communications, such as a communications manager **1120**, an input/output (I/O) controller **1110**, a transceiver **1115**, an antenna **1125**, at least one memory **1130**, code **1135**, and at least one processor **1140**. These components may be in electronic communication with each other or otherwise coupled (e.g., operatively, communicatively, functionally, electronically, electrically) via one or more buses (e.g., a bus **1145**).

(126) The I/O controller **1110** may manage input and output signals for the device **1105**. The I/O controller **1110** may also manage peripherals not integrated into the device **1105**. In some cases, the I/O controller **1110** may represent a physical connection or port to an external peripheral. In some cases, the I/O controller **1110** may utilize an operating system such as iOS®, ANDROID®, MS-DOS®, MS-WINDOWS®, OS/2®, UNIX®, LINUX®, or another known operating system. Additionally, or alternatively, the I/O controller **1110** may represent or interact with a modem, a keyboard, a mouse, a touchscreen, or a similar device. In some cases, the I/O controller **1110** may be implemented as part of one or more processors, such as the at least one processor **1140**. In some cases, a user may interact with the device **1105** via the I/O controller **1110** or via hardware components controlled by the I/O controller **1110**.

(127) In some cases, the device **1105** may include a single antenna **1125**. However, in some other cases, the device **1105** may have more than one antenna **1125**, which may be capable of concurrently transmitting or receiving multiple wireless transmissions. The transceiver **1115** may communicate bi-directionally, via the one or more antennas **1125**, wired, or wireless links as described herein. For example, the transceiver **1115** may represent a wireless transceiver and may communicate bi-directionally with another wireless transceiver. The transceiver **1115** may also include a modem to modulate the packets, to provide the modulated packets to one or more antennas **1125** for transmission, and to demodulate packets received from the one or more antennas **1125**. The transceiver **1115**, or the transceiver **1115** and one or more antennas **1125**, may be an example of a transmitter **815**, a transmitter **915**, a receiver **810**, a receiver **910**, or any combination thereof or component thereof, as described herein.

(128) The at least one memory **1130** may include random access memory (RAM) and read-only

memory (ROM). The at least one memory **1130** may store computer-readable, computer-executable code **1135** including instructions that, when executed by the at least one processor **1140**, cause the device **1105** to perform various functions described herein. The code **1135** may be stored in a non-transitory computer-readable medium such as system memory or another type of memory. In some cases, the code **1135** may not be directly executable by the at least one processor **1140** but may cause a computer (e.g., when compiled and executed) to perform functions described herein. In some cases, the at least one memory **1130** may contain, among other things, a basic I/O system (BIOS) which may control basic hardware or software operation such as the interaction with peripheral components or devices.

(129) The at least one processor **1140** may include an intelligent hardware device (e.g., a general-purpose processor, a DSP, a CPU, a microcontroller, an ASIC, an FPGA, a programmable logic device, a discrete gate or transistor logic component, a discrete hardware component, or any combination thereof). In some cases, the at least one processor **1140** may be configured to operate a memory array using a memory controller. In some other cases, a memory controller may be integrated into the at least one processor **1140**. The at least one processor **1140** may be configured to execute computer-readable instructions (such as code **1135**) stored in a memory (e.g., the at least one memory **1130**) to cause the device **1105** to perform various functions (e.g., functions or tasks supporting a coaxial OFE for OWC). For example, the device **1105** or a component of the device **1105** may include at least one processor **1140** and at least one memory **1130** coupled with or to the at least one processor **1140**, the at least one processor **1140** and at least one memory **1130** configured to perform various functions described herein. In some examples, the at least one processor **1140** may include multiple processors and the at least one memory **1130** may include multiple memories. One or more of the multiple processors may be coupled with one or more of the multiple memories, which may, individually or collectively, be configured to perform various functions herein.

(130) The communications manager **1120** may support OWC at a UE in accordance with examples as disclosed herein. For example, the communications manager **1120** is capable of, configured to, or operable to support a means for receiving, from a network entity via an OWC link, a first optical wireless signal using one or more photodetectors positioned on a photodetector panel of the UE, where the photodetector panel includes a hole around which the one or more photodetectors are positioned, and where the photodetector panel is located a first distance from a curved optical device of the UE via which the first optical wireless signal is received. The communications manager **1120** is capable of, configured to, or operable to support a means for transmitting, to the network entity via the OWC link, a second optical wireless signal using a light source of the UE that is located a second distance from the curved optical device via which the second optical wireless signal is transmitted, where the second optical wireless signal passes through the hole in the photodetector panel based on the second distance being greater than the first distance.

(131) By including or configuring the communications manager **1120** in accordance with examples as described herein, the device **1105** may support techniques for improved form factor and miniaturization of the device **1105**. For example, by positioning components of an OFE on a same axis, the device **1105** may support a smaller lens tube or container for the OFE, which may improve form factor and support a reduced size of the device **1105**. The device **1105** may also improve communication reliability by supporting beam steering in the downlink and uplink transmission directions, which may direct a greater amount of power to transmitters or receivers that communicate optical wireless signals, improving the accuracy and reliability of such signals.

(132) In some examples, the communications manager **1120** may be configured to perform various operations (e.g., receiving, monitoring, transmitting) using or otherwise in cooperation with the transceiver **1115**, the one or more antennas **1125**, or any combination thereof. Although the communications manager **1120** is illustrated as a separate component, in some examples, one or more functions described with reference to the communications manager **1120** may be supported

by or performed by the at least one processor **1140**, the at least one memory **1130**, the code **1135**, or any combination thereof. For example, the code **1135** may include instructions executable by the at least one processor **1140** to cause the device **1105** to perform various aspects of a coaxial OFE for OWC as described herein, or the at least one processor **1140** and the at least one memory **1130** may be otherwise configured to, individually or collectively, perform or support such operations.

(133) FIG. **12** shows a flowchart illustrating a method **1200** that supports a coaxial OFE for OWC in accordance with aspects of the present disclosure. The operations of the method **1200** may be implemented by a UE or its components as described herein. For example, the operations of the method **1200** may be performed by a UE **115** as described herein with reference to FIGS. **1** through **11**. In some examples, a UE may execute a set of instructions to control the functional elements of the UE to perform the described functions. Additionally, or alternatively, the UE may perform aspects of the described functions using special-purpose hardware.

(134) At **1205**, the method may include receiving, from a network entity via an OWC link, a first optical wireless signal using one or more photodetectors positioned on a photodetector panel of the UE, where the photodetector panel includes a hole around which the one or more photodetectors are positioned, and where the photodetector panel is located a first distance from a curved optical device of the UE via which the first optical wireless signal is received. The operations of block **1205** may be performed in accordance with examples as disclosed herein. In some examples, aspects of the operations of **1205** may be performed by a photodetector component **1025** as described herein with reference to FIG. **10**.

(135) At **1210**, the method may include transmitting, to the network entity via the OWC link, a second optical wireless signal using a light source of the UE that is located a second distance from the curved optical device via which the second optical wireless signal is transmitted, where the second optical wireless signal passes through the hole in the photodetector panel based on the second distance being greater than the first distance. The operations of block **1210** may be performed in accordance with examples as disclosed herein. In some examples, aspects of the operations of **1210** may be performed by a light source component **1030** as described herein with reference to FIG. **10**.

(136) FIG. **13** shows a flowchart illustrating a method **1300** that supports a coaxial OFE for OWC in accordance with aspects of the present disclosure. The operations of the method **1300** may be implemented by a UE or its components as described herein. For example, the operations of the method **1300** may be performed by a UE **115** as described herein with reference to FIGS. **1** through **11**. In some examples, a UE may execute a set of instructions to control the functional elements of the UE to perform the described functions. Additionally, or alternatively, the UE may perform aspects of the described functions using special-purpose hardware.

(137) At **1305**, the method may include receiving, from a network entity via an OWC link, a first optical wireless signal using one or more photodetectors positioned on a photodetector panel of the UE, where the photodetector panel includes a hole around which the one or more photodetectors are positioned, and where the photodetector panel is located a first distance from a curved optical device of the UE via which the first optical wireless signal is received. The operations of block **1305** may be performed in accordance with examples as disclosed herein. In some examples, aspects of the operations of **1305** may be performed by a photodetector component **1025** as described herein with reference to FIG. **10**.

(138) At **1310**, the method may include transmitting, to the network entity via the OWC link, a second optical wireless signal using a light source of the UE that is located a second distance from the curved optical device via which the second optical wireless signal is transmitted, where the second optical wireless signal passes through the hole in the photodetector panel based on the second distance being greater than the first distance. The operations of block **1310** may be performed in accordance with examples as disclosed herein. In some examples, aspects of the operations of **1310** may be performed by a light source component **1030** as described herein with

reference to FIG. 10.

(139) At **1315**, to support transmitting the second optical wireless signal, the method may include transmitting the second optical wireless signal via a first lens a third distance from the curved optical device and a second lens a fourth distance from the curved optical device, where the first lens collimates the second optical wireless signal from the light source to the second lens and the second lens condenses the second optical wireless signal through the hole of the photodetector panel. The operations of block **1315** may be performed in accordance with examples as disclosed herein. In some examples, aspects of the operations of **1315** may be performed by a relay component **1035** as described herein with reference to FIG. 10.

(140) FIG. 14 shows a flowchart illustrating a method **1400** that supports a coaxial OFE for OWC in accordance with aspects of the present disclosure. The operations of the method **1400** may be implemented by a UE or its components as described herein. For example, the operations of the method **1400** may be performed by a UE **115** as described herein with reference to FIGS. 1 through 11. In some examples, a UE may execute a set of instructions to control the functional elements of the UE to perform the described functions. Additionally, or alternatively, the UE may perform aspects of the described functions using special-purpose hardware.

(141) At **1405**, the method may include receiving, from a network entity via an OWC link, a first optical wireless signal using one or more photodetectors positioned on a photodetector panel of the UE, where the photodetector panel includes a hole around which the one or more photodetectors are positioned, and where the photodetector panel is located a first distance from a curved optical device of the UE via which the first optical wireless signal is received. The operations of block **1405** may be performed in accordance with examples as disclosed herein. In some examples, aspects of the operations of **1405** may be performed by a photodetector component **1025** as described herein with reference to FIG. 10.

(142) At **1410**, to support receiving the first optical wireless signal, the method may include receiving the first optical wireless signal using a set of multiple photodetectors of the one or more photodetectors. The operations of block **1410** may be performed in accordance with examples as disclosed herein. In some examples, aspects of the operations of **1410** may be performed by a photodetector component **1025** as described herein with reference to FIG. 10.

(143) At **1415**, to support receiving the first optical wireless signal, the method may include performing an equal gain combination operation on a set of multiple signals output by the set of multiple photodetectors. The operations of block **1415** may be performed in accordance with examples as disclosed herein. In some examples, aspects of the operations of **1415** may be performed by an equal gain component **1040** as described herein with reference to FIG. 10.

(144) At **1420**, the method may include transmitting, to the network entity via the OWC link, a second optical wireless signal using a light source of the UE that is located a second distance from the curved optical device via which the second optical wireless signal is transmitted, where the second optical wireless signal passes through the hole in the photodetector panel based on the second distance being greater than the first distance. The operations of block **1420** may be performed in accordance with examples as disclosed herein. In some examples, aspects of the operations of **1420** may be performed by a light source component **1030** as described herein with reference to FIG. 10.

(145) FIG. 15 shows a flowchart illustrating a method **1500** that supports a coaxial OFE for OWC in accordance with aspects of the present disclosure. The operations of the method **1500** may be implemented by a UE or its components as described herein. For example, the operations of the method **1500** may be performed by a UE **115** as described herein with reference to FIGS. 1 through 11. In some examples, a UE may execute a set of instructions to control the functional elements of the UE to perform the described functions. Additionally, or alternatively, the UE may perform aspects of the described functions using special-purpose hardware.

(146) At **1505**, the method may include receiving, from a network entity via an OWC link, a first

optical wireless signal using one or more photodetectors positioned on a photodetector panel of the UE, where the photodetector panel includes a hole around which the one or more photodetectors are positioned, and where the photodetector panel is located a first distance from a curved optical device of the UE via which the first optical wireless signal is received. The operations of block **1505** may be performed in accordance with examples as disclosed herein. In some examples, aspects of the operations of **1505** may be performed by a photodetector component **1025** as described herein with reference to FIG. **10**.

(147) At **1510**, to support receiving the first optical wireless signal, the method may include receiving the first optical wireless signal using a first subset of photodetectors of the one or more photodetectors and a second subset of photodetectors of the one or more photodetectors. The operations of block **1510** may be performed in accordance with examples as disclosed herein. In some examples, aspects of the operations of **1510** may be performed by a photodetector component **1025** as described herein with reference to FIG. **10**.

(148) At **1515**, to support receiving the first optical wireless signal, the method may include performing a first equal gain combination operation on a first set of multiple signals output by the first subset of photodetectors. The operations of block **1515** may be performed in accordance with examples as disclosed herein. In some examples, aspects of the operations of **1515** may be performed by an equal gain component **1040** as described herein with reference to FIG. **10**.

(149) At **1520**, to support receiving the first optical wireless signal, the method may include performing a second equal gain combination operation on a second set of multiple signals output by the second subset of photodetectors. The operations of block **1520** may be performed in accordance with examples as disclosed herein. In some examples, aspects of the operations of **1520** may be performed by an equal gain component **1040** as described herein with reference to FIG. **10**.

(150) At **1525**, the method may include transmitting, to the network entity via the OWC link, a second optical wireless signal using a light source of the UE that is located a second distance from the curved optical device via which the second optical wireless signal is transmitted, where the second optical wireless signal passes through the hole in the photodetector panel based on the second distance being greater than the first distance. The operations of block **1525** may be performed in accordance with examples as disclosed herein. In some examples, aspects of the operations of **1525** may be performed by a light source component **1030** as described herein with reference to FIG. **10**.

(151) The following provides an overview of aspects of the present disclosure:

(152) Aspect 1: A method for OWC at a UE, comprising: receiving, from a network entity via an OWC link, a first optical wireless signal using one or more photodetectors positioned on a photodetector panel of the UE, wherein the photodetector panel comprises a hole around which the one or more photodetectors are positioned, and wherein the photodetector panel is located a first distance from a curved optical device of the UE via which the first optical wireless signal is received; and transmitting, to the network entity via the OWC link, a second optical wireless signal using a light source of the UE that is located a second distance from the curved optical device via which the second optical wireless signal is transmitted, wherein the second optical wireless signal passes through the hole in the photodetector panel based at least in part on the second distance being greater than the first distance.

(153) Aspect 2: The method of aspect 1, wherein transmitting the second optical wireless signal comprises: transmitting the second optical wireless signal via a first lens a third distance from the curved optical device and a second lens a fourth distance from the curved optical device, wherein the first lens collimates the second optical wireless signal from the light source to the second lens and the second lens condenses the second optical wireless signal through the hole of the photodetector panel.

(154) Aspect 3: The method of aspect 2, wherein the third distance is less than the second distance and greater than the fourth distance, and the fourth distance is greater than the first distance.

- (155) Aspect 4: The method of any of aspects 2 through 3, wherein a fifth distance between the light source and the first lens corresponds to a focal length of the first lens.
- (156) Aspect 5: The method of any of aspects 2 through 4, wherein a first ratio of focal length to aperture diameter of the first lens is the same as a second ratio of focal length to aperture diameter of the curved optical device.
- (157) Aspect 6: The method of any of aspects 2 through 5, wherein a first focal length of the first lens is the same as a second focal length of the second lens and less than a third focal length of the curved optical device.
- (158) Aspect 7: The method of any of aspects 1 through 6, wherein receiving the first optical wireless signal comprises: receiving the first optical wireless signal using a plurality of photodetectors of the one or more photodetectors; and performing an equal gain combination operation on a plurality of signals output by the plurality of photodetectors.
- (159) Aspect 8: The method of aspect 7, wherein the plurality of photodetectors are associated with a same RF chain.
- (160) Aspect 9: The method of any of aspects 1 through 8, wherein receiving the first optical wireless signal comprises: receiving the first optical wireless signal using a first subset of photodetectors of the one or more photodetectors and a second subset of photodetectors of the one or more photodetectors; performing a first equal gain combination operation on a first plurality of signals output by the first subset of photodetectors; and performing a second equal gain combination operation on a second plurality of signals output by the second subset of photodetectors.
- (161) Aspect 10: The method of aspect 9, wherein the first subset of photodetectors is associated with a first RF chain and the second subset of photodetectors is associated with a second RF chain.
- (162) Aspect 11: The method of any of aspects 1 through 10, wherein the first distance is less than a focal length of the curved optical device.
- (163) Aspect 12: The method of any of aspects 1 through 11, wherein the one or more photodetectors comprises a first set of photodetectors, the first set of photodetectors comprising two photodetectors aligned vertically with the hole and two photodetectors aligned horizontally with the hole.
- (164) Aspect 13: The method of any of aspects 1 through 12, wherein the curved optical device is a lens or a mirror.
- (165) Aspect 14: A UE for OWC, comprising one or more memories storing processor-executable code, and one or more processors coupled with the one or more memories and individually or collectively operable to execute the code to cause the UE to perform a method of any of aspects 1 through 13.
- (166) Aspect 15: A UE for OWC, comprising at least one means for performing a method of any of aspects 1 through 13.
- (167) Aspect 16: A non-transitory computer-readable medium storing code for OWC, the code comprising instructions executable by one or more processors to perform a method of any of aspects 1 through 13.
- (168) Aspect 17: A UE for OWC, including: a curved optical device; a photodetector panel located a first distance from the curved optical device, the photodetector panel including one or more photodetectors and a hole around which the one or more photodetectors are positioned; a light source located a second distance from the curved optical device; at least one processor; and at least one memory coupled with the at least one processor, with instructions stored in the at least one memory, the instructions being executable by the at least one processor, individually or in any combination, to cause the UE to: establish an OWC link with a network entity; and communicate, with the network entity via the OWC link, one or more optical wireless signals using at least one of the light source or the one or more photodetectors of the photodetector panel.
- (169) Aspect 18: The UE of aspect 17, where the instructions to communicate the one or more

optical wireless signals are executable by the at least one processor, individually or in any combination, to cause the UE to: transmit, using the light source, the one or more optical wireless signals through the hole of the photodetector panel via the curved optical device based at least in part on the second distance being greater than the first distance.

(170) Aspect 19: The UE of any of aspects 17 through 18, further including: a first lens a third distance from the curved optical device, where the third distance is less than the second distance and greater than the first distance; and a second lens a fourth distance from the curved optical device, where the fourth distance is greater than the first distance and less than the third distance.

(171) Aspect 20: The UE of aspect 19, where the instructions to communicate the one or more optical wireless signals are executable by the at least one processor, individually or in any combination, to cause the UE to: transmit, using the light source, the one or more optical wireless signals via the first lens, the second lens, and the curved optical device, where the first lens collimates the one or more optical wireless signals from the light source to the second lens and the second lens condenses the one or more optical wireless signals through the hole of the photodetector panel and to the curved optical device.

(172) Aspect 21: The UE of any of aspects 19 through 20, where a fifth distance between the light source and the first lens corresponds to a focal length of the first lens.

(173) Aspect 22: The UE of any of aspects 19 through 21, where the curved optical device, the photodetector panel, the first lens, the second lens, and the light source are aligned on a same axis.

(174) Aspect 23: The UE of any of aspects 19 through 22, where a first focal length of the first lens is the same as a second focal length of the second lens and less than a third focal length of the curved optical device.

(175) Aspect 24: The UE of any of aspects 19 through 23, where a first ratio of focal length to aperture diameter of the first lens is the same as a second ratio of focal length to aperture diameter of the curved optical device.

(176) Aspect 25: The UE of any of aspects 19 through 24, where a diameter of the curved optical device is greater than a diameter of the first lens and a diameter of the second lens.

(177) Aspect 26: The UE of any of aspects 17 through 25, where the instructions to communicate the one or more optical wireless signals are executable by the at least one processor, individually or in any combination, to cause the UE to: receive the one or more optical wireless signals using a plurality of photodetectors of the one or more photodetectors; and perform an equal gain combination operation on a plurality of signals output by the plurality of photodetectors.

(178) Aspect 27: The UE of aspect 26, where the plurality of photodetectors are associated with a same radio frequency chain.

(179) Aspect 28: The UE of any of aspects 17 through 27, where the instructions to communicate the one or more optical wireless signals are executable by the at least one processor, individually or in any combination, to cause the UE to: receive the one or more optical wireless signals using a first subset of photodetectors of the one or more photodetectors and a second subset of photodetectors of the one or more photodetectors; perform a first equal gain combination operation on a first plurality of signals output by the first subset of photodetectors; and perform a second equal gain combination operation on a second plurality of signals output by the second subset of photodetectors.

(180) Aspect 29: The UE of aspect 28, where the first subset of photodetectors are associated with a first radio frequency chain and the second subset of photodetectors are associated with a second radio frequency chain.

(181) Aspect 30: The UE of any of aspects 28 through 29, where each photodetector of the first subset of photodetectors is a first size and each photodetector of the second subset of photodetectors is a second size, the second size being larger than the first size.

(182) Aspect 31: The UE of any of aspects 17 through 30, where the first distance is less than a focal length of the curved optical device.

(183) Aspect 32: The UE of any of aspects 17 through 31, where the one or more photodetectors includes a first set of photodetectors positioned on the photodetector panel, the first set of photodetectors including two photodetectors aligned vertically with the hole and two photodetectors aligned horizontally with the hole.

(184) Aspect 33: The UE of any of aspects 17 through 32, where the curved optical device is a lens or a mirror.

(185) It should be noted that the methods described herein describe possible implementations, and that the operations and the steps may be rearranged or otherwise modified and that other implementations are possible. Further, aspects from two or more of the methods may be combined.

(186) Although aspects of an LTE, LTE-A, LTE-A Pro, or NR system may be described for purposes of example, and LTE, LTE-A, LTE-A Pro, or NR terminology may be used in much of the description, the techniques described herein are applicable beyond LTE, LTE-A, LTE-A Pro, or NR networks. For example, the described techniques may be applicable to various other wireless communications systems such as Ultra Mobile Broadband (UMB), Institute of Electrical and Electronics Engineers (IEEE) 802.11 (Wi-Fi), IEEE 802.16 (WiMAX), IEEE 802.20, Flash-OFDM, as well as other systems and radio technologies not explicitly mentioned herein.

(187) Information and signals described herein may be represented using any of a variety of different technologies and techniques. For example, data, instructions, commands, information, signals, bits, symbols, and chips that may be referenced throughout the description may be represented by voltages, currents, electromagnetic waves, magnetic fields or particles, optical fields or particles, or any combination thereof.

(188) The various illustrative blocks and components described in connection with the disclosure herein may be implemented or performed using a general-purpose processor, a DSP, an ASIC, a CPU, an FPGA or other programmable logic device, discrete gate or transistor logic, discrete hardware components, or any combination thereof designed to perform the functions described herein. A general-purpose processor may be a microprocessor but, in the alternative, the processor may be any processor, controller, microcontroller, or state machine. A processor may also be implemented as a combination of computing devices (e.g., a combination of a DSP and a microprocessor, multiple microprocessors, one or more microprocessors in conjunction with a DSP core, or any other such configuration). Any functions or operations described herein as being capable of being performed by a processor may be performed by multiple processors that, individually or collectively, are capable of performing the described functions or operations.

(189) The functions described herein may be implemented using hardware, software executed by a processor, firmware, or any combination thereof. If implemented using software executed by a processor, the functions may be stored as or transmitted using one or more instructions or code of a computer-readable medium. Other examples and implementations are within the scope of the disclosure and appended claims. For example, due to the nature of software, functions described herein may be implemented using software executed by a processor, hardware, firmware, hardwiring, or combinations of any of these. Features implementing functions may also be physically located at various positions, including being distributed such that portions of its functions are implemented at different physical locations.

(190) Computer-readable media includes both non-transitory computer storage media and communication media including any medium that facilitates transfer of a computer program from one location to another. A non-transitory storage medium may be any available medium that may be accessed by a general-purpose or special-purpose computer. By way of example, and not limitation, non-transitory computer-readable media may include RAM, ROM, electrically erasable programmable ROM (EEPROM), flash memory, compact disk (CD) ROM or other optical disk storage, magnetic disk storage or other magnetic storage devices, or any other non-transitory medium that may be used to carry or store desired program code means in the form of instructions or data structures and that may be accessed by a general-purpose or special-purpose computer, or a

general-purpose or special-purpose processor. Also, any connection is properly termed a computer-readable medium. For example, if the software is transmitted from a website, server, or other remote source using a coaxial cable, fiber optic cable, twisted pair, digital subscriber line (DSL), or wireless technologies such as infrared, radio, and microwave, then the coaxial cable, fiber optic cable, twisted pair, DSL, or wireless technologies such as infrared, radio, and microwave are included in the definition of computer-readable medium. Disk and disc, as used herein, include CD, laser disc, optical disc, digital versatile disc (DVD), floppy disk and Blu-ray disc. Disks may reproduce data magnetically, and discs may reproduce data optically using lasers. Combinations of the above are also included within the scope of computer-readable media. Any functions or operations described herein as being capable of being performed by a memory may be performed by multiple memories that, individually or collectively, are capable of performing the described functions or operations.

(191) As used herein, including in the claims, “or” as used in a list of items (e.g., a list of items prefaced by a phrase such as “at least one of” or “one or more of”) indicates an inclusive list such that, for example, a list of at least one of A, B, or C means A or B or C or AB or AC or BC or ABC (i.e., A and B and C). Also, as used herein, the phrase “based on” shall not be construed as a reference to a closed set of conditions. For example, an example step that is described as “based on condition A” may be based on both a condition A and a condition B without departing from the scope of the present disclosure. In other words, as used herein, the phrase “based on” shall be construed in the same manner as the phrase “based at least in part on.”

(192) As used herein, including in the claims, the article “a” before a noun is open-ended and understood to refer to “at least one” of those nouns or “one or more” of those nouns. Thus, the terms “a,” “at least one,” “one or more,” “at least one of one or more” may be interchangeable. For example, if a claim recites “a component” that performs one or more functions, each of the individual functions may be performed by a single component or by any combination of multiple components. Thus, the term “a component” having characteristics or performing functions may refer to “at least one of one or more components” having a particular characteristic or performing a particular function. Subsequent reference to a component introduced with the article “a” using the terms “the” or “said” may refer to any or all of the one or more components. For example, a component introduced with the article “a” may be understood to mean “one or more components,” and referring to “the component” subsequently in the claims may be understood to be equivalent to referring to “at least one of the one or more components.” Similarly, subsequent reference to a component introduced as “one or more components” using the terms “the” or “said” may refer to any or all of the one or more components. For example, referring to “the one or more components” subsequently in the claims may be understood to be equivalent to referring to “at least one of the one or more components.”

(193) The term “determine” or “determining” encompasses a variety of actions and, therefore, “determining” can include calculating, computing, processing, deriving, investigating, looking up (such as via looking up in a table, a database or another data structure), ascertaining and the like. Also, “determining” can include receiving (e.g., receiving information), accessing (e.g., accessing data stored in memory) and the like. Also, “determining” can include resolving, obtaining, selecting, choosing, establishing, and other such similar actions.

(194) In the appended figures, similar components or features may have the same reference label. Further, various components of the same type may be distinguished by following the reference label by a dash and a second label that distinguishes among the similar components. If just the first reference label is used in the specification, the description is applicable to any one of the similar components having the same first reference label irrespective of the second reference label, or other subsequent reference label.

(195) The description set forth herein, in connection with the appended drawings, describes example configurations and does not represent all the examples that may be implemented or that

are within the scope of the claims. The term “example” used herein means “serving as an example, instance, or illustration,” and not “preferred” or “advantageous over other examples.” The detailed description includes specific details for the purpose of providing an understanding of the described techniques. These techniques, however, may be practiced without these specific details. In some instances, known structures and devices are shown in block diagram form in order to avoid obscuring the concepts of the described examples.

(196) The description herein is provided to enable a person having ordinary skill in the art to make or use the disclosure. Various modifications to the disclosure will be apparent to a person having ordinary skill in the art, and the generic principles defined herein may be applied to other variations without departing from the scope of the disclosure. Thus, the disclosure is not limited to the examples and designs described herein but is to be accorded the broadest scope consistent with the principles and novel features disclosed herein.

Claims

1. A method for optical wireless communication by a user equipment (UE), comprising: receiving, from a network entity via an optical wireless communication link, a first optical wireless signal using one or more photodetectors positioned on a photodetector panel of the UE, wherein the photodetector panel comprises a hole around which the one or more photodetectors are positioned, and wherein the photodetector panel is located a first distance from a curved optical device of the UE via which the first optical wireless signal is received; and transmitting, to the network entity via the optical wireless communication link, a second optical wireless signal using a light source of the UE that is located a second distance from the curved optical device via which the second optical wireless signal is transmitted, wherein the second optical wireless signal passes through the hole in the photodetector panel based at least in part on the second distance being greater than the first distance.

2. The method of claim 1, wherein transmitting the second optical wireless signal comprises: transmitting the second optical wireless signal via a first lens a third distance from the curved optical device and a second lens a fourth distance from the curved optical device, wherein the first lens collimates the second optical wireless signal from the light source to the second lens and the second lens condenses the second optical wireless signal through the hole of the photodetector panel.

3. The method of claim 2, wherein: the third distance is less than the second distance and greater than the fourth distance, and the fourth distance is greater than the first distance.

4. The method of claim 2, wherein a fifth distance between the light source and the first lens corresponds to a focal length of the first lens.

5. The method of claim 2, wherein a first ratio of focal length to aperture diameter of the first lens is the same as a second ratio of focal length to aperture diameter of the curved optical device.

6. The method of claim 1, wherein receiving the first optical wireless signal comprises: receiving the first optical wireless signal using a plurality of photodetectors of the one or more photodetectors; and performing an equal gain combination operation on a plurality of signals output by the plurality of photodetectors.

7. The method of claim 6, wherein the plurality of photodetectors are associated with a same radio frequency chain.

8. The method of claim 1, wherein receiving the first optical wireless signal comprises: receiving the first optical wireless signal using a first subset of photodetectors of the one or more photodetectors and a second subset of photodetectors of the one or more photodetectors; performing a first equal gain combination operation on a first plurality of signals output by the first subset of photodetectors; and performing a second equal gain combination operation on a second plurality of signals output by the second subset of photodetectors.

9. The method of claim 8, wherein the first subset of photodetectors is associated with a first radio frequency chain and the second subset of photodetectors is associated with a second radio frequency chain.

10. The method of claim 1, wherein the first distance is less than a focal length of the curved optical device.

11. The method of claim 1, wherein the one or more photodetectors comprises a first set of photodetectors, the first set of photodetectors comprising two photodetectors aligned vertically with the hole and two photodetectors aligned horizontally with the hole.

12. The method of claim 1, wherein the curved optical device is a lens or a mirror.

13. A user equipment (UE) for optical wireless communication, comprising: a curved optical device; a photodetector panel located a first distance from the curved optical device, the photodetector panel comprising one or more photodetectors and a hole around which the one or more photodetectors are positioned; a light source located a second distance from the curved optical device; at least one processor; and at least one memory coupled with the at least one processor, with instructions stored in the at least one memory, the instructions being executable by the at least one processor, individually or in any combination, to cause the UE to: establish an optical wireless communication link with a network entity; and communicate, with the network entity via the optical wireless communication link, one or more optical wireless signals using at least one of the light source or the one or more photodetectors of the photodetector panel.

14. The UE of claim 13, wherein the instructions to communicate the one or more optical wireless signals are executable by the at least one processor, individually or in any combination, to cause the UE to: transmit, using the light source, the one or more optical wireless signals through the hole of the photodetector panel via the curved optical device based at least in part on the second distance being greater than the first distance.

15. The UE of claim 13, further comprising: a first lens a third distance from the curved optical device, wherein the third distance is less than the second distance and greater than the first distance; and a second lens a fourth distance from the curved optical device, wherein the fourth distance is greater than the first distance and less than the third distance.

16. The UE of claim 15, wherein the instructions to communicate the one or more optical wireless signals are executable by the at least one processor, individually or in any combination, to cause the UE to: transmit, using the light source, the one or more optical wireless signals via the first lens, the second lens, and the curved optical device, wherein the first lens collimates the one or more optical wireless signals from the light source to the second lens and the second lens condenses the one or more optical wireless signals through the hole of the photodetector panel and to the curved optical device.

17. The UE of claim 15, wherein a fifth distance between the light source and the first lens corresponds to a focal length of the first lens.

18. The UE of claim 15, wherein the curved optical device, the photodetector panel, the first lens, the second lens, and the light source are aligned on a same axis.

19. The UE of claim 15, wherein a first ratio of focal length to aperture diameter of the first lens is the same as a second ratio of focal length to aperture diameter of the curved optical device.

20. The UE of claim 15, wherein a diameter of the curved optical device is greater than a diameter of the first lens and a diameter of the second lens.

21. The UE of claim 13, wherein the instructions to communicate the one or more optical wireless signals are executable by the at least one processor, individually or in any combination, to cause the UE to: receive the one or more optical wireless signals using a plurality of photodetectors of the one or more photodetectors; and performing an equal gain combination operation on a plurality of signals output by the plurality of photodetectors.

22. The UE of claim 21, wherein the plurality of photodetectors are associated with a same radio frequency chain.

23. The UE of claim 13, wherein the instructions to communicate the one or more optical wireless signals are executable by the at least one processor, individually or in any combination, to cause the UE to: receive the one or more optical wireless signals using a first subset of photodetectors of the one or more photodetectors and a second subset of photodetectors of the one or more photodetectors; performing a first equal gain combination operation on a first plurality of signals output by the first subset of photodetectors; and performing a second equal gain combination operation on a second plurality of signals output by the second subset of photodetectors.
24. The UE of claim 23, wherein the first subset of photodetectors is associated with a first radio frequency chain and the second subset of photodetectors is associated with a second radio frequency chain.
25. The UE of claim 23, wherein each photodetector of the first subset of photodetectors is a first size and each photodetector of the second subset of photodetectors is a second size, the second size being larger than the first size.
26. The UE of claim 13, wherein the first distance is less than a focal length of the curved optical device.
27. The UE of claim 13, wherein the one or more photodetectors comprises a first set of photodetectors positioned on the photodetector panel, the first set of photodetectors comprising two photodetectors aligned vertically with the hole and two photodetectors aligned horizontally with the hole.
28. The UE of claim 13, wherein the curved optical device is a lens or a mirror.
29. A user equipment (UE) for optical wireless communication, comprising: at least one processor; and at least one memory coupled with the at least one processor, with instructions stored in the at least one memory, the instructions being executable by the at least one processor, individually or in any combination, to cause the UE to: receive, from a network entity via an optical wireless communication link, a first optical wireless signal using one or more photodetectors positioned on a photodetector panel of the UE, wherein the photodetector panel comprises a hole around which the one or more photodetectors are positioned, and wherein the photodetector panel is located a first distance from a curved optical device of the UE via which the first optical wireless signal is received; and transmit, to the network entity via the optical wireless communication link, a second optical wireless signal using a light source of the UE that is located a second distance from the curved optical device via which the second optical wireless signal is transmitted, wherein the second optical wireless signal passes through the hole in the photodetector panel based at least in part on the second distance being greater than the first distance.
30. A user equipment (UE) for optical wireless communication, comprising: means for receiving, from a network entity via an optical wireless communication link, a first optical wireless signal using one or more photodetectors positioned on a photodetector panel of the UE, wherein the photodetector panel comprises a hole around which the one or more photodetectors are positioned, and wherein the photodetector panel is located a first distance from a curved optical device of the UE via which the first optical wireless signal is received; and means for transmitting, to the network entity via the optical wireless communication link, a second optical wireless signal using a light source of the UE that is located a second distance from the curved optical device via which the second optical wireless signal is transmitted, wherein the second optical wireless signal passes through the hole in the photodetector panel based at least in part on the second distance being greater than the first distance.
-