

US Patent & Trademark Office

Patent Public Search | Text View

United States Patent	12402025
Kind Code	B2
Date of Patent	August 26, 2025
Inventor(s)	He; Linhai

Beam failure detection measurement relaxation for cells with multiple transmission reception points

Abstract

Methods, systems, and devices for wireless communications are described. In some examples, a user equipment (UE) may receive a control message indicating one or more parameters for measuring multiple reference signals. The one or more parameters may be associated with adjusting one or more measurement periodicities. The UE may measure respective channel quality metrics for the multiple reference signals, where the multiple reference signals includes a first set of reference signals associated with a first transmission reception point. The UE may adjust a measurement periodicity for the first set of reference signals according to a first parameter of the one or more parameters based on a first channel quality metric associated with the first set of reference signals, where the measurement periodicity for the first set of reference signals is separately adjustable relative to a measurement periodicity for the second set of reference.

Inventors:	He; Linhai (San Diego, CA)
Applicant:	QUALCOMM Incorporated (San Diego, CA)
Family ID:	1000008780385
Assignee:	QUALCOMM Incorporated (San Diego, CA)
Appl. No.:	18/163109
Filed:	February 01, 2023

Prior Publication Data

Document Identifier	Publication Date
US 20240259851 A1	Aug. 01, 2024

Publication Classification

Int. Cl.: H04W24/10 (20090101); H04L5/00 (20060101)

U.S. Cl.:

CPC **H04W24/10** (20130101); **H04L5/0051** (20130101);

Field of Classification Search

CPC: H04W (24/10); H04W (36/0088); H04W (36/085); H04W (36/0094); H04W (36/0058);
 H04L (5/0051); H04B (7/0695); H04B (7/088)

References Cited

U.S. PATENT DOCUMENTS

Patent No.	Issued Date	Patentee Name	U.S. Cl.	CPC
2022/0225121	12/2021	Wanuga et al.	N/A	N/A
2022/0302983	12/2021	Zhou	N/A	H04B 7/0695
2023/0019889	12/2022	He	N/A	N/A
2024/0214838	12/2023	Shen	N/A	H04W 72/53

FOREIGN PATENT DOCUMENTS

Patent No.	Application Date	Country	CPC
2021254590	12/2020	WO	N/A
2022011530	12/2021	WO	N/A
2024025449	12/2023	WO	N/A

OTHER PUBLICATIONS

Fujitsu: “BFD relaxation for serving cell with mTRP”, 3GPP TSG-RAN WG2 Meeting #120, R2-2211843, 3rd Generation Partnership Project (3GPP), Mobile Competence Centre, 650, Route Des Lucioles, F-06921 Sophia-Antipolis Cedex, France, vol. 3GPP RAN 2, No. Toulouse, FR, Nov. 14, 2022-Nov. 18, 2022, Nov. 4, 2022, 2 Pages, XP052215936, paragraph [002.]. cited by applicant
International Search Report and Written Opinion—PCT/US2023/085129—ISA/EPO—Apr. 8, 2024 (2302136WO). cited by applicant
Vivo: “Report of [AT118-e][003][ePowSav] RLM and BFD relaxation (vivo)”, 3GPP TSG-RAN WG2 Meeting #119-e, R2-2209003, 3rd Generation Partnership Project (3GPP), Mobile Competence Centre, 650, Route Des Lucioles, F-06921 Sophia-Antipolis Cedex, France, vol. RAN WG2, No. Electronic, Aug. 17, 2022-Aug. 26, 2022, Sep. 3, 2022, 26 Pages, XP052262263, paragraph [03.2]. cited by applicant

Primary Examiner: Ngo; Chuong A

Attorney, Agent or Firm: Holland & Hart LLP/Qualcomm Incorporated

Background/Summary

FIELD OF TECHNOLOGY

(1) The following relates to wireless communications, including beam failure detection (BFD) measurement relaxation for cells with multiple transmission reception points (TRPs).

BACKGROUND

(2) Wireless communications systems are widely deployed to provide various types of

communication content such as voice, video, packet data, messaging, broadcast, and so on. These systems may be capable of supporting communication with multiple users by sharing the available system resources (e.g., time, frequency, and power). Examples of such multiple-access systems include fourth generation (4G) systems such as Long Term Evolution (LTE) systems, LTE-Advanced (LTE-A) systems, or LTE-A Pro systems, and fifth generation (5G) systems which may be referred to as New Radio (NR) systems. These systems may employ technologies such as code division multiple access (CDMA), time division multiple access (TDMA), frequency division multiple access (FDMA), orthogonal FDMA (OFDMA), or discrete Fourier transform spread orthogonal frequency division multiplexing (DFT-S-OFDM). A wireless multiple-access communications system may include one or more base stations, each supporting wireless communication for communication devices, which may be known as user equipment (UE).

SUMMARY

(3) The described techniques relate to improved methods, systems, devices, and apparatuses that support beam failure detection (BFD) measurement relaxation for cells with multiple transmission reception points (TRPs). Generally, the techniques described herein may enable a user equipment (UE), associated with multiple TRPs of a cell, to adjust a measurement periodicity for at least a first set of reference signals from a plurality of reference signals associated with the multiple TRPs. For example, the UE may receive a control message indicative of one or more parameters associated with measuring the multiple reference signals, where the one or more parameters are associated with one or more measurement periodicities associated with the multiple reference signals. Additionally, the UE may measure respective channel quality metrics for the multiple reference signals, where the multiple reference signals includes the first set of reference signals associated with a first TRP of the cell and a second set of reference signals associated with a second TRP of the cell. The UE may adjust a measurement periodicity for the first set of reference signals according to a first parameter of the one or more parameters based on a first channel quality metric associated with the first set of reference signals. The measurement periodicity for the first set of reference signals may be separately adjustable relative to a measurement periodicity for the second set of reference signals. As such, the UE may maintain the measurement periodicity for the second set of reference signals or may adjust the measurement periodicity for the second set of reference signals based on a second channel quality metric associated with the second set of reference signals.

(4) A method for wireless communications at a UE is described. The method may include receiving a control message indicative of one or more parameters associated with measuring a set of multiple reference signals, where the one or more parameters are associated with adjusting one or more measurement periodicities associated with the set of multiple reference signals, measuring respective channel quality metrics for the set of multiple reference signals, where the set of multiple reference signals includes a first set of reference signals associated with a first TRP of a cell and a second set of reference signals associated with a second TRP of the cell, and adjusting a measurement periodicity for the first set of reference signals according to a first parameter of the one or more parameters based on a first channel quality metric associated with the first set of reference signals, where the measurement periodicity for the first set of reference signals is separately adjustable relative to a measurement periodicity for the second set of reference signals.

(5) An apparatus for wireless communications is described. The apparatus may include a memory, a transceiver, and at least one processor of a UE, the at least one processor coupled with the memory and the transceiver. The at least one processor may be configured to cause the apparatus to receive, via the transceiver, a control message indicative of one or more parameters associated with measuring a set of multiple reference signals, where the one or more parameters are associated with adjusting one or more measurement periodicities associated with the set of multiple reference signals, measure respective channel quality metrics for the set of multiple reference signals, where the set of multiple reference signals includes a first set of reference signals associated with a first

TRP of a cell and a second set of reference signals associated with a second TRP of the cell, and adjust a measurement periodicity for the first set of reference signals according to a first parameter of the one or more parameters based on a first channel quality metric associated with the first set of reference signals, where the measurement periodicity for the first set of reference signals is separately adjustable relative to a measurement periodicity for the second set of reference signals.

(6) Another apparatus for wireless communications at a UE is described. The apparatus may include means for receiving a control message indicative of one or more parameters associated with measuring a set of multiple reference signals, where the one or more parameters are associated with adjusting one or more measurement periodicities associated with the set of multiple reference signals, means for measuring respective channel quality metrics for the set of multiple reference signals, where the set of multiple reference signals includes a first set of reference signals associated with a first TRP of a cell and a second set of reference signals associated with a second TRP of the cell, and means for adjusting a measurement periodicity for the first set of reference signals according to a first parameter of the one or more parameters based on a first channel quality metric associated with the first set of reference signals, where the measurement periodicity for the first set of reference signals is separately adjustable relative to a measurement periodicity for the second set of reference signals.

(7) A non-transitory computer-readable medium storing code for wireless communications at a UE is described. The code may include instructions executable by a processor to receive a control message indicative of one or more parameters associated with measuring a set of multiple reference signals, where the one or more parameters are associated with adjusting one or more measurement periodicities associated with the set of multiple reference signals, measure respective channel quality metrics for the set of multiple reference signals, where the set of multiple reference signals includes a first set of reference signals associated with a first TRP of a cell and a second set of reference signals associated with a second TRP of the cell, and adjust a measurement periodicity for the first set of reference signals according to a first parameter of the one or more parameters based on a first channel quality metric associated with the first set of reference signals, where the measurement periodicity for the first set of reference signals is separately adjustable relative to a measurement periodicity for the second set of reference signals.

(8) In some examples of the method, apparatuses, and non-transitory computer-readable medium described herein, adjusting the measurement periodicity for the first set of reference signals may include operations, features, means, or instructions for adjusting a time gap between successive measurements for the first set of reference signals based on a first SINR ratio associated with the first set of reference signals exceeding a first threshold.

(9) In some examples of the method, apparatuses, and non-transitory computer-readable medium described herein, the control message indicates the first threshold associated with the first set of reference signals and a second threshold associated with the second set of reference signals.

(10) In some examples of the method, apparatuses, and non-transitory computer-readable medium described herein, the first threshold and the second threshold may be the same based on the first TRP and the second TRP being associated with the cell.

(11) In some examples of the method, apparatuses, and non-transitory computer-readable medium described herein, the first threshold and the second threshold may be different based on the first TRP being associated with the first set of reference signals and the second TRP being associated with the second set of reference signals.

(12) Some examples of the method, apparatuses, and non-transitory computer-readable medium described herein may further include operations, features, means, or instructions for maintaining the measurement periodicity for the second set of reference signals based on a second channel quality metric associated with the second set of reference signals failing to exceed a threshold.

(13) Some examples of the method, apparatuses, and non-transitory computer-readable medium described herein may further include operations, features, means, or instructions for maintaining

the measurement periodicity for the second set of reference signals may be based on a SINR ratio associated with the second set of reference signals failing to exceed a threshold and the second channel quality metric may be the SINR ratio.

(14) Some examples of the method, apparatuses, and non-transitory computer-readable medium described herein may further include operations, features, means, or instructions for adjusting the measurement periodicity for the second set of reference signals according to a second parameter of the one or more parameters based on a second channel quality metric associated with the second set of reference signals.

(15) In some examples of the method, apparatuses, and non-transitory computer-readable medium described herein, the first parameter and the second parameter may be the same based on the first TRP and the second TRP being associated with the cell.

(16) In some examples of the method, apparatuses, and non-transitory computer-readable medium described herein, the first parameter and the second parameter may be different based on the first TRP being associated with the first set of reference signals and the second TRP being associated with the second set of reference signals.

(17) Some examples of the method, apparatuses, and non-transitory computer-readable medium described herein may further include operations, features, means, or instructions for adjusting the measurement periodicity for the second set of reference signals may be based on a SINR ratio associated with the second set of reference signals exceeding a threshold and the second channel quality metric may be the SINR ratio.

(18) Some examples of the method, apparatuses, and non-transitory computer-readable medium described herein may further include operations, features, means, or instructions for transmitting a report indicating the adjustment of the measurement periodicity for the first set of reference signals, where the report includes an indication of a first CORESET identifier associated with the first TRP of the cell.

(19) In some examples of the method, apparatuses, and non-transitory computer-readable medium described herein, the report further indicates an adjustment of the measurement periodicity for the second set of reference signals and the report includes an indication of a second CORESET identifier associated with the second TRP of the cell.

(20) In some examples of the method, apparatuses, and non-transitory computer-readable medium described herein, the report may be transmitted via UE assistance information.

(21) Some examples of the method, apparatuses, and non-transitory computer-readable medium described herein may further include operations, features, means, or instructions for determining a mobility metric associated with the UE, where adjusting the measurement periodicity for the first set of reference signals may be based on the mobility metric associated with the UE being associated with a low mobility scenario.

(22) In some examples of the method, apparatuses, and non-transitory computer-readable medium described herein, the mobility metric may be associated with the first TRP and the second TRP based on the first TRP and the second TRP being associated with the cell.

(23) Some examples of the method, apparatuses, and non-transitory computer-readable medium described herein may further include operations, features, means, or instructions for receiving a second control message indicative of a set of multiple CORESET identifiers, where each CORESET identifier may be associated with a respective TRP of the cell.

(24) Some examples of the method, apparatuses, and non-transitory computer-readable medium described herein may further include operations, features, means, or instructions for adjusting the measurement periodicity for the first set of reference signals includes increasing a time gap between successive measurements of the first set of reference signals based on the first parameter.

(25) A method for wireless communications at a network entity is described. The method may include transmitting a first control message indicative of a set of multiple CORESET identifiers, where each CORESET identifier is associated with a respective TRP of a cell, transmitting a

second control message indicative of one or more parameters associated with adjusting one or more measurement periodicities associated with measurements of a set of multiple reference signals by a UE, where the set of multiple reference signals includes a first set of reference signals associated with a first TRP of the cell and a second set of reference signals associated with a second TRP of the cell, and receiving a report indicative of an adjustment, by the UE, of a measurement periodicity for the first set of reference signals according to a first parameter of the one or more parameters, where the measurement periodicity for the first set of reference signals is separately adjustable relative to a measurement periodicity for the second set of reference signals.

(26) An apparatus for wireless communications at is described. The apparatus may include a memory and at least one processor of a network entity, the at least one processor coupled with the memory. The at least one processor may be configured to cause the apparatus to transmit a first control message indicative of a set of multiple CORESET identifiers, where each CORESET identifier is associated with a respective TRP of a cell, transmit a second control message indicative of one or more parameters associated with adjusting one or more measurement periodicities associated with measurements of a set of multiple reference signals by a UE, where the set of multiple reference signals includes a first set of reference signals associated with a first TRP of the cell and a second set of reference signals associated with a second TRP of the cell, and receive a report indicative of an adjustment, by the UE, of a measurement periodicity for the first set of reference signals according to a first parameter of the one or more parameters, where the measurement periodicity for the first set of reference signals is separately adjustable relative to a measurement periodicity for the second set of reference signals.

(27) Another apparatus for wireless communications at a network entity is described. The apparatus may include means for transmitting a first control message indicative of a set of multiple CORESET identifiers, where each CORESET identifier is associated with a respective TRP of a cell, means for transmitting a second control message indicative of one or more parameters associated with adjusting one or more measurement periodicities associated with measurements of a set of multiple reference signals by a UE, where the set of multiple reference signals includes a first set of reference signals associated with a first TRP of the cell and a second set of reference signals associated with a second TRP of the cell, and means for receiving a report indicative of an adjustment, by the UE, of a measurement periodicity for the first set of reference signals according to a first parameter of the one or more parameters, where the measurement periodicity for the first set of reference signals is separately adjustable relative to a measurement periodicity for the second set of reference signals.

(28) A non-transitory computer-readable medium storing code for wireless communications at a network entity is described. The code may include instructions executable by a processor to transmit a first control message indicative of a set of multiple CORESET identifiers, where each CORESET identifier is associated with a respective TRP of a cell, transmit a second control message indicative of one or more parameters associated with adjusting one or more measurement periodicities associated with measurements of a set of multiple reference signals by a UE, where the set of multiple reference signals includes a first set of reference signals associated with a first TRP of the cell and a second set of reference signals associated with a second TRP of the cell, and receive a report indicative of an adjustment, by the UE, of a measurement periodicity for the first set of reference signals according to a first parameter of the one or more parameters, where the measurement periodicity for the first set of reference signals is separately adjustable relative to a measurement periodicity for the second set of reference signals.

(29) In some examples of the method, apparatuses, and non-transitory computer-readable medium described herein, first control message indicates one or more thresholds associated with channel quality metrics for the set of multiple reference signals, including a first threshold associated with the first set of reference signals and a second channel quality threshold associated with the second set of reference signals.

- (30) In some examples of the method, apparatuses, and non-transitory computer-readable medium described herein, the first threshold and the second threshold may be the same based on the first TRP and the second TRP being associated with the cell.
- (31) In some examples of the method, apparatuses, and non-transitory computer-readable medium described herein, the first threshold and the second threshold may be different based on the first TRP being associated with the first set of reference signals and the second TRP being associated with the second set of reference signals.
- (32) In some examples of the method, apparatuses, and non-transitory computer-readable medium described herein, the report includes an indication of a CORESET identifier of the set of multiple CORESET identifiers and the CORESET identifier may be associated with the first TRP of the cell.
- (33) In some examples of the method, apparatuses, and non-transitory computer-readable medium described herein, the report further indicates an adjustment, by the UE, of the measurement periodicity for the second set of reference signals according to a second parameter of the one or more parameters and the report includes an indication of a CORESET identifier associated with the second TRP of the cell.
- (34) In some examples of the method, apparatuses, and non-transitory computer-readable medium described herein, the first parameter and the second parameter may be the same based on the first TRP and the second TRP being associated with the cell.
- (35) In some examples of the method, apparatuses, and non-transitory computer-readable medium described herein, the first parameter and the second parameter may be different based on the first TRP being associated with the first set of reference signals and the second TRP being associated with the second set of reference signals.
- (36) In some examples of the method, apparatuses, and non-transitory computer-readable medium described herein, the report may be received via UE assistance information.
-

Description

BRIEF DESCRIPTION OF THE DRAWINGS

- (1) FIG. 1 illustrates an example of a wireless communications system that supports beam failure detection (BFD) measurement relaxation for cells with multiple transmission reception points (TRPs) in accordance with one or more aspects of the present disclosure.
- (2) FIG. 2 illustrates an example of a wireless communications system that supports BFD measurement relaxation for cells with multiple TRPs in accordance with one or more aspects of the present disclosure.
- (3) FIG. 3 illustrates an example of a process flow that supports BFD measurement relaxation for cells with multiple TRPs in accordance with one or more aspects of the present disclosure.
- (4) FIGS. 4 and 5 illustrate block diagrams of devices that support BFD measurement relaxation for cells with multiple TRPs in accordance with one or more aspects of the present disclosure.
- (5) FIG. 6 illustrates a block diagram of a communications manager that supports BFD measurement relaxation for cells with multiple TRPs in accordance with one or more aspects of the present disclosure.
- (6) FIG. 7 illustrates a diagram of a system including a device that supports BFD measurement relaxation for cells with multiple TRPs in accordance with one or more aspects of the present disclosure.
- (7) FIGS. 8 and 9 illustrate block diagrams of devices that support BFD measurement relaxation for cells with multiple TRPs in accordance with one or more aspects of the present disclosure.
- (8) FIG. 10 illustrates a block diagram of a communications manager that supports BFD measurement relaxation for cells with multiple TRPs in accordance with one or more aspects of the present disclosure.

(9) FIG. 11 illustrates a diagram of a system including a device that supports BFD measurement relaxation for cells with multiple TRPs in accordance with one or more aspects of the present disclosure.

(10) FIGS. 12 through 14 illustrate flowcharts showing methods that support BFD measurement relaxation for cells with multiple TRPs in accordance with one or more aspects of the present disclosure.

DETAILED DESCRIPTION

(11) Some wireless communications systems may support beam failure detection (BFD). For example, a user equipment (UE) may periodically monitor one or more reference signals associated with a network entity (e.g., serving cell) to detect beam failure. In some examples, the UE may be in a low-mobility scenario and respective channel quality metrics associated with the one or more reference signals may exceed a threshold. In such cases, the UE may increase the periodicity at which the UE monitors the one or more reference signals associated with the network entity for BFD. In other words, the UE may measure the one or more reference signals less often, such as by increasing a time gap between measuring the one or more reference signals, which may be referred to BFD measurement relaxation

(12) In some cases, the network entity may be associated with multiple transmission reception points (TRPs), and each TRP may be associated with one or more reference signals, which may be referred to as reference signal sets. For example, the multiple TRPs may include a first TRP associated with a first reference signal set and a second TRP associated with a second reference signal set. In such cases, the UE may measure channel quality metrics of each reference signal of the first reference signal set and the second reference signal set to determine whether the UE may perform BFD measurement relaxation. That is, the UE may be in a low mobility scenario and a channel quality metric associated with the first reference signal set may exceed the threshold while a channel quality metric associated with the second reference signal set may fail to exceed the threshold. In such cases, the UE may refrain from adjusting a measurement periodicity of the first reference signal set and a measurement periodicity of the second reference signal set based on the channel quality metric associated with the second reference signal set failing to exceed the threshold (e.g., despite the channel quality metric associated with the first reference signal set exceeding the threshold), resulting in inefficient power consumption and resource utilization.

(13) Accordingly, techniques described herein may support per-TRP BFD measurement relaxation. In such cases, a UE may receive control signaling indicating one or more parameters associated with adjusting a measurement periodicity of multiple reference signal sets, the multiple reference signal sets including a first reference signal set associated with a first TRP of a cell and a second reference signal set associated with a second TRP of the cell. The one or more parameters may include a first threshold and a first relaxation factor associated with the first reference signal set and a second threshold and second relaxation threshold associated with the second reference signal set. As such, the UE may measure channel quality metrics of each reference signal set and may adjust a measurement periodicity of the first reference signal set, a measurement periodicity of the second reference signal set, or both, based on respective channel quality metrics. For example, the UE may adjust the measurement periodicity of the first reference signal set according to the first relaxation factor based on a first channel quality metric associated with the first reference signal set exceeding the threshold. Conversely, the UE may maintain the measurement periodicity of the second reference signal set based on a second channel quality metric associated with the second reference signal set failing to exceed the second threshold.

(14) Thus, for example, for a multi-TRP cell, one or more criteria (e.g., signal quality criteria, mobility criteria, or both) associated with relaxation of the periodicity with which BFD-related measurements are performed may be evaluated on a per-TRP basis (e.g., rather than on a cell-wide basis). Evaluating such criteria on a per-TRP basis may beneficially allow relaxation of the periodicity of BFD measurements for any TRP for which the associated criteria are met, even if one

or more other TRPs of the same cell do not qualify for relaxation, thereby enhancing power savings, among other potential benefits.

(15) Aspects of the disclosure are initially described in the context of wireless communications systems. Aspects of the disclosure are then described in the context of a process flow. Aspects of the disclosure are further illustrated by and described with reference to apparatus diagrams, system diagrams, and flowcharts that relate to BFD measurement relaxation for cells with multiple TRPs.

(16) FIG. 1 illustrates an example of a wireless communications system **100** that supports BFD measurement relaxation for cells with multiple TRPs in accordance with one or more aspects of the present disclosure. The wireless communications system **100** may include one or more network entities **105**, one or more UEs **115**, and a core network **130**. In some examples, the wireless communications system **100** may be a Long Term Evolution (LTE) network, an LTE-Advanced (LTE-A) network, an LTE-A Pro network, a New Radio (NR) network, or a network operating in accordance with other systems and radio technologies, including future systems and radio technologies not explicitly mentioned herein.

(17) The network entities **105** may be dispersed throughout a geographic area to form the wireless communications system **100** and may include devices in different forms or having different capabilities. In various examples, a network entity **105** may be referred to as a network element, a mobility element, a radio access network (RAN) node, or network equipment, among other nomenclature. In some examples, network entities **105** and UEs **115** may wirelessly communicate via one or more communication links **125** (e.g., a radio frequency (RF) access link). For example, a network entity **105** may support a coverage area **110** (e.g., a geographic coverage area) over which the UEs **115** and the network entity **105** may establish one or more communication links **125**. The coverage area **110** may be an example of a geographic area over which a network entity **105** and a UE **115** may support the communication of signals according to one or more radio access technologies (RATs).

(18) The UEs **115** may be dispersed throughout a coverage area **110** of the wireless communications system **100**, and each UE **115** may be stationary, or mobile, or both at different times. The UEs **115** may be devices in different forms or having different capabilities. Some example UEs **115** are illustrated in FIG. 1. The UEs **115** described herein may be capable of supporting communications with various types of devices, such as other UEs **115** or network entities **105**, as shown in FIG. 1.

(19) As described herein, a node of the wireless communications system **100**, which may be referred to as a network node, or a wireless node, may be a network entity **105** (e.g., any network entity described herein), a UE **115** (e.g., any UE described herein), a network controller, an apparatus, a device, a computing system, one or more components, or another suitable processing entity configured to perform any of the techniques described herein. For example, a node may be a UE **115**. As another example, a node may be a network entity **105**. As another example, a first node may be configured to communicate with a second node or a third node. In one aspect of this example, the first node may be a UE **115**, the second node may be a network entity **105**, and the third node may be a UE **115**. In another aspect of this example, the first node may be a UE **115**, the second node may be a network entity **105**, and the third node may be a network entity **105**. In yet other aspects of this example, the first, second, and third nodes may be different relative to these examples. Similarly, reference to a UE **115**, network entity **105**, apparatus, device, computing system, or the like may include disclosure of the UE **115**, network entity **105**, apparatus, device, computing system, or the like being a node. For example, disclosure that a UE **115** is configured to receive information from a network entity **105** also discloses that a first node is configured to receive information from a second node.

(20) In some examples, network entities **105** may communicate with the core network **130**, or with one another, or both. For example, network entities **105** may communicate with the core network **130** via one or more backhaul communication links **120** (e.g., in accordance with an S1, N2, N3, or

other interface protocol). In some examples, network entities **105** may communicate with one another via a backhaul communication link **120** (e.g., in accordance with an X2, Xn, or other interface protocol) either directly (e.g., directly between network entities **105**) or indirectly (e.g., via a core network **130**). In some examples, network entities **105** may communicate with one another via a midhaul communication link **162** (e.g., in accordance with a midhaul interface protocol) or a fronthaul communication link **168** (e.g., in accordance with a fronthaul interface protocol), or any combination thereof. The backhaul communication links **120**, midhaul communication links **162**, or fronthaul communication links **168** may be or include one or more wired links (e.g., an electrical link, an optical fiber link), one or more wireless links (e.g., a radio link, a wireless optical link), among other examples or various combinations thereof. A UE **115** may communicate with the core network **130** via a communication link **155**.

(21) One or more of the network entities **105** described herein may include or may be referred to as a base station **140** (e.g., a base transceiver station, a radio base station, an NR base station, an access point, a radio transceiver, a NodeB, an eNodeB (eNB), a next-generation NodeB or a giga-NodeB (either of which may be referred to as a gNB), a 5G NB, a next-generation eNB (ng-eNB), a Home NodeB, a Home eNodeB, or other suitable terminology). In some examples, a network entity **105** (e.g., a base station **140**) may be implemented in an aggregated (e.g., monolithic, standalone) base station architecture, which may be configured to utilize a protocol stack that is physically or logically integrated within a single network entity **105** (e.g., a single RAN node, such as a base station **140**).

(22) In some examples, a network entity **105** may be implemented in a disaggregated architecture (e.g., a disaggregated base station architecture, a disaggregated RAN architecture), which may be configured to utilize a protocol stack that is physically or logically distributed among two or more network entities **105**, such as an integrated access backhaul (IAB) network, an open RAN (O-RAN) (e.g., a network configuration sponsored by the O-RAN Alliance), or a virtualized RAN (vRAN) (e.g., a cloud RAN (C-RAN)). For example, a network entity **105** may include one or more of a central unit (CU) **160**, a distributed unit (DU) **165**, a radio unit (RU) **170**, a RAN Intelligent Controller (RIC) **175** (e.g., a Near-Real Time RIC (Near-RT RIC), a Non-Real Time RIC (Non-RT RIC)), a Service Management and Orchestration (SMO) **180** system, or any combination thereof. An RU **170** may also be referred to as a radio head, a smart radio head, a remote radio head (RRH), a remote radio unit (RRU), or a TRP (TRP). One or more components of the network entities **105** in a disaggregated RAN architecture may be co-located, or one or more components of the network entities **105** may be located in distributed locations (e.g., separate physical locations). In some examples, one or more network entities **105** of a disaggregated RAN architecture may be implemented as virtual units (e.g., a virtual CU (VCU), a virtual DU (VDU), a virtual RU (VRU)).

(23) The split of functionality between a CU **160**, a DU **165**, and an RU **170** is flexible and may support different functionalities depending on which functions (e.g., network layer functions, protocol layer functions, baseband functions, RF functions, and any combinations thereof) are performed at a CU **160**, a DU **165**, or an RU **170**. For example, a functional split of a protocol stack may be employed between a CU **160** and a DU **165** such that the CU **160** may support one or more layers of the protocol stack and the DU **165** may support one or more different layers of the protocol stack. In some examples, the CU **160** may host upper protocol layer (e.g., layer 3 (L3), layer 2 (L2)) functionality and signaling (e.g., Radio Resource Control (RRC), service data adaptation protocol (SDAP), Packet Data Convergence Protocol (PDCP)). The CU **160** may be connected to one or more DUs **165** or RUs **170**, and the one or more DUs **165** or RUs **170** may host lower protocol layers, such as layer 1 (L1) (e.g., physical (PHY) layer) or L2 (e.g., radio link control (RLC) layer, medium access control (MAC) layer) functionality and signaling, and may each be at least partially controlled by the CU **160**. Additionally, or alternatively, a functional split of the protocol stack may be employed between a DU **165** and an RU **170** such that the DU **165** may support one or more layers of the protocol stack and the RU **170** may support one or more

different layers of the protocol stack. The DU **165** may support one or multiple different cells (e.g., via one or more RUs **170**). In some cases, a functional split between a CU **160** and a DU **165**, or between a DU **165** and an RU **170** may be within a protocol layer (e.g., some functions for a protocol layer may be performed by one of a CU **160**, a DU **165**, or an RU **170**, while other functions of the protocol layer are performed by a different one of the CU **160**, the DU **165**, or the RU **170**). A CU **160** may be functionally split further into CU control plane (CU-CP) and CU user plane (CU-UP) functions. A CU **160** may be connected to one or more DUs **165** via a midhaul communication link **162** (e.g., F1, F1-c, F1-u), and a DU **165** may be connected to one or more RUs **170** via a fronthaul communication link **168** (e.g., open fronthaul (FH) interface). In some examples, a midhaul communication link **162** or a fronthaul communication link **168** may be implemented in accordance with an interface (e.g., a channel) between layers of a protocol stack supported by respective network entities **105** that are in communication via such communication links.

(24) In wireless communications systems (e.g., wireless communications system **100**), infrastructure and spectral resources for radio access may support wireless backhaul link capabilities to supplement wired backhaul connections, providing an IAB network architecture (e.g., to a core network **130**). In some cases, in an IAB network, one or more network entities **105** (e.g., IAB nodes **104**) may be partially controlled by each other. One or more IAB nodes **104** may be referred to as a donor entity or an IAB donor. One or more DUs **165** or one or more RUs **170** may be partially controlled by one or more CUs **160** associated with a donor network entity **105** (e.g., a donor base station **140**). The one or more donor network entities **105** (e.g., IAB donors) may be in communication with one or more additional network entities **105** (e.g., IAB nodes **104**) via supported access and backhaul links (e.g., backhaul communication links **120**). IAB nodes **104** may include an IAB mobile termination (IAB-MT) controlled (e.g., scheduled) by DUs **165** of a coupled IAB donor. An IAB-MT may include an independent set of antennas for relay of communications with UEs **115**, or may share the same antennas (e.g., of an RU **170**) of an IAB node **104** used for access via the DU **165** of the IAB node **104** (e.g., referred to as virtual IAB-MT (vIAB-MT)). In some examples, the IAB nodes **104** may include DUs **165** that support communication links with additional entities (e.g., IAB nodes **104**, UEs **115**) within the relay chain or configuration of the access network (e.g., downstream). In such cases, one or more components of the disaggregated RAN architecture (e.g., one or more IAB nodes **104** or components of IAB nodes **104**) may be configured to operate according to the techniques described herein.

(25) For instance, an access network (AN) or RAN may include communications between access nodes (e.g., an IAB donor), IAB nodes **104**, and one or more UEs **115**. The IAB donor may facilitate connection between the core network **130** and the AN (e.g., via a wired or wireless connection to the core network **130**). That is, an IAB donor may refer to a RAN node with a wired or wireless connection to core network **130**. The IAB donor may include a CU **160** and at least one DU **165** (e.g., and RU **170**), in which case the CU **160** may communicate with the core network **130** via an interface (e.g., a backhaul link). IAB donor and IAB nodes **104** may communicate via an F1 interface according to a protocol that defines signaling messages (e.g., an F1 AP protocol). Additionally, or alternatively, the CU **160** may communicate with the core network via an interface, which may be an example of a portion of backhaul link, and may communicate with other CUs **160** (e.g., a CU **160** associated with an alternative IAB donor) via an Xn-C interface, which may be an example of a portion of a backhaul link.

(26) An IAB node **104** may refer to a RAN node that provides IAB functionality (e.g., access for UEs **115**, wireless self-backhauling capabilities). A DU **165** may act as a distributed scheduling node towards child nodes associated with the IAB node **104**, and the IAB-MT may act as a scheduled node towards parent nodes associated with the IAB node **104**. That is, an IAB donor may be referred to as a parent node in communication with one or more child nodes (e.g., an IAB donor may relay transmissions for UEs through one or more other IAB nodes **104**). Additionally, or

alternatively, an IAB node **104** may also be referred to as a parent node or a child node to other IAB nodes **104**, depending on the relay chain or configuration of the AN. Therefore, the IAB-MT entity of IAB nodes **104** may provide a Uu interface for a child IAB node **104** to receive signaling from a parent IAB node **104**, and the DU interface (e.g., DUs **165**) may provide a Uu interface for a parent IAB node **104** to signal to a child IAB node **104** or UE **115**.

(27) For example, IAB node **104** may be referred to as a parent node that supports communications for a child IAB node, or referred to as a child IAB node associated with an IAB donor, or both. The IAB donor may include a CU **160** with a wired or wireless connection (e.g., a backhaul communication link **120**) to the core network **130** and may act as parent node to IAB nodes **104**. For example, the DU **165** of IAB donor may relay transmissions to UEs **115** through IAB nodes **104**, or may directly signal transmissions to a UE **115**, or both. The CU **160** of IAB donor may signal communication link establishment via an F1 interface to IAB nodes **104**, and the IAB nodes **104** may schedule transmissions (e.g., transmissions to the UEs **115** relayed from the IAB donor) through the DUs **165**. That is, data may be relayed to and from IAB nodes **104** via signaling via an NR Uu interface to MT of the IAB node **104**. Communications with IAB node **104** may be scheduled by a DU **165** of IAB donor and communications with IAB node **104** may be scheduled by DU **165** of IAB node **104**.

(28) In the case of the techniques described herein applied in the context of a disaggregated RAN architecture, one or more components of the disaggregated RAN architecture may be configured to support BFD measurement relaxation for cells with multiple TRPs as described herein. For example, some operations described as being performed by a UE **115** or a network entity **105** (e.g., a base station **140**) may additionally, or alternatively, be performed by one or more components of the disaggregated RAN architecture (e.g., IAB nodes **104**, DUs **165**, CUs **160**, RUs **170**, RIC **175**, SMO **180**).

(29) A UE **115** may include or may be referred to as a mobile device, a wireless device, a remote device, a handheld device, or a subscriber device, or some other suitable terminology, where the “device” may also be referred to as a unit, a station, a terminal, or a client, among other examples. A UE **115** may also include or may be referred to as a personal electronic device such as a cellular phone, a personal digital assistant (PDA), a tablet computer, a laptop computer, or a personal computer. In some examples, a UE **115** may include or be referred to as a wireless local loop (WLL) station, an Internet of Things (IoT) device, an Internet of Everything (IoE) device, or a machine type communications (MTC) device, among other examples, which may be implemented in various objects such as appliances, or vehicles, meters, among other examples.

(30) The UEs **115** described herein may be able to communicate with various types of devices, such as other UEs **115** that may sometimes act as relays as well as the network entities **105** and the network equipment including macro eNBs or gNBs, small cell eNBs or gNBs, or relay base stations, among other examples, as shown in FIG. 1.

(31) The UEs **115** and the network entities **105** may wirelessly communicate with one another via one or more communication links **125** (e.g., an access link) using resources associated with one or more carriers. The term “carrier” may refer to a set of RF spectrum resources having a defined physical layer structure for supporting the communication links **125**. For example, a carrier used for a communication link **125** may include a portion of a RF spectrum band (e.g., a bandwidth part (BWP)) that is operated according to one or more physical layer channels for a given radio access technology (e.g., LTE, LTE-A, LTE-A Pro, NR). Each physical layer channel may carry acquisition signaling (e.g., synchronization signals, system information), control signaling that coordinates operation for the carrier, user data, or other signaling. The wireless communications system **100** may support communication with a UE **115** using carrier aggregation or multi-carrier operation. A UE **115** may be configured with multiple downlink component carriers and one or more uplink component carriers according to a carrier aggregation configuration. Carrier aggregation may be used with both frequency division duplexing (FDD) and time division duplexing (TDD) component

carriers. Communication between a network entity **105** and other devices may refer to communication between the devices and any portion (e.g., entity, sub-entity) of a network entity **105**. For example, the terms “transmitting,” “receiving,” or “communicating,” when referring to a network entity **105**, may refer to any portion of a network entity **105** (e.g., a base station **140**, a CU **160**, a DU **165**, a RU **170**) of a RAN communicating with another device (e.g., directly or via one or more other network entities **105**).

(32) Signal waveforms transmitted via a carrier may be made up of multiple subcarriers (e.g., using multi-carrier modulation (MCM) techniques such as orthogonal frequency division multiplexing (OFDM) or discrete Fourier transform spread OFDM (DFT-S-OFDM)). In a system employing MCM techniques, a resource element may refer to resources of one symbol period (e.g., a duration of one modulation symbol) and one subcarrier, in which case the symbol period and subcarrier spacing may be inversely related. The quantity of bits carried by each resource element may depend on the modulation scheme (e.g., the order of the modulation scheme, the coding rate of the modulation scheme, or both), such that a relatively higher quantity of resource elements (e.g., in a transmission duration) and a relatively higher order of a modulation scheme may correspond to a relatively higher rate of communication. A wireless communications resource may refer to a combination of an RF spectrum resource, a time resource, and a spatial resource (e.g., a spatial layer, a beam), and the use of multiple spatial resources may increase the data rate or data integrity for communications with a UE **115**.

(33) The time intervals for the network entities **105** or the UEs **115** may be expressed in multiples of a basic time unit which may, for example, refer to a sampling period of $T_{\text{sub.s}} = 1/(\Delta f_{\text{sub.max}} \cdot N_{\text{sub.f}})$ seconds, for which $\Delta f_{\text{sub.max}}$ may represent a supported subcarrier spacing, and $N_{\text{sub.f}}$ may represent a supported discrete Fourier transform (DFT) size. Time intervals of a communications resource may be organized according to radio frames each having a specified duration (e.g., 10 milliseconds (ms)). Each radio frame may be identified by a system frame number (SFN) (e.g., ranging from 0 to 1023).

(34) Each frame may include multiple consecutively numbered subframes or slots, and each subframe or slot may have the same duration. In some examples, a frame may be divided (e.g., in the time domain) into subframes, and each subframe may be further divided into a quantity of slots. Alternatively, each frame may include a variable quantity of slots, and the quantity of slots may depend on subcarrier spacing. Each slot may include a quantity of symbol periods (e.g., depending on the length of the cyclic prefix prepended to each symbol period). In some wireless communications systems **100**, a slot may further be divided into multiple mini-slots associated with one or more symbols. Excluding the cyclic prefix, each symbol period may be associated with one or more (e.g., $N_{\text{sub.f}}$) sampling periods. The duration of a symbol period may depend on the subcarrier spacing or frequency band of operation.

(35) A subframe, a slot, a mini-slot, or a symbol may be the smallest scheduling unit (e.g., in the time domain) of the wireless communications system **100** and may be referred to as a transmission time interval (TTI). In some examples, the TTI duration (e.g., a quantity of symbol periods in a TTI) may be variable. Additionally, or alternatively, the smallest scheduling unit of the wireless communications system **100** may be dynamically selected (e.g., in bursts of shortened TTIs (sTTIs)).

(36) Physical channels may be multiplexed for communication using a carrier according to various techniques. A physical control channel and a physical data channel may be multiplexed for signaling via a downlink carrier, for example, using one or more of time division multiplexing (TDM) techniques, frequency division multiplexing (FDM) techniques, or hybrid TDM-FDM techniques. A control region (e.g., a CORESET (CORESET)) for a physical control channel may be defined by a set of symbol periods and may extend across the system bandwidth or a subset of the system bandwidth of the carrier. One or more control regions (e.g., CORESETs) may be configured for a set of the UEs **115**. For example, one or more of the UEs **115** may monitor or search control

regions for control information according to one or more search space sets, and each search space set may include one or multiple control channel candidates in one or more aggregation levels arranged in a cascaded manner. An aggregation level for a control channel candidate may refer to an amount of control channel resources (e.g., control channel elements (CCEs)) associated with encoded information for a control information format having a given payload size. Search space sets may include common search space sets configured for sending control information to multiple UEs **115** and UE-specific search space sets for sending control information to a specific UE **115**.

(37) A network entity **105** may provide communication coverage via one or more cells, for example a macro cell, a small cell, a hot spot, or other types of cells, or any combination thereof. The term “cell” may refer to a logical communication entity used for communication with a network entity **105** (e.g., using a carrier) and may be associated with an identifier for distinguishing neighboring cells (e.g., a physical cell identifier (PCID), a virtual cell identifier (VCID), or others). In some examples, a cell also may refer to a coverage area **110** or a portion of a coverage area **110** (e.g., a sector) over which the logical communication entity operates. Such cells may range from smaller areas (e.g., a structure, a subset of structure) to larger areas depending on various factors such as the capabilities of the network entity **105**. For example, a cell may be or include a building, a subset of a building, or exterior spaces between or overlapping with coverage areas **110**, among other examples.

(38) A macro cell generally covers a relatively large geographic area (e.g., several kilometers in radius) and may allow unrestricted access by the UEs **115** with service subscriptions with the network provider supporting the macro cell. A small cell may be associated with a lower-powered network entity **105** (e.g., a lower-powered base station **140**), as compared with a macro cell, and a small cell may operate using the same or different (e.g., licensed, unlicensed) frequency bands as macro cells. Small cells may provide unrestricted access to the UEs **115** with service subscriptions with the network provider or may provide restricted access to the UEs **115** having an association with the small cell (e.g., the UEs **115** in a closed subscriber group (CSG), the UEs **115** associated with users in a home or office). A network entity **105** may support one or multiple cells and may also support communications via the one or more cells using one or multiple component carriers.

(39) In some examples, a carrier may support multiple cells, and different cells may be configured according to different protocol types (e.g., MTC, narrowband IoT (NB-IoT), enhanced mobile broadband (eMBB)) that may provide access for different types of devices.

(40) In some examples, a network entity **105** (e.g., a base station **140**, an RU **170**) may be movable and therefore provide communication coverage for a moving coverage area **110**. In some examples, different coverage areas **110** associated with different technologies may overlap, but the different coverage areas **110** may be supported by the same network entity **105**. In some other examples, the overlapping coverage areas **110** associated with different technologies may be supported by different network entities **105**. The wireless communications system **100** may include, for example, a heterogeneous network in which different types of the network entities **105** provide coverage for various coverage areas **110** using the same or different radio access technologies.

(41) The wireless communications system **100** may be configured to support ultra-reliable communications or low-latency communications, or various combinations thereof. For example, the wireless communications system **100** may be configured to support ultra-reliable low-latency communications (URLLC). The UEs **115** may be designed to support ultra-reliable, low-latency, or critical functions. Ultra-reliable communications may include private communication or group communication and may be supported by one or more services such as push-to-talk, video, or data. Support for ultra-reliable, low-latency functions may include prioritization of services, and such services may be used for public safety or general commercial applications. The terms ultra-reliable, low-latency, and ultra-reliable low-latency may be used interchangeably herein.

(42) In some examples, a UE **115** may be configured to support communicating directly with other UEs **115** via a device-to-device (D2D) communication link **135** (e.g., in accordance with a peer-to-

peer (P2P), D2D, or sidelink protocol). In some examples, one or more UEs **115** of a group that are performing D2D communications may be within the coverage area **110** of a network entity **105** (e.g., a base station **140**, an RU **170**), which may support aspects of such D2D communications being configured by (e.g., scheduled by) the network entity **105**. In some examples, one or more UEs **115** of such a group may be outside the coverage area **110** of a network entity **105** or may be otherwise unable to or not configured to receive transmissions from a network entity **105**. In some examples, groups of the UEs **115** communicating via D2D communications may support a one-to-many (1:M) system in which each UE **115** transmits to each of the other UEs **115** in the group. In some examples, a network entity **105** may facilitate the scheduling of resources for D2D communications. In some other examples, D2D communications may be carried out between the UEs **115** without an involvement of a network entity **105**.

(43) The core network **130** may provide user authentication, access authorization, tracking, Internet Protocol (IP) connectivity, and other access, routing, or mobility functions. The core network **130** may be an evolved packet core (EPC) or 5G core (5GC), which may include at least one control plane entity that manages access and mobility (e.g., a mobility management entity (MME), an access and mobility management function (AMF)) and at least one user plane entity that routes packets or interconnects to external networks (e.g., a serving gateway (S-GW), a Packet Data Network (PDN) gateway (P-GW), or a user plane function (UPF)). The control plane entity may manage non-access stratum (NAS) functions such as mobility, authentication, and bearer management for the UEs **115** served by the network entities **105** (e.g., base stations **140**) associated with the core network **130**. User IP packets may be transferred through the user plane entity, which may provide IP address allocation as well as other functions. The user plane entity may be connected to IP services **150** for one or more network operators. The IP services **150** may include access to the Internet, Intranet(s), an IP Multimedia Subsystem (IMS), or a Packet-Switched Streaming Service.

(44) The wireless communications system **100** may operate using one or more frequency bands, which may be in the range of 300 megahertz (MHz) to 300 gigahertz (GHz). Generally, the region from 300 MHz to 3 GHz is known as the ultra-high frequency (UHF) region or decimeter band because the wavelengths range from approximately one decimeter to one meter in length. UHF waves may be blocked or redirected by buildings and environmental features, which may be referred to as clusters, but the waves may penetrate structures sufficiently for a macro cell to provide service to the UEs **115** located indoors. Communications using UHF waves may be associated with smaller antennas and shorter ranges (e.g., less than 100 kilometers) compared to communications using the smaller frequencies and longer waves of the high frequency (HF) or very high frequency (VHF) portion of the spectrum below 300 MHz.

(45) The wireless communications system **100** may utilize both licensed and unlicensed RF spectrum bands. For example, the wireless communications system **100** may employ License Assisted Access (LAA), LTE-Unlicensed (LTE-U) radio access technology, or NR technology using an unlicensed band such as the 5 GHz industrial, scientific, and medical (ISM) band. While operating using unlicensed RF spectrum bands, devices such as the network entities **105** and the UEs **115** may employ carrier sensing for collision detection and avoidance. In some examples, operations using unlicensed bands may be based on a carrier aggregation configuration in conjunction with component carriers operating using a licensed band (e.g., LAA). Operations using unlicensed spectrum may include downlink transmissions, uplink transmissions, P2P transmissions, or D2D transmissions, among other examples.

(46) A network entity **105** (e.g., a base station **140**, an RU **170**) or a UE **115** may be equipped with multiple antennas, which may be used to employ techniques such as transmit diversity, receive diversity, multiple-input multiple-output (MIMO) communications, or beamforming. The antennas of a network entity **105** or a UE **115** may be located within one or more antenna arrays or antenna panels, which may support MIMO operations or transmit or receive beamforming. For example,

one or more base station antennas or antenna arrays may be co-located at an antenna assembly, such as an antenna tower. In some examples, antennas or antenna arrays associated with a network entity **105** may be located at diverse geographic locations. A network entity **105** may include an antenna array with a set of rows and columns of antenna ports that the network entity **105** may use to support beamforming of communications with a UE **115**. Likewise, a UE **115** may include one or more antenna arrays that may support various MIMO or beamforming operations. Additionally, or alternatively, an antenna panel may support RF beamforming for a signal transmitted via an antenna port.

(47) Beamforming, which may also be referred to as spatial filtering, directional transmission, or directional reception, is a signal processing technique that may be used at a transmitting device or a receiving device (e.g., a network entity **105**, a UE **115**) to shape or steer an antenna beam (e.g., a transmit beam, a receive beam) along a spatial path between the transmitting device and the receiving device. Beamforming may be achieved by combining the signals communicated via antenna elements of an antenna array such that some signals propagating along particular orientations with respect to an antenna array experience constructive interference while others experience destructive interference. The adjustment of signals communicated via the antenna elements may include a transmitting device or a receiving device applying amplitude offsets, phase offsets, or both to signals carried via the antenna elements associated with the device. The adjustments associated with each of the antenna elements may be defined by a beamforming weight set associated with a particular orientation (e.g., with respect to the antenna array of the transmitting device or receiving device, or with respect to some other orientation).

(48) The wireless communications system **100** may support per-TRP BFD measurement relaxation. In such cases, a UE **115** may receive control signaling indicating one or more parameters associated with adjusting a measurement periodicity of multiple reference signal sets, the multiple reference signal sets including a first reference signal set associated with a first TRP of a network entity **105** (e.g., serving cell) and a second reference signal set associated with a second TRP of the network entity **105**. The one or more parameters may include a first threshold and a first relaxation factor associated with the first reference signal set and a second threshold and second relaxation threshold associated with the second reference signal set. In some examples, the first threshold and the second threshold may be the same. Additionally, or alternatively, the first relaxation parameter and the second relaxation parameter may be the same.

(49) As such, the UE **115** may measure channel quality metrics of each reference signal set and may adjust a measurement periodicity of the first reference signal set, a measurement periodicity of the second reference signal set, or both, based on respective channel quality metrics. For example, the UE **115** may adjust the measurement periodicity of the first reference signal set according to the first relaxation factor based on a first channel quality metric associated with the first reference signal set exceeding the threshold. Conversely, the UE **115** may maintain the measurement periodicity of the second reference signal set based on a second channel quality metric associated with the second reference signal set failing to exceed the second threshold.

(50) FIG. 2 illustrates an example of a wireless communications system **200** that supports BFD measurement relaxation for cells with multiple TRPs in accordance with one or more aspects of the present disclosure. The wireless communications system **200** may implement or be implemented by aspects of the wireless communication system **100**. For example, the wireless communications system **200** may include one or more network entities **105** (e.g., a network entity **105** associated with a TRP **205-a** and a TRP **205-b**) and one or more UEs **115** (e.g., a UE **115-a**), which may represent examples of corresponding devices as described with reference to FIG. 1. In some examples, the UE **115-a** may adjust a measurement periodicity for a first set of reference signals associated with the TRP **205-a**, a second set of reference signals associated with the TRP **205-b**, or both.

(51) Some wireless communications systems, such as the wireless communications system **200**,

may support BFD. For example, a UE **115**, such as the UE **115-a**, may periodically monitor one or more reference signals **220** associated with a network entity **105** (e.g., serving cell, SpCell) to detect beam failure. In some examples, the UE **115-a** may be in a low-mobility scenario (e.g., the UE **115-a** may satisfy low mobility criterion) and channel quality metrics associated with the one or more reference signals **220** may exceed a threshold (e.g., the one or more reference signals **220** may satisfy serving cell quality criterion). That is, the UE **115-a** may evaluate (e.g., measure) the one or more reference signals **220** (e.g., downlink reference signals (DL-RS)) associated with the network entity **105** (e.g., using an algorithm) to determine that the UE **115-a** is operating in a low mobility scenario (e.g., the UE **115-a** satisfies low mobility criterion for radio resource management (RRM) relaxation). Additionally, the UE **115-a** may measure a signal to interference and noise (SINR) of the one or more reference signals **220** and compare the SINRs to the threshold to determine whether the SINRs associated with the one or more references signals **220** exceed the threshold (e.g., are higher than the threshold, $Q_{sub.in}$, by a configured offset, $Q_{sub.x}$).

(52) In such cases (the UE **115-a** satisfies the low mobility criterion and the one or more reference signals **220** satisfy the serving cell quality criterion), the UE **115-a** may increase the periodicity at which the UE **115-a** monitors the one or more reference signals **220** associated with the network entity **105** for BFD (e.g., apply a longer measurement periodicity). In other words, the UE **115-a** may increase a time gap **230** between measuring the one or more reference signals **220**, which may be referred to BFD measurement relaxation

(53) In some cases, the network entity **105** may be associated with multiple transmission reception points (TRPs) **205** and each TRP **205** may be associated with one or more reference signals **220** (e.g., BFD-RSs), which may be referred to as reference signal sets **215** (e.g., BFD-RS set). In such cases, each reference signal set **215** may be associated with a set of BFD parameters (e.g., BFD parameters are configured independently for each reference signal set **215**). For example, the multiple TRPs may include a TRP **205-a** associated with a reference signal set **215-a** and a TRP **205-b** associated with a reference signal set **215-b**. In such cases, the UE **115-a** may evaluate BFD for the network entity **105** based on each reference signal set **215**. That is, the UE **115-a** may determine that BFD has not occurred (e.g., the network entity **105** fulfills or satisfies good serving cell quality criterion) based on a reference signal **220** (e.g., resource associated with the reference signal **220**) from the reference signal set **215-a**, a reference signal **220** from the reference signal set **215-b**, or both, satisfying a threshold (e.g., the good serving cell criterion is fulfilled as long as any references signal **220** associated with the network entity **105** fulfills the good serving cell criterion, or satisfied the threshold, regardless of which reference signal set **215** the reference signal **220** is associated with).

(54) Additionally, the UE **115-a** may perform BFD measurement relaxation for the network entity **105** associated with the multiple TRPs **205**. In such cases, the UE **115-a** may measure channel quality metrics of each reference signal **220** of the first reference signal set **215-a** and each reference signal **220** of the reference signal set **215-b** to determine whether the UE **115-a** may adjust a measurement periodicity of the first reference signal set **215-a** and the reference signal set **215-b**. For example, the UE **115-a** may be in a low mobility scenario and a channel quality metric associated with the first reference signal set **215-a** may exceed a threshold while a channel quality metric associated with the reference signal set **215-b** may fail to exceed the threshold. In such cases, the UE **115-a** may refrain from adjusting the measurement periodicity of the first reference signal set **215-a** and the measurement periodicity of the reference signal set **215-b** based on the channel quality metric associated with the reference signal set **215-b** failing to exceed the threshold (e.g., despite the channel quality metric associated with the first reference signal set **215-a** exceeding the threshold). In other words, the UE **115-a** adjusting the measurement periodicity of the first reference signal set **215-a** and the measurement periodicity of the reference signal set **215-b** based on the channel quality metrics associated with each reference signal set **215** satisfying the threshold (e.g., BFD measurement relaxation is performed per cell), resulting in inefficient power

consumption and resource utilization.

(55) Accordingly, techniques described herein may support per-TRP **205** BFD measurement relaxation. For example, the UE **115-a** may receive a control message **210-a** indicating multiple TRPs **205** of a network entity **105**, including a TRP **205-a** and a TRP **205-b** (e.g., may configure the UE **115-a** for multi-TRP communications). For example, the control message **210-a** may indicate a first control resource set (CORESET) identifier associated with the TRP **205-a** and a second CORESET identifier associated with the TRP **205-b**. Additionally, each TRP **205** may be associated with one or more reference signals **220**, which may be referred to as reference signal sets **215**. For example, the TRP **205-a** may be associated with a reference signal set **215-a** and the TRP **205-b** may be associated with a reference signal set **215-b**. The UE **115-a** may receive the control message **210-a** from the TRP **205-a** (e.g., depicted), the TRP **205-b**, or both.

(56) Additionally, the UE **115-a** may receive a control message **210-b** indicating one or more parameters associated with measuring the multiple reference signals **220** associated with the multiple reference signal sets **215**, including the reference signal set **215-a** associated with the TRP **205-a** of the network entity **105** and the reference signal set **215-b** associated with the TRP **205-b** of the network entity **105**. The one or more parameters may be associated with adjusting a measurement periodicity of each reference signal set **215**. For example, the one or more parameters may include a first threshold (e.g., a first $Q_{\text{sub},x}$, a first offset from $Q_{\text{sub},\text{in}}$) and a first relaxation factor associated with the reference signal set **215-a** (e.g., associated with the TRP **205-a**) and a second threshold (e.g., a second $Q_{\text{sub},x}$, a second offset from $Q_{\text{sub},\text{in}}$) and a second relaxation factor associated with the reference signal set **215-b** (e.g., associated with the TRP **205-b**). The UE **115-a** may receive the control message **210-b** from the TRP **205-a** (e.g., depicted), the TRP **205-b**, or both.

(57) In some examples, the first threshold may be the same as the second threshold based on the TRP **205-a** and the TRP **205-b** being associated with the network entity **105** (e.g., a same thresholds is configured per cell group). Alternatively, the first threshold may be different than the second threshold based on the TRP **205-a** being associated with the reference signal set **215-a** and the TRP **205-b** being associated with the reference signal set **215-b** (e.g., the thresholds are configured per reference signal set **215**). Additionally, or alternatively, the first relaxation factor may be the same as the second relaxation factor based on the TRP **205-a** and the TRP **205-b** being associated with the network entity **105** (e.g., a same relaxation factor is configured per cell group). Alternatively, the first relaxation factor may be different than the second relaxation factor based on the TRP **205-a** being associated with the reference signal set **215-a** and the TRP **205-b** being associated with the reference signal set **215-b** (e.g., the relaxation factors are configured per reference signal set **215**).

(58) The thresholds may be based on a channel quality metric associated with the reference signal sets **215**. For example, the thresholds may be SINR thresholds such that a reference signal **220** of the reference signal set **215-a** satisfies the first threshold based on a SINR of the reference signal **220** exceeding the first threshold. In other words, the TRP **205-a** may satisfy (e.g., fulfill) good serving cell criterion based on one or more reference signals **220** of the reference signal set **215-a** satisfying the first threshold. Conversely, the reference signal **220** of the reference signal set **215-a** may fail to satisfy the first threshold based on the SINR of the reference signal **220** failing to exceed (e.g., or meeting) the first threshold. In other words, the TRP **205-a** may fail to satisfy the good serving cell criterion based on the reference signals **220** (e.g., all reference signals **220**) of the reference signal set **215-a** failing to satisfy the first threshold.

(59) As such, the UE **115-a** may measure respective channel quality metrics (e.g., SINRs) for the multiple reference signals **220** of the reference signal sets **215** and compare the respective channel quality metrics to the respective thresholds. For example, as discussed previously, the UE **115-a** may measure respective channel quality metrics of each reference signal **220** of the reference signal set **215-a** and compare the channel quality metrics to the first threshold. Similarly, the UE **115-a** may measure respective channel quality metrics of each reference signal **220** of the reference signal

set **215-b** and compare the channel quality metrics to the second threshold.

(60) Additionally, the UE **115-a** may measure a mobility metric associated with the network entity **105** (e.g., associated with the TRP **205-a** and the TRP **205-b**, per cell group). In some examples, the UE **115-a** may satisfy low mobility criterion based on the mobility metric satisfying a mobility threshold. In other words, the UE **115-a** may be in a low mobility scenario based on the mobility metric satisfying the threshold.

(61) As such, the UE **115-a** may perform BFD measurement relaxation per-TRP **205**. That is, the UE **115-a** may adjust a measurement periodicity of the reference signal set **215-a** based on the UE **115-a** being in a low mobility scenario (e.g., satisfying the low mobility criterion) and based on channel quality metrics associated with one or more reference signals **220** of the reference signal set **215-a** satisfying the first threshold. In such cases, the UE **115-a** may adjust the measurement periodicity of the reference signal set **215-a** based on the first relaxation factor. In other words, the first relaxation factor (e.g., and the second relaxation factor) may indicate an adjustment to a time gap **230** between successive measurements of reference signals **220**.

(62) For example, (e.g., prior to BFD measurement relaxation of the reference signal set **215-a**), the UE **115-a** may measure reference signals **220** of the reference signal set **215-a** according to a first measurement periodicity of the reference signal set **215-a** associated with a time gap **230-a** (e.g., the time gap **230-a** may occur between each measurement of the reference signals **220** of the reference signal set **215-a**). Further, the UE **115-a** may adjust the measurement periodicity of the reference signal set **215-a** from the first measurement periodicity of the reference signal set **215-a** to a second measurement periodicity of the reference signal set **215-a**. The second measurement periodicity of the reference signal set **215-a** may be associated with a time gap **230-b** (e.g., the time gap **230-b** may occur between each measurement of the reference signals **220** of the reference signal set **215-a**), where the time gap **230-b** is longer in duration than the time gap **230-a**. In some examples, the first relaxation factor may indicate the time gap **230-b**. In some other examples, the first relaxation factor may indicate a scaling factor between the time gap **230-a** and the time gap **230-b**.

(63) Additionally, the UE **115-a** may adjust the measurement periodicity of the reference signal set **215-a** from the second measurement periodicity of the reference signal set **215-a** to the first measurement periodicity of the reference signal set **215-a** based on the UE **115-a** entering a high mobility scenario or based on the channel quality metrics associated with the reference signals **220** (e.g., all reference signals **220**) of the reference signal set **215-a** falling below the first threshold.

(64) Conversely, the UE **115-a** may maintain the measurement periodicity of the reference signal set **215-a** based on the UE **115-a** being in a high mobility scenario (e.g., not satisfying the low mobility criterion) or based on the channel quality metrics associated with the reference signals **220** (e.g., all reference signals **220**) of the reference signal set **215-a** failing to satisfy the first threshold.

(65) Similarly, the UE **115-a** may adjust a measurement periodicity of the reference signal set **215-b** based on the UE **115-a** being in a low mobility scenario (e.g., satisfying the low mobility criterion) and based on channel quality metrics associated with one or more reference signals **220** of the reference signal set **215-b** satisfying the second threshold. In such cases, the UE **115-a** may adjust the measurement periodicity of the reference signal set **215-b** based on the second relaxation factor. Conversely, the UE **115-a** may maintain the measurement periodicity of the reference signal set **215-b** based on the UE **115-a** being in a high mobility scenario (e.g., not satisfying the low mobility criterion) or based on the channel quality metrics associated with the reference signals **220** (e.g., all reference signals **220**) of the reference signal set **215-b** failing to satisfy the second threshold.

(66) Additionally, the UE **115-a** may transit a report **225** (e.g., relaxation status report **225**) indicating the adjustment of the measurement periodicity for the reference signal set **215-a**, the adjustment of the measurement periodicity for the reference signal set **215-b**, or both. In other words, increasing (e.g., extending) the measurement periodicity (e.g., increasing a time gap **230**)

for a reference signal set **215** may be associated with the respective TRP **205** entering relaxation. Conversely, decreasing (e.g., reducing) the measurement periodicity (e.g., decreasing a time gap **230**) for a reference signal set **215** may be associated with the respective TRP **205** exiting relaxation. As such, the UE **115-a** may transmit the report **225** indicating a change in relaxation status of the TRP **205-a**, the TRP **205-b**, or both, based on adjusting the measurement periodicity for the reference signal set **215-a**, adjusting the measurement periodicity for the reference signal set **215-b**, or both. The report **225** may include an indication of the first CORESET associated with the TRP **205-a**, the second CORESET associated with the TRP **205-b**, or both, respectively (e.g., rather than an identifier associated with the network entity **105**, a cell identifier). The UE **115-a** may transmit the report **225** to the TRP **205-a** (e.g., depicted), the TRP **205-b**, or both.

(67) Though described in the context of the TRP **205-a** and the TRP **205-b**, this is not to be regarded as a limitation of the present disclosure. In this regard, any quantity of TRPs **205** (e.g., any quantity of reference signal sets **215**) may be considered with regards to the techniques described herein.

(68) FIG. 3 illustrates an example of a process flow **300** that supports BFD measurement relaxation for cells with multiple TRPs in accordance with one or more aspects of the present disclosure. The process flow **300** may implement or be implemented by aspects of the wireless communication system **100** and the wireless communications system **200**. For example, the process flow **300** may include one or more network entities **105** (e.g., a network entity **105** associated with a wireless device **305-a** and a wireless device **305-b**) and one or more UEs **115** (e.g., a UE **115-b**), which may represent examples of corresponding devices as described with reference to FIG. 1. In some examples, the UE **115-b** may adjust a measurement periodicity for a first set of reference signals associated with the wireless device **305-a**, a second set of reference signals associated with the wireless device **305-b**, or both.

(69) At **310**, the wireless device **305-a** (e.g., TRP **305-a**), the wireless device **305-b** (e.g., TRP **305-b**), or both, may transmit, to the UE **115-b**, a first control message indicative of a plurality of CORESET identifiers, where each CORESET identifier is associated with a respective wireless device **305** (e.g., TRP) of a cell (e.g., network entity **105**). In other words, the UE **115-b** may be configured for multi-TRP communications. For example, a first CORESET identifier may be associated with the wireless device **305-a** and a second CORESET identifier may be associated with the wireless device **305-b**.

(70) At **315**, the wireless device **305-a**, the wireless device **305-b**, or both, may transmit, to the UE **115-b**, one or more second control messages indicative of a set of (e.g., one or more) parameters associated with adjusting one or more measurement periodicities associated with measurements of multiple reference signals by the UE **115-b**. The one or more parameters may be associated with adjusting measurement periodicities with the multiple reference signals. Additionally, the multiple reference signals may include a first set of reference signals associated with the wireless device **305-a** and a second set of reference signals associated with the wireless device **305-b**.

(71) For example, the wireless device **305-a** may transmit a second control message indicating a first subset of the set of parameters associated with adjusting a measurement periodicity of the first set of reference signals associated with the wireless device **305-a**. Additionally, or alternatively, the wireless device **305-b** may transmit a second control message indicating a second subset of the set of parameters associated with adjusting a measurement periodicity of the second set of reference signals associated with the wireless device **305-b**. In another example, the wireless device **305-a**, the wireless device **305-b**, or both, may transmit a second control message indicating the first subset of the set of parameters and the second subset of the set of parameters (e.g., indicating the set of parameters).

(72) In some cases, the first subset of the set of parameters may include a first relaxation factor (e.g., a first parameter of the set of parameters), a first threshold (e.g., a second parameter of the set of parameters), or both, and the second subset of the set of parameters may include a second

relaxation factor (e.g., a third parameter of the set of parameters), a second threshold (e.g., a fourth parameter of the set of parameters), or both.

(73) In some examples, the first relaxation factor and the second relaxation factor may be the same based on the wireless device **305-a** and the wireless device **305-b** being associated with the network entity **105** (e.g., a same cell). Alternatively, the first relaxation factor and the second relaxation factor may be different based on the first wireless device **305-a** being associated with the first set of reference signals and the second wireless device **305-b** being associated with the second set of reference signals.

(74) Similarly, the first threshold and the second threshold may be the same based on the first wireless device **305-a** and the second wireless device **305-b** being associated with the network entity **105**. Alternatively, the first threshold and the second threshold may be different based on the first wireless device **305-a** being associated with the first set of reference signals and the second wireless device **305-b** being associated with the second set of reference signals.

(75) In some cases, at **320**, the wireless device **305-a** may transmit the first set of reference signals. The first set of reference signals may include one or more first reference signals.

(76) In some cases, at **325**, the wireless device **305-b** may transmit the second set of reference signals. The second set of reference signals may include one or more second reference signals.

(77) At **330**, the UE **115-b** may measure respective channel quality metrics for the multiple reference signals. That is, the UE **115-b** may measure each of the one or more first reference signals and each of the one or more second reference signals. The respective channel quality metrics may be SINRs.

(78) In some cases, at **335**, the UE **115-b** may determine a mobility metric associated with the UE **115-b**. The mobility metric may be associated with the wireless device **305-a** and the wireless device **305-b** based on the wireless device **305-a** and the wireless device **305-b** being associated with the network entity **105** (e.g., being part of a same cell group associated with the network entity **105**).

(79) At **340**, the UE **115-b** may adjust the measurement periodicity for the first set of reference signals according to the first parameter of the set of parameters based on a first channel quality metric (e.g., a first SINR) associated with the first set of reference signals (e.g., exceeding the first threshold). The measurement periodicity for the first set of reference signals may be separately adjustable relative to the measurement periodicity for the second set of reference signals.

(80) As such, the UE **115-b** may maintain the measurement periodicity for the second set of reference signals based on a second channel quality metric (e.g., a second SINR) associated with the second set of reference signals (e.g., meeting or failing to exceed the second threshold). Alternatively, the UE **115-b** may adjust the measurement periodicity for the second set of reference signals according to the third parameter of the set of parameters based on the second channel quality metric associated with the second set of reference signals (e.g., exceeding the second threshold).

(81) In some examples, adjusting the measurement periodicity of the first set of reference signals may include adjusting a time gap between successive measurement for the first set of reference signals based on the first SINR associated with the first set of reference signals (e.g., associated with at least one of the one or more first reference signals) exceeding the first threshold. Similarly, adjusting the measurement periodicity of the second set of reference signals may include adjusting a time gap between successive measurement for the second set of reference signals based on the second SINR associated with the second set of reference signals (e.g., associated with at least one of the one or more second reference signals) exceeding the second threshold. Additionally, the UE **115-b** may adjust the measurement periodicity of the first set of reference signals, the measurement periodicity of the second set of reference signals, or both, based on the mobility metric associated with the UE **115-b** being associated with a low mobility scenario (e.g., failing to exceed a mobility threshold).

(82) Conversely, maintaining the measurement periodicity for the second set of reference signals may include maintaining the measurement periodicity for the second set of reference signals based on the second SINR associated with the second set of reference signals (e.g., associated with each of the one or more second reference signals) failing to exceed (e.g., or meeting) the second threshold.

(83) At **345**, the UE **115-b** may transmit (e.g., to the wireless device **305-a**, the wireless device **305-b**, or both) a report indicating the adjustment of the measurement periodicity for the first set of reference signals. In such cases, the report may include an indication of the first CORESET identifier associated with the wireless device **305-a**. In some examples, the report may further indicate the adjustment of the measurement periodicity for the second set of reference signals. In such cases, the report may include an indication of the second CORESET identifier associated with the wireless device **305-b**. In some examples, the UE **115-b** may transmit the report via UE assistance information.

(84) FIG. 4 illustrates a block diagram **400** of a device **405** that supports BFD measurement relaxation for cells with multiple TRPs in accordance with one or more aspects of the present disclosure. The device **405** may be an example of aspects of a UE **115** as described herein. The device **405** may include a receiver **410**, a transmitter **415**, and a communications manager **420**. The device **405** may also include a processor. Each of these components may be in communication with one another (e.g., via one or more buses).

(85) The receiver **410** may provide a means for receiving information such as packets, user data, control information, or any combination thereof associated with various information channels (e.g., control channels, data channels, information channels related to BFD measurement relaxation for cells with multiple TRPs). Information may be passed on to other components of the device **405**. The receiver **410** may utilize a single antenna or a set of multiple antennas.

(86) The transmitter **415** may provide a means for transmitting signals generated by other components of the device **405**. For example, the transmitter **415** may transmit information such as packets, user data, control information, or any combination thereof associated with various information channels (e.g., control channels, data channels, information channels related to BFD measurement relaxation for cells with multiple TRPs). In some examples, the transmitter **415** may be co-located with a receiver **410** in a transceiver module. The transmitter **415** may utilize a single antenna or a set of multiple antennas.

(87) The communications manager **420**, the receiver **410**, the transmitter **415**, or various combinations thereof or various components thereof may be examples of means for performing various aspects of BFD measurement relaxation for cells with multiple TRPs as described herein. For example, the communications manager **420**, the receiver **410**, the transmitter **415**, or various combinations or components thereof may support a method for performing one or more of the functions described herein.

(88) In some examples, the communications manager **420**, the receiver **410**, the transmitter **415**, or various combinations or components thereof may be implemented in hardware (e.g., in communications management circuitry). The hardware may include a processor, a digital signal processor (DSP), a central processing unit (CPU), an application-specific integrated circuit (ASIC), a field-programmable gate array (FPGA) or other programmable logic device, a microcontroller, discrete gate or transistor logic, discrete hardware components, or any combination thereof configured as or otherwise supporting a means for performing the functions described in the present disclosure. In some examples, a processor and memory coupled with the processor may be configured to perform one or more of the functions described herein (e.g., by executing, by the processor, instructions stored in the memory).

(89) Additionally, or alternatively, in some examples, the communications manager **420**, the receiver **410**, the transmitter **415**, or various combinations or components thereof may be implemented in code (e.g., as communications management software or firmware) executed by a

processor. If implemented in code executed by a processor, the functions of the communications manager **420**, the receiver **410**, the transmitter **415**, or various combinations or components thereof may be performed by a general-purpose processor, a DSP, a CPU, an ASIC, an FPGA, a microcontroller, or any combination of these or other programmable logic devices (e.g., configured as or otherwise supporting a means for performing the functions described in the present disclosure).

(90) In some examples, the communications manager **420** may be configured to perform various operations (e.g., receiving, obtaining, monitoring, outputting, transmitting) using or otherwise in cooperation with the receiver **410**, the transmitter **415**, or both. For example, the communications manager **420** may receive information from the receiver **410**, send information to the transmitter **415**, or be integrated in combination with the receiver **410**, the transmitter **415**, or both to obtain information, output information, or perform various other operations as described herein.

(91) The communications manager **420** may support wireless communications at a UE in accordance with examples as disclosed herein. For example, the communications manager **420** may be configured as or otherwise support a means for receiving a control message indicative of one or more parameters associated with measuring a set of multiple reference signals, where the one or more parameters are associated with adjusting one or more measurement periodicities associated with the set of multiple reference signals. The communications manager **420** may be configured as or otherwise support a means for measuring respective channel quality metrics for the set of multiple reference signals, where the set of multiple reference signals includes a first set of reference signals associated with a first TRP of a cell and a second set of reference signals associated with a second TRP of the cell. The communications manager **420** may be configured as or otherwise support a means for adjusting a measurement periodicity for the first set of reference signals according to a first parameter of the one or more parameters based on a first channel quality metric associated with the first set of reference signals, where the measurement periodicity for the first set of reference signals is separately adjustable relative to a measurement periodicity for the second set of reference signals.

(92) By including or configuring the communications manager **420** in accordance with examples as described herein, the device **405** (e.g., a processor controlling or otherwise coupled with the receiver **410**, the transmitter **415**, the communications manager **420**, or a combination thereof) may support techniques for BFD measurement relaxation for multi-TRP scenarios which may result in reduced processing, reduced power consumption, and more efficient utilization of communication resources, among other advantages.

(93) FIG. 5 illustrates a block diagram **500** of a device **505** that supports BFD measurement relaxation for cells with multiple TRPs in accordance with one or more aspects of the present disclosure. The device **505** may be an example of aspects of a device **405** or a UE **115** as described herein. The device **505** may include a receiver **510**, a transmitter **515**, and a communications manager **520**. The device **505** may also include a processor. Each of these components may be in communication with one another (e.g., via one or more buses).

(94) The receiver **510** may provide a means for receiving information such as packets, user data, control information, or any combination thereof associated with various information channels (e.g., control channels, data channels, information channels related to BFD measurement relaxation for cells with multiple TRPs). Information may be passed on to other components of the device **505**. The receiver **510** may utilize a single antenna or a set of multiple antennas.

(95) The transmitter **515** may provide a means for transmitting signals generated by other components of the device **505**. For example, the transmitter **515** may transmit information such as packets, user data, control information, or any combination thereof associated with various information channels (e.g., control channels, data channels, information channels related to BFD measurement relaxation for cells with multiple TRPs). In some examples, the transmitter **515** may be co-located with a receiver **510** in a transceiver module. The transmitter **515** may utilize a single

antenna or a set of multiple antennas.

(96) The device **505**, or various components thereof, may be an example of means for performing various aspects of BFD measurement relaxation for cells with multiple TRPs as described herein. For example, the communications manager **520** may include a parameter component **525**, a measuring component **530**, a relaxation component **535**, or any combination thereof. The communications manager **520** may be an example of aspects of a communications manager **420** as described herein. In some examples, the communications manager **520**, or various components thereof, may be configured to perform various operations (e.g., receiving, obtaining, monitoring, outputting, transmitting) using or otherwise in cooperation with the receiver **510**, the transmitter **515**, or both. For example, the communications manager **520** may receive information from the receiver **510**, send information to the transmitter **515**, or be integrated in combination with the receiver **510**, the transmitter **515**, or both to obtain information, output information, or perform various other operations as described herein.

(97) The communications manager **520** may support wireless communications at a UE in accordance with examples as disclosed herein. The parameter component **525** may be configured as or otherwise support a means for receiving a control message indicative of one or more parameters associated with measuring a set of multiple reference signals, where the one or more parameters are associated with adjusting one or more measurement periodicities associated with the set of multiple reference signals. The measuring component **530** may be configured as or otherwise support a means for measuring respective channel quality metrics for the set of multiple reference signals, where the set of multiple reference signals includes a first set of reference signals associated with a first TRP of a cell and a second set of reference signals associated with a second TRP of the cell. The relaxation component **535** may be configured as or otherwise support a means for adjusting a measurement periodicity for the first set of reference signals according to a first parameter of the one or more parameters based on a first channel quality metric associated with the first set of reference signals, where the measurement periodicity for the first set of reference signals is separately adjustable relative to a measurement periodicity for the second set of reference signals.

(98) FIG. **6** illustrates a block diagram **600** of a communications manager **620** that supports BFD measurement relaxation for cells with multiple TRPs in accordance with one or more aspects of the present disclosure. The communications manager **620** may be an example of aspects of a communications manager **420**, a communications manager **520**, or both, as described herein. The communications manager **620**, or various components thereof, may be an example of means for performing various aspects of BFD measurement relaxation for cells with multiple TRPs as described herein. For example, the communications manager **620** may include a parameter component **625**, a measuring component **630**, a relaxation component **635**, a reporting component **640**, a mobility component **645**, or any combination thereof. Each of these components may communicate, directly or indirectly, with one another (e.g., via one or more buses).

(99) The communications manager **620** may support wireless communications at a UE in accordance with examples as disclosed herein. The parameter component **625** may be configured as or otherwise support a means for receiving a control message indicative of one or more parameters associated with measuring a set of multiple reference signals, where the one or more parameters are associated with adjusting one or more measurement periodicities associated with the set of multiple reference signals. The measuring component **630** may be configured as or otherwise support a means for measuring respective channel quality metrics for the set of multiple reference signals, where the set of multiple reference signals includes a first set of reference signals associated with a first TRP of a cell and a second set of reference signals associated with a second TRP of the cell. The relaxation component **635** may be configured as or otherwise support a means for adjusting a measurement periodicity for the first set of reference signals according to a first parameter of the one or more parameters based on a first channel quality metric associated with the first set of reference signals, where the measurement periodicity for the first set of reference signals is

separately adjustable relative to a measurement periodicity for the second set of reference signals.
(100) In some examples, to support adjusting the measurement periodicity for the first set of reference signals, the relaxation component **635** may be configured as or otherwise support a means for adjusting a time gap between successive measurements for the first set of reference signals based on a first SINR associated with the first set of reference signals exceeding a first threshold.

(101) In some examples, the control message indicates the first threshold associated with the first set of reference signals and a second threshold associated with the second set of reference signals.

(102) In some examples, the first threshold and the second threshold are the same based on the first TRP and the second TRP being associated with the cell.

(103) In some examples, the first threshold and the second threshold are different based on the first TRP being associated with the first set of reference signals and the second TRP being associated with the second set of reference signals.

(104) In some examples, the relaxation component **635** may be configured as or otherwise support a means for maintaining the measurement periodicity for the second set of reference signals based on a second channel quality metric associated with the second set of reference signals failing to exceed a threshold.

(105) In some examples, maintaining the measurement periodicity for the second set of reference signals is based on an SINR associated with the second set of reference signals failing to exceed a threshold. In some examples, the second channel quality metric is the SINR.

(106) In some examples, the relaxation component **635** may be configured as or otherwise support a means for adjusting the measurement periodicity for the second set of reference signals according to a second parameter of the one or more parameters based on a second channel quality metric associated with the second set of reference signals.

(107) In some examples, the first parameter and the second parameter are the same based on the first TRP and the second TRP being associated with the cell.

(108) In some examples, the first parameter and the second parameter are different based on the first TRP being associated with the first set of reference signals and the second TRP being associated with the second set of reference signals.

(109) In some examples, adjusting the measurement periodicity for the second set of reference signals is based on an SINR associated with the second set of reference signals exceeding a threshold. In some examples, the second channel quality metric is the SINR.

(110) In some examples, the reporting component **640** may be configured as or otherwise support a means for transmitting a report indicating the adjustment of the measurement periodicity for the first set of reference signals, where the report includes an indication of a first CORESET identifier associated with the first TRP of the cell.

(111) In some examples, the report further indicates an adjustment of the measurement periodicity for the second set of reference signals. In some examples, the report includes an indication of a second CORESET identifier associated with the second TRP of the cell.

(112) In some examples, the report is transmitted via UE assistance information.

(113) In some examples, the mobility component **645** may be configured as or otherwise support a means for determining a mobility metric associated with the UE, where adjusting the measurement periodicity for the first set of reference signals is based on the mobility metric associated with the UE being associated with a low mobility scenario.

(114) In some examples, the mobility metric is associated with the first TRP and the second TRP based on the first TRP and the second TRP being associated with the cell.

(115) In some examples, the parameter component **625** may be configured as or otherwise support a means for receiving a second control message indicative of a set of multiple CORESET identifiers, where each CORESET identifier is associated with a respective TRP of the cell.

(116) In some examples, adjusting the measurement periodicity for the first set of reference signals

includes increasing a time gap between successive measurements of the first set of reference signals based on the first parameter.

(117) FIG. 7 illustrates a diagram of a system **700** including a device **705** that supports BFD measurement relaxation for cells with multiple TRPs in accordance with one or more aspects of the present disclosure. The device **705** may be an example of or include the components of a device **405**, a device **505**, or a UE **115** as described herein. The device **705** may communicate (e.g., wirelessly) with one or more network entities **105**, one or more UEs **115**, or any combination thereof. The device **705** may include components for bi-directional voice and data communications including components for transmitting and receiving communications, such as a communications manager **720**, an input/output (I/O) controller **710**, a transceiver **715**, an antenna **725**, a memory **730**, code **735**, and a processor **740**. These components may be in electronic communication or otherwise coupled (e.g., operatively, communicatively, functionally, electronically, electrically) via one or more buses (e.g., a bus **745**).

(118) The I/O controller **710** may manage input and output signals for the device **705**. The I/O controller **710** may also manage peripherals not integrated into the device **705**. In some cases, the I/O controller **710** may represent a physical connection or port to an external peripheral. In some cases, the I/O controller **710** may utilize an operating system such as iOS®, ANDROID®, MS-DOS®, MS-WINDOWS®, OS/2®, UNIX®, LINUX®, or another known operating system. Additionally, or alternatively, the I/O controller **710** may represent or interact with a modem, a keyboard, a mouse, a touchscreen, or a similar device. In some cases, the I/O controller **710** may be implemented as part of a processor, such as the processor **740**. In some cases, a user may interact with the device **705** via the I/O controller **710** or via hardware components controlled by the I/O controller **710**.

(119) In some cases, the device **705** may include a single antenna **725**. However, in some other cases, the device **705** may have more than one antenna **725**, which may be capable of concurrently transmitting or receiving multiple wireless transmissions. The transceiver **715** may communicate bi-directionally, via the one or more antennas **725**, wired, or wireless links as described herein. For example, the transceiver **715** may represent a wireless transceiver and may communicate bi-directionally with another wireless transceiver. The transceiver **715** may also include a modem to modulate the packets, to provide the modulated packets to one or more antennas **725** for transmission, and to demodulate packets received from the one or more antennas **725**. The transceiver **715**, or the transceiver **715** and one or more antennas **725**, may be an example of a transmitter **415**, a transmitter **515**, a receiver **410**, a receiver **510**, or any combination thereof or component thereof, as described herein.

(120) The memory **730** may include random access memory (RAM) and read-only memory (ROM). The memory **730** may store computer-readable, computer-executable code **735** including instructions that, when executed by the processor **740**, cause the device **705** to perform various functions described herein. The code **735** may be stored in a non-transitory computer-readable medium such as system memory or another type of memory. In some cases, the code **735** may not be directly executable by the processor **740** but may cause a computer (e.g., when compiled and executed) to perform functions described herein. In some cases, the memory **730** may contain, among other things, a basic I/O system (BIOS) which may control basic hardware or software operation such as the interaction with peripheral components or devices.

(121) The processor **740** may include an intelligent hardware device (e.g., a general-purpose processor, a DSP, a CPU, a microcontroller, an ASIC, an FPGA, a programmable logic device, a discrete gate or transistor logic component, a discrete hardware component, or any combination thereof). In some cases, the processor **740** may be configured to operate a memory array using a memory controller. In some other cases, a memory controller may be integrated into the processor **740**. The processor **740** may be configured to execute computer-readable instructions stored in a memory (e.g., the memory **730**) to cause the device **705** to perform various functions (e.g.,

functions or tasks supporting BFD measurement relaxation for cells with multiple TRPs). For example, the device **705** or a component of the device **705** may include a processor **740** and memory **730** coupled with or to the processor **740**, the processor **740** and memory **730** configured to perform various functions described herein.

(122) The communications manager **720** may support wireless communications at a UE in accordance with examples as disclosed herein. For example, the communications manager **720** may be configured as or otherwise support a means for receiving a control message indicative of one or more parameters associated with measuring a set of multiple reference signals, where the one or more parameters are associated with adjusting one or more measurement periodicities associated with the set of multiple reference signals. The communications manager **720** may be configured as or otherwise support a means for measuring respective channel quality metrics for the set of multiple reference signals, where the set of multiple reference signals includes a first set of reference signals associated with a first TRP of a cell and a second set of reference signals associated with a second TRP of the cell. The communications manager **720** may be configured as or otherwise support a means for adjusting a measurement periodicity for the first set of reference signals according to a first parameter of the one or more parameters based on a first channel quality metric associated with the first set of reference signals, where the measurement periodicity for the first set of reference signals is separately adjustable relative to a measurement periodicity for the second set of reference signals.

(123) By including or configuring the communications manager **720** in accordance with examples as described herein, the device **705** may support techniques for BFD measurement relaxation for multi-TRP scenarios which may result in improved communication reliability, reduced latency, improved user experience related to reduced processing, reduced power consumption, more efficient utilization of communication resources, improved coordination between devices, longer battery life, and improved utilization of processing capability, among other advantages.

(124) In some examples, the communications manager **720** may be configured to perform various operations (e.g., receiving, monitoring, transmitting) using or otherwise in cooperation with the transceiver **715**, the one or more antennas **725**, or any combination thereof. Although the communications manager **720** is illustrated as a separate component, in some examples, one or more functions described with reference to the communications manager **720** may be supported by or performed by the processor **740**, the memory **730**, the code **735**, or any combination thereof. For example, the code **735** may include instructions executable by the processor **740** to cause the device **705** to perform various aspects of BFD measurement relaxation for cells with multiple TRPs as described herein, or the processor **740** and the memory **730** may be otherwise configured to perform or support such operations.

(125) FIG. **8** illustrates a block diagram **800** of a device **805** that supports BFD measurement relaxation for cells with multiple TRPs in accordance with one or more aspects of the present disclosure. The device **805** may be an example of aspects of a network entity **105** as described herein. The device **805** may include a receiver **810**, a transmitter **815**, and a communications manager **820**. The device **805** may also include a processor. Each of these components may be in communication with one another (e.g., via one or more buses).

(126) The receiver **810** may provide a means for obtaining (e.g., receiving, determining, identifying) information such as user data, control information, or any combination thereof (e.g., I/Q samples, symbols, packets, protocol data units, service data units) associated with various channels (e.g., control channels, data channels, information channels, channels associated with a protocol stack). Information may be passed on to other components of the device **805**. In some examples, the receiver **810** may support obtaining information by receiving signals via one or more antennas. Additionally, or alternatively, the receiver **810** may support obtaining information by receiving signals via one or more wired (e.g., electrical, fiber optic) interfaces, wireless interfaces, or any combination thereof.

(127) The transmitter **815** may provide a means for outputting (e.g., transmitting, providing, conveying, sending) information generated by other components of the device **805**. For example, the transmitter **815** may output information such as user data, control information, or any combination thereof (e.g., I/Q samples, symbols, packets, protocol data units, service data units) associated with various channels (e.g., control channels, data channels, information channels, channels associated with a protocol stack). In some examples, the transmitter **815** may support outputting information by transmitting signals via one or more antennas. Additionally, or alternatively, the transmitter **815** may support outputting information by transmitting signals via one or more wired (e.g., electrical, fiber optic) interfaces, wireless interfaces, or any combination thereof. In some examples, the transmitter **815** and the receiver **810** may be co-located in a transceiver, which may include or be coupled with a modem.

(128) The communications manager **820**, the receiver **810**, the transmitter **815**, or various combinations thereof or various components thereof may be examples of means for performing various aspects of BFD measurement relaxation for cells with multiple TRPs as described herein. For example, the communications manager **820**, the receiver **810**, the transmitter **815**, or various combinations or components thereof may support a method for performing one or more of the functions described herein.

(129) In some examples, the communications manager **820**, the receiver **810**, the transmitter **815**, or various combinations or components thereof may be implemented in hardware (e.g., in communications management circuitry). The hardware may include a processor, a DSP, a CPU, an ASIC, an FPGA or other programmable logic device, a microcontroller, discrete gate or transistor logic, discrete hardware components, or any combination thereof configured as or otherwise supporting a means for performing the functions described in the present disclosure. In some examples, a processor and memory coupled with the processor may be configured to perform one or more of the functions described herein (e.g., by executing, by the processor, instructions stored in the memory).

(130) Additionally, or alternatively, in some examples, the communications manager **820**, the receiver **810**, the transmitter **815**, or various combinations or components thereof may be implemented in code (e.g., as communications management software or firmware) executed by a processor. If implemented in code executed by a processor, the functions of the communications manager **820**, the receiver **810**, the transmitter **815**, or various combinations or components thereof may be performed by a general-purpose processor, a DSP, a CPU, an ASIC, an FPGA, a microcontroller, or any combination of these or other programmable logic devices (e.g., configured as or otherwise supporting a means for performing the functions described in the present disclosure).

(131) In some examples, the communications manager **820** may be configured to perform various operations (e.g., receiving, obtaining, monitoring, outputting, transmitting) using or otherwise in cooperation with the receiver **810**, the transmitter **815**, or both. For example, the communications manager **820** may receive information from the receiver **810**, send information to the transmitter **815**, or be integrated in combination with the receiver **810**, the transmitter **815**, or both to obtain information, output information, or perform various other operations as described herein.

(132) The communications manager **820** may support wireless communications at a network entity in accordance with examples as disclosed herein. For example, the communications manager **820** may be configured as or otherwise support a means for transmitting a first control message indicative of a set of multiple CORESET identifiers, where each CORESET identifier is associated with a respective TRP of a cell. The communications manager **820** may be configured as or otherwise support a means for transmitting a second control message indicative of one or more parameters associated with adjusting one or more measurement periodicities associated with measurements of a set of multiple reference signals by a UE, where the set of multiple reference signals includes a first set of reference signals associated with a first TRP of the cell and a second

set of reference signals associated with a second TRP of the cell. The communications manager **820** may be configured as or otherwise support a means for receiving a report indicative of an adjustment, by the UE, of a measurement periodicity for the first set of reference signals according to a first parameter of the one or more parameters, where the measurement periodicity for the first set of reference signals is separately adjustable relative to a measurement periodicity for the second set of reference signals.

(133) By including or configuring the communications manager **820** in accordance with examples as described herein, the device **805** (e.g., a processor controlling or otherwise coupled with the receiver **810**, the transmitter **815**, the communications manager **820**, or a combination thereof) may support techniques for BFD measurement relaxation for multi-TRP scenarios which may result in reduced processing, reduced power consumption, and more efficient utilization of communication resources, among other advantages.

(134) FIG. **9** illustrates a block diagram **900** of a device **905** that supports BFD measurement relaxation for cells with multiple TRPs in accordance with one or more aspects of the present disclosure. The device **905** may be an example of aspects of a device **805** or a network entity **105** as described herein. The device **905** may include a receiver **910**, a transmitter **915**, and a communications manager **920**. The device **905** may also include a processor. Each of these components may be in communication with one another (e.g., via one or more buses).

(135) The receiver **910** may provide a means for obtaining (e.g., receiving, determining, identifying) information such as user data, control information, or any combination thereof (e.g., I/Q samples, symbols, packets, protocol data units, service data units) associated with various channels (e.g., control channels, data channels, information channels, channels associated with a protocol stack). Information may be passed on to other components of the device **905**. In some examples, the receiver **910** may support obtaining information by receiving signals via one or more antennas. Additionally, or alternatively, the receiver **910** may support obtaining information by receiving signals via one or more wired (e.g., electrical, fiber optic) interfaces, wireless interfaces, or any combination thereof.

(136) The transmitter **915** may provide a means for outputting (e.g., transmitting, providing, conveying, sending) information generated by other components of the device **905**. For example, the transmitter **915** may output information such as user data, control information, or any combination thereof (e.g., I/Q samples, symbols, packets, protocol data units, service data units) associated with various channels (e.g., control channels, data channels, information channels, channels associated with a protocol stack). In some examples, the transmitter **915** may support outputting information by transmitting signals via one or more antennas. Additionally, or alternatively, the transmitter **915** may support outputting information by transmitting signals via one or more wired (e.g., electrical, fiber optic) interfaces, wireless interfaces, or any combination thereof. In some examples, the transmitter **915** and the receiver **910** may be co-located in a transceiver, which may include or be coupled with a modem.

(137) The device **905**, or various components thereof, may be an example of means for performing various aspects of BFD measurement relaxation for cells with multiple TRPs as described herein. For example, the communications manager **920** may include a CORESET parameter **925**, a parameter component **930**, a feedback component **935**, or any combination thereof. The communications manager **920** may be an example of aspects of a communications manager **820** as described herein. In some examples, the communications manager **920**, or various components thereof, may be configured to perform various operations (e.g., receiving, obtaining, monitoring, outputting, transmitting) using or otherwise in cooperation with the receiver **910**, the transmitter **915**, or both. For example, the communications manager **920** may receive information from the receiver **910**, send information to the transmitter **915**, or be integrated in combination with the receiver **910**, the transmitter **915**, or both to obtain information, output information, or perform various other operations as described herein.

(138) The communications manager **920** may support wireless communications at a network entity in accordance with examples as disclosed herein. The CORESET parameter **925** may be configured as or otherwise support a means for transmitting a first control message indicative of a set of multiple CORESET identifiers, where each CORESET identifier is associated with a respective TRP of a cell. The parameter component **930** may be configured as or otherwise support a means for transmitting a second control message indicative of one or more parameters associated with adjusting one or more measurement periodicities associated with measurements of a set of multiple reference signals by a UE, where the set of multiple reference signals includes a first set of reference signals associated with a first TRP of the cell and a second set of reference signals associated with a second TRP of the cell. The feedback component **935** may be configured as or otherwise support a means for receiving a report indicative of an adjustment, by the UE, of a measurement periodicity for the first set of reference signals according to a first parameter of the one or more parameters, where the measurement periodicity for the first set of reference signals is separately adjustable relative to a measurement periodicity for the second set of reference signals.

(139) FIG. **10** illustrates a block diagram **1000** of a communications manager **1020** that supports BFD measurement relaxation for cells with multiple TRPs in accordance with one or more aspects of the present disclosure. The communications manager **1020** may be an example of aspects of a communications manager **820**, a communications manager **920**, or both, as described herein. The communications manager **1020**, or various components thereof, may be an example of means for performing various aspects of BFD measurement relaxation for cells with multiple TRPs as described herein. For example, the communications manager **1020** may include a CORESET parameter **1025**, a parameter component **1030**, a feedback component **1035**, or any combination thereof. Each of these components may communicate, directly or indirectly, with one another (e.g., via one or more buses) which may include communications within a protocol layer of a protocol stack, communications associated with a logical channel of a protocol stack (e.g., between protocol layers of a protocol stack, within a device, component, or virtualized component associated with a network entity **105**, between devices, components, or virtualized components associated with a network entity **105**), or any combination thereof.

(140) The communications manager **1020** may support wireless communications at a network entity in accordance with examples as disclosed herein. The CORESET parameter **1025** may be configured as or otherwise support a means for transmitting a first control message indicative of a set of multiple CORESET identifiers, where each CORESET identifier is associated with a respective TRP of a cell. The parameter component **1030** may be configured as or otherwise support a means for transmitting a second control message indicative of one or more parameters associated with adjusting one or more measurement periodicities associated with measurements of a set of multiple reference signals by a UE, where the set of multiple reference signals includes a first set of reference signals associated with a first TRP of the cell and a second set of reference signals associated with a second TRP of the cell. The feedback component **1035** may be configured as or otherwise support a means for receiving a report indicative of an adjustment, by the UE, of a measurement periodicity for the first set of reference signals according to a first parameter of the one or more parameters, where the measurement periodicity for the first set of reference signals is separately adjustable relative to a measurement periodicity for the second set of reference signals.

(141) In some examples, first control message indicates one or more thresholds associated with channel quality metrics for the set of multiple reference signals, including a first threshold associated with the first set of reference signals and a second threshold associated with the second set of reference signals.

(142) In some examples, the first threshold and the second threshold are the same based on the first TRP and the second TRP being associated with the cell.

(143) In some examples, the first threshold and the second threshold are different based on the first TRP being associated with the first set of reference signals and the second TRP being associated

with the second set of reference signals.

(144) In some examples, the report includes an indication of a first CORESET identifier of the set of multiple CORESET identifiers. In some examples, the first CORESET identifier is associated with the first TRP of the cell.

(145) In some examples, the report further indicates an adjustment, by the UE, of the measurement periodicity for the second set of reference signals according to a second parameter of the one or more parameters. In some examples, the report includes an indication of a second CORESET identifier associated with the second TRP of the cell.

(146) In some examples, the first parameter and the second parameter are the same based on the first TRP and the second TRP being associated with the cell.

(147) In some examples, the first parameter and the second parameter are different based on the first TRP being associated with the first set of reference signals and the second TRP being associated with the second set of reference signals.

(148) In some examples, the report is received via UE assistance information.

(149) FIG. 11 illustrates a diagram of a system 1100 including a device 1105 that supports BFD measurement relaxation for cells with multiple TRPs in accordance with one or more aspects of the present disclosure. The device 1105 may be an example of or include the components of a device 805, a device 905, or a network entity 105 as described herein. The device 1105 may communicate with one or more network entities 105, one or more UEs 115, or any combination thereof, which may include communications over one or more wired interfaces, over one or more wireless interfaces, or any combination thereof. The device 1105 may include components that support outputting and obtaining communications, such as a communications manager 1120, a transceiver 1110, an antenna 1115, a memory 1125, code 1130, and a processor 1135. These components may be in electronic communication or otherwise coupled (e.g., operatively, communicatively, functionally, electronically, electrically) via one or more buses (e.g., a bus 1140).

(150) The transceiver 1110 may support bi-directional communications via wired links, wireless links, or both as described herein. In some examples, the transceiver 1110 may include a wired transceiver and may communicate bi-directionally with another wired transceiver. Additionally, or alternatively, in some examples, the transceiver 1110 may include a wireless transceiver and may communicate bi-directionally with another wireless transceiver. In some examples, the device 1105 may include one or more antennas 1115, which may be capable of transmitting or receiving wireless transmissions (e.g., concurrently). The transceiver 1110 may also include a modem to modulate signals, to provide the modulated signals for transmission (e.g., by one or more antennas 1115, by a wired transmitter), to receive modulated signals (e.g., from one or more antennas 1115, from a wired receiver), and to demodulate signals. In some implementations, the transceiver 1110 may include one or more interfaces, such as one or more interfaces coupled with the one or more antennas 1115 that are configured to support various receiving or obtaining operations, or one or more interfaces coupled with the one or more antennas 1115 that are configured to support various transmitting or outputting operations, or a combination thereof. In some implementations, the transceiver 1110 may include or be configured for coupling with one or more processors or memory components that are operable to perform or support operations based on received or obtained information or signals, or to generate information or other signals for transmission or other outputting, or any combination thereof. In some implementations, the transceiver 1110, or the transceiver 1110 and the one or more antennas 1115, or the transceiver 1110 and the one or more antennas 1115 and one or more processors or memory components (for example, the processor 1135, or the memory 1125, or both), may be included in a chip or chip assembly that is installed in the device 1105. In some examples, the transceiver may be operable to support communications via one or more communications links (e.g., a communication link 125, a backhaul communication link 120, a midhaul communication link 162, a fronthaul communication link 168).

(151) The memory 1125 may include RAM and ROM. The memory 1125 may store computer-

readable, computer-executable code **1130** including instructions that, when executed by the processor **1135**, cause the device **1105** to perform various functions described herein. The code **1130** may be stored in a non-transitory computer-readable medium such as system memory or another type of memory. In some cases, the code **1130** may not be directly executable by the processor **1135** but may cause a computer (e.g., when compiled and executed) to perform functions described herein. In some cases, the memory **1125** may contain, among other things, a BIOS which may control basic hardware or software operation such as the interaction with peripheral components or devices.

(152) The processor **1135** may include an intelligent hardware device (e.g., a general-purpose processor, a DSP, an ASIC, a CPU, an FPGA, a microcontroller, a programmable logic device, discrete gate or transistor logic, a discrete hardware component, or any combination thereof). In some cases, the processor **1135** may be configured to operate a memory array using a memory controller. In some other cases, a memory controller may be integrated into the processor **1135**. The processor **1135** may be configured to execute computer-readable instructions stored in a memory (e.g., the memory **1125**) to cause the device **1105** to perform various functions (e.g., functions or tasks supporting BFD measurement relaxation for cells with multiple TRPs). For example, the device **1105** or a component of the device **1105** may include a processor **1135** and memory **1125** coupled with the processor **1135**, the processor **1135** and memory **1125** configured to perform various functions described herein. The processor **1135** may be an example of a cloud-computing platform (e.g., one or more physical nodes and supporting software such as operating systems, virtual machines, or container instances) that may host the functions (e.g., by executing code **1130**) to perform the functions of the device **1105**. The processor **1135** may be any one or more suitable processors capable of executing scripts or instructions of one or more software programs stored in the device **1105** (such as within the memory **1125**). In some implementations, the processor **1135** may be a component of a processing system. A processing system may generally refer to a system or series of machines or components that receives inputs and processes the inputs to produce a set of outputs (which may be passed to other systems or components of, for example, the device **1105**). For example, a processing system of the device **1105** may refer to a system including the various other components or subcomponents of the device **1105**, such as the processor **1135**, or the transceiver **1110**, or the communications manager **1120**, or other components or combinations of components of the device **1105**. The processing system of the device **1105** may interface with other components of the device **1105**, and may process information received from other components (such as inputs or signals) or output information to other components. For example, a chip or modem of the device **1105** may include a processing system and one or more interfaces to output information, or to obtain information, or both. The one or more interfaces may be implemented as or otherwise include a first interface configured to output information and a second interface configured to obtain information, or a same interface configured to output information and to obtain information, among other implementations. In some implementations, the one or more interfaces may refer to an interface between the processing system of the chip or modem and a transmitter, such that the device **1105** may transmit information output from the chip or modem. Additionally, or alternatively, in some implementations, the one or more interfaces may refer to an interface between the processing system of the chip or modem and a receiver, such that the device **1105** may obtain information or signal inputs, and the information may be passed to the processing system. A person having ordinary skill in the art will readily recognize that a first interface also may obtain information or signal inputs, and a second interface also may output information or signal outputs.

(153) In some examples, a bus **1140** may support communications of (e.g., within) a protocol layer of a protocol stack. In some examples, a bus **1140** may support communications associated with a logical channel of a protocol stack (e.g., between protocol layers of a protocol stack), which may include communications performed within a component of the device **1105**, or between different

components of the device **1105** that may be co-located or located in different locations (e.g., where the device **1105** may refer to a system in which one or more of the communications manager **1120**, the transceiver **1110**, the memory **1125**, the code **1130**, and the processor **1135** may be located in one of the different components or divided between different components).

(154) In some examples, the communications manager **1120** may manage aspects of communications with a core network **130** (e.g., via one or more wired or wireless backhaul links). For example, the communications manager **1120** may manage the transfer of data communications for client devices, such as one or more UEs **115**. In some examples, the communications manager **1120** may manage communications with other network entities **105**, and may include a controller or scheduler for controlling communications with UEs **115** in cooperation with other network entities **105**. In some examples, the communications manager **1120** may support an X2 interface within an LTE/LTE-A wireless communications network technology to provide communication between network entities **105**.

(155) The communications manager **1120** may support wireless communications at a network entity in accordance with examples as disclosed herein. For example, the communications manager **1120** may be configured as or otherwise support a means for transmitting a first control message indicative of a set of multiple CORESET identifiers, where each CORESET identifier is associated with a respective TRP of a cell. The communications manager **1120** may be configured as or otherwise support a means for transmitting a second control message indicative of one or more parameters associated with adjusting one or more measurement periodicities associated with measurements of a set of multiple reference signals by a UE, where the set of multiple reference signals includes a first set of reference signals associated with a first TRP of the cell and a second set of reference signals associated with a second TRP of the cell. The communications manager **1120** may be configured as or otherwise support a means for receiving a report indicative of an adjustment, by the UE, of a measurement periodicity for the first set of reference signals according to a first parameter of the one or more parameters, where the measurement periodicity for the first set of reference signals is separately adjustable relative to a measurement periodicity for the second set of reference signals.

(156) By including or configuring the communications manager **1120** in accordance with examples as described herein, the device **1105** may support techniques for BFD measurement relaxation for multi-TRP scenarios which may result in improved communication reliability, reduced latency, improved user experience related to reduced processing, reduced power consumption, more efficient utilization of communication resources, improved coordination between devices, longer battery life, and improved utilization of processing capability, among other advantages.

(157) In some examples, the communications manager **1120** may be configured to perform various operations (e.g., receiving, obtaining, monitoring, outputting, transmitting) using or otherwise in cooperation with the transceiver **1110**, the one or more antennas **1115** (e.g., where applicable), or any combination thereof. Although the communications manager **1120** is illustrated as a separate component, in some examples, one or more functions described with reference to the communications manager **1120** may be supported by or performed by the transceiver **1110**, the processor **1135**, the memory **1125**, the code **1130**, or any combination thereof. For example, the code **1130** may include instructions executable by the processor **1135** to cause the device **1105** to perform various aspects of BFD measurement relaxation for cells with multiple TRPs as described herein, or the processor **1135** and the memory **1125** may be otherwise configured to perform or support such operations.

(158) FIG. **12** illustrates a flowchart showing a method **1200** that supports BFD measurement relaxation for cells with multiple TRPs in accordance with one or more aspects of the present disclosure. The operations of the method **1200** may be implemented by a UE or its components as described herein. For example, the operations of the method **1200** may be performed by a UE **115** as described with reference to FIGS. **1** through **7**. In some examples, a UE may execute a set of

instructions to control the functional elements of the UE to perform the described functions. Additionally, or alternatively, the UE may perform aspects of the described functions using special-purpose hardware.

(159) At **1205**, the method may include receiving a control message indicative of one or more parameters associated with measuring a set of multiple reference signals, where the one or more parameters are associated with adjusting one or more measurement periodicities associated with the set of multiple reference signals. The operations of **1205** may be performed in accordance with examples as disclosed herein. In some examples, aspects of the operations of **1205** may be performed by a parameter component **625** as described with reference to FIG. **6**. Additionally, or alternatively, means for performing **1205** may, but not necessarily, include, for example, antenna **725**, transceiver **715**, communications manager **720**, memory **730** (including code **735**), processor **740** and/or bus **745**.

(160) At **1210**, the method may include measuring respective channel quality metrics for the set of multiple reference signals, where the set of multiple reference signals includes a first set of reference signals associated with a first TRP of a cell and a second set of reference signals associated with a second TRP of the cell. The operations of **1210** may be performed in accordance with examples as disclosed herein. In some examples, aspects of the operations of **1210** may be performed by a measuring component **630** as described with reference to FIG. **6**. Additionally, or alternatively, means for performing **1210** may, but not necessarily, include, for example, antenna **725**, transceiver **715**, communications manager **720**, memory **730** (including code **735**), processor **740** and/or bus **745**.

(161) At **1215**, the method may include adjusting a measurement periodicity for the first set of reference signals according to a first parameter of the one or more parameters based on a first channel quality metric associated with the first set of reference signals, where the measurement periodicity for the first set of reference signals is separately adjustable relative to a measurement periodicity for the second set of reference signals. The operations of **1215** may be performed in accordance with examples as disclosed herein. In some examples, aspects of the operations of **1215** may be performed by a relaxation component **635** as described with reference to FIG. **6**. Additionally, or alternatively, means for performing **1215** may, but not necessarily, include, for example, antenna **725**, transceiver **715**, communications manager **720**, memory **730** (including code **735**), processor **740** and/or bus **745**.

(162) FIG. **13** illustrates a flowchart showing a method **1300** that supports BFD measurement relaxation for cells with multiple TRPs in accordance with one or more aspects of the present disclosure. The operations of the method **1300** may be implemented by a UE or its components as described herein. For example, the operations of the method **1300** may be performed by a UE **115** as described with reference to FIGS. **1** through **7**. In some examples, a UE may execute a set of instructions to control the functional elements of the UE to perform the described functions. Additionally, or alternatively, the UE may perform aspects of the described functions using special-purpose hardware.

(163) At **1305**, the method may include receiving a control message indicative of one or more parameters associated with measuring a set of multiple reference signals, where the one or more parameters are associated with adjusting one or more measurement periodicities associated with the set of multiple reference signals. The operations of **1305** may be performed in accordance with examples as disclosed herein. In some examples, aspects of the operations of **1305** may be performed by a parameter component **625** as described with reference to FIG. **6**. Additionally, or alternatively, means for performing **1305** may, but not necessarily, include, for example, antenna **725**, transceiver **715**, communications manager **720**, memory **730** (including code **735**), processor **740** and/or bus **745**.

(164) At **1310**, the method may include measuring respective channel quality metrics for the set of multiple reference signals, where the set of multiple reference signals includes a first set of

reference signals associated with a first TRP of a cell and a second set of reference signals associated with a second TRP of the cell. The operations of **1310** may be performed in accordance with examples as disclosed herein. In some examples, aspects of the operations of **1310** may be performed by a measuring component **630** as described with reference to FIG. 6. Additionally, or alternatively, means for performing **1310** may, but not necessarily, include, for example, antenna **725**, transceiver **715**, communications manager **720**, memory **730** (including code **735**), processor **740** and/or bus **745**.

(165) At **1315**, the method may include adjusting a measurement periodicity for the first set of reference signals according to a first parameter of the one or more parameters based on a first channel quality metric associated with the first set of reference signals, where the measurement periodicity for the first set of reference signals is separately adjustable relative to a measurement periodicity for the second set of reference signals. The operations of **1315** may be performed in accordance with examples as disclosed herein. In some examples, aspects of the operations of **1315** may be performed by a relaxation component **635** as described with reference to FIG. 6. Additionally, or alternatively, means for performing **1315** may, but not necessarily, include, for example, antenna **725**, transceiver **715**, communications manager **720**, memory **730** (including code **735**), processor **740** and/or bus **745**.

(166) At **1320**, the method may include transmitting a report indicating the adjustment of the measurement periodicity for the first set of reference signals, where the report includes an indication of a first CORESET identifier associated with the first TRP of the cell. The operations of **1320** may be performed in accordance with examples as disclosed herein. In some examples, aspects of the operations of **1320** may be performed by a reporting component **640** as described with reference to FIG. 6. Additionally, or alternatively, means for performing **1320** may, but not necessarily, include, for example, antenna **725**, transceiver **715**, communications manager **720**, memory **730** (including code **735**), processor **740** and/or bus **745**.

(167) FIG. 14 illustrates a flowchart showing a method **1400** that supports BFD measurement relaxation for cells with multiple TRPs in accordance with one or more aspects of the present disclosure. The operations of the method **1400** may be implemented by a network entity or its components as described herein. For example, the operations of the method **1400** may be performed by a network entity as described with reference to FIGS. 1 through 3 and 8 through 11. In some examples, a network entity may execute a set of instructions to control the functional elements of the network entity to perform the described functions. Additionally, or alternatively, the network entity may perform aspects of the described functions using special-purpose hardware.

(168) At **1405**, the method may include transmitting a first control message indicative of a set of multiple CORESET identifiers, where each CORESET identifier is associated with a respective TRP of a cell. The operations of **1405** may be performed in accordance with examples as disclosed herein. In some examples, aspects of the operations of **1405** may be performed by a CORESET parameter **1025** as described with reference to FIG. 10. Additionally, or alternatively, means for performing **1405** may, but not necessarily, include, for example, antenna **1115**, transceiver **1110**, communications manager **1120**, memory **1125** (including code **1130**), processor **1135** and/or bus **1140**.

(169) At **1410**, the method may include transmitting a second control message indicative of one or more parameters associated with adjusting one or more measurement periodicities associated with measurements of a set of multiple reference signals by a UE, where the set of multiple reference signals includes a first set of reference signals associated with a first TRP of the cell and a second set of reference signals associated with a second TRP of the cell. The operations of **1410** may be performed in accordance with examples as disclosed herein. In some examples, aspects of the operations of **1410** may be performed by a parameter component **1030** as described with reference to FIG. 10. Additionally, or alternatively, means for performing **1410** may, but not necessarily, include, for example, antenna **1115**, transceiver **1110**, communications manager **1120**, memory

1125 (including code **1130**), processor **1135** and/or bus **1140**.

(170) At **1415**, the method may include receiving a report indicative of an adjustment, by the UE, of a measurement periodicity for the first set of reference signals according to a first parameter of the one or more parameters, where the measurement periodicity for the first set of reference signals is separately adjustable relative to a measurement periodicity for the second set of reference signals. The operations of **1415** may be performed in accordance with examples as disclosed herein. In some examples, aspects of the operations of **1415** may be performed by a feedback component **1035** as described with reference to FIG. **10**. Additionally, or alternatively, means for performing **1415** may, but not necessarily, include, for example, antenna **1115**, transceiver **1110**, communications manager **1120**, memory **1125** (including code **1130**), processor **1135** and/or bus **1140**.

(171) The following provides an overview of aspects of the present disclosure:

(172) Aspect 1: A method for wireless communications at a UE, comprising: receiving a control message indicative of one or more parameters associated with measuring a plurality of reference signals, wherein the one or more parameters are associated with adjusting one or more measurement periodicities associated with the plurality of reference signals; measuring respective channel quality metrics for the plurality of reference signals, wherein the plurality of reference signals comprises a first set of reference signals associated with a first TRP of a cell and a second set of reference signals associated with a second TRP of the cell; and adjusting a measurement periodicity for the first set of reference signals according to a first parameter of the one or more parameters based at least in part on a first channel quality metric associated with the first set of reference signals, wherein the measurement periodicity for the first set of reference signals is separately adjustable relative to a measurement periodicity for the second set of reference signals.

(173) Aspect 2: The method of aspect 1, wherein the channel quality metrics comprise SINR ratios, and wherein adjusting the measurement periodicity for the first set of reference signals comprises: adjusting a time gap between successive measurements for the first set of reference signals based at least in part on a first SINR ratio associated with the first set of reference signals exceeding a first threshold.

(174) Aspect 3: The method of aspect 2, wherein the control message indicates the first threshold associated with the first set of reference signals and a second threshold associated with the second set of reference signals.

(175) Aspect 4: The method of aspect 3, wherein the first threshold and the second threshold are the same based at least in part on the first TRP and the second TRP being associated with the cell.

(176) Aspect 5: The method of aspect 3, wherein the first threshold and the second threshold are different based at least in part on the first TRP being associated with the first set of reference signals and the second TRP being associated with the second set of reference signals.

(177) Aspect 6: The method of any of aspects 1 through 5, further comprising: maintaining the measurement periodicity for the second set of reference signals based at least in part on a second channel quality metric associated with the second set of reference signals failing to exceed a threshold.

(178) Aspect 7: The method of aspect 6, wherein maintaining the measurement periodicity for the second set of reference signals is based at least in part on a SINR ratio associated with the second set of reference signals failing to exceed a threshold, and the second channel quality metric is the SINR ratio.

(179) Aspect 8: The method of any of aspects 1 through 5, further comprising: adjusting the measurement periodicity for the second set of reference signals according to a second parameter of the one or more parameters based at least in part on a second channel quality metric associated with the second set of reference signals.

(180) Aspect 9: The method of aspect 8, wherein the first parameter and the second parameter are the same based at least in part on the first TRP and the second TRP being associated with the cell.

- (181) Aspect 10: The method of aspect 8, wherein the first parameter and the second parameter are different based at least in part on the first TRP being associated with the first set of reference signals and the second TRP being associated with the second set of reference signals.
- (182) Aspect 11: The method of any of aspects 8 through 10, wherein adjusting the measurement periodicity for the second set of reference signals is based at least in part on a SINR ratio associated with the second set of reference signals exceeding a threshold, and the second channel quality metric is the SINR ratio.
- (183) Aspect 12: The method of any of aspects 1 through 11, further comprising: transmitting a report indicating the adjustment of the measurement periodicity for the first set of reference signals, wherein the report comprises an indication of a first CORESET identifier associated with the first TRP of the cell.
- (184) Aspect 13: The method of aspect 12, wherein the report further indicates an adjustment of the measurement periodicity for the second set of reference signals, and the report comprises an indication of a second CORESET identifier associated with the second TRP of the cell.
- (185) Aspect 14: The method of any of aspects 12 through 13, wherein the report is transmitted via UE assistance information.
- (186) Aspect 15: The method of any of aspects 1 through 14, further comprising: determining a mobility metric associated with the UE, wherein adjusting the measurement periodicity for the first set of reference signals is based at least in part on the mobility metric associated with the UE being associated with a low mobility scenario.
- (187) Aspect 16: The method of aspect 15, wherein the mobility metric is associated with the first TRP and the second TRP based at least in part on the first TRP and the second TRP being associated with the cell.
- (188) Aspect 17: The method of any of aspects 1 through 16, further comprising: receiving a second control message indicative of a plurality of CORESET identifiers, wherein each CORESET identifier is associated with a respective TRP of the cell.
- (189) Aspect 18: The method of any of aspects 1 through 17, wherein adjusting the measurement periodicity for the first set of reference signals comprises increasing a time gap between successive measurements of the first set of reference signals based at least in part on the first parameter.
- (190) Aspect 19: A method for wireless communications at a network entity, comprising: transmitting a first control message indicative of a plurality of CORESET identifiers, wherein each CORESET identifier is associated with a respective TRP of a cell; transmitting a second control message indicative of one or more parameters associated with adjusting one or more measurement periodicities associated with measurements of a plurality of reference signals by a UE, wherein the plurality of reference signals comprises a first set of reference signals associated with a first TRP of the cell and a second set of reference signals associated with a second TRP of the cell; and receiving a report indicative of an adjustment, by the UE, of a measurement periodicity for the first set of reference signals according to a first parameter of the one or more parameters, wherein the measurement periodicity for the first set of reference signals is separately adjustable relative to a measurement periodicity for the second set of reference signals.
- (191) Aspect 20: The method of aspect 19, wherein first control message indicates one or more thresholds associated with channel quality metrics for the plurality of reference signals, including a first threshold associated with the first set of reference signals and a second channel quality threshold associated with the second set of reference signals.
- (192) Aspect 21: The method of aspect 20, wherein the first threshold and the second threshold are the same based at least in part on the first TRP and the second TRP being associated with the cell.
- (193) Aspect 22: The method of aspect 20, wherein the first threshold and the second threshold are different based at least in part on the first TRP being associated with the first set of reference signals and the second TRP being associated with the second set of reference signals.
- (194) Aspect 23: The method of any of aspects 19 through 22, wherein the report comprises an

indication of a CORESET identifier of the plurality of CORESET identifiers, and the CORESET identifier is associated with the first TRP of the cell.

(195) Aspect 24: The method of any of aspects 19 through 23, wherein the report further indicates an adjustment, by the UE, of the measurement periodicity for the second set of reference signals according to a second parameter of the one or more parameters, and the report comprises an indication of a CORESET identifier associated with the second TRP of the cell.

(196) Aspect 25: The method of aspect 24, wherein the first parameter and the second parameter are the same based at least in part on the first TRP and the second TRP being associated with the cell.

(197) Aspect 26: The method of aspect 24, wherein the first parameter and the second parameter are different based at least in part on the first TRP being associated with the first set of reference signals and the second TRP being associated with the second set of reference signals.

(198) Aspect 27: The method of any of aspects 19 through 26, wherein the report is received via UE assistance information.

(199) Aspect 28: An apparatus for wireless communications at a UE, comprising a processor; a transceiver; and at least one processor coupled with the memory and the transceiver, the at least one processor configured to cause the apparatus to perform a method of any of aspects 1 through 18.

(200) Aspect 29: An apparatus for wireless communications at a UE, comprising at least one means for performing a method of any of aspects 1 through 18.

(201) Aspect 30: A non-transitory computer-readable medium storing code for wireless communications at a UE, the code comprising instructions executable by a processor to perform a method of any of aspects 1 through 18.

(202) Aspect 31: An apparatus for wireless communications at a network entity, comprising a processor; and at least one processor coupled with the memory, the at least one processor configured to cause the apparatus to perform a method of any of aspects 19 through 27.

(203) Aspect 32: An apparatus for wireless communications at a network entity, comprising at least one means for performing a method of any of aspects 19 through 27.

(204) Aspect 33: A non-transitory computer-readable medium storing code for wireless communications at a network entity, the code comprising instructions executable by a processor to perform a method of any of aspects 19 through 27.

(205) It should be noted that the methods described herein describe possible implementations, and that the operations and the steps may be rearranged or otherwise modified and that other implementations are possible. Further, aspects from two or more of the methods may be combined.

(206) Although aspects of an LTE, LTE-A, LTE-A Pro, or NR system may be described for purposes of example, and LTE, LTE-A, LTE-A Pro, or NR terminology may be used in much of the description, the techniques described herein are applicable beyond LTE, LTE-A, LTE-A Pro, or NR networks. For example, the described techniques may be applicable to various other wireless communications systems such as Ultra Mobile Broadband (UMB), Institute of Electrical and Electronics Engineers (IEEE) 802.11 (Wi-Fi), IEEE 802.16 (WiMAX), IEEE 802.20, Flash-OFDM, as well as other systems and radio technologies not explicitly mentioned herein.

(207) Information and signals described herein may be represented using any of a variety of different technologies and techniques. For example, data, instructions, commands, information, signals, bits, symbols, and chips that may be referenced throughout the description may be represented by voltages, currents, electromagnetic waves, magnetic fields or particles, optical fields or particles, or any combination thereof.

(208) The various illustrative blocks and components described in connection with the disclosure herein may be implemented or performed using a general-purpose processor, a DSP, an ASIC, a CPU, an FPGA or other programmable logic device, discrete gate or transistor logic, discrete hardware components, or any combination thereof designed to perform the functions described herein. A general-purpose processor may be a microprocessor but, in the alternative, the processor

may be any processor, controller, microcontroller, or state machine. A processor may also be implemented as a combination of computing devices (e.g., a combination of a DSP and a microprocessor, multiple microprocessors, one or more microprocessors in conjunction with a DSP core, or any other such configuration).

(209) The functions described herein may be implemented using hardware, software executed by a processor, firmware, or any combination thereof. If implemented using software executed by a processor, the functions may be stored as or transmitted using one or more instructions or code of a computer-readable medium. Other examples and implementations are within the scope of the disclosure and appended claims. For example, due to the nature of software, functions described herein may be implemented using software executed by a processor, hardware, firmware, hardwiring, or combinations of any of these. Features implementing functions may also be physically located at various positions, including being distributed such that portions of functions are implemented at different physical locations.

(210) Computer-readable media includes both non-transitory computer storage media and communication media including any medium that facilitates transfer of a computer program from one location to another. A non-transitory storage medium may be any available medium that may be accessed by a general-purpose or special-purpose computer. By way of example, and not limitation, non-transitory computer-readable media may include RAM, ROM, electrically erasable programmable ROM (EEPROM), flash memory, compact disk (CD) ROM or other optical disk storage, magnetic disk storage or other magnetic storage devices, or any other non-transitory medium that may be used to carry or store desired program code means in the form of instructions or data structures and that may be accessed by a general-purpose or special-purpose computer, or a general-purpose or special-purpose processor. Also, any connection is properly termed a computer-readable medium. For example, if the software is transmitted from a website, server, or other remote source using a coaxial cable, fiber optic cable, twisted pair, digital subscriber line (DSL), or wireless technologies such as infrared, radio, and microwave, then the coaxial cable, fiber optic cable, twisted pair, DSL, or wireless technologies such as infrared, radio, and microwave are included in the definition of computer-readable medium. Disk and disc, as used herein, include CD, laser disc, optical disc, digital versatile disc (DVD), floppy disk and Blu-ray disc. Disks may reproduce data magnetically, and discs may reproduce data optically using lasers. Combinations of the above are also included within the scope of computer-readable media.

(211) As used herein, including in the claims, “or” as used in a list of items (e.g., a list of items prefaced by a phrase such as “at least one of” or “one or more of”) indicates an inclusive list such that, for example, a list of at least one of A, B, or C means A or B or C or AB or AC or BC or ABC (i.e., A and B and C). Also, as used herein, the phrase “based on” shall not be construed as a reference to a closed set of conditions. For example, an example step that is described as “based on condition A” may be based on both a condition A and a condition B without departing from the scope of the present disclosure. In other words, as used herein, the phrase “based on” shall be construed in the same manner as the phrase “based at least in part on.”

(212) The term “determine” or “determining” encompasses a variety of actions and, therefore, “determining” can include calculating, computing, processing, deriving, investigating, looking up (such as via looking up in a table, a database or another data structure), ascertaining and the like. Also, “determining” can include receiving (e.g., receiving information), accessing (e.g., accessing data stored in memory) and the like. Also, “determining” can include resolving, obtaining, selecting, choosing, establishing, and other such similar actions.

(213) In the appended figures, similar components or features may have the same reference label. Further, various components of the same type may be distinguished by following the reference label by a dash and a second label that distinguishes among the similar components. If just the first reference label is used in the specification, the description is applicable to any one of the similar components having the same first reference label irrespective of the second reference label, or other

subsequent reference label.

(214) The description set forth herein, in connection with the appended drawings, describes example configurations and does not represent all the examples that may be implemented or that are within the scope of the claims. The term “example” used herein means “serving as an example, instance, or illustration,” and not “preferred” or “advantageous over other examples.” The detailed description includes specific details for the purpose of providing an understanding of the described techniques. These techniques, however, may be practiced without these specific details. In some instances, known structures and devices are shown in block diagram form in order to avoid obscuring the concepts of the described examples.

(215) The description herein is provided to enable a person having ordinary skill in the art to make or use the disclosure. Various modifications to the disclosure will be apparent to a person having ordinary skill in the art, and the generic principles defined herein may be applied to other variations without departing from the scope of the disclosure. Thus, the disclosure is not limited to the examples and designs described herein but is to be accorded the broadest scope consistent with the principles and novel features disclosed herein.

Claims

1. An apparatus for wireless communications at a user equipment (UE), comprising: memory; a transceiver; and at least one processor of a user equipment (UE), the at least one processor coupled with the memory and the transceiver and configured to cause the apparatus to: receive, via the transceiver, a control message indicative of one or more parameters associated with measuring a plurality of reference signals, wherein the one or more parameters are associated with adjusting one or more measurement periodicities associated with the plurality of reference signals; measure respective channel quality metrics for the plurality of reference signals, wherein the plurality of reference signals comprises a first set of reference signals associated with a first transmission reception point of a cell and a second set of reference signals associated with a second transmission reception point of the cell; and adjust a measurement periodicity for the first set of reference signals according to a first parameter of the one or more parameters based at least in part on a first channel quality metric associated with the first set of reference signals, wherein the measurement periodicity for the first set of reference signals is separately adjustable relative to a measurement periodicity for the second set of reference signals.
2. The apparatus of claim 1, wherein, to adjust the measurement periodicity for the first set of reference signals, the processor is configured to cause the apparatus to: adjust a time gap between successive measurements for the first set of reference signals based at least in part on a first signal to interference and noise ratio associated with the first set of reference signals exceeding a first threshold.
3. The apparatus of claim 2, wherein the control message indicates the first threshold associated with the first set of reference signals and a second threshold associated with the second set of reference signals.
4. The apparatus of claim 3, wherein the first threshold and the second threshold are the same based at least in part on the first transmission reception point and the second transmission reception point being associated with the cell or are different based at least in part on the first transmission reception point being associated with the first set of reference signals and the second transmission reception point being associated with the second set of reference signals.
5. The apparatus of claim 1, the at least one processor further configured to cause the apparatus to: maintain the measurement periodicity for the second set of reference signals based at least in part on a second channel quality metric associated with the second set of reference signals.
6. The apparatus of claim 5, wherein the at least one processor is configured to cause the apparatus to maintain the measurement periodicity for the second set of reference signals based at least in part

on a signal to interference and noise ratio associated with the second set of reference signals failing to exceed a threshold, and wherein the second channel quality metric is the signal to interference and noise ratio.

7. The apparatus of claim 1, the at least one processor further configured to cause the apparatus to: adjust the measurement periodicity for the second set of reference signals according to a second parameter of the one or more parameters based at least in part on a second channel quality metric associated with the second set of reference signals.

8. The apparatus of claim 7, wherein the first parameter and the second parameter are the same based at least in part on the first transmission reception point and the second transmission reception point being associated with the cell or are different based at least in part on the first transmission reception point being associated with the first set of reference signals and the second transmission reception point being associated with the second set of reference signals.

9. The apparatus of claim 7, wherein the at least one processor is configured to cause the apparatus to adjust the measurement periodicity for the second set of reference signals based at least in part on a signal to interference and noise ratio associated with the second set of reference signals exceeding a threshold, and wherein the second channel quality metric is the signal to interference and noise ratio.

10. The apparatus of claim 1, the at least one processor further configured to cause the apparatus to: transmit, via the transceiver, a report indicating the adjustment of the measurement periodicity for the first set of reference signals, wherein the report comprises an indication of a first control resource set identifier associated with the first transmission reception point of the cell.

11. The apparatus of claim 10, wherein the report further indicates an adjustment of the measurement periodicity for the second set of reference signals, and wherein the report comprises an indication of a second control resource set identifier associated with the second transmission reception point of the cell.

12. The apparatus of claim 1, the at least one processor further configured to cause the apparatus to: determine a mobility metric associated with the UE, wherein adjusting the measurement periodicity for the first set of reference signals is based at least in part on the mobility metric associated with the UE being associated with a low mobility scenario.

13. The apparatus of claim 1, the at least one processor further configured to cause the apparatus to: receive, via the transceiver, a second control message indicative of a plurality of control resource set identifiers, wherein each control resource set identifier is associated with a respective transmission reception point of the cell.

14. An apparatus for wireless communications at a wireless device, comprising: memory; and at least one processor of a network entity, the at least one processor coupled with the memory and configured to cause the apparatus to: transmit a first control message indicative of a plurality of control resource set identifiers, wherein each control resource set identifier is associated with a respective transmission reception point of a cell; transmit a second control message indicative of one or more parameters associated with adjusting one or more measurement periodicities associated with measurements of a plurality of reference signals by a user equipment (UE), wherein the plurality of reference signals comprises a first set of reference signals associated with a first transmission reception point of the cell and a second set of reference signals associated with a second transmission reception point of the cell; and receive a report indicative of an adjustment, by the UE, of a measurement periodicity for the first set of reference signals according to a first parameter of the one or more parameters, wherein the measurement periodicity for the first set of reference signals is separately adjustable relative to a measurement periodicity for the second set of reference signals.

15. The apparatus of claim 14, wherein first control message indicates one or more thresholds associated with channel quality metrics for the plurality of reference signals, including a first threshold associated with the first set of reference signals and a second threshold associated with

the second set of reference signals.

16. The apparatus of claim 15, wherein the first threshold and the second threshold are the same based at least in part on the first transmission reception point and the second transmission reception point being associated with the cell or are different based at least in part on the first transmission reception point being associated with the first set of reference signals and the second transmission reception point being associated with the second set of reference signals.

17. The apparatus of claim 14, wherein the report comprises an indication of a first control resource set identifier of the plurality of control resource set identifiers, and wherein the first control resource set identifier is associated with the first transmission reception point of the cell.

18. The apparatus of claim 14, wherein the report further indicates an adjustment, by the UE, of the measurement periodicity for the second set of reference signals according to a second parameter of the one or more parameters, and wherein the report comprises an indication of a second control resource set identifier associated with the second transmission reception point of the cell.

19. The apparatus of claim 18, wherein the first parameter and the second parameter are the same based at least in part on the first transmission reception point and the second transmission reception point being associated with the cell or are different based at least in part on the first transmission reception point being associated with the first set of reference signals and the second transmission reception point being associated with the second set of reference signals.

20. A method for wireless communications at a user equipment (UE), comprising: receiving a control message indicative of one or more parameters associated with measuring a plurality of reference signals, wherein the one or more parameters are associated with adjusting one or more measurement periodicities associated with the plurality of reference signals; measuring respective channel quality metrics for the plurality of reference signals, wherein the plurality of reference signals comprises a first set of reference signals associated with a first transmission reception point of a cell and a second set of reference signals associated with a second transmission reception point of the cell; and adjusting a measurement periodicity for the first set of reference signals according to a first parameter of the one or more parameters based at least in part on a first channel quality metric associated with the first set of reference signals, wherein the measurement periodicity for the first set of reference signals is separately adjustable relative to a measurement periodicity for the second set of reference signals.
