

US Patent & Trademark Office

Patent Public Search | Text View

United States Patent	12407949
Kind Code	B2
Date of Patent	September 02, 2025
Inventor(s)	Lim; Wooi Kip

Optical sensor mechanism capable of improving signal sensitivity of motion detection as well as consuming lower power

Abstract

An optical sensor device includes a pixel array and a control circuit. The pixel array has pixel units arranged in N rows and M columns, and a pixel unit comprises: a photo transistor, configured to capture and generate a first image signal during a first shutter exposure time interval of a first time and to capture and generate a second image signal during a second shutter exposure time interval of a second time, the first time and the second time being consecutive; a first integration capacitor, coupled to the photo transistor, for storing the first image signal; and a second integration capacitor, coupled to the photo transistor, for storing the second image signal. The control circuit performs a motion detection to determine whether a motion occurs according to a difference between the two image signals.

Inventors:	Lim; Wooi Kip (Penang, MY)
Applicant:	PixArt Imaging Inc. (Hsin-Chu, TW)
Family ID:	94386901
Assignee:	PixArt Imaging Inc. (Hsin-Chu, TW)
Appl. No.:	18/229169
Filed:	August 01, 2023

Prior Publication Data

Document Identifier	Publication Date
US 20250047991 A1	Feb. 06, 2025

Publication Classification

Int. Cl.: H04N25/53 (20230101); G03B7/093 (20210101); G06T7/20 (20170101); H04N25/62 (20230101); H04N25/771 (20230101)

U.S. Cl.:

CPC **H04N25/53** (20230101); **G03B7/093** (20130101); **G06T7/20** (20130101); **H04N25/62** (20230101); **H04N25/771** (20230101); G06T2207/10144 (20130101)

Field of Classification Search

CPC: H04N (25/53); H04N (25/62); H04N (25/771); H04N (25/707); G03B (7/093); G06T (7/20); G06T (2207/10144)

USPC: 348/297

References Cited

U.S. PATENT DOCUMENTS

Patent No.	Issued Date	Patentee Name	U.S. Cl.	CPC
2009/0321641	12/2008	Park	257/E31.054	G01J 5/20
2019/0026901	12/2018	Fu	N/A	H04N 25/76
2020/0351417	12/2019	Hanwell	N/A	H04N 23/45

Primary Examiner: Ye; Lin
Assistant Examiner: Nguyen; Chan T

Background/Summary

BACKGROUND OF THE INVENTION

1. Field of the Invention
- (1) The invention relates to an optical sensor mechanism, and more particularly to optical sensor devices and corresponding methods.
2. Description of the Prior Art
- (2) Generally speaking, the performance of a conventional optical sensor device is easily degraded due to different shot noise levels of different light conditions. For example, the conventional optical sensor device may detect a false motion caused by a higher shot noise. The conventional optical sensor device cannot accurately perform the motion detection. In addition, the conventional optical sensor may consume higher power.

SUMMARY OF THE INVENTION

- (3) Therefore one of the objectives of the invention is to provide optical sensor devices and methods to solve the above-mentioned problems.
- (4) According to an embodiment, an optical sensor device is disclosed. The optical sensor device comprises a pixel array and a control circuit. The pixel array has a plurality of pixel units arranged in N rows and M columns, and a first pixel unit in the plurality of pixel units comprise a photo transistor, a first integration capacitor, and a second integration capacitor. The photo transistor is configured to capture and generate a first image signal during a first shutter exposure time interval of a first time and to capture and generate a second image signal during a second shutter exposure time interval of a second time, and the first time and the second time are consecutive. The first integration capacitor is coupled to the photo transistor and used for storing the first image signal. The second integration capacitor is coupled to the photo transistor and used for storing the second

image signal. The control circuit is coupled to the first pixel unit. The first shutter exposure time interval is different from the second shutter exposure time interval. The control circuit performs a motion detection to determine whether a motion occurs according to a difference between the first image signal captured during the first shutter exposure time interval and the second image signal captured during the second shutter exposure time interval.

(5) According to an embodiment, a method of an optical sensor device is disclosed. The method comprises: providing the above-mentioned pixel array, configuring the first shutter exposure time interval to be different from the second shutter exposure time interval; and performing a motion detection to determine whether a motion occurs according to a difference between the first image signal captured during the first shutter exposure time interval and the second image signal captured during the second shutter exposure time interval.

(6) These and other objectives of the present invention will no doubt become obvious to those of ordinary skill in the art after reading the following detailed description of the preferred embodiment that is illustrated in the various figures and drawings.

Description

BRIEF DESCRIPTION OF THE DRAWINGS

(1) FIG. 1 is a circuit diagram of a novel pixel unit such as a bipolar junction transistor (BJT) sensing pixel (or referred to as a BJT pixel unit) disposed in a pixel array according to an embodiment of the invention.

(2) FIG. 2 is a diagram of an optical sensor device comprising multiple BJT sensing pixels in FIG. 1 according to an embodiment of the invention.

(3) FIG. 3 is a diagram showing an example of the shutter exposure time intervals of times T1-T3 according to an embodiment of the invention.

(4) FIG. 4 is a diagram of examples showing the relation between the light intensity and pixel output signal voltage level according to an embodiment of the invention.

(5) FIG. 5 is a circuit diagram of two novel BJT sensing pixels disposed at different spatial locations of the same column of a pixel array according to an embodiment of the invention.

(6) FIG. 6 is a diagram of an optical sensor device according to an embodiment of the invention.

(7) FIG. 7 is a diagram of an example of the control signals NSH1 and NSH2 and the read controls signals RD1 and RD2 of FIG. 5 according to an embodiment of the invention.

DETAILED DESCRIPTION

(8) The invention aims at providing a technical solution of optical sensor devices having BJT sensing pixels and capable of accurately determining whether a motion occurs in the sensed images/frames as well as merely consuming low power.

(9) Refer to FIG. 1. FIG. 1 is a circuit diagram of a novel pixel unit **100** such as a bipolar junction transistor (BJT) sensing pixel (or referred to as a BJT pixel unit) disposed in a pixel array according to an embodiment of the invention. As shown in FIG. 1, the BJT sensing pixel **100** comprises a photo transistor such as a BJT-based photo sensing transistor BJT, a shutter control circuit **105**, a readout control circuit **110**, a first integration capacitor INT, and a second integration capacitor INTD. The shutter control circuit **105** comprises MOS transistors such as NMOS (N-channel MOS) transistors m1, m2, m4, and PMOS (P-channel) transistors m3 and m5. The readout control circuit **110** comprises multiple MOS transistors m6-m16, and two source follower transistors sf1 and sf2.

(10) As shown in FIG. 1, for example, the transistor m1 has a first terminal (e.g. a drain terminal) coupled to the control terminal (e.g. a gate terminal of transistor m2) and a first terminal (e.g. the drain terminal) of transistor m3, a second terminal (e.g. a source terminal) coupled to the ground level GNDA, and a control terminal (gate terminal) coupled to the base of the BJT transistor BJT.

The transistor m2 has the gate terminal coupled to the drain terminal of transistor m1 and the drain terminal of transistor m3, has the drain terminal coupled to the source terminal of transistor m4, source terminal of transistor m5, and source terminal of transistor m9, and has the source terminal coupled to the emitter of the BJT transistor BJT. The transistor m3 has the gate terminal coupled to the control signal PBB, the source terminal coupled to the supply voltage vdda such as 1.8 Volts (but not limited), and the drain terminal coupled to the gate terminal of transistor m2 and drain terminal of transistor m1. The circuit structures and connections of the other MOS transistors are shown in FIG. 1.

(11) Particularly, the transistor m5 has the gate terminal coupled to the control signal NSH1, has the source terminal coupled to the drain terminal of transistor m2, and has the drain terminal coupled to the drain terminal of transistor m6 and source terminal of transistor m7. The transistor m7 has the gate terminal coupled to the control signal NS1, has the source terminal coupled to the drain terminal of transistor m6, and has the drain terminal coupled to the first integration capacitor INT and the gate terminal of the source follower transistor sf1. The first integration capacitor INT has the first end coupled to the drain terminal of transistor m7 and gate terminal of source follower transistor sf1, and has a second end coupled to the ground level GNDA. The source follower transistor sf1 has a drain terminal coupled to the supply voltage vdda, has a source terminal coupled to the drain terminal of the transistor m8, and has a gate terminal coupled to the drain terminal of transistor m7 and the first integration capacitor INT.

(12) In addition, the transistor m9 has the gate terminal coupled the control signal NSH2, has the source terminal coupled to the drain terminal of transistor m2, source terminal of transistor m4, and source terminal of transistor m5, and has the drain terminal coupled to the drain terminal of transistor m10 and source terminal of transistor m11. The transistor m11 has the gate terminal coupled to the control signal NS2, the source terminal coupled to the drain terminal of transistor NSJH2, and has the drain terminal coupled to the gate terminal of source follower transistor sf2 and the second integration capacitor INTD. The second integration capacitor INTD has the first end coupled to the drain terminal of transistor m11 and gate terminal of source follower transistor sf2, and has the second end coupled to the ground level GNDA. The source follower transistor sf2 has the drain terminal coupled to the supply voltage vdda, has the gate terminal coupled to the drain terminal of transistor m11 and the first end of second integration capacitor INTD, and has the source terminal coupled to the drain terminal of the transistor m12.

(13) In this embodiment, the control signals PBB, NSH, NSH1, and NS1 can be used to respectively control (turn on/off) the transistors m3, m4, m5, and m7 to collect a light signal and transfer the charge of the light signal from the BJT photo transistor into the first integration capacitor INT during a first shutter exposure time interval ST1 at time T1, so that the light signal collected/captured at time T1 can be stored in the first integration capacitor INT. The control signal RD is a read control signal, and then the transistor m8 can be turned on by the control signal RD to work with the first source follower transistor sf1 to generate and output the first output signal OUT corresponding to the light signal collected at time T1. Identically, the control signals PBB, NSH, NSH2, and NS2 can be used to respectively control (turn on/off) the transistors m3, m4, m9, and m11 to collect a light signal and transfer the charge of the light signal from the BJT photo transistor into the second integration capacitor INTD during a second shutter exposure time interval ST2 at time T2, so that the light signal collected/captured at time T2 can be stored in the second integration capacitor INTD. Then the transistor m12 can be turned on by the control signal RD to work with the second source follower transistor sf2 to generate and output the second output signal OUTD corresponding to the light signal collected at time T2. Similarly, the light signal can be collected during the first shutter exposure time interval ST1 at time T3 following time T2, and the light signal can be collected during the second shutter exposure time interval ST2 at time T4 following time T3. FIG. 3 shows an example of the shutter exposure time intervals of times T1-T3 according to an embodiment of the invention. Further, the control signal RST, i.e. a reset control

signal, is coupled to the gate terminal of transistors **m13** and **m15** to control the transistors **m13** and **m15** to reset the operation of readout control circuit **110** and is not detailed for brevity.

(14) By doing so, based on the circuit structure of each BJT sensing pixel **100** in FIG. **1**, two light signals can be collected at different times respectively. At time **T1**, the control signals **NSH1** and **NS1** are at a low level such as level '0' to select and turn on the corresponding PMOS transistors **m5** and **m7**, and the control signals **NSH2** and **NS2** are at a high level such as level '1' and thus the PMOS transistors **m9** and **m11** are not turned on (i.e. not selected). In this situation, a first collected light signal/data can pass through the turned-on PMOS transistors **m5** and **m7**, and thus it is stored into the first integration capacitor **INT**. Then, at time **T2** (later than time **T1**), the control signals **NSH2** and **NS2** are at the low level and thus the corresponding PMOS transistors **m9** and **m11** are selected and turned on, and the control signals **NSH1** and **NS1** are at the high level and thus the PMOS transistors **m5** and **m7** are not turned off (not selected). In this situation, a second collected light signal/data can pass through the corresponding turned-on PMOS transistors **m9** and **m11** and it is stored into the second integration capacitor **INTD**. That is, the first integration capacitor **INT** and second integration capacitor **INTD** respectively have two light data/signals which are collected at different times.

(15) Equivalently, when the control signal **RD** is at the high level, the transistors **m8** and **m12** are turned on respectively, and the two light signals are read and transferred out as the first output signal **OUT** and second output signal **OUTD** respectively. Actually, the first light signal is read out from the integration capacitor **INT** when the control signal **RD** is at the high level and the control signal **NSH1** switches from the low level into the high level, and then the second light signal is read out from the integration capacitor **INTD** when the control signal **RD** is at the high level and the control signal **NSH2** switches from the low level into the high level, as shown in FIG. **3**.

(16) Refer to FIG. **2**. FIG. **2** is a diagram of an optical sensor device **200** comprising multiple BJT sensing pixels **100** according to an embodiment of the invention. In FIG. **2**, the optical sensor device **200** comprises a pixel array **205** and a control circuit **210**. The pixel array **205** comprises a plurality of pixel units such as the BJT sensing pixels **100** of FIG. **1** arranged in **N** rows and **M** columns. Each BJT sensing pixel **100** is arranged to output its two output signals **OUT** and **OUTD** to the control circuit **210** at different times. The control circuit **210** is used to generate the above-mentioned control signals **PBB**, **NSH**, **NSH1**, **NS1**, **NSH2**, **NS2**, **RST**, and **RD** to each BJT sensing pixel **100** respectively so as to obtain and receive two output signals **OUT** and **OUTD** of the each BJT sensing pixel **100**.

(17) In practice, the control circuit **210** comprises a first current source **CS1**, a second current source **CS2**, a first switch unit **SW1**, a second switch unit **SW2**, a first buffer capacitor **C1**, a second buffer capacitor **C2**, a comparator **COMP**, and a counter **215**.

(18) In FIG. **2**, for one BJT sensing pixel **100**, the first integration capacitor's **INT** output signal **OUT** and the second integration capacitor's **INTD** output signal **OUTD** are transmitted into the control circuit **210**. The current sources **CS1** and **CS2** are used for providing reference current signals for the output signals **OUT** and **OUTD**. The first switch unit **SW1** and second switch unit **SW2** are controlled to be at the closed state. The output signals **OUT** and **OUTD** can be transferred through the switch unit **SW2** and switch unit **SW1** and then are stored by the buffer capacitor **C2** and buffer capacitor **C1** with bias voltages **Vref** on the other plates of capacitors **C1-C2**.

(19) The control circuit **210** is arranged to receive the two output signals **OUT** and **OUTD** to check the difference when the first switch unit **SW1** and second switch unit **SW2** are turned on to be at a closed state (i.e. a conductive state). Then, the first switch unit **SW1** and second switch unit **SW2** are turned off to be non-conductive after the two output signals **OUTD** and **OUT** are respectively stored by the two buffer capacitors **C1** and **C2**, respectively.

(20) After the first and second switch units **SW1** and **SW2** are turned off to be at an open state (i.e. non-conductive state), the bias voltage provided at the other plate of the buffer capacitor **C2** is controlled by the control circuit **210** to be kept at **Vref** while the bias voltage provided at the other

plate of the buffer capacitor C1 is controlled by the control circuit **210** to sweep from Vref to Vref-Vth and Vref+Vth; for example (but not limited), the bias voltage may sweep from Vref to Vref-Vth and then sweep from Vref-Vth to Vref+Vth. That is, the control circuit **210** controls the bias voltage provided at the other plate of the buffer capacitor C2 sweeping or switching into a different reference voltage level for two times. It should be noted that, in this embodiment (but not limited), Vth is a threshold voltage used/configured by the comparator COMP (or by the control circuit **210**) in a global setting applied to all the BJT sensing pixels **100** included within the pixel array **205**. However, this is not intended to be a limitation. For instance, the threshold voltage Vth may be at different levels for different BJT sensing pixels **100** in the pixel array **205**.

(21) The comparator COMP compares the waveform of output signal OUTD centered at the level Vref-Vth with that of the output signal OUT centered at the level Vref to generate a first comparison resultant bit/signal and then compares the waveform of output signal OUTD centered at the level Vref+Vth with that of the output signal OUT centered at the level Vref to generate a second comparison resultant bit/signal, so as to sequentially generate and output the two comparison resultant bits/signals into the counter **215**. Based on the first and second comparison resultant bits, the counter **215** can determine whether the second output signal OUTD collected at time T2 is dimmer/brighter than the first output signal OUT collected at time T1 or not.

(22) For example (but not limited), if the second output signal OUTD collected at time T2 is dimmer than the first output signal OUT collected at time T1 due to an enough/significant pixel change, then the first and second comparison resultant bits may indicate '11', and thus a counting value (the initial value is equal to zero) counted by the counter **215** is accumulated and incremented by one so as to recording a significant pixel difference.

(23) If the second output signal OUTD collected at time T2 is brighter than the first output signal OUT collected at time T1 due to an enough/significant pixel change, then the first and second comparison resultant bits may indicate '00', and thus the counting value (the initial value is equal to zero) counted by the counter **215** is also accumulated and incremented by one so as to recording a significant pixel difference. If the first and second comparison resultant bits may indicate '01' and '10', then the counting value is not increased and not accumulated.

(24) For all BUT sensing pixels **100** of the pixel array **205**, the counter **215** is arranged to use its counting value to accumulate the number of BJT sensing pixels in the whole pixel array **205** that have significant pixel differences corresponding to the comparison resultant bits '11' or '00'. The control circuit **210** is arranged to compare the counting value with a preset threshold of count number to determine whether a motion occurs to generate a motion signal which can be used and triggered to wake up an entire sensor system which the optical sensor device **200** disposed in. For example, when the accumulated counting value is greater than the preset threshold of count number, the control circuit **210** (or optical sensor device **200**) can determine that a motion occurs and in other situations the control circuit **210** can determine that no motions occur.

(25) Refer back to FIG. 3. In FIG. 3, at time T1, the control signal NSH1 becomes at the low level to select and turn on the transistor m5. During the shutter exposure time interval ST1 of time T1, the control signal NS1 also turns on the transistor m7 while the control signal RD turns off the transistor m8, so that the charge will be stored by the first integration capacitor INT. Then, during time's T1 second time interval (i.e. read out and compare interval) following the shutter exposure time interval ST1, the control signal NSH1 becomes at the high level to turn off the transistor m5, the control signal NSH2 is kept at the high level to turn off the transistor m9, and the control signal RD turns on the transistor m8 to make the first integration capacitor INT transfer the stored charge out the BJT sensing pixel **100** as the first output signal OUT and transmit the first output signal OUT to the control circuit **210**. During time's T1 read out and compare interval, the first output signal OUT is transmitted to the control circuit **210**, and the control circuit **210** compares the currently received first output signal OUT with the previously received/stored second output signal OUTD based on the operations of sweeping the bias voltage at the other plate of the buffer

capacitor C1 as shown in FIG. 2 so as to determine whether a significant pixel difference occurs between the output signals OUT and OUTD. Once a significant pixel difference occurs, the counting value counted by the counter 215 is incremented by one.

(26) It should be noted that, during the shutter exposure time interval ST1, all the BJT sensing pixels 100 of the whole pixel array 205 are used to sense light rays (which may be reflected from a working surface), and then during time's T1 read out and compare interval, the control circuit 210 (or optical sensor device 200) checks whether more or all the BJT sensing pixels 100 of the whole pixel array 205 is/are associated with the significant pixel difference so as to calculate and accumulate the specific counting value at time T1 for more or all the BJT sensing pixels 100. If the accumulated specific counting value at time T1 is greater than the preset threshold of count number, then the control circuit 210 determines that a motion occurs at time T1.

(27) Similarly, during the shutter exposure time interval ST2 at time T2, the control signal NSH2 becomes at the low level to select and turn on the transistor m9. During the shutter exposure time interval ST2, the control signal NS2 also turns on the transistor m11 while the control signal RD turns off the transistor m12, so that the charge will be stored by the second integration capacitor INTD. Then, during time's T2 second time interval (i.e. read out and compare interval) following the shutter exposure time interval ST2, the control signal NSH2 becomes at the high level to turn off the transistor m9, the control signal NSH1 is kept at the high level to turn off the transistor m5, and the control signal RD turns on the transistor m12 to make the second integration capacitor INTD transfer the stored charge out the BJT sensing pixel 100 as the second output signal OUTD and transmit the second output signal OUTD to the control circuit 210.

(28) During time's T2 read out and compare time interval, the second output signal OUTD is transmitted to the control circuit 210, and then the control circuit 210 compares the currently received second output signal OUTD with the previously received first output signal OUT (i.e. the output signal collected at the above-mentioned time interval ST1) based on the operations of sweeping the bias voltage at the other plate of the buffer capacitor C1 as shown in FIG. 2 so as to determine whether a significant pixel difference occurs between the output signals OUT and OUTD. Once a significant pixel difference occurs, the counting value counted by the counter 215 is incremented by one.

(29) Similarly, during the shutter exposure time interval ST2 at time T2, all the BJT sensing pixels 100 of the whole pixel array 205 are used to sense light rays (which may be reflected from the working surface), and then during time's T2 read out and compare interval, the control circuit 210 (or optical sensor device 200) checks whether more or all the BJT sensing pixels 100 of the whole pixel array 205 is/are associated with the significant pixel difference so as to calculate and accumulate the specific counting value at time T2 for more or all the BJT sensing pixels 100. If the accumulated specific counting value at time T2 is greater than the preset threshold of count number, then the control circuit 210 determines that a motion occurs at time T2.

(30) The above-mentioned operations are similar or identical for time T3. During the shutter exposure time interval ST1 at time T3, all the BJT sensing pixels 100 of the whole pixel array 205 are used to sense light rays (which may be reflected from the working surface), and then during time's T3 read out and compare interval, the control circuit 210 (or optical sensor device 200) checks whether more or all the BJT sensing pixels 100 of the whole pixel array 205 is/are associated with the significant pixel difference so as to calculate and accumulate the specific counting value at time T3 for more or all the BJT sensing pixels 100. If the accumulated specific counting value at time T3 is greater than the preset threshold of count number, then the control circuit 210 determines that a motion occurs at time T3. The other operations are similar and are not detailed for brevity.

(31) Further, equivalently the photo transistor BJT of one BJT sensing pixel 100 is configured to capture and generate an image signal (pixel image) during the shutter exposure time interval ST1 and then generate another image signal during the shutter exposure time interval ST2 which

equivalently follows the shutter exposure time interval ST1 since time T2 follows time T1. The two pixel images are stored by the two integration capacitors INT and INTD, as mentioned in the above paragraphs. In addition, the motion detection performed by the optical sensor device **200** (or control circuit **210**) is to determine whether a motion occurs based on the difference between the two pixel images captured at different shutter exposure time intervals having identical/different time lengths. In addition, in one embodiment, the employed shutter exposure time interval may alter between the different shutter exposure time intervals having different time lengths. The first shutter exposure time interval ST1 and the second shutter exposure time interval ST2 alternately occur for consecutive times.

(32) The provided optical sensor device **200** having the multiple BJT sensing pixels **100** can be used to boost/improve the sensitivity of the motion detection operation and can be arranged to wake up the sensor system during the rest or idle period without the need of running full digital operations. The optical sensor device **200** can boost the sensitivity of a sensor to detect changes in the image, i.e. motion.

(33) In the embodiment, for example (but not limited), when the pixel value corresponding to the second output signal OUTD collected at time T2 is above or below to a threshold pixel value corresponding to the threshold voltage V_{th} , the control circuit **210** can determine that the BJT sensing pixel's **100** pixel value at time T2 is brighter or dimmer than that at time T1.

(34) In one embodiment, the threshold voltage V_{th} is configured to be high enough to avoid false motion caused by the shot noise of the images.

(35) In other embodiments, when the pixel unit **100** senses a brighter light, the shot noise content in the output signal OUT/OUTD also will increase proportionally, and the control circuit **210** can dynamically adjust the threshold voltage V_{th} to increase the threshold voltage V_{th} applied for the increased shot noise level and maintains the threshold voltage V_{th} applied for the kept shot noise level so as to mitigate the those different noise levels.

(36) For example (but not limited), if the voltage level of an output signal of a brighter pixel unit (i.e. having a high pixel value) is 500 mV, then its peak-to-peak shot noise level may be ± 10 mV. In this situation, the threshold voltage V_{th} may be configured to be equal to or higher than the absolute value of ± 10 mV to avoid false motion. Actually, a sensed image may comprise high/medium/low pixel values; for instance, the voltage level of an output signal of a pixel unit having a low pixel value may be 250 mV, then its peak-to-peak shot noise level may be ± 5 mV. In this situation, it is merely needed to configure the threshold voltage V_{th} be equal to or higher than the absolute value of ± 5 mV to avoid false motion. The sensitivity of motion detection operation will be degraded if the threshold voltage V_{th} is always higher for the all pixel units.

(37) To solve this problem, in one embodiment, the control circuit **210** can dynamically adjust the threshold voltage V_{th} for different pixel units **100**. That is, the optical sensor device **200** may use a high threshold voltage for a pixel unit having a high pixel value to mitigate a high shot noise level, a medium threshold voltage for a pixel unit having a medium pixel value to mitigate a medium shot noise level, and a low threshold voltage for a pixel unit having a low pixel value to mitigate a low shot noise level. Using a medium threshold voltage to mitigate a medium shot noise level and/or using a low threshold voltage to mitigate a low shot noise level can boost the signal sensitivity of the motion detection operation as well as accurately avoiding false motions.

(38) It may be hard to adaptively adjust the threshold voltage V_{th} for different pixel units **100** of the pixel array **205** in some situations. To solve the problems, the invention provides the operation of dynamically adjusting shutter exposure time intervals at consecutive times to equivalently achieve boosting the signal sensitivity of motion detection, and in the embodiments it is not needed to directly adjust the threshold voltage V_{th} for different pixel units **100** of the pixel array **205**. For example, in the embodiments, to boost the signal sensitivity of motion detection operation, the control circuit **210** can dynamically adjust or vary the shutter time intervals of different times such as T1, T2, and T3 to obtain/get different sensed images then to compare the sensed images. The

operation of dynamically adjust or vary the shutter time intervals of the different times such as T1, T2, and T3 can be used to replace the operation and function of the threshold voltage Vth. The threshold voltage Vth may be configured as zero, and it is not needed to sweep the bias voltage Vref to both of Vref-Vth and Vref+Vth, and the comparator COMP can directly compare the output signals OUTD and OUT to generate a comparison resultant bit/signal into the counter 215.

(39) Refer to FIG. 3 again. For a specific pixel unit 100 (or most or all pixel units), the control circuit 210 can control the exposure time intervals of consecutive times corresponding to consecutive images/frames to have different time lengths. For example, the shutter exposure time interval ST1 at time T1 for the specific pixel unit 100 at a first image, i.e. the interval during which the control signal NSH1 is at the low level, is equal to a longer exposure time interval such as 10 us (but not limited). The shutter exposure time interval ST2 at time T2 for the specific pixel unit 100 at a second image, i.e. the interval during which the control signal NSH2 is at the low level, is equal to a shorter exposure time interval (e.g. 9 us) shorter than the exposure time interval 10 us. The shutter exposure time interval ST1 at time T3 for the specific pixel unit 100 at a third image, i.e. the interval during which the control signal NSH1 is at the low level again, is equal to the longer exposure time interval 10 us. That is, the control circuit 210 (or optical sensor device 200) can control its shutter exposure time interval switching and alternating between the longer and shorter time intervals at consecutive times.

(40) If no motions occur, then the pixel value of the specific pixel unit 100 collected at the shutter exposure time interval ST2 should be dimmer than that of the specific pixel unit 100 collected at the shutter exposure time interval ST1 since the shutter exposure time interval ST2 is shorter than the shutter exposure time interval ST1. In this situation, the second output signal OUTD is lower/dimmer than the first output signal OUT and the comparator COMP generates the comparison resultant bit '1' into the counter 215 if no motions occur between two consecutive shutter exposure operations/intervals. If a motion occurs, then for example (but not limited) the pixel value of the specific pixel unit 100 collected at the shutter exposure time interval ST2 may significantly change and become brighter than that of the specific pixel unit 100 collected at the shutter exposure time interval ST1. In this situation, the output of comparator COMP will toggle to bit '0' to preliminarily indicate that a significant change occurs in the pixel unit 100. By collecting the comparison resultant bits of most/all pixel units 100 of the pixel array 205 sequentially outputted from the comparator COMP, the counter 215 can count and accumulate the number of bits '0' and then compare the number of bits '0' with a specific threshold number to finally determine whether a motion occurs in the image collected during the shorter shutter exposure time interval ST2. For example, the optical sensor device 200 (or control circuit 210) can decide that a motion occurs at a specific time such as T2 if the number of bits '0' corresponding to the shorter shutter exposure time interval ST2 is greater than the specific threshold number.

(41) In one embodiment, if it is detected that a motion occurs at time T2, then the control circuit 210 may stop toggling/alternating the shutter exposure time interval between ST1 and ST2 and may use one of ST1 and ST2 as the shutter exposure time interval and keeps the shutter exposure time interval. This is not intended to be a limitation of the invention.

(42) In other embodiments, if it is detected that no motions occur at time T2, then the control circuit 210 may continue to toggle the shutter exposure time interval between ST1 and ST2 to perform a motion detection operation. For example (but not limited), assume that the comparator COMP generates the comparison resultant bit '1' into the counter 215 if no motions occur at time T2, the control circuit 210 at time T3 controls and toggles the shutter exposure time interval back to the longer shutter exposure time interval ST1. If no motions occur at time T3, then the pixel value of the specific pixel unit 100 collected during the longer shutter exposure time interval ST1 of time T3 should be brighter/higher than that of the specific pixel unit 100 collected during the shorter shutter exposure time interval ST2 of time T2, and thus the comparator COMP generates and outputs the comparison resultant bit '0' to indicate no motions at time T3. In this example, if a

motion occurs at time T3, then for example (but not limited) the pixel value of the specific pixel unit **100** collected during the longer shutter exposure time interval ST1 of time T3 may significantly change and become dimmer than that of the specific pixel unit **100** collected during the shorter shutter exposure time interval ST2 of time T2, and thus in this situation the output of comparator COMP will toggle to bit '1' to preliminarily indicate that a significant pixel change occurs in the pixel unit **100** at time T3. Then, by collecting the comparison resultant bits of most/all pixel units **100** in the pixel array **205** sequentially outputted from the comparator COMP, the counter **215** can count and accumulate the number of bits '1' and then compare the number of bits '1' with a specific threshold number to finally determine whether a motion occurs in the image collected during the longer shutter exposure time interval ST1. For example, the optical sensor device **200** (or control circuit **210**) can decide that a motion occurs at a specific time such as T3 if the number of bits '1' corresponding to the longer shutter exposure time interval ST1 is greater than the specific threshold number.

(43) In one embodiment, the control circuit **210** can finally determine that a motion occurs only when at least detecting that the number of bits '1' corresponding to the longer shutter exposure time interval ST1 is greater than the specific threshold number and at least detecting that the number of bits '0' corresponding to the shorter shutter exposure time interval ST2 is greater than the specific threshold number at consecutive times. This modification also falls within the scope of the invention.

(44) In other embodiment, the control circuit **210** may individually and respectively adjust and vary the shutter exposure time intervals of the different pixel units **100** within the pixel array **205** based on the different pixel output levels of the different pixel units **100**.

(45) FIG. 4 is a diagram of examples showing the relation between the light intensity and pixel output signal voltage level according to an embodiment of the invention. In FIG. 4, the line L1 indicates the relation between the light intensity and pixel output signal voltage level under a condition of using the longer shutter exposure time interval ST1, and the line L2 indicates the relation between the light intensity and pixel output signal voltage level under a condition of using the shorter shutter exposure time interval ST2. For example (but not limited), at a low light intensity LI1, the pixel output voltage level collected during the longer shutter exposure time interval ST1 may be 250 mV plus ± 5 mV shot noise level. At a high light intensity LI2, the pixel output voltage level collected during the longer shutter exposure time interval ST1 may be 500 mV plus ± 10 mV shot noise level. That is, the shot noise level is proportionally increased with the light intensity. As mentioned above, the control circuit **210** may adjust the threshold voltage V_{th} in response to the different light intensities so as to avoid detecting false motion caused by the shot noise as well as to maintain the signal sensitivity of motion detection.

(46) In the embodiments, to provide an equivalent threshold voltage to avoid false motion by toggling between the longer shutter exposure time interval ST1 and shorter shutter exposure time interval ST2, the control circuit **210** (or optical sensor device **200**) can determine the line L2 as shown in FIG. 4 based on the pixel output voltage level 250 mV plus ± 5 mV shot noise level corresponding to the low light intensity LI1 and the pixel output voltage level 500 mV plus ± 10 mV shot noise level corresponding to the high light intensity LI2. For instance, the optical sensor device **200** can finely tune or adjust the actual time length of the shorter shutter exposure time interval ST2 to make the corresponding the line L2 be below the line L1 and be separated by enough discrimination voltage ranges. For example, the control circuit **210** can configure the discrimination voltage range at the high light intensity LI2 be equal to two times of the absolute value of ± 10 mV shot noise level, i.e. 20 mV shown in FIG. 4. The control circuit **210** can configure the discrimination voltage range at the low light intensity LI2 be equal to two times of the absolute value of ± 5 mV shot noise level, i.e. 10 mV as shown in FIG. 4.

(47) By doing so, the optical sensor device **200** can find and obtain the finely tuned time length of the shorter exposure time interval ST2, e.g. 9 μ s (but not limited). In practice, the control circuit

210 can directly and respectively control the shutter control circuits **105** of different BJT sensing pixels **100** providing and using the shutter exposure time intervals having different time lengths, and this is more convenient and flexible compared to the operation of dynamically adjusting the value of threshold voltage V_{th} as shown in FIG. 2 for different BJT sensing pixels **100**. In addition, the performance of adjusting the exposure time intervals for different BJT sensing pixels **100** is improved, compared to using the fixed value of threshold voltage V_{th} for all the BJT sensing pixels **100**.

(48) In other embodiments, the comparison operation, executed by the control circuit **210** and sequentially upon one BJT sensing pixel by one BJT sensing pixel, can be replaced by using a built-in comparison mechanism disposed within each BJT sensing pixel, so as to further reduce the power consumption to achieve for low power motion detection requirements.

(49) Refer to FIG. 5 in conjunction with FIG. 6. FIG. 5 is a circuit diagram of two novel BJT sensing pixels disposed at different spatial locations of the same column of a pixel array according to an embodiment of the invention. FIG. 6 is a diagram of an optical sensor device **600** according to an embodiment of the invention. The optical sensor device **600** comprises the pixel array **605** and the control circuit **610** having the counter **215**, wherein the pixel array **605** comprises the array circuit **606** having the BJT sensing pixels of FIG. 5 arranged in N rows and M columns, M column-based bias current sources **607** arranged in one row and M columns, and M column-based built-in comparison circuits **608** arranged in one row and M columns; the integer N for example is equal to two (but not limited), and the integer M is equal to 30 (but not limited).

(50) The pixel array **605** can simultaneously generate and output M comparison resultant signals OUT_1-OUT_M (e.g. M is 30) of each row into the control circuit **610**. For example, the pixel array **605** has two rows, and the pixel array **605** can generate a set of comparison resultant signals OUT_1-OUT_30 into the control circuit **610** and then generate another set of comparison resultant signals OUT_1-OUT_30 into the control circuit **610**; that the, the control circuit **610** receives comparison resultant signals OUT_1-OUT_M (e.g. M is 30) for N times; N for example is 2.

(51) The control circuit **610** is coupled to the pixel array **605** and is used for generating the read control signals of N rows such as RD1 for the first row and RD2 for the second row into the pixel array **605** to make the pixel array **605** outputting the M comparison resultant signals at the first row in response to the control signal RD1 and then make the pixel array **605** outputting the M comparison resultant signals at the second row in response to the control signal RD2, and for controlling the counter **215** receiving the M comparison resultant signals of each row of the pixel array **605** to count the total number of specific bits '1' or '0' indicating the significant pixel changes. That is, the control circuit **610** excludes the comparison operation.

(52) Refer back to FIG. 5. FIG. 5 shows the two novel BJT sensing pixels **500_1** and **500_2** at the same column (e.g. the first column) of the pixel array **605**, one column-based bias current source **607** disposed at the same column, and one built-in column-based comparison circuit **608** disposed at the same column. The BJT sensing pixels **500_1** and **500_2** have the same circuit structures and components. For instance, the BJT sensing pixel **500_1** (or **500_2**) comprises the circuit elements/structures similar to those comprised by the BJT sensing pixel **100** and thus are not detailed for brevity. Compared to the embodiment of FIG. 1, the difference is that the drain terminal D3 of source follower transistor sf1 of BJT sensing pixel **500_1** at the first row and first column of pixel array **605** is coupled to a first input end of the column-based comparison circuit **608**, the drain terminal D4 of source follower transistor sf2 of BJT sensing pixel **500_1** is coupled to a second input end of the column-based comparison circuit **608**, the drain terminal D1 of source follower transistor sf1 of BJT sensing pixel **500_2** at the second row and first column of pixel array **605** is coupled to the first input end of the column-based comparison circuit **608**, the drain terminal D2 of source follower transistor sf2 of BJT sensing pixel **500_2** is coupled to the second input end of the column-based comparison circuit **608**, and the output signals OUT and OUTD of all the BJT sensing pixels **500_1** and **500_2** at the same column are coupled to the column-based bias current

source **607** which has another end coupled to the ground level and is used to providing the bias current such as 5 uA for the output signals OUT and OUTD.

(53) Each built-in column-based comparison circuit **608** as shown in FIG. 5 and FIG. 6 comprises transistors m50, m51, m52, and m53. The PMOS transistor m50 has a first terminal (e.g. a drain terminal) coupled to the drains terminals (i.e. D3 and D1) of first source follower transistors sf1 of all the BJT sensing pixels **500_1** and **500_2** disposed at the same column, has a second terminal (e.g. a source terminal) coupled to the supply voltage vdda such as 1.8 Volts (but not limited), and has a control terminal (e.g. a gate terminal) coupled to its drain terminal. The PMOS transistor m51 has a first terminal (e.g. a drain terminal) coupled to the drains terminals (i.e. D4 and D2) of second source follower transistors sf2 of all the BJT sensing pixels **500_1** and **500_2** disposed at the same column, has a second terminal (e.g. a source terminal) coupled to the supply voltage vdda, and has a control terminal (e.g. a gate terminal) coupled to the gate terminal of the PMOS transistor m50. The PMOS transistor m52 has a first terminal (e.g. a drain terminal) coupled to an output of the M built-in comparison circuit **608** and at which a comparison resultant bit/signal (e.g. OUT_1) for one of the BJT sensing pixels **500_1/500_2** at the same column is generated and outputted, has a second terminal (e.g. a source terminal) coupled to the supply voltage vdda, and has a control terminal (e.g. a gate terminal) coupled to the drain terminal of the PMOS transistor m51. The PMOS transistor m53 has a first terminal (e.g. a drain terminal) coupled to the output of the M built-in comparison circuit (or coupled to the drain terminal of the transistor m52), has a second terminal (e.g. a source terminal) coupled to the ground level, and has a control terminal (e.g. a gate terminal) coupled to a bias voltage nbias.

(54) As shown in FIG. 5, for example (but not limited), the two source follower transistors sf1 and sf2 within a BIT sensing pixel **500_1** (or **500_2**) in FIG. 5 can form into a differential pair of a comparator.

(55) The drain terminals D3 & D4 of the two source follower transistors sf1 and sf2 are routed out from the BJT sensing pixel **500_1** in FIG. 5 to build a top part of a comparator circuit. In addition, the drain terminals D1 & D2 of the two source follower transistors sf1 and sf2 can be routed out from the BJT sensing pixel **500_2** in FIG. 5 to build a top part of a comparator circuit.

(56) The first output signal OUT and second output signal OUTD are transmitted from the BJT sensing pixel **500_1** (or **500_2**) in FIG. 5 and will be shorted outside of the BJT sensing pixel **500_1** (or **500_2**) and will connect to the corresponding bias current (e.g. 5 uA) if the current source **607** at the same column so as to form a bottom part of the comparator.

(57) Thus, when the control signal RD1 (i.e. a read control signal to read pixel data at a first row) becomes high level '1', the BJT sensing pixel **500_1** at the first row and at the first column is selected (the transistors m8 and m12 of the BJT sensing pixel **500_1** are enabled and turned on by the control signal RD1 while the transistors m8 and m12 of the BJT sensing pixel **500_2** are not turned on by the control signal RD2 since in this situation the other read control signal such as RD2 is at the low level).

(58) Alternatively, when the control signal RD2 (i.e. a read control signal to read pixel data at a second row following the first row) becomes high level '1', the BJT sensing pixel **500_2** at the second row and first column is selected (the transistors m8 and m12 of the BJT sensing pixel **500_2** are enabled and turned on by the control signal RD2 while the transistors m8 and m12 of the BJT sensing pixel **500_1** are not turned on by the control signal RD1 since in this situation the other read control signal such as RD1 is at the low level).

(59) For this circuit structure and connection of the BJT sensing pixel **500_1** (or **500_2**), if the voltage level of its first output signal OUT is higher than that of its second output signal OUTD, then the comparison resultant bit, indicated by OUT_1, generated from the corresponding comparison circuit is equal to '0'.

(60) FIG. 7 is a diagram of an example of the control signals NSH1 and NSH2 and the read controls signals RD1 and RD2 of FIG. 5 according to an embodiment of the invention. In the

embodiment, the first integration capacitors INT of the BJT sensing pixel **500_1** and **500_2** are used to store the light signal collected during the first shutter exposure time interval **ST1** (e.g. a longer exposure time interval such as 10 us) of time **T1**, and the second integration capacitors INTD of the BJT sensing pixel **500_1** and **500_2** are used to store the light signal collected during the second shutter exposure time interval **ST2** (e.g. a shorter exposure time interval such as 9 us) of a time earlier than time **T1** (not shown in FIG. 7).

(61) During time's **T1** read out and compare time interval following the time interval **ST1**, when the read control signal **RD1** becomes high and read control signal **RD2** becomes low, the output signals **OUT** and **OUTD** of all the BJT sensing pixels at the same row such as the first row of pixel array **605** are read out and compared to respectively generate and output the comparison resultant bits/signals **OUT_1-OUT_30** into the control circuit **610**, as shown in FIG. 6. Later, when the read control signal **RD2** becomes high and read control signal **RD1** becomes low, the output signals **OUT** and **OUTD** of all the BJT sensing pixels at the same row such as the second row of pixel array **605** are read out and compared again to respectively generate and output the comparison resultant bits/signals **OUT_1-OUT_30** into the control circuit **610**, as shown in FIG. 6. Thus, in this situation, the control circuit **610** can receive $N \times M$ comparison resultant bits, e.g. 2×30 comparison resultant bits. Since the first output signal **OUT** corresponds to the longer shutter exposure time interval **ST1** compared to the second output signal **OUTD**, the voltage level of first output signal **OUT** will be higher than that of the second output signal **OUTD** if no motions occur, and thus a comparison resultant bit such as **OUT_1** ideally should be equal to '1'. If a motion occurs, then the comparison resultant bit toggle to '0'. Thus, the control circuit **610** can employ the counter **215** to count for the number of specific bits '0' indicating significant pixel change and then compare the total number of specific bits '0' at time **T1** with a number threshold to resultantly determine whether a motion occurs at time **T1**.

(62) Similarly, at time **T2**, the second integration capacitors INTD of the BJT sensing pixel **500_1** and **500_2** are used to store the light signal collected during the second shutter exposure time interval **ST2** at time **T2**. During time's **T2** read out and compare time interval following the time interval **ST2**, when the read control signal **RD1** becomes high and read control signal **RD2** becomes low, the output signals **OUT** and **OUTD** of all the BJT sensing pixels at the same row such as the first row of pixel array **605** are read out and compared to respectively generate and output the comparison resultant bits/signals **OUT_1-OUT_30** into the control circuit **610**. Later, when the read control signal **RD2** becomes high and read control signal **RD1** becomes low, the output signals **OUT** and **OUTD** of all the BJT sensing pixels at the same row such as the second row of pixel array **605** are read out and compared again to respectively generate and output the comparison resultant bits/signals **OUT_1-OUT_30** into the control circuit **610**. Thus, in this situation, the control circuit **610** at time **T2** can also receive $N \times M$ comparison resultant bits, e.g. 2×30 comparison resultant bits. Since the second output signal **OUTD** corresponds to the shorter shutter exposure time interval **ST2** compared to the first output signal **OUT**, the voltage level of first output signal **OUT** will be higher than that of the second output signal **OUTD** if no motions occur, and thus a comparison resultant bit such as **OUT_1** ideally should be equal to '1'. If a motion occurs, then the comparison resultant bit toggle to '0'. Thus, the control circuit **610** can employ the counter **215** to count for the number of specific bits '0' indicating significant pixel change and then compare the total number of specific bits '0' at time **T1** with a number threshold to resultantly determine whether a motion occurs at time **T2**. These operations and functions at time **T3** or later time are similar to the above-mentioned operations and functions of the circuits in the above previous paragraphs.

(63) Further, it should be noted that the first integration capacitor INT will be overwritten by the light signal collected during the longer shutter exposure time interval **ST1** of time **T3**, and the second integration capacitor INTD will be overwritten by the light signal collected during the shorter shutter exposure time interval **ST1** of later time **T4** (not shown in figure)).

(64) An advantage is that the embodiment of the circuit design/structure in FIG. 5 in conjunction with FIG. 6 consumes only 5 uA per pixel unit compared to the embodiment in FIG. 1 in conjunction with FIG. 2 which may need to consume 160 uA per pixel unit, to transfer/transmit each pixel signal to the external comparator or comparator circuit. For instance, the current provided by each of the current sources CS1 and CS2 may be equal to 160 uA while that provided by each column current source may merely consume 5 uA which is significantly smaller than 160 uA.

(65) Further, as shown in FIG. 7, it is merely needed to use a shorter transfer time compared to the embodiment of FIG. 2 since it operates one row by one row. For example (but not limited), to achieve the pixel transfer of the all the pixel units arranged in 30 rows and 30 columns, the optical sensor device 600 merely needs transfer the pixel data for 30 times to complete the read out of all pixel values of one image/frame, rather than transferring the pixel data for 900 times.

(66) Those skilled in the art will readily observe that numerous modifications and alterations of the device and method may be made while retaining the teachings of the invention. Accordingly, the above disclosure should be construed as limited only by the metes and bounds of the appended claims.

Claims

1. An optical sensor device, comprising: a pixel array having a plurality of pixel units arranged in N rows and M columns, a first pixel unit in the plurality of pixel units comprising: a photo transistor, configured to capture and generate a first image signal during a first shutter exposure time interval of a first time and to capture and generate a second image signal during a second shutter exposure time interval of a second time, the first time and the second time being consecutive; a first integration capacitor, coupled to the photo transistor, for storing the first image signal; and a second integration capacitor, coupled to the photo transistor, for storing the second image signal; and a control circuit, coupled to the first pixel unit; wherein the first shutter exposure time interval is different from the second shutter exposure time interval; the control circuit performs a motion detection to determine whether a motion occurs according to a difference between the first image signal captured during the first shutter exposure time interval and the second image signal captured during the second shutter exposure time interval; the first pixel unit outputs the first image signal as a first output signal and outputs the second image signal as a second output signal respectively into the control circuit; the control circuit is used to compare the first output signal with the second output signal, which is biased by different threshold voltages, to generate a first comparison resultant bit and a second comparison resultant bit into a counter of the control circuit; and, the counter is used to increment a counting vale by one only when the first comparison resultant bit and the second comparison resultant bit are identical.

2. The optical sensor device of claim 1, wherein the photo transistor is a bipolar junction transistor (BJT), and the first pixel unit is a BIT sensing pixel.

3. The optical sensor device of claim 1, wherein the first shutter exposure time interval and the second shutter exposure time interval alternately occur for consecutive times.

4. The optical sensor device of claim 1, wherein the control circuit compares the first image signal with the second image signal to preliminarily determine whether a motion occurs.

5. The optical sensor device of claim 4, wherein the second shutter exposure time interval is shorter than the first shutter exposure time interval when the first time is followed by the second time; the control circuit determines that no motions occur at the second time when the second image signal is dimmer than the first image signal; and the control circuit determines that a motion occurs when the second image signal is brighter than the first image signal.

6. The optical sensor device of claim 4, wherein the second shutter exposure time interval is shorter than the first shutter exposure time interval when the second time is followed by the first time; the

control circuit determines that no motions occur when the second image signal is brighter than the first image signal; and, the control circuit determines that a motion occurs when the second image signal is dimmer than the first image signal.

7. The optical sensor device of claim 1, wherein the control circuit comprises: a first current source, coupled to the second output signal sent from the first pixel unit; a second current source, coupled to the first output signal sent from the first pixel unit; a first buffer capacitor, for storing the second output signal; a second buffer capacitor, for storing the first output signal; a first switch unit, disposed between and selectively coupled between the first buffer capacitor and the second output signal; a second switch unit, disposed between and selectively coupled between the second buffer capacitor and the first output signal; and a comparator, coupled to the first buffer capacitor and the second buffer capacitor, for comparing the first output signal with the second output signal, which is biased by the different threshold voltages, to generate the first comparison resultant bit and the second comparison resultant bit into the counter.

8. The optical sensor device of claim 7, wherein the control circuit dynamically adjust the different threshold voltages for different pixel units in response to different light intensities, and compares the first image signal with the second image one pixel unit by one pixel unit.

9. The optical sensor device of claim 1, wherein the second shutter exposure time interval is determined based on a first light intensity, a first shot noise level of the first light intensity, a second light intensity, and a second shot noise level of the second light intensity; the first shot noise level is lower than the second shot noise level when the second light intensity is higher than the first light intensity.

10. The optical sensor device of claim 1, wherein the pixel array further comprises: M column-based bias current sources, each column-based bias current source providing a bias current for output signals sent from pixel units disposed at a corresponding column; M column-based comparison circuits, coupled to the pixel units disposed at the corresponding column, each column-based comparison circuit being used to compare the output signals to generate and output a corresponding comparison resultant bit into the control circuit in response to a specific read control signal of a specific row, sent from the control circuit.

11. The optical sensor device of claim 10, wherein the control circuit comprises a counter, and the counter counts for multiple comparison resultant bits of all pixel units of the pixel array to generate a number of specific bits indicating significant pixel change and then compares the number of specific bits with a number threshold to resultantly determine whether a motion occurs.

12. The optical sensor device of claim 10, wherein the M column-based comparison circuits of the pixel array simultaneously generate M comparison resultant bits of pixel units at the specific row in response to the specific read control signal of the specific row.

13. A method of an optical sensor device, comprising: providing a pixel array having a plurality of pixel units arranged in N rows and M columns, a first pixel unit in the plurality of pixel units comprising: a photo transistor, configured to capture and generate a first image signal during a first shutter exposure time interval of a first time and to capture and generate a second image signal during a second shutter exposure time interval of a second time, the first time and the second time being consecutive; a first integration capacitor, coupled to the photo transistor, for storing the first image signal; and a second integration capacitor, coupled to the photo transistor, for storing the second image signal; and configuring the first shutter exposure time interval to be different from the second shutter exposure time interval; performing a motion detection to determine whether a motion occurs according to a difference between the first image signal captured during the first shutter exposure time interval and the second image signal captured during the second shutter exposure time interval; providing a comparator to comparing a first output signal with a second output signal, which is biased by different threshold voltages, to generate a first comparison resultant bit and a second comparison resultant bit into a counter, the first pixel unit outputting the first image signal as the first output signal and outputting the second image signal as the second

output signal respectively; and incrementing a counter's counting value by one only when the first comparison resultant bit and the second comparison resultant bit are identical.

14. The method of claim 13, wherein the first shutter exposure time interval and the second shutter exposure time interval alternately occur for consecutive times.

15. The method of claim 13, further comprising: comparing the first image signal with the second image signal to preliminarily determine whether a motion occurs.

16. The method of claim 15, wherein the second shutter exposure time interval is shorter than the first shutter exposure time interval when the first time is followed by the second time; and, the method comprises: determining that no motions occur at the second time when the second image signal is dimmer than the first image signal; and determining that a motion occurs when the second image signal is brighter than the first image signal.

17. The method of claim 15, wherein the second shutter exposure time interval is shorter than the first shutter exposure time interval when the second time is followed by the first time; and, the method further comprises: determining that no motions occur when the second image signal is brighter than the first image signal; and determining that a motion occurs when the second image signal is dimmer than the first image signal.

18. The method of claim 13, wherein the method further comprises: providing a first current source coupled to the second output signal sent from the first pixel unit; providing a second current source coupled to the first output signal sent from the first pixel unit; providing a first buffer capacitor to store the second output signal; providing a second buffer capacitor to store the first output signal; providing a first switch unit, disposed between and selectively coupled between the first buffer capacitor and the second output signal; and providing a second switch unit, disposed between and selectively coupled between the second buffer capacitor and the first output signal.

19. The method of claim 18, where the method further comprises: dynamically adjusting the different threshold voltages for different pixel units in response to different light intensities, and comparing the first image signal with the second image one pixel unit by one pixel unit.

20. The method of claim 13, wherein the method further comprises: determining the second shutter exposure time interval based on a first light intensity, a first shot noise level of the first light intensity, a second light intensity, and a second shot noise level of the second light intensity; the first shot noise level is lower than the second shot noise level when the second light intensity is higher than the first light intensity.

21. The method of claim 13, wherein the pixel array further comprises: M column-based bias current sources, each column-based bias current source providing a bias current for output signals sent from pixel units disposed at a corresponding column; M column-based comparison circuits, coupled to the pixel units disposed at the corresponding column, each column-based comparison circuit being used to compare the output signals to generate and output a corresponding comparison resultant bit into the control circuit in response to a specific read control signal of a specific row, sent from the control circuit.

22. The method of claim 21, wherein the method further comprises: providing a counter to count for multiple comparison resultant bits of all pixel units of the pixel array to generate a number of specific bits indicating significant pixel change; and comparing the number of specific bits with a number threshold to resultantly determine whether a motion occurs.

23. The method of claim 21, wherein the M column-based comparison circuits of the pixel array simultaneously generate M comparison resultant bits of pixel units at the specific row into in response to the specific read control signal of the specific row.
