

US Patent & Trademark Office

Patent Public Search | Text View

United States Patent

12407593

Kind Code

B2

Date of Patent

September 02, 2025

Inventor(s)

Ratnam; Vishnu Vardhan et al.

Wi-Fi based fine ranging using carrier phase information

Abstract

A method includes obtaining Wi-Fi channel state information (CSI) parameters measured at an anchor and a target device from Wi-Fi frames transmitted between the anchor and the target device, the CSI parameters comprising, for each of the anchor and the target device, frame transmission and reception times, a carrier phase of the CSI, a crystal offset factor, and a packet detection time error. The method also includes determining a round trip time (RTT) estimate or a relative change in the RTT estimate as a function of the CSI parameters. The method further includes estimating a range between the anchor and the target device as a function of the RTT estimate, or estimating a change in the range between the anchor and the target device as a function of the relative change in the RTT estimate.

Inventors: Ratnam; Vishnu Vardhan (Plano, TX), Sadiq; Bilal (Plano, TX), Chen; Hao (Allen, TX), Sehgal; Abhishek (Frisco, TX), Ng; Boon Loong (Plano, TX), Zhang; Jianzhong (Dallas, TX)

Applicant: Samsung Electronics Co., Ltd. (Suwon-si, KR)

Family ID: 91589334

Assignee: Samsung Electronics Co., Ltd. (Suwon-si, KR)

Appl. No.: 18/486906

Filed: October 13, 2023

Prior Publication Data

Document Identifier

Publication Date

US 20240223484 A1

Jul. 04, 2024

Related U.S. Application Data

us-provisional-application US 63434433 20221221

Publication Classification

Int. Cl.: H04L43/0864 (20220101); H04L25/02 (20060101); H04L27/26 (20060101); H04L43/0829 (20220101)

U.S. Cl.:

CPC H04L43/0864 (20130101); H04L25/0202 (20130101); H04L27/2659 (20130101); H04L27/266 (20130101); H04L43/0841 (20130101);

Field of Classification Search

CPC: H04L (43/0864); H04L (25/0202); H04L (27/2659); H04L (27/266); H04L (43/0841)

USPC: 709/224

References Cited

U.S. PATENT DOCUMENTS

Patent No.	Issued Date	Patentee Name	U.S. Cl.	CPC
10536805	12/2019	Nallampatti Ekambaram et al.	N/A	N/A
11683779	12/2022	Seth et al.	N/A	N/A
2019/0053124	12/2018	Bitra	N/A	H04W 76/10
2019/0158335	12/2018	Stanciu	N/A	H04L 27/2657
2019/0190806	12/2018	Bhushan	N/A	H04W 72/20
2020/0137715	12/2019	Edge et al.	N/A	N/A
2020/0229124	12/2019	Soriaga et al.	N/A	N/A
2020/0305113	12/2019	Seth	N/A	H04L 45/121
2022/0078644	12/2021	Chennichetty et al.	N/A	N/A
2022/0299629	12/2021	Liu et al.	N/A	N/A
2022/0394505	12/2021	Franke	N/A	H04W 24/10
2023/0071554	12/2022	Zhang et al.	N/A	N/A
2023/0072377	12/2022	Leroy et al.	N/A	N/A

FOREIGN PATENT DOCUMENTS

Patent No.	Application Date	Country	CPC
205810346	12/2015	CN	N/A
106162858	12/2018	CN	H04W 56/001
114785435	12/2021	CN	N/A
102022200588	12/2021	DE	H04W 28/0289
20220009460	12/2021	KR	N/A

OTHER PUBLICATIONS

IEEE Standards Association; IEEE Std 802.11—2020; IEEE Standard for Information Technology—Telecommunications and Information Exchange between Systems—Local and Metropolitan Area Networks—Specific Requirements; “Part 11: Wireless LAN Medium Access Control (MAC) and Physical Layer (PHY) Specifications”; Dec. 3, 2020; 4379 pgs. cited by applicant

Sourour, E., et al., “Frequency offset estimation and correction in the IEEE 802.11a WLAN”, IEEE 60th Vehicular Technology Conference, 2004, 5 pages. cited by applicant

Obeidat, H., et al., “A Review of Indoor Localization Techniques and Wireless Technologies”, Wireless Personal Communications (2021) 119:289-327, 39 pages. cited by applicant

Vasisht, D., et al., “Decimeter-Level Localization with a Single WiFi Access Point”, Proceedings of the 13th USENIX Symposium on Networked Systems Design and Implementation (NSDI '16), Santa Clara, CA, USA, Mar. 16-18, 2016, 15 pages. cited by applicant

Raissinia, A., et al., “Draft PAR for 320 MHz Positioning TGBk Project”, IEEE P802.11 Wireless LANs, IEEE 802.11-22/1325r5, Aug. 2022, 3 pages. cited by applicant

IEEE P802.11azTM/D5.0 May 2022, Draft Standard for Information Technology—Telecommunications and information exchange between systems Local and metropolitan area networks—Specific requirements “Part 11: Wireless LAN Medium Access Control (MAC) and Physical Layer (PHY) Specifications, Amendment 4: Enhancements for positioning”, 287 p. cited by applicant

International Search Report and Written Opinion issued Feb. 13, 2024 regarding International Application No.

Primary Examiner: Lazaro; David R

Assistant Examiner: Henry; Mariegeorges A

Background/Summary

(1) This application claims priority under 35 U.S.C. § 119(e) to U.S. Provisional Patent Application No. 63/434,433, filed on Dec. 21, 2022, which is hereby incorporated by reference in its entirety.

TECHNICAL FIELD

(1) This disclosure relates generally to wireless communications systems. Embodiments of this disclosure relate to methods and apparatuses for Wi-Fi based fine ranging by using carrier phase information.

BACKGROUND

(2) Various positioning and localization techniques have grown in popularity over the last decade in parallel with the growth in the number of personal wireless devices and the growth in wireless infrastructure. While the use cases are plentiful and include smart homes and buildings, surveillance, disaster management, industry and healthcare, they all require wide availability and good accuracy. A key step of most positioning/localization solutions is ranging which involves identification of the distance (or a difference in distances) of the target device from a set of anchor devices whose locations are known.

SUMMARY

(3) Embodiments of the present disclosure provide methods and apparatuses for Wi-Fi based fine ranging by using carrier phase information.

(4) In one embodiment, a method includes obtaining Wi-Fi channel state information (CSI) parameters measured at an anchor and a target device from Wi-Fi frames transmitted between the anchor and the target device, the CSI parameters comprising, for each of the anchor and the target device, frame transmission and reception times, a carrier phase of the CSI, a crystal offset factor, and a packet detection time error. The method also includes determining a round trip time (RTT) estimate or a relative change in the RTT estimate as a function of the CSI parameters. The method further includes estimating a range between the anchor and the target device as a function of the RTT estimate, or estimating a change in the range between the anchor and the target device as a function of the relative change in the RTT estimate.

(5) In another embodiment, a device includes a transceiver and a processor operably connected to the transceiver. The processor is configured to: obtain Wi-Fi CSI parameters measured at an anchor and a target device from Wi-Fi frames transmitted between the anchor and the target device, the CSI parameters comprising, for each of the anchor and the target device, frame transmission and reception times, a carrier phase of the CSI, a crystal offset factor, and a packet detection time error; determine a RTT estimate or a relative change in the RTT estimate as a function of the CSI parameters; and estimate a range between the anchor and the target device as a function of the RTT estimate, or estimate a change in the range between the anchor and the target device as a function of the relative change in the RTT estimate.

(6) In another embodiment, a non-transitory computer readable medium includes program code that, when executed by a processor of a device, causes the device to: obtain Wi-Fi CSI parameters measured at an anchor and a target device from Wi-Fi frames transmitted between the anchor and the target device, the CSI parameters comprising, for each of the anchor and the target device, frame transmission and reception times, a carrier phase of the CSI, a crystal offset factor, and a packet detection time error; determine a RTT estimate or a relative change in the RTT estimate as a function of the CSI parameters; and estimate a range between the anchor and the target device as a function of the RTT estimate, or estimate a change in the range between the anchor and the target device as a function of the relative change in the RTT estimate.

(7) Other technical features may be readily apparent to one skilled in the art from the following figures, descriptions, and claims.

(8) Before undertaking the DETAILED DESCRIPTION below, it may be advantageous to set forth definitions of certain words and phrases used throughout this patent document. The term "couple" and its derivatives refer to any direct or indirect communication between two or more elements, whether or not those elements are in physical contact with one another. The terms "transmit," "receive," and "communicate," as well as derivatives

thereof, encompass both direct and indirect communication. The terms “include” and “comprise,” as well as derivatives thereof, mean inclusion without limitation. The term “or” is inclusive, meaning and/or. The phrase “associated with,” as well as derivatives thereof, means to include, be included within, interconnect with, contain, be contained within, connect to or with, couple to or with, be communicable with, cooperate with, interleave, juxtapose, be proximate to, be bound to or with, have, have a property of, have a relationship to or with, or the like. The term “controller” means any device, system or part thereof that controls at least one operation. Such a controller may be implemented in hardware or a combination of hardware and software and/or firmware. The functionality associated with any particular controller may be centralized or distributed, whether locally or remotely. The phrase “at least one of,” when used with a list of items, means that different combinations of one or more of the listed items may be used, and only one item in the list may be needed. For example, “at least one of: A, B, and C” includes any of the following combinations: A, B, C, A and B, A and C, B and C, and A and B and C. As used herein, such terms as “1st” and “2nd,” or “first” and “second” may be used to simply distinguish a corresponding component from another and does not limit the components in other aspect (e.g., importance or order). It is to be understood that if an element (e.g., a first element) is referred to, with or without the term “operatively” or “communicatively”, as “coupled with,” “coupled to,” “connected with,” or “connected to” another element (e.g., a second element), it means that the element may be coupled with the other element directly (e.g., wiredly), wirelessly, or via a third element.

(9) As used herein, the term “module” may include a unit implemented in hardware, software, or firmware, and may interchangeably be used with other terms, for example, “logic,” “logic block,” “part,” or “circuitry”. A module may be a single integral component, or a minimum unit or part thereof, adapted to perform one or more functions. For example, according to an embodiment, the module may be implemented in a form of an application-specific integrated circuit (ASIC).

(10) Moreover, various functions described below can be implemented or supported by one or more computer programs, each of which is formed from computer readable program code and embodied in a computer readable medium. The terms “application” and “program” refer to one or more computer programs, software components, sets of instructions, procedures, functions, objects, classes, instances, related data, or a portion thereof adapted for implementation in a suitable computer readable program code. The phrase “computer readable program code” includes any type of computer code, including source code, object code, and executable code. The phrase “computer readable medium” includes any type of medium capable of being accessed by a computer, such as read only memory (ROM), random access memory (RAM), a hard disk drive, a compact disc (CD), a digital video disc (DVD), or any other type of memory. A “non-transitory” computer readable medium excludes wired, wireless, optical, or other communication links that transport transitory electrical or other signals. A non-transitory computer readable medium includes media where data can be permanently stored and media where data can be stored and later overwritten, such as a rewritable optical disc or an erasable memory device.

(11) Definitions for other certain words and phrases are provided throughout this patent document. Those of ordinary skill in the art should understand that in many if not most instances, such definitions apply to prior as well as future uses of such defined words and phrases.

Description

BRIEF DESCRIPTION OF THE DRAWINGS

(1) For a more complete understanding of the present disclosure and its advantages, reference is now made to the following description taken in conjunction with the accompanying drawings, in which like reference numerals represent like parts:

(2) FIG. 1 illustrates an example wireless network according to various embodiments of the present disclosure;

(3) FIG. 2A illustrates an example AP according to various embodiments of the present disclosure;

(4) FIG. 2B illustrates an example STA according to various embodiments of the present disclosure;

(5) FIG. 3 illustrates an example measurement phase of an FTM session comprising one burst and 3 measurements (FTMs) per burst;

(6) FIG. 4 illustrates an example system in which Wi-Fi-based fine range estimation can be performed according to various embodiments of the present disclosure;

(7) FIG. 5 illustrates an example timeline for CSI acquisition frame transmission in the system of FIG. 4 according to various embodiments of the present disclosure;

(8) FIG. 6 illustrates a typical frame structure of an 802.11a frame;

(9) FIG. 7 illustrates an example timing diagram showing a timing calculation from a CSI Acquisition

request/response frame for use by the system of FIG. 4, according to various embodiments of the present disclosure;

(10) FIGS. 8A and 8B illustrate charts showing the effect of the packet start time error on the phase of CSI at a target device and an anchor, according to various embodiments of the present disclosure;

(11) FIGS. 9A and 9B illustrate charts comparing estimation of device velocity based on transmission periodicity of CSI acquisition frames, according to various embodiments of the present disclosure;

(12) FIG. 10 illustrates a process of an anchor performing Wi-Fi based fine ranging according to various embodiments of the present disclosure;

(13) FIG. 11 illustrates a process of a target device performing Wi-Fi based fine ranging according to various embodiments of the present disclosure;

(14) FIG. 12 illustrates a process of a ranging device performing Wi-Fi based fine ranging according to various embodiments of the present disclosure; and

(15) FIG. 13 illustrates a flow chart of a method for Wi-Fi based fine ranging by exploiting carrier phase information according to various embodiments of the present disclosure.

DETAILED DESCRIPTION

(16) FIGS. 1 through 13, discussed below, and the various embodiments used to describe the principles of the present disclosure in this patent document are by way of illustration only and should not be construed in any way to limit the scope of the disclosure. Those skilled in the art will understand that the principles of the present disclosure may be implemented in any suitably arranged system or device.

(17) Aspects, features, and advantages of the disclosure are readily apparent from the following detailed description, simply by illustrating a number of particular embodiments and implementations, including the best mode contemplated for carrying out the disclosure. The disclosure is also capable of other and different embodiments, and its several details can be modified in various obvious respects, all without departing from the spirit and scope of the disclosure. Accordingly, the drawings and description are to be regarded as illustrative in nature, and not as restrictive. The disclosure is illustrated by way of example, and not by way of limitation, in the figures of the accompanying drawings.

(18) The present disclosure covers several components which can be used in conjunction or in combination with one another or can operate as standalone schemes. Certain embodiments of the disclosure may be derived by utilizing a combination of several of the embodiments listed below. Also, it should be noted that further embodiments may be derived by utilizing a particular subset of operational steps as disclosed in each of these embodiments. This disclosure should be understood to cover all such embodiments.

(19) FIG. 1 illustrates an example wireless network 100 according to various embodiments of the present disclosure. The embodiment of the wireless network 100 shown in FIG. 1 is for illustration only. Other embodiments of the wireless network 100 could be used without departing from the scope of this disclosure.

(20) The wireless network 100 includes access points (APs) 101 and 103. The APs 101 and 103 communicate with at least one network 130, such as the Internet, a proprietary Internet Protocol (IP) network, or other data network. The AP 101 provides wireless access to the network 130 for a plurality of stations (STAs) 111-114 within a coverage area 120 of the AP 101. The APs 101-103 may communicate with each other and with the STAs 111-114 using Wi-Fi or other WLAN (wireless local area network) communication techniques. The STAs 111-114 may communicate with each other using peer-to-peer protocols, such as Tunneled Direct Link Setup (TDLS).

(21) Depending on the network type, other well-known terms may be used instead of “access point” or “AP,” such as “router” or “gateway.” For the sake of convenience, the term “AP” is used in this disclosure to refer to network infrastructure components that provide wireless access to remote terminals. In WLAN, given that the AP also contends for the wireless channel, the AP may also be referred to as a STA. Also, depending on the network type, other well-known terms may be used instead of “station” or “STA,” such as “mobile station,” “subscriber station,” “remote terminal,” “user equipment,” “wireless terminal,” or “user device.” For the sake of convenience, the terms “station” and “STA” are used in this disclosure to refer to remote wireless equipment that wirelessly accesses an AP or contends for a wireless channel in a WLAN, whether the STA is a mobile device (such as a mobile telephone or smartphone) or is normally considered a stationary device (such as a desktop computer, AP, media player, stationary sensor, television, etc.).

(22) Dotted lines show the approximate extents of the coverage areas 120 and 125, which are shown as approximately circular for the purposes of illustration and explanation only. It should be clearly understood that the coverage areas associated with APs, such as the coverage areas 120 and 125, may have other shapes, including irregular shapes, depending upon the configuration of the APs and variations in the radio environment associated with natural and man-made obstructions.

(23) As described in more detail below, one or more of the APs may include circuitry and/or programming to enable Wi-Fi based fine ranging by exploiting carrier phase information. Although FIG. 1 illustrates one example of a wireless network **100**, various changes may be made to FIG. 1. For example, the wireless network **100** could include any number of APs and any number of STAs in any suitable arrangement. Also, the AP **101** could communicate directly with any number of STAs and provide those STAs with wireless broadband access to the network **130**. Similarly, each AP **101** and **103** could communicate directly with the network **130** and provide STAs with direct wireless broadband access to the network **130**. Further, the APs **101** and/or **103** could provide access to other or additional external networks, such as external telephone networks or other types of data networks.

(24) FIG. 2A illustrates an example AP **101** according to various embodiments of the present disclosure. The embodiment of the AP **101** illustrated in FIG. 2A is for illustration only, and the AP **103** of FIG. 1 could have the same or similar configuration. However, APs come in a wide variety of configurations, and FIG. 2A does not limit the scope of this disclosure to any particular implementation of an AP.

(25) The AP **101** includes multiple antennas **204a-204n** and multiple transceivers **209a-209n**. The AP **101** also includes a controller/processor **224**, a memory **229**, and a backhaul or network interface **234**. The transceivers **209a-209n** receive, from the antennas **204a-204n**, incoming radio frequency (RF) signals, such as signals transmitted by STAs **111-114** in the network **100**. The transceivers **209a-209n** down-convert the incoming RF signals to generate IF or baseband signals. The IF or baseband signals are processed by receive (RX) processing circuitry in the transceivers **209a-209n** and/or controller/processor **224**, which generates processed baseband signals by filtering, decoding, and/or digitizing the baseband or IF signals. The controller/processor **224** may further process the baseband signals.

(26) Transmit (TX) processing circuitry in the transceivers **209a-209n** and/or controller/processor **224** receives analog or digital data (such as voice data, web data, e-mail, or interactive video game data) from the controller/processor **224**. The TX processing circuitry encodes, multiplexes, and/or digitizes the outgoing baseband data to generate processed baseband or IF signals. The transceivers **209a-209n** up-converts the baseband or IF signals to RF signals that are transmitted via the antennas **204a-204n**.

(27) The controller/processor **224** can include one or more processors or other processing devices that control the overall operation of the AP **101**. For example, the controller/processor **224** could control the reception of forward channel signals and the transmission of reverse channel signals by the transceivers **209a-209n** in accordance with well-known principles. The controller/processor **224** could support additional functions as well, such as more advanced wireless communication functions. For instance, the controller/processor **224** could support beam forming or directional routing operations in which outgoing signals from multiple antennas **204a-204n** are weighted differently to effectively steer the outgoing signals in a desired direction. The controller/processor **224** could also support OFDMA operations in which outgoing signals are assigned to different subsets of subcarriers for different recipients (e.g., different STAs **111-114**). Any of a wide variety of other functions could be supported in the AP **101** by the controller/processor **224** including enabling Wi-Fi based fine ranging by exploiting carrier phase information. In some embodiments, the controller/processor **224** includes at least one microprocessor or microcontroller. The controller/processor **224** is also capable of executing programs and other processes resident in the memory **229**, such as an OS. The controller/processor **224** can move data into or out of the memory **229** as required by an executing process.

(28) The controller/processor **224** is also coupled to the backhaul or network interface **234**. The backhaul or network interface **234** allows the AP **101** to communicate with other devices or systems over a backhaul connection or over a network. The interface **234** could support communications over any suitable wired or wireless connection(s). For example, the interface **234** could allow the AP **101** to communicate over a wired or wireless local area network or over a wired or wireless connection to a larger network (such as the Internet). The interface **234** includes any suitable structure supporting communications over a wired or wireless connection, such as an Ethernet or RF transceiver. The memory **229** is coupled to the controller/processor **224**. Part of the memory **229** could include a RAM, and another part of the memory **229** could include a Flash memory or other ROM.

(29) As described in more detail below, the AP **101** may include circuitry and/or programming for Wi-Fi based fine ranging by exploiting carrier phase information. Although FIG. 2A illustrates one example of AP **101**, various changes may be made to FIG. 2A. For example, the AP **101** could include any number of each component shown in FIG. 2A. As a particular example, an access point could include a number of interfaces **234**, and the controller/processor **224** could support routing functions to route data between different network addresses. Alternatively, only one antenna and transceiver path may be included, such as in legacy APs. Also, various components in FIG. 2A could be combined, further subdivided, or omitted and additional components

could be added according to particular needs.

(30) FIG. 2B illustrates an example STA **111** according to various embodiments of the present disclosure. The embodiment of the STA **111** illustrated in FIG. 2B is for illustration only, and the STAs **112-114** of FIG. 1 could have the same or similar configuration. However, STAs come in a wide variety of configurations, and FIG. 2B does not limit the scope of this disclosure to any particular implementation of a STA.

(31) The STA **111** includes antenna(s) **205**, transceiver(s) **210**, a microphone **220**, a speaker **230**, a processor **240**, an input/output (I/O) interface (IF) **245**, an input **250**, a display **255**, and a memory **260**. The memory **260** includes an operating system (OS) **261** and one or more applications **262**.

(32) The transceiver(s) **210** receives from the antenna(s) **205**, an incoming RF signal (e.g., transmitted by an AP **101** of the network **100**). The transceiver(s) **210** down-converts the incoming RF signal to generate an intermediate frequency (IF) or baseband signal. The IF or baseband signal is processed by RX processing circuitry in the transceiver(s) **210** and/or processor **240**, which generates a processed baseband signal by filtering, decoding, and/or digitizing the baseband or IF signal. The RX processing circuitry sends the processed baseband signal to the speaker **230** (such as for voice data) or is processed by the processor **240** (such as for web browsing data).

(33) TX processing circuitry in the transceiver(s) **210** and/or processor **240** receives analog or digital voice data from the microphone **220** or other outgoing baseband data (such as web data, e-mail, or interactive video game data) from the processor **240**. The TX processing circuitry encodes, multiplexes, and/or digitizes the outgoing baseband data to generate a processed baseband or IF signal. The transceiver(s) **210** up-converts the baseband or IF signal to an RF signal that is transmitted via the antenna(s) **205**.

(34) The processor **240** can include one or more processors and execute the basic OS program **261** stored in the memory **260** in order to control the overall operation of the STA **111**. In one such operation, the processor **240** controls the reception of forward channel signals and the transmission of reverse channel signals by the transceiver(s) **210** in accordance with well-known principles. The processor **240** can also include processing circuitry configured to enable Wi-Fi based fine ranging by exploiting carrier phase information. In some embodiments, the processor **240** includes at least one microprocessor or microcontroller.

(35) The processor **240** is also capable of executing other processes and programs resident in the memory **260**, such as operations for enabling Wi-Fi based fine ranging by exploiting carrier phase information. The processor **240** can move data into or out of the memory **260** as required by an executing process. In some embodiments, the processor **240** is configured to execute a plurality of applications **262**, such as applications to enable Wi-Fi based fine ranging by exploiting carrier phase information. The processor **240** can operate the plurality of applications **262** based on the OS program **261** or in response to a signal received from an AP. The processor **240** is also coupled to the I/O interface **245**, which provides STA **111** with the ability to connect to other devices such as laptop computers and handheld computers. The I/O interface **245** is the communication path between these accessories and the processor **240**.

(36) The processor **240** is also coupled to the input **250**, which includes for example, a touchscreen, keypad, etc., and the display **255**. The operator of the STA **111** can use the input **250** to enter data into the STA **111**. The display **255** may be a liquid crystal display, light emitting diode display, or other display capable of rendering text and/or at least limited graphics, such as from web sites. The memory **260** is coupled to the processor **240**. Part of the memory **260** could include a random-access memory (RAM), and another part of the memory **260** could include a Flash memory or other read-only memory (ROM).

(37) Although FIG. 2B illustrates one example of STA **111**, various changes may be made to FIG. 2B. For example, various components in FIG. 2B could be combined, further subdivided, or omitted and additional components could be added according to particular needs. In particular examples, the STA **111** may include any number of antenna(s) **205** for MIMO communication with an AP **101**. In another example, the STA **111** may not include voice communication or the processor **240** could be divided into multiple processors, such as one or more central processing units (CPUs) and one or more graphics processing units (GPUs). Also, while FIG. 2B illustrates the STA **111** configured as a mobile telephone or smartphone, STAs could be configured to operate as other types of mobile or stationary devices.

(38) As discussed earlier, various positioning and localization techniques have grown in popularity over the last decade in parallel with the growth in the number of personal wireless devices and the growth in wireless infrastructure. While the use cases are plentiful and include smart homes and buildings, surveillance, disaster management, industry and healthcare, they all require wide availability and good accuracy. A key step of most positioning/localization solutions is ranging which involves identification of the distance (or a difference in distances) of the target device from a set of anchor devices whose locations are known. Correspondingly several ranging techniques have been proposed in Ultra-wide band (UWB), Lidar and Wi-Fi. In fact, WiFi standards

like 802.11mc and 802.11az have been specifically tailored for enabling WiFi-based ranging, such as via the Fine Timing Measurement (FTM) protocol. FTM is a wireless network management procedure that allows a Wi-Fi station (STA) to accurately measure the distance (or range) from other STAs (e.g., an access point) by measuring the round-trip time (RTT) between the two.

(39) An STA wanting to localize itself, known as the initiating STA, with respect to other STAs, known as responding STAs, schedules an FTM session during which the STAs exchange messages and measurements. The FTM session consists of three phases: negotiation, measurement exchange, and termination.

(40) The measurement phase consists of one or more bursts, and each burst consists of one or more (Fine Time) measurements. The duration of a burst and the number of measurements therein are defined by the parameters burst duration and FTMs per burst. The bursts are separated by an interval defined by the parameter burst duration. In the negotiation phase, the initiating STA negotiates with the responding STA key parameters, such as frame format and bandwidth, number of bursts, burst duration, the burst period, and the number of measurements per burst.

(41) FIG. 3 illustrates an example measurement phase **300** of an FTM session comprising one burst and 3 measurements (FTMs) per burst.

(42) As shown in FIG. 3, the initiating STA (I-STA) **302** sends an Initial FTM Request frame **306** to the responding STA (R-STA) **304**, triggering the start of the FTM session. The R-STA **304** responds with an ACK **308**.

(43) The R-STA **304** then sends the first FTM frame **310** to the I-STA **302** and captures the time it is sent $t_{\text{sub.1.sup.}(1)}$. Upon receiving the first FTM frame **310**, the I-STA **302** captures the time it was received $t_{\text{sub.2.sup.}(1)}$. The I-STA **302** responds with an ACK **312**, and captures the time it is sent $t_{\text{sub.3.sup.}(1)}$. Upon receiving the ACK **312**, the R-STA **304** captures the time it was received $t_{\text{sub.4.sup.}(1)}$.

(44) The R-STA **304** sends a second FTM frame **314** to the I-STA **302** and captures the time it is sent $t_{\text{sub.1.sup.}(2)}$. The purpose of the second FTM frame **314** is twofold: First, the second FTM frame **314** is a follow-up to the first FTM frame **310**, i.e., it is used to transfer the timestamps $t_{\text{sub.1.sup.}(1)}$ and $t_{\text{sub.4.sup.}(1)}$ recorded by the R-STA **304**. Second, the second FTM frame **314** starts a second measurement. Upon receiving the second FTM frame **314**, the I-STA **302** extracts the timestamps $t_{\text{sub.1.sup.}(1)}$ and $t_{\text{sub.4.sup.}(1)}$ and computes the RTT according to the following equation:

$$(45) \text{RTT} = (t_4^{(1)} - t_1^{(1)}) - (t_3^{(1)} - t_2^{(1)}).$$

(46) The I-STA **302** also responds with an ACK **316**, and captures the time the second FTM frame **314** was received $t_{\text{sub.2.sup.}(2)}$.

(47) The two STAs **302** and **304** continue exchanging FTM frames and ACKs for as many measurements as has been negotiated between the two. In the measurement phase **300**, this includes a third FTM frame **318** and a third ACK **320**.

(48) In order to be useful for positioning and proximity apps, the RTT between the two STAs **302** and **304** can be translated into a distance, such as by the following equation:

$$(49) d = \frac{\text{RTT}}{2} c.$$

where d is the distance between the two STAs and c is the speed of light.

(50) Each FTM of the burst will yield a distance sample, with multiple distance samples per burst. Given multiple FTM bursts and multiple measurements per burst, the distance samples can be combined in different ways to produce a representative distance measurement. For example, the mean distance, the median distance, or some other percentile of distance can be reported. Furthermore, other statistics (e.g., the standard deviation) could be reported as well to be used by the positioning algorithm.

(51) The FTM based mechanism is fundamentally limited by the bandwidth and SNR of the Wi-Fi system. For example, for 80 MHz Wi-Fi bandwidth and typical channel SNRs, approximately 1-3 meters ranging accuracy is feasible with high probability. This ranging accuracy in turn limits the localization accuracy to about a similar order. Such a level of accuracy may be unsuitable for several applications which require or benefit from a much finer range resolution. Although multiple adjacent FTM measurements can be averaged to improve range accuracy, the accuracy suffers when the target device is moving between the FTM measurements being averaged. IEEE is working on increasing the bandwidth of Wi-Fi-ranging to 320 MHz, which comes at a significant price and power penalty. Some indirect methods to increase bandwidth by bandwidth stitching are also impractical since they require hardware changes and need devices to hop across multiple bands.

(52) To address these and other issues, this disclosure provides systems and methods for Wi-Fi based fine ranging by exploiting carrier phase information. As described in more detail below, the disclosed embodiments augment the accuracy of Wi-Fi RTT estimation by exploiting the Wi-Fi CSI measured at the anchor and the target device. In particular, the disclosed embodiments use the inter-subcarrier phase of CSI to improve the

estimation of packet detection time and correspondingly the round-trip time via super-resolution methods. In addition, the disclosed embodiments use the absolute phase of the CSI, known as the carrier phase component, to estimate relative changes in range in between adjacent measurements, with an accuracy related to the carrier frequency.

(53) The disclosed embodiments provide multiple advantageous benefits over conventional systems that perform Wi-Fi RTT estimation, including much greater accuracy. For example, with a 5 GHz carrier frequency, the accuracy of range difference measurements using the disclosed embodiments can potentially be <1 cm (i.e., about the order of two wavelengths), independent of bandwidth.

(54) Although the details below are provided assuming a Wi-Fi system as an example, this shall not be considered as a restriction and the provided embodiments shall be applicable to any wireless communication technology that is capable of bi-directional communication, can capture a time of transmission of transmission and reception of messages, and track the channel state information either in the frequency domain (such as with an OFDM system) or in delay domain (such as in a UWB system).

(55) FIG. 4 illustrates an example system 400 in which Wi-Fi-based fine range estimation can be performed according to various embodiments of the present disclosure. As shown in FIG. 4, the system 400 includes a Wi-Fi anchor 401 with one antenna and a Wi-Fi target device 402 with one antenna, whose distance or range from the anchor 401 is to be measured. It is noted that the presence of only one antenna at either device is merely an example, and should not be construed as a limitation on the embodiments presented in this disclosure. In some embodiments, the anchor 401 can be an AP and the target device 402 can be a Wi-Fi STA or vice versa. In other embodiments, both the anchor 401 and the target device 402 can be STAs or both can be APs.

(56) FIG. 5 illustrates an example timeline 500 for CSI acquisition frame transmission in the system 400 according to various embodiments of the present disclosure. As shown in FIG. 5, to enable estimation of the range, the anchor 401 may transmit a sequence of Wi-Fi channel state information (CSI) acquisition request frames 501, indexed as $p = \{1, 2, \dots, P\}$. For each such CSI frame p , the target device 402 may also transmit a CSI acquisition response frame 502, which can be, for example, an acknowledgement frame.

(57) These CSI acquisition frame exchanges between the anchor 401 and the target device 402 may take place on a specific channel from a plurality of available channels. The list of available channels may be, for example, provided by the anchor 401. The available channels can also include multiple carrier frequency channels, as in multi-link operation of Wi-Fi-7. The anchor 401, the target device 402, or another ranging device may initiate a procedure for selecting the appropriate channel, from the list of available channels, for performing these exchanges. Such a selection can be based on several factors, including one or more of: The RSSI and/or the OBSS interference on the channel. The bandwidth and carrier frequency of the channel. The occupancy of the channel. The band capabilities of the target and anchor device. The primary and secondary channel assignments for the anchor device (if applicable), etc.

(58) For example, a channel with less occupancy (to ensure predictable inter-frame exchange times) and lower carrier frequency (to maximize the trackable velocity) can be preferable for the carrier-phase based differential range estimation used in Operation 6 (described later). In one example, the identified channel may first be requested by a target device, and it may then be confirmed by the anchor device, or an alternative may be suggested by the target device. In some embodiments, the channel can be identified by indicating operating class, channel number, and secondary channel offset for the determined channel.

(59) In some embodiments, the CSI acquisition frames (including the CSI acquisition request frames 501 and the CSI acquisition response frames 502) can be transmitted using orthogonal frequency division multiplexing (OFDM) over K sub-carriers indexed as:

$$(60) \quad = \{ \text{.Math. } \frac{K+1}{2} \text{ .Math. } , \dots , 0 , \dots , \text{.Math. } \frac{K-1}{2} \text{ .Math. } \} .$$

Each such CSI acquisition frame may have a short training field (STF) and a long training field (LTF), followed by several OFDM symbols. For example, in Wi-Fi 802.11a, each frame is transmitted via OFDM modulation, with $K=64$ subcarriers in each 20 MHz bandwidth and a symbol duration of $T_{\text{sub.s}}=4 \mu\text{s}$ (including $0.8 \mu\text{s}$ of guard interval $T_{\text{sub.cp}}$). FIG. 6 illustrates a typical frame structure 600 of an 802.11a frame.

(61) Using the overall information collected from the CSI acquisition request frames 501 and the CSI acquisition response frames 502, the goal is to obtain, at the anchor 401 or the target device 402, an accurate round-trip time (RTT) estimate for use in ranging.

(62) In some embodiments, for each CSI acquisition request or response frame p sent by either the anchor 401 or the target device 402, the corresponding recipient can estimate the channel CSI using one or more of the OFDM symbols in the frame and using one or more subcarriers in the one or more OFDM symbols. For example, these OFDM symbols can be from the LTF of the frame. Without loss of generality, let the $M_{\text{sub.1}}$ -th OFDM symbol of the CSI acquisition request frame 501 be used for estimating CSI at the target device 402,

while the M.sub.2-th OFDM symbol of the CSI acquisition response frame **502** be used for estimating CSI at the anchor **401**. Each CSI acquisition request frame **501** and the corresponding CSI acquisition response frame **502** can be used together to obtain an estimate of the RTT corresponding to frame p, as shall be explained below.

(63) For simplicity, it is assumed that the channel between the anchor **401** and the target device **402** is a strongly line of sight (LoS) channel with a one-way propagation delay of $p_{\text{sub.p}}$ for CSI frame sequence p. Note that RTT is twice the propagation delay (i.e., $\text{RTT}=2p_{\text{sub.p}}$). It is also assumed that the system clock between the anchor **401** and the target device **402** may have an unknown clock offset $\Delta T_{\text{sub.p}}$ at the start of transmission of the p-th CSI acquisition request frame **501**. It is further assumed that the difference in the carrier phase between the anchor **401** and the target device **402** is $\phi_{\text{sub.p}}$ at the start of transmission of the p-th CSI acquisition request frame **501**. Note that since the target device **402** can be moving and the oscillators at the two devices **401** and **402** (which generate the system clock and carrier) may also drift apart, therefore $p_{\text{sub.p}}$, $\Delta T_{\text{sub.p}}$, can change with the frame index $p=\{1, \dots, P\}$.

(64) The anchor **401** and the target device **402** each have their own crystal oscillator. It is assumed that the oscillator frequency of the target device **402** may differ from the oscillator frequency of the anchor **401** by an unknown factor of $\eta_{\text{sub.p}}$ (typically $|\eta_{\text{sub.p}}| \approx 10^{-5}$). Note that $\eta_{\text{sub.p}}$ causes the carrier frequency at the target device **402** to be $(1+\eta_{\text{sub.p}})f_{\text{sub.c}}$, where $f_{\text{sub.c}}$ is the carrier frequency at the anchor **401**. Also note that this offset also causes the OFDM symbol duration for packets generated at the target device **402** to be of duration $(1-\eta_{\text{sub.p}})T_{\text{sub.s}}$, where $T_{\text{sub.s}}$ is the symbol duration at the anchor **401**. Since the difference in the carrier frequencies of the two devices **401** and **402**, called carrier frequency offset (CFO), is dependent on $\eta_{\text{sub.p}}$, a CFO estimation performed for each frame p can also be used to estimate the value of $\eta_{\text{sub.p}}$ as will be described in greater detail below. Note that although $\eta_{\text{sub.p}}$ can be dependent on the frame index p, the value of $\eta_{\text{sub.p}}$ may vary smoothly with time, i.e., may be very similar for adjacent values of p.

(65) FIG. 7 illustrates an example timing diagram **700** showing a timing calculation from a CSI Acquisition request/response frame for use by the system **400**, according to various embodiments of the present disclosure.

(66) As shown in FIG. 7, the anchor **401** sends the p-th CSI acquisition request frame **501** at time $t_{\text{sub.p},1}$ (measured in its own clock). The time of reception of CSI acquisition request frame **501**, as measured by the target device **402** in its own clock, is $t_{\text{sub.p},1.\text{sup.R}}$. It can then be shown that:

$$(67) t_{p,1}^R = t_{p,1} + (1 + \eta_{\text{sub.p}}) p_{\text{sub.p}} + T_p - p_{p,1}, \approx t_{p,1} + p_{\text{sub.p}} + T_p - p_{p,1},$$

where $\tau_{\text{sub.p},1}$ is the error in the detection of the frame start time at the target device **402**. Using the STF and LTF of the CSI acquisition request frame **501**, and the pilot sub-carriers within all the OFDM symbols of the frame **501**, a very fine and accurate estimate of the carrier frequency offset $\eta_{\text{sub.p}} f_{\text{sub.c}}$ can be obtained at the target device **402**, and used to compensate for the intra-frame carrier phase rotation. After removing this intra-frame carrier phase rotation, the measured CSI (for subcarriers $k \in \text{custom character}$) from the M.sub.1-th symbol of the CSI acquisition request frame **501** can be expressed as:

$$(68) H_{p,k}^1 = e^{-j \phi_{\text{sub.p}}} e^{-j 2 \pi f_{\text{sub.c}} p_{\text{sub.p}}} e^{-j 2 \pi \eta_{\text{sub.p}} f_{\text{sub.c}} (p_{\text{sub.p}} - \frac{p_{p,1}}{1+\eta_{\text{sub.p}}})} e^{-\frac{j 2 \pi f_k p_{p,1}}{1+\eta_{\text{sub.p}}}} e^{-\frac{j 2 \pi f_k p_{p,1} M_1 T_s}{1+\eta_{\text{sub.p}}}} e^{-\frac{j 2 \pi \phi_{\text{sub.p}}}{N}},$$

where $f_{\text{sub.k}}=k/(T_{\text{sub.s}}-T_{\text{sub.cp}})$ is the frequency offset of the k-th subcarrier from the carrier frequency at the anchor **401**, $T_{\text{sub.cp}}$ is the duration of the guard interval/cyclic prefix in an OFDM symbol, $n_{\text{sub.p}} \in \{0, \dots, N\}$ is an arbitrary integer and N is an arbitrary phase ambiguity factor that depends on the receiver implementation. Typically, $N=1, 2$, or 4 . Using the fact that $\eta_{\text{sub.p}} p_{\text{sub.p}} \approx 0$ and $f_{\text{sub.cp}} p_{\text{sub.p}}$, $f_{\text{sub.k}} \tau_{\text{sub.p},1}$, $f_{\text{sub.k}} M_{\text{sub.1}} T_{\text{sub.s}}$ are typically much smaller than $1/\eta_{\text{sub.p}}$ this can be approximated as:

$$(69) H_{p,k}^1 \approx e^{-j \phi_{\text{sub.p}}} e^{-j 2 \pi f_{\text{sub.c}} p_{\text{sub.p}}} e^{-j 2 \pi f_k p_{p,1}} e^{-\frac{j 2 \pi \phi_{\text{sub.p}}}{N}}.$$

(70) Note that this CSI can be used to obtain an estimate $\{\text{circumflex over } (\tau)\}_{\text{sub.p},1}$ of $\tau_{\text{sub.p},1}$ and an estimate

$$(71) \hat{\tau}_{p,1} \text{ of } \text{mod}\{2 \pi f_{\text{sub.c}} p_{\text{sub.p}} + \phi_{\text{sub.p}} - \frac{2 \pi \phi_{\text{sub.p}}}{N}, 2 \pi\}$$

at the target device **402**.

(72) Similarly, the target device **402** sends the p-th CSI acquisition response frame **502** at time $t_{\text{sub.p},2}$ (measured in its own clock). Let the time of reception of the CSI acquisition response frame **502**, as measured by the anchor **401** in its own clock, be $t_{\text{sub.p},2.\text{sup.R}}$. It can then be shown that:

(73)

$$t_{p,2}^R - t_{p,1} = \frac{t_{p,2} - t_{p,1}}{p_{\text{sub.p}} + 1} + \frac{1+2}{p_{\text{sub.p}} + 1} p_{\text{sub.p}} - \frac{T_p}{p_{\text{sub.p}} + 1} - p_{p,2}, \text{ Math. } t_{p,2}^R = t_{p,2} - \frac{p}{p_{\text{sub.p}} + 1} (t_{p,2} - t_{p,1} - T_p - p_{p,2}) + p_{\text{sub.p}} - T_p - p_{p,2},$$

where $\tau_{\text{sub.p},2}$ is the error in the detection of the frame start time at the anchor **401**. Using the fact that

$$(74) \frac{\tau_{\text{sub.p},2}^2}{p_{\text{sub.p}}} \approx 0 \text{ and } p_{p,1} \ll t_{p,2}^R - t_{p,1}^R,$$

the following can be determined:

$$(75) 0t_{p,2}^R \approx t_{p,2} - T_{p,1}^{sw} + T_p - t_{p,2}$$

where

$$(76) T_{p,1}^{sw} = t_{p,2} - t_{p,1}^R$$

is the switching time between the reception of the p-th CSI acquisition request frame **501** and transmission of the p-th CSI acquisition response frame **502** as measured by the target device **402**.

(77) Using the STF and LTF of the CSI acquisition response frame **502**, and the pilot sub-carriers within all the OFDM symbols of the frame, a very fine and accurate estimate of the carrier frequency offset— $\eta_{\text{sub.pf.sub.c}}$ can be obtained at the anchor **401** and used to compensate the intra-frame carrier phase rotation. After removing this intra-frame carrier phase rotation, the measured CSI (for $k \in \text{custom character}$) at the anchor **401** from the M.sub.2-th symbol of the CSI acquisition response frame **502** can be expressed as:

$$(78) H_{p,k}^2 = e^{j\phi_p} e^{j2\pi f_c(t_{p,2}^R - t_{p,1})} e^{j2\pi(1+\eta_{\text{sub.pf.sub.c}})f_{k,p,2}M_2T_s} e^{j2\pi(1+\eta_{\text{sub.pf.sub.c}})f_{k,p,2}M_2T_s} e^{j\frac{2\pi n_{p,2}}{N}},$$

where ϕ_p is an unknown phase that models the aggregate asymmetry between the transmit and receive chains of the anchor **401** and the target device **402**.

(79) Using the fact that $\eta_{\text{sub.p,sub.2}} \approx 0$, and $f_{\text{sub.cp.sub.p}}$, $f_{\text{sub.kt.sub.p,2}}$, $f_{\text{sub.kM.sub.2T.sub.s}}$ are typically much smaller than $1/\eta_{\text{sub.p}}$, the measured CSI can be approximated as:

$$(80) H_{p,k}^2 \approx e^{j\phi_p} e^{j2\pi f_c(t_{p,2}^R - t_{p,1})} e^{j2\pi(1+\eta_{\text{sub.pf.sub.c}})f_{k,p,2}M_2T_s} e^{j\frac{2\pi n_{p,2}}{N}},$$

where

$$(81) T_{p,2}^{sw} = t_{p,2}^R - t_{p,1}$$

is the switching time between the reception of the p-th CSI acquisition response frame **502** and transmission of the p-th CSI acquisition request frame **501** as measured by the anchor **401**. Note that this CSI can be used to obtain an estimate

$$(82) \hat{\eta}_{p,2} \text{ of } \eta_{p,2} \text{ and } \hat{\eta}_{p,2} \text{ of } \text{mod}\{2\pi f_c T_{p,2}^{sw} - \frac{2\pi n_{p,2}}{N}, 2\pi\}$$

at the anchor **401**.

(83) In order to perform Wi-Fi based fine ranging by exploiting carrier phase information, a ranging device (which can represent the anchor **401**, the target device **402**, or another ranging device) performs multiple operations. Each of the operations will now be described, and the overall processes that include the operations will be described later.

(84) Operation 1: Coarse Estimation of the Crystal Offset Factor η

(85) In Operation 1, the crystal offset factor η , which represents the offset between the target device **402**'s crystal oscillator and the anchor **401**'s crystal oscillator, is estimated and stored. In some embodiments, this estimation operation may be skipped. In some embodiments, this estimation operation can be performed based on a trigger condition such as, for example, whenever a CSI acquisition frame is received or transmitted. Note that as shown in FIG. 6, each CSI acquisition packet has a STF, a LTF and several OFDM symbols each carrying some pilot subcarriers. Using a combination of the fields and the pilot subcarriers in the p-th CSI acquisition request frame, a fine estimate of the carrier frequency offset between the target device **402** and the anchor **401** can be obtained at the target device **402** as $\{\text{circumflex over (f)}\}_{\text{sub.p,1.sup.CFO}}$. The target device **402** can then obtain an estimate of the crystal offset factor as:

$$(86) \hat{\eta}_{p,1} = \hat{f}_{p,1}^{\text{CFO}} / f_c.$$

In some embodiments, a smoothing filter can further be applied to average over the past estimates and thus improve the accuracy. For example, this can be given as:

$$(87) \hat{\eta}_{p,1} = \text{Math.p}_{q=p-A} \frac{\hat{f}_{p,1}^{\text{CFO}}}{(A+1)f_c} \text{ or } \hat{\eta}_{p,1} = \left(\frac{\hat{f}_{p,1}^{\text{CFO}}}{f_c} \right) + (1 - \text{ })^{\wedge}_{p-1,1}$$

(88) Similarly, using a combination of the fields and the pilot subcarriers in the p-th CSI acquisition response frame, a fine estimate of the carrier frequency offset between the anchor **401** and the target device **402** can be obtained at the anchor **401** as $\{\text{circumflex over (f)}\}_{\text{sub.p,2.sup.CFO}}$. The anchor **401** can then obtain an estimate of the crystal offset factor as

$$(89) \hat{\eta}_{p,2} = \hat{f}_{p,2}^{\text{CFO}} / f_c.$$

In some embodiments, a smoothing filter can further be applied to average over the past estimates and thus improve the accuracy, such as described above.

Operation 2: Estimation of the CSI Phase Parameters

(90) In Operation 2, the slope and y-intercept of the CSI phase obtained from the CSI acquisition request frame

501 and the CSI acquisition response frame **502** can be estimated at the target device **402** and the anchor **401**, respectively. In some embodiments, this estimation can be performed based on a trigger condition such as, for example, whenever a CSI acquisition frame is received or transmitted. Note that as shown above, if there is an error of $\tau_{p,1}$ in the estimation of the packet reception time for the p -th CSI acquisition request frame **501**, then the corresponding CSI has the form:

$$(91) H_{p,k}^1 \approx e^{j2\pi f_c \tau_{p,1}} e^{-j2\pi f_k \tau_{p,1}} e^{j2\pi \frac{n_{p,1}}{N}}$$

(92) In other words, the CSI has a linearly varying slope as a function of $k \in \text{custom character}$, as depicted in FIGS. **8A** and **8B**.

(93) FIGS. **8A** and **8B** illustrate charts **801** and **802** showing the effect of the packet start time error on the phase of CSI at the target device **402** and the anchor **401**, according to various embodiments of the present disclosure. In FIG. **8A**, the chart **801** shows the phase of CSI as a function of the subcarrier index k at the target device **402**. In FIG. **8A**, the chart **802** shows the phase of CSI as a function of the subcarrier index k at the anchor **401**. In both cases, the CSI has a linearly varying slope as a function of k .

(94) Correspondingly, estimates $\{\hat{\tau}\}_{p,1}$, $\{\hat{\psi}\}_{p,1}$ of $\tau_{p,1}$ and carrier phase

$$(95) 0_{p,1} \triangleq \text{mod}\{2\pi f_c \tau_{p,1} + \pi - \frac{2\pi n_{p,1}}{N}, 2\pi\},$$

respectively, can be obtained at the target device **402** from

$$(96) \{H_{p,k}^1, \text{Math. } k \in \text{custom character}\}$$

using an algorithm such as Algorithm 1 shown below. Using the same algorithm, estimates

$$(97) \hat{\tau}_{p,2}, \hat{\psi}_{p,2} \text{ of } \tau_{p,2} \text{ and } \psi_{p,2} \triangleq \text{mod}\{2\pi f_c \tau_{p,2} - 2\pi n_{p,2} T_{p,2}^{\text{sw}} - \pi - \frac{2\pi n_{p,2}}{N}, 2\pi\},$$

respectively, can be estimated at the anchor **401** from

$$(98) \{H_{p,k}^2, \text{Math. } k \in \text{custom character}\}.$$

Algorithm 1: Inputs: Complex channel inputs from all subcarriers $\{H_{p,k} | k \in \text{custom character}\}$. Optional Inputs: Complex channels and their phase-outputs from past A CSI frames: $\{\hat{\tau}\}_{p,q}$, $\{\hat{\psi}\}_{p,q}$ $\{H_{q,k} | k \in \text{custom character}\}$ for $q=p-A, \dots, p-1$. Perform one of the following estimation methods: 1. Perform root-MUSIC estimation on $H_{p,k}$ to obtain the dominant delays of the channel. Set the largest delay or the first dominant delay to $\{\hat{\tau}\}_{p,p}$ and estimate:

$$(99) \hat{\tau}_{p,p} = -\text{angle}\{ \text{Math. } k \in \text{custom character} H_{p,k} e^{j2\pi f_k \hat{\tau}_{p,p}} \}$$

$$(100) \hat{\psi}_{p,p} = \text{argmin}_{k \in \text{custom character}} \{ \text{Math. } (\angle H_{p,k} + 2\pi f_k \hat{\tau}_{p,p})^2 \}$$

$$(101) \hat{\tau}_{p,p} = \text{argmin}_{k \in \text{custom character}} \{ \text{Math. } (\angle H_{p,k} + 2\pi f_k \hat{\tau}_{p,p})^2 \}, \text{ where the weight can be, for example:}$$

$$(102) w_k = \text{Math. } H_{p,k} \text{ Math. }^2 \text{ or } w_k = \frac{1}{A+1} \text{ Math. }^p_{q=p-A} \text{ Math. } H_{q,k} \text{ Math. }^2, \text{ etc. 4. Compute } B_{p,k}$$

$$(103) B_k = \frac{1}{A} \text{ Math. }^{p-1}_{q=p-A} H_{q,k} e^{j[2\pi f_k \hat{\tau}_{q,p} + \hat{\psi}_{q,p}]}$$

$$(104) \hat{\tau}_{p,p} = \text{argmin}_{k \in \text{custom character}} \{ \text{Math. } \text{Math. } B_k^* H_{p,k} \text{ Math. } [\angle(B_k^* H_{p,k}) + 2\pi f_k \hat{\tau}_{p,p}]^2 \}$$

as the average CSI for the last A CSI acquisition request frames after performing the phase correction, i.e.,

$$(105) 0B_k = \frac{1}{A} \text{ Math. }^{p-1}_{q=p-A} H_{q,k} e^{j[2\pi f_k \hat{\tau}_{q,p} + \hat{\psi}_{q,p}]}$$

$$(106) \hat{\tau}_{p,p} = \text{argmax}_{k \in \text{custom character}} \{ \text{Math. } \text{Math. } B_k^* H_{p,k} e^{j2\pi f_k \hat{\tau}_{p,p}} \text{ Math. } , \hat{\psi}_{p,p} = -\text{angle}\{ \}$$

$\{\hat{\tau}\}_{p,p}$, $\{\hat{\psi}\}_{p,p}$

Operation 3: Sharing of the Ranging Parameters

(107) In some embodiments, the target device **402** measures $t_{p,1}$, $t_{p,2}$ and estimates $\eta_{p,1}$, $\{\hat{\tau}\}_{p,1}$, $\{\hat{\psi}\}_{p,1}$ using Operations 1 and 2 above and then stores them. Similarly, the anchor **401** measures $t_{p,1}$, $t_{p,2}$ and estimates $\eta_{p,2}$, $\{\hat{\tau}\}_{p,2}$, $\{\hat{\psi}\}_{p,2}$ using Operations 1 and 2 above and stores them. In some embodiments, Operation 1 may be skipped by either the target device **402** or the anchor **401**, and they may use a pre-determined value such as $\eta_{p,1}=0$ or $\eta_{p,2}=0$, respectively. These values are then subsequently shared to a ranging device that is responsible for performing the range estimation. Such a ranging device can be the anchor **401**, the target device **402**, or any other suitable device. The condition for sharing the parameters can be a trigger. For example, the trigger can be after each CSI acquisition request/response frames exchange is complete, or it can be after a batch of multiple CSI acquisition request/response frame exchanges are complete.

(108) In some embodiments, the target device **402** and/or the anchor **401** may not store, or they may not transmit, the values of $\eta_{\text{sub.p},1}$ and/or $\eta_{\text{sub.p},2}$ to the ranging device. In some embodiments, where the ranging device is the target device **402**, the parameters to be shared from the anchor **401** can be encoded within the CSI acquisition response frame **502**. In some embodiments, when sharing the parameters, an identifier field may also be included to uniquely identify the anchor **401** and the target device **402** to which the parameters belong. Such an identifier can be, for example, the MAC address of either device. In some embodiments, the frame index p may also be included when sharing the information to indicate the sequence number of the measurements. In some embodiments, the anchor **401** and/or the target device **402** may also determine the type of RTT estimation algorithms that should be used and may include the determined result in the information shared with the ranging device.

(109) Operation 4: Fine Estimation of Crystal Offset Factor

(110) In some embodiments, this operation may be simplified, and the fine crystal offset factor $\eta_{\text{sub.p}}$ may be set as

$$(111) \hat{\eta}_{\text{sub.p}} = \frac{\hat{\eta}_{\text{sub.p},1} + \hat{\eta}_{\text{sub.p},2}}{2}.$$

In some embodiments, when the values of $\eta_{\text{sub.p},1}$ and/or $\eta_{\text{sub.p},2}$ are not shared with the ranging device, the ranging device may use a predetermined value (such as 0) for the missing value. In some embodiments, the CSI acquisition request frame **501** can be kept as a long frame to ensure that the estimate of $\eta_{\text{sub.p},1}$ has higher precision. In some embodiments, depending on the size or length of the CSI acquisition request frame **501** and the CSI acquisition response frame **502**, the precision of the frequency offset estimates $\eta_{\text{sub.p},1}$ and $\eta_{\text{sub.p},2}$ can be different. Correspondingly, a weighted combination of the two frequency offset estimates can be used, i.e., use

$$(112) \hat{\eta}_{\text{sub.p}} = \hat{\eta}_{\text{sub.p},1} + (1 - \alpha) \hat{\eta}_{\text{sub.p},2} \text{ instead of } \frac{\hat{\eta}_{\text{sub.p},1} + \hat{\eta}_{\text{sub.p},2}}{2}.$$

(113) In some embodiments, the precision of $\{\text{circumflex over } (\eta)\}_{\text{sub.p}}$ from above may be insufficient and a further estimation step may be performed using the values of $\{\text{circumflex over } (\psi)\}_{\text{sub.p},1}$, $\{\text{circumflex over } (\psi)\}_{\text{sub.p},2}$, $t_{\text{sub.p},1}$, $t_{\text{sub.p},2,\text{sup.R}}$ that are accumulated over a window of time $W=0.5$ s (or another suitable length of time). This estimation step can be based on the observation that:

$$(114) N(\hat{\eta}_{\text{sub.p},1} - \hat{\eta}_{\text{sub.p},2} - \hat{\eta}_{\text{sub.p-1},1} + \hat{\eta}_{\text{sub.p-1},2}) = \text{mod}\{2 N f_c [\hat{\eta}_{\text{sub.p},2} (t_{p,2}^R - t_{p-1,2}^R) + \hat{\eta}_{\text{sub.p-1},1} (t_{p,1} - t_{p-1,1})]\},$$

and noting that $\eta_{\text{sub.p}}$ remains almost the same for W time. In one example, this estimation may be performed using an algorithm such as Algorithm 2 shown below:

Algorithm 2: Inputs: $\{\text{circumflex over } (\psi)\}_{\text{sub.p},1}$, $\{\text{circumflex over } (\psi)\}_{\text{sub.p},2}$, $t_{\text{sub.p},1}$, $t_{\text{sub.p},2,\text{sup.R}}$, $\{\text{circumflex over } (\eta)\}_{\text{sub.p}}$ for $p=1, \dots, P$.

$W=0.5$ secs.

$T_{\text{sub.max}}=1$ ms.

$W_{\text{sub.max}} = \lceil (t_{\text{sub.p},1} - t_{\text{sub.p-1},1}) / W \rceil$.

$Q = \{ \}$. For $w=1:1:W_{\text{sub.max}}$

$T_{\text{sub.st}} = t_{\text{sub.p},1} + (w-1)W$.

$T_{\text{sub.end}} = t_{\text{sub.p},1} + wW$.

$Q = \{1 \leq p \leq P \mid T_{\text{sub.st}} \leq t_{\text{sub.p},1} \leq T_{\text{sub.end}}, |t_{\text{sub.p},1} - t_{\text{sub.p-1},1}| < T_{\text{sub.max}}\}$. //Here the $T_{\text{sub.max}}$ limit can be to ensure that the variation in $\eta_{\text{sub.p}}$ over the window of W can be neglected. Compute:

$$(115) f_{\text{opt}} = \underset{\substack{\text{Math. } f_{\text{sub.p}} \leq F}}{\text{argmax}}_{p \in Q} \text{Re}\{ \text{Math. } p \in Q e^{jN(\hat{\eta}_{\text{sub.p},1} - \hat{\eta}_{\text{sub.p},2} - \hat{\eta}_{\text{sub.p-1},1} + \hat{\eta}_{\text{sub.p-1},2})} e^{-j2 N(f_{\text{sub.p}} + \hat{f}_{\text{sub.p}})[t_{p,2}^R - t_{p-1,2}^R + t_{p,1} - t_{p-1,1}]} \}$$

$$\hat{\eta}_{\text{sub.p}} = \hat{\eta}_{\text{sub.p}} + f_{\text{opt}} / f_c \text{ for all } p \in Q. \bar{Q} = \bar{Q} \cup Q. \text{ EndFor For } p \in \{1, \dots, P\} \setminus Q \text{ Set } \{\text{circumflex over } (\eta)\}_{\text{sub.p}}$$

by performing linear interpolation of $\{\text{circumflex over } (\eta)\}_{\text{sub.q}}$ values from $q \in Q$ EndFor Outputs: $\{\text{circumflex over } (\eta)\}_{\text{sub.p}}$

Operation 5: Coarse RTT Estimation

(116) In this operation, the frame transmission times $t_{\text{sub.p},1}$, $t_{\text{sub.p},1,\text{sup.R}}$, $t_{\text{sub.p},2}$ and $t_{\text{sub.p},2,\text{sup.R}}$ along with the estimated parameters $\{\text{circumflex over } (\tau)\}_{\text{sub.p},1}$, $\{\text{circumflex over } (\tau)\}_{\text{sub.p},2}$ are then used by the ranging device to obtain a coarse estimate of the round-trip time. In one embodiment, the RTT can be estimated as:

$$(117) p = (t_{p,2}^R - t_{p,1} + \hat{\eta}_{\text{sub.p},2}) - (t_{p,2} - t_{p,1}^R + \hat{\eta}_{\text{sub.p},1}) + \hat{\eta}_{\text{sub.p}} T_{p,1}^{\text{sw}},$$

where

$$(118) T_{p,1}^{\text{sw}} = t_{p,2} - t_{p,1}^R.$$

Using the equations for $t_{\text{sub.p},1,\text{sup.R}}$ and $t_{\text{sub.p},2,\text{sup.R}}$ this can be further expressed as:

$$(119) \bar{p} = 2 \bar{p} - (\bar{p} - \hat{p}) T_{p,1}^{sw} + (\bar{p}_{,1} - \hat{p}_{,1}) + (\bar{p}_{,2} - \hat{p}_{,2})$$

(120) Note that $2\bar{p}_{.sub.p}$ is the true $RTT_{.sub.p}$ while the other terms are the residual errors. In some embodiments, to reduce the impact of the second term $(\Delta\eta_{.sub.p})T_{.sub.p,1}^{sup.sw}$ the value of $T_{.sub.p,1}^{sup.sw}$ can be minimized by selecting the CSI acquisition response frame **502** as the ACK frame sent for the CSI acquisition request frame **501**. In this case, the value of $T_{.sub.p,1}^{sup.sw}$ is equal to the duration of the CSI acquisition request frame **501** plus a short interframe spacing duration of 10 μs . In some embodiments, the CSI acquisition request frame **501** can be a Null Data Packet (NDP) to keep its duration also short.

(121) Operation 6: Fine RTT Estimation

(122) In some embodiments, the use of Fine RTT estimation to improve the coarse RTT estimate is optional and can be determined by the ranging device based on the reported parameters from the anchor **401** and/or the target device **402**. For example, the condition to perform fine RTT estimation can be based on (i) the RSSI between the anchor **401** and the target device **402** being above a threshold, or (ii) there being a strong static path in the CSI measured by either device **401** and **402**, or (iii) the Rician K-factor of the measured CSI being above a threshold, or (iv) there being a running application that needs the fine RTT estimates. In some embodiments, the anchor **401** and/or the target device **402** may make the determination of whether to use the fine RTT estimation operation and may include the determination in the list of parameters shared with the ranging device. When the fine RTT estimation operation is used, the ranging device may add together the estimates $\{\text{circumflex over } (\psi)\}_{.sub.p,1}$ and $\{\text{circumflex over } (\psi)\}_{.sub.p,2}$ to obtain the sum carrier phase:

$$(123) \bar{p} = N[\hat{p}_{,1} + \hat{p}_{,2} + \hat{p}^2 f_c T_{p,2}^{sw}],$$

where

$$(124) 0T_{p,2}^{sw} = t_{p,2}^R - t_{p,1}.$$

Using the equations for $\{\text{circumflex over } (\psi)\}_{.sub.p,1}$, $\{\text{circumflex over } (\psi)\}_{.sub.p,2}$ it can be shown that:

$$(125) \bar{p} = \text{mod}\{4 N f_c \bar{p} - N^2 N(\hat{p} - \hat{p}) f_c T_{p,2}^{sw} + N(\hat{p}_{,1} - \hat{p}_{,1}) + N(\hat{p}_{,2} - \hat{p}_{,2}), 2\}.$$

(126) By comparing $\psi_{.sub.p}$ to $\psi_{.sub.p-1}$, the incremental distance moved can be estimated as:

$$(127) \bar{p} - \bar{p}_{-1} \approx \text{mod}\{4 N f_c (\hat{p} - \hat{p}_{-1}), 2\},$$

where the error terms are ignored for convenience. As long as $|\bar{p}_{.sub.p} - \bar{p}_{.sub.p-1}|$ is smaller than

$$(128) \frac{1}{4Nf_c},$$

the change in propagation delay can be estimated as $(\psi_{.sub.p} - \psi_{.sub.p-1})/4\pi Nf_{.sub.c}$.

(129) In some embodiments, the anchor **401** and the target device **402** may make such CSI acquisition frame exchanges over L frequencies of operation: $f_{.sub.c}^{sup.(1)}$, $f_{.sub.c}^{sup.(2)}$, $\dots$, $f_{.sub.c}^{sup.(L)}$. An example of this can be in the multi-link operation devices provided by IEEE 802.11be. In such a case, multiple observations can be obtained as:

$$(130) \bar{p}^{(\ell)} - \bar{p}_{-1}^{(\ell)} \approx \text{mod}\{4 N f_c^{(\ell)} (\hat{p} - \hat{p}_{-1}), 2\},$$

for $1 \leq \text{custom character} \leq L$. These multiple L measurements can then be used to uniquely identify the value of $\bar{p}_{.sub.p} - \bar{p}_{.sub.p-1}$ even if $|\bar{p}_{.sub.p} - \bar{p}_{.sub.p-1}|$ is larger than

$$(131) \frac{1}{4Nf_c},$$

by using, for example, the Chinese remainder theorem. A similar result can also be obtained in a single link case, by frequency hopping across L different carrier frequencies.

(132) Note that the resolution of distance in the relative phase measurements $\psi_{.sub.p} - \psi_{.sub.p-1}$ is proportional to $1/f_{.sub.c}$, which can be orders of magnitude finer than the resolution of Operation 5, which can then be used in either of the below embodiments to refine the coarse RTT estimate.

(133) In various embodiments, using such relative phase measurements between adjacent CSI acquisition frame exchanges, the coarse RTT estimates from Operation 5 from adjacent CSI acquisition frame exchanges can be combined to improve the estimation accuracy. As an example, some such fine RTT estimation methods can be one or more of the following:

$$(134) \bar{RTT}_p = +(1 - \lambda)(\bar{p} - 1 + \frac{\bar{p} - \bar{p}_{-1}}{2 N f_c}), \quad \text{where } 0 \leq \lambda \leq 1 \text{ is the weight for current coarse RTT estimate.}$$

$$(135) \bar{RTT}_p = +(1 - \lambda)(\bar{RTT}_{p-1} + \frac{\bar{p} - \bar{p}_{-1}}{2 N f_c}), \quad \text{where } 0 \leq \lambda \leq 1 \text{ is the weight for current coarse RTT estimate.}$$

(136) $\bar{RTT}_p = \text{Math.}_{q=p-A}^p \bar{p}_{-q}$, where $\text{Math.}_{a=0}^A a = 1$ are weights for different neighboring coarse RTT estimates. Note that this embodiment may not require computation of $\psi_{.sub.p}$, $\psi_{.sub.p-1}$. Another method can be used to feed

$$(137) \bar{p} \text{ and } \frac{\bar{p} - \bar{p}_{-1}}{2 N f_c} \text{ independently as the range and velocity estimates to a Kalman filter or a particle filter}$$

x axis are not equally spaced (i.e., not periodically transmitted). As a result, the plot lines **921-923** do not pass through a plot point at each transmission time. Thus, the plot lines **921-923** can be rejected as possible candidates. Only the plot line **924** passes through a plot point at each transmission time. Thus, the plot line **924** is the only likely candidate, and the estimate of $\{\text{circumflex over } (v)\}$ can be determined by the slope of the plot line **924** with little or no ambiguity.

(150) Operation 7: Conversion to Range Estimation

(151) Using the estimate of RTT, the range estimate  can be obtained as:

$$(152) \hat{p} = (3 \times 10^8) \bar{RTT}_p / 2$$

(153) FIG. **10** illustrates a process **1000** of an anchor **401** performing Wi-Fi based fine ranging according to various embodiments of the present disclosure. At step **1001**, the anchor **401** may receive a trigger indicating to start the ranging process **1000**. Such a trigger can be sent by the target device **402** or the ranging device, or can be generated from another algorithm within the anchor **401**, for example. As an example, the trigger condition can be the RSSI between the target device **402** and anchor **401** being higher than a certain value. At step **1003**, upon receiving the trigger, the anchor **401** may start transmitting the CSI acquisition request frames at the appropriate transmission times. At step **1005**, for each such request frame, the anchor **401** may receive a CSI acquisition response frame. At step **1007**, upon receipt of the CSI acquisition response frame, the anchor **401** may perform Operations 1 and 2 to obtain estimates $\eta_{\text{sub.p},2}$, $\{\text{circumflex over } (\tau)\}_{\text{sub.p},2}$, $\{\text{circumflex over } (\psi)\}_{\text{sub.p},2}$. At step **1009**, at the appropriate time, some of these estimates along with the time values $t_{\text{sub.p},1}$, $t_{\text{sub.p},2,\text{sup.R}}$ may be transmitted to the ranging device. The anchor **401** may then continue to transmit the following CSI acquisition request frame at the appropriate time. Upon receiving an external trigger, the transmission of the request frames may be halted at step **1011**.

(154) FIG. **11** illustrates a process **1100** of a target device **402** performing Wi-Fi based fine ranging according to various embodiments of the present disclosure. The target device **402** may receive a trigger indicating to start the ranging process **1100**. Such a trigger can be sent by the anchor **401** or the ranging device, for example, or can even just be the receipt of a CSI acquisition request frame from the anchor. At step **1101**, upon receiving a CSI acquisition request frame, the target device **402** may store the reception time. At step **1103**, the target device **402** may use the received CSI acquisition request frame to obtain estimates of $\eta_{\text{sub.p},1}$, $\{\text{circumflex over } (\tau)\}_{\text{sub.p},1}$, $\{\text{circumflex over } (\psi)\}_{\text{sub.p},1}$ using Operations 1 and 2. At step **1105**, in response to the CSI acquisition request frame, the target device **402** may also transmit a CSI acquisition response frame. At step **1107**, at the appropriate time, some of these estimates $\eta_{\text{sub.p},1}$, $\{\text{circumflex over } (\tau)\}_{\text{sub.p},1}$, $\{\text{circumflex over } (\psi)\}_{\text{sub.p},1}$ along with the time values $t_{\text{sub.p},1,\text{sup.R}}$, $t_{\text{sub.p},2}$ may be transmitted to the ranging device. The target device **402** may then continue to wait for future CSI acquisition request frames. Upon receiving an external trigger, it may halt listening for or responding to CSI acquisition request frames.

(155) FIG. **12** illustrates a process **1200** of a ranging device performing Wi-Fi based fine ranging according to various embodiments of the present disclosure. At step **1201**, upon receipt of an external trigger, the ranging device may initiate the ranging process **1200**. The trigger may contain an indication for performing carrier-phase based measurement. Upon receipt of the trigger, the ranging device may perform a carrier phase based measurement based on the indication in the trigger. Such a trigger can be some external condition or just the receipt of the CSI acquisition parameters from the anchor **401** and/or the target device **402**. The ranging device may further trigger the anchor **401** or the target device **402** to begin the CSI acquisition frame exchanges. At step **1203**, the ranging device may obtain some of the estimated and stored parameters $t_{\text{sub.p},1,\text{sup.R}}$, $t_{\text{sub.p},2}$, $\eta_{\text{sub.p},1}$, $\{\text{circumflex over } (\tau)\}_{\text{sub.p},1}$, $\{\text{circumflex over } (\psi)\}_{\text{sub.p},1}$ from the target device **402** and $t_{\text{sub.p},1}$, $t_{\text{sub.p},2,\text{sup.R}}$, $\eta_{\text{sub.p},2}$, $\{\text{circumflex over } (\tau)\}_{\text{sub.p},2}$, $\{\text{circumflex over } (\psi)\}_{\text{sub.p},2}$ from the anchor **401**. It may also obtain identifier information and sequence number information to uniquely identify the device pair and the sequence number of the frame exchange. At step **1205**, the ranging device may perform Operation 4 to obtain a finer estimate of the crystal offset factor $\{\text{circumflex over } (\eta)\}_{\text{sub.p}}$ using the acquired information. At step **1207**, the ranging device may perform Operation 5 to get a coarse estimate of the RTT. At step **1209**, the ranging device may optionally perform Operation 6 to get a fine estimate of the RTT. For example, the condition to perform fine estimation can be based on the RSSI between the anchor **401** and the target device **402** being above a threshold or there being a strong static path in the CSI measured by either of them or there being a running application that needs the fine RTT estimates. At step **1211**, the ranging device may perform Operation 7 to convert the RTT estimate to a range estimate and forward the range information to another application, such as a localization engine. At step **1213**, the ranging device may receive an external trigger to stop the ranging process. The ranging device may further trigger the target device **402** or the anchor **401** to stop the CSI acquisition frame exchanges.

(156) Note that although the embodiments above were described assuming that the CSI Acquisition request

frame is sent by the anchor **401** and the response is sent by the target device **402**, the above embodiments are equally applicable if the CSI acquisition request frame is sent by the target device **402** and the response is then sent by the anchor **401**. Thus, this description is only for illustration and should not be construed as a limitation of the current disclosure.

(157) In some embodiments, after Operation 4, the ranging device may only be interested in measuring either of the following: the differential range $\varphi_{p,1} - \varphi_{p,2}$, which is the change in the absolute range $\varphi_{p,1}$ between adjacent measurements, or the relative range $\varphi_{p,1} - \varphi_{p,2}$, which is the change in the absolute range $\varphi_{p,1}$ over an interval of time.

(158) In this case, after Operation 4, the ranging device may directly obtain the sum phase according to the following:

$$\varphi_p = N[\varphi_{p,1} + \varphi_{p,2} + \varphi_p^2 f_c T_{p,2}^{sw}].$$

(160) These can be used, for example, for direction finding, velocity estimation, gesture recognition, triangulation-based localization, and the like. Additionally, the differential range can be estimated as:

$$\varphi_p = (3 \times 10^8) \frac{\text{mod}\{\varphi_p - \varphi_{p-1} + \varphi_{p,2}\}}{4 N f_c}.$$

(162) In some embodiments, a motion model can be used for the user to estimate the differential range as:

$$\varphi_p = S_p(t_{p,1} - t_{p-1,1}), \text{ where:}$$

$$S_p = \underset{\text{Math. } s \cdot \text{Math. } \leq S_{\max}}{\text{argmax}} \cdot \text{Math. } q \in \varphi_p e^{j(\varphi_p - \varphi_q)} e^{\frac{j4 \cdot N f_c S[t_{p,1} - t_{q,1}]}{3 \times 10^8}} \cdot \text{Math. } , \text{ and}$$

$$\varphi_p = \{1 \leq q \leq P \cdot \text{Math. } \cdot \text{Math. } t_{q,1} - t_{p,1} \cdot \text{Math. } \leq 0.25\}.$$

(164) Finally, the estimate the relative range can be obtained as:

$$\varphi_p = \text{Math. } q=2 (3 \times 10^8) \frac{\text{mod}\{\varphi_p - \varphi_{p-1} + \varphi_{p,2}\}}{4 N f_c}.$$

(166) Experiments have been performed to test these embodiments. The experiments include both devices exhibiting slow movement (e.g., a speed < 50 mm/second) and devices exhibiting fast movement (e.g., a speed > 50 mm/second). Results from these experiments show that the disclosed embodiments are capable of providing differential and relative range estimation with mm-level accuracy in WiFi systems by tracking the carrier phase even in multi-path channels.

(167) Although FIGS. 4 through 12 illustrate example techniques for Wi-Fi based fine ranging and related details, various changes may be made to FIGS. 4 through 12. For example, various components in FIGS. 4 through 12 could be combined, further subdivided, or omitted and additional components could be added according to particular needs. In addition, while shown as a series of steps, various operations in FIGS. 4 through 12 could overlap, occur in parallel, occur in a different order, or occur any number of times. In another example, steps may be omitted or replaced by other steps.

(168) FIG. 13 illustrates a flow chart of a method **1300** for Wi-Fi based fine ranging by exploiting carrier phase information according to various embodiments of the present disclosure, as may be performed by one or more components of the wireless network **100** (e.g., the AP **101** or the STA **111**), which may represent an anchor **401**, a target device **402**, or a separate ranging device. The embodiment of the method **1300** shown in FIG. 13 is for illustration only. One or more of the components illustrated in FIG. 13 can be implemented in specialized circuitry configured to perform the noted functions or one or more of the components can be implemented by one or more processors executing instructions to perform the noted functions.

(169) As illustrated in FIG. 13, the method **1300** begins at step **1301**. At step **1301**, a device obtains Wi-Fi CSI parameters measured at an anchor and a target device from Wi-Fi frames transmitted between the anchor and the target device. The CSI parameters include, for each of the anchor and the target device, frame transmission and reception times, a carrier phase of the CSI, a crystal offset factor, and a packet detection time error. This could include, for example, the STA **111** obtaining Wi-Fi CSI parameters measured at the anchor **401** and the target device **402** from Wi-Fi frames transmitted between the anchor and the target device, such as by performing Operation 1, Operation 2, Operation 3, or a combination of two or more of these.

(170) In some embodiments, each crystal offset factor is estimated based on a carrier frequency offset (CFO) between the target device and the anchor. In some embodiments, each packet detection time error is estimated based on a slope angle of a phase of the CSI as a function of a subcarrier index. In some embodiments, each carrier phase of the CSI is estimated based on a phase of the CSI at a zero subcarrier. In some embodiments, the device performs Operation 4 to increase a precision of the crystal offset factor by using values of carrier phases and corresponding frame transmission and reception times accumulated over a time window.

(171) At step **1303**, the device determines a RTT estimate as a function of the CSI parameters. This could

include, for example, the STA **111** determining a RTT estimate as a function of the CSI parameters.

(172) In some embodiments, the device determines the RTT estimate by performing Operation 5 to estimate a coarse RTT estimate using the frame transmission and reception times and correcting for the packet detection time error and a crystal offset factor error. In some embodiments, the device further determines the RTT estimate by performing Operation 6 to estimate a relative change in the RTT estimate between adjacent frame exchanges using a sum carrier phase of the CSI, and combine the relative change in the RTT estimate with the coarse RTT estimate to obtain a fine RTT estimate. In some embodiments, the device estimates the relative change in the RTT estimate by estimating a velocity of the target device based on the sum carrier phase of the CSI obtained over the adjacent frame exchanges, and estimating the relative change in the RTT estimate based on the estimated velocity of the target device. In some embodiments, the sum carrier phase of the CSI is estimated by adding the carrier phase of the CSI measured at the anchor and the target device, and removing a component corresponding to the crystal offset factor and the frame transmission and reception times.

(173) At step **1305**, the device estimates a range between the anchor and the target device as a function of the RTT estimate. This could include, for example, the STA **111** performing Operation 7 to estimate a range between the anchor **401** and the target device **402** as a function of the RTT estimate. At step **1307**, the device transmits the estimated range to at least one of the anchor or the target device. This could include, for example, the STA **111** transmitting the estimated range to the anchor **401**, the target device **402**, or both.

(174) Although FIG. **13** illustrates one example of a method **1300** for Wi-Fi based fine ranging by exploiting carrier phase information, various changes may be made to FIG. **13**. For example, while shown as a series of steps, various steps in FIG. **13** could overlap, occur in parallel, occur in a different order, or occur any number of times.

(175) Although the present disclosure has been described with an exemplary embodiment, various changes and modifications may be suggested to one skilled in the art. It is intended that the present disclosure encompass such changes and modifications as fall within the scope of the appended claims. None of the description in this application should be read as implying that any particular element, step, or function is an essential element that must be included in the claims scope. The scope of patented subject matter is defined by the claims.

Claims

1. A method comprising: obtaining Wi-Fi channel state information (CSI) parameters measured at an anchor and a target device from Wi-Fi frames transmitted between the anchor and the target device, the CSI parameters comprising, for each of the anchor and the target device, frame transmission and reception times, a carrier phase of the CSI, a crystal offset factor, and a packet detection time error, wherein each crystal offset factor is estimated based on a carrier frequency offset (CFO) between the target device and the anchor; determining a round trip time (RTT) estimate or a relative change in the RTT estimate as a function of the CSI parameters; and estimating a range between the anchor and the target device as a function of the RTT estimate, or estimating a change in the range between the anchor and the target device as a function of the relative change in the RTT estimate.
2. The method of claim 1, wherein determining the RTT estimate further comprises: estimating a coarse RTT estimate using the frame transmission and reception times and correcting for the packet detection time error and a crystal offset factor error; and combining the relative change in the RTT estimate with the coarse RTT estimate to obtain a fine RTT estimate.
3. The method of claim 1, wherein determining the relative change in the RTT estimate further comprises: estimating the relative change in the RTT estimate between adjacent frame exchanges using a sum carrier phase of the CSI.
4. The method of claim 3, wherein estimating the relative change in the RTT estimate comprises: estimating a velocity of the target device based on the sum carrier phase of the CSI obtained over the adjacent frame exchanges; and estimating the relative change in the RTT estimate based on the estimated velocity of the target device.
5. The method of claim 3, wherein the sum carrier phase of the CSI is estimated by adding the carrier phase of the CSI measured at the anchor and the target device, and removing a component corresponding to the crystal offset factor and the frame transmission and reception times.
6. The method of claim 1, wherein: each packet detection time error is estimated based on a slope angle of a phase of the CSI as a function of a subcarrier index; and each carrier phase of the CSI is estimated based on a phase of the CSI at a zero subcarrier.
7. The method of claim 1, further comprising: increasing a precision of the crystal offset factor by using values

of carrier phases and corresponding frame transmission and reception times accumulated over a time window.

8. The method of claim 1, wherein obtaining the CSI parameters comprises one of: measuring the CSI parameters at the target device and receiving the CSI parameters from the anchor; measuring the CSI parameters at the anchor and receiving the CSI parameters from the target device; or receiving the CSI parameters from both the target device and the anchor.

9. The method of claim 1, further comprising: transmitting the estimated range to at least one of the anchor or the target device.

10. A device comprising: a transceiver; and a processor operably connected to the transceiver, the processor configured to: obtain Wi-Fi channel state information (CSI) parameters measured at an anchor and a target device from Wi-Fi frames transmitted between the anchor and the target device, the CSI parameters comprising, for each of the anchor and the target device, frame transmission and reception times, a carrier phase of the CSI, a crystal offset factor, and a packet detection time error, wherein each crystal offset factor is estimated based on a carrier frequency offset (CFO) between the target device and the anchor; determine a round trip time (RTT) estimate or a relative change in the RTT estimate as a function of the CSI parameters; and estimate a range between the anchor and the target device as a function of the RTT estimate, or estimate a change in the range between the anchor and the target device as a function of the relative change in the RTT estimate.

11. The device of claim 10, wherein to determine the RTT estimate, the processor is further configured to: estimate a coarse RTT estimate using the frame transmission and reception times and correct for the packet detection time error and a crystal offset factor error; and combine the relative change in the RTT estimate with the coarse RTT estimate to obtain a fine RTT estimate.

12. The device of claim 10, wherein to determine the relative change in the RTT estimate, the processor is further configured to: estimate the relative change in the RTT estimate between adjacent frame exchanges using a sum carrier phase of the CSI.

13. The device of claim 12, wherein to estimate the relative change in the RTT estimate, the processor is configured to: estimate a velocity of the target device based on the sum carrier phase of the CSI obtained over the adjacent frame exchanges; and estimate the relative change in the RTT estimate based on the estimated velocity of the target device.

14. The device of claim 12, wherein the processor is configured to estimate the sum carrier phase of the CSI by adding the carrier phase of the CSI measured at the anchor and the target device, and removing a component corresponding to the crystal offset factor and the frame transmission and reception times.

15. The device of claim 10, wherein: each packet detection time error is estimated based on a slope angle of a phase of the CSI as a function of a subcarrier index; and each carrier phase of the CSI is estimated based on a phase of the CSI at a zero subcarrier.

16. The device of claim 10, wherein the processor is further configured to: increase a precision of the crystal offset factor by using values of carrier phases and corresponding frame transmission and reception times accumulated over a time window.

17. The device of claim 10, wherein to obtain the CSI parameters, the processor is configured to perform one of: measure the CSI parameters at the target device and receive the CSI parameters from the anchor; measure the CSI parameters at the anchor and receive the CSI parameters from the target device; or receive the CSI parameters from both the target device and the anchor.

18. The device of claim 10, wherein the processor is further configured to: transmit the estimated range to at least one of the anchor or the target device.

19. A non-transitory computer readable medium comprising program code that, when executed by a processor of a device, causes the device to: obtain Wi-Fi channel state information (CSI) parameters measured at an anchor and a target device from Wi-Fi frames transmitted between the anchor and the target device, the CSI parameters comprising, for each of the anchor and the target device, frame transmission and reception times, a carrier phase of the CSI, a crystal offset factor, and a packet detection time error, wherein each crystal offset factor is estimated based on a carrier frequency offset (CFO) between the target device and the anchor; determine a round trip time (RTT) estimate or a relative change in the RTT estimate as a function of the CSI parameters; and estimate a range between the anchor and the target device as a function of the RTT estimate, or estimate a change in the range between the anchor and the target device as a function of the relative change in the RTT estimate.

20. The non-transitory computer readable medium of claim 19, wherein the program code to determine the RTT estimate further comprises program code to: estimate a coarse RTT estimate using the frame transmission and reception times and correct for the packet detection time error and a crystal offset factor error; and combine the relative change in the RTT estimate with the coarse RTT estimate to obtain a fine RTT estimate.

