

US Patent & Trademark Office

Patent Public Search | Text View

United States Patent	12413515
Kind Code	B1
Date of Patent	September 09, 2025
Inventor(s)	Iwasaki; Sean

Multi-functional device for communications networks and methods and systems utilizing same

Abstract

The present subject matter relates to methods, circuitry and equipment providing a multi-functional, cost effective, media independent, open platform device for communication services using differential signaling interfaces. The methods, circuitry and equipment comprise a plurality of input amplifiers, output amplifiers, and retimers. A non-blocking cross-point switch may be used to switch any differential signals from the cross-point switch input to output. The device aggregates communication services from a plurality of lower service capacity connectors and interfaces to a single higher capacity connector and interfaces. The device can establish a demarcation point with a single device capable of supporting any communication services, any physical media interfaces, from any location.

Inventors:	Iwasaki; Sean (Chicago, IL)
Applicant:	Iwasaki; Sean (Chicago, IL)
Family ID:	74566805
Appl. No.:	18/224120
Filed:	July 20, 2023

Related U.S. Application Data

continuation parent-doc US 17699427 20220321 US 11750511 child-doc US 18224120
continuation parent-doc US 17004299 20200827 US 11283710 20220322 child-doc US 17699427
continuation parent-doc US 15687862 20170828 US 10637776 20200428 child-doc US 16839260
continuation parent-doc US 15294858 20161017 US 10446909 20191015 child-doc US 16415899
continuation-in-part parent-doc US 16917475 20200630 US 11444870 20220913 child-doc US 17004299
continuation-in-part parent-doc US 16839260 20200403 US 11431625 20220830 child-doc US 16917475
continuation-in-part parent-doc US 16415899 20190517 US 10985440 20210420 child-doc US

16917475
us-provisional-application US 62905852 20190925
us-provisional-application US 62381168 20160830
us-provisional-application US 62243957 20151020

Publication Classification

Int. Cl.: **H04L45/60** (20220101); **H04L49/00** (20220101); **H04L49/109** (20220101); **H04L49/35** (20220101)

U.S. Cl.:

CPC **H04L45/60** (20130101); **H04L49/109** (20130101); **H04L49/30** (20130101); **H04L49/355** (20130101);

Field of Classification Search

CPC: H04L (45/60); H04L (49/109); H04L (49/30); H04L (49/355)

References Cited

U.S. PATENT DOCUMENTS

Patent No.	Issued Date	Patentee Name	U.S. Cl.	CPC
2012/0069880	12/2011	Lemson	375/220	H04W 72/04
2012/0294320	12/2011	Corbett	372/20	H01S 5/06255
2013/0136446	12/2012	Hotchkiss	398/25	H04B 10/40
2016/0156997	12/2015	Hotchkiss	398/45	H04L 1/0057
2020/0092848	12/2019	Lemson	N/A	H04B 1/18

Primary Examiner: Kim; Harry H

Background/Summary

RELATED APPLICATION(S) (1) This application is a continuation in part of U.S. application Ser. No. 16/917,475 entitled Circuitry for Demarcation Devices and Methods Utilizing Same, filed Jun. 30, 2020, which is a continuation-in-part of U.S. application Ser. No. 16/839,260 entitled Multi-functional Circuitry for Communications Networks and Methods and Devices Utilizing Same, filed Apr. 3, 2020, which is a continuation of U.S. application Ser. No. 15/687,862 entitled Multi-functional Circuitry for Communications Networks and Methods and Devices Utilizing Same, filed Aug. 28, 2017, now U.S. Pat. No. 10,637,776 issued Apr. 28, 2020, and which claims priority to U.S. Provisional Application Ser. No. 62/381,168 filed Aug. 30, 2016, the entire disclosures of which are herein incorporated by reference. This application is also a continuation-in-part of U.S. application Ser. No. 16/415,899 entitled Small Form Factor Pluggable Unit with Wireless Capabilities, filed May 17, 2019, which is a continuation of U.S. application Ser. No. 15/294,858 entitled Small Form Factor Pluggable Unit with Wireless Capabilities, filed Oct. 17, 2016, now U.S. Pat. No. 10,446,909 issued on Oct. 15, 2019, and which claims priority to Provisional Application Ser. No. 62/243,957 filed Oct. 20, 2015, the entire disclosures of which are herein

BACKGROUND

(1) A breakout or fanout cable is an optical fiber (fiber) or wire connectorized cable assembly containing a high-density connector attached to several insulated cables bundled together in a single outer jacket, a jacketed cable bundle. The jacketed cable bundle then splits or separates into several individual jacketed cables where each jacketed cable is attached to a connector. Breakout cables can be passive optical fiber or wire passive or active wire design. Breakout cables are an economical and effect solution to replace equipment patch panels and fiber splice connector box, and installation time and material. Breakout cable assemblies are most commonly used to consolidate and organize individual fiber patch cables between and within a network by reducing the physical size and clutter with large quantities of patch cables. Optical fiber breakout cables available with LC, SC, and ST fiber connectors attached to the individual jacketed fiber cable, as well as support for Single-Mode (OS2) and Multimode (OM1, OM2, OM3, & OM4) fiber specifications, and lengths from 1 to 100 meters. The wire and fiber cables design and jacket material and construction vary per user application and installation environment. Break out cable jacket material may have standard riser (OFNR) or fire-retardant Plenum (OFNP) insulation for additional protection against fire. The breakout jacket may be reinforced with specialty jacketing, such as an armored jacket, for additional protection and deployment in previously uninhabitable areas.

(2) By way of further background, small Form-factor Pluggable (SFP) devices are standardized, hot-pluggable devices used to provide communication services for the communication market. The SNIA SFF Technology Affiliate (TA) Small Form Factor (SFF) and various other Multi Source Agreement (MSA) Committees defines the mechanical, electrical, and software specifications of the SFP device to ensure interoperability among SFP devices and chassis. SFF Committee document INF-8074i Rev 1.0 provide specifications for SFP (Small Form Factor Pluggable) Transceiver, SFF-8431 Rev 4.1 provide specifications for SFP+ 10 Gb/s and Low Speed Electrical Interface provide specifications for SFP+ devices, SFF-8402 Rev 1.1 provide specification for SFP+ 1×28 Gb/s Pluggable Transceiver Solution (SFP28), SFF-8436 Rev 4.9 provides specification for QSFP+4×10 Gb/s Pluggable Transceiver, SFF-8665 Rev 1.9 provide specifications for QSFP+28 Gb/s 4×Pluggable Transceiver Solution (QSFP28). QSFP-DD Hardware Rev 5.1 provide specifications for QSFP Double Density 8×Pluggable Transceiver, and OSFP Module Specification Rev 3.0 provide specifications for OSFP Octal Small Form Factor Pluggable Module represent a few of the specifications for SFP transceiver devices. These documents also reference other documents providing specifications for the associated SFP transceiver cage and connector. SFP devices are designed to be inserted within a cage, which the cage is attached to the communication equipment circuit assembly. An example of this cage SFF Committee document SFF-8432 Rev 5.1 SFP+ provides specifications for the SFP+ module and cage. SFP devices are available with different exterior connectors for various applications. SFP devices are available with coaxial connectors, SC/LC optical connectors, and RJ modular jack types connectors.

(3) SFF Committee document SFF-8472 Rev 12.3 Diagnostic Monitoring Interface for Optical Transceivers and SFF-8636 Rev 2.10a provide specifications for the Management Interface for 4-lane Modules and Cables provide specifications on the SFP device's identity, status, and real-time operating conditions. These documents and other documents listed above describes a register and memory map which provides alarms, warnings, vendor identity, SFP description and type, SFP real time diagnostic, and vendor specific registers. This information is to be used by the SFP host equipment.

(4) Due to its small and portable physical size, SFP Devices have expanded in specifications to

address other applications. SFP Devices are represented as SFP, SFP+, SFP28, QSFP, QSFP+, QSPF28, QSFP-DD, OSPF, and all other current and future SFP and MSA technologies. SFP Devices are standardized among equipment vendors and network operators to support interoperability. Due to the low cost, size, and interoperability. SFP Devices are used extensively in all communication service applications.

(5) By way of still further background, the telecommunication service and network have significantly evolved towards communication equipment providing an extremely high service capacity in a smaller mechanical form factor. At present the capacity these very high capacity communication equipment can support is challenged with managing power usage and heat dissipation, which involve service restrictions, QSFP and SFP device usage restrictions, and equipment installation restrictions. The extremely high service capacity communication equipment will require using lower power QSFP and SFP devices to manage the power usage and heat dissipation. These lower power QSFP and SFP devices do not support long distance transmission, higher transmission rates, or other media applications.

(6) By way of still further background, the telecommunication service and network still support a variety of communication services and technologies. The Service Provider must still manage the deployment of legacy to state-of-the-art communication services and their associated communication equipment, which typically involve different communication service interfaces and physical media. The Service Provider use of very compact state-of-the art communication equipment with high density connectors further consolidates the deployment of services at the Demarcation Point. The Demarcation point establishes the boundaries which define privacy, ownership, and responsibilities between the Service Provider and their Customer. The Service Provider typically deploys different equipment at different locations, which complicates the Demarcation Point.

(7) One example of a prior art breakout cable assembly is illustrated in the diagram of FIG. 1 (prior art). A QSFP to four LC fiber breakout Cable **900** comprises a QSFP Connector **908** attached to jacketed Cable **906** bundle at one-end and four fiber LC Connectors **902a**, **902b**, **902c**, and **902d** each connector attached to the individual jacketed cable **904a**, **904b**, **904c**, **904d**. The QSFP Connector **908** is an active device which supports eight fiber cables, where eight fiber cables are partitioned into four jacketed Cables **904a**, **904b**, **904c**, and **904d**. Cables **904a**, **904b**, **904c**, and **904d** are each comprised of two fiber cables, specifically a transmit and receive fiber cable. The Cables **904a**, **904b**, **904c**, and **904d** are each connected to fiber LC Connectors **902a**, **902b**, **902c**, and **902d**.

(8) There are a number of disadvantages to this type of breakout cable assembly **900**. This breakout fiber cable has a fixed cable length and cannot provide the flexibility of supporting different fiber cable lengths for the bundled Cable **906** or individual Cable **904a**, **904b**, **904c**, or **904d**. This fiber breakout Cable **900** is designed with a specific cable type and material, such as multimode fiber for indoor applications. If the communication service application requires an outdoor long distance application, a fiber breakout Cable **900** designed using an armored jacketed single mode fiber would be required. Still further, the prior art Cable **900** Connectors **902a**, **902b**, **902c**, and **902d** can only connect to communication equipment with LC fiber connectors. There may be applications which require RJ45, coax, or wireless interfaces.

(9) Another example of a prior art breakout cable assembly is illustrated in the diagram of FIG. 2 (prior art). A QSFP+ to SFP+ breakout Cable **910** comprises a QSFP Connector **918** attached to jacketed Cable **916** bundle at one-end and four SFP Connectors **912a**, **912b**, **912c**, and **912d** each SFP connector attached to the individual jacketed cable **914a**, **914b**, **914c**, **914d**. The QSFP Connector **918** is an active device which supports eight fiber cables, where eight fiber cables are partitioned into four jacketed Cables **914a**, **914b**, **914c**, and **914d**. Cables **914a**, **914b**, **914c**, and **914d** are each comprised of two fiber cables, specifically a transmit and receive fiber cable. The Cables **914a**, **914b**, **914c**, and **914d** are each connected to active SFP Connectors **912a**, **912b**, **912c**,

and **912d**.

(10) There are a number of disadvantages to this type of breakout cable assembly **920**. This breakout fiber cable has a fixed cable length and cannot provide the flexibility of supporting different fiber cable lengths for the bundled Cable **916** or individual Cable **914a**, **914b**, **914c**, or **914d**. This fiber breakout Cable **910** is designed with a specific cable type and material, such as multimode fiber for indoor applications. If the communication service application requires an outdoor long cable length application, a fiber breakout Cable **910** designed using an armored jacketed extended length single mode fiber would be required. Still further, the prior art Cable **910** Connectors **912a**, **912b**, **912c**, and **912d** can only connect to communication equipment with SFP connectors. There may be applications which require RJ45, coax, or wireless interfaces.

(11) Another example of a prior art breakout cable assembly is illustrated in the diagram of FIG. 3 (prior art). A QSFP-DD to SFP28 breakout Cable **920** comprises a QSFP-DD Connector **928** attached to jacketed Cable **926** bundle at one-end and eight SFP Connectors **922a**, **922b**, **922c**, **922d**, **922e**, **922f**, **922g**, and **922h** each SFP connector attached to the individual jacketed cable **924a**, **924b**, **924c**, **924d**, **924e**, **924f**, **924g**, and **924h**. The QSFP-DD Connector **928** is an active device which supports sixteen fiber cables, where the sixteen fiber cables are partitioned into eight jacketed Cables **924a**, **924b**, **924c**, **924d**, **924e**, **924f**, **924g**, and **924h**. Cables **924a**, **924b**, **924c**, **924d**, **924e**, **924f**, **924g**, and **924h** are each comprised of two fiber cables, specifically a transmit and receive fiber cable. The Cables **924a**, **924b**, **924c**, **924d**, **924e**, **924f**, **924g**, and **924h** are each connected to active SFP Connectors **922a**, **922b**, **922c**, **922d**, **922e**, **922f**, **922g**, and **912h**.

(12) There are a number of disadvantages to this type of breakout cable assembly **920**. This breakout fiber cable has a fixed cable length and cannot provide the flexibility of supporting different fiber cable lengths for the bundled Cable **926** or individual Cable **924a**, **924b**, **924c**, **924d**, **924e**, **924f**, **924g** or **924h**. This fiber breakout Cable **920** is designed with a specific cable type and material, such as multimode fiber for indoor applications. If the communication service application requires an outdoor long distance application, a fiber breakout Cable **920** designed using an armored jacketed single mode fiber would be required. Still further, the prior art Cable **910** Connectors **924a**, **924b**, **924c**, **924d**, **924e**, **924f**, **924g**, and **924h** can only connect to communication equipment with SFP connectors. There may be applications which require RJ45, coax, or wireless interfaces.

(13) Still another example of a prior art breakout cable assembly is illustrated in the diagram of FIG. 4 (prior art). A MPO to LC breakout Cassette **930** comprises a MPO Receptable **938** attached to Cable **936** bundle at one-end and four fiber LC Receptables **932a**, **932b**, **932c**, and **932d** each fiber LC receptable attached to the individual cable **934a**, **934b**, **934c**, and **934d**. The MPO Receptable **938** is a passive device which supports eight fiber cables, where the eight fiber cables are partitioned into four fiber Cables **934a**, **934b**, **934c**, and **934d**. Cables **934a**, **934b**, **934c**, and **934d** are each comprised of two fiber cables, specifically a transmit and receive fiber cable. The Cables **934a**, **934b**, **934c**, and **934d** are each connected to the fiber LC Receptacles **932a**, **932b**, **932c**, and **932d**.

(14) There are a number of disadvantages to this type of breakout Cassette **930**. This breakout Cassette **930** uses fixed fiber LC connectors and cannot interface other physical media interfaces such as RJ45, coax, or wireless. The breakout Cassette **930** is a passive device, which will restrict the length of fiber cables connected to the fiber LC Receptables **932a**, **932b**, **932c**, and **932d** and the MPO Receptable **938**.

(15) The following references provide general background information regarding the subject matter hereof, and each are herein incorporated by reference: U.S. Pat. No. 8,406,587 B2 titled Quad Small Form Factor Pluggable (QSFP) Adapter Module, issued to Mudd, et al. on Mar. 26, 2013. U.S. Pat. No. 9,100,123 B2 titled QSFP To 4×10GBase-T Converter Cable Assembly, issued to Tang, et al. on Aug. 4, 2015. U.S. Pat. No. 6,975,209 B2 titled In-Line Power Tap Device for Ethernet Data Signal, issued to Gromov on Dec. 13, 2005. U.S. Patent Application Publication No.

2004/0062498 A1 titled Optical Polarity Modules And Systems, published to Del Grosso et al. on Apr. 1, 2004. U.S. Patent Application Publication No. 2016/0342563 A1 titled Converter Module, published to Tomada on Nov. 24, 2016.

SUMMARY

(16) In a preferred embodiment, the Communications Network Device of the present disclosure is a flexible and applicable device for facilitating communication services from complex and diverse networks. This Device, which aggregates communication services from a plurality of lower service capacity connectors and interfaces to a single higher capacity connector and interfaces, is designed to use industry standard devices and technology, namely small pluggable devices and differential signaling. In turn, the Device has many advantages over prior art and many new advantages to address issues confronting present and future Networks.

(17) The Device is especially useful to aggregate different communication services from communication equipment in different locations by accepting different communication service, different physical media connector interfaces, and any cable types, cable material, and/or cable lengths. The Device allows for the ability to change or repair communication services by replacing the SFP devices and/or associated cabling.

(18) The methods, systems, devices, circuitry and equipment of the present disclosure have the ability to provide independent media conversion on each of the SFP devices. The Device can support different physical media interfaces media such as fiber, coax, wire, and wireless by using SFP and QSFP devices. The Device allows the physical media interface connectors to be changed by replacing the SFP or QSFP devices.

(19) The methods, systems, Devices and Circuitry disclosed herein allow the Network to change service paths between a low to a high density port connectors. The Device uses a non-blocking cross-point switch to switch any differential signals from the cross-point switch input to output. The Device has the ability to change communication service paths, allowing the Network flexibility to offer new or change communication services within a Network or at a Network Demarcation Point. The Device is also able to provide communication service redundancy by switching communication paths between the Device's ports.

(20) The methods, systems, Devices and Circuitry disclosed herein are designed to have very low latency between the Device's ports to address applications involving 5G or latency sensitive networks. The Device realizes very low latencies by using differential paths between the Device's functional blocks. The Device design of differential signaling paths between functional blocks yields very low latency through the Device. The Device low latency of 350 ps or lower for future Networks, namely 5G use of differential signaling provides a low latency.

(21) The methods, systems, Devices and Circuitry of the present disclosure can establish a Demarcation Point through an SFP Device or the Device SFP Port. The SFP Device can provide the Demarcation Point with a wired, coax, optical, or wireless interface with the appropriate SFP Device. Alternately, the methods, systems, Devices and Circuitry of the present disclosure can establish a Demarcation Point through an SFP Port. In one embodiment, the Device Port is the Demarcation Point and the SFP Device is the responsibility of the other Network. The methods, systems, Devices and Circuitry of the present disclosure can establish a Demarcation Point with a single device capable of supporting any communication services, any physical media interfaces, from any location.

(22) The methods, systems, Devices and Circuitry of the present disclosure can also establish an Extended Demarcation Point for communication service. The present disclosure can provide an extended Demarcation point by installing the Device further within the Second Network and using the SFP devices as the Extended Demarcation Point. The Device functionality in small mechanical size offers the Second Network the advantages of installing the Device anywhere.

(23) The methods, systems, Devices and Circuitry of the present disclosure can also allow another communication equipment to manage heat dissipation and power usage by having the other

communication equipment to use lower power QSFP and SFP type devices. SFP28, QSFP+, QSFP28, QSFP-DD, OSFP devices can each dissipate up to 15 W or greater for long distance transmission. On high capacity communication equipment heat dissipated can be over 1000 W, which this amount of power and heat can prevent the installation of other communication equipment within the same communication equipment rack or enclosure. The Device can function as an intermediate device, where the Device installs these extended range SFP and QSFP devices to provide the long distance transmission to the other Network. The Device in turn will connect to the communication equipment using lower power SFP or QSFP Device or cabling.

(24) The Device of the present disclosure is also provided with remote testing capabilities, allowing for the provision of testing of the communication services. Existing prior art devices are not designed to have remote loopback testing capabilities and provide performance monitoring capabilities. The Device of the present disclosure includes the ability to perform intrusive loopback testing to verify the communication services. These remote testing and performance monitoring capabilities will allow the Service Providers to address the maintenance and troubleshooting of communication services remotely, i.e., without local presence. The ability to provide performance monitoring and testing will increase the reliability and quality of the service of the Device.

(25) The methods, systems, devices, circuitry and equipment of the present disclosure has the ability to identify, provide status, provision, and test the SFP devices and the communication services using loopbacks. As previously discussed, the SFP devices are designed to be compliant to the industry standard SFF-8472 digital diagnostics monitoring (DDM) functions which define management specifications on the SFP identity, status, provisioning, and other vendor specific information and controls. The Device accesses the DDM information from the SFP device through a serial communication interface Inter-Integrated Circuit (I2C). This I2C interface is low speed serial communication protocol implemented using two electrical signals, which the electrical signal interface is located at the SFP device printed circuit board edge connector of the Device.

(26) The methods, systems, Devices, and Circuitry of the present disclosure can also provide security to the SFP and QSFP type devices, cable, and associated communication services by restricting access. When the Device is installed in a communication equipment rack, the Device placement of the Service Provider's SFP or QSFP housing at the rear of the Device restricts access to the SFP or QSFP device, the attached cabling, and the associated signaling. In another embodiment, the Service Provider's SFP or QSFP housing at the front of the Device restricts access to the SFP or QSFP device by way of a cover to prevent the removal of SFP or QSFP device and cabling.

Description

BRIEF DESCRIPTION OF THE DRAWINGS

(1) FIG. 1 is a diagram illustrating a prior art fiber breakout cable assembly connectorized with a QSFP+ housing and four fiber LC connectors.

(2) FIG. 2 is a diagram illustrating a prior art connectorized wired breakout cable assembly connectorized with a QSFP+ housing and four SFP+ housings.

(3) FIG. 3 is a diagram illustrating a prior art fiber connectorized breakout cable assembly connectorized with a QSDP-DD housing and eight SFP+ housings.

(4) FIG. 4 is a diagram illustrating a prior art fiber cassette device comprised with a fiber MPO receptacle and four fiber LC receptables.

(5) FIG. 5 is a block diagram illustrating methods, systems, devices, circuitry and equipment of the present disclosure used to aggregate communication services between a communication device having a QSFP+ port and two communication equipment and a Tower, utilizing four SFP+ ports.

(6) FIG. 6 is a block diagram illustrating methods, systems, devices, circuitry and equipment of the

present disclosure having the ability to provide different physical media interfaces, cabling, and media conversion on any SFP and QSFP devices.

- (7) FIG. 7 is a block diagram illustrating methods, systems, devices, circuitry and equipment of the present disclosure having the ability to provide loopback testing.
- (8) FIG. 8 is a block diagram illustrating methods, systems, devices, circuitry and equipment of the present disclosure establishing a Demarcation Point with a QSFP+ device.
- (9) FIG. 9 is a block diagram illustrating methods, systems, devices, circuitry and equipment of the present disclosure establishing a Demarcation Point with four SFP+ devices.
- (10) FIG. 10 is a block diagram illustrating methods, systems, devices, circuitry and equipment of the present disclosure used to aggregate communication services between a communication equipment device having a QSFP-DD port and two communication equipment, utilizing a total of eight SFP28 ports.
- (11) FIG. 11 is a block diagram illustrating methods, systems, devices, circuitry and equipment of the present disclosure establishing a Demarcation Point with a QSFP-DD device.
- (12) FIG. 12 is a block diagram illustrating methods, systems, devices, circuitry and equipment of the present disclosure establishing a Demarcation Point with eight SFP28 devices.
- (13) FIG. 13 is a block diagram illustrating methods, systems, devices, circuitry and equipment of the present disclosure used to aggregate communication services between a communication equipment device having a QSFP-DD port and two communication equipment with QSFP28 ports.
- (14) FIG. 14 is a block diagram illustrating methods, systems, devices, circuitry and equipment of the present disclosure establishing a Demarcation Point with a QSFP-DD device.
- (15) FIG. 15 is a block diagram illustrating methods, systems, devices, circuitry and equipment of the present disclosure establishing a Demarcation Point with two QSFP28 devices.
- (16) FIG. 16 is a schematic diagram illustrating methods, systems, devices, circuitry and equipment of the present disclosure having circuitry used to amplify, equalize, and retune differential signal paths between a QSFP+ device and four SFP+ devices.
- (17) FIG. 17 is a schematic diagram illustrating the methods, systems, devices, circuitry and equipment of the present disclosure having circuitry used to amplify, equalize, retune, and switch differential signal paths between a QSFP+ device and four SFP+ devices.
- (18) FIG. 18 is a schematic diagram illustrating methods, systems, devices, circuitry and equipment of the present disclosure having circuitry used to amplify, equalize, and retune differential signal paths between a QSFP-DD device and eight SFP28 devices.
- (19) FIG. 19 is a schematic diagram illustrating methods, systems, devices, circuitry and equipment of the present disclosure having circuitry used to amplify, equalize, retune, and switch differential signal paths between a QSFP-DD device and eight SFP28 devices.
- (20) FIG. 20 is a schematic diagram illustrating methods, systems, devices, circuitry and equipment of the present disclosure having circuitry used to amplify, equalize, and retune differential signal paths between a QSFP-DD device and two QSFP28 devices.
- (21) FIG. 21 is a schematic diagram illustrating another methods, systems, devices, circuitry and equipment of the present disclosure having circuitry used to amplify, equalize, retune, and switch differential signal paths between a QSFP-DD device and two QSFP28 devices.
- (22) FIG. 22 is a diagram illustrating a graphical representation of one embodiment of the Device of the present disclosure and illustrating security on the QSFP device.

DETAILED DESCRIPTION

(23) The methods, systems, Devices, Circuitry and equipment of the present disclosure provide numerous advantages, novel features and/or improvements in providing various communication services and associated testing and maintenance for establishing a Demarcation for communication networks, including but not limited to providing the functionality of service monitoring via wireless. Discussed below and shown in the drawings are some of these advantages, novel features and/or improvements. Additional advantages, novel features and/or improvements will become

apparent to those skilled in the art upon examination of the disclosure herein and the accompanying drawings, or may be learned by production or operation of the examples.

(24) FIG. 5 illustrates a diagram of an embodiment of the communications system and equipment of the present disclosure, wherein a Device **100a** (if with circuitry **150a**) or **100b** (if with circuitry **150b**) interfaces four communication service, two communication services from Communication Equipment **300**, one communication service from Communication Equipment **310**, and one communication service from Communication Tower **320**. The Device **100a** or **100b** then aggregates the four communication services for transmission to Communication Equipment **400** by way of a single QSFP Device **200a**. This embodiment allows the use of different cabling types, cable lengths, and the ability to change and replace any cable or SFP and QSFP type devices. This embodiment allows the communication services to be aggregated from separate communication equipment and different equipment locations. This embodiment also allows the communication equipment to extend communication services, provide the communication equipment a method to manage heat dissipation on communication equipment, and provide the communication equipment a method to manage power usage, by having the communication equipment use lower power SFP, SFP+, SFP28, SFP56, QSFP, QSFP+, and QSFP28 devices.

(25) As illustrated in FIG. 5, the Network is comprised of a Device **100a** or **100b** having five Ports **102a**, **104a**, **106a**, **108a**, and **140a**, Communication Equipment **300** having two Ports **302**, **304**, Communication Equipment **310** having one Port **312**, a wireless Communication Tower **320** and Communication Equipment **400** having one Port **402**. Cables **500a**, **502a**, **504a**, **506p**, and **508o** can individually vary in length, type, and material for the given application. The individual cables can be replaced for repair or application changes. The Device **100a** or **100b** has a SFP Device **202a** connected to Port **102a**, a SFP Device **204a** connected to Port **104a**, a SFP Device **206a** connected to Port **106a**, a SFP Device **208a** connected to Port **108a**, and a QSFP Device **200a** connected to Port **140a**. The Device **100a** or **100b** has Paths **602**, **604**, **606**, and **608** which define transmit and receive differential signal paths between the SFP Ports **102a**, **104a**, **106a**, and **108a** and Circuitry **150a** or **150b** of the Device. Path **600** defines four transmit and receive differential signal paths between the QSFP Port **140a** and Circuitry **150a** and **150b** of the Device. The Circuitry **150a** or **150b** is comprised of input and output differential amplifiers and retimers through differential signal paths, as shown and discussed in more detail with respect to FIGS. **16** and **17** respectively. Device **100a** has Circuitry **150a** whereas Device **100b** has Circuitry **150b**. The Circuitry **150b** of Device **100b** has a cross-connect switch which provides non-blocking cross-connects between all Paths. Further details on Circuitry **150a** and **150b** are illustrated in FIGS. **16** and **17**, respectively.

(26) Two fiber Cables **502a** and **504a** are used to interface the communication services between Communication Equipment **300** and Device **100a** or **100b**, specifically connecting the fiber Cable **502a** from SFP Device **202a** in Port **102a** of Device **100a** or **100b** to Port **302** of the Communication Equipment **300**, and connecting the fiber Cable **504a** from SFP Device **204a** in Port **104a** to Port **304** of the Communication Equipment **300**. A flame retardant plenum Cable **506p** is used to interface the communication service between Communication Equipment **310** and Device **100a** or **100b**, specifically connecting the plenum Cable **506p** from SFP Device **206a** in Port **106a** of Device **100a** or **100b** to Port **312** of Communication Equipment **310**. An outside armored fiber Cable **508o** is used to interface the communication services between the Communication Tower **320** and Device **100a** or **100b**, specifically connecting the outdoor fiber Cable **508o** from SFP Device **208a** in Port **108a** of Device **100a** or **100b** to the Communication Tower **320**. The Device **100a** or **100b** in turn connects to the Communication Equipment **400** through a fiber Cable **500a**, specifically connecting the QSFP Device **200a** in Port **140a** of Device **100a** or **100b** to Port **402** of the Communication Equipment **400**.

(27) FIG. 6 illustrates a diagram of an embodiment of the communications system and equipment of the present disclosure, wherein a Device **100a** or **100b** interfaces four communication services, two communication services from Communication Equipment **300**, one communication service

from Communication Equipment **310**, and one communication service from Communication Tower **320**. The Device **100a** or **100b** then aggregates the four communication services for transmission to Communication Equipment **400** by way of a single QSFP Device **200a**. This embodiment allows the use of different cabling types, cable lengths, and the ability to change and replace any cable or SFP and QSFP type devices. This embodiment allows media conversion on the SFP and QSFP devices. This embodiment allows the communication services to be aggregated from separate communication equipment and different equipment locations. This embodiment also allows the communication equipment to extend communication services, provide the communication equipment a method to manage heat dissipation on communication equipment, and provide the communication equipment a method to manage power usage, by having the communication equipment use lower power SFP, SFP+, SFP28, SFP56, QSFP, QSFP+, and QSFP28 devices.

(28) As illustrated in FIG. **6**, the Network is comprised of a Device **100a** or **100b** having five Ports **102a**, **104a**, **106a**, **108a**, and **140a**, Communication Equipment **300** having two Ports **302**, **304**, Communication Equipment **310** having one Port **312**, Communication Tower **320** and Communication Equipment **400** having one Port **402**. The Device **100a** or **100b** has a SFP Device **202a** connected to Port **102a**, a SFP Device **204b** connected to Port **104a**, a SFP Device **206c** connected to Port **106a**, a SFP Device **208d** connected to Port **108a**, and a QSFP Device **200a** connected to Port **140a**. The Device **100a** or **100b** has Paths **602**, **604**, **606**, and **608** which define transmit and receive differential signal paths between the SFP Ports **102a**, **104a**, **106a**, and **108a** and Circuitry **150a** or **150b** of the Device. Path **600** defines four transmit and receive differential signal paths between the QSFP Port **140a** and Circuitry **150a** and **150b** of the Device. Device **100a** has Circuitry **150a** whereas Device **100b** has Circuitry **150b**. The Circuitry **150a** or **150b** is comprised of input and output differential amplifiers and retimers through differential signal paths. The Circuitry **150b** of Device **100b** has a cross-connect switch which provides non-blocking cross-connects between all Paths. Further details on Circuitry **150a** and **150b** are illustrated in FIGS. **16** and **17**, respectively.

(29) A standard indoor fiber Cable **502a** is used to interface the communication services between Communication Equipment **300** and Device **100a** or **100b**, specifically connecting the indoor fiber Cable **502a** from SFP Device **202a** in Port **102a** of Device **100a** or **100b** to Port **302** of the Communication Equipment **300**. An Ethernet RJ45 connectorized wired Cable **504b** is used to interface the communication services between the Communication Equipment **300** and Device **100a** or **100b**, specifically connecting the wired Cable **504b** from a RJ45 SFP Device **204b** in Port **104a** to Port **304** of the Communication Equipment **300**. A coax Cable **506c** is used to interface the communication service between Communication Equipment **310** and Device **100a** or **100b**, specifically connecting the coax Cable **506c** from a Coax SFP Device **206c** in Port **106a** of Device **100a** or **100b** to Port **312** of Communication Equipment **310**. An outside armored single fiber Cable **508o** is used to interface the communication services between the Communication Tower **320** and Device **100a** or **100b**, specifically connecting the outdoor fiber Cable **508o** from a Wave Division Multiplexing (WDM) SFP Device **208d** in Port **108a** of Device **100a** or **100b** to the Communication Tower **320**. A fiber Cable **500a** is used to interface the four communication services between the Communication Equipment **400** and Device **100a** or **100b**, specifically connecting the fiber Cable **500a** from QSFP Device **200a** in Port **140a** of Device **100a** or **100b** to Port **402** of the Communication Equipment **400**.

(30) The SFP and QSFP Devices in this embodiment can be alternatively replaced by various other SFP Devices and their derivative. SFP Devices presently are defined for SFP, SFP+, SFP28, SFP56, QSFP, QSFP+, QSFP28, QSFP-DD and OSPF technologies. These other SFP Devices provide different media interfaces and connection types, e.g., wire cable, optical cable, coax cable, and wireless.

(31) FIG. **7** illustrates a diagram of an embodiment of the communications system and equipment of the present disclosure, wherein a Device **100a** or **100b** interfaces four communication services,

two communication services from Communication Equipment **300**, one communication service from Communication Equipment **310**, and one communication service from Communication Tower **320**. The Device **100a** or **100b** then aggregates the four communication services for transmission to Communication Equipment **400** by way of a single QSFP Device **200a**. This embodiment also illustrates the Device performing loopback for testing the SFP and QSFP devices and associated communication services, which Communication Equipment **300** and **400** will be able to evaluate and diagnosis the communication services. This embodiment also allows the use of different cabling types, cable lengths, and the ability to change and replace any cable or SFP and QSFP type devices. This embodiment allows the communication services to be aggregated from separate communication equipment and different equipment locations. This embodiment also allows the communication equipment to extend communication services, provide the communication equipment a method to manage heat dissipation on communication equipment, and provide the communication equipment a method to manage power usage, by having the communication equipment use lower power SFP, SFP+, SFP28, SFP56, QSFP, QSFP+, and QSFP28 devices.

(32) As illustrated in FIG. 7, the Network is comprised of a Device **100a** or **100b** having five Ports **102a**, **104a**, **106a**, **108a**, and **140a**, Communication Equipment **300** having two Ports **302**, **304**, Communication Equipment **310** having one Port **312**, Communication Tower **320** and Communication Equipment **400** having one Port **402**. The Device **100a** or **100b** has a SFP Device **202a** connected to Port **102a**, a SFP Device **204b** connected to Port **104a**, a SFP Device **206c** connected to Port **106a**, a SFP Device **208d** connected to Port **108a**, and a QSFP Device **200a** connected to Port **140a**. The Device **100a** or **100b** has Paths **602**, **604**, **606**, and **608** which define transmit and receive differential signal paths between the SFP Ports **102a**, **104a**, **106a**, and **108a** and Circuitry **150a** or **150b** of the Device. Path **600** defines four transmit and receive differential signal paths between the QSFP Port **140a** and Circuitry **150a** and **150b** of the Device. Device **100a** has Circuitry **150a** whereas Device **100b** has Circuitry **150b**. The Circuitry **150a** or **150b** is comprised of input and output differential amplifiers and retimers through differential signal paths. The Circuitry **150b** of Device **100b** has a cross-connect switch which provides non-blocking cross-connects between all Paths. The Device **100a** or **100b** can perform loopback testing in Circuitry **150a** or **150b**. Loopback circuitry **700** is looping back any and all differential signaling paths of Path **600**, Loopback circuitry **702** is looping back Path **602**, Loopback circuitry **704** is looping back Path **604**, Loopback circuitry **706** is looping back Path **606**, and Loopback circuitry **708** is looping back Path **608**. Further details on Circuitry **150a** and **150b** are illustrated in FIGS. **16** and **17**, respectively.

(33) A standard indoor fiber Cable **502a** is used to interface the communication services between Communication Equipment **300** and Device **100a** or **100b**, specifically connecting the indoor fiber Cable **502a** from SFP Device **202a** in Port **102a** of Device **100a** or **100b** to Port **302** of the Communication Equipment **300**. An Ethernet RJ45 connectorized wired Cable **504b** is used to interface the communication services between the Communication Equipment **300** and Device **100a** or **100b**, specifically connecting the wired Cable **504b** from a RJ45 SFP Device **204b** in Port **104a** to Port **304** of the Communication Equipment **300**. A coax Cable **506c** is used to interface the communication service between Communication Equipment **310** and Device **100a** or **100b**, specifically connecting the coax Cable **506c** from a Coax SFP Device **206c** in Port **106a** of Device **100a** or **100b** to Port **312** of Communication Equipment **310**. An outdoor fiber Cable **508o** is used to interface the communication services between the Communication Tower **320** and Device **100a** or **100b**, specifically connecting the outdoor single fiber Cable **508o** from a Wave Division Multiplexing (WDM) SFP Device **208d** in Port **108a** of Device **100a** or **100b** to the Communication Tower **320**. A fiber Cable **500a** is used to interface the four communication services between the Communication Equipment **400** and Device **100a** or **100b**, specifically connecting the fiber Cable **500a** from QSFP Device **200a** in Port **140a** of Device **100a** or **100b** to Port **402** of the Communication Equipment **400**.

(34) The SFP and QSFP Devices in this embodiment can be alternatively replaced by various other SFP Devices and their derivative. SFP Devices presently are defined for SFP, SFP+, SFP28, SFP56, QSFP, QSFP+, QSPF28, QSFP-DD and OSPF technologies.

(35) FIG. 8 illustrates a diagram of another embodiment of the communications system and equipment of the present disclosure, wherein the Device **100a** or **100b** of the present disclosure establishes a Demarcation Point **10** between a First Network **20** and a Second Network **30**, specifically through QSFP Device **200b** in Port **140a**, in communication with a Port **402** on the Communication Equipment **400** of the Second Network **30**. The Device **100a** or **100b** provides a cost effective and efficient method and system of providing a Demarcation Point on four communication services by way of a single WDM QSFP Device **200b**. This embodiment also allows the use of different cabling types, cable lengths, and the ability to change and replace any cable or SFP and QSFP type devices. This embodiment allows the communication services to be aggregated from separate communication equipment and different equipment locations. This embodiment also allows the communication equipment to extend communication services, provide the communication equipment a method to manage heat dissipation on communication equipment, and provide the communication equipment a method to manage power usage, by having the communication equipment use lower power SFP, SFP+, SFP28, SFP56, QSFP, QSFP+, and QSFP28 devices.

(36) As illustrated in FIG. 8, the First Network **20** is comprised of a Device **100a** or **100b** having five Ports **102a**, **104a**, **106a**, **108a**, and **140a**, Communication Equipment **300** having Port **302**, Communication Equipment **310** having Port **312**, Communication Equipment **320** having Port **322**, and Communication Equipment **330** having a Port **332**. The Device **100a** or **100b** has a SFP Device **202a** connected to Port **102a**, a SFP Device **204a** connected to Port **104a**, a SFP Device **206a** connected to Port **106a**, a SFP Device **208a** connected to Port **108a**, and a Wave Division Multiplexing (WDM) QSFP Device **200b** connected to Port **140a**. The Device **100a** and **100b** have Paths **602**, **604**, **606**, and **608** which define transmit and receive differential signal paths between the SFP Ports **102a**, **104a**, **106a**, and **108a** and Circuitry **150a** or **150b** of the Device. Path **600** defines four transmit and receive differential signal paths between the WDM QSFP Port **140a** of the Device and Circuitry **150a** and **150b**. The Circuitry **150a** or **150b** is comprised of input and output differential amplifiers and retimers through differential signal paths. Device **100a** has Circuitry **150a** whereas Device **100b** has Circuitry **150b**. The Circuitry **150b** of Device **100b** has a cross-connect switch which provides non-blocking cross-connects between all Paths. Further details on Circuitry **150a** and **150b** are illustrated in FIGS. 16 and 17, respectively. The Second Network **30** includes Communication Equipment **400** having Port **402**.

(37) In this embodiment, the First Network **20** establishes a Demarcation Point **10** with Device **100a** or **100b** through QSFP Device **200b**. A fiber Cable **500a** is used to interface the four communication services between the Communication Equipment **400** and Device **100a** or **100b**, specifically connecting the fiber Cable **500a** from WDM QSFP Device **200b** in Port **140a** of Device **100a** or **100b** to Port **402** of the Communication Equipment **400** of the Second Network **30**. The Device **100a** or **100b** in turn connects to the Communication Equipment **300** of the First Network **20** through a fiber Cable **502a**, specifically connecting SFP Device **202a** to Port **302** of the Communication Equipment **300**, a fiber Cable **504a**, specifically connecting SFP Device **204a** to Port **312** of the Communication Equipment **310**, a fiber Cable **506a**, specifically connecting SFP Device **206a** to Port **322** of the Communication Equipment **320**, and a fiber Cable **508a**, specifically connecting SFP Device **208a** to Port **332** of the Communication Equipment **330** of the First Network **20**. The SFP and QSFP Devices in this embodiment can be alternatively replaced by various other SFP Devices and their derivative. SFP Devices presently are defined for SFP, SFP+, SFP28, SFP56, QSFP, QSFP+, QSPF28, QSFP-DD and OSPF technologies. These other SFP Devices provide different media interfaces and connection types, e.g., wire cable, optical cable, coax cable, and wireless.

(38) FIG. 9 illustrates a diagram of another embodiment of the communications system and equipment of the present disclosure, wherein the Device **100a** or **100b** of the present disclosure establishes a Demarcation Point **10** between a First Network **20** and a Second Network **30**, specifically through SFP Device **202a** and **204a** in communication with a Port **402** and **404** respectively on the Communication Equipment **400** of the Second Network **30**, through SFP Device **206b** in communication with Port **412** on the Communication Equipment **410** of the Second Network **30**, and through SFP Device **208d** in communication with the Communication Tower **420** of the Second Network **30**. The Device **100a** or **100b** provides a cost effective and efficient method and system for a communication service Demarcation Point by allowing the First Network to provide four communication services. This embodiment allows the use of different cabling types, cable lengths, and the ability to change and replace any cable or SFP and QSFP type devices. This embodiment allows the communication services to be aggregated from separate communication equipment and different equipment locations. This embodiment also allows the communication equipment to extend communication services, provide the communication equipment a method to manage heat dissipation on communication equipment, and provide the communication equipment a method to manage power usage, by having the communication equipment use lower power SFP, SFP+, SFP28, SFP56, QSFP, QSFP+, and QSFP28 devices.

(39) As illustrated in FIG. 9, the First Network **20** is comprised of a Device **100a** or **100b** having five Ports **102a**, **104a**, **106a**, **108a**, and **140a**, and Communication Equipment **300** having a Port **302**. The Device **100a** or **100b** has a SFP Device **202a** connected to Port **102a**, a SFP Device **204a** connected to Port **104a**, a SFP Device **206b** connected to Port **106a**, a SFP Device **208d** connected to Port **108a**, and a QSFP Device **200b** connected to Port **140a**. The Device **100a** or **100b** has Paths **602**, **604**, **606**, and **608** which define transmit and receive differential signal paths between the SFP Ports **102a**, **104a**, **106a**, and **108a** and Circuitry **150a** or **150b** of the Device. Path **600** defines four transmit and receive differential signal paths between the QSFP Port **140a** and Circuitry **150a** or **150b** of the Device. The Circuitry **150a** or **150b** is comprised of input and output differential amplifiers and retimers through differential signal paths. Device **100a** has Circuitry **150a** whereas Device **100b** has Circuitry **150b**. The Circuitry **150b** of Device **100b** has a cross-connect switch which provides non-blocking cross-connects between all Paths. Further details on Circuitry **150a** and **150b** are illustrated in FIGS. 16 and 17, respectively. The Second Network **30** includes Communication Equipment **400** having Ports **402** and **404**, Communication Equipment **410** having Port **412**, and Communication Tower **420**.

(40) In this embodiment, the First Network **20** establishes a Demarcation Point **10** with Device **100a** or **100b** through SFP Device **202a**, **204a**, **206b**, and **208a**. A fiber Cable **502a** is used to interface the communication services between the Communication Equipment **400** and Device **100a** or **100b**, specifically connecting the fiber Cable **502a** from SFP Device **202a** in Port **102a** of Device **100a** or **100b** to Port **402** of the Communication Equipment **400** of the Second Network **30**. A fiber Cable **504a** is used to interface the communication services between the Communication Equipment **400** and Device **100a** or **100b**, specifically connecting the fiber Cable **504a** from SFP Device **204a** in Port **104a** of Device **100a** or **100b** to Port **404** of the Communication Equipment **400** of the Second Network **30**. A wire Cable **506b** is used to interface communication services between Communication Equipment **410** and Device **100a** or **100b**, specifically connecting the wire Cable **506b** from SFP Device **206b** in Port **106a** of Device **100a** or **100b** to Port **412** of the Communication Equipment **410** of the Second Network **30**. An outdoor fiber Cable **508o** is used to interface communication services between Communication Tower **420** and Device **100a** or **100b**, specifically connecting the outdoor fiber Cable **508o** from SFP Device **208d** in Port **108a** of Device **100a** or **100b** to the Communication Tower **420** of the Second Network **30**. The Device **100a** or **100b** in turn connects to the Communication Equipment **300** of the First Network **20** through a fiber Cable **500a**, specifically connecting the wave division multiplexing (WDM) SFP Device **200b** in Port **140a** of Device **100a** or **100b** to the Port **302** of the Communication Equipment **300** of the

First Network **20**. The SFP and QSFP Devices in this embodiment can be alternatively replaced by various other SFP Devices and their derivative. SFP Devices presently are defined for SFP, SFP+, SFP28, SFP56, QSFP, QSFP+, QSPF28, QSFP-DD and OSPF technologies. These other SFP Devices provide different media interfaces and connection types, e.g., wire cable, optical cable, coax cable, and wireless.

(41) FIG. **10** illustrates a diagram of an embodiment of the communications system and equipment of the present disclosure, wherein a Device **100d** (if with circuitry **150d**) or **100e** (if with circuitry **150e**) interfaces eight communication services, four communication services from Communication Equipment **300** and four communication service from Communication Equipment **310**, and aggregates the eight communication services for transmission to Communication Equipment **400** by way of a QSFP-DD Device **240a**. This embodiment allows the use of different cabling types, cable lengths, and the ability to change and replace any cable or SFP and QSFP type devices. This embodiment allows the communication services to be aggregated from separate communication equipment and different equipment locations. This embodiment also allows the communication equipment to extend communication services, provide the communication equipment a method to manage heat dissipation on communication equipment, and provide the communication equipment a method to manage power usage, by having the communication equipment use lower power SFP+, SFP28, SFP56, QSFP, QSFP+, QSFP28, QSFP-DD, and OSFP devices.

(42) As illustrated in FIG. **10**, the Network is comprised of a Device **100d** or **100e** having nine Ports **102a**, **104a**, **106a**, **108a**, **110a**, **112a**, **114a**, **116a**, and **140b**, Communication Equipment **300** having four Ports **302**, **304**, **306**, and **308**, Communication Equipment **310** having four Ports **312**, **314**, **316**, and **318**, and Communication Equipment **400** having one Port **402**. Cables **500a**, **502a**, **504a**, **506a**, **508a**, **510a**, **512a**, **514a**, and **516a** can individually vary in length, type, and material for the given application. The individual cables can also be replaced for repair or application changes. The Device **100d** or **100e** has a SFP28 Device **202f** connected to Port **102a**, a SFP28 Device **204f** connected to Port **104a**, a SFP28 Device **206f** connected to Port **106a**, a SFP28 Device **208f** connected to Port **108a**, a SFP28 Device **210f** connected to Port **110a**, a SFP28 Device **212f** connected to Port **112a**, a SFP28 Device **214f** connected to Port **114a**, a SFP28 Device **216f** connected to Port **116a**, and a QSFP-DD Device **240a** connected to Port **140b**. The Device **100d** or **100e** has Paths **602**, **604**, **606**, **608**, **610**, **612**, **614**, and **616** which define transmit and receive differential signal paths between the SFP Ports **102a**, **104a**, **106a**, **108a**, **110a**, **112a**, **114a**, and **116a** and Circuitry **150d** or **150c** of the Device. Path **600** defines eight transmit and receive differential signal paths between the QSFP-DD Port **140b** and Circuitry **150d** and **150e** of the Device. The Circuitry **150d** or **150e** is comprised of input and output differential amplifiers and retimers through differential signal paths, as shown and discussed in more detail with respect to FIGS. **18** and **19** respectively. Device **100d** has Circuitry **150d** whereas Device **100e** has Circuitry **150e**. The Circuitry **150e** of Device **100e** has a cross-connect switch which provides non-blocking cross-connects between all Paths. Further details on Circuitry **150d** and **150e** are illustrated in FIGS. **18** and **19**, respectively.

(43) Four fiber Cables **502a**, **504a**, **506a**, and **508a** are used to interface the four communication services between Communication Equipment **300** and Device **100d** or **100e**, specifically connecting a fiber Cable **502a** from SFP Device **202f** in Port **102a** on Device **100d** or **100e** to Port **302**, a fiber Cable **504a** from SFP Device **204f** in Port **104a** of Device **100d** or **100e** to Port **304**, a fiber Cable **506a** from SFP Device **206f** in Port **106a** of Device **100d** or **100e** to Port **306**, and a fiber Cable **508a** from SFP Device **208f** in Port **108a** of Device **100d** or **100e** to Port **308**. Another four fiber Cables **510a**, **512a**, **514a**, and **516a** are used to interface the four communication service between Communication Equipment **310** and Device **100d** or **100e**, specifically connecting a fiber Cable **510a** from SFP Device **210f** in Port **110a** of Device **100d** or **100e** to Port **312**, a fiber Cable **512a** from SFP Device **212f** in Port **112a** of Device **100d** or **100e** to Port **314**, a fiber Cable **514a** from SFP Device **214f** in Port **114a** of Device **100d** or **100e** to Port **316**, and a fiber Cable **516a**

from SFP Device **216f** in Port **116a** of Device **100d** or **100e** to Port **318**. The Device **100d** or **100e** in turn connects to the Communication Equipment **400** through a fiber Cable **500a**, specifically connecting the QSFP-DD Device **240a** in Port **140b** of Device **100d** or **100e** to Port **402** of the Communication Equipment **400**. The SFP28 and QSFP-DD Devices in this embodiment can be alternatively replaced by various other SFP Devices and their derivative. SFP Devices presently are defined for SFP, SFP+, SFP28, SFP56, QSFP, QSFP+, QSPF28, QSFP-DD and OSFP technologies. These other SFP Devices provide different media interfaces and connection types, e.g., wire cable, optical cable, coax cable, and wireless.

(44) FIG. **11** illustrates a diagram of another embodiment of the communications system and equipment of the present disclosure, wherein the Device **100d** or **100e** of the present disclosure establishes a Demarcation Point **10** between a First Network **20** and a Second Network **30**, specifically through QSFP-DD Device **240a** in Port **140b**, in communication with a Port **402** on the Communication Equipment **400** of the Second Network **30**. The Device **100d** or **100e** provides a cost effective and efficient method and system of providing Demarcation Point on eight communication services by way of a single QSFP-DD Device **240a**. This embodiment allows the use of different cabling types, cable lengths, and the ability to change and replace any cable or SFP and QSFP type devices. This embodiment allows the communication services to be aggregated from separate communication equipment and different equipment locations. This embodiment also allows the communication equipment to extend communication services, provide the communication equipment a method to manage heat dissipation on communication equipment, and provide the communication equipment a method to manage power usage, by having the communication equipment use lower power SFP+, SFP28, SFP56, QSFP, QSFP+, QSFP28, QSFP-DD, and OSFP devices.

(45) As illustrated in FIG. **11**, the First Network **20** is comprised of a Device **100d** or **100e** having nine Ports **102a**, **104a**, **106a**, **108a**, **110a**, **112a**, **114a**, **116a**, and **140b**, Communication Equipment **300** having four Ports **302**, **304**, **306**, and **308**, and Communication Equipment **310** having four Ports **312**, **314**, **316**, and **318**. The Second Network is comprised of Communication Equipment **400** having one Port **402**. Cables **500a**, **502a**, **504a**, **506a**, **508a**, **510a**, **512a**, **514a**, and **516a** can individually vary in length, type, and material for the given application. The individual cables can also be replaced for repair or application changes. The Device **100d** or **100e** has a SFP28 Device **202f** connected to Port **102a**, a SFP28 Device **204f** connected to Port **104a**, a SFP28 Device **206f** connected to Port **106a**, a SFP28 Device **208f** connected to Port **108a**, a SFP28 Device **210f** connected to Port **110a**, a SFP28 Device **212f** connected to Port **112a**, a SFP28 Device **214f** connected to Port **114a**, a SFP28 Device **216f** connected to Port **116a**, and a QSFP-DD Device **240a** connected to Port **140b**. The Device **100d** or **100e** has Paths **602**, **604**, **606**, **608**, **610**, **612**, **614**, and **616** which define transmit and receive differential signal paths between the SFP Ports **102a**, **104a**, **106a**, **108a**, **110a**, **112a**, **114a**, and **116a** and Circuitry **150d** or **150e**. Path **600** defines eight transmit and receive differential signal paths between the QSFP-DD Port **140b** and Circuitry **150d** and **150e** of the Device. The Circuitry **150d** or **150e** is comprised of input and output differential amplifiers and retimers through differential signal paths. Device **100d** has Circuitry **150d** whereas Device **100c** has Circuitry **150e**. The Circuitry **150e** of Device **100e** has a cross-connect switch which provides non-blocking cross-connects between all Paths. Further details on Circuitry **150d** and **150e** are illustrated in FIGS. **18** and **19**, respectively. The Second Network **30** includes Communication Equipment **400** having Port **402**.

(46) In this embodiment, the First Network **20** establishes a Demarcation Point **10** with Device **100d** or **100e** through QSFP-DD Device **240a**. A fiber Cable **500a** is used to interface the eight communication services between the Communication Equipment **400** and Device **100d** or **100e**, specifically connecting the fiber Cable **500a** from QSFP-DD Device **240a** in Port **140b** of Device **100d** or **100e** to Port **402** of the Communication Equipment **400** of the Second Network **30**. The Device **100d** or **100e** in turn connects to the Communication Equipment **300** of the First Network

20 through four fiber Cables **502a**, **504a**, **506a**, and **508a**. Fiber Cable **502a** connects SFP28 Device **202f** to Port **302** of the Communication Equipment **300**, a fiber Cable **504a** connects SFP28 Device **204f** to Port **304** of the Communication Equipment **300**, a fiber Cable **506a** connects SFP28 Device **206f** to Port **306** of the Communication Equipment **300**, and a fiber Cable **508a** connects SFP Device **208f** to Port **308** of the Communication Equipment **300** of the First Network **20**. The Device **100d** or **100e** connects another four fiber Cables **510a**, **512a**, **514a**, and **516a** to the Communication Equipment **310** of the First Network **20**. A fiber Cable **510a** connects SFP28 Device **210f** to Port **312** of the Communication Equipment **310**, a fiber Cable **512a** connects SFP28 Device **212f** to Port **314** of the Communication Equipment **310**, a fiber Cable **514a** connects SFP28 Device **214f** to Port **306** of the Communication Equipment **300**, and a fiber Cable **516a** connects SFP28 Device **216f** to Port **318** of the Communication Equipment **310** of the First Network **20**. The SFP28 and QSFP-DD Devices in this embodiment can be alternatively replaced by various other SFP Devices and their derivative. SFP Devices presently are defined for SFP, SFP+, SFP28, SFP56, QSFP, QSFP+, QSPF28, QSFP-DD and OSPF technologies. These other SFP Devices provide different media interfaces and connection types, e.g., wire cable, optical cable, coax cable, and wireless.

(47) FIG. **12** illustrates a diagram of another embodiment of the communications system and equipment of the present disclosure, wherein the Device **100d** or **100e** of the present disclosure establishes a Demarcation Point **10** between a First Network **20** and a Second Network **30**, specifically through SFP28 Device **202f**, **204f**, **206f**, **208f**, **210f**, **212f**, **214f**, and **216f** in communications with Port **402** and **404** on the Communication Equipment **400** of the Second Network, with Port **412** and **414**, on the Communication Equipment **410** of the Second Network, with Port **422** and **424**, on the Communication Equipment **420** of the Second Network, and with Port **432** and **434**, on the Communication Equipment **430** of the Second Network, respectively. The Device **100d** or **100e** provides a cost effective and efficient method and system for a communication service Demarcation Point by allowing the First Network to provide eight communications services. This embodiment allows the use of different cabling types, cable lengths, and the ability to change and replace any cable or SFP and QSFP type devices. This embodiment allows the communication services to be aggregated from separate communication equipment and different equipment locations. This embodiment also extend communication services, provide a method to manage heat dissipation on communication equipment, and provide a method to manage power dissipation on communication equipment by using low-power SFP, QSFP, QSFP+, QSFP28, QSFP-DD, and OSFP devices to mitigate heat and power, and the ability to deploy extended communication services.

(48) As illustrated in FIG. **12**, the First Network **20** is comprised of a Device **100d** or **100e** having nine Ports **102a**, **104a**, **106a**, **108a**, **110a**, **112a**, **114a**, **116a**, and **140b**, and Communication Equipment **300** having a Port **302**. The Device **100d** or **100e** has a SFP28 Device **202f** connected to Port **102a**, a SFP28 Device **204f** connected to Port **104a**, a SFP28 Device **206f** connected to Port **106a**, a SFP28 Device **208f** connected to Port **108a**, a SFP28 Device **210f** connected to Port **110a**, a SFP28 Device **212f** connected to Port **112a**, a SFP28 Device **214f** connected to Port **114a**, a SFP28 Device **216f** connected to Port **116a**, and a QSFP-DD Device **240a** connected to Port **140b**. The Device **100d** and **100e** have Paths **602**, **604**, **606**, **608**, **610**, **612**, **614**, and **616** which define transmit and receive differential signal paths between the SFP Ports **102a**, **104a**, **106a**, **108a**, **110a**, **112a**, **114a**, and **116a** and Circuitry **150d** or **150e** of the Device. Path **600** defines eight transmit and receive differential signal paths between the QSFP Port **140b** of the Device and Circuitry **150d** and **150e**. The Circuitry **150d** or **150e** is comprised of input and output differential amplifiers and retimers through differential signal paths. Device **100d** has Circuitry **150d** whereas Device **100e** has Circuitry **150e**. The Circuitry **150e** of Device **100e** has a cross-connect switch which provides non-blocking cross-connects between all Paths. Further details on Circuitry **150d** and **150e** are illustrated in FIGS. **18** and **19**, respectively. The Second Network **30** includes Communication

Equipment **400** having Ports **402** and **404**, Communication Equipment **410** having Ports **412** and **414**, Communication Equipment **420** having Ports **422** and **424**, and Communication Equipment **430** having Ports **432** and **434**.

(49) In this embodiment, the First Network **20** establishes a Demarcation Point **10** with Device **100d** or **100e** through SFP28 Device **202f**, **204f**, **206f**, **208f**, **210f**, **212f**, **214f**, and **216f**. Fiber Cables **502a** and **504a** are used to interface the communication services between the Communication Equipment **400** and Device **100d** or **100e**, specifically connecting the fiber Cable **502a** from SFP28 Device **202f** in Port **102a** of Device **100d** or **100e** to Port **402** of the Communication Equipment **400** and connecting the fiber Cable **504a** from SFP28 Device **204f** in Port **104a** of Device **100d** or **100e** to Port **404** of the Communication Equipment **400** of the Second Network **30**. Fiber Cables **506a** and **508a** are used to interface the communication services between the Communication Equipment **410** and Device **100d** or **100e**, specifically connecting the fiber Cable **506a** from SFP28 Device **206f** in Port **106a** of Device **100d** or **100e** to Port **412** of the Communication Equipment **410** and connecting the fiber Cable **508a** from SFP28 Device **208f** in Port **108a** of Device **100d** or **100e** to Port **414** of the Communication Equipment **410** of the Second Network **30**. Fiber Cables **510a** and **512a** are used to interface the communication services between the Communication Equipment **420** and Device **100d** or **100e**, specifically connecting the fiber Cable **510a** from SFP28 Device **210f** in Port **110a** of Device **100d** or **100e** to Port **422** of the Communication Equipment **420** and connecting the fiber Cable **512a** from SFP28 Device **212f** in Port **112a** of Device **100d** or **100e** to Port **424** of the Communication Equipment **420** of the Second Network **30**. Fiber Cables **514a** and **516a** are used to interface the communication services between the Communication Equipment **430** and Device **100d** or **100e**, specifically connecting the fiber Cable **514a** from SFP28 Device **214f** in Port **114a** of Device **100d** or **100e** to Port **432** of the Communication Equipment **430** and connecting the fiber Cable **516a** from SFP28 Device **216f** in Port **116a** of Device **100d** or **100e** to Port **434** of the Communication Equipment **430** of the Second Network **30**. The Device **100d** or **100e** in turn connects to the Communication Equipment **300** of the First Network **20** through a fiber Cable **500a**, specifically connecting the QSFP-DD Device **240a** in Port **140b** of Device **100d** or **100e** to the Port **302** of the Communication Equipment **300** of the First Network **20**.

(50) The SFP28 and QSFP-DD Devices in this embodiment can be alternatively replaced by various other SFP Devices and their derivative. SFP Devices presently are defined for SFP, SFP+, SFP28, SFP56, QSFP, QSFP+, QSPF28, QSFP-DD and OSFP technologies. These other SFP Devices provide different media interfaces and connection types, e.g., wire cable, optical cable, coax cable, and wireless.

(51) FIG. **13** illustrates a diagram of an embodiment of the communications system and equipment of the present disclosure, wherein a Device **100f** (if with circuitry **150f**) or **100g** (if with circuitry **150g**) interfaces eight communication services, four communication services from Communication Equipment **300** and four communication services from Communication Equipment **310**. The Device **100f** or **100g** then aggregates the eight communication services for transmission to Communication Equipment **400** by way of a single QSFP-DD Device **240a**. This embodiment allows the use of different cabling types, cable lengths, and the ability to change and replace any cable or QSFP-DD, OSFP and QSFP type devices. This embodiment allows the communication services to be aggregated from separate communication equipment and different equipment locations. This embodiment also allows the communication equipment to extend communication services, provide the communication equipment a method to manage heat dissipation on communication equipment, and provide the communication equipment a method to manage power usage, by having the communication equipment use lower power QSFP, QSFP-DD, and OSFP devices.

(52) As illustrated in FIG. **13**, the Network is comprised of a Device **100f** or **100g** having three Ports **102b**, **104b**, and **140b**, Communication Equipment **300** having a Port **302**, Communication

Equipment **310** having a Port **312**, and Communication Equipment **400** having one Port **402**. Cables **500a**, **502a**, and **504a** can individually vary in length, type, and material for the given application. The individual cables can be replaced for repair or application changes. The Device **100g** or **100f** has a QSFP28 Device **232a** connected to Port **102b**, a QSFP28 Device **234a** connected to Port **104b**, and a QSFP-DD Device **240a** connected to Port **140b**. The Device **100f** or **100g** has Paths **602** and **604**, which each Path defines four transmit and receive differential signal paths between the SFP Ports **102b** and **104b** and Circuitry **150f** or **150g** of the Device. Path **600** defines eight transmit and receive differential signal paths between the QSFP-DD Port **140b** and the Circuitry **150f** and **150g** of the Device. The Circuitry **150f** or **150g** is comprised of input and output differential amplifiers and retimers through differential signal paths, as shown and discussed in more detail with respect to FIGS. **20** and **21** respectively. Device **100f** has Circuitry **150f** whereas Device **100g** has Circuitry **150g**. The Circuitry **150g** of Device **100g** has a cross-connect switch which provides non-blocking cross-connects between all Paths. Further details on Circuitry **150f** and **150g** are illustrated in FIGS. **20** and **21**, respectively.

(53) A fiber Cable **502a** is used to interface four communication services between Communication Equipment **300** and Device **100f** or **100g**, specifically connecting the fiber Cable **502a** from QSFP28 Device **232a** in Port **102b** of Device **100f** or **100g** to Port **302** of the Communication Equipment **300**. A fiber Cable **504a** is used to interface the four communication services between Communication Equipment **310** and Device **100f** or **100g**, specifically connecting the fiber Cable **504a** from QSFP28 Device **234a** in Port **104b** to Port **312** of the Communication Equipment **310**. The Device **100f** or **100g** in turn connects to the Communication Equipment **400** through a fiber Cable **500a**, specifically connecting the QSFP-DD Device **240a** in Port **140b** of Device **100f** or **100g** to Port **402** of the Communication Equipment **400**.

(54) FIG. **14** illustrates a diagram of an embodiment of the communications system and equipment of the present disclosure, wherein a Device **100f** or **100g** of the present disclosure establishes a Demarcation Point **10** between a First Network **20** and a Second Network **30**, specifically through QSFP-DD Device **240a** in Port **140b**, in communication with a Port **402** on the Communication Equipment **400** of the Second Network **30**. The Device **100f** or **100g** provides a cost effective and efficient method and system of providing Demarcation Point on eight communication services by way of a single QSFP-DD Device **240a**. This embodiment allows the use of different cabling types, cable lengths, and the ability to change and replace any cable or QSFP-DD, OSFP and QSFP28 type devices. This embodiment allows the communication services to be aggregated from separate communication equipment and different equipment locations. This embodiment also allows the communication equipment to extend communication services, provide the communication equipment a method to manage heat dissipation on communication equipment, and provide the communication equipment a method to manage power usage, by having the communication equipment use lower power QSFP+, QSFP28, QSFP-DD, and OSFP devices.

(55) As illustrated in FIG. **14**, the First Network **20** is comprised of a Device **100f** or **100g** having three Ports **102b**, **104b**, and **140b**, Communication Equipment **300** having a Port **302**, and Communication Equipment **310** having a Port **312**. Cables **500a**, **502a**, and **504a** can individually vary in length, type, and material for the given application. The individual cables can be replaced for repair or application changes. The Device **100g** or **100f** has a QSFP28 Device **232a** connected to Port **102b**, a QSFP28 Device **234a** connected to Port **104b**, and a QSFP-DD Device **240a** connected to Port **140b**. The Device **100f** or **100g** has Paths **602** and **604**, which each Path defines four transmit and receive differential signal paths between the SFP Ports **102b** and **104b** and Circuitry **150f** or **150g** of the Device. Path **600** defines eight transmit and receive differential signal paths between the QSFP-DD Port **140b** and the Circuitry **150f** and **150g** of the Device. The Circuitry **150f** or **150g** is comprised of input and output differential amplifiers and retimers through differential signal paths. Device **100f** has Circuitry **150f** whereas Device **100g** has Circuitry **150g**. The Circuitry **150g** of Device **100g** has a cross-connect switch which provides non-blocking cross-

connects between all Paths. Further details on Circuitry **150f** and **150g** are illustrated in FIGS. **20** and **21**, respectively. The Second Network **30** includes Communication Equipment **400** having Port **402**.

(56) In this embodiment, the First Network **20** establishes a Demarcation Point **10** with Device **100f** or **100g** through QSFP-DD Device **240a**. A fiber Cable **502a** is used to interface four communication services between Communication Equipment **300** and Device **100f** or **100g**, specifically connecting the fiber Cable **502a** from QSFP28 Device **232a** in Port **102b** of Device **100f** or **100g** to Port **302** of the Communication Equipment **300**. A fiber Cable **504a** is used to interface four communication services between Communication Equipment **310** and Device **100f** or **100g**, specifically connecting the fiber Cable **504a** from QSFP28 Device **234a** in Port **104b** to Port **312** of the Communication Equipment **310**. The Device **100f** or **100g** in turn connects to the Communication Equipment **400** through a fiber Cable **500a**, specifically connecting the QSFP-DD Device **240a** in Port **140b** of Device **100f** or **100g** to Port **402** of the Communication Equipment **400**.

(57) FIG. **15** illustrates a diagram of an embodiment of the communications system and equipment of the present disclosure, wherein a Device **100f** or **100g** of the present disclosure establishes a Demarcation Point **10** between a First Network **20** and a Second Network **30**, specifically through QSFP28 Device **232a** in Port **102b**, in communication with a Port **402** on the Communication Equipment **400** of the Second Network **30** and QSFP28 Device **234a** in Port **104b**, in communication with a Port **412** on the Communication Equipment **410** of the Second Network **30**. The Device **100f** or **100g** provides a cost effective and efficient method and system of providing Demarcation Point on eight communication services by way of a single QSFP-DD Device **240a**. This embodiment allows the use of different cabling types, cable lengths, and the ability to change and replace any cable or QSFP-DD, OSFP, QSFP28, other QSFP type devices. This embodiment allows the communication services to be aggregated from separate communication equipment and different equipment locations. This embodiment also allows the communication equipment to extend communication services, provide the communication equipment a method to manage heat dissipation on communication equipment, and provide the communication equipment a method to manage power usage, by having the communication equipment use lower power QSFP+, QSFP28, QSFP-DD, and OSFP devices.

(58) As illustrated in FIG. **15**, the First Network **20** is comprised of a Device **100f** or **100g** having three Ports **102b**, **104b**, and **140b**, and Communication Equipment **300** having a Port **302**. Cables **500a**, **502a**, and **504a** can individually vary in length, type, and material for the given application. The individual cables can be replaced for repair or application changes. The Device **100g** or **100f** has a QSFP28 Device **232a** connected to Port **102b**, a QSFP28 Device **234a** connected to Port **104b**, and a QSFP-DD Device **240a** connected to Port **140b**. The Device **100f** or **100g** has Paths **602** and **604**, which each Path defines four transmit and receive differential signal paths between the SFP Ports **102b** and **104b** and Circuitry **150f** or **150g** of the Device. Path **600** defines eight transmit and receive differential signal paths between the QSFP-DD Port **140b** and the Circuitry **150f** and **150g** of the Device. The Circuitry **150f** or **150g** is comprised of input and output differential amplifiers and retimers through differential signal paths. Device **100f** has Circuitry **150f** whereas Device **100g** has Circuitry **150g**. The Circuitry **150g** of Device **100g** has a cross-connect switch which provides non-blocking cross-connects between all Paths. Further details on Circuitry **150f** and **150g** are illustrated in FIGS. **20** and **21**, respectively. The Second Network **30** includes Communication Equipment **400** having Port **402** and Communication Equipment **410** having Port **412**.

(59) In this embodiment, the First Network **20** establishes a Demarcation Point **10** with Device **100f** or **100g** through QSFP28 Device **232a** and **234a**. A fiber Cable **502a** is used to interface four communication services between Communication Equipment **400** and Device **100f** or **100g**, specifically connecting the fiber Cable **502a** from QSFP28 Device **232a** in Port **102b** of Device

100f or **100g** to Port **402** of the Communication Equipment **400**. A fiber Cable **504a** is used to interface the four communication services between Communication Equipment **410** and Device **100f** or **100g**, specifically connecting the fiber Cable **504a** from QSFP28 Device **234a** in Port **104b** to Port **412** of the Communication Equipment **410**. The Device **100f** or **100g** in turn connects to the Communication Equipment **300** through a fiber Cable **500a**, specifically connecting the QSFP-DD Device **240a** in Port **140b** of Device **100f** or **100g** to Port **302** of the Communication Equipment **300**.

(60) FIG. **16** illustrates a schematic diagram of one embodiment of the Circuitry **150a** of the present disclosure, representing for example a communication Device **100a** with a plurality of Port connectors **102a**, **104a**, **106a**, **108a**, and **140a**, which are each connected to an input and output differential amplifier, wherein the differential amplifiers connect to a retimer. As shown in FIG. **16**, the communication Device **100a** port connectors Port **102a**, Port **104a**, Port **106a**, and Port **108a**, also correspondingly represented as Port **1**, Port **2**, Port **3**, and Port **4** respectively, are each configured to interface two differential signal paths, specifically a transmit and receive differential signal path from a Network. The communication Device **100a** port connector Port **140a** also represented as Port **5**, is configured to interface eight differential signal paths, specifically four transmit and receive differential signal paths from a Network. Further, in use, a SFP Device as described above is inserted into Port **102a**, Port **104a**, Port **106a**, and Port **108a** and a QSFP Device as described above is inserted into Port **140a**. The QSFP and SFP Devices connect to one or more cables as described above. The QSFP and SFP Devices can be alternatively replaced by various other derivatives of QSFP and SFP Devices, respectively.

(61) More specifically, FIG. **16** illustrates a diagram of Circuitry **150a** of the present disclosure involving five Ports and sixteen differential signal paths. Port **1** has two differential signal paths **P1** and **P2**, represented as **602**. Port **2** has two differential signal paths **P3** and **P4**, represented as **604**. Port **3** has two differential signal paths **P5** and **P6**, represented as **606**. Port **4** has two differential signal paths **P7** and **P8**, represented as **608**. Port **5** has eight differential signal paths **P9**, **P10**, **P11**, **P12**, **P13**, **P14**, **P15**, and **P16**, represented as **600**.

(62) As illustrated in FIG. **16**, there are eight input broadband differential amplifiers **A1**, **A2**, **A3**, **A4**, **A5**, **A6**, **A7**, and **A8**, represented collectively as **156**. The broadband differential amplifiers provide amplification and conditioning of the input signal. There are eight retimers **RT1**, **RT2**, **RT3**, **RT4**, **RT5**, **RT6**, **RT7**, and **RT8**, represented collectively as **154**. The retimers extract timing from the input signals and retransmit the signal with a corrected timing. The retimer removes jitter and inter-symbol interference from the input signal. There are eight high speed output differential amplifiers **Y1**, **Y2**, **Y3**, **Y4**, **Y5**, **Y6**, **Y7**, and **Y8**, represented collectively as **152**. The high speed output differential amplifiers provide fixed or variable output voltages with and without pre-emphasis. Highly integrated circuits (IC) incorporate the input broadband differential amplifiers, retimers, and the output broadband differential amplifiers. Low latency of 350 ps and lower are achieved with using differential signal paths between the input differential amplifiers **A**, the output differential amplifiers **Y**, and retimers **RT**.

(63) Port **1** comprises a path **P1** representing an output differential signal and a path **P2** representing an input differential signal. Port **2** comprises a path **P3** representing an output differential signal and a path **P4** representing an input differential signal. Port **3** comprises a path **P5** representing an output differential signal and a path **P6** representing an input differential signal. Port **4** comprises a path **P7** representing an output differential signal and a path **P8** representing an input differential signal. Port **5** comprises a path **P9** representing an output differential signal, a path **P10** representing an input differential signal, a path **P11** representing an output differential signal, a path **P12** representing an input differential signal, a path **P13** representing an output differential signal, a path **P14** representing an input differential signal, a path **P15** representing an output differential signal, and a path **P16** representing an input differential signal.

(64) Path **P1** output differential signals connect to the output differential amplifier **Y1**. The input

signal to differential amplifier Y1 can be a differential or common-mode signal. This input signal to differential amplifier Y1 connects to the output of retimer RT1.

(65) Path P2 input differential signals connect to the input differential amplifier A2. The output signal from differential amplifier A2 can be a differential or common-mode signal. This output signal from differential amplifier A2 connects to the input of retimer RT2.

(66) Path P3 output differential signals connect to the output differential amplifier Y3. The input signal to differential amplifier Y3 can be a differential or common-mode signal. This input signal to differential amplifier Y3 connects to the output of retimer RT3.

(67) Path P4 input differential signals connect to the input differential amplifier A4. The output signal from differential amplifier A4 can be a differential or common-mode signal. This output signal from differential amplifier A4 connects to the input of retimer RT4.

(68) Path P5 output differential signals connect to the output differential amplifier Y5. The input signal to differential amplifier Y5 can be a differential or common-mode signal. This input signal to differential amplifier Y5 connects to the output of retimer RT5.

(69) Path P6 input differential signals connect to the input differential amplifier A6. The output signal from differential amplifier A6 can be a differential or common-mode signal. This output signal from differential amplifier A6 connects to the input of retimer RT6.

(70) Path P7 output differential signals connect to the output differential amplifier Y7. The input signal to differential amplifier Y7 can be a differential or common-mode signal. This input signal to differential amplifier Y7 connects to the output of retimer RT7.

(71) Path P8 input differential signals connect to the input differential amplifier A8. The output signal from differential amplifier A8 can be a differential or common-mode signal. This output signal from differential amplifier A8 connects to the input of retimer RT8.

(72) Path P9 output differential signals connect to the output differential amplifier Y8. The input signal to differential amplifier Y8 can be a differential or common-mode signal. This input signal to differential amplifier Y8 connects to the output of retimer RT8.

(73) Path P10 input differential signals connect to the input differential amplifier A7. The output signal from differential amplifier A7 can be a differential or common-mode signal. This output signal from differential amplifier A7 connects to the input of retimer RT7.

(74) Path P11 output differential signals connect to the output differential amplifier Y6. The input signal to differential amplifier Y6 can be a differential or common-mode signal. This input signal to differential amplifier Y6 connects to the output of retimer RT6.

(75) Path P12 input differential signals connect to the input differential amplifier A5. The output signal from differential amplifier A5 can be a differential or common-mode signal. This output signal from differential amplifier A5 connects to the input of retimer RT5.

(76) Path P13 output differential signals connect to the output differential amplifier Y4. The input signal to differential amplifier Y4 can be a differential or common-mode signal. This input signal to differential amplifier Y4 connects to the output of retimer RT4.

(77) Path P14 input differential signals connect to the input differential amplifier A3. The output signal from differential amplifier A3 can be a differential or common-mode signal. This output signal from differential amplifier A3 connects to the input of retimer RT3.

(78) Path P15 output differential signals connect to the output differential amplifier Y2. The input signal to differential amplifier Y2 can be a differential or common-mode signal. This input signal to differential amplifier Y2 connects to the output of retimer RT2.

(79) Path P16 input differential signals connect to the input differential amplifier A1. The output signal from differential amplifier A1 can be a differential or common-mode signal. This output signal from differential amplifier A1 connects to the input of retimer RT1.

(80) FIG. 17 illustrates a schematic diagram of one embodiment of the Circuitry 150b of the present disclosure, representing for example a communication Device 100b with a plurality of Port connectors 102a, 104a, 106a, 108a, and 140a, which are each connected to an input and output

differential amplifier, wherein the input differential amplifier connects to a cross-point switch, the cross-point switch connects to the retimer, and the retimer connects to the output differential amplifier. As shown in FIG. 17, the communication Device **100b** port connectors Port **102a**, Port **104a**, Port **106a**, and Port **108a** also correspondingly represented as Port **1**, Port **2**, Port **3**, and Port **4** respectively, are each configured to interface two differential signal paths, specifically a transmit and receive differential signal path from a Network. The communication Device **100b** port connector Port **140a** also represented as Port **5**, is configured to interface eight differential signal paths, specifically four transmit and receive differential signal paths to a Network. Further, in use, a SFP Device as described above is inserted into Port **102a**, Port **104a**, Port **106a**, and Port **108a** and a QSFP Device as described above is inserted into Port **140a**. The QSFP and SFP Devices connect to one or more cables as described above. The QSFP and SFP Devices can be alternatively replaced by various other derivatives of QSFP and SFP Devices, respectively.

(81) More specifically, FIG. 17 illustrates a diagram of Circuitry **150b** of the present disclosure involving five Ports and sixteen differential signal paths. Port **1** has two differential signal paths P1 and P2, represented as **602**. Port **2** has two differential signal paths P3 and P4, represented as **604**. Port **3** has two differential signal paths P5 and P6, represented as **606**. Port **4** has two differential signal paths P7 and P8, represented as **608**. Port **5** has eight differential signal paths P9, P10, P11, P12, P13, P14, P15, and P16, represented as **600**.

(82) As illustrated in FIG. 17, there are eight input broadband differential amplifiers A1, A2, A3, A4, A5, A6, A7, and A8, represented collectively as **156**. The broadband differential amplifiers provide amplification and conditioning of the input signal. There are eight retimers RT1, RT2, RT3, RT4, RT5, RT6, RT7, and RT8, represented collectively as **154**. The retimers extract timing from the input signals and retransmit the signal with a corrected timing. The retimer removes jitter and inter-symbol interference from the input signal. There is an 8×8 non-blocking cross-point switch SW, represented as **158a**. The 8×8 non-blocking cross-point Switch **158a** allows any output O to be connected to any input I of the switch SW. There are eight high speed output differential amplifiers Y1, Y2, Y3, Y4, Y5, Y6, Y7, and Y8, represented collectively as **152**. The high speed output differential amplifiers provide fixed or variable output voltages with and without pre-emphasis. Highly integrated circuits (IC) incorporate the input broadband differential amplifiers, retimers, and the output broadband differential amplifiers. Low latency of 350 ps and lower are achieved with using differential signal paths between the input differential amplifiers A, the output differential amplifiers Y, the retimers RT, and the cross-point switch SW.

(83) Port **1** comprises a path P1 representing an output differential signal and a path P2 representing an input differential signal. Port **2** comprises a path P3 representing an output differential signal and a path P4 representing an input differential signal. Port **3** comprises a path P5 representing an output differential signal and a path P6 representing an input differential signal. Port **4** comprises a path P7 representing an output differential signal and a path P8 representing an input differential signal. Port **5** comprises a path P9 representing an output differential signal, a path P10 representing an input differential signal, a path P11 representing an output differential signal, a path P12 representing an input differential signal, a path P13 representing an output differential signal, a path P14 representing an input differential signal, a path P15 representing an output differential signal, and a path P16 representing an input differential signal.

(84) Path P1 output differential signals connect to the output differential amplifier Y1. The input signal to differential amplifier Y1 can be a differential or common-mode signal. This input signal to differential amplifier Y1 connects to the output O1 of the cross-point switch SW.

(85) Path P2 input differential signals connect to the input differential amplifier A2. The output signal from differential amplifier A2 can be a differential or common-mode signal. This output signal from differential amplifier A2 connects to the input of retimer RT2. The output of the retimer RT2 connects to the input I2 of the cross-point switch SW.

(86) Path P3 output differential signals connect to the output differential amplifier Y3. The input

signal to differential amplifier Y3 can be a differential or common-mode signal. This input signal to differential amplifier Y3 connects to the output O3 of the cross-point switch SW.

(87) Path P4 input differential signals connect to the input differential amplifier A4. The output signal from differential amplifier A4 can be a differential or common-mode signal. This output signal from differential amplifier A4 connects to the input of retimer RT4. The output of the retimer RT4 connects to the input I4 of the cross-point switch SW.

(88) Path P5 output differential signals connect to the output differential amplifier Y5. The input signal to differential amplifier Y5 can be a differential or common-mode signal. This input signal to differential amplifier Y5 connects to the output O5 of the cross-point switch SW.

(89) Path P6 input differential signals connect to the input differential amplifier A6. The output signal from differential amplifier A6 can be a differential or common-mode signal. This output signal from differential amplifier A6 connects to the input of retimer RT6. The output of the retimer RT6 connects to the input I6 of the cross-point switch SW.

(90) Path P7 output differential signals connect to the output differential amplifier Y7. The input signal to differential amplifier Y7 can be a differential or common-mode signal. This input signal to differential amplifier Y7 connects to the output O7 of the cross-point switch SW.

(91) Path P8 input differential signals connect to the input differential amplifier A8. The output signal from differential amplifier A8 can be a differential or common-mode signal. This output signal from differential amplifier A8 connects to the input of retimer RT8. This output of the retimer RT8 connects to the input I8 of the cross-point switch SW.

(92) Path P9 output differential signals connect to the output differential amplifier Y8. The input signal to differential amplifier Y8 can be a differential or common-mode signal. This input signal to differential amplifier Y8 connects to the output O8 of the cross-point switch SW.

(93) Path P10 input differential signals connect to the input differential amplifier A7. The output signal from differential amplifier A7 can be a differential or common-mode signal. This output signal from differential amplifier A7 connects to the input of the retimer RT7. The output of the retimer RT7 connects to the input I7 of cross-point switch SW.

(94) Path P11 output differential signals connect to the output differential amplifier Y6. The input signal to differential amplifier Y6 can be a differential or common-mode signal. This input signal to differential amplifier Y6 connects to the output O6 of the cross-point switch SW.

(95) Path P12 input differential signals connect to the input differential amplifier A5. The output signal from differential amplifier A5 can be a differential or common-mode signal. This output signal from differential amplifier A5 connects to the input of the retimer RT5. The output of the retimer RT5 connects to the input I5 of cross-point switch SW.

(96) Path P13 output differential signals connect to the output differential amplifier Y4. The input signal to differential amplifier Y4 can be a differential or common-mode signal. This input signal to differential amplifier Y4 connects to the output O4 of the cross-point switch SW.

(97) Path P14 input differential signals connect to the input differential amplifier A3. The output signal from differential amplifier A3 can be a differential or common-mode signal. This output signal from differential amplifier A3 connects to the input of the retimer RT3. The output of the retimer RT3 connects to the input I3 of cross-point switch SW.

(98) Path P15 output differential signals connect to the output differential amplifier Y2. The input signal to differential amplifier Y2 can be a differential or common-mode signal. This input signal to differential amplifier Y2 connects to the output O2 of the cross-point switch SW.

(99) Path P16 input differential signals connect to the input differential amplifier A1. The output signal from differential amplifier A1 can be a differential or common-mode signal. This output signal from differential amplifier A1 connects to the input of the retimer RT1. The output of the retimer RT1 connects to the input I1 of cross-point switch SW.

(100) FIG. 18 illustrates a schematic diagram of one embodiment of the Circuitry 150d of the present disclosure, representing for example a communication Device 100d with a plurality of Port

connectors **102a**, **104a**, **106a**, **108a**, **110a**, **112a**, **114a**, **116a**, and **140b**, which are each connected to an input and output differential amplifier, wherein the differential amplifier connects to a retimer. As shown in FIG. **18**, the communication Device **100d** eight port connectors Port **102a**, Port **104a**, Port **106a**, Port **108a**, Port **110a**, Port **112a**, Port **114a**, and Port **116a** also correspondingly represented as Port **1**, Port **2**, Port **3**, Port **4**, Port **5**, Port **6**, Port **7**, and Port **8** respectively, are each configured to interface two differential signal paths, specifically a transmit and receive differential signal path, to a Network. The communication Device **100d** connector Port **140b** also represented as Port **9** is configured to interface sixteen differential signal paths, specifically eight transmit and receive differential signal paths, to the Network. Further, in use, a SFP Device as described above is inserted into Port **102a**, Port **104a**, Port **106a**, Port **108a**, Port **110a**, Port **112a**, Port **114a** and Port **116a** and a QSFP-DD Device as described above is inserted into Port **140b**. The QSFP-DD and SFP28 Devices connect to one or more cables as described above. The QSFP-DD and SFP28 Devices can be alternatively replaced by various other derivatives of QSFP-DD and SFP28 Devices, respectively.

(101) More specifically, FIG. **18** illustrates a diagram of Circuitry **150d** of the present disclosure involving nine Ports and thirty two differential signal paths. Port **1** has two differential signal paths **P1** and **P2**, represented as **602**. Port **2** has two differential signal paths **P3** and **P4**, represented as **604**. Port **3** has two differential signal paths **P5** and **P6**, represented as **606**. Port **4** has two differential signal paths **P7** and **P8**, represented as **608**. Port **5** has two differential signal paths **P9** and **P10**, represented as **610**. Port **6** has two differential signal paths **P11** and **P12**, represented as **612**. Port **7** has two differential signal paths **P13** and **P14**, represented as **614**. Port **8** has two differential signal paths **P15** and **P16**, represented as **616**. Port **9** has sixteen differential signal paths **P17**, **P18**, **P19**, **P20**, **P21**, **P22**, **P23**, **P24**, **P25**, **P26**, **P27**, **P28**, **P29**, **P30**, **P31**, and **P32**, represented as **600**.

(102) As illustrated in FIG. **18**, there are sixteen input broadband differential amplifiers **A1**, **A2**, **A3**, **A4**, **A5**, **A6**, **A7**, **A8**, **A9**, **A10**, **A11**, **A12**, **A13**, **A14**, **A15**, and **A16**, represented collectively as **156**. The broadband differential amplifiers provide amplification and conditioning of the input signal. There are sixteen retimers **RT1**, **RT2**, **RT3**, **RT4**, **RT5**, **RT6**, **RT7**, **RT8**, **RT9**, **RT10**, **RT11**, **RT12**, **RT13**, **RT14**, **RT15**, and **RT16**, represented collectively as **154**. The retimers extract timing from the input signals and retransmit the signal with a corrected timing. The retimer removes jitter and inter-symbol interference from the input signal. There are sixteen high speed output differential amplifiers **Y1**, **Y2**, **Y3**, **Y4**, **Y5**, **Y6**, **Y7**, **Y8**, **Y9**, **Y10**, **Y11**, **Y12**, **Y13**, **Y14**, **Y15**, and **Y16**, represented collectively as **152**. The high speed output differential amplifiers provide fixed or variable output voltages with and without pre-emphasis. Highly integrated circuits (IC) incorporate the input broadband differential amplifiers, retimers, and the output broadband differential amplifiers. Low latency of 350 ps and lower are achieved with using differential signal paths between the input differential amplifiers **A**, the output differential amplifiers **Y**, and the retimers **RT**.

(103) Port **1** comprises a path **P1** representing an output differential signal and a path **P2** representing an input differential signal. Port **2** comprises a path **P3** representing an output differential signal and a path **P4** representing an input differential signal. Port **3** comprises a path **P5** representing an output differential signal and a path **P6** representing an input differential signal. Port **4** comprises a path **P7** representing an output differential signal and a path **P8** representing an input differential signal. Port **5** comprises a path **P9** representing an output differential signal and a path **P10** representing an input differential signal. Port **6** comprises a path **P11** representing an output differential signal and a path **P12** representing an input differential signal. Port **7** comprises a path **P13** representing an output differential signal and a path **P14** representing an input differential signal. Port **8** comprises a path **P15** representing an output differential signal and a path **P16** representing an input differential signal. Port **9** comprises a path **P17** representing an output differential signal, a path **P18** representing an input differential signal, a path **P19** representing an output differential signal, a path **P20** representing an input differential signal, a path **P21**

representing an output differential signal, a path P22 representing an input differential signal, a path P23 representing an output differential signal, and a path P24 representing an input differential signal, a path P25 representing an output differential signal, a path P26 representing an input differential signal, a path P27 representing an output differential signal, a path P28 representing an input differential signal, a path P29 representing an output differential signal, a path P30 representing an input differential signal, a path P31 representing an output differential signal, and a path P32 representing an input differential signal.

(104) Path P1 output differential signals connect to the output differential amplifier Y1. The input signal to differential amplifier Y1 can be a differential or common-mode signal. This input signal to differential amplifier Y1 connects to the output of retimer RT1.

(105) Path P2 input differential signals connect to the input differential amplifier A2. The output signal from differential amplifier A2 can be a differential or common-mode signal. This output signal from differential amplifier A2 connects to the input of retimer RT2.

(106) Path P3 output differential signals connect to the output differential amplifier Y3. The input signal to differential amplifier Y3 can be a differential or common-mode signal. This input signal to differential amplifier Y3 connects to the output of retimer RT3.

(107) Path P4 input differential signals connect to the input differential amplifier A4. The output signal from differential amplifier A4 can be a differential or common-mode signal. This output signal from differential amplifier A4 connects to the input of retimer RT4.

(108) Path P5 output differential signals connect to the output differential amplifier Y5. The input signal to differential amplifier Y5 can be a differential or common-mode signal. This input signal to differential amplifier Y5 connects to the output of retimer RT5.

(109) Path P6 input differential signals connect to the input differential amplifier A6. The output signal from differential amplifier A6 can be a differential or common-mode signal. This output signal from differential amplifier A6 connects to the input of retimer RT6.

(110) Path P7 output differential signals connect to the output differential amplifier Y7. The input signal to differential amplifier Y7 can be a differential or common-mode signal. This input signal to differential amplifier Y7 connects to the output of retimer RT7.

(111) Path P8 input differential signals connect to the input differential amplifier A8. The output signal from differential amplifier A8 can be a differential or common-mode signal. This output signal from differential amplifier A8 connects to the input of retimer RT8.

(112) Path P9 output differential signals connect to the output differential amplifier Y9. The input signal to differential amplifier Y9 can be a differential or common-mode signal. This input signal to differential amplifier Y9 connects to the output of retimer RT9.

(113) Path P10 input differential signals connect to the input differential amplifier A10. The output signal from differential amplifier A10 can be a differential or common-mode signal. This output signal from differential amplifier A10 connects to the input of retimer RT10.

(114) Path P11 output differential signals connect to the output differential amplifier Y11. The input signal to differential amplifier Y11 can be a differential or common-mode signal. This input signal to differential amplifier Y11 connects to the output of retimer RT11.

(115) Path P12 input differential signals connect to the input differential amplifier A12. The output signal from differential amplifier A12 can be a differential or common-mode signal. This output signal from differential amplifier A12 connects to the input of retimer RT12.

(116) Path P13 output differential signals connect to the output differential amplifier Y13. The input signal to differential amplifier Y13 can be a differential or common-mode signal. The input signal to differential amplifier Y13 connects to the output of retimer RT13.

(117) Path P14 input differential signals connect to the input differential amplifier A14. The output signal from differential amplifier A14 can be a differential or common-mode signal. This output signal from differential amplifier A14 connects to the input of retimer RT14.

(118) Path P15 output differential signals connect to the output differential amplifier Y15. The

input signal to differential amplifier Y15 can be a differential or common-mode signal. This input signal to differential amplifier Y15 connects to the output of retimer RT15.

(119) Path P16 input differential signals connect to the input differential amplifier A16. The output signal from differential amplifier A16 can be a differential or common-mode signal. This output signal from differential amplifier A16 connects to the input of retimer RT16.

(120) Path P17 output differential signals connect to the output differential amplifier Y16. The input signal to differential amplifier Y16 can be a differential or common-mode signal. This input signal to differential amplifier Y16 connects to the output of retimer RT16.

(121) Path P18 input differential signals connect to the input differential amplifier A15. The output signal from differential amplifier A15 can be a differential or common-mode signal. This output signal from differential amplifier A15 connects to the input of retimer RT15.

(122) Path P19 output differential signals connect to the output differential amplifier Y14. The input signal to differential amplifier Y14 can be a differential or common-mode signal. This input signal to differential amplifier Y14 connects to the output of retimer RT14.

(123) Path P20 input differential signals connect to the input differential amplifier A13. The output signal from differential amplifier A13 can be a differential or common-mode signal. This output signal from differential amplifier A13 connects to the input of retimer RT13.

(124) Path P21 output differential signals connect to the output differential amplifier Y12. The input signal to differential amplifier Y12 can be a differential or common-mode signal. This input signal to differential amplifier Y12 connects to the output of retimer RT12.

(125) Path P22 input differential signals connect to the input differential amplifier A11. The output signal from differential amplifier A11 can be a differential or common-mode signal. This output signal from differential amplifier A11 connects to the input of retimer RT11.

(126) Path P23 output differential signals connect to the output differential amplifier Y10. The input signal to differential amplifier Y10 can be a differential or common-mode signal. This input signal to differential amplifier Y10 connects to the output of retimer RT10.

(127) Path P24 input differential signals connect to the input differential amplifier A9. The output signal from differential amplifier A9 can be a differential or common-mode signal. This output signal from differential amplifier A9 connects to the input of retimer RT9.

(128) Path P25 output differential signals connect to the output differential amplifier Y8. The input signal to differential amplifier Y8 can be a differential or common-mode signal. This input signal to differential amplifier Y8 connects to the output of retimer RT8.

(129) Path P26 input differential signals connect to the input differential amplifier A7. The output signal from differential amplifier A7 can be a differential or common-mode signal. This output signal from differential amplifier A7 connects to the input of retimer RT7.

(130) Path P27 output differential signals connect to the output differential amplifier Y6. The input signal to differential amplifier Y6 can be a differential or common-mode signal. This input signal to differential amplifier Y6 connects to the output of retimer RT6.

(131) Path P28 input differential signals connect to the input differential amplifier A5. The output signal from differential amplifier A5 can be a differential or common-mode signal. This output signal from differential amplifier A5 connects to the input of retimer RT5.

(132) Path P29 output differential signals connect to the output differential amplifier Y4. The input signal to differential amplifier Y4 can be a differential or common-mode signal. The input signal to differential amplifier Y4 connects to the output of retimer RT4.

(133) Path P30 input differential signals connect to the input differential amplifier A3. The output signal from differential amplifier A3 can be a differential or common-mode signal. This output signal from differential amplifier A3 connects to the input of retimer RT3.

(134) Path P31 output differential signals connect to the output differential amplifier Y2. The input signal to differential amplifier Y2 can be a differential or common-mode signal. This input signal to differential amplifier Y2 connects to the output of retimer RT2.

(135) Path P32 input differential signals connect to the input differential amplifier A1. The output signal from differential amplifier A1 can be a differential or common-mode signal. This output signal from differential amplifier A1 connects to the input of retimer RT1.

(136) FIG. 19 illustrates a schematic diagram of one embodiment of the Circuitry 150e of the present disclosure, representing for example a communication Device 100e with a plurality of Port connectors 102a, 104a, 106a, 108a, 110a, 112a, 114a, 116a, and 140b, which are each connected to an input and output differential amplifier, wherein the input differential amplifier connects to a cross-point switch, the cross-point switch connects to the retimer, the retimer connects to the output differential amplifier. As shown in FIG. 19, the communication Device 100e eight port connectors Port 102a, Port 104a, Port 106a, Port 108a, Port 110a, Port 112a, Port 114a, and Port 116a also correspondingly represented as Port 1, Port 2, Port 3, Port 4, Port 5, Port 6, Port 7, and Port 8 respectively, are each configured to interface two differential signal paths, specifically a transmit and receive differential signal path, to a Network. The communication Device 100e connector Port 140b also represented as Port 9 is configured to interface sixteen differential signal paths, specifically eight transmit and receive differential signal paths, to a Network. Further, in use, a SFP Device as described above is inserted into Port 102a, Port 104a, Port 106a, Port 108a, Port 110a, Port 112a, Port 114a and Port 116a and a QSFP-DD Device as described above is inserted into Port 140b. The QSFP-DD and SFP Devices connect to one or more cables as described above. The QSFP-DD and SFP Device can be alternatively replaced by various other derivatives of QSFP-DD and SFP Devices, respectively.

(137) More specifically, FIG. 19 illustrates a diagram of Circuitry 150e of the present disclosure involving nine Ports and thirty-two differential signal paths. Port 1 has two differential signal paths P1 and P2, represented as 602. Port 2 has two differential signal paths P3 and P4, represented as 604. Port 3 has two differential signal paths P5 and P6, represented as 606. Port 4 has two differential signal paths P7 and P8, represented as 608. Port 5 has two differential signal paths P9 and P10, represented as 610. Port 6 has two differential signal paths P11 and P12, represented as 612. Port 7 has two differential signal paths P13 and P14, represented as 614. Port 8 has two differential signal paths P15 and P16, represented as 616. Port 9 has sixteen differential signal paths P17, P18, P19, P20, P21, P22, P23, P24, P25, P26, P27, P28, P29, P30, P31, and P32, represented as 130.

(138) As illustrated in FIG. 19, there are sixteen input broadband differential amplifiers A1, A2, A3, A4, A5, A6, A7, A8, A9, A10, A11, A12, A13, A14, A15, and A16, represented collectively as 156. The broadband differential amplifiers provide amplification and conditioning of the input signal. There are sixteen retimers RT1, RT2, RT3, RT4, RT5, RT6, RT7, RT8, RT9, RT10, RT11, RT12, RT13, RT14, RT15, and RT16, represented collectively as 154. The retimers extract timing from the input signals and retransmit the signal with a corrected timing. The retimer removes jitter and inter-symbol interference from the input signal. There is a 16×16 non-blocking cross-point switch SW, represented as 158b. The 16×16 non-blocking cross-point Switch 158b allows any output O to be connected to any input I of the switch SW. There are sixteen high speed output differential amplifiers Y1, Y2, Y3, Y4, Y5, Y6, Y7, Y8, Y9, Y10, Y11, Y12, Y13, Y14, Y15, and Y16, represented collectively as 152. The high speed output differential amplifiers provide fixed or variable output voltages with and without pre-emphasis. Highly integrated circuits (IC) incorporate the input broadband differential amplifiers, retimers, and the output broadband differential amplifiers. Low latency of 350 ps and lower are achieved with using differential signal paths between the input differential amplifiers A, the output differential amplifiers Y, the retimers RT, and the cross-point switch SW.

(139) Port 1 comprises a path P1 representing an output differential signal and a path P2 representing an input differential signal. Port 2 comprises a path P3 representing an output differential signal and a path P4 representing an input differential signal. Port 3 comprises a path P5 representing an output differential signal and a path P6 representing an input differential signal.

Port **4** comprises a path **P7** representing an output differential signal and a path **P8** representing an input differential signal. Port **5** comprises a path **P9** representing an output differential signal and a path **P10** representing an input differential signal. Port **6** comprises a path **P11** representing an output differential signal and a path **P12** representing an input differential signal. Port **7** comprises a path **P13** representing an output differential signal and a path **P14** representing an input differential signal. Port **8** comprises a path **P15** representing an output differential signal and a path **P16** representing an input differential signal. Port **9** comprises a path **P17** representing an output differential signal, a path **P18** representing an input differential signal, a path **P19** representing an output differential signal, a path **P20** representing an input differential signal, a path **P21** representing an output differential signal, a path **P22** representing an input differential signal, a path **P23** representing an output differential signal, and a path **P24** representing an input differential signal, a path **P25** representing an output differential signal, a path **P26** representing an input differential signal, a path **P27** representing an output differential signal, a path **P28** representing an input differential signal, a path **P29** representing an output differential signal, a path **P30** representing an input differential signal, a path **P31** representing an output differential signal, and a path **P32** representing an input differential signal.

(140) Path **P1** output differential signals connect to the output differential amplifier **Y1**. The input signal to differential amplifier **Y1** can be a differential or common-mode signal. This input signal to differential amplifier **Y1** connects to the output **O1** of cross-point switch **SW**.

(141) Path **P2** input differential signals connect to the input differential amplifier **A2**. The output signal from differential amplifier **A2** can be a differential or common-mode signal. This output signal from differential amplifier **A2** connects to the input of retimer **RT2**. The output of retimer **RT2** connects to input **I2** of the cross-point switch **SW**.

(142) Path **P3** output differential signals connect to the output differential amplifier **Y3**. The input signal to differential amplifier **Y3** can be a differential or common-mode signal. This input signal to differential amplifier **Y3** connects to the output **O3** of cross-point switch **SW**.

(143) Path **P4** input differential signals connect to the input differential amplifier **A4**. The output signal from differential amplifier **A4** can be a differential or common-mode signal. This output signal from differential amplifier **A4** connects to the input of retimer **RT4**. The output of retimer **RT4** connects to input **I4** of the cross-point switch **SW**.

(144) Path **P5** output differential signals connect to the output differential amplifier **Y5**. The input signal to differential amplifier **Y5** can be a differential or common-mode signal. This input signal to differential amplifier **Y5** connects to the output **O5** of cross-point switch **SW**.

(145) Path **P6** input differential signals connect to the input differential amplifier **A6**. The output signal from differential amplifier **A6** can be a differential or common-mode signal. This output signal from differential amplifier **A6** connects to the input of retimer **RT6**. The output of retimer **RT6** connects to input **I6** of the cross-point switch **SW**.

(146) Path **P7** output differential signals connect to the output differential amplifier **Y7**. The input signal to differential amplifier **Y7** can be a differential or common-mode signal. This input signal to differential amplifier **Y7** connects to the output **O7** of cross-point switch **SW**.

(147) Path **P8** input differential signals connect to the input differential amplifier **A8**. The output signal from differential amplifier **A8** can be a differential or common-mode signal. This output signal from differential amplifier **A8** connects to the input of retimer **RT8**. The output of retimer **RT8** connects to input **I8** of the cross-point switch **SW**.

(148) Path **P9** output differential signals connect to the output differential amplifier **Y9**. The input signal to differential amplifier **Y9** can be a differential or common-mode signal. This input signal to differential amplifier **Y9** connects to the output **O9** of cross-point switch **SW**.

(149) Path **P10** input differential signals connect to the input differential amplifier **A10**. The output signal from differential amplifier **A10** can be a differential or common-mode signal. This output signal from differential amplifier **A10** connects to the input of retimer **RT10**. The output of retimer

RT10 connects to input I10 of the cross-point switch SW.

(150) Path P11 output differential signals connect to the output differential amplifier Y11. The input signal to differential amplifier Y11 can be a differential or common-mode signal. This input signal to differential amplifier Y11 connects to the output O11 of cross-point switch SW.

(151) Path P12 input differential signals connect to the input differential amplifier A12. The output signal from differential amplifier A12 can be a differential or common-mode signal. This output signal from differential amplifier A12 connects to the input of retimer RT12. The output of retimer RT12 connects to input I12 of the cross-point switch SW.

(152) Path P13 output differential signals connect to the output differential amplifier Y13. The input signal to differential amplifier Y13 can be a differential or common-mode signal. This input signal to differential amplifier Y13 connects to the output O13 of cross-point switch SW.

(153) Path P14 input differential signals connect to the input differential amplifier A14. The output signal from differential amplifier A14 can be a differential or common-mode signal. This output signal from differential amplifier A14 connects to the input of retimer RT14. The output of retimer RT14 connects to input I14 of the cross-point switch SW.

(154) Path P15 output differential signals connect to the output differential amplifier Y15. The input signal to differential amplifier Y15 can be a differential or common-mode signal. This input signal to differential amplifier Y15 connects to the output O15 of cross-point switch SW.

(155) Path P16 input differential signals connect to the input differential amplifier A16. The output signal from differential amplifier A16 can be a differential or common-mode signal. This output signal from differential amplifier A16 connects to the input of retimer RT16. The output of retimer RT16 connects to input I16 of the cross-point switch SW.

(156) Path P17 output differential signals connect to the output differential amplifier Y16. The input signal to differential amplifier Y16 can be a differential or common-mode signal. This input signal to differential amplifier Y16 connects to the output O16 of cross-point switch SW.

(157) Path P18 input differential signals connect to the input differential amplifier A15. The output signal from differential amplifier A15 can be a differential or common-mode signal. This output signal from differential amplifier A15 connects to the input of the retimer RT15. The output of the retimer RT15 connects to the input I15 of the cross-point switch SW.

(158) Path P19 output differential signals connect to the output differential amplifier Y14. The input signal to differential amplifier Y14 can be a differential or common-mode signal. This input signal to differential amplifier Y14 connects to the output O14 of cross-point switch SW.

(159) Path P20 input differential signals connect to the input differential amplifier A13. The output signal from differential amplifier A13 can be a differential or common-mode signal. This output signal from differential amplifier A13 connects to the input of the retimer RT13. The output of the retimer RT13 connects to the input I13 of the cross-point switch SW.

(160) Path P21 output differential signals connect to the output differential amplifier Y12. The input signal to differential amplifier Y12 can be a differential or common-mode signal. This input signal to differential amplifier Y12 connects to the output O12 of cross-point switch SW.

(161) Path P22 input differential signals connect to the input differential amplifier A11. The output signal from differential amplifier A11 can be a differential or common-mode signal. This output signal from differential amplifier A11 connects to the input of the retimer RT11. The output of the retimer RT11 connects to the input I11 of the cross-point switch SW.

(162) Path P23 output differential signals connect to the output differential amplifier Y10. The input signal to differential amplifier Y10 can be a differential or common-mode signal. This input signal to differential amplifier Y10 connects to the output O10 of cross-point switch SW.

(163) Path P24 input differential signals connect to the input differential amplifier A9. The output signal from differential amplifier A9 can be a differential or common-mode signal. This output signal from differential amplifier A9 connects to the input of the retimer RT9. The output of the retimer RT9 connects to the input I9 of the cross-point switch SW.

(164) Path P25 output differential signals connect to the output differential amplifier Y8. The input signal to differential amplifier Y8 can be a differential or common-mode signal. This input signal to differential amplifier Y8 connects to the output O8 of cross-point switch SW.

(165) Path P26 input differential signals connect to the input differential amplifier A7. The output signal from differential amplifier A7 can be a differential or common-mode signal. This output signal from differential amplifier A7 connects to the input of the retimer RT7. The output of the retimer RT7 connects to the input I7 of the cross-point switch SW.

(166) Path P27 output differential signals connect to the output differential amplifier Y6. The input signal to differential amplifier Y6 can be a differential or common-mode signal. This input signal to differential amplifier Y6 connects to the output O6 of cross-point switch SW.

(167) Path P28 input differential signals connect to the input differential amplifier A5. The output signal from differential amplifier A5 can be a differential or common-mode signal. This output signal from differential amplifier A5 connects to the input of the retimer RT5. The output of the retimer RT5 connects to the input I5 of the cross-point switch SW.

(168) Path P29 output differential signals connect to the output differential amplifier Y4. The input signal to differential amplifier Y4 can be a differential or common-mode signal. This input signal to differential amplifier Y4 connects to the output O4 of cross-point switch SW.

(169) Path P30 input differential signals connect to the input differential amplifier A3. The output signal from differential amplifier A3 can be a differential or common-mode signal. This output signal from differential amplifier A3 connects to the input of the retimer RT3. The output of the retimer RT3 connects to the input I3 of the cross-point switch SW.

(170) Path P31 output differential signals connect to the output differential amplifier Y2. The input signal to differential amplifier Y2 can be a differential or common-mode signal. This input signal to differential amplifier Y2 connects to the output O2 of cross-point switch SW.

(171) Path P32 input differential signals connect to the input differential amplifier A1. The output signal from differential amplifier A1 can be a differential or common-mode signal. This output signal from differential amplifier A1 connects to the input of the retimer RT1. The output of the retimer RT1 connects to the input I1 of the cross-point switch SW.

(172) FIG. 20 illustrates a schematic diagram of one embodiment of the Circuitry 150f of the present disclosure, representing for example a communication Device 100f with a plurality of Port connectors 102b, 104b, and 140b, which are each connected to an input and output differential amplifier, wherein the differential amplifier connects to a retimer. As shown in FIG. 21, the communication Device 100f two port connectors Port 102b and Port 104b also correspondingly represented as Port 1 and Port 2 respectively, are each configured to interface eight differential signal paths, specifically four transmit and receive differential signal paths to a Network. The communication Device 100f connector Port 140b also represented as Port 3 is configured to interface sixteen differential signal paths, specifically eight transmit and receive differential signal paths, to a Network. Further, in use, a QSFP Device as described above is inserted into Port 102b and Port 104b and a QSFP-DD Device as described above is inserted into Port 140b. The QSFP-DD and QSFP Devices connect to one or more cables as described above. The QSFP-DD and QSFP Device can be alternatively replaced by various other derivatives of QSFP-DD and QSFP Devices, respectively.

(173) More specifically, FIG. 21 illustrates a diagram of Circuitry 150f of the present disclosure involving three Ports and thirty two differential signal paths. Port 1 has eight differential signal paths P1, P2, P3, P4, P5, P6, P7, and P8, represented as 602. Port 2 has eight differential signal paths P9, P10, P11, P12, P13, P14, P15, and P16, represented as 604. Port 3 has sixteen differential signal paths P17, P18, P19, P20, P21, P22, P23, P24, P25, P26, P27, P28, P29, P30, P31, and P32, represented as 600.

(174) As illustrated in FIG. 21, there are sixteen input broadband differential amplifiers A1, A2, A3, A4, A5, A6, A7, A8, A9, A10, A11, A12, A13, A14, A15, and A16, represented collectively as 156e.

The broadband differential amplifiers provide amplification and conditioning of the input signal. There are sixteen retimers RT1, RT2, RT3, RT4, RT5, RT6, RT7, RT8, RT9, RT10, RT11, RT12, RT13, RT14, RT15, and RT16, represented collectively as **154e**. The retimers extract timing from the input signals and retransmit the signal with a corrected timing. The retimer removes jitter and inter-symbol interference from the input signal. There are sixteen high speed output differential amplifiers Y1, Y2, Y3, Y4, Y5, Y6, Y7, Y8, Y9, Y10, Y11, Y12, Y13, Y14, Y15, and Y16, represented collectively as **152e**. The high speed output differential amplifiers provide fixed or variable output voltages with and without pre-emphasis. Highly integrated circuits (IC) incorporate the input broadband differential amplifiers, retimers, and the output broadband differential amplifiers. Low latency of 350 ps and lower are achieved with using differential signal paths between the input differential amplifiers A, the output differential amplifiers Y, and the retimers RT.

(175) Port **1** comprises a path P1 representing an output differential signal, a path P2 representing an input differential signal, a path P3 representing an output differential signal, a path P4 representing an input differential signal, a path P5 representing an output differential signal, a path P6 representing an input differential signal, a path P7 representing an output differential signal, and a path P8 representing an input differential signal. Port **2** comprises a path P9 representing an output differential signal, a path P10 representing an input differential signal, a path P11 representing an output differential signal, a path P12 representing an input differential signal, a path P13 representing an output differential signal, a path P14 representing an input differential signal, a path P15 representing an output differential signal, and a path P16 representing an input differential signal. Port **3** comprises a path P17 representing an output differential signal, a path P18 representing an input differential signal, a path P19 representing an output differential signal, a path P20 representing an input differential signal, a path P21 representing an output differential signal, a path P22 representing an input differential signal, a path P23 representing an output differential signal, and a path P24 representing an input differential signal, a path P25 representing an output differential signal, a path P26 representing an input differential signal, a path P27 representing an output differential signal, a path P28 representing an input differential signal, a path P29 representing an output differential signal, a path P30 representing an input differential signal, a path P31 representing an output differential signal, and a path P32 representing an input differential signal.

(176) Path P1 output differential signals connect to the output differential amplifier Y1. The input signal to differential amplifier Y1 can be a differential or common-mode signal. This input signal to differential amplifier Y1 connects to the output of retimer RT1.

(177) Path P2 input differential signals connect to the input differential amplifier A2. The output signal from differential amplifier A2 can be a differential or common-mode signal. This output signal from differential amplifier A2 connects to the input of retimer RT2.

(178) Path P3 output differential signals connect to the output differential amplifier Y3. The input signal to differential amplifier Y3 can be a differential or common-mode signal. This input signal to differential amplifier Y3 connects to the output of retimer RT3.

(179) Path P4 input differential signals connect to the input differential amplifier A4. The output signal from differential amplifier A4 can be a differential or common-mode signal. This output signal from differential amplifier A4 connects to the input of retimer RT4.

(180) Path P5 output differential signals connect to the output differential amplifier Y5. The input signal to differential amplifier Y5 can be a differential or common-mode signal. This input signal to differential amplifier Y5 connects to the output of retimer RT5.

(181) Path P6 input differential signals connect to the input differential amplifier A6. The output signal from differential amplifier A6 can be a differential or common-mode signal. This output signal from differential amplifier A6 connects to the input of retimer RT6.

(182) Path P7 output differential signals connect to the output differential amplifier Y7. The input signal to differential amplifier Y7 can be a differential or common-mode signal. This input signal to

differential amplifier Y7 connects to the output of retimer RT7.

(183) Path P8 input differential signals connect to the input differential amplifier A8. The output signal from differential amplifier A8 can be a differential or common-mode signal. This output signal from differential amplifier A8 connects to the input of retimer RT8.

(184) Path P9 output differential signals connect to the output differential amplifier Y9. The input signal to differential amplifier Y9 can be a differential or common-mode signal. This input signal to differential amplifier Y9 connects to the output of retimer RT9.

(185) Path P10 input differential signals connect to the input differential amplifier A10. The output signal from differential amplifier A10 can be a differential or common-mode signal. This output signal from differential amplifier A10 connects to the input of retimer RT10.

(186) Path P11 output differential signals connect to the output differential amplifier Y11. The input signal to differential amplifier Y11 can be a differential or common-mode signal. This input signal to differential amplifier Y11 connects to the output of retimer RT11.

(187) Path P12 input differential signals connect to the input differential amplifier A12. The output signal from differential amplifier A12 can be a differential or common-mode signal. This output signal from differential amplifier A12 connects to the input of retimer RT12.

(188) Path P13 output differential signals connect to the output differential amplifier Y13. The input signal to differential amplifier Y13 can be a differential or common-mode signal. The input signal to differential amplifier Y13 connects to the output of retimer RT13.

(189) Path P14 input differential signals connect to the input differential amplifier A14. The output signal from differential amplifier A14 can be a differential or common-mode signal. This output signal from differential amplifier A14 connects to the input of retimer RT14.

(190) Path P15 output differential signals connect to the output differential amplifier Y15. The input signal to differential amplifier Y15 can be a differential or common-mode signal. This input signal to differential amplifier Y15 connects to the output of retimer RT15.

(191) Path P16 input differential signals connect to the input differential amplifier A16. The output signal from differential amplifier A16 can be a differential or common-mode signal. This output signal from differential amplifier A16 connects to the input of retimer RT16.

(192) Path P17 output differential signals connect to the output differential amplifier Y16. The input signal to differential amplifier Y16 can be a differential or common-mode signal. This input signal to differential amplifier Y16 connects to the output of retimer RT16.

(193) Path P18 input differential signals connect to the input differential amplifier A15. The output signal from differential amplifier A15 can be a differential or common-mode signal. This output signal from differential amplifier A15 connects to the input of retimer RT15.

(194) Path P19 output differential signals connect to the output differential amplifier Y14. The input signal to differential amplifier Y14 can be a differential or common-mode signal. This input signal to differential amplifier Y14 connects to the output of retimer RT14.

(195) Path P20 input differential signals connect to the input differential amplifier A13. The output signal from differential amplifier A13 can be a differential or common-mode signal. This output signal from differential amplifier A13 connects to the input of retimer RT13.

(196) Path P21 output differential signals connect to the output differential amplifier Y12. The input signal to differential amplifier Y12 can be a differential or common-mode signal. This input signal to differential amplifier Y12 connects to the output of retimer RT12.

(197) Path P22 input differential signals connect to the input differential amplifier A11. The output signal from differential amplifier A11 can be a differential or common-mode signal. This output signal from differential amplifier A11 connects to the input of retimer RT11.

(198) Path P23 output differential signals connect to the output differential amplifier Y10. The input signal to differential amplifier Y10 can be a differential or common-mode signal. This input signal to differential amplifier Y10 connects to the output of retimer RT10.

(199) Path P24 input differential signals connect to the input differential amplifier A9. The output

signal from differential amplifier A9 can be a differential or common-mode signal. This output signal from differential amplifier A9 connects to the input of retimer RT9.

(200) Path P25 output differential signals connect to the output differential amplifier Y8. The input signal to differential amplifier Y8 can be a differential or common-mode signal. This input signal to differential amplifier Y8 connects to the output of retimer RT8.

(201) Path P26 input differential signals connect to the input differential amplifier A7. The output signal from differential amplifier A7 can be a differential or common-mode signal. This output signal from differential amplifier A7 connects to the input of retimer RT7.

(202) Path P27 output differential signals connect to the output differential amplifier Y6. The input signal to differential amplifier Y6 can be a differential or common-mode signal. This input signal to differential amplifier Y6 connects to the output of retimer RT6.

(203) Path P28 input differential signals connect to the input differential amplifier A5. The output signal from differential amplifier A5 can be a differential or common-mode signal. This output signal from differential amplifier A5 connects to the input of retimer RT5.

(204) Path P29 output differential signals connect to the output differential amplifier Y4. The input signal to differential amplifier Y4 can be a differential or common-mode signal. The input signal to differential amplifier Y4 connects to the output of retimer RT4.

(205) Path P30 input differential signals connect to the input differential amplifier A3. The output signal from differential amplifier A3 can be a differential or common-mode signal. This output signal from differential amplifier A3 connects to the input of retimer RT3.

(206) Path P31 output differential signals connect to the output differential amplifier Y2. The input signal to differential amplifier Y2 can be a differential or common-mode signal. This input signal to differential amplifier Y2 connects to the output of retimer RT2.

(207) Path P32 input differential signals connect to the input differential amplifier A1. The output signal from differential amplifier A1 can be a differential or common-mode signal. This output signal from differential amplifier A1 connects to the input of retimer RT1.

(208) FIG. 21 illustrates a diagram of one embodiment of the Circuitry 150g of the present disclosure, representing for example a communication Device 100g with a plurality of Port connectors 102b, 104b, and 140b, which are each connected to an input and output differential amplifier, wherein the input differential amplifier connects to a cross-point switch, the cross-point switch connects to the retimer, and the retimers connect to the output differential amplifier. As shown in FIG. 21, the communication Device 100g two port connectors Port 102b and Port 104b also correspondingly represented as Port 1 and Port 2 respectively, are each configured to interface eight differential signal paths, specifically four transmit and receive differential signal paths to a Network. The communication Device 100g connector Port 140b also represented as Port 3 is configured to interface sixteen differential signal paths, specifically eight transmit and receive differential signal paths to a Network. Further, in use, a QSFP28 Device as described above is inserted into Port 102b and Port 104b and a QSFP-DD Device as described above is inserted into Port 140b. The QSFP-DD and QSFP28 Devices connect to one or more cables as described above. The QSFP-DD and QSFP28 Devices can be alternatively replaced by various other derivatives of QSFP-DD and QSFP28 Devices, respectively.

(209) More specifically, FIG. 21 illustrates a diagram of Circuitry 150g of the present disclosure involving three Ports and thirty-two differential signal paths. Port 1 has eight differential signal paths P1, P2, P3, P4, P5, P6, P7, and P8, represented as 602. Port 2 has eight differential signal paths P9, P10, P11, P12, P13, P14, P15, and P16, represented as 604. Port 3 has sixteen differential signal paths P17, P18, P19, P20, P21, P22, P23, P24, P25, P26, P27, P28, P29, P30, P31, and P32, represented as 600.

(210) As illustrated in FIG. 21, there are sixteen input broadband differential amplifiers A1, A2, A3, A4, A5, A6, A7, A8, A9, A10, A11, A12, A13, A14, A15, and A16, represented collectively as 156. The broadband differential amplifiers provide amplification and conditioning of the input signal.

There are sixteen retimers **RT1**, **RT2**, **RT3**, **RT4**, **RT5**, **RT6**, **RT7**, **RT8**, **RT9**, **RT10**, **RT11**, **RT12**, **RT13**, **RT14**, **RT15**, and **RT16**, represented collectively as **154**. The retimers extract timing from the input signals and retransmit the signal with a corrected timing. The retimer removes jitter and inter-symbol interference from the input signal. There is a 16×16 non-blocking cross-point switch **SW**, represented as **158b**. The 16×16 non-blocking cross-point Switch **158b** allows any output **O** to be connected to any input **I** of the switch **SW**. There are sixteen high speed output differential amplifiers **Y1**, **Y2**, **Y3**, **Y4**, **Y5**, **Y6**, **Y7**, **Y8**, **Y9**, **Y10**, **Y11**, **Y12**, **Y13**, **Y14**, **Y15**, and **Y16**, represented collectively as **152**. The high speed output differential amplifiers provide fixed or variable output voltages with and without pre-emphasis. Highly integrated circuits (IC) incorporate the input broadband differential amplifiers, retimers, and the output broadband differential amplifiers. Low latency of 350 ps and lower are achieved with using differential signal paths between the input differential amplifiers **A**, the output differential amplifiers **Y**, the retimers **RT**, and the cross-point switch **SW**.

(211) Port **1** comprises a path **P1** representing an output differential signal, a path **P2** representing an input differential signal, a path **P3** representing an output differential signal, a path **P4** representing an input differential signal, a path **P5** representing an output differential signal, a path **P6** representing an input differential signal, a path **P7** representing an output differential signal, and a path **P8** representing an input differential signal. Port **2** comprises a path **P9** representing an output differential signal, a path **P10** representing an input differential signal, a path **P11** representing an output differential signal, a path **P12** representing an input differential signal, a path **P13** representing an output differential signal, a path **P14** representing an input differential signal, a path **P15** representing an output differential signal, and a path **P16** representing an input differential signal. Port **3** comprises a path **P17** representing an output differential signal, a path **P18** representing an input differential signal, a path **P19** representing an output differential signal, a path **P20** representing an input differential signal, a path **P21** representing an output differential signal, a path **P22** representing an input differential signal, a path **P23** representing an output differential signal, and a path **P24** representing an input differential signal, a path **P25** representing an output differential signal, a path **P26** representing an input differential signal, a path **P27** representing an output differential signal, a path **P28** representing an input differential signal, a path **P29** representing an output differential signal, a path **P30** representing an input differential signal, a path **P31** representing an output differential signal, and a path **P32** representing an input differential signal.

(212) Path **P1** output differential signals connect to the output differential amplifier **Y1**. The input signal to differential amplifier **Y1** can be a differential or common-mode signal. This input signal to differential amplifier **Y1** connects to the output **O1** of cross-point switch **SW**.

(213) Path **P2** input differential signals connect to the input differential amplifier **A2**. The output signal from differential amplifier **A2** can be a differential or common-mode signal. This output signal from differential amplifier **A2** connects to the input of retimer **RT2**. The output of retimer **RT2** connects to input **I2** of the cross-point switch **SW**.

(214) Path **P3** output differential signals connect to the output differential amplifier **Y3**. The input signal to differential amplifier **Y3** can be a differential or common-mode signal. This input signal to differential amplifier **Y1** connects to the output **O3** of cross-point switch **SW**.

(215) Path **P4** input differential signals connect to the input differential amplifier **A4**. The output signal from differential amplifier **A4** can be a differential or common-mode signal. This output signal from differential amplifier **A4** connects to the input of retimer **RT4**. The output of retimer **RT4** connects to input **I4** of the cross-point switch **SW**.

(216) Path **P5** output differential signals connect to the output differential amplifier **Y5**. The input signal to differential amplifier **Y5** can be a differential or common-mode signal. This input signal to differential amplifier **Y5** connects to the output **O5** of cross-point switch **SW**.

(217) Path **P6** input differential signals connect to the input differential amplifier **A6**. The output

signal from differential amplifier A6 can be a differential or common-mode signal. This output signal from differential amplifier A6 connects to the input of retimer RT6. The output of retimer RT6 connects to input I6 of the cross-point switch SW.

(218) Path P7 output differential signals connect to the output differential amplifier Y7. The input signal to differential amplifier Y7 can be a differential or common-mode signal. This input signal to differential amplifier Y7 connects to the output O7 of cross-point switch SW.

(219) Path P8 input differential signals connect to the input differential amplifier A8. The output signal from differential amplifier A8 can be a differential or common-mode signal. This output signal from differential amplifier A8 connects to the input of retimer RT8. The output of retimer RT8 connects to input I8 of the cross-point switch SW.

(220) Path P9 output differential signals connect to the output differential amplifier Y9. The input signal to differential amplifier Y9 can be a differential or common-mode signal. This input signal to differential amplifier Y9 connects to the output O9 of cross-point switch SW.

(221) Path P10 input differential signals connect to the input differential amplifier A10. The output signal from differential amplifier A10 can be a differential or common-mode signal. This output signal from differential amplifier A10 connects to the input of retimer RT10. The output of retimer RT10 connects to input I10 of the cross-point switch SW.

(222) Path P11 output differential signals connect to the output differential amplifier Y11. The input signal to differential amplifier Y11 can be a differential or common-mode signal. This input signal to differential amplifier Y11 connects to the output O11 of cross-point switch SW.

(223) Path P12 input differential signals connect to the input differential amplifier A12. The output signal from differential amplifier A12 can be a differential or common-mode signal. This output signal from differential amplifier A12 connects to the input of retimer RT12. The output of retimer RT12 connects to input I12 of the cross-point switch SW.

(224) Path P13 output differential signals connect to the output differential amplifier Y13. The input signal to differential amplifier Y13 can be a differential or common-mode signal. This input signal to differential amplifier Y13 connects to the output O13 of cross-point switch SW.

(225) Path P14 input differential signals connect to the input differential amplifier A14. The output signal from differential amplifier A14 can be a differential or common-mode signal. This output signal from differential amplifier A14 connects to the input of retimer RT14. The output of retimer RT14 connects to input I14 of the cross-point switch SW.

(226) Path P15 output differential signals connect to the output differential amplifier Y15. The input signal to differential amplifier Y15 can be a differential or common-mode signal. This input signal to differential amplifier Y15 connects to the output O15 of cross-point switch SW.

(227) Path P16 input differential signals connect to the input differential amplifier A16. The output signal from differential amplifier A16 can be a differential or common-mode signal. This output signal from differential amplifier A16 connects to the input of retimer RT16. The output of retimer RT16 connects to input I16 of the cross-point switch SW.

(228) Path P17 output differential signals connect to the output differential amplifier Y16. The input signal to differential amplifier Y16 can be a differential or common-mode signal. This input signal to differential amplifier Y16 connects to the output O16 of cross-point switch SW.

(229) Path P18 input differential signals connect to the input differential amplifier A15. The output signal from differential amplifier A15 can be a differential or common-mode signal. This output signal from differential amplifier A15 connects to the input of the retimer RT15. The output of the retimer RT15 connects to the input I15 of the cross-point switch SW.

(230) Path P19 output differential signals connect to the output differential amplifier Y14. The input signal to differential amplifier Y14 can be a differential or common-mode signal. This input signal to differential amplifier Y14 connects to the output O14 of cross-point switch SW.

(231) Path P20 input differential signals connect to the input differential amplifier A13. The output signal from differential amplifier A13 can be a differential or common-mode signal. This output

signal from differential amplifier A13 connects to the input of the retimer RT13. The output of the retimer RT13 connects to the input I13 of the cross-point switch SW.

(232) Path P21 output differential signals connect to the output differential amplifier Y12. The input signal to differential amplifier Y12 can be a differential or common-mode signal. This input signal to differential amplifier Y12 connects to the output O12 of cross-point switch SW.

(233) Path P22 input differential signals connect to the input differential amplifier A11. The output signal from differential amplifier A11 can be a differential or common-mode signal. This output signal from differential amplifier A11 connects to the input of the retimer RT11. The output of the retimer RT11 connects to the input I11 of the cross-point switch SW.

(234) Path P23 output differential signals connect to the output differential amplifier Y10. The input signal to differential amplifier Y10 can be a differential or common-mode signal. This input signal to differential amplifier Y10 connects to the output O10 of cross-point switch SW.

(235) Path P24 input differential signals connect to the input differential amplifier A9. The output signal from differential amplifier A9 can be a differential or common-mode signal. This output signal from differential amplifier A9 connects to the input of the retimer RT9. The output of the retimer RT9 connects to the input I9 of the cross-point switch SW.

(236) Path P25 output differential signals connect to the output differential amplifier Y8. The input signal to differential amplifier Y8 can be a differential or common-mode signal. This input signal to differential amplifier Y8 connects to the output O8 of cross-point switch SW.

(237) Path P26 input differential signals connect to the input differential amplifier A7. The output signal from differential amplifier A7 can be a differential or common-mode signal. This output signal from differential amplifier A7 connects to the input of the retimer RT7. The output of the retimer RT7 connects to the input I7 of the cross-point switch SW.

(238) Path P27 output differential signals connect to the output differential amplifier Y6. The input signal to differential amplifier Y6 can be a differential or common-mode signal. This input signal to differential amplifier Y6 connects to the output O6 of cross-point switch SW.

(239) Path P28 input differential signals connect to the input differential amplifier A5. The output signal from differential amplifier A5 can be a differential or common-mode signal. This output signal from differential amplifier A5 connects to the input of the retimer RT5. The output of the retimer RT5 connects to the input I5 of the cross-point switch SW.

(240) Path P29 output differential signals connect to the output differential amplifier Y4. The input signal to differential amplifier Y4 can be a differential or common-mode signal. This input signal to differential amplifier Y4 connects to the output O4 of cross-point switch SW.

(241) Path P30 input differential signals connect to the input differential amplifier A3. The output signal from differential amplifier A3 can be a differential or common-mode signal. This output signal from differential amplifier A3 connects to the input of the retimer RT3. The output of the retimer RT3 connects to the input I3 of the cross-point switch SW.

(242) Path P31 output differential signals connect to the output differential amplifier Y2. The input signal to differential amplifier Y2 can be a differential or common-mode signal. This input signal to differential amplifier Y2 connects to the output O2 of cross-point switch SW.

(243) Path P32 input differential signals connect to the input differential amplifier A1. The output signal from differential amplifier A1 can be a differential or common-mode signal. This output signal from differential amplifier A1 connects to the input of the retimer RT1. The output of the retimer RT1 connects to the input I1 of the cross-point switch SW.

(244) FIG. 22 illustrates a graphical representation of an embodiment of the communications system and equipment of the present disclosure. Device 100a having four Ports 102a, 104a, 106a, and 108a where each port support an SFP+ device and a Port 140a that support a QSFP+. Port 140a is positioned at the rear of the Device 100a to provide security for the QSFP+ device, the cabling, and the communication services. The rear placement of the Port 140a prevents unauthorized access to the QSFP+ device and cabling.

(245) The Ethernet Management Port **252** provides remote or local Ethernet communications to the Device **100a** for status, performance monitor, testing, and provisioning on the SFP+ and QSFP+ devices and Device **100a**.

(246) The Craft Interface Port **254** provides local RS232 serial communications to the Device **100a** for status, performance monitor, testing, and provisioning on the SFP+ and QSFP+ devices and Device **100a**.

(247) While the embodiment(s) disclosed herein are illustrative of the structure, function and operation of the exemplary methods, systems, devices, circuitry, and equipment, it should be understood that various modifications may be made thereto with departing from the teachings herein. Further, the components of the methods, systems, devices, circuitry and equipment disclosed herein can take any suitable form, including any suitable hardware, software, circuitry or other components capable of adequately performing their respective intended functions, as may be known in the art.

(248) While the foregoing discussion presents the teachings in an exemplary fashion with respect to the disclosed methods, systems, devices, circuitry and equipment for communication services, it will be apparent to those skilled in the art that the present disclosure may apply to other methods, systems, devices, circuitry and equipment for communication services. Further, while the foregoing has described what are considered to be the best mode and/or other examples, it is understood that various modifications may be made therein and that the subject matter disclosed herein may be implemented in various forms and examples, and that the methods, systems, devices, equipment and circuitry may be applied in numerous applications, only some of which have been described herein.

Claims

1. A device for communication service, comprising: circuitry on the device, wherein the circuitry includes a plurality of input amplifiers, a plurality of output amplifiers, and a plurality of retimers; a plurality of ports, wherein the plurality of ports are connected to the circuitry; a plurality of Small Form-factor Pluggable SFP variant devices in the plurality of ports, wherein the plurality of Small Form-factor Pluggable SFP variant devices each interface a communication service to the device; wherein the device is adapted to aggregate communication services from a plurality of lower service capacity connectors and interfaces to a single higher capacity connector and interface.
2. The device of claim 1, wherein the circuitry further includes a non-blocking cross-point switch.
3. The device of claim 1, wherein the plurality of ports include a plurality of Small Form-factor Pluggable SFP variant ports and a single Quad Small Form-factor Pluggable QSFP variant port.
4. The device of claim 3, wherein a Small Form-factor Pluggable SFP variant device is connected to each of the Small Form-factor Pluggable SFP variant ports, and a Quad Small Form-factor Pluggable QSFP variant device is connected to the Quad Small Form-factor Pluggable QSFP variant port.
5. The device of claim 3, wherein the plurality of Small Form-factor Pluggable SFP variant ports each establish two differential signal paths.
6. The device of claim 3, wherein the Quad Small Form-factor Pluggable QSFP variant port establishes eight differential signal paths.
7. The device of claim 3, wherein the Quad Small Form-factor Pluggable QSFP variant port establishes sixteen differential signal paths.
8. The device of claim 1, wherein the plurality of ports include a plurality of Quad Small Form-factor Pluggable QSFP variant ports and a single Quad Small Form-factor Pluggable-Density QSFP-DD variant port.
9. The device of claim 8, wherein a Quad Small Form-factor Pluggable QSFP variant device is connected to each of the Quad Small Form-factor Pluggable QSFP variant ports, and a Quad Small

Form-factor Pluggable-Double Density QSFP-DD variant device is connected to the Quad Small Form-factor Pluggable-Double Density QSFP-DD variant port.

10. The device of claim 8, wherein the plurality of Quad Small Form-factor Pluggable QSFP variant ports each establish eight differential signal paths.

11. The device of claim 8, wherein the Quad Small Form-factor Pluggable-Double Density QSFP-DD variant port establishes sixteen differential signal paths.

12. The device of claim 1, wherein the circuitry extends communication service.

13. The device of claim 1, wherein the circuitry provides signal loopback of the communication services.

14. A system for communication service, comprising: a first communication network; a second communication network; a communication device on the first network, wherein the communication device comprises a plurality of ports connected to circuitry having a plurality of input amplifiers, a plurality of output amplifiers, and a plurality of retimers; a plurality of Small Form-factor Pluggable SFP variant devices connected in the plurality of ports; a communication service interfaced to each of the plurality of Small Form-factor Pluggable SFP variant devices; wherein the system is adapted to aggregate communication services from a plurality of lower service capacity connectors and interfaces to a single higher capacity connector and interface; and a demarcation point established by the communication device.

15. The system of claim 14, wherein the circuitry further includes a non-blocking cross-point switch.

16. The system of claim 14, wherein the plurality of ports include a plurality of Small Form-factor Pluggable SFP variant ports each having a Small Form-factor Pluggable SFP variant device connected therein and a single Quad Small Form-factor Pluggable QSFP variant port having a Quad Small Form-factor Pluggable QSFP variant device connected therein.

17. The system of claim 16, wherein the plurality of Small Form-factor Pluggable SFP variant ports each establish two differential signal paths.

18. The system of claim 16, wherein the Quad Small Form-factor Pluggable QSFP variant port establishes one of eight differential signal paths and sixteen differential signal paths.

19. The system of claim 16, wherein the plurality of ports include a plurality of Quad Small Form-factor Pluggable QSFP variant ports each having a Quad Small Form-factor Pluggable QSFP variant device connected therein and a single Quad Small Form-factor Pluggable-Double Density QSFP-DD variant port having a Quad Small Form-factor Pluggable-Double Density QSFP-DD variant device connected therein.

20. The system of claim 19, wherein the plurality of Quad Small Form-factor Pluggable QSFP variant ports each establish eight differential signal paths.

21. The system of claim 19, wherein the Quad Small Form-factor Pluggable-Double Density QSFP-DD variant port establishes sixteen differential signal paths.

22. A method for communication service, comprising: providing a communication device comprising a plurality of Small Form-factor Pluggable SFP variant ports, a single Quad Small Form-factor Pluggable QSFP variant port, and circuitry connected to the plurality of Small Form-factor Pluggable SFP variant ports and the Quad Small Form-factor Pluggable QSFP variant port, wherein the circuitry includes a plurality of input amplifiers, a plurality of output amplifiers, and a plurality of retimers; interfacing first network communication equipment with the plurality of Small Form-factor Pluggable SFP variant ports by inserting a Small Form-factor Pluggable SFP variant device into each of the plurality of Small Form-factor Pluggable SFP variant ports, and connecting each of the Small Form-factor Pluggable SFP variant devices to the first network communication equipment; interfacing second network communication equipment with the Quad Small Form-factor Pluggable QSFP variant port by inserting a Quad Small Form-factor Pluggable QSFP variant device into each of the Quad Small Form-factor Pluggable QSFP variant port, and connecting the Quad Small Form-factor Pluggable QSFP variant device to the second network

communication equipment; aggregating communication services from a plurality of lower service capacity connectors and interfaces to a single higher capacity connector and interface; and establishing a demarcation point with the communication device.

23. A system for communication service, comprising: a first communication network; a second communication network; a communication device on the first network, wherein the communication device comprises a plurality of ports connected to circuitry having a plurality of input amplifiers, a plurality of output amplifiers, and a plurality of retimers; a plurality of Small Form-factor Pluggable SFP variant devices connected in the plurality of ports; a communication service interfaced to each of the plurality of Small Form-factor Pluggable SFP variant devices; wherein the system is adapted to aggregate communication services from a plurality of lower service capacity connectors and interfaces to a single higher capacity connector and interface; and wherein the system is adapted to extend communication services established by the communication device.

24. The system of claim 23, wherein the system is adapted to provide at least one of a plurality of physical media interface variants from Small Form-factor Pluggable SFP and/or Quad Small Form-factor Pluggable QSFP variant devices connected from the communication device port(s).

25. The system of claim 23, wherein the system is adapted to provide for remote testing through signal loopback of the communication service.

26. A method for communication service, comprising: providing a communication device comprising a plurality of Small Form-factor Pluggable SPF variant ports, a single Quad Small Form-factor Pluggable QSFP variant port, and circuitry connected to the plurality of Small Form-factor Pluggable SFP variant ports and the Quad Small Form-factor Pluggable QSFP variant port, wherein the circuitry includes a plurality of input amplifiers, a plurality of output amplifiers, and a plurality of retimers; interfacing first network communication equipment with the plurality of Small Form-factor Pluggable SFP variant ports by inserting a Small Form-factor Pluggable SFP variant device into each of the plurality of Small Form-factor Pluggable SFP variant ports, and connecting each of the Small Form-factor Pluggable SFP variant devices to the first network communication equipment; interfacing second network communication equipment with the Quad Small Form-factor Pluggable QSFP variant port by inserting a Quad Small Form-factor Pluggable QSFP variant device into each of the Quad Small Form-factor Pluggable QSFP variant port, and connecting the Quad Small Form-factor Pluggable QSFP variant device to the second network communication equipment; aggregating communication services from a plurality of lower service capacity connectors and interfaces to a single higher capacity connector and interface; and extending communication services with the communication device.

27. The method of claim 26 further comprising the step of providing at least one of a plurality of physical media interface variants from Small Form-factor Pluggable SFP and/or Quad Small Form-factor Pluggable QSFP variant devices connected to the communication devices port(s).

28. The method of claim 26 further comprising the step of remotely testing the communications service by signal loopback from the communication device.
