

# US Patent & Trademark Office

## Patent Public Search | Text View

United States Patent

12405431

Kind Code

B2

Date of Patent

September 02, 2025

Inventor(s)

Zhang; Honghao et al.

### Optical module

#### Abstract

An optical module includes a light receiving assembly and a first fiber optic adapter. The light receiving assembly includes a first lens group, a plurality of wavelength division demultiplexers and at least one light receiving component. The first lens group is configured to split optical signals transmitted to the first cavity body for a first time according to a wavelength to obtain a first optical signal beam and a second optical signal beam. The plurality of wavelength division demultiplexers include a first wavelength division demultiplexer and a second wavelength division demultiplexer. The first wavelength division demultiplexer is configured to split the first optical signal beam for a second time according to a wavelength. The second wavelength division demultiplexer is configured to split the second optical signal beam for a second time according to a wavelength. The light receiving component includes a plurality of light receiving chips.

**Inventors:** Zhang; Honghao (Shandong, CN), Zhang; Jiaao (Shandong, CN), Wang; Bin (Shandong, CN), Huang; Xujie (Shandong, CN), Ye; Shuhua (Shandong, CN), Liu; Xueru (Shandong, CN), Fu; Qin hao (Shandong, CN), Xie; Yifan (Shandong, CN), Tang; Yi (Shandong, CN), Dong; Benzhen g (Shandong, CN)

**Applicant:** HISENSE BROADBAND MULTIMEDIA TECHNOLOGIES CO., LTD.  
(Shandong, CN)

**Family ID:** 80775727

**Assignee:** HISENSE BROADBAND MULTIMEDIA TECHNOLOGIES CO., LTD.  
(Qingdao, CN)

**Appl. No.:** 18/122534

**Filed:** March 16, 2023

#### Prior Publication Data

**Document Identifier**

US 20230228955 A1

**Publication Date**

Jul. 20, 2023

## Foreign Application Priority Data

|    |                |               |
|----|----------------|---------------|
| CN | 202010988113.2 | Sep. 18, 2020 |
| CN | 202010988117.0 | Sep. 18, 2020 |
| CN | 202010989983.1 | Sep. 18, 2020 |
| CN | 202010989984.6 | Sep. 18, 2020 |

## Related U.S. Application Data

continuation-in-part parent-doc WO PCT/CN2020/134054 20201204 PENDING child-doc US 18122534

---

## Publication Classification

**Int. Cl.:** H04B10/00 (20130101); G02B6/42 (20060101)

**U.S. Cl.:**

CPC G02B6/4246 (20130101); G02B6/4281 (20130101); G02B6/4292 (20130101);

## Field of Classification Search

**CPC:** G02B (6/4246); G02B (6/4281); G02B (6/4292); G02B (6/29367); G02B (6/4215)

---

## References Cited

### U.S. PATENT DOCUMENTS

| Patent No.   | Issued Date | Patentee Name   | U.S. Cl.   | CPC         |
|--------------|-------------|-----------------|------------|-------------|
| 5611006      | 12/1996     | Tabuchi         | 385/35     | G02B 6/423  |
| 9419717      | 12/2015     | Huang           | N/A        | H04B 10/40  |
| 11474311     | 12/2021     | Lin             | N/A        | G02B 6/4214 |
| 2002/0110313 | 12/2001     | Anigbo          | 385/47     | G02B 6/2938 |
| 2006/0013541 | 12/2005     | Plickert        | 385/47     | G02B 6/4246 |
| 2011/0311229 | 12/2010     | Kondo et al.    | N/A        | N/A         |
| 2015/0098127 | 12/2014     | Kurokawa        | 359/484.03 | H04B 10/50  |
| 2015/0104177 | 12/2014     | Kato            | 398/79     | H04B 10/40  |
| 2015/0256259 | 12/2014     | Huang           | 398/139    | G02B 6/4261 |
| 2015/0295658 | 12/2014     | Chen            | 398/43     | H04J 14/06  |
| 2015/0326319 | 12/2014     | Okii            | 398/135    | H04B 10/40  |
| 2016/0047987 | 12/2015     | Du              | 359/484.05 | G02B 6/2773 |
| 2016/0131843 | 12/2015     | Amit            | 156/60     | G02B 6/4221 |
| 2016/0191166 | 12/2015     | Wang            | 398/135    | G02B 6/42   |
| 2017/0269315 | 12/2016     | Yeh             | N/A        | G02B 6/4274 |
| 2018/0003908 | 12/2017     | Jung et al.     | N/A        | N/A         |
| 2018/0017745 | 12/2017     | Lin et al.      | N/A        | N/A         |
| 2018/0123697 | 12/2017     | Kubota          | N/A        | G02B 27/283 |
| 2019/0103936 | 12/2018     | Kawamura et al. | N/A        | N/A         |
| 2019/0187391 | 12/2018     | Fujimura        | N/A        | H10F 77/407 |

|              |         |             |        |                 |
|--------------|---------|-------------|--------|-----------------|
| 2020/0012055 | 12/2019 | Ye          | N/A    | G02B<br>6/29367 |
| 2020/0014484 | 12/2019 | Chen        | N/A    | H04B<br>10/2589 |
| 2020/0244364 | 12/2019 | Jin et al.  | N/A    | N/A             |
| 2022/0011528 | 12/2021 | Fujimura    | N/A    | G02B 6/4212     |
| 2022/0014272 | 12/2021 | Shin et al. | N/A    | N/A             |
| 2022/0326456 | 12/2021 | Zhang       | N/A    | G02B 6/4292     |
| 2023/0194802 | 12/2022 | Sun         | 385/14 | H04B 10/673     |
| 2023/0228955 | 12/2022 | Zhang       | 385/93 | G02B 6/4292     |
| 2023/0258883 | 12/2022 | Zhang       | 385/15 | G02B 6/4284     |

#### **FOREIGN PATENT DOCUMENTS**

| <b>Patent No.</b> | <b>Application Date</b> | <b>Country</b> | <b>CPC</b> |
|-------------------|-------------------------|----------------|------------|
| 102449518         | 12/2011                 | CN             | N/A        |
| 102681111         | 12/2011                 | CN             | N/A        |
| 104503044         | 12/2014                 | CN             | N/A        |
| 107046444         | 12/2016                 | CN             | N/A        |
| 107132626         | 12/2016                 | CN             | N/A        |
| 107342817         | 12/2016                 | CN             | N/A        |
| 107402425         | 12/2016                 | CN             | N/A        |
| 206710651         | 12/2016                 | CN             | N/A        |
| 108267821         | 12/2017                 | CN             | N/A        |
| 109407230         | 12/2018                 | CN             | N/A        |
| 109597169         | 12/2018                 | CN             | N/A        |
| 109814201         | 12/2018                 | CN             | N/A        |
| 110376691         | 12/2018                 | CN             | N/A        |
| 110471148         | 12/2018                 | CN             | N/A        |
| 110488433         | 12/2018                 | CN             | N/A        |
| 110858016         | 12/2019                 | CN             | N/A        |
| 210775927         | 12/2019                 | CN             | N/A        |
| 2016170363        | 12/2015                 | JP             | N/A        |
| 2017032731        | 12/2016                 | JP             | N/A        |
| 2018098858        | 12/2017                 | WO             | N/A        |
| 2020105779        | 12/2019                 | WO             | N/A        |

#### **OTHER PUBLICATIONS**

Chinese Notification of Grant of Invention Patent Rights in corresponding Chinese Application No. 202010988117.0, dated Sep. 6, 2023, translated, 7 pages. cited by applicant

International Search Report and Written Opinion dated Jun. 18, 2021 in corresponding International Application No. PCT/CN2020/134054, translated, 21 pages. cited by applicant

Chinese First Office Action dated Jul. 4, 2022 in corresponding Chinese Application No. 202010988113.2, translated, 14 pages. cited by applicant

Chinese First Office Action dated Jul. 27, 2022 in corresponding Chinese Application No. 202010988117.0, translated, 13 pages. cited by applicant

Chinese Second Office Action dated Mar. 14, 2023 in corresponding Chinese Application No. 202010988117.0, translated, 12 pages. cited by applicant

Chinese First Office Action dated Jul. 25, 2022 in corresponding Chinese Application No. 202010989983.1, translated, 17 pages. cited by applicant

Chinese First Office Action dated Jul. 25, 2022 in corresponding Chinese Application No.

*Primary Examiner:* Bello; Agustin

*Attorney, Agent or Firm:* MH2 TECHNOLOGY LAW GROUP LLP

---

## **Background/Summary**

**CROSS-REFERENCE TO RELATED APPLICATIONS** (1) This application is a continuation-in-part application of International Patent Application No. PCT/CN2020/134054, filed on Dec. 4, 2020, which claims priorities to Chinese Patent Application No. 202010989984.6, filed on Sep. 18, 2020; Chinese Patent Application No. 202010988117.0, filed on Sep. 18, 2020; Chinese Patent Application No. 202010988113.2, filed on Sep. 18, 2020; and Chinese Patent Application No. 202010989983.1, filed on Sep. 18, 2020, which are incorporated herein by reference in their entireties.

### **TECHNICAL FIELD**

(1) The present disclosure relates to the field of optical communication technologies, and in particular, to an optical module.

### **BACKGROUND**

(2) With the development of new services and application scenarios such as cloud computing, mobile internet, and video, the development and progress of optical communication technology has become increasingly important. In the optical communication technology, an optical module is a tool for achieving interconversion between an optical signal and an electrical signal and is one of the key components in an optical communication device. Moreover, with the development of optical communication technology, it is required that a transmission rate of the optical module is continuously increasing.

### **SUMMARY**

(3) An optical module is provided. The optical module includes a shell, a circuit board, a light receiving assembly, and a first fiber optic adapter. The circuit board is disposed in the shell. The light receiving assembly is disposed in the shell and is electrically connected with the circuit board. The light receiving assembly is configured to convert received optical signals into electrical signals. The fiber optic adapter is connected with the light receiving assembly, and the first fiber optic adapter is configured to transmit optical signals from an outside of the optical module to the light receiving assembly. The light receiving assembly includes a first cavity body, a first lens group, a plurality of wavelength division demultiplexers, and at least one light receiving component. The first cavity body is connected with the first fiber optic adapter. The first lens group is disposed in the first cavity body, and the first lens group is configured to split the optical signals transmitted by the first fiber optic adapter to the first cavity body for a first time according to a wavelength, so as to obtain a first optical signal beam and a second optical signal beam. The plurality of wavelength division demultiplexers are disposed in the first cavity body. The plurality of wavelength division demultiplexers include a first wavelength division demultiplexer and a second wavelength division demultiplexer. The first wavelength division demultiplexer is configured to receive the first optical signal beam and split the first optical signal beam for a second time according to a wavelength. The second wavelength division demultiplexer is configured to receive the second optical signal beam and split the second optical signal beam for a second time according to a wavelength. The at least one light receiving component is disposed in

the first cavity body. The light receiving component includes a plurality of light receiving chips. The plurality of light receiving chips are configured to receive the optical signals split for the second time by the plurality of wavelength division demultiplexers and convert the optical signals into the electrical signals.

---

## Description

### BRIEF DESCRIPTION OF THE DRAWINGS

(1) In order to describe the technical solutions in the present disclosure more clearly, accompanying drawings to be used in some embodiments of the present disclosure will be introduced briefly below. However, the accompanying drawings to be described below are merely accompanying drawings of some embodiments of the present disclosure, and a person of ordinary skill in the art may obtain other drawings according to these drawings. In addition, the accompanying drawings to be described below may be regarded as schematic diagrams but are not limitations on an actual size of a product, an actual process of a method and an actual timing of a signal involved in the embodiments of the present disclosure.

(2) FIG. 1 is a connection diagram of an optical communication system, in accordance with some embodiments;

(3) FIG. 2 is a diagram showing a structure of an optical network terminal, in accordance with some embodiments;

(4) FIG. 3 is a diagram showing a structure of an optical module, in accordance with some embodiments;

(5) FIG. 4 is an exploded view of an optical module, in accordance with some embodiments;

(6) FIG. 5 is a sectional view of an optical module, in accordance with some embodiments;

(7) FIG. 6 is an exploded view of a light emitting assembly and a light receiving assembly, in accordance with some embodiments;

(8) FIG. 7 is a diagram showing a structure of a light receiving assembly without a first cover plate, in accordance with some embodiments;

(9) FIG. 8 is a partial enlarged view of the circle A in FIG. 7;

(10) FIG. 9 is a diagram showing an optical path of a wavelength division demultiplexer, in accordance with some embodiments;

(11) FIG. 10 is a top view of a light receiving assembly without a first cover plate, in accordance with some embodiments;

(12) FIG. 11 is a sectional view showing a portion of a light receiving assembly, in accordance with some embodiments;

(13) FIG. 12 is a diagram showing an optical path of a first lens group, in accordance with some embodiments;

(14) FIG. 13 is a diagram showing an optical path of another first lens group, in accordance with some embodiments;

(15) FIG. 14 is an exploded view showing a portion of a light receiving assembly, in accordance with some embodiments;

(16) FIG. 15 is a sectional view of a first fiber optic adapter and a light receiving assembly, in accordance with some embodiments;

(17) FIG. 16 is a sectional view of a first fiber optic adapter and a displacement component, in accordance with some embodiments;

(18) FIG. 17 is a diagram showing a structure of a first cavity body, in accordance with some embodiments;

(19) FIG. 18 is a diagram showing a structure of a first cavity body from another perspective, in accordance with some embodiments;

(20) FIG. 19 is a diagram showing a structure of a light receiving assembly without a first cover plate and a displacement component, in accordance with some embodiments:

(21) FIG. 20 is a sectional view of the light receiving assembly in FIG. 19; and

(22) FIG. 21 is a sectional view of a first cavity body and a first cover plate, in accordance with some embodiments.

#### DETAILED DESCRIPTION

(23) Some embodiments of the present disclosure will be clearly and completely described below with reference to the accompanying drawings. However, the described embodiments are merely some but not all embodiments of the present disclosure. All other embodiments obtained by a person of ordinary skill in the art based on embodiments of the present disclosure shall be included in the protection scope of the present disclosure.

(24) Unless the context requires otherwise, throughout the specification and the claims, the term “comprise” and other forms thereof such as the third-person singular form “comprises” and the present participle form “comprising” are construed as an open and inclusive meaning, i.e., “including, but not limited to.” In the description of the specification, the terms such as “one embodiment,” “some embodiments,” “exemplary embodiments,” “example,” “specific example,” or “some examples” are intended to indicate that specific features, structures, materials, or characteristics related to the embodiment(s) or example(s) are included in at least one embodiment or example of the present disclosure. Schematic representations of the above terms do not necessarily refer to the same embodiment(s) or example(s). In addition, the specific features, structures, materials, or characteristics described herein may be included in any one or more embodiments or examples in any suitable manner.

(25) Hereinafter, the terms such as “first” and “second” are only used for descriptive purposes and are not to be construed as indicating or implying the relative importance or implicitly indicating the number of indicated technical features. Therefore, the feature defined with the term such as “first” or “second” may explicitly or implicitly include one or more of the features. In the description of the embodiments of the present disclosure, the term “a plurality of” or “the plurality of” means two or more unless otherwise specified.

(26) In the description of some embodiments, the term “connected” and derivatives thereof may be used. The term “connected” should be understood in a broad sense. For example, the term “connected” may represent a fixed connection, a detachable connection, or a one-piece connection, or may represent a direct connection, or may represent an indirect connection through an intermediate medium.

(27) The phrase “A and/or B” includes the following three combinations: only A, only B, and a combination of A and B.

(28) The use of the phrase “applicable to” or “configured to” herein means an open and inclusive expression, which does not exclude devices that are applicable to or configured to perform additional tasks or steps.

(29) The term such as “about,” “substantially,” or “approximately” as used herein includes a stated value and an average value within an acceptable range of deviation of a particular value. The acceptable range of deviation is determined by a person of ordinary skill in the art, considering measurement in question and errors associated with measurement of a particular quantity (i.e., limitations of a measurement system).

(30) The term such as “parallel,” “perpendicular,” or “equal” as used herein includes a stated condition and a condition similar to the stated condition. A range of the similar condition is within an acceptable deviation range, and the acceptable deviation range is determined by a person of ordinary skill in the art, considering measurement in question and the error associated with the measurement of a particular quantity (i.e., the limitation of a measurement system).

(31) In optical communication technologies, light is used to carry information to be transmitted, and an optical signal carrying the information is transmitted to an information processing device

such as a computer through an information transmission device such as an optical fiber or an optical waveguide, so as to achieve transmission of the information. Since an optical signal has a characteristic of passive transmission when being transmitted through the optical fiber or the optical waveguide, low-cost and low-loss information transmission may be achieved. In addition, a signal transmitted by the information transmission device such as the optical fiber or the optical waveguide is an optical signal, while a signal that can be recognized and processed by the information processing device such as the computer is an electrical signal. Therefore, in order to establish information connection between the information transmission device such as the optical fiber or the optical waveguide and the information processing device such as the computer, it is necessary to achieve interconversion between the electrical signal and the optical signal.

(32) An optical module implements the interconversion between the optical signal and the electrical signal in the field of optical fiber communication technologies. The optical module includes an optical port and an electrical port. The optical module achieves optical communication with the information transmission device such as the optical fiber or the optical waveguide through the optical port and achieves electrical connection with an optical network terminal (e.g., an optical modem) through the electrical port. The electrical connection is mainly used for achieving power supply, transmission of an inter-integrated circuit (I2C) signal, transmission of data signal, and grounding. The optical network terminal transmits an electric signal to the information processing device such as the computer through a network cable or a wireless fidelity (Wi-Fi) technology.

(33) FIG. 1 is a connection diagram of an optical communication system, in accordance with some embodiments. As shown in FIG. 1, an optical communication system mainly includes a remote server **1000**, a local information processing device **2000**, an optical network terminal **100**, an optical module **200**, an optical fiber **101**, and a network cable **103**.

(34) An end of the optical fiber **101** is connected to the remote server **1000**, and the other end of the optical fiber **101** is connected to the optical network terminal **100** through the optical module **200**. The optical fiber itself can support long-distance signal transmission such as several-kilometer (6-kilometer to 8-kilometer) signal transmission. On this basis, ultra-long-distance transmission may be achieved theoretically if a repeater is used. Therefore, in a typical optical communication system, a distance between the remote server **1000** and the optical network terminal **100** may typically reach several kilometers, tens of kilometers, or hundreds of kilometers.

(35) An end of the network cable **103** is connected to the local information processing device **2000**, and the other end of the network cable **103** is connected to the optical network terminal **100**. The local information processing device **2000** may include any or more of the following devices: a router, a switch, a computer, a mobile phone, a tablet computer, a television, or the like.

(36) A physical distance between the remote server **1000** and the optical network terminal **100** is greater than a physical distance between the local information processing device **2000** and the optical network terminal **100**. Connection between the local information processing device **2000** and the remote server **1000** is accomplished by the optical fiber **101** and the network cable **103**, and connection between the optical fiber **101** and the network cable **103** is accomplished by the optical module **200** and the optical network terminal **100**.

(37) The optical network terminal **100** includes a housing in a substantially cuboid shape, and an optical module interface **102** and a network cable interface **104** that are disposed on the housing. The optical module interface **102** is configured to be connected to the optical module **200**, so that bidirectional electrical signal connection is established between the optical network terminal **100** and the optical module **200**. The network cable interface **104** is configured to be connected to the network cable **103**, so that bidirectional electrical signal connection is established between the optical network terminal **100** and the network cable **103**. Connection between the optical module **200** and the network cable **103** is established by the optical network terminal **100**. For example, the optical network terminal **100** transmits electrical signals from the optical module **200** to the network cable **103** and transmits electrical signals from the network cable **103** to the optical

module **200**. Therefore, the optical network terminal **100**, as a master monitor of the optical module **200**, can monitor the operation of the optical module **200**. In addition to the optical network terminal **100**, the master monitor of the optical module **200** may further include an optical line terminal (OLT).

(38) The optical module **200** includes an optical port and an electrical port. The optical port is configured to be connected to the optical fiber **101**, so that bidirectional optical signal connection is established between the optical module **200** and the optical fiber **101**. The electrical port is configured to be connected to the optical network terminal **100**, so that bidirectional electrical signal connection is established between the optical module **200** and the optical network terminal **100**. The interconversion between the optical signal and the electrical signal is achieved by the optical module **200**, so that connection is established between the optical fiber **101** and the optical network terminal **100**. For example, optical signals from the optical fiber **101** are converted into electrical signals by the optical module **200**, and then the electrical signals are input into the optical network terminal **100**. Electrical signals from the optical network terminal **100** are converted into optical signals by the optical module **200**, and then the optical signal are input into the optical fiber **101**. Since the optical module **200** is a tool for achieving interconversion between the optical signal and the electrical signal and has no function of processing data, information does not change in the above photoelectric conversion process.

(39) A bidirectional signal transmission channel is established between the remote server **1000** and the local information processing device **2000** by the optical fiber **101**, the optical module **200**, the optical network terminal **100**, and the network cable **103**.

(40) FIG. 2 is a diagram showing a structure of an optical network terminal, in accordance with some embodiments. In order to clearly show a connection relationship between the optical module **200** and the optical network terminal **100**, FIG. 2 shows only a structure of the optical network terminal **100** related to the optical module **200**. As shown in FIG. 2, the optical network terminal **100** further includes a PCB circuit board **105** disposed in the housing, a cage **106** disposed on a surface of the PCB circuit board **105**, a heat sink **107** disposed on the cage **106**, and an electrical connector disposed inside the cage **106**. The electrical connector is configured to be connected to the electrical port of the optical module **200**; and the heat sink **107** has protruding structures such as fins for increasing a heat dissipation area.

(41) The optical module **200** is inserted into the cage **106** of the optical network terminal **100** and is fixed by the cage **106**. Heat generated by the optical module **200** is conducted to the cage **106** and is then diffused by the heat sink **107**. After the optical module **200** is inserted into the cage **106**, the electrical port of the optical module **200** is connected to the electrical connector inside the cage **106**, so that the bidirectional electrical signal connection is established between the optical module **200** and the optical network terminal **100**. In addition, the optical port of the optical module **200** is connected to the optical fiber **101**, so that the bidirectional optical signal connection is established between the optical module **200** and the optical fiber **101**.

(42) FIG. 3 is a diagram showing a structure of an optical module, in accordance with some embodiments. FIG. 4 is an exploded view of an optical module, in accordance with some embodiments. As shown in FIGS. 3 and 4, the optical module **200** includes a shell, and a circuit board **300**, a light emitting assembly **400**, and a light receiving assembly **500** that are disposed inside the shell. However, the present disclosure is not limited thereto. In some embodiments, the optical module **200** includes one of the light emitting assembly **400** and the light receiving assembly **500**.

(43) The shell includes an upper shell **201** and a lower shell **202**. The upper shell **201** covers the lower shell **202** to form the shell with two openings **204** and **205**, and an outer contour of the shell is generally in a shape of a cuboid.

(44) In some embodiments, the lower shell **202** includes a bottom plate **2021** and two lower side plates **2022** that are located on two sides of the bottom plate **2021** respectively and disposed



perpendicular to the bottom plate **2021**; the upper shell **201** includes a cover plate **2011**, and the cover plate **2011** covers the two lower side plates **2022** of the lower shell **202** to form the shell. (45) In some embodiments, the lower shell **202** includes a bottom plate **2021** and two lower side plates **2022** that are located on two sides of the bottom plate **2021** respectively and disposed perpendicular to the bottom plate **2021**; the upper shell **201** includes a cover plate **2011** and two upper side plates that are located on two sides of the cover plate respectively and disposed perpendicular to the cover plate **2011**. The two upper side plates are combined with the two lower side plates **2022**, so that the upper shell **201** covers the lower shell **202**.

(46) A direction in which a connecting line between the two openings **204** and **205** extends may or may not be the same as a length direction of the optical module **200**. For example, the opening **204** is located at an end (the right end in FIG. 3) of the optical module **200**, and the opening **205** is also located at an end (the left end in FIG. 3) of the optical module **200**. Alternatively, the opening **204** is located at an end of the optical module **200**, while the opening **205** is located at a side of the optical module **200**. The opening **204** is the electrical port, and a connecting finger **301** of the circuit board **300** extends from the electrical port **204**, and is inserted into the master monitor (e.g., the optical network terminal **100**). The opening **205** is the optical port and is configured to be connected to the external optical fiber **101**, so that the optical fiber **101** is connected to the light emitting assembly **400** and the light receiving assembly **500** in the optical module **200**.

(47) With help of an assembly manner of combining the upper shell **201** with the lower shell **202**, it is helpful to install components such as the circuit board **300**, the light emitting assembly **400**, and the light receiving assembly **500** into the shell, and these components may be encapsulated and protected by the upper shell **201** and the lower shell **202**. In addition, during assembly of the components such as the circuit board **300**, the light emitting assembly **400**, and the light receiving assembly **500**, it is also helpful to arrange positioning elements, heat dissipation elements, and electromagnetic shielding elements of these components, which facilitates automated implementation of production.

(48) In some embodiments, the upper shell **201** and the lower shell **202** are made of a metallic material, which facilitates electromagnetic shielding and heat dissipation.

(49) In some embodiments, the optical module **200** further includes an unlocking component **203** located outside the shell thereof. The unlocking component **203** is configured to implement or release fixed connection between the optical module **200** and the master monitor.

(50) For example, the unlocking component **203** is located outside the two lower side plates **2022** of the lower shell **202** and includes an engagement component that is matched with a cage of the master monitor (e.g., the cage **106** of the optical network terminal **100**). When the optical module **200** is inserted into the cage **106**, the optical module **200** is fixed in the cage **106** by the engagement component of the unlocking component **203**. When the unlocking component **203** is pulled, the engagement component of the unlocking component **203** moves with the pulling, and then a connection relationship between the engagement component and the master monitor is changed to release an engagement relationship between the optical module **200** and the master monitor, so that the optical module **200** may be drawn out of the cage **106**.

(51) The circuit board **300** includes circuit wires, electronic elements, and chips. The electronic elements and the chips are connected together by the circuit wires according to a circuit design, so as to achieve functions such as power supply, electrical signal transmission, and grounding. The electronic elements may include, for example, a capacitor, a resistor, a triode, and a metal-oxide-semiconductor field-effect transistor (MOSFET). The chips may include, for example, a microcontroller unit (MCU), a laser driver chip, a transimpedance amplifier (TIA), a limiting amplifier, a clock and data recovery (CDR) chip, a power management chip, or a digital signal processing (DSP) chip.

(52) The circuit board **300** is generally a rigid circuit board, and the rigid circuit board may also achieve a bearing function due to its relatively hard material. For example, the rigid circuit board

may stably bear the electronic elements and the chips. The rigid circuit board may also be inserted into an electrical connector inside the cage of the master monitor.

(53) The circuit board **300** further includes the connecting finger **301** formed on a surface of the end thereof, and the connecting finger **301** is composed of a plurality of pins independent of each other. The circuit board **300** is inserted into the cage **106** and is conductively connected to the electrical connector inside the cage **106** through the connecting finger **301**. The connecting finger **301** may be disposed on only a surface (e.g., the upper surface shown in FIG. **4**) of the circuit board **300** or may be disposed on both upper and lower surfaces of the circuit board **300** to adapt to an occasion with a demand for a large number of pins. The connecting finger **301** is configured to establish electrical connection with the master monitor, so as to achieve power supply, grounding, transmission of I2C signals, and transmission of data signals. Of course, flexible circuit boards are also used in some optical modules. A flexible circuit board is generally used in conjunction with a rigid circuit board as a supplement for the rigid circuit board.

(54) In some embodiments, the light emitting assembly **400** and the light receiving assembly **500** are located on a side of the circuit board **300** away from the connecting finger **301**, and the light emitting assembly **400** and the light receiving assembly **500** are arranged in a stack (e.g., stacked one on top of the other). For example, as shown in FIG. **4**, the light emitting assembly **400** is disposed on a side of the light receiving assembly **500** proximate to the upper shell **201**. That is to say, the light emitting assembly **400** is closer to the upper shell **201** than the light receiving assembly **500**. Alternatively, the light emitting assembly **400** is disposed on a side of the light receiving assembly **500** away from the upper shell **201**. That is to say, the light emitting assembly **400** is farther from the upper shell **201** than the light receiving assembly **500**.

(55) In a case where the light emitting assembly **400** is closer to the upper shell **201** than the light receiving assembly **500**, the lower shell **202** may directly support the light receiving assembly **500**, and the light receiving assembly **500** supports the light emitting assembly **400**. Of course, in some embodiments, the lower shell **202** may also support the light receiving assembly **500** through a cushion block.

(56) In some embodiments, the light emitting assembly **400** and the light receiving assembly **500** are physically separated from the circuit board **300**, and each are electrically connected to the circuit board **300** through a corresponding flexible circuit board or electrical connecting member. Since the light emitting assembly **400** and the light receiving assembly **500** each have a large volume and cannot be disposed on the circuit board **300**, the light emitting assembly **400** and the light receiving assembly **500** are disposed separately from the circuit board **300** and are electrically connected to the circuit board **300** through the flexible circuit board or the electrical connecting member.

(57) FIG. **5** is a sectional view of an optical module, in accordance with some embodiments. As shown in FIG. **5**, the optical module **200** further includes a first fiber optic adapter **510** and a second fiber optic adapter **410**. The second fiber optic adapter **410** is disposed at an end of the light emitting assembly **400** away from the circuit board **300**, and the second fiber optic adapter **410** is connected to the light emitting assembly **400**. The second fiber optic adapter **410** is configured to transmit an optical signal from the light emitting assembly **400** to the outside of the optical module **200**. The first fiber optic adapter **510** is disposed at an end of the light receiving assembly **500** away from the circuit board **300**, and the first fiber optic adapter **510** is connected to the light receiving assembly **500**. The first fiber optic adapter **510** is configured to transmit an optical signal from the outside of the optical module **200** to the light receiving assembly **500**.

(58) As shown in FIG. **5**, the second fiber optic adapter **410** and the first fiber optic adapter **510** are located at a same height in a height direction (e.g., the MN direction) of the optical module **200**. The second fiber optic adapter **410** and the first fiber optic adapter **510** are connected to optical fiber connectors outside the optical module **200**, respectively. Since the optical fiber connector is a standard part, and a shape and size of the optical fiber connector limit positions of the two fiber

optic adapters of the optical module **200**, it is required that the second fiber optic adapter **410** and the first fiber optic adapter **510** are disposed at the same height.

(59) FIG. **6** is an exploded view of a light emitting assembly and a light receiving assembly, in accordance with some embodiments. FIG. **7** is a diagram showing a structure of a light receiving assembly without a first cover plate, in accordance with some embodiments. FIG. **8** is a partial enlarged view of the circle A in FIG. **7**.

(60) In some embodiments, as shown in FIGS. **6** and **7**, the light receiving assembly **500** includes a first cavity body **520**, a first cover plate **504**, and a light receiving component **505**. For example, as shown in FIG. **7**, the first cavity body **520** includes a base **5201**, a side wall **5202**, and a cavity **5203**. The side wall **5202** is arranged around the base **5201**, and the base **5201** and the side wall **5202** jointly define the cavity **5203**. The cavity **5203** is configured to accommodate optical components (e.g., lenses) and a light receiving component **505** (e.g., an electrical element such as a light receiving chip or a transimpedance amplifier) in the light receiving assembly **500**. The first cover plate **504** covers the first cavity body **520** to close the cavity **5203**.

(61) An end of the first cavity body **520** is connected to the first fiber optic adapter **510**, so as to receive the optical signal from the outside of the optical module **200** through the first fiber optic adapter **510** and transmit the received optical signal to the light receiving component **505** through the optical components disposed in the first cavity body **520**.

(62) For example, as shown in FIG. **7**, the base **5201** is in a shape of a rectangle, and the side wall **5202** includes four side sub-walls **5202A** connected in sequence. The first cavity body **520** further includes a first via hole **522** and a first opening **521**. The first via hole **522** and the first opening **521** are disposed on two opposite side sub-walls **5202A** of the four side sub-walls **5202A**, respectively. The first via hole **522** is proximate to the first fiber optic adapter **510** and communicates with the cavity **5203**. The first fiber optic adapter **510** is connected to the first cavity body **520** through the first via hole **522**. The first opening **521** is proximate to the circuit board **300**, and the first opening **521** penetrates a corresponding side sub-wall **5202A** and communicates with the cavity **5203**. The optical module **200** further includes a flexible circuit board **310**, and the flexible circuit board **310** is inserted into the cavity **5203** through the first opening **521**. An end of the flexible circuit board **310** is inserted into the first opening **521** and fixed in the cavity **5203**, and the other end of the flexible circuit board **310** is electrically connected with the circuit board **300**. For example, the end of the flexible circuit board **310** is electrically connected with the light receiving component **505**.

(63) Of course, in some embodiments, the light receiving component **505** in the first cavity body **520** may also be connected to the circuit board **300** through an electrical connecting member (e.g., a metallized circuit board composed of multiple layers). For example, the optical module **200** further includes the electrical connecting member. The electrical connecting member passes through the first opening **521** and is electrically connected with the light receiving component **505**. The electrical connecting member is connected with the circuit board **300** through the flexible circuit board **310**, so as to achieve electrical connection between the circuit board **300** and the light receiving assembly **500**.

(64) In some embodiments, the first cavity body **520** and the first cover plate **504** may be made of a metal material. For example, the first cavity body **520** and the first cover plate **504** are metal members processed by die casting and milling.

(65) In the optical module **200** provided by some embodiments of the present disclosure, the light receiving assembly **500** is configured to receive a plurality of optical signals with different wavelengths and split the plurality of optical signals with different wavelengths according to the wavelength. The plurality of optical signals with different wavelengths are transmitted into the first cavity body **520** through the first fiber optic adapter **510**. The optical components in the first cavity body **520** split the optical signals according to the wavelength and transmit the optical signals after being split to a photosensitive surface of a corresponding light receiving chip. The light receiving chip receives a corresponding optical signal through the photosensitive surface. Since a light

receiving chip usually receives an optical signal of one wavelength, the light receiving component **505** includes a plurality of light receiving chips, so as to receive the plurality of optical signals with different wavelengths.

(66) For example, in a case where the light receiving assembly **500** is configured to receive optical signals of four different wavelengths, the light receiving component **505** includes four light receiving chips, so as to receive the optical signals of four wavelengths. Alternatively, as shown in FIG. **8**, in a case where the light receiving assembly **500** is configured to receive optical signals of eight different wavelengths, the light receiving component **505** includes eight light receiving chips (**583** and **593**), so as to receive the optical signals of eight wavelengths.

(67) In some embodiments, as shown in FIG. **7**, the light receiving assembly **500** further includes a first lens group **530** and a plurality of wavelength division demultiplexers (DeMUXs) **506**. The first lens group **530** includes a plurality of lenses, so as to split the optical signals transmitted from the first fiber optic adapter **510** to the first cavity body **520** for a first time according to a wavelength through mutual cooperation of the plurality of lenses. The plurality of optical signals split by the first lens group **530** each are incident on the corresponding wavelength division demultiplexer **506**.

(68) For example, the first lens group **530** splits the optical signals transmitted from the first fiber optic adapter **510** to the first cavity body **520** into two optical signals according to the wavelength. As shown in FIG. **7**, the plurality of wavelength division demultiplexers **506** include a first wavelength division demultiplexer **540** and a second wavelength division demultiplexer **550**. The two optical signals split by the first lens group **530** are incident on the first wavelength division demultiplexer **540** and the second wavelength division demultiplexer **550** respectively.

(69) A wave band usually includes multiple wavelengths. For example, the light receiving assembly **500** is used to receive optical signals of eight different wavelengths (e.g., optical signals of wavelengths  $\lambda_1$ ,  $\lambda_2$ ,  $\lambda_3$ ,  $\lambda_4$ ,  $\lambda_5$ ,  $\lambda_6$ ,  $\lambda_7$  and  $\lambda_8$ ). Here, the wavelengths  $\lambda_1$ ,  $\lambda_2$ ,  $\lambda_3$ , and  $\lambda_4$  are close to each other, and the wavelengths  $\lambda_1$ ,  $\lambda_2$ ,  $\lambda_3$ , and  $\lambda_4$  are within a first wave band. The wavelengths  $\lambda_5$ ,  $\lambda_6$ ,  $\lambda_7$  and  $\lambda_8$  are close to each other, and the wavelengths  $\lambda_5$ ,  $\lambda_6$ ,  $\lambda_7$  and  $\lambda_8$  are within a second wave band. The first lens group **530** splits the optical signals transmitted by the first fiber optic adapter **510** into a first optical signal beam and a second optical signal beam. The optical signals within the first wave band constitute the first optical signal beam, and the optical signals within the second wave band constitute the second optical signal beam. Of course, in some embodiments, the first lens group **530** may also split the optical signals into three, four or more optical signals according to the wavelength.

(70) The two optical signals split by the first lens group **530** each are incident on the corresponding wavelength division demultiplexer **506**. The wavelength division demultiplexer **506** splits the optical signals incident on the wavelength division demultiplexer **506** for a second time according to the wavelength and transmits the optical signals after being split for the second time to the corresponding light receiving chip.

(71) FIG. **9** is a diagram showing an optical path of a wavelength division demultiplexer, in accordance with some embodiments. As shown in FIG. **9**, the wavelength division demultiplexer **506** has a light input end **506A** and a light output end **506B**. The light output end **506B** of the wavelength division demultiplexer **506** is proximate to the light receiving component **505**, and the light input end **506A** of the wavelength division demultiplexer **506** is opposite to the light output end **506B**. The wavelength division demultiplexer **506** includes a light inlet for receiving optical signals of multiple wavelengths, and the light inlet is located at the light input end **506A** of the wavelength division demultiplexer **506**. The wavelength division demultiplexer **506** further includes a plurality of light outlets for exit of the optical signals, each of the plurality of light outlets is used for exit of an optical signal of one wavelength. The plurality of light outlets are located at the light output end **506B** of the wavelength division demultiplexer **506**. The number of the light outlets is equal to the number of the plurality of optical signals with different wavelengths.

(72) The beam splitting process of the wavelength division demultiplexer **506** is described below

by considering an example in which optical signals of four different wavelengths (e.g.,  $\beta 1$ ,  $\beta 2$ ,  $\beta 3$ , and  $\beta 4$ ) exit from the wavelength division demultiplexer **506**, and the wavelength division demultiplexer **506** includes four light outlets. It will be noted that the four light outlets are a first light outlet, a second light outlet, a third light outlet, and a fourth light outlet.

(73) A beam of optical signals with four different wavelengths (e.g.,  $\beta 1$ ,  $\beta 2$ ,  $\beta 3$ , and  $\beta 4$ ) enters into the wavelength division demultiplexer **506** through the light inlet of the wavelength division demultiplexer **506**. An optical signal of the wavelength  $\beta 1$  is reflected multiple times (e.g., six times) at a plurality of (e.g., six) different positions in the wavelength division demultiplexer **506** to reach the first light outlet; an optical signal of the wavelength  $\beta 2$  is reflected multiple times (e.g., four times) at a plurality of (e.g., four) different positions in the wavelength division demultiplexer **506** to reach the second light outlet; an optical signal of the wavelength  $\beta 3$  is reflected multiple times (e.g., twice) at a plurality of (e.g., two) different positions in the wavelength division demultiplexer **506** to reach the third light outlet; and an optical signal of the wavelength  $\beta 4$  is incident on the wavelength division demultiplexer **506** and reaches the fourth light outlet directly without being reflected. In this way, by providing the wavelength division demultiplexer **506**, optical signals of different wavelengths are input through a same light inlet and are output through different light outlets, so that the wavelength division demultiplexer **506** can split optical signals of different wavelengths.

(74) It can be understood that, the wavelength division demultiplexer **506** transmits and reflects optical signals of different wavelengths by different film layers disposed at different positions on two sides of the wavelength division demultiplexer **506**, so as to split a beam of optical signals with different wavelengths into a plurality of optical signals with different wavelengths.

(75) Of course, in some embodiments, the wavelength division demultiplexer **506** may also be used for splitting optical signals of two, three, five, or more wavelengths, and the present disclosure is not limited thereto.

(76) The light receiving assembly **500** in some embodiments of the present disclosure will mainly be described below by considering an example in which the light receiving assembly **500** is configured to receive optical signals of eight different wavelengths, the optical signals with eight different wavelengths are within two wave bands (e.g., the first wave band and the second wave band), respectively, each of the two wave bands includes optical signals with four different wavelengths, and the light receiving assembly **500** includes two wavelength division demultiplexers **506**.

(77) In some embodiments, the light receiving assembly **500** may include one or more light receiving components **505**. For example, as shown in FIG. 7, the plurality of light receiving components **505** include a first light receiving component **580** and a second light receiving component **590**. The first lens group **530** splits the optical signals transmitted by the first fiber optic adapter **510** for the first time according to the wavelength, so as to obtain the first optical signal beam and the second optical signal beam.

(78) The first optical signal beam is incident on the first wavelength division demultiplexer **540**. The first wavelength division demultiplexer **540** splits the first optical signal beam into a first group of optical signals with four channels and transmits the first group of optical signals with four channels to the first light receiving component **580**.

(79) The second optical signal beam is incident on the second wavelength division demultiplexer **550**. The second wavelength division demultiplexer **550** splits the second optical signal beam into a second group of optical signals with four channels and transmits the second group of optical signals with four channels to the second light receiving component **590**.

(80) In some embodiments, as shown in FIG. 8, the first light receiving component **580** includes a first light receiving chip **583**, and the second light receiving component **590** includes a second light receiving chip **593**. For example, the first light receiving component **580** includes a plurality of first light receiving chips **583**, so as to correspond to the optical signals with the plurality of channels

after being split by the first wavelength division demultiplexer **540**; and the second light receiving component **590** includes a plurality of second light receiving chips **593**, so as to correspond to the optical signals with the plurality of channels after being split by the second wavelength division demultiplexer **550**. The light receiving chip (e.g., the first light receiving chip **583** and the second light receiving chip **593**) may be a photoelectric detector (PD), so as to convert the received optical signal into the electrical signal (e.g., a current signal). For example, the photoelectric detector includes an avalanche photon diode (APD) and a PIN photo diode (PIN-PD).

(81) In some embodiments, the first light receiving component **580** and the second light receiving component **590** each include a metallized ceramic. The plurality of light receiving chips of the first light receiving component **580** and the second light receiving component **590** each are disposed on a surface of the corresponding metallized ceramic. The metallized ceramic has a circuit pattern on a surface thereof, so as to power the light receiving chips. The metallized ceramic may be mounted on the flexible circuit board **310**. Of course, in some embodiments, the light receiving component may not be provided with the metallized ceramic, in this case, the light receiving chips are directly mounted on the flexible circuit board **310**. The metallized ceramic refers to a ceramic with a metal layer deposited on a surface thereof, and the metal layer is provided with a circuit pattern.

(82) In addition, as shown in FIG. **8**, the light receiving component **505** further includes a transimpedance amplifier **507**. The transimpedance amplifier **507** is connected with the corresponding light receiving chip, so as to receive a current signal generated by the light receiving chip and convert the received current signal into a voltage signal. The transimpedance amplifier **507** is connected with the corresponding light receiving chip through a wire bonding process. For example, the transimpedance amplifier **507** is connected to the light receiving chip through a gold bonding wire. The transimpedance amplifier **507** may be mounted on the flexible circuit board **310**, or the transimpedance amplifier **507** may be disposed on the electrical connecting member.

(83) For example, as shown in FIG. **8**, the first light receiving component **580** includes a first substrate **581** and a first transimpedance amplifier **582**, and the first transimpedance amplifier **582** is disposed on a side of the first substrate **581** proximate to the circuit board **300**. The first substrate **581** is made of the metallized ceramic, and the first substrate **581** is provided with a plurality (e.g., four) of first light receiving chips **583**. The first substrate **581** facilitates the installation of the first light receiving chips **583**. The first light receiving chips **583** are connected to the first transimpedance amplifier **582** through the wiring bonding process.

(84) However, the longer lengths of connecting lines (e.g., the gold bonding wires) between the first light receiving chips **583** and the first transimpedance amplifier **582**, the greater the inductance of the connecting lines and the worse the matching of the signals. An amplitude of the signal (e.g., small signal) output by the first light receiving chip **583** is small, and the signal is easy to be interfered, resulting in low signal quality. Therefore, it is required that the first light receiving chips **583** are provided proximate to the first transimpedance amplifier **582**, so as to reduce the lengths of the connecting lines and improve the transmission quality of the signals. For example, the first transimpedance amplifier **582** is disposed on a side of the first substrate **581** and is proximate to the first substrate **581**. Moreover, the first substrate **581** may also raise a height of each first light receiving chip **583**, so as to make electrodes of the first light receiving chips **583** and pins of the first transimpedance amplifier **582** at a same height, thereby shortening the lengths of the connecting lines between the first light receiving chips **583** and the first transimpedance amplifier **582**.

(85) As shown in FIG. **8**, the second light receiving component **590** includes a second substrate **591** and a second transimpedance amplifier **592**, and the second transimpedance amplifier **592** is disposed on a side of the second substrate **591** proximate to the circuit board **300**. The second substrate **591** is made of the metallized ceramic, and the second substrate **591** is provided with a plurality (e.g., four) of second light receiving chips **593**. The second substrate **591** may facilitate the installation of the second light receiving chips **593**. The second light receiving chips **593** are

connected to the second transimpedance amplifier **592** through the wiring bonding process. Similar to the first substrate **581**, the second substrate **591** is proximate to the second transimpedance amplifier **592**, so as to reduce lengths of connecting lines between the second light receiving chips **593** and the second transimpedance amplifier **592**. Moreover, the second substrate **591** may also raise a height of each second light receiving chip **593**, so as to make electrodes of the second light receiving chips **593** and pins of the second transimpedance amplifier **592** at a same height, thereby shortening the lengths of the connecting lines between the second light receiving chips **593** and the second transimpedance amplifier **592**.

(86) It will be noted that, if the pins of a transimpedance amplifier **507** may correspond to the electrodes of the first light receiving chips **583** and the second light receiving chips **593**, the light receiving assembly **500** may use one transimpedance amplifier **507**. In this case, the first light receiving chips **583** and the second light receiving chips **593** may be disposed on a same metallized ceramic substrate.

(87) In some embodiments, as shown in FIGS. **7** and **8**, the light receiving assembly **500** further includes a second lens assembly **560** and a third lens assembly **570**. The second lens assembly **560** and the third lens assembly **570** are disposed in the cavity **5203** of the first cavity body **520**.

(88) The second lens assembly **560** is located on an optical path between the first wavelength division demultiplexer **540** and the first light receiving component **580**, and the second lens assembly **560** is configured to transmit the first group of optical signals with the plurality of channels (four channels) after being split by the first wavelength division demultiplexer **540** to the first light receiving component **580**.

(89) The third lens assembly **570** is located on an optical path between the second wavelength division demultiplexer **550** and the second light receiving component **590**, and the third lens assembly **570** is configured to transmit the second group of optical signals with the plurality of channels (four channels) after being split by the second wavelength division demultiplexer **550** to the second light receiving component **590**.

(90) In the optical module **200** provided by some embodiments of the present disclosure, optical axes of the first group of optical signals with the plurality of channels and the second group of optical signals with the plurality of channels are parallel to a bottom surface of the first cavity body **520**, and the photosensitive surfaces of the first light receiving chips **583** and the second light receiving chips **593** each are also parallel to the bottom surface of the first cavity body **520**. It will be noted that, the bottom surface of the first cavity body **520** may refer to a bottom surface of the cavity **5203**. For example, the bottom surface of the cavity **5203** may be parallel to the horizontal plane. In order to make the first light receiving chips **583** and the second light receiving chips **593** receive the corresponding optical signal (e.g., the first group of optical signals with the plurality of channels or the second group of optical signals with the plurality of channels), as shown in FIG. **8**, the second lens assembly **560** includes a first reflecting prism **561**, and the third lens assembly **570** includes a second reflecting prism **571**.

(91) The first reflecting prism **561** is disposed on a side (e.g., the upper side) of the first substrate **581** away from the base **5201**, and a projection of the first reflecting prism **561** on the first substrate **581** covers the plurality of first light receiving chips **583** disposed on the first substrate **581**. The first reflecting prism **561** is configured to reflect the first group of optical signals with the plurality of channels after being split by the first wavelength division demultiplexer **540** to the corresponding first light receiving chip **583**. In this way, it is possible to change a direction of the optical axis of the first group of optical signals with the plurality of channels through the reflection of the first reflecting prism **561**, so that the optical axis of the first group of optical signals with the plurality of channels is changed from a direction parallel to the bottom surface of the first cavity body **520** to a direction perpendicular to the bottom surface the first cavity body **520**. As a result, the first group of optical signals with the plurality of channels are vertically incident on the photosensitive surface of the corresponding first light receiving chip **583**.

(92) Similarly, the second reflecting prism **571** is disposed on a side (e.g., the upper side) of the second substrate **591** away from the base **5201**, and a projection of the second reflecting prism **571** on the second substrate **591** covers the plurality of second light receiving chips **593** disposed on the second substrate **591**. The second reflecting prism **571** is configured to reflect the second group of optical signals with the plurality of channels after being split by the second wavelength division demultiplexer **550** to the corresponding second light receiving chip **593**. In this way, it is possible to change a direction of the optical axis of the second group of optical signals with the plurality of channels through the reflection of the second reflecting prism **571**, so that the optical axis of the second group of optical signals with the plurality of channels is changed from the direction parallel to the bottom surface of the first cavity body **520** to the direction perpendicular to the bottom surface the first cavity body **520**. As a result, the second group of optical signals with the plurality of channels are vertically incident on the photosensitive surface of the corresponding second light receiving chip **593**.

(93) In some embodiments, referring to FIG. **8**, the first reflecting prism **561** has a first reflecting surface **5610**, and the second reflecting prism **571** has a second reflecting surface **5710**. An included angle between the first reflecting surface **5610** and an exiting direction of the first group of optical signals with the plurality of channels after being split by the first wavelength division demultiplexer **540** is  $45^\circ$ , and a projection of the first reflecting surface **5610** on the first substrate **581** covers the plurality of first light receiving chips **583** disposed on the first substrate **581**. An included angle between the second reflecting surface **5710** and an exiting direction of the second group of optical signals with the plurality of channels after being split by the second wavelength division demultiplexer **550** is  $45^\circ$ , and a projection of the second reflecting surface **5710** on the second substrate **591** covers the plurality of second light receiving chips **593** disposed on the second substrate **591**.

(94) FIG. **10** is a top view of a light receiving assembly without a first cover plate, in accordance with some embodiments.

(95) In some embodiments, as shown in FIG. **10**, the second lens assembly **560** further includes a plurality of first converging lenses **562**, and the third lens assembly **570** further includes a plurality of second converging lenses **572**.

(96) The plurality of first converging lenses **562** each are disposed on a light-exit side of the first wavelength division demultiplexer **540**, and the plurality of first converging lenses **562** correspond to a plurality of light outlets of the first wavelength division demultiplexer **540** respectively. Each first converging lens **562** is configured to converge the corresponding optical signal exiting from the first wavelength division demultiplexer **540** to the first reflecting prism **561**.

(97) The plurality of second converging lenses **572** each are disposed on a light-exit side of the second wavelength division demultiplexer **550**, and the plurality of second converging lenses **572** correspond to a plurality of light outlets of the second wavelength division demultiplexer **550** respectively. Each second converging lens **572** is configured to converge the corresponding optical signal exiting from the second wavelength division demultiplexer **550** to the second reflecting prism **571**.

(98) For example, the second lens assembly **560** includes four first converging lenses **562**, and the third lens assembly **570** includes four second converging lenses **572**.

(99) FIG. **11** is a sectional view showing a portion of a light receiving assembly, in accordance with some embodiments. As shown in FIGS. **8** and **11**, the first wavelength division demultiplexer **540** splits the first optical signal beam incident thereon into the first group of optical signals with the plurality of channels according to the wavelength. The first group of optical signals with the plurality of channels each are incident on the corresponding first converging lens **562** and then are incident on the first reflecting prism **561** after being converged by the corresponding first converging lens **562**. After an optical signal incident on the first reflecting prism **561** is reflected by the first reflecting surface **5610**, a transmission direction of the optical signal is changed from the



direction parallel to the bottom surface of the first cavity body **520** to the direction perpendicular to the bottom surface of the first cavity body **520**, and is incident on the corresponding first light receiving chip **583** located on a side (e.g., the lower side) of the first reflecting prism **561** proximate to the base **5201**.

(100) In some embodiments, the first lens group **530** includes a plurality of lenses. The plurality of lenses may split the optical signals transmitted by the first fiber optic adapter **510** into the first optical signal beam and the second optical signal beam according to the wavelength. For example, the first lens group **530** includes four lenses arranged in sequence. In this way, by applying a film on a surface of the corresponding lens, it is possible to reflect or refract the optical signals within different wave bands, so as to split the optical signals according to the wavelength.

(101) FIG. **12** is a diagram showing an optical path of a first lens group, in accordance with some embodiments.

(102) For example, as shown in FIGS. **10** and **12**, the first lens group **530** includes a first lens **531**, a second lens **532**, a third lens **533**, and a fourth lens **534**. The first lens **531**, the second lens **532**, the third lens **533**, and the fourth lens **534** are arranged in sequence in a width direction (e.g., the SK direction) of the first cavity body **520**. The optical signals, transmitted by the first fiber optic adapter **510** to the first cavity body **520** include optical signals of wavelengths  $\lambda_1$ ,  $\lambda_2$ ,  $\lambda_3$ ,  $\lambda_4$ ,  $\lambda_5$ ,  $\lambda_6$ ,  $\lambda_7$ , and  $\lambda_8$ .

(103) As shown in FIGS. **10** and **12**, a beam of optical signals including eight wavelengths is incident on a second surface **531B** of the first lens **531**. The second surface **531B** of the first lens **531** reflects the beam of optical signals, so as to change a transmission direction of the beam of optical signal.

(104) The beam of optical signals reflected by the first lens **531** is incident on a first surface **532A** of the second lens **532**, and the first surface **532A** of the second lens **532** refracts the beam of optical signals. The beam of optical signals after being refracted is incident into the second lens **532** and is incident on a second surface **532B** of the second lens **532** after passing through the second lens **532**. The second surface **532B** of the second lens **532** is coated with an angle selection film. The beam of optical signals incident on the second surface **532B** of the second lens **532** exits from the second lens **532** after being refracted by the second surface **532B** of the second lens **532**.

(105) The beam of optical signals exiting from the second lens **532** is incident on a first surface **533A** of the third lens **533**. The first surface **533A** of the third lens **533** is coated with an angle selection film. In this way, after the second lens **532** adjusts an incident angle of the beam of optical signals, optical signals within the first wave band incident on the first surface **533A** of the third lens **533** may be reflected, and optical signals within the second wave band incident on the first surface **533A** of the third lens **533** may be refracted. The optical signals within the first wave band in the beam of optical signals are reflected by the first surface **533A** of the third lens **533**, so as to form the first optical signal beam. The optical signals within the second wave band in the beam of optical signals are refracted by the first surface **533A** of the third lens **533**, so as to form the second optical signal beam.

(106) The first optical signal beam reflected by the first surface **533A** of the third lens **533** is incident on the second surface **532B** of the second lens **532**. Since an incident angle of the first optical signal beam again incident on the second surface **532B** of the second lens **532** has changed, the first optical signal beam may be reflected to a light input end of the first wavelength division demultiplexer **540** by the second surface **532B** of the second lens **532**.

(107) The second optical signal beam refracted by the first surface **533A** of the third lens **533** is incident into the third lens **533** and is incident on a second surface **533B** of the third lens **533** after passing through the third lens **533**. The second optical signal beam incident on the second surface **533B** of the third lens **533** exits from the third lens **533** after being refracted by the second surface **533B** of the third lens **533**.

(108) The second optical signal beam exiting from the third lens **533** is incident on a first surface

**534A** of the fourth lens **534** and is reflected to a light input end of the second wavelength division demultiplexer **550** by the first surface **534A** of the fourth lens **534**.

(109) It will be noted that the first surface and the second surface of the above lenses are only used to distinguish working surfaces on two sides of the corresponding lens. In FIG. **10**, a surface of each lens proximate to the lower side is the first surface, and a surface opposite the first surface and proximate to the upper side is the second surface. For the up and down direction here, reference may be made to the KS direction in FIG. **10**.

(110) As shown in FIG. **10**, the optical signals transmitted by the first fiber optic adapter **510** are incident into the first cavity body **520** in a length direction (e.g., the PQ direction) of the first cavity body **520**. Therefore, in order to reduce a length of the first cavity body **520**, a size of the space, occupied by the optical components to achieve splitting the optical signals for the first time, needs to be reduced in the length direction of the first cavity body **520**.

(111) In this case, the first lens **531** is configured to change a transmission direction of the optical signals incident into the first cavity body **520**, so as to convert the transmission direction of the optical signals from the length direction of the first cavity body **520** to the width direction of the first cavity body **520**. The second lens **532** is configured to transmit the optical signals within the first and second wave bands exiting from the first lens **531** and reflect the optical signals within the first wave band reflected by the third lens **533**. The third lens **533** is configured to reflect the optical signals within the first wave band and transmit the optical signals within the second wave band. The fourth lens **534** is configured to reflect the optical signals within the second wave band.

(112) In this way, by providing the first lens **531**, the second lens **532**, the third lens **533**, and the fourth lens **534**, the beam of optical signals including different wavelengths may be split for the first time according to the wavelength, and the two beams of optical signals after being split may be transmitted to the corresponding wavelength division demultiplexer **506** along the length direction of the first cavity body **520**.

(113) In some embodiments, as shown in FIG. **12**, an included angle  $\theta_{\text{sub.1}}$  between a normal line  $L_{\text{sub.1}}$  of the second surface **531B** of the first lens **531** and a transmission direction (e.g., the first direction A) of the optical signals transmitted by the first fiber optic adapter **510** to the first cavity body **520** is  $45^\circ$ . An included angle  $\theta_{\text{sub.2}}$  between the normal line  $L_{\text{sub.1}}$  of the second surface **531B** of the first lens **531** and a normal line  $L_{\text{sub.2}}$  of the first surface **532A** of the second lens **532** is  $90^\circ$ . That is to say, an included angle between the normal line  $L_{\text{sub.2}}$  of the first surface **532A** of the second lens **532** and the first direction A is  $135^\circ$ . An included angle  $\theta_{\text{sub.3}}$  between the normal line  $L_{\text{sub.1}}$  of the second surface **531B** of the first lens **531** and a normal line  $L_{\text{sub.3}}$  of the first surface **533A** of the third lens **533** is  $37^\circ$ . That is to say, an included angle between the normal line  $L_{\text{sub.3}}$  of the first surface **533A** of the third lens **533** and the first direction A is  $82^\circ$  (e.g., a sum of the included angle  $\theta_{\text{sub.1}}$  and the included angle  $\theta_{\text{sub.3}}$ ). An included angle between the normal line  $L_{\text{sub.1}}$  of the second surface **531B** of the first lens **531** and a normal line  $L_{\text{sub.4}}$  of the first surface **534A** of the fourth lens **534** is  $180^\circ$ . That is to say, the second surface **531B** of the first lens **531** is parallel to the first surface **534A** of the fourth lens **534**, and an included angle  $\theta_{\text{sub.4}}$  between the normal line  $L_{\text{sub.4}}$  of the first surface **534A** of the fourth lens **534** and the first direction A is  $45^\circ$ . Moreover, by applying a film on the second surface **532B** of the second lens **532** and applying a film on the first surface **533A** of the third lens **533**, it is possible to split the optical signals within the first wave band and the optical signals within the second wave band from the beam of optical signals.

(114) FIG. **13** is a diagram showing an optical path of another first lens group, in accordance with some embodiments.

(115) Of course, the first lens group **530** is not limited to the combination of the above multiple lenses. In some embodiments, as shown in FIG. **13**, the first lens group **530** includes a first lens **531**, an optical filter **537**, a fourth lens **534**, and a fifth lens **535**. The first lens **531**, the fifth lens **535**, the optical filter **537**, and the fourth lens **534** are arranged in the width direction of the first

cavity body **520**.

(116) The first lens **531** is configured to reflect the optical signals transmitted by the first fiber optic adapter **510** to the first cavity body **520**, so as to change a propagation direction of the optical signals. The optical filter **537** is configured to receive the optical signals reflected by the first lens **531**, reflect the first optical signal beam in the optical signals, and transmit the second optical signal beam in the optical signals. The fifth lens **535** is configured to reflect the first optical signal beam to the first wavelength division demultiplexer **540**. The fourth lens **534** is configured to reflect the second optical signal beam to the second wavelength division demultiplexer **550**.

(117) A beam of optical signals including eight wavelengths is incident on a second surface **531B** of the first lens **531**. The second surface **531B** of the first lens **531** reflects the beam of optical signals, so as to change a transmission direction of the beam of optical signals.

(118) The beam of optical signals reflected by the first lens **531** is incident on the optical filter **537**. A portion (e.g., the first optical signal beam) of the beam of optical signals incident on the optical filter **537** is reflected by the optical filter **537**, and another portion (e.g., the second optical signal beam) of the beam of optical signals incident on the optical filter **537** is transmitted through the optical filter **537**.

(119) The first optical signal beam reflected by the optical filter **537** is incident on the fifth lens **535**. The fifth lens **535** reflects the first optical signal beam to the light input end of the first wavelength division demultiplexer **540**.

(120) The second optical signal beam transmitted through the optical filter **537** is incident on a first surface **534A** of the fourth lens **534**. The first surface **534A** of the fourth lens **534** reflects the second optical signal beam to the light input end of the second wavelength division demultiplexer **550**.

(121) In this way, by providing the first lens **531**, the optical filter **537**, the fourth lens **534** and the fifth lens **535**, the beam of optical signals including different wavelengths may be split for the first time according to the wavelength, and the two beams of optical signals after being split may be transmitted to the corresponding wavelength division demultiplexer **506** along the length direction of the first cavity body **520**.

(122) Of course, in some embodiments, the first lens group **530** may also include other numbers of lenses. For example, the first lens group **530** may include three lenses. Two of the three lenses are the first lens **531** and the fourth lens **534** in FIG. 10. The other of the three lenses is a sixth lens, and the sixth lens is disposed between the first lens **531** and the fourth lens **534**. A first surface of the sixth lens is configured to reflect the optical signals within the first wave band and transmit the optical signals within the second wave band, and a second surface of the sixth lens is configured to transmit the optical signals within the second wave band. In this way, the beam of optical signals may also be split by the first lens **531**, the sixth lens, and the fourth lens **534** according to the wavelength.

(123) In some embodiments, as shown in FIGS. 7 and 11, the light receiving assembly **500** further includes a flat lens **523**. The flat lens **523** is disposed in the first via hole **522** and is disposed obliquely with respect to the transmission direction of the optical signals transmitted by the first fiber optic adapter **510**. The optical signals transmitted by the first fiber optic adapter **510** to the first via hole **522** are incident on the second surface **531B** of the first lens **531** after passing through the flat lens **523**.

(124) When the optical signals are incident on the second surface **531B** of the first lens **531**, a part of the optical signals may be transmitted through the second surface **531B** of the first lens **531** and be incident on a first surface **531A** of the first lens **531**, and then be incident into the first via hole **522** again after being reflected by the first surface **531A** of the first lens **531** and refracted by the second surface **531B** of the first lens **531** in turn. The flat lens **523** disposed obliquely may prevent the optical signals incident into the first via hole **522** again from affecting the optical signals transmitted by the first fiber optic adapter **510** to the first via hole **522**.

(125) Moreover, in order to avoid excessive displacement of the optical signals passing through the flat lens **523**, it is necessary to arrange an oblique angle of the flat lens **523** reasonably. In some embodiments, an included angle **85** between an optical axis (referring to the dashed line L.sub.5 in FIG. **11**) of the flat lens **523** and a central axis (referring to the dashed line L.sub.6 in FIG. **11**) of the first via hole **522** satisfies a preset threshold. The preset threshold is any value within a range of 4° to 6° inclusive. For example, the preset threshold is 4°, 5°, or 6°. In this way, it may not only prevent the optical signals reflected by the first lens **531** and incident into the first via hole **522** again from affecting the transmission of the optical signals, but also prevent the optical signals transmitted by the first fiber optic adapter **510** to the first via hole **522** from shifting too much after passing through the flat lens **523**. In addition, the flat lens **523** may also close the first via hole **522**, so as to facilitate the sealing of the first cavity body **520**.

(126) In the optical module **200** provided by some embodiments of the present disclosure, the light receiving assembly **500** is connected to the external optical fiber through the first fiber optic adapter **510**, and optical signals transmitted by the external optical fiber are transmitted into the first cavity body **520** through first fiber optic adapter **510**. The first cavity body **520** receives the optical signals transmitted by the first fiber optic adapter **510** and splits the optical signals for the first time according to the wavelength and the optical signals for the second time according to the wavelength through the first lens group **530** and the plurality of wavelength division demultiplexers **506** in turn. The optical signals after being split twice are transmitted to the light receiving component **505** and converted into electrical signals (e.g., current signals or voltage signals) by the light receiving component **505**. Thus, the optical module **200** may receive the optical signals including multiple wavelengths transmitted by the external optical fiber and may simultaneously transmit optical signals of multiple wavelengths in a single optical fiber.

(127) It is generally required that, the second fiber optic adapter **410** and the first fiber optic adapter **510** are located at a same height, while the light emitting assembly **400** and the light receiving assembly **500** in some embodiments of the present disclosure are stacked up and down. Therefore, it is necessary to adjust an optical path height of the optical signals transmitted by the first fiber optic adapter **510** or an optical path height of the optical signals output by the light emitting assembly **400** to the second fiber optic adapter **410**.

(128) In some embodiments, as shown in FIG. **7**, the light receiving assembly **500** further includes a displacement component **524**. An end of the displacement component **524** is connected with the first fiber optic adapter **510**, and the other end of the displacement component **524** is connected with the first cavity body **520**. The displacement component **524** is configured to adjust the optical path height of the optical signals transmitted by the first fiber optic adapter **510** in the height direction of the optical module **200**.

(129) For example, in the height direction of the optical module **200**, the optical path height of the optical signals transmitted by the first fiber optic adapter **510** is higher than an optical path height of the optical signals transmitted in the first cavity body **520**. In this way, it is possible to reduce the optical path height of the optical signals transmitted by the first fiber optic adapter **510** through the displacement component **524**, so that the optical signals may be transmitted from the first fiber optic adapter **510** with a relatively high position to the first cavity body **520** with a relatively low position.

(130) FIG. **14** is an exploded view showing a portion of a light receiving assembly, in accordance with some embodiments. FIG. **15** is a sectional view of a first fiber optic adapter and a light receiving assembly, in accordance with some embodiments.

(131) In some embodiments, as shown in FIGS. **14** and **15**, the displacement component **524** includes a displacement prism **524A**, a prism cavity body **524B**, and a second cover plate **524C**.

(132) The prism cavity body **524B** includes a prism accommodating cavity **524D**, and the displacement prism **524A** is disposed in the prism accommodating cavity **524D**. The displacement prism **524A** is configured to adjust the optical path height of the optical signals transmitted by the

first fiber optic adapter **510** in the height direction of the optical module **200**. For example, the displacement prism **524A** adjusts the optical signals transmitted at a height to another height through two or more reflections.

(133) For example, as shown in FIG. **15**, the displacement prism **524A** includes a third reflecting surface **5241** and a fourth reflecting surface **5242**. The third reflecting surface **5241** and the fourth reflecting surface **5242** are parallel to each other, and an included angle between each of the two reflecting surfaces and the optical axis of the optical signals transmitted by the first fiber optic adapter **510** is  $45^\circ$ . The optical signals are reflected twice through the two reflecting surfaces, so that the optical signals transmitted at a relatively high height are adjusted to be transmitted at a relatively low height.

(134) The prism cavity body **524B** is connected with the first fiber optic adapter **510** and the first cavity body **520**. The first fiber optic adapter **510** communicates with the prism cavity body **524B** through prism accommodating cavity **524D**, and the prism accommodating cavity **524D** communicates with the first via hole **522**. A side of the prism cavity body **524B** proximate to the first cavity body **520** is open, so as to form a second opening **5240**. The second cover plate **524C** is configured to close the second opening **5240**. For example, the second cover plate **524C** covers a side of the prism accommodating cavity **524D** proximate to the first cavity body **520**, so as to limit the displacement prism **524A** inside the prism accommodating cavity **524D**, and the second cover plate **524C** may be fixedly connected with the prism cavity body **524B** through glue. In this way, it is possible to improve an installation accuracy of the displacement prism **524A**.

(135) The second cover plate **524C** closes a portion of the second opening **5240**. An exposed portion of the second opening **5240** forms a second via hole **524F**, and the second via hole **524F** communicates with the first via hole **522**.

(136) In some embodiments, as shown in FIG. **15**, the displacement component **524** further includes a support step **524I** and a cover plate groove **524J**. The support step **524I** is disposed in the prism accommodating cavity **524D**, so as to support and limit the displacement prism **524A**. The cover plate groove **524J** is disposed on a side of the prism accommodating cavity **524D** proximate to the first cavity body **520**, so as to fix the second cover plate **524C**.

(137) In some embodiments, as shown in FIG. **15**, the displacement component **524** further includes a connecting hole **524E**, and the connecting hole **524E** is disposed on a side of the prism cavity body **524B** proximate to the first fiber optic adapter **510**, and the connecting hole **524E** communicates with the prism accommodating cavity **524D**. For example, the connecting hole **524E** includes a counterbore **5243** and a connecting sub-hole **5244** communicated with each other, the counterbore **5243** is closer to the first fiber optic adapter **510** than the connecting sub-hole **5244**, and the connecting sub-hole **5244** communicates with the prism accommodating cavity **524D**.

(138) In this case, the first fiber optic adapter **510** includes an adapter body **513** and a connector **511**. The connector **511** is disposed at an end of the adapter body **513** proximate to the displacement component **524**, and the connector **511** is matched with the connecting hole **524E**. For example, the connector **511** is inserted into the counterbore **5243**.

(139) In addition, the first fiber optic adapter **510** further includes a collimating lens **512**, and the collimating lens **512** is disposed on a side of the connector **511** proximate to the displacement component **524** and is located in the connecting sub-hole **5244**. The collimating lens **512** is configured to collimate the optical signals transmitted by the first fiber optic adapter **510**.

(140) FIG. **16** is a sectional view of a first fiber optic adapter and a displacement component, in accordance with some embodiments.

(141) In some embodiments, as shown in FIG. **16**, the displacement component **524** further includes a first connecting groove **524H** and a first protrusion **524G**. The first connecting groove **524H** is disposed on a bottom wall of the counterbore **5243** and is proximate to an inner wall of the counterbore **5243**. The first connecting groove **524H** is recessed in a direction away from the first fiber optic adapter **510**, so as to form the first protrusion **524G** on the bottom wall of the

counterbore **5243**. The first protrusion **524G** abuts against an end of the connector **511** proximate to the displacement component **524**, so as to support the end of the connector **511**.

(142) In this way, by providing the first connecting groove **524H**, it is convenient to process the first protrusion **524G**. For example, the first connecting groove **524H** is convenient for a tool retraction of a turning tool when the first protrusion **524G** is processed through a turning process. Moreover, when the first fiber optic adapter **510** is connected with the prism cavity body **524B** through glue dispensing, excess glue may also flow into the first connecting groove **524H**, so as to avoid glue overflow affecting the collimating effect of the collimating lens **512**.

(143) It is assumed that a direction of the optical axis of the optical signals transmitted from the outside of the optical module **200** to the first fiber optic adapter **510** is parallel to the horizontal plane, and the optical signals are transmitted along a central axis of the first fiber optic adapter **510**. A transmission path of the optical signals is shown in FIG. **15**. As shown in FIG. **15**, the optical signals whose optical axis is horizontal are incident on the collimating lens **512** of the first fiber optic adapter **510**, and then are incident on the third reflecting surface **5241** of the displacement prism **524A** after being collimated by the collimating lens **512**. The optical signals incident on the third reflecting surface **5241** are reflected for a first time by the third reflecting surface **5241**, and the optical axis of the optical signals is converted from a horizontal direction to a vertical direction. The optical signals whose optical axis is vertical are incident on the fourth reflecting surface **5242** of the displacement prism **524A** and are reflected for a second time by the fourth reflecting surface **5242**. The optical axis of the optical signals is converted from the vertical direction to the horizontal direction. The optical signals reflected by the fourth reflecting surface **5242** are transmitted through the flat lens **523** through the second via hole **524F** and then are incident into the first cavity body **520** through the first via hole **522**.

(144) In some embodiments of the present disclosure, it is possible to adjust a height of the optical axis of the optical signals through the displacement prism **524A** in a case where the direction of the optical axis of the optical signals is parallel to the horizontal plane, so that the light emitting assembly **400** and the light receiving assembly **500** are arranged in a stack.

(145) In order to facilitate connection between the displacement component **524** and the first cavity body **520**, in some embodiments, as shown in FIG. **14**, the first cavity body **520** further includes a connecting portion **525**. The connecting portion **525** is disposed on a side of the side wall **5202** (e.g., a side sub-wall **5202A** in FIG. **7**) proximate to the displacement component **524**, and the connecting portion **525** is configured to be clamped with the displacement component **524**.

(146) For example, as shown in FIG. **14**, the connecting portion **525** includes a first connecting plate **525A** and a second connecting plate **525B**. The first connecting plate **525A** and the second connecting plate **525B** are opposite to each other and are located on two sides of the displacement component **524** respectively. The first connecting plate **525A** and the second connecting plate **525B** are approximately perpendicular to the side sub-wall **5202A**. Sides of the first connecting plate **525A** and the second connecting plate **525B** proximate to the displacement component **524** each are connected with an outer surface of the prism cavity body **524B**, so as to make the prism cavity body **524B** be clamped between the first connecting plate **525A** and the second connecting plate **525B**. Here, the first connecting plate **525A** and the second connecting plate **525B** may be two protrusions, and portions of the side wall **5202** protrudes outward to form the two protrusions, so that the first cavity body **520** is a one-piece member.

(147) In some embodiments, the connecting portion **525** further includes a support structure, and the support structure may be disposed on a side of the first connecting plate **525A** or the second connecting plate **525B**, so as to increase a connecting area between the first connecting plate **525A** and the side wall **5202** or the second connecting plate **525B** and the side wall **5202**, thereby improving the structural strength of the first connecting plate **525A** or the second connecting plate **525B**.

(148) FIG. **17** is a diagram showing a structure of a first cavity body, in accordance with some

embodiments. For example, as shown in FIG. 17, the connecting portion 525 further includes a support structure 525C, and the support structure 525C is disposed on a side of the second connecting plate 525B away from the first connecting plate 525A. The support structure 525C is connected with the second connecting plate 525B and the side wall 5202, so as to increase the structural strength of the second connecting plate 525B, thereby improving the reliability of connection between the prism cavity body 524B and the first cavity body 520.

(149) In some embodiments of the present disclosure, the displacement component 524 is provided between the first fiber optic adapter 510 and the first cavity body 520. The optical signals transmitted by the first fiber optic adapter 510 are incident into the first cavity body 520 through the displacement component 524. The displacement component 524 may adjust the optical path height of the optical signals transmitted by the first fiber optic adapter 510, so as to adjust the optical path height of the optical signals transmitted by the first fiber optic adapter 510 to the first cavity body 520. In this way, by adjusting the optical path height between the first fiber optic adapter 510 and the first cavity body 520, the light emitting assembly 400 and the light receiving assembly 500 may be stacked up and down in a case where the second fiber optic adapter 410 and the first fiber optic adapter 510 are located at a same height, so as to meet requirements of the light emitting assembly 400 and the light receiving assembly 500 for a large volume. Of course, in some embodiments, the displacement component 524 may also be disposed on the light emitting assembly 400, so as to adjust an optical path height between the light emitting assembly 400 and the second fiber optic adapter 410.

(150) FIG. 18 is a diagram showing a structure of a first cavity body from another perspective, in accordance with some embodiments.

(151) In some embodiments, as shown in FIGS. 17 and 18, the first cavity body 520 further includes a first mounting post 527. The first mounting post 527 is disposed on the base 5201, and the first mounting post 527 is in a shape of a right prism (e.g., a triangular prism).

(152) The first mounting post 527 includes a first mounting surface 527A and a second mounting surface 527B, and there is a preset included angle between the first mounting surface 527A and the second mounting surface 527B, so as to match a relative mounting angle between the first lens 531 and the second lens 532. The first lens 531 is connected with (e.g., abuts against) the first mounting surface 527A, so as to limit and support the first lens 531 through the first mounting surface 527A. The second lens 532 is connected with (e.g., abuts against) the second mounting surface 527B, so as to limit and support the second lens 532 through the second mounting surface 527B.

(153) In some embodiments of the present disclosure, by providing the first mounting post 527 including the first mounting surface 527A and the second mounting surface 527B, it is convenient to achieve the coupling of the first lens 531 and the second lens 532 in a passive manner, thereby improving the installation efficiency and accuracy of the first lens 531 and the second lens 532.

(154) In some embodiments, the first cavity body 520 further includes a first groove 527C. The first groove 527C is disposed on the base 5201 and is recessed towards a bottom of the base 5201. The first groove 527C is disposed adjacent to the first mounting surface 527A and the second mounting surface 527B of the first mounting post 527, and a projection of the first groove 527C on the base 5201 is located outside a projection of the first mounting post 527 on the base 5201. In this way, it is convenient to process the first mounting surface 527A and the second mounting surface 527B by providing the first groove 527C.

(155) For example, by providing the first groove 527C, it is convenient to achieve a tool retraction of a turning tool when the first mounting post 527 is processed through a turning process. Moreover, by providing the first groove 527C, it is possible to avoid an arc chamfer at the connecting position between the first mounting surface 527A and the base 5201, and an arc chamfer at the connecting position between the second mounting surface 527B and the base 5201, so that the first lens 531 and the second lens 532 may be closely contacted with the first mounting surface 527A and the second mounting surface 527B respectively, so as to improve the installation

accuracy of the first lens **531** and the second lens **532**. In addition, when the first lens **531** and the second lens **532** are connected with the base **5201** through glue dispensing, excess glue may flow into the first groove **527C**, so as to prevent the glue from affecting the installation accuracy of the first lens **531** and the second lens **532**.

(156) In some embodiments, as shown in FIGS. **17** and **18**, the first cavity body **520** further includes a second mounting post **502**. The second mounting post **502** is disposed on the base **5201**, and the second mounting post **502** is in a shape of a right prism (e.g., a quadrangular prism). The second mounting post **502** includes a third mounting surface **502A** and a fourth mounting surface **502B** disposed opposite to each other. The first wavelength division demultiplexer **540** is connected with (e.g., abuts against) the third mounting surface **502A**, so as to limit and fix the first wavelength division demultiplexer **540** through the third mounting surface **502A**. The second wavelength division demultiplexer **550** is connected with (e.g., abuts against) the fourth mounting surface **502B**, so as to limit and fix the second wavelength division demultiplexer **550** through the fourth mounting surface **502B**.

(157) In some embodiments, the third mounting surface **502A** is parallel to the fourth mounting surface **502B**.

(158) In some embodiments of the present disclosure, by providing the second mounting post **502** including the third mounting surface **502A** and the fourth mounting surface **502B**, it is convenient to achieve the coupling of the first wavelength division demultiplexer **540** and the second wavelength division demultiplexer **550** in a passive manner, so that it is convenient to improve the installation efficiency and accuracy of the first wavelength division demultiplexer **540** and the second wavelength division demultiplexer **550**.

(159) In some embodiments, as shown in FIG. **18**, the first cavity body **520** further includes a second groove **502C** and a third groove **502D**. The second groove **502C** and the third groove **502D** each are disposed on the base **5201**, and the second groove **502C** and the third groove **502D** each are recessed towards the bottom of the base **5201**. The second groove **502C** is located on a side of the second mounting post **502** proximate to the first wavelength division demultiplexer **540**, and the second groove **502C** is disposed adjacent to the third mounting surface **502A**. The third groove **502D** is located on a side of the second mounting post **502** proximate to the second wavelength division demultiplexer **550**, and the third groove **502D** is disposed adjacent to the fourth mounting surface **502B**.

(160) In this way, by providing the second groove **502C** and the third groove **502D**, it is convenient to process the third mounting surface **502A** and the fourth mounting surface **502B**.

(161) For example, by providing the second groove **502C** and the third groove **502D**, it is convenient to achieve a tool retraction of a turning tool when the third mounting surface **502A** and the fourth mounting surface **502B** are processed by a turning process. Moreover, by providing the second groove **502C** and the third groove **502D**, it is possible to avoid an arc chamfer at a connecting position between the third mounting surface **502A** and the base **5201** and an arc chamfer at a connecting position between the fourth mounting surface **502B** and the base **5201**, so that the first wavelength division demultiplexer **540** and the second wavelength division demultiplexer **550** may be closely contacted with the third mounting surface **502A** and the fourth mounting surface **502B**, respectively, so as to improve the installation accuracy of the first wavelength division demultiplexer **540** and the second wavelength division demultiplexer **550**. In addition, when the first wavelength division demultiplexer **540** and the second wavelength division demultiplexer **550** are connected with the second mounting post **502** through glue dispensing, excess glue may flow into the second groove **502C** and the third groove **502D**, so as to prevent the glue from affecting the installation accuracy of the first wavelength division demultiplexer **540** and the second wavelength division demultiplexer **550**.

(162) In some embodiments, as shown in FIG. **17**, the first cavity body **520** further includes a fourth groove **528** and a fifth groove **529**. The fourth groove **528** and the fifth groove **529** are



disposed on the base **5201** and are recessed towards the bottom of the base **5201**. The fourth groove **528** and the fifth groove **529** each are used to accommodate the glue used in glue dispensing. The first wavelength division demultiplexer **540** is disposed on a top portion of the fourth groove **528**, and the second wavelength division demultiplexer **550** is disposed on a top portion of the fifth groove **529**.

(163) For example, when the first wavelength division demultiplexer **540** and the second wavelength division demultiplexer **550** are being fixed, the glue is dropped into the fourth groove **528** and the fifth groove **529**, and then the first wavelength division demultiplexer **540** and the second wavelength division demultiplexer **550** are placed at the top portions of the fourth groove **528** and the fifth groove **529** respectively. In this way, the first wavelength division demultiplexer **540** and the second wavelength division demultiplexer **550** may be fixed on the base **5201** after the glue is solidified.

(164) In some embodiments, as shown in FIG. **18**, the fourth groove **528** includes a first glue accommodating groove **528A**, a first overflow glue accommodating groove **528B**, and a first blocking wall **528C**. The first blocking wall **528C** is disposed between the first glue accommodating groove **528A** and the first overflow glue accommodating groove **528B**, so that the first glue accommodating groove **528A** and the first overflow glue accommodating groove **528B** are spaced apart. For example, the first glue accommodating groove **528A** is in a shape of a circle, and the first overflow glue accommodating groove **528B** is in a shape of a circular ring and is disposed around the first glue accommodating groove **528A**. However, the present disclosure is not limited thereto.

(165) During a process of fixing the first wavelength division demultiplexer **540**, the glue is dropped into the first glue accommodating groove **528A**, and the glue overflows from the first glue accommodating groove **528A**, so as to avoid affecting the installation firmness of the first wavelength division demultiplexer **540** due to insufficient glue. Then, the first wavelength division demultiplexer **540** covers the first glue accommodating groove **528A**, and the excess glue in the first glue accommodating groove **528A** overflows into the first overflow glue accommodating groove **528B**, so as to prevent the glue from overflowing the fourth groove **528** to affect the installation accuracy of the first wavelength division demultiplexer **540**.

(166) Similarly, in some embodiments, as shown in FIG. **18**, the fifth groove **529** includes a second glue accommodating groove **529A**, a second overflow glue accommodating groove **529B**, and a second blocking wall **529C**. The second blocking wall **529C** is disposed between the second glue accommodating groove **529A** and the second overflow glue accommodating groove **529B**, so that the second glue accommodating groove **529A** and the second overflow glue accommodating groove **529B** are spaced apart. For example, the second glue accommodating groove **529A** is in a shape of a circle, the second overflow glue accommodating groove **529B** is in a shape of a circular ring, and the second overflow glue accommodating groove **529B** is disposed around the second glue accommodating groove **529A**. However, the present disclosure is not limited thereto.

(167) A function of the fifth groove **529** is similar to that of the fourth groove **528**, and details will not be repeated herein.

(168) In some embodiments, as shown in FIGS. **10** and **17**, the first cavity body **520** further includes a third mounting post **503A**, a fourth mounting post **503B**, and a fifth mounting post **503C**. The third mounting post **503A**, the fourth mounting post **503B**, and the fifth mounting post **503C** are disposed on the base **5201**, and the third mounting post **503A**, the fourth mounting post **503B**, and the fifth mounting post **503C** are arranged at intervals in the width direction of the first cavity body **520**. The first reflecting prism **561** is disposed between the third mounting post **503A** and the fourth mounting post **503B**, and the second reflecting prism **571** is disposed between the fourth mounting post **503B** and the fifth mounting post **503C**.

(169) In this way, the first reflecting prism **561** may be fixed and limited by the third mounting post **503A** and the fourth mounting post **503B**, and the second reflecting prism **571** may be fixed and

limited by the fourth mounting post **503B** and the fifth mounting post **503C**. In addition, a portion of a surface of the base **5201** between the third mounting post **503A** and the fourth mounting post **503B** forms a fifth mounting surface **503D**, so as to support the first reflecting prism **561**; and a portion of a surface of the base **5201** between the fourth mounting post **503B** and the fifth mounting post **503C** forms a sixth mounting surface **503E**, so as to support the second reflecting prism **571**.

(170) In some embodiments, as shown in FIG. **17**, the base **5201** of the first cavity body **520** includes a first support surface **501A** and a second support surface **501B**. The first support surface **501A** is a first portion of a surface (e.g., the top surface) of the base **5201** proximate to the first cover plate **504**, and the second support surface **501B** is a second portion of the top surface of the base **5201** proximate to the first cover plate **504**. The first support surface **501A** is farther away from the circuit board **300** than the second support surface **501B**, and the first support surface **501A** is higher than the second support surface **501B**, so as to form a step **501C** between the first support surface **501A** and the second support surface **501B**. The first mounting post **527**, the second mounting post **502**, the third mounting post **503A**, the fourth mounting post **503B**, the fifth mounting post **503C**, the first reflecting prism **561**, and the second reflecting prism **571** each are disposed on the first support surface **501A**. The second support surface **501B** is configured to support the flexible circuit board **310** or the electrical connecting member extending into the first cavity body **520**.

(171) Therefore, by providing the step **501C**, it is possible to divide the top surface of base **5201** according to the height. In this way, the first support surface **501A** may raise heights of the fifth mounting surface **503D** and the sixth mounting surface **503E**, so as to raise heights of the first reflecting prism **561** and the second reflecting prism **571**, which facilitates the installation of the first reflecting prism **561** and the first light receiving component **580** and the installation of the second reflecting prism **571** and the second light receiving component **590**. In addition, the step **501C** may also limit the flexible circuit board **310** extending into the first cavity body **520**.

(172) FIG. **19** is a diagram showing a structure of a light receiving assembly without a first cover plate and a displacement component, in accordance with some embodiments. FIG. **19** shows the first mounting post **527**, the second mounting post **502**, the fourth groove **528**, and the fifth groove **529** in use.

(173) As shown in FIGS. **18** and **19**, a side of the first lens **531** is attached to the first mounting surface **527A** of the first mounting post **527**, and a side of the second lens **532** is attached to the second mounting surface **527B** of the first mounting post **527**. A side of the first wavelength division demultiplexer **540** is attached to the third mounting surface **502A** of the second mounting post **502**, and the first wavelength division demultiplexer **540** covers the fourth groove **528**. A side of the second wavelength division demultiplexer **550** is attached to the fourth mounting surface **502B** of the second mounting post **502**, and the second wavelength division demultiplexer **550** covers the fifth groove **529**. The first reflecting prism **561** is disposed between the third mounting post **503A** and the fourth mounting post **503B**, and the second reflecting prism **571** is disposed between the fourth mounting post **503B** and the fifth mounting post **503C**.

(174) FIG. **20** is a sectional view of the light receiving assembly in FIG. **19**.

(175) For example, as shown in FIG. **20**, in a case where the side of the second lens **532** is attached to the second mounting surface **527B** of the first mounting post **527**, the second lens **532** covers a portion of the first groove **527C**. In a case where the first wavelength division demultiplexer **540** is mounted on the base **5201**, the first wavelength division demultiplexer **540** covers the first glue accommodating groove **528A** and the first overflow glue accommodating groove **528B**. The first support surface **501A** raises a height in which the first wavelength division demultiplexer **540** is located, so that there is a certain height difference between a surface (e.g., the bottom surface) of the first wavelength division demultiplexer **540** proximate to the base **5201** and the second support surface **501B**, so as to facilitate installing the first light receiving component **580** on the first

support surface **501A**. An end of the flexible circuit board **310** away from the circuit board **300** abuts against the step **501C**. In addition, a portion of the flexible circuit board **310** extending into the first cavity body **520** may be fixed on the second support surface **501B** through thermal conductive adhesive.

(176) In some embodiments, as shown in FIG. **20**, the first cavity body **520** further includes a second connecting groove **526A**. The second connecting groove **526A** is disposed at an end (e.g., the top end) of the side wall **5202** away from the base **5201** and is recessed towards the base **5201**. The glue may be filled in the second connecting groove **526A**, so that the first cover plate **504** may be fixedly connected with the first cavity body **520**.

(177) In some embodiments, the second connecting groove **526A** is in a shape of a closed ring, so as to increase an area of a region between the first cover plate **504** and the side wall **5202** for bonding, thereby improving the reliability of encapsulation of the first cover plate **504** and the first cavity body **520**.

(178) In some embodiments, as shown in FIG. **20**, the first cavity body **520** further includes a repair opening **526B**. The repair opening **526B** is disposed at the top end of the side wall **5202** and is located at an edge of the top end of the side wall **5202**. The repair opening **526B** communicates with the second connecting groove **526A**. In a case where the components inside the first cavity body **520** need to be repaired after the first cover plate **504** and the first cavity body **520** are encapsulated, the first cover plate **504** may be disassembled from the first cavity body **520** through the repair opening **526B**. In this way, the first cover plate **504** may be removed without damaging the first cover plate **504** or the first cavity body **520**, so as to reduce the difficulty and cost of maintenance of the optical module **200**.

(179) FIG. **21** is a sectional view of a first cavity body and a first cover plate, in accordance with some embodiments.

(180) In some embodiments, as shown in FIG. **21**, the first cover plate **504** includes a cover plate body **5041** and a second protrusion **5042**. The second protrusion **5042** is disposed on an edge of the cover plate body **5041** and protrudes towards a direction proximate to the base **5201**. The second protrusion **5042** matches the second connecting groove **526A**. In this way, in a case where the first cavity body **520** is fixedly connected with the first cover plate **504** through the glue, the second connecting groove **526A** matches with the second protrusion **5042**, so as to increase the bonding area between the glue and the first cover plate **504**, so as to improve the reliability of sealing the first cover plate **504** and the first cavity body **520**.

(181) In some embodiments, as shown in FIG. **21**, the first cavity body **520** further includes a third via hole **526C** and a sealing plug **526D**. The third via hole **526C** is disposed in the side wall **5202** of the first cavity body **520** proximate to the first fiber optic adapter **510**, and the third via hole **526C** communicates with the cavity **5203**. The sealing plug **526D** is configured to close the third via hole **526C**. Since the first cavity body **520** needs to be heated and baked during the manufacturing process of the light receiving assembly **500**. It is possible to facilitate the air circulation in the cavity **5203** of the first cavity body **520** through the third via hole **526C**. After the first cavity body **520** is heated and baked, by using the sealing plug **526D** to seal the third via hole **526C**, it is possible to prevent the air outside the first cavity body **520** from entering the cavity **5203** of the first cavity body **520** through the third via hole **526C**.

(182) A person skilled in the art will understand that the scope of disclosure in the present disclosure is not limited to specific embodiments discussed above, and may modify and substitute some elements of the embodiments without departing from the spirits of this application. The scope of the application is limited by the appended claims.

## Claims

1. An optical module, comprising: a shell; a circuit board disposed in the shell; a light receiving assembly disposed in the shell and electrically connected with the circuit board, the light receiving assembly being configured to convert received optical signals into electrical signals; and a first fiber optic adapter connected with the light receiving assembly, the first fiber optic adapter being configured to transmit optical signals from an outside of the optical module to the light receiving assembly; wherein the light receiving assembly includes: a first cavity body connected with the first fiber optic adapter; a first lens group disposed in the first cavity body, the first lens group being configured to split the optical signals transmitted by the first fiber optic adapter to the first cavity body for a first time according to a wavelength, so as to obtain a first optical signal beam and a second optical signal beam; a plurality of wavelength division demultiplexers disposed in the first cavity body, the plurality of wavelength division demultiplexers including: a first wavelength division demultiplexer configured to receive the first optical signal beam and split the first optical signal beam for a second time according to a wavelength; and a second wavelength division demultiplexer configured to receive the second optical signal beam and split the second optical signal beam for a second time according to a wavelength; and at least one light receiving component disposed in the first cavity body, the light receiving component including a plurality of light receiving chips, and the plurality of light receiving chips being configured to receive the optical signals split for the second time by the plurality of wavelength division demultiplexers and convert the optical signals into the electrical signals; wherein the first cavity body includes: a base, the base including: a first support surface, the first lens group and the plurality of wavelength division demultiplexers being disposed on the first support surface; and a second support surface, the light receiving component being disposed on the second support surface, the first support surface being farther from the circuit board than the second support surface, and the first support surface being higher than the second support surface, so as to provide a step between the first support surface and the second support surface; a side wall disposed around the base; a cavity defined by the base and the side wall; and a first via hole disposed on the side wall and communicating with the cavity, the first fiber optic adapter being connected with the first cavity body through the first via hole.

2. The optical module according to claim 1, wherein the first lens group includes: a first lens configured to reflect the optical signals transmitted by the first fiber optic adapter to the first cavity body, so as to change a propagation direction of the optical signals; a second lens configured to receive and transmit the optical signals reflected by the first lens, and reflect the first optical signal beam from a third lens to the first wavelength division demultiplexer; the third lens configured to receive the optical signals transmitted by the second lens, reflect the first optical signal beam, and transmit the second optical signal beam, so as to split the optical signals for the first time; and a fourth lens configured to reflect the second optical signal beam to the second wavelength division demultiplexer; wherein the first lens, the second lens, the third lens, and the fourth lens are sequentially arranged in a width direction of the first cavity body.

3. The optical module according to claim 2, wherein the first cavity body further includes: a first mounting post disposed on the base, the first mounting post including a first mounting surface and a second mounting surface, and a preset included angle being provided between the first mounting surface and the second mounting surface, the first lens being connected with the first mounting surface, and the second lens being connected with the second mounting surface; and a second mounting post disposed on the base, the second mounting post including a third mounting surface and a fourth mounting surface disposed opposite to each other, the first wavelength division demultiplexer being connected with the third mounting surface, and the second wavelength division demultiplexer being connected with the fourth mounting surface.

4. The optical module according to claim 3, wherein the first cavity body further includes: a first groove disposed on the base and recessed towards a bottom of the base, the first groove being

located outside the first mounting post and disposed adjacent to the first mounting surface and the second mounting surface; a second groove disposed on the base and recessed towards the bottom of the base, the second groove being located on a side of the second mounting post proximate to the first wavelength division demultiplexer, and disposed adjacent to the third mounting surface; and a third groove disposed on the base and recessed towards the bottom of the base, the third groove being located on a side of the second mounting post proximate to the second wavelength division demultiplexer, and disposed adjacent to the fourth mounting surface.

5. The optical module according to claim 1, wherein the first cavity body further includes: a fourth groove disposed on the base and recessed towards a bottom of the base, the first wavelength division demultiplexer being disposed above the fourth groove, and the fourth groove including: a first glue accommodating groove; a first overflow glue accommodating groove disposed around the first glue accommodating groove; and a first blocking wall disposed between the first glue accommodating groove and the first overflow glue accommodating groove, so that the first glue accommodating groove and the first overflow glue accommodating groove are spaced apart; and a fifth groove disposed on the base and recessed towards the bottom of the base, the second wavelength division demultiplexer being disposed above the fifth groove, and the fifth groove including: a second glue accommodating groove; a second overflow glue accommodating groove disposed around the second glue accommodating groove; and a second blocking wall disposed between the second glue accommodating groove and the second overflow glue accommodating groove, so that the second glue accommodating groove and the second overflow glue accommodating groove are spaced apart.

6. The optical module according to claim 1, wherein the first lens group includes: a first lens configured to reflect the optical signals transmitted by the first fiber optic adapter to the first cavity body, so as to change a propagation direction of the optical signals; an optical filter configured to receive the optical signals reflected by the first lens, reflect the first optical signal beam, and transmit the second optical signal beam; a fourth lens configured to reflect the second optical signal beam to the second wavelength division demultiplexer; and a fifth lens configured to reflect the first optical signal beam to the first wavelength division demultiplexer.

7. The optical module according to claim 1, wherein the at least one light receiving component includes: a first light receiving component including a plurality of first light receiving chips; and a second light receiving component including a plurality of second light receiving chips; the plurality of light receiving chips including the plurality of first light receiving chips and the plurality of second light receiving chips; and the light receiving assembly further includes: a second lens assembly including a first reflecting prism, the first reflecting prism being disposed on the first support surface, a projection of the first reflecting prism on the base covering the first light receiving chips, and the first reflecting prism being configured to reflect the optical signals split for the second time by the first wavelength division demultiplexer to the first light receiving chips; and a third lens assembly including a second reflecting prism, the second reflecting prism being disposed on the first supporting surface, a projection of the second reflecting prism on the base covering the second light receiving chips, and the second reflecting prism being configured to reflect the optical signals split for the second time by the second wavelength division demultiplexer to the second light receiving chips.

8. The optical module according to claim 7, wherein the first light receiving component further includes: a first substrate, the first light receiving chips being disposed on the first substrate; and a first transimpedance amplifier disposed on a side of the first substrate proximate to the circuit board, electrodes of the first light receiving chips and pins of the first transimpedance amplifier being located at a same height; and the second light receiving component further includes: a second substrate, the second light receiving chips being disposed on the second substrate; and a second transimpedance amplifier disposed on a side of the second substrate proximate to the circuit board, electrodes of the second light receiving chips and pins of the second transimpedance amplifier

being located at a same height.

9. The optical module according to claim 7, wherein the first cavity body further includes: a third mounting post; a fourth mounting post, the first reflecting prism being disposed between the third mounting post and the fourth mounting post, and the first reflecting prism being connected with the third mounting post and the fourth mounting post; and a fifth mounting post, the second reflecting prism being disposed between the fourth mounting post and the fifth mounting post, and the second reflecting prism being connected with the fourth mounting post and the fifth mounting post; wherein the third mounting post, the fourth mounting post, and the fifth mounting post are disposed on the first support surface and arranged at intervals in a width direction of the first cavity body.

10. The optical module according to claim 1, wherein the first cavity body further includes a first opening, the first opening being disposed on the side wall and proximate to the circuit board, and the first opening penetrating the side wall and communicating with the cavity; wherein the optical module further satisfies one of the following: the optical module further comprises a flexible circuit board, the flexible circuit board being electrically connected with the light receiving component through the first opening, an end of the flexible circuit board abutting against the step, and another end of the flexible circuit board being electrically connected with the circuit board; or, the optical module further comprises an electrical connecting member, the electrical connecting member being electrically connected with the light receiving component through the first opening, the light receiving component being disposed on the electrical connecting member, and the electrical connecting member being electrically connected with the circuit board through a flexible circuit board.

11. The optical module according to claim 1, wherein the light receiving assembly further includes a flat lens, and the flat lens is disposed in the first via hole and disposed obliquely with respect to a central axis of the first via hole.

12. The optical module according to claim 11, wherein an included angle between an optic axis of the flat lens and the central axis of the first via hole satisfies a preset threshold, and the preset threshold is any value within a range of  $4^{\circ}$  to  $6^{\circ}$  inclusive.

13. The optical module according to claim 1, further comprising: a light emitting assembly disposed in the shell and electrically connected with the circuit board, the light emitting assembly and the light receiving assembly being arranged in a stack, and the light emitting assembly being configured to emit optical signals; and a second fiber optic adapter connected with the light emitting assembly, the second fiber optic adapter and the first fiber optic adapter being located at a same height, and the second fiber optic adapter being configured to transmit the optical signals from the light emitting assembly to an outside of the optical module; wherein the light receiving assembly further includes a displacement component, the displacement component being connected with the first fiber optic adapter and the first cavity body, and the displacement component being configured to adjust an optical path height of the optical signals transmitted by the first fiber optic adapter in a height direction of the optical module.

14. The optical module according to claim 13, wherein the displacement component includes: a prism cavity body connected with the first fiber optic adapter and the first cavity body, the prism cavity body including a prism accommodating cavity, the first fiber optic adapter communicating with the prism cavity body through the prism accommodating cavity, and the prism accommodating cavity communicating with the first via hole; and a displacement prism disposed in the prism accommodating cavity, the displacement prism being configured to adjust the optical path height of the optical signals transmitted by the first fiber optic adapter in the height direction of the optical module.

15. The optical module according to claim 14, wherein a side of the prism accommodating cavity proximate to the first cavity body is open, so as to constitute a second opening; and wherein the displacement component further includes a second cover plate, the second cover plate covering the prism cavity body, so as to close a portion of the second opening, an exposed portion of the second

opening constituting a second via hole, and the second via hole communicating with the first via hole.

16. The optical module according to claim 14, wherein the displacement component further includes: a connecting hole disposed on a side of the prism cavity body proximate to the first fiber optic adapter and communicating with the prism accommodating cavity, the connecting hole including: a counterbore; and a connecting sub-hole communicating with the prism accommodating cavity and the counterbore, and the counterbore being closer to the first fiber optic adapter than the connecting sub-hole; a first connecting groove disposed on a bottom wall of the counterbore and proximate to an inner wall of the counterbore; and a first protrusion, the first connecting groove being recessed in a direction away from the first fiber optic adapter, so as to constitute the first protrusion on the bottom wall of the counterbore; and the first fiber optic adapter includes: an adapter body; and a connector disposed on an end of the adapter body proximate to the displacement component and matched with the connecting hole, an end of the connector proximate to the displacement component abutting against the first protrusion.

17. The optical module according to claim 14, wherein the first cavity body further includes a connecting portion, the connecting portion being disposed on a side of the side wall proximate to the displacement component, and the connecting portion being connected to the prism cavity body, the connecting portion including: a first connecting plate; and a second connecting plate, the first connecting plate being opposite to the second connecting plate, and the first connecting plate and the second connecting plate being located on two sides of the displacement component respectively, the prism cavity body being clamped between the first connecting plate and the second connecting plate, and sides of the first connecting plate and the second connecting plate proximate to the prism cavity body each being connected with an outer surface of the prism cavity body.

18. The optical module according to claim 17, wherein the connecting portion further satisfies at least one of the following: the connecting portion further includes a support structure, the support structure being disposed on a side of the first connecting plate away from the second connecting plate, and the support structure being connected with the first connecting plate and the side wall, so as to support the first connecting plate; or the connecting portion further includes a support structure, the support structure being disposed on a side of the second connecting plate away from the first connecting plate, and the support structure being connected with the second connecting plate and the side wall, so as to support the second connecting plate.

19. The optical module according to claim 14, wherein the displacement prism includes: a third reflecting surface; and a fourth reflecting surface, the third reflecting surface being parallel to the fourth reflecting surface, and the third reflecting surface being configured to reflect the optical signals transmitted by the first fiber optic adapter to the fourth reflecting surface, and the fourth reflecting surface being configured to reflect the optical signals reflected by the third reflecting surface to the first via hole.

---