

# US Patent & Trademark Office

## Patent Public Search | Text View

---

|                      |                    |
|----------------------|--------------------|
| United States Patent | 12408068           |
| Kind Code            | B2                 |
| Date of Patent       | September 02, 2025 |
| Inventor(s)          | Zhang; Dan et al.  |

---

### Adapting a radar transmission based on a congestion level

---

#### Abstract

This disclosure provides systems, devices, apparatus, and methods, including computer programs encoded on storage media, for adapting a radar transmission based on a congestion level. A wireless device, such as a radar device, a UE, a base station, a vehicle, etc., may detect a congestion level of a wireless communication environment that includes the wireless device. The wireless device may have at least one of a first FOV or a first range within the wireless communication environment. The wireless device may transmit, based on the congestion level exceeding a threshold, a radar signal that corresponds to the wireless device having at least one of a second FOV or a second range in the wireless communication environment that is smaller than the at least one of the first FOV or the first range.

---

**Inventors:** Zhang; Dan (San Diego, CA), Gulati; Kapil (Belle Mead, NJ), Li; Junyi (Fairless Hills, PA)

**Applicant:** QUALCOMM Incorporated (San Diego, CA)

**Family ID:** 80741103

**Assignee:** QUALCOMM Incorporated (San Diego, CA)

**Appl. No.:** 17/476448

**Filed:** September 15, 2021

#### Prior Publication Data

| Document Identifier | Publication Date |
|---------------------|------------------|
| US 20220095151 A1   | Mar. 24, 2022    |

#### Related U.S. Application Data

us-provisional-application US 63081837 20200922

---

## Publication Classification

**Int. Cl.:** H04W28/02 (20090101); H04W16/28 (20090101)

**U.S. Cl.:**

**CPC** H04W28/0226 (20130101); H04W16/28 (20130101); H04W28/0289 (20130101);

## Field of Classification Search

**CPC:** H04W (28/0226); H04W (16/28); H04W (28/0289); G01S (7/0236); G01S (13/343); G01S (13/345); G01S (13/931); G01S (7/023)

---

## References Cited

### U.S. PATENT DOCUMENTS

| Patent No.   | Issued Date | Patentee Name | U.S. Cl. | CPC          |
|--------------|-------------|---------------|----------|--------------|
| 10605911     | 12/2019     | Parker        | N/A      | G01S 13/42   |
| 10779189     | 12/2019     | Khoryaev      | N/A      | H04L 47/283  |
| 2017/0019923 | 12/2016     | Agardh        | N/A      | H04W 74/0808 |
| 2017/0293016 | 12/2016     | McCloskey     | N/A      | G01S 13/08   |
| 2019/0103663 | 12/2018     | Ichinose      | N/A      | H01Q 21/0037 |
| 2019/0195985 | 12/2018     | Lin           | N/A      | G01S 13/931  |
| 2019/0324136 | 12/2018     | Amadjikpe     | N/A      | G01S 13/70   |
| 2020/0025866 | 12/2019     | Gulati et al. | N/A      | N/A          |
| 2020/0185804 | 12/2019     | Watanabe      | N/A      | G01S 13/584  |
| 2022/0082681 | 12/2021     | Rao           | N/A      | G01S 7/352   |
| 2022/0365169 | 12/2021     | Lefevre       | N/A      | G01S 7/0235  |

### OTHER PUBLICATIONS

International Search Report and Written Opinion—PCT/US2021/050722—ISA/EPO—Jan. 10, 2022. cited by applicant

---

*Primary Examiner:* Liu; Siming

*Attorney, Agent or Firm:* Procopio, Cory, Hargreaves & Savitch LLP/QUALCOMM Incorporated

---

## Background/Summary

CROSS REFERENCE TO RELATED APPLICATION(S) (1) This application claims the benefit of and priority to U.S. Provisional Application Ser. No. 63/081,837, entitled “Adapting a Radar Transmission based on a Congestion Level” and filed on Sep. 22, 2020, which is expressly incorporated by reference herein in its entirety.

### INTRODUCTION

(1) The present disclosure relates generally to radar devices, and more particularly, to adjusting a radar transmission.

(2) Wireless communication systems are widely deployed to provide various telecommunication

services such as telephony, video, data, messaging, and broadcasts. Typical wireless communication systems may employ multiple-access technologies capable of supporting communication with multiple users by sharing available system resources. Examples of such multiple-access technologies include code division multiple access (CDMA) systems, time division multiple access (TDMA) systems, frequency division multiple access (FDMA) systems, orthogonal frequency division multiple access (OFDMA) systems, single-carrier frequency division multiple access (SC-FDMA) systems, and time division synchronous code division multiple access (TD-SCDMA) systems.

(3) These multiple access technologies have been adopted in various telecommunication standards to provide a common protocol that enables different wireless devices to communicate on a municipal, national, regional, and even global level. An example telecommunication standard is 5G New Radio (NR). 5G NR is part of a continuous mobile broadband evolution promulgated by Third Generation Partnership Project (3GPP) to meet new requirements associated with latency, reliability, security, scalability (e.g., with Internet of Things (IoT)), and other requirements. 5G NR includes services associated with enhanced mobile broadband (eMBB), massive machine type communications (mMTC), and ultra-reliable low latency communications (URLLC). Some aspects of 5G NR may be based on the 4G Long Term Evolution (LTE) standard. There exists a need for further improvements in 5G NR technology. These improvements may also be applicable to other multi-access technologies and the telecommunication standards that employ these technologies.

#### SUMMARY

(4) The following presents a simplified summary of one or more aspects in order to provide a basic understanding of such aspects. This summary is not an extensive overview of all contemplated aspects, and is intended to neither identify key or critical elements of all aspects nor delineate the scope of any or all aspects. Its sole purpose is to present some concepts of one or more aspects in a simplified form as a prelude to the more detailed description that is presented later.

(5) In an aspect of the disclosure, a method of wireless communication at a wireless device is provided. The method may include detecting a congestion level of a wireless communication environment that includes the wireless device, the wireless device having at least one of a first field of view (FOV) or a first range within the wireless communication environment; and transmitting, based on the congestion level exceeding a threshold, a radar signal that corresponds to the wireless device having at least one of a second FOV or a second range in the wireless communication environment that is smaller than the at least one of the first FOV or the first range.

(6) In another aspect of the disclosure, an apparatus for wireless communication at a wireless device is provided. The apparatus includes a memory and at least one processor coupled to the memory, the memory and the at least one processor configured to detect a congestion level of a wireless communication environment that includes the wireless device, the wireless device having at least one of a first FOV or a first range within the wireless communication environment; and transmit, based on the congestion level exceeding a threshold, a radar signal that corresponds to the wireless device having at least one of a second FOV or a second range in the wireless communication environment that is smaller than the at least one of the first FOV or the first range.

(7) In another aspect of the disclosure, an apparatus for wireless communication at a wireless device is provided. The apparatus may include means for detecting a congestion level of a wireless communication environment that includes the wireless device, the wireless device having at least one of a first FOV or a first range within the wireless communication environment; and means for transmitting, based on the congestion level exceeding a threshold, a radar signal that corresponds to the wireless device having at least one of a second FOV or a second range in the wireless communication environment that is smaller than the at least one of the first FOV or the first range.

(8) In another aspect of the disclosure, a computer-readable medium storing computer executable code for wireless communication at a wireless device is provided. The computer-readable medium may be non-transitory, for example. The code when executed by a processor causes the processor to

detect a congestion level of a wireless communication environment that includes the wireless device, the wireless device having at least one of a first FOV or a first range within the wireless communication environment; and transmit, based on the congestion level exceeding a threshold, a radar signal that corresponds to the wireless device having at least one of a second FOV or a second range in the wireless communication environment that is smaller than the at least one of the first FOV or the first range.

(9) In an aspect of the disclosure, a method of wireless communication at a wireless device is provided. The method may include measuring a congestion level of a wireless communication environment that includes a first wireless device, the first wireless device having at least one of a first FOV or a first range within the wireless communication environment; and transmitting a message to the first wireless device based on the congestion level, the message associated with the first wireless device having at least one of a second FOV or a second range in the wireless communication environment that is smaller than the at least one of the first FOV or the first range.

(10) In another aspect of the disclosure, an apparatus for wireless communication at a wireless device is provided. The apparatus includes a memory and at least one processor coupled to the memory, the memory and the at least one processor configured to measure a congestion level of a wireless communication environment that includes a first wireless device, the first wireless device having at least one of a first FOV or a first range within the wireless communication environment; and transmit a message to the first wireless device based on the congestion level, the message associated with the first wireless device having at least one of a second FOV or a second range in the wireless communication environment that is smaller than the at least one of the first FOV or the first range.

(11) In another aspect of the disclosure, an apparatus for wireless communication at a wireless device is provided. The apparatus may include means for measuring a congestion level of a wireless communication environment that includes a first wireless device, the first wireless device having at least one of a first FOV or a first range within the wireless communication environment; and means for transmitting a message to the first wireless device based on the congestion level, the message associated with the first wireless device having at least one of a second FOV or a second range in the wireless communication environment that is smaller than the at least one of the first FOV or the first range.

(12) In another aspect of the disclosure, a computer-readable medium storing computer executable code for wireless communication at a wireless device is provided. The computer-readable medium may be non-transitory, for example. The code when executed by a processor causes the processor to measure a congestion level of a wireless communication environment that includes a first wireless device, the first wireless device having at least one of a first FOV or a first range within the wireless communication environment; and transmit a message to the first wireless device based on the congestion level, the message associated with the first wireless device having at least one of a second FOV or a second range in the wireless communication environment that is smaller than the at least one of the first FOV or the first range.

(13) To the accomplishment of the foregoing and related ends, the one or more aspects comprise the features hereinafter fully described and particularly pointed out in the claims. The following description and the annexed drawings set forth in detail certain illustrative features of the one or more aspects. These features are indicative, however, of but a few of the various ways in which the principles of various aspects may be employed, and this description is intended to include all such aspects and their equivalents.

---

## Description

## BRIEF DESCRIPTION OF THE DRAWINGS

- (1) FIG. 1 is a diagram illustrating an example of a radar device and a wireless communications system.
- (2) FIG. 2 is a diagram illustrating radar signals transmitted by a vehicle and reflected from a target and a false target.
- (3) FIG. 3 is a diagram illustrating a transmitted signal and a return signal of a radar.
- (4) FIG. 4 is a diagram illustrating an example of a wireless device capable of sensing a radar signal.
- (5) FIGS. 5A-5B illustrate example range spectrum diagrams.
- (6) FIG. 6 illustrates examples for reducing a maximum range of a radar.
- (7) FIGS. 7A-7B illustrate example diagrams corresponding to different ranges for a field of view of a radar.
- (8) FIG. 8 is a flowchart of a method of wireless communication at a wireless device according to one example.
- (9) FIG. 9 is a flowchart of a method of wireless communication at a wireless device according to one example.
- (10) FIG. 10 is a flowchart of a method of wireless communication at a second wireless device according to one example.
- (11) FIG. 11 is a flowchart of a method of wireless communication at a wireless device according to one example.
- (12) FIG. 12 is a diagram illustrating an example of a hardware implementation for an example apparatus.

## DETAILED DESCRIPTION

(13) The detailed description set forth below in connection with the appended drawings is intended as a description of various configurations and is not intended to represent the only configurations in which the concepts described herein may be practiced. The detailed description includes specific details for the purpose of providing a thorough understanding of various concepts. However, it will be apparent to those skilled in the art that these concepts may be practiced without these specific details. In some instances, well known structures and components are shown in block diagram form in order to avoid obscuring such concepts.

(14) Several aspects of telecommunication systems will now be presented with reference to various apparatus and methods. These apparatus and methods will be described in the following detailed description and illustrated in the accompanying drawings by various blocks, components, circuits, processes, algorithms, etc. (collectively referred to as “elements”). These elements may be implemented using electronic hardware, computer software, or any combination thereof. Whether such elements are implemented as hardware or software depends upon the particular application and design constraints imposed on the overall system.

(15) By way of example, an element, or any portion of an element, or any combination of elements may be implemented as a “processing system” that includes one or more processors. Examples of processors include microprocessors, microcontrollers, graphics processing units (GPUs), central processing units (CPUs), application processors, digital signal processors (DSPs), reduced instruction set computing (RISC) processors, systems on a chip (SoC), baseband processors, field programmable gate arrays (FPGAs), programmable logic devices (PLDs), state machines, gated logic, discrete hardware circuits, and other suitable hardware configured to perform the various functionality described throughout this disclosure. One or more processors in the processing system may execute software. Software shall be construed broadly to mean instructions, instruction sets, code, code segments, program code, programs, subprograms, software components, applications, software applications, software packages, routines, subroutines, objects, executables, threads of execution, procedures, functions, etc., whether referred to as software, firmware, middleware,

microcode, hardware description language, or otherwise.

(16) Accordingly, in one or more example examples, the functions described may be implemented in hardware, software, or any combination thereof. If implemented in software, the functions may be stored on or encoded as one or more instructions or code on a computer-readable medium. Computer-readable media includes computer storage media. Storage media may be any available media that can be accessed by a computer. By way of example, and not limitation, such computer-readable media can comprise a random-access memory (RAM), a read-only memory (ROM), an electrically erasable programmable ROM (EEPROM), optical disk storage, magnetic disk storage, other magnetic storage devices, combinations of the aforementioned types of computer-readable media, or any other medium that can be used to store computer executable code in the form of instructions or data structures that can be accessed by a computer.

(17) While aspects and implementations are described in this application by illustration to some examples, those skilled in the art will understand that additional implementations and use cases may come about in many different arrangements and scenarios. Aspects described herein may be implemented across many differing platform types, devices, systems, shapes, sizes, and packaging arrangements. For example, implementations and/or uses may come about via integrated chip implementations and other non-module-component based devices (e.g., end-user devices, vehicles, communication devices, computing devices, industrial equipment, retail/purchasing devices, medical devices, artificial intelligence (AI)-enabled devices, etc.). While some examples may or may not be specifically directed to use cases or applications, a wide assortment of applicability of described aspects may occur. Implementations may range a spectrum from chip-level or modular components to non-modular, non-chip-level implementations and further to aggregate, distributed, or original equipment manufacturer (OEM) devices or systems incorporating one or more aspects of the described aspects. In some practical settings, devices incorporating described aspects and features may also include additional components and features for implementation and practice of claimed and described aspect. For example, transmission and reception of wireless signals necessarily includes a number of components for analog and digital purposes (e.g., hardware components including antenna, RF-chains, power amplifiers, modulators, buffer, processor(s), interleaver, adders/summers, etc.). It is intended that aspects described herein may be practiced in a wide variety of devices, chip-level components, systems, distributed arrangements, aggregated or disaggregated components, end-user devices, etc. of varying sizes, shapes, and constitution.

(18) A ranging radar may be incorporated in or on equipment for performing collision avoidance and other related sensing techniques. As one example, a ranging radar may be provided at a vehicle, industrial equipment, environment sensing equipment, etc. The radar may be configured to transmit a radar signal/pulse and receive a return signal based on a reflection of the radar signal from an object/target. A radar device may determine a time delay between transmission of the radar signal and the reception of the return signal in order to calculate a distance between the radar device and one or more physical objects from which the return signal is reflected. In some aspects, a physical object from which a radar signal is reflected may be referred to as a target. In some cases, the radar device may detect a false target, or may falsely detect a location of a target, based on a received signal that is not an accurate reflection of the radar signal from a target. Such interference may interfere with the radar signal and may at least partially occlude the target from accurate detection by the radar device. For example, with the radar device may receive a signal, which is not a reflection of the radar device's own signal, with a shortened distance/time offset and with increased power in comparison to an actual reflection of the radar signal. If the radar device assumes that the signal is a reflection of the radar device's own signal, it will falsely detect a target. A false target may refer to an inaccurate detection of a target by the radar device.

(19) In some examples, multiple devices in an area may operate ranging radars or may transmit other sensing signals. As an example, other sensing devices may perform a similar detection of objects based on a transmission and reflection of a type of signal similar to a radar signal. The other

sensing devices may use a signal that is at least somewhat different than a radar signal. The transmission of multiple radar signals, or other signals from other sensing devices, near a radar device may lead to increasing interference to accurate radar detection at the radar device. Each sensing device or radar device may transmit signals independently, e.g., without coordinated control. The radar device may receive the return signal (e.g., reflected signal) based on the radar device's own signal and/or may receive a different signal as interference transmitted from a different radar device or a different sensing device. The reception of an interfering signal may lead to inaccurate radar detection at the radar device. For example, when multiple radar sources operate within a particular range of the radar device, the other radar sources may cause interference to the reception and object determination of the radar device.

(20) Aspects presented herein provide for a radar device to adjust radar transmission or detection parameters based on a current congestion level. In one or more aspects, the radar/equipment may determine a congestion level based on a content and a number of messages received by the radar (e.g., via a Uu link or a sidelink) or based on interference that the radar device determines from a false peak or an increased noise floor on a range spectrum associated with a radar image at the radar device. "Congestion" refers to interference to/from a radar device caused by one or more other radar signals in a wireless communication environment. "Congestion level" refers to an amount of the one or more stray radar signals that are generating the interference in the wireless communication environment. In one example, the radar may determine the congestion level within a range of the radar based on a number of detected devices and/or an amount of signals detected by radar. The range may refer to an area surrounding the radar or a distance from the radar. According to one or more aspects, if the congestion level exceeds a threshold, the radar may reduce the maximum detection range of the radar by decreasing a sweeping up time ( $T_{sub.up}$ ) and providing a larger discontinuous transmission (DTX) time between radar pulses.

(21) In one example, the radar device may reduce the transmit power to reduce a maximum detection range of the radar. By decreasing the maximum detection range of the radar, detection of closer objects may be prioritized without impacting the radar device's detection of a speed and/or a direction of the closer objects. In one example, the range of the radar may be reduced to reduce interference to the radar. Decreasing the range of the radar may also cause the radar to generate less interference to other devices within the wireless communication environment (e.g., other devices within proximity to the radar). While objects that have a larger physical distance may still be detected in some cases, the radar device may be configured to reduce a priority, or de-prioritize, detection of more distant objects as the congestion level of radar signals in the current environment increases. For example, the radar device may prioritize the detection of objects that are closer (e.g., have a closer physical distance) to the radar device as the congestion level increases. The adjustment of a radar signal, e.g., to reduce a transmit power and/or reduce a detection range, based on a congestion level in a surrounding area enables the radar device to reduce interference that may be caused to other nearby devices. As the adjustment is based on a congestion level, the transmission power and/or detection range may be increased when there are lower congestion levels and lower likelihood of interference.

(22) FIG. 1 is a diagram **100** illustrating an example of a wireless communications system and an access network in which base stations **102** or **180** may wirelessly communicate with user equipments (UEs) **104**, such as a roadside unit (RSU) **117** or other device that may transmit/receive sidelink communications. Some wireless devices may perform radar signal sensing. For example, a radar device **103** may transmit a wireless signal **105** and use information about the signal to image an environment or determine information about a target **107** based on range, Doppler, and/or angle information determined from the wireless signal. The signal may include a defined waveform, such as a frequency modulated continuous wave (FMCW), a pulse waveform, or a chirp waveform, among other examples of a defined waveform.

(23) In some examples, the radar device **103** may transmit a radar signal to determine information

about a target or an environment. A radar signal sensing component **198** in the radar device **103** may transmit the radar signal. The radar signal sensing component **198** may be configured to detect a congestion level of a wireless communication environment that includes the wireless device, the wireless device having at least one of a first field of view (FOV) or a first range within the wireless communication environment; and transmit, based on the congestion level exceeding a threshold, a radar signal that corresponds to the wireless device having at least one of a second FOV or a second range in the wireless communication environment that is smaller than the at least one of the first FOV or the first range. FIGS. 7A and 7B illustrate example aspects of transmission of a radar signal associated with different FOVs. In certain aspects, a UE **104** may include a congestion indicator component **199** configured to measure a congestion level of a wireless communication environment that includes a first wireless device, the first wireless device having at least one of a first FOV or a first range within the wireless communication environment; and transmit a message to the first wireless device based on the congestion level, the message associated with the first wireless device having at least one of a second FOV or a second range in the wireless communication environment that is smaller than the at least one of the first FOV or the first range.

(24) The radar device **103** may compare the received signal to the transmitted signal to determine information about the target **107** or environment. Radar signal sensing may be employed for automotive radar, e.g., detecting an environment around a vehicle, nearby vehicles or items, detecting information for smart cruise control, collision avoidance, etc. Radar signal sensing may be employed for gesture recognition, e.g., a human activity recognition, a hand motion recognition, a facial expression recognition, a keystroke detection, sign language detection, etc. Radar signal sensing may be employed to acquire contextual information, e.g., location detection, tracking, determining directions, range estimation, etc. Radar signal sensing may be employed to image an environment, e.g., to provide a 3-dimensional (3D) map for virtual reality (VR) applications. Radar devices may be employed to provide high resolution localization, e.g., for industrial Internet-of-things (IIoT) applications. In some examples, the radar device **103** may provide consumer level radar with advanced detection capabilities. Radar signal sensing may provide touchless or device free interaction with a device or system. For example, a wireless device may detect user gestures to trigger an operation at the wireless device.

(25) In some examples, radar signal sensing may be based on frequency ranges that overlap with wireless communication systems for the signal **105**, such as the wireless communication system illustrated in FIG. 1. The radar device **103** may use a waveform for the signal **105** that relates to a communication system. As one non-limiting example, radar signal sensing may be based on a signal in a mmW frequency range, such as a Frequency Range2 (FR2), Frequency Range 2x (FR2x), and/or Frequency Range 4 (FR4) signal, which may provide improved range for radar signal detection. In some examples, the radar device **103** may have the capability to perform radar signal sensing and wireless communication. In some examples, the radar device **103** may be a component of a UE **104**, a base station **102** or **180**, or other access point in the communication system of FIG. 1. In some examples, the radar device **103** may be a wireless communication device (e.g., a UE **104**, base station **102/180**, or other access point) that supports radar transmission and detection. In other examples, the radar device **103** may perform radar signal transmission and sensing without having wireless communication capabilities. As illustrated in FIG. 1, the radar device **103** may use directional beams to transmit the radar signal **105**. For example, the radar device **103** may transmit the radar signal in a particular direction relative to the radar device. The radar device **103** may be within or outside of a coverage area **110** of a base station **102** or **180**.

(26) The wireless communications system illustrated in FIG. 1 (also referred to as a wireless wide area network (WWAN)) includes base stations **102**, UEs **104**, an Evolved Packet Core (EPC) **160**, and another core network **190** (e.g., a 5G Core (5GC)). The base stations **102** may include macrocells (high power cellular base station) and/or small cells (low power cellular base station). The macrocells include base stations. The small cells include femtocells, picocells, and microcells.



(27) The base stations **102** configured for 4G LTE (collectively referred to as Evolved Universal Mobile Telecommunications System (UMTS) Terrestrial Radio Access Network (E-UTRAN)) may interface with the EPC **160** through first backhaul links **132** (e.g., S1 interface). The base stations **102** configured for 5G NR (collectively referred to as Next Generation RAN (NG-RAN)) may interface with core network **190** through second backhaul links **184**. In addition to other functions, the base stations **102** may perform one or more of the following functions: transfer of user data, radio channel ciphering and deciphering, integrity protection, header compression, mobility control functions (e.g., handover, dual connectivity), inter-cell interference coordination, connection setup and release, load balancing, distribution for non-access stratum (NAS) messages, NAS node selection, synchronization, radio access network (RAN) sharing, multimedia broadcast multicast service (MBMS), subscriber and equipment trace, RAN information management (RIM), paging, positioning, and delivery of warning messages. The base stations **102** may communicate directly or indirectly (e.g., through the EPC **160** or core network **190**) with each other over third backhaul links **134** (e.g., X2 interface). The first backhaul links **132**, the second backhaul links (e.g., an Xn interface), and the third backhaul links **134** may be wired or wireless.

(28) In some aspects, a base station **102** or **180** may be referred as a RAN and may include aggregated or disaggregated components. As an example of a disaggregated RAN, a base station may include a central unit (CU) **106**, one or more distributed units (DU) **115**, and/or one or more remote units (RU) **119**, as illustrated in FIG. 1. A RAN may be disaggregated with a split between an RU **119** and an aggregated CU/DU. A RAN may be disaggregated with a split between the CU **106**, the DU **115**, and the RU **119**. A RAN may be disaggregated with a split between the CU **106** and an aggregated DU/RU. The CU **106** and the one or more DUs **115** may be connected via an F1 interface. A DU **115** and an RU **119** may be connected via a fronthaul interface. A connection between the CU **106** and a DU **115** may be referred to as a midhaul, and a connection between a DU **115** and an RU **119** may be referred to as a fronthaul. The connection between the CU **106** and the core network may be referred to as the backhaul. The RAN may be based on a functional split between various components of the RAN, e.g., between the CU **106**, the DU **115**, or the RU **119**. The CU **106** may be configured to perform one or more aspects of a wireless communication protocol, e.g., handling one or more layers of a protocol stack, and the DU(s) **115** may be configured to handle other aspects of the wireless communication protocol, e.g., other layers of the protocol stack. In different implementations, the split between the layers handled by the CU **106** and the layers handled by the DU **115** may occur at different layers of a protocol stack. As one, non-limiting example, a DU **115** may provide a logical node to host a radio link control (RLC) layer, a medium access control (MAC) layer, and at least a portion of a physical (PHY) layer based on the functional split. An RU **119** may provide a logical node configured to host at least a portion of the PHY layer and radio frequency (RF) processing. A CU **106** may host higher layer functions, e.g., above the RLC layer, such as a service data adaptation protocol (SDAP) layer, a packet data convergence protocol (PDCP) layer. In other implementations, the split between the layer functions provided by the CU, DU, or RU may be different.

(29) An access network may include one or more integrated access and backhaul (IAB) nodes **111** that exchange wireless communication with a UE **104** or other IAB node **111** to provide access and backhaul to a core network. In an IAB network of multiple IAB nodes, an anchor node may be referred to as an IAB donor. The IAB donor may be a base station **102** or **180** that provides access to a core network **190** or EPC **160** and/or control to one or more IAB nodes **111**. The IAB donor may include a CU **106** and a DU **115**. IAB nodes **111** may include a DU **115** and a mobile termination (MT). The DU **115** of an IAB node **111** may operate as a parent node, and the MT may operate as a child node.

(30) The base stations **102** may wirelessly communicate with the UEs **104**. Each of the base stations **102** may provide communication coverage for a respective geographic coverage area **110**. There may be overlapping geographic coverage areas **110**. For example, the small cell **102'** may

have a coverage area **110'** that overlaps the coverage area **110** of one or more macro base stations **102**. A network that includes both small cell and macrocells may be known as a heterogeneous network. A heterogeneous network may also include Home Evolved Node Bs (eNBs) (HeNBs), which may provide service to a restricted group known as a closed subscriber group (CSG). The communication links **120** between the base stations **102** and the UEs **104** may include uplink (UL) (also referred to as reverse link) transmissions from a UE **104** to a base station **102** and/or downlink (DL) (also referred to as forward link) transmissions from a base station **102** to a UE **104**. The communication links **120** may use multiple-input and multiple-output (MIMO) antenna technology, including spatial multiplexing, beamforming, and/or transmit diversity. The communication links may be through one or more carriers. The base stations **102**/UEs **104** may use spectrum up to Y MHz (e.g., 5, 10, 15, 20, 100, 400, etc. MHz) bandwidth per carrier allocated in a carrier aggregation of up to a total of Yx MHz (x component carriers) used for transmission in each direction. The carriers may or may not be adjacent to each other. Allocation of carriers may be asymmetric with respect to DL and UL (e.g., more or fewer carriers may be allocated for DL than for UL). The component carriers may include a primary component carrier and one or more secondary component carriers. A primary component carrier may be referred to as a primary cell (PCell) and a secondary component carrier may be referred to as a secondary cell (SCell).

(31) Certain UEs **104** may communicate with each other using device-to-device (D2D) communication link **158**. The D2D communication link **158** may use the DL/UL WWAN spectrum. The D2D communication link **158** may use one or more sidelink channels, such as a physical sidelink broadcast channel (PSBCH), a physical sidelink discovery channel (PSDCH), a physical sidelink shared channel (PSSCH), and a physical sidelink control channel (PSCCH). D2D communication may be through a variety of wireless D2D communications systems, such as for example, WiMedia, Bluetooth, ZigBee, Wi-Fi based on the Institute of Electrical and Electronics Engineers (IEEE) 802.11 standard, LTE, or NR.

(32) Some examples of sidelink communication may include vehicle-based communication devices that can communicate from vehicle-to-vehicle (V2V), vehicle-to-infrastructure (V2I) (e.g., from the vehicle-based communication device to road infrastructure nodes such as an RSU **117**), vehicle-to-network (V2N) (e.g., from the vehicle-based communication device to one or more network nodes, such as a base station), vehicle-to-pedestrian (V2P), cellular vehicle-to-everything (C-V2X), and/or a combination thereof and/or with other devices, which can be collectively referred to as vehicle-to-anything (V2X) communications. Sidelink communication may be based on V2X or other D2D communication, such as Proximity Services (ProSe), etc. In addition to UEs, sidelink communication may also be transmitted and received by other transmitting and receiving devices, such as the RSU **117**, etc. Sidelink communication may be exchanged using a PC5 interface, in some examples.

(33) The wireless communications system may further include a Wi-Fi access point (AP) **150** in communication with Wi-Fi stations (STAs) **152** via communication links **154**, e.g., in a 5 GHz unlicensed frequency spectrum or the like. When communicating in an unlicensed frequency spectrum, the STAs **152**/AP **150** may perform a clear channel assessment (CCA) prior to communicating in order to determine whether the channel is available.

(34) The small cell **102'** may operate in a licensed and/or an unlicensed frequency spectrum. When operating in an unlicensed frequency spectrum, the small cell **102'** may employ NR and use the same unlicensed frequency spectrum (e.g., 5 GHz, or the like) as used by the Wi-Fi AP **150**. The small cell **102'**, employing NR in an unlicensed frequency spectrum, may boost coverage to and/or increase capacity of the access network.

(35) The electromagnetic spectrum is often subdivided, based on frequency/wavelength, into various classes, bands, channels, etc. In 5G NR, two initial operating bands have been identified as frequency range designations FR1 (410 MHz-7.125 GHz) and FR2 (24.25 GHz-52.6 GHz). The frequencies between FR1 and FR2 are often referred to as mid-band frequencies. Although a

portion of FR1 is greater than 6 GHz, FR1 is often referred to (interchangeably) as a “sub-6 GHz” band in various documents and articles. A similar nomenclature issue sometimes occurs with regard to FR2, which is often referred to (interchangeably) as a “millimeter wave” band in documents and articles, despite being different from the extremely high frequency (EHF) band (30 GHz-300 GHz) which is identified by the International Telecommunications Union (ITU) as a “millimeter wave” band.

(36) The frequencies between FR1 and FR2 are often referred to as mid-band frequencies. Recent 5G NR studies have identified an operating band for these mid-band frequencies as frequency range designation FR3 (7.125 GHz-24.25 GHz). Frequency bands falling within FR3 may inherit FR1 characteristics and/or FR2 characteristics, and thus may effectively extend features of FR1 and/or FR2 into mid-band frequencies. In addition, higher frequency bands are currently being explored to extend 5G NR operation beyond 52.6 GHz. For example, three higher operating bands have been identified as frequency range designations FR4a or FR4-1 (52.6 GHz-71 GHz), FR4 (52.6 GHz-114.25 GHz), and FR5 (114.25 GHz-300 GHz). Each of these higher frequency bands falls within the EHF band.

(37) With the above aspects in mind, unless specifically stated otherwise, it should be understood that the term “sub-6 GHz” or the like if used herein may broadly represent frequencies that may be less than 6 GHz, may be within FR1, or may include mid-band frequencies. Further, unless specifically stated otherwise, it should be understood that the term “millimeter wave” or the like if used herein may broadly represent frequencies that may include mid-band frequencies, may be within FR2, FR4, FR4-a or FR4-1, and/or FR5, or may be within the EHF band.

(38) A base station **102**, whether a small cell **102'** or a large cell (e.g., macro base station), may include and/or be referred to as an eNB, gNodeB (gNB), or another type of base station. Some base stations **180**, such as a gNB may operate in a traditional sub 6 GHz spectrum, in millimeter wave frequencies, and/or near millimeter wave frequencies in communication with the UE **104**. When the gNB operates in millimeter wave or near millimeter wave frequencies, the gNB may be referred to as a millimeter wave base station. The millimeter wave base station **180** may utilize beamforming **182** with the UE **104** to compensate for the path loss and short range. The base station **180** and the UE **104** may each include a plurality of antennas, such as antenna elements, antenna panels, and/or antenna arrays to facilitate the beamforming.

(39) The base station **180** may transmit a beamformed signal to the UE **104** in one or more transmit directions **182'**. The UE **104** may receive the beamformed signal from the base station **180** in one or more receive directions **182''**. The UE **104** may also transmit a beamformed signal to the base station **180** in one or more transmit directions. The base station **180** may receive the beamformed signal from the UE **104** in one or more receive directions. The base station **180**/UE **104** may perform beam training to determine the best receive and transmit directions for each of the base station **180**/UE **104**. The transmit and receive directions for the base station **180** may or may not be the same. The transmit and receive directions for the UE **104** may or may not be the same.

(40) The EPC **160** may include a Mobility Management Entity (MME) **162**, other MMEs **164**, a Serving Gateway **166**, a Multimedia Broadcast Multicast Service (MBMS) Gateway **168**, a Broadcast Multicast Service Center (BM-SC) **170**, and a Packet Data Network (PDN) Gateway **172**. The MME **162** may be in communication with a Home Subscriber Server (HSS) **174**. The MME **162** is the control node that processes the signaling between the UEs **104** and the EPC **160**. Generally, the MME **162** provides bearer and connection management. All user Internet protocol (IP) packets are transferred through the Serving Gateway **166**, which itself is connected to the PDN Gateway **172**. The PDN Gateway **172** provides UE IP address allocation as well as other functions. The PDN Gateway **172** and the BM-SC **170** are connected to the IP Services **176**. The IP Services **176** may include the Internet, an intranet, an IP Multimedia Subsystem (IMS), a PS Streaming Service, and/or other IP services. The BM-SC **170** may provide functions for MBMS user service provisioning and delivery. The BM-SC **170** may serve as an entry point for content provider

MBMS transmission, may be used to authorize and initiate MBMS Bearer Services within a public land mobile network (PLMN), and may be used to schedule MBMS transmissions. The MBMS Gateway **168** may be used to distribute MBMS traffic to the base stations **102** belonging to a Multicast Broadcast Single Frequency Network (MBSFN) area broadcasting a particular service, and may be responsible for session management (start/stop) and for collecting eMBMS related charging information.

(41) The core network **190** may include an Access and Mobility Management Function (AMF) **192**, other AMFs **193**, a Session Management Function (SMF) **194**, and a User Plane Function (UPF) **195**. The AMF **192** may be in communication with a Unified Data Management (UDM) **196**. The AMF **192** is the control node that processes the signaling between the UEs **104** and the core network **190**. Generally, the AMF **192** provides QoS flow and session management. All user Internet protocol (IP) packets are transferred through the UPF **195**. The UPF **195** provides UE IP address allocation as well as other functions. The UPF **195** is connected to the IP Services **197**. The IP Services **197** may include the Internet, an intranet, an IP Multimedia Subsystem (IMS), a Packet Switch (PS) Streaming (PSS) Service, and/or other IP services.

(42) The base station may include and/or be referred to as a gNB, Node B, eNB, an access point, a base transceiver station, a radio base station, a radio transceiver, a transceiver function, a basic service set (BSS), an extended service set (ESS), a transmit reception point (TRP), or some other suitable terminology. The base station **102** provides an access point to the EPC **160** or core network **190** for a UE **104**. Examples of UEs **104** include a cellular phone, a smart phone, a session initiation protocol (SIP) phone, a laptop, a personal digital assistant (PDA), a satellite radio, a global positioning system, a multimedia device, a video device, a digital audio player (e.g., MP3 player), a camera, a game console, a tablet, a smart device, a wearable device, a vehicle, an electric meter, a gas pump, a large or small kitchen appliance, a healthcare device, an implant, a sensor/actuator, a display, or any other similar functioning device. Some of the UEs **104** may be referred to as IoT devices (e.g., parking meter, gas pump, toaster, vehicles, heart monitor, etc.). The UE **104** may also be referred to as a station, a mobile station, a subscriber station, a mobile unit, a subscriber unit, a wireless unit, a remote unit, a mobile device, a wireless device, a wireless communications device, a remote device, a mobile subscriber station, an access terminal, a mobile terminal, a wireless terminal, a remote terminal, a handset, a user agent, a mobile client, a client, or some other suitable terminology.

(43) FIG. 2 is a diagram **200** illustrating radar signals transmitted by a radar device **204** associated with a vehicle **202** and reflected from a target **206** or vehicle **210** and signals that lead to a detection of a false target, which may also be referred to as a false detection of a target, at the radar device **204**. The radar device **204** may be a component of the vehicle **202** or may be removably located at the vehicle **202**. The radar device **204** may be a separate device, which may be associated with the vehicle **202**. A ranging radar (e.g., radar device **204**) may be incorporated in the vehicle **202** for performing collision avoidance and other related techniques. Vehicle **210** may similarly include a ranging radar. Although FIG. 2 illustrates an example of a radar application for a vehicle, the aspects described in connection with FIG. 2 are similarly applicable to non-vehicular radar devices. A radar device **204** at the vehicle **202** may be configured to transmit a radar signal/pulse (e.g., **230**) corresponding to an FOV **250** and receive a return signal (e.g., reflected signal **232**) based on a reflection of the radar signal from an object, which may be referred to as a target. The radar device **204** at the vehicle **202** may measure a time delay between transmission of the radar signal and reception of the return (e.g., reflected) signal for determining a distance to the object from which the return signal was reflected. In some cases, the radar device **204** may detect a false target, or may falsely detect a target, based on an interfering radar signal from another radar device. A false target, or a false detection of a target, refers to the detection of a target at a location that is not an accurate presence of a target and is instead due to interference. FIG. 2 illustrates the vehicle **210** having another radar device that may transmit similar radar signals (e.g., direct transmission

234) to the radar device 204. As illustrated in the example in FIG. 2, the radar signal 230 from the radar device 204 may be reflected from one or more targets (e.g., 206 and/or 210). The radar device 204 may also receive interference, such as direct signals (e.g., 234) from the vehicle 210 or device 208 that lead the radar device 204 at the vehicle 202 to detect a false target, or to falsely detect a target at an inaccurate location, based on a shortened distance/time offset and with higher power. For example, if the radar device 204 receives the direct signal from the device 208 and interprets the signal as a reflection of the radar device's own signal, the radar device 204 will falsely detect a target that is closer than the device 208. In some aspects, a false target detection may be based on a reflection of another device's signal rather than a direct signal. For example, the radar device 204 may receive a reflection of the signal from the radar device at the vehicle 210 that is reflected from the device 208. If the radar device 204 at the vehicle 202 is not able to distinguish the signal of other device transmissions from the radar reflections of its own radar signal, the vehicle 202 may misinterpret the received signal and incorrectly measure the distance to the target 206a. The vehicle 202 may determine the presence of a false target 206b at an incorrect location based on the signal.

(44) The interference increases as a number of vehicles equipped with sensing devices, such as ranging radars, increases in a given area. There may be no or little coordination among the sensing devices/radars. For example, the vehicle 210 and the device 208 may transmit radar signals, or other signals, independent of conditions associated with the radar device 204 of the vehicle 202. Therefore, the signal received by the radar device 204 of the vehicle 202 may include not only the return/reflection of the radar device's own signal but may also include a different signal (e.g., interference) transmitted from a radar (e.g., 214) associated with another vehicle, such as the vehicle 210 or another signal from one or more additional devices, such as the device 208. The added signals may lead to detection of false targets, if the radar device 204 interprets the additional signals as a reflection of its own radar signal. Accordingly, multiple radar sources operating in proximity to each other may cause significant interference to other radars of the multiple radar sources. As certain radar waveforms, such as a frequency modulated continuous wave (FMCW), received by the radar device 204 of the vehicle 202 may be signature-less, the radar return signal may be indistinguishable from the different radar signals transmitted from the multiple radar sources.

(45) The vehicle 202 and/or the radar device 204 may be configured to perform aspects in connection with the radar signal sensing component 198 of FIG. 1. Further, the false targets 206b may be configured to perform aspects in connection with the congestion indicator component 199 of FIG. 1.

(46) FIG. 3 is a diagram 300 that illustrates a waveform of a transmitted signal 302 and a corresponding return signal 304 that may be transmitted and received by a radar device, such as the radar device 103 in FIG. 1 and/or the radar device 204 or 214 in FIG. 2. For example, FIG. 2 illustrates the signal 230 transmitted by the radar device 204 in FIG. 2 may correspond to the transmitted signal 302, and the reflected signal 232 in FIG. 2 may correspond to the return signal 304. The signals 302-304 may be associated with an FMCW waveform utilized by the radar for frequency sweeping. The transmitted signal 302 may correspond to an instantaneous frequency that increases from zero to a higher frequency and subsequently decreases from the higher frequency to zero based on a sinusoidal operation. Each sweep up and down may correspond to an individual pulse or chirp of the FMCW. A chirp time may be indicated by  $T_{sub.c}$  and a sweeping up time may be indicated by  $T_{sub.up}$ . For instance, the frequency may sweep up from 77 GHz to 78 GHz to provide a sweeping bandwidth of 1 GHz. A time period that elapses for the sweeping up of the 1 GHz of bandwidth may correspond to  $T_{sub.up}$ . After the radar sweeps up to 78 GHz, an additional/non-zero length of time may elapse for the radar to sweep down and return to 77 GHz. The additional/non-zero length of time may correspond to  $T_{sub.down}$ . Thus,  $T_{sub.up} + T_{sub.down}$  may equal  $T_{sub.c}$  (e.g., the duration of the chirp/pulse). In examples, the radar may be configured based on certain  $T_{sub.c}$  parameters.

(47) The radar may receive a series of chirps via the return signal **304** that match the transmitted signal **302**, albeit delayed based on a location of an object from which the return signal is reflected. As a distance between the radar and the object increases, the corresponding delay may become larger. The distance to the object may be determined based on determining the delay. For example, rather than directly measuring a time of the delay, a frequency delta between the transmitted signal **302** and the return signal **304** may be determined, where the frequency delta may be proportional to the delay. The range of the object may be further determined based on the delay being proportional to the range. The frequency delta may be associated with a range spectrum and a beat frequency (F.sub.b) determined based on a Fast Fourier Transform (FFT). The beat frequency may correspond to a mixed output of the transmitted signal **302** and the return signal **304**. A slope for sweeping up the frequency may be defined (e.g., 1 GHz per T.sub.up seconds), such that a rate at which the slope changes may correspond to a beta ( $\beta$ ) parameter.

(48) The parameters of the transmitted signal **302** and the return signal **304** may be indicative of a maximum (e.g., theoretical) detectable range of an FMCW receiver of the radar. For longer range radars, 100-300 m may be the maximum detectable range. The parameters may also be indicative of a maximum detectable speed/velocity (e.g., 30-40 m/s). For example, based on multiple received chirps, the velocity of the object may be determined based on a Doppler spectrum and a direction of the object may be determined based on a direction of arrival (DoA) spectrum. In examples, outputs such as  $x(t) = e^{j\beta t^2}$ ;  $y(t) = x(t - \tau) = e^{j\beta(t - \tau)^2}$ ; and/or  $y(t)x^*(t) = e^{-j2\pi\beta\tau t} e^{j\beta\tau^2}$  may be determined based on the parameters of the FMCW waveform, where x corresponds to a transmitted chirp signal, y corresponds to a received chirp signal, t corresponds to time, j corresponds to  $\sqrt{-1}$ , and  $\tau$  corresponds to a delay between a transmitted chirp and a received chirp. That is, three different frequency analyses may be performed to determine range, velocity, and/or direction.

(49) FIG. 4 is a block diagram of a first wireless device **410** having components for wireless transmission. The wireless device **410** may be a radar device (e.g., similar to the radar device **103**) configured to perform the aspects presented herein, or the wireless device may include a radar device **103**. For example, the first wireless device **410** may support wireless communication and the transmission and reception of radar signals. In some examples, the wireless device **410** may be capable of communication with another wireless device **450**, e.g., based on sidelink and/or an access link, such as described in connection with FIG. 1. The wireless device **410** may include one or more antennas **420** and may include a transmitter/receiver **418** with a corresponding transmit processor **416** and receive processor **470** that are configured to perform radar transmission and measurement, such as described in connection with FIGS. 2-3. The one or more antenna **420**, transmitter/receiver **418**, transmit processor **416**, and receive processor **470** may transmit a radar signal and receive reflections of the radar signal. The controller/processor **475** may determine radio frequency (RF) sensing information about a target based on the received signal. The transmit processor **416** and the receive processor **470** may be in communication with a channel estimator **474**.

(50) In some examples, the wireless device **410** may be capable of wireless communication in addition to RF sensing. For communication, packets may be provided to a controller/processor **475**. The controller/processor **475** implements layer 3 and layer 2 functionality. The transmit (TX) processor **416** and the receive (RX) processor **470** implement layer 1 functionality associated with various signal processing functions. Different spatial streams may be provided to a different antenna **420** via a separate transmitter TX. Each transmitter TX may modulate an RF carrier with a respective spatial stream for transmission.

(51) At the wireless device **450**, each receiver **454** RX receives a signal through its respective antenna **452**. Each receiver **454** RX recovers information modulated onto an RF carrier and provides the information to the receive (RX) processor **456**. The TX processor **468** and the RX processor **456** implement layer 1 functionality associated with various signal processing functions.

The RX processor **456** may perform spatial processing on the information to recover any spatial streams destined for the wireless device **450**. If multiple spatial streams are destined for the wireless device **450**, they may be combined by the RX processor **456** into a single stream, such as an OFDM symbol stream. The RX processor **456** may convert the OFDM symbol stream from the time-domain to the frequency domain using a Fast Fourier Transform (FFT). The frequency domain signal may comprise a separate OFDM symbol stream for each subcarrier of the OFDM signal. The symbols on each subcarrier, and the reference signal, are recovered and demodulated by determining the most likely signal constellation points transmitted by the wireless device **410**. These soft decisions may be based on channel estimates computed by the channel estimator **458**. The soft decisions may then be decoded and deinterleaved to recover the data and control signals that were originally transmitted by the wireless device **410** on the physical channel. The data and control signals may then be provided to the controller/processor **459**, which implements layer 3 and layer 2 functionality.

(52) The controller/processor **459** can be associated with a memory **460** that stores program codes and data. The memory **460** may be referred to as a computer-readable medium. The controller/processor **459** may provide demultiplexing between transport and logical channels, packet reassembly, deciphering, header decompression, and control signal processing to recover IP packets from the EPC **160**. The controller/processor **459** may also be responsible for error detection using an ACK and/or NACK protocol to support HARQ operations.

(53) Channel estimates derived by a channel estimator **458** from a reference signal or feedback transmitted by the wireless device may be used by the TX processor **468** to select the appropriate coding and modulation schemes, and to facilitate spatial processing. The spatial streams generated by the TX processor **468** may be provided to different antenna **452** via separate transmitters **454TX**. Each transmitter **454TX** may modulate an RF carrier with a respective spatial stream for transmission.

(54) The received transmission may be processed at the wireless device **410** in a manner similar to that described in connection with the receiver function at the wireless device **450**. Each receiver RX receives a signal through its respective antenna **420**. Each receiver RX recovers information modulated onto an RF carrier and provides the information to a RX processor **470**.

(55) The controller/processor **475** can be associated with a memory **476** that stores program codes and data. The memory **476** may be referred to as a computer-readable medium. In the UL, the controller/processor **475** provides demultiplexing between transport and logical channels, packet reassembly, deciphering, header decompression, control signal processing to recover packets from the wireless device **450**. The controller/processor **475** may also be responsible for error detection using an ACK and/or NACK protocol to support HARQ operations.

(56) At least one of the TX processor **416**, the RX processor **470**, or the controller/processor **475** may be configured to perform aspects in connection with the radar signal sensing component **198** of FIG. 1 to adjust a radar transmission based on a congestion level in a wireless communication environment.

(57) At least one of the TX processor **468**, the RX processor **456**, or the controller/processor **459** may be configured to perform aspects in connection with the congestion indicator component **199** of FIG. 1 to reduce congestion in a wireless communication environment.

(58) FIGS. 5A-5B illustrate range spectrum diagrams **500-550**. If transmitted signals of a radar and an interferer (e.g. a radar component associated with the vehicle **202** and the separate radar device **204**) sweep the frequency in a same direction, interference received by the radar may cause a false peak (e.g., "ghost target") to be indicated on the range spectrum. For example, a target may be indicated as a peak on the diagram **500** based on a received signal (of the radar device's own radar signal) reflected from the target. A false peak may occur when the radar device receives a signal from a different device (e.g., a different radar device, sensing device, etc.) rather than its own reflected signal. However, because an interferer signal may be indistinguishable from a signal of

the intended target, the peak may correspond to the interferer/false target.

(59) If transmitted signals of the radar and the interferer sweep the frequency in opposite directions, interference received by the radar may cause wideband noise to be indicated on the range spectrum. For example, the interferer may utilize different chirps, such as for sweeping down the frequency while the radar is sweeping up the frequency in an opposite sweeping direction. In such cases, the interferer may be indicated as wideband noise, as illustrated in the diagram 550. Regardless of whether the interference is indicated as a peak or as wideband noise, the interference may be severe enough that the intended target may not be detectable. For instance, a level of wideband noise may correspond to  $-85$  dB, while the intended target may correspond to a lower dB level, such as  $-100$  dB.

(60) The radar may transmit a series of pulses into an environment for which the radar may already have information indicative of intended targets and/or clutter located in a field of view (FOV) of the radar. For example, the radar may have such information for performing tracking operations. By identifying the false peaks and/or measuring the noise level, the radar may determine a portion of the received power that is not associated with a return signal of the radar. The congestion level may also be determined based on the portion of the received power that is not associated with the return signal of the radar. Additionally, or alternatively, the radar may pause operations and “listen” for signals from other radar signal transmitters. Radar signals received (e.g., from the other radar signal transmitters) during the paused operations of the radar may be indicative of the congestion level.

(61) FIG. 6 is a diagram 600 that illustrates parameter adjustments to reduce a range of a radar, according to one example. The radar may be utilized by a vehicle to perform collision avoidance techniques based on detection of objects, such as other vehicles, pedestrians, etc., in proximity to the radar/vehicle. In a congested environment (e.g., an environment having other radar devices transmitting interfering radar signals), detection of closer objects/targets may be of higher priority than detection of objects/targets that are farther away. For instance, vehicle navigation techniques in urban environments may prioritize detection of objects that are 20 m away over detection of objects that are 200 m, as driving speeds may be slower in such environments. While objects that are far away may still be detected in some cases, the radar/vehicle may be configured to determine that detection of the far away objects may decrease in priority as the congestion level of radar signals in the environment increases. That is, detection of objects that are closer to the radar/vehicle may increase in priority as the congestion level increases.

(62) Congestion sensing by the radar/vehicle may be performed based on a content and a number of detected messages. In one example, a radar device associated with a vehicle may determine a congestion level based on content and/or a number of detected messages such as vehicle-to-vehicle (V2V) messages, vehicle-to-infrastructure (V2I) messages, and/or vehicle-to-everything (V2X) messages. In another example, a radar device may determine a congestion level based on content or an amount of sidelink messages. In other examples, the detected messages may be sidelink messages that are not associated with a vehicle or may be non-sidelink messages that provide information about other radar devices and/or radar congestion. The messages may be configured for other vehicles and devices to communicate with the radar/vehicle. The congestion level may be determined based on a number of messages received by the radar, which may be further indicative of a number of target objects in proximity to the radar/vehicle. For example, a UE being carried by a pedestrian may be configured to periodically transmit location information that may be received by the vehicle and indicate a location of the pedestrian with respect to the vehicle.

(63) Based on vehicle message channels, infrastructure such as a base station may also communicate with the radar/vehicle. In examples, communications received from the base station may be based on messages transmitted by other devices, such as the UE carried by the pedestrian. The infrastructure may provide an indication of the congestion level to the vehicle when the infrastructure determines that there is a threshold level of congestion in proximity to the vehicle.



(64) Additionally, congestion sensing may be performed by the radar based on interference determined from a false peak or an increased noise floor on a range spectrum. In examples, location tracking information may be utilized together with interference information to perform the congestion sensing. In less congested environments, a radar image may be associated with a nominal noise floor. For example, some targets may be determined based on the radar image, which may or may not include a nominal amount of interference. However, in higher congestion environments, the noise floor may be increased, which may correspond to more targets on the radar image and/or a high level of interference. Hence, the congestion level of the environment may be determined by the radar/vehicle based on the radar image.

(65) As long as radar signal transmissions are configured to be adapted based on a congestion measure or a congestion indicator, the technique that is used for determining the congestion level may vary. After the congestion level is determined to exceed a defined threshold based on a congestion sensing technique, a detection range of the radar waveform may be reduced, which may thereby provide decreased interference. The congestion level exceeding the defined threshold may indicate that detection of longer range objects in a field of view may be of decreased priority, and that the detection range of the radar may be decreased to prioritize detection of shorter range objects.

(66) A maximum detectable range ( $R_{sub,max}$ ) may be determined based on parameters such as the speed of light ( $c$ ), a bandwidth ( $B$ ) that is swept by the radar (e.g., 1 GHz, 500 MHz, etc.), a sweeping up time ( $T_{sub,up}$ ), and a sampling frequency ( $f_{sub,s}$ ). That is,  $R_{sub,max} = (c/2B)T_{sub,up}f_{sub,s}$ . The maximum detectable range may be decreased by decreasing  $T_{sub,up}$ . For example, as indicated in the diagram **600**, if  $T_{sub,up}$  is decreased by half without adjusting the bandwidth or the sampling frequency,  $R_{sub,max}$  may likewise be decreased by half.

(67) In a field of view having a shortened detection range, the radar may be configured to detect a same velocity as detectable for the field of view having the longer detection range. That is,  $V_{sub,max} = c/(4f_{sub,c}T_{sub,c})$ . The carrier frequency ( $f_{sub,c}$ ) and the chirp time ( $T_{sub,c}$ ) may remain unchanged. By reducing  $T_{sub,up}$ , a duration of the transmitted pulse may be shortened but the radar may continue to transmit further chirps based on  $T_{sub,c}$ . Therefore, discontinuous transmission (DTX) between the chirps is increased and, based on the increased DTX, the likelihood of interference may be decreased, thus decreasing the interference level.

(68) Further, the transmit power ( $P_{sub,tx}$ ) used to overcome a path loss of the radar signal for realizing a defined receive power ( $P_{sub,rx}$ ) may be reduced based on the shortened range of the field of view. That is, a maximum path loss may become smaller as the range of the field of view is decreased. Thus, decreasing the transmit power may provide decreased interference. For example,  $P_{sub,rx} = P_{sub,tx} + G_{sub,tx} + G_{sub,rx} + RCS - 30 \log_{10}(4\pi) - 40 \log_{10} R$ , where  $G_{sub,tx}$  corresponds to a transmit gain,  $G_{sub,rx}$  corresponds to a receive gain, RCS corresponds to a radar cross section, and  $R$  corresponds to a range of the radar.

(69) FIGS. 7A-7B illustrate diagrams **700-750** corresponding to different ranges of a field of view of a radar. For example, the diagram **700** corresponds to a longer range for the field of view and the diagram **750** corresponds to a shorter range for the field of view. The shorter time duration for each chirp or pulse in FIG. 7B corresponds to a shorter range for the field of view of the radar device. The radar may detect the congestion level based on a number of devices/transmitted signals in proximity to the radar. If the congestion level exceeds a threshold, the radar may reduce the maximum detection range (e.g., of the diagram **700**) by reducing the sweeping up time ( $T_{sub,up}$ ). Hence, a larger DTX may be provided between pulses (e.g., to provide the diagram **750**). The transmit power may also be reduced based on reducing the maximum detection range.

(70) By shortening the range of the field of view, the radar may prioritize detection of closer objects without impacting detection of a speed or a direction of the objects. That is, only the range of the radar is reduced for reducing interference and increase detection of the closer objects. Shortening the range of the field of view may also cause the radar to generate less interference to

other devices in proximity to the radar.

(71) Accordingly, a radar signal may be adapted based on detection of congestion in a wireless communication environment. For example, short-distance radar may be more reliable in congested environments. Thus, a radar node may adjust one or more parameters of the radar signal for short range sensing, such as by reducing the chirp length and/or the transmit power.

(72) FIG. 8 is a flowchart 800 of a method of wireless communication at a wireless device. The wireless device may be the radar device 103, 204; the vehicle 202; and/or an apparatus 1202 (e.g., a vehicular radar or a non-vehicular radar). The method may be performed to reduce interference at or by the wireless device.

(73) At 802, the wireless device may detect a congestion level of a wireless communication environment that includes the wireless device—the wireless device having at least one of a first FOV or a first range within the wireless communication environment. For example, referring to FIGS. 1 and 7, the radar device 103 may detect congestion via communication with a UE 104, which may be an RSU or another radar device, measuring the wireless communication environment (e.g., via wireless signal 105), etc. The diagram 700 illustrates a longer range for a FOV (e.g., first FOV and first range of the radar device 103/204). The detection, at 802, may be performed by the detection component 1240 of the apparatus 1202 in FIG. 12.

(74) At 804, the wireless device may transmit, based on the congestion level exceeding a threshold, a radar signal that correspond to the wireless device having at least one of a second FOV or a second range within the wireless communication environment, the at least one of the second FOV or the second range being smaller than the at least one of the first FOV or the first range. For example, referring to FIGS. 1-2 and 7, the radar device 103/204 may transmit the radar signal 105 that corresponds to the shorter range FOV illustrated in the diagram 750, rather than the longer range FOV illustrated in the diagram 700. The at least one of the second FOV or the second range (e.g., illustrated in the diagram 750) that is smaller than the at least one of the first FOV or the first range (e.g., illustrated in the diagram 700) may increase a detection accuracy of the radar device 103/204 for one or more targets 107/206a in the wireless communication environment. The transmission, at 804, may be performed by the transmission component 1234 of the apparatus 1202 in FIG. 12.

(75) FIG. 9 is a flowchart 900 of a method of wireless communication at a wireless device. The wireless device may be the radar device 103, 204; the vehicle 202; and/or an apparatus 1202 (e.g., a vehicular radar or a non-vehicular radar). The method may be performed to reduce interference at or by the wireless device.

(76) At 902a, the wireless device may receive one or more sidelink messages from one or more sidelink devices, wherein the detection of the congestion level being based on an amount of sidelink messages received by the wireless device. For example, referring to FIG. 1, certain UEs 104, which may include the radar device 103, may communicate with each other using the D2D communication link 158 via one or more sidelink channels. The reception, at 902a, may be performed by the reception component 1230 of the apparatus 1202 in FIG. 12.

(77) At 902a, the wireless device may receive one or more sidelink messages from one or more sidelink devices, wherein the detection of the congestion level is based on an amount of sidelink messages received by the wireless device. For example, referring to FIG. 1, certain UEs 104, which may include the radar device 103, may communicate with each other using the D2D communication link 158 via one or more sidelink channels. The reception, at 902a, may be performed by the reception component 1230 of the apparatus 1202 in FIG. 12.

(78) At 902c, the wireless device may additionally or alternatively receive a message that indicates, to the wireless device, the congestion level of the wireless communication environment—the wireless device detects the congestion level based on the message. For example, referring to FIG. 1, certain UEs 104, which may include the radar device 103, may communicate with each other using the D2D communication link 158 via one or more sidelink channels. In aspects, the message

may be received from at least one of a base station **102** or a sidelink device, such as the UE **104**/RSU. The reception, at **902c**, may be performed by the reception component **1230** of the apparatus **1202** in FIG. **12**.

(79) At **904**, the wireless device may (e.g., based on any of **902a-902c**) detect a congestion level of a wireless communication environment that includes the wireless device—the wireless device has at least one of a first FOV or a first range within the wireless communication environment. For example, referring to FIGS. **1** and **7**, the radar device **103** may detect congestion via communication with a UE **104**, which may be an RSU or another radar device, measuring the wireless communication environment (e.g., via wireless signal **105**), etc. The diagram **700** illustrates a longer range for a FOV (e.g., first FOV and first range of the radar device **103/204**). The wireless device (e.g., radar device **103**) may be a vehicular radar or a non-vehicular radar. The detection, at **904**, may be performed by the detection component **1240** of the apparatus **1202** in FIG. **12**. The at least one of the second FOV or the second range that is smaller than the at least one of the first FOV or the first range may correspond to at least one of a first decrease in interference associated with the transmitted radar signal or a second decrease in interference associated with the received reflection of the radar signal.

(80) At **906**, the wireless device may adjust one or more parameters of a radar signal to transmit the radar signal that corresponds to the wireless device having at least one of a second FOV or a second range that is smaller than the at least one of the first FOV or the first range. For example, the wireless device may decrease the at least one of the first FOV or the first range to the at least one of the second FOV or the second range. The wireless device may increase a DTX time between chirps, pulses, or transmissions of the radar signal. For example, referring to FIGS. **1-2** and **6-7**, the diagram **600** illustrates parameter adjustments for decreasing a range of the radar device **103**. The diagram **750** illustrates a shorter range for a FOV (e.g., second FOV and second range of the radar device **103/204**) that is smaller than the longer range for the FOV (e.g., first FOV and first range of the radar device **103/204**) illustrated in the diagram **700**. Based on the diagram **600**, the one wireless device may decrease a sweeping up time (T.sub.up) of the radar signal transmitted by the radar device **103/204**. The wireless device may decrease a transmit power (P.sub.tx) of the radar signal **105** transmitted by the radar device **103/204**. The P.sub.tx may correspond to a decreased path loss of the radar signal **105** transmitted by the radar device **103/204**. The adjustment, at **906**, may be performed by the transmission component **1234** of the apparatus **1202** in FIG. **12**.

(81) At **908**, the wireless device may transmit, based on the congestion level exceeding a threshold, a radar signal that correspond to the wireless device having at least one of the second FOV or the second range in the wireless communication environment that is smaller than the at least one of the first FOV or the first range. For example, referring to FIGS. **1-2** and **7**, the radar device **103/204** may transmit the radar signal **105** that corresponds to the shorter range FOV illustrated in the diagram **750**, rather than the longer range FOV illustrated in the diagram **700**. The at least one of the second FOV or the second range (e.g., illustrated in the diagram **750**) that is smaller than the at least one of the first FOV or the first range (e.g., illustrated in the diagram **700**) may increase a detection accuracy of the radar device **103/204** for one or more targets **107/206a** in the wireless communication environment. The transmission, at **908**, may be performed by the transmission component **1234** of the apparatus **1202** in FIG. **12**.

(82) At **910**, the wireless device may receive a reflection of the radar signal based on the one or more parameters. For example, referring to FIGS. **1-2** and **6**, the radar device **103/204** may receive a reflected signal from the target **206a** (e.g., based on the parameters illustrated in the diagram **600**). The at least one of the second FOV or the second range (e.g., illustrated in the diagram **750**) that is smaller than the at least one of the first FOV or the first range (e.g., illustrated in the diagram **700**) may correspond to at least one of a first decrease in interference of the radar signal **105** transmitted by the radar device **103/204** or a second decrease in interference to the reflection of the radar signal received at the radar device **204**. The interference may be decreased based on an

increase to a DTX time between chirps of the radar device **103/204**. The reception, at **910**, may be performed by the reception component **1230** of the apparatus **1202** in FIG. **12**.

(83) FIG. **10** is a flowchart **1000** of a method of wireless communication at a second wireless device. The second wireless device may be the UE **104**, the base station **102**, the false target **206b**; and/or an apparatus **1202** (e.g., a vehicular/non-vehicular radar, a roadside unit (RSU), etc.). The method may be performed to reduce congestion in a wireless environment.

(84) At **1002**, the second wireless device may measure a congestion level of a wireless communication environment that includes a first wireless device—the first wireless device has at least one of a first FOV or a first range within the wireless communication environment. For example, referring to FIGS. **1** and **7**, the UE **104** measure radar signals, such as the radar signal **105** of the radar device **103** to determine a congestion level in a wireless communication environment. The diagram **700** illustrates that the radar device **103** may have a longer range for the FOV (e.g., first FOV and first range of the radar device **103**). The measurement, at **1002**, may be performed by the measurement component **1246** of the apparatus **1202** in FIG. **12**.

(85) At **1004**, the second wireless device may transmit a message to the first wireless device based on the congestion level—the message being associated with the first wireless device having at least one of a second FOV or a second range in the wireless communication environment that is smaller than the at least one of the first FOV or the first range. For example, referring to FIGS. **1** and **7**, the UE **104**, which may correspond to an RSU or other sidelink device, may communicate with the radar device **103** using the D2D communication link **158** via one or more sidelink channels. The communication may be associated with at least one of the second FOV or the second range (e.g., illustrated in the diagram **750**) that is smaller than the at least one of the first FOV or the first range (e.g., illustrated in the diagram **700**). The transmission, at **1004**, may be performed by the transmission component **1234** of the apparatus **1202** in FIG. **12**. For example, the message may include one or more parameters relating to a decrease in the at least one FOV or the first range to the second FOV or the second range.

(86) FIG. **11** is a flowchart **1100** of a method of wireless communication at a wireless device. The wireless device may be the radar device **103**, **204**; the vehicle **202**; and/or an apparatus **1202** (e.g., a vehicular radar or a non-vehicular radar). The method may be performed to reduce interference at or by the wireless device.

(87) At **1102**, the wireless device may receive one or more sidelink messages from one or more sidelink devices in a radar detection range of a wireless device for determining a congestion level corresponding to an amount of sidelink messages received by the wireless device. The reception may be performed, e.g., by the reception component **1230** of the RF baseband processor **1204** in the apparatus **1202**. For example, referring to FIG. **1**, certain UEs **104**, which may include the radar device **103**, may communicate with each other using the D2D communication link **158** via one or more sidelink channels. An interference/congestion level within a range of the wireless signal **105** may be determined based on a number of communications received by the UE **104**/radar device **103** over the D2D communication link **158**.

(88) At **1104**, the wireless device may receive radar signal information that does not correspond to a radar signal of the wireless device to determine the congestion level based on the radar signal information. For example, referring to FIGS. **1** and **5**, the radar device **103** may determine the interference/congestion level based on a peak and/or wideband noise in a range spectrum (e.g., range spectrum diagrams **500-550**), where the peak and/or the wideband noise may be associated with radar signals of other radar signal transmitters. The reception may be performed, e.g., by the reception component **1230** of the RF baseband processor **1204** of the apparatus **1202**.

(89) At **1106**, the wireless device may receive a message indicating the congestion level for determining the congestion level from the message. For example, referring to FIG. **1**, certain UEs **104**, which may include the radar device **103**, may receive a message from another device via a Uu communication link **120** and/or the D2D communication link **158**. The UE **104**/radar device **103**

may determine the congestion level based on the received message. In examples, the message may be received from a base station **102/180** or a sidelink device (e.g., a second UE **104**). The reception may be performed, e.g., by the reception component **1230** of the RF baseband processor **1204** of the apparatus **1202**.

(90) At **1108**, the wireless device may determine the congestion level of a wireless communication environment surrounding the wireless device, the wireless communication environment associated with a first area. For example, referring to FIGS. **1** and **5**, the radar device **103** may determine the interference/congestion level in at least a first portion of the access network environment that surrounds the radar device **103**, e.g., based on a peak and/or wideband noise in the range spectrum diagrams **500-550**. The determination may be performed, e.g., by the detection component **1240** of the RF sensing manager **1232** of the apparatus **1202**.

(91) At **1110**, the wireless device may decrease the radar detection range of the wireless device if the congestion level exceeds a threshold, the decreased detection range associated with a second area that is smaller than the first area. The reduction may be performed, e.g., by the range reduction component **1242** of the RF sensing manager **1232** of the apparatus **1202**. For example, referring to FIGS. **1** and **5-6**, the radar device **103** may shorten a range of the field of view in accordance with the diagram **750** based on the peak and/or the wideband noise exceeding a threshold dB indicative of a threshold congestion level in the range spectrum diagrams **500-550**. The decreased range of the diagram **750** may correspond to at least a second portion of the access network environment that surrounds the radar device **103**. The detection range of the wireless device (e.g., radar device **103**) may be decreased based on reducing a sweeping up time ( $T_{sub.up}$ ) (e.g., as indicated via the diagrams **600** and **750**) of the radar signal **105** emitted by the wireless/radar device **103**. The decreased radar detection range (e.g., indicated via the diagrams **600** and **750**) may reduce interference caused by one or more sensor signals **105** emitted by the one or more other devices (e.g., UEs **104** and/or base station **102/180**). The interference may be reduced based on an increased DTX time between chirps ( $T_{sub.c}$ ) of the wireless device/radar device **103**, as illustrated in the diagram **750**. The decreased detection range (e.g., associated with the diagram **750**) may increase detection of a target object in the second area of the access network that is smaller than the first area of the access network.

(92) At **1112**, the wireless device may reduce a transmit power ( $P_{sub.tx}$ ) of a radar signal for the decreased detection range of the wireless device. The reduction may be performed, e.g., by the transmission power reduction component **1244** of the RF sensing manager **1232** of the apparatus **1202**. For example, referring to FIGS. **1** and **6-7**, the radar device **103** may reduce the  $P_{sub.tx}$  of the radar signal **105** based on the diagram **600** to decrease a range of a field of view of the radar device **103**, as indicated via the diagrams **700-750**. The reduced  $P_{sub.tx}$  may be associated with a reduced path loss, as indicated via the diagram **600**, for the radar signal **105** emitted by the wireless/radar device **103**.

(93) At **1114**, the wireless device may transmit the radar signal having one or more adjusted parameters based on the decreased radar detection range. For example, referring to FIGS. **1** and **6-7**, the radar device **103** may transmit the wireless signal **105** based on the parameters indicated via the diagram **600** to shorten the range of the field of view, as illustrated via the diagram **750**. The transmission may be performed, e.g., by the transmission component **1234** of the apparatus **1202**.

(94) At **1116**, the wireless device may receive a reflection of the radar signal to perform radar detection. For example, referring to FIG. **2**, the vehicle **202** may receive a reflected signal to detect a target **206a**. The reception may be performed, e.g., by the reception component **1230** of the RF baseband processor **1204** of the apparatus **1202**.

(95) FIG. **12** is a diagram **1200** illustrating an example of a hardware implementation for an apparatus **1202**. The apparatus **1202** is a radar signal sensing device and includes an RF baseband processor **1204** (also referred to as a modem) coupled to an RF transceiver **1222** and a radar component **1224**, such as a radar transceiver. In some examples, the apparatus may be capable of

wireless communication in addition to radar signal sensing. For example, the apparatus may be a radar device, a UE, a base station, or another access point that is capable of radar signal sensing. If the radar signal sensing device is a UE, the processor may be coupled to one or more subscriber identity modules (SIM) cards **1220**, an application processor **1206** coupled to a secure digital (SD) card **1208** and a screen **1210**, a Bluetooth module **1212**, a wireless local area network (WLAN) module **1214**, a Global Positioning System (GPS) module **1216**, and a power supply **1218**. The RF baseband processor **1204** communicates through the RF transceiver **1222** and/or the radar component **1224** with the UE **104** and/or BS **102/180**. The RF baseband processor **1204** may include a computer-readable medium/memory. The computer-readable medium/memory may be non-transitory. The RF baseband processor **1204** is responsible for general processing, including the execution of software stored on the computer-readable medium/memory. The software, when executed by the RF baseband processor **1204**, causes the RF baseband processor **1204** to perform the various functions described supra. The computer-readable medium/memory may also be used for storing data that is manipulated by the RF baseband processor **1204** when executing software. The RF baseband processor **1204** further includes a reception component **1230**, an RF sensing manager **1232**, and a transmission component **1234**. The RF sensing manager **1232** includes the one or more illustrated components. The components within the RF sensing manager **1232** may be stored in the computer-readable medium/memory and/or configured as hardware within the RF baseband processor **1204**. The RF baseband processor **1204** may be a component of the wireless device **450** and may include the memory **460** and/or at least one of the TX processor **468**, the RX processor **456**, and the controller/processor **459**. In one configuration, the apparatus **1202** may be a modem chip and include just the RF baseband processor **1204**, and in another configuration, the apparatus **1202** may be the entire RF sensing device (e.g., radar device **103**) and include the additional modules of the apparatus **1202**.

(96) The reception component **1230** may be configured, e.g., as described in connection with **1102**, **1104**, **1106**, and **1116**, to receive one or more sidelink messages from one or more sidelink devices in a radar detection range of a wireless device for determining a congestion level corresponding to an amount of sidelink messages received by the wireless device; to receive radar signal information that does not correspond to a radar signal of the wireless device to determine the congestion level based on the radar signal information; to receive a message indicating the congestion level for determining the congestion level from the message; and to receive a reflection of the radar signal to perform radar detection. The RF sensing manager **1232** may include a detection component **1240** that is configured, e.g., as described in connection with **1108**, to determine the congestion level of a wireless communication environment surrounding the wireless device, the wireless communication environment associated with a first area. The RF sensing manager **1232** may further include a range reduction component **1242** that is configured, e.g., as described in connection with **1110**, to decrease the radar detection range of the wireless device if the congestion level exceeds a threshold, the decreased detection range associated with a second area that is smaller than the first area. The RF sensing manager **1232** may further include a transmission power reduction component **1244** that is configured, e.g., as described in connection with **1112**, to reduce a transmit power (P.sub.tx) of a radar signal for the decreased detection range of the wireless device. The transmission component **1234** may be configured, e.g., as described in connection with **1114**, to transmit the radar signal having one or more adjusted parameters based on the decreased radar detection range.

(97) In further aspects, the reception component **1230** may be configured, e.g., as described in connection with **902a**, **902c**, and **910**, to receive one or more sidelink messages from one or more sidelink devices—the wireless device detects the congestion level based on an amount of sidelink messages received by the wireless device; to receive a message that indicates, to the wireless device, the congestion level of the wireless communication environment—the wireless device detects the congestion level based on the message; and to receive a reflection of the radar signal

based on the one or more parameters. The RF sensing manager **1232** may further include a measurement component **1246** that is configured, e.g., as described in connection with **902b**, to measure the congestion level based on one or more other radar signals received by the wireless device that do not correspond to the radar signal transmitted by the wireless device—the wireless device detects the congestion level based on measuring the one or more other radar signals. The RF sensing manager **1232** may further include a detection component **1240** that is configured, e.g., as described in connection with **802** and **904**, to detect a congestion level of a wireless communication environment that includes the wireless device—the wireless device has at least one of a first FOV or a first range within the wireless communication environment. The transmission component **1234** may be configured, e.g., as described in connection with **804**, **906**, and **908**, to adjust one or more parameters of a radar signal to transmit the radar signal that corresponds to the wireless device having at least one of a second FOV or a second range that is smaller than the at least one of the first FOV or the first range; and to transmit, based on the congestion level exceeding a threshold, a radar signal that correspond to the wireless device having at least one of the second FOV or the second range in the wireless communication environment that is smaller than the at least one of the first FOV or the first range.

(98) In further aspects, the RF sensing manager **1232** may further include a measurement component **1246** that is configured, e.g., as described in connection with **1002**, to measure a congestion level of a wireless communication environment that includes a first wireless device—the first wireless device has at least one of a first FOV or a first range within the wireless communication environment. The transmission component **1234** may be configured, e.g., as described in connection with **1004**, to transmit a message to the first wireless device based on the congestion level—the message is associated with the first wireless device having at least one of a second FOV or a second range in the wireless communication environment that is smaller than the at least one of the first FOV or the first range.

(99) The apparatus may include additional components that perform each of the blocks of the algorithm in the aforementioned flowcharts of FIGS. **8-11**. As such, each block in the aforementioned flowcharts of FIGS. **8-11** may be performed by a component and the apparatus may include one or more of those components. The components may be one or more hardware components specifically configured to carry out the stated processes/algorithm, implemented by a processor configured to perform the stated processes/algorithm, stored within a computer-readable medium for implementation by a processor, or some combination thereof.

(100) In one configuration, the apparatus **1202**, and in particular the RF baseband processor **1204**, includes means for determining a congestion level of a wireless communication environment surrounding the wireless device, the wireless communication environment associated with a first area (e.g., at least the detection component **1240** of the RF sensing manager **1232**); and means for decreasing a radar detection range of the wireless device if the congestion level exceeds a threshold, the decreased detection range associated with a second area that is smaller than the first area (e.g., at least the range reduction component **1242**). The apparatus **1202** may further include means for transmitting a radar signal having one or more adjusted parameters based on the decreased radar detection range (e.g., at least the transmission component **1234** and/or RF transceiver); and means for receiving a reflection of the radar signal to perform radar detection (e.g., at least the reception component **1230**, the RF transceiver **1222**, and/or the radar component **1224**). The apparatus **1202** may further include means for reducing a transmit power ( $P_{sub.tx}$ ) of a radar signal for the decreased detection range of the wireless device (e.g., at least the transmission power reduction component **1244**). The apparatus **1202** may further include means for receiving one or more sidelink messages from one or more sidelink devices in the radar detection range of the wireless device, wherein the wireless device determines the congestion level corresponding to an amount of sidelink messages received by the wireless device (e.g., at least the reception component **1230**). The apparatus **1202** may further include means for transmitting a radar signal,

wherein the wireless device determines the congestion level based on a return signal from one or more reflections of the radar signal (e.g., at least the transmission component **1234**). The apparatus **1202** may further include means for receiving a message indicating the congestion level, wherein the wireless device determines the congestion level from the message (e.g., at least the reception component **1230**).

(101) In another configuration, the apparatus **1202**, and in particular the RF baseband processor **1204**, includes means for detecting a congestion level of a wireless communication environment that includes the wireless device, the wireless device having at least one of a first FOV or a first range within the wireless communication environment; and means for transmitting, based on the congestion level exceeding a threshold, a radar signal that correspond to the wireless device having at least one of a second FOV or a second range within the wireless communication environment that is smaller than the at least one of the first FOV or the first range. The apparatus **1202** may further include means for adjusting one or more parameters of the radar signal to transmit the radar signal that corresponds to the wireless device having the at least one of the second FOV or the second range, the at least one of the second FOV or the second range being smaller than the at least one of the first FOV or the first range; and means for receiving a reflection of the radar signal based on the one or more parameters. The apparatus **1202** may further include means for receiving one or more sidelink messages from one or more sidelink devices, wherein the wireless device detects the congestion level based on an amount of sidelink messages received by the wireless device. The apparatus **1202** may further include means for measuring the congestion level based on one or more other radar signals received by the wireless device that do not correspond to the radar signal transmitted by the wireless device, wherein the wireless device detects the congestion level based on measuring the one or more other radar signals. The apparatus **1202** may further include means for receiving a message that indicates, to the wireless device, the congestion level of the wireless communication environment, wherein the wireless device detects the congestion level based on the message.

(102) In another configuration, the apparatus **1202**, and in particular the RF baseband processor **1204**, includes means for measuring a congestion level of a wireless communication environment that includes a first wireless device, the first wireless device having at least one of a first FOV or a first range within the wireless communication environment; and means for transmitting a message to the first wireless device based on the congestion level, the message associated with the first wireless device having at least one of a second FOV or a second range in the wireless communication environment that is smaller than the at least one of the first FOV or the first range.

(103) The aforementioned means may be one or more of the aforementioned components of the apparatus **1202** configured to perform the functions recited by the aforementioned means. As described supra, the apparatus **1202** may include the TX Processor **468**, the RX Processor **456**, and the controller/processor **459**. As such, in one configuration, the aforementioned means may be the TX Processor **468**, the RX Processor **456**, and the controller/processor **459** configured to perform the functions recited by the aforementioned means.

(104) It is understood that the specific order or hierarchy of blocks in the processes/flowcharts disclosed is an illustration of example approaches. Based upon design preferences, it is understood that the specific order or hierarchy of blocks in the processes/flowcharts may be rearranged. Further, some blocks may be combined or omitted. The accompanying method claims present elements of the various blocks in a sample order, and are not meant to be limited to the specific order or hierarchy presented.

(105) The previous description is provided to enable any person skilled in the art to practice the various aspects described herein. Various modifications to these aspects will be readily apparent to those skilled in the art, and the generic principles defined herein may be applied to other aspects. Thus, the claims are not intended to be limited to the aspects shown herein, but is to be accorded the full scope consistent with the language claims, wherein reference to an element in the singular



is not intended to mean “one and only one” unless specifically so stated, but rather “one or more.” Terms such as “if,” “when,” and “while” should be interpreted to mean “under the condition that” rather than imply an immediate temporal relationship or reaction. That is, these phrases, e.g., “when,” do not imply an immediate action in response to or during the occurrence of an action, but simply imply that if a condition is met then an action will occur, but without requiring a specific or immediate time constraint for the action to occur. The word “exemplary” is used herein to mean “serving as an example, instance, or illustration.” Any aspect described herein as “exemplary” is not necessarily to be construed as preferred or advantageous over other aspects. Unless specifically stated otherwise, the term “some” refers to one or more. Combinations such as “at least one of A, B, or C,” “one or more of A, B, or C,” “at least one of A, B, and C,” “one or more of A, B, and C,” and “A, B, C, or any combination thereof” include any combination of A, B, and/or C, and may include multiples of A, multiples of B, or multiples of C. Specifically, combinations such as “at least one of A, B, or C,” “one or more of A, B, or C,” “at least one of A, B, and C,” “one or more of A, B, and C,” and “A, B, C, or any combination thereof” may be A only, B only, C only, A and B, A and C, B and C, or A and B and C, where any such combinations may contain one or more member or members of A, B, or C. All structural and functional equivalents to the elements of the various aspects described throughout this disclosure that are known or later come to be known to those of ordinary skill in the art are expressly incorporated herein by reference and are intended to be encompassed by the claims. Moreover, nothing disclosed herein is intended to be dedicated to the public regardless of whether such disclosure is explicitly recited in the claims. The words “module,” “mechanism,” “element,” “device,” and the like may not be a substitute for the word “means.” As such, no claim element is to be construed as a means plus function unless the element is expressly recited using the phrase “means for.”

(106) The following examples are illustrative only and may be combined with aspects of other examples or teachings described herein, without limitation.

(107) The following aspects are illustrative only and may be combined with other aspects or teachings described herein, without limitation.

(108) Aspect 1 is a method of wireless communication at a wireless device, including: detecting a congestion level of a wireless communication environment that includes the wireless device, the wireless device having at least one of a first field of view (FOV) or a first range within the wireless communication environment; and transmitting, based on the congestion level exceeding a threshold, a radar signal that corresponds to the wireless device having at least one of a second FOV or a second range within the wireless communication environment, the at least one of the second FOV or the second range being smaller than the at least one of the first FOV or the first range.

(109) Aspect 2 may be combined with aspect 1 and further includes performing an adjustment of one or more parameters associated with the radar signal to transmit the radar signal that corresponds to the wireless device having the at least one of the second FOV or the second range that is smaller than the at least one of the first FOV or the first range.

(110) Aspect 3 may be combined with any of aspects 1-2 and further includes receiving a reflection of the radar signal based on the one or more parameters.

(111) Aspect 4 may be combined with any of aspects 1-3 and includes decreasing a sweeping up time ( $T_{sub.up}$ ) of the radar signal based on the one or more parameters.

(112) Aspect 5 may be combined with any of aspects 1-4 and includes decreasing a transmit power ( $P_{sub.tx}$ ) of the radar signal transmitted by the wireless device.

(113) Aspect 6 may be combined with any of aspects 1-5 and includes that the  $P_{sub.tx}$  corresponds to a decreased path loss of the radar signal.

(114) Aspect 7 may be combined with any of aspects 1-6 and includes that the at least one of the second FOV or the second range that is smaller than the at least one of the first FOV or the first range corresponds to at least one of a first decrease in interference associated with the transmitted

radar signal or a second decrease in interference associated with the received reflection of the radar signal.

(115) Aspect 8 may be combined with any of aspects 1-7 and includes increasing a DTX time between chirps of the wireless device.

(116) Aspect 9 may be combined with any of aspects 1-8 and includes decreasing the at least one of the first FOV or the first range to the at least one of the second FOV or the second range.

(117) Aspect 10 may be combined with any of aspects 1-9 and further includes receiving one or more sidelink messages from one or more sidelink devices, wherein the detecting the congestion level being based on an amount of sidelink messages received by the wireless device.

(118) Aspect 11 may be combined with any of aspects 1-10 and includes that the wireless device detects the congestion level based on an amount of sidelink messages received by the wireless device.

(119) Aspect 12 may be combined with any of aspects 1-11 and further includes measuring the congestion level based on one or more other received radar signals that do not correspond to the transmitted radar signal transmitted by the wireless device.

(120) Aspect 13 may be combined with any of aspects 1-12 and includes that the wireless device detects the congestion level based on measuring the one or more other radar signals.

(121) Aspect 14 may be combined with any of aspects 1-13 and further includes receiving a message that indicates the congestion level of the wireless communication environment, the detecting the congestion level being based on the message.

(122) Aspect 15 may be combined with any of aspects 1-14 and includes that the wireless device detects the congestion level based on the message.

(123) Aspect 16 may be combined with any of aspects 1-15 and includes that the message is received from at least one of a base station or a sidelink device.

(124) Aspect 17 may be combined with any of aspects 1-16 and includes that the wireless device is a vehicular radar or a non-vehicular radar.

(125) Aspect 18 may be combined with any of aspects 1-17 and further includes performing the method based on at least one of an antenna or a transceiver.

(126) Aspect 19 is a method of wireless communication at a second wireless device, including: measuring a congestion level of a wireless communication environment that includes a first wireless device, the first wireless device having at least one of a first FOV or a first range within the wireless communication environment; and transmitting a message to the first wireless device based on the congestion level, the message associated with the first wireless device having at least one of a second FOV or a second range in the wireless communication environment that is smaller than the at least one of the first FOV or the first range.

(127) Aspect 20 may be combined with aspect 19 and includes that the message includes one or more parameters to decrease the at least one of the first FOV or the first range to the at least one of the second FOV or the second range.

(128) Aspect 21 may be combined with any of aspects 19-20 and further includes performing the method based on at least one of an antenna or a transceiver.

(129) Aspect 22 is an apparatus for wireless communication including memory and an at least one processor, the memory and the at least one processor configured to perform the method of any of aspects 1-18.

(130) In aspect 23, the apparatus of aspect 22 further includes at least one antenna and a transceiver coupled to the at least one antenna and the at least one processor.

(131) Aspect 24 is an apparatus for wireless communication including means for performing the method of any of aspects 1-18.

(132) In aspect 25, the apparatus of aspect 24 further includes at least one antenna and a transceiver coupled to the at least one antenna.

(133) Aspect 26 is a non-transitory computer-readable storage medium storing computer executable

code, the code when executed by at least one processor causes the at least one processor to perform the method of any of aspects 1-18.

(134) Aspect 27 is an apparatus for wireless communication including memory and an at least one processor, the memory and the at least one processor configured to perform the method of any of aspects 19-21.

(135) In aspect 28, the apparatus of aspect 27 further includes at least one antenna and a transceiver coupled to the at least one antenna and the at least one processor.

(136) Aspect 29 is an apparatus for wireless communication including means for performing the method of any of aspects 19-21.

(137) In aspect 30, the apparatus of aspect 29 further includes at least one antenna and a transceiver coupled to the at least one antenna.

(138) Aspect 31 is a non-transitory computer-readable storage medium storing computer executable code, the code when executed by at least one processor causes the at least one processor to perform the method of any of aspects 19-21.

## Claims

1. An apparatus for wireless communication at a wireless device, comprising: memory; and one or more processors coupled to the memory and configured to cause the wireless device to: transmit, for a first radar signal sensing that has a first range, a first radar signal that has a first chirp time and a first sweeping up time, wherein the first range is based on the first chirp time and the first sweeping up time; measure wireless signals of a wireless communication environment, wherein the wireless communication environment includes the wireless device; detect, based on the measured wireless signals, that a congestion level associated with the wireless communication environment exceeds a threshold congestion level; decrease, based on the detected congestion level that exceeds the threshold congestion level, one or more parameters for a second radar signal sensing, wherein the one or more decreased parameters comprise at least a second sweeping up time that is shorter than the first sweeping up time and a second range that is smaller than the first range; and transmit, for the second radar signal sensing, a second radar signal that has the first chirp time and the second sweeping up time.

2. The apparatus of claim 1, wherein the one or more processors are further configured to cause the wireless device to: receive a reflection of the second radar signal that has the first chirp time and the second sweeping up time.

3. The apparatus of claim 2, wherein the one or more decreased parameters comprise a transmit power ( $P_{sub.tx}$ ) associated with the second radar signal sensing.

4. The apparatus of claim 3, wherein the decreased  $P_{sub.tx}$  corresponds to a decreased path loss associated with the second radar signal sensing.

5. The apparatus of claim 2, wherein the second range that is smaller than the first range corresponds to at least one of a first decrease in first interference associated with the second radar signal sensing or a second decrease in second interference associated with the received reflection of the second radar signal.

6. The apparatus of claim 5, wherein the one or more decreased parameters comprises a pulse duration of the second radar signal that is associated with the second sweeping up time, wherein a discontinuous transmission (DTX) time between pulses associated with the second radar signal sensing is increased based on the pulse duration.

7. The apparatus of claim 1, wherein the one or more processors are further configured to cause the wireless device to: receive one or more sidelink messages from one or more sidelink devices, wherein the measured wireless signals of the wireless communication environment comprise the one or more sidelink messages, and wherein, to detect that the congestion level associated with the wireless communication environment exceeds the threshold congestion level, the one or more

processors are configured to cause the wireless device to detect the congestion level based on an amount of the one or more sidelink messages received from the one or more sidelink devices.

8. The apparatus of claim 1, wherein the measured wireless signals of the wireless communication environment comprise one or more other received radar signals that do not correspond to the transmitted first radar signal.

9. The apparatus of claim 1, wherein the one or more processors are further configured to cause the wireless device to: receive a message that indicates the congestion level associated with the wireless communication environment, and wherein, to detect that the congestion level associated with the wireless communication environment exceeds the threshold congestion level, the one or more processors are configured to cause the wireless device to detect the congestion level based on the message.

10. The apparatus of claim 9, wherein the message is from at least one of a network node or a sidelink device.

11. The apparatus of claim 1, wherein the wireless device is a vehicular radar or a non-vehicular radar, the apparatus further comprising: at least one antenna; and a transceiver coupled to the at least one antenna and the one or more processors.

12. The apparatus of claim 1, wherein to detect that the congestion level exceeds the threshold congestion level, the one or more processors are configured to cause the wireless device to detect the congestion level based on one or more of: a portion of a received power of the wireless signals that is not associated with a return signal of the first radar signal sensing, a false peak associated with a radar image based on the first radar signal sensing, or an increased noise floor on a range spectrum associated with the radar image.

13. An apparatus for wireless communication at a second wireless device, comprising: memory; and one or more processors coupled to the memory and configured to cause the second wireless device to: measure wireless signals of a wireless communication environment, wherein the wireless communication environment includes a first radar signal of a first wireless device, wherein the first radar signal is associated with a first chirp time and a first sweeping up time, wherein the first radar signal is associated with a first radar signal sensing that has a first range, and wherein the first range is based on the first chirp time and the first sweeping up time; detect, based on the measured wireless signals, that a congestion level of the wireless communication environment exceeds a threshold congestion level; and transmit, based on the detected congestion level that exceeds the threshold congestion level, a message to the first wireless device to decrease one or more parameters for a second radar signal sensing, the one or more parameters comprising at least a second sweeping up time that is shorter than the first sweeping up time and a second range that is smaller than the first range.

14. The apparatus of claim 13, wherein the message includes the one or more parameters.

15. A method of wireless communication at a wireless device, comprising: transmitting, for a first radar signal sensing that has a first range, a first radar signal that has a first chirp time and a first sweeping up time, wherein the first range is based on the first chirp time and the first sweeping up time; measuring wireless signals of a wireless communication environment, wherein the wireless communication environment includes the wireless device; detecting, based on the measured wireless signals, that a congestion level associated with the wireless communication environment exceeds a threshold congestion level; decreasing, based on the detected congestion level that exceeds the threshold congestion level, one or more parameters for a second radar signal sensing, wherein the one or more decreased parameters comprise at least a second sweeping up time that is shorter than the first sweeping up time and a second range that is smaller than the first range; and transmitting, for the second radar signal sensing, a second radar signal that has the first chirp time and the second sweeping up time.

16. The method of claim 15, further comprising: receiving a reflection of the second radar signal that has the first chirp time and the second sweeping up time.

17. The method of claim 16, wherein the one or more parameters comprise a transmit power (P.sub.tx) of the second radar signal sensing.
18. The method of claim 17, wherein the P.sub.tx corresponds to a decreased path loss of the second radar signal sensing.
19. The method of claim 16, wherein the second range corresponds to at least one of a first decrease in first interference associated with the second radar signal sensing or a second decrease in second interference associated with the received reflection of the second radar signal.
20. The method of claim 19, wherein the one or more decreased parameters comprises a pulse duration of the second radar signal that is associated with the second sweeping up time, wherein a discontinuous transmission (DTX) time between pulses associated with the second radar signal sensing is increased based on the pulse duration.
21. The method of claim 15, further comprising receiving one or more sidelink messages from one or more sidelink devices, wherein the measured wireless signals of the wireless communication environment comprise the one or more sidelink messages, and wherein, the detecting that the congestion level associated with the wireless communication environment exceeds the threshold congestion level is based on an amount of sidelink messages received by the wireless device.
22. The method of claim 15, wherein the wireless signals of the wireless communication environment comprise one or more other received radar signals that do not correspond to the transmitted first radar signal.
23. The method of claim 15, further comprising receiving a message that indicates the congestion level of the wireless communication environment, wherein the detecting that the congestion level associated with the wireless communication environment exceeds the threshold congestion level is based on the message.
24. The method of claim 23, wherein the message is from at least one of a network node or a sidelink device.
25. The method of claim 15, wherein the wireless device is a vehicular radar or a non-vehicular radar.
26. A method of wireless communication at a second wireless device, comprising: measuring wireless signals of a wireless communication environment, wherein the wireless communication environment includes a first radar signal of a first wireless device that has a first chirp time and a first sweeping up time, wherein the first radar signal is associated with a first radar signal sensing that has a first range, and wherein the first range is based on the first chirp time and the first sweeping up time; detecting, based on the measured wireless signals, that a congestion level of the wireless communication environment exceeds a threshold congestion level; and transmitting, based on the detected congestion level that exceeds the threshold congestion level, a message to the first wireless device to decrease one or more parameters for a second radar signal sensing, the one or more parameters comprising at least a second sweeping up time that is shorter than the first sweeping up time and a second range that is smaller than the first range.
27. The method of claim 26, wherein the message includes the one or more parameters relating to the decrease of the first range to the second range.
28. A non-transitory computer-readable medium storing computer executable code at a wireless device, the code when executed by at least one processor causes the wireless device to: transmit, for a first radar signal sensing that has a first range, a first radar signal that has a first chirp time and a first sweeping up time, wherein the first range is based on the first chirp time and the first sweeping up time; measure wireless signals of a wireless communication environment, wherein the wireless communication environment includes the wireless device; detect, based on the measured wireless signals, that a congestion level associated with the wireless communication environment exceeds a threshold congestion level; decrease, based on the detected congestion level that exceeds the threshold congestion level, one or more parameters for a second radar signal sensing, wherein the one or more decreased parameters comprise at least a second sweeping up time that is shorter

than the first sweeping up time and a second range that is smaller than the first range; and transmit, for the second radar signal sensing, a second radar signal that has the first chirp time and the second sweeping up time.

29. A non-transitory computer-readable medium storing computer executable code at a second wireless device, the code when executed by at least one processor causes the second wireless device to: measure wireless signals of a wireless communication environment, wherein the wireless communication environment includes a first radar signal of a first wireless device that has a first chirp time and a first sweeping up time, wherein the first radar signal is associated with a first radar signal sensing that has a first range, wherein the first range is based on the first chirp time and the first sweeping up time; detect, based on the measured wireless signals, that a congestion level of the wireless communication environment exceeds a threshold congestion level; and transmit, based on the detected congestion level that exceeds the threshold congestion level, a message to the first wireless device to decrease one or more parameters for a second radar signal sensing, the one or more parameters comprising at least a second sweeping up time that is shorter than the first sweeping up time and a second range that is smaller than the first range.

---