

US Patent & Trademark Office

Patent Public Search | Text View

United States Patent	12412019
Kind Code	B2
Date of Patent	September 09, 2025
Inventor(s)	Lai; Po-Chia et al.

Method and system for latch-up prevention

Abstract

An integrated circuit design method includes receiving an integrated circuit design, and determining a floor plan for the integrated circuit design. The floor plan includes an arrangement of a plurality of functional cells and a plurality of tap cells. Potential latchup locations in the floor plan are determined, and the arrangement of at least one of the functional cells or the tap cells is modified based on the determined potential latchup locations.

Inventors: Lai; Po-Chia (Fremont, CA), Chen; Kuo-Ji (Taipei county, TW), Chen; Wen-Hao (Hsin-Chu, TW), Lin; Wun-Jie (Hsinchu, TW), Su; Yu-Ti (Tainan, TW), Islam; Rabiul (Austin, TX), Ying; Shu-Yi (Hsinchu County, TW), Rusu; Stefan (Sunnyvale, CA), Li; Kuan-Te (Taoyuan, TW), Scott; David Barry (Plano, TX)

Applicant: Taiwan Semiconductor Manufacturing Company, Ltd. (Hsinchu, TW)

Family ID: 69138351

Assignee: Taiwan Semiconductor Manufacturing Company, Ltd. (Hsinchu, TW)

Appl. No.: 18/190309

Filed: March 27, 2023

Prior Publication Data

Document Identifier	Publication Date
US 20230237237 A1	Jul. 27, 2023

Related U.S. Application Data

division parent-doc US 17129195 20201221 US 11615227 child-doc US 18190309
division parent-doc US 16263841 20190131 US 10872190 child-doc US 17129195
us-provisional-application US 62698645 20180716

Publication Classification

Int. Cl.: **G06F30/30** (20200101); **G01R31/50** (20200101); **G06F30/327** (20200101);
G06F30/367 (20200101); **G06F30/392** (20200101); **G06F30/398** (20200101);
H10D89/10 (20250101); G06F117/02 (20200101)

U.S. Cl.:

CPC **G06F30/392** (20200101); **G01R31/50** (20200101); **G06F30/327** (20200101);
G06F30/367 (20200101); **G06F30/398** (20200101); **H10D89/10** (20250101);
G06F2117/02 (20200101)

Field of Classification Search

CPC: G06F (30/392); G06F (30/327); G06F (30/367); G06F (30/398); G06F (2117/02); G06F
(30/30); G06F (30/39); G06F (2119/18); G01R (31/50); H01L (27/0207); H01L (27/0203)

References Cited

U.S. PATENT DOCUMENTS

Patent No.	Issued Date	Patentee Name	U.S. Cl.	CPC
6848089	12/2004	Galland	716/115	G06F 30/367
7474011	12/2008	Lien	257/373	G06F 30/367
RE42776	12/2010	Clark et al.	N/A	N/A
8482070	12/2012	Flatresse et al.	N/A	N/A
9595508	12/2016	Xu	N/A	G06F 30/3312
10872190	12/2019	Lai et al.	N/A	N/A
2002/0105049	12/2001	Barney	326/103	H01L 27/118
2008/0122473	12/2007	Lien et al.	N/A	N/A
2013/0026580	12/2012	Morimoto et al.	N/A	N/A
2014/0223399	12/2013	Sato	716/109	G06F 30/398
2015/0102421	12/2014	Morimoto et al.	N/A	N/A
2015/0227669	12/2014	Joshi	716/115	G11C 11/417
2016/0336343	12/2015	Kuo et al.	N/A	N/A

FOREIGN PATENT DOCUMENTS

Patent No.	Application Date	Country	CPC
102903719	12/2012	CN	N/A
2016-146504	12/2017	JP	N/A

Primary Examiner: Chiang; Jack

Assistant Examiner: Bowers; Brandon

Attorney, Agent or Firm: Merchant & Gould P.C.

Background/Summary

CROSS REFERENCE TO RELATED APPLICATION (1) This application is a divisional of application Ser. No. 17/129,195, filed Oct. 15, 2021, which is a divisional of application Ser. No. 16/263,841, filed Jan. 31, 2019, which claims the benefit of U.S. Provisional Application No. 62/698,645, filed Jul. 16, 2018. The entire disclosures of the referenced applications are incorporated by reference.

BACKGROUND

(1) Integrated circuits typically include thousands of components having complex interrelationships. These circuits are generally designed using highly automated processes known as electronic design automation (EDA). EDA begins from a functional specification provided in a hardware description language (HDL) and continues through the specification of a circuit design including the specification of elementary circuit components called cells, the physical arrangement of the cells, and the wiring that interconnects the cells. The cells implement logic or other electronic functions using a particular integrated circuit technology.

(2) EDA can be divided into a series of stages such as synthesis, placement, routing, etc. Each of these steps can involve selecting cells from a library of cells. Typically, a very large number of different circuit designs using various cell combinations can meet a functional specification for a circuit. Latchup is a type of short circuit that sometimes occurs in integrated circuits due to parasitic bipolar transistors formed by adjacent junctions in the integrated circuit. EDA tools may include tap cells in integrated circuit designs, which can provide a body bias of transistors to prevent latchup.

Description

BRIEF DESCRIPTION OF THE DRAWINGS

(1) Aspects of the present disclosure are best understood from the following detailed description when read with the accompanying figures. It is noted that, in accordance with the standard practice in the industry, various features are not drawn to scale. In fact, the dimensions of the various features may be arbitrarily increased or reduced for clarity of discussion.

(2) FIG. 1 is a block diagram illustrating an example of a processing system in accordance with some embodiments.

(3) FIG. 2 is a process flow diagram illustrating aspects of an example of an integrated circuit design method in accordance with some embodiments.

(4) FIGS. 3A, 3B, and 3C illustrate aspects of an example of an integrated circuit floor plan in accordance with some embodiments.

(5) FIG. 4 illustrates aspects of another example of an integrated circuit floor plan in accordance with some embodiments.

(6) FIG. 5 is a process flow diagram illustrating aspects of an example of an integrated circuit design method in accordance with some embodiments.

(7) FIG. 6 is a schematic diagram illustrating an example of a standard cell model in accordance with some embodiments.

(8) FIG. 7 is a schematic diagram illustrating another example of a standard cell model in accordance with some embodiments.

(9) FIG. 8 illustrates an example of a cell modeling process in accordance with some embodiments.

(10) FIG. 9 illustrates another example of a cell modeling process in accordance with some embodiments.

(11) FIG. 10 illustrates aspects of another example of a tap cell modeling process in accordance with some embodiments.

(12) FIGS. 11-14 illustrate various examples of tap cell configurations in accordance with some

embodiments.

(13) FIG. 15 is a process flow diagram illustrating aspects of an example of an integrated circuit design method in accordance with some embodiments.

(14) FIG. 16 is a process flow diagram illustrating aspects of another example of an integrated circuit design method in accordance with some embodiments.

(15) FIG. 17 illustrates an example of a two dimensional user interface display in accordance with some embodiments.

(16) FIG. 18 illustrates an example of a three dimensional user interface display in accordance with some embodiments.

DETAILED DESCRIPTION

(17) The following disclosure provides many different embodiments, or examples, for implementing different features of the provided subject matter. Specific examples of components and arrangements are described below to simplify the present disclosure. These are, of course, merely examples and are not intended to be limiting. For example, the formation of a first feature over or on a second feature in the description that follows may include embodiments in which the first and second features are formed in direct contact, and may also include embodiments in which additional features may be formed between the first and second features, such that the first and second features may not be in direct contact. In addition, the present disclosure may repeat reference numerals and/or letters in the various examples. This repetition is for the purpose of simplicity and clarity and does not in itself dictate a relationship between the various embodiments and/or configurations discussed.

(18) Further, spatially relative terms, such as “beneath,” “below,” “lower,” “above,” “upper” and the like, may be used herein for ease of description to describe one element or feature's relationship to another element(s) or feature(s) as illustrated in the figures. The spatially relative terms are intended to encompass different orientations of the device in use or operation in addition to the orientation depicted in the figures. The apparatus may be otherwise oriented (rotated 90 degrees or at other orientations) and the spatially relative descriptors used herein may likewise be interpreted accordingly.

(19) Electronic Design Automation (EDA) tools and methods facilitate the design, partition, and placement of microelectronic integrated circuits on a semiconductor substrate. This process typically includes turning a behavioral description of the circuit into a functional description, which is then decomposed into logic functions and mapped into cells using a standard cell library. Once mapped, a synthesis is performed to turn the structural design into a physical layout, a clock tree is built to synchronize the structural elements, and the design is optimized post layout.

(20) FIG. 1 is a block diagram illustrating an example of a processing system 100 in accordance with some embodiments disclosed herein. The processing system 100 may be used to implement an EDA system in accordance with various processes discussed herein. The processing system 100 includes a processing unit 110, such as a desktop computer, a workstation, a laptop computer, a dedicated unit customized for a particular application, a smart phone or tablet, etc. The processing system 100 may be equipped with a display 114 and one or more input/output devices 112, such as a mouse, a keyboard, touchscreen, printer, etc. The processing unit 110 also includes a central processing unit (CPU) 120, memory 122, a mass storage device 124, a video adapter 126, and an I/O interface 128 connected to a bus 130.

(21) The bus 130 may be one or more of any type of several bus architectures including a memory bus or memory controller, a peripheral bus, or video bus. The CPU 120 may comprise any type of electronic data processor, and the memory 122 may comprise any type of system memory, such as static random access memory (SRAM), dynamic random access memory (DRAM), or read-only memory (ROM).

(22) The mass storage device 124 may comprise any type of storage device configured to store data, programs, and other information and to make the data, programs, and other information

accessible via the bus **130**. The mass storage device **124** may comprise, for example, one or more of a hard disk drive, a magnetic disk drive, an optical disk drive, flash memory, or the like.

(23) The term computer readable media as used herein may include computer storage media such as the system memory and storage devices mentioned above. Computer storage media may include volatile and nonvolatile, removable and non-removable media implemented in any method or technology for storage of information, such as computer readable instructions, data structures, or program modules. The memory **122** and mass storage device **124** are computer storage media examples (e.g., memory storage). The mass storage device may further store a library of standard cells, as will be discussed further herein below.

(24) Computer storage media may include RAM, ROM, electrically erasable read-only memory (EEPROM), flash memory or other memory technology, CD-ROM, digital versatile disks (DVD) or other optical storage, magnetic cassettes, magnetic tape, magnetic disk storage or other magnetic storage devices, or any other article of manufacture which can be used to store information and which can be accessed by the processing device **100**. Any such computer storage media may be part of the processing device **100**. Computer storage media does not include a carrier wave or other propagated or modulated data signal.

(25) Communication media may be embodied by computer readable instructions, data structures, program modules, or other data in a modulated data signal, such as a carrier wave or other transport mechanism, and includes any information delivery media. The term “modulated data signal” may describe a signal that has one or more characteristics set or changed in such a manner as to encode information in the signal. By way of example, and not limitation, communication media may include wired media such as a wired network or direct-wired connection, and wireless media such as acoustic, radio frequency (RF), infrared, and other wireless media.

(26) The video adapter **126** and the I/O interface **128** provide interfaces to couple external input and output devices to the processing unit **110**. As illustrated in FIG. **1**, examples of input and output devices include the display **114** coupled to the video adapter **126** and the I/O device **112**, such as a mouse, keyboard, printer, and the like, coupled to the I/O interface **128**. Other devices may be coupled to the processing unit **110**, and additional or fewer interface cards may be utilized. For example, a serial interface card (not shown) may be used to provide a serial interface for a printer. The processing unit **110** also may include a network interface **140** that may be a wired link to a local area network (LAN) or a wide area network (WAN) **116** and/or a wireless link.

(27) Embodiments of the processing system **100** may include other components. For example, the processing system **100** may include power supplies, cables, a motherboard, removable storage media, cases, and the like. These other components, although not shown, are considered part of the processing system **100**.

(28) In some examples, software code is executed by the CPU **120** to analyze a user design to create a physical integrated circuit layout. The software code may be accessed by the CPU **120** via the bus **130** from the memory **122**, mass storage device **124**, or the like, or remotely through the network interface **140**. Further, in some examples, the physical integrated circuit layout is created based on a functional integrated circuit design, which may be received through the I/O interface **128** and/or stored in the memory **122** or **124** in accordance with various methods and processes implemented by the software code.

(29) A standard cell can include an entire device, such as a transistor, diode, capacitor, resistor, or inductor, or can include a group of several devices arranged to achieve some particular function, such as an inverter, a flip-flop, a memory cell, or an amplifier, among others. In addition to making functional design easier to conceptualize, the use of standard cells can reduce verification time for design rule checking (DRC) of the layout features within the IC, because a standard cell that is repeated throughout the layout can be checked a single time in DRC rather than each instantiation being checked individually. Based on the received functional circuit description, the system **100** is configured to select standard cells from the cell library.

(30) FIG. 2 generally illustrates an example integrated circuit design and fabrication process **200** that may be implemented by the processing system **100** for generating a physical layout from a user supplied behavioral/functional design. The user design **202** specifies the desired behavior or function of the circuit based upon various signals or stimuli applied to the inputs of the overall design, and may be written in a suitable programming language. The design **202** may be uploaded into the processing unit **110** (see FIG. 1) through the I/O interface **128** by a user. Alternatively, the design **202** may be uploaded and/or saved on the memory **122** or mass storage device **124**, or the design **202** may be uploaded through the network interface **140** from a remote user.

(31) A synthesis **204** is performed on the design, in which the behavior and/or functions desired from the design **202** are transformed to a functionally equivalent logic gate-level circuit description by matching the design to standard cells, such as from one or more cell libraries **208**. The cell library **208** contains a listing of pre-designed components, or functional cells, each of which may perform a predetermined function. The cells are stored in the cell library **208** as information comprising internal circuit elements, the various connections to these circuit elements, a pre-designed physical layout pattern that includes the unit height of each cell along with the cell's designed power rails, dopant implants, wells, etc. Additionally, the stored cell may also comprise a shape of the cell, terminal positions for external connections, delay characteristics, power consumption, etc. The synthesis **204** results in a functionally equivalent logic gate-level circuit description, such as a gate-level netlist **206**. The cell library **208** may be stored, for example, in one or more databases contained in the mass storage **124**. Based on the gate-level netlist **206**, a photolithographic mask **210** may be generated, which is used to fabricate the integrated circuit **212**.

(32) The cell library **208** may further include tap cells. Tap cells prevent the undesirable latchup of integrated circuits, which can result from parasitic bipolar transistors formed in integrated circuits. Through the tap cells, n-well regions are coupled to VDD power rails, and p-well regions or p-type substrates are coupled to VSS power rails (typically electrical ground).

(33) In some examples, a design "floorplan" is determined that includes a plurality of rows into which the standard cells are arranged. FIGS. 3A-3C illustrate various iterations of an example floor plan **300**. The floor plan **300** provides the layout for an integrated circuit, such as would be manufactured according to the method shown in FIG. 2. As such, the floor plan **300** illustrates the arrangement of functional cells **310** and tap cells **312** in rows **304** on a substrate **302**.

(34) In some integrated design processes, a predetermined, maximum tap-to-tap distance may be specified, and tap cells are distributed in the floor plan accordingly. This maximum tap-to-tap distance may be determined, for example, using test chips with arrays of inverters that provide a worst case latchup condition to determine cell placements so as to avoid latchup. However, depending on the actual functional design for the integrated circuit device to be manufactured, such maximum tap-to-tap distances do not determine or even estimate the potential latchup susceptibility across actual cell distributions for a particular design. This can result in providing too many tap cells, causing area waste for designs where a lower tap density would suffice, and further potentially resulting in timing degradation such as in high-performance products. In such high-performance designs, higher tap density may interfere with optimal cell placement, making critical wiring paths longer. Further, some areas may be provided with insufficient tap cells, resulting in latchup.

(35) In accordance with some aspects of the present disclosure, latchup susceptibility is determined for in standard place and route (P&R) blocks of a floor plan. Additionally, solutions to address critical latchup areas are provided.

(36) Referring to FIG. 3A, in some examples, the tap cells **312** are initially located in predetermined locations in the rows **304**. In the example shown in FIG. 3A, the tap cells **312** are initially positioned to extend vertically in columns at either side of the floor plan **300**, as well as in a vertical column in the center area of the floor plan **300**. Note that the floor plan **300** further includes locations **306** where there are no functional cells **310** or tap cells **312** initially placed.

(37) FIG. 4 illustrates another initial floor plan **400**, prior to the placement of the functional cells **310**. In the example of FIG. 4, certain rows **304** of the floor plan **400** include only tap cells **312**. The substrate **302** in the floor plan **400** shown in FIG. 4 defines an outer periphery having a first, or top border **402** and a second, or bottom border **404** opposite the first border **402**. In the floor plan **400** shown in FIG. 4, a first row **304a** directly adjacent the top border **402** and a second row **304b** directly adjacent the bottom border **404** include only tap cells **312**. Additionally, another row **304c** extending horizontally across the center of the floor plan **400** includes only tap cells **312**. Adding such dedicated rows of tap cells greatly reduces the potential for latchup in integrated circuit devices, without consuming significant area in the floor plan **400**. The illustrated example shows three horizontal rows of tap cells, though in other embodiments more or fewer rows of tap cells could be provided. Typically, tap cells are provided in vertical columns up-and-down a floor plan. The rows **304** shown in the example of FIG. 4 include only tap cells, so the floor plan provides additional tap cells as compared to prior tap cell implementations. Additionally, equally spacing the tap cell rows **304** from the top and bottom borders **402**, **404** helps further reduce latch up potential.

(38) Referring now to FIG. 5, further aspects of an example method **220** for designing an integrated circuit are illustrated. Various steps of the method **220** are performed, for example, by the processor **120** and system **100** shown in FIG. 1. At an operation **222**, the standard cell models are created for each of the standard cells stored in the cell library **232**. The cell models may further be stored in the cell library **232**.

(39) FIGS. 6 and 7 conceptually illustrate aspects of the cell model creation process for standard functional cells **310** and tap cells **312**, respectively, as shown in the operation **222** of FIG. 5. As shown in FIG. 6, P-wells **612** and N-wells **610** for the functional cells **310** may be modeled by using distributed resistors **614** and **616**, respectively. To characterize DC and AC currents of the cells **310**, current sources **620** are provided to inject current into each well **610**, **612**. In some implementations, the current is injected in the middle of the cell **310**. FIG. 7 illustrates a model for a tap cell **312**, in which the continuous P-well **612** and N-well **610** are modeled by the distributed resistors **616**, **614**. To model pickup resistance, resistors **622**, **624** are connected in the middle of the cell resistors **614**, **616**, between the respective voltage sources VDD and VSS. The illustrated models shown in FIGS. 6 and 7 provide a simple and elegant model to characterize DC and AC currents of the cells **310**, **312**. In other examples, additional components such as capacitors and inductors could be added to the models to characterize further aspects of the cells as necessary.

(40) FIGS. 8 and 9 illustrate additional aspects of the cell modeling process. FIGS. 8 and 9 each show a portion of a floor plan **300** that includes functional standard cells **310** and tap cells **312**, as well as VDD and VSS voltage sources. Each of the standard cells **310** and the tap cells **312** are modeled as described in conjunction with FIGS. 6 and 7. In FIGS. 8 and 9, the model representations **340**, **341** of the illustrated cells are shown below the floor plan **300**, with the resistors **616** simulating the P-well. The models of the functional cells **310** include the current sources **620** that inject current from the middle of the cells **310** to the resistors **616** representing the P-well **612** to simulate the behavior of the appropriate functional cells **310**. The models further include filler cells **311** that simply fill in an open space in the floor plan and do not inject current into the well. Based on the modeled aspects of the standard cells and other factors such as leakage and resistance (distance between tap cells **312** and functional cells **310**), voltage droop across the various P-wells and N-wells of the floor plan may be determined. For simplicity only P-wells are illustrated in the models shown in FIGS. 8 and 9. In other examples, the models may further include N-wells.

(41) FIG. 10 shows another modeling example where multiple height cells are modeled. Taller cells inject current into multiple P-well or N-well segments. Thus, the single height cell **310a** injects current only into a single well. The double height cell **310b** is symmetrical. For modeling purposes, it is assumed that the current is equally distributed into the multiple well segments. The triple height cell **310c** is not symmetrical. Thus, each well segment is characterized separately when

building cell models.

(42) Generally, if voltage droop across a P-well or N-well exceeds some predetermined value at a given location, latchup risk is increased at that location. In some examples, a local well voltage exceeding 0.5 volts is likely to cause latchup.

(43) Referring back to FIG. 5, the functional circuit design is received by the system **100** at operation **224**. Based on the function design, an initial floor plan is created at operation **226**, such as the floor plan **300** shown in FIG. 3A. Using the models for the functional cells **310** and tap cells **312**, potential latchup positions are identified as indicated in operation **228**. Latchup positions may be identified, for example, based on the determined voltage droop. Based on the determined latchup locations, the floor plan **300** is modified in operation **230**. For example, modifying the floor plan could include moving functional cells **310** and/or tap cells **312**, adding additional tap cells **312**, using different types of tap cells **312**, etc. to address identified latchup issues.

(44) FIG. 3B shows an example where the floor plan **300** has been modified by adding additional tap cells **310a** to some of the open areas **306** to address the determined potential latchup areas. In FIG. 3C, additional smaller tap cells **310b** have been added to smaller open areas **306**. Determining the locations and sizes for the added tap cells is discussed further herein below.

(45) FIGS. 11-14 illustrate examples of different tap cells **312** employed in various embodiments. In certain embodiments, a default tap cell **312** includes two P-well contacts **802** and two N-well contacts **800**, as shown in FIG. 11. As noted above, the tap cells **312** are employed to prevent the undesirable latchup of integrated circuits, which can result from parasitic bipolar transistors formed in the integrated circuits. The tap cells **312** thus provide the P-well contacts **802** to couple the P-well or P-type substrates to the VSS power rails. The N-well contacts **800** are used to couple the N-well regions or N-type substrates to the VDD power rails. Providing additional P-well and/or N-well contacts may increase the size of the cell, but the additional contacts reduce resistance, providing additional current paths to reduce latchup.

(46) To reduce the contact resistance in floor plan locations that are critical for latchup, larger tap cells with additional contacts may be employed, such as the tap cell **312** shown in FIG. 12, which has four P-well contacts **802** and four N-well contacts **800**. The larger tap cell **312** shown in FIG. 12 can also be configured, for example, in a 2+6 configuration (two N-well/six P-well contacts) as shown in FIG. 13, or in a 6+2 configuration as shown in FIG. 14 within the same cell area footprint as the version shown in FIG. 11. This provides lower contact resistance to either P-well or N-well contacts as desired to reduce latchup. Thus, 2+2 tap cell **312** of FIG. 11 could be used for non-critical latchup areas of the footprint, while the larger tap cell arrangements such as, for example, 4+4, 2+6, 6+2, etc. could be used for latchup critical areas.

(47) FIG. 15 illustrates further aspects of an example integrated design process **240**. As shown in FIGS. 2 and 5, a function design is received. Based on the received design, a block placement file is read in operation **242**, cell data for the appropriate functional cells **310** is obtained from the cell library in operation **244**, and a technology file is read in operation **246**. Aspects of the functional cells **310** and tap cells **312** are modeled, including building a network of current sources and resistances for the cells that model the various wells and tap contacts as shown in operation **248** using the models shown in FIGS. 6-9, for example.

(48) The floor plan is then examined, and based on the model information developed in operation **248**, voltage droop across well locations is determined in operation **250** based on the models and other factors as described above in conjunction with FIGS. 6-9. If the voltage droop across a well location exceeds a predetermined value, such as 0.5 volts in some examples, a potential latchup location is identified. In this manner, potential latchup locations in a floor plan may be determined. Based on the determined latchup locations, available locations for inserting additional tap cells are identified in operation **252**. As shown in FIGS. 3A-3C, available locations for placement of additional tap cells **312** could include the open spaces **306** in the floor plan **300** where functional cells **310** and tap cells **312** were not previously located. In some examples, the voltage droop

calculations of operation **250** are then repeated to continue identifying and reducing latchup locations.

(49) Still further, in some examples, functional cells **310** may be moved in response to the latchup location determination to create additional space for inserting additional tap cells, as shown in operation **254**. The latchup location identification process **250** may be repeated following operation **254** to further reduce latchup hotspots. Thus, the process shown in FIG. **15** provides an iterative process for addressing and removing potential latchup hotspots.

(50) FIG. **16** is a flow diagram illustrating still further aspects of the disclosed design process, illustrating a tap cell insertion process **260**. The process **260** begins at block **262**, where the existing floor plan is evaluated according to the process shown in FIG. **15**, for example. If no latchup locations are identified, no changes to the floor plan are necessary and the existing floor plan is used as shown in operation **264**.

(51) If latchup locations are identified, the floor plan **300** is modified. In operation **266**, one or more of the tap cells **312** of the existing floor plan **300** are swapped with different tap cell configurations. For instance, a standard 4+4 tap cell such as that shown in FIG. **11** could be replaced by a larger tap cell, such as those shown in FIGS. **12-14**. In some implementations, the illustrated method is an iterative process to find an optimal balance between several factors such as latchup risk, leakage, floorplan size, etc. For instance, many additional tap cells and/or larger tap cells could be added in the operation **266** discussed above. While this may greatly reduce latchup risks, the additional and/or larger tap cells could result in other factors such as leakage or floorplan size unacceptably increasing. Thus, following operation **266**, if no latchup areas are identified, overall leakage current for the floor plan **300** is determined in operation **268**, based on the information regarding the functional cells **310** determined during the modeling process **248** of FIG. **15**. Additional calculations are performed in some examples, such as determining the overall layout size of the floor plan.

(52) Based on the leakage current and layout size determined in operation **268**, tap-to-tap distances may be adjusted in operation **270** to make better use of the floor plan area, such as by reducing leakage and layout size. Additionally, if latchup locations are identified in operation **266**, operation **270** may be executed to change tap-to-tap locations, thus addressing identified latchup hotspots.

(53) If no latchup areas are identified following operation **270**, overall leakage current for the floor plan **300** and overall layout size of the floor plan are again calculated in operation **272** to optimize the floorplan layout as noted above. In operation **274**, if latchup areas or hotspots are identified following operation **270**, areas near identified latchup locations are analyzed to identify open spaces **306** proximate to the latchup areas. Tap cells **312** may then be inserted in these areas to address latchup locations.

(54) If no latchup areas are identified following operation **274**, overall leakage current for the floor plan **300** and overall layout size of the floor plan are again calculated in operation **276** to optimize the device layout. Further, the overall leakage current and layout size calculations from operations **268**, **272**, and **276** are compared to select the floor plan arrangement having the smallest layout area and smallest leakage current while still adequately reducing latchup risks.

(55) In operation **278**, if latchup hotspots are identified following operation **274**, functional cells in the latchup area may be relocated to make room for inserting additional tap cells. Following operation **278**, the process **260** may be repeated to identify the best floor plan layout that avoids latchup issues.

(56) In accordance with still further aspects of the disclosure, latchup locations are displayed in a user interface to assist in addressing latchup issues. The user interface may be displayed via the display **114** of the system **100** shown in FIG. **1**. FIGS. **17** and **18** illustrate example user interfaces **820**, **821**, where well voltages **822** are displayed for portions the rows **304** of the floor plan **300**. The user interface **820** of FIG. **17** illustrates a two dimensional display, while the user interface **821** shown in FIG. **18** provides a three dimensional display. In an area **824**, well voltage exceeds 0.5

volts, identifying a latchup critical area. This area 824 may thus be addressed using the various example processes disclosed herein for eliminating latchup critical areas.

(57) Various disclosed embodiments thus provide procedures to determine latchup risk for place and route blocks and present the circuit designer a graphical representation of the latchup susceptibility across the design. Further, processes for reducing latchup risk in critical areas of a design, as well as options to minimize tap cell overhead in non-critical areas of the design are provided. Disclosed examples also illustrate adaptive solutions that are tailored to match the magnitude of the latchup risk and minimize tap cell overhead.

(58) Disclosed embodiments include an integrated circuit that includes a substrate defining an outer periphery having a first border and a second border opposite the first border. A plurality of circuit elements are in or on the substrate arranged in a plurality of rows. The circuit elements are defined by standard layout cells selected from a cell library. The standard cells include tap cells, and the plurality of rows includes a first row that includes only tap cells.

(59) In accordance with further disclosed embodiments, a method of designing an integrated circuit includes receiving an integrated circuit design. A floor plan for the integrated circuit design is determined. The floor plan includes an arrangement of a plurality of functional cells, where each of the functional cells are configured to perform a predefined function. The floor plan further includes a plurality of tap cells. Potential latchup locations are determined in the floor plan, and the arrangement of at least one of the functional cells or the tap cells is modified based on the determined potential latchup locations.

(60) In accordance with still further disclosed embodiments, an integrated circuit design system includes a processor and computer readable media accessible by the processor. The computer readable media stores a cell library defining a plurality of functional cells configured to perform a predefined function and a plurality of tap cells, as well as instructions that when executed by the processor implement a method for designing an integrated circuit. The method includes receiving an integrated circuit design, and selecting a plurality of the functional cells from the cell library based on the functional integrated circuit design. The plurality of the functional cells are arranged into a floor plan, and a plurality of the tap cells are arranged into predetermined locations of the floor plan. Potential latchup locations in the floor plan are determined.

(61) The foregoing outlines features of several embodiments so that those skilled in the art may better understand the aspects of the present disclosure. Those skilled in the art should appreciate that they may readily use the present disclosure as a basis for designing or modifying other processes and structures for carrying out the same purposes and/or achieving the same advantages of the embodiments introduced herein. Those skilled in the art should also realize that such equivalent constructions do not depart from the spirit and scope of the present disclosure, and that they may make various changes, substitutions, and alterations herein without departing from the spirit and scope of the present disclosure.

Claims

1. A method, comprising: providing a cell library defining a plurality of functional cells configured to perform a predefined function and a plurality of tap cells; receiving an integrated circuit design; selecting a plurality of the functional cells from the cell library based on the integrated circuit design; arranging the plurality of the functional cells into a floor plan, wherein the floor plan includes a plurality of rows; arranging a plurality of the tap cells into predetermined locations of the floor plan; modeling AC and DC current of the functional cells of the floor plan to determine voltage droop of the floor plan; and determining potential latchup locations in the floor plan based on the voltage droop of the floor plan.

2. The method of claim 1, wherein the floor plan includes at least one row that contains only tap cells.

3. The method of claim 1, wherein determining potential latchup locations in the floor plan based on the voltage droop of the floor plan includes determining whether the voltage droop exceeds a predetermined value.
 4. The method of claim 1, further comprising modifying the arrangement of at least one of the functional cells or the tap cells based on the determined potential latchup locations.
 5. The method of claim 4, wherein modifying the arrangement includes moving selected ones of the tap cells to different locations in the floor plan.
 6. The method of claim 4, wherein modifying the arrangement includes adding additional tap cells to the floor plan.
 7. The method of claim 4, wherein modifying the arrangement includes moving selected ones of the functional cells to different locations in the floor plan.
 8. The method of claim 4, further comprising: relocating at least some of the plurality of the tap cells arranged into the floor plan based on the determined potential latchup locations.
 9. A method, comprising: selecting a plurality of functional cells, configured to perform predefined functions, from a cell library based on an integrated circuit design; arranging the plurality of functional cells into a floor plan; arranging a plurality of tap cells from the cell library into locations of the floor plan; modeling AC and DC current of the functional cells of the floor plan to determine voltage droop of the floor plan; and determining potential latchup locations in the floor plan based on the voltage droop of the floor plan.
 10. The method of claim 9, wherein the floor plan includes at least one row that contains only tap cells.
 11. The method of claim 9, wherein determining potential latchup locations in the floor plan based on the voltage droop of the floor plan includes determining whether the voltage droop exceeds a predetermined value.
 12. The method of claim 9, further comprising modifying the arrangement of at least one of the functional cells or the tap cells based on the determined potential latchup locations.
 13. The method of claim 12, wherein modifying the arrangement includes moving selected ones of the tap cells to different locations in the floor plan.
 14. The method of claim 12, wherein modifying the arrangement includes adding additional tap cells to the floor plan.
 15. The method of claim 12, wherein modifying the arrangement includes moving selected ones of the functional cells to different locations in the floor plan.
 16. The method of claim 9, further comprising: relocating at least some of the plurality of tap cells arranged into the floor plan based on the determined potential latchup locations.
 17. A method, comprising: selecting a plurality of functional cells, configured to perform predefined functions, from a cell library based on an integrated circuit design; arranging the plurality of functional cells into a floor plan; arranging a plurality of tap cells from the cell library into locations of the floor plan; modeling AC and DC current of the functional cells of the floor plan to determine voltage droop of the floor plan; and determining potential latchup locations in the floor plan based on the voltage droop of the floor plan and determining whether the voltage droop exceeds a predetermined value.
 18. The method of claim 17, wherein the floor plan includes at least one row that contains only tap cells.
 19. The method of claim 17, further comprising modifying the arrangement of at least one of the functional cells or the tap cells based on the determined potential latchup locations.
 20. The method of claim 17, further comprising: relocating at least some of the plurality of tap cells arranged into the floor plan based on the determined potential latchup locations.
-