

# US Patent & Trademark Office

## Patent Public Search | Text View

---

|                      |                     |
|----------------------|---------------------|
| United States Patent | 12412851            |
| Kind Code            | B2                  |
| Date of Patent       | September 09, 2025  |
| Inventor(s)          | Tsai; Po-Hao et al. |

---

### Semiconductor device and method of manufacture

---

#### Abstract

A device includes a redistribution structure, a first semiconductor device, a first antenna, and a first conductive pillar on the redistribution structure that are electrically connected to the redistribution structure, an antenna structure over the first semiconductor device, wherein the antenna structure includes a second antenna that is different from the first antenna, wherein the antenna structure includes an external connection bonded to the first conductive pillar, and a molding material extending between the antenna structure and the redistribution structure, the molding material surrounding the first semiconductor device, the first antenna, the external connection, and the first conductive pillar.

---

**Inventors:** Tsai; Po-Hao (Zhongli, TW), Chuang; Po-Yao (Hsinchu, TW), Yew; Ming-Chih (Hsinchu, TW), Jeng; Shin-Puu (Hsinchu, TW)

**Applicant:** Taiwan Semiconductor Manufacturing Co., Ltd. (Hsinchu, TW)

**Family ID:** 69320634

**Assignee:** Taiwan Semiconductor Manufacturing Company, Ltd. (Hsinchu, TW)

**Appl. No.:** 18/664508

**Filed:** May 15, 2024

#### Prior Publication Data

| Document Identifier | Publication Date |
|---------------------|------------------|
| US 20240304572 A1   | Sep. 12, 2024    |

#### Related U.S. Application Data

continuation parent-doc US 18186348 20230320 US 12021045 child-doc US 18664508  
continuation parent-doc US 17222044 20210405 US 11610854 20230321 child-doc US 18186348

## Publication Classification

**Int. Cl.:** **H01L23/66** (20060101); **H01L21/56** (20060101); **H01L23/00** (20060101); **H01L23/31** (20060101); **H01L23/48** (20060101); **H01L23/498** (20060101); **H01L23/538** (20060101); **H01Q1/22** (20060101); **H01Q9/04** (20060101); **H01Q9/28** (20060101); **H01Q21/06** (20060101)

**U.S. Cl.:**

**CPC** **H01L23/66** (20130101); **H01L21/566** (20130101); **H01L23/3107** (20130101); **H01L23/481** (20130101); **H01L23/49822** (20130101); **H01L23/5383** (20130101); **H01L24/09** (20130101); **H01L24/17** (20130101); **H01Q1/2283** (20130101); **H01Q9/045** (20130101); **H01Q9/285** (20130101); **H01Q21/062** (20130101); **H01Q21/065** (20130101); H01L24/16 (20130101); H01L24/32 (20130101); H01L24/73 (20130101); H01L2223/6677 (20130101); H01L2224/02372 (20130101); H01L2224/02379 (20130101); H01L2224/16227 (20130101); H01L2224/32225 (20130101); H01L2224/73204 (20130101)

## Field of Classification Search

**CPC:** H01L (23/66); H01L (21/566); H01L (24/09); H01L (23/481); H01L (23/3107); H01L (24/17); H01L (2223/6677); H01L (2224/02372); H01L (2224/02379); H01L (2224/13111); H01L (2224/13139); H01L (2224/29199); H01L (2224/29124); H01L (2224/29184); H01L (2224/29166); H01L (2224/13147); H01L (2224/056); H01L (2224/29155); H01L (2224/2919); H01L (2224/29147); H01L (2224/29339); H01L (24/19); H01Q (1/2283); H01Q (9/285); H01Q (9/045); H01Q (21/062); H01Q (21/065)

---

## References Cited

### U.S. PATENT DOCUMENTS

| Patent No.   | Issued Date | Patentee Name   | U.S. Cl. | CPC        |
|--------------|-------------|-----------------|----------|------------|
| 10763225     | 12/2019     | Kim             | N/A      | H01L 24/82 |
| 2006/0099738 | 12/2005     | Yamazaki        | N/A      | N/A        |
| 2009/0168367 | 12/2008     | Fujii           | N/A      | N/A        |
| 2012/0280366 | 12/2011     | Kamgaing et al. | N/A      | N/A        |
| 2016/0172761 | 12/2015     | Garcia et al.   | N/A      | N/A        |
| 2016/0240492 | 12/2015     | Wolter et al.   | N/A      | N/A        |
| 2017/0077039 | 12/2016     | Liao et al.     | N/A      | N/A        |
| 2017/0229769 | 12/2016     | Yokoyama et al. | N/A      | N/A        |
| 2017/0236776 | 12/2016     | Huynh et al.    | N/A      | N/A        |
| 2017/0346185 | 12/2016     | Wang et al.     | N/A      | N/A        |
| 2019/0189572 | 12/2018     | Chiang et al.   | N/A      | N/A        |
| 2020/0212536 | 12/2019     | Gupta et al.    | N/A      | N/A        |

### FOREIGN PATENT DOCUMENTS

| Patent No. | Application Date | Country | CPC |
|------------|------------------|---------|-----|
|------------|------------------|---------|-----|

|             |         |    |     |
|-------------|---------|----|-----|
| 101194360   | 12/2007 | CN | N/A |
| 101728327   | 12/2009 | CN | N/A |
| 103915421   | 12/2013 | CN | N/A |
| 104701304   | 12/2014 | CN | N/A |
| 106449432   | 12/2016 | CN | N/A |
| 106972005   | 12/2016 | CN | N/A |
| 106992160   | 12/2016 | CN | N/A |
| 107078406   | 12/2016 | CN | N/A |
| 107437654   | 12/2016 | CN | N/A |
| 108336494   | 12/2017 | CN | N/A |
| 20090071386 | 12/2008 | KR | N/A |
| 20140014260 | 12/2013 | KR | N/A |
| 20160067961 | 12/2015 | KR | N/A |
| 2016056387  | 12/2015 | WO | N/A |

---

*Primary Examiner:* Kusumakar; Karen

*Attorney, Agent or Firm:* Slater Matsil, LLP

---

## **Background/Summary**

**PRIORITY CLAIM AND CROSS-REFERENCE** (1) This application is a continuation of U.S. patent application Ser. No. 18/186,348 entitled “Semiconductor Device and Method of Manufacture,” filed on Mar. 20, 2023, now U.S. Pat. No. 12,021,045, issued Jun. 25, 2024, which is a continuation of U.S. patent application Ser. No. 17/222,044 entitled “Semiconductor Device and Method of Manufacture,” filed on Apr. 5, 2021, now U.S. Pat. No. 11,610,854 issued Mar. 21, 2023, which is a continuation of U.S. patent application Ser. No. 16/530,276 entitled “Semiconductor Device and Method of Manufacture,” filed on Aug. 2, 2019, now U.S. Pat. No. 10,971,461 issued Apr. 6, 2021, which claims priority to and the benefit of U.S. Provisional Application No. 62/718,996 entitled “Multi-Antenna in Heterogeneous Fan-Out Structure,” filed on Aug. 16, 2018, each application is hereby incorporated herein by reference in its entirety.

## **BACKGROUND**

(1) The semiconductor industry has experienced rapid growth due to continuous improvements in the integration density of a variety of electronic components (e.g., transistors, diodes, resistors, capacitors, etc.). For the most part, this improvement in integration density has come from repeated reductions in minimum feature size (e.g., shrinking the semiconductor process node towards the sub-20 nm node), which allows more components to be integrated into a given area. As the demand for miniaturization, higher speed and greater bandwidth, as well as lower power consumption and latency has grown recently, there has grown a need for smaller and more creative packaging techniques of semiconductor dies.

(2) As semiconductor technologies further advance, stacked and bonded semiconductor devices have emerged as an effective alternative to further reduce the physical size of a semiconductor device. In a stacked semiconductor device, active circuits such as logic, memory, processor circuits and the like are fabricated at least partially on separate substrates and then physically and electrically bonded together in order to form a functional device. Such bonding processes utilize sophisticated techniques, and improvements are desired.

---

## Description

### BRIEF DESCRIPTION OF THE DRAWINGS

- (1) Aspects of the present disclosure are best understood from the following detailed description when read with the accompanying figures. It is noted that, in accordance with the standard practice in the industry, various features are not drawn to scale. In fact, the dimensions of the various features may be arbitrarily increased or reduced for clarity of discussion.
- (2) FIGS. 1-3A, 3B, 4, 5, 6A, 6B, 7, 8A, 8B, 9A, 9B, 10A, 10B, 10C and 11 illustrate cross-sectional views and plan views of intermediate steps of forming an antenna package, in accordance with some embodiments.
- (3) FIGS. 12 through 16 illustrate cross-sectional views of intermediate steps of forming an antenna package, in accordance with some embodiments.
- (4) FIGS. 17 through 21 illustrate cross-sectional views of intermediate steps of forming an antenna package, in accordance with some embodiments.
- (5) FIGS. 22 through 24 illustrate cross-sectional views of intermediate steps of forming an antenna package, in accordance with some embodiments.
- (6) FIGS. 25 through 30 illustrate cross-sectional views of intermediate steps of forming an antenna package, in accordance with some embodiments.
- (7) FIG. 31 illustrates a perspective view of an antenna package having sidewall antennas, in accordance with some embodiments.
- (8) FIGS. 32A through 32C illustrate cross-sectional views of intermediate steps of forming an antenna package, in accordance with some embodiments.

### DETAILED DESCRIPTION

- (9) The following disclosure provides many different embodiments, or examples, for implementing different features of the invention. Specific examples of components and arrangements are described below to simplify the present disclosure. These are, of course, merely examples and are not intended to be limiting. For example, the formation of a first feature over or on a second feature in the description that follows may include embodiments in which the first and second features are formed in direct contact, and may also include embodiments in which additional features may be formed between the first and second features, such that the first and second features may not be in direct contact. In addition, the present disclosure may repeat reference numerals and/or letters in the various examples. This repetition is for the purpose of simplicity and clarity and does not in itself dictate a relationship between the various embodiments and/or configurations discussed.
- (10) Further, spatially relative terms, such as “beneath,” “below,” “lower,” “above,” “upper” and the like, may be used herein for ease of description to describe one element or feature's relationship to another element(s) or feature(s) as illustrated in the figures. The spatially relative terms are intended to encompass different orientations of the device in use or operation in addition to the orientation depicted in the figures. The apparatus may be otherwise oriented (rotated 90 degrees or at other orientations) and the spatially relative descriptors used herein may likewise be interpreted accordingly.
- (11) Embodiments will be described below with respect to a particular application utilizing a heterogeneous fan out structure for millimeter wave radio frequency applications. However, the embodiments are not intended to be limited to these embodiments, and the embodiments may be used in a wide variety of applications. The embodiments described herein may allow for multiple types of antennas to be formed in a single package. For example, dipole antennas, end-fire antennas, and patch antennas may all be formed in the same package. By including multiple antenna types, the directionality of the antenna operation of the package may be improved. In some cases, the techniques described herein may allow for reduced size of the package. By forming one or more antennas on a core substrate, the cost of manufacture of the package may be reduced.

Some embodiments include thermal vias which may improve heat dissipation within the package. (12) FIGS. **1-11** illustrate intermediate steps of forming an antenna package **300**, in accordance with some embodiments. FIGS. **1** through **5** illustrate cross-sectional views and plan views of intermediate steps of forming an antenna structure **120** (see FIG. **5**), in accordance with some embodiments. FIGS. **6A** through **9B** illustrate cross-sectional views and plan views of intermediate steps of forming a device structure **200** (see FIGS. **9A-B**), in accordance with some embodiments. FIGS. **10A-C** illustrate cross-sectional views of intermediate steps of forming an antenna package **300**, in accordance with some embodiments. FIG. **11** illustrates a cross-sectional view of an antenna package **300**, in accordance with some embodiments.

(13) FIG. **1** shows a cross-sectional view of a core substrate **101**, in accordance with some embodiments. In some embodiments, the core substrate **101** may be a double-sided copper-clad laminate (CCL) substrate or the like. The core substrate **101** may have a thickness between about 200  $\mu\text{m}$  and about 1000  $\mu\text{m}$ , such as about 400  $\mu\text{m}$  or about 900  $\mu\text{m}$ . In some embodiments, the core substrate **101** includes an insulation substrate **100** having conductive layers **102** disposed on opposite surfaces of the insulation substrate **100**. For example, the insulation substrate **100** may be an insulating core, and may include one or more layers of insulating materials such as fiberglass-reinforced resin materials, printed circuit board (PCB) materials, build-up films such as Ajinomoto build-up film (ABF), pre-impregnated composite fiber (prepreg) materials, polymer materials, paper, glass fiber, non-woven glass fabric, glass, ceramic, other laminates, the like, or combinations thereof. The conductive layers **102** may be one or more layers of copper, nickel, aluminum, other conductive materials, or combination thereof laminated or formed onto opposing sides of the insulation substrate **100**. In some embodiments, the conductive layers **102** may have a thickness between about 5  $\mu\text{m}$  and about 50  $\mu\text{m}$ . In some cases, the use of an insulation substrate **100** as described can provide greater stability for the antenna structure **120** (see FIG. **5**) or for the antenna package **300** (see FIGS. **10A-11**).

(14) Referring to FIG. **2**, openings **104** are formed in the core substrate **101**. In some embodiments, the openings **104** are formed by, for example, a laser drilling technique. Other processes, e.g., mechanical drilling, etching, or the like, may also be used in other embodiments. The openings **104** may have lateral cross-section that is a rectangular shape, a circular shape, or another shape. In some embodiments, the openings **104** may have a lateral cross-section that is between about 50  $\mu\text{m}$  and about 500  $\mu\text{m}$ .

(15) In some embodiments, an optional surface preparation process may be performed after the openings **104** are formed. The surface preparation process may include a process that cleans exposed surfaces of the core substrate **101** with one or more cleaning solutions. The cleaning solutions may include sulfuric acid, chromic acid, a neutralizing alkaline solution, a water rinse, the like, or a combination. In some cases, the surface preparation process removes or reduces residues, oils, native oxide films, etc. In some embodiments, an optional desmear process may be performed to clean regions near the openings **104**. The desmear process may be performed in addition to or instead of the surface preparation process. For example, the desmear process may remove residual material of the insulation substrate **100** remaining on surfaces of the core substrate **101**. The desmear process may be accomplished mechanically (e.g., blasting with a fine abrasive in a wet slurry), chemically (e.g., rinsing with a combination of organic solvents, permanganate etc.), or by a combination of mechanical and chemical desmearing. Following the surface preparation process or desmear process, a conditioning treatment may be performed using a chemical conditioner that facilitates adsorption of an activator used during subsequent electroless plating. In some embodiments, the conditioning treatment may be followed by micro-etching of the conductive layers **102** to roughen the conductive surface for better bonding between the metal foil and the later deposited conductive material (see FIG. **3A**).

(16) In FIGS. **3A-B**, conductive features are formed on surfaces of the insulation substrate **100** and the openings **104** (see FIG. **2**) are filled with conductive material to form through-via structures

extending through the insulation substrate **100**, in accordance with some embodiments. FIG. **3B** shows a plan view, and FIG. **3A** shows a cross-sectional view along the cross-section A-A' labeled in FIG. **3B**. Described in greater detail below, the conductive features may include, for example, patch antennas **110**, end-fire antennas **112**, other types of driven antennas, parasitic antennas, or arrays of antennas. The conductive features may also include ground planes **114** or other conductive features (e.g., routing, traces, or conductive lines) not shown in FIGS. **3A-B**. For example, conductive features may be connected by routing that is not shown in the example cross-sectional views. Described in greater detail below, the through-via structures may include, for example, thermal vias **106**, feedline vias **108**, or other types of through-vias. As shown in FIGS. **3A-B**, some conductive features may be connected to through-via structures.

(17) In some embodiments, the conductive features and through-via structures are formed by first forming a patterned mask over a first side of the core substrate **101**. The patterned mask may be, for example, a patterned photoresist layer. Openings in the patterned mask expose portions of the conductive layer **102** on which conductive material will subsequently be formed. The openings in the patterned mask also may expose the openings **104** in the insulation substrate **100**. The conductive material may then be deposited on the exposed regions of the conductive layer **102** and within the openings **104** using, for example, a plating process, an electroless plating process, or another process. After depositing the conductive material, the patterned mask layer (e.g., the photoresist) may be removed using a wet chemical process or a dry process (e.g., an ashing process). Portions of the conductive layer **102** that were covered by the patterned mask layer may be removed with the patterned mask layer or using a separate etching process. A similar process may then be performed on the opposite side of the core substrate **101** to form conductive features (or remaining portions of through-vias) on the opposite side of the core substrate **101**. In this manner, the conductive material may form conductive features and through-vias.

(18) Although not shown in this example, it is understood that the method of using a core substrate having conductive layers, forming openings extending through the core substrate, forming a patterned conductive material and removing unwanted portions of the conductive layers may be performed repeatedly to vertically stack multiple alternating layers of insulation material and conductive material with through-vias for connecting vertically adjacent layers having conductive features.

(19) The conductive features formed may include one or more patch antennas **110**, such as those shown in FIGS. **3A-B**. The patch antennas **110** may be formed on a top surface of the insulation substrate **100**. The patch antennas **110** may be configured to operate in the microwave spectrum, such as at a frequency of about 28 GHz or at one or more other frequencies. The patch antennas **110** may be configured to operate having a directionality that is mostly normal to (e.g., perpendicular to) the top surface of the insulation substrate **100** (see FIG. **11**). In some embodiments, the radiation direction of a patch antenna **110** is adjustable, and may be controlled by the locations and/or number of power feed lines **108** connected to the patch antenna **110** (multiple power feed lines **108** are not shown in FIGS. **3A-B**). Four patch antennas **110** are shown in FIG. **3B**, but any number of patch antennas **110** may be disposed in any arrangement on the top surface of the insulation substrate **100**. The patch antennas **110** may be the same size and shape or have different sizes or different shapes. The patch antennas **110** may have a rectangular shape or another shape, and may have lateral dimensions between about 1.0 mm and about 10 mm. As shown in FIG. **3A**, groundplanes **114** for the patch antennas **110** may be formed on the bottom surface of the insulation substrate **100**. The groundplanes **114** may be electrically grounded relative to the patch antennas **110**, and are configured such that a changing electric field is generated between a patch antenna **110** and its corresponding groundplane **114** during operation of the patch antenna **110**. In some embodiments, the groundplanes **114** may be formed in a layer within the insulation substrate **100** or may be external to the antenna structure **120**. A patch antenna **110** may be electrically connected to a feedline via **108**, through which the patch antenna **110** may be driven. In other

embodiments, the patch antenna **110** is driven through a conductive trace disposed on the top surface of the insulation substrate **100** (not shown in FIGS. **3A-B**).

(20) In some embodiments, the patch antenna **110** is parasitically driven. (An example parasitic patch antenna **410** is shown in FIG. **12**.) In a parasitically driven antenna, the antenna itself is electrically isolated, and an adjacent conductive feature is driven. Changing electric fields are generated in the driven conductive feature, and these electric fields interact with the antenna and create changing electric fields within the antenna. The changing electric fields created within the antenna cause the antenna to radiate. In this manner, the parasitic antenna is parasitically driven by the conductive feature. More than one antenna may be parasitically driven by a single conductive feature. The conductive feature may be, for example, a conductive trace, a via, a directly driven antenna, another parasitically driven antenna, a combination, or the like.

(21) The conductive features may also include one or more end-fire antennas **112**, such as those shown in FIGS. **3A-B**. The end-fire antennas **112** may be formed on a top surface of the insulation substrate **100**. The end-fire antennas **112** may be parasitic antennas, and may be parasitically driven by the patch antennas **110** such that both the end-fire antennas **112** and the patch antennas **110** operate together. The end-fire antennas **112** may be configured to operate in the microwave spectrum, such as at a frequency of about 28 GHz or at one or more other frequencies, which may include frequencies used by patch antennas **110**. The end-fire antennas **112** may be configured to operate having a directionality that is mostly parallel to the top surface of the insulation substrate **100** (see FIG. **11**). Four end-fire antennas **112** near each edge of the insulation substrate **100** are shown in FIG. **3B**, but any number of end-fire antennas **112** may be disposed in any arrangement on the top surface of the insulation substrate **100**. The end-fire antennas **112** may be the same size and shape or have different sizes or different shapes. The end-fire antennas **112** shown in FIG. **3B** are intended as representative examples. The end-fire antennas **112** have an L-shape similar to the embodiment shown in FIG. **3B**, but may also have any suitable shape in other embodiments, such as a rectangular shape, an irregular shape, a T-shape, a 2L-shape (e.g., two mirrored L-shapes), an H-shape, the like, or another shape. In some cases, an end-fire antenna **112** may include multiple separated regions, such as an array of parallel lines, though any suitable shapes or combinations of shapes may be used. The end-fire antennas **112** may have lateral dimensions between about 0.6 mm and about 3.0 mm. The embodiments described herein allow for both patch antennas **110** and end-fire antennas **112** to be formed on the same substrate, which may allow for the overall antenna structure **120** (see FIG. **5**) to have a greater antenna coverage (i.e., a larger directionality pattern).

(22) The through-vias formed may include one or more feedline vias **108** and one or more thermal vias **106**, such as those shown in FIGS. **3A-B**. The feedline vias **108** may extend through the insulation substrate **100** to provide electrical connection to patch antennas **110** or other conductive features disposed on the top surface of the insulation substrate **100**. A feedline via **108** may be aligned to a corresponding patch antenna **110** to connect to that patch antenna **110** at any suitable location on that patch antenna **110**. In some embodiments, a patch antenna **110** may be connected to more than one feedline via **108**. In some cases, some conductive material may be formed over an end of a feedline via **108** such that the conductive material extends over a surface of the insulation substrate **100**. In some embodiments, the feedline vias **108** have a lateral width within the insulation substrate **100** that is between about 10  $\mu\text{m}$  and about 300  $\mu\text{m}$ .

(23) The thermal vias **106** may extend through the insulation substrate **100** to facilitate the transfer of heat away from a device (e.g., semiconductor device **220**, see FIG. **11**). The use of thermal vias **106** in this manner may allow for improved thermal dissipation, which can improve performance and reduce the chance of undesired thermal effects, such as temperature-related changes to antenna performance. FIGS. **3A-B** show an example arrangement of thermal vias **106**, but any number of thermal vias **106** may be formed in any arrangement. In some cases, some conductive material may be formed over an end of a thermal via **106** such that the conductive material extends over a surface of the insulation substrate **100**. In some embodiments, the thermal vias **106** have a lateral width

within the insulation substrate **100** that is between about 50  $\mu\text{m}$  and about 500  $\mu\text{m}$ .

(24) Turning now to FIG. 4, a patterned protective layer **116** is formed over both surfaces of the insulation substrate **100**, in accordance with some embodiments. The protective layer **116** may be a solder resist material, and may be formed to protect portions of the insulation substrate **100**, groundplanes **114**, through-vias such as thermal vias **106** or feedline vias **108**, or other conductive features. In some embodiments, the protective layer **116** may be a photosensitive material. The photosensitive material may first be formed over the insulation substrate **100** by printing, lamination, spin-coating, or the like. The photosensitive material may then be exposed to an optical pattern and developed, forming openings in the photosensitive material. In other embodiments, the protective layer **116** may be formed by depositing a non-photosensitive dielectric layer (e.g., silicon oxide, silicon nitride, the like, or a combination), forming a patterned photoresist mask over the dielectric layer using suitable photolithography techniques, and then etching the dielectric layer using the patterned photoresist mask using a suitable etching process (e.g., wet etching or dry etching). The protective layer **116** may be formed and patterned over both sides of the insulation substrate **100** using the same techniques. In some embodiments, the protective layer **116** may have a thickness between about 10  $\mu\text{m}$  and about 100  $\mu\text{m}$ . Other processes and materials may also be used.

(25) In some embodiments, an optional solderability treatment may then be performed on the exposed surfaces of the feedline vias **108**, patch antennas **110**, end-fire antennas **112**, groundplanes **114**, or other conductive features. The treatment may include an electroless nickel-electroless palladium-immersion gold technique (ENEPIG) process, an organic solderability preservative (OSP) process, or the like.

(26) Turning to FIG. 5, conductive connectors **118** are then formed on exposed portions of the feedline vias **108** to form the antenna structure **120**, in accordance with some embodiments. For example, as shown in FIG. 5, connectors **118** may be formed on exposed bottom ends of the feedline vias **108**. In some embodiments, conductive connectors **118** may be formed on exposed portions of other conductive features. The connectors **118** may be, for example, ball grid array (BGA) connectors, solder balls, metal pillars, controlled collapse chip connection (C4) bumps, micro bumps, or the like. The connectors **118** may include a material such as solder, lead-free solder, copper, aluminum, gold, nickel, silver, palladium, tin, the like, or a combination thereof. In some embodiments, the connectors **118** are formed by initially forming a layer of solder through a technique such as evaporation, electroplating, printing, solder transfer, ball placement, or the like. Once a layer of solder has been formed on the structure, a reflow may be performed in order to shape the material into the desired bump shapes.

(27) Turning now to FIGS. 6A through 9B, cross-sectional views and plan views of intermediate steps of forming a device structure **200** (see FIGS. 9A-B) are illustrated, in accordance with some embodiments. With reference now to FIG. 6A, there is illustrated a carrier substrate **201** and a redistribution layer **203** over the carrier substrate **201**. In an embodiment, the carrier substrate **201** includes, for example, silicon based materials, such as glass or silicon oxide, or other materials, such as aluminum oxide, combinations of any of these materials, or the like. The carrier substrate **201** may be planar in order to accommodate a formation of the redistribution structure **210** (see FIG. 7) or other subsequently formed layers.

(28) In some embodiments, a release layer (not shown in FIG. 6A) may be formed on the top surface of the carrier substrate **201** to facilitate subsequent debonding of the carrier substrate **201**. The release layer may be formed of a polymer-based material, which may be removed along with the carrier substrate **201** from the overlying structures that will be formed in subsequent steps. In some embodiments, the release layer is an epoxy-based thermal-release material, which loses its adhesive property when heated, such as a Light-to-Heat-Conversion (LTHC) release coating. In other embodiments, the release layer may be an ultra-violet (UV) glue, which loses its adhesive property when exposed to UV light. The release layer may be dispensed as a liquid and cured, may



be a laminate film laminated onto the carrier substrate **201**, or the like. The top surface of the release layer may be leveled and may have a high degree of co-planarity.

(29) FIG. **6A** shows the formation of a redistribution layer **203** and insulating layers **202** and **204** over the carrier substrate **201**, in accordance with some embodiments. The redistribution layer **203** and insulating layers **202** and **204** may be part of a redistribution structure, such as redistribution structure **210** shown in FIG. **7**. In an embodiment, the insulating layer **202** is formed over the carrier substrate **201** (or release layer, if present). The insulating layer **202** may be made of one or more suitable dielectric materials such as an oxide (e.g., silicon oxide), a nitride (e.g., silicon nitride), a polymer material, a low-k dielectric material, another dielectric material, combinations of these, or the like. The insulating layer **202** may be formed by a process such as spin-coating, lamination, CVD, the like, or a combination thereof. The insulating layer **202** may have a thickness of between about 2  $\mu\text{m}$  and about 25  $\mu\text{m}$ , such as about 7  $\mu\text{m}$ , although any suitable thickness may be used. Openings into the insulating layer **202** may be formed using a suitable photolithographic mask and etching process. For example, a photoresist may be formed and patterned over the insulating layer **202**, and one or more etching processes (e.g., a wet etch process or a dry etch process) are utilized to remove portions of the insulating layer **202**. In some embodiments, the insulating layer **202** is formed of a photosensitive polymer such as PBO, polyimide, BCB, or the like, in which openings may be patterned directly using a photolithographic mask and etching process.

(30) In an embodiment, the redistribution layer **203** may be formed by initially forming a seed layer (not shown) of one or more layers of titanium, copper, or a titanium copper alloy through a suitable formation process such as PVD, CVD, sputtering, or the like. The seed layer is formed over the insulating layer **202** and within openings in the insulating layer **202**. A photoresist (also not shown) may then be formed to cover the seed layer and then be patterned to expose those portions of the seed layer that are located where the redistribution layer **203** will subsequently be formed. Once the photoresist has been formed and patterned, a conductive material may be formed on the seed layer. The conductive material may be a material such as copper, titanium, tungsten, aluminum, another metal, a combination, or the like. The conductive material may be formed through a deposition process such as electroplating or electroless plating, or the like. However, while the material and methods discussed are suitable to form the conductive material, these materials are merely examples. Any other suitable materials or any other suitable processes of formation, such as CVD or PVD, may alternatively be used to form the redistribution layer **203**. Once the conductive material has been formed, the photoresist may be removed through a suitable removal process such as ashing or chemical stripping. Additionally, after the removal of the photoresist, those portions of the seed layer that were covered by the photoresist may be removed through, for example, a suitable wet etch process or dry etch process, which may use the conductive material as an etch mask. The remaining portions of the seed layer and conductive material form the redistribution layer **203**.

(31) In some embodiments, the redistribution layer **203** may be formed using an electrochemical deposition process that fills the openings in the insulating layer **202** with conductive material such that the conductive material remains approximately level during deposition. In some embodiments, the electrochemical deposition process is a copper electroplating process in which the electroplating solution comprises metal ions, an accelerator additive, a suppressor additive, and/or a leveler additive. In some embodiments, the electroplating solution includes the metal ions to be electroplated (e.g., copper ions) and the associated anions in an acid solution. In some embodiments, the electroplating solution may comprise one or more copper salts that provide copper ions, including, for example copper sulfate, copper sulfonate, copper acetate, copper gluconate, copper fluoroborate, cupric nitrate, copper alkanesulfonates, copper arylsulfonates, the like, or a combination. In some embodiments, the copper salt is present in an amount sufficient to provide an amount of copper ions between about 10 g/L and about 180 g/L in the electroplating

solution. The electroplating solution may also comprise alloying elements or chloride ions, in some embodiments. In some embodiments, the acid solution comprises an acid such as sulfuric acid, nitric acid, methanesulfonic acid, phenylsulfonic acid, the like, or a combination thereof. In some embodiments, the electrochemical deposition process is performed at a temperature between about 20° C. and about 60° C. In some embodiments, the current density of the electrochemical deposition process is between about 1 ASD and about 10 ASD.

(32) In some embodiments, the accelerator additive is configured to increase the rate of the electroplating reaction. In some embodiments, the accelerator additive is a molecule which adsorbs on surfaces and increases the local current density at a given applied voltage. In some embodiments, the accelerator additive contains pendant sulfur atoms, which may participate in the cupric ion reduction reaction and thus strongly influence the nucleation and surface growth of metal films. In some embodiments, the accelerator additive comprises bis-(3-sulfopropyl) disulfide (SPS), mercaptopropanesulfonic acid (MPS), dimercaptopropanesulfonic acid (DPS), ethylenedithiodipropyl sulfonic acid, bis-( $\omega$ -sulfobutyl)-disulfide, methyl-( $\omega$ -sulfopropyl)-disulfide, N,N-dimethyldithiocarbamic acid (3-sulfopropyl) ester, (O-ethyldithiocarbonato)-S-(3-sulfopropyl)-ester, 3-[(amino-iminomethyl)-thiol]-1-propanesulfonic acid, 3-(2-benzylthiazolylthio)-1-propanesulfonic acid, bis-(sulfopropyl)-disulfide, alkali metal salts thereof, its derivatives, the like, or a combination thereof. In some embodiments, the accelerator additive has a molecular weight of 100 to 400. In some embodiments, the accelerator additive has a molar concentration between about 10 mol/L and about 20 mol/L.

(33) In some embodiments, the suppressor additive comprises a polymer and is configured to decrease the local current density at a given applied voltage, thus retarding electroplating. In some embodiments, the suppressor additive comprises a polyether compound. In some embodiments, the suppressor additive comprises polyalkylene oxide random copolymers including as polymerized units two or more alkylene oxide monomers or ethylene oxide-propylene oxide random copolymers. In some embodiments, the suppressor additive is derived from polyethylene oxide (PEO), polypropylene oxide (PPO), polyethylene glycol (PEG), polypropylene glycol (PPG), or their derivatives or co-polymers. In some embodiments, the suppressor additive has a molecular weight between about 10000 and about 15000. In some embodiments, the suppressor additive has a molar concentration between about 5 mol/L and about 20 mol/L.

(34) In some embodiments, the leveler additive refers to an organic additive that is capable of providing a substantially planar metal electroplating layer. In some embodiments, the leveler additive comprises one or more nitrogen, amine, imide, imidazole or pyrrolidone groups, and may also comprise sulfur functional groups. In some embodiments, the leveler additive comprises one or more five- and six-member rings and/or conjugated organic compound derivatives. In some embodiments, nitrogen groups may form part of the ring structure. In some embodiments, in the amine-containing leveler additives, the amines are primary, secondary or tertiary alkyl amines. In some embodiments, the amine is an aryl amine or a heterocyclic amine. In some embodiments, the amines include, but are not limited to, dialkylamines, trialkylamines, arylalkylamines, triazoles, imidazole, triazole, tetrazole, benzimidazole, benzotriazole, piperidine, morpholines, piperazine, pyridine, pyrrolidone, oxazole, benzoxazole, pyrimidine, quonoline, isoquinoline, the like, or a combination thereof. In some embodiments, the leveler additive comprises polyvinylpyrrolidone (PVP). In some embodiments, the leveler additive has a molecular weight of 100 to 10000. In some embodiments, the leveler additive has a molar concentration of 10 mol/L to 20 mol/L.

(35) In some embodiments, the concentration of accelerator additive and the leveler additive in the electroplating solution is approximately equal. By having similar concentrations of accelerator additive and leveler additive, the redistribution layer **203** may be formed having a more level surface (e.g., with less dishing or bumps) in redistribution layers **203** of different dimensions (e.g., first redistribution layer portion **203A** and second redistribution layer portion **203B**, discussed below). In some cases, a higher concentration of leveler additive can release surface tension in

larger deposition areas (e.g., **203B**), which allows for a more level surface. In some cases, a higher concentration of accelerator additive can improve the planarity of smaller deposition areas (e.g., **203A**). In some cases, the individual concentrations of accelerator additive and leveler additive may be between about 1-2 times as much as the concentration of suppressor additive.

(36) In some embodiments, a patterned photoresist may be formed to cover portions of the insulating layer **202** on which conductive material is not wished to be deposited. After the conductive material is formed in this manner, the top surface of the conductive material formed within the openings may be about level with the top surface of the conductive material formed over the insulating layer **202**. The use of this deposition process may allow for more planar redistribution structures, which can reduce the chance of process defects and allow for a thinner structure. Once the conductive material has been formed, the photoresist may be removed through a suitable removal process such as ashing or chemical stripping. The remaining portions of the conductive material form the redistribution layer **203**.

(37) In an embodiment, an insulating layer **204** is formed over the redistribution layer **203** and insulating layer **202**, which may be formed in a process and with materials similar to the insulating layer **202**. Alternatively, the insulating layer **204** may be formed differently than the insulating layer **202**.

(38) In some embodiments, the openings formed in the insulating layer **202** may be of different sizes, such that the conductive material subsequently deposited in the openings forms portions of the redistribution layer **203** within the insulating layer **202** have different dimensions. As an example, FIG. 6B illustrates a representative close-up view of a region of the structure shown in FIG. 6A. FIG. 6B shows a first redistribution layer portion **203A** and a second redistribution layer portion **203B** formed in two differently-sized openings in the insulating layer **202**, according to some embodiments. The first redistribution layer portion **203A** has a bottom length DA and a height HA, and the second redistribution layer portion **203B** has a bottom length DB and a height HB. In some embodiments, the length DA may be between about 20  $\mu\text{m}$  and about 100  $\mu\text{m}$ , and the length DB may be between about 100  $\mu\text{m}$  and about 400  $\mu\text{m}$ . In some embodiments, a ratio of DB to DA may be between about 1:1 and about 20:1. In some embodiments, the height HA or the height HB may be between about 2  $\mu\text{m}$  and about 15  $\mu\text{m}$ . In some embodiments, a ratio of HB to HA may be between about 0.7:1 and about 1.3:1.

(39) In some embodiments, the use of redistribution layer **203** portions having different dimensions (e.g., lengths DA or DB) may allow for external connectors (e.g., solder balls or the like) of different sizes to be formed on the redistribution layer **203** portions. For example, an external connector having a smaller size may subsequently be connected to redistribution layer portion **203A** than an external connector connected to redistribution layer portion **203B**. For example, an integrated passive device (IPD) may be connected to the redistribution layer **203**, and may be able to be connected using smaller external connectors. In this manner, connectors of different sizes may be used to more efficiently use space, which may allow for smaller package size. By allowing for more level deposition in redistribution layer portions having different dimensions, the use of the electrochemical deposition process described above can facilitate the use of redistribution layer portions having different dimensions by improving process uniformity and improving electrical connections to the redistribution layer portions.

(40) Turning to FIG. 7, additional insulating layers and redistribution layers are used to form redistribution structure **210**. In an embodiment, after the insulating layer **204** has been formed over the redistribution layer **203**, openings may be made through the insulating layer **204** by removing portions of the insulating layer **204** to expose at least a portion of the underlying redistribution layer **203**. The openings allow for contact between the redistribution layer **203** and an overlying redistribution layer **205** (described further below). The openings may be formed using a suitable photolithographic mask and etching process, although any suitable process to expose portions of the redistribution layer **203** may alternatively be used.

(41) The redistribution layer **205** may be formed to provide additional routing along with electrical connection within the redistribution structure **210**. In an embodiment, the redistribution layer **205** may be formed using materials and processes similar to the redistribution layer **203**. For example, a seed layer may be formed, a photoresist may be placed and patterned on top of the seed layer in a desired pattern for the redistribution layer **205**, conductive material is plated into the patterned openings of the photoresist, the photoresist is removed, and the seed layer is etched. The redistribution layer **205** may also be formed using an electrochemical deposition process.

(42) After the redistribution layer **205** has been formed, an insulating layer **206** may be formed over the redistribution layer **205**. In an embodiment, the insulating layer **206**, which may be similar to the insulating layers **202** or **204**, may be formed from a polymer such as PBO, or may be formed of a similar material as the insulating layer **202** or **204** (e.g., polyimide or a polyimide derivative). The insulating layer **206** may be formed to have a thickness of between about 2  $\mu\text{m}$  and about 15  $\mu\text{m}$ , such as about 5  $\mu\text{m}$ .

(43) After the insulating layer **206** has been formed, openings may be made through the insulating layer **206** by removing portions of the insulating layer **206** to expose at least a portion of the underlying redistribution layer **205**. The openings allow for contact between the redistribution layer **205** and an overlying redistribution layer **207**. The openings may be formed using a suitable photolithographic mask and etching process, although any suitable process to expose portions of the redistribution layer **205** may be used.

(44) The redistribution layer **207** may be formed to provide additional routing along with electrical connection within the redistribution structure **210**. In an embodiment, the redistribution layer **207** may be formed using materials and processes similar to the redistribution layers **203**, or **205**. For example, a seed layer may be formed, a photoresist may be placed and patterned on top of the seed layer in a desired pattern for the redistribution layer **207**, conductive material is plated into the patterned openings of the photoresist, the photoresist is removed, and the seed layer is etched.

(45) After the redistribution layer **207** has been formed, an insulating layer **208** may be formed over the redistribution layer **207**. In an embodiment, the insulating layer **208**, which may be similar to the insulating layers **202**, **204**, or **206**, may be formed from a polymer such as PBO, or may be formed of a similar material as the insulating layer **202**, **204** or **206** (e.g., polyimide or a polyimide derivative). The insulating layer **208** may be formed to have a thickness of between about 2  $\mu\text{m}$  and about 15  $\mu\text{m}$ , such as about 5  $\mu\text{m}$ .

(46) After the insulating layer **208** has been formed, openings may be made through the insulating layer **208** by removing portions of the insulating layer **208** to expose at least a portion of the underlying redistribution layer **207**. The openings allow for contact between the redistribution layer **207** and an overlying redistribution layer **209**. The openings may be formed using a suitable photolithographic mask and etching process, although any suitable process to expose portions of the redistribution layer **207** may be used.

(47) The redistribution layer **209** may be formed to provide additional routing along with electrical connection within the redistribution structure **210**. In an embodiment, the redistribution layer **209** may be formed using materials and processes similar to the redistribution layers **203**, **205**, or **207**. For example, a seed layer may be formed, a photoresist may be placed and patterned on top of the seed layer in a desired pattern for the redistribution layer **209**, conductive material is plated into the patterned openings of the photoresist, the photoresist is removed, and the seed layer is etched. In other embodiments, different numbers of insulating layers or redistribution layers may be formed in the redistribution structure **210** than those described herein. In some embodiments, the redistribution structure **210** may be, for example, a fan-out structure.

(48) Turning to FIGS. **8A-B**, conductive pillars **214** and dipole antennas **212** are formed over the redistribution layer **209**. FIG. **8B** shows a plan view, and FIG. **8A** shows a cross-sectional view along the cross-section B-B' labeled in FIG. **8B**. In some embodiments, the conductive pillars **214** and dipole antennas **212** are formed by initially forming a photoresist over the insulating layer **208**

and redistribution layer **209** and then patterning the photoresist into the desired pattern for the conductive pillars **214** and dipole antennas **212**. The patterned photoresist may expose portions of the redistribution layer **209**. The conductive material (e.g., copper or the like) may be formed over the patterned photoresist to form the conductive pillars **214** and dipole antennas **212**. The conductive material may be formed using a suitable process such as plating, electroless plating, CVD, PVD, or the like. After deposition of the conductive material, the photoresist and any excess conductive material may be removed using, for example, a wet chemical process and/or a dry process (e.g., an ashing process).

(49) In some embodiments, the conductive pillars **214** and the dipole antennas **212** may be formed having a thickness between about 40  $\mu\text{m}$  and about 400  $\mu\text{m}$ . The conductive pillars **214** may have a rectangular shape, a circular shape, or another shape, and may be formed having a width between about 40  $\mu\text{m}$  and about 300  $\mu\text{m}$ . The dipole antennas **212** may be formed having any suitable dimensions or shape, which may depend on the antenna frequencies appropriate for the application, or which may depend on other desired antenna characteristics. In some embodiments, different dipole antennas **212** having different dimensions may be formed on the same structure. In some embodiments, the dipole antenna **212** comprises an L-shaped element having a width between about 0.6 mm and about 5 mm and a length between about 0.6 mm and about 5 mm. FIG. **8B** shows an embodiment having three dipole antennas **212** on each side of the structure and four conductive pillars **214**, but any number of conductive pillars **214** or dipole antennas **212** may be formed having any suitable arrangement. In some cases, forming the dipole antennas **212** on the redistribution layer **209** may decrease the routing distance between the dipole antennas **212** and semiconductor devices **220** (see FIGS. **9A-B** below) connected to the redistribution layer **209**. Decreasing the routing distance can decrease power consumption, improve power integrity, and/or improve the signal-to-noise ratio of the dipole antennas **212**.

(50) FIGS. **9A-B** illustrate connections of semiconductor devices **220** to the redistribution structure **210**, according to some embodiments. Connecting one or more semiconductor devices **220** to the redistribution structure **210** forms a device structure **200**. FIG. **9A** shows an embodiment of a device structure **200** in which one semiconductor device **220** is connected to the redistribution structure **210**, and FIG. **9B** shows an embodiment of a device structure **200** in which multiple semiconductor devices **220A** and **220B** are connected to the redistribution structure **210**. The semiconductor devices **220A** and **220B** may be different types of semiconductor devices. In other embodiments, more than two semiconductor devices **220** may be connected to the redistribution structure **210**. In some embodiments, a semiconductor device **220** may be a device that provides logic functions for connected structures, a radio frequency chip (e.g., an RFIC), a radio frequency front end (RFFE) device, an amplifier device (e.g., a low-noise amplifier or a power amplifier), a filter device (e.g., a low-loss filter), a baseband logic device, a power management integrated circuit (PMIC), a surface mounted device (SMD), the like, or a combination.

(51) In some embodiments, the semiconductor device **220** includes contact pads **221** electrically connected to the semiconductor device **220**. The contact pads **221** may be connected to the redistribution layer **209** of the redistribution structure **210** by external connectors **222**, thus connecting the semiconductor device **220** to the redistribution structure **210**. The external connectors **222** may be conductive bumps (e.g., microbumps) or conductive pillars utilizing materials such as solder and copper. In an embodiment in which the external connectors **222** are contact bumps, the external connectors **222** may include a material such as tin or other suitable materials, such as silver, lead-free tin, or copper. In an embodiment in which the external connectors **222** are tin solder bumps, the external connectors **222** may be formed by initially forming a layer of tin through such commonly used methods such as evaporation, electroplating, printing, solder transfer, ball placement, etc., to a thickness of, e.g., about 20  $\mu\text{m}$ . Once a layer of tin has been formed on the structure, a reflow may be performed in order to shape the material into the desired bump shape.

(52) Once formed, the semiconductor device **220** may be placed on the redistribution layer **209** using, e.g., a pick and place tool. For example, the external connectors **222** of the semiconductor device **220** may be aligned with and placed in physical contact with corresponding locations of the redistribution layer **209**. Once in physical contact, a reflow process may be performed in order to reflow the first external connectors **222** and bond the semiconductor device **220** with the redistribution layer **209**. For the embodiment shown in FIG. **9B**, both semiconductor devices **220A** and **220B** may be placed and bonded using a similar technique. After bonding, a semiconductor device **220** may have a height above the redistribution structure **210** that is greater than the height of the dipole antennas **212** or conductive pillars **214**, as shown in FIGS. **9A-B**, but a semiconductor device **220** may have a height above the redistribution structure **210** that is about the same or less than the height of the dipole antennas **212** or conductive pillars **214** in other embodiments. In some embodiments, a semiconductor device **220** and a dipole antenna **212** or conductive pillar **214** may have a difference in heights that is between about 50  $\mu\text{m}$  and about 300  $\mu\text{m}$ . In some embodiments, different semiconductor devices **220** (e.g., **220A** and **220B**) may have different heights above the redistribution structure **210** after bonding.

(53) Once the semiconductor device **220** has been bonded (multiple semiconductor devices **220A** and **220B** may be bonded either simultaneously or separately), an underfill material **223** may be placed between the redistribution structure **210** and the semiconductor device **220** (or between the redistribution structure **210** and the semiconductor devices **220A** and **220B**) in order to help protect and isolate the devices. In an embodiment, the underfill material **223** is a protective material used to cushion and support the semiconductor device **220** from operational and environmental degradation, such as stresses caused by the generation of heat during operation. The underfill material **223** may include, for example, a liquid epoxy or other protective material, which may be cured to harden, and which may be dispensed by, e.g., injection.

(54) FIG. **10A** illustrates a placement of the antenna structure **120** into electrical connection with the device structure **200**, forming antenna package **300**. In an embodiment, the connectors **118** (on the antenna structure **120**) are placed into physical contact with the conductive pillars **214** of the device structure **200** using, e.g., a pick and place process. Once in physical contact, a reflow process may be utilized to bond the connectors **118** of the antenna structure **120** to the conductive pillars **214**. In some embodiments, a vertical gap is present between a top surface of a semiconductor device **220** and a bottom surface of the antenna structure **120**, which may be between about 10  $\mu\text{m}$  and about 100  $\mu\text{m}$ . In some embodiments, no vertical gap is present between the semiconductor device **220** and the antenna structure **120**.

(55) Once the antenna structure **120** has been connected to the device structure **200**, a molding material **302** may be formed between the antenna structure **120** and the device structure **200**. In an embodiment, the molding material **302** may be an encapsulant or a molding compound and may be placed using a molding device. For example, the carrier substrate **201** may be placed within a cavity of the molding device, and the cavity may be hermetically sealed. The molding material **302** may be placed within the cavity either before the cavity is hermetically sealed or else may be injected into the cavity through an injection port. In other embodiments, the molding material **302** may be formed using another suitable technique. In some embodiments, the molding material **302** may be a molding compound resin such as polyimide, PPS, PEEK, PES, a heat resistant crystal resin, combinations of these, or the like. In some embodiments, the molding material **302** may be an underfill material such as a molding underfill material. In some embodiments, the molding material **302** may have the same composition as the underfill material **223**. In some embodiments, the molding material **302** may be cured after formation, for example, using a heating process, exposure to UV radiation, or another suitable process.

(56) By disposing the semiconductor device **220** between the redistribution structure **210** and the antenna structure **120**, the semiconductor device **220** may be located closer to features such as dipole antennas **212** or patch antennas **110**, which can reduce power consumption and improve

higher-frequency operation of the antenna package **300**. Additionally, the thermal vias **106** of the antenna structure **120** being disposed above the semiconductor device **220** can allow for improved thermal dissipation, as the thermal vias **106** are able to facilitate the transfer of heat away from the semiconductor device **220**. In some embodiments, a thermal adhesive layer **304** may be disposed between the semiconductor device **220** and the antenna structure **120** to also facilitate heat transfer to the thermal vias **106**. An embodiment antenna package **300** having a thermal adhesive layer **304** is shown in FIG. **10B**. The thermal adhesive layer **304** may be formed on the semiconductor device **220** prior to or after placement on the redistribution structure **210**. In some embodiments, the thermal adhesive layer **304** may be a material such as high thermal conductivity polymer films, silver pastes, thermal interface materials (TIM), graphene, the like, or a combination. The thermal adhesive layer **304** may have a thickness between about 5  $\mu\text{m}$  and about 50  $\mu\text{m}$ .

(57) FIG. **10C** shows an embodiment of an antenna package **300** in which the conductive pillar **214** protrudes from a bonding pad **215**. A close-up view of an example bonding pad **215**, conductive pillar **214**, and connector **118** is also shown in FIG. **10C**. The bonding pad **215** extends over the surface of the insulating layer **208**, and may be formed as part of the redistribution layer **209**. As described previously (see FIG. **10A**), after placing a connector **118** made of a solder material on a conductive pillar **214**, a reflow process may be performed. Due to wetting action during the reflow process, the solder material of the connector **118** may spread over the top surface of the bonding pad **215**, which may cause the connector **118** to have a more vertical profile after the reflow process is completed. By controlling the dimensions of the bonding pad **215** and the conductive pillar **214**, the profile shape of the connector **118** may be controlled. For example, the profile shape of the connector **118** may be controlled by e.g., an amount of material used for the connector **118**, to be vertical, straight, tapered, convex, or another shape. In some embodiments, a height H1 of the conductive pillar **214** may be between about 3  $\mu\text{m}$  and about 100  $\mu\text{m}$ . In some embodiments, the height H2 of the connector **118** may be between about 80  $\mu\text{m}$  and about 400  $\mu\text{m}$  after reflow. The height H2 may be greater than the height H1. In some embodiments, the width D1 of the conductive pillar **214** may be between about 20  $\mu\text{m}$  and about 200  $\mu\text{m}$ . In some embodiments, the width D2 of the connector **118** may be between about 80  $\mu\text{m}$  and about 250  $\mu\text{m}$  after joining. The width D2 may be greater than the width D1. In some embodiments, the upper regions of the connector **118** may have a width D2' that is the same as a width D2 of lower regions of the connector **118**, but in some cases the ratio between a width D2' and a width D2 may be between about 0.8 and about 1.2. The conductive pillar **214** or the connector **118** may include one layer or multiple layers of materials.

(58) FIG. **11** illustrates a debonding of the carrier substrate **201** and a placement of external connections **306** to the antenna package **300**. In an embodiment, the carrier substrate **201** may be debonded from the structure using, e.g., a thermal process to alter the adhesive properties of a release layer disposed on the carrier substrate **201**. In a particular embodiment an energy source such as an ultraviolet (UV) laser, a carbon dioxide (CO.sub.2) laser, or an infrared (IR) laser, is utilized to irradiate and heat the release layer until the release layer loses at least some of its adhesive properties. Once performed, the carrier substrate **201** and the release layer may be physically separated and removed from the structure.

(59) The external connections **306** are formed or placed in electrical connection with the redistribution layer **203**. In some embodiments, the external connections **306** may be a ball grid array (BGA) including a eutectic material such as solder, although any suitable materials may be used. In an embodiment, in which the external connections **306** are solder balls, the external connections **306** may be formed using a ball drop method, such as a direct ball drop process. In another embodiment, the solder balls may be formed by initially forming a layer of tin through any suitable method such as evaporation, electroplating, printing, solder transfer, and then performing a reflow in order to shape the material into the desired bump shape.

(60) Once the external connections **306** have been formed or placed, the structure may be

singulated into a discrete antenna package **300**, as shown in FIG. **11**. In an embodiment, the structure may be singulated using one or more saw blades that separate the structure into discrete pieces. However, any suitable method of singulation, including laser ablation or one or more wet etches, may also be utilized.

(61) By forming an antenna package **300** as described, multiple types of antennas can be integrated into a single package. For example, the antenna package **300** includes patch antennas **110** having a vertical directionality, end-fire antennas **112** having a lateral directionality, and dipole antennas **212** also having a lateral directionality. Through the use of multiple types of antennas, the directionality and beam-steering of the overall antenna package **300** may be improved. For example, by using both end-fire antennas **112** and dipole antennas **212**, the range, shape, and strength of the lateral directionality can be increased. The use of multiple types of antennas can also allow for multiple-in/multiple-out (MIMO) antenna operation. In particular, the use of multiple types of antennas can allow for individual antennas having a smaller size or for antenna arrays having fewer elements, which can reduce the overall size of the antenna package. The use of multiple types of antennas as described can also allow for more flexibility in the size, shape, design, or arrangement of the antennas. In some cases, the improved design flexibility may allow for improved bandwidth or for improved frequency control of the antennas.

(62) FIGS. **12** through **16** illustrate intermediate steps of forming an antenna package **600** (see FIG. **16**), in accordance with some embodiments. FIG. **12** illustrates a cross-sectional view an antenna structure **400**, in accordance with some embodiments. FIGS. **13-15** illustrate cross-sectional views of intermediate steps of forming a device structure **500**, in accordance with some embodiments. FIG. **16** illustrates a cross-sectional view an antenna package **600**, in accordance with some embodiments.

(63) FIG. **12** illustrates an antenna structure **400**, in accordance with some embodiments. The antenna structure **400** may be similar to the antenna structure **120** described previously with respect to FIGS. **1-5**, except that the antenna structure **400** is a multi-level structure, and that no thermal vias are present. In some embodiments, the antenna structure **400** may be formed in a manner similar to that described for antenna structure **120** in FIGS. **1-5**. For example, the antenna structure **400** may be formed from a core substrate that includes a first insulation substrate **100A** having conductive layers disposed on opposite surfaces, which may be similar to conductive layers **102** (see FIG. **1**). The conductive material may be deposited in a manner similar to that described with respect to FIGS. **2** and **3A**.

(64) A second insulation substrate **100B** having a conductive layer on a surface may then be attached to the first insulation substrate **100A**, the conductive layer facing away from the first insulation substrate **100A**. The first insulation substrate **100A** or the second insulation substrate **100B** may be similar to the insulation substrate **100** described in FIG. **1**. After attaching the second insulation substrate **100B**, openings may be formed in the second insulation substrate **100B** to expose the conductive material on the first insulation substrate **100A**. Then, conductive material may be deposited having a pattern on the second insulation substrate **100B**, similar to FIGS. **2** and **3A**. Connectors **118** are attached to the conductive material, and may be similar to connectors **118** described in FIG. **5** and may be formed in a similar manner. A protective layer **116** similar to protective layer **116** may also be formed, and other steps such a solderability treatment may also be performed as described previously.

(65) In this manner, a multilayer antenna structure **400** may be formed from insulation substrates, and an example of a three-layer structure is shown in FIG. **12**. In some embodiments, additional insulation substrates and conductive material may be used to form a multilayer antenna structure **400** having another number of layers such as 4 or more layers. As shown in FIG. **12**, the antenna structure **400** includes end-fire antennas **112** formed on a top surface of the first insulation substrate **100A**. The end-fire antennas **112** may be similar to the end-fire antennas **112** described previously (see FIGS. **3A-B**). The antenna structure **400** also includes parasitic patch antennas **410** and



directly-driven patch antennas **408** that are electrically connected to feedline vias **409**. The patch antennas **408/410** or feedline vias **409** may be similar to those described previously (see FIGS. **3A-B**). In other embodiments, the feedline vias **409** are electrically connected to conductive features and the patch antennas **408** are driven directly through the electrical connection. Any suitable combination of parasitic patch antennas **410** and directly-driven patch antennas **408** may be used. (66) The multilayer antenna structure **400** shown in FIG. **12** includes conductive routing, which may be formed in any layer of conductive material. The multilayer antenna structure **400** also includes a groundplane **402** formed on the bottom surface of the second insulation substrate **100B** and connected to external connectors **118**. The groundplane **402** may be, for example, the groundplane associated with the patch antennas **408**. FIG. **12** shows the antenna structure having a single groundplane **402**, but in other embodiments, two or more groundplanes **402** may be formed. In some embodiments, the groundplane **402** may be connected to one external connector **118** or more than two external connectors **118**. In some embodiments, the groundplane **402** may have a lateral dimension (length or width) between about 3 mm and about 15 mm.

(67) Turning to FIGS. **13-15**, a device structure **500** is formed according to some embodiments. In FIG. **13**, a redistribution structure **210** is formed over a carrier substrate **201**. The redistribution structure **210** may be formed in a manner similar to that described previously with regard to FIGS. **6A-7**. For example, the redistribution structure **210** may be formed from a series of seed layers and plating processes which are used to build up successive layers of redistribution layers and insulating layers. In some embodiments, the redistribution structure **210** described with respect to FIGS. **13-16** may have fewer layers than the redistribution structure **210** described with respect to FIGS. **6A-7**. For example, the redistribution structure **210** shown in FIGS. **13-16** may have two redistribution layers or three redistribution layers instead of the four redistribution layers shown.

(68) In FIG. **14**, dipole antennas **212** and conductive pillars **214** are formed over and connected to the redistribution structure **210**. The dipole antennas **212** and conductive pillars **214** may be similar to those described previously with respect to FIGS. **8A-B**, and may be formed in a similar manner. For example, a photoresist may be formed over the redistribution structure **210** and patterned where the dipole antennas **212** and the conductive pillars **214** are desired to be formed, and a conductive material deposited onto the exposed portions of the redistribution structure **210**. Once formed, the photoresist and excess conductive material may be removed.

(69) In FIG. **15**, a semiconductor device **220** is connected to the redistribution structure **210**. The semiconductor device **220** may be one or more semiconductor devices **220** similar to those described previously with respect to FIGS. **9A-B**, and may be connected to the redistribution structure **210** in a similar manner. The semiconductor device **220** may have a height above the redistribution structure **210** that is lower than, about the same, or higher than a height of the dipole antennas **212** or conductive pillars **214**.

(70) Turning to FIG. **16**, an antenna package **600** is formed by bonding the antenna structure **400** to the device structure **500**, and a molding material **302** is formed between the antenna structure **400** and the device structure **500**. The antenna structure **400** may be bonded to the device structure **500** in a manner similar to that previously described for FIGS. **10A-C**. For example, the connectors **118** of the antenna structure **400** may be placed on the conductive pillars **214** of the device structure **500**, and then a reflow process may be performed. A molding material **302** may then be formed, which may be similar to the molding material **302** described previously for FIGS. **10A-C**.

(71) In an embodiment, the carrier substrate **201** may be debonded from the structure using, e.g., a thermal process to alter the adhesive properties of a release layer disposed on the carrier substrate **201**. In a particular embodiment an energy source such as an ultraviolet (UV) laser, a carbon dioxide (CO<sub>2</sub>) laser, or an infrared (IR) laser, is utilized to irradiate and heat the release layer until the release layer loses at least some of its adhesive properties. Once performed, the carrier substrate **201** and the release layer may be physically separated and removed from the structure. External connections **306** may then be formed or placed in electrical connection with the

redistribution structure **210**. The external connections **306** may be similar to the external connections **306** described previously with respect to FIG. **11**.

(72) By having an antenna package **600** with a groundplane **402** formed in a multilayer antenna structure **400** as shown in FIG. **16**, performance of the antenna package **600** may be improved. For example, a single large groundplane or a groundplane connected to the device structure **500** by multiple connectors **118** (e.g., a groundplane similar to groundplane **402** shown in FIG. **16**) may have more stable electrical performance or provide stronger grounding for the patch antennas **408/410**. In this manner, the performance of the patch antennas **410** may also be improved. In some embodiments, the use of a multilayer antenna structure **400** may allow for more routing to be formed in the antenna structure **400**, and thus less routing (e.g., redistribution layers) may be formed in the redistribution structure **210**. By forming more of the routing in the antenna structure **400**, the cost of the antenna package **600** may be reduced.

(73) FIGS. **17** through **21** illustrate intermediate steps of forming an antenna package **900** (see FIG. **21**), in accordance with some embodiments. FIG. **17** illustrates a cross-sectional view of an antenna structure **700**, in accordance with some embodiments. FIGS. **18-20** illustrate cross-sectional views of intermediate steps of forming a device structure **800** (see FIG. **20**), in accordance with some embodiments. FIG. **21** illustrates a cross-sectional view of the antenna package **900**, in accordance with some embodiments.

(74) FIG. **17** illustrates an antenna structure **700**, in accordance with some embodiments. The antenna structure **700** may be similar to the antenna structure **120** described previously with respect to FIGS. **1-5**, except that the thermal vias **106** are connected by a conductive layer **701**. In some embodiments, the antenna structure **700** may be formed in a manner similar to that described for antenna structure **120** in FIGS. **1-5**. For example, the antenna structure **700** may be formed from a core substrate that includes an insulation substrate **100** having conductive layers disposed on opposite surfaces, which may be similar to conductive layers **102** (see FIG. **1**). Openings may be formed through the insulation substrate **100**, and then conductive material may be deposited having a pattern to form through-via structures (e.g. feedline vias **108** or thermal vias **106**) or other conductive features such as antennas (e.g., patch antennas **110** or end-fire antennas **112**), features such as parasitic elements **703** or conductive elements **702** (described below), or other features such as groundplanes, routing, etc. The conductive material may be deposited in a manner similar to that described with respect to FIGS. **2** and **3A**. The patch antennas **110**, end-fire antennas **112**, feedline vias **108**, and thermal vias **106** may be similar to those described previously (see FIGS. **3A-B**). Connectors **118** are attached to the conductive material on the bottom surface of the insulation substrate **100**, and may be similar to connectors **118** described in FIG. **5** and may be formed in a similar manner. In some embodiments, the connectors **118** are electrically connected to conductive elements **702**, and the conductive elements **702** are directly driven by signals conducted through the connectors **118**. In some embodiments, parasitic patch antennas **110** may be connected by feedline vias **108** to parasitic elements **703** disposed on the opposite side of the insulation substrate **100** from the patch antennas **110**. The parasitic elements **703** may be parasitically driven by the conductive elements **702**, which also parasitically drives the patch antennas **110** through the feedline vias **108**. A protective layer **116** similar to protective layer **116** may also be formed, and other steps such a solderability treatment may also be performed as described previously.

(75) Turning to FIGS. **18-20**, a device structure **800** (see FIG. **20**) is formed according to some embodiments. In FIG. **18**, a redistribution structure **210** is formed over a carrier substrate **201**. The redistribution structure **210** may be formed in a manner similar to that described previously with regard to FIGS. **6A-7**. For example, the redistribution structure **210** may be formed from a series of seed layers and plating processes which are used to build up successive layers of redistribution layers and insulating layers. In some embodiments, the redistribution structure **210** described with respect to FIGS. **18-21** may have fewer layers than the redistribution structure **210** described with respect to FIGS. **6A-7**. For example, the redistribution structure **210** shown in FIGS. **18-21** may

have two redistribution layers or three redistribution layers instead of the four redistribution layers shown.

(76) Also shown in FIG. 18, dipole antennas **212** and conductive pillars **214** are formed over and connected to the redistribution structure **210**. The dipole antennas **212** and conductive pillars **214** may be similar to those described previously with respect to FIGS. 8A-B, and may be formed in a similar manner. For example, a photoresist may be formed over the redistribution structure **210** and patterned where the dipole antennas **212** and the conductive pillars **214** are desired to be formed, and a conductive material deposited onto the exposed portions of the redistribution structure **210**. Once formed, the photoresist and excess conductive material may be removed. A semiconductor device **220** is then connected to the redistribution structure **210**. The semiconductor device **220** may be one or more semiconductor devices **220** similar to those described previously with respect to FIGS. 9A-B, and may be connected to the redistribution structure **210** in a similar manner. The semiconductor device **220** may have a height above the redistribution structure **210** that is lower than or about the same as a height of the dipole antennas **212** or conductive pillars **214**.

(77) Turning to FIG. 19, a molding material **302** is formed over the redistribution structure **210**, the dipole antennas **212**, the conductive pillars **214**, and the semiconductor device **220**. The molding material **302** may be similar to the molding material **302** described previously for FIGS. 10A-C. After forming the molding material **302**, a planarization process (e.g., a CMP process) may be performed. The planarization process may expose top surfaces of the dipole antennas **212**, conductive pillars **214**, or semiconductor device **220**. In some embodiments, a thermal adhesive (not shown in FIG. 19) similar to the thermal adhesive **304** (see FIG. 10B) may be formed over the semiconductor device **220** prior to formation of the molding material **302**.

(78) In FIG. 20, a patterned conductive layer is formed over the molding material **302** and the conductive pillars **214**, forming bonding pads **802**, groundplane **804**, routing, or other conductive features. In an embodiment, a photoresist layer is formed over the structure and then patterned to expose portions of the conductive pillars **214** and molding material **302** over which the conductive material is to be formed. The conductive material may then be deposited using a process such as CVD, PVD, plating, or the like. In some embodiments, the conductive material may be copper, titanium, tungsten, aluminum, another metal, a combination, or the like. After the conductive material has been deposited, the photoresist and excess conductive material may be removed using a wet chemical process and/or a dry process (e.g., an ashing process). In some embodiments, the conductive material may be formed having a thickness between about 5  $\mu\text{m}$  and about 20  $\mu\text{m}$ . In this manner, a device structure **800** may be formed.

(79) As shown in FIG. 20, the conductive material may be formed over conductive pillars **214** to form bonding pads **802**, used for subsequent bonding to the connectors **118** of the antenna structure **700** (see FIG. 21). One or more groundplanes **804** may also be formed from the conductive material, portions of which may be formed over and connected to conductive pillars **214**. In some embodiments, the groundplane **804** may have a lateral dimension (length or width) between about 3 mm and about 15 mm. As shown in FIG. 20, the groundplane **804** may be formed extending over the semiconductor device **220**. The groundplane **804** is shown connected to two conductive pillars **214**, but in other embodiments the groundplane may be connected to one conductive pillar **214** or more than two conductive pillars **214**.

(80) Turning to FIG. 21, an antenna package **900** is formed by bonding the antenna structure **700** to the device structure **800**, and a molding material **902** is formed between the antenna structure **700** and the device structure **800**. The antenna structure **700** may be bonded to the device structure **800** in a manner similar to that previously described for FIGS. 10A-C. For example, the connectors **118** of the antenna structure **700** may be placed on the bonding pads **802** of the device structure **800**, and then a reflow process may be performed. A molding material **902** may then be formed, which may be similar to the molding material **302** described previously for FIGS. 10A-C, and which may be formed in a similar manner.

(81) By forming the groundplane **804** as part of the device structure **800** instead of as part of the antenna structure **700**, more space in the antenna structure **700** may be available for forming additional routing, antennas, or other conductive features. In some embodiments, more routing formed in the antenna structure **700** may allow for fewer redistribution layers to be formed in the redistribution structure **210**. More available space for conductive features may also allow greater design flexibility for the routing, antennas, etc. For example, dipole antennas **212**, patch antennas **110**, or end-fire antennas **112** may be formed having larger sizes, or additional dipole antennas **212**, patch antennas **110**, or end-fire antennas **112** may be formed. In some embodiments, an additional groundplane may be formed in the antenna structure (e.g., groundplane **114** shown in FIG. 3A or groundplane **402** shown in FIG. 12, or the like) to provide improved electrical performance and more stable antenna operation.

(82) FIGS. 22 through 24 illustrate intermediate steps of forming an antenna package **1200** (see FIG. 24), in accordance with some embodiments. FIG. 22 illustrates a cross-sectional view an antenna structure **1000**, in accordance with some embodiments. FIG. 23 illustrates a cross-sectional view of a device structure **1100**, in accordance with some embodiments. FIG. 24 illustrates a cross-sectional view an antenna package **1200**, in accordance with some embodiments.

(83) FIG. 22 illustrates an antenna structure **1000**, in accordance with some embodiments. The antenna structure **1000** may be similar to the antenna structure **120** described previously with respect to FIGS. 1-5, except a groundplane **1001** is connected to multiple connectors **118**. In other embodiments, more than one groundplane **1001** may be formed, and the groundplane **1001** may be connected to any number of connectors **118**. In some embodiments, the antenna structure **1000** may be formed in a manner similar to that described for antenna structure **120** in FIGS. 1-5. For example, the antenna structure **1000** may be formed from a core substrate that includes an insulation substrate **100** having conductive layers disposed on opposite surfaces, which may be similar to conductive layers **102** (see FIG. 1). Openings may be formed through the insulation substrate **100**, and then conductive material may be deposited having a pattern to form through-via structures (e.g. feedline vias **108**) or other conductive features such as antennas (e.g., patch antennas **110** or end-fire antennas **112**), groundplanes **1001**, routing, etc. The conductive material may be deposited in a manner similar to that described with respect to FIGS. 2 and 3A. The patch antennas **110**, end-fire antennas **112**, and feedline vias **108** may be similar to those described previously (see FIGS. 3A-B). Connectors **118** are attached to the conductive material (e.g., the feedline vias **108** and groundplane **1001**) on the bottom surface of the insulation substrate **100**, and may be similar to connectors **118** described in FIG. 5 and may be formed in a similar manner. A protective layer **116** similar to protective layer **116** may also be formed, and other steps such a solderability treatment may also be performed as described previously.

(84) Turning to FIGS. 23, a device structure **1100** is formed according to some embodiments. A redistribution structure **210** is formed over a carrier substrate **201**. The redistribution structure **210** may be formed in a manner similar to that described previously with regard to FIGS. 6A-7. For example, the redistribution structure **210** may be formed from a series of seed layers and plating processes which are used to build up successive layers of redistribution layers and insulating layers. In some embodiments, the redistribution structure **210** described with respect to FIG. 23 may have fewer layers than the redistribution structure **210** described with respect to FIGS. 6A-7. For example, the redistribution structure **210** shown in FIG. 23 may have two redistribution layers or three redistribution layers instead of the four redistribution layers shown.

(85) Also shown in FIG. 23, dipole antennas **212** and conductive pillars **214** are formed over and connected to the redistribution structure **210**. The dipole antennas **212** and conductive pillars **214** may be similar to those described previously with respect to FIGS. 8A-B, and may be formed in a similar manner. For example, a photoresist may be formed over the redistribution structure **210** and patterned where the dipole antennas **212** and the conductive pillars **214** are desired to be formed, and a conductive material deposited onto the exposed portions of the redistribution structure **210**.

Once formed, the photoresist and excess conductive material may be removed.

(86) A semiconductor device **220** is then connected to the redistribution structure **210**. The semiconductor device **220** may be connected to the redistribution structure **210** in a similar manner as described previously with respect to FIGS. **9A-B**. The semiconductor device **220** may have a height above the redistribution structure **210** that is lower than, about the same, or higher than a height of the dipole antennas **212** or conductive pillars **214**.

(87) The semiconductor device **220** may be one or more semiconductor devices **220** similar to those described previously with respect to FIGS. **9A-B**, except that the semiconductor device **220** shown in FIG. **23** has a conductive layer **225** formed on its top surface. In some embodiments, the conductive layer **225** is formed on the semiconductor device **220** prior to connecting the semiconductor device **220** to the redistribution structure **210**. The conductive layer **225** may be deposited using a process such as CVD, PVD, plating, or the like. In some embodiments, the conductive layer **225** may be copper, titanium, tungsten, aluminum, another metal, a combination, or the like. In some embodiments, the conductive layer **225** is formed having a thickness between about 3  $\mu\text{m}$  and about 20  $\mu\text{m}$ . In some embodiments, the conductive layer **225** is electrically connected to the semiconductor device **220**.

(88) Turning to FIG. **24**, an antenna package **1200** is formed by bonding the antenna structure **1000** to the device structure **1100**, and a molding material **302** is formed between the antenna structure **1000** and the device structure **1100**. The antenna structure **1000** may be bonded to the device structure **1100** in a manner similar to that previously described for FIGS. **10A-C**. For example, the connectors **118** of the antenna structure **700** may be placed on conductive pillars **214** of the device structure **1000**. As shown in FIG. **24**, connectors **118** are also placed on the conductive layer **225** of the semiconductor device **220** to electrically connect the groundplane **1001** to the conductive layer **225**. A reflow process may be performed. A molding material **302** may then be formed, which may be similar to the molding material **302** described previously for FIGS. **10A-C**, and which may be formed in a similar manner.

(89) By connecting the groundplane **1001** to the conductive layer **225** of the semiconductor device **220**, the conductive layer **225** may act as a groundplane in addition to groundplane **1001**. Due to the grounding of the conductive layer **225** in this manner, the size of the groundplane **1001** may be reduced. In some embodiments, the groundplane **1001** may be electrically connected to the redistribution structure **210** through conductive pillars **214**.

(90) By reducing the size of the groundplane **1001** or forming fewer conductive pillars **214**, more space in the antenna structure **1000** may be available for forming additional routing, antennas, or other conductive features. In some embodiments, more routing formed in the antenna structure **1000** may allow for fewer redistribution layers to be formed in the redistribution structure **210**. More available space for conductive features may also allow greater design flexibility for the routing, antennas, etc. For example, dipole antennas **212**, patch antennas **110**, or end-fire antennas **112** may be formed having larger sizes, or additional dipole antennas **212**, patch antennas **110**, or end-fire antennas **112** may be formed.

(91) FIGS. **25** through **30** illustrate intermediate steps of forming an antenna package **1500** (see FIG. **30**) having sidewall antennas **1510**, in accordance with some embodiments. FIGS. **25** and **26** illustrate cross-sectional views of an antenna structure **1300**, in accordance with some embodiments. FIGS. **27-29** illustrate cross-sectional views of intermediate steps of forming a device structure **1400**, in accordance with some embodiments. FIG. **30** illustrates a cross-sectional view an antenna package **1500**, in accordance with some embodiments.

(92) FIG. **25** illustrates an antenna structure **1300**, in accordance with some embodiments. The antenna structure **1300** may be similar to the antenna structure **120** described previously with respect to FIGS. **1-5**, except that through-via structures are formed having an interior dielectric material **1304** (described in greater detail below). In some embodiments, the antenna structure **1300** may be formed in a manner similar to that described for antenna structure **120** in FIGS. **1-5**. For

example, the antenna structure **1300** may be formed from a core substrate that includes an insulation substrate **100** having conductive layers disposed on opposite surfaces, which may be similar to conductive layers **102** (see FIG. 1). Openings may be formed through the insulation substrate **100** using e.g., a laser drilling process. Through-via structures are subsequently formed within the openings (e.g., upper sidewall antennas **1302**, feedline vias **1308**, or thermal vias **1306**, described below). In some embodiments, the openings have a width between about 80  $\mu\text{m}$  and about 300  $\mu\text{m}$ , such as about 100  $\mu\text{m}$ . In some embodiments, the height:width aspect ratio of the openings is between about 3:1 and about 9:1, such as about 5:1. The openings may have the same width or aspect ratio or have different widths or aspect ratios. The height of the openings may correspond to the thickness of the insulation substrate **100**. The openings may have a rectangular shape, a circular shape, or another shape.

(93) In some embodiments, a patterned mask (e.g., a patterned photoresist layer) is then formed over a first side of the insulation substrate **100**, in which openings in the patterned mask correspond to regions on which conductive material will subsequently be formed. The openings in the patterned mask also may expose the openings in the insulation substrate **100**. The conductive material may then be deposited on the insulation substrate **100** and within the openings using, for example, a plating process, an electroless plating process, or another process. In some embodiments, the conductive material is deposited having a thickness between about 3  $\mu\text{m}$  and about 50  $\mu\text{m}$ , such as about 10  $\mu\text{m}$ . The conductive material may be, for example, copper or the like. In this manner, conductive features and through-via structures may be formed. The conductive features may include, for example, patch antennas **110**, end-fire antennas **112**, other types of driven antennas, parasitic antennas, or arrays of antennas. The conductive features may also include groundplanes **114** or other conductive features (e.g., pads, routing, traces, or conductive lines).

(94) In some embodiments, a larger height:width aspect ratio of the openings in the insulation substrate **100** may result in the openings being incompletely filled with the conductive material. In some cases, conductive material deposited on the sidewalls of the openings may not merge to fill the interior region of the opening. As an example, for copper plated to a thickness of about 10  $\mu\text{m}$  on the sidewalls of an opening having about a 500  $\mu\text{m}$ :100  $\mu\text{m}$  height:width aspect ratio, a void may remain extending through the interior region of the opening. Other examples are possible and considered within the scope of this disclosure. In some embodiments, after forming the conductive material, the openings may then be filled with a dielectric material **1304**. The dielectric material **1304** may provide protection for the conductive material and structural support for the antenna structure **1300**. In some embodiments, the dielectric material **1304** may be a material such as a resin, solder mask, or another material. The dielectric material **1304** may be formed using, e.g., a spin-on process or another process.

(95) In this manner, through-via structures may be formed in the antenna structure **1300**. As shown in FIG. 25, the through-via structures may include feedline vias **1308**, thermal vias **1306**, and upper sidewall antennas **1302**. The feedline vias **1308** may be similar in function to the feedline vias **108** described previously with respect to FIG. 3A. For example, the feedline vias **1308** may be connected to patch antennas **110** and the patch antennas **110** may be driven through the feedline vias **1308** (either directly driven or parasitically driven). The thermal vias **1306** may be similar in function to the thermal vias **106** described previously with respect to FIG. 3A. For example, the thermal vias **1306** may be configured to transfer heat from a semiconductor device **220** (see FIG. 30). The upper sidewall antennas **1302** are upper portions of sidewall antennas **1510** formed in the antenna package **1500**, described below with respect to FIG. 30. The feedline vias **1308**, thermal vias **1306**, or upper sidewall antennas **1302** may have similar widths or may have different widths.

(96) Turning to FIG. 26, a representative close-up view of through-via structures **1301** are shown. The through-via structures **1301** may be feedline vias **1308**, thermal vias **1306**, or upper sidewall antennas **1302**. The through-via structures **1301** include dielectric material **1304** surrounded by conductive material **1303**. The conductive material **1303** may be a material such as copper or the

like, as described above. As shown in FIG. 26, conductive material disposed over the through-vias structures **1301** and over the insulation substrate **100** may form pads **1305**. In some cases, the pads **1305** may be part of a conductive feature such as a patch antenna, routing, or another feature. In some embodiments, the conductive material **1303** may have a thickness between about 3  $\mu\text{m}$  and about 50  $\mu\text{m}$ , such as about 10  $\mu\text{m}$ . In some embodiments, a pitch L1 between adjacent through-via structures **1301** may be between about 400  $\mu\text{m}$  and about 100  $\mu\text{m}$ , such as about 250  $\mu\text{m}$ . In some embodiments, a distance L2 between adjacent pads **1305** may be between about 15  $\mu\text{m}$  and about 50  $\mu\text{m}$ , such as about 30  $\mu\text{m}$ . In some embodiments, a width L3 of a pad **1305** may be between about 200  $\mu\text{m}$  and about 350  $\mu\text{m}$ , such as about 220  $\mu\text{m}$ . In some embodiments, the width L4 of a through-via structure **1301** may be between about 150  $\mu\text{m}$  and about 250  $\mu\text{m}$ , such as about 200  $\mu\text{m}$ . The width L4 may correspond to the opening formed in the insulation substrate **100** for the through-via structure **1301**.

(97) Returning to FIG. 25, after depositing the conductive material of the patch antennas **110**, feedline vias **1308**, thermal vias **1306**, upper sidewall antennas **1302**, and other conductive features, the patterned mask layer (e.g., the photoresist) may be removed using a wet chemical process or a dry process (e.g., an ashing process). Conductive material may then be patterned in a similar manner on the opposite side of the insulation substrate **100** to form conductive features (or remaining portions of through-vias) on the opposite side of the insulation substrate **100**. In this manner, the conductive material may form conductive features and through-vias. Connectors **118** are then attached to the conductive material on the bottom surface of the insulation substrate **100**, and may be similar to connectors **118** described in FIG. 5 and may be formed in a similar manner. A protective layer **116** similar to protective layer **116** may also be formed, and other steps such a solderability treatment may also be performed as described previously. In this manner, the antenna structure **1300** may be formed, though the antenna structure **1300** may be formed using other processes in other embodiments.

(98) Turning to FIGS. 27-30, a device structure **1400** (see FIG. 30) is formed according to some embodiments. In FIG. 27, a redistribution structure **210** is formed over a carrier substrate **201**. The redistribution structure **210** may be formed in a manner similar to that described previously with regard to FIGS. 6A-7. For example, the redistribution structure **210** may be formed from a series of seed layers and plating processes which are used to build up successive layers of redistribution layers and insulating layers.

(99) Turning to FIG. 28, lower sidewall antennas **1402** and conductive pillars **214** are formed over and connected to the redistribution structure **210**. The conductive pillars **214** may be similar to those described previously with respect to FIGS. 8A-B, and may be formed in a similar manner. For example, a photoresist may be formed over the redistribution structure **210** and patterned where the lower sidewall antennas **1402** and the conductive pillars **214** are desired to be formed, and a conductive material deposited onto the exposed portions of the redistribution structure **210**. Once formed, the photoresist and excess conductive material may be removed. The lower sidewall antennas **1402** are lower portions of sidewall antennas **1510** formed in the antenna package **1500**, described below with respect to FIG. 30. The lower sidewall antennas **1402** may be formed from a similar material and in a similar manner as the conductive pillars **214**, and may be formed in the same process steps as the conductive pillars **214**. In some embodiments, the lower sidewall antennas **1402** may be formed having a height between about 80  $\mu\text{m}$  and about 300  $\mu\text{m}$ . The lower sidewall antennas **1402** may have a rectangular cross-sectional shape, a circular cross-sectional shape, or another shape.

(100) Turning to FIG. 29, a semiconductor device **220** is then connected to the redistribution structure **210**. The semiconductor device **220** may be one or more semiconductor devices **220** similar to those described previously with respect to FIGS. 9A-B, and may be connected to the redistribution structure **210** in a similar manner. The semiconductor device **220** may have a height above the redistribution structure **210** that is lower than, about the same, or higher than a height of

the lower sidewall antennas **1402** or conductive pillars **214**. In this manner, the device structure **1400** may be formed, though the device structure **1400** may be formed using other processes in other embodiments.

(101) Turning to FIG. **30**, an antenna package **1500** is formed by bonding the antenna structure **1300** to the device structure **1400**, and a molding material **302** is formed between the antenna structure **1300** and the device structure **1400**. The antenna structure **1300** may be bonded to the device structure **1400** in a manner similar to that previously described for FIGS. **10A-C**. For example, the connectors **118** of the antenna structure **1300** may be placed on conductive pillars **214** and lower sidewall antennas **1402** of the device structure **1400**. A reflow process may be performed. A molding material **302** may then be formed, which may be similar to the molding material **302** described previously for FIGS. **10A-C**, and which may be formed in a similar manner.

(102) As shown in FIG. **30**, upper sidewall antennas **1302** are bonded to corresponding lower sidewall antennas **1402**, forming sidewall antennas **1510**. The sidewall antennas **1510** extend from the redistribution structure **210** to the top surface of the antenna structure **1300**. The overall height of the sidewall antennas **1510** may be between about 300  $\mu\text{m}$  and about 2 mm. In some embodiments, a distance between a sidewall of the antenna package **1500** and a sidewall antenna **1510** may be between about 50  $\mu\text{m}$  and about 200  $\mu\text{m}$ . The sidewall antennas **1510** may be driven directly or parasitically. In some cases, a sidewall antenna **1510** as described herein may have greater efficiency, greater power, or greater bandwidth than an antenna having smaller overall height. In this manner, sidewall antennas having larger overall height may be integrated within an antenna package. The sidewall antennas **1510** may be used in the same antenna package along with other types of antennas (e.g., patch antennas, dipole antennas, end-fire antennas such as those described herein), and thus the operation of the antenna package may be improved by utilizing multiple types of antennas.

(103) FIG. **31** shows a perspective view of an antenna package **1600** having sidewall antennas **1510**, according to some embodiments. The antenna package **1600** may be similar to the antenna package **1500** described in FIG. **30**. Some features of the antenna package **1600** are not shown in FIG. **31** for clarity, such as the molding material **302** or other features such as feedline vias **1308**, thermal vias **1306**, patch antennas **110**, end-fire antennas **112**, etc. The sidewall antennas **1510** may be similar to those described above in FIG. **30** and may, for example, include lower sidewall antennas **1402** formed on a redistribution structure **210**, and connectors **118** and upper sidewall antennas **1302** formed as part of an antenna structure **1300**. As shown in FIG. **31**, multiple sidewall antennas **1510** may be formed in an arrangement surrounding the semiconductor device **220**. In other embodiments, the multiple sidewall antennas **1510** may be formed in a different arrangement, such as partially surrounding the semiconductor device **220** or another arrangement. Another number of sidewall antennas **1510** may be formed than is shown in FIG. **31**. In some embodiments, the sidewall antennas **1510** may be laterally separated by a distance between about 200  $\mu\text{m}$  and about 1 mm. The number and arrangement of sidewall antennas **1510** may be configured to have the antenna characteristics desired for the antenna package **1600**. In some embodiments, some sidewall antennas **1510** may be used for output operation and other sidewall antennas **1510** may be used for input operation. Other antennas such as patch antennas **110** or end-fire antennas **112** may also be formed in the antenna structure **1600**, and may be used for additional input and/or output operation. In this manner, the antenna package **1600** may operate as a Multiple-In Multiple-Out (MIMO) device.

(104) FIGS. **32A-C** illustrate intermediate steps of forming an antenna package **1900** (see FIG. **32C**), in accordance with some embodiments. In some embodiments, the antenna package **1900** shown in FIG. **32C** may be an Integrated Fan-Out (InFO) structure.

(105) In FIG. **32A**, dipole antennas **212** and conductive pillars **214** are formed over a carrier substrate **201**, and a semiconductor device **220** is placed on the carrier substrate **201**. In some embodiments, a release layer (not shown) may be formed on the carrier substrate **201**. The dipole



antennas **212** and conductive pillars **214** may be similar to those described previously with respect to FIGS. **8A-B**, and may be formed in a similar manner. For example, a photoresist may be formed over the carrier substrate **201** and patterned where the dipole antennas **212** and the conductive pillars **214** are desired to be formed. In some embodiments, a seed layer (not shown) may first be formed, and the photoresist formed over the seed layer. A conductive material is then deposited onto the exposed portions of the carrier substrate **201** or onto the exposed portions of the seed layer (if present). Once formed, the photoresist, excess conductive material, and excess portions of the seed layer (if present) may be removed. The semiconductor device **220** may be placed using e.g., a pick-and-place process or another suitable process.

(106) In FIG. **32B**, an encapsulant **1702** is formed around the dipole antennas **212**, conductive pillars **214** and semiconductor device **220**. A planarization process (e.g., a CMP process) may be performed after forming the encapsulant **1702**. The encapsulant **1702** may be a material similar to the molding material **302** described previously with respect to FIGS. **10A-C**, or may be a resin, polyimide, PPS, PEEK, PES, another material, combinations of these, or the like. A redistribution structure **1710** is formed over the dipole antennas **212**, conductive pillars **214**, semiconductor device **220**, and encapsulant **1702**. The redistribution structure **1710** may be formed in a manner similar to that described previously with regard to FIGS. **6A-7**. For example, the redistribution structure **1710** may be formed from a series of seed layers and plating processes which are used to build up successive layers of redistribution layers and insulating layers. The redistribution structure **1710** may be electrically connected to the dipole antennas **212**, conductive pillars **214**, and the semiconductor device **220**. External connections **306** may then be formed or placed in electrical connection with the redistribution structure **1710**, forming a device structure **1700**. The external connections **306** may be similar to the external connections **306** described previously with respect to FIG. **11**.

(107) Turning to FIG. **32C**, an antenna package **1900** is formed by bonding an antenna structure **1800** to the device structure **1700**. The antenna structure **1800** may be similar to antenna structures described previously, such as antenna structure **120** (see FIG. **5**), antenna structure **400** (see FIG. **12**), antenna structure **700** (see FIG. **17**), antenna structure **1000** (see FIG. **22**), or antenna structure **1300** (see FIG. **25**), though the antenna structure **1800** may be different from these in some embodiments. The carrier substrate **201** is first debonded from the device structure **1700**. The antenna structure **1800** may be bonded to the device structure **1700** in a manner similar to that previously described for FIGS. **10A-C**. For example, the connectors **118** of the antenna structure **1800** may be placed on the conductive pillars **214** of the device structure **1700**, and then a reflow process may be performed. A molding material **302** may then be formed between the antenna structure **1800** and the device structure **1700**, which may be similar to the molding material **302** described previously for FIGS. **10A-C**. In this manner, an antenna package **1900** may be formed having multiple types of antennas (e.g., dipole antennas **212**, patch antennas **110**, and end-fire antennas **112**) and having thermal vias **106**.

(108) By utilizing the embodiments described herein, the performance of a device including antennas (“an antenna package”) may be improved and the size of the device may be decreased. Different features of embodiments described herein may be combined to achieve these and other benefits. In some cases, the use of multiple types of antennas in a single antenna package as described herein may allow for improved directionality or efficiency of operation. In some cases, the use of a core substrate for forming some antennas and other conductive features may reduce costs of manufacturing an antenna package. As an example, forming more conductive routing in the antenna structure may allow for a smaller redistribution structure within the antenna package, which can reduce cost of manufacture. In some cases, the groundplane of an antenna may be formed on the outside of the antenna structure or on a semiconductor device within the antenna package such that more space for routing or antennas is available within the antenna structure. This can allow for greater design flexibility of antennas or other features. In some cases, the formation

of thermal vias as described herein can allow for improved heat dissipation within the antenna package, which can improve performance and reduce the chance of thermal failure.

(109) In an embodiment, a device includes a redistribution structure, a first semiconductor device, a first antenna, and a first conductive pillar on the redistribution structure that are electrically connected to the redistribution structure, an antenna structure over the first semiconductor device, wherein the antenna structure includes a second antenna that is different from the first antenna, wherein the antenna structure includes an external connection bonded to the first conductive pillar, and a molding material extending between the antenna structure and the redistribution structure, the molding material surrounding the first semiconductor device, the first antenna, the external connection, and the first conductive pillar. In an embodiment, the antenna structure further includes a third antenna that is different from the first antenna and that is different from the second antenna. In an embodiment, the first antenna is a dipole antenna. In an embodiment, the second antenna is a patch antenna. In an embodiment, the antenna structure includes an insulation substrate and at least one via extending through the insulation substrate. In an embodiment, the at least one via includes a thermal via disposed over the first semiconductor device. In an embodiment, the first semiconductor device is a radio frequency chip. In an embodiment, the device includes a thermal adhesive on the first semiconductor device, the thermal adhesive extending from the first semiconductor device to the antenna structure. In an embodiment, the antenna structure includes a copper-clad laminate structure.

(110) In an embodiment, a device includes a redistribution structure, an antenna structure disposed over the redistribution structure, the antenna structure including an insulating layer, a patch antenna on a top surface of the insulating layer, an end-fire antenna on a top surface of the insulating layer, a through-via extending through the insulating layer, and a connector electrically connecting the through-via to the redistribution structure, a dipole antenna connected to the redistribution structure and interposed between the redistribution structure and the antenna structure, and a first semiconductor device connected to the redistribution structure and disposed between the redistribution structure and the antenna structure. In an embodiment, the through-via is connected to the patch antenna. In an embodiment, the through-via is a thermal via. In an embodiment, the device includes a groundplane disposed on the bottom surface of the insulating layer. In an embodiment, the device includes a molding material extending over and surrounding the dipole antenna and the first semiconductor device. In an embodiment, the device includes a groundplane disposed on the molding material.

(111) In an embodiment, a method includes forming a redistribution structure over a carrier wafer, forming multiple first antennas and multiple conductive pillars on the redistribution structure, attaching a first semiconductor device to the redistribution structure, forming multiple second antennas on an antenna substrate, forming a multiple external connectors on the antenna substrate, attaching the multiple external connectors to the multiple conductive pillars, wherein the first semiconductor device and the multiple first antennas are disposed between the redistribution structure and the antenna substrate, forming a molding material between the redistribution structure and the antenna substrate, and removing the carrier wafer. In an embodiment, the method includes forming multiple through vias in the antenna substrate. In an embodiment, the multiple first antennas include dipole antennas and the multiple second antennas include patch antennas. In an embodiment, the method includes forming a conductive layer on a surface of the first semiconductor device and attaching at least one of the multiple external connectors to the conductive layer. In an embodiment, the method includes attaching a second semiconductor device to the redistribution structure.

(112) The foregoing outlines features of several embodiments so that those skilled in the art may better understand the aspects of the present disclosure. Those skilled in the art should appreciate that they may readily use the present disclosure as a basis for designing or modifying other processes and structures for carrying out the same purposes and/or achieving the same advantages

of the embodiments introduced herein. Those skilled in the art should also realize that such equivalent constructions do not depart from the spirit and scope of the present disclosure, and that they may make various changes, substitutions, and alterations herein without departing from the spirit and scope of the present disclosure.

## Claims

1. A device, comprising: a redistribution structure; an antenna structure disposed over the redistribution structure, the antenna structure comprising: an insulating layer; a plurality of antennas; thermal vias extending through the insulating layer; and a first conductive layer on a bottom surface of the insulating layer, the first conductive layer coupled to the thermal vias; and a first semiconductor device connected to the redistribution structure, wherein the first semiconductor device is between the redistribution structure and the antenna structure.
2. The device of claim 1, wherein the plurality of antennas comprises a patch antenna.
3. The device of claim 1, wherein the plurality of antennas comprises an end-fire antenna.
4. The device of claim 1, further comprising: a molding material over the first semiconductor device between the first semiconductor device and the antenna structure.
5. The device of claim 4, further comprising: a first through via extending through the molding material; a second through via extending through the molding material; and a groundplane on a surface of the molding material, the groundplane coupled to the first through via and the second through via.
6. The device of claim 5, further comprising an another antenna on the redistribution structure, wherein the molding material extends along sidewalls of the another antenna.
7. The device of claim 6, wherein the another antenna extends completely through the molding material.
8. A device comprising: a redistribution structure; a first semiconductor device attached to the redistribution structure; a first conductive pillar on the redistribution structure; a first encapsulant over the redistribution structure and along sidewalls of the first semiconductor device, wherein an upper surface of the first encapsulant is level with an upper surface of the first semiconductor device; and an antenna structure attached to the first conductive pillar, the antenna structure comprising an antenna substrate and a first antenna on an upper surface of the antenna substrate.
9. The device of claim 8, wherein the antenna structure is attached to the first conductive pillar by a solder connector.
10. The device of claim 8, wherein the antenna structure comprises: one or more thermal vias extending through the antenna substrate.
11. The device of claim 10, wherein the antenna structure comprises: a conductive line interconnecting the one or more thermal vias.
12. The device of claim 11, wherein the conductive line is between the substrate and the first semiconductor device.
13. The device of claim 8, wherein the antenna structure comprises an end-fire antenna and a patch antenna.
14. The device of claim 8, further comprising a dipole antenna in the first encapsulant.
15. A device comprising: a redistribution structure; a first conductive pillar on the redistribution structure; an antenna structure attached to the redistribution structure, a lower surface of the antenna structure facing the redistribution structure, the antenna structure comprising: an insulating layer; a first antenna on a lower surface of the insulating layer and electrically coupled to the first conductive pillar; and a first conductive layer on the lower surface of the insulating layer, the first conductive layer coupled to ground; and a first semiconductor device connected to the redistribution structure, wherein the first semiconductor device is between the redistribution structure and the antenna structure.

16. The device of claim 15, further comprising: an encapsulant over an upper surface of the first semiconductor device.
  17. The device of claim 16, further comprising: a second antenna on the redistribution structure, wherein the encapsulant covers an upper surface of the second antenna.
  18. The device of claim 17, further comprising: a second conductive pillar on the redistribution structure, wherein the first conductive layer is attached to the second conductive pillar.
  19. The device of claim 15, wherein the antenna structure is attached to the first conductive pillar using a solder joint.
  20. The device of claim 15, wherein the antenna structure comprises thermal vias.
-