

US Patent & Trademark Office

Patent Public Search | Text View

United States Patent	12413918
Kind Code	B2
Date of Patent	September 09, 2025
Inventor(s)	Rasmussen; Benny Bøgvad

Hearing device with decoupler

Abstract

A hearing device comprising a behind-the-ear module and a tube element extending from the behind-the-ear module is disclosed. The behind-the-ear module comprises a signal processor for processing received audio signals into a signal modified to compensate for a user's hearing impairment, and an antenna configured for emission and reception of electromagnetic radiation at a first frequency. The hearing device further comprises at least one electrically conducting element, wherein a first section of the at least one electrically conducting element extends into the tube element, and at least one decoupling element, the at least one decoupling element being configured to electrically decouple the first section and the behind-the-ear module at the first frequency while maintaining an electrical connection between the first section and the behind-the-ear module at second frequencies.

Inventors:	Rasmussen; Benny Bøgvad (Frederiksberg, DK)
Applicant:	GN Hearing A/S (Ballerup, DK)
Family ID:	70058108
Assignee:	GN HEARING A/S (Ballerup, DK)
Appl. No.:	17/191687
Filed:	March 03, 2021

Prior Publication Data

Document Identifier	Publication Date
US 20210306778 A1	Sep. 30, 2021

Foreign Application Priority Data

EP	20166530	Mar. 28, 2020
----	----------	---------------

Publication Classification

Int. Cl.: H04R25/00 (20060101)

U.S. Cl.:

CPC H04R25/607 (20190501); H04R25/50 (20130101);

Field of Classification Search

CPC: H04R (25/505); H04R (25/70); H04R (25/554); H04R (25/356); H04R (25/60); H04R (25/65); H04R (25/604); H04R (25/652); H04R (25/43); H04R (25/558); H04R (25/607); H04R (25/50); H04R (2225/41); H04R (2225/61); H04R (2225/63); H04R (2225/021); H04R (2225/51)

USPC: 381/330; 381/331; 381/324

References Cited

U.S. PATENT DOCUMENTS

Patent No.	Issued Date	Patentee Name	U.S. Cl.	CPC
2007/0014423	12/2006	Darbut	381/330	H04R 25/65
2009/0169038	12/2008	Knudsen et al.	N/A	N/A
2009/0196444	12/2008	Solum	381/315	H01Q 1/273
2013/0223664	12/2012	Meskens et al.	N/A	N/A
2014/0328507	12/2013	Rabel	381/315	H04R 25/554
2015/0043763	12/2014	Troelsen	343/718	H04R 25/554
2017/0188163	12/2016	Rabel	N/A	H04R 25/55

FOREIGN PATENT DOCUMENTS

Patent No.	Application Date	Country	CPC
101155216	12/2007	CN	N/A
106878901	12/2016	CN	N/A
WO 2015/127973	12/2014	WO	N/A
WO-2015127973	12/2014	WO	H04R 25/554

OTHER PUBLICATIONS

European Search Report dated Nov. 12, 2020 for EP Appln. No. 20166530.4. cited by applicant
Foreign Exam Report for EP Patent Appln. No. 20166530.4 dated Aug. 21, 2023. cited by applicant
Foreign Office action dated Apr. 4, 2025 for Chinese patent application No. 202110318412. cited by applicant

Primary Examiner: Matar; Ahmad F.

Assistant Examiner: Diaz; Sabrina

Attorney, Agent or Firm: Vista IP Law Group, LLP

Background/Summary

RELATED APPLICATION DATA

(1) This application claims priority to, and the benefit of, European Patent Application No. EP 20166530.4 filed on Mar. 28, 2020. The entire disclosure of the above application is expressly incorporated by reference herein.

FIELD

(2) The present disclosure relates to hearing devices and methods therefore, particularly hearing devices having wireless communication capabilities and thus hearing devices comprising antennas for communication.

(3) The present disclosure further relates to a hearing device configured to communicate using magnetic induction and/or to communicate through the use of radio frequencies.

(4) The hearing device may be used in a binaural hearing device system. The hearing device may be hearing devices for compensating a hearing loss of a user. During operation, the hearing device is worn in or at the ear of a user, such as for alleviating a hearing loss of the user.

BACKGROUND

(5) Hearing devices are very small and delicate devices and comprise many electronic and metallic components contained in a housing or shell small enough to fit in the ear canal of a human or be located behind the outer ear. The many electronic and metallic components in combination with the small size of the hearing device housing or shell impose high design constraints on antennas to be used in hearing devices with wireless communication capabilities, both MI antennas and RF antennas.

(6) Moreover, particularly antennas in hearing devices must be designed to achieve a satisfactory performance despite these limitations and other narrow design constraints imposed by the size of the hearing device and the proximity to a user's head.

(7) The developments within wireless technologies in general have led to even higher expectations of the communication capabilities of the hearing devices, despite a concurrent continuous efforts to make hearing devices smaller and more cost effective to manufacture.

(8) Still further, in binaural hearing device systems, the requirements to the quality of the communication between the hearing devices in the binaural hearing device system are ever increasing, and so is the requirements for communication between the hearing device and other electronic devices, such as smart phones, accessory devices, etc., and include demands for low latency, higher bandwidth, and low noise, increasing the requests for effective antennas in the hearing devices.

(9) Therefore, there is a need for an improved design of hearing devices providing communication with other hearing devices or electronic devices.

SUMMARY

(10) In accordance with the present disclosure, one or more of the above-mentioned and other objects are obtained by the disclosed hearing device.

(11) In accordance with one aspect of the disclosure, a hearing device is provided, the hearing device comprising a behind-the-ear module and a tube element extending from the behind-the-ear module, wherein the behind-the-ear module comprises a signal processor for processing received audio signals into a signal modified to compensate for a user's hearing impairment and an antenna configured for emission and reception of electromagnetic radiation at a first frequency. The hearing device further comprises at least one electrically conducting element, wherein a first section of the at least one electrically conducting element extends into the tube element, and at least one decoupling element, the at least one decoupling element being configured to electrically decouple the first section and the behind-the-ear module at the first frequency while maintaining an electrical connection between the first section and the behind-the-ear module at second frequencies.

(12) The hearing device typically comprises a first transducer, such as a microphone to generate one or more microphone output signals based on a received audio signal. The one or more microphone output signals are provided to the signal processor for processing the one or more microphone output signals. A receiver or speaker is connected to an output of the signal processor, for example for converting the output of the signal processor into a signal modified to compensate for a user's hearing impairment, and provides the modified signal to the speaker.

(13) The signal processor may comprise elements such as processing elements, an amplifier, a compressor and/or a noise reduction system etc. The signal processor device may further have a filter function, such as compensation filter for optimizing the output signal.

(14) In some embodiments, the at least one decoupling element is provided between the signal processor and the first section of the electrically conductive element. In some embodiments, the at least one decoupling element is provided in the signal path between the signal processor and the electrically conductive element extending into the tube element. In some embodiments, the at least one decoupling element is provided between the wireless communication unit and the first section of the at least one electrically conductive element, such as between the wireless communication unit and any electrically conductive element extending into the tube element. The at least one decoupling element may be provided in the signal path between the wireless communication unit and the at least one electrically conductive element extending into the tube element, such as between the wireless communication unit and any electrically conductive element extending into the tube element.

(15) In some embodiments, the decoupling element is configured to reduce or block signal content at or about the first frequency, so that any coupling with the antenna is eliminated.

(16) It is an advantage of providing at least one decoupling element being configured to electrically decouple the first section and the behind-the-ear module at the first frequency while maintaining an electrical connection between the first section and the behind-the-ear module at second frequencies, in that it is hereby ensured that the first section of the electrically conducting element does not act as an antenna, and/or does not interfere with the antenna functionality at the first frequency.

Typically, a first section of an electrically conducting element extending into a tube element, such as a first section of an electrically conducting element interconnecting components of a behind-the-ear module and electrical components of an ear element of the hearing device, is a long wire. Such a long wire could, if not decoupled at the first frequency, interfere with the antenna functionality of the antenna in the hearing device, either by electromagnetic interference, by artificially extending the length of the antenna in the hearing device, by coupling between the antenna in the hearing device and the electrically conducting element, etc., which would influence the antenna functionality improperly. Particularly, as the length of the tube element varies for various head configurations, the length of the electrically conducting elements, such as wires, are not known, and thereby, any influence of the electrically conducting elements is not known, and will give an unspecified disturbance.

(17) By means of the decoupling element, the at least one electrically conducting element extending into the tube element is configured to be decoupled from the components of the behind-

the-ear module at the first frequency. Hereby, any antenna functionality of the electrically conducting element at the first frequency is suppressed.

(18) The hearing device comprises an antenna. The antenna may be any antenna configured for emission and reception of electromagnetic radiation at the first frequency. The antenna may be interconnected with a wireless communication unit. The wireless communication unit is configured for wireless communication, including wireless data communication, and is in this respect interconnected with the antenna for emission and reception of an electromagnetic field. The wireless communication unit may be configured for interconnecting the signal processor with the antenna for providing wireless communication with other hearing devices and/or other external electronic devices. The hearing device may be configured for communicating with one or more external devices, such as one or more external electronic devices, including at least one smart phone, at least one tablet, at least one hearing accessory device, including at least one spouse microphone, remote control, audio testing device, etc., or, in some embodiments, with another hearing device, such as another hearing device located at another ear, typically in a binaural hearing device system.

(19) The wireless communication unit may comprise a transmitter, a receiver, a transmitter-receiver pair, such as a transceiver, and/or a radio unit. The wireless communication unit may be configured for communication using any protocol as known for a person skilled in the art, including Bluetooth, including Bluetooth Low Energy, Bluetooth Smart, etc., WLAN standards, manufacture specific protocols, such as tailored proximity antenna protocols, such as proprietary protocols, such as low-power wireless communication protocols, such as CSR mesh, etc.

(20) The antenna may be a magnetic antenna. The antenna may be an electrical antenna. The antenna may be configured to resonate at the first frequency. In some embodiments, the antenna is a resonant antenna at the first frequency. It is an advantage of operating the antenna at or close to the resonance frequency, such as at the frequency at which the antenna is resonant, as the efficiency of the antenna may be at or proximate a maximum efficiency at the resonant frequency.

(21) The antenna may be configured for operation at radio frequencies, such as at radio frequencies above 800 MHz, such as above 1 GHz, such as above 1.5 GHz, such as at about 1.6 GHz, such as at about 2.4 GHz. The antenna may be configured for operation at radio frequencies, such as in one or more ISM frequency bands; such as in one or more ISM frequency bands appropriate for communication in a hearing device. In some embodiments, the hearing device may use the 2.45 ± 0.05 GHz ISM band and/or the 1.6 GHz ISM band.

(22) The antenna may be configured for operation at frequencies in a range from 800 MHz to 6 GHz. The antenna may be any antenna capable of operating at these frequencies. The antenna may be implemented in any way, and the antenna may be a monopole antenna, a dipole antenna, etc. The antenna may be a loop antenna, such as an open loop antenna. The antenna may be any antenna as known, such as any electrical antenna, and the antenna may be, or may comprise, an elongated conducting material, the elongated conducting material being configured to emit or receive electromagnetic radiation in any known way.

(23) The hearing device further comprises at least one electrically conducting element, wherein a first section of the at least one electrically conducting element extends into the tube element. The at least one electrically conducting element may be a wire, such as a lead wire, such as an electrical wire, a cable, a cord, etc.

(24) In some embodiments, the second frequencies include all frequencies except the first frequency. In some embodiments, the second frequencies include frequencies which are above and/or below the first frequency. In some embodiments, the second frequencies include all frequencies outside a range of frequencies about the first frequency, such as all frequencies outside a range of frequencies being $\pm 10\%$ of the first frequency, such as all frequencies outside a range of frequencies being $\pm 5\%$ of the first frequency, such as all frequencies outside a range of frequencies being $\pm 3\%$ of the first frequency, such as all frequencies outside a range of

frequencies being $\pm 1\%$ of the first frequency.

(25) Having at least one decoupling element configured to electrically decouple the first section of the at least one electrically conducting element and the behind-the-ear module at the first frequency while maintaining an electrical connection between the first section and the behind-the-ear module at second frequencies provides that any electromagnetic coupling at or around the first frequency between electronic components in the behind-the-ear module and the at least one electrically conducting element is reduced. In some embodiments, the at least one electrically conducting element is decoupled at the first frequency so that the at least one electrically conducting element does not interfere or couple with the antenna at the first frequency. In some embodiments, the at least one electrically conducting element is decoupled at the first frequency so that the at least one electrically conducting element does not have an antenna functionality. In some embodiments, the at least one electrically conducting element is decoupled at the first frequency so that the at least one electrically conducting element does not have an antenna functionality at the first frequency.

(26) In some embodiments, the at least one electrically conducting element has a second section, and wherein the at least one decoupling element is provided between the first section and the second section; the at least one decoupling element being configured to electrically decouple the first section from the second section at the first frequency, while maintaining an electrical connection between the first section and the second section at the second frequencies. In some embodiments, the at least one decoupling element is provided in series between the first section and the second section.

(27) In some embodiments, the second section of the at least one electrically conducting element extends at least partly in the behind-the-ear module.

(28) In some embodiments, the at least one electrically conducting element is an electrically conducting element extending from the behind-the-ear module and into the tube element. The decoupling element may be provided between the second section extending in the behind-the-ear module and the first section extending in the tube element.

(29) In some embodiments, the at least one decoupling element has a high impedance at the first frequency, preferably an impedance above 1 k Ω . In some embodiments, the at least one decoupling element has an impedance is above 1 k Ω , such as above 1.5 k Ω , such as above 4 k Ω , such as above 5 k Ω .

(30) In some embodiments, the at least one decoupling element is an inductor having a self-resonant frequency at the first frequency. In some embodiments, the at least one decoupling element is an inductor having a self-resonant frequency being within a range or a bandwidth centered about the first frequency. In some embodiments, the self-resonant frequency of the inductor is within a range of $\pm 10\%$ of the first frequency, such as within a range of $\pm 5\%$, such as within a range of the $\pm 3\%$ of the first frequency. In some embodiments, the coupling element is an inductor, such as a separate physical component including an inductor, such as an SMD type inductor.

(31) It is an advantage of using an inductor at its resonance frequency in that the decoupling is provided within a narrow range of frequencies about the resonance frequency of the inductor. It is an advantage that the decoupling is performed only at the first frequency, or only within a frequency range about the first frequency, such as within a range of $\pm 10\%$ of the first frequency, such as within a range of $\pm 5\%$, such as within a range of the $\pm 3\%$ of the first frequency. Hereby, disturbance of any signals transmitted on the at least one electrically conductive element are minimized, as only signals at frequencies within such specified ranges are decoupled.

(32) In some embodiments, the hearing device comprises one or more conducting elements, thus, the at least one conducting element may comprise one, two, three, four, etc, conducting elements, such as wires extending into the tube element. In some embodiments, each of the at least one conducting elements is connected in series with at least one decoupling element. In this way, each conducting element, such as each wire, extending into the tube element is connected to electrical

components of the behind-the-ear module through the at least one decoupling element.

(33) In some embodiments, the at least one decoupling element comprises a primary decoupling element and a secondary decoupling element, the primary decoupling element and the secondary decoupling element being connected in series.

(34) The primary decoupling element may be configured to decouple the at least one conducting element from the behind-the-ear module at the first frequency, while the secondary decoupling element may be configured to decouple the at least one conducting element from the behind-the-ear module at another frequency, different from the first frequency while maintaining an electrical connection at second frequencies.

(35) In some embodiments, the at least one decoupling element is provided in the behind-the-ear module.

(36) In some embodiments, the tube element is configured to provide a sound signal to the ear of a user, such sound signal may be provided to the ear of a user either acoustically or electrically.

(37) In some embodiments, the hearing device further comprises an electro-mechanical interface configured to releasably, such as detachably, attach the tube element to the behind-the-ear module. Such releasably attachment may be performed in any way as well-known for a skilled person, such as using male/female connector parts, using snap or click assemblies, etc. It is an advantage of being able to disconnect the tube element from the behind-the-ear module, in that e.g. the tube element may be exchanged, for example due to wear and tear of the tube element, so that the tube element may be fitted to the user, e.g. to obtain a desired size of tube element, etc., the tube element may be replaced to obtain a proper fit, or detached e.g. for cleaning or replacement with limited efforts and with minimised coupling with the behind-the-ear module as such.

(38) In some embodiments, the electro-mechanical interface has a first part forming part of the behind-the-ear module and a second part forming part of the tube element. At least one of the decoupling elements may be provided in the second part of the electro-mechanical interface. The decoupling element provided in the second part of the electro-mechanical interface may be connected in series with the wire/conducting element. At least one of the decoupling elements may be provided in or adjacent the first part forming part of the behind-the-ear module. The decoupling element provided in or adjacent the first part of the electro-mechanical interface may be connected in series with the wire/conducting element.

(39) It is an advantage of providing the at least one coupling element in the electro-mechanical interface, such as either in the first part of the electro-mechanical interface, or in the second part of the electro-mechanical interface, in that the coupling element is then provided as close as possible, such as in proximity or adjacent, to the part of the electrical conducting element extending into the tube element, such as in proximity to the first section of the at least one electrical conducting element. This improves the decoupling between the behind-the-ear module and the wire extending into the tube element, so as to e.g. make the decoupling more efficient.

(40) The first part and the second part of the electro-mechanical interface may be provided as a plug and a socket for receiving the plug, respectively.

(41) In some embodiments, the electrical interconnection at second frequencies are provided through the electro-mechanical interface.

(42) In some embodiments, the hearing device comprises a wireless communication unit being interconnected with the antenna configured for emission and reception of electromagnetic radiation having a first bandwidth centered about the first frequency.

(43) In some embodiments, the wireless communication unit being interconnected with the antenna, or with an additional antenna, is further configured for emission and reception of electromagnetic radiation having a second bandwidth centered about a third frequency. The first and third frequencies may be frequencies suitable for wireless communication, such as suitable for wireless communication in a hearing aid, the first and third frequencies may be selected as frequencies about 2.4 GHZ, about 1.6 GHZ, at about 900 MHZ, etc.

(44) In some embodiments, the first section of the electrically conducting element is not decoupled from the behind-the-ear module at the third frequency. In some embodiments, the first section is configured as an antenna at the third frequency.

(45) In some embodiments, the at least one decoupling element is further configured to electrically decouple the first section and the behind-the-ear module at the third frequency, the third frequency being different from the first frequency and the second frequencies. In some embodiments, a first primary decoupling element provided in series with the first section of the electrically conducting element is configured for decoupling the first section at the first frequency. A first secondary decoupling element may be provided in series with the first section of the electrically conducting element and the first primary decoupling element and being configured for decoupling the first section at the third frequency. The first primary decoupling element may be an inductor having a self-resonant frequency at the first frequency. The first secondary decoupling element may be an inductor having a self-resonant frequency at the third frequency.

(46) In some embodiments, the first frequency is selected in the 2.4 GHz ISM band, and the third frequency is selected in the 1.6 GHz ISM band. It is an advantage that the hearing device may communicate wirelessly with hearing devices or electronic devices at two different frequencies, such as at a first frequency and at a third frequency. It is an advantage that the hearing device may communicate wirelessly with hearing devices or electronic devices using the 2.4 GHz ISM band and/or the 1.6 GHz ISM band.

(47) In some embodiments, the hearing device comprises a plurality of electrically conducting elements and a plurality of decoupling elements configured to electrically decouple the plurality of electrically conducting elements from the behind-the-ear module at the first frequency and optionally at the third frequency. Each of the plurality of electrically conducting elements is connected in series with one or more of the plurality of decoupling elements.

(48) Thus, each of the decoupling elements may be connected in series with one or more decoupling elements. When connected with two decoupling elements, one of the decoupling elements may be configured to decouple at the first frequency and one of the decoupling elements may be configured to decouple at the third frequency.

(49) In some embodiments, each of the plurality of electrically conductive elements, that is all electrical connections, between the behind-the-ear module and the tube element are electrically decoupled at the first frequency. In some embodiments, each of the plurality of electrically conductive elements, that is all electrical connections, between the behind-the-ear module and the tube element are electrically decoupled at the first frequency, and optionally, also at the third frequency.

(50) In some embodiments, the hearing device further comprises an ear element, the ear element being configured to be positioned in the ear of a user to e.g. receive the modified signal from the signal processor via the tube element, and provide the modified signal to the ear of a user. The ear element may be attached to the tube element. The ear element may be attached to the tube element opposite the behind-the-ear module. The ear element may be any ear element, such as an ear element configured to be provided at least partly in the ear canal, to be provided completely in the canal, the ear element may be a receiver-in-the-ear element (RIE element) etc.

(51) In some embodiments, the ear element comprises an ear-mold with no electrical parts. The ear element may be an ear-mold, such as an ear plug, configured to ensure that sound provided via the tube element reaches the ear canal of a user. In some embodiments, the tube element is configured to provide the modified signal to an ear of a user through a sound tube so that the tube element comprises a sound tube. In some embodiments, the ear element comprises at least one in-ear electrical component, such as at least one transducer; the at least one in-ear electrical component may be electrically connected with electrical components of the behind-the-ear module. The electrical components of the behind-the-ear element may comprise any one or more of the signal processor, the battery, the antenna, the wireless communication unit, etc. The at least one in-ear

electrical component may comprise a transducer. The electrical components of the ear element may comprise one or more transducers.

(52) In some embodiments, the at least one electrically conducting element is configured to provide signals between the behind-the-ear module and the ear element. The signals may include audio type signals, such as transducer type signals, such as signals provided from a transducer to e.g. the signal processor or vice versa. The signals may comprise data and/or power signals, such as signals providing data, such as settings; such as power signals, between the behind-the-ear module and the ear element. For example, the modified signal from the signal processor may be provided via the at least one electrically conducting element to an ear of a user. The tube element may comprise the electrically conducting element, such as a wire, a cable, etc., such as at least the first section of the electrically conducting element.

(53) In some embodiments, the ear element may comprise one or more microphones, and one or more electrically conducting elements may be one or more microphone signal lines connecting the one or more microphones provided in the ear element to at least the signal processor in the behind-the-ear module. In some embodiments, the one or more microphones may be powered by the battery in the behind-the-ear module, so that the one or more electrically conducting elements may be one or more power lines for the one or more microphones provided in the ear element.

(54) In some embodiments, the ear element comprises a receiver, the ear element being configured to be inserted into the ear canal of the user, the tube element interconnects the ear element and the behind-the-ear module, and wherein the modified signal is configured to be provided to the receiver, via the electrically conducting element.

(55) In some embodiments, the hearing device comprises at least a first electrically conducting element and a second electrically conducting element, and wherein the first electrically conducting element is connected with a first decoupling element, and the second electrically conducting element is connected with a second decoupling element and wherein the first decoupling element has a lower impedance than the second decoupling element(s) at audible frequencies. For example the impedance of the second decoupling element may be 10% lower than the impedance of the first decoupling element. Hereby, it may be ensured that the impedance for audio signals is as low as possible, while keeping the size of the components as small as possible. Thus, as e.g. second decoupling elements having a lower impedance at audible frequencies tend to be larger in physical size than the first decoupling elements, the second decoupling elements may be used only for audio type signals and not for e.g. power signals or data signals which are less influenced by the impedance of the decoupling elements, to thereby reduce the size of the decoupling components.

(56) In some embodiments, the decoupling element has a low impedance, such as an impedance below 1000, such as below 500, such as below 100, such as below 50, at the second frequencies, such as at audible frequencies, such as at frequencies between 20 Hz and 20 KHz. It is an advantage of keeping the impedance of the decoupling element low, in that signals at audible frequencies, which are low power signals, are not degraded significantly by the presence of the decoupling element in the signal path.

(57) In some embodiments, one or more of the electrically conducting elements may comprise a shielding element, shielding the electrically conducting elements.

(58) In an aspect of an embodiment, a tube element for a hearing device is provided. The tube element comprises an ear element configured to be inserted into the ear of a user, an electrically conducting element extending into the tube element, and a plug element configured for attachment to the behind-the-ear module, a tube section interconnecting the ear element and the plug element, wherein the plug element comprises a decoupling element, the decoupling element being provided in series with the electrically conducting element; the decoupling element being configured to decouple the electrically conducting element from the behind-the-ear module at a first frequency when the plug element is attached to the behind-the-ear module.

(59) In some embodiments, the decoupling element is an inductor with a self-resonant frequency at

the first frequency.

(60) It should be noted that the hearing device as such is of a small size so that the behind-the-ear module is able to fit behind the outer ear of a user, and the tube element, coupling the behind-the-ear housing to the in-the-ear module is of a small size, and configured to be as imperceptible as possible, to ensure that the overall impression of the hearing device maintains a small size to be as un-noticeable to the user as possible.

(61) In some embodiments, the conducting element, such as the electrical interconnection, may be insulated; however, typically, such insulation, to be sufficient for efficiently shielding any electromagnetic noise, would increase the diameter of the electrical interconnection more than desired for a hearing device use.

(62) The present disclosure relates to different aspects including the hearing device and the tube element described above and in the following, and corresponding hearing devices, binaural hearing devices, tube elements, systems, methods, devices, uses and/or product means, each yielding one or more of the benefits and advantages described in connection with the first mentioned aspect, and each having one or more embodiments corresponding to the embodiments described in connection with the first mentioned aspect and/or disclosed in the appended claims. Any embodiments described in connection with the first aspect of hearing devices, apply equally to any further aspects, *mutatis mutandis*.

(63) It is also to be understood that the terminology used herein is for purpose of describing particular embodiments only, and is not intended to be limiting. It should be noted that, as used in the specification and the appended claim, the articles “a”, “an”, and “the” are intended to mean that there are one or more of the elements unless the context explicitly dictates otherwise. Thus, for example, reference to “a unit” or “the unit” may include several devices, and the like. Furthermore, the words “comprising”, “including”, “containing” and similar wordings does not exclude other elements or steps.

Description

BRIEF DESCRIPTIONS OF THE DRAWINGS

(1) The above and other features and advantages will become readily apparent to those skilled in the art by the following detailed description of exemplary embodiments thereof with reference to the attached drawings, in which:

(2) FIGS. 1*a* and 1*b* schematically illustrate an example of components in a hearing device,

(3) FIGS. 2*a* and 2*b* schematically illustrate an example hearing device according to the present disclosure,

(4) FIG. 3 schematically illustrates an example hearing device according to the present disclosure, having two decoupling elements in series,

(5) FIGS. 4*a*-4*d* schematically illustrate an example hearing device according to the present disclosure, with a plug and socket arrangement between the behind-the-ear module and the tube element,

(6) FIG. 5 schematically illustrates an example of a tube assembly according to the present disclosure,

(7) FIG. 6 is a graph showing the impedance of an inductor at the self resonant frequency.

DETAILED DESCRIPTION

(8) The present disclosure will become apparent from the detailed description given below. The detailed description and specific examples disclose preferred embodiments by way of illustration only. Those skilled in the art understand from guidance in the detailed description that changes and modifications may be made within the scope of the claimed invention. The detailed description and specific examples disclose preferred embodiments by way of illustration only. Those skilled in the

art understand from guidance in the detailed description that changes and modifications may be made within the scope of the claimed invention. Thus, the claimed invention may be embodied in other forms and should not be construed as limited to the herein disclosed embodiments. The disclosed embodiments are provided to fully convey the scope of the claimed invention to the skilled person.

(9) Various embodiments are described hereinafter with reference to the figures. Like reference numerals refer to like elements throughout. Like elements will, thus, not be described in detail with respect to the description of each figure. It should also be noted that the figures are only intended to facilitate the description of the embodiments. They are not intended as an exhaustive description of the claimed invention or as a limitation on the scope of the claimed invention. In addition, an illustrated embodiment needs not have all the aspects or advantages shown. An aspect or an advantage described in conjunction with a particular embodiment is not necessarily limited to that embodiment and can be practiced in any other embodiments even if not so illustrated, or if not so explicitly described.

(10) Throughout, the same reference numerals are used for identical or corresponding parts.

(11) A block-diagram of an embodiment of a hearing device **10** is shown in FIG. **1a**. The hearing device **10** comprises a behind-the-ear module **9** and a tube element **16** extending from the behind-the-ear module **9**. The behind-the-ear module comprises a signal processor **12** for processing received audio signals into a signal modified to compensate for a user's hearing impairment, an antenna **15** configured for emission and reception of electromagnetic radiation at a first frequency. The hearing device **10** further comprises at least one electrically conducting element **18**, wherein a first section **17** of the at least one electrically conducting element extends into the tube element **16**. The hearing device further comprises at least one decoupling element **19**. The at least one decoupling element **19** being configured to electrically decouple the first section **17** and the behind-the-ear module **9** at the first frequency while maintaining an electrical connection between the first section **17** and the behind-the-ear module **9** at second frequencies. The at least one decoupling element **19** may thus be configured to electrically decouple the first section **17** and electrical components of the behind-the-ear module **9** at the first frequency while maintaining an electrical connection between the first section **17** and electrical components of the behind-the-ear module **9** at second frequencies. The electrical components of the behind-the-ear module **9** may comprise the signal processor **12**, the wireless communication unit **14**, the antenna **15**, the microphone **11**, the battery **8**, etc.

(12) The hearing device **10** comprises a behind-the-ear module **9** comprising a first transducer, i.e. microphone **11**, to generate one or more microphone output signals based on a received audio signal. The one or more microphone output signals are provided to a signal processor **12** for processing the one or more microphone output signals. A receiver or speaker **13** is connected to an output of the signal processor **12** for converting the output of the signal processor into a signal modified to compensate for a user's hearing impairment, and provides the modified signal to the speaker **13**. The speaker output is provided to the ear of a user via a tube element **16**, such as a sound tube.

(13) The hearing device signal processor **12** may comprise elements such as an amplifier, a compressor and/or a noise reduction system etc. The hearing device may further have a filter function, such as compensation filter for optimizing the output signal.

(14) The hearing device **10**, and more particularly the behind-the-ear module **9**, further comprises a wireless communication unit **14** interconnected with antenna **15**. The wireless communication unit **14** and the antenna **15** may be configured for wireless data communication using emission and reception of electromagnetic fields. A wireless communication unit may be implemented as transceiver **14**. The hearing device **10** further comprises a power source **8**, such as a battery or a rechargeable battery. The battery **8** may supply power to any one or more of the signal processor **12**, the receiver, the one or more microphones **11**, the wireless communication unit **14**, etc.

(connections not shown). The antenna **16** is configured for communication with another electronic device, in some embodiments configured for communication with another hearing device, such as another hearing device located at another ear, typically in a binaural hearing device system.

(15) In FIG. **1b** another block-diagram of an embodiment of a hearing device **10** is shown. A block-diagram of an embodiment of a hearing device **10** is shown in FIG. **1a**. The hearing device **10** comprises a behind-the-ear module **9** and a tube element **16** extending from the behind-the-ear module **9**. The behind-the-ear module comprises a signal processor **12** for processing received audio signals into a signal modified to compensate for a user's hearing impairment, an antenna **15** configured for emission and reception of electromagnetic radiation at a first frequency. The hearing device **10** further comprises at least one electrically conducting element **18**, wherein a first section **17** of the at least one electrically conducting element extends into the tube element **16**. The hearing device further comprises at least one decoupling element **19**. The at least one decoupling element **19** being configured to electrically decouple the first section **17** and the behind-the-ear module **9** at the first frequency while maintaining an electrical connection between the first section **17** and the behind-the-ear module **9** at second frequencies. In FIG. **1b**, the receiver **13** is provided in an ear element **20**, and the at least one decoupling element **19** may thus be configured to electrically decouple the first section **17** of the electrically conducting element and electrical components of the behind-the-ear module **9**, such as the signal processor **12**, and/or the wireless communication unit **14**, at the first frequency while maintaining an electrical connection between the first section **17** and electrical components of the behind-the-ear module **9**, such as the signal processor **12** at second frequencies.

(16) The receiver or speaker **13** is provided in ear element **20** configured to be positioned in or at the ear of a user, such as at least partly in the ear canal, such as completely in the ear canal. The receiver **13** is connected to the output of the signal processor **12** for converting the output of the signal processor into a signal modified to compensate for a user's hearing impairment, and provides the modified signal to the speaker **13**. The speaker output is provided to the ear of a user via a tube element **16**, via electrically conducting element **18**. As is seen, the hearing device thus further comprises ear element **20**, the ear element **20** being configured to be inserted into the ear canal of the user, the tube element **16** interconnecting the ear element **20** and the behind-the-ear module **9**, and wherein the ear element **20** comprises at least one in-ear electrical component **13**. This may include a receiver, and the modified signal may be configured to be provided to the receiver, via the at least one electrically conducting element **17**.

(17) FIG. **2a** shows schematically a hearing device **10**. The at least one electrically conducting element **18** comprises the first section **17** and the second section **21** is seen as extending from the signal processor **12** and into the tube element **16**. It is envisaged that the at least one electrically conducting element could be extending from any of the electrical components in the behind-the-ear modules and that the signal processor is used for illustration purposes. In FIG. **2a**, the at least one electrically conducting element has a second section **21**, and the at least one decoupling element **19** is provided between the first section **17** and the second section **21**; the at least one decoupling element **19** being configured to electrically decouple the first section **17** from the second section **21** at the first frequency, while maintaining an electrical connection between the first section **17** and the second section **21** at the second frequencies. As is seen from FIG. **2a**, the decoupling element **19** is positioned in the behind-the-ear module **9** and the second section **21** of the at least one electrically conducting element extends at least partly in the behind-the-ear module **9**. Preferably, the at least one decoupling element **19** is provided adjacent the tube element **16**, or in close proximity to the tube element **16**. In some examples, this may provide that the decoupling is provided close to the part **28** of the electrically conducting element extending into the tube element **16**.

(18) FIG. **2b** shows schematically a hearing device **10** corresponding to the hearing device **10** of FIG. **2a**. As is seen from FIG. **2b**, the decoupling element **19** is positioned in the tube element **16**

and the second section **21** of the at least one electrically conducting element extends at least partly in the behind-the-ear module **9**; and partly in the tube element **16**.

(19) The at least one decoupling element has a high impedance at the first frequency, preferably an impedance above 1 k Ω , such as above 4 k Ω , such as above 5 k Ω . The at least one decoupling element may be an inductor having a self-resonant frequency at the first frequency.

(20) FIG. **3** shows an embodiment in which the at least one decoupling element is further configured to electrically decouple the first section and the behind-the-ear module at a third frequency, the third frequency being different from the first frequency and the second frequencies. In FIG. **3**, the at least one decoupling element comprises a primary decoupling element **23** and a secondary decoupling element **24**. The primary decoupling element **23** and the secondary decoupling element **24** are being connected in series. The primary decoupling element may be configured to decouple the at least one conducting element from the behind-the-ear module at the first frequency, while the secondary decoupling element may be configured to decouple the at least one conducting element from the behind-the-ear module at another frequency, such as at a third frequency different from the first frequency while maintaining an electrical connection at second frequencies.

(21) The primary decoupling element **23** may have a self resonant frequency at the first frequency, such as about the first frequency, as discussed above, and the secondary decoupling element **24** may have a self resonant frequency at the other frequency, such as at the third frequency different from the first frequency. Hereby, any signals at the first frequency and the third frequency are blocked or at least significantly attenuated while maintaining an electrical connection at any other frequencies, i.e. at second frequencies.

(22) FIGS. **4a-d** show embodiments of a hearing device **10** further comprising an electro-mechanical interface **25** configured to releasably attach the tube element **16** to the behind-the-ear module **9**.

(23) The electro-mechanical interface **25** has a first part **26** forming part of the behind-the-ear module **9** and a second part **27** forming part of the tube element **16**. The first part **26** and the second part **27** are configured to be releasably connected in any known way and comprises electrical contacts so that when connected, an electrical connection is provided between first section **17** and second section **21** of each electrically conducting element **18**. The first part **26** may be implemented as a socket for receiving the second part **27**, which may be implemented as a plug. The first part **26** may form an integrated part of the behind-the-ear module **9**. The second part **27** may form an integrated part of the tube element **16**.

(24) In FIG. **4a**, the at least one decoupling element **19** is provided in the second part **27** of the electro-mechanical interface **25**. When the first part **26** and the second part **27** are connected, an electrical connection between the first section **17** and the second section **21** is formed, while the decoupling element **19** is configured to decouple the first section **17** and the second section **21** at the first frequency, such as configured to decouple the first section **17** and the behind-the-ear module **9**, such as the first section **17** and electrical components, illustrated by signal processor **12**, of the behind-the-ear module **9** at the first frequency. Hereby, any coupling at the first frequency between the first section **17** and the behind-the-ear module **9** is at least reduced.

(25) In FIG. **4b**, the at least one decoupling element **19** is provided in the first part **26** of the electro-mechanical interface **25**.

(26) Providing the at least one decoupling element **19** in the electro-mechanical interface, such as in the first part **26** or in the second part **27**, may in some examples provide that the decoupling is performed as close to the part of the electrically conducting element **28** extending into the tube element **16** as possible. In such case, the coupling may be efficiently reduced.

(27) In FIG. **4c**, the at least one decoupling element **19** is provided in the behind-the-ear module **9**. Preferably, the at least one decoupling element is provided adjacent to the first part **26**, or in close proximity to the first part **26**, to ensure that the decoupling is provided as close to the part of the

electrically conducting element extending into the tube element **16**. The first part **26** of the electro-mechanical interface **25** forming part of the behind-the-ear module **9** and a second part **27** forming part of the tube element **16**. In FIG. **4c**, the first part **26** and the second part **27** are seen as being detached from each other, or disconnected.

(28) In FIG. **4d**, a hearing device having a plurality of electrically conducting elements comprising first sections **17'**, **17''**, **17'''** and second sections **21'**, **21''**, **21'''** is illustrated.

(29) The second sections may connect to any electrical component in the behind-the-ear module **9**, including but not limited to, the power source **8**, the signal processor **12**, the wireless communication unit **14**, etc. The first sections **17'**, **17''**, **17'''** may via connection to the second sections **21'**, **21''**, **21'''** connect to for example, but not limited to, electrical components in the ear element **20**, such as to transducers, such as to a receiver, one or more microphones, etc. In some embodiments, an electrically conducting element may not connect to any components in the ear element **20**, however, it is envisaged that also such electrically conductive elements are decoupled at the first and optionally also the third frequency.

(30) In FIG. **4d**, the first part **26** and the second part **27** of the electro-mechanical interface **25** is shown as connected. In FIG. **4d**, a second section **21'** extends from the signal processor **12**, through the first part **26** and to the second part **27**. In the second part **27**, the second section **21'** connects to the decoupling element **19'** for decoupling the first section **17'** at the first frequency. The first section **17'** extends from the decoupling element **19'** into the tube element **16**. A further second section **21''** extends from anywhere in the behind-the-ear module, such as from the power source **8**, the wireless communication unit **14**, etc., and via the first part **25** to the decoupling element **19''** being positioned in the first part **26**. The first section **17''** extends from the decoupling element **19''**, through the second part **27** and into the tube element **16**. Thereby, the decoupling element **19''** decouples the first section **17''** from the second section **21''** extending in the behind-the-ear module. A further second section **21'''** extends from the signal processor **12** to the decoupling element **19'''** being positioned in the behind-the-ear module **9**. The first section **17'''** extends from the decoupling element **19'''** through the first part **26** and the second part **27** and extends into the tube element **16**. The decoupling elements **19'**, **19''**, **19'''** are thus provided in series with the first sections **17'**, **17''**, **17'''** and the second sections **21'**, **21''**, **21'''**.

(31) It is envisaged that to obtain the best decoupling, each electrically conducting element extending into the tube element **16** should be decoupled using a decoupling element. Hereby, an efficient decoupling can be obtained between each of the at least one electrically conducting elements in the tube element **16** and the behind-the-ear module **9**. As illustrated in the figures, the hearing device may comprise a plurality of electrically conducting elements **17'**, **17''**, **17'''**, **21'**, **21''**, **21'''** and a plurality of decoupling elements **19'**, **19''**, **19'''** configured to electrically decouple the plurality of electrically conducting elements from the behind-the-ear module at the first frequency. As is seen each of the plurality of electrically conducting elements is connected in series with one or more of the plurality of decoupling elements.

(32) In one example, the electrically conducting element **17'**, **21'** extending from the signal processor **12** connects the signal processor to the receiver **13** in the ear element **20**. Thus, the electrically conducting element carries the audio signal from the signal processor **12** to the receiver **13**. Such an audio signal is typically a low power signal at audible frequencies, and therefore, to ensure the best quality of the audio signal received by the receiver **13**, the decoupling element **19'** may be a decoupling element having a low impedance at the second frequencies, such as at the audible frequencies of the audio signal. The decoupling element may have an impedance which is lower than e.g. a decoupling element providing power to e.g. a microphone in the ear element **20**. As the size of the decoupling element, such as the size of the inductor, is typically larger when the impedance should be minimized. By using only low impedance decoupling elements, for sensitive audio signals, the size of the hearing device can be minimized as other signals may be provided using decoupling elements having a higher impedance, and thus smaller physical size.

(33) For example, at least a first electrically conducting element, such as **17'**, **21'**, and a second electrically conducting element, such as **17''**, **21''**, may be connected with a first decoupling element, such as **19'**, and a second decoupling element, such as **19''**, and the first decoupling element **19'** may have lower impedance than the second decoupling element **19''** at audible frequencies.

(34) FIG. 5 shows a tube assembly **30** for a hearing device, the tube assembly **30** comprises an ear element **20** configured to be inserted into the ear of a user, a plug element **27** configured for attachment to a behind-the-ear module (not shown), a tube element **16** interconnecting the ear element **20** and the plug element **27**, and an electrically conducting element **17** extending into the tube element. The plug element **20** comprises a decoupling element **19**, the decoupling element **19** being provided in series with the electrically conducting element **17**; the decoupling element being configured to decouple the electrically conducting element **17** from the behind-the-ear module at a first frequency when the plug element **27** is attached to the behind-the-ear module. It is envisaged that there may be a number of electrically conducting elements **17** extending into the tube element; typically, each electrically conducting element will have a decoupling element mounted in series therewith. The decoupling element may be an inductor with a self-resonant frequency at the first frequency.

(35) FIG. 6 shows the impedance of a decoupling element according to an embodiment of the present disclosure. The 2.4 GHz ISM band is illustrated by line **33**, extending in a range about the center frequency of 2.4 GHz. The impedance of two inductors are shown with lines **31** and **32**. It is seen that both inductors have a self-resonance at about 2.4 GHz, making such inductors efficient for decoupling at 2.4 GHz. It is envisaged that other inductors could be used for decoupling at e.g. a third frequency, so that the self resonant frequency would be selected at or at about the third frequency.

(36) The person skilled in the art realizes that the claimed invention is not limited to the preferred embodiments described above. The person skilled in the art further realizes that modifications and variations are possible within the scope of the appended claims. Additionally, variations to the disclosed embodiments can be understood and effected by the skilled person in practicing the claimed invention, from a study of the drawings, the disclosure, and the appended claims.

Claims

1. A hearing device comprising: a behind-the-ear module and a tube assembly, the tube assembly configured to releasably attach to the behind-the-ear module; wherein the behind-the-ear module comprises: a signal processor configured to process an audio signal and to provide an output signal to compensate for a hearing impairment of a user; an antenna configured for electromagnetic radiation emission at a first frequency and/or electromagnetic radiation reception at the first frequency; wherein the tube assembly comprises: a tube element; a wire in the tube element; a decoupling element configured to electrically decouple the wire in the tube element and the behind-the-ear module at the first frequency, and to maintain an electrical connection between the wire and the behind-the-ear module at a second frequency that is different from the first frequency; and a connector fixedly coupled with the tube element, wherein the connector is configured to releasably attach (1) the tube element and (2) the wire in the tube element, physically to the behind-the-ear module; wherein at least a part of the decoupling element is at the connector, and is away from the behind-the-ear module when the connector is detached from the behind-the-ear module, and wherein the at least the part of the decoupling element is detachable from the behind-the-ear module, and is away from the tube element while the connector is fixedly coupled with the tube element; and wherein the decoupling element comprises a primary decoupling element and a secondary decoupling element, the primary decoupling element and the secondary decoupling element being connected in series and having respective self-resonant frequencies.

2. The hearing device according to claim 1, wherein the connector has another wire, and wherein the decoupling element is between the wire and the other wire; and wherein the decoupling element is configured to electrically decouple the wire from the other wire at the first frequency, and to maintain an electrical connection between the wire and the other wire at the second frequency.
3. The hearing device according to claim 2, wherein the other wire extends at least partly in the behind-the-ear module.
4. The hearing device according to claim 1, wherein the decoupling element has an impedance above 1 k Ω at the first frequency.
5. The hearing device according to claim 1, wherein the primary decoupling element comprises an inductor, and wherein the self-resonant frequency of the inductor is at the first frequency or at anywhere within a range defined by the first frequency $\pm 10\%$ of the first frequency.
6. The hearing device according to claim 1, wherein the decoupling element is further configured to electrically decouple the behind-the-ear module at a third frequency, the third frequency being different from the first frequency and the second frequency.
7. The hearing device according to claim 1, further comprising an earpiece, the earpiece being configured to be inserted into an ear canal of the user, the tube element interconnecting the earpiece and the behind-the-ear module.
8. The hearing device according to claim 7, wherein the earpiece comprises a receiver, and wherein the signal processor is configured to provide the output signal to the receiver, and wherein the wire is connected to the receiver.
9. The hearing device according to claim 1, wherein the decoupling element has an impedance below 100 Ω at the second frequency.
10. The hearing device according to claim 1, wherein the second frequency comprises an audible frequency.
11. The hearing device according to claim 1, further comprising an electrically conducting element and an additional decoupling element; wherein the wire is connected with the decoupling element, and the electrically conducting element is connected with the additional decoupling element; and wherein the decoupling element and the additional decoupling element have different respective impedances.
12. The hearing device according to claim 1, further comprising a microphone in the behind-the-ear module.
13. The hearing device according to claim 1, wherein an entirety of the decoupling element is at the connector at the end of the tube element.
14. The hearing device according to claim 1, wherein another part of the decoupling element is at the behind-the-ear module.
15. A tube assembly for a hearing device, comprising: an ear element configured to be inserted into an ear of a user, the ear element comprising a microphone; a connector configured to releasably attach to a behind-the-ear module; a tube element interconnecting the ear element and the connector; and a wire in the tube element; wherein the connector comprises a decoupling element, and wherein the connector is fixedly coupled with the tube element; wherein the decoupling element of the connector is configured to decouple the wire in the tube element from the behind-the-ear module at a first frequency when the connector is attached to the behind-the-ear module, wherein the decoupling element of the connector is away from the behind-the-ear module when the connector is detached from the behind-the-ear module, and wherein the decoupling element is detachable from the behind-the-ear module, and is away from the tube element while the connector is fixedly coupled with the tube element; and wherein the decoupling element comprises a primary decoupling element and a secondary decoupling element, the primary decoupling element and the secondary decoupling element being connected in series and having respective self-resonant frequencies.
16. The tube assembly according to claim 15, where the primary decoupling element comprises an

inductor, and wherein the self-resonant frequency of the inductor is at the first frequency or at anywhere within a range defined by the first frequency $\pm 10\%$ of the first frequency.

17. The tube assembly according to claim 15, wherein the decoupling element is coupled in series with respect to the wire.

18. The tube assembly according to claim 15, wherein the connector and the tube element are formed as a unit that is separate from the behind-the-ear module.

19. The tube assembly of claim 15, wherein the wire comprises a receiver wire.

20. The tube assembly of claim 15, wherein the wire comprises a microphone wire.

21. The tube assembly of claim 15, further comprising another wire, wherein the decoupling element of the connector is coupled between the wire and the other wire.

22. The tube assembly of claim 21, wherein the decoupling element and the other wire are in the connector, and wherein a majority of the wire is in the tube element.

23. A hearing device comprising: a behind-the-ear module, a tube element extending from the behind-the-ear module, and an earpiece, the earpiece comprising a receiver; wherein the behind-the-ear module comprises a signal processor, the signal processor configured to process an audio signal and to provide an output signal to compensate for a hearing impairment of a user; a receiver wire connecting the receiver of the earpiece to the behind-the-ear module; and a decoupling element configured to electrically decouple a section of the receiver wire and the behind-the-ear module at a first frequency, and to electrically connect the section of the receiver wire and the behind-the-ear module at a second frequency that is different from the first frequency; wherein the hearing device further comprises a connector configured to releasably attach the tube element and the receiver wire from the behind-the-ear module, the connector being fixedly coupled with the tube element, wherein at least a part of the decoupling element is inside the connector, and wherein the at least the part of the decoupling element is detachable from the behind-the-ear module, and is away from the tube element while the connector is fixedly coupled with the tube element; and wherein the decoupling element comprises a primary decoupling element and a secondary decoupling element, the primary decoupling element and the secondary decoupling element being connected in series and having respective self-resonant frequencies.

24. The hearing device according to claim 23, further comprising a microphone wire, and an additional decoupling element configured to electrically decouple a section of the microphone wire and the behind-the-ear module at the first frequency.

25. The hearing device according to claim 24, wherein the additional decoupling element is configured to electrically connect the section of the microphone wire and the behind-the-ear module at the second frequency that is different from the first frequency.

26. A hearing device comprising: a behind-the-ear module, a tube element extending from the behind-the-ear module, and an earpiece, the earpiece comprising a receiver and a microphone; wherein the behind-the-ear module comprises a signal processor, the signal processor configured to process an audio signal and to provide an output signal to compensate for a hearing impairment of a user; a receiver wire connecting the receiver of the earpiece to the behind-the-ear module; a decoupling element configured to electrically decouple a section of the receiver wire and the behind-the-ear module at a first frequency, and to electrically connect the section of the receiver wire and the behind-the-ear module at multiple second frequencies that are different from the first frequency; wherein at least a part of the decoupling element is at a connector at an end of the tube element, the connector being fixedly coupled with the tube element, and wherein the at least the part of the decoupling element is detachable from the behind-the-ear module, and is away from the tube element while the connector is fixedly coupled with the tube element; and wherein the decoupling element comprises a primary decoupling element and a secondary decoupling element, the primary decoupling element and the secondary decoupling element being connected in series and having respective self-resonant frequencies.

27. The hearing device according to claim 26, wherein another part of the decoupling element is at

the behind-the-ear module.

28. The hearing device according to claim 26, wherein the at least a part of the decoupling element is located away from electronics inside the behind-the-ear module.
