

US Patent & Trademark Office

Patent Public Search | Text View

United States Patent Application Publication

20250280573

Kind Code

A1

Publication Date

September 04, 2025

Inventor(s)

SAGGIO; Mario Giuseppe et al.

4H-SIC ELECTRONIC DEVICE WITH IMPROVED SHORT-CIRCUIT PERFORMANCES, AND MANUFACTURING METHOD THEREOF

Abstract

An electronic device includes a semiconductor body of silicon carbide, and a body region at a first surface of the semiconductor body. A source region is disposed in the body region. A drain region is disposed at a second surface of the semiconductor body. A doped region extends seamlessly at the entire first surface of the semiconductor body and includes one or more first sub-regions having a first doping concentration and one or more second sub-regions having a second doping concentration lower than the first doping concentration. Thus, the device has zones alternated to each other having different conduction threshold voltage and different saturation current.

Inventors: SAGGIO; Mario Giuseppe (Aci Bonaccorsi, IT), MAGRI'; Angelo (Belpasso, IT), ZANETTI; Edoardo (Valverde, IT), GUARNERA; Alfio (Trecastagni, IT)

Applicant: STMicroelectronics S.r.l. (Agrate Brianza, IT)

Family ID: 78962723

Assignee: STMicroelectronics S.r.l. (Agrate Brianza, IT)

Appl. No.: 19/209627

Filed: May 15, 2025

Foreign Application Priority Data

IT	102020000015076	Jun. 23, 2020
----	-----------------	---------------

Related U.S. Application Data

parent US continuation 18464141 20230908 parent-grant-document US 12342582 child US 19209627

Publication Classification

Int. Cl.: H10D62/10 (20250101); H10D62/832 (20250101)

U.S. Cl.:

CPC H10D62/102 (20250101); H10D62/8325 (20250101);

Background/Summary

BACKGROUND

Technical Field

[0001] The present disclosure relates to an electronic device and a manufacturing method thereof. In particular, the present disclosure refers to an electronic device provided with selective regions having different conduction threshold voltage or, alternatively, different saturation current.

Description of the Related Art

[0002] FIG. 1 shows a basic structure of a vertical MOSFET device 1, in lateral view and in a tri-axial reference system of orthogonal axis X, Y, Z. In a typical embodiment, the MOSFET device 1 includes a plurality of these basic structures that work together, sharing a same drain terminal (D), with all gate terminals (G) connected together by a deposited polysilicon mesh (not shown), and all of the source terminals (S) electrically connected and linked by a top metal layer 10.

[0003] As depicted in FIG. 1, the MOSFET device 1 comprises a semiconductor body 2, of semiconductor material (which includes a substrate and, optionally, one or more epitaxial layers), having a top surface 2a and a bottom surface 2b. The semiconductor body 2 is, e.g., N-doped. At the bottom surface 2b, a drain region 4 is formed, e.g., by implanting dopant species of N-type (N⁺ doped). At the top surface 2a body regions 5 (P doped) surround source regions 8 (N⁺ doped). Gate structures 6, including a stack formed by a gate conductive layer 6a and a gate dielectric layer 6b, extend on the top surface 2a, overlapping in part the source regions 8. A respective insulating layer 9 covers the gate structures 6.

[0004] The top metal layer 10 electrically contacts the source regions 8 and the body regions 5 at superficial portions 16 and 17 respectively, in order to bias, during use, the source regions 8 and the body regions 5 at a same biasing voltage.

[0005] To improve the electrical contact between the top metal layer 10 and the body regions 5, a P-well region (P⁺ doped) 14 is formed in some of the body regions 5 and facing the top surface 2a in a region corresponding to the superficial portion 17. Typically, a silicide interfacing layer (not shown) is formed at the superficial portion 17, to form an ohmic contact between the metal 10 and the implanted P-well region 14. The P-well region 14 is formed only where the metal layer 10 is designed to contact the body regions 5. The

[0006] P-well region 14 is arranged between source regions 8, in a respective body region 5. Where, by design, it has been decided to form the contact between the top metal layer 10 and the source regions 8 (i.e., at the superficial region 16), the respective source region 8 extends continuously within the body region 5 which houses it, facing the top surface 2a at the superficial region 16. Further layers, to enhance the electrical contact between the metal 10 and the source 8 may be formed, in a per se known way and not shown.

[0007] During the ON state of the MOSFET device 1, while gate-source voltage V_{sub.GS} is above

threshold, a conduction current is localized in the drain region **4** and in the region of the semiconductor body **2** below the gate structure **6** (current flow **18**). During OFF state of the MOSFET device **1**, the voltage drop across the drain D and source S is sustained by a PN junction at reverse bias, and a very small current (leakage) flows through the PN junction. If the voltage increases too much and the electrical field reaches a critical value, the PN junction goes into breakdown, and the current starts to flow through the body region **5**. If an overvoltage is applied to the PN junction, a current flows through it while the MOSFET device **1** limits the actual drain-source breakdown voltage (BV.sub.DS). The breakdown mechanism itself is not destructive for a PN junction. However, overheating caused by the high breakdown current and voltage damages the PN junction unless sufficient heat sinking is provided.

[0008] Considering the MOSFET structure in greater detail, one may see that the PN junction is not a “perfect diode”. The diode is the collector-base junction of a Bipolar Junction Transistor (BJT), also called the parasitic transistor, made by the N⁺ source **8**, P/P⁺ body **5**, and N⁺ drain **4**, with the base shorted to the emitter by the metal layer **10**.

[0009] When designing the device, the behavior of the same in failure mode at the short circuit event should be taken into account, where the simultaneous presence of high current and high voltage produces a thermal runaway, leading to the destruction of the device (e.g., typical case of event that occurs when an electric motor halts).

[0010] As is known, some semiconductor materials are ideal for producing electronic components, such as diodes or transistors, in particular for power applications. These materials have wide forbidden band gap, in particular, have an energy value E_g of the forbidden band gap greater than 1.1 eV, low on-state resistance ($R_{sub.ON}$), high value of thermal conductivity, high operating frequency, and high velocity saturation of charge carriers. A material having said characteristics, and designed to be used for manufacturing electronic components, is silicon carbide (SiC). In particular, silicon carbide, in its different polytypes (e.g., 3C-SiC, 4H-SiC, 6H-SiC), is preferable to silicon as regards the properties listed previously.

[0011] Electronic devices provided on a silicon-carbide substrate, as compared to similar devices provided on a silicon substrate, present numerous advantageous characteristics, such as low output resistance in conduction, low leakage current, high working temperature, and high working frequencies.

[0012] However, the above issues are not fully overcome by the use of SiC and, to improve the avalanche capability of the MOSFET device, common solutions foresee an edge structure having a much higher breakdown threshold with respect to the active area. However, due to limitation of efficiency at the edges of the device, this target is not always feasible.

[0013] The resistance in ON-state is furthermore impacted, since the source resistance depends upon the doping value of the source region **8**.

BRIEF SUMMARY

[0014] In various embodiments, the present disclosure provides an electronic device and a manufacturing method thereof, that overcome the drawbacks of the prior art. In one or more embodiments of the present disclosure provide the technical advantage of limiting the thermal runaway, and a method that limits the saturation current and the power dissipated locally, with minimum impact on the output resistance of the device.

[0015] According to the present disclosure, an electronic device and a manufacturing method thereof are provided.

[0016] In at least one embodiment, an electronic device is provided that includes a semiconductor body of silicon carbide (SiC) having a first and a second surface, opposite to one another along a direction. A body region, having a first conductivity, extends in the semiconductor body at the first surface. A source region, having a second conductivity opposite to the first conductivity, extends in the body region at the first surface of the semiconductor body. A doped region, having the second conductivity, extends continuously at the entire first surface of the semiconductor body, and

includes one or more first sub-regions having a first doping density and one or more second sub-regions having a second doping density lower than the first doping density.

[0017] In at least one embodiment, a method for manufacturing an electronic device is provided that includes: forming a body region, having a first conductivity, in a semiconductor body of silicon carbide (SiC) at a first surface, the semiconductor body having a second surface opposite to the first surface along a direction; forming a source region, having a second conductivity opposite to the first conductivity, in the body region at the first surface of the semiconductor body; forming a drain region, having the second conductivity, at the second surface; and forming a doped region, having the second conductivity, extending seamlessly at the entire first surface of the semiconductor body, the forming the doped region includes: forming one or more first sub-regions having a first doping density; and forming one or more second sub-regions having a second doping density lower than the first doping density.

[0018] In at least one embodiment, a device is provided that includes a semiconductor body having a first surface, and a second surface opposite the first surface along a direction. A body region, having a first conductivity, extends in the semiconductor body at the first surface. A source region, having a second conductivity opposite to the first conductivity, extends in the body region at the first surface of the semiconductor body. A drain region, having the second conductivity, extends at the second surface of the semiconductor body. A doped region, having the second conductivity, extends continuously at the entire first surface of the semiconductor body. The doped region includes a first sub-region having a first doping density and a second sub-region having a second doping density lower than the first doping density. A first gate structure is on the first doped region, and a second gate structure is on the second doped region.

BRIEF DESCRIPTION OF THE SEVERAL VIEWS OF THE DRAWINGS

[0019] For a better understanding of the present disclosure, preferred embodiments thereof are now described, purely by way of non-limiting example, with reference to the attached drawings, wherein:

[0020] FIG. 1 shows a MOSFET device of a known type;

[0021] FIG. 2 shows a MOSFET device according to an embodiment of the present disclosure;

[0022] FIGS. 3A and 3B show process steps to manufacture the MOSFET device of FIG. 2; and

[0023] FIGS. 4A-4D show plan views of respective layouts of implanted regions of the MOSFET device of FIG. 2, according to respective embodiments of the present disclosure.

Description

DETAILED DESCRIPTION

[0024] FIG. 2 shows a portion of MOSFET device **100** according to an embodiment of the present disclosure. FIG. 2 is a lateral cross-section view, in the same tri-axial reference system of orthogonal axis X, Y, Z of FIG. 1.

[0025] As already discussed with reference to FIG. 1, the portion shown in FIG. 2 may be a basic structure, or “cell”, that may be used to develop a MOSFET device **100** by replicating the basic structure a desired number of times; such basic structures work together, sharing a common drain terminal (D), a common gate terminal (G), and a common source terminal(S).

[0026] It is apparent that, when replicating the portion of FIG. 2, variations in the basic structure may be introduced, as apparent to the skilled person in the art, for example in order to comply with one or more among design requirements, area occupation, electrical requirements, manufacturing requirements, etc.

[0027] The MOSFET device **100** comprises a semiconductor body **102**, of semiconductor material (which includes, for example, a substrate and, optionally, one or more epitaxial layers), having a top surface **102a** and a bottom surface **102b** opposite to one another along axis Z.

[0028] In particular, the semiconductor body **102** is made of silicon carbide (SiC), more in particular 4H-SiC. The semiconductor body **102** is, in one embodiment, N-doped. Facing the bottom surface **102b** is a drain region **104**, e.g., formed by implanted dopant species of N-type (N+ doped). Body regions **105** (P doped) are arranged at the top surface **102a**.

[0029] Source regions **108** (N+ doped) are formed by implantation in the semiconductor body **102**, within the body regions **105**, facing the top surface **102a**. Therefore, the body regions **105** surround respective source regions **108** formed therein.

[0030] Gate structures **106** extend on the top surface **102a**, and include a stack formed by a gate conductive layer **106a** (e.g., of metal material) and a gate dielectric layer **106b** (of insulating or dielectric material). A respective insulating layer **109** covers each gate structure **106**, to electrically insulate the gate structures **106** from the metal layer **110**. The gate structures **106** overlap in part the source regions **8**; a respective channel region **118** is formed, during use, in the region of the semiconductor body **102** below the gate structures **106**, between body regions **105**/source regions **108**, in a per se known way. The current path is pictured in FIG. 2 with a dashed line **118** and goes from the source regions **108** towards the drain region **104** (vertical conduction).

[0031] The active area of the MOSFET device **100** is the area where current conduction takes place and, in particular, where the channel is formed. Typically, the active area is surrounded, either completely or partially, by an edge termination region, not shown and per se known. The edge termination region is, e.g., an implanted region having a P conductivity type.

[0032] In a way which is not shown in detail and which is per se known, all gate structures **106** are electrically connected together (e.g., by a polysilicon mesh), and all of the source regions **108** are electrically connected together.

[0033] The top metal layer **110** is in electrical contact with the source regions **108** and the body regions **105** at respective contact zones, in order to bias, during use, the source regions **108** and the body regions **105** at a same biasing voltage.

[0034] To improve the electrical contact between the top metal layer **110** and the body regions **105**, an electrical-contact interface (P+ doped) **114** is formed in one or more body regions **105**, at the top surface **2a**. Typically, each electrical-contact interface **114** includes a silicide interfacing layer (not shown), to form an ohmic contact between the top metal layer **110** and the respective electrical-contact interface **114**. The electrical-contact interface **114** is formed where the metal layer **110** reaches the top surface **102a** to contact the body regions **105**.

[0035] According to an aspect of the present disclosure, an electrical-contact interface **116** is also present between the top metal layer **110** and the region of the semiconductor body where, by design, it has been decided to form the contact between the top metal layer **110** and the source regions **108**.

[0036] According to an aspect of the present disclosure, the device **100** presents an implanted region **120** extending in proximity to, or directly facing, the top surface **102a**, along the entire extension of the device **100**. The implanted region **120** is of N-type and has the function of modulating the saturation current of the device **100**. In this context, the saturation current is the maximum current that the device sustains at a given gate voltage V_g and remains almost constant exceeding a certain drain-source voltage V_{DS} (knee voltage) once exceeded the linear region (where the on-state resistance R_{on} is identified). The saturation current value is limited by the switch-on voltage value of the device (V_{th}): a higher V_{th} corresponds to a lower saturation current.

[0037] The implanted region **120** is designed so as to present at least a first sub-region **121** having a first N-type dopant value, and at least a second sub-region **123** having a second N-type dopant value, lower than the first value of the first sub-region **121**.

[0038] The implanted region **120** extends, facing the top surface **102a**, within the body regions **105**, the source regions **108**, and in the zone below the gate dielectric **106b** intended to house the conductive channel and in the drain regions **104**.

[0039] Therefore, the implanted region **120** is in electrical contact with the body regions **105**, the

source regions **108** and the electrical-contact interfaces **114**.

[0040] The depth of the implanted region **120** in the semiconductor body **102**, measured from the top surface **102a** along the Z direction, ranges from 10 nm to 0.1 μm , in particular from 20 nm to 50 nm.

[0041] Where the implant dose is increased (first sub-region **121**), the threshold voltage V_{th} is lowered, i.e., the gate-source voltage value $V_{sub.GS}$ necessary to generate, or switch on, the conductive channel with respect to the second sub-region **123**, is reduced. The threshold voltage V_{th} is defined as the gate-source voltage $V_{sub.GS}$ at which the drain-source current $I_{sub.DS}$ is equal to 250 $\mu\text{A}/\text{mm}$.sup.2.

[0042] By localizing the implant in proximity to the top surface **102a** (in particular at the interface between the semiconductor body **102** and the gate dielectric layer **106b**) it is possible to influence the threshold voltage V_{th} in that specific zone of the device **100**, as a consequence of the saturation of interface defects typically present in SiC (e.g., as demonstrated by I. Pintilie et al., "Analysis of electron traps at the 4H-SiC/SiO₂ interface; influence by nitrogen implantation prior to wet oxidation", Journal of Applied Physics 108, 024503, 2010).

[0043] In this manner, during operation, the sub-region **121**, having higher dopant density, switches on with a voltage $V_{sub.GS}$ lower than the voltage $V_{sub.GS}$ required for switching on the sub-region **123**. As a result, as the voltage $V_{sub.GS}$ increases, a conductive channel is formed first in the sub-region **121** and, subsequently, in the sub-region **123**. Furthermore, when the voltage $V_{sub.GS}$ is such to switch on both the channel in the sub-region **121** and in the sub-region **123**, however, a higher current density is observed in the sub-region **121**.

[0044] The N-type dopant concentration in the first sub-region **121** is such that it exceeds the surface concentration of the body region **105** by a factor ranging from 5 to 20 times the concentration of the body region **105**; the N-type dopant concentration in the second sub-region **123** is such that it exceeds the surface concentration of the body region **105** by a factor ranging from 2 to 10 times the concentration of the body region **105**.

[0045] The ratio V_{th2}/V_{th1} between the threshold voltage V_{th2} of the sub-region **123** and the threshold voltage V_{th1} of the sub-region **121** ranges from 1.1 to 2.5 and is defined by the ratio of dopant concentration present in the two sub-regions.

[0046] Thus, with an appropriate layout of the implanted region **120**, it is possible to define zones of the device **100** designed to carry a greater electric current with respect to other zones of the device **100** or, in other words, it is possible to design zones of the device **100** where the carried current is limited, limiting, as a result, the saturation current in these zones. Zones dedicated to the carriage of the highest electric current are chosen on the basis of design considerations, selecting them among the most robust device zones or distributing this current uniformly such that there is no excessive concentration in some zones with respect to others.

[0047] As to the manufacturing process of the implanted region **120**, reference is made to FIGS. 3A and 3B, which show a portion of a semiconductor wafer limited to the features of the same that are useful to understand the present disclosure. FIGS. 3A and 3B illustrate exclusively manufacturing steps useful for the formation of the implanted region **120**, while remaining process steps for starting and completing the manufacturing of the device **100** are not described or illustrated, as they are not part of the present disclosure.

[0048] With reference to FIG. 3A, after having formed the body regions **105** through an implant of P doping species, and the source regions **108** through an implant of N doping species, a first unmasked implant of N-type species (e.g., Nitrogen or Phosphorus) is carried out, in order to form a first implanted region **130** in the interface **102a**. This first implant (shown by means of arrows in FIG. 3A) is carried out with implant energy in the range 10-100 keV. A protection layer **134** may be formed on the surface **102a** in order to obviate any surface damage of the semiconductor body **102** deriving from the implant.

[0049] The implant at step of FIG. 3A forms, in particular, the second sub-region **123** described

with reference to FIG. 2, and contributes to forming the first sub-region **121**.

[0050] Then, FIG. 3B, a second masked implant of N-type species (for example, Nitrogen or Phosphorus) is carried out, in order to complete the formation of the first sub-region **121**.

[0051] This second implant (shown by means of arrows **136** in FIG. 3B) is carried out with implant energy in the range 10-100 keV. A mask **137** used for the second implant leaves exposed superficial portions of the semiconductor body **102** corresponding to the regions where only the first sub-region **121** is to be formed. In one embodiment, the mask **137** may be formed as a hard mask, depositing a mask layer, for example of silicon oxide, on the surface **102a** of the semiconductor body **102** and shaping this mask layer to expose the superficial regions of the semiconductor body **102** where it is desired to implant the sub-region **121**.

[0052] Then, an annealing step is carried out, to favor the activation of all the implanted species of the sub-regions **121**, **123**. The annealing step is carried out at temperature in the range 1600-1800° C. This annealing step may be dedicated for the formation of the implanted region **120**, or common to the implanted region **120** and to the body and/or source and/or drain regions.

[0053] FIG. 4A illustrates, purely by way of example, a top view of a portion of the device **100** limited to the body regions **105** and to the implants of the first sub-region **121** (as said, the sub-region **123** is considered to be uniformly present at all the surface **102a** of the device **100**—not including portions of the surface **102a** which do not belong to the device **100**). As is noted, in this embodiment, a plurality of body regions **105** extend in the form of strips parallel to each other along the Y-axis direction; a plurality of first sub-regions **121** extend in the form of strips parallel to each other along the X-axis direction, overlapping the plurality of body regions **105**. At designer's choice, the first sub-regions **121** may cover a variable percentage of the body regions **105**, i.e., cover a percentage ranging from 50% to 80% of the body regions **105**.

[0054] FIGS. 4B-4D illustrate, according to respective embodiments alternative to each other and to that of FIG. 4A, respective top views of a portion of the device **100** limited to the body regions **105** and to the implants of the first sub-region **121**. As is noted, in these embodiments, a plurality of body regions **105** extend in the form of strips parallel to each other along the Y-axis direction, similarly to FIG. 4A; a plurality of first sub-regions **121** extend in the form of strips parallel to each other along the same Y-axis direction, partially overlapping the plurality of body regions **105**.

[0055] The strips of the first sub-regions **121** may extend completely overlapping respective strips of the body regions **105** as illustrated in FIG. 4B, or only partially overlapping them, as illustrated in FIGS. 4C and 4D.

[0056] FIG. 4B (and similarly FIG. 4C) illustrates first sub-regions **121** which extend to cover body regions **105** alternated to each other (one every two, i.e., the total area of the first sub-regions **121** is equal to 50% of the total area of the body regions **105**).

[0057] FIG. 4C illustrates first sub-regions **121** which extend between strips arranged side by side and directly facing each other of the body regions **105**, partially overlapping these body regions **105** arranged side by side. As for FIG. 4B, the total extension (or area) of the first sub-regions **121** is equal to 50% of the total area of the body regions **105**.

[0058] FIG. 4D illustrates an implementation of the first “checkerboard” sub-regions **121**, where the first sub-regions **121** extend along the body regions **105** discontinuously.

[0059] From what has been described, the advantages that the disclosure achieves are apparent.

[0060] The embodiments of the present disclosure have been found to increase the ruggedness during short-circuit tests. In fact, the structure of FIG. 2 (in the various described embodiments) allows to modulate the saturation current of the MOSFET device **100** at selected portions of the device **100**, with a minimum impact on the output resistance of the device **100**.

[0061] The layout design is carried out so as to eliminate zones with high current density. For example, therefore at wires or clips, the saturation current is limited, to uniform the total current which circulates in the device and to avoid the destruction of the device in case of short circuit.

[0062] Finally, it is clear that modifications and variations may be made to what has been described

and illustrated herein, without thereby departing from the scope of the present disclosure.

[0063] For example, the embodiments previously disclosed refer to a N-channel MOSFET. However, the present disclosure may be applied, as apparent to the skilled person, to a P-channel MOSFET as well.

[0064] In some embodiments, an electronic device (**100**) may be summarized as including a semiconductor body (**102**) of silicon carbide, SiC, having a first (**102a**) and a second surface (**102b**), opposite to one another along a direction (Z). A body region (**105**) has a first conductivity (P), and extends in the semiconductor body (**102**) at the first surface (**102a**). A source region (**108**) has a second conductivity (N), opposite to the first conductivity (P), and extends in the body region (**105**) at the first surface (**102a**) of the semiconductor body (**102**). A drain region (**104**) has the second conductivity (N), and extends at the second surface (**102b**) of the semiconductor body (**102**). A doped region (**120**), having the second conductivity (N), extends continuously at the entire first surface (**102a**) of the semiconductor body (**102**), and includes one or more first sub-regions (**121**) having a first doping density and one or more second sub-regions (**123**) having a second doping density lower than the first doping density.

[0065] In some embodiments, the first sub-regions (**121**) are alternated with the second sub-regions (**123**) so to form zones alternated to each other having different conduction threshold voltage (V_{th1} , V_{th2}) or, alternatively, different saturation current.

[0066] In some embodiments, each first sub-region (**121**) and each second sub-region (**123**) is designed in such a way that the ratio (V_{th2}/V_{th1}) between a conduction threshold voltage (V_{th2}) of each second sub-region (**123**) and a conduction threshold voltage (V_{th1}) of each first sub-region (**121**) ranges from 1.1 to 2.5.

[0067] In some embodiments, the first and the second sub-regions (**121**, **123**) have a depth, in the semiconductor body from the surface (**102a**) ranging from 10 nm to 0.1 μm .

[0068] In some embodiments, the first doping density has a value ranging from 5 to 20 times a respective doping density value of the body region (**105**) and the second doping density has a respective value ranging from 2 to 10 times the doping density value of the body region (**105**).

[0069] In some embodiments, the first sub-regions (**121**) are contiguous to, and electrically connected to, respective second sub-regions (**123**).

[0070] In some embodiments, the second sub-regions (**123**) occupy a volume of the doped region (**120**) ranging from 50% to 80%.

[0071] In some embodiments, a gate structure (**106**) is disposed on the first surface (**102a**) of the semiconductor body. The gate structure includes: a gate dielectric layer (**106b**), a metal gate layer (**106a**) on the gate dielectric layer (**106b**), and an insulating layer surrounding the metal gate layer (**106a**). The doped region (**120**) may extend within the source regions, the body regions and below the gate structure (**106**).

[0072] In some embodiments, the semiconductor body (**102**) is of 4H-SiC.

[0073] In some embodiments, a method for manufacturing an electronic device (**100**) may be summarized as including the steps of: arranging a semiconductor body (**102**) of silicon carbide, SiC, having a first (**102a**) and a second surface (**102b**), opposite to one another along a direction (Z); forming a body region (**105**), having a first conductivity (P), in the semiconductor body (**102**) at the first surface (**102a**); forming a source region (**108**), having a second conductivity (N) opposite to the first conductivity (P), in the body region (**105**) at the first surface (**102a**) of the semiconductor body (**102**); and forming a drain region (**104**), having the second conductivity (N), at the second surface (**102b**), characterized in that it further comprises the step of forming a doped region (**120**), having the second conductivity (N), extending seamlessly at the entire first surface (**102a**) of the semiconductor body (**102**), including the sub-steps of: forming one or more first sub-regions (**121**) having a first doping density; and forming one or more second sub-regions (**123**) having a second doping density lower than the first doping density.

[0074] In some embodiments, the first sub-regions (**121**) are alternated with the second sub-regions

(123) so to form zones alternated to each other having different conduction threshold voltage (V_{th1} , V_{th2}) or, alternatively, different saturation current.

[0075] In some embodiments, each first sub-region (121) and each second sub-region (123) is designed in such a way that the ratio (V_{th2}/V_{th1}) between a conduction threshold voltage (V_{th2}) of each second sub-region (123) and a conduction threshold voltage (V_{th1}) of each first sub-region (121) ranges from 1.1 to 2.5.

[0076] In some embodiments, the first and the second sub-regions (121, 123) have a depth, in said semiconductor body from the surface (102a) ranging from 10 nm to 0.1 μm .

[0077] In some embodiments, forming said doped region (120) includes the steps of: carrying out an unmasked implant at the entire first surface (102a), thus forming a uniformly doped region having the second doping density; arranging an implant mask (137) on the first surface (102a), said implant mask (137) exposing superficial regions of the semiconductor body (102) at which it is desired to form the first sub-regions (121); carrying out a masked implant, using said implant mask (137), to form selectively doped regions having the first doping concentration.

[0078] In some embodiments, the first doping density has a value ranging from 5 to 20 times a respective doping density value of the body region (105) and the second doping density has a respective value ranging from 2 to 10 times the doping density value of the body region (105).

[0079] In some embodiments, the first sub-regions (121) are contiguous to, and electrically connected to, respective second sub-regions (123).

[0080] In some embodiments, the second sub-regions (123) occupy a volume of the doped region (120) ranging from 50% to 80%.

[0081] The various embodiments described above can be combined to provide further embodiments. These and other changes can be made to the embodiments in light of the above-detailed description. In general, in the following claims, the terms used should not be construed to limit the claims to the specific embodiments disclosed in the specification and the claims, but should be construed to include all possible embodiments along with the full scope of equivalents to which such claims are entitled. Accordingly, the claims are not limited by the disclosure.

Claims

1. An electronic device, comprising: a semiconductor body of silicon carbide (SiC) having a first and a second surface opposite to each other; a body region, having a first conductivity, extending in the semiconductor body at the first surface; a source region, having a second conductivity opposite to the first conductivity, extending in the body region at the first surface; a drain region, having the second conductivity, at the second surface; a doped region, having the second conductivity, extending along the first surface of the semiconductor body, and the doped region including one or more first sub-regions having a first doping density and one or more second sub-regions having a second doping density lower than the first doping density; a first gate structure overlaps the doped region, the source region, and the body region; and an insulating portion on the first gate structure and covering the first gate structure, the insulating portion fully overlapping the gate structure and the source region.
2. The electronic device of claim 1, wherein the doped region contacts the body region.
3. The electronic device of claim 1, further comprising a channel region extends from the doped region to the drain region.
4. The electronic device of claim 3, wherein the first gate structure overlaps the channel region.
5. The electronic device of claim 4, wherein the first gate structure includes: a gate dielectric on the doped region and overlapping the body region, the source region, and the channel region; a metal gate layer on the gate dielectric, the metal gate layer separated from the doped region by the gate dielectric, the metal gate layer overlapping the body region, the source region, the doped region, and the channel region.

6. The electronic device of claim 5, further comprising a metal layer on the insulating portion and on the doped region, the metal layer overlapping the insulating portion, the doped region, the first gate structure, and the channel region, and wherein the insulating portion electrically insulates the first gate structure from the metal layer.

7. The electronic device of claim 6, comprising a second gate structure spaced from the first gate structure and overlapping the doped region.

8. An electronic device, comprising: a semiconductor body of silicon carbide (SiC), having a first doping density of a first conductivity type, having a first and a second surface that are opposite to each other; a body region, having a second conductivity opposite to the first conductivity, extending in the semiconductor body at the first surface; a source region, having the first conductivity, extending in the body region, the source region including a first end and a second end opposite to the first end, the first end and the second end are within the body region; a drain region, having the first conductivity, extending at the second surface of the semiconductor body; a doped region, having the first conductivity, extending along the first surface of the semiconductor body, and having a second doping density, higher than the first doping density; a channel region aligned with and overlapped by the doped region, the channel region in closer proximity to the first end of the source region than the second end of the source region; a gate structure overlapping the doped region, overlapping the channel region, overlapping the source region, and overlapping the body region; and an insulating portion covering and fully overlapping the gate structure and the source region, the insulating portion extends past the second end of the source region.

9. The device of claim 8, wherein the doped region contacts the body region.

10. The device of claim 8, wherein the doped region includes: one or more first sub-regions with the second doping density; and one or more second sub-regions with a third doping density lower than the second doping density.

11. The device of claim 8, wherein the gate structure includes: a gate dielectric on the doped region and overlapping the body region, the source region, and the channel region; and a metal gate layer on the gate dielectric, the metal gate layer separated from the doped region by the gate dielectric, the metal gate layer overlapping the body region, the source region, the doped region, and the channel region.

12. The device of claim 8, further comprising an electrical contact interface in the body region.

13. The device of claim 12, wherein the end of the insulating portion overlaps and is aligned with the electrical contact interface.

14. The device of claim 12, wherein the electrical contact interface is in contact with the doped region.

15. The device of claim 8, further comprising a metal layer on the insulating portion and on the doped region, the metal layer overlapping the insulating portion, the doped region, the gate structure, and the channel region, and wherein the insulating portion electrically insulates the gate structure from the metal layer.

16. The device of claim 8, wherein the insulating terminates at an end spaced outward from the second end of the source region.

17. A device, comprising: a semiconductor body of silicon carbide (SiC) having a first and a second surface opposite to each other; a first body region, having a first conductivity, extending in the semiconductor body at the first surface; a second body region, having the first conductivity, extending in the semiconductor body at the first surface; a source region, having a second conductivity opposite to the first conductivity, extending in the body region at the first surface; a drain region, having the second conductivity, at the second surface; a doped region, having the second conductivity, extending along the first surface of the semiconductor body, and the doped region including one or more first sub-regions having a first doping density and one or more second sub-regions having a second doping density lower than the first doping density, and at least one of the one or more first-sub-regions extends from the first body region to the second body

region; a channel region aligned with and overlapped by the doped region; a gate structure overlaps the doped region, the source region, the body region; and an insulating portion on the gate structure and covering the gate structure, the insulating portion fully overlapping the gate structure and the source region, and wherein at least one respective first sub-region of the one or more first sub-regions is between the insulating portion and the channel region.

18. The device of claim 17, wherein the gate structure includes: a gate dielectric on the doped region and overlapping the body region, the source region, and the channel region; a metal gate layer on the gate dielectric, the metal gate layer separated from the doped region by the gate dielectric, the metal gate layer overlapping the body region, the source region, the doped region, and the channel region.

19. The device of claim 17, further comprising a metal layer on the insulating portion and on the doped region, the metal layer overlapping the insulating portion, the doped region, the first gate structure, and the channel region, and wherein the insulating portion electrically insulates the first gate structure from the metal layer.

20. The device of claim 17, wherein the doped region contacts the first body region and the second body region.

21. The device of claim 17, further comprising an electrical contact interface in the body region.
