



US 20250279260A1

(19) **United States**

(12) **Patent Application Publication**
Shaw et al.

(10) **Pub. No.: US 2025/0279260 A1**

(43) **Pub. Date: Sep. 4, 2025**

(54) **PLASMA PROCESSING BIAS CONTROL
BASED ON IMPEDANCE**

(71) Applicant: **Advanced Energy Industries, Inc.**,
Denver, CO (US)

(72) Inventors: **Denis Shaw**, Fort Collins, CO (US);
Daniel Carter, Fort Collins, CO (US)

(21) Appl. No.: **18/591,261**

(22) Filed: **Feb. 29, 2024**

Publication Classification


(51) **Int. Cl.**
H01J 37/32 (2006.01)


(52) **U.S. Cl.**
CPC **H01J 37/32183** (2013.01); **H01J**
2237/24564 (2013.01); **H01J 2237/327**
(2013.01)

(57) **ABSTRACT**

Bias supply power control based on an impedance indicator. In one embodiment, a bias supply includes a first node and circuitry configured to apply a waveform to the first node, wherein the waveform includes a peak voltage and a ramp voltage. The bias supply also includes a controller configured to receive an impedance indicator of a load coupled to the first node, and to direct the circuitry to control the ramp voltage based on the impedance indicator.

400








FIG. 2A




FIG. 2B






FIG. 3

**FIG. 4**

**FIG. 5**




FIG. 6




FIG. 7




FIG. 8




FIG. 9




FIG. 10




FIG. 11

PLASMA PROCESSING BIAS CONTROL BASED ON IMPEDANCE

BACKGROUND

Field of the Disclosure

[0001] The present disclosure relates generally to plasma processing. More specifically, but without limitation, the present disclosure relates to controlling a bias voltage during plasma processing.

Background

[0002] Plasma processing is a versatile technology used in semiconductor manufacturing, enabling precise control over material removal, deposition, and surface modification to fabricate advanced electronic devices. For some types of plasma processing, such as plasma etching, two types of power are applied to a plasma chamber: source power and bias power. Source power generates and sustains the plasma within the chamber. Bias power regulates the energy of plasma ions bombarding the substrate (e.g., silicon wafer) to control material removal.

[0003] In certain applications, bias power helps minimize charging effects on the substrate. Charging can occur when ions accumulate on the surface of the substrate, altering the potential difference between the substrate and plasma, and influencing ion trajectories in unpredictable ways. By neutralizing this charge, bias power contributes to maintaining accurate and consistent etching profiles on the substrate. However, current techniques for controlling bias power rely on assumptions or predictions of the capacitances present in the plasma chamber which can be inaccurate.

SUMMARY

[0004] An aspect may be characterized as a bias supply including a first node and circuitry configured to apply a waveform to the first node, wherein the waveform includes a peak voltage and a ramp voltage. The bias supply also includes a controller configured to receive an impedance indicator of a load coupled to the first node, and to direct the circuitry to control the ramp voltage based on the impedance indicator.

[0005] Another aspect may be characterized as a method for controlling bias power. The method includes applying a waveform to a first node, wherein the waveform includes a peak voltage and a ramp voltage. The method also includes receiving an impedance indicator of a load coupled to the first node, and controlling the ramp voltage based on the impedance indicator.

[0006] Yet another aspect may be characterized as a non-transient computer-readable storage medium having instructions embodied thereon, the instructions are executable by a processor and/or capable of programming a field programmable gate array, the instructions including instructions for: applying a waveform to a first node, wherein the waveform includes a peak voltage and a ramp voltage; receiving an impedance indicator of a load coupled to the first node; and controlling the ramp voltage based on the impedance indicator.

BRIEF DESCRIPTION OF THE DRAWINGS

[0007] FIG. 1 is a block diagram of a plasma processing system in accordance with an embodiment of this disclosure.

[0008] FIG. 2A illustrates an example waveform that can be generated by a bias supply of the present disclosure.

[0009] FIG. 2B illustrates an example substrate voltage resulting from the waveform of FIG. 2A.

[0010] FIG. 3 illustrates a first graph of an example output voltage that can be generated by bias supply, a second graph of an example corresponding substrate voltage and a third graph of an example corresponding impedance indicator.

[0011] FIG. 4 is a flowchart illustrating a method of biasing a substrate for plasma processing in an example embodiment.

[0012] FIG. 5 is a block diagram of an example bias supply that may be used to implement a bias supply of the disclosure.

[0013] FIG. 6 illustrates an example topology that may be used to implement a bias supply of the disclosure.

[0014] FIG. 7 illustrates an example timing chart for operating the bias supply of FIG. 6.

[0015] FIG. 8 is a block diagram of yet another example bias supply that may be used to implement bias supply of the disclosure.

[0016] FIG. 9 illustrates an example timing chart for operating the bias supply of FIG. 8.

[0017] FIG. 10 is a block diagram of another example bias supply that may be used to implement bias supply of the disclosure.

[0018] FIG. 11 is a block diagram depicting physical components of a controller that may be utilized to realize control aspects disclosed herein.

DETAILED DESCRIPTION

[0019] The following modes, features or aspects, given by way of example only, are described in order to provide a more precise understanding of the subject matter of several embodiments.

[0020] FIG. 1 is a block diagram of a plasma processing system 100 in accordance with an embodiment of this disclosure. Plasma processing system 100 is an example system (e.g., deposition or etch system) in which a bias supply 150 may be utilized. In this example, plasma processing system 100 includes a generator 102, match network 104, and plasma chamber 110. Generator 102 provides power (e.g., RF power) via match network 104 to plasma chamber 110 to ignite and sustain a plasma 114. Plasma chamber 110 includes one or more electrodes 112 configured to generate plasma 114 from the source power of generator 102. Within plasma chamber 110, a substrate 116 (e.g., silicon wafer) is supported or held by a chuck 118 (e.g., ions and electrons of plasma 114 react with and modify the surface of substrate 116 through processes such as etching or deposition).

[0021] Bias supply 150 provides a controlled electrical bias to substrate 116 for fine-tuning plasma processing conditions. In particular, bias supply 150 may be configured to apply an output voltage V_{out} to chuck 118 (e.g., an electrostatic chuck or electrode) configured to create an electric field between plasma 114 and substrate 116. The electrical potential difference between plasma 114 and substrate 116 is referred to as substrate voltage V_{sub} , and the magnitude of this voltage determines the kinetic energy of ions of plasma 114 striking the surface of substrate 116. Substrate voltage V_{sub} also affects the ion energy distribution (IED) at the surface of substrate 116 which is a factor in the uniformity and quality of plasma processing results.

[0022] Conventional plasma processing techniques bias with an output voltage comprising a direct-current (DC) pulsed waveform or sinusoidal waveform. However, DC pulsed waveforms result in an undesirable and difficult-to-control spread of ion energies, and sinusoidal waveforms result in an undesirable IED having multiple concentrations of ion energies. For improved control of IED, bias supply 150 may provide an asymmetric waveform as described in greater detail below.

[0023] FIG. 2A illustrates an example waveform 200 that can be generated by bias supply 150 of the present disclosure. FIG. 2B illustrates an example substrate voltage 250 resulting from the waveform 200 of FIG. 2A. As shown in FIG. 2A, waveform 200 may comprise an asymmetric, periodic voltage (e.g., V_{out}) comprising a first section that begins with a first negative voltage V_1 , followed by an increase to a peak voltage 201, followed by a decrease, or step voltage 202, to a second negative voltage V_2 . It also comprises a second section that begins with the second negative voltage V_2 and includes a ramp voltage 203 between the second negative voltage V_2 and a third negative voltage V_3 .

[0024] The increase, or step, from first negative voltage V_1 to peak voltage 201 may comprise a voltage reversal which resets or neutralizes the charge on the surface of substrate 116. This drives substrate voltage V_{sub} to a corresponding peak voltage 251 that is slightly positive to reset the charge on the surface of substrate 116. Assuming, for example, a 400 kHz frequency of waveform 200, voltage reversal may repeat approximately every 2.5 μ sec. Subsequent to the voltage reversal (e.g., approximately 500 nsec after the voltage reversal), step voltage 202 drops to second negative voltage V_2 and the magnitude of this voltage drop defines an initial negative substrate voltage 252. Step voltage 202 may comprise a parameter used as a setpoint to produce ions at a desired energy level.

[0025] Ramp voltage 203 decreases over time between second negative voltage V_2 and third negative voltage V_3 . Ramp voltage 203 may comprise a slope, sometimes referred to as dV/dt , configured to counteract an accumulation of charge on substrate 116 by ions from plasma 114 until the next reversal/reset occurs. For instance, when the slope of ramp voltage 203 is appropriately set, it produces a corresponding voltage section 253 of substrate voltage V_{sub} that is constant, or approximately constant, and maintains the desired ion energy level as defined by the initial negative substrate voltage 252. By contrast, if the change in bias voltage over time is too steep or not steep enough (e.g., as indicated by dashed line 204) an over-compensated condition or under-compensated condition (e.g., as indicated by dashed line 254) occurs in the substrate voltage V_{sub} , which can result in undesirable IED and poor processing outcomes. However, it will be appreciated that, in some embodiments, it may be desirable to achieve a broader spread of ion energies and thus ramp voltage 203 may be deliberately controlled to effectuate an over-compensated condition or under-compensated condition in applications for which this is desirable.

[0026] Referring again to FIG. 1, bias supply 150 is configured to apply a ramp voltage (e.g., ramp voltage 203) to neutralize the effects of accumulating charge on the surface of substrate 116. In conventional plasma biasing techniques, determination of the slope of ramp voltage 203 involves measurement or prediction of capacitances present

in plasma chamber 110. For instance, if chuck capacitance C_{chuck} (e.g., a series capacitance measured from the bias electrode feed to the surface of the bias electrode) is known, this information may be used to adjust the ion current compensation created by the ramp voltage. However, a downside to this approach is that chuck capacitance C_{chuck} may be unknown or uncertain due to effects of operating frequency, mechanical degradation, or chamber-to-chamber mismatch.

[0027] To address these issues, plasma processing system 100 is enhanced with bias supply 150 configured to dynamically control a ramp voltage (e.g., ramp voltage 203) based on an impedance indicator 122. Plasma processing system 100 also includes one or more sensors 120 configured to monitor or measure one or more parameters indicative of an impedance value or change of plasma 114, and to provide the parameter(s) in the form of an impedance indicator 122 to bias supply 150. Advantageously, bias supply 150 is able to dynamically and accurately control ramp voltage 203, and thus a desired substrate voltage V_{sub} , without relying on knowledge of chamber capacitances. As described in greater detail below, this control technique leverages the relationship between plasma impedance and substrate voltage V_{sub} by using real-time impedance value indicators as a feedback mechanism.

[0028] FIG. 3 illustrates a first graph 310 of an example output voltage V_{out} that can be generated by bias supply 150, a second graph 320 of an example corresponding substrate voltage V_{sub} , and a third graph 330 of an example corresponding impedance indicator. Assume, for this example, the impedance indicator is a reflection coefficient, sometimes denoted as gamma, that represents the ratio of voltage reflected back toward generator 102. The reflection coefficient is an indicator of plasma impedance because it relates to the mismatch between the plasma impedance and source impedance.

[0029] As shown in first graph 310, bias supply 150 may output a first portion 311 of a periodic waveform that has an abrupt positive/negative transition. This drives a corresponding first portion 321 of substrate voltage V_{sub} shown in second graph 320. When substrate voltage V_{sub} changes rapidly, the characteristics of the plasma sheath (i.e., a boundary layer that forms between plasma 114 and substrate 116), such as its thickness and the electric field within it, also change rapidly. Since plasma impedance is a measure of how easily these particles can move (i.e., how easily current can flow), a change in the sheath results in a change in the plasma impedance. Accordingly, during application of first portion 311 of waveform, plasma impedance changes as indicated by fluctuation 331 in reflection coefficient of third graph 310.

[0030] On the other hand, during application of a ramp voltage 313 (e.g., a second portion of the waveform that is between positive/negative transitions), plasma impedance is generally stable. That is, if the slope of ramp voltage 313 is appropriately set to counteract ion charge accumulation, it results in a corresponding second portion 323 of substrate voltage V_{sub} that is constant, as shown in second graph 320, indicating substrate 116 is appropriately compensated. Moreover, when substrate voltage V_{sub} is constant during ramp voltage 313, plasma impedance also remains constant during this period, as shown by the corresponding second portion 333 of the reflection coefficient that is flat between fluctuations 331.

[0031] If the ramp voltage slope is not appropriately set, as indicated by dashed line 314, it results in a corresponding second portion 324 of substrate voltage V_{sub} that is non-constant, indicating substrate 116 is over-compensated or under-compensated. For instance, if the slope is too steep it may result in V_{sub} with a negative slope and ion current over-compensating substrate 116, and if the slope is too gradual it may result in V_{sub} with a positive slope and ion current under-compensating substrate 116. Moreover, if V_{sub} has a slope, or is non-constant, during the ramp voltage (e.g., as shown by second portion 324 of second graph 320), it may cause plasma impedance to have a corresponding second portion 334 that is non-constant during this period (e.g., as shown by dashed line of third graph 330). Put another way, during a time period that the ramp voltage is being applied, a detected slope in plasma impedance may indicate an undesirable substrate voltage V_{sub} condition.

[0032] Accordingly, in this example, bias supply 150 may use the reflection coefficient to control the slope of the ramp voltage and correct the substrate voltage V_{sub} to a desired value or profile. Sensor 120 may measure the reflection coefficient during a ramp voltage portion of a non-sinusoidal bias. If the reflection coefficient is detected or determined to have a non-zero slope during this period, bias supply 150 increases or decreases the slope of the ramp voltage such that the reflection coefficient, and thus substrate voltage V_{sub} , returns to constant. In other words, bias supply 150 may adjust the slope of ramp voltage until it detects or determines its impedance indicator feedback is flat, indicating a desired current compensation of substrate 116. By biasing the electrical potential of substrate 116 with this control technique, the energy of ions striking the surface of substrate 116 is precisely controlled without reliance on potentially inaccurate system parameters such as chuck capacitance C_{chuck} .

[0033] In one embodiment, bias supply 150 is configured to process/analyze the sensor data to extract a portion of impedance indicator(s) 122 to use for feedback control. That is, bias supply 150 may determine impedance indicator values measured during the ramp voltage portion of the waveform and use those values for feedback control, and ignore values measured during other portions of the waveform. In continuing with the example of FIG. 3, for instance, bias supply 150 may use a frequency threshold to filter out fluctuations 331 in the reflection coefficient. This extracts impedance indicator values, or a portion of an impedance indicator waveform (e.g., second portion 333/334 between times t1 and t2 in third graph 330) that is a non-fluctuating portion corresponding in time with the ramp voltage. Bias supply 150 may use the non-fluctuating portion or stable portion of the impedance indicator waveform as feedback for controlling ramp voltage.

[0034] In some embodiments, it may be desirable to effectuate an over-compensated condition or under-compensated condition of substrate 116, and bias supply 150 may control the ramp voltage to induce the impedance indicator 122 to have a slope, or be non-constant, such that substrate voltage V_{sub} has the desired slope or non-constant value. That is, bias supply 150 may adjust the slope of the ramp voltage until it detects or determines its impedance indicator feedback reaches the desired profile, and then maintain the ramp voltage that induces the desired profile. In some embodiments, bias supply 150 controls a duration of the ramp voltage based on impedance indicator 122.

[0035] Although reflection coefficient discussed with respect to FIG. 3 is one example of impedance indicator 122, it will be appreciated that one or more alternative parameters may be used. One example of impedance indicator 122 is the measured magnitude of plasma impedance. Another example is Voltage Standing Wave Ratio (VSWR), which is ratio of the maximum voltage to the minimum voltage in the standing wave pattern along a transmission line 103 (e.g., electrical coupling which delivers RF power generated by generator 102 to plasma chamber 110) and is indicative of plasma impedance since it is a measure how effectively RF power is transmitted from the power source into plasma 114. Another example of impedance indicator 122 is peak-to-peak voltage of the RF waveform applied to plasma 114. Changes in the peak-to-peak voltage can indicate fluctuations in the plasma impedance. Similarly, changes in voltage, current, power (e.g., forward, reflected, or delivered power), and phase in the RF waveform can also indicate fluctuations in the plasma impedance and thus also represent potential candidates for impedance indicator 122.

[0036] Additionally, one or more sensors 120 used to detect impedance indicator(s) 122 can vary in type and integration within plasma processing system 100. Sensor 120 may be electrically coupled with transmission line 103 to measure plasma impedance values. Additionally, sensor 120 may be communicatively coupled to bias supply 150 via wired or wireless communication line 105 to provide impedance indicator 122 for feedback control. Sensor 120 may comprise a standalone sensor or be integrated with generator 102 and/or match network 104. For instance, sensor 120 may be arranged at an output of generator 102 and/or match network 104, and measure plasma impedance seen by generator 102 or transmission line 103. Sensor 120 may comprise, for example, a V-I sensor, directional coupler, phase and gain sensor, voltage sensor, or current sensor.

[0037] In some embodiments, bias supply 150 converts and/or calculates plasma impedance measurements from sensor data. For example, bias supply 150 may include analog-to-digital conversion components to convert analog signals from sensor 120 to digital representations of the measured characteristic of plasma impedance. Alternatively, sensor 120 may include analog-to-digital conversion components, and bias supply 150 may receive the digital representation and/or converted version of the measured characteristic of plasma impedance. Additionally, bias supply 150 may receive and store thresholds or instructions for processing/analyzing one or more types of impedance indicators. For instance, a frequency threshold is described above with respect to a reflection coefficient example, and it will be appreciated that corresponding thresholds of other parameter and indicator types may be implemented.

[0038] It will further be appreciated that numerous variations of plasma processing system 100 are possible to suit a wide range of applications and desired processing outcomes. For example, plasma processing system 100 may incorporate multiple generators 102 and/or multiple bias supplies 150. One or more generators 102 and one or more bias supplies 150 may be coupled to the same electrode (e.g., electrode 112 or chuck 118). One or more filters may serve to isolate generator 102 and bias supply 150. Moreover, electrode 112 may be implemented with an inductively coupled plasma (ICP) source, a dual capacitively-coupled plasma source (CCP) having a secondary top electrode biased at another RF frequency, a helicon plasma source, a

microwave plasma source, a magnetron, or some other independently operated source of plasma energy. In any case, the plasma load is characterized by its impedance, which is a complex value that includes both resistive and reactive components, and this impedance can change dynamically as processing conditions change.

[0039] FIG. 4 is a flowchart illustrating a method 400 of biasing a substrate for plasma processing in an example embodiment. The steps of the method are described with reference to the plasma processing system 100 of FIG. 1, but those skilled in the art will appreciate that the method may be performed in other systems. The steps of the flowcharts described herein are not all inclusive, may include other steps not shown, and may be performed in an alternative order.

[0040] In step 402, bias supply 150 applies a waveform to a first node, wherein the waveform includes a peak voltage and a ramp voltage. In step 404, bias supply 150 receives an impedance indicator of a load coupled to the first node. In step 406, bias supply 150 controls the ramp voltage based on the impedance indicator.

[0041] FIG. 5 is a block diagram of an example bias supply 500 that may be used to implement bias supply of the disclosure. Bias supply 500 generally functions to apply a periodic voltage function (e.g., output voltage V_{out}) to an output node 556, sometimes referred to as a first node. Bias supply 500 includes, or couples with, a controller 552 configured to communicatively couple with a sensor (e.g., sensor 120) and receive impedance indicator 122. Bias supply 500 also includes circuitry 554 coupled with controller 552 and configured to generate the periodic voltage function based on input from controller 552. In one embodiment, controller 552 determines or calculates an adjustment of slope of the ramp voltage based on impedance indicator 122, and directs circuitry 554 to effectuate or induce the adjustment in the ramp voltage.

[0042] FIG. 6 is a block diagram of another example bias supply 600 that may be used to implement bias supply of the disclosure. Bias supply 600 includes an output 610 (also referred to as an output node or first node), a switch 620, and a voltage source 630. In addition, a first inductor 640 is coupled between switch 620 and output 610, and a second inductor 650 is coupled between voltage source 630 and output 610. Also shown is a controller 660 that is configured to open and close switch 620 to produce a voltage (e.g., V_{out}). Switch 620 may include a body diode to allow for reverse current flow even when switch 620 is not controlled to be in an on state. Switch 620 may be realized, for example, by silicon carbide metal-oxide semiconductor field-effect transistors (SiC MOSFETs), though other types of switches may be used. Switch 620 may be driven by a drive signal 611 from controller 660, and drive signal 611 may be electrical or optical.

[0043] FIG. 7 illustrates an example timing chart for operating bias supply 600 of FIG. 6. The timing chart depicts electrical aspects of bias supply 600 and a plasma processing chamber. Controller 660 may be configured to cause an application of a periodic voltage (e.g., V_{out}) between output 610 and a ground connection 670 (or return node) by repeatedly closing switch 620 for a time just long enough for current i_{L1} through first inductor 640, and hence switch 620, to complete a full cycle from zero to a peak value, back to zero, to a peak value in an opposite direction and back to zero. Current delivered to the load through output 610 may

be returned to bias supply 600 through ground connection 670 that is common with the load. Ion current may be properly compensated when current i_{L2} through the second inductor, L2, equals the ion current. Controller 660 may also be configured to adjust a voltage of voltage source 630 and a time between the repeated switch closures to produce a periodic voltage V_{out} that achieves a desired substrate voltage V_{sub} .

[0044] FIG. 8 is a block diagram of yet another example bias supply 800 that may be used to implement bias supply of the disclosure. Bias supply 800 utilizes three voltages V1, V2, and V3. As shown, an output 810 may be capacitively coupled through chuck capacitance C_{chuck} , and thus it may be unnecessary to control a DC level of V_{out} and the three voltages can be reduced to two by choosing one of V1, V2 or V3 to be ground (0V). A separate chucking supply may be used so it is not necessary to control the DC level of V_{out} . If a separate chucking supply is not used, all three voltages can be controlled to control the DC level of V_{out} . Although not shown for clarity, the two switches S1 and S2 may be controlled by a switch controller via electrical or optical connection to enable the switch controller to open and close switches S1 and S2. The depicted switches S1 and S2 may be realized by single pole, single throw switches, and as a non-limiting example, switches S1 and S2 may be realized by SiC MOSFETs.

[0045] In this implementation, the voltages V1, V2, and V3 may be DC-sourced voltages. As shown, first switch S1 is disposed to switchably connect a first voltage V1 to output 810 through an inductive element and second switch S2 is disposed to switchably couple the second voltage, V2, to output 810 through an inductive element. In this implementation the two switches connect to a common node 870, and a common inductive element, L1, is disposed between common node 870 and output 810. Other arrangements of the inductive elements are possible. For example, there may be two separate inductive elements with one inductive element connecting S1 to output 810 and another connecting S2 to output 810. In another example one inductive element may connect S1 to S2 and another inductive element may connect either S1 or S2 to output 810.

[0046] FIG. 9 illustrates an example timing chart for operating bias supply 800 of FIG. 8. This timing chart depicts: 1) a cycle of the asymmetric periodic voltage waveform (e.g., V_{out}) of bias supply 800 applied to output 810; 2) a corresponding substrate voltage; and 3) corresponding switch positions of switches S1 and S2. As shown, the periodic voltage waveform that is output by bias supply 800 is asymmetric, so that a first half-cycle of the voltage waveform does not have a corresponding symmetrical component during a last half-cycle of the voltage waveform. In operation, first switch S1 is closed momentarily to increase, along a first portion 960 of the voltage waveform (between voltage V_0 and V_a) a level of the voltage at output 810 to a first voltage level, V_a . The level V_a is maintained along a second portion 962 of the waveform. Second switch S2 is then closed momentarily to decrease, along a third portion 964 of the waveform, the level of the voltage waveform at output 810 to a second voltage level, V_b . Note that S1 and S2 are open except for short periods of time. As shown, the negative voltage swing along the third portion 964 affects the substrate voltage; thus, a magnitude of $V_a - V_b$ may be controlled to affect the substrate voltage.

[0047] In this embodiment, while the first and second switches S1, S2 are open, the third voltage, V3, is applied to output 810 through a second inductive element L2 to further decrease a level of the voltage at the output node along a fourth portion 966 of the voltage waveform. The negative voltage ramp along fourth portion 966 may be established to maintain the substrate voltage by compensating for ions that impact the substrate.

[0048] Thus, S1 momentarily connects and then disconnects the first voltage, V1, to output 810 through first inductive element L1, and after a period of time, S2 connects and then disconnects the second voltage (e.g., ground) to output 810 through first inductive element L1. Third voltage V3, is coupled to output 810 through second inductive element L2. In this implementation, first voltage V1 may be higher than third voltage V3, and the momentary connection and disconnection of first voltage V1 to output 810 causes the voltage at output 810 to increase along first portion 960 of the voltage waveform to first voltage level Va, and first voltage level Va is sustained along second portion 962 of the waveform. First voltage level Va may be above first voltage V1, and second voltage V2 (e.g., ground) may be less than first voltage level Va. The momentary connecting and then disconnecting of second voltage V2 causes the voltage at output 810 to decrease at third portion 964 to second voltage level Vb that is below second voltage V2 (e.g., ground).

[0049] FIG. 10 is a block diagram of another example bias supply 1000 that may be used to implement bias supply of the disclosure. Bias supply includes a waveform generator 1002 and linear power amplifier 1004. Waveform generator 1002 may be a programmable arbitrary waveform generator configured to produce a low voltage version of the asymmetric periodic voltage waveform in response to a signal from a controller and/or sensor. For instance, a controller (e.g., controller 552) may provide a control signal 1001 to waveform generator 1002 to control the ramp voltage based upon the impedance indicator. For example, controller 552 may control waveform generator 1002 to adjust the slope of the ramp voltage to induce the impedance indicator to be constant, or approximately constant, during the application of the ramp voltage. Linear amplifier 1004 may comprise a class B amplifier or similar that amplifies the low voltage asymmetric periodic voltage waveform from the waveform generator to produce the asymmetric periodic voltage waveform (e.g., V_{out}) at output 1010.

[0050] The various illustrative logical blocks, modules, and circuits described in connection with the embodiments disclosed herein may be implemented or performed with a general-purpose processor, a digital signal processor (DSP), an application specific integrated circuit (ASIC), a field programmable gate array (FPGA) or other programmable logic device, discrete gate or transistor logic, discrete hardware components, or any combination thereof designed to perform the functions described herein. A general-purpose processor may be a microprocessor, but in the alternative, the processor may be any conventional processor, controller, microcontroller, or state machine. A processor may also be implemented as a combination of computing devices, e.g., a combination of a DSP and a microprocessor, a plurality of microprocessors, one or more microprocessors in conjunction with a DSP core, or any other such configuration.

[0051] The steps of a method or algorithm described in connection with the embodiments disclosed herein may be embodied directly in hardware, in a software module

executed by a processor, or in a combination of the two. A software module may reside in RAM memory, flash memory, ROM memory, EPROM memory, EEPROM memory, registers, hard disk, a removable disk, a CD-ROM, or any other form of storage medium known in the art. An exemplary storage medium is coupled to the processor such that the processor can read information from, and write information to, the storage medium. In the alternative, the storage medium may be integral to the processor. The processor and the storage medium may reside in an ASIC.

[0052] Many embodiments and methods described herein may be realized using a processor in connection with processor executable instructions and a field programmable gate array (programmed by hardware description language instructions). In some embodiments, the FPGA is used for high-speed processing and control, including switching control, measurement, pulsing, and multi-level operation while a processor is utilized for other lower-speed processing. Referring to FIG. 11 for example, shown is a block diagram depicting physical components of a controller that may be utilized to realize control aspects disclosed herein.

[0053] As shown, in this embodiment a display 1112 and nonvolatile memory 1120 are coupled to a bus 1122 that is also coupled to random access memory ("RAM") 1124, a processing portion (which includes N processing components) 1126, a field programmable gate array (FPGA) 1127, and a transceiver component 1128 that includes N transceivers. Although the components depicted in FIG. 11 represent physical components, FIG. 11 is not intended to be a detailed hardware diagram; thus, many of the components depicted in FIG. 11 may be realized by common constructs or distributed among additional physical components. Moreover, it is contemplated that other existing and yet-to-be developed physical components and architectures may be utilized to implement the functional components described with reference to FIG. 11.

[0054] This display 1112 generally operates to provide a user interface for a user, and in several implementations, the display is realized by a touchscreen display. In general, the nonvolatile memory 1120 is non-transitory memory that functions to store (e.g., persistently store) data and processor-executable code (including executable code that is associated with effectuating the methods described herein). In some embodiments for example, the nonvolatile memory 1120 includes bootloader code, operating system code, file system code, and non-transitory processor-executable code to facilitate the execution of a method or functions described herein for controlling a bias power based on plasma impedance. Alternatively or additionally, nonvolatile memory 1120 may receive and store thresholds or instructions for processing/extracting impedance indicators for feedback control.

[0055] In many implementations, the nonvolatile memory 1120 is realized by flash memory (e.g., NAND or ONENAND memory), but it is contemplated that other memory types may be utilized as well. Although it may be possible to execute the code from the nonvolatile memory 1120, the executable code in the nonvolatile memory is typically loaded into RAM 1124 and executed by one or more of the N processing components in the processing portion 1126. The N processing components in connection with RAM 1124 generally operate to execute the instructions stored in nonvolatile memory 1120 to enable execution of the algorithms and functions disclosed herein. It should be

recognized that several algorithms or functions are disclosed herein, but some of these algorithms or functions are not represented in flowcharts. Processor-executable code to effectuate methods described herein may be persistently stored in nonvolatile memory **1120** and executed by the N processing components in connection with RAM **1124**. As one of ordinary skill in the art will appreciate, the processing portion **1126** may include a video processor, digital signal processor (DSP), micro-controller, graphics processing unit (GPU), or other hardware processing components or combinations of hardware and software processing components (e.g., an FPGA or an FPGA including digital logic processing portions). In addition, or in the alternative, non-transitory FPGA-configuration-instructions may be persistently stored in nonvolatile memory **1120** and accessed (e.g., during boot up) to configure a field programmable gate array (FPGA) to implement the algorithms disclosed herein.

[0056] The input component **1130** may receive impedance related signals (e.g., signals indicative of plasma impedance). Although not required, in some implementations the FPGA **1127** may be used to realize sampling-related components and the FPGA **1127** may sample the impedance related signals and provide digital representations. In some embodiments, the processing portion **1126** (in connection with processor-executable instructions stored in the non-volatile memory **1120**) are used to realize the controllers disclosed herein, and functions of the controller may reside in a bias supply and/or other components of a plasma processing system. But the FPGA **1127** may also be used to implement these functions. In addition, the input component **1130** may receive phase information and/or a synchronization signal between bias supplies and source generator **102** that are indicative of one or more aspects of an environment within a plasma processing chamber and/or synchronized control between a source generator and the bias supply (e.g., single switch, dual switch bias supply). The signals received at the input component **1130** may include, for example, synchronization signals, impedance control signals, or control signals from a user interface (e.g., thresholds or instructions for filtering impedance indicator values for feedback control).

[0057] The output component **1140** generally operates to provide one or more analog or digital signals to effectuate the gate drive signals for opening and closing of the switches. The output component **1140** may also control one or more aspects of the power supplies described herein. The depicted transceiver component **1128** includes N transceiver chains, which may be used for communicating with external devices via wireless or wireline networks. Each of the N transceiver chains may represent a transceiver associated with a particular communication scheme (e.g., WiFi, Ethernet, Profibus, etc.).

[0058] As will be appreciated by one skilled in the art, aspects of the present disclosure may be embodied as a system, method or computer program product. Accordingly, aspects of the present disclosure may take the form of an entirely hardware embodiment, an entirely software embodiment (including firmware, resident software, micro-code, etc.) or an embodiment combining software and hardware aspects that may all generally be referred to herein as a “circuit,” “module” or “system.” Furthermore, aspects of the present disclosure may take the form of a computer program

product embodied in one or more computer readable medium(s) having computer readable program code embodied thereon.

What is claimed is:

1. A bias supply, comprising:

a first node;

circuitry configured to apply a waveform to the first node, wherein the waveform includes a peak voltage and a ramp voltage; and

a controller configured to receive an impedance indicator of a load coupled to the first node, and to direct the circuitry to control the ramp voltage based on the impedance indicator.

2. The bias supply of claim 1, wherein:

the impedance indicator comprises a measured parameter indicative of a plasma impedance presented to a source generator; and

the impedance indicator is measured during application of the ramp voltage.

3. The bias supply of claim 2, wherein:

the controller is configured to direct the circuitry to adjust a slope of the ramp voltage to induce the impedance indicator to be constant, or approximately constant, during the application of the ramp voltage.

4. The bias supply of claim 3, wherein:

the controller is configured to determine a non-fluctuating portion of the impedance indicator measured during the application of the ramp voltage, and to direct the circuitry to control the non-fluctuating portion to be constant, or approximately constant, during the application of the ramp voltage.

5. The bias supply of claim 4, wherein:

the controller is configured to extract the non-fluctuating portion of the impedance indicator based on a threshold.

6. The bias supply of claim 2, wherein:

the controller is configured to receive the impedance indicator from a sensor coupled to the source generator.

7. The bias supply of claim 1, wherein:

the controller is configured to direct the circuitry to control a duration of the ramp voltage based on the impedance indicator.

8. The bias supply of claim 1, wherein:

the impedance indicator comprises one or more of:

- a measured magnitude of plasma impedance;
- a measured reflection coefficient of power reflected;
- a measured voltage standing wave ratio (VSWR);
- a measured forward power;
- a measured delivered power;
- a measured voltage;
- a measured current; and
- a measured phase.

9. The bias supply of claim 1, wherein:

the waveform is an asymmetric periodic voltage waveform, comprising:

- a first section that begins with a first negative voltage, followed by an increase to the peak voltage, followed by a decrease to a second negative voltage; and

- a second section that begins with the second negative voltage and includes the ramp voltage between the second negative voltage and a third negative voltage.

- 10.** A method comprising:
 applying a waveform to a first node, wherein the waveform includes a peak voltage and a ramp voltage;
 receiving an impedance indicator of a load coupled to the first node; and
 controlling the ramp voltage based on the impedance indicator.
- 11.** The method of claim **10**, further comprising:
 measuring the impedance indicator during application of the ramp voltage, wherein the impedance indicator is a measured parameter indicative of a plasma impedance presented to a source generator.
- 12.** The method of claim **11**, further comprising:
 adjusting a slope of the ramp voltage to induce the impedance indicator to be constant, or approximately constant, during the application of the ramp voltage.
- 13.** The method of claim **12**, further comprising:
 extracting a non-fluctuating portion of the impedance indicator corresponding with the application of the ramp voltage; and
 adjusting a slope of the ramp voltage to induce the non-fluctuating portion of the impedance indicator to be constant, or approximately constant, during the application of the ramp voltage.
- 14.** The method of claim **10**, wherein:
 the waveform is an asymmetric periodic voltage waveform, comprising:
 a first section that begins with a first negative voltage, followed by an increase to the peak voltage, followed by a decrease to a second negative voltage; and
 a second section that begins with the second negative voltage and includes the ramp voltage between the second negative voltage and a third negative voltage.
- 15.** A non-transitory computer-readable storage medium having instructions embodied thereon, the instructions are executable by a processor and/or capable of programming a field programmable gate array, the instructions comprising instructions for:
 applying a waveform to a first node, wherein the waveform includes a peak voltage and a ramp voltage;
 receiving an impedance indicator of a load coupled to the first node; and
 controlling the ramp voltage based on the impedance indicator.
- 16.** The non-transitory computer-readable storage medium of claim **15**, wherein:
 the impedance indicator is a measured parameter indicative of a plasma impedance presented to a source generator; and
 the impedance indicator is measured during application of the ramp voltage.
- 17.** The non-transitory computer-readable storage medium of claim **16**, wherein the instructions comprise instructions for:
 adjusting a slope of the ramp voltage to induce the impedance indicator to be constant, or approximately constant, during the application of the ramp voltage.
- 18.** The non-transitory computer-readable storage medium of claim **17**, wherein the instructions comprise instructions for:
 extracting a non-fluctuating portion of the impedance indicator corresponding with the application of the ramp voltage; and
 adjusting a slope of the ramp voltage to induce the non-fluctuating portion of the impedance indicator to be constant, or approximately constant, during the application of the ramp voltage.
- 19.** The non-transitory computer-readable storage medium of claim **16**, wherein:
 the impedance indicator comprises one or more of:
 a measured magnitude of plasma impedance;
 a measured reflection coefficient of power reflected;
 a measured voltage standing wave ratio (VSWR);
 a measured forward power;
 a measured delivered power;
 a measured voltage;
 a measured current; and
 a measured phase.
- 20.** The non-transitory computer-readable storage medium of claim **15**, wherein:
 the waveform is an asymmetric periodic voltage waveform, comprising:
 a first section that begins with a first negative voltage, followed by an increase to the peak voltage, followed by a decrease to a second negative voltage; and
 a second section that begins with the second negative voltage and includes the ramp voltage between the second negative voltage and a third negative voltage.

* * * * *