

US Patent & Trademark Office

Patent Public Search | Text View

United States Patent	12417727
Kind Code	B2
Date of Patent	September 16, 2025
Inventor(s)	Charisoulis; Thomas et al.

Super pixel architecture for high dynamic range

Abstract

A display system of a display includes a first light emitting diode, a second light emitting diode, a current source, and at least one transistor. The first and the second light emitting diodes emit light. The current source provides a constant current to the first light emitting diode and the second light emitting diode. Moreover, the at least one transistor removes the current or shunts the current towards the first light emitting diode, the second light emitting diode, or both. Removing the current or shunting the current towards the first light emitting diode, the second light emitting diode, or both, may blend outputs of the first light emitting diode and the second light emitting diode.

Inventors: Charisoulis; Thomas (San Carlos, CA), Choudhary; Saif (San Jose, CA), Li; Xia (San Jose, CA), Nauta; Tore (Santa Cruz, CA)

Applicant: Apple Inc. (Cupertino, CA)

Family ID: 1000008821417

Assignee: Apple Inc. (Cupertino, CA)

Appl. No.: 17/853261

Filed: June 29, 2022

Prior Publication Data

Document Identifier	Publication Date
US 20230091644 A1	Mar. 23, 2023

Related U.S. Application Data

us-provisional-application US 63247009 20210922

Publication Classification

Int. Cl.: G09G3/3233 (20160101); G09G3/20 (20060101)

U.S. Cl.:

CPC G09G3/2074 (20130101); G09G3/3233 (20130101); G09G2300/0439 (20130101); G09G2300/0842 (20130101); G09G2320/0233 (20130101)

Field of Classification Search

CPC: G09G (3/2074); G09G (3/3233); G09G (2300/0439); G09G (2300/0842); G09G (2320/0233); G09G (2300/0443); G09G (2300/0814); G09G (3/32)

References Cited

U.S. PATENT DOCUMENTS

Patent No.	Issued Date	Patentee Name	U.S. Cl.	CPC
2003/0030601	12/2002	Komiya	345/76	G09G 3/2074
2005/0104875	12/2004	Kwak	345/204	G09G 3/3233
2005/0200573	12/2004	Kwak	345/76	G09G 3/3233
2006/0061525	12/2005	Kim	345/76	H10K 59/131
2006/0114193	12/2005	Kwak	345/76	G09G 3/3233
2012/0133682	12/2011	Kawano	345/690	G09G 3/3233
2015/0145906	12/2014	Uetake	345/694	G09G 3/207
2016/0210892	12/2015	Ohara	N/A	G09G 3/2022
2016/0307510	12/2015	Duan	N/A	G09G 3/3258
2017/0039934	12/2016	Ma	N/A	G09G 3/3233
2018/0053460	12/2017	Watsuda	N/A	G09G 3/32
2019/0355301	12/2018	Lee	N/A	G09G 3/3275
2019/0362667	12/2018	Ma	N/A	G06V 40/1318
2020/0020274	12/2019	Yue	N/A	G09G 3/32
2020/0135092	12/2019	Ahmed	N/A	H01L 27/1214
2021/0335216	12/2020	Nie	N/A	G09G 3/3233
2022/0293052	12/2021	Lee	N/A	H01L 27/156
2023/0274696	12/2022	Liu	345/212	H01L 27/156

OTHER PUBLICATIONS

Kong, Duk-Jo et al., "Color tunable monolithic InGaN/GaN LED having a multi-junction structure," Optics Express, vol. 24, No. 6, Mar. 17, 2016, pp. 1-8. cited by applicant

Primary Examiner: Piziali; Jeff

Attorney, Agent or Firm: Fletcher Yoder, P.C.

Background/Summary

CROSS-REFERENCE TO RELATED APPLICATIONS (1) This application claims priority to U.S. Provisional Application No. 63/247,009, filed Sep. 22, 2021, entitled, "SUPER PIXEL ARCHITECTURE FOR HIGH DYNAMIC RANGE," the disclosure of which is incorporated by reference in its entirety for all purposes.

SUMMARY

(1) A summary of certain embodiments disclosed herein is set forth below. It should be understood that these aspects are presented merely to provide the reader with a brief summary of these certain embodiments and that these aspects are not intended to limit the scope of this disclosure. Indeed, this disclosure may encompass a variety of aspects that may not be set forth below.

(2) The present disclosure relates generally to systems and devices for light emitting diodes to operate at peak efficiency currents while also providing a high dynamic range.

(3) In some embodiments, a super pixel may include multiple subpixels. The super pixel may be a symmetric super pixel that has symmetric subpixels, in which the areas and the dimensions (e.g., length and width) of the subpixels are the same. In some embodiments, the super pixel may be an asymmetric super pixel that has asymmetric subpixels, in which the areas and the dimensions of the subpixels are different. The subpixels may be turned on one by one or turned off one by one for granular control over brightness or dimming of the super pixel.

(4) Moreover, the subpixels may be controlled individually to vary the amount of current going to each of the light emitting diodes for the subpixels. For example, a display system of a display may include one or more transistors (e.g., operating as switches) to remove current or shunt current from a current source providing constant current. In particular, removing and shunting the current may cause light emitting diodes for the subpixels to be partially on or off (e.g., not completely on or off or not completely illuminating or not illuminating). Also, removing the current or shunting the current towards the light emitting diodes for the subpixels may blend outputs of the light emitting diodes to provide a smooth transition of brightness at the pixels, preventing or reducing perceivable artifacts on the display.

(5) Various refinements of the features noted above may exist in relation to various aspects of the present disclosure. Further features may also be incorporated in these various aspects as well. These refinements and additional features may exist individually or in any combination. For instance, various features discussed below in relation to one or more of the illustrated embodiments may be incorporated into any of the above-described aspects of the present disclosure alone or in any combination. The brief summary presented above is intended only to familiarize the reader with certain aspects and contexts of embodiments of the present disclosure without limitation to the claimed subject matter.

Description

BRIEF DESCRIPTION OF THE DRAWINGS

(1) Various aspects of this disclosure may be better understood upon reading the following detailed description and upon reference to the drawings in which:

(2) FIG. 1 is a block diagram of an electronic device, according to an embodiment of the present disclosure;

(3) FIG. 2 is a perspective view of a notebook computer representing an embodiment of the electronic device of FIG. 1;

(4) FIG. 3 is a front view of a handheld device representing another embodiment of the electronic device of FIG. 1;

(5) FIG. 4 is a front view of another handheld device representing another embodiment of the electronic device of FIG. 1;

- (6) FIG. 5 is a front view of a desktop computer representing another embodiment of the electronic device of FIG. 1;
- (7) FIG. 6 is a front view and side view of a wearable electronic device representing another embodiment of the electronic device of FIG. 1;
- (8) FIG. 7 is a block diagram of a μ -LED display that employs micro-drivers (μ Ds) to drive μ -LED sub-pixels with control signals from row drivers (RDs) and data signals from column drivers (CDs), according to embodiments of the present disclosure;
- (9) FIG. 8 is a block diagram of a symmetric super pixel, according to embodiments of the present disclosure;
- (10) FIG. 9 is a block diagram of an asymmetric super pixel, according to embodiments of the present disclosure;
- (11) FIG. 10 is a schematic diagram of a stacked light emitting diode circuit with light emitting diodes of super pixels, according to embodiments of the present disclosure;
- (12) FIG. 11 is a flow diagram of a data flow for driving the symmetric super pixel and the asymmetric super pixel based on a gray level, according to embodiments of the present disclosure;
- (13) FIG. 12 is a flow diagram of a data flow for driving light emitting diodes of the symmetric super pixel and the asymmetric super pixel based on a brightness setting, according to embodiments of the present disclosure;
- (14) FIG. 13 is schematic diagram of the stacked light emitting diode circuit using light emitting diodes in parallel, according to embodiments of the present disclosure; and
- (15) FIG. 14 is schematic diagram of the stacked light emitting diode circuit using light emitting diodes in series, according to embodiments of the present disclosure.

DETAILED DESCRIPTION OF SPECIFIC EMBODIMENTS

- (16) When introducing elements of various embodiments of the present disclosure, the articles “a,” “an,” and “the” are intended to mean that there are one or more of the elements. The terms “comprising,” “including,” and “having” are intended to be inclusive and mean that there may be additional elements other than the listed elements. Additionally, it should be understood that references to “one embodiment,” “an embodiment,” or “some embodiments” of the present disclosure are not intended to be interpreted as excluding the existence of additional embodiments that also incorporate the recited features. Use of the term “approximately” or “near” should be understood to mean including close to a target (e.g., design, value, amount), such as within a margin of any suitable or contemplable error (e.g., within 0.1% of a target, within 1% of a target, within 5% of a target, within 10% of a target, within 25% of a target, and so on).
- (17) The present disclosure provides techniques for driving light emitting diodes (LED) of a pixel with peak current efficiency or approximately peak current efficiency while providing a high dynamic range for the pixel. Generally, pulse amplitude modulation (PAM), pulse width modulation (PWM), or both, may facilitate controlling light intensity for the dynamic range. Pulse amplitude modulation is a modulation technique in which the amplitude (e.g., signal strength) of the pulsed carrier signal is varied in proportion according to the amplitude of the message signal. Pulse width modulation is a modulation technique in which the width of the pulses is varied. Pulse width modulation allows varying the amount of time the signal is high (e.g., on), such as by changing the proportion of time the signal is high compared to when it is low (e.g., off) over a consistent time interval. As such, pulse width modulation reduces the average power delivered by an electrical signal by effectively breaking apart the driving time into smaller parts. Often, displays use pulse amplitude modulation to drive LEDs for a high total dynamic range. However, pulse amplitude modulation decreases efficiency of LEDs at low current, and thus, pulse amplitude modulation may render the LEDs less effective for driving for a dim luminance using the low currents. As such, displays may use a combination of both pulse amplitude modulation and pulse width modulation. However, pulse width modulation may provide a relatively lower maximum total dynamic range than the pulse amplitude modulation.

(18) Moreover, displays are often thin film transistor (TFT) displays, which are generally a variant of a liquid crystal displays (LCDs) that use TFTs to improve image qualities such as addressability and contrast. In TFT displays, gray levels are provided using pulse amplitude modulation. However, TFTs are associated with a maximum current limitation, resulting in limited range for the total dynamic range. In LED displays, the peak current efficiencies may be the same or approximately the same as the TFT maximum currents. This may result in a shorter panel lifetime, for example, as the TFTs operate close to the maximum current limitation, as well as result in LEDs operating at low currents to avoid TFT reliability issues (e.g., LEDs operating at low efficiencies). The peak current efficiencies being the same or approximately the same as the TFT maximum currents may also result in non-uniform LED responses for low currents driving the LEDs.

(19) As such, the systems and methods described herein disclose driving LEDs at peak current efficiencies while providing high total dynamic range for varying gray levels. With the foregoing in mind, FIG. 1 illustrates an electronic device 10 according to an embodiment of the present disclosure may include, among other things, one or more processor(s) 12, memory 14, nonvolatile storage 16, a display 18, input structures 22, an input/output (I/O) interface 24, a network interface 26, a power source 28, and a transceiver 30. The various functional blocks shown in FIG. 1 may include hardware elements (including circuitry), software elements (including computer code stored on a computer-readable medium) or a combination of both hardware and software elements. It should be noted that FIG. 1 is merely one example of a particular implementation and is intended to illustrate the types of components that may be present in electronic device 10.

(20) By way of example, the electronic device 10 may represent a block diagram of the notebook computer depicted in FIG. 2, the handheld device depicted in FIG. 3, the handheld device depicted in FIG. 4, the desktop computer depicted in FIG. 5, the wearable electronic device depicted in FIG. 6, or similar devices. It should be noted that the processor(s) 12 and other related items in FIG. 1 may be generally referred to herein as “data processing circuitry.” Such data processing circuitry may be embodied wholly or in part as software, hardware, or any combination thereof. Furthermore, the processor(s) 12 and other related items in FIG. 1 may be a single contained processing module or may be incorporated wholly or partially within any of the other elements within the electronic device 10.

(21) In the electronic device 10 of FIG. 1, the processor(s) 12 may be operably coupled with a memory 14 and a nonvolatile storage 16 to perform various algorithms. Such algorithms or instructions executed by the processor(s) 12 may be stored in any suitable article of manufacture that includes one or more tangible, computer-readable media. The tangible, computer-readable media may include the memory 14 and/or the nonvolatile storage 16, individually or collectively, to store the algorithms or instructions. The memory 14 and the nonvolatile storage 16 may include any suitable articles of manufacture for storing data and executable instructions, such as random-access memory, read-only memory, rewritable flash memory, hard drives, and optical discs. In addition, programs (e.g., an operating system) encoded on such a computer program product may also include instructions that may be executed by the processor(s) 12 to enable the electronic device 10 to provide various functionalities.

(22) In certain embodiments, the display 18 may be a liquid crystal display (LCD), which may facilitate users to view images generated on the electronic device 10. In some embodiments, the display 18 may include a touch screen, which may facilitate user interaction with a user interface of the electronic device 10. Furthermore, it should be appreciated that, in some embodiments, the display 18 may include one or more light-emitting diode (LED) displays, organic light-emitting diode (OLED) displays, active-matrix organic light-emitting diode (AMOLED) displays, or some combination of these and/or other display technologies. The display 18 may drive the LEDs with amplitude modulation and/or pulse width modulation. Briefly, and as will be described in detail herein, the display 18 may include super pixels that facilitate in the LEDs operating at peak current efficiencies while providing a high dynamic range (e.g., while driving with pulse width modulation).

(23) The input structures **22** of the electronic device **10** may enable a user to interact with the electronic device **10** (e.g., pressing a button to increase or decrease a volume level). The I/O interface **24** may enable the electronic device **10** to interface with various other electronic devices, as may the network interface **26**. The network interface **26** may include, for example, one or more interfaces for a personal area network (PAN), such as a BLUETOOTH® network, for a local area network (LAN) or wireless local area network (WLAN), such as an 802.11x WI-FI® network, and/or for a wide area network (WAN), such as a 3.sup.rd generation (3G) cellular network, universal mobile telecommunication system (UMTS), 4.sup.th generation (4G) cellular network, long term evolution (LTE®) cellular network, long term evolution license assisted access (LTE-LAA) cellular network, 5.sup.th generation (5G) cellular network, and/or New Radio (NR) cellular network. In particular, the network interface **26** may include, for example, one or more interfaces for using a Release-15 cellular communication standard of the 5G specifications that include the millimeter wave (mmWave) frequency range (e.g., 24-300 GHz). The transceiver **30** of the electronic device **10**, which includes the transmitter and the receiver, may allow communication over the aforementioned networks (e.g., 5G, Wi-Fi, LTE-LAA, and so forth).

(24) The network interface **26** may also include one or more interfaces for, for example, broadband fixed wireless access networks (e.g., WIMAX®), mobile broadband Wireless networks (mobile WIMAX®), asynchronous digital subscriber lines (e.g., ADSL, VDSL), digital video broadcasting-terrestrial (DVB-T®) network and its extension DVB Handheld (DVB-H®) network, ultra-wideband (UWB) network, alternating current (AC) power lines, and so forth.

(25) In some embodiments, the electronic device **10** communicates over the aforementioned wireless networks (e.g., WI-FI®, WIMAX®, mobile WIMAX®, 4G, LTE®, 5G, and so forth) using the transceiver **30**. The transceiver **30** may include circuitry useful in both wirelessly receiving the reception signals at the receiver and wirelessly transmitting the transmission signals from the transmitter (e.g., data signals, wireless data signals, wireless carrier signals, radio frequency signals). Indeed, in some embodiments, the transceiver **30** may include the transmitter and the receiver combined into a single unit, or, in other embodiments, the transceiver **30** may include the transmitter separate from the receiver. The transceiver **30** may transmit and receive radio frequency signals to support voice and/or data communication in wireless applications such as, for example, PAN networks (e.g., BLUETOOTH®), WLAN networks (e.g., 802.11x WI-FI®), WAN networks (e.g., 3G, 4G, 5G, NR, and LTE® and LTE-LAA cellular networks), WIMAX® networks, mobile WIMAX® networks, ADSL and VDSL networks, DVB-T® and DVB-H® networks, UWB networks, and so forth. As further illustrated, the electronic device **10** may include the power source **28**. The power source **28** may include any suitable source of power, such as a rechargeable lithium polymer (Li-poly) battery and/or an alternating current (AC) power converter.

(26) In certain embodiments, the electronic device **10** may take the form of a computer, a portable electronic device, a wearable electronic device, or other type of electronic device. Such computers may be generally portable (such as laptop, notebook, and tablet computers), or generally used in one place (such as desktop computers, workstations, and/or servers). In certain embodiments, the electronic device **10** in the form of a computer may be a model of a MacBook®, MacBook® Pro, MacBook Air®, iMac®, Mac® mini, or Mac Pro® available from Apple Inc. of Cupertino, California. By way of example, the electronic device **10**, taking the form of a notebook computer **10A**, is illustrated in FIG. 2 in accordance with one embodiment of the present disclosure. The depicted notebook computer **10A** may include a housing or enclosure **36**, a display **18**, input structures **22**, and ports of an I/O interface **24**. In one embodiment, the input structures **22** (such as a keyboard and/or touchpad) may be used to interact with the computer **10A**, such as to start, control, or operate a graphical user interface (GUI) and/or applications running on computer **10A**. For example, a keyboard and/or touchpad may allow a user to navigate a user interface and/or an application interface displayed on display **18**.

(27) FIG. 3 depicts a front view of a handheld device **10B**, which represents one embodiment of the

electronic device **10**. The handheld device **10B** may represent, for example, a portable phone, a media player, a personal data organizer, a handheld game platform, or any combination of such devices. By way of example, the handheld device **10B** may be a model of an iPhone® available from Apple Inc. of Cupertino, California. The handheld device **10B** may include an enclosure **36** to protect interior components from physical damage and/or to shield them from electromagnetic interference. The enclosure **36** may surround the display **18**. The I/O interfaces **24** may open through the enclosure **36** and may include, for example, an I/O port for a hardwired connection for charging and/or content manipulation using a standard connector and protocol, such as the Lightning connector provided by Apple Inc. of Cupertino, California, a universal serial bus (USB), or other similar connector and protocol.

(28) The input structures **22**, in combination with the display **18**, may allow a user to control the handheld device **10B**. For example, the input structures **22** may activate or deactivate the handheld device **10B**, navigate user interface to a home screen, a user-configurable application screen, and/or activate a voice-recognition feature of the handheld device **10B**. Other input structures **22** may provide volume control, or may toggle between vibrate and ring modes. The input structures **22** may also include a microphone that may obtain a user's voice for various voice-related features, and a speaker that may enable audio playback and/or certain phone capabilities. The input structures **22** may also include a headphone input that may provide a connection to external speakers and/or headphones.

(29) FIG. **4** depicts a front view of another handheld device **10C**, which represents another embodiment of the electronic device **10**. The handheld device **10C** may represent, for example, a tablet computer, or one of various portable computing devices. By way of example, the handheld device **10C** may be a tablet-sized embodiment of the electronic device **10**, which may be, for example, a model of an iPad® available from Apple Inc. of Cupertino, California.

(30) Turning to FIG. **5**, a computer **10D** may represent another embodiment of the electronic device **10** of FIG. **1**. The computer **10D** may be any computer, such as a desktop computer, a server, or a notebook computer, but may also be a standalone media player or video gaming machine. By way of example, the computer **10D** may be an iMac®, a MacBook®, or other similar device by Apple Inc. of Cupertino, California. It should be noted that the computer **10D** may also represent a personal computer (PC) by another manufacturer. A similar enclosure **36** may be provided to protect and enclose internal components of the computer **10D**, such as the display **18**. In certain embodiments, a user of the computer **10D** may interact with the computer **10D** using various peripheral input structures **22**, such as the keyboard **22A** or mouse **22B** (e.g., input structures **22**), which may connect to the computer **10D**.

(31) Similarly, FIG. **6** depicts a wearable electronic device **10E** representing another embodiment of the electronic device **10** of FIG. **1** that may be configured to operate using the techniques described herein. By way of example, the wearable electronic device **10E**, which may include a wristband **43**, may be an Apple Watch® by Apple Inc. of Cupertino, California. However, in other embodiments, the wearable electronic device **10E** may include any wearable electronic device such as, for example, a wearable exercise monitoring device (e.g., pedometer, accelerometer, heart rate monitor), or other device by another manufacturer. The display **18** of the wearable electronic device **10E** may include a touch screen display **18** (e.g., LCD, LED display, OLED display, active-matrix organic light emitting diode (AMOLED) display, and so forth), as well as input structures **22**, which may allow users to interact with a user interface of the wearable electronic device **10E**.

(32) With the foregoing in mind, a block diagram of an architecture of a micro light emitting diode (μ -LED) display **18** appears in FIG. **7**. Although the following descriptions describe μ -LEDs, the systems and methods described herein may apply to any LED, such as LEDs, mini LEDs, and so forth. As shown, the display **18** may use a Red Green Blue (RGB) display panel **60** with pixels, which include red, green, and blue μ -LEDs (e.g., subpixels). Support circuitry **62** may receive RGB-format video image data **64**. It should be appreciated, however, that the display **18** may

alternatively display other formats of image data, in which case the support circuitry **62** may receive image data of such different image format. In the support circuitry **62**, a video timing controller (TCON) **66** may receive and use the image data **64** in a serial signal to determine a data clock signal (DATA_CLK) to control the provision of the image data **64** in the display **18**. The video TCON **66** also passes the image data **64** to serial-to-parallel circuitry **68** that may deserialize the image data **64** signal into several parallel image data signals **70**. That is, the serial-to-parallel circuitry **68** may collect the image data **64** into the particular data signals **70** that are passed on to specific columns among a total of M respective columns in the display panel **60**. As such, the data **70** is labeled DATA[0], DATA[1], DATA[2], DATA[3] . . . DATA[M-3], DATA[M-2], DATA[M-1], and DATA[M]. The data **70** respectively contain image data corresponding to pixels in the first column, second column, third column, fourth column . . . fourth-to-last column, third-to-last column, second-to-last column, and last column, respectively. The data **70** may be collected into more or fewer columns depending on the number of columns that make up the display panel **60**.

(33) As noted above, the video TCON **66** may generate the data clock signal (DATA_CLK). An emission timing controller (TCON) **72** may generate an emission clock signal (EM_CLK). Collectively, these may be referred to as Row Scan Control signals. Circuitry on the display panel **60** may use the Row Scan Control signals to display the image data **70**. The display panel **60** includes column drivers (CDs) **74**, row drivers (RDs) **76**, and micro-drivers (μ Ds) **78**. Each μ D **78** drives a number (e.g., one or more) of pixels **80** having μ -LEDs as subpixels **82**. In some embodiments, each pixel **80** includes at least one red μ -LED, at least one green μ -LED, and at least one blue μ -LED to represent the image data **64** in RGB format.

(34) A power supply **84** may provide a reference voltage (V.sub.ref) **86** to drive the μ -LEDs, a digital power signal **88**, and an analog power signal **90**. In some cases, the power supply **84** may provide more than one reference voltage (V.sub.ref) **86** signal. Namely, μ -LEDs of subpixels **82** of different colors may be driven using different reference voltages. As such, the power supply **84** may provide more than one reference voltage (V.sub.ref) **86**. Additionally or alternatively, other circuitry on the display panel **60** may step the reference voltage (V.sub.ref) **86** up or down to obtain different reference voltages to drive different colors of μ -LEDs.

(35) To allow the μ Ds **78** to drive the μ -LED subpixels **82** of the pixels **80**, the column drivers (CDs) **74** and the row drivers (RDs) **76** may operate in concert. Each column driver (CD) **74** may drive the respective image data **70** signal for that column in a digital form. Meanwhile, each RD **76** may provide the data clock signal (DATA_CLK) and the emission clock signal (EM_CLK) appropriately to activate the row of μ Ds **78** driven by the RD **76**. A row of μ Ds **78** may be activated when the RD **76** that controls that row sends the data clock signal (DATA_CLK). This may cause the now-activated μ Ds **78** of that row to receive and store the digital image data **70** signal that is driven by the column drivers (CDs) **74**. The μ Ds **78** of that row then may drive the pixels **80** based on the stored digital image data **70** signal based on the emission clock signal (EM_CLK). That is, the μ Ds **78** may drive the pixels **80** for a duration corresponding to the pulse width generated by the emission clock signal (EM_CLK).

(36) As previously mentioned, driving the LEDs (e.g., μ -LEDs) using pulse width modulation may facilitate the LEDs operating at peak efficiency current but comprise the dynamic range. As such, the LEDs of the display **18** may additionally or alternatively be driven with pulse amplitude modulation. However, pulse amplitude modulation may decrease efficiency at gray levels for dim luminesces. As will be discussed with respect to FIGS. **8-14**, the super pixel described herein may facilitate the LEDs to operate at peak efficiency currents and also provide a high dynamic range.

(37) To illustrate, FIG. **8** depicts a symmetric super pixel **100A** of a display panel **60**. In particular, a pixel **80**, as previously described, may include one or more subpixels **82**. In some embodiments, each of the subpixels **82** may correspond to a μ -LEDs for a different color, such as a red, green, and a blue subpixel. In the depicted embodiment, each of the subpixels **82** may include an area of 36×36 micrometers (μ m). In contrast, and as shown, a pixel **80** and/or a subpixel **82** may be divided

into multiple portions making up a symmetric super pixel **100A**. Specifically, the symmetric super pixel **100A** includes four super subpixels **102**. Although the depicted embodiment and corresponding descriptions describe the symmetric super pixel **100A** as having four super subpixels **102**, which represents a particular embodiment, the symmetric super pixel **100** may have two or more super subpixels **102**. Each of the super subpixels **102** include the same area and dimensions (e.g., length and width). That is, the super subpixels **102** are symmetric. Here, the super pixel **100A** has an area of $36 \times 36 \mu\text{m}$ and as such, each of the super subpixels **102** have an area of $18 \times 18 \mu\text{m}$. The super subpixels **102** having areas smaller than the subpixels **82** may facilitate control of a smaller area of the super pixel **100A** and thus, more granular control overall for the super pixel **100A**. That is, rather than the μDs **78** driving respective $\mu\text{-LEDs}$ for the subpixels **82** that have an area of $36 \times 36 \mu\text{m}$, the μDs **78** may drive smaller areas (e.g., $18 \times 18 \mu\text{m}$) to provide an increased and more dynamic, individual control over the brightness levels emitted by the overall LED for the super pixel **100A**. For example, to reduce brightness, a first super subpixel **102A** having an area of $18 \times 18 \mu\text{m}$ may be turned off. Similarly, a second super subpixel **102B**, a third super subpixel **102C**, and/or a fourth super subpixel **102D** may be turned off based on the desired level of brightness or dimming. Thus, the super subpixels **102** may continue to drive at the same peak current while increasing the dynamic range. In particular, the four super subpixels **102** may increase the dynamic range by a factor of four (e.g., $4\times$). As such, the brightness of the LEDs (e.g., $\mu\text{-LEDs}$) of the super pixel **100** may be reduced up to a factor of four without reducing the current to the LED.

(38) FIG. **9** depicts an asymmetric super pixel **100B** of a display panel **60**. As previously described, the pixel **80** may include one or more subpixels **82** that may correspond to a different colors, such as a red, a green, and a blue subpixel. The subpixels **82** may each include an area of $36 \times 36 \mu\text{m}$. The subpixel **82** may be divided into multiple portions making up an asymmetric super pixel **100B**. Specifically, the asymmetric super pixel **100B** includes two asymmetric super subpixels **102** having different areas and/or different dimensions. Although the depicted embodiment and corresponding descriptions describe the asymmetric super pixel **100B** as having two super asymmetric super subpixels **103**, which represents a particular embodiment, the asymmetric super pixel **100B** may have two or more asymmetric super subpixels **102**. Each of the asymmetric super subpixels **103** may include different areas, and thus, are symmetric. In the depicted embodiment, the super asymmetric pixel **100B** has an area of $36 \times 36 \mu\text{m}$ that is divided into two asymmetric super subpixels **103**. A first asymmetric super subpixels **103A** has an area of $8 \times 8 \mu\text{m}$ and a second asymmetric super subpixel **103B** has an area of $35 \times 35 \mu\text{m}$. As previously mentioned, the small areas of the asymmetric super subpixels **103** may facilitate granular control for the asymmetric super pixel **100B**, increasing the total dynamic range. That is, rather than the μDs **78** driving respective $\mu\text{-LEDs}$ for the subpixels **82** that have an area of $36 \times 36 \mu\text{m}$, the μDs **78** may drive smaller areas (e.g., $35 \times 35 \mu\text{m}$ or $8 \times 8 \mu\text{m}$) to provide increased and more dynamic, individual control over the brightness levels emitted by the overall LED for the asymmetric super pixel **100B**. (39) By way of example, both of the asymmetric super subpixels **103** may be turned on for high brightness, while the larger second asymmetric super subpixel **103B** may be turned off for low brightness. When both asymmetric super subpixels **103** are turned on or if either of the asymmetric super subpixels **103** are turned off, the LED (e.g., $\mu\text{-LEDs}$) of the asymmetric super pixel **100B** is still driving with a constant peak efficiency current. The dynamic range is equivalent to the ratio of the larger pixel to the smaller pixel, and as such, the dynamic range of the asymmetric super pixel **100B** is $1/20.\text{sup.th.}$ Thus, the dynamic range is increased by a factor of 20 (e.g., $20\times$).

(40) In some embodiments, the super pixels **100** may include symmetric and/or asymmetric super subpixels **102**, **103**, and the super subpixels **102**, **103** may have different areas (e.g., different than $8 \times 8 \mu\text{m}$, $35 \times 35 \mu\text{m}$, and so forth). Furthermore, the super subpixel colors may also vary. That is, rather than the super pixel **100** including a particular number of red, green, or blue super subpixels, the super pixel **100** may include one or more or none of the red, green, or blue subpixels. The areas and symmetry of the super pixel **100** may be based on the color to be emitted and/or a desired

dynamic range for the super pixel **100** or super subpixels **102**, **103**. For example, the dynamic range associated with red may be higher than green, and as such, may require a more granular control. As such, a red super pixel **100** may have a large number of super subpixels **102**, **103** of small dimensions (e.g., smaller super subpixels **102**, **103** as the number of super subpixels **102**, **103** increases).

(41) FIG. **10** is a schematic diagram of a stacked LED circuit **110** with a super pixel **100**. As shown, the stacked LED circuit **110** includes a first LED **112A** and a second LED **112B** of (e.g., super pixels **100** or super subpixels **102**, **103** of the super pixel **100**). Although the systems and methods described herein describe two LEDs **112** corresponding to two super pixels **100**, which represents a particular embodiment, the systems and methods may include two or more LEDs **112** (e.g., two, four, twenty, one hundred, and so forth). The number of LEDs **112** may be based on a desired dynamic range for the pixels **80**. For example, the number of LEDs **112** may be linearly associated with the total dynamic range (e.g., increase number of LEDs **112** to increase total dynamic range). In some embodiments, the LEDs **112** may be μ -LEDs. Moreover, each of the super pixels **100** may have one or more super subpixels **102**, **103** (e.g., two, three, four, eight, and so forth).

(42) The stacked LED circuit **110** also includes an analog power supply **111** (AVDD) connected to a first resistor **114**. A quotient of the AVDD **111** and the resistor **114** may provide a steady current source to a first transistor **116A** and a second transistor **116B** in a cascode formation. The AVDD **111**, the first resistor **114**, and the transistors **116** may collectively function as a current source **105**, as indicated by the dashed line box. The stacked LED circuit **110** also includes a second resistor **118** connected in series with the second LED **112B**, and connected to a negative voltage **120** (V.sub.Neg). The V.sub.Neg **120** may receive negative voltage from a power supply and may be used to turn on the LEDs **112**.

(43) The transistors **116** may be P-channel metal—oxide—semiconductor (PMOS) transistors. An input at a gate of the first transistor **116** may include an emission signal (EM) that may enable driving circuitry for LEDs **112** to drive the LEDs **112**, and an output of the first transistor **116A** may include a drain voltage (V.sub.DrTr). An input at a gate of the second transistor **116B** may include a reference voltage signal (V.sub.Ref), and output from the second transistor **116B** may include current for the LEDs **112** (e.g., diode current). As previously discussed, the V.sub.Ref may refer to a reference voltage to drive the LEDs **112**.

(44) The first LED **112A** and the second LED **112B** are connected in series and since they illuminate at the same time, the brightness for the super pixel **100** may be doubled. As such, the current source **105** may drive the LEDs **112** with half the amount of current to reduce the brightness back to the intended level of brightness. By reducing the driving current to half, the stacked LED circuit **110** may reduce power consumption. The power overhead resulting from the transistors **116** using some power intended for the LEDs **112**, may also result in a voltage drop due across a resistance (e.g., an IR drop) as a product of current (I) passing through resistance (R), such as through the first resistor **114** and/or the second resistor **118**. By reducing the driving current to half, the stacked LED circuit **110** may also reduce the IR drop across the first resistor **114** and/or the second resistor **118**. By way of example, the stacked LED circuit **110** may reduce power consumption by at least 25% in comparison to a cascode current source with a single LED **112** or the LEDs **112** not connected in series (e.g., in parallel).

(45) The LEDs **112** may be two different LEDs **112** (e.g., μ -LEDs) corresponding to two different super subpixels **102**, **103** of a super pixel **100**, such as a symmetric super pixel **100A** and/or an asymmetric super pixel **100B**. In some embodiments, the LEDs **112** may be two different LEDs **112** corresponding to two super pixels **100**, such as a symmetric super pixel **100A** and/or an asymmetric super pixel **100B** having super subpixels **102**, **103**.

(46) The LEDs **112** may be turned off one by one to decrease brightness. Moreover, the LEDs **112** may have different maximum current densities (J_{max}) and as such, if one of the LEDs **112**

becomes inefficient (e.g., current efficiency below a threshold efficiency), the other LED **112** may compensate. That is, the inefficient LED **112** may be turned off and the efficient LED **112** may emit light at a higher level so that the brightness is constant. To vary the brightness, symmetric super subpixels **102** and/or the asymmetric super subpixels **103** of the super pixels **100** may be used, along with the output blending techniques described herein.

(47) To illustrate, FIG. **11** is a block diagram **150** for driving an LED **112** for the symmetric super pixel **100A** and for the asymmetric super pixel **100B** (e.g., μ -LEDs for the super subpixels **102**, **103**) based on a gray level **152**. Any suitable device that may control the electronic device **10** and/or the circuitry of the display **18**, such as the processor **12** (e.g., one or more processors), may perform the processes described herein (e.g., with respect to FIG. **8-14**), such as turning on (e.g., to emit light) or turning off (e.g., to stop emitting light) one or more LEDs **112** and/or μ -LEDs for the super pixels **100** or super subpixels **102**, **103**. The processes may be implemented by executing software or instructions stored in a tangible, non-transitory, computer-readable medium, such as the memory **14** (e.g., one or more memory devices), using the processors **12**. The processor **12** of the electronic device **10** may execute instructions to perform the processes that are stored in the memory **14** and carried out by the processor **12**. In some embodiments, display driving circuitry may perform the processes described herein. For example, the display driving circuitry may perform the process steps described in FIG. **11** and FIG. **12**. While the processes may be described using steps in a specific sequence (e.g., turning on a first super subpixel **102A**, **103A** and subsequently a second super subpixel **102B**, **103B**), it should be understood that the present disclosure contemplates that the described steps may be performed in different sequences than the sequence illustrated, and certain described steps may be skipped or not performed altogether.

(48) As shown, the super pixels **100** may emit light for more than four gray levels **152**. In additional or alternative embodiments, the super pixels **100** may emit light for one or more gray levels **152**. For a first gray level **152A**, which is the lowest gray level (e.g., dimmest luminance) in the current embodiment, the first symmetric super subpixel **102A** may be turned on while the remaining symmetric super subpixels **102** are turned off. For a second gray level **152B**, which is the second lowest gray level (e.g., second dimmest luminance) in the current embodiment, the first and the second symmetric super subpixels **102A**, **102B** may be turned on while the remaining symmetric super subpixels **102** are turned off. For a third gray level **152C**, which is the third lowest gray level (e.g., moderate luminance) in the current embodiment, the first through the third symmetric super subpixels **102A-C** may be turned on while the fourth symmetric super subpixel **102D** is turned off. Each of four gray levels **152** may be associated with a single emission clock toggle (e.g., via the first transistor **116A**) for driving the μ Ds **78** driving the LEDs **112** for the symmetric pixel **100A** or μ -LEDs for the respective super subpixels **102**. After four or more gray levels, all the μ -LEDs of the subpixels **102** may emit light and additional toggles may be used for additional luminance (e.g., up to 252 toggles of the emission clock).

(49) Similarly, for the asymmetric super pixel **100B**, the first asymmetric super subpixel **103B** may be turned on while the second asymmetric super subpixel **103B** is turned off. For the second, third, and fourth gray levels **152B-D** and up to N (e.g., one or more, such as four) gray levels, the luminance is increased by a factor of 20 and the emission clock may be toggled to increase brightness for the first asymmetric super subpixel **103A**. As previously discussed, the asymmetric super pixel **100B** provides a dynamic range of 20. After the luminance reaches a factor of 20 (e.g., 20 luminance), the second asymmetric super subpixel **103B** may be turned on. For additional brightness for higher gray levels **152**, pulse width modulation may be used and the emission clock may be toggled, up to 255 toggles. In some embodiments, pulse amplitude modulation may be used.

(50) FIG. **12** is a block diagram **170** for driving an LED **112** for the symmetric super pixel **100A** and for the asymmetric super pixel **100B** (e.g., μ -LED for the super subpixels **102**, **103**) based on a brightness setting **172** (e.g., 5 to 2000 nits). As shown, the super pixels **100** may emit light for

varying brightness settings. In the depicted embodiment, a first brightness setting **172A**, which includes a range of 5 to 500 nits, the first symmetric super subpixel **102A** may be turned on while the remaining symmetric super subpixels **102** are turned off. For a second brightness setting **172B**, which includes a range of 500 to 1000 nits, the first and the second symmetric super subpixels **102A**, **102B** may be turned on while the remaining symmetric super subpixels **102** are turned off. For a third brightness setting **172C**, which includes a range of 1000 to 1500 nits, the first through the third symmetric super subpixels **102A-C** may be turned on while the fourth symmetric super subpixel **102D** is turned off. For a fourth brightness setting **172D**, which includes a range of 1500 to 2000 nits, each of the symmetric super subpixels **102** may be turned on.

(51) For the asymmetric super pixel **100B**, a fifth brightness setting **172E**, which includes a range of 5 to 100 nits, the first asymmetric super subpixel **103A** may be turned on while the second asymmetric super subpixel **103B** is turned off. During a sixth brightness setting **172F**, which includes a range of 100 to 2000 nits, the first and the second asymmetric super subpixels **103A** and **103B** may be turned on. Generally, the brightness settings **172** may correspond to the dynamic range associated with the super pixels **100** and the dimensions of the respective super subpixels **102**, **103**. For example, if the maximum brightness emitted by the super pixels **100** is 2000, the brightness setting ranges **172** may correspond to the dynamic range provided by each of the super subpixels **102**, **103**. By way of example, for the asymmetric super pixel **100B**, the brightness setting range may be based on a factor of 20 when the dynamic range is 20. That is, the sixth brightness setting **172F** has a range that is greater by a factor of 20 (e.g., range of 100 to 2000 is 20 times larger than a range of 5 to 100).

(52) Generally, when switching between LEDs **112** (e.g., μ -LEDs turning on super subpixels **102**, **103**), the change in luminance may create perceivable artifacts on the display **18**. For example, when changing the luminance based on gray levels **152**, as described with respect to FIG. **11**, the gray level **152** at which the LEDs **112** switched may create a perceivable step in an otherwise smooth gray level transition or ramp. Similarly, when changing the luminance provided by the LEDs **112** based on the brightness setting **172**, an abrupt jump in brightness may occur when increasing the brightness. The significant variance in brightness may also result in perceivable artifacts on the display **18**. To prevent or reduce the artifacts, the LEDs **112** may be controlled to vary the luminance gradually. That is, a first LED **112A** may be turned off and a second LED **112B** may be turned on, or the first LED **112A** may remain turned on when the second LED **112B** is turned on, using light blending techniques applied to the stacked LED circuit **110**.

(53) FIG. **13** is schematic diagram of the stacked LED circuit **200** with LEDs **112** in parallel for the super pixels **100** (e.g., μ -LEDs of super subpixels **102**, **103**). The depicted circuit may facilitate light blending, which may refer to a blending of the outputs from the LEDs **112**. In particular, the stacked LED circuit **200** with LEDs **112** in parallel may be used when blending between LEDs **112** for a change in luminance based on gray levels **152**. As will be described herein, the gates of two complementary TFTs may be connected to a data storage capacitor, while W/L ratios are selected based on a blending point. This stacked LED circuit **200** with LEDs **112** in parallel may cause current to flow towards either of the TFTs controlling a first LED **112**, the second LED **112**, or both, based on the particular gray level. The current flow may effectively blend outputs of the LEDs **112**.

(54) As shown, the circuit **200** includes the current source **105**, a voltage source **202**, an emit signal **203** (EMITB), a blending circuit **204**, a data source **205**, a current control transistor **207**, the first LED **112A**, the second LED **112B**, and a negative power supply **211**. The data source **205** may include data indicating and/or controlling the amount of current from the current source **105** to provide to the blending circuit **204**, which drives the LEDs **112** for a particular gray level. In particular, the current source **105** may input current to the current control transistor **207** based on the data source **205** and the emit signal **203** may control (e.g., enable or block) the amount of current outputted from the current control transistor **207** to the blending circuit **204**. The current

source **105** may provide a calibrated current source for driving the LEDs **112**. That is, the current source **105** may provide a constant current source to the LEDs **112**. The voltage source **202** may pre-charge the LEDs **112**. Specifically, the LEDs **112** may be initially driven with the voltage source **202** until they are stabilized or reach an operating voltage. At this point, the LEDs **112** may be switched to being driven by the current source **105**.

(55) As shown, the LEDs **112** are connected in parallel. At a first node **206A**, the first LED **112A** may connect to the voltage source **202** and at a second node **206B**, the second LED **112B** may connect to the voltage source **202**. When the LEDs **112** are switched to being driven by the current source **105**, the provided current may evenly or approximately evenly split between the first LED **112A** and the second LED **112B** (e.g., half to the first LED **112A** and half to the second LED **112B**). That amount of current may vary based on the subpixels **102**, **103**.

(56) In particular, a first light blending transistor **210A** and a second light blending transistor **210B** may be selectively enabled to control the amount of current passing through to each of the respective first LED **112** and the second LED **112B**, such as by selecting the voltage across the light blending transistors **210**. The light blending transistors **210** may be complementary, in which the first light blending transistors **210A** is a P-type metal-oxide-semiconductor (PMOS) transistor and the second light blending transistor **210B** switch is an N-type metal-oxide-semiconductor (NMOS) transistor. The NMOS second light blending transistors **210B** may turn off as a gate voltage of the NMOS second light blending transistor **210B** decreases. On the other hand, the PMOS first light blending transistors **210A** may turn on as a gate voltage of the PMOS first light blending transistor **210A** decreases since the PMOS first light blending transistor **210A** receives negative voltage from a negative power supply **211** (ELVSS), further driving the PMOS first light blending transistor **210A** to turn on. As such, the higher the absolute magnitude of the voltage stored in capacitors for charging the LEDs **112**, the lower the gate voltage becomes, causing the second light blending transistor **210B** to turn off. As a result, the current may be provided to the second light blending transistor **210B** and the second LED **112B**.

(57) A relatively higher gate voltage may cause the current to be provided to the first light blending transistor **210A** and the first LED **112A**. Thus, that amount of brightness to be emitted by the LEDs **112** and the super pixels **100** (e.g., the subpixels **102**, **103**) may be controlled using the first light blending transistor **210A** and the second light blending transistor **210B**. Light blending via the first light blending transistor **210A** and the second light blending transistor **210B** may determine how much current goes to the first light blending transistor **210A** and the first LED **112A** and the second light blending transistor **210B** and the second LED **112B**.

(58) That is, the first LED **112A** and the second LED **112B** may be turned on at different times. Turning them on and off may be controlled for blending to provide a smooth transition, rather than turning them on in response to another LED **112** turning off. Furthermore, as previously mentioned, the current going into the LED **112** may not change (e.g., J_{max} is constant) while blending. Instead, the amount of current going to the first light blending transistor **210A** or the second light blending transistor **210B** may vary, and the brightness emitted at the super pixels **100** may be controlled by reducing the maximum current density (J_{max}).

(59) FIG. **14** is schematic diagram of the stacked LED circuit **220** with LEDs **112** in series for the super pixels **100** (e.g., μ -LEDs of super subpixels **102**, **103**). This stacked LED circuit **220** with LEDs **112** in series may be used when blending between LEDs **112** based on the brightness setting **172**. In particular, a source and drain of a TFT may be connected across an LED **112**, such as the large second asymmetric super pixel **103B**, and a gate of the TFT may connect an external line that controls the amount of current removed from the large second asymmetric super pixel **103B**.

Controlling the amount of current removed may be modulated to blend the outputs of the LEDs **112** together based on the desired brightness level. In some embodiments, the stacked LED circuit **200** and **220** discussed with respect to FIG. **13** and FIG. **14**, may be combined to create light blending for gray levels **152** and brightness settings **172**.

(60) As shown, the circuit 220 may include the same components as FIG. 13, such as the current source 105, the voltage source 202, the emit signal 203 (EMITB), the data source 205, the current control transistor 207, the first LED 112A, the second LED 112B, and the negative power supply 211. These components may operate as described with respect to FIG. 13. For example, the LEDs 112 may be driven by the current source 105 via the emit signal 203, or the voltage source 202. As shown, the circuit 220 includes the LEDs 112 in series. The circuit 220 also includes a third transistor 210C that is configurable to select the first LED 112 and/or the second LED 112B.

(61) The current source 105 may provide the constant current source, as previously discussed. However, the current going to each the LEDs 112 (e.g., μ -LEDs) may vary, such as to control the subpixels 102, 103. As previously mentioned, the third light blending transistor 210C may select the first LED 112 and/or the second LED 112 by functioning as a bypass switch. As such, when the third light blending transistor 210C is turned on, current from the current source 105 may be shunted (e.g., directed) from going into the LED 112. Shunting the current may result in the LED 112 receiving less current and thus, may the light emitting from the LED 112 may be dimmer. Generally, the light blending transistors 210 do not have to be entirely on or off (e.g., operate as an on or off switch). They can be in an intermediate mode of a switch (e.g., partially on or partially off), in which some of the current may pass through the light blending transistors 210 and some will go through the LED 112 (e.g., so the LEDs 112 are not fully on or off). Thus, the systems and methods described herein disclose driving LEDs at peak current efficiencies while providing high total dynamic range for varying gray levels and/or brightness settings.

(62) It is well understood that the use of personally identifiable information should follow privacy policies and practices that are generally recognized as meeting or exceeding industry or governmental requirements for maintaining the privacy of users. In particular, personally identifiable information data should be managed and handled so as to minimize risks of unintentional or unauthorized access or use, and the nature of authorized use should be clearly indicated to users.

(63) The techniques presented and claimed herein are referenced and applied to material objects and concrete examples of a practical nature that demonstrably improve the present technical field and, as such, are not abstract, intangible or purely theoretical. Further, if any claims appended to the end of this specification contain one or more elements designated as “means for [perform]ing [a function] . . .” or “step for [perform]ing [a function] . . .,” it is intended that such elements are to be interpreted under 35 U.S.C. 112(f). However, for any claims containing elements designated in any other manner, it is intended that such elements are not to be interpreted under 35 U.S.C. 112(f).

Claims

1. A display system of a display, comprising: a first light emitting diode configured to emit light; a second light emitting diode configured to emit light; a current source configured to provide a constant current to the first light emitting diode and the second light emitting diode based on a data signal; and a plurality of transistors configured to receive the data signal, wherein the transistors of the plurality of transistors are configured to adjust an amount of the current or shunt the current towards the first light emitting diode, the second light emitting diode, or both based on the data signal.
2. The display system of claim 1, wherein adjusting the amount of current towards the first light emitting diode, the second light emitting diode, or both, blends outputs of the first light emitting diode and the second light emitting diode.
3. The display system of claim 1, wherein the first light emitting diode and the second light emitting diode are connected in series.
4. The display system of claim 3, wherein a transistor of the plurality of transistors removes current from the second light emitting diode connected in series with the first light emitting diode, and

wherein the second light emitting diode comprises a larger area than the first light emitting diode.

5. The display system of claim 1, wherein adjusting the amount of causes the first light emitting diode, the second light emitting diode, or both, to be partially on or partially off.

6. The display system of claim 1, wherein adjusting the amount of provides different amounts of current towards the first light emitting diode and the second light emitting diode.

7. The display system of claim 6, wherein the current from the current source remains constant when a transistor of the plurality of transistors removes or shunts the current to the first light emitting diode and the second light emitting diode.

8. The display system of claim 1, wherein the first light emitting diode and the second light emitting diode are connected in parallel.

9. The display system of claim 8, wherein or shunt adjusting the amount of the current towards the first light emitting diode and the second light emitting diode connected in parallel is based at least on a gray level.

10. The display system of claim 1, wherein or shunt adjusting the amount of the current towards the first light emitting diode and the second light emitting diode connected in series is based at least on a brightness setting.

11. The display system of claim 1, wherein the plurality of transistors comprises of a first transistor that is a P-type transistor and a second transistor that is a N-type transistor.
