

US Patent & Trademark Office

Patent Public Search | Text View

United States Patent Application Publication	20250283968
Kind Code	A1
Publication Date	September 11, 2025
Inventor(s)	ZHOU; Qi et al.

RESOLVING AOA AMBIGUITY BASED ON ROTATION OF USER EQUIPMENT

Abstract

A method for determining a true phase difference of arrival (PDOA), includes: determining a plurality of candidate unwrapped PDOAs for a signal transmitted by a target object and received by at least a first antenna and a second antenna of a user equipment (UE), where the plurality of candidate unwrapped PDOAs corresponds to a plurality of orientations of the UE, where a separation distance between the first antenna and the second antenna is greater than or equal to half of a wavelength of the signal; comparing the plurality of unwrapped candidate PDOAs; and identifying a true PDOA based on the comparison.

Inventors:	ZHOU; Qi (Milpitas, CA), ZHAO; Liang (Saratoga, CA), GOMEZ MARTINEZ; Feliciano (Los Gatos, CA)
Applicant:	QUALCOMM Incorporated (San Diego, CA)
Family ID:	1000007759933
Appl. No.:	18/598283
Filed:	March 07, 2024

Publication Classification

Int. Cl.:	G01S3/46 (20060101); G01S5/10 (20060101)
U.S. Cl.:	
CPC	G01S3/46 (20130101); G01S5/10 (20130101);

Background/Summary

BACKGROUND

[0001] Finding a lost object using wireless signals between a user equipment and the lost object often relies on the availability of antennas for the determination of 3D Angle of Arrival (AoA) information. Typically, the separation between each pair of antennas is required to be less than half of the wavelength of the signal received by the antennas in order to avoid angle ambiguity.

SUMMARY

[0002] In an example, a method for determining a true phase difference of arrival (PDOA), includes: determining a plurality of candidate unwrapped PDOAs for a signal transmitted by a target object and received by at least a first antenna and a second antenna of a user equipment (UE), where the plurality of candidate unwrapped PDOAs corresponds to a plurality of orientation of the UE, where a separation distance between the first antenna and the second antenna is greater than or equal to half of a wavelength of the signal; comparing the plurality of unwrapped candidate PDOAs; and identifying a true PDOA based on the comparison.

[0003] In another example, a user equipment (UE), includes: a first antenna; a second antenna; one or more memories; and one or more processors communicatively coupled to the one or more memories, the one or more processors being configured to: determine a plurality of candidate unwrapped phase difference of arrivals (PDOAs) for a signal transmitted by a target

object and received by at least the first antenna and the second antenna, where the plurality of candidate unwrapped PDOAs corresponds to a plurality of orientations of the UE, where a separation distance between the first antenna and the second antenna is greater than or equal to half of a wavelength of the signal; compare the plurality of unwrapped candidate PDOAs; and identify a true PDOA based on the comparison.

[0004] In another example, a non-transitory, processor-readable storage medium including processor-readable instructions to cause one or more processors to: determine a plurality of candidate unwrapped phase difference of arrivals (PDOAs) for a signal transmitted by a target object and received by at least a first antenna and a second antenna of a user equipment (UE), where the plurality of candidate unwrapped PDOAs corresponds to a plurality of orientations of the UE, where a separation distance between the first antenna and the second antenna is greater than or equal to half of a wavelength of the signal; compare the plurality of unwrapped candidate PDOAs; and identify a true PDOA based on the comparison.

Description

BRIEF DESCRIPTION OF THE DRAWINGS

[0005] FIG. 1 is a simplified diagram of an example system including a user equipment and a target object to be found.

[0006] FIG. 2A illustrates a block diagram of an example of a user equipment.

[0007] FIG. 2B illustrates a block diagram of components of the example user equipment shown in FIG. 2A.

[0008] FIG. 3 illustrates a block diagram of an example of a target object.

[0009] FIG. 4A illustrates a coordinate system for the reception of a signal by a first and a second antenna of the user equipment.

[0010] FIG. 4B illustrates the relationship between a spatial angle and a phase delay for different antenna separation distances L smaller than, equal, and greater than $\lambda/2$.

[0011] FIG. 5A is a diagram showing relationships between a target position, a target direction vector, an antenna vector, a unit antenna vector, and a spatial angle of arrival.

[0012] FIG. 5B is a diagram showing multiple unit antenna vectors obtained by rotating the user equipment.

[0013] FIG. 6 illustrates a flow diagram of a method for determining a true phase difference of arrival (PDOA), where a separation L between two antennas of the user equipment is greater than or equal to $\lambda/2$.

[0014] FIG. 7 is a flow diagram illustrating a first example implementation of identifying the true PDOA.

[0015] FIGS. 8A-8C are diagrams showing the measurement of a wrapped PDOA.

[0016] FIG. 9 is a flow diagram illustrating a second example implementation of identifying the true PDOA.

[0017] FIG. 10 is a diagram illustrating generation of a list of candidate unwrapped PDOA vectors.

[0018] FIGS. 11A-11C are diagrams illustrating the projection of unwrapped PDOA vectors onto a subspace.

[0019] FIG. 12 is a flow diagram illustrating a third example implementation of identifying the true PDOA.

[0020] FIGS. 13 and 14 are diagrams illustrating projections of candidate unwrapped PDOA vectors onto an ellipsoid residing within a subspace.

[0021] FIG. 15 is a flow diagram illustrating a fourth example implementation of identifying the true PDOA.

[0022] FIG. 16 illustrates an example user experience in locating the target object.

DETAILED DESCRIPTION

[0023] Techniques are discussed herein for determining a true phase difference of arrival (PDOA) using phase delay information determined from two antennas with a separation distance L greater than or equal to $\lambda/2$, where λ is the wavelength of the wireless ranging signal. The PDOA of a wireless signal received by an antenna of a user equipment (UE) is dependent on a spatial angle θ . When $L \geq \lambda/2$, the spatial angles θ have aliasing, where the PDOA corresponds to multiple spatial angles θ , i.e., the measured PDOA includes both “wrapped” and “unwrapped” angles, which injects angle ambiguity. Only one of the unwrapped angles corresponds to the true PDOA. Examples for resolving angle ambiguities and determining the true PDOA, where $L \geq \lambda/2$, may be based on comparisons of PDOA measurements obtained for different orientations of the UE. In one example, the comparison may leverage the fact that the true PDOA will be consistent over rotations of the UE, while untrue PDOAs will diverge over the rotations. In another example, the comparison may leverage the fact that a physically valid PDOA vector must lie in a subspace of a measurement matrix for a plurality of candidate unwrapped PDOAs and untrue PDOAs will likely be outside of the subspace. Once the angle ambiguities are resolved, and the true PDOA is determined, the true PDOA may be used to determine the Angle of Arrival (AoA) and the location of a target object using wireless ranging signals and positions of the UE. Other capabilities may be provided and not every implementation according to the disclosure must provide any, let alone all, of the capabilities discussed.

[0024] The description herein may refer to sequences of actions to be performed, for example, by elements of a computing device. Various actions described herein can be performed by specific circuits (e.g., an application specific integrated circuit (ASIC)), by program instructions being executed by one or more processors, or by a combination of both. Sequences of actions described herein may be embodied within a non-transitory computer-readable medium having stored thereon a corresponding set of computer instructions that upon execution would cause an associated processor to perform the functionality described herein. Thus, the various examples described herein may be embodied in a number of different forms, all of which are within the scope of the disclosure, including claimed subject matter.

[0025] FIG. 1 is a simplified diagram of an example system including a user equipment and a target object to be found. In general, the user equipment (UE) 105 may be any wireless communication device (e.g., a mobile phone, router, tablet computer, laptop computer, consumer asset tracking device, Internet of Things (IoT) device, etc.). A UE 105 may be mobile

(e.g., at certain times) be stationary. As used herein, the term “UE” may be referred to interchangeably as an “access terminal” or “AT,” a “client device,” a “wireless device,” a “subscriber device,” a “subscriber terminal,” a “subscriber station,” a “user terminal” or UT, a “mobile terminal,” a “mobile station,” a “mobile device,” or variations thereof. The UE **105** may be embodied by any of a number of types of devices including but not limited to printed circuit (PC) cards, compact flash devices, external or internal modems, wireless or wireline phones, smartphones, tablets, consumer asset tracking devices, asset tags, and so on. The UE **105** may comprise and/or may be referred to as a device, a mobile device, a wireless device, or by some other name. Moreover, the UE **105** may correspond to a cellphone, smartphone, laptop, tablet, PDA, consumer asset tracking device, navigation device, Internet of Things (IoT) device, health monitors, security systems, smart city sensors, smart meters, wearable trackers, virtual reality headsets, augmented reality glasses, or some other portable or moveable device. The UE **105** supports wireless communication with the target object **102** using one or more Radio Access Technologies (RATs) such as IEEE 802.11 WiFi® (also referred to as Wi-Fi®), Bluetooth® (BT), Ultra-wideband (UWB), etc., that may be used by wireless ranging techniques.

[0026] The target object **102** may be another UE. The target object may be any of a variety of devices, e.g., a set of earbuds (or one earbud), earbud chargers, a set of headphones, a smart tag, or any other device capable of wireless communication with the UE **105** using one or more of the RATs that may be used for wireless ranging.

[0027] Referring to FIG. **1**, to locate the target object **102** according to an example embodiment, the UE **105** changes orientations. The UE **105** communicates with the target object **102** using signals of one or more RATs. A phase difference of arrival (PDOA) between two antennas are measured for different orientations of the UE **105**. The time of arrival of a signal at the first antenna **246** may be measured and compared to the time of arrival of the signal at the second antenna **250**. The relative phase delay between the signal at the first antenna **246** and the second antenna **250** can be measured to calculate the PDOA. The UE **105** may calculate the angle of arrival (AoA) based on PDOA and may calculate a position of the target object **102** and a direction of the target object **102** relative to the position of the UE **105** based on the AoA.

[0028] FIG. **2A** illustrates an example user equipment **200**. The UE **200** may be an example of UE **105**. The UE **200** may comprise one or more processors **210**, one or more memories **211** including software (SW) **212**, and one or more wireless transceivers **240**, although any of these devices may be referred to in the singular (e.g., the processor **210**) while including one or more of the respective devices. The UE **200** may further comprise a first antenna **246** and a second antenna **250**. The one or more processors **210** and the one or more memories **211** may be communicatively coupled to each other by a bus **220** (which may be configured, e.g., for optical and/or electrical communication). The transceiver **240** is configured for wireless communication using one or more RATs.

[0029] FIG. **2B** illustrates an example user equipment **280**. The UE **280** may be an example of the UE **200** shown in FIG. **2B**. The UE **280** may comprise a computing platform including one or more processors **210**, one or more memories **211** including software (SW) **212**, one or more sensors **213**, a transceiver interface **214** for the transceiver **215** that includes the wireless transceiver **240**, a user interface **216**, a camera **218**, and a position device (PD) **219**. The one or more processors **210**, the one or more memories **211**, the one or more sensors **213**, the transceiver interface **214**, the user interface **216**, the camera **218**, and the position device **219** may be communicatively coupled to each other by a bus **220** (which may be configured, e.g., for optical and/or electrical communication). The one or more processors **210** may include one or more intelligent hardware devices, e.g., a central processing unit (CPU), one or more microcontrollers, an application specific integrated circuit (ASIC), etc. The one or more processors **210** may comprise multiple processors including one or more general-purpose/application processors **230**, one or more Digital Signal Processors (DSP) **231**, one or more modem processors **232**, one or more video processors **233**, and/or one or more sensor processors **234**. For example, the sensor processor **234** may comprise, e.g., processors for RF (radio frequency) sensing (with one or more wireless signals transmitted and reflection(s) used to identify, map, and/or track an object), and/or ultrasound, etc. The one or more modem processors **232** may support dual SIM/dual connectivity (or even more SIMs). For example, a SIM (Subscriber Identity Module or Subscriber Identification Module) may be used by an Original Equipment Manufacturer (OEM), and another SIM may be used by an end user of the UE **280** for connectivity. The one or more memories **211** may be one or more non-transitory storage media that may include random access memory (RAM), flash memory, disc memory, and/or read-only memory (ROM), etc. The one or more memories **211** may store the software **212** which may be processor-readable, processor-executable software code containing instructions that may be configured to, when executed, cause the one or more processors **210** to perform various functions described herein. Alternatively, the software **212** may not be directly executable by the one or more processors **210** but may be configured to cause the one or more processors **210**, e.g., when compiled and executed, to perform the functions. The description herein may refer to the one or more processors **210** performing a function, but this includes other implementations such as where the one or more processors **210** executes software and/or firmware. The description herein may refer to the one or more processors **210** performing a function as shorthand for one or more of the processors **230-234** performing the function. The description herein may refer to the UE **280** performing a function as shorthand for one or more appropriate components of the UE **280** performing the function. Functionality of the one or more processors **210** is discussed more fully below.

[0030] The configuration of the UE **280** shown in FIG. **2B** is an example and not limiting of the disclosure, including the claims, and other configurations may be used. For example, an example configuration of the UE **280** includes one or more of the processors **230-234** of the processor **210**, the memory **211**, a wireless transceiver, and one or more of the sensor(s) **213**, the user interface **216**, the camera **218**, and/or the PD **219**.

[0031] The UE **280** may comprise the modem processor **232** that may be capable of performing baseband processing of signals received and down-converted by the transceiver **215**. The modem processor **232** may perform baseband processing of signals to be upconverted for transmission by the transceiver **215**. Also, or alternatively, baseband processing may be

performed by the general-purpose/application processor **230** and/or the DSP **231**. Other configurations, however, may be used to perform baseband processing.

[0032] The UE **280** may include the sensor(s) **213** that may include, for example, an Inertial Measurement Unit (IMU) **270**, one or more magnetometers **271**, and/or one or more environment sensors **272**. The IMU **270** may comprise, for example, one or more accelerometers **273** (e.g., collectively responding to acceleration of the UE **280** in three dimensions) and/or one or more gyroscopes **274** (e.g., three-dimensional gyroscope(s)). The sensor(s) **213** may include the one or more magnetometers **271** (e.g., three-dimensional magnetometer(s)) to determine orientation (e.g., relative to magnetic north and/or true north) that may be used for any of a variety of purposes, e.g., to support one or more compass applications. The environment sensor(s) **272** may comprise, for example, one or more temperature sensors, one or more barometric pressure sensors, one or more ambient light sensors, one or more camera imagers, and/or one or more microphones, etc. The sensor(s) **213** may generate analog and/or digital signals indications of which may be stored in the memory **211** and processed by the DSP **231** and/or the general-purpose/application processor **230** in support of one or more applications such as, for example, applications directed to positioning and/or navigation operations. The sensor(s) **213** may comprise one or more of other various types of sensors such as one or more optical sensors, one or more weight sensors, and/or one or more radio frequency (RF) sensors, etc.

[0033] The sensor(s) **213** may be used in relative location measurements, relative location determination, motion determination, etc. Information detected by the sensor(s) **213** may be used for motion detection, relative displacement, dead reckoning, sensor-based location determination, and/or sensor-assisted location determination. The sensor(s) **213** may be useful to determine whether the UE **280** is fixed (stationary) or mobile. For example, for relative positioning information, the sensors/IMU may be used to determine the angle and/or orientation of the other device with respect to the UE **280**, etc.

[0034] The IMU **270** may be configured to provide measurements about a direction of motion and/or a speed of motion of the UE **280**, which may be used in relative location determination. For example, the one or more accelerometers **273** and/or the one or more gyroscopes **274** of the IMU **270** may detect, respectively, a linear acceleration and a speed of rotation of the UE **280**. The linear acceleration and speed of rotation measurements of the UE **280** may be integrated over time to determine an instantaneous direction of motion as well as a displacement of the UE **280**. The instantaneous direction of motion and the displacement may be integrated to track a location of the UE **280**. For example, a reference position of the UE **280** may be determined for a moment in time and measurements from the accelerometer(s) **273** and the gyroscope(s) **274** taken after this moment in time may be used (e.g., in dead reckoning) to determine present position of the UE **280** based on movement (direction and distance) of the UE **280** relative to the reference location.

[0035] The magnetometer(s) **271** may determine magnetic field strengths in different directions which may be used to determine orientation of the UE **280**. For example, the orientation may be used to provide a digital compass for the UE **280**. The magnetometer(s) may include a two-dimensional magnetometer configured to detect and provide indications of magnetic field strength in two orthogonal dimensions. The magnetometer(s) **271** may include a three-dimensional magnetometer configured to detect and provide indications of magnetic field strength in three orthogonal dimensions. The magnetometer(s) **271** may provide means for sensing a magnetic field and providing indications of the magnetic field, e.g., to the one or more processors **210**.

[0036] The transceiver **215** may include a wireless transceiver **240** configured to communicate with other devices through wireless connections. For example, the wireless transceiver **240** may include a wireless transmitter **242** and a wireless receiver **244** coupled to a first antenna **246** and a second antenna **250** for transmitting and/or receiving wireless signals **248** and **252**, respectively, and transducing signals from the wireless signals **248** and **252** to wired (e.g., electrical and/or optical) signals and from wired (e.g., electrical and/or optical) signals to the wireless signals **248** and **252**. The wireless receiver **244** includes appropriate components (e.g., one or more amplifiers, one or more frequency filters, and an analog-to-digital converter). The wireless transmitter **242** may include multiple transmitters that may be discrete components or combined/integrated components, and/or the wireless receiver **244** may include multiple receivers that may be discrete components or combined/integrated components. The wireless transceiver **240** may be configured to communicate signals according to a variety of radio access technologies (RATs) such as cellular (e.g., 3GPP defined communications including 4G, LTE, 5G NR, 6G, and the like), IEEE 802.11 (including IEEE 802.11az), WiFi®, WiFi® Direct (WiFi®-D), Bluetooth®, Ultra-Wide Band (UWB) (including 802.15.4), etc. A “radio,” as used herein, refers to a wireless transmitter and/or wireless receiver configured to communicate signals according to a specific RAT. The transceiver **215** may be communicatively coupled to the transceiver interface **214**, e.g., by optical and/or electrical connection. The transceiver interface **214** may be at least partially integrated with the transceiver **215**. The wireless transmitter **242** and the wireless receiver **244** may include multiple transmitters and/or multiple receivers, respectively, for sending and/or receiving, respectively, appropriate signals.

[0037] The user interface **216** may comprise one or more of several devices such as, for example, a speaker, microphone, display device, vibration device, keyboard, touch screen, etc. The user interface **216** may include more than one of any of these devices. The user interface **216** may be configured to enable a user to interact with one or more applications hosted by the UE **280**. For example, the user interface **216** may store indications of analog and/or digital signals in the one or more memories **211** to be processed by DSP **231** and/or the general-purpose/application processor **230** in response to action from a user or a request from an application. Similarly, applications hosted on the UE **280** may store indications of analog and/or digital signals in the one or more memories **211** to present an output signal to a user. The user interface **216** may include an audio input/output (I/O) device comprising, for example, a speaker, a microphone, digital-to-analog circuitry, analog-to-digital circuitry, an amplifier and/or gain control circuitry (including more than one of any of these devices). Other configurations of an audio I/O device may be used. Also, or alternatively, the user interface **216** may comprise one or more touch sensors responsive to touching and/or pressure, e.g., on a keyboard and/or touch screen of the user interface **216**.

[0038] The UE **280** may include the camera **218** for capturing still or moving imagery. The camera **218** may comprise, for example, an imaging sensor (e.g., a charge coupled device or a CMOS (Complementary Metal-Oxide Semiconductor) imager), a lens, analog-to-digital circuitry, frame buffers, etc. Additional processing, conditioning, encoding, and/or compression of signals representing captured images may be performed by the general-purpose/application processor **230** and/or the DSP **231**. Also, or alternatively, the video processor **233** may perform conditioning, encoding, compression, and/or manipulation of signals representing captured images. The video processor **233** may decode/decompress stored image data for presentation on a display device (not shown), e.g., of the user interface **216**.

[0039] The position device (PD) **219** may be configured to determine a position of the UE **280**, motion of the UE **280**, and/or relative position of the UE **280**, and/or time. The PD **219** may work in conjunction with the one or more processors **210** and the one or more memories **211** as appropriate to perform at least a portion of one or more positioning methods, although the description herein may refer to the PD **219** being configured to perform, or performing, in accordance with the positioning method(s). The PD **219** may also or alternatively be configured to determine location of the UE **280** using terrestrial-based signals (e.g., at least some of the wireless signals **248**) for trilateration. The PD **219** may be configured to use one or more images from the camera **218** and image recognition combined with known locations of landmarks (e.g., natural landmarks such as mountains and/or artificial landmarks such as buildings, bridges, streets, etc.) to determine location of the UE **280**. The PD **219** may be configured to determine a relative motion or orientation by the UE **280** by comparing multiple images captured by the camera **218** and tracking how a common “point of interest” within the images moves between images. The PD **219** may be configured to use one or more other techniques (e.g., relying on the UE's self-reported location (e.g., part of the UE's position beacon)) for determining the location of the UE **280**, and may use a combination of techniques (e.g., satellite and terrestrial positioning signals) to determine the location of the UE **280**. The PD **219** may include one or more of the sensors **213** (e.g., gyroscope(s), accelerometer(s), magnetometer(s), etc.) that may sense orientation and/or motion of the UE **280** and provide indications thereof that the one or more processors **210** (e.g., the general-purpose/application processor **230** and/or the DSP **231**) may be configured to use to determine motion (e.g., a velocity vector and/or an acceleration vector) of the UE **280**. The PD **219** may be configured to provide indications of uncertainty and/or error in the determined position and/or motion. Functionality of the PD **219** may be provided in a variety of manners and/or configurations, e.g., by the general-purpose/application processor **230**, the transceiver **215**, and/or another component of the UE **280**, and may be provided by hardware, software, firmware, or various combinations thereof.

[0040] FIG. 3 illustrates an example target object **300**. The target object **300** may be an example of the target object **102**. The target object **300** may comprise one or more processors **310**, one or more memories **330** (possibly including SW **312**), and one or more wireless transceivers **320**, although any of these devices may be referred to in the singular (e.g., the processor **310**) while including one or more of the respective devices. The one or more processors **310** and the one or more memories **330** may be communicatively coupled to each other by a bus **340** (which may be configured, e.g., for optical and/or electrical communication). The transceiver **320** may be configured for wireless communication using one or more RATs. For example, the transceiver **320** may be configured to wirelessly communicate with the transceiver **240** of the UE **200** using one or more RATs.

[0041] In one embodiment, the UE **105** (e.g., of FIG. 1) includes at least two antennas, the first antenna **246** and the second antenna **250**. FIG. 4A illustrates a coordinate system for the reception of a signal by the first and second antennas **246**, **250**. Both the first and second antennas **246**, **250** receive the same wireless signal at a spatial angle θ . The first antenna **246** receives a wireless signal at reception point **402**, and the second antenna **250** receives the same wireless signal at reception point **404**. L is the separation distance between the first antenna **246** and the second antenna **250**. The wireless signal received by the first antenna **246** travels an extra distance δ than the wireless signal received by the second antenna **250**, with $\delta = L \cdot \cos \theta$. The PDOA of the wireless signals received by the first antenna **246** and the second antenna **250** is dependent on the spatial angle θ . FIG. 4B illustrates the relationship between the spatial angle θ and the PDOA for different antenna separation distances L . When $L = \lambda/4$, the PDOA corresponds to one spatial angle θ . However, when L becomes larger than $\lambda/2$, such as $L = 6\lambda/10$, $L = 7\lambda/10$, or $L = 2\lambda$, the spatial angles θ have aliasing, where the PDOA corresponds to multiple spatial angles θ , injecting angle ambiguity. When $L < \lambda/2$, the PDOA stays in the range $(-\pi, \pi)$, and the PDOA angle may be measured without ambiguity. When $L \geq \lambda/2$, the PDOA may include angles outside of the $(-\pi, \pi)$ range, i.e., the PDOA may “wrap” around the range, resulting in the measured PDOA which is wrapped corresponding to multiple spatial angles θ . Only one of the multiple spatial angles θ corresponds to the true AoA.

[0042] FIG. 5A is a diagram illustrating a geometric arrangement in the measurement of a PDOA for a UE with two antennas. A first antenna (e.g., antenna **246**) may be assumed to be located at the origin of the coordinates, while the second antenna (e.g., antenna **250**) may be located at a position $\{\text{right arrow over (a)}\} = (a_{\text{sub.x}}, a_{\text{sub.y}}, a_{\text{sub.z}})_{\text{sup.T}}$, where $\{\text{right arrow over (a)}\}$ is the antenna vector with length $L = \|\{\text{right arrow over (a)}\}\|$. Assume that the target object **102** is at position $\{\text{right arrow over (x.sub.T)}\}$, and the target object **102** is sending an RF signal (e.g., UWB, WiFi, BT, etc.) that can be detected by the UE **105**. Once the RF signal arrives at the antennas **246**, **250** of the UE **105**, the PDOA Φ may be given by:

$$[00001] \quad \theta = \frac{2 \cdot L \cdot \cos(\theta)}{2 \cdot L \cdot \frac{\text{fwdarw.} \cdot \text{Math.} \cdot \text{fwdarw.} \cdot X_T}{\text{Math.} \cdot \text{fwdarw.} \cdot \text{Math.} \cdot \text{fwdarw.} \cdot X_T}} = \frac{2 \cdot L \cdot \text{fwdarw.} \cdot \text{Math.} \cdot \text{fwdarw.} \cdot u}{\text{Math.} \cdot \text{fwdarw.} \cdot \text{Math.} \cdot \text{fwdarw.} \cdot X_T} \quad (\text{Eq. 1})$$

where θ is the spatial angle between the vector for the target position $\{\text{right arrow over (x.sub.T)}\}$ and the antenna vector $\{\text{right arrow over (a)}\}$, $\{\text{right arrow over (a)}\}$ is a unit vector in the direction of $\{\text{right arrow over (a)}\}$, and $\{\text{right arrow over (u)}\}$ is a unit vector in the direction of $\{\text{right arrow over (x.sub.T)}\}$. The diagram of FIG. 5A illustrates the relationship between $\{\text{right arrow over (x.sub.T)}\}$, $\{\text{right arrow over (u)}\}$, $\{\text{right arrow over (a)}\}$, $\{\text{right arrow over (a)}\}$, and θ . When the antenna spacing L is less than $\lambda/2$, the PDOA P stays in the range $(-\pi, \pi)$, which may be measured without angle ambiguity.

Given the measured PDOA Φ , the original spatial angle θ may be determined using Eq. 2:

$$[00002] \quad \theta = \arccos\left(\frac{\lambda\Phi}{L}\right) \quad (\text{Eq. 2})$$

[0043] When the UE **105** is rotated to different orientations, multiple PDOAs $\Phi_{\text{sub}.i}$ may be measured, with a PDOA $\Phi_{\text{sub}.i}$ and an antenna vector $\alpha_{\text{sub}.i}$ corresponding to each orientation of the UE **105**. Here, the UE **105** is rotated with no displacement, or with a displacement much smaller than the distance to the target object **102** and may be disregarded. FIG. 5B illustrates three antenna vectors ($\{\vec{\alpha}_{\text{sub}.1}\}$, $\{\vec{\alpha}_{\text{sub}.2}\}$, $\{\vec{\alpha}_{\text{sub}.3}\}$) obtained by rotating the UE **105** to three different orientations. The PDOA vector $\{\vec{\Phi}\}$ may be expressed in matrix form:

[00003]

$$\begin{aligned} \vec{\Phi} &= \begin{bmatrix} \Phi_1 \\ \Phi_2 \\ \vdots \\ \Phi_N \end{bmatrix} = \frac{L}{\lambda} \begin{bmatrix} a_{1x} & a_{1y} & a_{1z} \\ a_{2x} & a_{2y} & a_{2z} \\ \vdots & \vdots & \vdots \\ a_{Nx} & a_{Ny} & a_{Nz} \end{bmatrix} \begin{bmatrix} u_x \\ u_y \\ u_z \end{bmatrix} = \mathbf{A} \vec{u} \quad (\text{Eq. 3}) \end{aligned}$$

where $\mathbf{A}$ is the measurement matrix and N is the number of different orientations. To determine the position of the target object **102**, the goal is to determine the value of $\{\vec{u}\}$ given the matrix $\mathbf{A}$ and the PDOA vector $\{\vec{\Phi}\}$. The unit vector $\vec{u}$ can be found using Eq. 4:

$$[00004] \quad \vec{u} = \mathbf{A}^+ \vec{\Phi} = (\mathbf{A}^T \mathbf{A})^{-1} \mathbf{A}^T \vec{\Phi} \quad (\text{Eq. 4})$$

[0044] When $L \geq \lambda/2$, the measured PDOA includes multiple “unwrapped” angles. Here, the symbol Φ is used to refer to unwrapped PDOAs, and the symbol ϕ is used to refer to wrapped PDOAs. Wrapped PDOAs $\phi_{\text{sub}.i}$ include angles that are measured and that are in the $(-\pi, \pi)$ range. The corresponding unwrapped PDOAs $\Phi_{\text{sub}.i}$ may include angles outside of the $(-\pi, \pi)$ range. The relationship between wrapped and unwrapped PDOAs may be expressed as a $\text{mod}(\cdot)$ function in Equation 5 and as a vector in Equation 6:

$$[00005] \quad \phi_i = \text{wrap}(\Phi_i) = ((\Phi_i + \pi) \bmod (2\pi)) - \pi \quad (\text{Eq. 5})$$

$$[00006] \quad \vec{\phi} = \begin{bmatrix} \phi_1 \\ \phi_2 \\ \vdots \\ \phi_N \end{bmatrix} = \begin{bmatrix} \text{wrap}(\Phi_1) \\ \text{wrap}(\Phi_2) \\ \vdots \\ \text{wrap}(\Phi_N) \end{bmatrix} = \text{wrap}\left(\begin{bmatrix} \Phi_1 \\ \Phi_2 \\ \vdots \\ \Phi_N \end{bmatrix}\right) \quad (\text{Eq. 6})$$

For a given wrapped PDOA $\phi_{\text{sub}.1}$, there are multiple unwrapped PDOAs $\Phi_{\text{sub}.i}$ that are consistent with the same wrapped PDOAs or Only one of the multiple unwrapped PDOAs $\Phi_{\text{sub}.i}$ is the true PDOA, i.e., that correctly matches the value of the wrapped PDOA $\phi_{\text{sub}.1}$.

[0045] Examples for resolving angle ambiguities and determining the true PDOA, where a separation L between two antennas of the UE **105** is greater than or equal to $\lambda/2$, may be based on comparisons of PDOA measurements obtained for different orientations of the UE **105**. Once the angle ambiguities are resolved, and the true PDOA is determined, the true PDOA may be used to determine a location of the target object **102**.

[0046] FIG. 6 illustrates a flow diagram of a method **600** for determining a true PDOA, where a separation L between two antennas of the UE **105** is greater than or equal to $\lambda/2$. The method **600** is, however, an example only and not limiting. The method **600** may be altered, e.g., by having one or more stages added, removed, rearranged, combined, performed concurrently, and/or by having one or more single stages split into multiple stages.

[0047] At stage **610**, the method **600** includes determining a plurality of candidate unwrapped PDOAs for a signal transmitted by a target object **102** and received by at least a first antenna **246** and a second antenna **250** of the UE **105**, where the plurality of candidate unwrapped PDOAs corresponds to a plurality of orientations of the UE **105**, where a separation distance between the first antenna **246** and the second antenna **250** is greater than or equal to half of the wavelength λ of the signal. The one or more processors **210**, possibly in combination with the memory **211**, may comprise means for determining the plurality of candidate unwrapped PDOAs for the signal transmitted by the target object and received by at least the first antenna and the second antenna of the UE.

[0048] At stage **620**, the method **600** includes comparing the plurality of candidate unwrapped PDOAs. The one or more processors **210**, possibly in combination with the memory **211**, may comprise means for comparing the plurality of candidate unwrapped PDOAs.

[0049] At stage **630**, the method **600** includes identifying a true PDOA based on the comparison. The one or more processors **210**, possibly in combination with the memory **211**, may comprise means for identifying the true PDOA based on the comparison.

[0050] Referring to FIG. 7, in a first example implementation of the method **600**, the comparison of the plurality of candidate unwrapped PDOAs leverages the fact that the AOA ambiguity will diverge over rotations of the UE **105**, while the true AOA will converge. The method **700**, shown in FIG. 7, is an example only and not limiting. The method **700** may be altered, e.g., by having one or more stages added, removed, rearranged, combined, performed concurrently, and/or by having one or more single stages split into multiple stages.

[0051] At stage **710**, the method **700** includes determining the plurality of candidate unwrapped PDOAs for the signal

transmitted by the target object **102** and received by at least the first antenna **246** and the second antenna **250** of the UE **105**, where the plurality of candidate unwrapped PDOAs includes a first subset of unwrapped PDOAs corresponding to a first wrapped PDOA and a second subset of unwrapped PDOAs corresponding to a second wrapped PDOA, where the first wrapped PDOA corresponds to a first orientation of the UE **105** and the second wrapped PDOA corresponds to a second orientation of the UE **105**, where the separation distance between the first antenna **246** and the second antenna **250** is greater than or equal to half of the wavelength of the signal. The one or more processors **210**, possibly in combination with the memory **211**, may comprise means for determining the plurality of candidate unwrapped PDOAs for the signal transmitted by the target object and received by at least the first antenna **246** and the second antenna **250** of the UE **105**. The method **700** may be applied to UE's with three or more antennas with separation distances L between each pair of two antennas being greater than or equal to $\lambda/2$.

[0052] At stage **720**, the method **700** includes determining a first subset of candidate AOAs corresponding to the first subset of candidate unwrapped PDOAs and a second subset of candidate AOAs corresponding to the second subset of candidate unwrapped PDOAs. The one or more processors **210**, possibly in combination with the memory **211**, may comprise means for determining the first subset of candidate AOAs corresponding to the first subset of candidate unwrapped PDOAs and a second subset of candidate AOAs corresponding to the second subset of candidate unwrapped PDOAs.

[0053] At stage **730**, the method **700** includes determining a plurality of divergences between the second subset of candidate AOAs and the corresponding first subset of candidate AOAs. The one or more processors **210**, possibly in combination with the memory **211**, may comprise means for determining the plurality of divergences between the second subset of candidate AOAs and the corresponding first subset of candidate AOAs.

[0054] At stage **740**, the method **700** includes identifying one or more of the first subset of candidate AOAs as untrue AOAs based on the plurality of divergences. The one or more processors **210**, possibly in combination with the memory **211**, may comprise means for identifying the one or more of the first subset of candidate AOAs as untrue AOAs.

[0055] At stage **750**, the method **700** includes determining a remaining candidate AOA of the first subset of candidate AOAs that has not been identified as an untrue AOA. The one or more processors **210**, possibly in combination with the memory **211**, may comprise means for determining the remaining candidate AOA of the first subset of candidate AOAs that has not been identified as an untrue AOA.

[0056] At stage **760**, the method **700** includes identifying the remaining candidate AOA as the true AOA. The one or more processors **210**, possibly in combination with the memory **211**, may comprise means for identifying the remaining candidate AOA as the true AOA.

[0057] For example, referring to FIG. 7, at stage **710**, for a first orientation of the UE **105**, a first wrapped PDOA ϕ may be measured. The first subset of candidate unwrapped PDOAs corresponding to the first wrapped PDOA ϕ may include $\{\Phi_{\text{sub.1}}, \dots, \Phi_{\text{sub.N}}\}$. At stage **720**, the first subset of candidate unwrapped PDOAs $\{\Phi_{\text{sub.1}}, \dots, \Phi_{\text{sub.N}}\}$ are used to compute a first subset of candidate AOA $\{\theta_{\text{sub.1}}, \dots, \theta_{\text{sub.N}}\}$ using Equation 2. The UE **105** may then be rotated at an angle of rotation t as measured by one or more of the sensors **213** of the UE **105** to a second orientation. At stage **710**, a second wrapped PDOA ϕ' may be measured. The second subset of candidate unwrapped PDOAs corresponding to the second wrapped PDOA ϕ' may include $\{\Phi'_{\text{sub.1}}, \dots, \Phi'_{\text{sub.N}}\}$. At stage **720**, the second subset of candidate unwrapped PDOAs $\{\Phi'_{\text{sub.1}}, \dots, \Phi'_{\text{sub.N}}\}$ are used to compute a second subset of candidate AOAs $\{\theta'_{\text{sub.1}}, \dots, \theta'_{\text{sub.N}}\}$ using Equation 2. At stage **730**, assuming that the AOA measurements meet an accuracy threshold, the divergences of one or more of the second subset of candidate AOAs $\{\theta'_{\text{sub.1}}, \dots, \theta'_{\text{sub.N}}\}$ from the first subset of candidate AOAs $\{\theta_{\text{sub.1}}, \dots, \theta_{\text{sub.N}}\}$ may be defined as $|\Delta\theta_{\text{sub.i}} - \tau|$, where $\Delta\theta_{\text{sub.i}} = \theta'_{\text{sub.i}} - \theta_{\text{sub.i}}$. At stage **720**, a candidate AOA (e.g., $\theta_{\text{sub.1}}$) in the first subset of candidate AOAs corresponding to the largest divergence (e.g., $|\Delta\theta_{\text{sub.1}} - \tau| > |\Delta\theta_{\text{sub.2}} - \tau|, \dots, |\Delta\theta_{\text{sub.1}} - \tau| > |\Delta\theta_{\text{sub.N}} - \tau|$) may be determined to be an untrue AOA. If one or more angle ambiguities remain in the first subset of candidate AOAs, then stages **730** and **740** may be repeated for one or more subsequent rotations of the UE **105** to identify more candidate AOAs as untrue AOAs, until, at stage **750**, one candidate AOA of the first subset of candidate AOAs remains that has not been identified as an untrue AOA. At stage **760**, the one remaining candidate AOA is identified as the true AOA. The true AOA may be used to determine the target direction $\{\text{right arrow over } (u^*)\}$ to the target object **102**.

[0058] With the method **700**, for any given L , a non-ambiguity range of angles may be calculated, such that a AOA within the non-ambiguity range of angles is the true AOA. The method **700** may leverage the non-ambiguity range of angles by prompting the user to rotate the UE **105** in a direction that may result in an AOA within the non-ambiguity range of angles. In this manner, the true AOA may be identified with fewer repetitions of stages **730** and **740**. The UE **105** may display one or more instructions to change the orientation of the UE **105** by rotating the UE **105** in one or more directions. For example, the target object **102** and the antennas **246**, **250** of the UE **105** may reside in a plane. For example, the UE **105** may display one or more instructions to rotate the UE **105** along an axis, while maintaining the target object **102** and the antennas **246**, **250** in the plane. For another example, the one or more instructions may include tilting the UE **105** in a first direction from the axis and then in a second and opposite direction from the axis (e.g., “shaking” the UE **105**).

[0059] In a second example implementation of the method **600**, identification of the true PDOA may be based on a projection of the plurality of unwrapped PDOAs onto a column space of a measurement matrix. FIGS. **8A-8C** are diagrams illustrating the projection of unwrapped PDOAs. Referring to FIGS. **8A** and **8B**, a linear transformation is performed on the unit vector $\{\text{right arrow over } (u)\}$ with the measurement matrix A (see Eq. 3) to obtain a vector of unwrapped PDOAs $\{\text{right arrow over } (\Phi)\}$, where $\{\text{right arrow over } (\Phi)\} = A \cdot \{\text{right arrow over } (u)\} \in C_{\text{sub.A}}$. $C_{\text{sub.A}}$ is the column space of A , i.e., the subspace spanned by the columns of the measurement matrix A . Referring to FIGS. **8B** and **8C**, a wrapping process due to $L \geq \lambda/2$ produces a vector of wrapped PDOA measurements $\{\text{right arrow over } (\phi)\}$. The second example implementation leverages the fact that, although $\{\text{right arrow over } (\Phi)\}$ has N components, $\{\text{right arrow over } (\phi)\}$ is

restricted to lie in a subspace of dimension three spanned by the columns of A . Because the wrapping is not a linear transformation, the wrapping will produce an output $\{\text{right arrow over } (\varphi)\}$, which is likely to be outside of $C.\text{sub}.A$. [0060] FIG. 9 is a flow diagram illustrating the second example implementation of the method 600. The method 900 is an example only and not limiting. The method 900 may be altered, e.g., by having one or more stages added, removed, rearranged, combined, performed concurrently, and/or by having one or more single stages split into multiple stages. [0061] At stage 910, the method 900 includes measuring a wrapped PDOA vector for a signal transmitted by a target object 102 and received by at least a first antenna 246 and a second antenna 250 of the UE 105, where the wrapped PDOA vector corresponds to a plurality of orientations of the UE 105, where a separation distance between the first antenna 246 and the second antenna 250 is greater than or equal to half of the wavelength of the signal. The one or more processors 210, possibly in combination with the memory 211, may comprise means for measuring the wrapped PDOA vector for a signal transmitted by a target object 102 and received by at least a first antenna 246 and a second antenna 250 of the UE 105. The method 900 may be applied to UE's with three or more antennas with separation distances L between each pair of two antennas being greater than or equal to $\lambda/2$.

[0062] At stage 920, the method 90 includes generating a plurality of candidate unwrapped PDOA vectors based on the measured wrapped PDOA vector. The one or more processors 210, possibly in combination with the memory 211, may comprise means for generating a plurality of candidate unwrapped PDOA vectors based on the measured wrapped PDOA vector.

[0063] At stage 930, the method 900 includes generating a plurality of projections onto a subspace formed by a column space of a measurement matrix for the plurality of candidate unwrapped PDOA vectors. The one or more processors 210, possibly in combination with the memory 211, may comprise means for generating a plurality of projections onto a subspace formed by a column space of a measurement matrix for the plurality of candidate unwrapped PDOA vectors. For example, referring to FIG. 10, consider a full vector of wrapped PDOAs $\{\text{right arrow over } (\varphi)\}$ 1004 (e.g., $\varphi.\text{sub}.1, \varphi.\text{sub}.2, \dots, \varphi.\text{sub}.N$ each corresponding to an orientation of the UE 105) corresponding a vector $\{\text{right arrow over } (\Phi)\}$ 1002. Assume that each component of the vector of wrapped PDOA $\{\text{right arrow over } (\varphi)\}$ may be unwrapped into $m.\text{sub}.i$ possible angles 1006 ($\beta.\text{sub}.i.1, \dots, \beta.\text{sub}.i.m.\text{sub}.i$). Referring to FIG. 11A, a set of candidate unwrapped PDOA vectors $\{\text{right arrow over } (\beta.\text{sub}.k)\}$ 1008 may be built with the combinations of values for the components of the vector $\{\text{right arrow over } (\varphi)\}$. Given N components, where each component may have $m.\text{sub}.i$ values, M different candidate unwrapped PDOA vectors 1008 may be produced, where $M = \prod_{i=1}^N m.\text{sub}.i$. For $\{\text{right arrow over } (\beta.\text{sub}.k)\}$, where $k \in \{1, \dots, M\}$, one of the candidate unwrapped PDOA, $\{\text{right arrow over } (\beta.\text{sub}.k)\}$, will match the true PDOA.

[0064] To identify the true PDOA $\{\text{right arrow over } (\Phi)\}$, the method 900 leverages the fact that a physically valid PDOA vector $\{\text{right arrow over } (\Phi)\}$ must lie in the subspace $C.\text{sub}.A$. The candidate unwrapped PDOA vectors $\{\text{right arrow over } (\beta.\text{sub}.k)\}$ that do not correspond to the true PDOA $\{\text{right arrow over } (\Phi)\}$ will be the result of adding integer multiples of 2π to the components of the true PDOA $\{\text{right arrow over } (\Phi)\}$ and will likely be outside of subspace $C.\text{sub}.A$. For example, referring to FIG. 11B, building on the projection of the PDOA vector $\{\text{right arrow over } (\Phi)\}$ (shown in FIG. 8C), the method 900 generates $\{\text{right arrow over } (\beta.\text{sub}.k)\}$.

[0065] At stage 920, the method 900 includes determining a plurality of distances between the plurality of candidate unwrapped PDOAs and the corresponding plurality of projections onto the subspace. The one or more processors 210, possibly in combination with the memory 211, may comprise means for determining a plurality of distances between the plurality of candidate unwrapped PDOAs and the corresponding plurality of projections onto the subspace. For example, referring to FIG. 11B, each $\{\text{right arrow over } (\beta.\text{sub}.k)\}$ may be projected onto the subspace $C.\text{sub}.A$ to obtain $\{\text{right arrow over } (\gamma.\text{sub}.k)\}$, using the projection equation:

$$[00007] \quad \overset{\text{.fwdarw.}}{k} = A(A^T A)^{-1} A^T \overset{\text{.fwdarw.}}{k} \quad (\text{Eq. 7})$$

A plurality of distances between $\{\text{right arrow over } (\beta.\text{sub}.k)\}$ and $\{\text{right arrow over } (\gamma.\text{sub}.k)\}$ (i.e., $\|\{\text{right arrow over } (\beta.\text{sub}.k)\} - \{\text{right arrow over } (\gamma.\text{sub}.k)\}\|$) may be determined.

[0066] At stage 950, the method 900 includes identifying the candidate unwrapped PDOA vectors of the plurality of candidate unwrapped PDOA vectors corresponding to a smallest distance of the plurality of distances as the true PDOA vector. The one or more processors 210, possibly in combination with the memory 211, may comprise means for identifying the candidate unwrapped PDOA vector of the plurality of candidate unwrapped PDOA vectors corresponding to a smallest distance of the plurality of distances as the true PDOA vector. For example, referring to FIG. 11B, a candidate $\{\text{right arrow over } (\beta.\text{sub}.b)\}$ closest to its corresponding projection $\{\text{right arrow over } (\gamma.\text{sub}.b)\}$ (e.g., $\{\text{right arrow over } (\beta.\text{sub}.6)\}$ and its corresponding projection $\{\text{right arrow over } (\gamma.\text{sub}.6)\}$) is identified as the true PDOA $\{\text{right arrow over } (\Phi)\}$ vector. Referring to FIG. 11C, the target direction to the target object 102 may then be determined using $\{\text{right arrow over } (u^*)\} = A.\text{sup.}+. \text{Math.}\{\text{right arrow over } (\gamma.\text{sub}.b)\}$.

[0067] A third example implementation of identifying the true PDOA includes a variation of the method 900. In the third example implementation, the comparison of the plurality of candidate unwrapped PDOA vectors may be based on a projection of the unwrapped PDOA vectors on an ellipsoid residing in the column space of a measurement matrix. The third example implementation leverages the fact that $\{\text{right arrow over } (u)\} \in S.\text{sub}.1.\text{sup}.3$ (S is a sphere of unit radius in a 3-dimensional space $R.\text{sub}.3$) and thus, $\{\text{right arrow over } (\Phi)\} = A.\text{Math.}\{\text{right arrow over } (u)\}$ lies on the ellipsoid given by $E.\text{sub}.A = A.\text{Math.}S.\text{sub}.1.\text{sup}.3$ (the ellipsoid in $R.\text{sub}.N$ formed by the linear transformation of all points in $S.\text{sub}.1.\text{sup}.3$ using matrix A).

[0068] FIG. 12 is a flow diagram illustrating the third example implementation of the method 600. The method 1200 is an

example only and not limiting. The method **1200** may be altered, e.g., by having one or more stages added, removed, rearranged, combined, performed concurrently, and/or by having one or more single stages split into multiple stages. [0069] At stage **1210**, the method **1200** includes measuring a wrapped PDOA vector for a signal transmitted by a target object **102** and received by at least a first antenna **246** and a second antenna **250** of the UE **105**, where the wrapped PDOA vector corresponds to a plurality of orientations of the UE **105**, where a separation distance between the first antenna **246** and the second antenna **250** is greater than or equal to half of the wavelength of the signal. The one or more processors **210**, possibly in combination with the memory **211**, may comprise means for measuring a wrapped PDOA vector for a signal transmitted by a target object **102** and received by at least a first antenna **246** and a second antenna **250** of the UE **105**. [0070] At stage **1220**, the method **1200** includes generating a plurality of candidate unwrapped PDOA vectors based on the measured wrapped PDOA vector. The one or more processors **210**, possibly in combination with the memory **211**, may comprise means for generating a plurality of candidate unwrapped PDOA vectors based on the measured wrapped PDOA vector.

[0071] At stage **1230**, the method **1200** includes generating a plurality of projections onto an ellipsoid residing in the subspace formed by a column space of the measurement matrix for the plurality of candidate unwrapped PDOA vectors. The one or more processors **210**, possibly in combination with the memory **211**, may comprise means for generating the plurality of projections onto the ellipsoid residing in the subspace formed by a column space of the measurement matrix for the plurality of candidate unwrapped PDOA vectors. The ellipsoid may result from applying the measurement matrix to a unit sphere in three dimensional space.

[0072] At stage **1240**, the method **1200** includes determining a plurality of distances between the plurality of candidate unwrapped PDOA vectors and the corresponding plurality of projections onto the ellipsoid. The one or more processors **210**, possibly in combination with the memory **211**, may comprise means for determining the plurality of distances between the plurality of candidate unwrapped PDOA vectors and the corresponding plurality of projections onto the ellipsoid.

[0073] At stage **1250**, the method **1200** includes identifying the candidate unwrapped PDOA vector of the plurality of candidate unwrapped PDOA vectors corresponding to a smallest distance of the plurality of distances as the true PDOA vector. The one or more processors **210**, possibly in combination with the memory **211**, may comprise means for identifying the candidate unwrapped PDOA vector of the plurality of candidate PDOA vectors corresponding to the smallest distance of the plurality of distances as the true PDOA vector.

[0074] For example, referring to FIG. **13**, the projection of $\{\text{right arrow over } (\beta.\text{sub.k})\}$ onto an ellipsoid E.sub.A is given by $\{\text{right arrow over } (\eta.\text{sub.k})\}$. A list of M candidate unwrapped PDOA vectors $\{\{\text{right arrow over } (\beta.\text{sub.k})\}\}$ may be generated, in the same manner as above with reference to method **900**. At stage **1210**, each $\{\text{right arrow over } (\beta.\text{sub.k})\}$ is projected onto the ellipsoid E.sub.A using projection function $\mu.\text{sub.A}(\cdot)$ to obtain $\{\{\text{right arrow over } (\eta.\text{sub.k})\}\}$:

$$[00008] \quad \text{.fwdarw.}_k = \text{A} \left(\text{.fwdarw.}_k \right) \quad (\text{Eq. 8})$$

At stage **1220**, the distance between each $\{\text{right arrow over } (\beta.\text{sub.k})\}$ and its corresponding projection may be calculated:

$$[00009] \quad k = \text{.Math.}_k - \text{.fwdarw.}_k \cdot \text{.Math.}_k \quad (\text{Eq. 9})$$

At stage **1230**, the k with the lowest distance $\epsilon.\text{sub.k}$, i.e., the candidate $\{\text{right arrow over } (\beta.\text{sub.k})\}$ closest to the ellipsoid E.sub.A, may be selected. The original $\{\text{right arrow over } (u)\}$ may be obtained based on a pseudoinverse A^+ :

$$[00010] \quad k_o = \text{argmin}_k \{ k \} \quad (\text{Eq. 10}) \quad \text{.fwdarw.}_k^* = A^+ \cdot \text{.fwdarw.}_k \quad (\text{Eq. 11})$$

Referring to FIG. **14**, the projection of $\{\text{right arrow over } (\beta.\text{sub.k})\}$ onto the subspace C.sub.A is given by $\{\text{right arrow over } (\gamma.\text{sub.k})\}$. The error vector $\epsilon.\text{sub.k} = \{\text{right arrow over } (\gamma.\text{sub.k})\} - \{\text{right arrow over } (\eta.\text{sub.k})\}$ is in subspace C.sub.A, while the error vector $\epsilon.\text{sub.k.sup.}\perp = \{\text{right arrow over } (\beta.\text{sub.k})\} - \{\text{right arrow over } (\beta.\text{sub.k})\}$ is orthogonal to subspace C.sub.A. Thus, $\epsilon.\text{sub.k.sup.}\perp$ and $\epsilon.\text{sub.k}$ are orthogonal to each other. By applying the Pythagorean theorem, the distance between $\{\text{right arrow over } (\beta.\text{sub.k})\}$ and its corresponding projection $\{\text{right arrow over } (\eta.\text{sub.k})\}$ onto the ellipsoid E.sub.A is:

$$[00011] \quad \text{.Math.}_k \cdot \text{.Math.}_k = \text{.Math.}_k^2 - \text{.fwdarw.}_k^2 \cdot \text{.Math.}_k^2 = \sqrt{\text{.Math.}_k^2 - \text{.fwdarw.}_k^2}^2 + \text{.Math.}_k^2 - \text{.fwdarw.}_k^2 \cdot \text{.Math.}_k^2 \quad (\text{Eq. 12})$$

[0075] The computing resources required to obtain the distance $\epsilon.\text{sub.k}$ may be computationally expensive. In a fourth example implementation of identifying the true PDOA vector, a variation of the method **1200** avoids the requirement to compute the distance $\|\epsilon.\text{sub.k}\|$ for each $\{\text{right arrow over } (\beta.\text{sub.k})\}$. FIG. **15** is a flow diagram illustrating the fourth example implementation of the method **600**. The method **1500** is an example only and not limiting. The method **1500** may be altered, e.g., by having one or more stages added, removed, rearranged, combined, performed concurrently, and/or by having one or more single stages split into multiple stages.

[0076] At stage **1510**, the method includes determining a set of candidate unwrapped PDOA vectors corresponding to one or more wrapped PDOA vectors. The set of candidate unwrapped PDOA vectors may include the plurality of candidate unwrapped PDOA vectors referenced in FIG. **10**. The one or more processors **210**, possibly in combination with the memory **211**, may comprise means for determining the set of candidate unwrapped PDOAs.

[0077] At stage **1512**, the method **1500** includes generating a plurality of projections onto a subspace of a measurement matrix for the set of candidate unwrapped PDOA vectors. The one or more processors **210**, possibly in combination with the memory **211**, may comprise means for generating the plurality of projections onto the subspace of the measurement matrix for the set of candidate unwrapped PDOA vectors.

[0078] At stage **1514**, the method **1500** includes determining a plurality of first distances between the set of candidate unwrapped PDOA vectors and the corresponding plurality of projections onto the subspace. The one or more processors **210**, possibly in combination with the memory **211**, may comprise means for determining the plurality of first distances between the set of candidate unwrapped PDOA vectors and the corresponding plurality of projections onto the subspace.

[0079] At stage **1516**, the method **1500** includes selecting a first candidate unwrapped PDOA vector in the set of candidate unwrapped PDOA vectors corresponding to a smallest first distance as a current best candidate. The one or more processors **210**, possibly in combination with the memory **211**, may comprise means for selecting a first candidate unwrapped PDOA vector in the set of candidate unwrapped PDOA vectors corresponding to a smallest first distance as a current best candidate.

[0080] At stage **1518**, the method **1500** includes computing a second distance to an ellipsoid residing within the subspace for the current best candidate. The one or more processors **210**, possibly in combination with the memory **211**, may comprise means for computing a second distance to an ellipsoid residing within the subspace for the current best candidate. The ellipsoid may result from applying the measurement matrix to a unit sphere in three dimensional space.

[0081] At stage **1520**, the method **1500** includes removing the current best candidate from the set of candidate unwrapped PDOA vectors. The one or more processors **210**, possibly in combination with the memory **211**, may comprise means for removing the current best candidate from the set of candidate unwrapped PDOA vectors.

[0082] At stage **1522**, the method **1500** includes determining whether the set of candidate unwrapped PDOA vectors is empty. The one or more processors **210**, possibly in combination with the memory **211**, may comprise means for determining whether the set of candidate unwrapped PDOA vectors is empty.

[0083] At stage **1524**, if the set is not empty, the method **1500** includes removing one or more candidate unwrapped PDOA vectors in the set of candidate unwrapped PDOA vectors that correspond to one or more first distances larger than the second distance. The one or more processors **210**, possibly in combination with the memory **211**, may comprise means for, removing one or more candidate unwrapped PDOAs in the set of candidate unwrapped PDOA vectors that correspond to one or more first distances larger than the second distance. By removing candidate unwrapped PDOAs with first distances larger than the second distance, the computing of the projections to the ellipsoid is avoided for the removed candidates. The projections onto the subspace are thus used to filter out candidates in the set of unwrapped PDOA vectors that are less likely than the current best candidate to be the true PDOA vector.

[0084] At stage **1526**, the method **1500** includes determining whether the set of candidate unwrapped PDOA vectors is empty. The one or more processors **210**, possibly in combination with the memory **211**, may comprise means for determining whether the set of candidate unwrapped PDOA vectors is empty.

[0085] At stage **1528**, if the set is not empty, the method **1500** includes identifying a second candidate unwrapped PDOA vector in the set of candidate unwrapped PDOA vectors with the smallest first distance. The one or more processors **210**, possibly in combination with the memory **211**, may comprise means for identifying a second candidate unwrapped PDOA vector in the set of candidate unwrapped PDOA vectors with the smallest first distance.

[0086] At stage **1530**, the method **1500** includes removing the second candidate from the set of candidate unwrapped PDOA vectors. The one or more processors **210**, possibly in combination with the memory **211**, may comprise means for removing the second candidate from the set of candidate unwrapped PDOA vectors.

[0087] At stage **1532**, the method **1500** includes computing a third distance to the ellipsoid for the second candidate unwrapped PDOA vector. The one or more processors **210**, possibly in combination with the memory **211**, may comprise means for computing a third distance to the ellipsoid for the second candidate unwrapped PDOA vector.

[0088] At stage **1534**, the method **1500** includes determining whether the third distance is smaller than the second distance. The one or more processors **210**, possibly in combination with the memory **211**, may comprise means for determining whether the third distance is smaller than the second distance.

[0089] At stage **1536**, if the third distance is smaller than the second distance, then the method **1500** includes setting the second candidate unwrapped PDOA vector as the current best candidate. The one or more processors **210**, possibly in combination with the memory **211**, may comprise means for setting the second candidate unwrapped PDOA vector as the current best candidate. If the third distance is not smaller than the second distance, the first candidate remains the current best candidate.

[0090] After stages **1534** and **1536**, the method **1500** repeats stages **1522** through **1536** until the set of unwrapped candidate PDOA vectors is determined to be empty.

[0091] At stage **1538**, when the set of candidate unwrapped PDOA vectors is empty, the method **1500** includes returning the current best candidate as the true PDOA vector. The one or more processors **210**, possibly in combination with the memory **211**, may comprise means for returning the current best candidate as the true PDOA vector.

[0092] For example, referring again to FIG. 14, at stage **1510**, for a set of unwrapped PDOAs, $G = \{\{\overrightarrow{\beta_{\text{sub}.1}}\}, \dots, \{\overrightarrow{\beta_{\text{sub}.M}}\}\}$, a set of indices, $M := \{1, \dots, M\}$, for the set G may be built. At stage **1512**, projections $\{\{\overrightarrow{\gamma_{\text{sub}.1}}\}, \dots, \{\overrightarrow{\gamma_{\text{sub}.M}}\}\}$ onto the subspace $C_{\text{sub}.A}$ for the set G may be generated. At stage **1514**, the distances between the set G and the corresponding projections $\{\{\overrightarrow{\gamma_{\text{sub}.1}}\}\}, \dots, \{\overrightarrow{\gamma_{\text{sub}.M}}\}\}$ may be computed:

$$[00012] \quad \frac{1}{k} = \text{Math.} \overset{\text{.fwdarw.}}{k} - \overset{\text{.fwdarw.}}{k} \text{Math. forall } k \in M \quad (\text{Eq. 13})$$

[0093] At stage **1516**, the shortest distance to the subspace $C_{\text{sub}.A}$ may be selected as the current best candidate. Assume that index b is determined to be $b = \text{argmin}_{\text{sub}.k \in M} \{\epsilon_{\text{sub}.k.\text{sup.}} \perp\}$. At stage **1518**, the distance to the ellipsoid $E_{\text{sub}.A}$ may be computed for the candidate corresponding to index b :

$$[00013] \quad b = \text{Math}.\overset{\text{.fwdarw.}}{b} - \text{Math}.\overset{\text{.fwdarw.}}{b} \quad (\text{Eq. 14})$$

[0094] At stage **1520**, the index b is then removed from M . At stages **1522** and **1524**, if M is not empty, any other candidates corresponding to distances to the subspace $C.\text{sub}.A$ that is larger than the distance for the candidate corresponding to index b may be removed from M , i.e., k is removed from M if $\epsilon.\text{sub}.k.\text{sup}.\perp \geq \epsilon.\text{sub}.b$.

[0095] At stages **1526** and **1528**, if M is not empty, from the remaining candidates in M , the candidate with the lowest $\epsilon.\text{sub}.k.\text{sup}.\perp$ may be identified. Assume that this candidate has index c . At stage **1530**, index c may be removed from M .

[0096] At stage **1532**, the distance to the ellipsoid for the candidate corresponding to index c may be computed:

$$[00014] \quad c = \text{Math}.\overset{\text{.fwdarw.}}{c} - \text{Math}.\overset{\text{.fwdarw.}}{c} \quad (\text{Eq. 15})$$

[0097] At stages **1534** and **1536**, if $\epsilon.\text{sub}.c < \epsilon.\text{sub}.b$, then $b := c$. Stages **1522** through **1536** may be repeated until M is empty. At stage **1538**, once M is empty, $\{\text{right arrow over } (\beta.\text{sub}.b)\}$ is returned as the candidate closest to the ellipsoid $E.\text{sub}.A$, and $\{\text{right arrow over } (\eta.\text{sub}.b)\}$ is returned as its corresponding projection onto the ellipsoid $E.\text{sub}.A$. In this manner, the number of candidates for which the distance to the ellipsoid $E.\text{sub}.A$ is computed may be reduced, saving computing resources.

[0098] The true PDOA vector identified based on the methods above may be used to determine a location of the target object **102** by the UE **105**. The method for determining the location of the target object **102** may use a phase delay in combination with other values (e.g., a corresponding position of the UE **105**, an orientation of the UE **105**, and a distance between the position of the UE **105** and the target object **102**). The method may determine the location of the target object **102** by building a loss function using the combination of values, accepting candidate positions of the target object **102** into the loss function, obtaining an output value for the loss function, and finding a candidate position for the target object **102** that produces the lowest output value for the loss function (i.e., minimizing the loss function). For example, a gradient descent method may be used to minimize the loss function. An initial estimate of the location of the target object **102** may be determined using the true PDOA vector. This initial estimate may be used as an initial location in the gradient descent, which may reduce the number of iterations in the gradient descent method to find the lowest output value for the loss function, which in turn saves computing resources. Further, when the loss function includes a global minimum and several local minima, by using the initial estimate determined based on the true PDOA vector, the possibility of converging at a local minimum instead of the global minimum may be reduced.

[0099] FIG. **16** illustrates an example user experience in locating the target object **102**. In this example, the UE **105** is a mobile device with one or more processors (e.g., the processor(s) **210**) executing an application (e.g., the software **212**) stored in one or more memories (e.g., the memories **211**). A user of the UE **105** executes the application, and the application displays an image **1610**, on the user interface of the UE **105**, that provides a list of items that support wireless ranging signals. The user selects one of the items as the target object **102**. In response to receiving the selection of the target object **102**, the application executing on the UE **105** causes a communication link between the transceivers of the UE **105** and the target object **102** to be established (e.g., between the transceivers **240**, **320**). The application displays an image **1620** on the user interface with instructions for the user to rotate the UE **105** in order to change the orientation of the UE **105**. Optionally, the user interface may instruct the user to rotate the UE **105** in a direction most likely to result in a PDOA within the non-ambiguity range of angles. As the UE **105** changes orientations, the application executes the method **600** as described above and calculates the position of the target object **102**. The application causes directional information to be displayed on the user interface as an image **1630** based on the position of the target object **102** and the orientation of the UE **105**. As the user continues to change orientations of the UE **105**, the position of the target object **102** is updated. The application displays updated directional information in an image **1640** based on the updated position of the target object **102** and an updated orientation of the UE **105**.

Implementation Examples

[0100] Clause 1. A method for determining a true phase difference of arrival (PDOA), comprising: determining a plurality of candidate unwrapped PDOAs for a signal transmitted by a target object and received by at least a first antenna and a second antenna of a user equipment (UE), wherein the plurality of candidate unwrapped PDOAs corresponds to a plurality of orientations of the UE, wherein a separation distance between the first antenna and the second antenna is greater than or equal to half of a wavelength of the signal; comparing the plurality of unwrapped candidate PDOAs; and identifying the true PDOA based on the comparison.

[0101] Clause 2. The method of claim **1**, wherein the plurality of candidate unwrapped PDOAs comprises a first subset of unwrapped PDOAs corresponding to a first wrapped PDOA and a second subset of unwrapped PDOAs corresponding to a second wrapped PDOA, wherein the first wrapped PDOA corresponds to a first orientation of the UE and the second wrapped PDOA corresponds to a second orientation of the UE, wherein the comparing of the plurality of unwrapped candidate PDOAs, comprises: determining a first subset of candidate angle of arrivals (AOAs) corresponding to the first subset of candidate unwrapped PDOAs and a second subset of candidate AOAs corresponding to the second subset of candidate unwrapped PDOAs; determining a plurality of divergences between the second subset of candidate AOAs and the corresponding first subset of candidate AOAs; identifying one or more of the first subset of candidate AOAs as untrue AOAs based on the plurality of divergences; determining a remaining candidate AOA of the first subset of candidate AOAs that has not been identified as an untrue AOA; and identifying the remaining candidate AOA as a true AOA.

[0102] Clause 3. The method of clause 2, further comprising: displaying one or more user instructions to change an orientation of the UE by rotating the UE in one or more directions.

[0103] Clause 4. The method of clause 3, wherein the one or more user instructions comprise one or more user instructions

to rotate the UE along an axis while maintaining the target object and at least the first antenna and the second antenna in a plane.

[0104] Clause 5. The method of clause 3, wherein the one or more user instructions comprise one or more user instructions to tilt the UE in a first direction from an axis and in a second direction from the axis.

[0105] Clause 6. The method of clause 1, wherein the determining of the plurality of candidate unwrapped PDOAs for the signal, the comparing of the plurality of unwrapped candidate PDOAs, and the identifying of the true PDOA based on the comparison, comprise: measuring a wrapped PDOA vector for the signal, wherein the wrapped PDOA corresponds to the plurality of orientations of the UE; generating a plurality of candidate unwrapped PDOA vectors based on the measured wrapped PDOA vector; generating a plurality of projections onto a subspace formed by a column space of a measurement matrix for the plurality of candidate unwrapped PDOA vectors; determining a plurality of distances between the plurality of candidate unwrapped PDOA vectors and the corresponding plurality of projections onto the subspace; and identifying the candidate unwrapped PDOA vector of the plurality of candidate unwrapped PDOA vectors corresponding to a smallest distance of the plurality of distances as a true PDOA vector.

[0106] Clause 7. The method of clause 6, wherein the generating of the plurality of projections onto the subspace and the determining of the plurality of distances between the plurality of candidate unwrapped PDOA vectors and the corresponding plurality of projections onto the subspace, comprise: generating the plurality of projections onto an ellipsoid residing in the subspace formed by the column space of the measurement matrix for the plurality of candidate unwrapped PDOA vectors, wherein the ellipsoid results from applying the measurement matrix to a unit sphere in a three dimensional space; and determining the plurality of distances between the plurality of candidate unwrapped PDOA vectors and the corresponding plurality of projections onto the ellipsoid.

[0107] Clause 8. The method of clause 6, wherein a set of candidate unwrapped PDOA vectors comprises the plurality of candidate unwrapped PDOA vectors, wherein the plurality of distances comprises a plurality of first distances between the set of candidate unwrapped PDOA vectors and the corresponding plurality of projections onto the subspace, wherein the identifying of the true PDOA vector comprises: selecting a first candidate unwrapped PDOA vector in the set of candidate unwrapped PDOA vectors corresponding to a smallest first distance as a current best candidate; computing a second distance to an ellipsoid residing within the subspace for the current best candidate, wherein the ellipsoid results from applying the measurement matrix to a unit sphere in a three dimensional space; and removing the current best candidate from the set of candidate unwrapped PDOA vectors.

[0108] Clause 9. The method of clause 8, wherein if the set of candidate unwrapped PDOA vectors is not empty, the identifying of the true PDOA vector further comprises: removing one or more candidate unwrapped PDOA vectors in the set of candidate unwrapped PDOA vectors that correspond to one or more first distances larger than the second distance; and if the set of candidate unwrapped PDOA vectors is not empty, identifying a second candidate unwrapped PDOA vector in the set of candidate unwrapped PDOA vectors with the smallest first distance; removing the second candidate unwrapped PDOA vector from the set of candidate unwrapped PDOA vectors; computing a third distance to the ellipsoid for the second candidate unwrapped PDOA vector; determining whether the third distance is less than the second distance; and setting the second candidate unwrapped PDOA vector as the current best candidate if the third distance is less than the second distance.

[0109] Clause 10. The method of clause 9, wherein if the set of candidate unwrapped PDOA vectors is empty, returning the current best candidate as the true PDOA vector.

[0110] Clause 11. The method of clause 1, further comprising: calculating a direction between the UE and the target object based on the true PDOA.

[0111] Clause 12. The method of clause 1, further comprising: determining the plurality of orientations of the UE based on one or more measurements from one or more sensors of the UE.

[0112] Clause 13. A user equipment (UE), comprising: a first antenna; a second antenna; one or more memories; and one or more processors communicatively coupled to the one or more memories, the one or more processors being configured to: determine a plurality of candidate unwrapped phase difference of arrivals (PDOAs) for a signal transmitted by a target object and received by at least the first antenna and the second antenna, wherein the plurality of candidate unwrapped PDOAs corresponds to a plurality of orientations of the UE, wherein a separation distance between the first antenna and the second antenna is greater than or equal to half of a wavelength of the signal; compare the plurality of unwrapped candidate PDOAs; and identify a true PDOA based on the comparison.

[0113] Clause 14. The UE of clause 13, wherein the plurality of candidate unwrapped PDOAs comprises a first subset of unwrapped PDOAs corresponding to a first wrapped PDOA and a second subset of unwrapped PDOAs corresponding to a second wrapped PDOA, wherein the first wrapped PDOA corresponds to a first orientation of the UE and the second wrapped PDOA corresponds to a second orientation of the UE, wherein the one or more processors configured to compare the plurality of unwrapped candidate PDOAs being further configured to: determine a first subset of candidate angle of arrivals (AOAs) corresponding to the first subset of candidate unwrapped PDOAs and a second subset of candidate AOAs corresponding to the second subset of candidate unwrapped PDOAs; determine a plurality of divergences between the second subset of candidate AOAs and the corresponding first subset of candidate AOAs; identify one or more of the first subset of candidate AOAs as untrue AOAs based on the plurality of divergences; determine a remaining candidate AOA of the first subset of candidate AOAs that has not been identified as an untrue AOA; and identify the remaining candidate AOA as a true AOA.

[0114] Clause 15. The UE of clause 14, wherein the one or more processors being further configured to: display one or more user instructions to change an orientation of the UE by rotating the UE in one or more directions.

[0115] Clause 16. The UE of clause 15, wherein the one or more user instructions comprise one or more user instructions to

rotate the UE along an axis while maintaining the target object and at least the first antenna and the second antenna in a plane.

[0116] Clause 17. The UE of clause 15, wherein the one or more user instructions comprise one or more user instructions to tilt the UE in a first direction from an axis and in a second direction from the axis.

[0117] Clause 18. The UE of clause 13, wherein the one or more processors configured to determine the plurality of candidate unwrapped PDOAs for the signal, compare the plurality of unwrapped candidate PDOAs, and identify the true PDOA based on the comparison, being further configured to: measure a wrapped PDOA vector for the signal, wherein the wrapped PDOA corresponds to the plurality of orientations of the UE; generate a plurality of candidate unwrapped PDOA vectors based on the measured wrapped PDOA vector; generate a plurality of projections onto a subspace formed by a column space of a measurement matrix for the plurality of candidate unwrapped PDOA vectors; determine a plurality of distances between the plurality of candidate unwrapped PDOA vectors and the corresponding plurality of projections onto the subspace; and identify the candidate unwrapped PDOA vector of the plurality of candidate unwrapped PDOA vectors corresponding to a smallest distance of the plurality of distances as a true PDOA vector.

[0118] Clause 19. The UE of clause 18, wherein the one or more processors configured to generate the plurality of projections onto the subspace and determine the plurality of distances between the plurality of candidate unwrapped PDOA vectors and the corresponding plurality of projections onto the subspace, being further configured to: generate the plurality of projections onto an ellipsoid residing in the subspace formed by the column space of the measurement matrix for the plurality of candidate unwrapped PDOA vectors, wherein the ellipsoid results from applying the measurement matrix to a unit sphere in a three dimensional space; and determine the plurality of distances between the plurality of candidate unwrapped PDOA vectors and the corresponding plurality of projections onto the ellipsoid.

[0119] Clause 20. The UE of clause 18, wherein a set of candidate unwrapped PDOA vectors comprises the plurality of candidate unwrapped PDOA vectors, wherein the plurality of distances comprises a plurality of first distances between the set of candidate unwrapped PDOA vectors and the corresponding plurality of projections onto the subspace, wherein the one or more processors configured to identify the true PDOA vector being further configured to: select a first candidate unwrapped PDOA vector in the set of candidate unwrapped PDOA vectors corresponding to a smallest first distance as a current best candidate; compute a second distance to an ellipsoid residing within the subspace for the current best candidate, wherein the ellipsoid results from applying the measurement matrix to a unit sphere in a three dimensional space; and remove the current best candidate from the set of candidate unwrapped PDOA vectors.

[0120] Clause 21. The UE of clause 20, wherein if the set of candidate unwrapped PDOA vectors is not empty, the one or more processors configured to identify the true PDOA vector being further to: remove one or more candidate unwrapped PDOA vectors in the set of candidate unwrapped PDOA vectors that correspond to one or more first distances larger than the second distance; and if the set of candidate unwrapped PDOA vectors is not empty, identify a second candidate unwrapped PDOA vector in the set of candidate unwrapped PDOA vectors with the smallest first distance; remove the second candidate unwrapped PDOA vector from the set of candidate unwrapped PDOA vectors; compute a third distance to the ellipsoid for the second candidate unwrapped PDOA vector; determine whether the third distance is less than the second distance; and set the second candidate unwrapped PDOA vector as the current best candidate if the third distance is less than the second distance.

[0121] Clause 22. The UE of clause 20, wherein if the set of candidate unwrapped PDOA vectors is empty, the one or more processors being further configured to: return the current best candidate as the true PDOA vector.

[0122] Clause 23. The UE of clause 13, wherein the one or more processors being further configured to: calculate a direction between the UE and the target object based on the true PDOA.

[0123] Clause 24. The UE of clause 13, wherein the one or more processors being further configured to: determine the plurality of orientations of the UE based on one or more measurements from one or more sensors of the UE.

[0124] Clause 25. A non-transitory, processor-readable storage medium comprising processor-readable instructions to cause one or more processors to: determine a plurality of candidate unwrapped phase difference of arrivals (PDOAs) for a signal transmitted by a target object and received by at least a first antenna and a second antenna of a user equipment (UE), wherein the plurality of candidate unwrapped PDOAs corresponds to a plurality of orientations of the UE, wherein a separation distance between the first antenna and the second antenna is greater than or equal to half of a wavelength of the signal; compare the plurality of unwrapped candidate PDOAs; and identify a true PDOA based on the comparison.

[0125] Clause 26. The medium of clause 25, wherein the plurality of candidate unwrapped PDOAs comprises a first subset of unwrapped PDOAs corresponding to a first wrapped PDOA and a second subset of unwrapped PDOAs corresponding to a second wrapped PDOA, wherein the first wrapped PDOA corresponds to a first orientation of the UE and the second wrapped PDOA corresponds to a second orientation of the UE, wherein the processor-readable instructions to cause the one or more processors to compare the plurality of unwrapped candidate PDOAs further comprise processor-readable instructions to cause the one or more processors to: determine a first subset of candidate angle of arrivals (AOAs) corresponding to the first subset of candidate unwrapped PDOAs and a second subset of candidate AOA corresponding to the second subset of candidate unwrapped PDOAs; determine a plurality of divergences between the second subset of candidate AOA and the corresponding first subset of candidate AOA; identify one or more of the first subset of candidate AOA as untrue AOA based on the plurality of divergences; determine a remaining candidate AOA of the first subset of candidate AOA that has not been identified as an untrue AOA; and identify the remaining candidate AOA as a true AOA.

[0126] Clause 27. The medium of clause 26, wherein the processor-readable instructions further cause the one or more processors to: display one or more user instructions to change an orientation of the UE by rotating the UE in one or more directions.

[0127] Clause 28. The medium of clause 27, wherein the one or more user instructions comprise one or more user instructions to rotate the UE along an axis while maintaining the target object and at least the first antenna and the second antenna in a plane.

[0128] Clause 29. The medium of clause 27, wherein the one or more user instructions comprise one or more user instructions to tilt the UE in a first direction from an axis and in a second direction from the axis.

[0129] Clause 30. The medium of clause 25, wherein the processor-readable instructions to cause the one or more processors to determine the plurality of candidate unwrapped PDOAs for the signal, compare the plurality of unwrapped candidate PDOAs, and identify the true PDOA based on the comparison, further comprise processor-readable instructions to cause the one or more processors to: measure a wrapped PDOA vector for the signal, wherein the wrapped PDOA corresponds to the plurality of orientations of the UE; generate a plurality of candidate unwrapped PDOA vectors based on the measured wrapped PDOA vector; generate a plurality of projections onto a subspace formed by a column space of a measurement matrix for the plurality of candidate unwrapped PDOA vectors; determine a plurality of distances between the plurality of candidate unwrapped PDOA vectors and the corresponding plurality of projections onto the subspace; and identify the candidate unwrapped PDOA vector of the plurality of candidate unwrapped PDOA vectors corresponding to a smallest distance of the plurality of distances as a true PDOA vector.

[0130] Clause 31. The medium of clause 30, wherein the processor-readable instructions to cause the one or more processors to generate the plurality of projections onto the subspace and determine the plurality of distances between the plurality of candidate unwrapped PDOA vectors and the corresponding plurality of projections onto the subspace, further comprise processor-readable instructions to cause the one or more processors to: generate the plurality of projections onto an ellipsoid residing in the subspace formed by the column space of the measurement matrix for the plurality of candidate unwrapped PDOA vectors, wherein the ellipsoid results from applying the measurement matrix to a unit sphere in a three dimensional space; and determine the plurality of distances between the plurality of candidate unwrapped PDOA vectors and the corresponding plurality of projections onto the ellipsoid.

[0131] Clause 32. The medium of clause 30, wherein a set of candidate unwrapped PDOA vectors comprises the plurality of candidate unwrapped PDOA vectors, wherein the plurality of distances comprises a plurality of first distances between the set of candidate unwrapped PDOA vectors and the corresponding plurality of projections onto the subspace, wherein the processor-readable instructions further comprise processor-readable instructions to cause the one or more processors to: select a first candidate unwrapped PDOA vector in the set of candidate unwrapped PDOA vectors corresponding to a smallest first distance as a current best candidate; compute a second distance to an ellipsoid residing within the subspace for the current best candidate, wherein the ellipsoid results from applying the measurement matrix to a unit sphere in a three dimensional space; and remove the current best candidate from the set of candidate unwrapped PDOA vectors.

[0132] Clause 33. The medium of clause 32, wherein if the set of candidate unwrapped PDOA vectors is not empty, the processor-readable instructions further comprise processor-readable instructions to cause the one or more processors to: remove one or more candidate unwrapped PDOA vectors in the set of candidate unwrapped PDOA vectors that correspond to one or more first distances larger than the second distance; and if the set of candidate unwrapped PDOA vectors is not empty, identify a second candidate unwrapped PDOA vector in the set of candidate unwrapped PDOA vectors with the smallest first distance; remove the second candidate unwrapped PDOA vector from the set of candidate unwrapped PDOA vectors; compute a third distance to the ellipsoid for the second candidate unwrapped PDOA vector; determine whether the third distance is less than the second distance; and set the second candidate unwrapped PDOA vector as the current best candidate if the third distance is less than the second distance.

[0133] Clause 34. The medium of clause 32, wherein if the set of candidate unwrapped PDOA vectors is empty, the processor-readable instructions further comprise processor-readable instructions to cause the one or more processors to: return the current best candidate as the true PDOA vector.

[0134] Clause 35. The medium of clause 25, wherein the processor-readable instructions further comprise processor-readable instructions to cause the one or more processors to: calculate a direction between the UE and the target object based on the true PDOA.

[0135] Clause 36. The medium of clause 25, wherein the processor-readable instructions further comprise processor-readable instructions to cause the one or more processors to: determine the plurality of orientations of the UE based on one or more measurements from one or more sensors of the UE.

[0136] Clause 37. A computing device, comprising: means for determining a plurality of candidate unwrapped phase difference of arrivals (PDOAs) for a signal transmitted by a target object and received by at least a first antenna and a second antenna of a user equipment (UE), wherein the plurality of candidate unwrapped PDOAs corresponds to a plurality of orientations of the UE, wherein a separation distance between the first antenna and the second antenna is greater than or equal to half of a wavelength of the signal; means for comparing the plurality of unwrapped candidate PDOAs; and means for identifying a true PDOA based on the comparison.

[0137] Clause 38. The device of clause 37, wherein the plurality of candidate unwrapped PDOAs comprises a first subset of unwrapped PDOAs corresponding to a first wrapped PDOA and a second subset of unwrapped PDOAs corresponding to a second wrapped PDOA, wherein the first wrapped PDOA corresponds to a first orientation of the UE and the second wrapped PDOA corresponds to a second orientation of the UE, wherein means for comparing the plurality of unwrapped candidate PDOAs, comprises: means for determining a first subset of candidate angle of arrivals (AOAs) corresponding to the first subset of candidate unwrapped PDOAs and a second subset of candidate AOA corresponding to the second subset of candidate unwrapped PDOAs; means for determining a plurality of divergences between the second subset of candidate AOA and the corresponding first subset of candidate AOA; means for identifying one or more of the first subset of

candidate AOA as untrue AOAs based on the plurality of divergences; means for determining a remaining candidate AOA of the first subset of candidate AOAs that has not been identified as an untrue AOA; and means for identifying the remaining candidate AOA as a true AOA.

[0138] Clause 39. The device of clause 38, further comprising: means for displaying one or more user instructions to change an orientation of the UE by rotating the UE in one or more directions.

[0139] Clause 40. The device of clause 39, wherein the one or more user instructions comprise one or more user instructions to rotate the UE along an axis while maintaining the target object and at least the first antenna and the second antenna in a plane.

[0140] Clause 41. The device of clause 39, wherein the one or more user instructions comprise one or more user instructions to tilt the UE in a first direction from an axis and in a second direction from the axis.

[0141] Clause 42. The device of clause 37, wherein the means for determining the plurality of candidate unwrapped PDOAs for the signal, comparing the plurality of unwrapped candidate PDOAs, and identifying the true PDOA based on the comparison, comprise: means for measuring a wrapped PDOA vector for the signal, wherein the wrapped PDOA corresponds to the plurality of orientations of the UE; means for generating a plurality of candidate unwrapped PDOA vectors based on the measured wrapped PDOA vector; means for generating a plurality of projections onto a subspace formed by a column space of a measurement matrix for the plurality of candidate unwrapped PDOA vectors; means for determining a plurality of distances between the plurality of candidate unwrapped PDOA vectors and the corresponding plurality of projections onto the subspace; and means for identifying the candidate unwrapped PDOA vector of the plurality of candidate unwrapped PDOA vectors corresponding to a smallest distance of the plurality of distances as a true PDOA vector.

[0142] Clause 43. The device of clause 42, wherein the means for generating the plurality of projections onto the subspace and means for determining the plurality of distances between the plurality of candidate unwrapped PDOA vectors and the corresponding plurality of projections onto the subspace, comprise: means for generating the plurality of projections onto an ellipsoid residing in the subspace formed by the column space of the measurement matrix for the plurality of candidate unwrapped PDOA vectors, wherein the ellipsoid results from applying the measurement matrix to a unit sphere in a three dimensional space; and means for determining the plurality of distances between the plurality of candidate unwrapped PDOA vectors and the corresponding plurality of projections onto the ellipsoid.

[0143] Clause 44. The device of clause 42, wherein a set of candidate unwrapped PDOA vectors comprises the plurality of candidate unwrapped PDOA vectors, wherein the plurality of distances comprises a plurality of first distances between the set of candidate unwrapped PDOA vectors and the corresponding plurality of projections onto the subspace, wherein the means for identifying the true PDOA vector comprises: means for selecting a first candidate unwrapped PDOA vector in the set of candidate unwrapped PDOA vectors corresponding to a smallest first distance as a current best candidate; means for computing a second distance to an ellipsoid residing within the subspace for the current best candidate, wherein the ellipsoid results from applying the measurement matrix to a unit sphere in a three dimensional space; and means for removing the current best candidate from the set of candidate unwrapped PDOA vectors.

[0144] Clause 45. The device of clause 44, wherein if the set of candidate unwrapped PDOA vectors is not empty, the means for identifying the true PDOA vector further comprises: means for removing one or more candidate unwrapped PDOA vectors in the set of candidate unwrapped PDOA vectors that correspond to one or more first distances larger than the second distance; and means for, if the set of candidate unwrapped PDOA vectors is not empty, means for identifying a second candidate unwrapped PDOA vector in the set of candidate unwrapped PDOA vectors with the smallest first distance; means for removing the second candidate unwrapped PDOA vector from the set of candidate unwrapped PDOA vectors; means for computing a third distance to the ellipsoid for the second candidate unwrapped PDOA vector; means for determining whether the third distance is less than the second distance; and means for setting the second candidate unwrapped PDOA vector as the current best candidate if the third distance is less than the second distance.

[0145] Clause 46. The device of clause 45, further comprising means for, if the set of candidate unwrapped PDOA vectors is empty, returning the current best candidate as the true PDOA vector.

[0146] Clause 47. The device of clause 37, further comprising: means for calculating a direction between the UE and the target object based on the true PDOA.

[0147] Clause 48. The device of clause 37, further comprising: means for determining the plurality of orientations of the UE based on one or more measurements from one or more sensors of the UE.

OTHER CONSIDERATIONS

[0148] Other examples and implementations are within the scope of the disclosure and appended claims. For example, due to the nature of software and computers, functions described above can be implemented using software executed by a processor, hardware, firmware, hardwiring, or a combination of any of these. Features implementing functions may also be physically located at various positions, including being distributed such that portions of functions are implemented at different physical locations.

[0149] As used herein, the singular forms “a,” “an,” and “the” include the plural forms as well, unless the context clearly indicates otherwise. Thus, reference to a device in the singular (e.g., “a device,” “the device”), including in the claims, includes one or more of such devices (e.g., “a processor” includes one or more processors, “the processor” includes one or more processors, “a memory” includes one or more memories, “the memory” includes one or more memories, etc.). The terms “comprises,” “comprising,” “includes,” and/or “including,” as used herein, specify the presence of stated features, integers, steps, operations, elements, and/or components, but do not preclude the presence or addition of one or more other features, integers, steps, operations, elements, components, and/or groups thereof.

[0150] Also, as used herein, “or” as used in a list of items (possibly prefaced by “at least one of” or prefaced by “one or more

of”) indicates a disjunctive list such that, for example, a list of “at least one of A, B, or C,” or a list of “one or more of A, B, or C” or a list of “A or B or C” means A, or B, or C, or AB (A and B), or AC (A and C), or BC (B and C), or ABC (i.e., A and B and C), or combinations with more than one feature (e.g., AA, AAB, ABBC, etc.). Thus, a recitation that an item, e.g., a processor, is configured to perform a function regarding at least one of A or B, or a recitation that an item is configured to perform a function A or a function B, means that the item may be configured to perform the function regarding A, or may be configured to perform the function regarding B, or may be configured to perform the function regarding A and B. For example, a phrase of “a processor configured to measure at least one of A or B” or “a processor configured to measure A or measure B” means that the processor may be configured to measure A (and may or may not be configured to measure B), or may be configured to measure B (and may or may not be configured to measure A), or may be configured to measure A and measure B (and may be configured to select which, or both, of A and B to measure). Similarly, a recitation of a means for measuring at least one of A or B includes means for measuring A (which may or may not be able to measure B), or means for measuring B (and may or may not be configured to measure A), or means for measuring A and B (which may be able to select which, or both, of A and B to measure). As another example, a recitation that an item, e.g., a processor, is configured to at least one of perform function X or perform function Y means that the item may be configured to perform the function X, or may be configured to perform the function Y, or may be configured to perform the function X and to perform the function Y. For example, a phrase of “a processor configured to at least one of measure X or measure Y” means that the processor may be configured to measure X (and may or may not be configured to measure Y), or may be configured to measure Y (and may or may not be configured to measure X), or may be configured to measure X and to measure Y (and may be configured to select which, or both, of X and Y to measure).

[0151] As used herein, unless otherwise stated, a statement that a function or operation is “based on” an item or condition means that the function or operation is based on the stated item or condition and may be based on one or more items and/or conditions in addition to the stated item or condition.

[0152] Substantial variations may be made in accordance with specific requirements. For example, customized hardware might also be used, and/or particular elements might be implemented in hardware, software (including portable software, such as applets, etc.) executed by a processor, or both. Further, connection to other computing devices such as network input/output devices may be employed. Components, functional or otherwise, shown in the figures and/or discussed herein as being connected or communicating with each other are communicatively coupled unless otherwise noted. That is, they may be directly or indirectly connected to enable communication between them.

[0153] The systems and devices discussed above are examples. Various configurations may omit, substitute, or add various procedures or components as appropriate. For instance, features described with respect to certain configurations may be combined in various other configurations. Different aspects and elements of the configurations may be combined in a similar manner. Also, technology evolves and, thus, many of the elements are examples and do not limit the scope of the disclosure or claims.

[0154] A wireless communication system is one in which communications are conveyed wirelessly, i.e., by electromagnetic and/or acoustic waves propagating through atmospheric space rather than through a wire or other physical connection, between wireless communication devices. A wireless communication system (also called a wireless communications system, a wireless communication network, or a wireless communications network) may not have all communications transmitted wirelessly but is configured to have at least some communications transmitted wirelessly. Further, the term “wireless communication device,” or similar term, does not require that the functionality of the device is exclusively, or even primarily, for communication, or that communication using the wireless communication device is exclusively, or even primarily, wireless, or that the device be a mobile device, but indicates that the device includes wireless communication capability (one-way or two-way), e.g., includes at least one radio (each radio being part of a transmitter, receiver, or transceiver) for wireless communication.

[0155] Specific details are given in the description herein to provide a thorough understanding of example configurations (including implementations). However, configurations may be practiced without these specific details. For example, well-known circuits, processes, algorithms, structures, and techniques have been shown without unnecessary detail in order to avoid obscuring the configurations. The description herein provides example configurations, and does not limit the scope, applicability, or configurations of the claims. Rather, the preceding description of the configurations provides a description for implementing described techniques. Various changes may be made in the function and arrangement of elements.

[0156] The terms “processor-readable medium,” “machine-readable medium,” and

[0157] “computer-readable medium,” as used herein, refer to any medium that participates in providing data that causes a machine to operate in a specific fashion. Using a computing platform, various processor-readable media might be involved in providing instructions/code to processor(s) for execution and/or might be used to store and/or carry such instructions/code (e.g., as signals). In many implementations, a processor-readable medium is a physical and/or tangible storage medium. Such a medium may take many forms, including but not limited to, non-volatile media and volatile media. Non-volatile media include, for example, optical and/or magnetic disks. Volatile media include, without limitation, dynamic memory.

[0158] Having described several example configurations, various modifications, alternative constructions, and equivalents may be used. For example, the above elements may be components of a larger system, wherein other rules may take precedence over or otherwise modify the application of the disclosure. Also, a number of operations may be undertaken before, during, or after the above elements are considered. Accordingly, the above description does not bound the scope of the claims.

[0159] Unless otherwise indicated, “about” and/or “approximately” as used herein when referring to a measurable value such as an amount, a temporal duration, and the like, encompasses variations of $\pm 20\%$ or $\pm 10\%$, $\pm 5\%$, or $\pm 0.1\%$ from the

specified value, as appropriate in the context of the systems, devices, circuits, methods, and other implementations described herein. Unless otherwise indicated, “substantially” as used herein when referring to a measurable value such as an amount, a temporal duration, a physical attribute (such as frequency), and the like, also encompasses variations of $\pm 20\%$ or $\pm 10\%$, $\pm 5\%$, or $\pm 0.1\%$ from the specified value, as appropriate in the context of the systems, devices, circuits, methods, and other implementations described herein.

[0160] A statement that a value exceeds (or is more than or above) a first threshold value is equivalent to a statement that the value meets or exceeds a second threshold value that is slightly greater than the first threshold value, e.g., the second threshold value being one value higher than the first threshold value in the resolution of a computing system. A statement that a value is less than (or is within or below) a first threshold value is equivalent to a statement that the value is less than or equal to a second threshold value that is slightly lower than the first threshold value, e.g., the second threshold value being one value lower than the first threshold value in the resolution of a computing system.

Claims

1. A method for determining a true phase difference of arrival (PDOA), comprising: determining a plurality of candidate unwrapped PDOAs for a signal transmitted by a target object and received by at least a first antenna and a second antenna of a user equipment (UE), wherein the plurality of candidate unwrapped PDOAs corresponds to a plurality of orientations of the UE, wherein a separation distance between the first antenna and the second antenna is greater than or equal to half of a wavelength of the signal; comparing the plurality of unwrapped candidate PDOAs; and identifying the true PDOA based on the comparison.
2. The method of claim 1, wherein the plurality of candidate unwrapped PDOAs comprises a first subset of unwrapped PDOAs corresponding to a first wrapped PDOA and a second subset of unwrapped PDOAs corresponding to a second wrapped PDOA, wherein the first wrapped PDOA corresponds to a first orientation of the UE and the second wrapped PDOA corresponds to a second orientation of the UE, wherein the comparing of the plurality of unwrapped candidate PDOAs, comprises: determining a first subset of candidate angle of arrivals (AOAs) corresponding to the first subset of candidate unwrapped PDOAs and a second subset of candidate AOAs corresponding to the second subset of candidate unwrapped PDOAs; determining a plurality of divergences between the second subset of candidate AOAs and the corresponding first subset of candidate AOAs; identifying one or more of the first subset of candidate AOAs as untrue AOAs based on the plurality of divergences; determining a remaining candidate AOA of the first subset of candidate AOAs that has not been identified as an untrue AOA; and identifying the remaining candidate AOA as a true AOA.
3. The method of claim 2, further comprising: displaying one or more user instructions to change an orientation of the UE by rotating the UE in one or more directions.
4. The method of claim 3, wherein the one or more user instructions comprise one or more user instructions to rotate the UE along an axis while maintaining the target object and at least the first antenna and the second antenna in a plane.
5. The method of claim 3, wherein the one or more user instructions comprise one or more user instructions to tilt the UE in a first direction from an axis and in a second direction from the axis.
6. The method of claim 1, wherein the determining of the plurality of candidate unwrapped PDOAs for the signal, the comparing of the plurality of unwrapped candidate PDOAs, and the identifying of the true PDOA based on the comparison, comprise: measuring a wrapped PDOA vector for the signal, wherein the wrapped PDOA corresponds to the plurality of orientations of the UE; generating a plurality of candidate unwrapped PDOA vectors based on the measured wrapped PDOA vector; generating a plurality of projections onto a subspace formed by a column space of a measurement matrix for the plurality of candidate unwrapped PDOA vectors; determining a plurality of distances between the plurality of candidate unwrapped PDOA vectors and the corresponding plurality of projections onto the subspace; and identifying the candidate unwrapped PDOA vector of the plurality of candidate unwrapped PDOA vectors corresponding to a smallest distance of the plurality of distances as a true PDOA vector.
7. The method of claim 6, wherein the generating of the plurality of projections onto the subspace and the determining of the plurality of distances between the plurality of candidate unwrapped PDOA vectors and the corresponding plurality of projections onto the subspace, comprise: generating the plurality of projections onto an ellipsoid residing in the subspace formed by the column space of the measurement matrix for the plurality of candidate unwrapped PDOA vectors, wherein the ellipsoid results from applying the measurement matrix to a unit sphere in a three dimensional space; and determining the plurality of distances between the plurality of candidate unwrapped PDOA vectors and the corresponding plurality of projections onto the ellipsoid.
8. The method of claim 6, wherein a set of candidate unwrapped PDOA vectors comprises the plurality of candidate unwrapped PDOA vectors, wherein the plurality of distances comprises a plurality of first distances between the set of candidate unwrapped PDOA vectors and the corresponding plurality of projections onto the subspace, wherein the identifying of the true PDOA vector comprises: selecting a first candidate unwrapped PDOA vector in the set of candidate unwrapped PDOA vectors corresponding to a smallest first distance as a current best candidate; computing a second distance to an ellipsoid residing within the subspace for the current best candidate, wherein the ellipsoid results from applying the measurement matrix to a unit sphere in a three dimensional space; and removing the current best candidate from the set of candidate unwrapped PDOA vectors.
9. The method of claim 8, wherein if the set of candidate unwrapped PDOA vectors is not empty, the identifying of the true PDOA vector further comprises: removing one or more candidate unwrapped PDOA vectors in the set of candidate

unwrapped PDOA vectors that correspond to one or more first distances larger than the second distance; and if the set of candidate unwrapped PDOA vectors is not empty, identifying a second candidate unwrapped PDOA vector in the set of candidate unwrapped PDOA vectors with the smallest first distance; removing the second candidate unwrapped PDOA vector from the set of candidate unwrapped PDOA vectors; computing a third distance to the ellipsoid for the second candidate unwrapped PDOA vector; determining whether the third distance is less than the second distance; and setting the second candidate unwrapped PDOA vector as the current best candidate if the third distance is less than the second distance.

10. The method of claim 9, wherein if the set of candidate unwrapped PDOA vectors is empty, returning the current best candidate as the true PDOA vector.

11. The method of claim 1, further comprising: calculating a direction between the UE and the target object based on the true PDOA.

12. The method of claim 1, further comprising: determining the plurality of orientations of the UE based on one or more measurements from one or more sensors of the UE.

13. A user equipment (UE), comprising: a first antenna; a second antenna; one or more memories; and one or more processors communicatively coupled to the one or more memories, the one or more processors being configured to: determine a plurality of candidate unwrapped phase difference of arrivals (PDOAs) for a signal transmitted by a target object and received by at least the first antenna and the second antenna, wherein the plurality of candidate unwrapped PDOAs corresponds to a plurality of orientations of the UE, wherein a separation distance between the first antenna and the second antenna is greater than or equal to half of a wavelength of the signal; compare the plurality of unwrapped candidate PDOAs; and identify a true PDOA based on the comparison.

14. The UE of claim 13, wherein the plurality of candidate unwrapped PDOAs comprises a first subset of unwrapped PDOAs corresponding to a first wrapped PDOA and a second subset of unwrapped PDOAs corresponding to a second wrapped PDOA, wherein the first wrapped PDOA corresponds to a first orientation of the UE and the second wrapped PDOA corresponds to a second orientation of the UE, wherein the one or more processors configured to compare the plurality of unwrapped candidate PDOAs being further configured to: determine a first subset of candidate angle of arrivals (AOAs) corresponding to the first subset of candidate unwrapped PDOAs and a second subset of candidate AOA corresponding to the second subset of candidate unwrapped PDOAs; determine a plurality of divergences between the second subset of candidate AOA and the corresponding first subset of candidate AOA; identify one or more of the first subset of candidate AOA as untrue AOA based on the plurality of divergences; determine a remaining candidate AOA of the first subset of candidate AOA that has not been identified as an untrue AOA; and identify the remaining candidate AOA as a true AOA.

15. The UE of claim 13, wherein the one or more processors configured to determine the plurality of candidate unwrapped PDOAs for the signal, compare the plurality of unwrapped candidate PDOAs, and identify the true PDOA based on the comparison, being further configured to: measure a wrapped PDOA vector for the signal, wherein the wrapped PDOA corresponds to the plurality of orientations of the UE; generate a plurality of candidate unwrapped PDOA vectors based on the measured wrapped PDOA vector; generate a plurality of projections onto a subspace formed by a column space of a measurement matrix for the plurality of candidate unwrapped PDOA vectors; determine a plurality of distances between the plurality of candidate unwrapped PDOA vectors and the corresponding plurality of projections onto the subspace; and identify the candidate unwrapped PDOA vector of the plurality of candidate unwrapped PDOA vectors corresponding to a smallest distance of the plurality of distances as a true PDOA vector.

16. The UE of claim 13, wherein the one or more processors being further configured to: calculate a direction between the UE and the target object based on the true PDOA.

17. A non-transitory, processor-readable storage medium comprising processor-readable instructions to cause one or more processors to: determine a plurality of candidate unwrapped phase difference of arrivals (PDOAs) for a signal transmitted by a target object and received by at least a first antenna and a second antenna of a user equipment (UE), wherein the plurality of candidate unwrapped PDOAs corresponds to a plurality of orientations of the UE, wherein a separation distance between the first antenna and the second antenna is greater than or equal to half of a wavelength of the signal; compare the plurality of unwrapped candidate PDOAs; and identify a true PDOA based on the comparison.

18. The medium of claim 17, wherein the plurality of candidate unwrapped PDOAs comprises a first subset of unwrapped PDOAs corresponding to a first wrapped PDOA and a second subset of unwrapped PDOAs corresponding to a second wrapped PDOA, wherein the first wrapped PDOA corresponds to a first orientation of the UE and the second wrapped PDOA corresponds to a second orientation of the UE, wherein the processor-readable instructions to cause the one or more processors to compare the plurality of unwrapped candidate PDOAs further comprise processor-readable instructions to cause the one or more processors to: determine a first subset of candidate angle of arrivals (AOAs) corresponding to the first subset of candidate unwrapped PDOAs and a second subset of candidate AOA corresponding to the second subset of candidate unwrapped PDOAs; determine a plurality of divergences between the second subset of candidate AOA and the corresponding first subset of candidate AOA; identify one or more of the first subset of candidate AOA as untrue AOA based on the plurality of divergences; determine a remaining candidate AOA of the first subset of candidate AOA that has not been identified as an untrue AOA; and identify the remaining candidate AOA as a true AOA.

19. The medium of claim 17, wherein the processor-readable instructions to cause the one or more processors to determine the plurality of candidate unwrapped PDOAs for the signal, compare the plurality of unwrapped candidate PDOAs, and identify the true PDOA based on the comparison, further comprise processor-readable instructions to cause the one or more processors to: measure a wrapped PDOA vector for the signal, wherein the wrapped PDOA corresponds to the plurality of orientations of the UE; generate a plurality of candidate unwrapped PDOA vectors based on the measured wrapped PDOA

vector; generate a plurality of projections onto a subspace formed by a column space of a measurement matrix for the plurality of candidate unwrapped PDOA vectors; determine a plurality of distances between the plurality of candidate unwrapped PDOA vectors and the corresponding plurality of projections onto the subspace; and identify the candidate unwrapped PDOA vector of the plurality of candidate unwrapped PDOA vectors corresponding to a smallest distance of the plurality of distances as a true PDOA vector.

20. The medium of claim 17, wherein the processor-readable instructions further comprise processor-readable instructions to cause the one or more processors to: calculate a direction between the UE and the target object based on the true PDOA.
