

US Patent & Trademark Office

Patent Public Search | Text View

United States Patent	12412494
Kind Code	B2
Date of Patent	September 09, 2025
Inventor(s)	Kim; Jaeun et al.

Display device including overload protection circuit

Abstract

A display device according to an embodiment includes a display, a first power module that outputs a first power, and a second power module that outputs a second power. The first power and the second power are supplied to the display. The first power module is configured to cut off the first power when an amount of input current exceeds an overload criterion, to identify whether the second power module is abnormal based on the second power, and to change the overload criterion from a first threshold current amount to a second threshold current amount that exceeds the first threshold current amount, in an abnormal state of the second power module.

Inventors: Kim; Jaeun (Suwon-si, KR), Joo; Sungyong (Suwon-si, KR), Lee; Jiwon (Suwon-si, KR)

Applicant: SAMSUNG ELECTRONICS CO., LTD. (Suwon-si, KR)

Family ID: 68387037

Assignee: SAMSUNG ELECTRONICS CO., LTD. (Suwon-si, KR)

Appl. No.: 18/403923

Filed: January 04, 2024

Prior Publication Data

Document Identifier	Publication Date
US 20240135845 A1	Apr. 25, 2024
US 20240233589 A9	Jul. 11, 2024

Foreign Application Priority Data

KR	10-2018-0052020	May. 04, 2018
----	-----------------	---------------

Related U.S. Application Data

Publication Classification

Int. Cl.: **G09G3/00** (20060101); **G09G5/10** (20060101)

U.S. Cl.:

CPC **G09G3/006** (20130101); **G09G5/10** (20130101); G09G2330/025 (20130101); G09G2330/04 (20130101)

Field of Classification Search

USPC: None

References Cited

U.S. PATENT DOCUMENTS

Patent No.	Issued Date	Patentee Name	U.S. Cl.	CPC
7502950	12/2008	Brands	713/340	G06F 3/1446
8009137	12/2010	Heo	N/A	N/A
8850246	12/2013	Lee et al.	N/A	N/A
9392653	12/2015	Lee et al.	N/A	N/A
9511784	12/2015	Oki et al.	N/A	N/A
9720638	12/2016	Joo et al.	N/A	N/A
10274987	12/2018	Puggelli et al.	N/A	N/A
2011/0141776	12/2010	Lin	N/A	N/A
2012/0299941	12/2011	Lee	N/A	N/A
2013/0088803	12/2012	Kim et al.	N/A	N/A
2017/0063149	12/2016	Castillo	N/A	N/A
2017/0201122	12/2016	Arduini et al.	N/A	N/A
2017/0272025	12/2016	Jimbo et al.	N/A	N/A
2017/0300079	12/2016	Puggelli et al.	N/A	N/A
2017/0331295	12/2016	Abeyasekera et al.	N/A	N/A
2017/0338609	12/2016	Holzherr	N/A	N/A

FOREIGN PATENT DOCUMENTS

Patent No.	Application Date	Country	CPC
2017-163176	12/2016	JP	N/A
10-1797523	12/2016	JP	N/A
10-2013-0037486	12/2012	KR	N/A
10-2013-0049049	12/2012	KR	N/A
10-2016-0016413	12/2015	KR	N/A
10-2008-0079449	12/2017	KR	N/A
WO2013/128585	12/2012	WO	N/A

OTHER PUBLICATIONS

International Search Report dated Jul. 19, 2019 from International Application No. PCT/KR2019/003500, 4 pages. cited by applicant
Office Action dated May 12, 2022 in U.S. Appl. No. 17/052,053. cited by applicant
Advisory Action dated Jan. 27, 2023 in U.S. Appl. No. 17/052,053. cited by applicant
Advisory Action dated Mar. 3, 2023 in U.S. Appl. No. 17/052,053. cited by applicant
Office Action dated Dec. 19, 2022 in Korean Patent Application No. 10-2018-0052020 (6 pages; 8 pages English translation). cited by applicant
Office Action dated Apr. 6, 2023 in U.S. Appl. No. 17/052,053. cited by applicant
Notice of Allowance dated Oct. 13, 2023 in U.S. Appl. No. 17/052,053. cited by applicant
Office Action dated Dec. 21, 2023 in Korean Patent Application No. 10-2023-0044371. cited by applicant
Office Action dated Nov. 22, 2022 in U.S. Appl. No. 17/052,053. cited by applicant
U.S. Appl. No. 17/052,053, filed Oct. 30, 2020, Jaeun Kim et al., Samsung Electronics Co., Ltd. cited by applicant

Primary Examiner: Matthews; Andre L

Attorney, Agent or Firm: STAAS & HALSEY LLP

Background/Summary

CROSS-REFERENCE TO RELATED APPLICATIONS (1) This application is a continuation application of U.S. patent application Ser. No. 17/052,053 filed on Oct. 30, 2020, which is a U.S. National Stage Application which claims the benefit under 35 U.S.C. § 371 of International Patent Application No. PCT/KR2019/003500 filed on Mar. 26, 2019, which claims foreign priority benefit under 35 U.S.C. § 119 of Korean Patent Application No. 10-2018-0052020 filed on May 4, 2018 in the Korean Intellectual Property Office, the contents of all of which are incorporated herein by reference.

TECHNICAL FIELD

(1) Embodiments disclosed in the disclosure relate to a power module implementation technology of a display device.

BACKGROUND ART

(2) A large-screen display device including a large display (e.g., a display of 400 inches or more) is often installed in public places (e.g., theaters). Such a large display may be formed by combining a plurality of small displays. Since a display device including the large display is used for a long time, failures are likely to occur.

(3) Each display module of the large-screen display device may include a dual power module. Accordingly, even if a failure occurs in one power module, the each display module may be driven using power of another power module. For example, the large-screen display device may include a first power module that supplies power to small displays of a first block (e.g., a left half) and a second power module that supplies power to small displays of a second block (e.g., a right half) among a plurality of small displays. Since an output terminal of the first power module and an output terminal of the second power module are interconnected (load share), when one of the first power module and the second power module fails, the plurality of small displays may receive power from the other.

DISCLOSURE

Technical Problem

- (4) Since a first power module and a second power module of the large-screen display device are each implemented to cover the rating of the large-screen display device (all a plurality of small displays), a volume of each of the power modules is large and a manufacturing cost may increase.
- (5) Various embodiments disclosed in the disclosure provide a display device including an overload prevention circuit capable of reducing the rating of a power module.
- (6) In addition, various embodiments disclosed in the disclosure provide a display device capable of stably supplying power even in an environment in which some of a plurality of power modules can supply power.

Technical Solution

- (7) A display device according to an embodiment disclosed in the disclosure includes a display, a first power module that outputs a first power, and a second power module that outputs a second power, wherein the first power and the second power are supplied to the display, and the first power module is configured to cut off the first power when an amount of input current exceeds an overload criterion, to identify whether the second power module is abnormal based on the second power, and to change the overload criterion from a first threshold current amount to a second threshold current amount that exceeds the first threshold current amount, in an abnormal state of the second power module.
- (8) In addition, a display device according to an embodiment disclosed in the disclosure includes a display, a first power module that outputs a first power, a second power module that outputs a second power, and a processor, wherein the first power and the second power are supplied to the display, wherein the processor is configured to sense an abnormal state of the second power module, based on the second power, and to reduce a luminance of the display to less than a threshold luminance, in the abnormal state of the second power module, and wherein the first power module is configured to cut off an output of the first power when an output current amount of the first power module exceeds a threshold current amount corresponding to a state in which the luminance of the display is the threshold luminance.

Advantageous Effects

- (9) According to the embodiments disclosed in the disclosure, it is possible to reduce the rated power of the power module. In addition to this, various effects that are directly or indirectly identified through the disclosure may be provided.

Description

DESCRIPTION OF DRAWINGS

- (1) FIG. 1 illustrates a structural diagram of a large-screen display device according to an embodiment.
- (2) FIG. 2 is a diagram illustrating an exemplary power supply when a failure occurs in a first power module, according to an embodiment.
- (3) FIG. 3 illustrates a configuration diagram of a display device according to an embodiment.
- (4) FIG. 4 illustrates a configuration diagram of a first power module including a first sensing circuit according to an embodiment.
- (5) FIG. 5 illustrates a detailed circuit diagram of a first sensing circuit and a second conversion circuit according to an embodiment.
- (6) FIG. 6 illustrates a configuration diagram of a first power module including a second sensing circuit according to an embodiment.
- (7) FIG. 7 illustrates a detailed circuit diagram of a first sensing circuit, a second sensing circuit, and a second conversion circuit according to an embodiment.
- (8) FIG. 8 illustrates output power of a first power module when a luminance of a display is normally reduced in an abnormal state of a second power module, according to an embodiment.

- (9) FIG. 9 illustrates output power of a first power module when a luminance of a display is not reduced in an abnormal state of a second power module, according to an embodiment.
- (10) FIG. 10 is a flowchart of a power control method of a first power module including a first sensing circuit according to an embodiment.
- (11) FIG. 11 is a flowchart of a power control method of a first power module including a second sensing circuit according to an embodiment.
- (12) FIG. 12 is another example of a display system according to an embodiment.
- (13) FIG. 13 illustrates another example of sensing an abnormal state of a first power module or a second power module by a processor according to an embodiment.
- (14) FIG. 14 is a graph illustrating a LS signal of a first integrated circuit according to an embodiment.
- (15) In connection with the description of the drawings, the same or similar reference numerals may be used for the same or similar components.

MODE FOR INVENTION

- (16) Hereinafter, various embodiments of the disclosure will be described with reference to the accompanying drawings. However, this is not intended to limit the disclosure to specific embodiments, and it should be understood that the disclosure includes various modifications, equivalents, and/or alternatives.
- (17) FIG. 1 illustrates an example of a structural diagram of a large-screen display device according to an embodiment.
- (18) Referring to FIG. 1, according to an embodiment, a large-screen display system **100** may include a plurality of display devices **110, 120, 130, 140, 150, 160, 170, 180, and 190**. Each of the display devices (e.g., **110, 120, 130, 140, 150, 160, 170, 180, and 190**) may include a first power module **P111** and a second power module **P112**. The first power module **P111** and the second power module **P112** have (load share) output terminals connected to each other, and may share power consumption of each of the display devices (e.g., **110, 120, 130, 140, 150, 160, 170, 180, and 190**). For example, when the rated power of the display device (e.g., **110**) is 200 W, the first power module **P111** and the second power module **P112** may each share 100 W of power consumption. In addition, when a failure occurs in one of the first power module **P111** and the second power module **P112**, the other, in which the failure does not occur, may supply power to the display device (e.g., **110**).
- (19) According to an embodiment, each display device (e.g., **110**) may include a plurality of display modules (e.g., **111**). Each of the display modules **111** may include, for example, a plurality of LEDs (e.g., **111_1**), and each LED **111_1** may constitute a unit pixel of the display module (e.g., **111**). Each of the display modules (e.g., **111**) may be, for another example, a single display module including a plurality of pixels (e.g., **111_1**).
- (20) FIG. 2 is a diagram illustrating an exemplary power supply when a failure occurs in a first power module, according to an embodiment.
- (21) Referring to FIG. 2, a first power module **P121** and a second power module **P122** of the display device **120** (e.g., **120** of FIG. 1) may share a load. For example, outputs of the first power module **P121** and the second power module **P122** are connected in parallel to each other to supply power to the display of the same display device. To this end, the rated power of the first power module **P121** and the second power module **P122** may be more than half of the rated power of the display device (e.g., **120**). For example, when the rated power of the display device (e.g., **120**) is 400 W, the first power module **P121** and the second power module **P122** may each be configured to have a rated power of 200 W or more.
- (22) When a failure occurs in the first power module **P121**, as the second power module **P122** supplies power to the display device (e.g., **120**), a consumer may not be able to recognize an occurrence of the failure of the display device (e.g., **120**).
- (23) FIG. 3 illustrates a configuration diagram of a display device according to an embodiment.

(24) Referring to FIG. 3, a display device **300** (e.g., the display device **110** of FIG. 1) may include a display **340** (e.g., a plurality of display modules (e.g., **111**) of FIG. 1), and a processor **330**, a first power module **310**, and a second power module **320**.

(25) According to an embodiment, the display **340** may receive output power (first power and second power) of the first power module **310** and the second power module **320**, and may be driven using the received power. The display **340** may be driven using the received power, and may output an image under control of the processor **330**.

(26) According to an embodiment, the processor **330** may execute an operation or a data processing related to control and/or communication of at least one other components of the display device **300**. The processor **330** may include, for example, at least one of a central processing unit (CPU), a graphics processing unit (GPU), a microprocessor, an application processor, an application specific integrated circuit (ASIC), and a field programmable gate arrays (FPGA), and may have a plurality of cores.

(27) According to an embodiment, the processor **330** may determine whether the first power module **310** is abnormal, based on output power (hereinafter, referred to as a 'first power') of the first power module **310**. For example, the processor **330** may determine that the first power module **310** is in an abnormal state when a first signal generated from the first power is less than or equal to a first threshold value. In addition, the processor **330** may determine whether the second power module **320** is abnormal, based on output power (hereinafter, referred to as a 'second power') of the second power module **320**. For example, the processor **330** may determine that the second power module **320** is in the abnormal state when a second signal generated from the second power is less than or equal to the first threshold value. In an embodiment, the processor **330** may control the display **340** such that the luminance of the display **340** becomes less than or equal to a threshold luminance when the abnormal state of the first power module **310** or the second power module **320** is identified.

(28) According to an embodiment, the first power module **310** may receive external power from an external power source, and may output the first power (e.g., 200 W) that is generated by rectifying the received external power, converting the rectified power into DC power, and down-converting a level of the DC power. The second power module **320** may receive the external power from the external power source, and may output the second power (e.g., 200 W) that is generated by rectifying the received external power, converting the rectified power into DC power, and down-converting a level of the DC power. The output power of the first power module **310** and the second power module **320** may be interconnected and transmitted to the display **340**. Accordingly, in a normal state, the display **340** may receive 200 W power from the first power module **310** and 200 W power from the second power module **320**.

(29) According to an embodiment, the first power module **310** (a first sensing circuit **317** of FIG. 4) may change an overload criterion of the first power module **310** in response to the normal state or the abnormal state of the second power module **320**. For example, when the second power module **320** is in the normal state, an output of the first power module **310** may be cut off based on a first threshold current amount (initial overload criterion 200 W).

(30) When the second power module **320** is in the abnormal state, the first power module **310** (the first sensing circuit **317** of FIG. 4) may change the overload criterion (e.g., change the first threshold current amount to a second threshold current amount). As the overload criterion is changed in the abnormal state of the second power module **320**, when an input current amount of the first power module **310** exceeds the second threshold current amount, a circuit of the first power module **310** may be configured such that the output of the first power module **310** is cut off. The first threshold current amount may be, for example, the rated current of the first power module **310**, and the second threshold current amount (e.g., 400 W) (>the first threshold current amount) may be, for example, a maximum limit current amount of the first power module **310**. The maximum limit current amount may be, for example, less than or equal to a maximum current

amount at which the first power module **310** normally drives the display **340** for a first specified time. The first specified time may correspond to, for example, a time required for the processor **330** to identify the abnormal state of the second power module **320** and to reduce the luminance of the display **340**.

(31) According to an embodiment, the second power module **320** (refer to the first sensing circuit **317** in FIG. 4) may change the overload criterion of the second power module **320** in response to the normal state or the abnormal state of the first power module **310**. For example, when the first power module **310** is in the normal state, the output of the second power module **320** may be cut off based on a third threshold current amount (initial overload criterion 200 W). When the first power module **310** is in the abnormal state, the second power module **320** (refer to the first sensing circuit **317** in FIG. 4) may change the overload criterion (e.g., change the first threshold current amount to the second threshold current amount). As the overload criterion is changed in the abnormal state of the first power module **310**, when the input current amount of the second power module **320** exceeds a fourth threshold current amount, a circuit of the first power module **310** may be configured such that the output of the second power module **320** is cut off.

(32) The third threshold current amount may be, for example, the rated current (e.g., 200 W) of the second power module **320**. The fourth threshold current amount (>the third threshold current amount) may be, for example, a maximum limit current amount (e.g., 400 W) of the second power module **320**. The maximum limit current amount may be, for example, a maximum current amount at which the second power module **320** normally drives the display **340** for the first specified time.

(33) According to various embodiments, the first power module **310** may identify the abnormal state of the second power module **320**, based on the first power. For example, the first power module **310** (refer to load resistors **R73** and **R74** and a comparator **U73** in FIG. 7) may identify that the second power module **320** is in the abnormal state when a voltage among the first power is equal to or greater than a specified voltage. The first power module **310** (a controller **U1** in FIG. 7), when it is identified that the luminance of the display **340** is not reduced in a state in which the output power of the first power module **310** is increased due to the abnormal state of the second power module **320**, may be provided to cut off (e.g., power off of the first power module **310**) the output of the first power module **310**. For example, the first power module **310** may include a load resistor (the load resistors **R73** and **R74** in FIG. 7) that is connected in series to the output of the first power module **310**, and a comparator (**U73** of FIG. 7) that outputs a specified signal (e.g., a high level signal) when a voltage across the load resistor exceeds a specified voltage corresponding to a fifth threshold current amount. In addition, the first power module **310** may include a delay element (a delay element **C71** in FIG. 7) that delays the output of the comparator by a second specified time (>the first specified time), and a controller (the controller **U1** of FIG. 7) that is provided to cut off the output of the first power module **310** (power off of the first power module **310**), based on a signal corresponding to the output of the comparator.

(34) The fifth threshold current amount may be, for example, a current consumption amount (e.g., corresponding to the maximum power consumption) of the display device **300** corresponding to a state in which the luminance of the display **340** is the threshold luminance. When a failure of the second power module **320** occurs, an output current amount of the first power module **310** may increase, and a voltage across the load resistor may be equal to or greater than a specified voltage. The controller may receive a signal corresponding to the specified signal after the second specified time from a time when the voltage corresponding to the output current amount is equal to or greater than the specified voltage due to the delay element. Accordingly, when the luminance of the display **340** is reduced as the processor **330** senses an abnormality in the second power module **320** after the time when the voltage across the load resistor is equal to or greater than the specified voltage, the controller may not receive a signal corresponding to the specified signal. In contrast, when the processor **330** senses the abnormality in the second power module **320** and fails to reduce the luminance of the display **340**, the controller may receive the signal corresponding to the specified

signal after the second specified time from the time when the voltage across the load resistor is equal to or greater than the specified voltage, and thus the controller may cut off the output of the first power module **310**.

(35) FIG. **4** illustrates a configuration diagram of a first power module including a first sensing circuit according to an embodiment.

(36) Referring to FIG. **4**, the first power module **310** (e.g., the first power module **310** of FIG. **3**) may include a rectifier circuit **311**, a first conversion circuit **313**, a second conversion circuit **315**, and the first sensing circuit **317**.

(37) According to an embodiment, the rectifier circuit **311** may receive AC power from the external power source and may full-wave rectify the received AC power. For example, the rectifier circuit **311** may include a bridge full-wave rectifier circuit.

(38) According to an embodiment, the first conversion circuit **313** may compensate for the power factor of the output power of the rectifier circuit **311** and may convert AC into DC. The first conversion circuit **313** may include an active power factor compensation circuit. For example, the first conversion circuit **313** may boost the received power such that a magnitude of the output voltage of the first conversion circuit **313** is within a specified range (e.g., $390 \leq 395V \leq 400V$). The first conversion circuit **313** may include, for example, at least one active power factor compensation circuit among a continuous conduction mode (CCM), a critical conduction mode (CRM), and an interleaved CRM.

(39) According to an embodiment, the first sensing circuit **317** may sense the abnormal state of the second power module **320**, based on the second power. The first sensing circuit **317** may sense the input current amount of the second conversion circuit **315** and may output a voltage (hereinafter, referred to as a 'monitoring voltage') corresponding to the sensed input current amount. The first sensing circuit **317** may differently output the monitoring voltage corresponding to the input current amount of the second conversion circuit **315** depending on whether the second power module **320** is abnormal. For example, in the normal state of the second power module **320**, the first sensing circuit **317** may output the monitoring voltage that is 'N' ('N' is a prime number) times the input current amount of the second conversion circuit **315**. For another example, when the second power module **320** is in the abnormal state, the first sensing circuit **317** may output the monitoring voltage of N/2 times the input current amount of the second conversion circuit **315**. Accordingly, the first sensing circuit **317** may support changing the overload criterion of the second conversion circuit **315** depending on whether the second power module **320** is abnormal.

(40) According to an embodiment, the second conversion circuit **315** may output power obtained by performing down-level conversion of power converted to DC by the first conversion circuit **313**. The output current amount of the second conversion circuit **315** may be adjusted based on a current amount consumption of a load circuit (e.g., a display) connected to the output terminal of the second conversion circuit **315**. For example, the second conversion circuit **315** (e.g., a control circuit) may include a feedback circuit (not illustrated), and may sense the current amount consumed by the load circuit through the feedback circuit. The second conversion circuit **315** (e.g., the control circuit) may adjust the output current amount of the second conversion circuit **315** such that the output current amount of the second conversion circuit **315** corresponds to the sensed current consumption amount. The second conversion circuit **315** may be configured to isolate a primary side from a secondary side. For example, the second conversion circuit **315** may include a half bridge LLC resonant converter or a flyback converter including at least one transformer.

(41) According to an embodiment, the second conversion circuit **315** may receive the monitoring voltage through the first sensing circuit **317** and may cut off the output of the second conversion circuit **315**, based on the monitoring voltage. For example, the second conversion circuit **315** may receive the monitoring voltage corresponding to the input current amount of the second conversion circuit **315** in the normal state of the second power module **320**, and may cut off the output of the first power module **310** when the monitoring voltage exceeds a second threshold level. As

described above, in the abnormal state of the second power module **320**, since the first sensing circuit **317** outputs the monitoring voltage corresponding to about $\frac{1}{2}$ times the normal state of the first power module **310**, the second conversion circuit **315** may change the overload criterion of the second conversion circuit **315** from the first threshold current amount to the second threshold current amount in the abnormal state of the second power module **320** due to the first sensing circuit **317**. For example, when the second power module **320** is in the normal state and the current amount sensed through the first sensing circuit **317** exceeds the first threshold current amount, the second conversion circuit **315** may cut off the output of the second conversion circuit **315**. In addition, when the second power module **320** is in the abnormal state and the current amount sensed through the first sensing circuit **317** exceeds the second threshold current amount, the second conversion circuit **315** may cut off the output of the second conversion circuit **315**.

(42) According to an embodiment, a third conversion circuit **319** may generate the first signal by level down-converting the first power. The first signal may be transferred to the processor **330**, and the processor **330** may determine whether the first power module **310** is abnormal, based on the first signal.

(43) According to the above-described embodiment, in case of the abnormal state of the second power module **320**, as the first power module **310** changes the overload criterion of the first power module **310**, the first power module **310** may output driving power of the display device **300**, at least until the luminance of the display **340** is reduced, on behalf of the second power module **320**. According to various embodiments, the second power module **320** may identify the abnormal state of the first power module **310** in the same or similar manner as the first power module **310**, and may change the overload criterion of the second power module **320** when the first power module **310** is in the abnormal state.

(44) FIG. 5 illustrates a detailed circuit diagram of a first sensing circuit and a second conversion circuit according to an embodiment.

(45) Referring to FIG. 5, the second conversion circuit **315** (e.g., the second conversion circuit **315** of FIG. 4) may include a first switching element **Q1**, a second switching element **Q2**, a transformer **T1**, a first capacitor **C1**, and the controller **U1**. The first sensing circuit **317** may include a photo coupler **U2**, a first resistor **R1**, a second resistor **R2**, a second capacitor **C2**, a fourth switching element **Q4**, and an inversion circuit **U3**. In an embodiment, some components may be omitted or additional components may be further included. In an embodiment, some of the components are combined to form a single entity, but functions of the corresponding components before the combination may be performed in the same manner.

(46) The first switching element **Q1** and the second switching element **Q2** may each include a first field effect transistor (FET) and a second FET. When the first FET is turned on under the control of the controller **U1**, the first FET may output the input power supplied to a drain to a source. When the second switching element **Q2** is turned on under the control of the controller **U1**, the second switching element **Q2** may output the input power supplied to a drain to a source. The drain of the first FET may be connected to an input terminal of the second conversion circuit **315**, and the source of the first FET may be connected to the primary side of the transformer **T1** through the drain of the second FET and the first capacitor **C1**. The source of the second FET may be connected to an input terminal of the first sensing circuit **317**.

(47) According to an embodiment, the transformer **T1** may receive the output of the first conversion circuit **313** through the first switching element **Q1**. The transformer **T1** may adjust the voltage received through the first switching element **Q1** to a level downward, based on a turns ratio of the primary and secondary windings, and may convert a current amount received through the first switching element **Q1** into a current amount based on the turns ratio and may output the conversion result.

(48) The inversion circuit **U3** may receive the second power (e.g., a second voltage) and may output the monitoring signal corresponding to the second power. The monitoring signal may be a

signal obtained by inverting the second voltage. The monitoring signal may exceed a third threshold level (e.g., 2.5V) when the second voltage is a low state, and may be less than or equal to the third threshold level when the second voltage is the high level.

(49) A first terminal of a third switching element Q3 and a second terminal of the third switching element Q3 may be opened or shorted depending on the magnitude of the voltage applied to a third terminal of the third switching element Q3. Since the third terminal of the third switching element Q3 receives the monitoring signal, the first terminal of the third switching element Q3 and the second terminal of the third switching element Q3 may be opened or shorted depending on the magnitude of the monitoring signal. When the monitoring signal is less than or equal to the third threshold level, the first terminal of the third switching element Q3 and the second terminal of the third switching element Q3 may be opened. When the monitoring signal exceeds the third threshold level, the first terminal of the third switching element Q3 and the second terminal of the third switching element Q3 may be shorted. Since the first terminal of the third switching element Q3 is in a pull-up state, and the second terminal of the third switching element Q3 is connected to a ground, when the monitoring signal exceeds the third threshold level, the first terminal and the second terminal of the third switching element Q3 may be changed to the low state. The third switching element Q3 may be, for example, 'TL431'.

(50) The photo coupler U2 may be electrically connected between the first terminal of the third switching element Q3 and the control terminal (a gate) of the fourth switching element Q4. The photo coupler U2 transfers a signal applied to the first terminal (output terminal) of the third switching element Q3 to the control terminal of the fourth switching element Q4, but may electrically isolate between the first terminal of the third switching element Q3 and the control terminal of the fourth switching element Q4. For example, an anode of a light emitting diode of the photo coupler U2 may be connected to the output voltage of the second conversion circuit 315, and a cathode of the light emitting diode of the photo coupler U2 may be connected to the first terminal of the third switching element Q3. A collector of a transistor of the photo coupler U2 may be connected to a voltage generated from the input power of the transformer T1, and an emitter of the photo coupler U2 may be connected to the control terminal of the fourth switching element Q4.

(51) The second capacitor C2 may receive at least a part of an output current of the primary winding of the transformer T1, and may couple the DC from the received current.

(52) A first terminal of the first resistor R1 may be connected to a first terminal of the second resistor R2, a second terminal of the second capacitor C2, and a first input terminal of the controller U1, and a second terminal of the resistor R1 may be connected to the ground. A first terminal of the second resistor R2 may be connected to the first terminal of the first resistor R1, a second terminal of the second capacitor C2, and the first input terminal of the controller U1, and a second terminal of the second resistor R2 may be connected to the ground through the fourth switching element Q4. The first resistor R1 and the second resistor R2 may convert the output current of the primary winding of the transformer T1 into a voltage corresponding to an output current amount of the primary winding.

(53) The fourth switching element Q4 may include a third FET. A drain of the third FET may receive at least a part of the primary side current of the transformer T1 through the second capacitor C2, and a source of the third FET may be connected to the ground. A gate of the third FET may receive a signal corresponding to the monitoring signal through the third switching element Q3 and the photo coupler U2. The signal corresponding to the monitoring signal may be electrically isolated from the monitoring signal, and may be a signal of substantially the same level. Accordingly, when the monitoring signal is less than or equal to the third threshold level, the fourth switching element Q4 may be turned off, and when the monitoring signal exceeds the third threshold level, the fourth switching element Q4 may be turned on. The fourth switching element Q4 may connect the second terminal of the second resistor R2 to the ground in the turned-on state.

(54) The controller U1 may form or close a path through which the output of the first conversion

circuit **313** is transferred to the primary side of the transformer **T1**, based on an output or an input of the second conversion circuit **315**.

(55) According to an embodiment, the controller **U1** may monitor power consumption (e.g., an amount of current consumption) of the load circuit connected to the secondary side of the transformer **T1** through a feedback circuit (not illustrated). The controller **U1** may adjust a turn-on period of the first switching element **Q1** and the second switching element **Q2**, based on the power consumption of the load circuit. As a result, the controller **U1** may control the first and second switching elements **Q1** and **Q2** such that the output current amount of the transformer **T1** corresponds to the power consumption of the load circuit.

(56) According to an embodiment, the controller **U1** may cut off the output of the second conversion circuit **315** when the input current amount of the second conversion circuit **315** exceeds the overload criterion. For example, the controller **U1** may receive a monitoring voltage corresponding to the input current amount of the transformer **T1**, and may control the first switching element **Q1** and the second switching element **Q2** such that the input power of the transformer **T1** is cut off when the received monitoring voltage exceeds the second threshold level.

(57) According to an embodiment, the controller **U1** may use the first sensing circuit **317** to change the overload criterion from the first threshold current amount to the second threshold current amount when the second power module **320** is in the abnormal state. In the abnormal state of the second power module **320**, since the monitoring voltage output from the first sensing circuit **317** is reduced by about $\frac{1}{2}$ times compared to the normal state of the second power module **320**, the controller **U1** may allow the second conversion circuit **315** to output twice the rated current amount of the first power module **310**.

(58) According to the above-described embodiment, since the second conversion circuit **315** may change the overload criterion of the first power module **310** by using the first sensing circuit **317**, the second conversion circuit **315** may support normal transfer of the output of the first power module **310** at least until the processor **330** identifies the abnormal state of the second power module **320** and lowers the luminance of the display **340**, while lowering the rating of the first power module **310**.

(59) According to various embodiments, since the detailed configuration of the second power module **320** is the same as or similar to the configuration of the first power module **310** illustrated in FIGS. **4** and **5**, detailed descriptions thereof will be omitted.

(60) FIG. **6** illustrates a configuration diagram of a first power module including a second sensing circuit according to an embodiment.

(61) Referring to FIG. **6**, the first power module **310** (e.g., the first power module **310** of FIG. **3**) may include the rectifier circuit **311**, the first conversion circuit **313**, the second conversion circuit **315**, the first sensing circuit **317**, and a second sensing circuit **318**. Since the first power module **310** of FIG. **6** is the same as or similar to the first power module **310** of FIG. **4**, in FIG. **6**, components different from the first power module **310** of FIG. **4** will be described.

(62) According to an embodiment, the first sensing circuit **317** may output the monitoring voltage corresponding to an input current amount of the second conversion circuit **315**.

(63) According to an embodiment, the second sensing circuit **318** may sense the abnormal state of the second power module **320**, based on the amount of output current of the second conversion circuit **315**. The second sensing circuit **318** may output a detection signal after the second specified time elapses from a time when the abnormal state of the second power module **320** is sensed. The detection signal may be, for example, a signal of an active low level. The second specified time may be later than a time required to reduce the luminance of the display **340** to the threshold luminance or less, as the processor **330** senses the abnormal state of the first power module and transmits an instruction for luminance control to the display **340**. The second specified time may be a time shorter (time point) than a maximum time at which the first power module **310** can output the second threshold current amount. For example, the second specified time may be a time set to

prevent burnout of circuit elements of the first power module **310** after a time required to adjust the luminance of the display **340**.

(64) According to an embodiment, the second conversion circuit **315** may output a current corresponding to a current amount consumed by the load circuit (e.g., the display) connected to the output terminal of the second conversion circuit **315**. For example, the second conversion circuit **315** may include the half bridge LLC resonant converter or the flyback converter including at least one transformer.

(65) The second conversion circuit **315** may cut off the output of the second conversion circuit **315** when the input current amount of the second conversion circuit **315** exceeds the second threshold current amount. For example, the second conversion circuit **315** may receive the monitoring voltage from the first sensing circuit **317**, and may cut off the output of the second conversion circuit **315** when the monitoring voltage exceeds a first threshold level. The second threshold current amount may be, for example, a maximum limit current amount of the first power module **310**. The maximum limit current amount may be, for example, less than or equal to the maximum current amount at which the first power module **310** normally drives the display **340** for the first specified time. The first specified time may be less than or equal to a time required for the processor **330** to identify the abnormal state of the second power module **320** and to reduce the luminance of the display **340**.

(66) The second conversion circuit **315** may cut off the output of the first power module **310** after the second specified time from after the abnormal state of the second power module **320** is identified. For example, the second conversion circuit **315** may sense the abnormal state of the second power module, based on the detection signal. By the way, since the second sensing circuit **318** outputs the detection signal after the second specified time from the time when the abnormal state of the second power module **320** is sensed, the second conversion circuit **315** may cut off the output of the first power module when the output current amount of the first power module **310** exceeds the fifth threshold current amount after the specified time from after the abnormal state of the second power module **320** is sensed. The fifth threshold current amount may be, for example, an output current amount (e.g., a maximum power consumption) of the first power module **310** corresponding to a state in which the luminance of the display **340** is the threshold luminance.

(67) According to the above-described embodiment, the first power module **310** may identify the abnormal state of the second power module **320**, based on a change in the first output current amount. When the luminance of the display **340** is not reduced below the threshold luminance by the processor **330** in the abnormal state of the second power module **320**, the first power module **310** may prevent a failure of the first power module **310** due to an overload of the first power module **310** by cutting off the output of the first power module **310**.

(68) FIG. 7 illustrates a detailed circuit diagram of a first sensing circuit and a second sensing circuit according to an embodiment.

(69) Referring to FIG. 7, the second conversion circuit **315** may include the first switching element **Q1**, the second switching element **Q2**, the transformer **T1**, the first capacitor **C1**, and the controller **U1**. Since the second conversion circuit **315** is the same as or similar to the second conversion circuit **315** of FIG. 4, a configuration of the controller **U1** that is different from the second conversion circuit **315** of FIG. 4 will be mainly described.

(70) The controller **U1** may include a first input terminal and a second input terminal, and may cut off the output of the second conversion circuit **315**, based on a signal received to the first input terminal or the second input terminal. For example, when the signal received to the first input terminal exceeds the second threshold level corresponding to the second threshold current amount, the controller **U1** may cut off the output of the second conversion circuit **315** by using the first switching element **Q1** and the second switching element **Q2**. For another example, the controller **U1** may cut off the output of the second conversion circuit **315** when the signal (detection signal) received to the second input terminal is less than or equal to a fourth threshold level. The fourth

threshold level may be, for example, a criterion by which the controller U1 determines whether a signal received to the second input terminal is in the low state.

(71) The first sensing circuit **317** may include the first resistor R1 and the second capacitor C2. The first resistor R1 may receive at least a part of the output current of the primary winding of the transformer T1 through the second capacitor C2, and may output the monitoring voltage (a voltage across the first resistor R1) corresponding to the received current. The second capacitor C2 may couple (or block) direct current from at least a part of the output current of the primary winding of the transformer T1.

(72) The second sensing circuit **318** may include the load resistors R73 and R74, the comparator U73, the third switching element Q3, a dividing circuit R75 and R76, the delay element C71, and a photo coupler U72.

(73) The load resistors R73 and R74 may be connected in series on the output path of the first power module **310**. The load resistors R73 and R74 may include, for example, the second resistor R73 and the third resistor R74 connected in parallel with each other. A voltage across the load resistors R73 and R74 may be input to the first input terminal (+ input) and the second input terminal (− input terminal) of the comparator U73.

(74) The comparator U73 may receive the voltage across the load resistors R73 and R74, and may output a specified signal when the voltage across the load resistors R73 and R74 exceeds a fifth threshold level. For example, the comparator U73 may be provided to output a signal having a low level when the voltage across the load resistors R73 and R74 is less than or equal to the fifth threshold level, and to output a signal having the high level when the voltage across the load resistors R73 and R74 exceeds the fifth threshold level. The fifth threshold level may be set to correspond to a case where the output current amount of the second conversion circuit **315** exceeds the fifth threshold current amount, based on, for example, resistance values of the load resistors R73 and R74.

(75) The delay element C71 may delay the output of the comparator U73 by the second specified time. The delay element C71 may be, for example, a capacitor having a capacitance capable of delaying the output of the comparator U73 by the second specified time. The second specified time may be later than a time required to reduce the luminance of the display **340** to the threshold luminance or less, as the processor **330** senses the abnormal state of the first power module and transmits the instruction for luminance control to the display **340**. The second specified time may be a time (time point) shorter than the maximum time at which the first power module **310** can output the second threshold current amount. For example, the second specified time may be a time set to prevent burnout of the circuit elements of the first power module **310** after a time required to adjust the luminance of the display **340**. The second specified time may be, for example, 150 ms.

(76) The dividing circuit R75 and R76 may be connected to the output terminal of the comparator U73, and may divide the output signal of the comparator U73 at a specified ratio for switching of the third switching element Q3. The dividing circuit R75 and R76 may include the fourth resistor R75 and the fifth resistor R76, a first terminal of the fourth resistor R75 may be connected to the output terminal of the comparator U73, and a second terminal of the fourth resistor R75 may be connected to a first terminal of the fifth resistor R76. A second terminal of the fifth resistor R76 may be connected to the ground. The second terminal of the fourth resistor R75 and the first terminal of the fifth resistor R76 may be connected to a third terminal of the third switching element Q3.

(77) Depending on a signal that is applied to the third terminal of the third switching element Q3, the first terminal of the third switching element Q3 and the second terminal of the third switching element Q3 may be shorted or opened. For example, when a voltage of less than or equal to the third threshold level (e.g., 2.5V) is applied to the third terminal of the third switching element Q3, the first terminal of the third switching element Q3 and the second terminal of the third switching element Q3 may be opened. When a voltage that exceeds the third threshold level (e.g., 2.5V) is

applied to the third terminal of the third switching element Q3, the first terminal of the third switching element Q3 and the second terminal of the third switching element Q3 may be shorted. In the above-described embodiment, the dividing circuit R75 and R76 and the third switching element Q3 function as an inverting circuit for inverting the output of the comparator U73, and may be configured in different forms.

(78) The photo coupler U72 may transfer a signal of the first terminal (output terminal) of the third switching element Q3 to the second input terminal of the controller U1. The photo coupler U72 may be provided to isolate the primary side signal and the secondary side signal of the second conversion circuit 315.

(79) In short, when the output current amount of the second conversion circuit 315 exceeds the fifth threshold current amount, the comparator U73 may output a specified signal. The specified signal may be delayed for the second specified time by the delay element C71 and may be applied to the second input terminal of the controller U1. As the processor 330 adjusts the luminance of the display 340 to be less than or equal to the threshold luminance, when the output current of the second conversion circuit 315 is changed to be less than or equal to the fifth threshold current amount, the comparator U73 may no longer output the specified signal. In this case, the controller U1 may adjust the output of the second conversion circuit 315, based on the current amount consumed by the display 340.

(80) In contrast, when the output current amount exceeds the fifth threshold current amount even after the lapse of the second specified time, as a signal corresponding to the specified signal is transferred to the second input terminal of the controller U1, the controller U1 may cut off the output of the second conversion circuit 315,

(81) According to the above-described embodiment, as the luminance of the display 340 is not reduced by the processor 330 in the abnormal state of the second power module 320, the first power module 310 may cut off the output of the first power module 310 to avoid overloading the first power module 310, using the second conversion circuit 315 and the second sensing circuit 318.

(82) According to various embodiments, the comparator U73 may be configured with an amplifier. In this embodiment, the amplifier may receive the voltage (the voltage corresponding to the output current amount of the first power module 310) across the load resistors R73 and R74, may amplify the input voltage by a specified amplification ratio, and may output the amplified voltage. The output voltage of the amplifier may be delayed by the delay element C71 by the second specified time. The output voltage of the amplifier may be delayed by the delay element C71 and then may be divided at a specified ratio by the dividing circuit R75 and R76. The voltage divided by the dividing circuit R75 and R76 may be applied to the third terminal of the third switching element Q3. The first terminal and the second terminal of the third switching element Q3 may be shorted when the voltage applied to the third terminal of the third switching element Q3 exceeds the third threshold level. The amplification ratio of the amplifier and the dividing ratio (the specified ratio) of the dividing circuit R75 and R76 may be determined such that a result voltage obtained by dividing the output voltage of the amplifier when the voltage across the load resistors R73 and R74 is greater than or equal to the fifth threshold level may exceed the third threshold level.

(83) According to various embodiments, since the detailed configuration of the second power module 320 is the same as or similar to the configuration of the first power module 310 illustrated in FIGS. 6 and 7, a detailed description thereof will be omitted.

(84) FIG. 8 illustrates output power of a first power module when a luminance of a display is normally reduced in an abnormal state of a second power module, according to an embodiment.

(85) Referring to FIGS. 7 and 8, before a time t1, the first power module 310 and the second power module 320 may be in the normal state. In this case, the first power module 310 and the second power module 320 may output the first power (e.g., 200 W) and the second power (e.g., 200 W), respectively.

(86) At time **t1**, the second power module **320** may enter the abnormal state due to a failure or the like. At time **t1**, the processor **330** may sense the abnormal state of the second power module **320**, and the luminance of the display **340** may be reduced at a time **t2**, based on the control of the processor **330**.

(87) The controller **U1** of the first power module **310** may determine whether the output current amount of the first power module **310** exceeds the fifth threshold current amount (300 W current consumption amount, a current amount that the first power module **310** handles the display **340** by itself while the luminance is adjusted) at the time **t1**, and may determine whether the output current amount of the first power module **310** exceeds the fifth threshold current amount at a time **t3**, which is the second specified time from the time **t1**.

(88) When the controller **U1** of the first power module **310** identifies that the output current amount of the first power module **310** does not exceed the fifth threshold current amount at the time **t3**,

(89) In response to the control of the processor **330**, the fifth threshold current amount (300 W current consumption amount, a current consumption amount that the first power module **310** may handle depending on the luminance adjustment of the display) may be supplied to the display **340** after the time **t2**.

(90) FIG. **9** illustrates output power of a first power module when a luminance of a display is not reduced in an abnormal state of a second power module, according to an embodiment.

(91) Referring to FIGS. **7** and **9**, before the time **t1**, the first power module **310** and the second power module **320** may be in the normal state. In this case, the first power module **310** and the second power module **320** may output the first power and the second power, respectively.

(92) At the time **t1**, the second power module **320** may be in the abnormal state due to a failure or the like. When, at a time **t1**, the processor **330** does not sense the abnormal state of the second power module **320** or an abnormality of another circuit (e.g., the display) of the display device **300** occurs, the first power module **310** may output a current (a current amount corresponding to 400 W) exceeding the fifth threshold current amount up to a time **t3**. In this case, the first power module **310** may cut off the output of the first power module **310**. For example, the controller **U1** of the first power module **310** may cut off the output of the second conversion circuit **315** by using the first switching element **Q1**.

(93) According to the above-described embodiment, as the first power module **310** cuts off the output of the first power module **310** when the abnormality occurs in the display device **300** including the second power module **320**, a burnout of the first power module **310** due to the overload on the first power module **310** may be prevented.

(94) FIG. **10** is a flowchart of a power control method of a first power module including a first sensing circuit according to an embodiment.

(95) Referring to FIGS. **4**, **5** and **10**, in operation **1010**, the first power module **310** may determine whether the second power module **320** is in the abnormal state, based on the input current amount (the amount of input current input to the primary side of the transformer of the first power module **310**).

(96) When the second power module **320** is in the normal state in operation **1010**, the controller **U1** of the first power module **310** in operation **1020** may monitor whether the input current amount of the first power module **310** is less than or equal to the first threshold current amount. The first threshold current amount (e.g., 200 W) may be, for example, a current amount corresponding to the rating of the first power module **310**.

(97) When the controller **U1** of the first power module **310** identifies the abnormal state of the second power module **320** in operation **1010** (e.g., receiving a signal corresponding to the abnormal state from the second power module **320**), in operation **1030**, whether the input current amount of the first power module **310** (e.g., the current amount supplied to the display) exceeds the second threshold current amount (e.g., 400 W) may be monitored. For example, as the second power module **320** fails to supply power to the display **340** normally, the first power module **310** may

control the output current amount corresponding to the power consumption amount of the display **340**, and correspondingly, whether the input current amount of the first power module **310** exceeds the second threshold current amount may be monitored. The second threshold current amount (>first threshold current amount) may be, for example, the maximum limit current amount of the first power module **310**. The maximum limit current amount may be, for example, less than or equal to the maximum current amount at which the first power module **310** normally drives for the first specified time (a time required for luminance adjustment). The first specified time may correspond to, for example, a time required for the processor **330** to identify the abnormal state of the second power module **320** and to reduce the luminance of the display **340**.

(98) In operation **1020**, when the input current amount of the first power module **310** exceeds the first threshold current amount in the normal state of the second power module **320**, in operation **1040**, the first power module **310** may cut off the output of the first power module **310**.

(99) In operation **1030**, when the input current amount of the first power module **310** exceeds the second threshold current amount, in operation **1040**, the output of the first power module **310** may be cut off.

(100) In operation **1020**, when the input current amount of the first power module **310** is less than or equal to the first threshold current amount in the normal state of the second power module **320** (a first case), the first power module **310** may adjust the output of the first power module **310**, based on the amount of output consumption of the first power module **310**.

(101) In operation **1030**, when the input current amount is less than or equal to the second threshold current amount in the abnormal state of the second power module **320** (in a second case), the first power module **310** may adjust the output of the first power module **310**, based on the amount of output consumption of the first power module **310**. The amount of output consumption may be, for example, a power consumption amount of a load circuit (e.g., a processor, a display, or the like) that consumes the output of the first power module **310** and the second power module **320**.

(102) FIG. **11** is a flowchart of a power control method of a first power module including a second sensing circuit according to an embodiment.

(103) Referring to FIGS. **7** and **11**, in operation **1110**, the first power module **310** may monitor whether the output current amount exceeds the fifth threshold current amount. The fifth threshold current amount may be, for example, an output current amount (e.g., the maximum power consumption) of the first power module **310** corresponding to a state in which the luminance of the display **340** is the threshold luminance.

(104) When it is determined that the output current amount exceeds the fifth threshold current amount, in operation **1120**, the first power module **310** may determine whether the time when the output current amount exceeds the fifth threshold current amount passes the second specified time.

(105) When the specified time elapses from the time when the output current amount exceeds the fifth threshold current amount (when the second specified time is elapsed), in operation **1130**, the first power module **310** may determine whether the output current amount exceeds a time when the fifth threshold current amount is exceeded.

(106) When it is determined in operation **1130** that the output current amount exceeds the fifth threshold current amount even after the lapse of the second specified time, in operation **1140**, the first power module **310** may cut off the output of the first power module **310**.

(107) When the time (interval) in which the output current amount exceeds the fifth threshold current amount does not pass the second specified time (interval), the first power module **310** may determine whether the second specified time is elapsed, while adjusting the output power of the first power module **310** (supplying the current amount depending on the fifth threshold power), based on the output consumption amount of the first power module **310**.

(108) When the output current amount is less than or equal to the fifth threshold current amount, in operation **1160**, the first power module **310** may adjust the output power of the first power module **310**, based on the output consumption amount of the first power module **310**. For example, the

output of the first power module **310** may be adjusted to correspond to the current consumption amount of the display **340**.

(109) FIG. **12** is another example of a display system according to an embodiment.

(110) Referring to FIG. **12**, a display system **1200** may include a first display device **1210** and a second display device **1220**. The embodiment of FIG. **12** is different from the above-described embodiments in that power of first and second power modules **1215** and **1225** included in the first and second display devices **1210** and **1220**, respectively are connected in parallel, and the description will be focused on the differences.

(111) The first display device **1210** may include a first processor **1211** (e.g., the processor **330** in FIG. **3**), a first display **1213** (e.g., the display **340** in FIG. **3**), and the first power module **1215** (e.g., the first power module **310** of FIG. **3**).

(112) The first processor **1211** and the first display **1213** may be driven using the output power of the first power module **1215**. Since the outputs of the first power module **1215** and the second power module **1225** are connected in parallel (load share), when a failure of the first power module **1215** occurs, the first processor **1211** and the first display **1213** may be driven using power from the second power module **1225**. The first processor **1211** may identify the abnormal state of the first power module **1215**, based on the first signal generated from the first power, and may reduce the luminance of the first display **1213** when the abnormality occurs in the first power module **1215**. For example, when the first signal generated from the first power is less than or equal to the first threshold value, the first processor **1211** may determine that the first power module **1215** is in the abnormal state, and may reduce the luminance of the first display **1213**.

(113) The second display device **1220** may include a second processor **1221** (e.g., the processor **330** of FIG. **3**), a second display **1223** (e.g., the display **340** of FIG. **3**), and the second power module **1225** (e.g., the second power module **320** of FIG. **3**).

(114) The second processor **1221** and the second display **1223** may be driven using the output power of the second power module **1225**. Since the outputs of the first power module **1215** and the second power module **1225** are parallel, when a failure of the second power module **1225** occurs, the second processor **1221** and the second display **1223** may be driven using power from the first power module **1215**. The second processor **1221** may identify an occurrence of the abnormality in the second power module **1225**, based on the second signal generated from the second power, and may reduce the luminance of the second display **1223** when the abnormality occurs in the second power module **1225**. For example, when the second signal generated from the second power is less than or equal to the first threshold value, the second processor **1221** may determine that the second power module **1225** is in the abnormal state, and may reduce the luminance of the second display **1223**.

(115) The first power module **1215** of the first display device **1210** and the second power module **1225** of the second display device **1220** may share a load. For example, since the outputs of the first power module **1215** and the second power module **1225** are connected in parallel to each other, power be supplied to the first and second displays **1213** and **1223** included in the first and second display devices **1210** and **1220** different from each other. When a failure occurs in the first power module **1215**, the second power module **1225** may support consumers to not be greatly aware of the occurrence of the failure in the first power module **1215** by supplying power to the first display **1213** and the first processor **1211**. Likewise, when a failure occurs in the second power module **1225**, the first power module **1215** may support consumers to not be greatly aware of the occurrence of the failure in the second power module **1225** by supplying power to the second display **1223** and the second processor **1221**.

(116) According to an embodiment, the first power module **1215** is provided to cut off the output of the first power module **1215** when an overload occurs in the first power module **1215**. However, when the overload of the first power module **1215** occurs due to the failure of the second power module **1225**, the first power module **1215** may support the first power module **1215** to replace the

function of the second power module **1225** by changing the overload criterion. For example, when the first sensing circuit (e.g., the first sensing circuit **317** of FIG. **4**) of the first power module **1215** identifies that the second power is not received from the second power module **1225**, the overload criterion may be changed. As another example, the first sensing circuit (e.g., the first sensing circuit **317** of FIG. **4**) of the first power module **1215** may change (e.g., increase) the overload criterion when the output power of the first power module **1215** increases due to a failure occurrence of the second power module **1225**. The configuration in which the first power module **1215** changes the overload criterion has been described above with reference to FIGS. **4** and **5**, and thus detailed description thereof will be omitted.

(117) According to various embodiments, when the first power module **1215** identifies that the luminance of the second display **1223** is not reduced when the abnormality occurs in the second power module **1225**, based on the output current amount of the first power module **1215**, the first power module **1215** may cut off the output of the first power module **1215**. For example, even after the second specified time elapses from the time when the output current amount of the first power module **1215** exceeds the fifth threshold current amount—as the luminance of the second display **1223** is not reduced—when the output current of the first power module **1215** exceeds the fifth threshold current amount, the controller (e.g., **U1** in FIG. **7**) of the first power module **1215** may cut off the output of the first power module **1215**. The configuration in which the first power module **1215** cuts off the output of the first power module **1215**, based on the output current amount of the first power module has been described above with reference to FIGS. **6** and **7**, and thus a detailed description thereof will be omitted.

(118) FIG. **13** illustrates another example of sensing an abnormal state of a first power module or a second power module by a processor according to an embodiment.

(119) Referring to FIG. **13**, an output (the first power) of the first power module (e.g., **310** in FIG. **6**) and an output (the second power) of the second power module (e.g., **320** in FIG. **3**) may be connected in parallel through a first load resistor **R1310** (e.g., the load resistors **R73** and **R74** in FIG. **7**) and a second load resistor **R1320**, respectively.

(120) A first integrated circuit **U1310** and a second integrated circuit **U1320** may be provided to equally match the output current amount of the first power module **310** and the output current amount of the second power module **320**, which are connected in parallel with each other. Each of the first integrated circuit **U1310** and the second integrated circuit **U1320** may be, for example, a load share integrated circuit (IC). The first integrated circuit **U1310** may compare the output current amount of the first power module **310** (the voltage across the first load resistor **R1310** or the output current amount of the first power) with the output current amount of the second power module **320** (the LS signal of the second integrated circuit **U1320**), and may increase the output current amount of the first power module **310** when the current amount of the first power module **310** is less than the output current amount of the second power module **320**. The first integrated circuit **U1310** may decrease the magnitude of the LS signal when the output current of the first power module **310** is greater than the output current of the second power. In this case, the second integrated circuit **U1320** may increase the output current amount of the second power module **320**, based on the magnitude of the LS signal.

(121) According to an embodiment, the first integrated circuit **U1310** may include an amplifier **1311**, a first comparator **1312**, a second comparator **1313**, a third comparator **1314**, a switching element **1315**, and an internal resistor **1316**, and the second integrated circuit **U1320** may include an amplifier **1321**, a first comparator **1322**, a second comparator **1323**, a third comparator **1324**, a switching element **1325**, and an internal resistor **1326**. When the output current amount (current corresponding to the first power) of the first power module **310** is greater than the output current amount (a current corresponding to the second power) of the second power module **320**, as the output voltage of the amplifier **1311** of the first integrated circuit **U1310** increases, the first comparator **1312** of the first integrated circuit **U1310** may output a high signal. In this case, the

second comparator **1313** and the third comparator **1314** output a low signal. On the other hand, as the output of the amplifier **1321** of the second integrated circuit **U1320** decreases, the output of the amplifier **1321** may be less than a signal (the LS signal) which is output from the first comparator **1312** of the first integrated circuit **U1310** and passed through a diode **1317**. Then, the first comparator **1322** of the second integrated circuit **U1320** may output the low signal, and the second comparator **1323** and the third comparator **1324** of the second integrated circuit **U1320** may output the high signal. Accordingly, the switching element **1325** of the second integrated circuit **U1320** is turned on, and may increase the output of the second power module **320** through a second feedback circuit **F1320**. For example, the second feedback circuit **F1320** may include a constant voltage circuit **U133**, a first resistor **R133**, a second resistor **R134**, and a photo coupler **U134**. First and second terminals of the constant voltage circuit **U133** (e.g., TL431) may be shorted when a voltage greater than a reference voltage (e.g. 2.5V) is applied to a third terminal of the constant voltage circuit **U133**, otherwise the first and second terminals of the constant voltage circuit **U133** may be opened. The first resistor **R133** and the second resistor **R134** may divide the voltage of the second power, the divided voltage may be applied to a third terminal of the constant voltage circuit **U133**. When the switching element **1325** of the second integrated circuit **U1320** is turned off, the voltage divided by the first resistor **R133** and the second resistor **R134** is equal to or greater than the reference voltage, but when the switching element **1325** is turned on, the voltage applied to the third terminal of the constant voltage circuit **U133** falls below the reference voltage due to the internal resistor **1326** of the second integrated circuit **U1320**, then the first and second terminals of the constant voltage circuit **U133** may be opened. In this case, the voltage of the feedback terminal of a controller **U1'** (e.g., **U1** in FIG. 7) of the second power module **320** is boosted, and the controller **U1'** (e.g., **U1** in FIG. 7) of the second power module **320** may increase the output power (the second power) of the second power module **320** by controlling (duty ratio increase control or switching frequency decrease control) at least one switching element (e.g., **Q1** and **Q2** of FIG. 7). According to various embodiments, when the output current of the second power module **320** is greater than the output current of the first power module **310**, the first integrated circuit **U1310**, the first feedback circuit **F1310**, and the controller **U1** (e.g., **U1** in FIG. 7) of the first power module **310** may increase the output power of the first power module **310** through the above-described control.

(122) The LS signal of the first integrated circuit **U1310** and the LS signal of the second integrated circuit **U1320** may be connected in parallel to each other and then may be transferred to the processor **330** through a diode **D1300**. The processor **330** may receive at least one of the LS signal of the first integrated circuit **U1310** and the LS signal of the second integrated circuit **U1320** through the diode **D1300**, and may determine whether the first power or the second power is abnormal, based on the magnitude of the received signal. The processor **330** may reduce the luminance of the display **340** to less than the threshold luminance when it is identified that the magnitude of the received signal is greater than or equal to the specified magnitude. According to the above-described embodiment, as the LS signal of the first integrated circuit **U1310** increases in proportion to the current amount of the first power, and the LS signal of the second integrated circuit **U1320** increases in proportion to the current amount of the second power, the signal received by the processor **330** through the diode **D1300** may increase in proportion to the current amount of the first power or the current amount of the second power. Therefore, the processor **330** may monitor whether the first power module **310** or the second power **320** is abnormal, based on the output signal (e.g., the LS signal) of the load share IC (the first integrated circuit **U1310** or the second integrated circuit **U1320**).

(123) FIG. 14 is a graph illustrating a LS signal of a first integrated circuit according to an embodiment. In FIG. 14, a horizontal axis represents the current amount of the first power, and a vertical axis represents the magnitude of the LS signal.

(124) Referring to FIG. 14, the LS signal of the first integrated circuit **U1310** may increase in

proportion to the current amount of the first power. For example, in the normal state of the first power module **310**, the LS signal of the first integrated circuit **U1310** may be about 2V. However, in the abnormal state (e.g., a state in which the current amount of the first power increases due to a failure of the second power module **320**) of the second power module **320**, the LS signal of the first integrated circuit **U1310** is about twice as large. (e.g., about 4V). Accordingly, the processor **330** may detect the abnormal state of the first power module **310** or the second power module **320** by monitoring the magnitude of the LS signal.

(125) According to various embodiments, each component (e.g., a module or a program) of the above-described components may include a single entity or multiple entities. According to various embodiments, one or more of the above-described components may be omitted, or one or more other components may be added. Alternatively or additionally, a plurality of components (e.g., modules or programs) may be integrated into a single component. In such a case, according to various embodiments, the integrated component may still perform one or more functions of each of the plurality of components in the same or similar manner as they are performed by a corresponding one of the plurality of components before the integration. According to various embodiments, operations performed by the module, the program, or another component may be carried out sequentially, in parallel, repeatedly, or heuristically, or one or more of the operations may be executed in a different order or omitted, or one or more other operations may be added. Accordingly, the scope of the disclosure should be construed as including all changes or various other embodiments based on the technical spirit of the disclosure.

Claims

1. A display device comprising: a display including a plurality of sub display which are driven by a driving power; a first power module, provided in each of the plurality of sub display, configured to output a first power as a portion of the driving power; and a second power module, provided in the each of the plurality of sub display, configured to output a second power as a remaining portion of the driving power, wherein an initial threshold current amount of the first power being output as the portion of the driving power is adjusted to a subsequent threshold current amount that is different from the initial threshold current amount of the first power based an abnormal state of the second power module, and an initial threshold current amount of the second power being output as the remaining portion of the driving power is adjusted to a subsequent threshold current amount that is different from the initial threshold current amount of the second power based an abnormal state of the first power module.
2. The display device of claim 1, wherein the first power module is configured to: identify whether the second power module is abnormal based on the second power; and output a third power corresponding to the driving power, in an abnormal state of the second power module.
3. The display device of claim 2, wherein the first power module is configured to: provide the third power after cutting off the output of second power.
4. The display device of claim 2, wherein the first power module is configured to: output the first power based on a first overload criterion that corresponds a first threshold current amount, in a normal state of the second power module; and output the third power based on a second overload criterion that corresponds a second threshold current amount greater than the first threshold current amount, in the abnormal state of the second power module.
5. The display device of claim 4, wherein the first power module is configured to: cut off the output of the first power based on an amount of input current of the first power module exceeding the first threshold current amount, in the normal state of the second power module; and cut off the output of the first power based on the amount of input current of the first power module exceeding the second threshold current amount, in the abnormal state of the second power module.
6. The display device of claim 2, further comprising: a processor, and wherein the processor is

configured to: set a luminance of the sub display which the first power and the second power are supplied, to a first luminance; and set a luminance of the sub display which the third power is supplied, to a second luminance less than the first luminance.

7. A display device comprising: a display including a plurality of sub display which are driven by a driving power; a first power module, provided in each of the plurality of sub display, configured to output a first power as a portion of the driving power; a second power module, provided in the each of the plurality of sub display, configured to output a second power as a remaining portion of the driving power; and a processor configured to: identify whether the first power module is abnormal based on the first power; and output a third power corresponding to the driving power using the second power module by adjusting an initial threshold current amount of the second power module, in an abnormal state of the first power module.

8. The display device of claim 7, wherein the processor is configured to: output the first power based on a first overload criterion that corresponds a first threshold current amount, in a normal state of the first power module; and output the third power based on a second overload criterion that corresponds a second threshold current amount greater than the first threshold current amount, in the abnormal state of the first power module.

9. The display device of claim 8, wherein the processor is configured to: cut off the output of the first power based on an amount of input current of the first power module exceeding the first threshold current amount, in the normal state of the first power module; and cut off the output of the first power based on the amount of input current of the first power module exceeding the second threshold current amount, in the abnormal state of the first power module.

10. The display device of claim 7, wherein the processor is configured to: set a luminance of the sub display which the first power and the second power are supplied, to a first luminance; and set a luminance of the sub display which the third power is supplied, to a second luminance less than the first luminance.

11. A method of operating of a display device comprising a display including a plurality of sub display which are driven by a driving power, comprising: outputting a first power using a first power module provided in the each of the plurality of sub display, the first power being out as a portion of the driving power; and outputting a second power using a second power module provided in the each of the plurality of sub display, the second power being output as a remaining portion of the driving power, wherein an initial threshold current amount of the first power being output as the portion of the driving power is adjusted to a subsequent threshold current amount that is different from the initial threshold current amount of the first power based on an abnormal state of the second power module, and an initial threshold current amount of the second power being output as the remaining portion of the driving power is adjusted to a subsequent threshold current amount that is different from the initial threshold current amount of the second power based an abnormal state of the first power module.

12. The method of claim 11, further comprising: identifying whether the second power module is abnormal based on the second power; and outputting a third power corresponding to the driving power, in an abnormal state of the second power module.

13. The method of claim 12, further comprising: providing the third power after cutting off the output of second power.

14. The method of claim 12, further comprising: outputting the first power based on a first overload criterion that corresponds a first threshold current amount, in a normal state of the second power module; and outputting the third power based on a second overload criterion that corresponds a second threshold current amount greater than the first threshold current amount, in the abnormal state of the second power module.

15. The method of claim 14, further comprising: cutting off the output of the first power based on an amount of input current of the first power module exceeding the first threshold current amount, in the normal state of the second power module; and cutting off the output of the first power based

on the amount of input current of the first power module exceeding the second threshold current amount, in the abnormal state of the second power module.

16. The method of claim 12, further comprising: setting a luminance of the sub display which the first power and the second power are supplied, to a first luminance; and setting a luminance of the sub display which the third power is supplied, to a second luminance less than the first luminance.
