

US Patent & Trademark Office

Patent Public Search | Text View

United States Patent	12418395
Kind Code	B2
Date of Patent	September 16, 2025
Inventor(s)	Kim; Hyunsu et al.

Transceiver, method of driving the same, and display device

Abstract

A transceiver includes a transmitter which transmits clock-embedded data through a line, where the clock-embedded data includes a clock training pattern, a start pattern, an encoded payload, and an end pattern, and a receiver which receives the clock-embedded data through the line, detects a clock embedding-related error from the clock-embedded data, and outputs an error flag corresponding to the clock embedding-related error to the transmitter.

Inventors: Kim; Hyunsu (Hwaseong-si, KR), Kim; Jundal (Asan-si, KR), Bae; Jongman (Seoul, KR)

Applicant: Samsung Display Co., Ltd. (Yongin-si, KR)

Family ID: 1000008819881

Assignee: SAMSUNG DISPLAY CO., LTD. (Gyeonggi-Do, KR)

Appl. No.: 18/072058

Filed: November 30, 2022

Prior Publication Data

Document Identifier	Publication Date
US 20230239133 A1	Jul. 27, 2023

Foreign Application Priority Data

KR	10-2022-0009027	Jan. 21, 2022
----	-----------------	---------------

Publication Classification

Int. Cl.: H04L7/04 (20060101); G06F3/147 (20060101); G09G3/20 (20060101)

U.S. Cl.:

CPC **H04L7/048** (20130101); **G06F3/147** (20130101); **G09G3/20** (20130101); **H04L7/041** (20130101); G09G2370/04 (20130101); G09G2370/10 (20130101)

Field of Classification Search

CPC: H04L (7/048); H04L (7/041); G06F (3/147); G09G (3/20); G09G (2370/04); G09G (2370/10)

References Cited

U.S. PATENT DOCUMENTS

Patent No.	Issued Date	Patentee Name	U.S. Cl.	CPC
9143272	12/2014	Chen et al.	N/A	N/A
2012/0105112	12/2011	Davis	327/142	G06F 11/1604
2014/0380136	12/2013	Ok	714/807	G06F 11/1004
2015/0160906	12/2014	Hwang	345/520	G09G 5/006
2016/0125794	12/2015	Park	345/522	G09G 3/2096
2017/0123470	12/2016	Srivastava	N/A	G06F 1/266
2020/0193884	12/2019	Kim	N/A	G09G 3/006
2020/0210110	12/2019	Richter	N/A	G11C 7/22
2020/0349879	12/2019	Park	N/A	G09G 3/3233
2021/0320783	12/2020	Masuda	N/A	H04L 7/0012
2021/0383770	12/2020	Chen	N/A	G09G 5/008

FOREIGN PATENT DOCUMENTS

Patent No.	Application Date	Country	CPC
1020150066659	12/2014	KR	N/A
1020160073295	12/2016	KR	N/A
1020170106605	12/2016	KR	N/A
1020150055250	12/2018	KR	N/A

Primary Examiner: Shah; Sujit

Attorney, Agent or Firm: CANTOR COLBURN LLP

Background/Summary

(1) This application claims priority to Korean Patent Application No. 10-2022-0009027, filed on Jan. 21, 2022, and all the benefits accruing therefrom under 35 USC § 119, the content of which in its entirety is herein incorporated by reference.

BACKGROUND

1. Field

(2) Embodiments relate to a transceiver. More particularly, embodiments related to a transceiver, a method of driving the transceiver, and a display device.

2. Description of the Related Art

(3) In general, a display device may communicate with a processor by using a mobile industry processor interface (MIPI) protocol. While performing the communication by using the MIPI protocol, a data line for transmitting data and a clock line for transmitting a clock signal may be

used.

SUMMARY

- (4) When performing a communication between a display device and a process by using a MIPI protocol, a use of a clock line may cause an increase in a physical or spatial cost and an increase in power consumption. Accordingly, a clock-embedded data scheme for transmitting clock information through the data line without the clock line may be used to prevent the increase in the physical or spatial cost and the increase in the power consumption caused by the use of the clock line. However, in the clock-embedded data scheme, handling of a clock embedding-related error (error detection, error transmission, etc.) may be desired.
- (5) Embodiments provide a transceiver, a method of driving the transceiver, and a display device in which a clock embedding-related error is handled.
- (6) A transceiver according to embodiments includes a transmitter which transmits clock-embedded data through a line, where the clock-embedded data includes a clock training pattern, a start pattern, an encoded payload, and an end pattern, and a receiver which receives the clock-embedded data, detects a clock embedding-related error from the clock-embedded data, and outputs an error flag corresponding to the clock embedding-related error to the transmitter.
- (7) In an embodiment, the clock embedding-related error may not be included in an error defined in a mobile industry processor interface (MIPI) D-PHY & DSI standard specification.
- (8) In an embodiment, the clock embedding-related error may include at least one selected from a loss-of-lock error, an initialization error, a start pattern error, an end pattern error, and an encoding key error.
- (9) In an embodiment, the at least one selected from the loss-of-lock error, the initialization error, the start pattern error, the end pattern error, and the encoding key error may be selectively masked.
- (10) In an embodiment, the receiver may include a reception unit which samples the clock-embedded data to generate first encoded data and a control signal, a decoder which decodes the first encoded data to generate first data, a reception controller which receives the control signal and the first data, and a main controller which outputs the error flag.
- (11) In an embodiment, the reception unit and the decoder may detect the clock embedding-related error.
- (12) In an embodiment, the clock embedding-related error detected by the reception unit may be transmitted to the main controller through the reception controller, and the clock embedding-related error detected by the decoder may be transmitted to the main controller through the reception unit and the reception controller.
- (13) In an embodiment, the clock embedding-related error detected by the reception unit may be directly transmitted to the main controller, and the clock embedding-related error detected by the decoder may be transmitted to the main controller through the reception unit.
- (14) In an embodiment, the transmitter may include a transmission controller which generates second data, an encoder which encodes the second data to generate second encoded data, and a transmission unit which generates the clock-embedded data based on the second encoded data.
- (15) In an embodiment, the error flag may include one of a pulse of a high voltage level, a pulse of a low voltage level, a signal increasing from the low voltage level to the high voltage level, and a signal decreasing from the high voltage level to the low voltage level.
- (16) In an embodiment, a width of the pulse of the high voltage level and a width of the pulse of the low voltage level may be selectively adjusted.
- (17) In an embodiment, the receiver may generate a clock signal by using the clock training pattern and the encoded payload.
- (18) A method of driving a transceiver according to embodiments includes transmitting, by a transmitter, clock-embedded data through a line to a receiver, where the clock-embedded data includes a clock training pattern, a start pattern, an encoded payload, and an end pattern, detecting a clock embedding-related error from the clock-embedded data, and outputting, by the receiver, an

- error flag corresponding to the clock embedding-related error to the transmitter.
- (19) In an embodiment, the clock embedding-related error may include at least one selected from a loss-of-lock error, an initialization error, a start pattern error, an end pattern error, and an encoding key error.
- (20) In an embodiment, the method may further include selectively masking the at least one selected from the loss-of-lock error, the initialization error, the start pattern error, the end pattern error, and the encoding key error.
- (21) In an embodiment, the error flag may include one of a pulse of a high voltage level, a pulse of a low voltage level, a signal increasing from the low voltage level to the high voltage level, and a signal decreasing from the high voltage level to the low voltage level.
- (22) In an embodiment, the method may further include selectively adjusting a width of the pulse of the high voltage level and a width of the pulse of the low voltage level.
- (23) In an embodiment, the method may further include transmitting, by the transmitter, a reset signal to the receiver based on the error flag.
- (24) A display device according to embodiments may include a display panel including a plurality of pixels, a display panel driver including a data driver which provides data voltages to the pixels, and a timing controller which controls driving of the data driver, and a receiver which receives clock-embedded data, detects a clock embedding-related error from the clock-embedded data, and outputs an error flag corresponding to the clock embedding-related error, where the clock-embedded data includes a clock training pattern, a start pattern, an encoded payload, and an end pattern.
- (25) In an embodiment, the display panel driver may be a timing controller-embedded driver (TED) in which the timing controller is embedded in the data driver, and the display panel driver may include the receiver.
- (26) In the transceiver, the method of driving the transceiver, and the display device according to the embodiments, the clock embedding-related error may be detected from the clock-embedded data, and the error flag corresponding to the clock embedding-related error may be output, so that the clock embedding-related error, which is not included in errors defined in the MIPI D-PHY & DSI standard specification, may be effectively handled.
-

Description

BRIEF DESCRIPTION OF THE DRAWINGS

- (1) Illustrative, non-limiting embodiments will be more clearly understood from the following detailed description taken in conjunction with the accompanying drawings.
- (2) FIG. 1 is a block diagram showing a transceiver according to an embodiment of the disclosure.
- (3) FIG. 2 is a view for describing an operation of a transmitter according to an embodiment of the disclosure.
- (4) FIG. 3 is a view for describing an operation of a receiver according to an embodiment of the disclosure.
- (5) FIG. 4 is a table showing errors defined in an MIPI D-PHY & DSI standard specification.
- (6) FIG. 5 is a table showing clock embedding-related errors.
- (7) FIG. 6 is a view for describing detection and transmission of a clock embedding-related error according to an embodiment of the disclosure.
- (8) FIG. 7 is a view for describing detection and transmission of a clock embedding-related error according to an embodiment of the disclosure.
- (9) FIG. 8 is a table for describing masking of the clock embedding-related error according to an embodiment of the disclosure.
- (10) FIG. 9 is a table for describing error flags according to embodiments of the disclosure.

(11) FIG. 10 is a view for describing a method of driving a transceiver according to an embodiment of the disclosure.

(12) FIG. 11 is a block diagram showing a display device and a processor according to an embodiment of the disclosure.

DETAILED DESCRIPTION

(13) The invention now will be described more fully hereinafter with reference to the accompanying drawings, in which various embodiments are shown. This invention may, however, be embodied in many different forms, and should not be construed as limited to the embodiments set forth herein. Rather, these embodiments are provided so that this disclosure will be thorough and complete, and will fully convey the scope of the invention to those skilled in the art. Like reference numerals refer to like elements throughout.

(14) It will be understood that when an element is referred to as being “on” another element, it can be directly on the other element or intervening elements may be present therebetween. In contrast, when an element is referred to as being “directly on” another element, there are no intervening elements present.

(15) It will be understood that, although the terms “first,” “second,” “third” etc. may be used herein to describe various elements, components, regions, layers and/or sections, these elements, components, regions, layers and/or sections should not be limited by these terms. These terms are only used to distinguish one element, component, region, layer or section from another element, component, region, layer or section. Thus, “a first element,” “component,” “region,” “layer” or “section” discussed below could be termed a second element, component, region, layer or section without departing from the teachings herein.

(16) The terminology used herein is for the purpose of describing particular embodiments only and is not intended to be limiting. As used herein, “a,” “an,” “the,” and “at least one” do not denote a limitation of quantity, and are intended to include both the singular and plural, unless the context clearly indicates otherwise. For example, “an element” has the same meaning as “at least one element,” unless the context clearly indicates otherwise. “At least one” is not to be construed as limiting “a” or “an.” “Or” means “and/or.” As used herein, the term “and/or” includes any and all combinations of one or more of the associated listed items. It will be further understood that the terms “comprises” and/or “comprising,” or “includes” and/or “including” when used in this specification, specify the presence of stated features, regions, integers, steps, operations, elements, and/or components, but do not preclude the presence or addition of one or more other features, regions, integers, steps, operations, elements, components, and/or groups thereof.

(17) Furthermore, relative terms, such as “lower” or “bottom” and “upper” or “top,” may be used herein to describe one element's relationship to another element as illustrated in the Figures. It will be understood that relative terms are intended to encompass different orientations of the device in addition to the orientation depicted in the Figures. For example, if the device in one of the figures is turned over, elements described as being on the “lower” side of other elements would then be oriented on “upper” sides of the other elements. The term “lower,” can therefore, encompass both an orientation of “lower” and “upper,” depending on the particular orientation of the figure. Similarly, if the device in one of the figures is turned over, elements described as “below” or “beneath” other elements would then be oriented “above” the other elements. The terms “below” or “beneath” can, therefore, encompass both an orientation of above and below.

(18) Unless otherwise defined, all terms (including technical and scientific terms) used herein have the same meaning as commonly understood by one of ordinary skill in the art to which this disclosure belongs. It will be further understood that terms, such as those defined in commonly used dictionaries, should be interpreted as having a meaning that is consistent with their meaning in the context of the relevant art and the present disclosure, and will not be interpreted in an idealized or overly formal sense unless expressly so defined herein.

(19) Hereinafter, a transceiver, a method of driving the transceiver, and a display device according

to embodiments of the disclosure will be described in detail with reference to the accompanying drawings.

(20) FIG. 1 is a block diagram showing a transceiver **100** according to an embodiment of the disclosure.

(21) Referring to FIG. 1, an embodiment of a transceiver **100** may include a transmitter **110**, a receiver **120**, and a line **130**.

(22) The transmitter **110** may transmit clock-embedded data CEDT, which includes a clock training pattern, a start pattern, an encoded payload, and an end pattern, through the line **130**. The receiver **120** may receive the clock-embedded data CEDT, detect a clock embedding-related error from the clock-embedded data CEDT, and output an error flag ER_FG corresponding to the clock embedding-related error to the transmitter **110**. The transmitter **110** may transmit a reset signal RS to the receiver **120** based on the error flag ER_FG.

(23) An embodiment of the transmitter **110** may include a transmission unit **111**, a transmission controller **112**, and an encoder **113**. An embodiment of the receiver **120** may include a reception unit **121**, a reception controller **122**, a decoder **123**, and a main controller **124**.

(24) The transmission unit **111** may be connected to the reception unit **121** through the line **130**. The transmission unit **111** and the reception unit **121** may be referred to as data channels. The transmission unit **111** and the reception unit **121** may correspond to a physical layer and/or a data link layer of an open systems interconnection (OSI) 7-layer model, a network interface layer of a transmission control protocol/internet protocol (TCP/IP) model, or a physical layer of a mobile industry processor interface (MIPI) protocol. The physical layer of the MIPI protocol may be configured according to various predetermined specifications such as D-PHY, C-PHY, and M-PHY. Hereinafter, embodiments in which the transmission unit **111** and the reception unit **121** are configured according to a D-PHY specification of the physical layer of the MIPI protocol will be exemplarily described.

(25) The transmission controller **112** and the reception controller **122** may correspond to a network layer and/or a transport layer of the OSI 7-layer model, an internet layer and/or a transport layer of the TCP/IP model, or a protocol layer of the MIPI protocol. The protocol layer of the MIPI protocol may be configured according to various predefined specifications such as a display serial interface (DSI) and a camera serial interface (CSI). Hereinafter, embodiments in which the transmission controller **112** and the reception controller **122** are configured according to a DSI specification of the protocol layer of the MIPI protocol will be exemplarily described.

(26) The main controller **124** may correspond to a session layer, a presentation layer, and/or an application layer of the OSI 7-layer model, an application layer of the TCP/IP model, or an application layer of the MIPI protocol. Hereinafter, embodiments in which the main controller **124** corresponds to the application layer of the MIPI protocol will be exemplarily described.

(27) According to an embodiment, the transmission unit **111**, the transmission controller **112**, and the encoder **113** may be separated from each other in terms of hardware, or two or more of the transmission unit **111**, the transmission controller **112**, and the encoder **113** may be integrated with each other in terms of hardware. According to an alternative embodiment, the transmission unit **111**, the transmission controller **112**, and the encoder **113** may be separated from each other in terms of software, or two or more of the transmission unit **111**, the transmission controller **112**, and the encoder **113** may be integrated with each other in terms of software. The transmitter **110** may be configured as (or defined by) a part (hardware or software) of another controller (e.g., an application processor (AP), a graphics processing unit (GPU), a central processing unit (CPU), etc.), and may be configured as independent hardware (e.g., a transmission-only integrated circuit (IC)).

(28) According to an embodiment, the reception unit **121**, the reception controller **122**, the decoder **123**, and the main controller **124** may be separated from each other in terms of hardware, and two or more of the reception unit **121**, the reception controller **122**, the decoder **123**, and the main

controller **124** may be integrated with each other in terms of hardware. According to an alternative embodiment, the reception unit **121**, the reception controller **122**, the decoder **123**, and the main controller **124** may be separated from each other in terms of software, and two or more of the reception unit **121**, the reception controller **122**, the decoder **123**, and the main controller **124** may be integrated with each other in terms of software. The receiver **120** may be configured as a part (hardware or software) of another controller (e.g., a timing controller (TCN), a TCN-embedded driver (TED), a driver IC (D-IC), etc.), and may be configured as independent hardware (e.g., a reception-only IC).

(29) The transmission controller **112** may provide second data DT2 including a payload to the encoder **113**. The payload may be effective data to be transmitted. The payload may include variable values rather than a predetermined pattern. The encoder **113** may encode the second data DT2 to generate second encoded data EDT2 including the encoded payload, and provide the second encoded data EDT2 to the transmission unit **111**. The transmission unit **111** may generate the clock-embedded data CEDT based on the second encoded data EDT2, and transmit the clock-embedded data CEDT through the line **130**. The transmission unit **111** may add another data to the second encoded data EDT2 according to a predetermined protocol to generate the clock-embedded data CEDT.

(30) The reception unit **121** may sample the clock-embedded data CEDT to generate first encoded data EDT1 including the encoded payload. The reception unit **121** may generate a clock signal by using the clock-embedded data CEDT, and sample the clock-embedded data CEDT based on the clock signal. In an embodiment, for example, the reception unit **121** may include a clock data recovery (CDR) circuit. The reception unit **121** may provide the first encoded data EDT1 to the decoder **123**. The decoder **123** may decode the first encoded data EDT1 to generate first data DT1 including the payload, and provide the first data DT1 to the reception controller **122**.

(31) The reception unit **121** may sample the clock-embedded data CEDT to generate a control signal HS used according to the protocol. The reception unit **121** may provide the control signal HS to the reception controller **122**. According to an embodiment, the receiver **120** may further include a delay unit, and the delay unit may delay the control signal HS by a decoding time and provide the delayed control signal HS to the reception controller **122**. In such an embodiment, the decoding time may be a time used for the decoder **123** to decode the first encoded data EDT1 to generate the first data DT1.

(32) The main controller **124** may output the error flag ER_FG corresponding to the clock embedding-related error.

(33) FIG. 2 is a view for describing an operation of a transmitter **110** according to an embodiment of the disclosure.

(34) Referring to FIG. 2, in an embodiment, the encoder **113** may receive the second data DT2 including a payload PL. The encoder **113** may encode the payload PL to generate an encoded payload EPL, and add data before and after the encoded payload EPL to generate the second encoded data EDT2. In an embodiment, for example, the second encoded data EDT2 may sequentially include a clock training pattern CLK-T, a start pattern STP, the encoded payload EPL, and an end pattern EDP.

(35) The clock training pattern CLK-T may include clock information. The receiver **120** may generate a clock signal having a specific frequency and a specific phase by using the clock information. The frequency and the phase of the clock signal generated by the clock data recovery circuit of the receiver **120** may be undesirably changed by an external factor (noise, a temperature, etc.). The receiver **120** may correct the frequency and the phase of the clock signal by using the clock training pattern CLK-T. According to an embodiment, the clock training pattern CLK-T may be a pattern in which one one and one zero are alternately repeated (e.g., 01010101 . . .).

According to an alternative embodiment, the clock training pattern CLK-T may include repeating units of a plurality of consecutive zeros and a plurality of consecutive ones (e.g.,

0000111100001111 . . .). According to embodiments, frequency information and phase information represented by the clock training pattern CLK-T may vary according to the number of consecutive zeros or the number of consecutive ones.

(36) The start pattern STP may be a pattern for indicating the start of transmission of the encoded payload EPL. The start pattern STP may be a pattern that may not be included (that is, prohibited from being used) in the encoded payload EPL. In an embodiment, for example, the start pattern STP may be configured as 24b'011100_000000_111111_110001'.

(37) The encoded payload EPL may include the clock information. In an embodiment, for example, where the encoded payload EPL includes many consecutive zeros or many consecutive ones, the signal may have less transition, so that the phase of the clock signal may not be sufficiently corrected in the reception unit **121**, and thus a skew of the clock signal may be caused. Therefore, the encoder **113** may encode the payload PL in a way such that the encoded payload EPL may have sufficiently many transitions (a change from 0 to 1 or a change from 1 to 0) as compared with the payload PL. In an embodiment, the encoder **113** may encode the payload PL in a way such that the encoded payload EPL may periodically have bits having a specific pattern.

(38) The end pattern EDP may be a pattern for indicating the end of transmission of the encoded payload EPL. In an embodiment, for example, the end pattern EDP may be configured as 24b'011100_111111_000000_110001'. The end pattern EDP may be a pattern that may not be included (that is, prohibited from being used) in the encoded payload EPL.

(39) The transmission unit **111** may receive the second encoded data EDT2 including the encoded payload EPL. The transmission unit **111** may add and transmit another data before and after the second encoded data EDT2 according to the predetermined protocol. In an embodiment, for example, where the predetermined protocol is the MIPI protocol, the transmission unit **111** may sequentially transmit a first pattern HS-zero, a second pattern HS-sync, the second encoded data EDT2, a third pattern HS-trail, and a fourth pattern HS-exit.

(40) The first pattern HS-zero may be a pattern for indicating a waiting period after entering a high-speed mode from a low-power mode. In an embodiment, for example, the first pattern HS-zero may be a pattern in which zero is repeated. The second pattern HS-sync may be a pattern for indicating the start of transmission of the second encoded data EDT2. In an embodiment, for example, the second pattern HS-sync may have a value of 0xB8h or a value of 00011101. The third pattern HS-trail may be a pattern for indicating the end of transmission of the second encoded data EDT2. The third pattern HS-trail may be a pattern in which a value opposite to last data of the second encoded data EDT2 is repeated. In an embodiment, for example, when the last data (bit) of the second encoded data EDT2 is 0, the third pattern HS-trail may be a pattern in which one is repeated. The fourth pattern HS-exit may be a pattern for indicating the end of the high-speed mode and the start of the low-power mode.

(41) FIG. 3 is a view for describing an operation of a receiver **120** according to an embodiment of the disclosure.

(42) Referring to FIG. 3, in an embodiment, the reception unit **121** may sample the clock-embedded data CEDT to provide the first encoded data EDT1 including the encoded payload EPL to the decoder **123**.

(43) The decoder **123** may decode the first encoded data EDT1 (i.e., the encoded payload EPL) to generate the first data DT1, and provide the first data DT1 to the reception controller **122**. The first data DT1 may include the payload PL and a dummy pattern DMY.

(44) The dummy pattern DMY may be encoded in advance by the encoder **113** to be embedded in the encoded payload EPL, or may be added by the decoder **123**. The dummy pattern DMY may be data in which an identical value is repeated. In an embodiment, for example, when a last value of the payload PL is 0, the dummy pattern DMY may be data in which one is repeated, and when the last value of the payload PL is 1, the dummy pattern DMY may be data in which zero is repeated.

(45) FIG. 4 is a table showing errors defined in an MIPI D-PHY & DSI standard specification.

(46) Referring to FIG. 4, when an error defined in an MIPI D-PHY & DSI standard specification occurs, the receiver **120** may transmit an error signal to the transmitter **110**. In an embodiment, for example, the error signal may be a 16-bit signal, and a state error may be preset for each bit.

(47) In an embodiment, for example, a bit in an address 0 of the error signal may indicate an occurrence state of a start-of-transmission (SoT) error, and the SoT error may be an error that occurs when transmission is performed without conforming to a protocol specified in an MIPI alliance.

(48) In an embodiment, for example, the bit in the address 1 of the error signal may indicate an occurrence state of an SoT synchronization error. When a state error corresponding to each address is detected, a bit of the corresponding address may be 1, and when the state error corresponding to each address is not detected, the bit of the corresponding address may be 0.

(49) FIG. 5 is a table showing clock embedding-related errors.

(50) Referring to FIG. 5, an embodiment of the clock embedding-related error may include at least one of a loss-of-lock error, an initialization error, a start pattern error (STP error), an end pattern error (EDP error), and an encoding key error. The clock embedding-related error may refer to an error that may occur in a scheme of embedding clock information in data, and may not be included in an error defined in the MIPI D-PHY & DSI standard specification described above.

(51) The loss-of-lock error may indicate a state in which the clock data recovery (CDR) circuit is out of a locked state without normally restoring the clock signal during a high speed data transmission (HSDT) operation. The initialization error may indicate a state in which the clock data recovery circuit is not normally locked even though the clock data recovery circuit has terminated an initialization operation based on the clock training pattern CLK-T.

(52) The start pattern error may indicate a case in which the start pattern STP is not normally input or a case in which an error occurs during a data restoration (e.g., clock data restoration) process even though the start pattern STP has been normally input. The end pattern error may indicate a case in which the end pattern EDP is not normally input.

(53) The encoding key error may indicate a case in which an input encoding key is a prohibited pattern that may not be generated based on an encoding protocol.

(54) FIG. 6 is a view for describing detection and transmission of a clock embedding-related error ER according to an embodiment of the disclosure.

(55) Referring to FIG. 6, in an embodiment, the reception unit **121** and the decoder **123** may detect a clock embedding-related error ER. According to an embodiment, the reception unit **121** may detect at least one selected from the loss-of-lock error, the initialization error, the start pattern error, and the end pattern error, and the decoder **123** may detect the encoding key error.

(56) The clock embedding-related error ER detected by the reception unit **121** may be transmitted to the main controller **124** through the reception controller **122**, and the clock embedding-related error ER detected by the decoder **123** may be transmitted to the main controller **124** through the reception unit **121** and the reception controller **122**. In such an embodiment, the clock embedding-related error ER detected by the reception unit **121** may be transmitted to the main controller **124** through a path passing through the reception controller **122** ({circle around (1)}), and the clock embedding-related error ER detected by the decoder **123** may be transmitted to the main controller **124** through a path passing through the reception unit **121** and the reception controller **122** ({circle around (1)}+{circle around (2)}).

(57) FIG. 7 is a view for describing detection and transmission of a clock embedding-related error ER according to an embodiment of the disclosure.

(58) Referring to FIG. 7, in an embodiment, the clock embedding-related error ER detected by the reception unit **121** may be directly transmitted to the main controller **124**, and the clock embedding-related error ER detected by the decoder **123** may be transmitted to the main controller **124** through the reception unit **121**.

(59) In such an embodiment, the clock embedding-related error ER detected by the reception unit

121 may be transmitted to the main controller **124** through a path that does not pass through the reception controller **122** ({circle around (3)}), and the clock embedding-related error ER detected by the decoder **123** may be transmitted to the main controller **124** through a path that passes through the reception unit **121** and does not pass through the reception controller **122** ({circle around (2)}+{circle around (3)}).

(60) FIG. **8** is a table for describing masking of the clock embedding-related error according to an embodiment of the disclosure.

(61) Referring to FIG. **8**, at least one selected from clock embedding-related errors may be selectively masked. According to an embodiment, at least one selected from the loss-of-lock error, the initialization error, the start pattern error, the end pattern error, and the encoding key error may be selectively masked.

(62) In an embodiment, for example, as shown in FIG. **8**, in a case where the loss-of-lock error is selectively masked, the main controller **124** may not output the error flag ER_FG even when the loss-of-lock error is detected by the reception unit **121**. In an embodiment, as shown in FIG. **8**, in a case where the initialization error is not selectively masked, the main controller **124** may output the error flag ER_FG when the initialization error is detected by the reception unit **121**.

(63) FIG. **9** is a table for describing error flags ER_FG according to embodiments of the disclosure.

(64) Referring to FIG. **9**, in an embodiment, the error flag ER_FG may include one of a pulse HP of a high voltage level HVL, a pulse LP of a low voltage level LVL, a signal LTHS increasing from the low voltage level LVL to the high voltage level HVL, and a signal HTLS decreasing from the high voltage level HVL to the low voltage level LVL. The high voltage level HVL in the signal LTHS increasing from the low voltage level LVL to the high voltage level HVL may indicate occurrence of the clock embedding-related error, and the low voltage level LVL in the signal HTLS decreasing from the high voltage level HVL to the low voltage level LVL may indicate occurrence of the clock embedding-related error.

(65) According to an embodiment, a width WT of the pulse HP of the high voltage level HVL and a width WT of the pulse LP of the low voltage level LVL may be selectively adjusted. A width and/or a frequency of the clock signal of the transmitter **110** may be different from a width and/or a frequency of the clock signal of the receiver **120**, or a setting for detecting the error flag ER_FG of the transmitter **110** may be different from a setting of generating the error flag ER_FG of the receiver **120**. Accordingly, the width WT of the pulse HP of the high voltage level HVL and the width WT of the pulse LP of the low voltage level LVL may be increased or decreased so that the error flag ER_FG generated by the receiver **120** may be detected by the transmitter **110**.

(66) FIG. **10** is a view for describing a method of driving a transceiver **100** according to an embodiment of the disclosure.

(67) Referring to FIG. **10**, in an embodiment of a method of driving a transceiver **100**, a transmitter **110** may transmit clock-embedded data CEDT to a receiver **120** through a line **130**.

(68) In such an embodiment, the receiver **120** may detect a clock embedding-related error ER from the clock-embedded data CEDT. A reception unit **121** and a decoder **123** may detect the clock embedding-related error ER including at least one selected from a loss-of-lock error, an initialization error, a start pattern error, an end pattern error, and an encoding key error. According to an embodiment, the reception unit **121** may detect at least one selected from the loss-of-lock error, the initialization error, the start pattern error, and the end pattern error, and the decoder **123** may detect the encoding key error.

(69) In such an embodiment, the reception unit **121** and the decoder **123** may transmit the clock embedding-related error ER to a main controller **124**. According to an embodiment, the clock embedding-related error ER detected by the reception unit **121** may be transmitted to the main controller **124** through a reception controller **122**, and the clock embedding-related error ER detected by the decoder **123** may be transmitted to the main controller **124** through the reception unit **121** and the reception controller **122**. According to an alternative embodiment, the clock

embedding-related error ER detected by the reception unit **121** may be directly transmitted to the main controller **124**, and the clock embedding-related error ER detected by the decoder **123** may be transmitted to the main controller **124** through the reception unit **121**.

(70) In such an embodiment, the main controller **124** may output an error flag ER_FG corresponding to the clock embedding-related error ER to the transmitter **110**. The error flag ER_FG may include one of a pulse of a high voltage level, a pulse of a low voltage level, a signal increasing from the low voltage level to the high voltage level, and a signal decreasing from the high voltage level to the low voltage level.

(71) According to an embodiment, a width of the pulse of the high voltage level and a width of the pulse of the low voltage level may be selectively adjusted so that the error flag ER_FG may be detected by the transmitter **110**.

(72) According to an embodiment, at least one selected from the loss-of-lock error, the initialization error, the start pattern error, the end pattern error, and the encoding key error may be selectively masked. Accordingly, even when a clock embedding-related error ER that is selectively masked occurs, the main controller **124** may not output the error flag ER_FG.

(73) In such an embodiment, the transmitter **110** may transmit a reset signal RS to the receiver **120** based on the error flag ER_FG. The receiver **120** may be initialized or may initiate reception of the clock-embedded data CEDT based on the reset signal RS transmitted from the transmitter **110**.

(74) FIG. **11** is a block diagram showing a display device **200** and a processor **300** according to an embodiment of the disclosure.

(75) Referring to FIG. **11**, an embodiment of a display device **200** may include a display panel **210**, a scan driver **220**, and a display panel driver **230**. The display panel driver **230** may include a data driver **232** and a timing controller **234**.

(76) The display panel **210** may display an image. The display panel **210** may include a plurality of pixels PX. The pixels PX may be substantially arranged in a matrix shape. Each of the pixels PX may emit a light, and the display panel **210** may display an image in which lights emitted from the pixels PX are combined. According to an embodiment, each of the pixels PX may emit a red light, a green light, a blue light, or a white light.

(77) The scan driver **220** may generate scan signals SS based on a scan control signal SCS. The scan driver **220** may provide the scan signals SS to the pixels PX. According to an embodiment, the scan driver **220** may be mounted on the display panel **210** in the form of a circuit.

(78) The data driver **232** may generate data voltages VDT based on a data control signal DCS and image data ID. The data driver **232** may generate the data voltages VDT corresponding to the image data ID. The data driver **232** may provide the data voltages VDT to the pixels PX.

(79) The timing controller **234** may control driving of the scan driver **220**. The timing controller **234** may generate the scan control signal SCS based on a control signal. The control signal may include a clock signal, a horizontal synchronization signal, a vertical synchronization signal, and the like. The timing controller **234** may provide the scan control signal SCS to the scan driver **220**.

(80) The timing controller **234** may control driving of the data driver **232**. The timing controller **234** may generate the data control signal DCS and the image data ID based on the control signal and input image data, and provide the data control signal DCS and the image data ID to the data driver **232**.

(81) According to an embodiment, the display panel driver **230** may be a timing controller-embedded driver (TED) in which the timing controller **234** is embedded in the data driver **232**. In embodiments described above, the display panel driver **230** may include the receiver **120** described above.

(82) The processor **300** may be one of an application processor (AP), a graphics processing unit (GPU), and a central processing unit (CPU). The processor **300** may include the transmitter **110** described above.

(83) The transceiver and the display device according to the embodiments may be applied to a

display device included in a computer, a notebook, a mobile phone, a smart phone, a smart pad, a PMP, a PDA, an MP3 player, or the like.

(84) The invention should not be construed as being limited to the embodiments set forth herein. Rather, these embodiments are provided so that this disclosure will be thorough and complete and will fully convey the concept of the invention to those skilled in the art.

(85) While the invention has been particularly shown and described with reference to embodiments thereof, it will be understood by those of ordinary skill in the art that various changes in form and details may be made therein without departing from the spirit or scope of the invention as defined by the following claims.

Claims

1. A transceiver comprising: a transmitter which transmits clock-embedded data through a line, wherein the clock-embedded data includes a clock training pattern, a start pattern, an encoded payload, and an end pattern, which are arranged in a listed order of the clock training pattern, the start pattern, the encoded payload, and the end pattern in the clock-embedded data; and a receiver which receives the clock-embedded data, detects a clock embedding-related error from the clock-embedded data, and outputs an error flag corresponding to the clock embedding-related error to the transmitter, wherein the clock training pattern includes clock information, the start pattern is a pattern for indicating a start of transmission of the encoded payload, the encoded payload includes the clock information, the end pattern is a pattern for indicating an end of transmission of the encoded payload, the receiver generates a clock signal having a specific frequency and a specific phase by using the clock information, and the transmitter is included in a processor and the receiver is included in a timing controller which controls driving of a data driver.
2. The transceiver of claim 1, wherein the clock embedding-related error is not included in errors defined in a mobile industry processor interface (MIPI) D-PHY & DSI standard specification.
3. The transceiver of claim 1, wherein the clock embedding-related error includes at least one selected from a loss-of-lock error, an initialization error, a start pattern error, an end pattern error, and an encoding key error.
4. The transceiver of claim 3, wherein the at least one selected from the loss-of-lock error, the initialization error, the start pattern error, the end pattern error, and the encoding key error is selectively masked.
5. The transceiver of claim 1, wherein the receiver includes: a reception unit which samples the clock-embedded data to generate first encoded data and a control signal; a decoder which decodes the first encoded data to generate first data; a reception controller which receives the control signal and the first data; and a main controller which outputs the error flag.
6. The transceiver of claim 5, wherein the reception unit and the decoder detect the clock embedding-related error.
7. The transceiver of claim 6, wherein the clock embedding-related error detected by the reception unit is transmitted to the main controller through the reception controller, and the clock embedding-related error detected by the decoder is transmitted to the main controller through the reception unit and the reception controller.
8. The transceiver of claim 6, wherein the clock embedding-related error detected by the reception unit is directly transmitted to the main controller, and the clock embedding-related error detected by the decoder is transmitted to the main controller through the reception unit.
9. The transceiver of claim 5, wherein the transmitter includes: a transmission controller which generates second data; an encoder which encodes the second data to generate second encoded data; and a transmission unit which generates the clock-embedded data based on the second encoded data.
10. The transceiver of claim 1, wherein the error flag includes one of a pulse of a high voltage

- level, a pulse of a low voltage level, a signal increasing from the low voltage level to the high voltage level, and a signal decreasing from the high voltage level to the low voltage level.
11. The transceiver of claim 10, wherein a width of the pulse of the high voltage level and a width of the pulse of the low voltage level are selectively adjusted.
12. The transceiver of claim 1, wherein the receiver generates a clock signal by using the clock training pattern and the encoded payload.
13. A method of driving a transceiver, the method comprising: transmitting, by a transmitter, clock-embedded data through a line to a receiver, wherein the clock-embedded data includes a clock training pattern, a start pattern, an encoded payload, and an end pattern, which are arranged in a listed order of the clock training pattern, the start pattern, the encoded payload, and the end pattern in the clock-embedded data; detecting a clock embedding-related error from the clock-embedded data; and outputting, by the receiver, an error flag corresponding to the clock embedding-related error to the transmitter, wherein the clock training pattern includes clock information, the start pattern is a pattern for indicating a start of transmission of the encoded payload, the encoded payload includes the clock information, the end pattern is a pattern for indicating an end of transmission of the encoded payload, the receiver generates a clock signal having a specific frequency and a specific phase by using the clock information, and the transmitter is included in a processor and the receiver is included in a timing controller which controls driving of a data driver.
14. The method of claim 13, wherein the clock embedding-related error includes at least one selected from a loss-of-lock error, an initialization error, a start pattern error, an end pattern error, and an encoding key error.
15. The method of claim 14, further comprising: selectively masking the at least one selected from the loss-of-lock error, the initialization error, the start pattern error, the end pattern error, and the encoding key error.
16. The method of claim 13, wherein the error flag includes one of a pulse of a high voltage level, a pulse of a low voltage level, a signal increasing from the low voltage level to the high voltage level, and a signal decreasing from the high voltage level to the low voltage level.
17. The method of claim 16, further comprising: selectively adjusting a width of the pulse of the high voltage level and a width of the pulse of the low voltage level.
18. The method of claim 13, further comprising: transmitting, by the transmitter, a reset signal to the receiver based on the error flag.
19. A display device comprising: a display panel including a plurality of pixels; a display panel driver including a data driver which provides data voltages to the pixels, and a timing controller which controls driving of the data driver; and a receiver which receives clock-embedded data from a transmitter, detects a clock embedding-related error from the clock-embedded data, and outputs an error flag corresponding to the clock embedding-related error to the transmitter, wherein the clock-embedded data includes a clock training pattern, a start pattern, an encoded payload, and an end pattern, which are arranged in a listed order of the clock training pattern, the start pattern, the encoded payload, and the end pattern in the clock-embedded data, wherein the clock training pattern includes clock information, the start pattern is a pattern for indicating a start of transmission of the encoded payload, the encoded payload includes the clock information, the end pattern is a pattern for indicating an end of transmission of the encoded payload, the receiver generates a clock signal having a specific frequency and a specific phase by using the clock information, and the transmitter is included in a processor and the receiver is included in the timing controller.
20. The display device of claim 19, wherein the display panel driver is a timing controller-embedded driver in which the timing controller is embedded in the data driver, and the display panel driver includes the receiver.
-