

US Patent & Trademark Office

Patent Public Search | Text View

United States Patent
Kind Code
Date of Patent
Inventor(s)

12418270
B2
September 16, 2025
Shaya; Benjamin Louis et al.

Methods and systems for automatically equalizing audio output based on room position

Abstract

The various implementations described herein include methods, devices, and systems for automatic audio equalization. In one aspect, a method is performed at an electronic device that includes speakers, microphones, processors and memory. The electronic device outputs audio user content from the speakers and automatically equalizes subsequent audio output of the device without user input. The automatic equalization includes: (1) obtaining audio content signals, including receiving outputted audio content at each microphone; (2) determining from the audio content signals phase differences between microphones; (3) obtaining a feature vector based on the phase differences; (4) obtaining a frequency correction from a correction database based on the obtained feature vector; and (5) applying the obtained frequency correction to the subsequent audio output.

Inventors: Shaya; Benjamin Louis (Mountain View, CA), Larsen; Rasmus (San Jose, CA), Lyon; Richard F. (Los Altos, CA), Smedegaard; Michael (Danville, CA)

Applicant: GOOGLE LLC (Mountain View, CA)

Family ID: 1000008820155

Assignee: GOOGLE LLC (Mountain View, CA)

Appl. No.: 18/405641

Filed: January 05, 2024

Prior Publication Data

Document Identifier	Publication Date
US 20240146274 A1	May. 02, 2024

Related U.S. Application Data

continuation parent-doc US 17191510 20210303 US 11888456 child-doc US 18405641
continuation parent-doc US 16719847 20191218 US 11005440 20210511 child-doc US 17191510
continuation parent-doc US 16058885 20180808 US 10523172 20191231 child-doc US 16719847

Publication Classification

Int. Cl.: **H04R29/00** (20060101); **G06F3/16** (20060101); **H03G5/16** (20060101); **H04R1/40** (20060101); **H04R3/00** (20060101); **H04R3/04** (20060101); **H04R3/12** (20060101); **H04S7/00** (20060101); G06N3/04 (20230101)

U.S. Cl.:

CPC **H03G5/165** (20130101); **G06F3/167** (20130101); **H04R1/403** (20130101); **H04R1/406** (20130101); **H04R3/005** (20130101); **H04R3/04** (20130101); **H04R3/12** (20130101); **H04R29/001** (20130101); **H04S7/301** (20130101); **H04S7/305** (20130101); G06N3/04 (20130101); H04R2420/07 (20130101); H04R2430/03 (20130101); H04S2420/00 (20130101); H04S2420/07 (20130101)

Field of Classification Search

CPC: H04R (3/005); H04R (29/001); H04R (2420/07); H04R (1/406); H04R (1/403); H04S (7/301); H04S (7/30)

USPC: 381/56; 381/103; 381/104; 381/107

References Cited

U.S. PATENT DOCUMENTS

Patent No.	Issued Date	Patentee Name	U.S. Cl.	CPC
4340780	12/1981	Odlen	N/A	N/A
5754774	12/1997	Bittinger et al.	N/A	N/A
6731760	12/2003	Pedersen	N/A	N/A
6766025	12/2003	Levy et al.	N/A	N/A
7769183	12/2009	Bharitkar et al.	N/A	N/A
8045721	12/2010	Burgan et al.	N/A	N/A
8331585	12/2011	Hagen et al.	N/A	N/A
8676728	12/2013	Velusamy et al.	N/A	N/A
9020153	12/2014	Britt, Jr.	N/A	N/A
9185199	12/2014	Zurek et al.	N/A	N/A
9219460	12/2014	Bush	N/A	N/A
9294859	12/2015	Ivanov et al.	N/A	N/A
9351091	12/2015	Ivanov et al.	N/A	N/A
9438996	12/2015	Maher et al.	N/A	N/A
9521497	12/2015	Schuster et al.	N/A	N/A
9689960	12/2016	Barton et al.	N/A	N/A
9763018	12/2016	McPherson et al.	N/A	N/A
9826328	12/2016	Mehta et al.	N/A	N/A
9888319	12/2017	Soulodre	N/A	H04R 5/02
9952825	12/2017	Sheen	N/A	N/A
9992595	12/2017	Choisel	N/A	H04S 7/305
10051393	12/2017	Rabinowitz	N/A	H04R 29/002
10127008	12/2017	Sheen et al.	N/A	N/A
10149087	12/2017	Choisel	N/A	H04S 7/301

10283137	12/2018	Pakarinen et al.	N/A	N/A
10440492	12/2018	Crockett	N/A	H04S 7/307
10459684	12/2018	Shih et al.	N/A	N/A
10523172	12/2018	Shaya et al.	N/A	N/A
11264044	12/2021	Delcroix et al.	N/A	N/A
11513216	12/2021	Kamath Koteshwara et al.	N/A	N/A
2003/0235318	12/2002	Bharitkar et al.	N/A	N/A
2005/0031129	12/2004	Devantier et al.	N/A	N/A
2005/0195984	12/2004	Miura et al.	N/A	N/A
2005/0207592	12/2004	Sporer et al.	N/A	N/A
2006/0153391	12/2005	Hooley et al.	N/A	N/A
2007/0025557	12/2006	Nackvi	N/A	N/A
2008/0075303	12/2007	Kim et al.	N/A	N/A
2008/0219470	12/2007	Kimijima	N/A	N/A
2009/0110218	12/2008	Swain	N/A	N/A
2011/0103590	12/2010	Christoph	N/A	N/A
2011/0163972	12/2010	Anzures et al.	N/A	N/A
2012/0183165	12/2011	Foo et al.	N/A	N/A
2013/0064042	12/2012	Aarts et al.	N/A	N/A
2013/0216071	12/2012	Maher et al.	N/A	N/A
2013/0346559	12/2012	Van Erven et al.	N/A	N/A
2014/0003635	12/2013	Mohammad et al.	N/A	N/A
2014/0064492	12/2013	Lakkundi et al.	N/A	N/A
2014/0185852	12/2013	Pereira	N/A	N/A
2014/0274212	12/2013	Zurek et al.	N/A	N/A
2015/0163616	12/2014	Chatterjee	N/A	N/A
2015/0289076	12/2014	Zhu et al.	N/A	N/A
2015/0341729	12/2014	Meskens et al.	N/A	N/A
2016/0029142	12/2015	Isaac	N/A	N/A
2016/0219392	12/2015	Vilermo et al.	N/A	N/A
2016/0315384	12/2015	van Erven et al.	N/A	N/A
2016/0366517	12/2015	Chandran et al.	N/A	N/A
2017/0025873	12/2016	Fathollahi	N/A	N/A
2017/0041445	12/2016	Ukai et al.	N/A	N/A
2017/0123755	12/2016	Hersh et al.	N/A	N/A
2017/0188167	12/2016	Li et al.	N/A	N/A
2017/0280223	12/2016	Cavarra et al.	N/A	N/A
2017/0295440	12/2016	Gran et al.	N/A	N/A
2018/0063626	12/2017	Pong et al.	N/A	N/A
2018/0098167	12/2017	Welch et al.	N/A	N/A
2018/0364901	12/2017	Fan	N/A	N/A
2019/0075414	12/2018	Bush	N/A	N/A
2021/0294845	12/2020	Bharitkar et al.	N/A	N/A

FOREIGN PATENT DOCUMENTS

Patent No.	Application Date	Country	CPC
103155526	12/2012	CN	N/A
103517178	12/2013	CN	N/A
104898970	12/2014	CN	N/A
105224280	12/2015	CN	N/A
105260071	12/2015	CN	N/A
105867766	12/2015	CN	N/A

106708403	12/2016	CN	N/A
0 772 374	12/1996	EP	N/A
2 567 554	12/2012	EP	N/A
2 986 034	12/2015	EP	N/A
WO-2011/139502	12/2010	WO	N/A
WO-2012/040363	12/2011	WO	N/A
WO-2014/036121	12/2013	WO	N/A
WO-2018/026799	12/2017	WO	N/A

OTHER PUBLICATIONS

International Preliminary Report on Patentability for Application No. PCT/US2018/042345, dated Apr. 8, 2020. cited by applicant

International Search Report and Written Opinion for Application No. PCT/US2018/042345, dated Dec. 21, 2018. cited by applicant

International Search Report and Written Opinion for Application No. PCT/US2018/045703, dated Nov. 14, 2019. cited by applicant

Jan Abildgaard Pedersen, “Adjusting a Loudspeaker to Its Acoustic Environmen—The ABC System,” Audio Engineer Society Convention Paper 5880 (Oct. 10-13, 2003). cited by applicant

Excerpts from Andrew Tanenbaum, Computer Networks (4th ed. 2003). cited by applicant

Excerpts from Morfey, Christopher L., Dictionary of Acoustics (2001). cited by applicant

BeoLab 5 Guide Retrieved from the Internet at:

<URL:https://content.abt.com/documents/6163/BeoLab5_om.pdf>. cited by applicant

Pioneer, “What is MCACC?,” (2021). Retrieved from the Internet at:

<URL:https://www.pioneerhomeusa.com/mcacc/>. cited by applicant

Creative, “Creative Unveils the World’s First Self-Calibrating Wireless Speaker System—the Creative D5xm™ Intelligent Wireless Speakers,” (2021). Retrieved from the Internet at:

<URL:https://sg.creative.com/corporate/pressroom?id=13359>. cited by applicant

Welcome to REW (2004-2020). Retrieved from the Internet at:

<URL:https://www.roomeqwizard.com/betahelp/help_en-GB/html/welcome.html>. cited by applicant

Anthem, “Current Products—Room Correction—Anthem Room Correction,” (2021). Retrieved from the Internet at: <URL:https://www.anthemav.com/products-current/series=arc/type=room-correction>. cited by applicant

“What is Audyssey MultEQ XT?” (2021). Retrieved from the Internet at:

<URL:https://denon.custhelp.com/app/answers/detail/a_id/32/~audyssey-multeq-xt>. cited by applicant

DIRAC Live, “Play or Record your favorite music. Experience music as it is intended,” (2021). Retrieved from the Internet at: <URL:https://live.dirac.com/>. cited by applicant

Trinnov Audio (2021). Retrieved from the Internet at: <URL:https://www.trinnov.com/>. cited by applicant

Sony, “help Guide; Multi Channel AV RECEIVERSTR-DH750/STR-DH550,” (2014). Retrieved from the Internet at: <URL:https://helpguide.sony.net/ha/strdh7555/v1/en/contents/TP0000299119.html>. cited by applicant

Bose, “Bose Soundbar 500,” (2021). Retrieved from the Internet at:

<URL:https://www.bose.com/en_us/support/articles/HC1971/productCodes/bose_soundbar_500/article.html>. cited by applicant

Yamaha, “Optimizing the speaker settings automatically (YPAO),” (2019). Retrieved from the Internet at:

<URL:https://manual.yamaha.com/av/18/rxv685/en-US/311793035.html>. cited by applicant

Google LLC, International Preliminary Report on Patentability, PCT/US2018/042345, Apr. 8, 2020, 13 pgs. cited by applicant

Google LLC, International Search Report/Written Opinion, PCT/US2018/042345, Dec. 21, 2018, 19 pgs. cited by applicant

Google LLC, International Search Report/Written Opinion, PCT/US2019/045703, Nov. 14, 2019, 9 pgs. cited by applicant

Notification of First Office Action for Chinese Application No. 201980053721.X, dated Aug. 23, 2021. cited

by applicant

First Examination Report for India Application No. 201947047310, dated Oct. 8, 2021. cited by applicant
Notification of Second Office Action for Chinese Application No. 201980053721.X, dated Jan. 27, 2022. cited
by applicant

Office Action for European Application No. 18753503.4, dated Jul. 13, 2022. cited by applicant

Primary Examiner: Paul; Disler

Attorney, Agent or Firm: MARSHALL, GERSTEIN & BORUN LLP

Background/Summary

CROSS-REFERENCE TO RELATED APPLICATIONS (1) This application is a continuation of U.S. patent application Ser. No. 17/191,510, filed Mar. 3, 2021, which is a continuation of U.S. patent application Ser. No. 16/719,847 (now U.S. Pat. No. 11,005,440), filed Dec. 18, 2019, which is a continuation of U.S. patent application Ser. No. 16/058,885 (now U.S. Pat. No. 10,523,172), filed Aug. 8, 2018, which claims priority to U.S. Provisional Patent Application No. 62/568,216, filed Oct. 4, 2017, and claims priority to U.S. Provisional Patent Application No. 62/568,219, filed Oct. 4, 2017, all of which are incorporated by reference herein in their entireties. (2) This application is related to U.S. patent application Ser. No. 16/058,820 (now U.S. Pat. No. 10,734,963), filed Aug. 8, 2018, and U.S. Pat. No. 6,731,760, each of which is incorporated by reference herein in its entirety.

FIELD

(1) This relates generally to audio equalization, including but not limited to methods and systems for automatic audio equalization not requiring user action.

BACKGROUND

(2) Electronic devices integrated with microphones and speakers have been widely used to collect voice inputs from users and to output sound (e.g., music and speech). The quality of the audio output can be affected by factors such as room environment and the placement of the speakers in the room. Manual audio equalization, a process in which the gain (response) for different frequencies of the audio output is adjusted, is commonly used to improve the quality of the output sound. However, manual equalization is a cumbersome and time consuming task for the user. Moreover, it requires a lot of knowledge about speakers, microphones, and rooms, which is too advanced for the average user.

(3) Accordingly, there is a need for users to be able to experience high quality audio without requiring time and effort of the user or a detailed knowledge of speakers, microphones, and audio equalization processes. It is desirable for an electronic device to be able to perform audio equalization automatically, independent of any user interaction.

SUMMARY

(4) There is a need for methods, devices, and systems for automatic audio equalization. Various implementations of systems, methods and devices within the scope of the appended claims each have several aspects, no single one of which is solely responsible for the attributes described herein. Without limiting the scope of the appended claims, after considering this disclosure, and particularly after considering the section entitled “Detailed Description” one will understand how the aspects of various implementations are used to automatically (without user inputs) equalize audio output.

(5) Audio devices, including electronic devices integrated with microphones and speakers, are widely used to collect voice inputs from users and to output sound such as music or speech. The output audio quality, and accordingly a user's listening experience, can be affected by factors such as the style of the room and the placement of the device/speakers in the room. For example, rooms with hard surfaces suffer from noticeable echo problems. The placement of a speaker at or near a boundary such as on the floor or next to a wall reinforces low frequency tones and can lead to a “boomy” bass. Thus, in order to achieve consistent output audio quality, equalization (e.g., correction) of bass frequencies is needed to

counteract the influence of the room and placement.

(6) Manual room equalization is typically a cumbersome process that must be repeated each time the room or placement changes. A user must have a microphone and has to record audio output responses at various positions in a room using the microphone. The user must then apply the required correction based on the collected responses. Furthermore, this manual equalization process requires a lot of knowledge about speakers, microphones, and rooms, which is too advanced for the average user. Automatic audio equalization provides an opportunity for users to achieve the best listening experience and at the same time, avoid the need for any setup or calibration process. Moreover, an automatic equalization process enables a user to rearrange the room or move the speakers without having to worry about conducting another tiresome manual equalization.

(7) There is a need to adjust a frequency response or equalization of the signal driving a speaker device to make it sound consistent whether it is placed in the open, or near a wall, or in a corner.

(8) Some methods of equalization use a microphone placed directly in front of the speaker (e.g., in two positions in front of the speaker). A formula is provided for estimating acoustic radiation resistance, as a function of frequency, which correlates with how much power the speaker couples into the room, so it can be used to estimate a compensating equalization when reflections from a wall cause an increase in radiation resistance at low frequencies. However, a manual approach with external microphones is not a viable solution in some circumstances.

(9) In accordance with some implementations, this adjustment is performed using microphones within the speaker device. This avoids the need for any setup or calibration process, or remote sensors.

(10) In accordance with some implementations, an automated equalization method uses microphones on top of a speaker, one near the front of the speaker and one near the back of the speaker, to sense the relative contributions of a wave traveling from the speaker toward the wall(s) behind and any waves reflected from those walls. In some instances and implementations, at low enough frequency (e.g., where the wavelength is long compared to the round trip distance to the reflectors), a certain delay, or phase shift, from a wave directly from the speaker is anticipated between the microphones; and a reduction of that delay or phase shift is anticipated between the microphones for a wave reflecting off the wall(s) behind the speaker.

(11) At higher frequencies, the effect of the reflection is more complicated, but with patterns that can be learned and recognized to retrieve a good equalization for each position. Therefore, in accordance with some implementations, when playing music, an automated equalization method measures the relative phases, using the music as stimulus, and performs some frequency analysis to estimate the phase pattern features.

(12) In some implementations, the electronic device includes a pair of microphones that are located on the sides of a speaker (e.g., in addition to microphones on a top of the speaker device). In some implementations, the device comprises multiple pairs of microphones with front-back separation. In some implementation, the multiple pairs of microphones are located on both the top and the sides of the speaker(s). In some implementations, the microphones are only on the body of the speaker, away from the drivers, not out in front. In some implementations, the microphones internal to the speaker device. For example, the microphones and the speakers are components of a same electronic device. In some implementations, the microphones are in internal positions where they are also useful for other functions such as speech recognition (e.g., in a voice-enabled smart speaker). In some implementations, the microphones are positioned to capture audio from one or more persons in the vicinity of the speaker device.

(13) In some implementations, the system performs audio equalization based on user content (e.g., music) output of the speaker rather than requiring a test signal (e.g., no beeps or sweep tones). In some implementations, phase shifts in received audio output are measured using one or more pairs of microphones. In some implementations, the relative phase (phase difference) between one or more pairs of microphones is measured. In some implementations, the frequency (acoustic) response is determined using relative amplitude spectral features. In some implementations, relative amplitude spectral features are used in combination with microphone matching and/or calibration. In some instances and implementations, giving weight the phase differences minimizes the impact of differences in

sensitivities between the microphones on the equalization process. In some implementations, equalization comprises correcting the frequency response at below a threshold frequency (e.g., below about 300 Hz, where the wavelength is about 1.1 m). In some instances and implementations, only the frequencies below the threshold frequency propagate in all directions, including backwards, from a speaker, and therefore are the only frequencies impacted by walls or corners behind the speaker.

(14) In some implementations, the relative positioning of the microphones with respect to one another is obtained and used to determine phase differences. In some implementations, the automatic equalization is performed without any information regarding relative positioning of the microphones with respect to the speaker(s).

(15) In some implementations, the automatic equalization is carried out based on an acoustical model. In some implementations, the device learns and recognizes patterns based on room position, and applies a corresponding equalization correction.

(16) In some implementations, the automatic equalization is carried out using machine learning. In some implementations, machine learning comprises training the device on desired corrections for a range of positions and/or frequencies (e.g., training targets can be obtained from expert listeners, or by measuring the spectrum at auxiliary microphones in the listening area, or by the ABC method using auxiliary microphones in front of the speaker driver). In some implementations, a nearest neighbor classifier algorithm is used to identify the appropriate correction (e.g., with phases estimated at frequencies in the 50-300 Hz range as the feature vector). In some implementations, a nonlinear logistic regression such as a multilayer neural network with sigmoidal output is used to identify the appropriate correction. In some implementations, utilizing machine learning enables corrections for many positions and reflecting materials. In some implementations, other machine learning methods are utilized.

(17) As described previously, room equalization is normally cumbersome to set up for the user. Typically the user has to perform acoustic measurements using a microphone (in for instance a smartphone) to capture measurement signals in various locations in a room.

(18) In some implementations, by using multiple electronic devices (e.g., a cluster of audio assistant products) located at different positions of a room, one speaker of one electronic device at a time is used to generate an acoustic signal, and microphones of the other electronic devices are used to capture respective acoustic responses at the respective positions of the room. In some implementations, information about the acoustic transfer function of a room is automatically captured by enabling each speaker to generate acoustic stimulus. In some implementations, the room response data are processed on a server system (e.g., in the cloud) using machine learning algorithms to generate a room equalization curve. In some implementations, the generated room equalization curve is downloaded to the electronic device, thus improving the in-room frequency response without user interaction.

(19) In one aspect, some implementations include a method for equalizing audio output performed at an electronic device having one or more speakers, a plurality of microphones, one or more processors, and memory. The method includes: (1) outputting audio user content from the one or more speakers located in a room; and (2) automatically and without user input, equalizing subsequent audio output of the electronic device, the equalizing including: (a) obtaining a collection of audio content signals, including receiving the outputted audio content at each microphone of the plurality of microphones; (b) determining from the collection of audio content signals a plurality of phase differences (e.g., transfer functions) between microphones of the plurality microphones; (c) obtaining a feature vector based on the plurality of phase differences; (d) obtaining a frequency correction (e.g., frequency correction curve) from a correction database based on the obtained feature vector; and (e) applying the obtained frequency correction to the subsequent audio output. In some implementations, the method further includes determining one or more phase differences between the outputted audio content and received audio content at one or more of the microphones. In some implementations, the plurality of microphones is positioned so as to be near-field with one another.

(20) In another aspect, some implementations include a method of generating a correction database. The method includes: for each position of a plurality of positions within a plurality of rooms: (1) positioning a speaker device at the position; (2) outputting via the speaker device training audio; (3) receiving the outputted training audio at two or more microphones; (4) generating a reference feature vector and

reference frequency correction based on the outputted training audio; and (5) adding the reference feature vector and reference frequency correction to the correction database.

(21) In another aspect, some implementations include a method of equalizing audio output performed at a computing system having one or more speakers, a plurality of microphones, one or more processors, and memory. The method includes: (1) outputting audio user content from the one or more speakers located in a room; and (2) automatically and without user input, equalizing an audio output of the computing system, the equalizing including: (a) receiving the outputted audio content at each microphone of the plurality of microphones; (b) based on the received audio content, determining an acoustic transfer function (e.g., impedance) for the room; (c) based on the determined acoustic transfer function, obtaining a frequency response (e.g., room/decibel gain) for the room; and (d) adjusting one or more properties of the speakers based on the determined frequency response. In some implementations, the equalization is performed independent of any specific user request. In some implementations, the equalization is performed without requiring any action from the user. In some implementations, the computing system determines its location within the room based on sonar, radar, or via a high-frequency mapping.

(22) In yet another aspect, some implementations include a method for training an equalization neural network. The method includes: (1) generating an audio equalization neural network by, for each position of a plurality of positions within a plurality of rooms: (a) positioning an audio system at the position, the audio system having a plurality of microphones and one or more speakers; (b) outputting one or more audio signals via the one or more speakers; (c) obtaining a collection of audio signals by receiving the outputted one or more audio signals at each of the plurality of microphones; (d) obtaining a feature vector for the position based on the collection of audio signals; and (e) adding one or more nodes corresponding to the feature vector to a neural network; and (2) training the equalization neural network.

(23) In yet another aspect, some implementations include a computing system including one or more processors and memory coupled to the one or more processors, the memory storing one or more programs configured to be executed by the one or more processors, the one or more programs including instructions for performing any of the methods described herein.

(24) In yet another aspect, some implementations include a non-transitory computer-readable storage medium storing one or more programs for execution by one or more processors of a computing system, the one or more programs including instructions for performing any of the methods described herein.

(25) Thus, devices, storage mediums, and computing systems are provided with methods for automatic audio equalization, thereby increasing the effectiveness, efficiency, and user satisfaction with such systems. Such methods may complement or replace conventional methods for audio equalization.

Description

BRIEF DESCRIPTION OF THE DRAWINGS

(1) For a better understanding of the various described implementations, reference should be made to the Description of Implementations below, in conjunction with the following drawings in which like reference numerals refer to corresponding parts throughout the figures.

(2) FIGS. 1A and 1B illustrate representative electronic devices for automatic audio equalization, in accordance with some implementations.

(3) FIG. 2 is a block diagram illustrating a representative operating environment that includes a plurality of electronic devices and a server system, in accordance with some implementations.

(4) FIG. 3A is a block diagram illustrating a representative electronic device, in accordance with some implementations.

(5) FIG. 3B is a block diagram illustrating sub-modules of the correction database and machine learning database of the electronic device in FIG. 3A, in accordance with some implementations.

(6) FIG. 4A is a block diagram illustrating a representative server system, in accordance with some implementations.

(7) FIG. 4B is a block diagram illustrating sub-modules of the correction database and machine learning database of the server system in FIG. 4A, in accordance with some implementations.

- (8) FIGS. 5A-5C illustrate example frequency responses, in accordance with some implementations.
- (9) FIGS. 6A and 6B illustrate example positioning and operation of the electronic device of FIG. 3A, in accordance with some implementations.
- (10) FIG. 6C is a side view of the electronic device positioned in FIG. 6B showing audio output of the electronic device, in accordance with some implementation.
- (11) FIG. 6D is a plan view of the electronic device positioned in FIG. 6B showing audio output of the electronic device, in accordance with some implementation.
- (12) FIGS. 7A-7C illustrate example positioning and operation of the electronic device of FIG. 3A, in accordance with some implementations.
- (13) FIG. 7D is a side view of the electronic device positioned in FIG. 7B showing audio output of the electronic device, in accordance with some implementation.
- (14) FIG. 7E is a plan view of the electronic device positioned in FIG. 7B showing audio output of the electronic device, in accordance with some implementation.
- (15) FIGS. 8A-8C illustrate example positioning and operation of the electronic device of FIG. 3A, in accordance with some implementations.
- (16) FIGS. 8D-8F are plan views illustrating an example operating sequence of the electronic device positioned in FIG. 8B, in accordance with some implementation.
- (17) FIGS. 9A-9H illustrate example responses of the electronic device of FIG. 3A in various locations in a room, in accordance with some implementations.
- (18) FIG. 10 is a flowchart representation of a method for automatic audio output equalization utilizing a single electronic device, in accordance with some implementations.
- (19) FIG. 11 is a flowchart representation of a method for automatic audio output equalization utilizing a plurality of electronic devices, in accordance with some implementations.
- (20) FIG. 12 is a block diagram illustrating a frequency correction process with machine learning utilizing a neural network, in accordance with some implementations.
- (21) FIG. 13 is a block diagram illustrating audio signal processing carried out at an equalization module of an electronic device, in accordance with some implementations.
- (22) FIGS. 14A-14B illustrate an example correction database at the electronic device, in accordance with some implementations.
- (23) Like reference numerals refer to corresponding parts throughout the several views of the drawings.

DETAILED DESCRIPTION

(24) Reference will now be made in detail to implementations, examples of which are illustrated in the accompanying drawings. In the following detailed description, numerous specific details are set forth in order to provide a thorough understanding of the various described implementations. However, it will be apparent to one of ordinary skill in the art that the various described implementations may be practiced without these specific details. In other instances, well-known methods, procedures, components, circuits, and networks have not been described in detail so as not to unnecessarily obscure aspects of the implementations.

(25) Electronic devices integrated with microphones and speakers are configured to receive and output sound. The sound output by these devices can be substantially affected by their placement in a listening room. For example, the bass frequencies of sound output by electronic devices can be substantially boosted as perceived by a listener depending on a number of nearby reflecting surfaces in a listening room (e.g., nearby furniture, walls, or ceiling). In some listening environments and/or for some audio content played on a speaker, distortion of sound output by electronic devices caused by room effects results in a less than ideal listening experience. In some implementations, these electronic devices are further configured to perform automatic audio equalization to correct for room effects on their output sound. In some implementations, the electronic devices correct for room effects through analysis of sound received by one or more microphones in the listening environment, independent of any user interaction, and thus enable a user to enjoy a high quality listening experience at any location with convenience and ease. In some implementations, the microphones employed for this purpose are microphones provided by the electronic device that is a source of the output sound to be equalized. In some implementations, the microphones employed for this purpose are microphones provided by other

electronic devices in the listening environment.

(26) Automatic equalization takes into account factors such as room and device positions. The speakers output audio which is collected by the microphones. From the collected audio, information including phase(s), phase difference(s), and the audio frequency response are determined. Using the determined information, the corresponding equalization correction is generated by either the electronic device (e.g., using a correction database available locally on the device) or at a server. Finally, the equalization correction is applied automatically and without user input to the electronic device.

(27) FIG. 1A illustrates an electronic device **100** for automatic audio equalization, in accordance with some implementations. The electronic device **100** includes one or more bass speakers **102** (e.g., **102-1** and **102-2**), one or more tweeter speakers **104**, and multiple microphones **106**. In some implementations, speakers **102** include different types of speakers, e.g., low-frequency bass speakers and high-frequency treble/tweeter speakers. In some implementations, the electronic device **100** includes three or more speakers **102**. In some implementations, the speakers **102** are arranged at different geometries (e.g., in a triangular configuration). In some implementations, the electronic device **100** does not include any tweeter speakers **104**. In some implementations, the electronic device **100** includes fewer than six microphones **106**. In some implementations, the electronic device **100** includes more than six microphones **106**. In some implementations, the microphones **106** include two or more different types of microphones.

(28) In FIG. 1A, the microphones **106** are arranged in groupings of three, where one of the microphones (e.g., the microphone **106-3**) is on a front face of the electronic device **100** and the other two microphones (e.g., the microphones **106-1** and **106-2**) in the grouping are on a side or top of the device. In some implementations, the microphones **106** are arranged at locations within the electronic device **100** other than the locations shown in FIG. 1A. In some implementations, the microphones **106** are grouped differently on the electronic device **100**. For example, the microphones **106** are arranged in groupings of four with one microphone on a front face and one microphone on a back face of the device **100**. In some implementations, the microphones **106** are oriented and/or positioned relative to the speakers **102**. For example, one microphone (e.g., **106-3**) faces the same direction as the speakers **102** and the other microphones (e.g., **106-1** and **106-2**) are perpendicular (or generally perpendicular) to the direction of the speakers **102**. As another example, one microphone (e.g., **106-3**) is positioned closer to the speakers **102** than the other microphones (e.g., **106-1** and **106-2**). Therefore, in some implementations, the microphones **106** are positioned such that phase differences are present in received audio and can be analyzed to determine room characteristics.

(29) FIG. 1B illustrates an electronic device **120** for automatic audio equalization, in accordance with some implementations. In some implementations, the electronic device **120** includes microphones **122**, an array of illuminators **124** (e.g., LEDs), and one or more speakers that are located behind the mesh **126**. Further, the rear side of the electronic device **120** optionally includes a power supply connector configured to couple to a power supply (not shown). In some implementations, the electronic device **120** includes more or less microphones **122** than shown in FIG. 1B. In some implementations, the microphones **122** are arranged at locations within the electronic device **120** other than the locations shown in FIG. 1B.

(30) In some implementations, the electronic device **100** and/or the electronic device **120** are voice-activated. In some implementations, the electronic device **100** and/or the electronic device **120** present a clean look having no visible button, and the interaction with the electronic device **120** is based on voice and touch gestures. Alternatively, in some implementations, the electronic device **100** and/or the electronic device **120** include a limited number of physical buttons (not shown), and the interaction with the electronic device is further based on presses of the button in addition to the voice and/or touch gestures.

(31) FIG. 2 is a block diagram illustrating an operating environment **200** that includes a plurality of electronic devices **100**, **120**, and **202**, and server systems **206**, **220**, in accordance with some implementations. The operating environment includes one or more electronic devices **100**, **120**, and **202** which are located at one or more positions within a defined space, e.g., in a single room or space of a structure, or within a defined area of an open space.

(32) Examples of an electronic device **100**, the electronic device **120**, a handheld computer, a wearable computing device, a personal digital assistant (PDA), a tablet computer, a laptop computer, a desktop computer, a cellular telephone, a smart phone, a voice-activated device, an enhanced general packet radio service (EGPRS) mobile phone, a media player, or a combination of any two or more of these data processing devices or other data processing devices.

(33) In accordance with some implementations, the electronic devices **100**, **120**, and **202** are communicatively coupled through communication network(s) **210** to a server system **206** and a smart assistant system **220**. In some implementations, at least some of the electronic devices (e.g., devices **100**, **120**, and **202-1**) are communicatively coupled to a local network **204**, which is communicatively coupled to the communication network(s) **210**. In some implementations, the local network **204** is a local area network implemented at a network interface (e.g., a router). In some implementations, the electronic devices **100**, **120**, and **202** that are communicatively coupled to the local network **204** also communicate with one another through the local network **204**. In some implementations, the electronic devices **100**, **120**, and **202** are communicatively coupled to one another (e.g., without going through the local network **204** or the communication network(s) **210**).

(34) Optionally, one or more of the electronic devices are communicatively coupled to the communication networks **210** and are not on the local network **204** (e.g., electronic device **202-N**). For example, these electronic devices are not on the Wi-Fi network corresponding to the local network **204** but are connected to the communication networks **210** through a cellular connection. In some implementations, communication between electronic devices **100**, **120**, and **202** that are on the local network **204** and electronic devices **100**, **120**, and **202** that are not on the local network **204** is performed through the voice assistance server **224**. In some implementations, the electronic devices **202** are registered in a device registry **222** and thus known to the voice assistance server **224**.

(35) In some implementations, the server system **206** includes a front end server **212** that facilitates communication between the server system **206** and electronic devices **100**, **120**, and **202** via the communication network(s) **210**. For example, the front end server **212** receives audio content (e.g., the audio content is music and/or speech) from the electronic devices **202**. In some implementations, the front end server **212** is configured to send information to the electronic devices **202**. In some implementations, the front end server **212** is configured to send equalization information (e.g., frequency corrections). For example, the front end server **212** sends equalization information to the electronic devices in response to received audio content. In some implementations, the front end server **212** is configured to send data and/or hyperlinks to the electronic devices **100**, **120**, and/or **202**. For example, the front end server **212** is configured to send updates (e.g., database updates) to the electronic devices.

(36) In some implementations, the server system **206** includes an equalization module **214** that determines from the audio signals collected from the electronic devices **202** information about the audio signals, such as frequencies, phase differences, transfer functions, feature vectors, frequency responses etc. In some implementations, the equalization module **214** obtains frequency correction data from the correction database **216** to be sent to the electronic device (e.g., via the front end server **212**). In some implementations, the frequency correction data is based on information about the audio signals. In some implementations, the equalization module **214** applies machine learning (e.g., in conjunction with a machine learning database **218**) to the audio signals to generate a frequency correction.

(37) In some implementations, the server system **206** includes a correction database **216** that stores frequency correction information. For example, the correction database **216** includes pairings of audio feature vectors and corresponding frequency corrections.

(38) In some implementations, the server system **206** includes a machine learning database **218** that stores machine learning information. In some implementations, the machine learning database **218** is a distributed database. In some implementations, the machine learning database **218** includes a deep neural network database. In some implementations, the machine learning database **218** includes supervised training and/or reinforcement training databases.

(39) FIG. 3A is a block diagram illustrating an electronic device **300**, in accordance with some implementations. In some implementations, the electronic device **300** is, or includes, any of the

electronic devices **100**, **202** of FIG. 2. The electronic device **300** includes one or more processor(s) **302**, one or more network interface(s) **304**, memory **306**, and one or more communication buses **308** for interconnecting these components (sometimes called a chipset).

(40) In some implementations, the electronic device **300** includes one or more input devices **312** that facilitate audio input and/or user input, such as microphones **314**, buttons **316**, and a touch sensor array **318**. In some implementations, the microphones **314** include the microphones **106**, the microphones **122**, and/or other microphones.

(41) In some implementations, the electronic device **300** includes one or more output devices **322** that facilitate audio output and/or visual output, including one or more speakers **324**, LEDs **326**, and a display **328**. In some implementations, the LEDs **326** include the illuminators **124** and/or other LEDs. In some implementations, the speakers **324** include the bass speakers **102**, the tweeter speakers **104**, the speakers of device **120**, and/or other speakers.

(42) In some implementations, the electronic device **300** includes radios **320** and one or more sensors **330**. The radios **320** enable one or more communication networks, and allow the electronic device **300** to communicate with other devices. In some implementations, the radios **320** are capable of data communications using any of a variety of custom or standard wireless protocols (e.g., IEEE 802.15.4, Wi-Fi, ZigBee, 6LoWPAN, Thread, Z-Wave, Bluetooth Smart, ISA100.5A, WirelessHART, MiWi, etc.) custom or standard wired protocols (e.g., Ethernet, HomePlug, etc.), and/or any other suitable communication protocol, including communication protocols not yet developed as of the filing date of this document.

(43) In some implementations, the sensors **330** include one or more movement sensors (e.g., accelerometers), light sensors, positioning sensors (e.g., GPS), and/or audio sensors. In some implementations, the positioning sensors include one or more location sensors (e.g., passive infrared (PIR) sensors) and/or one or more orientation sensors (e.g., gyroscopes).

(44) The memory **306** includes high-speed random access memory, such as DRAM, SRAM, DDR RAM, or other random access solid state memory devices; and, optionally, includes non-volatile memory, such as one or more magnetic disk storage devices, one or more optical disk storage devices, one or more flash memory devices, or one or more other non-volatile solid state storage devices. The memory **306**, optionally, includes one or more storage devices remotely located from one or more processor(s) **302**. The memory **306**, or alternatively the non-volatile memory within the memory **306**, includes a non-transitory computer-readable storage medium. In some implementations, the memory **306**, or the non-transitory computer-readable storage medium of the memory **306**, stores the following programs, modules, and data structures, or a subset or superset thereof: operating logic **332** including procedures for handling various basic system services and for performing hardware dependent tasks; a user interface module **334** for providing and displaying a user interface in which settings, captured data including hotwords, and/or other data for one or more devices (e.g., the electronic device **300** and/or other devices) can be configured and/or viewed; a radio communication module **336** for connecting to and communicating with other network devices (e.g., local network **204**, such as a router that provides Internet connectivity, networked storage devices, network routing devices, server system **206**, smart home server system **220** etc.) coupled to one or more communication networks **210** via one or more communication interfaces **304** (wired or wireless); an audio output module **338** for determining and/or presenting audio signals (e.g., in conjunction with the speakers **324**); a microphone module **340** for obtaining and/or analyzing audio signals (e.g., in conjunction with the microphones **314**); a positioning module **344** for obtaining and/or analyzing positioning information (e.g., orientation and/or location information), e.g., in conjunction with the sensors **330**; an equalization module **346** for equalizing audio output of the electronic device **300**, including, and not limited to: an audio analysis sub-module **3461** for analyzing audio signals collected from input devices (e.g., microphones), for example, determining audio properties (e.g., frequencies, phase shifts and/or phase differences) and/or generating fast Fourier transforms (FFTs) of audio frequencies; a correction sub-module **3462** for obtaining frequency corrections from a correction database **352** and/or applying the frequency corrections to the electronic device **300**; a transfer function sub-module **3463** for determining feature vectors, acoustic transfer functions (relating the audio outputs to the audio inputs), and/or frequency responses of the electronic

device **300** using the analyzed audio signals; and a weighting sub-module **3464** for assigning different weights to respective audio signals and/or audio properties (e.g., phase differences and/or signal-to-noise ratios); a training module **348** for generating and/or training audio models and, optionally, fingerprinting audio events associated with the electronic device **300**; a device database **350**, for storing information associated with the electronic device **300**, including, and not limited to: sensor information **3501** associated with the sensors **330**; device settings **3502** for the electronic device **300**, such as default options and preferred user settings; and communications protocol information **3503** specifying communication protocols to be used by the electronic device **300**; a correction database **352** for storing frequency correction information as described in greater detail in reference to FIG. 3B; and a machine learning database **354** for storing machine learning information as described in greater detail in reference to FIG. 3B.

(45) FIG. 3B is a block diagram illustrating sub-modules of the correction database **352** and machine learning database **354** of the electronic device **300** in FIG. 3A, in accordance with some implementations. In some implementations, the correction database **352** includes the following datasets or a subset or superset thereof: position data **3521** corresponding to different locations and/or orientations of associated audio devices (e.g., the positioning of microphones and/or speakers); vector data **3522** including phase shifts, phase differences, and/or feature vectors corresponding to different positions and/or orientations of associated audio devices; weight information **3523** including weights assigned to different signal-to-noise ratios, microphones, pairs of microphones, and/or positioning of microphones; training audio **3524** including training data (e.g., white noise, pink noise, etc.) for use with constructing the correction database **352**; and correction data **3525** storing information used to correct audio frequency responses of audio devices, including, and not limited to: frequency responses **3526** including frequency responses and/or feature vectors corresponding to different locations and/or orientations of audio devices; and frequency corrections **3527** corresponding to respective frequency responses **3526**.

(46) As also shown in FIG. 3B, the machine learning database **354** includes, in accordance with some implementations, the following datasets or a subset or superset thereof: neural network data **3541** including information corresponding to the operation of one or more neural network(s), including, and not limited to: positioning information **3542** including information (e.g., feature vectors) corresponding to different locations and/or orientations of audio devices; and correction data **3543** corresponding to the positioning information **3542**.

(47) Each of the above identified modules are optionally stored in one or more of the memory devices described herein, and corresponds to a set of instructions for performing the functions described above. The above identified modules or programs need not be implemented as separate software programs, procedures, modules or data structures, and thus various subsets of these modules may be combined or otherwise re-arranged in various implementations. In some implementations, the memory **306** stores a subset of the modules and data structures identified above. Furthermore, the memory **306**, optionally, stores additional modules and data structures not described above (e.g., module(s) for hotword detection and/or speech recognition in a voice-enabled smart speaker). In some implementations, a subset of the programs, modules, and/or data stored in the memory **306** are stored on and/or executed by the server system **206** and/or the voice assistance server **224**.

(48) FIG. 4A is a block diagram illustrating the server system **206**, in accordance with some implementations. The server system **206** includes one or more processor(s) **402**, one or more network interfaces **404**, memory **410**, and one or more communication buses **408** for interconnecting these components (sometimes called a chipset), in accordance with some implementations.

(49) The server system **206** optionally includes one or more input devices **406** that facilitate user input, such as a keyboard, a mouse, a voice-command input unit or microphone, a touch screen display, a touch-sensitive input pad, a gesture capturing camera, or other input buttons or controls. In some implementations, the server system **206** optionally uses a microphone and voice recognition or a camera and gesture recognition to supplement or replace the keyboard. The server system **206** optionally includes one or more output devices **408** that enable presentation of user interfaces and display content, such as one or more speakers and/or one or more visual displays.

(50) The memory **410** includes high-speed random access memory, such as DRAM, SRAM, DDR RAM, or other random access solid state memory devices; and, optionally, includes non-volatile memory, such as one or more magnetic disk storage devices, one or more optical disk storage devices, one or more flash memory devices, or one or more other non-volatile solid state storage devices. The memory **410**, optionally, includes one or more storage devices remotely located from the one or more processors **402**. The memory **410**, or alternatively the non-volatile memory within the memory **410**, includes a non-transitory computer-readable storage medium. In some implementations, the memory **410**, or the non-transitory computer-readable storage medium of the memory **410**, stores the following programs, modules, and data structures, or a subset or superset thereof: an operating system **416** including procedures for handling various basic system services and for performing hardware dependent tasks; a front end **212** for communicatively coupling the server system **206** to other devices (e.g., electronic devices **100**, **120**, and **202**) via the network interface(s) **404** (wired or wireless) and one or more networks, such as the Internet, other wide area networks, local area networks, metropolitan area networks, and so on; a user interface module **420** for enabling presentation of information (e.g., a graphical user interface for presenting application(s), widgets, websites and web pages thereof, games, audio and/or video content, text, etc.) either at the server system or at an electronic device; a device registration module **422** for registering devices (e.g., electronic device **300**) for use with the server system **206**; an equalization module **424** for equalizing audio output of an electronic device (e.g., electronic device **300**), including, and not limited to: an audio analysis sub-module **4241** for analyzing audio signals received from electronic device(s) (e.g., electronic device **300**), for example, determining audio properties (e.g., frequencies, phase shifts and/or phase differences) and/or generating fast Fourier transforms (FFTs) of audio frequencies; a correction sub-module **4242** for obtaining frequency corrections from a correction database **216** and/or applying the frequency corrections to an electronic device **300**; a transfer function sub-module **4243** for determining feature vectors, acoustic transfer functions (relating the audio outputs to the audio inputs), and/or frequency responses of an electronic device **300** using the analyzed audio signals; and a weighting sub-module **4244** for assigning different weights to respective audio signals and/or audio properties (e.g., phase differences and/or signal-to-noise ratios); a training module **426** for generating and/or training audio models and, optionally, fingerprinting audio events associated with electronic device(s) **300**; server system data **428** storing data associated with the server system **206**, including, but not limited to: client device settings **4281** including device settings for one or more electronic devices (e.g., electronic device(s) **300**), such as common device settings (e.g., service tier, device model, storage capacity, processing capabilities, communication capabilities, etc.), and information for automatic media display control; audio device settings **4282** including audio settings for audio devices associated with the server system **206** (e.g., electronic device(s) **300**), such as common and default settings (e.g., volume settings for speakers and/or microphones etc.); and a voice assistance data **4283** for voice-activated devices and/or user accounts of the voice assistance server **224**, such as account access information and information for one or more electronic devices **300** (e.g., service tier, device model, storage capacity, processing capabilities, communication capabilities, etc.); a correction database **216** storing frequency correction information as described in greater detail in reference to FIG. **4B**; and a machine learning database **218** storing machine learning information as described in greater detail in reference to FIG. **4B**.

(51) In some implementations, the server system **206** includes a notification module (not shown) for generating alerts and/or notifications for users of the electronic device(s). For example, in some implementations the correction database is stored locally on the electronic device of the user, the server system **206** may generate notifications to alert the user to download the latest version(s) or update(s) to the correction database.

(52) FIG. **4B** is a block diagram illustrating sub-modules of the correction database **216** and machine learning database **218** of the server system **206** in FIG. **4A**, in accordance with some implementations. In some implementations, the correction database **216** includes the following datasets or a subset or superset thereof: position data **4301** corresponding to different locations and/or orientations of associated audio devices (e.g., the positioning of microphones and/or speakers); vector data **4302** including phase shifts, phase differences, and/or feature vectors corresponding to different positions

and/or orientations of associated audio devices; weight information **4303** including weights assigned to different signal-to-noise ratios, microphones, pairs of microphones, and/or positioning of microphones; training audio **4304** including training data (e.g., white noise, pink noise, etc.) for use with constructing the correction database **216**; and correction data **4305** storing information used to correct audio frequency responses of audio devices, including, and not limited to: frequency responses **4306** including frequency responses and/or feature vectors corresponding to different locations and/or orientations of audio devices; and frequency corrections **4307** corresponding to respective frequency responses **4306**.

(53) As shown in FIG. **4B**, the machine learning database **218** includes, in accordance with some implementations, the following datasets or a subset or superset thereof: neural network data **4401** including information corresponding to the operation of one or more neural network(s), including, and not limited to: positioning information **4402** including information (e.g., feature vectors) corresponding to different locations and/or orientations of audio devices; and correction data **4403** corresponding to the positioning information **4402**.

(54) Each of the above identified elements may be stored in one or more of the memory devices described herein, and corresponds to a set of instructions for performing the functions described above. The above identified modules or programs need not be implemented as separate software programs, procedures, modules or data structures, and thus various subsets of these modules may be combined or otherwise re-arranged in various implementations. In some implementations, the memory **410**, optionally, stores a subset of the modules and data structures identified above. Furthermore, the memory **410** optionally stores additional modules and data structures not described above.

(55) FIGS. **5A-5C** illustrate example frequency responses of an audio device (e.g., electronic device **300**), in accordance with some implementations. In FIG. **5A**, a frequency response **508** is shown. The frequency response **508** measures the amplitude (e.g., gain and/or loudness) of the audio signal over a range of frequencies at which the audio is produced. The frequency response **508** is presented as a graph comprising amplitude (in units of decibel or dB) in the vertical axis **502** and frequency (in units of Hertz, or Hz) in the horizontal axis **504**.

(56) FIG. **5A** also shows a transition (or threshold) frequency $F_{sub.T}$ **506**. In some implementations, the transition frequency $F_{sub.T}$ **506** is based on the room in which the audio device is located. In some implementations, the transition frequency $F_{sub.T}$ **506** is a predetermined threshold (e.g., 250 Hz). The transition frequency $F_{sub.T}$ **506** is a frequency where the audio wavelength is comparable to the dimensions of the room and so in some instances the room resonances dominate. The transition frequency $F_{sub.T}$ **506** is sometimes referred to as a resonant frequency or Schroeder frequency, below which the room acts as a resonator.

(57) In some implementations, the frequency response **508** is a measured audio output response prior to equalization. In some implementations, the frequency response **508** is obtained using microphones on an electronic device (e.g., the microphones **106** in FIG. **1A** or the microphones **122** in FIG. **1B**). In some implementations, the frequency response **508** corresponds to a position of the audio device in a particular room or open space. As shown in FIG. **5A**, in some instances, the frequency response **508** includes fluctuations in amplitude within a range of frequencies (e.g., between 0 Hz and $F_{sub.T}$ **506**). In some instances the fluctuations are a result of positioning of the audio device within a room (e.g., proximity to boundaries and/or objects in the room) and characteristics of the room (e.g., audio-reflectivity of boundaries and/or objects in the room).

(58) FIG. **5A** further shows a target frequency response **510**. In some implementations, the target frequency response **510** is an ideal frequency response for a user of the audio device. In some implementations, the target frequency response **510** is a frequency response is an optimized frequency response across a band of frequencies. In some implementations, the target frequency response **510** represents a frequency response of the audio device in the absence of audio reflections, absorptions, and scatterings. Accordingly, in some instances, the target frequency response **510** does not exhibit fluctuations in amplitude over a range of frequencies (e.g., between 0 Hz and $F_{sub.T}$).

(59) As shown in FIG. **5A**, in some instances, the target frequency response **510** exhibits lower amplitude than the actual frequency response **508** at frequencies below the transition frequency $F_{sub.T}$ **506**. In some instances, the target frequency response **510** exhibits higher amplitude than the frequency

response **508** at frequencies above the transition frequency $F_{sub.T}$ **506**. In some implementations, the target frequency response **510** has uniform amplitude over a range of frequencies below the transition frequency $F_{sub.T}$ **506**. In some implementations, the target frequency response **510** has uniform amplitude over a range of frequencies above the transition frequency $F_{sub.T}$ **506**. In some implementations, the target frequency response **510** is obtained from a correction database (e.g., correction database **216**). In some implementations, the target frequency response **510** is obtained through analysis of the environs of the audio device, e.g., using machine learning.

(60) FIG. **5B** shows a corrected frequency response **518** in accordance with some implementations. In some implementations, the corrected frequency response **518** is an audio output response after equalization correction. In some implementations, the frequency response **518** is the frequency response from an audio device after a correction toward the target frequency response **510** has been applied.

(61) As shown in FIG. **5B**, the corrected frequency response **518** exhibits fairly uniform amplitude (e.g., compared to the frequency response **508**) over a range of frequencies below the transition frequency $F_{sub.T}$ **506**. In some implementations, (not shown) the frequency response **518** matches the target frequency response **510**. In some implementations, the frequency response **518** matches the target frequency response **510** at frequencies below the transition frequency $F_{sub.T}$ **506**. In some implementations, the frequency response **518** has similar amplitude to that of the target frequency response **510** below the transition frequency $F_{sub.T}$ **506**. In some implementations, the frequency response **518** displays more amplitude variations above the transition frequency $F_{sub.T}$ **506** compared to below the transition frequency $F_{sub.T}$ **506** (e.g., a greater correction is applied to frequencies below the transition frequency $F_{sub.T}$ **506**).

(62) FIG. **5C** shows a frequency response **528** in accordance with some implementations. In some implementations, the frequency response **528** is a measured audio output response before equalization. In some implementations, the frequency response **528** is obtained using microphones of the electronic device **300**, with the electronic device **300** located at a position in a room or in an open space. In some implementations, the frequency response **528** only includes amplitude contributions over a range of frequencies that is above the transition frequency $F_{sub.T}$ **506**. In some implementations, no equalization is applied to the frequency response **528** in accordance to a determination that the amplitude contributions of the frequency response **528** are only above the transition frequency $F_{sub.T}$ **506**.

(63) FIGS. **6A-6D**, **7A-E**, and **8A-8F** illustrate examples of positioning and operation of the electronic device **300** of FIG. **3A**, in accordance with some implementations. For simplicity, in these examples, the electronic device **300** is represented by the electronic device **100** (FIG. **1A**), however, in other implementations, the electronic device **300** includes an electronic device **120** (FIG. **1B**), an electronic device **202** (FIG. **2**), and/or other electronic device.

(64) FIG. **6A** shows a room **600** that includes the electronic device **100** positioned on a table **602** with the speakers **102** of the electronic device **100** facing upward. As shown in FIG. **6A**, the electronic device **100** is located near a center of the room **600** (e.g., not proximate to any of the walls or the ceiling) and thus reflection effects are less dominate as compared to the positioning illustrated in FIGS. **7** and **8**. In some implementations, (not shown) the room **600** includes multiple numbers and types of electronic devices, which are placed in any location and/or orientation within the room **600**. In some implementations, (not shown) the room **600** is a subset of an open space.

(65) FIG. **6B** shows the speakers **102** of the electronic device **100** producing audio **612**, in accordance with some implementations. Audio waves travel from the speaker(s) of the electronic device **100**, including waves **614** which are directed in the upward (+z) direction **616**. In some implementations, sound reflects off the table **602**. In some instances, because of the large distance between the electronic device **100** and the ceiling of the room **600**, little or no sound is reflected from the ceiling (e.g., an imperceptible amount to someone listening in the room). In some instances, the waves **614** reach the ceiling of the room **600** and are reflected from the ceiling. For example, based on a volume of the audio, a person listening in the room may or may not notice audio contributions from waves reflected from the ceiling. In cases where the audio contributions are noticeable, audio equalization is desired to minimize resulting distortions in the audio.

(66) FIGS. **6C** and **6D** show sound waves coming out of the electronic device **100** in multiple directions,

in accordance with some implementations. FIG. 6C shows a side view of the room **600** of FIG. 6B and FIG. 6D shows the corresponding plan view of the room **600**. In some implementations, when the electronic device **100** produces the audio output **612**, audio waves are emitted from the electronic device **100**, including the waves **614** which travel in the upward (+z) direction **616** as shown in FIG. 6C. In some implementations, when the electronic device **100** produces the audio output **612**, audio waves **624** are emitted from the electronic device **100** in a concentric, outward direction **626** (in the x-y plane).

(67) FIGS. 7A-7C illustrate example positioning and operation of the electronic device **300** of FIG. 3A, in accordance with some implementations. FIG. 7A shows the same room **600** with the electronic device **100** placed on the table **602**. In FIG. 7A, the electronic device **100** is oriented in an upright direction, with the speakers **102** facing the sofa, and proximate to one surface (e.g., the sofa). In some implementations and instances, each proximate surface results in an approximately 3 dB boost at low frequencies (e.g., frequencies below the transition frequency of the room), which audio equalization seeks to correct. FIG. 7B shows the electronic device **100** outputting audio **712**. Audio waves travel from the speakers **102** of the electronic device **100**, including waves **714** which travel in the leftward (-x) direction **716**. In some instances, the waves **714** hit the sofa and are reflected from the sofa. In some instances, the waves **714** hit the surface(s) of the walls and/or other objects in the room **600** and reflect off these walls and/or objects. In some instance, audio waves reflect off the table **602** and/or the ceiling of the room. The reflected audio waves produce distortions in the audio (e.g., resulting in the frequency response **508** shown in FIG. 5A).

(68) FIG. 7C shows waves **724** reflected from the sofa as a result of the waves **714** hitting the sofa. The waves **724** travel in the rightward (+x) direction **726** (e.g., in the opposite direction of travel of the waves **714**).

(69) FIGS. 7D and 7E show, respectively, side and plan views of the room **600** with the audio **712** coming out of the electronic device **100**, in accordance with some implementations. In the example shown in these Figures, waves are emitted from the electronic device **100**, including the waves **714** which travel in the leftward (-x) direction **714**. In this example, the waves **714** hit the left wall (or the y-z plane) of the room **600**, resulting in the reflected waves **724** which travel in the rightward (+x) direction **726** (e.g., in the opposite direction of travel of the waves **714**). In some instances, some of the reflected waves **724** travel back to the electronic device **100**.

(70) FIGS. 8A-8C illustrate example positioning and operation of the electronic device of FIG. 3A, in accordance with some implementations. FIG. 8A shows the room **600** with the electronic device **100** placed on the table **602**. In FIGS. 8A-8C, the table **602** is positioned to be close to a back edge **608** of the room **600** where the back wall **604** and the right wall **606** meet. The electronic device **100** is oriented in the upright direction, with its speakers directed toward the edge **608**. Thus, as illustrated in FIG. 8C, the sound produced by the speaker interacts with at least two surfaces. In some implementations and instances, the two proximate surfaces result in an approximately 6 dB boost at low frequencies, which audio equalization seeks to correct.

(71) FIG. 8B shows the electronic device **100** producing audio **812**. The audio output **812** includes waves **814** which radiate concentrically in an outward direction **816** toward the edge **608** between back wall **604** and the right wall **606**. In some instances, the waves **814** reflect off one or more of: the back wall **604**, the right wall **606**, and/or the edge **608**.

(72) FIG. 8C shows reflected waves **844**, including waves **844-1** that are reflected from the back wall **604**, waves **844-3** that are reflected from the right wall **606**, and waves **844-2** that are reflected from the edge wall **608**. In some instances, audio also reflects off the table **602** on which the electronic device **100** is placed. In some instances, the waves **814** hit one or more surface(s) and object(s) in the room **600** and are reflected off the surface(s) and/or object(s).

(73) FIGS. 8D-8F are plan views of the room **600** illustrating an example operating sequence of the electronic device **100** positioned as in FIG. 8B, in accordance with some implementations. FIG. 8D shows the position of the electronic device **100** in the room **600**. FIG. 8E shows the electronic device **100** outputting audio **812**. In some implementations, the outputted audio **812** includes the waves **814** traveling in the direction **816** toward the edge **608** between the back wall **604** and the right wall **606**. In some instances, the waves **814** hit the back wall **604**, the right wall **606**, and the edge **608**.

(74) FIG. 8F shows waves **844** reflecting from the back wall **604**, the right wall **606**, and the edge **608**. The reflected waves **844-1** are from the back wall **604** and travel in a direction **846-1**. The reflected waves **844-3** are from the right wall **606** and travel in a direction **846-3**, and the reflected waves **844-2** are from the edge **608** and travel in a direction **846-2**.

(75) In some implementations and instances (not shown), the electronic device **300** is proximate to three surfaces, resulting in an approximately 9 dB boost at low frequencies. Thus, as illustrated by the examples in FIGS. **6-8**, each different configuration affects the room transfer function (which affects the listening experience of users) and accordingly, there is a need to automatically determine the transfer functions and correct for them.

(76) FIGS. **9A-9I** illustrate example responses of the electronic device **300** presented in FIG. **3A**, at various locations in the room **600**, in accordance with some implementations. FIG. **9A** shows the electronic device **300** at a position A in the room **600**. FIG. **9B** shows that a frequency correction $FV(A)$ is applied to the electronic device **300**.

(77) In some implementations, the frequency correction $FV(A)$ is determined based a frequency response for the electronic device **300** at position A. In some implementations, the frequency response corresponds to audio produced by the device **300** while at position A. In some implementations, the audio output is in response to a user prompt (e.g., the user interacts with electronic device **300** via a user interface or pushes a button which enables audio to be played, or through a voice-activated command) In some implementations, the electronic device **300** is configured to output audio automatically (e.g., at a certain time of the day). In some implementations, the frequency correction $FV(A)$ is obtained from a correction database which is available locally on the electronic device **300** (e.g., correction database **352** in FIG. **3A**) and/or from a server system **206** (e.g., correction database **216** in FIGS. **2** and **4A**).

(78) FIGS. **9C-9H** illustrate responses to the electronic device **300** being moved from the position A to a position B in the room **600**. FIG. **9C** shows the electronic device **300** being moved from the position A to the position B. FIG. **9D** shows a first response of the electronic device **300** as a result of the change from the position A to the position B, in accordance with some implementations. In the example of FIG. **9D**, the electronic device **300** recognizes that it has been moved to the position B and accordingly, applies a frequency correction $FV(B)$ that corresponds to the position B. In some implementations, the frequency correction $FV(B)$ is from a correction database which is available locally on the electronic device (e.g., correction database **352**) and/or from a server system (e.g., correction database **216**). In some implementations, the electronic device **300** determines that it has moved to position B (e.g., via one or more sensors **330**) and applies a stored correction corresponding to position B. For example, the electronic device **300** has previously been placed in position B and has stored the corresponding correction.

(79) FIGS. **9E** and **9F** show a second response of electronic device **300** as a result of the change from the position A to the position B, in accordance with some implementations. In the example of FIGS. **9E-9F**, the electronic device **300** initially retains the frequency correction $FV(A)$ after it is moved to the position B. The electronic device **300** then proceeds to obtain and apply a frequency correction $FV(B)$ corresponding to position B. In some implementations, the electronic device **300** continuously or intermittently determines a frequency response and updates the frequency correction accordingly. For example, the electronic device **300** determines a frequency response every two minutes and retrieves a corresponding frequency correction from the correction database **352**. As another example, the electronic device **300** determines a frequency response every two minutes, compares the frequency response to the prior frequency response, and if different, obtains a new frequency correction. In some implementations, the electronic device **300** obtains a frequency correction in accordance with pre-determined conditions (e.g., the electronic device constantly monitors its location and proceeds to apply a frequency correction after determining that it has remained at a constant location after a certain time period).

(80) FIGS. **9G** and **9H** show a third response of the electronic device **300** as a result of the change from position A to the position B, in accordance some implementations. In the example of FIGS. **9G-9H**, the electronic device **300** recognizes that it has been moved from the position A and ceases to apply the frequency correction $FV(A)$ that corresponds to equalization for position A. In this example, the

electronic device **300** outputs audio at the position B without a correction applied until it obtains and applies the frequency correction FV(B).

(81) In some implementations, the application of frequency correction(s) during/after movement is based on user device settings (e.g., the device settings **3502**). For example, John likes to play music from his audio device while relaxing in the living room or cooking in the kitchen. Accordingly, he often places the device in two specific locations: on the coffee table in the living room, and on the countertop in the kitchen. For convenience, these locations (“living room” and “kitchen”) are saved as preferred settings along with their corresponding frequency corrections.

(82) Thus, when John is in the living room, the device obtains and applies the correction for the coffee table position, for example, in response to John notifying the device of its location (e.g., via an input device **312**) on the coffee table, or in response to the device determining its location on the coffee table (e.g., via GPS).

(83) At some later time, it is time for John to cook. As usual, he takes the audio device with him into the kitchen and sets it on the countertop. The device obtains and applies the correction for the countertop position, for example, in response to John notifying the device of its location (e.g., via an input device **312**), in response to the device determining its location (e.g., via GPS), in response to other events (e.g., start of audio playback, device powering up), or on a continuous basis. Thus, the device is able to quickly apply the frequency corrections at preferred locations, giving John the best listening experience.

(84) FIG. **10** is a flowchart representation of a method **1000** for automatic audio output equalization utilizing a single electronic device **300**, in accordance with some implementations.

(85) In some implementations, operations of the method **1000** are performed by: (1) one or more electronic devices **300**; (2) one or more server systems, such as server system **206**; or (3) a combination thereof. In some implementations, the method **1000** is governed by instructions that are stored in a non-transitory computer readable storage medium and that are executed by one or more processors of a device/computing system, such as the one or more processors **302** of the electronic device **300** and/or the one or more processors **402** of the server system **206**. For convenience, specific operations detailed below are described as being performed by a particular device or server.

(86) The electronic device **300** outputs (**1002**) audio. In some implementations, the electronic device **300** outputs the audio via one or more speakers (e.g., the speakers **102** and/or the speakers **104** in FIG. **1A**). In some implementations, the outputted audio comprises audio content (e.g., music) that is selected by a user. In some implementations, the outputted audio comprises a test signal, and/or training audio. In some implementations, the test signal and/or training audio includes beeps, sweeps, pink noise, and/or a combination of music from a plurality of music genres.

(87) In some implementations, the electronic device **300** receives (**1004**) its outputted audio. In some implementations, the outputted audio is received via one or more microphones (e.g., the microphones **122** in FIG. **1B**) on the electronic device **300**. In some implementations, the outputted audio content is received for a predetermined time period (e.g., 0.5 seconds, 1 second, 2 seconds, etc.). In some implementations, the outputted audio is received via one or more microphones distinct from the electronic device **300** (e.g., in addition to, or alternatively to, the microphones of the electronic device).

(88) In some implementations, in accordance with the receipt of the outputted audio, the electronic device **300** obtains (**1006**) a feature vector. In some implementations, obtaining the feature vector includes determining phase(s), phase difference(s), and/or frequencies of the received audio of the electronic device **300** (e.g., via the audio analysis sub-module **3461** in FIG. **3A**). In some implementations, the feature vector is generated based on phase differences in the outputted audio as received at different microphones of the electronic device **300**. In some implementations, obtaining the feature vector includes determining the frequency response of the electronic device **300** (e.g., via the transfer function sub-module **3463** in FIG. **3A**). In some implementations, obtaining the feature vector includes analyzing signal-to-noise ratios of received audio and/or assigning different weights to respective phase differences (e.g., via the weighting sub-module **3464** in FIG. **3A**). In some implementations, the electronic device **300** sends the received audio data to the server system **206** and the server system **206** generates the feature vector.

(89) In some implementations, after obtaining the feature vector, the electronic device **300** transmits

(e.g., via the radios **320** and/or the radio communication module **336**) the obtained feature vector to the server system **206** and the server system **206** receives (**1008**) the feature vector from the electronic device **300** (e.g., via the network interface **404** and/or the front end **212**). In some implementation, the server system **206** also receives information including frequency response(s), phase difference(s) and/or location information about the electronic device **300**.

(90) In some implementations, the server system **206** obtains (**1010**) a correction (e.g., via equalization module **214**) based on the received feature vector. In some implementations, the server system **206** generates the correction using a correction database that is located on the server system **206** (e.g., correction database **216** in FIG. 2). In some implementations, generating the correction comprises using machine learning method(s) to find the best match for the feature vector(s) (e.g., via machine learning database **218** in FIG. 2).

(91) In some implementations, the electronic device **300** obtains a correction (e.g., via equalization module **346**) based on the received feature vector. In some implementations, the electronic device **300** generates the correction using a correction database that is stored on the electronic device **300** (e.g., correction database **352** in FIGS. 3A and 3B) thus omitting the operations shown as performed at the server system **206** in FIG. 10. In some implementations, generating the correction comprises using machine learning method(s) to find the best match for the feature vector(s) (e.g., via machine learning database **354** in FIG. 3A).

(92) In some implementations, after the server system **206** generates the correction for the electronic device **300**, the server system **206** sends (**1012**) the generated correction to the electronic device (e.g., via the front end server **212** in FIG. 2). The electronic device **300** receives (**1014**) the correction from the server system **206** (e.g., via the radio communication module **336**).

(93) The electronic device **300** applies (**1016**) the correction to audio output by the electronic device **300**, thus achieving audio equalization (e.g., via correction sub-module **3462** in FIG. 3A). In some implementations, the correction is applied automatically and without user input. In some implementations, the user receives a prompt (e.g., a short messaging service (SMS) message or email displayed on the UI of the electronic device) and proceeds to authorize the device to apply the correction.

(94) In some instances and implementations, after the server system **206** receives the feature vector from the electronic device **300**, the server system **206** foregoes generating and sending a correction to the electronic device **300** in accordance with a determination that the outputted audio does not meet one or more predetermined conditions (e.g., signal-to-noise ratio, audio frequencies exceeding a transition frequency, etc.). Accordingly, no equalization is applied to the electronic device **300**.

(95) In some implementations, the electronic device **300** continuously or intermittently obtains a feature vector for its outputted audio and sends the feature vectors to the server system **206**. In some implementations, after applying the correction, the electronic device **300** forgoes obtaining a feature vector until the device determines that its positioning has changed.

(96) FIG. 11 is a flowchart representation of a method **1100** for automatic audio output equalization utilizing a plurality of electronic devices. In the example of FIG. 11, the plurality of electronic devices includes an electronic device **1192** (e.g., a device **120**, FIG. 1B), an electronic device **1194** (e.g., a device **100**, FIG. 1A), and an electronic device **1196** (e.g., a device **202**, FIG. 2), in accordance with some implementations. In some implementations, the electronic devices are located at different positions within a room. In some implementations, the plurality of electronic devices more or less than the three devices shown in the example of FIG. 11.

(97) In some implementations, the electronic device **1192** outputs (**1102**) audio. In some implementations, the electronic device **1192** outputs the audio via one or more speakers (e.g., the speakers **126** in FIG. 1B). In some implementations, the outputted audio comprises content (e.g., music) that is selected by a user. In some implementations, the outputted audio comprises a test signal, and/or training audio. In some implementations, the test signal and/or training audio includes beeps, sweeps, pink noise, and/or a combination of music from a plurality of music genres.

(98) In some implementations, the outputted audio from the electronic device **1192** is received by the other electronic devices, including the electronic device **1194** which receives (**1104**) the outputted audio,

and the electronic device **1196** which receives (**1106**) the outputted audio. In some implementations, the outputted audio is received by respective microphones in or on the electronic device **1194** (e.g., the microphones **106**) and the electronic device **1196** (e.g., microphones **314** in FIG. 3A). In some implementations, the electronic device **1194** and the electronic device **1196** are located at different positions of a room, and their respective microphones are used to capture the acoustic response for the audio output by electronic device **1192**. In some implementations, the electronic device **1194** and the electronic device **1196** receive outputted audio content for a respective predetermined time period (e.g., 0.5 seconds, 1 second, 2 seconds, etc.).

(99) In some implementations, the electronic device **1194** and the electronic device **1196** each obtain (**1108**, **1110**) a feature vector corresponding to the received audio. In some implementations, obtaining the respective feature vector at each of the electronic devices includes determining (e.g., using the audio analysis sub-module **3461** in FIG. 3A) respective phase(s), phase differences, and/or frequencies of the audio received via the microphone(s) at each of the electronic devices. In some implementations, a single feature vector is generated based on a collection of audio received at the various microphones of the electronic devices **1194**, **1196**. For example, each electronic device **1194**, **1196** sends audio data to a single destination device (e.g., server system **206**) and the destination device generates a corresponding feature vector. In some implementations, the destination device obtains relative positioning information for the electronic devices **1194**, **1196** and generates the feature vector based on the audio data and the relative positioning information.

(100) In some implementations, the electronic device **1194** and the electronic device **1196** each transmit the respective obtained feature vectors to the server system **206**. The server system **206** receives (**1112**) the respective generated feature vectors from the electronic device **1194** and the electronic device **1196** (e.g., via front end **212**). In some implementation, the server system **206** also receives audio information including respective frequency response(s), phase difference(s), and/or positioning information for the electronic devices **1194**, **1196**.

(101) The server system **206** obtains (**1114**) a correction for the electronic device **1192** using the obtained feature vectors. In some implementations, the server system **206** generates the correction using a correction database that is located on the server system **206** (e.g., correction database **216** in FIG. 2). In some implementations, generating the correction comprises using machine learning method(s) to find the best match for the feature vector(s) (e.g., via machine learning database **218** in FIG. 2). In some implementations, the server system **206** queries a correction database (e.g., correction database **216**) and receives a correction corresponding to the obtained feature vectors. In some implementations, the server system **206** assigns different weights to the respective feature vectors or components of the feature vectors. In some implementations, the server system **206** foregoes generating a correction based on a determination that the feature vectors meet one or more predetermined conditions (e.g., include only frequencies above a transition frequency and/or have a signal-to-noise ratio that exceeds a particular threshold).

(102) In some implementations, the electronic device **1192** receives the feature vectors from the electronic devices **1194**, **1196**. In some implementations, the electronic device **1192** obtains the correction based on the obtained feature vectors (e.g., using the correction database **352** and/or the machine learning database **354**).

(103) In some implementations, after obtaining the correction, the server system **206** sends (**1116**) the correction to the electronic device **1192**. The electronic device **1192** receives (**1118**) the correction sent by the server system **206**. The electronic device **1192** then applies (**1120**) the correction to achieve audio equalization. In some implementations, the correction is applied automatically and without user input (e.g., via the equalization module **346** in FIG. 3A).

(104) In light of these principles, we now turn to certain implementations.

(105) Machine Learning Techniques

(106) In some instances, machine learning is employed to automatically equalize audio output of an audio device (e.g., audio output of the electronic device **300**). Utilizing machine learning techniques enables the system to incorporate audio data from multiple distinct microphone devices. For example, as discussed previously with respect to FIG. 11, a first client device outputs user audio content and the

audio content is then received at other client devices in proximity to the first client device. In this example, a transfer function is generated based on the received audio content and the transfer function is input into a neural network to obtain a frequency correction. In some instances, the use of the neural network in this example enables the system to obtain a more precise frequency correction than is obtained from other implementations (e.g., from a pre-built correction database).

(107) FIG. 12 is a block diagram illustrating a frequency correction process with machine learning utilizing a neural network **1206**, in accordance with some implementations. In some implementations, one of the electronic devices (e.g., **300-1**) outputs audio and the outputted audio is received by each of the electronic devices **300** (e.g., using respective microphone(s) **314**). In some implementations, (not shown) the electronic device that outputs the audio does not itself receive/analyze the audio. In some implementations, as shown, each of the electronic devices **300** determines its respective audio transfer function **1212** based on the received audio output using its respective transfer function sub-module **3463**. In some implementations, (not shown) each electronic device **300** send audio data corresponding to the received audio output to a server system (e.g., the server system **206**) and the server system generates the transfer functions **1212**, e.g., using the transfer function sub-module **4243**.

(108) In some implementations, an aggregation **1204** (e.g., a concatenation) is applied to the transfer functions **1212** to obtain a room transfer function **1214**. In some implementations, the aggregation **1204** includes assigning a respective weight to the transfer functions **1212**. In some implementations, the room transfer function **1214** is input into the neural network **1206**, which outputs a corresponding room frequency correction **1216**. In some implementations, the neural network **1206** includes the neural network data **3541** of machine learning database **354**. In some implementations, the neural network **1206** includes the neural network data **4401** of machine learning database **218**.

(109) In some implementations, the neural network is updated with position information (e.g., feature vectors) and transfer functions corresponding to the locations and/or orientations of the electronic devices **300** (e.g., positioning information **4402** in FIG. 4B). In some implementations, the room frequency correction **1216** is associated with the corresponding positioning information (e.g., as correction data **4403**).

(110) In accordance with some implementation, a method for equalizing audio output is performed at a computing system (e.g., the electronic device **300**) having one or more speakers (e.g., speaker(s) **324**), a plurality of microphones (e.g., microphones **314**), one or more processors, and memory. The method includes: (1) outputting audio user content from the one or more speakers (e.g., via audio output module **338**) located in a room; and (2) automatically and without user input, equalizing (e.g., via equalization module **346**) an audio output of the computing system, the equalizing including: (a) receiving the outputted audio content at each microphone of the plurality of microphones; (b) based on the received audio content, determining an acoustic transfer function (e.g., an impedance) for the room (e.g., via audio analysis sub-module **3461**); (c) based on the determined acoustic transfer function, obtaining a frequency response (e.g., decibel gain) for the room (e.g., via audio analysis sub-module **3461**); and (d) adjusting one or more properties of the speakers based on the determined frequency response (e.g., via correction sub-module **3462**). In some implementations, the equalization is performed independent of any specific user request. In some implementations, the equalization is performed without requiring any action from the user. In some implementations, the computing system determines its location (and the location of its microphones) within the room based on sonar, radar, or via a high-frequency mapping. For example, FIG. 7B shows the electronic device **100** providing audio **712** and FIG. 7C shows the electronic device receiving reflected audio **724**. In some implementations, the device **100** generates a transfer function based on the received audio. In these implementations, the device **100** then inputs the transfer function to a neural network and obtains a frequency correction based on the transfer function. In some implementations, the device **100** then applies to the frequency correct to subsequent audio output, thereby equalizing the subsequent audio output as illustrated in FIGS. 5A and 5B.

(111) In some implementations, the acoustic transfer function is determined by utilizing one or more machine learning techniques. In some implementations, the machine learning techniques include utilizing a deep neural network. In some implementations, the machine learning includes supervised training and/or reinforcement training. In some implementations, the machine learning is performed at

the computing system (e.g., utilizing the correction sub-module **3462** in conjunction with the machine learning database **354**). In some implementations, the machine learning is performed at a remote server system (e.g., server system **206**).

(112) In some implementations, the method further includes sending the determined acoustic transfer function to a remote server system (e.g., server system **206**); and receives the frequency response from the remote server system in response to sending the determined acoustic transfer function.

(113) In some implementations, the one or more adjusted properties include a frequency property and/or a phase property. In some implementations, adjusting the one or more properties includes adjusting a gain for particular frequencies.

(114) In some implementations, the method further includes, prior to determining the acoustic transfer function, determining that the user content includes audio having a frequency below a transition frequency for the room (e.g., via the audio analysis sub-module **3461**). In some implementations, in accordance with a determination that the user content does not include an audio component below the transition frequency, the computing system forgoes determining the acoustic transfer function. In some implementations, the method further includes determining that the user content includes audio having a frequency below a threshold frequency (e.g., below 250 Hz, 300 Hz, or 350 Hz).

(115) In some implementations: (1) the one or more speakers include a plurality of speakers; (2) the method further includes determining relative positioning of the plurality of speakers; and (3) adjusting the one or more properties of the speakers is further based on the relative positioning of the plurality of speakers.

(116) In some implementations, the method further includes determining whether the computing system is operating in a monophonic mode. In some implementations, determining whether the computing system is operating in a stereophonic mode, surround sound mode, 5.1 mode, etc. In some implementations, adjusting the one or more properties of the speakers is further based on an operating mode of the computing system.

(117) In some implementations, the plurality of microphones includes microphones on a plurality of distinct devices. In some implementations, the plurality of microphones and the one or more speakers are positioned within a same device.

(118) In some implementations, determining the acoustic transfer function includes determining whether the one or more speakers are in proximity to one or more boundaries of the room. In some implementations and instances, each proximate boundary results in approximately 3 dB increase at low frequencies. In some implementations, the low frequencies include frequencies in the range of 50 Hz-500 Hz. In some implementations, the low frequencies are frequencies below a transition frequency of the room. In some implementations, the low frequencies correspond to bass frequencies.

(119) In some implementations, the equalizing is continuously performed while the audio user content is outputted. In some implementations, the equalizing is periodically performed while the audio user content is outputted. In some implementations, the equalizing is intermittently performed while the audio user content is outputted.

(120) In some implementations: (1) the method further includes determining relative positioning the plurality of microphones; and (2) the acoustic transfer function is determined based on the relative positioning of the plurality of microphones (e.g., in conjunction with phase differences in the received audio between microphones).

(121) In some implementations, the method further includes determining, via one or more cameras, a respective location of each microphone of the plurality of microphones in the room; and the acoustic transfer function for the room is based on the respective locations.

(122) In accordance with some implementations, a method includes: (1) generating an audio equalization neural network by, for each position of a plurality of positions within a plurality of rooms: (a) positioning an audio system at the position, the audio system having a plurality of microphones and one or more speakers; (b) outputting one or more audio signals via the one or more speakers; (c) obtaining a collection of audio signals by receiving the outputted one or more audio signals at each of the plurality of microphones; (d) obtaining a feature vector for the position based on the collection of audio signals; and (e) adding one or more nodes corresponding to the feature vector to a neural network;

and (2) training the equalization neural network.

(123) In some implementations, training the equalization neural network includes supervised training and/or reinforcement training. In some implementations, training the equalization neural network includes training the equalization neural network to generate a compensation function for one or more boundaries in proximity to the one or more speakers. In some implementations, the one or more boundaries include one or more surfaces on which the system is located.

(124) In accordance with some implementations, a computing system (e.g., the electronic device **300**) includes: (1) one or more processors (e.g., the processor(s) **302**); and (2) memory (e.g., the memory **306**) coupled to the one or more processors, the memory storing one or more programs configured to be executed by the one or more processors, the one or more programs including instructions for performing any of the operations or methods described above.

(125) In accordance with some implementations, a non-transitory computer-readable storage medium (e.g., a storage medium within the memory **306**) stores one or more programs, the one or more programs comprising instructions, which when executed by a computing system, cause the system to perform any of the operations or methods described above.

(126) Correction Database

(127) In some instances, a local correction database is employed to automatically equalize audio output of an audio device (e.g., audio output of the electronic device **300**). Utilizing a local database enables the device to perform equalizations without needing to be communicatively coupled to any other devices. Thus, a user may enjoy equalized audio content even when not in range of any communication networks. For example, as discussed previously with respect to FIG. **10**, the device outputs user audio content and the audio content is then received by microphones of the device. In this example, a feature vector is generated based on the received audio content and a corrections database (e.g., a corrections database stored at the device) is queried to obtain a frequency correction. In some instances, the use of a local database in this example enables the device to obtain a frequency correction more quickly than can be obtained from other implementations (e.g., from a remote neural network).

(128) FIG. **13** is a block diagram illustrating audio signal processing carried out at the equalization module **346** of the electronic device **300**, in accordance with some implementations. In some implementations, the electronic device **300** includes a microphones **314** (e.g., **314-1** through **314-4**) and speakers **324**. The speakers **324** produce audio and the microphones **314** receive the outputted audio.

(129) In some implementations, based on audio received by the microphone **314-2** and the microphone **314-4**, the electronic device **300** applies a phase difference operation **1302** to determine a phase difference **1312-1** between the audio received at the microphone **314-2** and the microphone **314-4** (e.g., using the audio analysis sub-module **3461**). In some implementations, the phase difference **1312-1** is used in a fast Fourier transform (FFT) operation **1304** to generate an FFT output **1314-1** (e.g., using the audio analysis sub-module **3461**).

(130) In some implementations, the FFT output **1314-1** is assigned a weight **1306-1**. In some implementations, the weight **1306-1** is assigned by the weighting sub-module **3464**, based on factors including, e.g., relative microphone positions, phase differences, and/or signal-to-noise ratios. In some implementations, the weight **1306-1** is a value (e.g., an integer), and the FFT output **1314-1** is multiplied by the value to obtain a feature vector FV.sub.1 **1316-1** corresponding to pair of microphones **314-2**, **314-4**. In some implementations, the weight **1306-1** is assigned to the phase difference **1312-1** before the FFT operation **1304**.

(131) In some implementations, the electronic device **300** includes more than two microphones and accordingly, the audio signaling process illustrated in FIG. **13** is performed for multiple pairs of the microphones to obtain a plurality of corresponding feature vectors **1316**. For example, the electronic device **300** is the electronic device **100** in FIG. **1A** which includes the microphones **106-1** through **106-6**. In this example, a respective feature vector **1316** is obtained for multiple microphone pairs, e.g., for the microphone pairs **106-1** and **106-2**, **106-1** and **106-3**, **106-4** and **106-5**, **106-4** and **106-6**. In some implementations, a feature vector of the audio output is obtained by aggregating (e.g., concatenating) the feature vectors **1316** (e.g., by concatenating **1316-1** through **1316-N**). Although FIG. **13** shows the equalization module **346**, in some implementations, the feature vectors **1316-1** is obtained at the

equalization module **214**.

(132) FIG. **14A** illustrates an example correction database **352** at the electronic device **300**, in accordance with some implementations. In some implementations, the correction database **352** comprises a table with columns for feature vectors **1404** and corrections **1406**. For example, as shown in FIG. **14A**, a feature vector **1404-1** has a corresponding correction **1406-1**.

(133) In some implementations, each feature vector **1404** is a weighted concatenation of feature vectors corresponding to individual pairs of microphones. In some implementations, (as shown) the feature vector **1404-1** is represented by $\alpha_{\text{sub.11}} \text{FV}_{\text{sub.11}} + \alpha_{\text{sub.12}} \text{FV}_{\text{sub.12}} + \dots + \alpha_{\text{sub.1N}} \text{FV}_{\text{sub.1N}}$, where a $\alpha_{\text{sub.ij}}$ is a weight assigned to the corresponding feature vector $\text{FV}_{\text{sub.ij}}$. In some implementations, the feature vector $\text{FV}_{\text{sub.ij}}$ is a feature vector corresponding to a pair j of microphones (e.g., **314-2** and **314-4**). In some implementations, a different weight $\alpha_{\text{sub.ij}}$ is assigned to different pairs of microphones (e.g., a higher weight is assigned to a front-to-back microphone pair than to a side-to-side microphone pair) and/or different frequency range(s) (e.g., a higher weight is assigned to the frequency range 100-200 Hz than the frequency range 3100-3200 Hz). In some implementations, a different weight $\alpha_{\text{sub.ij}}$ is assigned to different pairs of microphones based on the audio received by the pair of microphones (e.g., the signal-to-noise ratio). In some implementations, the feature vector $\text{FV}_{\text{sub.11}}$ is the feature vector $\text{FV}_{\text{sub.1}}$ **1316-1** in FIG. **13**. In some implementations, each of the feature vectors $\text{FV}_{\text{sub.11}}$ through $\text{FV}_{\text{sub.1N}}$ in **1404-1** is obtained using the audio signal processing carried out at the equalization module **346** as described in FIG. **13**.

(134) FIG. **14B** shows a structure of a representative feature vector $\text{FV}_{\text{sub.11}}$ **1414-1** in accordance with some implementations. As shown in FIG. **14B**, the feature vector $\text{FV}_{\text{sub.11}}$ includes a function of phase differences (e.g. denoted by $\Delta\phi$) at different frequencies (e.g. denoted by the subscripts f_1 , f_2 , and f_n etc.) in accordance with some implementations.

(135) In some implementations, as shown in FIG. **14A**, the correction **1406-1** includes a correction coefficient for each of a plurality of bands of audio frequencies. In some implementations, (as shown) the correction **1406-1** is represented as $[\text{C}_{\text{sub.11}}(f_{\text{sub.0-10}}), \text{C}_{\text{sub.12}}(f_{\text{sub.11-30}}), \dots, \text{C}_{\text{sub.1X}}(f_{\text{sub.M-N}})]$, where $\text{C}_{\text{sub.11}}$, $\text{C}_{\text{sub.12}}$, and $\text{C}_{\text{sub.1x}}$ are correction coefficients corresponding to the bands of frequencies $(f_{\text{sub.0-10}})$, $(f_{\text{sub.11-30}})$, and $(f_{\text{sub.M-N}})$ respectively, and where $(f_{\text{sub.0-10}})$ denotes the frequency band of 0-10 Hz, $(f_{\text{sub.11-30}})$ denotes the frequency band of 11-30 Hz, and $(f_{\text{sub.M-N}})$ denotes the frequency band of M-N Hz. In some implementations, the correction **1406-1** contains only frequencies below a transition frequency (e.g., the transition frequency $\text{F}_{\text{sub.T}}$ **506** in FIG. **5A**) and thus no correction is applied to frequencies above the transition frequency $\text{F}_{\text{sub.T}}$ **506**.

(136) In some implementations, to equalize audio output of a device, a feature vector is generated and then compared to the feature vectors **1404** in the correction database **352** (e.g., to determine which feature vector **1404** is most similar to the generated feature vector) to obtain the corresponding correction **1406**. In some implementations, the comparison includes applying a k-nearest neighbors algorithm. In some implementations, the comparison includes determining a Euclidean distance between the generated feature vector and each of the feature vectors **1404**. In some implementations, the comparison includes performing a least mean square (LMS) operation. Although FIG. **14A** shows the correction database **352**, in some implementations, the feature vectors **1404** and the corrections **1406** are stored in the correction database **216**.

(137) In accordance with some implementations, a method for equalizing audio output is performed at an electronic device (e.g., the electronic device **300**) having one or more speakers, a plurality of microphones, one or more processors, and memory. In some implementations, the method includes: (1) outputting audio user content from the one or more speakers (e.g., the speaker(s) **324**) located in a room; and (2) automatically and without user input, equalizing subsequent audio output of the electronic device (e.g., via the equalization module **346**), the equalizing including: (a) obtaining a collection of audio content signals (e.g., via the microphone module **340**), including receiving the outputted audio content at each microphone of the plurality of microphones; (b) determining from the collection of audio content signals a plurality of phase differences (e.g., transfer functions) between microphones of the plurality microphones (e.g., via the audio analysis sub-module **3461**); (c) obtaining a feature vector

based on the plurality of phase differences (e.g., via the audio analysis sub-module **3461**); (d) obtaining a frequency correction (e.g., frequency correction curve) from a correction database (e.g., the correction database **352**) based on the obtained feature vector (e.g., via the correction sub-module **3462**); and (e) applying the obtained frequency correction to the subsequent audio output (e.g., via audio output module **338**). In some implementations, applying the obtained frequency correction includes adjusting (lowering) a gain for a particular range of frequencies.

(138) In some implementations, the electronic device **300** performs operations (1) and (2) without input from external or remote devices. Thus, the electronic device **300** is enabled to perform the audio equalization while not communicatively coupled to any other devices.

(139) In some implementations, the method further includes determining one or more phase differences (e.g., via the audio analysis sub-module **3461**) between the outputted audio content and received audio content at one or more of the microphones. In some implementations, the microphones are positioned so as to be near-field with one another.

(140) In some implementations, the correction database is stored at the electronic device (e.g., the correction database **352**). In some implementations, the correction database includes a plurality of feature vectors (e.g., the frequency responses **3526**), each feature vector having a corresponding frequency correction (e.g., the frequency corrections **3527**). In some implementations, each feature vector of the plurality of feature vectors corresponds to a particular positioning of electronic device within a room.

(141) In some implementations, the method further includes: (1) positioning a speaker device (e.g., the electronic device **100**) at a particular position within a structure; (2) outputting via the speaker device training audio; (3) receiving the outputted training audio at two or more microphones; (4) generating a reference feature vector and reference frequency correction based on the outputted training audio (e.g., via the audio analysis sub-module **3461**); and (5) adding the reference feature vector and reference frequency correction to the correction database (e.g., the correction database **352**). In some implementations, the training audio (e.g., the training audio **3524**) includes pink noise and/or a combination of music from a plurality of music genres. In some implementations, generating the reference frequency correction includes applying the ABC method to the reference feature vector.

(142) In some implementations, obtaining the frequency correction from the correction database includes: (1) identifying a first feature vector of the plurality of feature vectors based on a comparison with the obtained feature vector; and (2) selecting the frequency correction that corresponds to the first feature vector. In some implementations, the comparison includes performing a least mean square (LMS) operation on the plurality of feature vectors. In some implementations, the comparison includes determining a Euclidean distance between the feature vectors. In some implementations, the comparison includes applying k-nearest neighbors algorithm. In some implementations, the comparison includes identifying a feature vector of the plurality of feature vectors that is most similar to the obtained feature vector.

(143) In some implementations, equalizing subsequent audio output includes equalizing a frequency band of subsequent audio output (e.g., a frequency band of 50 Hz-300 Hz). In some implementations: (1) the frequency band consists of a plurality of sub-bands; and (2) determining the plurality of phase differences includes, for a first and second microphone of the plurality of microphones: for each sub-band of the plurality of sub-bands, determining a corresponding phase difference between the first and second microphones; and (3) the feature vector is composed at least in part by concatenating a predefined function of the plurality of phase differences.

(144) In some implementations, determining the plurality of phase differences includes: (1) designating a plurality of microphone pairs from the plurality of microphones; and (2) for each microphone pair of the plurality of microphone pairs, determining a phase difference (e.g., a transfer function) between the received audio content at each microphone in the microphone pair. In some implementations, obtaining the feature vector includes applying a fast Fourier transform (FFT) to the plurality of phase differences.

(145) In some implementations, receiving the outputted audio content at each microphone includes receiving outputted audio content for a predetermined time period. In some implementations, the predetermined time period is 0.5 seconds, 1 second, 2 seconds, etc.

(146) In some implementations: (1) the method further includes assigning a plurality of weights (e.g., the weights **3523**) to the plurality of phase differences such that each phase difference of the plurality of phase differences is assigned a corresponding weight; and (2) the feature vector is based on the weighted plurality of phase differences. In some implementations, the plurality of weights is based on a signal-to-noise ratio for the received audio content at each microphone. In some implementations, the plurality of weights is based on relative positioning of the plurality of microphones. For example, microphones arranged so as to increase a relative phase difference in the outputted audio received at the microphones are weighted more highly than microphones in other arrangements.

(147) In some implementations, the method further includes, prior to obtaining the feature vector, determining that the outputted audio content includes audio having a frequency below a transition frequency for the room. In some implementations, the method further includes, prior to obtaining the feature vector, determining that the outputted audio content includes audio content in the range of 50 Hz-500 Hz. In some implementations, the method further includes, prior to obtaining the feature vector, determining that the outputted audio content includes bass frequencies. In some implementations, the method includes: (1) determining that the outputted audio content does not include audio having a frequency below the transition frequency; and (2) forgoing obtaining the feature vector.

(148) In some implementations, prior to obtaining the feature vector, the method further includes determining (e.g., the audio analysis sub-module **3461**) that the outputted audio content has an acoustic energy that meets one or more energy criteria for a particular range of frequencies (e.g., a range from 50 Hz to 500 Hz). In some implementations, in accordance with a determination that the outputted audio content does not have an acoustic energy that meets the one or more energy criteria, the method includes forgoing obtaining the feature vector.

(149) In some implementations, prior to obtaining the feature vector, the method includes determining (e.g., the audio analysis sub-module **3461**) that the outputted audio content has an audio coherence that meets one or more signal-to-noise criteria. In some implementations, in accordance with a determination that the outputted audio content does not have a coherence that meets the one or more criteria, the method includes forgoing obtaining the feature vector.

(150) In accordance with some implementations, a method of generating a correction database (e.g., the correction database **352**) includes: (1) for each position of a plurality of positions within a plurality of rooms: (a) positioning a speaker device (e.g., an electronic device **100**) at the position; (b) outputting via the speaker device training audio (e.g., outputting the training audio via the speakers **102** and/or the speakers **104**); (c) receiving the outputted training audio at two or more microphones (e.g., the microphones **106**); (d) generating a reference feature vector and reference frequency correction based on the outputted training audio (e.g., utilizing transfer function sub-module **3463** and correction sub-module **3462**); and (e) adding the reference feature vector and reference frequency correction to the correction database.

(151) In accordance with some implementations, a computing system (e.g., the electronic device **300**) includes: one or more processors; and memory coupled to the one or more processors, the memory storing one or more programs configured to be executed by the one or more processors, the one or more programs including instructions for performing any of the above methods and/or operations.

(152) In accordance with some implementations, a non-transitory computer-readable storage medium (e.g., within the memory **306**) stores one or more programs, the one or more programs comprising instructions, which when executed by a computing system, cause the system to perform any of the above methods and/or operations.

(153) For situations in which the systems discussed above collect information about users, the users may be provided with an opportunity to opt in/out of programs or features that may collect personal information (e.g., information about a user's preferences or usage of a smart device). In addition, in some implementations, certain data may be anonymized in one or more ways before it is stored or used, so that personally identifiable information is removed. For example, a user's identity may be anonymized so that the personally identifiable information cannot be determined for or associated with the user, and so that user preferences or user interactions are generalized (for example, generalized based on user demographics) rather than associated with a particular user.

(154) Although some of various drawings illustrate a number of logical stages in a particular order, stages that are not order dependent may be reordered and other stages may be combined or broken out. While some reordering or other groupings are specifically mentioned, others will be obvious to those of ordinary skill in the art, so the ordering and groupings presented herein are not an exhaustive list of alternatives. Moreover, it should be recognized that the stages could be implemented in hardware, firmware, software or any combination thereof.

(155) It will also be understood that, although the terms first, second, etc. are, in some instances, used herein to describe various elements, these elements should not be limited by these terms. These terms are only used to distinguish one element from another. For example, a first electronic device could be termed a second electronic device, and, similarly, a second electronic device could be termed a first electronic device, without departing from the scope of the various described implementations. The first electronic device and the second electronic device are both electronic devices, but they are not the same type of electronic device.

(156) The terminology used in the description of the various described implementations herein is for the purpose of describing particular implementations only and is not intended to be limiting. As used in the description of the various described implementations and the appended claims, the singular forms “a”, “an” and “the” are intended to include the plural forms as well, unless the context clearly indicates otherwise. It will also be understood that the term “and/or” as used herein refers to and encompasses any and all possible combinations of one or more of the associated listed items. It will be further understood that the terms “includes,” “including,” “comprises,” and/or “comprising,” when used in this specification, specify the presence of stated features, integers, steps, operations, elements, and/or components, but do not preclude the presence or addition of one or more other features, integers, steps, operations, elements, components, and/or groups thereof.

(157) As used herein, the term “if” is, optionally, construed to mean “when” or “upon” or “in response to determining” or “in response to detecting” or “in accordance with a determination that,” depending on the context. Similarly, the phrase “if it is determined” or “if [a stated condition or event] is detected” is, optionally, construed to mean “upon determining” or “in response to determining” or “upon detecting [the stated condition or event]” or “in response to detecting [the stated condition or event]” or “in accordance with a determination that [a stated condition or event] is detected,” depending on the context.

(158) The foregoing description, for purpose of explanation, has been described with reference to specific implementations. However, the illustrative discussions above are not intended to be exhaustive or to limit the scope of the claims to the precise forms disclosed. Many modifications and variations are possible in view of the above teachings. The implementations were chosen in order to best explain the principles underlying the claims and their practical applications, to thereby enable others skilled in the art to best use the implementations with various modifications as are suited to the particular uses contemplated.

Claims

1. A method for equalizing audio at an electronic device located in a defined space, comprising: outputting first audio content from at least one speaker of the electronic device; capturing, via a plurality of microphones, audio data representing a set of reflections of the first audio content within the defined space; based on the audio data that was captured, obtaining, by a processor of the electronic device, a frequency response for the defined space; obtaining, by the processor, a frequency correction based on the frequency response and a target frequency response obtained through an analysis of an environs of the electronic device, the frequency correction being over a range of frequencies above and below a transition frequency; and applying, by the processor, the frequency correction to subsequent audio content.
2. The method of claim 1, wherein obtaining the frequency response for the defined space comprises: obtaining, by the processor of the electronic device, the frequency response for the defined space, wherein the frequency response comprises a set of fluctuations in amplitude over the range of

frequencies.

3. The method of claim 1, wherein obtaining the frequency response for the defined space comprises: obtaining, by the processor of the electronic device, the frequency response for the defined space, wherein the frequency response corresponds to a position of the electronic device within the defined space.

4. The method of claim 1, wherein obtaining the frequency response for the defined space comprises: determining, by the processor based on the audio data that was captured, a plurality of phase differences between the plurality of microphones; and obtaining a feature vector based on the plurality of phase differences.

5. The method of claim 4, wherein obtaining the frequency correction based on the frequency response comprises: obtaining the frequency correction based on the feature vector.

6. The method of claim 1, wherein obtaining the frequency correction based on the frequency response comprises: obtaining, using a database local to the electronic device, the frequency correction based on the frequency response.

7. The method of claim 1, further comprising: outputting training audio from the at least one speaker of the electronic device; capturing, via the plurality of microphones, additional audio data representing an additional set of reflections of the training audio within the defined space; generating a reference feature vector and a reference frequency correction based on the additional audio data that was captured; and adding, to a correction database, the reference feature vector and the reference frequency correction.

8. The method of claim 7, wherein obtaining the frequency correction based on the frequency response comprises: obtaining, based on the reference feature vector and the reference frequency correction in the correction database, the frequency correction based on the frequency response.

9. An electronic device located in a defined space, comprising: at least one speaker; a plurality of microphones; a memory storing at least one computer program; and a processor interfaced with the at least one speaker, the plurality of microphones, and the memory, and configured to execute the at least one computer program to cause the processor to: cause the at least one speaker to output first audio content, capture, via the plurality of microphones, audio data representing a set of reflections of the first audio content within the defined space, based on the audio data that was captured, obtain a frequency response for the defined space, and obtain a frequency correction frequency based on the frequency response and a target frequency response obtained through an analysis of an environs of the electronic device, the frequency correction being over a range of frequencies above and below a transition frequency, and apply the frequency correction to subsequent audio content.

10. The electronic device of claim 9, wherein to obtain the frequency response for the defined space, the processor is configured to: obtain the frequency response for the defined space, wherein the frequency response comprises a set of fluctuations in amplitude over the range of frequencies.

11. The electronic device of claim 9, wherein to obtain the frequency response for the defined space, the processor is configured to: obtain the frequency response for the defined space, wherein the frequency response corresponds to a position of the electronic device within the defined space.

12. The electronic device of claim 9, wherein to obtain the frequency response for the defined space, the processor is configured to: determine, based on the audio data that was captured, a plurality of phase differences between the plurality of microphones, and obtain a feature vector based on the plurality of phase differences.

13. The electronic device of claim 12, wherein to obtain the frequency correction based on the frequency response, the processor is configured to: obtain the frequency correction based on the feature vector.

14. The electronic device of claim 9, further comprising: a database; wherein to obtain the frequency correction based on the frequency response, the processor is configured to: obtain, using the database, the frequency correction based on the frequency response.

15. The electronic device of claim 9, wherein the processor is configured to execute the at least one computer program to further cause the processor to: cause the at least one speaker to output training audio, capture, via the plurality of microphones, additional audio data representing an additional set of reflections of the training audio within the defined space, generate a reference feature vector and a

reference frequency correction based on the additional audio data that was captured, and add, to a correction database, the reference feature vector and the reference frequency correction.

16. The electronic device of claim 15, wherein to obtain the frequency correction based on the frequency response, the processor is configured to: obtain, based on the reference feature vector and the reference frequency correction in the correction database, the frequency correction based on the frequency response.
