

US Patent & Trademark Office

Patent Public Search | Text View

United States Patent Application Publication

20250279141

Kind Code

A1

Publication Date

September 04, 2025

Inventor(s)

LONDON; YANIR et al.

OPTICAL QUATERNARY CONTENT-ADDRESSABLE MEMORY AND ITS OPTICAL COMPUTING APPLICATIONS

Abstract

Systems and methods are provided for devices and methods for implementing fully optical quaternary content addressable memory (O-QCAM). In examples, the O-QCAM includes a search input configured to convert a multi-wavelength input signal encoded with a search word into a plurality of search optical signals; a plurality of QCAM word entries, each QCAM word entry comprising a plurality of O-QCAM cells; and a plurality of photodetectors, each photodetector optically coupled to a results end of a respective output match waveguide of an QCAM word entry. Each O-QCAM cell can be configured to store a reject value and one or more of a logic '0', a logic '1', and a wildcard value.

Inventors: LONDON; YANIR (Spring, TX), BUONANNO; LUCA (Spring, TX), PEDRETTI; GIACOMO (Cernusco sul Naviglio (MI), IT), VAN VAERENBERGH; THOMAS (Diegem, BE)

Applicant: HEWLETT PACKARD ENTERPRISE DEVELOPMENT LP (Spring, TX)

Family ID: 96880356

Appl. No.: 18/915800

Filed: October 15, 2024

Related U.S. Application Data

us-provisional-application US 63559378 20240229

Publication Classification

Int. Cl.: G11C15/00 (20060101)

U.S. Cl.:

Background/Summary

CROSS REFERENCE TO RELATED APPLICATIONS [0001] This application claims the benefit of and priority to U.S. Provisional Patent Application No. 63/559,378, filed on Feb. 29, 2024, the contents of which are incorporated herein by reference in their entirety.

BACKGROUND

[0002] Content addressable memory (CAM) is a type of memory that can perform a search operation in which a data string may be input as search content and the resulting output is an address of a location in the memory that stores matching data. This is in contrast to a read operation, in which an address is input and the resulting output is the data stored in the memory location corresponding to the searched address. Certain CAMs may be able to perform both the aforementioned search operation and the aforementioned read operation, while non-CAM memories may be able to perform the read operation but not the search operation.

[0003] Ternary CAM (TCAM) is a type of CAM in which the bit cells can store a wildcard data value in addition to two binary data values. When a bit cell that stores the wildcard value is searched, the result is a match regardless of what search criterion is used to search the bit cell. Certain TCAMs may also allow a search to be conducted on the basis of a wildcard search criterion. When a bit cell is searched based on the wildcard search criterion, the result is a match regardless of what value is stored in the bit cell.

Description

BRIEF DESCRIPTION OF THE DRAWINGS

[0004] The present disclosure, in accordance with one or more various examples, is described in detail with reference to the following figures. The figures are provided for purposes of illustration only and merely depict typical, non-limiting aspects of such examples.

[0005] FIG. 1 illustrates an example optical search engine in accordance with examples of the present disclosure.

[0006] FIGS. 2A and 2B illustrate an example optical search engine in accordance an example of the present disclosure.

[0007] FIGS. 3A and 3B illustrate an example optical search engine in accordance another example of the present disclosure.

[0008] FIGS. 4A and 4B illustrate an example optical search engine in accordance yet another example of the present disclosure.

[0009] FIGS. 5A and 5B illustrate an example optical search engine in accordance another example of the present disclosure.

[0010] FIG. 6 illustrates an example computing device in accordance with examples of the technology disclosed herein.

[0011] FIG. 7 depicts a schematic representation of an example Boolean constrain propagation function that can be executed in accordance with examples of the present disclosure.

[0012] FIG. 8 depicts an example Boolean function that can be executed in accordance with examples of the present disclosure.

[0013] FIG. 9 is an example computing component that may be used to implement various features of optical search engines in accordance with the implementations disclosed herein

[0014] FIG. 10 is a computing component that may be used to implement examples of the

disclosed technology.

[0015] The figures are not exhaustive and do not limit the present disclosure to the precise form disclosed.

DETAILED DESCRIPTION

[0016] Content addressable memory (CAM) is a type of memory generally used in high-speed search applications. CAMs comprise hardware that compares an input pattern against stored binary data. The stored data of a CAM is not accessed by its location, but rather access is performed based on its content. A search word is input to the CAM, the CAM searches for the search word in its contents, and, when found, the CAM returns the address of the location where the found contents reside. CAMs are powerful, efficient, and fast. The input patterns and data in CAMs are represented by logic '0's and logic '1's (generally referred to as a binary CAM or bCAM).

[0017] Quaternary CAM (QCAM) goes beyond the binary nature of bCAM, allowing for the storage and searching for a third value, referred to as a wildcard or "don't care" symbol, and a fourth value, referred to as a reject or "always care" symbol. In examples disclosed herein, the wildcard symbol may be represented as "X" and reject symbol may be represented as "p." A stored wildcard symbol can be treated like a match, regardless of whether the search criterion for the symbol of the stored data word is a logic '0' or a logic '1.' A stored reject symbol can be treated like a mismatch, regardless of whether the search criterion for the symbol of the stored data word is a logic '0' or a logic '1.' In this way, QCAMs allow for additional complexity as the input pattern can represent a range of patterns rather than only one pattern. As an illustrative example, an input pattern of "01XX0" could indicate a match for four separate stored words: 01000; 01010; 01100; and 01110, while an input pattern of "01pp0" could indicate a mismatch for any pattern that does not contain an "X" as the third and fourth symbol, and the rest of the pattern can return a match.

[0018] QCAMs can perform in-memory comparison operation in a massively parallel way, enabling extremely high throughput with a smaller footprint (e.g., reduced cell count) as compared to prior approaches. For example, the number of cells (n) for computing applications can be significantly lower as compared to bCAMs, as well as ternary CAMs (TCAMs). For instance, equality checks with CAMs or TCAMs can be performed for $2^{\text{sup}.n}$ items, while QCAMs can check up to

$$[00001] \binom{2n}{n}$$

items. Similarly, in the case of Boolean functions, bCAMs and TCAMs can be implemented to perform a Boolean function having an input space of $1:n$ cells, while a QCAM can be implemented to perform a Boolean function having an input space of $1:2n$ cells. As used herein, a "cell" may refer to structure that can be implemented to store a symbol value, such as logic '0', logic '1', 'X' (a wildcard value or "don't care" symbol), or 'p' (a reject value or "always care" symbol). Each symbol value may be stored at one or more bit positions. This increase in throughput can enable Internet packet routing, real-time network traffic monitoring, and more efficient access control lists, among other improvements in applications requiring fast memory comparisons.

[0019] Increasingly, data transfer is performed using optical communication technologies.

Transferring data using optics enables extremely higher bandwidth compared to traditional data transfer electronically. Although applications are frequently using integrated optics to transfer data, existing CAM implementations usually require electronic signals. Accordingly, costly optical to electrical conversions may be required to convert the data from the optical to the electrical domain. Existing CAM implementations can increasingly become bottlenecks due to the need for these conversions, reducing the overall efficiency and throughput possible within a network. Thus, the reduced number of cells used to implement a CAM, such as in the case of a QCAM, can provide improved throughput and reduced bottlenecks.

[0020] Examples of the technology disclosed herein provide systems and methods for implementing QCAMs in the optical domain with full quaternary search capabilities. In various

examples, an optical-QCAM (referred to herein as an O-QCAM) includes a plurality of word rows, each row comprising a plurality of O-QCAM cells. Each O-QCAM cell can store a symbol at one or more positions within a stored word and can store one of four values: logic '0', logic '1', 'X' (a wildcard value or "don't care" symbol), or 'p' (a reject value or "always care" symbol). Each cell can comprise one or more modulators arranged in one or more data rows. The symbol values can be stored in the optical domain using the one or more modulators tuned to pass or block a given wavelength of an input signal. Each bit position of the search word can be associated with one or more wavelengths of a multi wavelength input signal in some examples, and storing the word in the O-QCAM can comprise tuning the modulators to either pass or block according to an encoding scheme.

[0021] In various examples, the search word can be encoded on a multi-wavelength input signal, and a copy of the encoded signal can be coupled to each of the data rows of the O-QCAM cell. In various examples, an O-QCAM can comprise an optical search engine configured to store one or more QCAM stored words (also referred to herein as QCAM word entries). In various examples, a search word can be encoded using a single wavelength, with the value at each bit position encoded in the amplitude at that wavelength. In other examples, a search word can be encoded using a plurality of wavelengths, with the value at each bit position encoded in the amplitude of one of the wavelengths. In various examples, the optical search engine can comprise a hardware matrix multiplier comprising a plurality of multipath modulators configured to apply a matrix multiplication to an input signal encoded with a search word. In some examples, the optical search engine comprises a bank of QCAM stored words, wherein each QCAM stored word comprises a plurality of O-QCAM cells. Each bit position of a search word can be encoded on one or more wavelengths, and each bit position can be mapped to two input signals, in some examples. Based on the input waveguide on which an amplitude is detected, the optical search engine can indicate a match or mismatch between bits of the TCAM stored word and the search word.

[0022] FIG. 1 illustrates an example optical search engine **100** in accordance with examples of the present disclosure. The optical search engine **100** is provided for illustrative purposes only and should not be interpreted as limiting the scope of the disclosed technology to only the depicted example. For ease of discussion, the optical search engine **100** of FIG. 1 is discussed with respect to comparison of one search word and one QCAM stored word through the use of a modulator **101**, but in various examples the optical search engine **100** can include a plurality of modulators **101** associated with a plurality of QCAM stored words to enable comparison of a plurality of QCAM stored words against one or more search words. Furthermore, the optical search engine **100** can be used to compare a plurality of search words and one or more QCAM stored words.

[0023] As shown in FIG. 1, a search word **103** can be received by an input encoder **102**. In various examples, the optical search engine **100** may include one or more input encoders **102**, each input encoder **102** can be configured to encode a search word **103** of one or more received search words **103**. In other examples, a single input encoder **102** may be configured to encode one or more search words **103**. In some examples, an optical search engine input (not shown in FIG. 1) may be configured to receive the one or more search words **103** and transmit each received one or more search words to the input encoder **102**. The one or more search words **103** may be received over an electrical connection (e.g., over an electrical trace), over an optical routing element (e.g., a waveguide, optical fiber), or a combination of both.

[0024] In various examples, the input encoder **102** may be configured to encode the one or more received search words **103** in the time domain (e.g., time division multiplexing (TDM), wavelength domain (e.g., wavelength division multiplexing (WDM)), or spatial domain (e.g., multiplexing over a spatial dimension). In various examples, the bits of a given search word **103** may be encoded on the same wavelength, for example, in the case of TDM. In this example, each search word **103** may be encoded on a distinct wavelength of a plurality of wavelengths. In other examples, such as WDM implementations, bits of a given search word **103** may be encoded on different wavelengths.

In this case, each search word **103** may be encoded in the time domain (e.g., during different time slots). Table 1 illustrates an example encoding scheme in accordance with the technology disclosed herein.

TABLE-US-00001 TABLE 1 Encoded Encoded Search Word Search Signal Search Signal Symbol (S) Bit Value (s.sub.1) Bit Value (s.sub.2) 0 0 A 1 A 0 X 0 0 ρ A A

[0025] As shown in Table 1, each search word symbol S can be represented by two encoded search bit values s.sub.1, s.sub.2. To provide a search word symbol S of logic '1', light having an amplitude A can be transmitted within the first encoded search bit value s.sub.1 associated with the bit position and light having an amplitude of 0 can be transmitted within the second encoded search bit value s.sub.2. For the search word symbol S of logic '0', light having an amplitude of 0 can be transmitted as the first encoded search bit value s.sub.1 associated with the bit position and light having an amplitude A can be transmitted as second encoded search bit value s.sub.2. To provide a search word **103** of wildcard symbol 'X', light amplitude of 0 can be transmitted in both of the first encoded search bit value s.sub.1 and the second encoded search bit value s.sub.2. To provide the search word **103** as a reject symbol 'ρ', light having an amplitude A can be transmitted in both of the first encoded search bit value s.sub.1 and the second encoded search bit value s.sub.2.

[0026] In examples, a threshold amplitude A can be used to distinguish between light having an amplitude of 0 and light having an amplitude A. For example, light having an amplitude of 0 may refer to light having an amplitude that is less than the threshold amplitude A and, therefore, can be considered as having an amplitude of 0 (e.g., no light is transmitted or detected). In this case, the threshold amplitude A may be selected so to distinguish between light representing a logic "1" bit value from background noise, such that any light having an amplitude between A and 0 may be considered noise. Whereas, light having an amplitude of A may refer to light having an amplitude of at least A (e.g., equal to or above the threshold amplitude A). Thus, as an example, to provide a reject symbol 'ρ', light having an amplitude of equal to or above the threshold amplitude A can be transmitted in both of the first encoded search bit value s.sub.1 and the second encoded search bit value s.sub.2, while a wildcard symbol 'X' can be provided by light having an amplitude of less than the threshold amplitude A in both of first encoded search bit value s.sub.1 and the second encoded search bit value s.sub.2.

[0027] Although the examples herein are discussed with respect to the encoding scheme provided in Table 1, a person of ordinary skill in the art would understand that the assignment of light amplitude A and light of amplitude 0 in the associated encoded search bit values s.sub.1, s.sub.2 can be reversed in various examples. For example, the logical bit value '1' could have an amplitude of 0 transmitted within the first encoded search bit value s.sub.1 and transmit light having an amplitude A in the second encoded search bit value s.sub.2. In some examples, the amplitude A may be the same value for each bit position, while in other examples at least one bit position may transmit light of a different amplitude A than at least one other bit position. In various examples, the amplitude A for each bit can decrease from a maximum amplitude A.sub.0 for the first encoded search bit value s.sub.1 to a minimum amplitude A.sub.n for the nth encoded search bit value s.sub.n. In various examples, a more advanced amplitude scheme can be implemented, wherein the amplitude A for each encoded search bit value t can vary over a range of different amplitudes.

[0028] For ease of reference, the technology disclosed herein shall be described with respect to encoding of the search signal based on amplitude, but the encoding scheme can also be implemented based on different characteristics of light. As a non-limiting example, the input encoder **102** can be configured to encode the optical search signal using the polarization of the wavelength. For example, if the search word symbol S is a logic '1', the encoding scheme could comprise light of a first polarization within the first encoded search bit value s.sub.1 and light of a second polarization in the second encoded search bit value s.sub.2, the reverse association for a logic '0', and omitting light of the first polarization and the second polarization in both encoded search bit values s.sub.1, s.sub.2 to represent a wildcard symbol 'X'. In various examples, the

wildcard symbol 'X' can be represented by including light of either the first polarization or the second polarization in both encoded search bit values s.sub.1, s.sub.2. As another non-limiting example, the phase of light of the single wavelength can be used, with three different phases being utilized (two phases in combinations to represent logic '1' and '0', and a third phase for representing a wildcard 'X'). In various examples, the wildcard symbol 'X' can be represented by including light of either the first phase or the second phase in both encoded search bit values s.sub.1, s.sub.2. The technology should not be interpreted as limited to encoding based on amplitude, but can also be implemented based on phase, fundamental mode profile, or other degrees of freedom of light. As a non-limiting example, different modes of light can be utilized to differentiate between logic values for the bits. A logic '1' can be represented by having light of a first mode in the first encoded search bit value s.sub.1 and light of a second mode in the second encoded search bit value s.sub.2, a logic '0' can be represented by light of a second mode in the first encoded search bit value s.sub.1 and light of the first mode in the second encoded search bit value s.sub.2, and the wildcard value can be represented by having light of a third mode in both the first encoded search bit value s.sub.1 and the second encoded search bit value s.sub.2. As another non-limiting example, the wildcard value can be represented by not having light in either the first mode or the second mode during both the first encoded search bit value s.sub.1 and the second encoded search bit value s.sub.2. In such examples, the one or more routing elements can be configured to propagate at least three modes of light.

[0029] In various examples, the encoded search signal **110** (also referred to herein as a search optical signal) can comprise $2n$ encoded search bit values, where n is the number of bit positions in the search word. As a non-limiting example, the search word **103** may comprise 8 bit positions, and the encoded search signal **110** can comprise 8 sets of associated encoded search bit values representing 8 symbols (i.e., **16** encoded search bit values in total). In some examples, each associated search word symbol S may comprise more than one encoded search signal bit value. As a non-limiting example, a first encoded search word symbol S .sub.1 may comprise two encoded search signal bit values s.sub.1-1, s.sub.2-1 and the second encoded search word symbol S .sub.2 may comprise two encoded search signal bit values s.sub.1-2, s.sub.2-2. In various examples, the encoded search signal bit values s.sub.1, s.sub.2 associated with a bit position may be non-continuous (i.e., the encoded search signal bit values may be separated by one or more encoded search signal bit values not associated with the bit position). A key can be included to descramble the light signals at the photodetector **109**.

[0030] The encoded search signal **110** generated by the input encoder **102** can be coupled to an input routing element **104**. The input routing element **104** may comprise an optical waveguide, an optical fiber, or other optical routing medium known in the art. The input routing element may be made of, but not limited to, one or more of gallium arsenide (GaAs), indium phosphide (InP), silicon (Si), silicon nitride (SiN), LiNbO.sub.3, glass, and silica, among other materials. In various examples, the input routing element **104** may be disposed in a silicon photonics assembly. One or more of the elements illustrated in FIG. **1** may be disposed in a silicon photonics assembly. The input routing element **104** can include one or more coupling components (not shown in FIG. **1**) disposed at the first end to couple the encoded search signal **110** from the input encoder **102** and at the second end to couple the encoded search signal **110** into the modulator **101**. In various examples, a plurality of input routing elements **104** may be included, each input routing element **104** configured to couple the encoded search signal **110** from the input encoder **102** to a modulator **101** of a plurality of modulators **101**.

[0031] To perform a search operation, the modulator **101** can be modulated to represent a QCAM stored word, in some examples. In other examples, the modulator can be modulated to represent one or more QCAM stored words. In various examples, the modulator **101** may comprise one or more modulators, including but not limited to waveguide resonators (e.g., ring modulator), multipath interferometers (e.g. Mach Zehnder interferometer (MZI)), photonic crystals (e.g.,

lithium niobate (LiNbO₃)), phase shifters, polarization filters, lattice filters, or other modulator components capable of being driven by an electronic signal to tune the performance characteristics of the modulator **101**.

[0032] In various examples, the optical search engine **100** can include a plurality of modulators **101**. In some examples, each modulator **101** can be configured to compare a different QCAM stored word against the encoded search signal **110**. In some examples, one or more modulators **101** may be configured in parallel, with a copy of the encoded search signal **110** optically coupled to an input of each of the one or more modulators **101**. One or more modulators **101** may be connected in series in some examples, with the output of a first modulator **101** optically coupled to the input of a second modulator **101**, the output of the second modulator **101** optically coupled to a third modulator **101**, and so on.

[0033] In various examples, a programming controller **106** (also referred to as a driver) can be used to tune the one or more modulators **101** to represent the bit positions of the one or more QCAM stored words. In various examples, the programming controller **106** can be configured to control tuning of all of the modulators of the optical search engine, while in other examples a plurality of programming controllers **106** can be included, each of the plurality of programming controllers **106** configured to tune one or more modulators **101**. Each modulator **101** can be communicatively coupled to one or more tuning components (not shown in FIG. 1), each of the one or more tuning components capable of changing an optical characteristic of the one or more modulators that make up the modulator **101** to enable tuning of the performance of the modulator **101**. In various examples, the one or more tuning components can comprise one or more devices configured to change the refractive index of the core or cladding of the one or more modulators, control the number of free carriers, and/or create a red and/or blue shift of the resonance wavelength of the one or more modulators. Non-limiting examples of tuning components include heaters, electrical contacts, among other devices used to tune the resonance wavelength of optical components. In various examples, the programming controller **106** can comprise a processing component, a field programmable gate array (FPGA), an application specific integrated circuit (ASIC), or other type of processor present in computing systems. In some examples, the programming controller **106** can comprise a central processing unit (CPU), a graphics processing unit (GPU), or other processing component external to the optical search engine **100**.

[0034] Each of the QCAM stored words can be maintained in a QCAM word storage **108** in various examples. The QCAM word storage **108** can comprise a non-transitory machine-readable storage medium configured to store one or more QCAM words. Non-limiting examples of the QCAM word storage **108** can comprise common forms of memory including RAM, PROM, EPROM, FLASH-EPROM, NVRAM, memristors, optical storage memories, among electrical, optical, or electro-optical storage medium. In various examples, the QCAM word storage **108** can comprise one or more types of volatile and/or non-volatile memory. In various examples, the QCAM word storage **108** may be a dedicated memory component for the optical search engine **100** configured to store QCAM stored words, while in other examples the QCAM word storage **108** can be a partition or other assigned space in a shared memory component. The QCAM word storage **108** may be implemented in a storage area network (SAN) or other networked storage solution. The programming controller **106** can be communicatively coupled to the QCAM word storage **108** and configured to retrieve a QCAM stored word to compare against the encoded stored word through the modulator **101**. The programming controller **106** can maintain a mapping of QCAM stored words to the modulators **101** in a dedicated memory component of the programming controller **106** (not shown in FIG. 1), in the QCAM word storage **108**, or in another separate memory component communicatively coupled to the optical search engine **100** (not shown in FIG. 1), or a combination thereof. In some examples, each QCAM word can be stored in the QCAM word storage **108** in its encoded state, while in other examples the QCAM words can be stored in an un-encoded state. When storing the QCAM stored word in the encoded state, the latency between retrieving the

QCAM stored word and applying the associated drive signal by the programming controller **106** can be reduced, but the memory footprint of the QCAM word storage **108** may be larger than when the QCAM stored words are stored in an un-encoded state (since the size of the word is at least doubled in the encoded state to have a logic value for each encoded search bit value assigned to the bit position). The method of storage (encoded or un-encoded) depends on the requirements of the application in which the O-QCAM is implemented.

[0035] In performing an operation on the search word **103** encoded in accordance with Table 1, the programming controller **106** can be configured to tune the modulator **101** either to allow light of the wavelength of the encoded word or to block the light. Table 2 shows the operational state of the modulator **101** for each corresponding bit value of the QCAM stored word retrieved from the QCAM word storage **108**.

TABLE-US-00002 TABLE 2 QCAM Stored Encode Stored Encode Stored Data Word Data Bit
Data Bit Symbol (D) Value (d.sub.1) Value (d.sub.2) 1 0 (Block) 1 (Pass) 0 1 (Pass) 0 (Block) X 0
(Block) 0 (Block) p 1 (Pass) 1 (Pass)

[0036] As shown in Table 2, the modulator **101** can either be configured to “pass” light or “block” light based on an encoded stored data bit values d.sub.1, d.sub.2 corresponding to the bit position of the QCAM stored data symbol D. To represent an encoded stored data symbol of logic ‘1’, the modulator **101** can be tuned to block light at the encoded wavelength corresponding to the first encoded data bit value d.sub.1 associated with the bit position and tuned to pass light at the encoded wavelength corresponding to the second encoded data bit value d.sub.2. In various examples, “blocking” light can comprise removing light, attenuating light, or otherwise introducing optical loss at a given wavelength from a waveguide using one or more stop band or drop modulators, or through destructive interference of light at the given wavelength. “Blocking” light as used herein may refer to transmitting an amplitude of light that is less than an amplitude A and “passing” light as used herein may refer to transmitting an amplitude of light that is equal to or above the amplitude A, as described above. To represent a logic ‘0’, the modulator **101** can be tuned to pass light at the encoded wavelength corresponding to the first encoded data bit value d.sub.1 associated with the bit position and tuned to block light at the encoded wavelength corresponding to the first encoded data bit value d.sub.2. To represent a wildcard value ‘X’, the modulator **101** can be tuned to block light at the encoded wavelength for both encoded data bit values d.sub.1, d.sub.2 associated with the bit position. To represent a reject value ‘p’, the modulator **101** can be tuned to pass light at the encoded wavelength for both encoded data bit values d.sub.1, d.sub.2 associated with the bit position. In various examples, the programming controller **106** can be configured to apply a high-speed electrical signal to the one or more tuning components capable of changing the optical characteristics of the modulator **101** such that the modulator **101** can be configured in accordance with Table 2 during the encoded data bit values d.sub.1, d.sub.2.

[0037] Based on the logic states indicated in Tables 1 and 2, light will pass through the modulator **101** for an encoded search symbol S only when a mismatch occurs between the value of a bit position of the search word **103** and the corresponding value of the bit position of the QCAM stored word. Table 3 shows the results based on the encoded bit value on the optical search signal and of the corresponding modulator **101**.

TABLE-US-00003 TABLE 3 Search Word QCAM Stored Word Match/Mismatch (s1, s2) Symbol
(d.sub.1, d.sub.2) (passed/blocked) 0 (0, A) 0 (pass, block) Match (blocked) 0 (0, A) 1 (block, pass)
Mismatch (passed) 0 (0, A) X (block, block) Match (blocked) 0 (0, A) p (pass, pass) Mismatch
(passed) 1 (A, 0) 0 (pass, block) Mismatch (passed) 1 (A, 0) 1 (block, pass) Match (blocked) 1 (A,
0) X (block, block) Match (blocked) 1 (A, 0) p (pass, pass) Mismatch (passed) X (0, 0) 0 (pass,
block) Match (blocked) X (0, 0) 1 (block, pass) Match (blocked) X (0, 0) X (block, block) Match
(blocked) X (0, 0) p (pass, pass) Match (blocked) p (A, A) 0 (pass, block) Mismatch (passed) p (A,
A) 1 (block, pass) Mismatch (passed) p (A, A) X (block, block) Match (blocked) p (A, A) p (pass,

pass) Mismatch (passed)

[0038] As shown in Table 3, when the symbol of the encoded search word is a logical '1', the input (e.g., encoded optical search signal from the input encoder **102**) includes light of at an encoded wavelength having an amplitude A (e.g., equal to or above a threshold amplitude A) representing the first encoded search bit value s.sub.1 of the associated bit position and does not include light of the encoded wavelength during the representing the second encoded search bit value s.sub.2 (e.g., light on the input routing element **104** having an amplitude below a threshold amplitude A). If the bit value of the QCAM stored word at the corresponding bit position is also a logic '1', the modulator **101** can be driven to tune the modulator **101** to block light of the encoded wavelength representing the first encoded search signal bit value s.sub.1 and pass light of the encoded wavelength during the second representing the second encoded search signal bit value s.sub.2. Therefore, because the modulator **101** is configured to block light of the encoded wavelength for the first encoded search signal bit value s.sub.1, the light on the input routing element **104** is not permitted to pass through the modulator **101** and into an output routing element **107** (e.g., light at the output routing element **107** is below the threshold amplitude A). And, because there is no light on the input routing element **104** representing the second encoded search bit value s.sub.2, light at the output routing element **107** is below the threshold amplitude A (e.g., no light passes) even though it is configured to pass light because the light on the input routing element **104** representing the second encoded search bit value s.sub.2 is below the threshold amplitude A. Accordingly, the lack of light on the output routing element **107** indicates that the symbols of the search word **103** and the QCAM stored word at the respective bit position are matched.

[0039] When the symbol of the encoded word is a logical '0', the input (encoded optical search signal from the input encoder **102**) does not include light of an encoded wavelength representing the first encoded search bit value s.sub.1 (e.g., light on the input routing element **104** having an amplitude below a threshold amplitude A) of the associated bit position and does include light of the single wavelength having an amplitude A (e.g., equal to or above a threshold amplitude A) representing the second encoded search bit value s.sub.2. If the symbol of the QCAM stored word at the corresponding bit position is also a logic '0', the modulator **101** would be driven such that the modulator **101** is tuned to pass light of the encoded wavelength representing the first encoded search bit value s.sub.1 and block light of the encoded wavelength representing the second encoded search bit value s.sub.2. Therefore, because the modulator **101** is configured to pass light of the single wavelength representing the first encoded search bit value s.sub.1, no light (e.g., light having an amplitude below the threshold amplitude A) would pass through the modulator **101** and into the output routing element **107** (because light of the encoded wavelength included in the signal representing the first encoded search bit value s.sub.1 is below the threshold amplitude A). And, because the modulator **101** is configured to block light of the encoded wavelength representing the second encoded search bit value s.sub.2, the light on the input routing element **104** is not permitted to pass (e.g., attenuated) through the modulator **101** and into an output routing element **107**. Accordingly, the lack of light on the output routing element **107** indicates that the symbols of the search word **103** and the QCAM stored word at the respective bit position are matched.

[0040] In addition, if the symbol of the bit position of the QCAM stored word is a reject value 'p', regardless of whether the input is a logic '1' or '0', light is present on the output routing element **107** (e.g., the light has an amplitude equal to or above the threshold amplitude A). To represent the reject value 'p', the modulator **101** is driven by the programming controller **106** to pass light of the encoded wavelength on which the search word **103** is encoded representing the first and second encoded search bit values s.sub.1, s.sub.2. Therefore, a mismatch is indicated for that bit position whenever light is on the input routing element **104**, which is permitted to pass through the modulator **101** and into an output routing element **107**. Similarly, if the search word **103** included a reject value 'p' at a bit position, a mismatch would be indicated regardless of whether the input is a logic '1' or '0', because light would be present on the input routing element **104** (e.g., light having

an amplitude equal to or above the threshold amplitude A), and therefore light (e.g., light having an amplitude equal to or above than the threshold amplitude A) would pass the modulator **101** onto the output routing element **107**.

[0041] If the symbol of the bit position of the QCAM stored word is a wildcard value 'X', regardless of whether the input is a logic '1' or '0' or a reject value 'p', no light is present on the output routing element **107** (e.g., the light has an amplitude less than the threshold amplitude A). To represent the wildcard value 'X', the modulator **101** is driven by the programming controller **106** to block light of the encoded wavelength representing the first and second encoded search bit values s.sub.1, s.sub.2. Therefore, a match is always indicated for that bit position, regardless of the value at the corresponding bit position of the search word **103**. Similarly, if the search word **103** included a wildcard value 'X' at a bit position, a match would always be indicated regardless of the associated bit value at the bit position in the QCAM stored word because no light would be on the input routing element **104** (e.g., light having an amplitude less than the threshold amplitude A), and therefore no light (e.g., light having an amplitude less than the threshold amplitude A) would pass the modulator **101** onto the output routing element **107**.

[0042] A mismatch at a given bit position can be indicated by the presence of light on the output routing element **107** (e.g., equal to above a threshold amplitude A). As seen in Table 3, when the bit position of the input is a logic '1' but the bit position of the QCAM stored word is a logic '0' light is passed to the output routing element **107** representing the first encoded search bit value s.sub.1. The modulator **101** is configured to pass light of the single wavelength and the input includes light having an amplitude A (e.g., least an amplitude A) of the single wavelength on the input routing element **104** representing the first encoded search bit value s.sub.1. Therefore, the light would pass through the modulator **101** to the output routing element **107**. Where the bit values are reversed, light would be on the output routing element **107** representing the second encoded search bit value s.sub.2, indicating the mismatch between the search word **103** and the QCAM search word at the respective bit position.

[0043] In various examples, the encoding of the input search word **103** can be performed in accordance with a clock (CLK) signal from clock **105**. The CLK signal can be used to identify each of the encoded search bit values s.sub.1, s.sub.2 associated with each respective bit position of the search word **103**. In various examples, the CLK signal from clock **105** can also be used by the programming controller **106** to generate the drive signal used to configure the modulator **101** to represent the QCAM stored word. In some examples, the programming controller **106** can include one or more circuits to delay the CLK signal from clock **105** such that the programming controller **106** applies the drive signal in sync with the encoded search signal **110** as it is optically coupled into the modulator **101**. In some examples, a second CLK signal (different from the CLK signal used by the input encoder **102**) can be sent to the programming controller **106** from the same clock **105** or a different clock source.

[0044] As seen in FIG. 1, a photodetector **109** can be optically coupled to a result end of the output routing element **107** in various examples. The photodetector **109** can be configured to sense the amplitude of light present on the output routing element **107**, thereby detecting the mismatch and/or match for the respective bit position. In various examples, the photodetector **109** can comprise a photodiode or other type of circuit-type detector of photons. In various examples, each photodetector **109** can include circuitry configured to output a memory address corresponding to the stored word represented by the modulator **101**. In some examples, each photodetector **109** can output a match/mismatch indication to an encoder circuit (not shown in FIG. 1) configured to generate the memory address corresponding to the stored word of the modulator **101** for which a match indication is received from a photodetector **109**. In some examples, each photodetector **109** may send the indication to a processing circuit within the optical search engine **100** (not shown in FIG. 1) being configured to identify the memory address associated with the specific QCAM stored word represented by the modulator **101** and output an electrical signal to a memory controller or

other device controller access to the memory storage.

[0045] In various examples, the photodetector **109** can be configured to integrate the mismatches during a search cycle of the search word **103** (i.e., over the $2n$ encoded search bit values s), enabling the photodetector **109** to determine the sum of all mismatches between the search word **103** and the QCAM stored word represented by the modulator **101**. In various examples, the photodetector **109** can include circuitry configured to perform the integration of light for the duration of the search cycle, while in some examples the photodetector **109** can be configured with a long time-constant (TC) to enable integration to occur within the photodetector **109**. In some examples, the photodetector **109** can be configured to flag or otherwise identify at which bit positions a mismatch occurred.

[0046] Although a single modulator **101** is illustrated in FIG. 1, in various examples the optical search engine **100** can comprise a plurality of modulators **101**, each modulator **101** configured to represent a different QCAM stored word, or modulator **101** can be configured to represent a plurality of QCAM stored words. In this way, a plurality of stored words can be compared against the search word **103** during the same search operation.

[0047] In some examples, optical search engine **100** may be configured to perform a TDM QCAM. For example, the input encoder **102** may be configured to encode a received search word **103** in the time domain. In this case, the bits of each of the one or more search words **103** may be encoded during different time slots. In some examples, a plurality of search words **103** may be encoded by encoding each search word using a different encoding wavelength and the bits of the search words may be encoded during different time slots. In this case, one or more bits of each respective search word may be encoded in common time intervals. For example, a first bit from each of the plurality of search words may be encoded during a first time slot, while a second bit from each of the plurality of search words may be encoded during a second time slot, and so on.

[0048] Referring to Table 1, with reference to a single search word **103** as an illustrative example, encoded search bit values $s_{\text{sub.1}}$, $s_{\text{sub.2}}$ can be encoded during two time slots $t_{\text{sub.1}}$, $t_{\text{sub.2}}$, respectively. For example, to provide a search word symbol of logic '1', light having an amplitude A can be transmitted within the first time slot $t_{\text{sub.1}}$ (e.g., to represent encoded search bit values $s_{\text{sub.1}}$) associated with the bit position and light amplitude of approximately 0 can be transmitted within the second time slot $t_{\text{sub.2}}$ (e.g., to represent encoded search bit values $s_{\text{sub.2}}$). In various examples, the time slots $t_{\text{sub.1}}$, $t_{\text{sub.2}}$ associated with a bit position may comprise consecutive time slots, while in other examples the associated time slots $t_{\text{sub.1}}$, $t_{\text{sub.2}}$ with a bit position may comprise non-consecutive time slots. In various examples, the encoded search signal **110** can comprise $2n$ time slots, where n is the number of bit positions in the search word.

[0049] To perform a TDM search operation, the modulator **101** can be modulated in time to represent a QCAM stored word, according to the encoding scheme shown in Table 2 above. For example, the programming controller **106** can be configured to tune the modulator **101** either to allow light of the wavelength of the encoded word or to block the light during a time slot. Thus, the modulator **101** can either be configured to pass light or block light within the time slots t associated with the bit position of the QCAM stored word bit value. For example, to represent a logic '1', the modulator **101** can be tuned to block light at the encoded wavelength during the first time slot $t_{\text{sub.1}}$ associated with the bit position and tuned to pass light at the encoded wavelength during the second time slot $t_{\text{sub.2}}$. To represent a logic '0', the modulator **101** can be tuned to pass light at the encoded wavelength during the first time slot $t_{\text{sub.1}}$ associated with the bit position and tuned to block light at the encoded wavelength during the second time slot $t_{\text{sub.2}}$. To represent a wildcard value 'X', the modulator **101** can be tuned to block light at the encoded wavelength during both time slots $t_{\text{sub.1}}$, $t_{\text{sub.2}}$ associated with the bit position. To represent a reject value ' p ', the modulator **101** can be tuned to pass light at the encoded wavelength during both time slots $t_{\text{sub.1}}$, $t_{\text{sub.2}}$ associated with the bit position.

[0050] To encode a plurality of search words **103**, encoded search bit values $s_{\text{sub.1}}$, $s_{\text{sub.2}}$ of each

search word **103** can be encoded during two time slots $t_{\text{sub.1}}$, $t_{\text{sub.2}}$, respectively, using different wavelengths for each search word **103**. The modulator **101** can either be configured to pass light or block light within the time slots t associated with the bit position of the QCAM stored word bit value at the encoded wavelengths.

[0051] Using the encoding scheme discussed above, the optical search engine **100** can be configured to provide full optical quaternary search functionality through TDM encoding. In this way, the optical-to-electrical conversions can be avoided and the search can be performed faster. Utilizing the TDM encoding makes the optical search engine **100** more compatible with current photonics capabilities by reducing the need for optical buffers, reducing the latency in the system. Encoding in the time domain further enables each QCAM stored word to be represented with a single modulator **101** (which may comprise one or more optical elements (e.g., rings, MZIs, photonic crystals, etc.)), reducing the footprint of the optical search engine **100** and enabling more QCAM stored words to be compared against an input search word. Based on the logic states indicated in Tables 1 and 2, light will pass through the modulator **101** during a given time slot t only when a mismatch occurs between the value of the bit position of the search word **103** and the corresponding value of the bit position of the QCAM stored word, as set forth in Table 3 above.

[0052] In various examples, the photodetector **109** can be configured to integrate the mismatches over time for the duration of the search word **103** (i.e., for the duration of the $2n$ time slots t), enabling the photodetector **109** to determine the sum of all mismatches between the search word **103** and the QCAM stored word represented by the modulator **101**. In this way, the degree of mismatch between the search word **103** and the respective QCAM stored word.

[0053] U.S. Pat. No. 11,200,929, the disclosure of which is incorporated herein by reference in its entirety, provides examples optical search engines implemented for TDM-based optical TCAM. The optical search engines disclosed therein may be extended to the presently disclosed technology so to implement the encoding schemes as described above.

[0054] In some examples, optical search engine **100** may be configured to perform a WDM O-QCAM. For example, the input encoder **102** may be configured to encode a received search word **103** in the wavelength domain. In this case, each bit of a search word **103** may be encoded using different wavelengths of light. In some examples, a plurality of search words **103** may be encoded using different time slots. For example, the bits of each search word may be encoded using different wavelengths during a respective time slot designated for a given search word. For example, the bits of a first search word may be encoded during a first time slot using different wavelengths to encode each bit, while bits of another search word maybe encoded during a second time slot using the different wavelengths.

[0055] Referring to Table 1, encoded search bit values $s_{\text{sub.1}}$, $s_{\text{sub.2}}$ can be encoded using two wavelengths of light $\lambda_{\text{sub.1}}$, $\lambda_{\text{sub.2}}$, respectively. For example, to provide a search word symbol of logic '1', light having an amplitude A can be transmitted using a first wavelength $\lambda_{\text{sub.1}}$ (e.g., to represent encoded search bit values $s_{\text{sub.1}}$) associated with the bit position and light amplitude of approximately 0 can be transmitted using a second wavelength $\lambda_{\text{sub.2}}$ (e.g., to represent encoded search bit values $s_{\text{sub.2}}$). In various examples, the encoded search signal **110** can comprise $2n$ wavelengths, where $2n$ is the number of bit positions in the search word and n is the number of symbols.

[0056] To perform a WDM search operation, the modulator **101** can be modulated in the wavelength domain to represent a QCAM stored word, according to the encoding scheme shown in Table 2 above. For example, the programming controller **106** can be configured to tune the modulator **101** either to allow light of the respective wavelength of the encoded word or to block the light of the respective wavelength. Thus, the modulator **101** can either be configured to pass light or block light for a given wavelength λ associated with the bit position of the QCAM stored word bit value. For example, to represent a logic '1', the modulator **101** can be tuned to block light at the first wavelength $\lambda_{\text{sub.1}}$ associated with the bit position and tuned to pass light at the second

wavelength $\lambda_{\text{sub}.2}$. To represent a logic '0', the modulator **101** can be tuned to pass light at the first wavelength $\lambda_{\text{sub}.1}$ associated with the bit position and tuned to block light at the encoded the second wavelength $\lambda_{\text{sub}.2}$. To represent a wildcard value 'X', the modulator **101** can be tuned to block light at using both wavelengths $\lambda_{\text{sub}.1}$, $\lambda_{\text{sub}.2}$ associated with the bit position. To represent a reject value 'p', the modulator **101** can be tuned to pass light using both wavelengths $\lambda_{\text{sub}.1}$, $\lambda_{\text{sub}.2}$ associated with the bit position.

[0057] Using the encoding scheme discussed above, the optical search engine **100** can be configured to provide full optical quaternary search functionality through WDM encoding. In this way, the optical-to-electrical conversions can be avoided and the search can be performed faster. Utilizing the WDM encoding makes the optical search engine **100** more compatible with current photonics capabilities by reducing the need for optical buffers, reducing the latency in the system. Encoding in the wavelength domain further enables each QCAM stored word to be represented with a single modulator **101** (which may comprise one or more optical elements (e.g., rings, MZIs, photonic crystals, etc.)), reducing the footprint of the optical search engine **100** and enabling more QCAM stored words to be compared against an input search word. Additionally, encoding in the wavelength domain can enable processing a single search word within a single search cycle, thereby reducing latency.

[0058] In various examples, the photodetector **109** can be configured to integrate the mismatches by aggregating detected light for a search word **103**, enabling the photodetector **109** to determine the sum of all mismatches between the search word **103** and the QCAM stored word represented by the modulator **101**. In this way, the degree of mismatch between the search word **103** and the respective QCAM stored word.

[0059] U.S. Pat. No. 11,057,143, the disclosure of which is incorporated herein by reference in its entirety, provides examples optical search engines implemented for WDM-based optical TCAM. The optical search engines disclosed therein may be extended to the presently disclosed technology so to implement the encoding schemes as described above.

[0060] FIG. 2A an example optical search engine **200** in accordance an example of the present disclosure. The optical search engine **200**, in this example, may be implemented to perform TDM O-QCAM in accordance with the examples herein. The optical search engine **200** is provided for illustrative purposes only and should not be interpreted as limiting the scope of the disclosed technology to only the depicted example. In examples, optical search engine **200** may be implemented to compare a number of K search words, each having a number of L bits, and a number M QCAM stored words, each having a number of L bits. In various examples, optical search engine **200** performs the comparison optically executing matrix multiplication, for example, multiplying a $K \times L$ matrix representing the search words with an $M \times L$ matrix representing QCAM words that are stored in a memory, such as QCAM word storage **108** of FIG. 1.

[0061] As shown in FIG. 2A, a plurality of search words **203A-203K** (collectively referred to herein as search words **203**) can be received an input encoder **202**. The input encoder **202** may be substantially similar to input encoder **102** described above in connection with FIG. 1. For example, search words **203A-203K** can be encoded by the input encoder **202** by modulating input optical signals provided by one or more optical source(s) **211** to generate an encoded search signal **210**, similar to the encoding discussed with respect to FIG. 1. In various examples, the optical source(s) **211** can comprise one or more types of light emitting diodes (LEDs; potentially with subsequent narrow-band filters), multi-wavelength lasers (e.g., comb lasers), vertical cavity surface emitting lasers (VCSELs), or other light emission sources. In various examples, the optical source(s) **211** can be communicatively coupled to the input encoder **202** so that the input encoder **202** can encode the search words **203** on one or more optical signals of multiple wavelengths of light emitted by the optical source(s) **211**. In some examples, input encoder **202** may be implemented using modulators to encode input light from optical source(s) **211** with the bits of the search words **203**, for example, by modulating an optical power.

[0062] The input encoder **202** may be configured to encode the search words **203** in the time domain. In various examples, each of the search words **203** may be encoded using a different encoding wavelength (e.g., K different wavelengths), while the bits of each search word **203** may be encoded during different time slots according to encoding scheme described in Table 1 discussed above in connection with FIG. 1. For example, as shown in FIG. 2A, bits of search word **203A** can be encoded on first wavelength $\lambda_{\text{sub.1}}$, bits of search word **203B** can be encoded on second wavelength $\lambda_{\text{sub.2}}$, and so on until search word **203K** can be encoded on a k th wavelength λ_K , and encoded search bit values $s_{\text{sub.1}}$, $s_{\text{sub.2}}$ of each search word **203** can be encoded during two time slots $t_{\text{sub.1}}$, $t_{\text{sub.2}}$, respectively. In some examples, input encoder **202** may be implemented using modulators to tune an amplitude of the optical signal at each wavelength according to the encoding scheme.

[0063] The encoded search signal **210** generated by the input encoder **202** can be coupled to an input routing element **204**. Input routing element **204** may be an example implementation of input routing element **104** of FIG. 1. The input routing element **204** can include one or more coupling components **218** disposed at the first end to couple the encoded search signals **203** from the input encoder **202** and at the second end to into a search engine **212**. In the example of FIG. 2A, the input routing element **204** is coupled to a $1 \times K$ optical splitter as an example coupling components **218**, which splits the encoded search signal **203** on the input routing element **204** into multiple copies of the encoded search signal encoded search signal **210A-210K**.

[0064] In some examples, optical source(s) **211** may comprise multiple sources (e.g., a number G of optical sources) that supply multiple input optical signals to the input encoder **202**. In this case, the input encoder **202** may generate a number G of encoded search signals, each of which may be identical to encoded search signal **210**. The G encoded search signals may be input into G input routing elements each of which may include a coupling component. The coupling component, in this example, may be a $1 \times K/G$ splitter, each of which may split a respective encoded search signal into K copies of encoded search signal **210A-210K** that that are coupled to the search engine **212** via input routing elements **204A-204K**. This example may be useful where power budget restricts the amount of power that can be supplied to a single optical source **211**. Thus, multiple optical sources **211** can be used to address power budget limitations.

[0065] To perform a TDM search operation, the search engine **212** can be modulated in time to represent a plurality of QCAM stored words **213A-213M**. In various examples, the search engine **212** comprises a plurality of modulators **201**, each of which may be implemented as modulator **101** of FIG. 1. In an illustrative example, each modulator **201** may be a waveguide resonator (e.g., ring modulator) or other modulator component capable of being driven by an electronic signal to tune the performance characteristics of the modulators **201**. In the example of FIG. 2A, the search engine **212** comprises an $M \times K$ array of modulators **201**. For ease of illustration, only one modulator **201** is labeled with a reference number as an illustrative example.

[0066] The plurality of modulators may be tuned through operation of one or more driver(s) **206** (e.g., programming controller **106** of FIG. 1) to represent bit positions of the QCAM stored words **213A-213M**. The driver(s) **206** may be configured to encode the QCAM stored words **213A-213M** into the plurality of modulators in the time domain. For example, driver(s) **206** may receive bits of each QCAM stored word **213A-213M** from a memory (e.g., QCAM word storage **108** of FIG. 1) associated with different time slots and may be operated, during each respective time slot, to tune the plurality of modulators so to represent each bit of the QCAM stored word **213A-213M** during the different time slots. In this case, the entirety of each QCAM stored word **213A-213M** may not be stored in the optical search engine **212**. Instead, bits of each QCAM stored word **213A-213M** can be retrieved from memory (e.g., QCAM word storage **108** of FIG. 1) and used by driver(s) **206** to store different bits of each QCAM stored word **213A-213M** during different time slots. Each modulator **201** can be communicatively coupled to one or more tuning components, which can tuned by driver(s) **206**. Each of the one or more tuning components may be capable of changing an

optical characteristic of the one or more modulators that make up each modulator **201** to enable tuning of the performance of the modulator **201**. In various examples, the one or more tuning components can comprise one or more devices configured to change the refractive index of the core or cladding of the one or more modulators, control the number of free carriers, and/or create a red and/or blue shift of the resonance wavelength of the one or more modulators. Non-limiting examples of tuning components include heaters, electrical contacts, among other devices used to tune the resonance wavelength of optical components.

[0067] FIG. 2B illustrates an example implementation of search engine **212** in which the modulators are implemented as waveguide resonators. In the example of FIG. 2B, search engine **212** comprises waveguide resonators **201A-A** through **201M-K** coupled to input routing element **204A-204K**, as described in connection with FIG. 2B. The waveguide resonators **201A-A** through **201M-K** are arranged in rows. For example, as shown in FIG. 2B, waveguide resonators **201A-A** through **201M-A** are coupled to input routing element **204A** and waveguide resonators **201A-K** through **201M-K** are coupled to input routing element **204K**. The waveguide resonators **201A-A** through **201M-K** are designed for a plurality of resonance frequencies (e.g., $\lambda_{\text{sub.1}}$ through $\lambda_{\text{sub.k}}$), such that each row comprises one waveguide resonator of each resonance frequency and each column comprises one waveguide resonator of each resonance frequency.

[0068] The plurality of waveguide resonators **201A-A** through **201M-K** may be tuned through operation of driver(s) **206** (shown in FIG. 2B as driver(s) **206A** through **206M**) to represent bit positions of the QCAM stored words **213A-213M**. Each waveguide resonator **201A-A** through **201M-K** can be communicatively coupled to one or more tuning components **214** capable of changing an optical characteristic of the waveguide resonator **201A-A** through **201M-K**. In various examples, the one or more tuning components can comprise one or more devices configured to change the refractive index of the waveguide resonators **201A-A** through **201M-K** that causes a shift of the resonance frequency. A shift in the resonance frequency can result in blocking an input optical signal that propagates at the un-shifted resonance frequency. For example, waveguide resonator **201A-A** can have a resonance frequency corresponding to $\lambda_{\text{sub.1}}$ (e.g., speed of light divided by $\lambda_{\text{sub.1}}$), which can pass light at $\lambda_{\text{sub.1}}$ from the input routing element **204A** to a drop routing element **207A-A** (e.g., examples of output routing element **107** of FIG. 1). Similarly, waveguide resonators **201B-A** through **201M-K** can pass light to a respective drop routing element **207B-A** through **207M-K**. To block light, driver **206A** can drive tuning component **214** coupled to waveguide resonator **201A-A** to shift the resonance frequency and block (e.g., absorb) light at $\lambda_{\text{sub.1}}$ on input routing element **204A**. Driver(s) **206**, in some examples, can drive the tuning component **214** by tuning a voltage bias applied to the tuning component that induces the shift. The waveguide resonators **201B-A** through **201M-K** can be similarly driven to block light at corresponding wavelengths.

[0069] Returning to FIG. 2A, in performing an operation on the search words **203** encoded in accordance with Table 1, the driver(s) **206** can be configured to encode the QCAM stored words **213A-213M** into the search engine **212** by tuning the plurality of modulators **201** in time to either allow light of the respective wavelength of the encoded search word to pass or to block the light, according to the encoding scheme of Table 2. For example, bits of each QCAM stored word **213A-213M** can be encoded into a column of the $M \times K$ array of modulators **201** in time (e.g., different time slots) so to compare each bit of the search words **203** with each bit of the QCAM stored word **213A-213M**. In the example of FIG. 2A, the driver(s) **206** can be configured to tune a first column **216** of modulators **201** with a first bit of the QCAM stored data word **213A** during a first time slot $t_{\text{sub.1}}$ and a second bit of the QCAM stored data word **213A** during a second time slot $t_{\text{sub.2}}$. Thus, referring to Table 2, to represent an encoded stored data bit value logic '1', the modulators **201** in column **216** can be tuned to block light of an encoded wavelength during a first time slot $t_{\text{sub.1}}$ and tuned to pass light at the encoded wavelength during the second time slot $t_{\text{sub.2}}$. Each stored data word **213B-213M** can be similarly encoded into a corresponding column of the search

engine. In this example, two modulators **201** may constitute an O-QCAM cell, because two modulators **201** may be needed to represent a symbol value as two bit positions.

[0070] To provide for comparing a bit of each search word **203A-203K** to a bit of each stored word **213A-213M**, each modulator **201** of a given column of the $M \times K$ array is encoded according to a different wavelength (e.g., $\lambda_{\text{sub.1}}$ through $\lambda_{\text{sub.k}}$). The different wavelengths correspond to the different wavelengths used for carrying the bits of the search words **203A-203K**, such that M and K are equal in this example. Such that a given column of the $M \times K$ array comprises a modulator **201** tuned to pass or block light for each wavelength carried on the encoded search signals **210A-210K**. Accordingly, as an example referring to Table 2, to represent an encoded stored data bit value logic '1', a first modulator **201** in column **216** can be tuned to block light of a first encoded wavelength during a first time slot $t_{\text{sub.1}}$ and tuned to pass light at the first encoded wavelength during the second time slot $t_{\text{sub.2}}$, while the k th modulator **201** in column **216** can be tuned to block light of a k th encoded wavelength during a first time slot $t_{\text{sub.1}}$ and tuned to pass light at the k th encoded wavelength during the second time slot $t_{\text{sub.2}}$. Similarly, to represent a logic '0', the first modulator **201** in column **216** can be tuned to pass light of the first encoded wavelength during the first time slot $t_{\text{sub.1}}$ and tuned to block light at the first encoded wavelength during the second time slot $t_{\text{sub.2}}$, while the k th modulator **201** in column **216** can be tuned to pass light of a k th encoded wavelength during a first time slot $t_{\text{sub.1}}$ and tuned to block light at the k th encoded wavelength during the second time slot $t_{\text{sub.2}}$. To represent a wildcard value 'X', the first modulator **201** can be tuned to block light at the first encoded wavelength during time slots $t_{\text{sub.1}}$, $t_{\text{sub.2}}$ associated with the bit position, while the k th modulator **201** can be tuned to block light at the k th encoded wavelength during time slots $t_{\text{sub.1}}$, $t_{\text{sub.2}}$ associated with the bit position. To represent a reject value 'p', the first modulator **201** can be tuned to pass light at the first encoded wavelength during time slots $t_{\text{sub.1}}$, $t_{\text{sub.2}}$ associated with the bit position, while the k th modulator **201** can be tuned to pass light at the k th encoded wavelength during time slots $t_{\text{sub.1}}$, $t_{\text{sub.2}}$ associated with the bit position.

[0071] Based on the logic states indicated in Tables 1 and 2, according to an example, light will pass through the modulators **201** during a given time slot only when a mismatch occurs between the value of the bit position of the search words **203A-213N** and the corresponding value of the bit position of the QCAM stored words **213A-213M**. Table 3 shows the results based on the encoded bit value on the optical search signal and of the corresponding modulator **201**. Light passed by the modulators **201** can be coupled (e.g., evanescently coupled in the case of a ring modulator, or other optical element capable of coupling light from a modulator) to a group of output routing elements **215A-215K**, each of which represents a group of drop routing elements **207A-A** through **207M-K** (e.g., FIG. 2B) associated with a respective column. Each group of output routing element **215A-215K** may be coupled to a subset of the modulators **201**, for example, each group of output routing element **215A-215K** may be coupled to a subset of modulators encoded according to a given stored word **213A-213M**. For example, group of output routing element **215A**, which may comprise drop routing elements **207A-A** through **207K-A**, is coupled to each of modulators **201** of column **216** encoded with bits for stored data word **213A**. Thus, any mismatches occurring along the column **216** (e.g., light passed by modulators **201**) can be coupled into the group of output routing elements **215A**. Similarly, groups of output routing elements **215B-215K** may receive light from respective modulators **201** representing mismatches of a respective comparison.

[0072] Photodetectors (e.g., implementations of photodetector **109** of FIG. 1) can be optically coupled to a result end of the groups of output routing elements **215A-215K** in various examples. For example, as shown in FIG. 2B, photodetectors **209A-A** through **209M-K** can be optically coupled to a respective drop routing elements **207A-A** through **207A-K** and configured to sense the amplitude of light present on the respective drop routing element **207A-A** through **207A-K**, thereby detecting the mismatch and/or match for the respective bit position. Accordingly, each photodetector **209A-A** through **209M-K** may detect an amplitude of light at a corresponding

wavelength of light, thereby detecting the mismatch and/or match for a respective bit position. In some examples, each photodetectors **209A-A** through **209M-K** can output a match/mismatch indication to an encoder circuit (not shown) configured to generate match addresses **1** through **K** corresponding to the stored words **213A-213M** of the search engine **212** for which a match indication is received from photodetectors **209A-A** through **209M-K**. In some examples, each photodetector may send the indication to a processing circuit within the optical search engine **200** being configured to identify the memory address associated with the specific QCAM stored words represented by the search engine **212** and output an electrical signal to a memory controller or other device controller access to the memory storage.

[0073] In various examples, each photodetector **209A-A** through **209M-K** can be configured to integrate the mismatches over time for the duration of the search words **213A-213M** (i.e., for the duration of the $2n$ time slots t , also referred to as a search cycle), enabling the each photodetector **209A-A** through **209M-K** to determine a sum of all mismatches between a given search word **213A-213M** and a given QCAM stored word represented by the a column of the search engine **212**. In some examples, the photodetectors **209A-A** through **209M-K** can be configured to flag or otherwise identify at which bit positions a mismatch occurred.

[0074] Note that since matches/mismatches are detected from drop routing elements **207A-A** through **207A-K**, in this example, the plurality of modulators may be tuned through operation of driver(s) **206** to represent an inverse of the bit value at bit positions of the QCAM stored words **213A-213M**. This is because the coupling into respective drop routing elements **207A-A** through **207A-K** outputs an inverse of the state represented by the modulator and the input light. Thus, by tuning the modulators to represent inverse bits of the QCAM stored words **213A-213M**, as shown in FIG. 2B, examples herein can output detect matches and mismatches in accordance with Table 3 above.

[0075] FIG. 3A illustrates an example optical search engine **300** in accordance another example of the present disclosure. The optical search engine **300**, in this example, may be implemented to perform WDM O-QCAM in accordance with the examples herein. The optical search engine **300** is provided for illustrative purposes only and should not be interpreted as limiting the scope of the disclosed technology to only the depicted example. In examples, optical search engine **300** may be implemented to compare a number of K search words, each having a number of L bits, and a number M QCAM stored words, each having a number of L bits. In various examples, optical search engine **300** performs the comparison by optically executing matrix multiplication, for example, multiplying an $L \times K$ matrix representing the search words with an $M \times L$ matrix representing the QCAM stored words.

[0076] As shown in FIG. 3A, a plurality of search words **303A-303K** (collectively referred to herein as search words **303**) can be received an input encoder **302**. The input encoder **302** may be substantially similar to input encoder **102** described above in connection with FIG. 1. For example, search words **303A-303K** can be encoded by the input encoder **302** by modulating input optical signals provided by one or more optical source(s) **311** to generate encoded search signals **310A** through **310M**, similar to the encoding discussed with respect to FIGS. 1 and 2A. In various examples, the optical source(s) **311** can comprise one or more types of light emitting diodes (LEDs; potentially with subsequent narrow-band filters), multi-wavelength lasers (e.g., comb lasers), vertical cavity surface emitting lasers (VCSELs), or other light emission sources. In various examples, the optical source(s) **311** can be communicatively coupled to the input encoder **302** so that the input encoder **302** can encode the search words **303** on an optical signal of multiple wavelengths of light emitted by the optical source(s) **311**. In some examples, input encoder **302** may be implemented using modulators to encode input light from optical source(s) **311** with the bits of the search words **303**.

[0077] The input encoder **302** may be configured to encode the search words **303** in the wavelength domain. In various examples, each bit of a given search word **303** may be encoded using a different

encoding wavelength according to encoding scheme described in Table 1 discussed above in connection with FIG. 1, while each search word **303** may be encoded during different time slots. For example, as shown in FIG. 3A, a first bit of search word **303A** (e.g., logic “0”) can be encoded on first wavelength $\lambda_{\text{sub.1}}$, a second bit of search word **303A** (e.g., logic “1”) can be encoded on second wavelength $\lambda_{\text{sub.2}}$, and so on until a Lth bit of search word **303A** (e.g., logic “0”) can be encoded on a Lth wavelength $\lambda_{\text{sub.L}}$. In this example, each search word **303** can be encoded during a different time slot t.

[0078] The encoded search signals **310A-310M** generated by the input encoder **302** can be coupled to input routing elements **304A-304M** via a coupling component **318**. Each input routing elements **304A-304M** may an example implementation of input routing element **104** of FIG. 1. The input routing elements **304A-304M** can include one or more coupling components **318** disposed at the first end to couple the encoded search signals **310A-310M** from the input encoder **302** and at the second end to couple the encoded search signals **310A-310M** into a search engine **312**. In the example of FIG. 3A, the input routing elements **304A-304M** are coupled to a $1 \times M$ optical splitter, which splits an encoded search signal generated by the input encoder **302** into encoded search signals **310A-310M** on the input routing elements **304A-304M** into routing elements of the search engine **312**.

[0079] In some examples, optical source(s) **311** may comprise multiple sources (e.g., a number G of optical sources) that supply multiple input optical signals to the input encoder **302**. In this case, the input encoder **302** may generate a number G of encoded search signals. The NG encoded search signals may be input into G input routing elements each of which may include a coupling component. The coupling components, in this example, may be $1 \times M/G$ splitters, each of which may split a respective encoded search signal into encoded search signal **310A-310M** that are coupled to the search engine **312** via input routing elements **304A-304M**. This example may be useful where power budget restricts the amount of power that can be supplied to a single optical source **311**.

[0080] To perform a WDM based search operation, the search engine **312** can be wavelength modulated to represent a plurality of QCAM stored words stored in QCAM word storage **308** (e.g., an example implementation of QCAM word storage **108** of FIG. 1). In various examples, the search engine **312** comprises a plurality of modulators **301**, each of which may be implemented as modulator **101** of FIG. 1. In an illustrative example, each modulator **301** may be a waveguide resonator (e.g., ring modulator, ring filter, or the like) or other modulator component capable of being driven by an electronic signal to tune the performance characteristics of the modulators **301**. In the example of FIG. 3A, the search engine **312** comprises an $M \times L$ array of modulators **301**. For ease of illustration, only one modulator **301** is labeled with a reference number as an illustrative example.

[0081] The plurality of modulators may be tuned through operation of one or more driver(s) **306** (e.g., programming controller **106** of FIG. 1) to represent bit positions of the QCAM stored words stored in QCAM word storage **308**. Each modulator **301** can be communicatively coupled to one or more tuning components, each of the one or more tuning components may be capable of changing an optical characteristic of the one or more modulators that make up each modulator **301** to enable tuning of the performance of the modulator **301**. In various examples, the one or more tuning components can comprise one or more devices configured to change the refractive index of the core or cladding of the one or more modulators, control the number of free carriers, and/or create a red and/or blue shift of the resonance wavelength of the one or more modulators. Non-limiting examples of tuning components include heaters, electrical contacts, among other devices used to tune the resonance wavelength of optical components.

[0082] FIG. 3B illustrates an example implementation of search engine **312** in which the modulators are implemented as waveguide resonators **301A-A** through **301M-L**. In the example of FIG. 3B, search engine **312** comprises waveguide resonators **301A-A** through **301M-L** coupled to

input routing element **304A-304M**, as described in connection with FIG. 3B. The waveguide resonators **301A-A** through **301M-L** are arranged in rows. For example, as shown in FIG. 3B, waveguide resonators **301A-A** through **301A-L** are coupled to input routing element **304A** and waveguide resonators **301M-A** through **301M-L** are coupled to input routing element **304M**. The waveguide resonators **301A-A** through **301M-L** are designed for a plurality of resonance frequencies (e.g., $\lambda_{\text{sub.1}}$ through $\lambda_{\text{sub.L}}$), such that each row comprises one waveguide resonator of each resonance frequency.

[0083] The plurality of waveguide resonators **301A-A** through **301M-L** may be tuned through operation of driver(s) **306** to represent bit positions of the QCAM stored words. For example, each row of waveguide resonators **301A-A** through **301M-L** may be tuned according to a respective QCAM stored word. Each waveguide resonator **301A-A** through **301M-L** can be communicatively coupled to one or more tuning components **314** capable of changing an optical characteristic of the waveguide resonator **301A-A** through **301M-L**. In various examples, the one or more tuning components **314** can comprise one or more devices configured to change the refractive index of the waveguide resonators **301A-A** through **301M-L** that causes a shift of the resonance frequency. A shift in the resonance frequency can result in blocking an input optical signal that propagates at the un-shifted resonance frequency. For example, waveguide resonator **301A-A** can have a resonance frequency corresponding to $\lambda_{\text{sub.1}}$, which can pass light at $\lambda_{\text{sub.1}}$ from the input routing element **304A** to photodetector **309A** (e.g., an example of photodetector **109** of FIG. 1). Similarly, waveguide resonators **301A-B** through **301M-L** can pass light to a respective photodetector **309A-309M**. To block light, driver **306** can drive tuning component **314** coupled to waveguide resonator **301A-A** to shift the resonance frequency and block (e.g., absorb) light at $\lambda_{\text{sub.1}}$ on input routing element **304A**. Driver(s) **306**, in some examples, can drive the tuning components **314** by tuning a voltage bias applied to the tuning components that induces the shift. The waveguide resonators **301A-B** through **301M-L** can be similar driven to block light a corresponding wavelengths.

[0084] Returning to FIG. 3A, in performing an operation on the search words **303** encoded in accordance with Table 1, the driver(s) **306** can be configured to encode the QCAM stored words into the search engine **312** by tuning the plurality of modulators **301** to either allow light of an encoded wavelength to pass or to block the light of the encoded wavelength, according to the encoding scheme of Table 2. For example, each QCAM stored word can be encoded into a respective row of the $M \times L$ array of modulators **301**. For example, row **316**, as an illustrative example, can be encoded with a first QCAM stored word, while each other row can be encoded with a respective QCAM stored word. The driver(s) **306** can be configured to encode each modulator **301** of a given row with a bit value of the respective QCAM stored word. Each QCAM stored word may be associated with multiple wavelengths, and the driver(s) **306** may be configured to tune the modulators **301** of a respective row to allow light of the wavelengths to pass or to block light of the wavelengths according to the encoding scheme of Table 2. As an illustrative example, the driver(s) **306** can be configured to tune a first modulator of row **316** to block or pass light of a first wavelength according to a first bit of a first QCAM stored data word (e.g., logic “0” in this example), tune a second modulator of row **316** to block or pass light of the second wavelength according to a second bit of the first QCAM stored data word (e.g., logic “1” in this example), and so on down to a L th modulator of row **316** can be tuned to pass or block light of the L th wavelength according to an L th bit of the first QCAM stored data word (e.g., logic “0” in this example). Each QCAM stored data word is similarly encoded to a particular row, until the M th row is encoded. In this example, two modulators **301** may constitute an O-QCAM cell, because two modulators **301** may be needed to represent a symbol value as two bit positions.

[0085] Based on the logic states indicated in Tables 1 and 2, light will pass through the modulators **301** only when a mismatch occurs between the value of the bit position of a given search word **303** and the corresponding value of the bit position of the QCAM stored words. Table 3 shows the results based on the encoded bit value on the optical search signal and of the corresponding

modulator **301**. Light passed by the modulators **301** can be coupled to output routing elements **307A-307M** (e.g., examples of output routing element **107** of FIG. **1**). Each output routing element **307A-307M** may be coupled to a subset of the modulators **301**, for example, each output routing element **307A-307M** may be coupled to a row of the $M \times L$ array of modulators. For example, output routing element **307A** is coupled to each of modulators of a row **316** encoded with bits for the first QCAM stored data word. Thus, any mismatches occurring along the row **316** (e.g., light passed by modulators **301**) can be coupled into output routing element **307A**, representing mismatches of the current search word **303** with bits of the stored data word. Similarly, output routing element **307B-307M** may receive light from respective modulators **301** representing mismatches of a comparison on a respective row.

[0086] Photodetectors **309A-309M** (e.g., implementations of photodetector **109** of FIG. **1**) can be optically coupled to a result end of the output routing element **307A-307M** in various examples. The photodetectors **309A-309M** can be configured to sense the amplitude of light present on the respective output routing element **307A-307M**, thereby detecting the mismatch and/or match for the respective bit position. In some examples, demultiplexers may be disposed between the search engine **312** and photodetectors **309A-309M**, configured to filter various wavelengths of light on to respective downstream routing elements coupled to photodetectors. In this case, each photodetectors **309A-309M** may comprise a set of photodetectors for detecting amplitudes of light at each wavelength of light, thereby detecting the mismatch and/or match for a respective bit position. In some examples, each photodetectors **309A-309M** can output a match/mismatch indication to an encoder circuit **317** configured to generate the memory address corresponding to the QCAM stored data words of the search engine **312** for which a match indication is received from photodetectors **309A-309M**. In some examples, each photodetector may send the indication to a processing circuit within the optical search engine **300** being configured to identify the memory address associated with the specific QCAM stored words represented by the search engine **312** and output an electrical signal to a memory controller or other device controller access to the memory storage.

[0087] In various examples, each photodetector **309A-309M** can be configured with a wide bandwidth, enabling each photodetector **309A-309M** to detect match states resulting from a comparison between search word **303** and each QCAM stored word. In some examples, the photodetectors **309A-309M** can be configured to flag or otherwise identify at which bit positions a mismatch occurred.

[0088] FIG. **4A** illustrates an example optical search engine **400** in accordance yet another example of the present disclosure. The optical search engine **400**, in this example, may be implemented to perform TDM O-QCAM in accordance with the examples herein. The optical search engine **400** is provided for illustrative purposes only and should not be interpreted as limiting the scope of the disclosed technology to only the depicted example. Similar to optical search engine **200** of FIG. **2A**, optical search engine **400** may be implemented to compare a number of K search words, each having a number of L bits, and a number M QCAM stored words, each having a number of L bits.

[0089] Optical search engine **400** can be configured to generate encoded search signals **410A-410M** by an input encoder in a manner described above in connection with FIG. **2A**. As such, encoded search signals **410A-410M** may be substantially similar to encoded search signals **210A-210K**, except of a number of M encoded search signals are provided (e.g., the number of QCAM stored words). Furthermore, encoded search signals **410A-410M** can be coupled to input routing elements **404A-404M**, which may be examples of input routing elements **204A-204M**.

Accordingly, the description above in connection with FIG. **2A** applies equally to optical search engine **400**, which may comprise optical sources (e.g., optical source(s) **211**), coupling components (e.g., coupling components **218**), and other elements described above in connection with FIG. **2A**. Thus, input routing elements **404A-404M** can include one or more coupling components to couple the encoded search signals **410A-410M** from an input encoder into a search engine **412**.

[0090] To perform a TDM based search operation, the search engine **412** can be wavelength modulated to represent a plurality of QCAM stored word **413A-413M**. In various examples, the search engine **412** comprises a plurality of modulators **401A-401M**, each of which may be implemented as modulator **101** of FIG. **1**. In an illustrative example, each modulator **401A-401M** may be a Mach Zehnder Modulator (MZM) or other modulator component capable of being driven by an electronic signal to tune the performance characteristics of the modulators **401A-401M**. In the example of FIG. **4A**, the search engine **412** comprises an $M \times 1$ array of modulators **401A-401M**, each associated with a QCAM stored data word.

[0091] The plurality of modulators may be tuned through operation of one or more driver(s) (e.g., driver(s) **206** of FIG. **2A**) to represent bit positions of the QCAM stored words **413A-413M**. Each modulator **401A-401M** can be communicatively coupled to one or more tuning components capable of changing an optical characteristic of the one or more modulators. In various examples, the one or more tuning components can comprise one or more devices configured to change the refractive index of the core or cladding of the one or more modulators, control the number of free carriers, and/or create a red and/or blue shift of the resonance wavelength of the one or more modulators. Non-limiting examples of tuning components include heaters, electrical contacts, among other devices used to tune a phase of optical components. As an example, each modulator **401A-401M** can be tuned, via operation of the driver(s) **406** (shown in FIG. **4B**) to represent bits of each QCAM stored word **413A-413M**. That is, for example, modulator **401A** can be tuned to represent bits d.sub.1 through d.sub.L of QCAM stored word **413A**, while modulator **401M** can be tuned to represent bits d.sub.1 through d.sub.L of QCAM stored word **413M**. Thus, each modulator **401A-401M** can be tuned to represent an entire respective QCAM stored word **413A-413M**. As described below, QCAM stored word **413A-413M** can then compared against bits of each search word (e.g., **203A-203K**), encoded into encoded search signals **410A-410M**, during different time slots. For example, first bits of each search word (e.g., search words **303A-303K**), encoded into encoded search signals **410A-410M**, can be compared to the entirety of each QCAM stored word **413A-413M** during a first time slot via modulators **401A-401M**; second bits of each search word can be compared to the entirety of each QCAM stored word **413A-413M** during a second time slot; and so on until the Lth bit of each search word can be compared to the entirety of each QCAM stored word **413A-413M** during an Lth time slot.

[0092] FIG. **4B** illustrates an example implementation of modulator **401A**, as an example of modulator **401A-401M**, in which the modulators are implemented using an MZM **419**. In the example of FIG. **4B**, MZM **419** can be coupled to input routing element **404A**. The MZM **419**, in this example, can be implemented as a broadband modulator that configured to modulate the phase of multiple wavelengths (e.g., $\lambda_{\text{sub.1}}$ through $\lambda_{\text{sub.K}}$) independent of other wavelengths, such that each constructive and/or destructive interference occurs at the output of the MZM **419** on a per wavelength basis.

[0093] The MZM **419** may be tuned through operation of driver(s) **406** (e.g., driver(s) **306** of FIG. **3A**) to represent bit positions of the QCAM stored words. For example, MZM **419** may be tuned according to a respective QCAM stored word. MZM **419** can be communicatively coupled to one or more tuning components **414A-414C** capable of changing an optical characteristic of each arm of MZM **419**. Based on differences in the optical characteristics, for each wavelength, between the arms of the MZM **419**, destructive or constructive interference occurs that either blocks or passes light to output routing element **407A** (e.g., an example implementation of output routing element **107** of FIG. **1**). In various examples, the one or more tuning components can comprise one or more devices configured to change the refractive index of the waveguide constituting each arm of MZM **419** that causes a shift in the phase, on a per wavelength basis, of light propagating thereon, which can result in destructive or constructive interference. For example, constructive interference can occur at the output of MZM **419** for light of wavelength $\lambda_{\text{sub.1}}$, which can pass this light to detector component **420**. Similarly, MZM **419** can pass light at wavelengths $\lambda_{\text{sub.2}}$ through

λ .sub.K. To block light, driver **406** can drive tuning components **414A-414C** coupled to MZM **419** to shift the phase and block (e.g., destructive interference) light at λ .sub.1. Driver(s) **406**, in some examples, can drive the tuning components **414A-414C** by tuning voltage biases applied to the tuning components **414A-414C** that induces the shift. The MZM **419** can be similar driven to block light a wavelengths λ .sub.2 through λ .sub.K.

[0094] Returning to FIG. 4A, in performing an operation on the search words encoded in accordance with Table 1, the driver(s) can be configured to encode the QCAM stored words **413A-413M** into the search engine **412** by tuning the plurality of modulators **401A-401M** to either allow light of an encoded wavelength to pass or to block the light of the encoded wavelength, according to the encoding scheme of Table 2. For example, each QCAM stored word **413A-413M** can be encoded into a respective row of search engine **412**. For example, modulator **401A** can be encoded with a first QCAM stored word, while each other row can be encoded with a respective QCAM stored word. The driver(s) can be configured to retrieve the QCAM stored word **413A-413M** from memory (e.g., QCAM word storage **108** of FIG. 1) encode each modulator **401A-401M** with a bit value of the respective QCAM stored word. Each QCAM stored word may be associated with multiple wavelengths, and the driver(s) may be configured to tune the modulators **401A-401M** to allow light of the wavelengths to pass or to block light of the wavelengths according to the encoding scheme of Table 2. As an illustrative example, the driver(s) can be configured to tune a modulator **401A** (e.g., as shown in FIG. 4B) to block or pass light of a first wavelength according to a first bit of a first QCAM stored data word, tune a modulator **401A** to block or pass light of the second wavelength according to a second bit of the first QCAM stored data word, and so on until the modulator **401A** can be tuned to pass or block light of the Lth wavelength according to an Lth bit of the first QCAM stored data word. Each QCAM stored data word can be similarly encoded to a modulator **401B-401M**. In this example, each modulator **401B-401M** may constitute a distinct O-QCAM cell, because each modulator **401B-401M** can be implemented to represent one or more symbol values.

[0095] Based on the logic states indicated in Tables 1 and 2, light will pass through the modulators **401A-401M** only when a mismatch occurs between the value of the bit position of a given search word and the corresponding value of the bit position of the QCAM stored words **413A-413M**. Table 3 shows the results based on the encoded bit value on the optical search signal and of the corresponding modulator **401A-401M**. Light passed by the modulators **401A-401M** can be coupled to output routing elements **407A-407M** (e.g., examples of output routing element **107** of FIG. 1). Each output routing element **407A-407M** may be coupled to a modulator **401A-401M**, respectively. Thus, any mismatches occurring along the modulator **401A** can be coupled into output routing element **407A**, representing mismatches of the current search word with bits of the stored data word **413A**. Similarly, output routing element **407B-407M** may receive light from respective modulators **401B-401M** representing mismatches of a comparison on a respective row.

[0096] Detector components, an example of which is shown in FIG. 4B as detector component **420**, can be optically coupled to a result end of the output routing element **407A-407M** in various examples. Each detector component may include a set of photodetectors, illustratively shown in FIG. 4B as photodetectors **409A-409K**, that can be configured to sense an amplitude of light, at a respective wavelength, present on a respective output routing element, thereby detecting the mismatch and/or match for the respective bit position. That is, referring to FIG. 4B as an example, photodetectors **409A-409K** can be configured to sense an amplitude of light, at a respective wavelength λ .sub.1 through λ .sub.K, present on output routing element **407A**, thereby detecting the mismatch and/or match for the respective bit position.

[0097] In some examples, each detector component comprises demultiplexers disposed between the search engine **412** and respective set of photodetectors, configured to filter the various wavelengths of light on to respective downstream routing elements coupled to the photodetectors. For example, in the illustrative example of FIG. 4B, detector component **420** comprises demultiplexers **422A-**

422K optically coupled between output routing element **407A** and downstream routing elements **424A-424K**, respectively. Each demultiplexer **422A-422K**, which is illustratively implemented as a waveguide resonator, is configured to filter a respective wavelength of light propagating on the output routing element **407A** and couple the light into downstream routing elements **424A-424K**. The coupled light can then be supplied to a respective photodetector **409A-409K**. In the case of waveguide resonators, the demultiplexers **422A-422K** may have resonance frequencies corresponding to one of the encoded wavelengths (e.g., wavelengths $\lambda_{\text{sub.1}}$ through $\lambda_{\text{sub.K}}$), which enables the filtering described above. The set of photodetectors **409A-409K** for detecting amplitudes of light at a respective wavelength of light coupled from a respective demultiplexer **422A-422K**, thereby detecting the mismatch and/or match for a respective bit position.

[0098] In some examples, each detector component can output a match/mismatch indication to an encoder circuit (e.g., encoder circuit **317** of FIG. 3A) configured to generate the memory address corresponding to the QCAM stored data words of the search engine **412** for which a match indication is received from detector components. In some examples, each detector component may send the indication to a processing circuit communicably connected to the optical search engine **400** being configured to identify the memory address associated with the specific QCAM stored words represented by the search engine **412** and output an electrical signal to a memory controller or other device controller access to the memory storage.

[0099] In various examples, each detector component can be configured to integrate the mismatches over time for the duration of the search words (i.e., for the duration of the 2^n time slots t , also referred to as a search cycle), enabling each detector component to determine a sum of all mismatches between a given search word and a given QCAM stored word **413A-413M**. In some examples, the detector components can be configured to flag or otherwise identify at which bit positions a mismatch occurred.

[0100] FIG. 5A illustrates an example optical search engine **500** in accordance another example of the present disclosure. The optical search engine **500**, in this example, may be implemented to perform WDM O-QCAM in accordance with the examples herein, similar to optical search engines **300** of FIG. 3A. The optical search engine **500** is provided for illustrative purposes only and should not be interpreted as limiting the scope of the disclosed technology to only the depicted example. Optical search engine **500** may be implemented to compare a number of K search words, each having a number of L bits, and a number M QCAM stored words, each having a number of L bits.

[0101] As shown in FIG. 5A, a plurality of search words **503A-503K** (collectively referred to herein as search words **503**) can be received an input encoder **502**. The input encoder **502** may be substantially similar to input encoder **102** described above in connection with FIG. 1. For example, search words **503A-503K** can be encoded by the input encoder **502** by modulating input optical signals provided by one or more optical source(s) **511** to generate encoded search signals **510A** through **510M**, similar to the encoding discussed with respect to FIGS. 1, 3A, and 3B. The optical source(s) **511** may be substantially similar to the optical source(s) **311** of FIG. 3A. In various examples, the optical source(s) **511** can be communicatively coupled to the input encoder **502** so that the input encoder **502** can encode the search words **503** on an optical signal of multiple wavelengths of light emitted by the optical source(s) **511**. In some examples, input encoder **502** may be implemented using modulators to encode input light from optical source(s) **511** with the bits of the search words **503**.

[0102] The input encoder **502** may be configured to encode the search words **503** in the wavelength domain. Unlike prior examples, input encoder **502** may be configured to encode each search word according to an encoding scheme provided in Table 4 below.

TABLE-US-00004
TABLE 4 Encoded Search Word Signal Bit
Input Symbol Value (s.sub.1) Value (s.sub.2) Wavelength 0 0 1 $\lambda_{\text{sub.0}}$ 1 1 0 $\lambda_{\text{sub.1}}$ X 0 0 0 ρ 1 1 $\lambda_{\text{sub.0}}$, $\lambda_{\text{sub.1}}$

[0103] As shown in Table 4, each search word symbol can be represented by two encoded search

bit values s.sub.1, s.sub.2. To provide a search word symbol of logic '0', light having a wavelength λ .sub.0 can be transmitted within the first encoded search bit value s.sub.1 associated with the bit position and within the second encoded search bit value s.sub.2. For the search word symbol of logic '1', light having a wavelength λ .sub.1 can be transmitted within the first encoded search bit value s.sub.1 associated with the bit position and within the second encoded search bit value s.sub.2. To provide a search of wildcard symbol 'X', light amplitude of 0 (e.g., no light) can be transmitted in both of the first encoded search bit value s.sub.1 and the second encoded search bit value s.sub.2. To provide the search word symbol 'p', light of any wavelength (e.g., λ .sub.0 and/or λ .sub.1) can be transmitted in both of the first encoded search bit value s.sub.1 and the second encoded search bit value s.sub.2. In this example, each search word **503** can be encoded during a different time slot t.

[0104] The encoded search signals **510A-510M** generated by the input encoder **502** can be coupled to input routing elements **504A-504M** via a coupling component **518**. Each input routing elements **504A-504M** may be an example implementation of input routing element **104** of FIG. 1. The input routing elements **504A-504M** can include one or more coupling components **518** disposed at the first end to couple the encoded search signals **510A-510M** from the input encoder **502** and at the second end to couple the encoded search signals **510A-510M** into a search engine **512**. In the example of FIG. 5A, the input routing elements **504A-504M** can be coupled to a $1 \times M$ optical splitter, which splits an encoded search signal generated by the input encoder **502** into encoded search signals **510A-510M** on the input routing elements **504A-504M** into routing elements of the search engine **512**. In some examples, as described above in connection with FIG. 3A, a number of G optical sources **511** may be used and the coupling components may be $1 \times M/G$ splitters, each of which may split a respective encoded search signal into encoded search signal **510A-510M** that are coupled to the search engine **512** via input routing elements **504A-504M**.

[0105] To perform a search operation, the search engine **512** can be wavelength modulated to represent a plurality of QCAM stored words stored in QCAM word storage **508** (e.g., an example implementation of QCAM word storage **108** of FIG. 1). In various examples, the search engine **512** comprises a plurality of modulators **501**, each of which may be implemented as modulator **101** of FIG. 1. In an illustrative example, each modulator **501** may comprise a waveguide resonator (e.g., ring modulator) or other modulator components capable of being driven by an electronic signal to tune the performance characteristics of the modulators **501**. In the example of FIG. 5A, the search engine **512** comprises an $M \times L/2$ array of modulators **501** (e.g., one modulator for each QCAM search word symbol). For ease of illustration, only one modulator **501** is labeled with a reference number as an illustrative example.

[0106] The plurality of modulators may be tuned through operation of one or more driver(s) **506** (e.g., programming controller **106** of FIG. 1) to represent bit positions of the QCAM stored words stored in QCAM word storage **508**. Each modulator **501** can be communicatively coupled to one or more tuning components, each of the one or more tuning components may be capable of changing an optical characteristic of the one or more modulators that make up each modulator **501** to enable tuning of the performance of the modulator **501**. In various examples, the one or more tuning components can comprise one or more devices configured to change the refractive index of the core or cladding of the one or more modulators, control the number of free carriers, and/or create a red and/or blue shift of the resonance wavelength of the one or more modulators. Non-limiting examples of tuning components include heaters, electrical contacts, among other devices used to tune the resonance wavelength of optical components.

[0107] FIG. 5B illustrates an example implementation of a modulator **501** that can be included in search engine **512**. In the example of FIG. 5B, modulator **501** is provided as an illustrative example, and each modulator of the search engine **512** may be implemented in a similar manner as described herein. Modulator **501** comprises a waveguide resonator **524** coupled to a branch waveguide **526** of an interferometer **532**. In the example of FIG. 5B, branch waveguide **526** is

coupled to input routing element **504A** via a coupling component **513**. Coupling component **513** may be implemented as a 2×1 multi-mode interference (MMI) coupler in this example. Light on input routing element **504A** is first passed through coupling component **513** and couples into the waveguide resonator **524**. Based on the resonance frequency of the waveguide resonator **524**, clockwise (CW) propagating light (also referred to as transmitted light) may couple back to the branch waveguide **526**. Coupling component **513** in this example, may be 1×2 MMI coupler acting as a 50/50 splitter. Counterclockwise (CCW) propagating light (also referred to as reflected light) may reflect back toward the coupling component **513** when the transmitted light couples back into the branch waveguide **526**. The coupling component **513** acts as a splitter for the reflected light which is guided through a feedback waveguide **528** towards a coupling component **522** (e.g., a 2×2 MMI coupler in this example). The transmitted light is passed to the coupling component **515** and is split equally between a drop waveguide **534** and a coupling component **522** via waveguide **530**, where the transmitted light is recombined with the reflected light. The coupling component **522** passes the recombined light to output routing elements **507A** and **507B** connected to a detector component **520A**.

[0108] The recombined light from the coupling component **522** is the result of interference between the transmitted and reflected light and are detected by photodetectors **509A** and **509B**. Interference may be constructive or destructive depending on the phase difference between the transmitted and reflected light. To adjust this phase to obtain the desired interference, a tuning component **514B** is coupled to the feedback waveguide **528**, for example, a resistive heater element. By setting a current through the tuning component **514B**, the phase difference can be tuned for constructive or destructive interference.

[0109] The modulator **501** may be tuned through operation of driver(s) **506** (e.g., programming controller **106** of FIG. 1) to represent symbols of the QCAM stored words. For example, modulator **501** may be tuned according to a respective QCAM stored word according to the encoding scheme shown in Table 4 below.

TABLE-US-00005

TABLE 5	Encode	Stored	Encode	Stored	QCAM	Stored	Data	Bit	Data	Bit
Resonance Word Symbol	Value (d.sub.1)	Value (d.sub.2)	Wavelength	1	0	1	λ .sub.0	0	1	0
	λ .sub.0, λ .sub.1	ρ	1	1	Detuned/None					

[0110] Modulator **501** can be communicatively coupled to one or more tuning components **514** capable of changing an optical characteristic of interferometer **532**. Based on differences in the optical characteristics within the modulator **501**, light can be blocked or passed light to output routing elements **507A** and **507B** (e.g., an example implementations of output routing element **107** of FIG. 1). In various examples, the one or more tuning components **514** can comprise one or more devices configured to change the refractive index of a waveguide constituting each branch of interferometer **532** that causes a shift in the phase of light propagating thereon. For example, two resonance frequencies can be achieved due to back scattering in the interferometer **532**. For example, Eigen modes can of an optical signal input into the interferometer **532** via input routing elements **504A** be centered around Eigen frequencies $\omega = \omega_{\text{sub.0}} \pm \frac{1}{2}\gamma$, where γ represents a scattering lifetime. As a result, optical signals traveling on the waveguide **530** can have one resonance frequency and optical signals traveling on the waveguide **528** can have another resonance frequency. Thus, examples herein can independently tune each resonance frequency via tuning components **514** by causing a shift in the phase of light propagating thereon to select a desired resonance frequency (e.g., none, $\lambda_{\text{sub.0}}$, $\lambda_{\text{sub.1}}$, or both) and, thereby, encoding a desired symbol according to Table 5 above.

[0111] Returning to FIG. 5A, in performing an operation on the search words encoded in accordance with Table 4, the driver(s) **506** can be configured to encode the QCAM stored words into the search engine **512** by tuning the modulators to either allow light of an encoded wavelength to pass or to block the light of the encoded wavelength, according to the encoding scheme of Table 5. For example, each QCAM stored word, stored in QCAM word storage **508**, can be provided to

driver(s) **506** and used to encode each QCAM stored word into a respective row search engine **512**. For example, modulators of row **516** can be encoded with a first QCAM stored word, while each other row can be encoded with a respective QCAM stored word. The driver(s) **506** can be configured to encode each modulator of a given row with a symbol value of the respective QCAM stored word. Each QCAM stored word may be associated with multiple wavelengths, and the driver(s) **506** may be configured to tune the modulators to allow light of the encoded wavelengths to pass or to block light of the encoded wavelengths according to the encoding scheme of Table 5. As an illustrative example, the driver(s) **506** can be configured to tune modulator **501** (e.g., as shown in FIG. 5B) to block or pass light of an encoded wavelength according to a first symbol value of a first QCAM stored data word (e.g., $\lambda_{\text{sub.0}}$ for the case of logic “0” in this example), tune a second modulator to block or pass light of an encoded wavelength according to a second symbol of the first QCAM stored data word (e.g., $\lambda_{\text{sub.1}}$ for the case of logic “1” in this example), and so on until the final modulator can be tuned to pass or block light of an encoded wavelength according to an (L/2)th symbol of the first QCAM stored data word (e.g., $\lambda_{\text{sub.0}}$ for the case of logic “0” in this example). In the case of a “p”, a modulator can be detuned to block light of any encoded wavelength. In the case of an “X”, a modulator can be detuned to pass light of any encoded wavelength. Each QCAM stored data word can be similarly encoded to a respective row of the search engine **512**. In this example, each modulator **501** may constitute a distinct O-QCAM cell, because each modulator **501** may be implemented to represent a symbol value.

[0112] Based on the logic states indicated in Tables 4 and 5, light will pass through the modulators **501** only when a mismatch occurs between the value of the symbol of a given search word **503** and the corresponding value of the symbol of the QCAM stored words. Table 6 shows the results based on the encoded symbol value on the optical search signal and of the corresponding modulator **401**.

TABLE-US-00006 TABLE 6 Search Word QCAM Stored Match/ Symbol Word Symbol Mismatch State Throughput

0	0	Match	0	0	1	Mismatch	$\lambda_{\text{sub.0}}$	0	X	Match	0	0	p	Mismatch	$\lambda_{\text{sub.0}}$	1	0
Mismatch	$\lambda_{\text{sub.1}}$	1	1	Match	0	1	X	Match	0	1	p	Mismatch	$\lambda_{\text{sub.1}}$	X	0	Match	0
Match	0	X	p	Match	0	p	0	Mismatch	$\lambda_{\text{sub.1}}$	p	1	Mismatch	$\lambda_{\text{sub.0}}$	p	X	Match	0
Match	$\lambda_{\text{sub.0}}$	$\lambda_{\text{sub.1}}$															

[0113] Light passed by the modulators **501** can be coupled to groups of output routing elements **515A-515M**, each of which represents a group of output routing elements **507A** and **507B** (e.g., FIG. 5B). Each group of output routing elements **515A-515M** may be coupled to a subset of the modulators **501**, for example, each group of output routing element **515A-515M** may be coupled to a row of the search engine **512**. For example, group of output routing elements **515A** is coupled to each of modulators of a row **516** encoded with symbols for the first QCAM stored data word. Thus, any mismatches occurring along the row **516** (e.g., light passed by modulators **501**) can be coupled into the group of output routing elements **515A**, representing mismatches of the current search word **503** with symbols of the stored data word. Similarly, groups of output routing element **515B-515M** may receive light from respective modulators representing mismatches of a comparison on a respective row.

[0114] Detector components **520A-520M**, an example of which is shown in FIG. 5B as detector component **520A**, can be optically coupled to a result end of the group of output routing element **515A-515M** in various examples. Each detector component **520A-520M** may be configured to detect throughput from Table 6. In this example, detector component **520A-520M** may each include a set of photodetectors, illustratively shown in FIG. 5B as photodetectors **509A** and **509B**, that can be configured to sense light present on a respective output routing element. The photodetectors **509A** and **509B** can detect the presence (or absence) of light at a particular encoded wavelength, thereby detecting the mismatch and/or match for the respective symbol according to Table 6 above. That is, referring to FIG. 5B as an example, photodetectors **509A** and **509B** can be configured to sense an amplitude of light, at wavelength $\lambda_{\text{sub.1}}$ and/or $\lambda_{\text{sub.0}}$, present on output routing element **507A** and/or **507B**, thereby detecting the mismatch and/or match for the respective bit position. For

example, photodetector **509A** can be configured to sense an amplitude of light at wavelength $\lambda_{\text{sub.1}}$ present on output routing element **507A** and photodetector **509B** can be configured to sense an amplitude of light at wavelength $\lambda_{\text{sub.0}}$ present on output routing element **507B**. While the above example describes utilizing both photodetectors **509A** and **509B**, examples herein may be utilize one of photodetectors **509A** and **509B**. That is, for example, determinations according to Table 6 may be made using either photodetector **509A** or photodetector **509B** to sense an amplitude of light at wavelengths $\lambda_{\text{sub.1}}$ and $\lambda_{\text{sub.0}}$.

[0115] In some examples, each detector component comprises demultiplexers (e.g., such as shown in FIG. 4B) disposed between the search engine **512** and respective set of photodetectors, configured to filter the various wavelengths of light on to respective downstream routing elements coupled to the photodetectors.

[0116] In some examples, each detector component can output a match/mismatch indication to an encoder circuit **517** configured to generate the memory address corresponding to the QCAM stored data words of the search engine **512** for which a match indication is received from detector components. In some examples, each detector component may send the indication to a processing circuit within the optical search engine **500** being configured to identify the memory address associated with the specific QCAM stored words represented by the search engine **512** and output an electrical signal to a memory controller or other device controller access to the memory storage.

[0117] In various examples, each detector component can be configured to integrate the mismatches over time for the duration of the search words (i.e., for the duration of the 2^n time slots t , also referred to as a search cycle), enabling each detector component to determine a sum of all mismatches between a given search word and a given QCAM stored word. In some examples, the detector components can be configured to flag or otherwise identify at which bit positions a mismatch occurred.

[0118] The example of FIGS. 5A and 5B can provide for power savings and reduced energy consumption during a search. This is because, the examples described above in connection with FIGS. 5A and 5B are configured to represent a symbol using a single modulator and thus one tuning component. Whereas, other examples may rely on two modulators to represent a symbol, for example, by representing two bit positions that constitute a symbol, which requires additional tuning components and complexity.

[0119] While optical search engine **500** is described with reference to modulator **501** shown in FIG. 5B, examples herein need not be limited to this specific example. Other optical modulator or filters may be implemented that can be operated to control a resonance frequency so to achieve the encoding scheme set forth in Tables 5 and 6. For example, backcoupling manipulation in ring resonators, as known in the art, can be utilized to control resonance. These devices can be implemented as a modulator that can be tuned to represent QCAM stored words according to Table 5.

[0120] The optical search engines discussed with respect to FIGS. 1-5B can be implemented within a QCAM component of a device, increasing the speed and efficiency of the search compared to traditional bCAMs and TCAMs. FIG. 6 illustrates an example computing device **600** in accordance with examples of the technology disclosed herein. The example computing device **600** is provided for illustrative purpose and should not be interpreted as limiting the scope of the technology only to the depicted example. The example computing device **600** may include more or fewer components in various examples. When common references are used between figures, it should be interpreted that all descriptions associated with such reference is applicable to all instances of the reference unless otherwise stated.

[0121] As shown in FIG. 6, the computing device **600** can comprise a processor **603**. In various examples, the processor **603** can be one or more of a general purpose processor (GPU), an application specific integrated circuit (ASIC), a field programmable gate array (FPGA), or other computer processor device known in the art. In various examples, the processor **603** can comprise a

co-processor configured to control operation of the QCAM search functionality of the computing device **600**. In some examples, the processor **603** can be configured to send an electrical search word to optical search engine **650**. In various examples, the optical search engine **650** can be configured to implement the examples discussed above with respect to FIGS. **1-5B**. One or more applications executed by the processor **603** may request access to a portion of memory within the same network as the computing device **600** by submitting a search word electronically of the electrical search input line **601**. The optical search engine **650** can encode the search word on the optical search signals, as discussed with respect to FIGS. **1-5B**. In various examples, the search word may be submitted to the optical search engine **650** optically over the optical search input **602** from an optical source **604**.

[0122] In various examples, the optical source **604** may comprise an output from an optical transceiver (not shown in FIG. **6**) of the computing device **600**. The optical transceiver may be configured to receive an optical signal encoded with the search word from one or more other devices connected to the computing device **600**. In some examples, the optical source **604** can comprise an optical fiber or other optical transmission medium within the computing device **600** and connected to one or more other components within the computing device and/or to the interior output of a faceplate connector. The optically-received search word over the optical search input **602** can be multiplexed into the plurality of optical search signals like that discussed with respect to FIGS. **1-5B**.

[0123] In various examples, the processor **603** can be communicatively coupled to the programming controller **606**. As discussed with respect to FIGS. **1-5B**, the programming controller **606** can be configured to program the plurality of modulators within the optical search engine **650** such that the state of each modulator is driven in accordance with the encoding scheme discussed with respect to Tables 2 and 5. In various examples, the processor **603** may send a word to be stored to the programming controller **606**, which can then determine how the electrical drive signal should be encoded. In some examples, the processor **603** and the programming controller **606** may be the same component. In some examples, the programming controller **606** can be configured to receive instructions for operation of the modulators of the optical search engine **650** for each word.

[0124] After performing the search, one or more output signals **607** may be output by the optical search engine **650**. In various examples, the output signals **607** can comprise one or more memory addresses in a memory component within the network and accessible by the computing device **600**, whether directly or indirectly (i.e., through another device within the network), corresponding to one or more stored words represented by the plurality of modulators of the optical search engine **650** that were determined to match the search word. The output signal **607** can be sent to either a converter **670**, a laser **660**, or a combination of both. If the memory address corresponding to the matched QCAM stored word(s) is to be sent to an electronic component (e.g., a memory controller directly connected to the computing device **600**) to gain access to the content at the requested memory address(es), the output signal **607** can be sent to the converter **670**, which is configured to convert the output signal into an electrical signal comprising the memory address(es). In various examples, the converter **670** may comprise an analog-to-digital converter (ADC). If the output signal **607** is to be sent optically to another entity (e.g., another computing device over an optical interconnect), the output signal **607** can be sent to a laser **660** configured to convert the output into an optical signal to be transmitted to another entity, such as a memory controller or another device.

[0125] The optical search engines discussed with respect to FIGS. **1-5B** can be implemented within a O-QCAM component of a device (such as computing device **600**) to execute various functions, increasing the speed and efficiency of the execution compared to traditional bCAMs and TCAMs with a reduced physical footprint.

[0126] FIG. **7** depicts a schematic representation of an example function-Boolean constrain propagation—that can be executed in accordance with examples of the present disclosure. FIG. **7** includes search words **710** that may be supplied to a search engine programmed with QCAM stored

words shown in matrix **720**. In examples, the QCAM stored words represented as matrix **720** may be programmed into modulators of any of the search engines described in connection with FIGS. **1-5B**, for example, by tuning the tuning components coupled to modulators that make up a particular search engine according to Tables 2 and/or Table 5. The search engine can output results **730** via output routing elements that can be decoded, using Tables 3 and/or Table 6, and used provide a solution to the Boolean constrain propagation. The example of FIG. **7** is provided for illustrative purposes only and should not be interpreted as limiting the scope of the disclosed technology to only the depicted example.

[0127] Boolean constraint propagation is a common way to address the solution of Boolean constraints of a particular clause. For example, the QCAM stored words **730** of FIG. **7** may represent the function provided in conjunctive normal form:

$$[00002] f = (x_1 \vee x_2 \vee \neg x_4) \wedge (\neg x_1 \vee x_3 \vee x_4) \wedge (x_2 \vee \neg x_3 \vee x_4) \quad \text{Eq. 1}$$

[0128] Eq. 1 represents a Boolean function where an optical search engine seeks to find values for x.sub.1, x.sub.2, x.sub.3, and x.sub.4 that solve the problem. To solve the problem, f may be set equal to one and in each parenthetical that are clauses. In the example of Eq. 1, there are three clauses, each having inclusive operations or negated operations. For example, in the first clause (e.g., (x.sub.1 $\vee$ x.sub.2 $\vee$ $\neg$ x.sub.4)), x.sub.1 and x.sub.2 are inclusive and x.sub.4 is negated. The first clause can be mapped to a row of matrix **720** (e.g., row **722**), which may be used as a first QCAM stored word. For example, in the case of search engines **312**, **412**, and **512** the first clause may be used to program the first row. In the case of search engine **212**, the first clause may be used to program the first column as a function of time. In this example, a non-negated item (e.g., x.sub.1 and x.sub.2) are represented as a stored data symbol value of logic “0”, negated items (e.g., x.sub.4) are represented as a stored data symbol value of logic “1”, and if the item is not present in the clause (e.g., x.sub.3) the item is represented as a wildcard “X”. The subsequence clauses can be used to program other rows. The O-QCAM can be programmed according to Table 2 or Table 5, depending on the implementation.

[0129] To perform the Boolean constraint propagation, the search engine receives search words **710** and searches the O-QCAM for a violation (e.g., match) of with the QCAM stored word. Each search word can be encoded by an input encoder (e.g., input encoders **102**, **202**, **302**, **402**, and/or **502**) according to Tables 1 and/or 4. At a first time step (t1), a first search word **712** is used by an input encoder to generate a first encoded search signal having a logic “0” in a first position and a reject symbol “p” in all other positions. The results **730** for the first time step (t1) outputs mismatches on all match lines (ML) (e.g., output from output routing elements). Thus, the output is all logic “0”, which means that none of the clauses is violated.

[0130] At each subsequent time step, one of the reject symbols can be replaced with a value symbol of logic “0” or “1”. In the example of FIG. **7**, the second search word **714** at the second time step (t2) replaces a reject symbol for x.sub.4 with a logic “0”. Other examples may replace different positions and/or may use logic “1” instead of logic “0”. The second search word **714** is applied to the search engine programmed with matrix **720** to output a corresponding result. In this case, again the result **730** for the second time step represents no violations. This process repeats is repeated until a violation (e.g., a match **732**) is located, for example, at the fourth time step (t4) in this example. This means a match (e.g., violation) was located using the fourth search word **716**, which means the problem is solved.

[0131] In the case of Boolean constraint propagation, the examples herein can be used to locate the change to where a match is located in between at least on clause and a search word. Thus, the reject symbol “p” can be beneficial to represent variables that are have not yet been assigned, for example, in the search words **710**, and the wildcard symbol “X” can be used for absent for otherwise not involved variables.

[0132] As another example, the optical search engines discussed with respect to FIGS. **1-5B** can be

implemented for any arbitrary Boolean function (F). For example, a search engine in accordance with the above examples can be provided having a number of n O-QCAM cells for implementing an arbitrary Boolean function (F), where the input space contains 2^n elements. In the case of a Boolean function (F) over n Boolean variables the number of cells n can be determined as $2^{\sup(n-1)}$. Thus, in examples, the input space of the Boolean function (F) can be provided as $[0:2^n-1]$, such that the function has an interval of integers between 0 and 2^n-1 . In examples, intervals of the input space can be supplied to an input encoder (e.g., input encoders **102**, **202**, **302**, **402**, and/or **502**) to encode search words according to Tables 1 and/or 4 and the N O-QCAM cells of the search engine can be driven by driver(s) (e.g., programming controller **106** and/or driver(s) **206**, **306**, **406**, and/or **506**) according to Tables 2 and/or 5. The solution to the Boolean function (F) can be output by the search engine and decoded according to Tables 3 and/or 6.

[0133] As an illustrative example, FIG. 8 depicts an example Boolean function **810**, which is shown as a function of variable y. Boolean function **810** corresponds to an input space of $[0:7]$ and can be implemented in N=4 O-QCAM cells. In this example, Boolean function **810** can be implemented as a row of a search engine. For example, Boolean function **810** can be implemented as four cells in the case of search engines **212**, **312**, and/or **512** or as one cell in the case of optical search engine **412**. Table 7 below provides an example of encoded states that can be programmed into example search engines according to Table 2 and/or Table 5 described above.

TABLE-US-00007 TABLE 7 cell.sub.0 = 0 cell.sub.1 = X cell.sub.2 = 1 cell.sub.3 = p

[0134] Table 8 below provides the example input space where each input integer value represents a search word that can be encoded by an input encoder, according to Tables 1 and/or 4, to generate encoded search signals (e.g., the input encoder may operate to map the encoded inputs symbol values as search words by modulating an input optical signal from an optical source).

TABLE-US-00008 TABLE 8 Input Encoded Input integer value col.sub.0 col.sub.1 col.sub.2 col.sub.3 0 0 X X X 1 1 X X X 2 X 0 X X 3 X 1 X X 4 X X 0 X 5 X X 1 X 6 X X X 0 7 X X X 1

[0135] Accordingly, as can be seen from the above, the number of cells for implementing the example Boolean function **810** is significantly less than compared to conventional approaches using bCAM and TCAMs. That is, for example, arbitrary Boolean functions performed with bCAM or TCAMs may be limited to n cells, while with O-QCAMs 2^n cells can be supported (e.g., a factor of 2). The Boolean function **810** is provided for illustrative purposes only and should not be interpreted as limiting the scope of the disclosed technology to only the depicted example. Other, increasingly more complex or multiple Boolean functions may be implemented in the examples disclosed herein. Thus, the benefits demonstrated by the above example may be increasingly impactful as the complexity of the Boolean function(s) implemented increases.

[0136] As another example, the optical search engines discussed with respect to FIGS. 1-5B can be implemented for equality check. For example, a search engine in accordance with the above examples can be provided having a number of n O-QCAM cells that can be implemented to execute an equality check over

[00003][$0:(\frac{2^n}{n}) - 1$]

intervals of input space. Whereas, bCAM and TCAM based search engines may be able to execute an equality check over 2^n intervals of input space.

[0137] As an illustrative example, in the search engines discussed with respect to FIGS. 1-5B, three O-QCAM cells (e.g., n=3) can be implemented to perform an equality check over 20 intervals, whereas bCAM and TCAM may only be able to check 8 intervals. Table 9 below provides an example of an equality check over 20 intervals, (e.g., rows $[0:19]$). The encoded search symbols values of the interval input space can be shown in Table 9 can be supplied to an input encoder (e.g., input encoders **102**, **202**, **302**, **402**, and/or **502**) to encode search words according to Tables 1 and/or 4. The encoded QCAM data symbol values can be programmed into three O-QCAM cells by driver(s) (e.g., programming controller **106** and/or driver(s) **206**, **306**, **406**, and/or **506**)

according to Tables 2 and/or 5. As shown in Table 9, the number of wildcard symbols “X” is equal to the number of a reject symbols “p” in each row. This is because, in the examples disclosed herein, the reject symbol “p” can be used to search a wildcard symbol “X” in the input encoding and the wildcard symbol “X” can be used to search a reject symbol “p”.

TABLE-US-00009 TABLE 9 Encoded Search Symbol Encoded QCAM Data Value Symbol Value

Column 3	Column 2	Column 1	Cell 3	Cell 2	Cell 1	0	0	0	0	0	0	1	0	0	1	0	1	2	0	1	0	0	1	0	3	0	1	1	0																																	
1	1	4	1	0	0	1	0	0	5	1	0	1	1	0	1	6	1	1	0	1	1	0	7	1	1	1	1	1	8	0	X	p	0	p	X	9	0	p	X	0	X	p	10	X	0	p	0	X														
11	X	p	0	p	X	0	12	p	0	X	X	0	p	13	p	X	0	X	p	0	14	1	X	p	1	p	X	15	1	p	X	1	X	p	16	X	1	p	p	1	X	17	X	p	1	p	X	1	18	p	1	X	X	1	p	19	p	X	1	X	p	1

[0138] The requests of the example equality check are shown in Table 10 below, which can be output by the search engine and decoded according to Tables 3 and/or 6. Each search symbol value of Table 9 is compared to each QCAM data symbol value of Table 9 to provide the below results. In the below example, each True “T” represents a match result, for example, no light on an output routing element of the search engine and each False “F” represents a mismatch. For example, the results of the equality check of the search symbol value for interval 8 (e.g., row 9) in Table 9 compared to the QCAM data symbol value of interval 8 is True “T” (e.g., $s.sub.8.Math.d.sub.8=[0,1,0,0,1,1].Math.[1,0,1,1,0,0]=0$, based on the encoding scheme of Tables 1 and 2 and/or Tables 4 and 5), which can be represented as no light output by the search engines described in the connection with FIGS. 1-5B. Whereas, the results of the equality check of the search symbol value for interval 8 (e.g., row 9) in Table 9 compared to the QCAM data symbol value of interval 10 is False “F” (e.g., $s.sub.8.Math.d.sub.10=[0,1,0,0,1,1].Math.[1,1,1,0,0,0]=1$, based on the encoding scheme of Tables 1 and 2 and/or Tables 4 and 5), which can be represented as light output by the search engines described in the connection with FIGS. 1-5B.

TABLE-US-00010 TABLE 10 QCAM Symbol Value

0	1	2	3	4	5	6	7	8	9	10	11	12	13	14	15	16	17	18	19	Search
0	T	F	F	F	F	F	F	F	F	F	F	F	F	F	F	F	F	F	F	Symbol
1	F	T	F	F	F	F	F	F	F	F	F	F	F	F	F	F	F	F	F	Value
2	F	F	T	F	F	F	F	F	F	F	F	F	F	F	F	F	F	F	F	3
3	F	F	F	T	F	F	F	F	F	F	F	F	F	F	F	F	F	F	F	4
4	F	F	F	F	T	F	F	F	F	F	F	F	F	F	F	F	F	F	F	5
5	F	F	F	F	F	T	F	F	F	F	F	F	F	F	F	F	F	F	F	6
6	F	F	F	F	F	F	F	F	F	F	F	F	F	F	F	F	F	F	F	7
7	F	F	F	F	F	F	F	F	F	F	F	F	F	F	F	F	F	F	F	8
8	F	F	F	F	F	F	F	F	F	F	F	F	F	F	F	F	F	F	F	9
9	F	F	F	F	F	F	F	F	F	F	F	F	F	F	F	F	F	F	F	10
10	F	F	F	F	F	F	F	F	F	F	F	F	F	F	F	F	F	F	F	11
11	F	F	F	F	F	F	F	F	F	F	F	F	F	F	F	F	F	F	F	12
12	F	F	F	F	F	F	F	F	F	F	F	F	F	F	F	F	F	F	F	13
13	F	F	F	F	F	F	F	F	F	F	F	F	F	F	F	F	F	F	F	14
14	F	F	F	F	F	F	F	F	F	F	F	F	F	F	F	F	F	F	F	15
15	F	F	F	F	F	F	F	F	F	F	F	F	F	F	F	F	F	F	F	16
16	F	F	F	F	F	F	F	F	F	F	F	F	F	F	F	F	F	F	F	17
17	F	F	F	F	F	F	F	F	F	F	F	F	F	F	F	F	F	F	F	18
18	F	F	F	F	F	F	F	F	F	F	F	F	F	F	F	F	F	F	F	19
19	F	F	F	F	F	F	F	F	F	F	F	F	F	F	F	F	F	F	F	T

[0139] FIG. 9 illustrates a computing component that may be used to implement the optical search engines in accordance with various examples of the disclosed technology. Referring now to FIG. 9, computing component 900 may be, for example, a server computer, a controller, or any other similar computing component capable of processing data. In the example implementation of FIG. 9, the computing component 900 includes a hardware processor 902, and machine-readable storage medium 904.

[0140] Hardware processor 902 may be one or more central processing units (CPUs), semiconductor-based microprocessors, and/or other hardware devices suitable for retrieval and execution of instructions stored in machine-readable storage medium 904. Hardware processor 902 may fetch, decode, and execute instructions, such as instructions 906-916, to control processes or operations optical search engines described in accordance with the examples in FIGS. 1-5B. As an alternative or in addition to retrieving and executing instructions, hardware processor 902 may include one or more electronic circuits that include electronic components for performing the functionality of one or more instructions, such as a field programmable gate array (FPGA), application specific integrated circuit (ASIC), or other electronic circuits.

[0141] A machine-readable storage medium, such as machine-readable storage medium 904, may be any electronic, magnetic, optical, or other physical storage device that contains or stores

executable instructions. Thus, machine-readable storage medium **904** may be, for example, Random Access Memory (RAM), non-volatile RAM (NVRAM), an Electrically Erasable Programmable Read-Only Memory (EEPROM), a storage device, an optical disc, and the like. In some examples, machine-readable storage medium **904** may be a non-transitory storage medium, where the term “non-transitory” does not encompass transitory propagating signals. As described in detail below, machine-readable storage medium **904** may be encoded with executable instructions, for example, instructions **906-916**.

[0142] Hardware processor **902** may execute instruction **906** to receive one or more search words. For example, one or more search words can be received by an input encoder (e.g., one of input encoders **102**, **202**, **302**, **402**, and/or **502** of FIGS. **1**, **2A**, **3A**, **4A**, and **5A**).

[0143] Hardware processor **902** may execute instruction **908** to encode a multi-wavelength input signal with the one or more search words to generate one or more encoded search signals. For example, the input encoder may encode multi-wavelength input signals with the one or more search words to generate encoded search signals, such as, for example, encoded search signals **110**, **210A-210K**, **310A-310M**, **410A-410M**, and/or **510A-510M** as described in connection with FIGS. **1**, **2A**, **3A**, **4A**, and **5A**. In examples, each bit position of a search word of the one or more search words can be encoded as an amplitude, a wavelength, or a combination of both.

[0144] Hardware processor **902** may execute instruction **910** to store a plurality of O-QCAM entries into a plurality of O-QCAM cells of an optical search engine. In examples, at least one of the plurality of O-QCAM cells stores a reject value (e.g., a “p”). In examples, a program controller (e.g., program controller **106** of FIG. **1**) and/or driver(s) (e.g., driver(s) **206**, **306**, **406**, and/or **506**) can receive, from a word storage (e.g., QCAM word storage **108**, **308** and/or **408**) at least one word to be stored as an O-QCAM entry of the plurality of O-QCAM entries. The at least one word, in examples, can comprise a plurality of bits. The program controller/driver(s) can be operated to store a bit value for each bit of the plurality of bits within an O-QCAM cell of the plurality of O-QCAM cells of the O-QCAM entry.

[0145] The plurality of O-QCAM cells may constitute the optical search engine (e.g., search engine **100**, **200**, **300**, **400**, and/or **500**). Each O-QCAM cell may be implemented as one or more modulators (e.g., modulators **101**, **201**, **301**, **401**, and/or **501**) that can be implemented to store a symbol value, such as logic ‘0’, logic ‘1’, a wildcard symbol ‘X’, or a reject value ‘p’. In examples, the program controller/driver(s) can be operated to tune modulators of an optical search engine to represent bits of each QCAM word, for example, as described above in connection with FIGS. **1-5B**. In examples, each bit position of an O-QCAM entry can be encoded as an amplitude, a wavelength, or a combination of both.

[0146] For example, an O-QCAM cell, in some examples, may be configured to represent a reject value when a first modulator is tuned (e.g., by the program controller/driver(s)) to pass light of a first wavelength of a bit position-specific set of wavelengths and a second modulator is tuned to pass light of a second wavelength of the bit position-specific set of wavelengths. The O-QCAM cell may be configured to represent a logic ‘0’, for example, when the first modulator is tuned to pass light of the first wavelength of the bit position-specific set of wavelengths and the second modulator is tuned to block light of the second wavelength of the bit position-specific set of wavelengths. The O-QCAM cell may be configured to represent a logic ‘1’, for example, when the first modulator is tuned to block light of the first wavelength of the bit position-specific set of wavelengths and the second modulator is tuned to pass light of the second wavelength of the bit position-specific set of wavelengths. The O-QCAM cell can be configured to represent a wildcard value, for example, when the first modulator is tuned to block light of the first wavelength of the bit position-specific set of wavelengths and the second modulator is tuned to block light of the second wavelength of the bit position-specific set of wavelengths.

[0147] In another example, each O-QCAM cell may comprise a first modulator. In this example, the O-QCAM cell can be configured to represent a reject value when the first modulator is tuned to

pass light of a first wavelength during a first time slot and during a second time slot. The O-QCAM cell, in this example, can be configured to represent a logic '0' when the first modulator is tuned to pass light of the first wavelength during a first time slot and the first modulator is tuned to block light of the first wavelength during a second time slot. The O-QCAM cell, in this example, can be configured represents a logic '1' when the first modulator is tuned to block light of the first wavelength during a first time slot and the first modulator is tuned to block light of the first wavelength during a second time slot. The O-QCAM cell, in this example, can be configured to represent a wildcard value when the first modulator is tuned to block light of the first wavelength during a first time slot and during a second time slot.

[0148] Hardware processor **902** may execute instruction **912** to input the one or more encoded search signals to an input waveguide of each of the plurality O-QCAM entries of the optical search engine. For example, the input encoder may couple the encoded search signals to input waveguides, such as input waveguides **104**, **204A-204K**, **304A-304M**, **404A-404M**, and/or **504A-504M**, that couple the encoded search signals to the optical search engine, as described above in connection with FIGS. **1-5B**.

[0149] Hardware processor **902** may execute instruction **914** to sense, by a plurality of photodetectors, a resultant output signal on an output routing waveguide of a plurality of output routing waveguides of the optical search engine. Each output routing waveguide can be associated with at least one O-QCAM entry of the optical search engine. For example, photodetectors (e.g., photodetectors **109**, **209A-A** through **209M-K**, **309A-309M**, **409A-409K**, and/or **509A-509B**) can detect resultant output signals from the optical search engine and provide an indication of a match or mismatch based on the resultant output signal, as described above in connection with FIGS. **1-5B**.

[0150] Hardware processor **902** may execute instruction **916**, based on detecting light on an output waveguide associated with the O-QCAM cell storing the reject value, indicating, by the respective photodetector, a mismatch between the encoded search signals received from the input encoder and the stored reject value.

[0151] In examples, the optical search engine can be programmed to execute one or more functions. For example, the optical search engine can be programmed to execute Boolean constrain propagation, as described above in connection with FIG. **7**. In this example, a conjunctive normal form of a function comprises a plurality of clauses and each clause can be mapped to a QCAM word entry of the plurality of QCAM word entries. In another example, the optical search engine can be programmed to execute a Boolean function comprising $2n-1$ input integers mapped to the plurality of QCAM word entries, for example, as described above in connection with FIG. **8**. In another example, the optical search engine can be programmed to execute an equality check comprising

$$[00004][0:(\binom{2n}{n} - 1)]$$

input entries mapped to the plurality of QCAM word entries. In the above examples, n may represent the number of O-QCAM cells in the plurality of O-QCAM cells.

[0152] FIG. **10** depicts a block diagram of an example computer system **1000** in which various examples of the disclosed technology described herein may be implemented. The computer system **1000** includes a bus **1002** or other communication mechanism for communicating information, one or more hardware processors **1004** coupled with bus **1002** for processing information. Hardware processor(s) **1004** may be, for example, one or more general purpose microprocessors. The computer system **1000** may be implemented as one or more component of the optical search engines described in connection with FIGS. **1-5B**, for example, input encoders, programming controller or driver(s), QCAM word storage, etc.

[0153] The computer system **1000** also includes a main memory **1006**, such as a random access memory (RAM), cache and/or other dynamic storage devices, coupled to bus **1002** for storing

information and instructions to be executed by processor **1004**. Main memory **1006** also may be used for storing temporary variables or other intermediate information during execution of instructions to be executed by processor **1004**. Such instructions, when stored in storage media accessible to processor **1004**, render computer system **1000** into a special-purpose machine that is customized to perform the operations specified in the instructions. For example, main memory **1006** may store instructions, that when executed by processor(s) **1004**, cause computer system **1000** to perform one or more of the operations described in connection with FIG. 9.

[0154] The computer system **1000** further includes a read only memory (ROM) **1008** or other static storage device coupled to bus **1002** for storing static information and instructions for processor **1004**. A storage device **1010**, such as a magnetic disk, optical disk, or USB thumb drive (Flash drive), etc., is provided and coupled to bus **1002** for storing information and instructions.

[0155] The computer system **1000** may be coupled via bus **1002** to a display **1012**, such as a liquid crystal display (LCD) (or touch screen), for displaying information to a computer user. An input device **1014**, including alphanumeric and other keys, is coupled to bus **1002** for communicating information and command selections to processor **1004**. Another type of user input device is cursor control **1016**, such as a mouse, a trackball, or cursor direction keys for communicating direction information and command selections to processor **1004** and for controlling cursor movement on display **1012**. In some examples, the same direction information and command selections as cursor control may be implemented via receiving touches on a touch screen without a cursor.

[0156] The computing system **1000** may include a user interface module to implement a GUI that may be stored in a mass storage device as executable software codes that are executed by the computing device(s). This and other modules may include, by way of example, components, such as software components, object-oriented software components, class components and task components, processes, functions, attributes, procedures, subroutines, segments of program code, driver(s), firmware, microcode, circuitry, data, databases, data structures, tables, arrays, and variables.

[0157] In general, the word “component,” “engine,” “system,” “database,” “data store,” and the like, as used herein, can refer to logic embodied in hardware or firmware, or to a collection of software instructions, possibly having entry and exit points, written in a programming language, such as, for example, Java, C or C++. A software component may be compiled and linked into an executable program, installed in a dynamic link library, or may be written in an interpreted programming language such as, for example, BASIC, Perl, or Python. It will be appreciated that software components may be callable from other components or from themselves, and/or may be invoked in response to detected events or interrupts. Software components configured for execution on computing devices may be provided on a computer readable medium, such as a compact disc, digital video disc, flash drive, magnetic disc, or any other tangible medium, or as a digital download (and may be originally stored in a compressed or installable format that requires installation, decompression or decryption prior to execution). Such software code may be stored, partially or fully, on a memory device of the executing computing device, for execution by the computing device. Software instructions may be embedded in firmware, such as an EPROM. It will be further appreciated that hardware components may be comprised of connected logic units, such as gates and flip-flops, and/or may be comprised of programmable units, such as programmable gate arrays or processors.

[0158] The computer system **1000** may implement the techniques described herein using customized hard-wired logic, one or more ASICs or FPGAs, firmware and/or program logic which in combination with the computer system causes or programs computer system **1000** to be a special-purpose machine. According to one example of the disclosed technology, the techniques herein are performed by computer system **1000** in response to processor(s) **1004** executing one or more sequences of one or more instructions contained in main memory **1006**. Such instructions may be read into main memory **1006** from another storage medium, such as storage device **1010**.

Execution of the sequences of instructions contained in main memory **1006** causes processor(s) **1004** to perform the process steps described herein. In alternative examples, hard-wired circuitry may be used in place of or in combination with software instructions.

[0159] The term “non-transitory media,” and similar terms, as used herein refers to any media that store data and/or instructions that cause a machine to operate in a specific fashion. Such non-transitory media may comprise non-volatile media and/or volatile media. Non-volatile media includes, for example, optical or magnetic disks, such as storage device **1010**. Volatile media includes dynamic memory, such as main memory **1006**. Common forms of non-transitory media include, for example, a floppy disk, a flexible disk, hard disk, solid state drive, magnetic tape, or any other magnetic data storage medium, a CD-ROM, any other optical data storage medium, any physical medium with patterns of holes, a RAM, a PROM, and EPROM, a FLASH-EPROM, NVRAM, any other memory chip or cartridge, and networked versions of the same.

[0160] Non-transitory media is distinct from but may be used in conjunction with transmission media. Transmission media participates in transferring information between non-transitory media. For example, transmission media includes coaxial cables, copper wire and fiber optics, including the wires that comprise bus **1002**. Transmission media can also take the form of acoustic or light waves, such as those generated during radio-wave and infra-red data communications.

[0161] The computer system **1000** also includes a network interface **1018** (also referred to as a communication interface) coupled to bus **1002**. Network interface **1018** provides a two-way data communication coupling to one or more network links that are connected to one or more local networks. For example, network interface **1018** may be an integrated services digital network (ISDN) card, cable modem, satellite modem, or a modem to provide a data communication connection to a corresponding type of telephone line. As another example, network interface **1018** may be a local area network (LAN) card to provide a data communication connection to a compatible LAN (or WAN component to communicated with a WAN). Wireless links may also be implemented. In any such implementation, network interface **1018** sends and receives electrical, electromagnetic or optical signals that carry digital data streams representing various types of information.

[0162] A network link typically provides data communication through one or more networks to other data devices. For example, a network link may provide a connection through local network to a host computer or to data equipment operated by an Internet Service Provider (ISP). The ISP in turn provides data communication services through the world wide packet data communication network now commonly referred to as the “Internet.” Local network and Internet both use electrical, electromagnetic or optical signals that carry digital data streams. The signals through the various networks and the signals on network link and through network interface **1018**, which carry the digital data to and from computer system **1000**, are example forms of transmission media.

[0163] The computer system **1000** can send messages and receive data, including program code, through the network(s), network link and network interface **1018**. In the Internet example, a server might transmit a requested code for an application program through the Internet, the ISP, the local network and the network interface **1018**.

[0164] The received code may be executed by processor **1004** as it is received, and/or stored in storage device **1010**, or other non-volatile storage for later execution.

[0165] Each of the processes, methods, and algorithms described in the preceding sections may be embodied in, and fully or partially automated by, code components executed by one or more computer systems or computer processors comprising computer hardware. The one or more computer systems or computer processors may also operate to support performance of the relevant operations in a “cloud computing” environment or as a “software as a service” (SaaS). The processes and algorithms may be implemented partially or wholly in application-specific circuitry. The various features and processes described above may be used independently of one another, or may be combined in various ways. Different combinations and sub-combinations are intended to

fall within the scope of this disclosure, and certain method or process blocks may be omitted in some implementations. The methods and processes described herein are also not limited to any particular sequence, and the blocks or states relating thereto can be performed in other sequences that are appropriate, or may be performed in parallel, or in some other manner. Blocks or states may be added to or removed from the disclosed examples. The performance of certain of the operations or processes may be distributed among computer systems or computers processors, not only residing within a single machine, but deployed across a number of machines.

[0166] As used herein, a circuit might be implemented utilizing any form of hardware, software, or a combination thereof. For example, one or more processors, controllers, ASICs, PLAS, PALs, CPLDs, FPGAs, logical components, software routines or other mechanisms might be implemented to make up a circuit. In implementation, the various circuits described herein might be implemented as discrete circuits or the functions and features described can be shared in part or in total among one or more circuits. Even though various features or elements of functionality may be individually described or claimed as separate circuits, these features and functionality can be shared among one or more common circuits, and such description shall not require or imply that separate circuits are required to implement such features or functionality. Where a circuit is implemented in whole or in part using software, such software can be implemented to operate with a computing or processing system capable of carrying out the functionality described with respect thereto, such as computer system **1000**.

[0167] As used herein, the term “or” may be construed in either an inclusive or exclusive sense. Moreover, the description of resources, operations, or structures in the singular shall not be read to exclude the plural. Conditional language, such as, among others, “can,” “could,” “might,” or “may,” unless specifically stated otherwise, or otherwise understood within the context as used, is generally intended to convey that certain examples include, while other examples do not include, certain features, elements and/or steps.

[0168] Terms and phrases used in this document, and variations thereof, unless otherwise expressly stated, should be construed as open ended as opposed to limiting. Adjectives such as “conventional,” “traditional,” “normal,” “standard,” “known,” and terms of similar meaning should not be construed as limiting the item described to a given time period or to an item available as of a given time, but instead should be read to encompass conventional, traditional, normal, or standard technologies that may be available or known now or at any time in the future. The presence of broadening words and phrases such as “one or more,” “at least,” “but not limited to” or other like phrases in some instances shall not be read to mean that the narrower case is intended or required in instances where such broadening phrases may be absent.

Claims

1. An optical quaternary content addressable memory (O-QCAM) comprising: a search input configured to convert a multi-wavelength input signal encoded with a search word into a plurality of search optical signals; a plurality of QCAM word entries, each QCAM word entry comprising a plurality of O-QCAM cells; and a plurality of photodetectors, each photodetector optically coupled to a results end of a respective output match waveguide of an QCAM word entry, wherein each O-QCAM cell is configured to store a reject value and one or more of: a logic ‘0’; a logic ‘1’; and a wildcard value.
2. The O-QCAM of claim 1, wherein each photodetector is configured to detect a mismatch between a respective search optical signal and a respective O-QCAM entry by detecting light of at least one wavelength of the multi-wavelength input signal.
3. The O-QCAM of claim 2, wherein, when the respective O-QCAM entry stores the reject value, each photodetector detects the mismatch between the respective search optical signal and the respective O-QCAM entry for any value of the respective search optical signal other than a

wildcard value.

4. The O-QCAM of claim 1, wherein each QCAM word entry comprises: an input waveguide configured to optically couple to one of a plurality of search optical signals; and an output match waveguide.
5. The O-QCAM of claim 4, wherein each O-QCAM cell comprises one or more modulators disposed between the input waveguide and the output match waveguide.
6. The optical O-QCAM of claim 1, wherein each O-QCAM cell comprises a set of modulators comprising a first modulator and a second modulator.
7. The optical O-QCAM of claim 6, wherein: an O-QCAM cell represents a reject value when the first modulator is tuned to pass light of a first wavelength of a bit position-specific set of wavelengths and the second modulator is tuned to pass light of a second wavelength of the bit position-specific set of wavelengths; an O-QCAM cell represents a logic '0' when the first modulator is tuned to pass light of the first wavelength of the bit position-specific set of wavelengths and the second modulator is tuned to block light of the second wavelength of the bit position-specific set of wavelengths; an O-QCAM cell represents a logic '1' when the first modulator is tuned to block light of the first wavelength of the bit position-specific set of wavelengths and the second modulator is tuned to pass light of the second wavelength of the bit position-specific set of wavelengths; and an O-QCAM cell represents a wildcard value when the first modulator is tuned to block light of the first wavelength of the bit position-specific set of wavelengths and the second modulator is tuned to block light of the second wavelength of the bit position-specific set of wavelengths.
8. The optical O-QCAM of claim 1, wherein each O-QCAM cell comprises a first modulator, wherein: an O-QCAM cell represents a reject value when the first modulator is tuned to pass light of a first wavelength during a first time slot and during a second time slot; an O-QCAM cell represents a logic '0' when the first modulator is tuned to pass light of the first wavelength during a first time slot and the first modulator is tuned to block light of the first wavelength during a second time slot; an O-QCAM cell represents a logic '1' when the first modulator is tuned to block light of the first wavelength during a first time slot and the first modulator is tuned to block light of the first wavelength during a second time slot; and an O-QCAM cell represents a wildcard value when the first modulator is tuned to block light of the first wavelength during a first time slot and during a second time slot.
9. The optical O-QCAM of claim 1, wherein O-QCAM is configured to execute Boolean constrain propagation, wherein a conjunctive normal form of a function comprises a plurality of clauses, wherein each clause is mapped to a QCAM word entry of the plurality of QCAM word entries.
10. The optical O-QCAM of claim 1, wherein the O-QCAM is configured to execute a Boolean function comprising $2n-1$ input integers mapped to the plurality of search optical signals, wherein n is a number of O-QCAM cells in the plurality of O-QCAM cells.
11. The optical O-QCAM of claim 1, wherein the O-QCAM is configured to execute an equality check comprising $[0; \binom{2n}{n} - 1]$ input entries mapped to the plurality of search optical signals, wherein n is the number of O-QCAM cells in the plurality of O-QCAM cells.
12. A method, comprising: receiving, by an input encoder, one or more search words; encoding, by the input encoder, a multi-wavelength input signal with the one or more search words to generate one or more encoded search signals; storing, by a programming controller, a plurality of optical quaternary content addressable memory (O-QCAM) entries into a plurality of O-QCAM cells of an optical search engine, wherein at least one of the plurality of O-QCAM cells stores a reject value; inputting, by the input encoder, the one or more encoded search signals to an input waveguide of each of the plurality O-QCAM entries of the optical search engine; sensing, by a plurality of photodetectors, a resultant output signal on an output routing waveguide of a plurality of output routing waveguides of the optical search engine, each output routing waveguide associated with at

least one O-QCAM entry of the optical search engine; and based on detecting light on an output waveguide associated with the O-QCAM cell storing the reject value, indicating, by the respective photodetector, a mismatch between the encoded search signal received from the input encoder and the stored reject value.

13. The method of claim 12, wherein each bit position of an O-QCAM entry and each bit position of a search word of the one or more search words are encoded as an amplitude, a wavelength, or a combination of both.

14. The method of claim 12, further comprising: receiving, by the programming controller, at least one word to be stored in a O-QCAM entry of the plurality of O-QCAM entries, the at least one word comprising a plurality of bits; and storing, by the programming controller, a bit value for each bit of the plurality of bits within a O-QCAM cell of the plurality of O-QCAM cells of the O-QCAM entry.

15. The method of claim 14, wherein each O-QCAM cell comprises a set of optical modulators, wherein: an O-QCAM cell represents a reject value when a first optical modulator of the set of optical modulators is tuned to pass light of a first wavelength of a bit position-specific set of wavelengths and a second modulator is tuned to pass light of a second wavelength of the bit position-specific set of wavelengths; an O-QCAM cell represents a logic '0' when the first modulator is tuned to pass light of the first wavelength of the bit position-specific set of wavelengths and the second modulator is tuned to block light of the second wavelength of the bit position-specific set of wavelengths; an O-QCAM cell represents a logic '1' when the first modulator is tuned to block light of the first wavelength of the bit position-specific set of wavelengths and the second modulator is tuned to pass light of the second wavelength of the bit position-specific set of wavelengths; and an O-QCAM cell represents a wildcard value when the first modulator is tuned to block light of the first wavelength of the bit position-specific set of wavelengths and the second modulator is tuned to block light of the second wavelength of the bit position-specific set of wavelengths.

16. The method of claim 14, wherein each O-QCAM cell comprises a first modulator, wherein: an O-QCAM cell represents a reject value when the first modulator is tuned to pass light of a first wavelength during a first time slot and during a second time slot; an O-QCAM cell represents a logic '0' when the first modulator is tuned to pass light of the first wavelength during a first time slot and the first modulator is tuned to block light of the first wavelength during a second time slot; an O-QCAM cell represents a logic '1' when the first modulator is tuned to block light of the first wavelength during a first time slot and the first modulator is tuned to block light of the first wavelength during a second time slot; and an O-QCAM cell represents a wildcard value when the first modulator is tuned to block light of the first wavelength during a first time slot and during a second time slot.

17. The method of claim 12, wherein the optical search engine is programmed, by the programming controller, to execute at least one of: Boolean constrain propagation, wherein a conjunctive normal form of a function comprises a plurality of clauses, wherein each clause is mapped to a QCAM word entry of the plurality of O-QCAM word entries; a Boolean function comprising $2n-1$ input integers mapped to the plurality of O-QCAM word entries; and an equality check comprising

$[0: \binom{2n}{n} - 1]$ input entries mapped to the plurality of O-QCAM word entries, wherein n is a number of O-QCAM cells in the plurality of O-QCAM cells.

18. An optical quaternary content addressable memory (O-QCAM), comprising: an input encoder configured to input encoded optical signals representative of one or more search words from a search word source; an optical search engine optically coupled to the input encoder, the optical search engine comprising a plurality of O-QCAM cells configured to store a plurality of QCAM stored words; and a photodetector array comprising a plurality of photodetectors optically coupled to a plurality of output routing waveguides of the optical search engine, each photodetector of the

photodetector array associated with an output routing waveguide of the plurality of output waveguides, wherein the optical search engine is configured to pass an input encoded optical signal corresponding to a bit position of an input search word to an output routing waveguide to indicate a mismatch between a bit the search word and a bit of a O-QCAM stored word irrespective the input encoded optical signal.

19. The O-QCAM of claim 18, wherein each O-QCAM cell comprises one or more modulators disposed between an input waveguide and the output match waveguide, the O-QCAM further comprising: a programming controller configured to store the plurality of QCAM stored words to respective O-QCAM cells by tuning the one or more modulators of the plurality of O-QCAM cells.

20. The O-QCAM of claim 19, wherein passing the input encoded optical signal comprising storing a reject value in an O-QCAM cell corresponding to the O-QCAM stored word.
