

US Patent & Trademark Office

Patent Public Search | Text View

United States Patent	12399582
Kind Code	B2
Date of Patent	August 26, 2025
Inventor(s)	Beyhs; Michael et al.

Ring input device with variable rotational resistance

Abstract

A ring input device, and more particularly to variable rotational resistance mechanisms within the ring input device that modulate the rotational friction of a rotating outer band to improve the user experience, is disclosed. Because finger rings are often small and routinely worn, electronic finger rings can be employed as unobtrusive communication devices that are readily available to communicate wirelessly with other devices capable of receiving those communications. Ring input devices according to examples of the disclosure can modulate the rotational friction of its rotating outer band in accordance with an item (e.g., user interface or parameter) being manipulated by the band.

Inventors: Beyhs; Michael (Pfaffenheck, DE), Huizar; Richard G. (San Marcos, CA), Ilievski; Filip (Belmont, CA), Lu; Jean Hsiang-Chun (Sunnyvale, CA), Miller; Thayne M. (Escondido, CA)

Applicant: Apple Inc. (Cupertino, CA)

Family ID: 1000008778435

Assignee: Apple Inc. (Cupertino, CA)

Appl. No.: 18/353044

Filed: July 14, 2023

Prior Publication Data

Document Identifier	Publication Date
US 20230359291 A1	Nov. 09, 2023

Related U.S. Application Data

continuation parent-doc US 17471024 20210909 US 11733790 child-doc US 18353044
us-provisional-application US 63083084 20200924
us-provisional-application US 63083088 20200924

Publication Classification

Int. Cl.: **G06F3/0362** (20130101); **G01D5/24** (20060101); **G06F3/038** (20130101)

U.S. Cl.:

CPC **G06F3/0362** (20130101); **G01D5/24** (20130101); **G06F3/038** (20130101);
G06F2203/0384 (20130101)

Field of Classification Search

CPC: G06F (3/0362); G06F (3/038); G06F (2203/0384); G01D (5/24)

References Cited

U.S. PATENT DOCUMENTS

Patent No.	Issued Date	Patentee Name	U.S. Cl.	CPC
8570273	12/2012	Smith	345/161	G06F 3/03547
10139906	12/2017	Bai	N/A	N/A
10317940	12/2018	Eim et al.	N/A	N/A
10635173	12/2019	Lim et al.	N/A	N/A
2002/0067160	12/2001	Oomkes	324/207.2	H01H 5/02
2003/0214481	12/2002	Xiong	N/A	N/A
2005/0237214	12/2004	Sanchirico, Jr.	70/333R	E05B 65/108
2006/0001646	12/2005	Hai	N/A	N/A
2006/0033703	12/2005	Olien	345/156	G06F 3/0362
2007/0164733	12/2006	Kabashima et al.	N/A	N/A
2007/0268268	12/2006	Allison	N/A	N/A
2007/0279401	12/2006	Ramstein	345/184	G06F 3/016
2010/0164908	12/2009	Hill	345/184	G06F 3/0362
2011/0007035	12/2010	Shai	345/179	G06F 3/0304
2012/0075173	12/2011	Ashbrook	345/156	G06F 3/0362
2012/0293410	12/2011	Bell	N/A	N/A
2013/0027341	12/2012	Mastandrea	N/A	N/A
2013/0135223	12/2012	Shai	N/A	N/A
2015/0208967	12/2014	Tateda et al.	N/A	N/A
2016/0378131	12/2015	Battlogg	74/553	F16H 59/0217
2016/0378184	12/2015	Dow et al.	N/A	N/A
2017/0045958	12/2016	Battlogg	N/A	G06F 1/169
2017/0108939	12/2016	Chilmulwar et al.	N/A	N/A
2017/0147138	12/2016	Dow	N/A	G06F 1/163
2017/0262083	12/2016	Huang	N/A	G06F 3/016
2018/0018026	12/2017	Bushnell	N/A	G06F 3/0362
2018/0052517	12/2017	Bulgarelli et al.	N/A	N/A
2018/0120891	12/2017	Eim	N/A	H04M 1/0235
2018/0193198	12/2017	Li et al.	N/A	N/A

2018/0210562	12/2017	Kao	N/A	G06F 3/0362
2018/0239429	12/2017	Gupta et al.	N/A	N/A
2019/0015014	12/2018	Lange	N/A	N/A
2019/0038222	12/2018	Krimon et al.	N/A	N/A
2019/0155385	12/2018	Lim et al.	N/A	N/A
2019/0187751	12/2018	Griffin	N/A	N/A
2019/0346941	12/2018	Griffin et al.	N/A	N/A
2020/0004346	12/2019	Vlasov	N/A	G06F 3/03543
2020/0142497	12/2019	Zhu et al.	N/A	N/A
2020/0178395	12/2019	Graber et al.	N/A	N/A
2020/0403470	12/2019	Tzeng	N/A	H02K 7/1861
2021/0096660	12/2020	Xie et al.	N/A	N/A
2021/0286448	12/2020	Dunant	N/A	G06F 3/0362
2022/0091683	12/2021	Beyhs et al.	N/A	N/A
2022/0300026	12/2021	Alzingre	N/A	G05G 9/047
2023/0341956	12/2022	Rizvi	N/A	G06F 3/0362

FOREIGN PATENT DOCUMENTS

Patent No.	Application Date	Country	CPC
101785046	12/2009	CN	N/A
103221901	12/2012	CN	N/A
103221902	12/2012	CN	N/A
105004464	12/2014	CN	N/A
106164808	12/2015	CN	N/A
106473725	12/2016	CN	N/A
2015/102175	12/2014	WO	N/A
2018/030887	12/2017	WO	N/A

OTHER PUBLICATIONS

Advisory Action received for U.S. Appl. No. 17/471,024, mailed on Dec. 16, 2022, 3 pages. cited by applicant

Final Office Action received for U.S. Appl. No. 16/834,888, mailed on Aug. 18, 2021, 25 pages. cited by applicant

Final Office Action received for U.S. Appl. No. 17/471,024, mailed on Nov. 4, 2022, 14 pages. cited by applicant

International Search Report received for PCT Patent Application No. PCT/US2020/040102, mailed on Sep. 24, 2020, 4 pages. cited by applicant

Non-Final Office Action received for U.S. Appl. No. 16/834,888, mailed on Jan. 22, 2021, 25 pages. cited by applicant

Non-Final Office Action Received for U.S. Appl. No. 17/471,024, mailed on Jun. 6, 2022, 12 Pages. cited by applicant

Notice of Allowance received for U.S. Appl. No. 16/834,888, mailed on Nov. 8, 2021, 13 pages. cited by applicant

Notice of Allowance received for U.S. Appl. No. 17/471,024, mailed on Apr. 5, 2023, 7 pages. cited by applicant

AMS Datasheet, "TMG3992", Gesture, Color, ALS, and Proximity Sensor Module with mobeam (TM) Barcode Emulation, V1-06, Feb. 27, 2018, 95 pages. cited by applicant

AMS Datasheet, "TMG49037", Gesture, Color and Proximity Sensor Module, v1-01, Aug. 20, 2019, 78 pages. cited by applicant

Han et al., "Frictio: Passive Kinesthetic Force Feedback for Smart Ring Output", Association for

Computing Machinery, Oct. 22-25, 2017, 12 pages. cited by applicant
Nordic Semiconductor, “nRF52832”, Multiprotocol Bluetooth 5, ANT/ANT+ and 2.4GHz
Proprietary System-on-Chip, Product Brief Version 2.0, Retrieved on Apr. 4, 2019, 2 pages. cited
by applicant
Tsukada et al., “Ubi-Finger: Gesture Input Device for Mobile Use”, Information Processing Society
of Japan, Jan. 2002, 8 pages. cited by applicant
Search Report received for Chinese Patent Application No. 202111118785.9, mailed on Mar. 21,
2024, 4 pages (2 pages of English Translation and 2 pages of Official Copy). cited by applicant
Search Report received for Chinese Patent Application No. 202111119256.0, mailed on Mar. 27,
2024, 4 pages (2 pages of English Translation and 2 pages of Official Copy). cited by applicant

Primary Examiner: Balaoing; Ariel A

Attorney, Agent or Firm: Kubota & Basol LLP

Background/Summary

CROSS-REFERENCE TO RELATED APPLICATIONS (1) This application is a continuation of U.S. patent application Ser. No. 17/471,024, filed Sep. 9, 2021, and published on Mar. 24, 2022 as U.S. Publication No. 2022-0091683, which claims the benefit of U.S. Provisional Application No. 63/083,082, filed Sep. 24, 2020, U.S. Provisional Application No. 63/083,084, filed Sep. 24, 2020, U.S. Provisional Application No. 63/083,092, filed Sep. 24, 2020, and U.S. Provisional Application No. 63/083,088, filed Sep. 24, 2020, the contents of which are incorporated herein by reference in their entireties for all purposes.

FIELD

(1) This relates to a ring input device, and more particularly to variable rotational resistance mechanisms within the ring input device that modulate the rotational friction of a rotating outer band to improve the user experience.

BACKGROUND

(2) Many types of electronic devices are presently available that are capable of receiving input to initiate operations. Examples of such devices include desktop, laptop and tablet computing devices, smartphones, media players, wearables such as watches and health monitoring devices, smart home control and entertainment devices, headphones and ear buds, and devices for computer-generated environments such as augmented reality, mixed reality, or virtual reality environments. Many of these devices can receive input through the physical touching of buttons or keys, mice, trackballs, joysticks, touch panels, touch screens and the like. Some devices can also detect and receive input from objects such as a finger or stylus in close proximity to, but not physically touching, the device. To provide the convenience of being able to receive input at greater distances without having to be in close proximity to an object, many of these devices can also communicate wirelessly with other electronic devices, for example via Bluetooth or Wifi.

SUMMARY

(3) This relates to a ring input device, and more particularly to variable rotational resistance mechanisms within the ring input device that modulate the rotational friction of a rotating outer band to improve the user experience. Because finger rings are often small and routinely worn, electronic finger rings can be employed as unobtrusive communication devices that are readily available to communicate wirelessly with other devices capable of receiving those communications. Ring input devices according to examples of the disclosure can modulate the rotational friction of its rotating outer band in accordance with an item (e.g., user interface or

parameter) being manipulated by the band. Although ring input devices may be primarily described and illustrated herein as electronic finger rings for convenience of explanation, it should be understood that the examples of the disclosure are not so limited, but also include ring input devices that are worn as part of a necklace, hoop earrings, electronic bracelet bands that are worn around the wrist, electronic toe rings, and the like.

Description

BRIEF DESCRIPTION OF THE DRAWINGS

- (1) FIGS. 1A-1C illustrate different configurations of a ring input device according to examples of the disclosure.
- (2) FIG. 1D is an exploded view of a ring input device according to examples of the disclosure.
- (3) FIG. 2 is a system block diagram of a ring input device according to examples of the disclosure.
- (4) FIG. 3A is a symbolic side view of a portion of a stationary inner band and a rotating outer band according to examples of the disclosure.
- (5) FIG. 3B illustrates a side symbolic view of a portion of a stationary inner band and a rotating outer band with a variable resistance generator supported on the inner band according to examples of the disclosure.
- (6) FIG. 3C illustrates a side symbolic view of a portion of a stationary inner band and a rotating outer band with a variable resistance generator containing magnetorheological fluid according to examples of the disclosure.
- (7) FIG. 3D illustrates a side symbolic view of a portion of a stationary inner band and a rotating outer band with a variable resistance generator supported on the outer band according to examples of the disclosure.
- (8) FIG. 4A is a symbolic side view of two portions of a stationary inner band and a rotating outer band in concentric alignment according to examples of the disclosure.
- (9) FIG. 4B is a symbolic side view of two portions of a stationary inner band and a rotating outer band in an eccentric relationship according to examples of the disclosure.
- (10) FIG. 5A is a symbolic side view of a portion of a stationary inner band and a rotating outer band with an electromagnetic rotational resistance generator according to examples of the disclosure.
- (11) FIG. 5B is a symbolic side view of a portion of a stationary inner band and a rotating outer band with an electromagnetic rotational resistance generator having a movable brake according to examples of the disclosure.
- (12) FIG. 6A is a symbolic end view of a stationary inner band, a rotating outer band, a guard rail and a variable resistance generator configured for axial resistance according to examples of the disclosure.
- (13) FIG. 6B is a symbolic end view of a stationary inner band, a rotating outer band, a guard rail and an electromagnetic resistance generator configured for axial electromagnetic force according to examples of the disclosure.
- (14) FIG. 7A is a symbolic end view of a rotating outer band and a magnetometer according to examples of the disclosure.
- (15) FIG. 7B illustrates two symbolic side views of a rotating outer band in two different positions, rotated 90 degrees from each other, and a magnetometer located in proximity to the outer band according to examples of the disclosure.
- (16) FIG. 8A is a normalized plot of rotation angle vs. magnetic field strength along the Y axis and along the Z axis according to one example of the disclosure.
- (17) FIG. 8B is a normalized plot of magnetic field strength along the Z axis vs. magnetic field strength along the Y axis according to the example of FIG. 8A.

- (18) FIG. 8C is a plot of rotation angle true position (in degrees) vs. calculated position (in degrees) according to the example of FIGS. 8A-8B.
- (19) FIG. 9A is a symbolic perspective view of a ring input device including a rotating outer band with physical indicators such as grooves according to examples of the disclosure.
- (20) FIG. 9B is a symbolic view of a user interface with icons displayed on the touchscreen of a companion device according to examples of the disclosure.
- (21) FIG. 10A is a side view of a band mechanism of a ring input device including low friction contact points and button bearings according to examples of the disclosure.
- (22) FIG. 10B is an enlarged side view of a pressure-sensitive input mechanism in the form of a dome switch button bearing as indicated by the dashed lines in FIG. 10A according to examples of the disclosure.
- (23) FIGS. 11A-11B are simplified symbolic side views (not to scale) of a rotating outer band and a stationary inner band, with the inner bands having different levels of rigidity according to examples of the disclosure.
- (24) FIG. 11C is a simplified symbolic side view (not to scale) of a rotating outer band and a stationary inner band, with the inner bands having stoppers on either side of a dome switch button bearing according to examples of the disclosure.
- (25) FIG. 12A is a symbolic side view of a portion of a band mechanism including a stationary inner band and a rotating outer band with sliding contacts to provide touch sensing according to examples of the disclosure.
- (26) FIG. 12B is a perspective view of a portion of a band mechanism showing a leaf spring sliding contact on a stationary inner band according to examples of the disclosure.
- (27) FIG. 13A is a symbolic side view of a section of a band mechanism showing a button bearing affixed to an inner band, where the button bearing can also serve as a sliding contact according to examples of the disclosure.
- (28) FIG. 13B is a symbolic side view of a section of a band mechanism showing a dome switch button bearing affixed to an inner band, where the button bearing can also serve as a sliding contact with a reduced number of traces according to examples of the disclosure.
- (29) FIG. 13C is a symbolic side view of a section of a band mechanism showing a sliding contact and a button bearing affixed to an inner band with a reduced number of traces according to examples of the disclosure.
- (30) FIG. 13D is flowchart of a method for detecting a valid touch or press input on a ring input device according to examples of the disclosure.
- (31) FIG. 13E is a symbolic side view of a section of a band mechanism showing two dome switch button bearings affixed to an inner band, where the button bearings can serve as sliding contacts with a reduced number of traces according to examples of the disclosure.
- (32) FIG. 14A is a system block diagram of an electronic jewel system of a ring input device including a scroll ball and a touch sensor according to examples of the disclosure.
- (33) FIG. 14B is a symbolic perspective view of a ring input device including an electronic jewel system with a scroll ball and a touch sensor according to examples of the disclosure.

DETAILED DESCRIPTION

(34) In the following description of examples, reference is made to the accompanying drawings which form a part hereof, and in which it is shown by way of illustration specific examples that can be practiced. It is to be understood that other examples can be used and structural changes can be made without departing from the scope of the disclosed examples.

(35) Examples of the disclosure relate to a ring input device. Because finger rings are routinely worn and are often small, electronic finger rings can be employed as unobtrusive, everyday communication devices that are readily available to communicate wirelessly with other devices capable of receiving those communications. Although ring input devices may be primarily described and illustrated herein as electronic finger rings for convenience of explanation, it should

be understood that the examples of the disclosure are not so limited, but also include ring input devices that are worn as part of a necklace, hoop earrings, electronic bracelet bands that are worn around the wrist, electronic toe rings, and the like. Some examples of the disclosure are directed to pressure-sensitive input mechanisms (e.g., buttons) within the ring input device that detect pressure to initiate an operation. Other examples of the disclosure are directed to a conductive outer band on the ring input device that can detect a touch to initiate an operation. Still other examples of the disclosure are directed to modulating the rotational friction of a rotating outer band on the ring input device to improve the user experience. Still other examples of the disclosure are directed to detecting the rotational position of the rotating outer band or detecting the position/orientation of the ring input device to provide additional input capabilities.

(36) FIGS. 1A-1C illustrate different configurations of ring input device **100** according to examples of the disclosure. In the example of FIG. 1A, ring input device **100** can include band mechanism **102** that can include stationary inner band **104**, rotating outer band **106**, and contact pads **108** (for making electrical contact with a user's finger, for example). Band mechanism **102** can, in some examples, be removably couplable to an electronic jewel system which may be simply referred to herein as “jewel” **110**, which is illustrated symbolically in FIG. 1A as a box, though in various examples in can be productized in a variety of different shapes and sizes. FIG. 1B illustrates ring input device **100** having a more compact, less obtrusive configuration of jewel **110** according to examples of the disclosure. To accommodate a flatter jewel **110** as in FIG. 1B, band mechanism **102** may be widened as compared to FIG. 1A (8 mm instead of 4 mm, for example). FIG. 1C illustrates ring input device **100** with the functionality of jewel **110** located inside a portion of a thickened stationary inner band **104**. It should be understood that the illustrations of FIGS. 1A-1C are example configurations that are not drawn to scale, and that any of the components of FIGS. 1A-1C can take on different shapes, sizes and thicknesses.

(37) Ring input device **100** of FIGS. 1A-1C can be utilized to provide wireless inputs for a wide variety of devices. For example, ring input device **100** can be used to provide inputs to companion wearable devices such as smart watches, health monitoring devices, headphones, ear buds and the like. Ring input device **100** can also be used to provide inputs to handheld devices such as smartphones (e.g., scrolling through a list using rotating outer band **106**), tablet and laptop computing devices, media players, styluses, wands or gloves for computer-generated environments, and the like. In addition, ring input device **100** can also be used to provide inputs to stationary devices such as desktop computers, smart home control and entertainment devices (e.g., turning on a lamp, changing a TV channel), and the like. In some examples, ring input device **100** can receive wireless input from a companion device and provide information to the wearer of the ring (e.g., the ring can receive a notification from a smartphone and generate a vibrating alert).

(38) FIG. 1D is an exploded view of ring input device **100** according to examples of the disclosure. In the example of FIG. 1D, band mechanism **102** is illustrated exploded in the axial direction, exposing example stationary inner band **104** and rotating outer band **106**. Also shown is guard rail **134**, which can couple to stationary inner band **104** to retain rotating outer band **106** while allow rotation of the outer band. Guard rail **134** can also include pogo pins **136** (described in further detail below) for providing electrical connections with jewel **110**, although connections other than pogo pins **136** can also be employed. In some examples, and in some instances depending on the configuration of pogo pins **136** (or connections, in general), jewel **110** can be removably coupled to guard rail **134** using screws, tabs, tongue-and-groove structures, and the like. FIGS. 1A-1C illustrate (in dashed lines) that jewel **110** can, in various examples, be removed or installed vertically, or slid in and out horizontally.

(39) FIG. 2 is a system block diagram of ring input device **200** according to examples of the disclosure. In the example of FIG. 2, band mechanism **202** can be electrically coupled to jewel **210** through connections **212**, which in some examples can be so-called “pogo pins,” which are spring-loaded electrical connectors that press into, and make electrical contact with, conductive areas

(lands or targets). Band mechanism **202** can include stationary inner band **204** and rotating outer band **206**. In some examples, stationary inner band **204** can include pressure sensitive input mechanism **214** and touch sensing mechanism **216**, although in other examples these blocks can be combined into one functional block. Stationary inner band **204** can also include variable resistance generator **232**. In some examples, pressure sensitive input mechanism **214** and touch sensing mechanism can be electrically coupled to rotating outer band **206** via a sliding connection, and variable resistance generator **232** can apply a frictional or magnetic influence on rotating outer band **206**.

(40) Electronic jewel system or “jewel” **210** can include controller **218** coupled to memory and/or storage **220**. Controller **218** can include one or more processors capable of executing programs stored in memory **220** to perform various functions. In examples of the disclosure, controller **218** can be connected to wireless transmitter or transceiver **224** and one or more of inertial measurement unit (IMU) **226**, magnetometer **228**, and haptics generator **230**. Memory **220** can include, but is not limited to, random access memory (RAM) or other types of memory or storage, watchdog timers and the like. Controller **218** can include, but is not limited to, touch sensing circuitry for driving and/or sensing one or more touch electrodes, including the generation of one or more stimulation signals at various frequencies and/or phases that can be selectively applied to the touch electrodes. Controller **218** can also be communicatively coupled to magnetometer **228** to process signals from the magnetometer to determine the amount of rotation of rotating outer band **206**, and to IMU **226** to process signals from the IMU to determine parameters such as the angular rate, orientation, position, and velocity of ring input device **200**. In some examples, controller **218** can be communicatively coupled to haptics generator **230** to initiate haptic feedback. Controller **218** can also be communicatively coupled to wireless transmitter or transceiver **224** to send inputs wirelessly, and in some examples to send and receive data and other information. In some examples, wireless transmitter or transceiver **224** can communicate wirelessly with desktop, laptop and tablet computing devices, smartphones, media players, wearables such as watches and health monitoring devices, smart home control and entertainment devices, headphones and ear buds, and devices for computer-generated environments such as augmented reality, mixed reality, or virtual reality environments, and the like.

(41) It should be apparent that the architecture shown in FIG. 2 is only one example architecture of jewel **210**, and that the system could have more or fewer components than shown, or a different configuration of components. The various components shown in FIG. 2 can be implemented in hardware, software, firmware or any combination thereof, including one or more signal processing and/or application specific integrated circuits.

(42) Note that one or more of the functions described herein can be performed by firmware stored in memory **220** and executed by a processor in controller **218**. The firmware can also be stored and/or transported within any non-transitory computer-readable storage medium for use by or in connection with an instruction execution system, apparatus, or device, such as a computer-based system, processor-containing system, or other system that can fetch the instructions from the instruction execution system, apparatus, or device and execute the instructions. In the context of this document, a “non-transitory computer-readable storage medium” can be any medium (excluding signals) that can contain or store the program for use by or in connection with the instruction execution system, apparatus, or device. In some examples, memory **220** can be a non-transitory computer readable storage medium. Memory **220** can have stored therein instructions, which when executed by a processor in controller **218**, can cause ring input device **200** to perform one or more functions and methods of one or more examples of this disclosure. The computer-readable storage medium can include, but is not limited to, an electronic, magnetic, optical, electromagnetic, infrared, or semiconductor system, apparatus or device, a portable computer diskette (magnetic), a random access memory (RAM) (magnetic), a read-only memory (ROM) (magnetic), an erasable programmable read-only memory (EPROM) (magnetic), a portable optical

disc such a CD, CD-R, CD-RW, DVD, DVD-R, or DVD-RW, or flash memory such as compact flash cards, secured digital cards, USB memory devices, memory sticks, and the like.

(43) The firmware can also be propagated within any transport medium for use by or in connection with an instruction execution system, apparatus, or device, such as a computer-based system, processor-containing system, or other system that can fetch the instructions from the instruction execution system, apparatus, or device and execute the instructions. In the context of this document, a “transport medium” can be any medium that can communicate, propagate or transport the program for use by or in connection with the instruction execution system, apparatus, or device. The transport medium can include, but is not limited to, an electronic, magnetic, optical, electromagnetic or infrared wired or wireless propagation medium.

(44) FIG. 3A is a symbolic side view of a portion of stationary inner band **304** and rotating outer band **306** according to examples of the disclosure. It should be noted that FIG. 3A is not drawn to scale, and that the gap between stationary inner band **304** and rotating outer band **306** can be on the order of several hundred microns. In some examples, an encoder (e.g., an optical encoder) can be used to detect the rotation of outer band **306**, though in other examples described hereinbelow, other devices such as a magnetometer can be used. As described above, stationary inner band **304** can include a variable resistance generator, which can apply a frictional or magnetic influence on rotating outer band **306** to effectively produce a feeling of modulated resistance to the rotation of the outer band. In the example of FIG. 3A, arrows are shown that symbolically represent the frictional or magnetic influence that can be applied to rotating outer band **306**. In some examples, this frictional or magnetic influence can be the result of an effective increase in the diameter of stationary inner band **304**, at least in portions of the inner band. In examples of the disclosure, this frictional or magnetic influence can be modulated so that rotating outer band **306** can become easier or harder to rotate, be frozen in place, produce the feeling of detents (bumps, catches, etc.) on the band, produce hard stops, and the like.

(45) Modulating the rotational resistance of rotating outer band **306** can provide a number of advantages. In general, a user interface being manipulated by the ring input device can affect the rotational resistance of outer band **306** to improve the user experience. For example, rotation of outer band **306** can become more difficult and eventually stop at the end of an input (e.g., when the rotation causes the end of a virtually displayed slider to be reached). In some examples, the frictional or magnetic influence can depend on the item (e.g., the parameter or user interface (UI)) being manipulated. In other examples, rotational resistance can be reduced when a list to be scrolled is long and fast scrolling is desired, or the rotational resistance can be increased when the list is short or when more precise scrolling is desired. In still other examples, rotational resistance can be increased or decreased depending on whether the item being manipulated should be changed slowly (e.g., the volume of a companion device) or quickly (e.g., scrolling through a lengthy document).

(46) The feeling of detents, caused by pulses of increased rotational resistance, can be advantageous when moving through a document in page view, moving in discrete increments, jumping from one icon to another, etc. However, because detents can be time sensitive, delays in receiving detents can render the feedback useless, or worse, lead to errors. Delays can be the result of the round-trip communication path of receiving an input at outer band **306**, wirelessly transmitting a signal to a companion device, receiving a reply from the companion device, and then generating the detent. Thus, in some examples, detent processing and generation can be handled locally, such as within the jewel.

(47) In other examples, strong rotational resistance, to the point of making rotating outer band **306** immobile, can be employed to ensure that no rotational inputs are inadvertently generated. In addition, strong rotational resistance can be applied only at the beginning of a rotation, and can be reduced as the user applies enough rotational force to overcome this strong initial rotational resistance. This strong initial rotational resistance can feel like the initial resistance of a switch

being flipped on or a knob being clicked on, and can ensure that no events are accidentally triggered. Similarly, strong rotational resistance can be applied only at the end of a rotation, and can be increased to require that the user apply enough rotational force to overcome this strong terminal rotational resistance. This strong terminal rotational resistance can feel like the final end resistance of a switch being flipped off or a knob being clicked off, requiring a strong affirmative action to end the activity. It should be understood that the preceding description of uses is non-limiting and merely illustrative, and that modulating the rotational resistance of rotating outer band **306** is contemplated for other purposes as well.

(48) FIG. **3B** illustrates a side symbolic view of a portion of stationary inner band **304** and rotating outer band **306** with variable resistance generator **332** supported on the inner band according to examples of the disclosure. In some examples of the disclosure, variable resistance generator **332** can be an electroactive polymer (EAP) which can change size and shape when stimulated by an electric field. The strength of the applied electric field can determine the amount of applied resistance to rotating outer band **306**, and pulsing the applied electric field at a particular duty cycle can create the feeling of detents in the rotating outer band. In some examples, variable resistance generator **332** can be an electromechanical brake, where electromagnetic force is used to press the variable resistance generator (in this example, in the form of a brake pad) against rotating outer band **306**. The strength of the applied electromagnetic force can determine the amount of applied resistance to rotating outer band **306**, and pulsing the applied electromagnetic force at a particular duty cycle can create the feeling of detents in the rotating outer band. In some examples, variable resistance generator **332** can be a shape memory alloy (SMA) which can change size and shape depending on its temperature, as controlled by current flow. The current flow can determine the amount of applied resistance to rotating outer band **306**, and pulsing the current at a particular duty cycle can create the feeling of detents in the rotating outer band. In some examples, variable resistance generator **332** can be an air bladder, which can change size and shape depending on its air (or other gas) content. The amount of air can determine the amount of applied resistance to rotating outer band **306**, and pulsing the volume of air at a particular duty cycle can create the feeling of detents in the rotating outer band. In some examples, variable resistance generator **332** can be a piezoelectric material which can change size and shape when a voltage is applied. The voltage level can determine the amount of applied resistance to rotating outer band **306**, and pulsing the voltage level at a particular duty cycle can create the feeling of detents in the rotating outer band. In some examples, variable resistance generator **332** can be an electroadhesive pad. The electroadhesive pad can include electrodes biased with alternating positive and negative voltages, creating an electric field therebetween. Positive and negative charges can then be induced on rotating outer band **306**, which can cause electrostatic adhesion to develop between the electrodes and the outer band, creating rotational resistance between them.

(49) FIG. **3C** illustrates a side symbolic view of a portion of stationary inner band **304** and rotating outer band **306** with variable resistance generator **332** containing magnetorheological fluid **338** according to examples of the disclosure. In the example of FIG. **3C**, magnetorheological fluid **338** can be retained in a membrane or other receptacle to hold the fluid between stationary inner band **304** and rotating outer band **306**. Because magnetorheological fluid **338** can increase in viscosity in the presence of a magnetic field to the point of effectively becoming a solid, the strength of the applied magnetic field can determine the viscosity and therefore the amount of applied resistance to rotating outer band **306**, and pulsing the applied magnetic field at a particular duty cycle can create the feeling of detents in the rotating outer band.

(50) FIG. **3D** illustrates a side symbolic view of a portion of stationary inner band **304** and rotating outer band **306** with variable resistance generator **332** supported on the outer band according to examples of the disclosure. The example of FIG. **3D** is similar to the example of FIG. **3B**, except that variable resistance generator is supported on rotating outer band **306**. In the example of FIG. **3D**, arrows are shown that symbolically represent the frictional or magnetic influence can be

applied to stationary inner band **304**. The various examples of variable resistance generator **332** described above in FIGS. **3A-3C** can also be employed in FIG. **3D**. In the example of FIG. **3D**, one or more additional electrical connections are needed between stationary inner band **304** and rotating outer band **306** to apply electric fields, electromagnetic force, current flow and the like to variable resistance generator **332**. In some examples, these connections can be made by leaf springs or other slidable contacts.

(51) FIG. **4A** is a symbolic side view of two portions of stationary inner band **404** and rotating outer band **406** in concentric alignment according to examples of the disclosure. In the examples of variable resistance generators **432** described above, if stationary inner band **404** and rotating outer band **406** are configured as concentric bands as in the example of FIG. **4A**, variable resistance generators **432** can be required on opposing sides of band mechanism **402** to apply complementary opposing forces and maintain the concentric relationship of the inner and outer bands. It should be understood that although FIG. **4A** only shows variable resistance generators **432** at bottom and top locations for ease of illustration, multiple variable resistance generators can be employed in any number of opposing locations along the band mechanism.

(52) FIG. **4B** is a symbolic side view of two portions of stationary inner band **404** and rotating outer band **406** in an eccentric relationship according to examples of the disclosure. In the examples of variable resistance generators **432** described above, if stationary inner band **404** and rotating outer band **406** are configured as eccentric bands as in the example of FIG. **4B**, variable resistance generators **432** need not be required on opposing sides of band mechanism **402** to maintain the eccentric relationship of the inner and outer bands. It should be understood that although FIG. **4B** only shows one variable resistance generator **432** at a bottom location for ease of illustration, multiple variable resistance generators can be employed in multiple locations along the band mechanism, although the geometry of the eccentric bands illustrated in FIG. **4B** can limit the location of variable resistance generators, and the effective “diameter increase” of each variable resistance generator may need to be different, depending on the location of the variable resistance generator along the band mechanism.

(53) FIG. **5A** is a symbolic side view of a portion of stationary inner band **504** and rotating outer band **506** with electromagnetic rotational resistance generator **540** according to examples of the disclosure. In the example of FIG. **5A**, electromagnetic rotational resistance generator **540** can include an array of coils **542** formed on stationary inner band **504** and an array of magnetic poles **544** formed on rotating outer band **506**. Poles **544** can be formed to have alternating opposite poles (e.g., a sequence of north-south-north-south, etc. poles), although in other examples different patterns of opposite poles can be employed. In the example of FIG. **5A**, the direction of current flow through each coil **542** can attract or repel the magnetized poles **544**. In some examples, individual coils **542** can be magnetized via directional current flow in accordance with the magnetization pattern of poles **544** to create forces of attraction with respect to poles **544** (see arrows) sufficient to resist the rotation of rotating outer band **506**, effectively creating a braking effect. The strength of the electromagnets formed by coils **542** can vary in accordance with their current flow to create a variable effective resistance. In some examples, the resistance to rotation that can be felt on rotating outer band **506** as a pole passes by the attractive forces of a coil can create a force profile that mimics the feeling of detents on the band mechanism. If the forces of attraction are strong enough, rotating outer band **506** can feel locked in place.

(54) FIG. **5B** is a symbolic side view of a portion of stationary inner band **504** and rotating outer band **506** with electromagnetic rotational resistance generator **540** having movable brake **546** according to examples of the disclosure. In the example of FIG. **5B**, magnetic rotational resistance generator **532** can include an array of coils **542** formed on brake **546** which can be movably coupled to stationary inner band **504**, and an array of magnetic poles **544** formed on rotating outer band **506**. In some examples, individual coils **542** can be magnetized via directional current flow in accordance with the magnetization pattern of poles **544** to create forces of attraction with respect to

poles **544** sufficient to resist the rotation of rotating outer band **506**. However, unlike the examples of FIG. 5A, coils **542** can be affixed to brake **546**, which can move towards rotating outer band **506** until it contacts the outer band, providing resistance and effectively creating a braking effect. The strength of the electromagnets formed by coils **542**, and therefore the movement of brake **546** and the amount of friction or resistance that is created with respect to rotating outer band **506** can vary in accordance with their current flow to create a variable effective resistance. If the resistance is strong enough, rotating outer band **506** can feel locked in place.

(55) In other examples, individual coils **542** can be magnetized via directional current flow in various timing sequences to create rotational movement in rotating outer band **506** without requiring a user's touch. In other examples, manual rotation of rotating outer band **506**, such as by a finger, can induce a current in coils **542**. This energy can then be harvested and stored for later use, such as by charging a battery within the jewel.

(56) FIG. 6A is a symbolic end view of stationary inner band **604**, rotating outer band **606**, guard rail **634** and variable resistance generator **632** configured for axial resistance according to examples of the disclosure. Unlike the descriptions of variable resistance generators associated with FIG. 5A which apply variable resistance in a radial direction, variable resistance generator **632** in the example of FIG. 6A can be affixed to a side rail of stationary inner band **604** and apply a variable resistance in an axial direction to a side wall of rotating outer band **606**. In some examples, variable resistance generator **632** can alternatively or additionally be affixed to guard rail **634** as shown in dashed lines in FIG. 6A. Any of the variable resistance generator examples described above can be used in the example of FIG. 6A.

(57) FIG. 6B is a symbolic end view of stationary inner band **604**, rotating outer band **606**, guard rail **634** and electromagnetic resistance generator **640** configured for axial electromagnetic force according to examples of the disclosure. Unlike the descriptions of electromagnetic resistance generators associated with FIG. 5B which apply electromagnetic force in a radial direction, electromagnetic resistance generator **640** in the example of FIG. 6B can be affixed to the side rails of stationary inner band **604** and side wall of rotating outer band **606** and produce electromagnetic forces of attraction and repulsion in an axial direction. In some examples, electromagnetic resistance generator **640** can alternatively or additionally be affixed to guard rail **634** and the opposing side wall of rotating outer band **606**, as shown in dashed lines in FIG. 6B.

(58) In addition to modulating the rotational resistance of rotating outer band **606** as described above, examples of the disclosure can also determine positional information such as the rotational position (e.g., the absolute angle of the rotation position) of the outer band. Determining the rotational position can provide a number of advantages. For example, rotation of outer band **606** from one determined rotational position to another can be used to compute a direction of rotation, an amount or angle of rotation, and the absolute position (e.g., a clockwise relative rotation of 15 degrees to an absolute 45 degree position). The direction, amount, and absolute position of rotation of outer band **606** can determine the direction and amount of scrolling through a list, the direction and amount of panning of an image, the direction and amount of cursor movement, and the direction and amount of change of a parameter being manipulated (e.g., the amount of volume change), to name just a few examples. In some examples, a series of rotations (e.g., a series of angles of rotation) can be recorded to recognize gestures and initiate certain actions. For example, a series of back-and-forth rotations between two locations (e.g., between the 4 o'clock and 6 o'clock positions) can be recognized as a gesture to initiate a particular operation (e.g., an erase operation). In other examples, the rotational position, captured over time, can be used to determine a velocity or acceleration of rotating outer band **606**. It should be understood that the preceding description of uses is non-limiting and merely illustrative, and that determining the rotational position of outer band **606** is contemplated for other purposes as well. However, determining the rotational position can be difficult because rotating outer band **606** can freely move in either direction in an unlimited fashion (in the absence of applied rotational resistance), without any starting or ending points or

other clear frame of reference.

(59) FIG. 7A is a symbolic end view of rotating outer band **706** and magnetometer **748** according to examples of the disclosure. In the example of FIG. 7A, rotating outer band **706** can be magnetized to form a single dipole, preferably with predictable and uniform magnetic field lines **750**. In some examples, rotating outer band **707** can be made of a low coercivity, high remanence material to retain its magnetization. In some examples, 17-4 steel (approximately 17% chromium, 4% nickel) can be used, although other types of metal can also be employed. Magnetometer **748** can be located proximate to rotating outer band **706** in an area where magnetic field lines **750** from the outer band are present. In some examples, magnetometer **748** can be located in the jewel of the ring input device. Magnetometer **748** can be used to obtain rotational input data and measure and/or compute the direction, strength, or relative change of a magnetic field from its location. Because the location of magnetometer **748** acts as a point of reference from which calibrated measurements are obtained, precise placement of the magnetometer within the electric field is not required.

(60) FIG. 7B illustrates two symbolic side views of rotating outer band **706** in two different positions, rotated 90 degrees from each other, and magnetometer **748** located in proximity to the outer band according to examples of the disclosure. In the upper view, rotating outer band **706** is oriented with its north pole (N) at the 12 o'clock position, and its south pole (S) at the 6 o'clock position. In the lower view, outer band **706** has been rotated clockwise by 90 degrees, so that N is at the 3 o'clock position and S is at the 9 o'clock position. Note that magnetic field lines **750** have also been rotated clockwise by 90 degrees, which changes the strength of the magnetic field in each axis. In some examples of the disclosure, magnetometer **748** can be a multiple axis magnetometer which can measure magnetic field strength in at least Y and Z orthogonal axes, and these measurements can thereafter be used to compute the rotational position of outer band **706** by comparing measurements of magnetic field strength at the original and rotated positions. Although FIGS. 7A-7B shows rotating outer band **706** magnetized to form a single dipole, in other examples the outer band can be magnetized to form multiple dipoles. While the single dipole example of FIG. 7A can provide the advantage of determining absolute rotational position, multiple dipoles can provide the advantage of higher spatial resolution, because each dipole can be used to obtain more precise rotational position information over a smaller rotational range (e.g., 0-90 degrees). However, multiple dipoles can make it more difficult to disambiguate magnetometer magnetic field strength measurements and compute absolute rotational position information.

(61) Magnetometer **748** can be calibrated prior to computing the rotational position of rotating outer band **706**. Calibration can be performed prior to delivery of the final product, or by a user, by rotating the outer band one or more times. During these rotations, magnetometer **748** can measure the magnetic field strength along the Y and Z axes, and the influence of the earth's magnetic field can be ignored, because it can be on the order of 1% of the magnetic field produced by the magnetized outer band. In some examples, these magnetic field strength values can then be normalized to values between -1.0 and +1.0, for example. However, if magnetometer **748** is to be calibrated to compensate for the earth's magnetic field, then the magnetometer may be required to measure the magnetic field strength along all three axes (X, Y and Z axes).

(62) FIG. 8A is a normalized plot of rotation angle vs. magnetic field strength along the Y axis (plot **852**) and along the Z axis (plot **854**) according to one example of the disclosure. FIG. 8B is a normalized plot **856** of magnetic field strength along the Z axis vs. magnetic field strength along the Y axis according to the example of FIG. 8A. Ideally, the plot of FIG. 8B would be a circle with points at (0.0, 1.0), (1.0, 0.0), (0.0, -1.0), and (-1.0, 0.0) (clockwise from the 12 o'clock position), and the Y and Z plots of FIG. 8A would be more regular and sinusoidal in shape, but due to imperfect, non-uniform magnetization of the outer rotating band (which can result in less predictability in the magnetic field lines), the plots can be distorted, as shown in FIGS. 8A-8B.

(63) FIG. 8C is a plot **858** of rotation angle true position (in degrees) vs. calculated position (in degrees) according to the example of FIGS. 8A-8B. The calculated (absolute) position can be

computed as $\theta = \arctan 2 (Y, Z)$, where Y is the measured (normalized) magnetic field strength along the Y axis, and Z is the measured (normalized) magnetic field strength along the Z axis. Ideally, the plot of FIG. 8C would be linear, but due to imperfect magnetization the plot can contain some perturbations. In some examples of the disclosure, a calibration lookup table can be used to apply offsets to the calculated positions so that the resulting calibrated positions can produce a more linear plot than the plot shown in FIG. 8C. This calibration lookup table can be populated with offset values based on empirical data taken prior to the delivery of the final product, or it can be populated during field calibrations that are initiated by a user, or initiated periodically according to an automated calibration plan. In other examples, instead of a calibration lookup table, the offset values can be computed using piecewise estimates or using a specific formula based on pre-stored calibration information.

(64) In some examples of the disclosure, Hall effect sensors can be utilized instead of a magnetometer. Multiple Hall effect sensors (e.g., three Hall effect sensors) can be affixed to the inner band and used to determine an absolute rotational position of rotating outer band **706** when the outer band is magnetized to form a single dipole. In some instances, Hall effect sensors can be advantageously utilized on the inner band to detect outer band rotations when space issues prevent a magnetometer from being located inside the jewel.

(65) Although the magnetometer can be used to determine the rotational position of the rotating outer band, in some situations it can be difficult for a user to actually rotate the band, or determine that rotation of the band is actually occurring, particularly when visual confirmation of rotation is inconvenient or impossible.

(66) FIG. 9A is a symbolic perspective view of ring input device **900** including rotating outer band **906** with physical indicators such as grooves **960** according to examples of the disclosure. In the example of FIG. 9A, rotating outer band **906** can include grooves **960** to enable a user to feel the band and determine whether the band is actually rotating, or whether the band is stationary or nearly stationary and the user's finger is merely sliding over the band. Although grooves **960** are illustrated in FIG. 9A, in other examples physical indicators such as raised ridges, cavities, bumps and the like can also be formed on rotating outer band **906** to provide the user with tactile feedback as an alternative to visual feedback. In some examples, grooves **960** or other indicators can be spaced at certain intervals to give the user a sense of the amount of rotation. For example, if grooves **960** are spaced at 30 degree intervals, a user that repetitively brushes outer band **906** with a finger to rotate the band may be able to feel the passage of multiple grooves, and can stop when the desired amount of rotation is achieved.

(67) In some examples, ring input device **900** may include linear resonant actuator (LRA) **962** or other haptic feedback device. LRA **962** can include a mass that moves linearly to generate haptic feedback. In the example of FIG. 9A, LRA **962** is located in jewel **910**, but in other examples it may be located elsewhere in ring input device **900**. In some examples, as an alternative to grooves **960**, LRA **962** can generate a vibration or other force when rotating outer band **906** has rotated a certain number of degrees, as determined using the previously described magnetometer. In other examples, LRA **962** (or other haptic feedback generator) can generate haptic feedback at specific times based on the amount of rotation, a computed angular velocity and/or acceleration of rotating outer band **906**, and/or the UI being manipulated, in either a uniform or non-uniform manner. For example, if it is determined that a UI including a short (e.g., 10 item) list is being scrolled, haptic feedback can be uniformly generated as each item in the list is highlighted. On the other hand, if the list is long (e.g., 100 items), haptic feedback can be generated as every 10th item is highlighted. In some examples, if the detected angular velocity is low (e.g., less than 90 degrees of rotation per second), haptic feedback can be generated as each item in the list is highlighted. However, if the detected angular velocity is high (e.g., greater than 90 degrees of rotation per second), haptic feedback can be generated as every 10th item is highlighted, or every 10th of a second, for example. Haptic feedback can also be generated non-uniformly. For example, based on an initial

angular acceleration and/or velocity determination of rotating outer band **906**, “momentum” scrolling of a UI can be performed, wherein the UI can scroll through a list of items that sharply increases in velocity, reaches a steady state, then decays in velocity until it stops. Haptic feedback can be non-uniformly generated to track the movement of the UI by increasing in frequency, reaching a steady state, and then decreasing in frequency until it stops, regardless of whether motion of outer band **906** continues after the initial angular acceleration and/or velocity determination. However, if outer band **906** is held or otherwise dampened to slow or stop rotation of the band, the haptic feedback can non-uniformly decrease in frequency to follow the deceleration of the band.

(68) In some examples, LRA **962** (or other haptic feedback generator) can generate different types of haptic feedback based on the amount of rotation, a computed angular velocity and/or acceleration of rotating outer band **906**, and/or the UI being manipulated, in either a uniform or non-uniform manner. For example, if the detected angular velocity of rotating outer band **906** is low, haptic feedback can be generated to simulate the feeling of a band being rotated with higher friction, and a coarse texture. In another example, if the detected angular velocity of rotating outer band **906** is high, haptic feedback can be generated to simulate the feeling of a band being rotated with lower friction, and a smoother texture. In another example, different textures of haptic feedback can be generated when an inertial measurement unit (described below) in ring input device **900** is used to move a 3D object in a computer-generated environment.

(69) In other examples, LRA **962** can be used in conjunction with grooves **960**, such that a vibration is generated each time the rotation of outer band **906** causes a groove to pass a certain location, where it can be detected using an optical sensor or the like. LRA **962** can also be used to generate haptic feedback independent of any rotation of outer band **906**. For example, LRA **962** can generate haptic feedback to provide an alert to a user based on movement detected by an inertial measurement unit (discussed below), sound inputs (e.g., audio commands), sensor inputs, and/or signals (e.g., notifications) received wirelessly at ring input device **900**, even when outer ring **906** is stationary.

(70) In addition to rotating outer band **906** to initiate or perform operations as described above, examples of the disclosure can also determine positional information such as the orientation and movement of ring input device **900** itself in free space. Determining the orientation and movement of ring input device **900** in free space can provide a number of advantages. For example, a wearer of ring input device **900** can move the ring around in free space to generate rotational or orientation signals, or perform gestures such as hand swipes or waving that can trigger the wireless transmission of commands to a companion device. In one particular example, the orientation and movement of ring input device **900** from one position to another can be used to move a cursor on a user interface or a 3D object being displayed. In some examples, the gestures can be recognized in ring input device **900**, and in other examples, data can be wirelessly transmitted for gesture processing by another device. It should be understood that the preceding description of uses is non-limiting and merely illustrative, and that determining the orientation and movement of ring input device **900** is contemplated for other purposes as well.

(71) An inertial measurement unit (IMU) **964** can be used to determine the orientation and movement of ring input device **900**. In the example of FIG. **9A**, IMU **964** is located in jewel **910**, but in other examples it may be located elsewhere in ring input device **900**. In some examples, IMU **964** can include one or more accelerometers to detect linear acceleration and gyroscopes to detect rotational rate. In some examples, IMU **964** can include an accelerometer and gyroscope for each of the principal axes: pitch, roll and yaw. In some examples, IMU **964** can transmit positional information to a processor within jewel **910** to enable the jewel to compute the orientation, position and movement of ring input device **900**. In other examples, one or more of these computations can be performed within IMU **964**.

(72) FIG. **9B** is a symbolic view of a user interface with icons **966** displayed on the touchscreen of

companion device **968** according to examples of the disclosure. In the example of FIG. **9B**, a touch input (explained hereinbelow) on rotating outer band **906** of a ring input device can be detected, and a signal can be wirelessly transmitted to companion device **968** to display a user interface and a cursor at initial position **970** (e.g., in the center of the user interface), or to display the cursor if the user interface was already being displayed. Thereafter, movement of ring input device **900** can be detected, and the cursor can move on the user interface in accordance with the detected movements of the ring. In the example of FIG. **9B**, the cursor has moved to present location **972**. In some examples, a press input (explained hereinbelow) can select the icon appearing under the cursor. In other examples, LRA **962** can generate haptic feedback as the cursor moves over an icon, providing additional advantageous feedback to the user. It should be understood that the example of FIG. **9B** is only one example of how IMU **964** can be utilized along with movements of ring input device **900** to initiate and/or perform operations on a companion device.

(73) When IMU **964** in ring input device **900** is used to control an object such as a 3D object being displayed, in some examples the virtual object can be rotated along all three axes (X, Y and Z). However, in other examples, one or two of the axes can be locked to limit the rotation of the object. For example, the Y axis can be locked such that movement of ring input device **900** can only cause rotations of the object about the X and/or Z axis. In some examples, moving a cursor over an axis, followed by a press input on outer band **906**, can cause that axis to be locked. Locking an axis can eliminate unintended motion and enable more precise movements to be detected by ring input device **900**.

(74) In addition to detecting the position of ring input device **900** or detecting the rotational position of outer ring **906** with or without modulated resistance as described above, detecting presses on rotating outer band **906** can provide additional advantages. For example, after outer band **906** is rotated to a desired position, one or more detected presses on the band can initiate further action, such as selection of an item. Even in the absence of rotation, a press on rotating outer band **906** can initiate operations, such as triggering a left mouse click input (single click) or a right mouse click input (double click), moving in discrete steps through a list, moving through a document using page view, jumping to different items or icons, incrementing or decrementing a parameter, or terminating an operation. A press and hold input, or a press and rotate input, can also be detected to perform or initiate other operations. It should be understood that the preceding description of uses is non-limiting and merely illustrative, and that detecting presses on rotating outer band **906** is contemplated for other purposes as well.

(75) FIG. **10A** is a side view of band mechanism **1002** of a ring input device including low friction contact points **1074** and button bearings **1076** according to examples of the disclosure. As defined herein, a button bearing is a mechanism that acts both as a button and also as a low-friction bearing. Low friction contact points **1074** and button bearings **1076** can allow outer band **1006** to rotate about stationary inner band **1004** with reduced friction. In some examples, both low friction contact points **1074** and button bearings **1076** can be ball bearings. In other examples, low friction contact points **1074** can be fixed contact points that extend along most or all of the width of stationary inner band **1004**, while button bearings **1076** can be ball bearings. In still other examples, low friction contact points **1074** can be fixed contact points, while button bearings **1076** can be pressure-sensitive input mechanisms such as dome switches or other types of switches or mechanisms capable of generating “open” and “closed” states. These pressure-sensitive input mechanisms can include resistive strain gauge sensors whose resistance changes with pressure, optical strain gauge sensors whose reflected light properties change with pressure, and more generally analog force sensors capable of generating analog output values in response to different levels of pressure. Other examples of pressure-sensitive input mechanisms can include capacitive force sensors, whose capacitance across two plates changes as pressure causes a deformable material between the two plates to compress and change the distance between the plates. Using pressure-sensitive input mechanisms for button bearings **1076** creates a multi-functional element,

where the pressure-sensitive input mechanisms serves as both a bearing for rotating outer band **1006** and also a mechanism for generating a press input.

(76) FIG. **10B** is an enlarged side view of a pressure-sensitive input mechanism in the form of dome switch button bearing **1076** as indicated by the dashed lines in FIG. **10A** according to examples of the disclosure. In some examples, dome switch button bearing **1076** can include a compressible dome (pointing downwards in the example of FIG. **10B**) made of a nonconductive material such as rubber or polyurethane that can compress under pressure but return to its original shape in the absence of pressure. Within compressible dome are one or more pairs of contacts that make electrical contact (e.g., short-circuit) when the dome is sufficiently compressed, but remain open in the absence of sufficient compression. Although two-stage dome switches (open or closed) are primarily disclosed herein, it should be understood that dome switches according to examples of the disclosure can include multiple-stage dome switches.

(77) Referring again to FIG. **10A**, pressure applied to rotating outer band **1006** at or near the locations of low friction contact points **1074** should result in little or no compression or movement when the contact points are formed as fixed contact points. Thus, fixed contact points can be used in locations where a press input is not expected, such as under the jewel. However, pressure applied to rotating outer band **1006** at or near the locations of dome switch button bearings **1076** can result in compression or movement of the dome switches, and possibly activation of the switches. The activation area of the dome switches can depend on the configuration of the dome switches (for example, the height of the dome, and/or the size and shape of the base upon which the dome sits), the gap between stationary inner band **1004** and rotating outer band **1006**, and the material of the inner band. In some examples, pressure applied within about 45 degrees on either side of the dome switches can still activate (i.e., close) the switches. Although two dome switch button bearings **1076** are shown in FIG. **10A**, in other examples only a single dome switch can be employed, or three or more dome switches can also be utilized. With two or more dome switches, different functions can be initiated depending on which dome switch is pressed, or the same function can be initiated regardless of which dome switch is pressed. In some examples, pressure applied between two adjacent dome switches can activate both switches, which can initiate other functions.

(78) As mentioned above, the activation area of the dome switches can vary. Variations in the activation area of a dome switch (and therefore the activation area of a button within the band mechanism of a ring input device) can provide a number of advantages. For example, a wide activation area can allow a user to activate a button without having to precisely know the location of that button within the rotating outer band. This can be especially useful when the user wants to press a button but is not looking at the ring. On the other hand, a narrow activation area can enable multiple buttons to be placed within the band mechanism, with each button capable of being activated independently. Narrow activation areas can also reduce inadvertent button presses.

(79) FIGS. **11A-11B** are simplified symbolic side views (not to scale) of rotating outer band **1106** and stationary inner band **1104**, with the inner bands having different levels of rigidity according to examples of the disclosure. FIG. **11A** is an example of a dome switch with a wide activation area, where stationary inner band **1104** can be formed from a material having high rigidity. When pressure is applied on rotating outer band **1106** at a location offset from dome switch button bearing **1176**, because neither the outer band nor stationary inner band **1104** experiences significant deformation, sufficient pressure can be applied against the dome switch to activate it. In some examples, pressure can be applied as much as 60 degrees or more on either side of dome switch button bearing **1176** to activate the switch.

(80) In contrast, FIG. **11B** is an example of a dome switch with a narrower activation area, where stationary inner band **1104** can be formed from a softer, more flexible material. When pressure is applied on rotating outer band **1106** at a location offset from dome switch button bearing **1176**, the outer band can contact the dome switch without activating it. As pressure on the dome switch continues (without sufficient pressure to activate the switch), stationary inner band **1104** can begin

to deform, and may continue to deform until it contacts rotating outer band **1106** at locations **1178**. At this point, further deformation of stationary inner band **1104** may cease, leaving dome switch button bearing **1176** without sufficient pressure to activate it. In the example of FIG. **11B**, activation may occur only when the pressure is applied close enough to dome switch button bearing **1176** such that the switch is activated before deformed stationary inner band **1104** makes contact with rotating outer band **1106**. In some examples, pressure can be applied no further than about 5 degrees on either side of dome switch button bearing **1176** before inner band **1104** contacts outer band **1106** and prevents activation of the switch.

(81) FIG. **11C** is a simplified symbolic side view (not to scale) of rotating outer band **1106** and stationary inner band **1104**, with the inner bands having stoppers **1180** on either side of dome switch button bearing **1176** according to examples of the disclosure. In the example of FIG. **11C**, stoppers **1180** are utilized to narrow the activation area of dome switch button bearing **1176**. Stoppers **1180** can be button bearings or fixed contact points that allow for direct pressure on dome switch button bearing **1176** to activate the switch, but also limit the radial travel of rotating outer band **1106** to prevent it from activating the switch when pressure is applied at a location offset from that of the switch. When pressure is initially applied on rotating outer band **1106** at a location offset from dome switch button bearing **1176**, the outer band may contact the dome switch without activating it. As pressure on the dome switch continues (without sufficient pressure to activate the switch), rotating outer band **1106** can come into contact with stopper **1180**. At this point, further pressure on dome switch button bearing **1176** may cease, leaving the switch without sufficient pressure to activate it. In the example of FIG. **11C**, activation may occur only when the pressure is applied close enough to dome switch button bearing **1176** such that the switch is activated before stopper **1180** makes contact with rotating outer band **1106**.

(82) In addition to detecting presses on outer band **1106** as described above, detecting touches on the outer band can provide additional advantages. For example, touch sensing can help distinguish a valid press input (e.g., caused by a user's finger) from an inadvertent press input (e.g., accidentally pressing outer band **1106** against a desk or other ungrounded object). In another example, after outer band **1106** is rotated to a desired position, one or more detected touches or taps on the band (without detected presses) can initiate further actions. Even in the absence of rotation, one or more detected touches or taps on outer band **1106** can initiate operations, such as bringing up a user interface, or "peeking" to temporarily view content. A touch-and-hold input, or a touch-and-rotate input (as opposed to a swipe-to-rotate input), can also be detected to perform or initiate other operations. It should be understood that the preceding description of uses is non-limiting and merely illustrative, and that detecting touches on rotating outer band **1106** is contemplated for other purposes as well.

(83) FIG. **12A** is a symbolic side view of a portion of band mechanism **1202** including stationary inner band **1204** and rotating outer band **1206** with sliding contacts **1282** to provide touch sensing according to examples of the disclosure. In some examples, touch sensing can be accomplished by utilizing the entire conductive outer band **1206** as a self-capacitance touch electrode, where the electrode's self-capacitance to ground can be measured, and changes to this self-capacitance can be detected and recognized as being the result of a touch. In the example of FIG. **12A**, sliding contacts **1282** can be affixed to stationary inner band **1204** and can make electrical contact with outer band **1206** (acting as a self-capacitance electrode) when the outer band is stationary, and can continue to maintain sliding contact with the outer band when it rotates, providing an electrical connection from outer band **1206** to inner band **1204**. Although FIG. **12A** shows two sliding contacts **1282**, in other examples only one sliding contact can be used, or more than two sliding contacts can be used. In addition, one or more ground contacts (not shown) on the interior of inner band **1204** can provide a reference ground for the ring input device, which can be coupled to earth ground when a user is wearing the ring and making contact with the ground contacts. With the electrical connections to the self-capacitance electrode and reference ground available at inner band **1204**, the

self-capacitance of outer band **1206** can be measured and touches can be detected.

(84) FIG. **12B** is a perspective view of stationary inner band **1204** showing leaf spring sliding contact **1282** on stationary inner band **1204** according to examples of the disclosure. In the example of FIG. **12B**, leaf spring sliding contact **1282** is oriented perpendicular to the direction of rotation of the outer band (not shown in FIG. **12B**). Although FIG. **12B** illustrates sliding contact **1282** as a leaf spring, in other examples different types of sliding contacts can be utilized, including brushes, fixed or rotating conductive bearings, and the like. In addition, in other examples the orientation of the sliding contact can be parallel to the direction of rotation of the outer band. In further examples, outer band **1206** can be formed from two parallel conductive (but isolated) circumferential strips, sliding contact **1282** can be formed as two isolated contacts oriented in parallel to the direction of rotation of the outer band for separately contacting the circumferential strips, and mutual capacitance sensing can be performed between the two circumferential strips.

(85) FIG. **13A** is a symbolic side view of a section of band mechanism **1302** showing button bearing **1376** affixed to inner band **1304**, where the button bearing can also serve as a sliding contact according to examples of the disclosure. In the example of FIG. **13A**, instead of utilizing a separate sliding contact to provide electrical contact with outer band **1306**, conductive surface **1384** can be added to the previously described dome switch button bearing **1376** to provide the sliding contact.

(86) Dome switch button bearing **1376** can include a nonconductive (e.g., rubber) dome, and button trace **1386** can be connected to a switch or bipolar mechanism in the dome switch (represented symbolically as a single pole, single throw switch in FIG. **13A**). However, in the example of FIG. **13A**, conductive surface **1384** can be added to the nonconductive dome, and touch trace **1388** can be connected to the conductive surface. In addition, ground contact **1390** on the interior of inner band **1304** can provide a reference ground for the ring input device, which can be coupled to earth ground when a user is wearing the ring and making contact with the ground contacts. In some examples, the “throw” contact of the switch mechanism can also be connected to ground contact **1390**. With button trace **1386**, touch trace **1388** and ground contact **1390** available at inner band **1304**, both a press of dome switch button bearing **1376** and a touch anywhere along outer band **1306** can be detected. Thus, dome switch button bearing **1376** can serve three functions: it can act as a bearing between inner band **1304** and outer band **1306**, it can provide touch trace **1388** for touch sensing, and it can provide button trace **1386** for press input sensing.

(87) FIG. **13B** is a symbolic side view of a section of band mechanism **1302** showing dome switch button bearing **1376** affixed to inner band **1304**, where the button bearing can also serve as a sliding contact with a reduced number of traces according to examples of the disclosure. The example of FIG. **13B** is similar to FIG. **13A**, except that button trace **1386** and touch trace **1388** can be electrically coupled together and brought out of button bearing **1376** as a single dual-function trace **1392**. This reduction of a trace can advantageously reduce the number of conductive lines, contacts, pads and pins needed to route the trace to the jewel of the ring input device, reduce cost, save space, and increase reliability. This reduction of a trace is possible because dual-function trace **1392** (which connects together button trace **1386** and touch trace **1388**) can be utilized for different purposes at different times. As shown in FIG. **13B**, when dome switch button bearing **1376** is not activated (i.e., the switch is open), dual-function trace **1392** is connected only to outer band **1306** via conductive surface **1384**, and the trace can be used to read the self-capacitance on the conductive surface (i.e., detect a touch) in the usual manner. When sufficient pressure has been applied to activate dome switch button bearing **1376** (i.e., the switch is closed), the closed switch can force trace **1392** to a fixed potential (e.g., ground **1390**), which can indicate that a valid press input has been received. At this point, because trace **1392** is held at a fixed potential, it can no longer be used to detect a touch. However, because a valid press input implies a touch, touch detection is no longer needed, and the fixed potential on trace **1392** can be interpreted as a valid touch.

(88) FIG. 13C is a symbolic side view of a section of band mechanism 1302 showing sliding contact 1382 and button bearing 1376 affixed to inner band 1304 with a reduced number of traces according to examples of the disclosure. The example of FIG. 13C is similar to FIG. 13B, except that instead of a conductive surface of dome switch button bearing 1376 providing electrical contact with conductive outer band 1306, a single sliding contact 1382 (discussed above) is used for that purpose. Nevertheless, button trace 1386 and touch trace 1388 can be electrically coupled together and brought out of button bearing 1376 as a single dual-function trace 1392. As with the examples of FIG. 13B, this reduction of a trace provides advantages and is possible because dual-function trace 1392 (which connects together button trace 1386 and touch trace 1388) can be utilized for different purposes at different times. As shown in FIG. 13B, when dome switch button bearing 1376 is not activated (i.e., the switch is open), dual-function trace 1392 is connected only to outer band 1306 via sliding contact 1382, and the trace can be used to read the self-capacitance on the conductive surface (i.e., detect a touch) in the usual manner. When sufficient pressure has been applied to activate dome switch button bearing 1376 (i.e., the switch is closed), the closed switch can force dual-function trace 1392 to a fixed potential (e.g., ground 1390), which can indicate that a valid press input has been received. At this point, because dual-function trace 1392 is held at a fixed potential it can no longer be used to detect a touch. However, because a valid press input implies a touch, touch detection is no longer needed, and the fixed potential on dual-function trace 1392 can be interpreted as a valid touch.

(89) FIG. 13D is flowchart of a method for detecting a valid touch or press input on a ring input device according to examples of the disclosure. In the example of FIG. 13D, at 1394 it can be determined whether outer band 1306 is being held at a fixed potential (e.g., ground), indicating that the dome switch has been activated (i.e., the dome switch is closed). When it is determined that outer band 1306 is not being held at a fixed potential (i.e., the dome switch is open), then at 1396 the self-capacitance of outer band 1306 can be determined. At 1398 it can be determined whether the self-capacitance is greater than a predetermined threshold (indicative of valid a touch from a grounded object such as a finger). When the self-capacitance is greater than the predetermined threshold, then at 1399 it can be determined that a valid touch input without a valid press input has been received, and thereafter the method can be re-initiated at 1394. When the self-capacitance is not greater than the predetermined threshold, then at 1397 it can be determined that no valid touch input and no valid press input has been received, and the method can thereafter be re-initiated at 1394. The predetermined threshold can be selected such that unintended touches of ungrounded or poorly grounded objects against outer band 1306 (e.g., hitting outer band 1306 against a table) should not increase the self-capacitance of outer band 1306 above the predetermined threshold and cause a valid touch input to be recognized.

(90) At 1394, a determination that outer band 1306 is being held at a fixed potential does not necessarily mean that a valid press input has been received, because an accidental press input can also activate (close) dome switch button bearing 1376 and force outer band 1306 to the fixed reference potential (e.g., ground). However, as mentioned above, touch sensing can help distinguish a valid press input (e.g., caused by a user's finger) from an inadvertent press input (e.g., caused by accidentally pressing outer band 1306 against an ungrounded object such as a desk). Because a valid touch input should always precede a valid press input, to disambiguate a valid press input from an inadvertent press input, when outer band 1306 is determined to be held at a fixed potential at 1394, then at 1395 a further determination can be made as to whether the self-capacitance of outer band 1306 was greater than the predetermined threshold (indicative of a valid touch input) just prior to the determination that the outer band was driven to a fixed potential. In some examples, this can be accomplished by saving the determined state of outer band at periodic intervals (e.g., 100 millisecond intervals). A valid press input (e.g., caused by a user's finger) will produce a sequence of valid touch input readings (i.e., self-capacitance levels above the predetermined threshold) prior to a fixed potential reading. An invalid press input (e.g., caused by

an ungrounded or poorly grounded object) will produce a sequence of invalid touch input readings (i.e., self-capacitance levels below the predetermined threshold) prior to a fixed potential reading. When the valid press input sequence is captured, then at **1391** it can be concluded that a valid press input has been received, and the method can thereafter be re-initiated at **1394**. On the other hand, when the invalid press input sequence is captured, then at **1393** it can be concluded that a valid press input has not been received (e.g., only a press input from a nonconductive object was received), and the method can thereafter be re-initiated at **1394**.

(91) FIG. **13E** is a symbolic side view of a section of band mechanism **1302** showing two dome switch button bearings **1376** affixed to inner band **1304**, where the button bearings can serve as sliding contacts with a reduced number of traces according to examples of the disclosure. In the example of FIG. **13E**, the button traces **1386** and touch traces **1388** of both dome switch button bearings **1376** are all electrically connected together and brought out as a single trace **1392**. This reduction of three traces can advantageously reduce the number of conductive lines, contacts, pads and pins needed to route the trace to the jewel of the ring input device, reduce cost, save space, and increase reliability. This reduction of traces is possible because trace **1392** can be utilized for different purposes at different times. As shown in FIG. **13E**, when both dome switch button bearings **1376** are not activated (i.e., the switches are open), trace **1392** is connected only to outer band **1306** via the touch traces **1388** and conductive surfaces **1384** of both dome switches, and trace **1392** can be used to read the self-capacitance on outer band **1306** (i.e., detect a touch) in the usual manner. When sufficient pressure has been applied to activate the center dome switch button bearing **1376** in FIG. **13E** (i.e., the switch is closed), the closed switch can force trace **1392** to a first fixed potential (e.g., ground **1390**), which can indicate that a valid press input has been received at the center dome switch. On the other hand, when sufficient pressure has been applied to activate the left dome switch button bearing **1376** in FIG. **13E** (i.e., the switch is closed), the closed switch can force trace **1392** to a second fixed potential (e.g., Vcc **1389**), which can indicate that a valid press input has been received at the left dome switch. Thus, the voltage level of the fixed potential at trace **1392** can determine which dome switch button bearing **1376** is being pressed. In either situation, because trace **1392** is held at a fixed potential when either of the two dome switch button bearings **1376** is pressed, it can no longer be used to detect a touch. However, because a valid press input implies a touch, touch detection is no longer needed, and the fixed potential on trace **1392** can be assumed to be a valid touch. It should be understood that in the example of FIG. **13E**, the two dome switch button bearings **1376** should not be activated at the same time, otherwise a short circuit between Vcc and ground, for example, could occur.

(92) FIG. **14A** is a system block diagram of electronic jewel system **1410** of a ring input device including scroll ball **1489** and touch sensor **1487** according to examples of the disclosure. The example of FIG. **14A** is similar to the system of FIG. **2**, except that it includes scroll ball **1489** and touch sensor **1487**. In some examples, touch sensor **1487** can be an optical sensor, but other examples it can be a capacitive touch sensor, a resistive touch sensor, an ultrasonic touch sensor, and the like. In some examples, either scroll ball **1489** or touch sensor **1487** can be included in electronic jewel system **1410**, but not both. In other examples, both scroll ball **1489** and touch sensor **1487** can be employed. Although the dashed lines of scroll ball **1489** and touch sensor **1487** indicate their optional nature, it should be understood that dashed and solid lines throughout the drawings are not intended to conclusively convey optional or required features. For example, IMU **1426**, magnetometer **1428**, haptics generator **1430**, scroll ball **1489** and touch sensor **1487** in FIG. **14A** can all be utilized or omitted in any number of combinations and permutations, as evidenced by the use of the word “example” or “examples” throughout the disclosure to ensure that no figure or description is interpreted as a requirement.

(93) FIG. **14B** is a symbolic perspective view of ring input device **1400** including electronic jewel system **1410** with scroll ball **1489** and touch sensor **1487** according to examples of the disclosure. As discussed above, in some examples electronic jewel system **1410** can include scroll ball **1489**.

Scroll ball **1489** can be used as an alternative to rotating outer band **1406** or in addition to the rotating outer band to provide directional input in two dimensions. Although not shown in FIG. **14B**, in some examples scroll ball **1489** can also include a tactile switch to detect a press input on the scroll ball. The tactile switch can be used as an alternative to, or in addition to a press input on rotating outer band. Scroll ball **1489** can enable a user to provide directional input in two dimensions to perform operations such as moving a cursor, scrolling through a list, panning an image, and the like. The tactile switch can be used for selecting an item, performing a mouse click, moving or taking discrete steps or increments, and the like. Similar operations can be performed by touch sensor **1487**, which in some examples can also include a tactile switch (not shown).

(94) In some examples, inputs from scroll ball **1489** and/or touch sensor **1487** can be utilized in combination with inputs from one or more other devices such as rotating outer band **1406** (and press inputs detectable thereon), IMU **1464** and/or magnetometer **1428** to generate different types of gesture inputs to perform or initiate different operations. To provide just one example (of many possible examples) for purposes of illustration only, two-dimensional movement on scroll ball **1489** can be detected along with up-and-down movement of ring input device **1400** (from IMU **1426**) to move an object in three dimensions in a computer-generated environment.

(95) As described above, the ring input device according to the examples of the disclosure can include a band mechanism having a stationary inner band and a rotating outer band. In some examples of the disclosure, the rotating outer band can be made out of a conductive material such as steel. The other parts of the band mechanism can be made of metal, ceramic, leather, fabric and the like to provide fashion choices. The band mechanism can be wide or narrow.

(96) As described above, the rotating outer band can produce variable rotational resistance, sense the rotational position of the outer band, detect the orientation and movement of the ring itself, provide haptic feedback whether the outer band is rotating or stationary, and can provide press and touch input sensing. The ring input device can be used to provide inputs to companion wearable devices such as smart watches, health monitoring devices, headphones and ear buds, provide inputs to handheld devices such as smartphones, tablet and laptop computing devices, media players, styluses, wands or gloves for computer-generated environments, and provide inputs to stationary devices such as desktop computers, smart home control and entertainment devices. In some examples, the ring input device can receive input from a companion device and provide information to the wearer of the ring (e.g., alerts).

(97) Because of its touch and press input capabilities, the outer band can be susceptible to inadvertent touch or press inputs from a wearer's other fingers. For example, if the ring input device is worn on the ring or middle finger, fingers on either side of the ring can accidentally generate touch or press inputs on either side of the ring, whereas if the ring is worn on the index finger, only the middle finger can accidentally generate touch or press inputs on one side of the ring. Accordingly, in some examples the ring portion can be protected by one or more guards to prevent adjacent fingers or other objects from generating accidental touches. In some examples, the ring input device can have a permanent guard and also locations for attachable (e.g., snap-fit) guards. These guards can be configurable to protect different areas of the outer band, depending on which finger the ring is being worn on.

(98) As described above, the ring input device according to examples of the disclosure can include a jewel that can contain most of the electronics of the ring. In some examples, the jewel can be removably connectable to the band mechanism using pogo pins or other electrical or magnetic connections. The jewel can be made or configured with different shapes, styles and/or colors to provide a fashion choice. The ability to attach different jewels to different band mechanisms can advantageously enable a single jewel design to work with different sizes of band mechanisms (for different finger sizes), to enable the replacement of one jewel with another, and to provide opportunities for mix-and-match fashion choices. In addition, the ability to attach different jewels can enable jewels with different capabilities to be connected to the band mechanism. For example,

different jewel designs can include different components for different sensing capabilities, larger or smaller batteries, different features, and different price points to enable a user to utilize a jewel most suited to the user's needs.

(99) In some examples, the removable jewel can advantageously allow the jewel to be removed and charged in a separate dock, charging pad, or by using a connector, while the band mechanism remains on the wearer's finger. In other example, the ring input device can be removed from the wearer and charged as a single unit. The closed loop configuration of the band mechanism of the ring input device can allow coils to be placed inside the band mechanism, and the ring can be slipped over a cylindrical post on a charging device for inductive charging.

(100) Although various examples and features of the ring input device may have been described above in different paragraphs and shown in different figures for convenience of explanation, it should be understood that different permutations and combinations of these features are contemplated in different examples of the disclosure.

(101) Therefore, according to the above, some examples of the disclosure are directed to a ring input device capable of detecting a press input, the ring input device comprising a band mechanism having an outer band and an inner band, a first pressure-sensitive input mechanism formed on the inner band and disposed between the inner band and the outer band, and an electronic jewel system communicatively couplable to the band mechanism, wherein the first pressure-sensitive input mechanism is configured for providing a first signal to the electronic jewel system for generating a first press input when the first pressure-sensitive input mechanism is activated. As an alternative to or in addition to one more of the examples disclosed above, in some examples the first pressure-sensitive input mechanism is configured to act as a bearing for the outer band in addition to generating the first press input. As an alternative to or in addition to one more of the examples disclosed above, in some examples the first pressure-sensitive input mechanism is configured to be activated when pressure within a first activation area on the outer band is received. As an alternative to or in addition to one more of the examples disclosed above, in some examples a material of the inner band, at least around the first pressure-sensitive input mechanism, is selected with a particular rigidity to provide the first activation area on the outer band of about 60 degrees on either side of the first pressure-sensitive input mechanism. As an alternative to or in addition to one more of the examples disclosed above, in some examples the first pressure-sensitive input mechanism is a button bearing. As an alternative to or in addition to one more of the examples disclosed above, in some examples the button bearing is a dome switch. As an alternative to or in addition to one more of the examples disclosed above, in some examples a material of the inner band, at least around the first pressure-sensitive input mechanism, is selected with a particular rigidity such that pressure on the outer band at a location offset from the first pressure-sensitive input mechanism causes the inner band to deform and contact the outer band prior to activation of the first pressure-sensitive input mechanism. As an alternative to or in addition to one more of the examples disclosed above, in some examples a material of the inner band, at least around the first pressure-sensitive input mechanism, is selected with a particular rigidity to produce a particular activation area. As an alternative to or in addition to one more of the examples disclosed above, in some examples the ring input device further comprises a plurality of stoppers formed on the inner band on either side of the first pressure-sensing mechanism, the plurality of stoppers configured such that pressure on the outer band at a location offset from the first pressure-sensitive input mechanism causes the outer band to contact one of the stoppers prior to activation of the first pressure-sensitive input mechanism. As an alternative to or in addition to one more of the examples disclosed above, in some examples the ring input device further comprises one or more contact points formed on the inner band and disposed between the inner band and the outer band, the one or more contact points located at areas of the band mechanism insensitive to pressure on the outer band. As an alternative to or in addition to one more of the examples disclosed above, in some examples the ring input device further comprises a second pressure-sensitive input mechanism

formed on the inner band and disposed between the inner band and the outer band, wherein the second pressure-sensitive input mechanism is configured for providing a second signal to the electronic jewel system for generating a second press input when the second pressure-sensitive input mechanisms is activated. As an alternative to or in addition to one more of the examples disclosed above, in some examples the outer band is configured to rotate with respect to the inner band, the electronic jewel system is configured for computing a rotational position of the outer band, and the electronic jewel system is configured for initiating an operation based on the first press input and the rotational position of the outer band.

(102) Some examples of the disclosure are directed to a method for detecting a press input on a ring input device, comprising providing a first bearing between an outer band and an inner band of the ring input device for enabling rotation of the outer band with respect to the inner band, and generating a first press input when a first pressure applied on the outer band at the first bearing causes a first pressure threshold at the first bearing to be exceeded. As an alternative to or in addition to one or more of the examples disclosed above, in some examples of the disclosure the method further comprises providing a first activation area on the outer band, wherein the application of the first pressure within the first activation area causes the first pressure threshold at the first bearing to be exceeded, and wherein the application of the first pressure outside the first activation area prevents the first pressure threshold at the first bearing from being exceeded. As an alternative to or in addition to one or more of the examples disclosed above, in some examples of the disclosure the method further comprises selecting a material of the inner band, at least around the first bearing, to have a particular rigidity to provide the first activation area on the outer band of about 60 degrees on either side of the first bearing. As an alternative to or in addition to one or more of the examples disclosed above, in some examples of the disclosure the method further comprises selecting a material of the inner band, at least around the first bearing, to have a particular flexibility such that pressure on the outer band at a location offset from the first bearing causes the inner band to deform and contact the outer band prior to the first pressure threshold at the first bearing being exceeded. As an alternative to or in addition to one or more of the examples disclosed above, in some examples of the disclosure the method further comprises selecting a material of the inner band, at least around the first bearing, with a particular rigidity to produce a particular activation area. As an alternative to or in addition to one or more of the examples disclosed above, in some examples of the disclosure the method further comprises physically stopping the outer band from activating the first bearing when pressure on the outer band is applied at a location offset from the first bearing.

(103) Some examples of the disclosure are directed to a ring input device capable of detecting a press input, comprising bearing means disposed between an outer band and an inner band of the ring input device for enabling rotation of the outer band with respect to the inner band, means for detecting an application of a first pressure on the outer band at the first bearing, and means for generating a first press input when the first pressure exceeds a first pressure threshold at the first bearing. As an alternative to or in addition to one more of the examples disclosed above, in some examples the ring input device further comprising means for physically stopping the outer band from activating the first bearing when pressure on the outer band is applied at a location offset from the first bearing.

(104) Some examples of the disclosure are directed to a ring input device capable of detecting a touch input, the ring input device comprising a band mechanism having a conductive outer band and an inner band, the conductive outer band configured for rotating with respect to the inner band, a first sliding contact formed on the inner band and configured to be in sliding contact with the conductive outer band, and an electronic jewel system communicatively couplable to the band mechanism, wherein the first sliding contact is configured for providing a first touch signal to the electronic jewel system for detecting a first touch input when the conductive outer band is touched. As an alternative to or in addition to one more of the examples disclosed above, in some examples

the electronic jewel system is configured for receiving the first touch signal and determining a self-capacitance of the conductive outer band to detect the first touch input. As an alternative to or in addition to one more of the examples disclosed above, in some examples the first sliding contact is a first leaf spring. As an alternative to or in addition to one more of the examples disclosed above, in some examples the first sliding contact is a first button bearing having a first conductive surface configured to be in sliding contact with the conductive outer band. As an alternative to or in addition to one more of the examples disclosed above, in some examples the first sliding contact is a first dome switch having a first conductive surface configured to be in sliding contact with the conductive outer band. As an alternative to or in addition to one more of the examples disclosed above, in some examples the first dome switch comprises a first dome upon which the first conductive surface is formed, the first conductive surface connected to a first touch trace, and a first switch mechanism configured for being activated when sufficient pressure is applied to the first dome, the first switch mechanism connected to a first button trace. As an alternative to or in addition to one more of the examples disclosed above, in some examples the electronic jewel system is configured for receiving the first touch trace to detect a first touch input, and receiving the first button trace to detect a first press input. As an alternative to or in addition to one more of the examples disclosed above, in some examples the first touch trace and the first button trace are connected together to form a first dual-function trace, and wherein the electronic jewel system is configured for using the first dual-function trace to detect a first touch input and a first press input. As an alternative to or in addition to one more of the examples disclosed above, in some examples the electronic jewel system is further configured for determining from the first dual-function trace whether the conductive outer band is being held at a fixed potential, in accordance with a determination that the conductive outer band is not being held at the fixed potential, determining from the dual-function trace a self-capacitance of the conductive outer band, in accordance with a determination that the self-capacitance of the conductive outer band is greater than a predetermined threshold, determining that a valid touch input and no valid press input have been received, and in accordance with a determination that the self-capacitance of the conductive outer band is less than or equal to the predetermined threshold, determining that no valid touch input and no valid press input have been received. As an alternative to or in addition to one more of the examples disclosed above, in some examples the electronic jewel system is further configured for, in accordance with a determination that the conductive outer band is being held at the fixed potential, determining whether a valid press input sequence has been received, in accordance with a determination that a valid press input sequence has been received, determining that a valid press input has been received, and in accordance with a determination that a valid press input sequence has not been received, determining that no valid press input has been received. As an alternative to or in addition to one more of the examples disclosed above, in some examples the ring input device further comprises a second sliding contact formed on the inner band and configured to be in sliding contact with the conductive outer band, wherein the second sliding contact is configured for providing a second touch signal to the electronic jewel system for detecting the first touch input when the conductive outer band is touched. As an alternative to or in addition to one more of the examples disclosed above, in some examples the second sliding contact is a second dome switch having a second conductive surface configured to be in sliding contact with the conductive outer band. As an alternative to or in addition to one more of the examples disclosed above, in some examples the second dome switch comprises a second dome upon which the second conductive surface is formed, the second conductive surface connected to a second touch trace, and a second switch mechanism configured for being activated when sufficient pressure is applied to the second dome, the second switch mechanism connected to a second button trace. As an alternative to or in addition to one more of the examples disclosed above, in some examples the electronic jewel system is configured for receiving the second touch trace to detect the first touch input, and receiving the second button trace to detect a second press input. As an alternative to or in addition to one more of

the examples disclosed above, in some examples the second touch trace and the second button trace are connected together to form a second dual-function trace, and the electronic jewel system is configured for using the second dual-function trace to detect the first touch input or a second press input.

(105) Some examples of the disclosure are directed to a method for detecting a touch input on a ring input device, comprising providing a first contact between an inner band and a conductive outer band of the ring input device that maintains sliding electrical contact with the conductive outer band as the outer band rotates with respect to the inner band, and generating a first touch signal on the first contact for detecting a first touch input when the conductive outer band is touched. As an alternative to or in addition to one or more of the examples disclosed above, in some examples of the disclosure the method further comprises using the first contact as a first bearing between the outer band and the inner band in addition to generating the first touch signal. As an alternative to or in addition to one or more of the examples disclosed above, in some examples of the disclosure the method further comprises receiving a first touch trace from the first bearing to provide the first touch signal for detecting the first touch input, and receiving a first button trace from the first bearing for detecting a first press input. As an alternative to or in addition to one or more of the examples disclosed above, in some examples of the disclosure the method further comprises connecting the first touch trace and the first button trace together to form a first dual-function trace, and using the first dual-function trace to detect a first touch input and a first press input. As an alternative to or in addition to one or more of the examples disclosed above, in some examples of the disclosure the method further comprises determining from the first dual-function trace whether the conductive outer band is being held at a fixed potential, in accordance with a determination that the conductive outer band is not being held at the fixed potential, determining from the dual-function trace a self-capacitance of the conductive outer band, in accordance with a determination that the self-capacitance of the conductive outer band is greater than a predetermined threshold, determining that a valid touch input and no valid press input have been received, and in accordance with a determination that the self-capacitance of the conductive outer band is less than or equal to the predetermined threshold, determining that no valid touch input and no valid press input have been received.

(106) Some examples of the disclosure are directed to a ring input device capable of providing and controlling rotational input, the ring input device comprising a band mechanism having an outer band and an inner band, the outer band capable of rotating with respect to the inner band, a first variable resistance generator formed on one or both of the inner band and the outer band, and an electronic jewel system communicatively couplable to the band mechanism, wherein the electronic jewel system is configured for controlling the first variable resistance generator to modulate a rotational resistance of the outer band with respect to the inner band in accordance with an item being manipulated. As an alternative to or in addition to one more of the examples disclosed above, in some examples the electronic jewel system is further configured to modulate the rotational resistance to produce a feeling of detents in the rotating outer band. As an alternative to or in addition to one more of the examples disclosed above, in some examples the electronic jewel system is further configured for controlling the first variable resistance generator to prevent rotation of the outer band. As an alternative to or in addition to one more of the examples disclosed above, in some examples the electronic jewel system is further configured for controlling the first variable resistance generator to increase the rotational resistance of the outer band at a beginning or an end of a rotational input. As an alternative to or in addition to one more of the examples disclosed above, in some examples the first variable resistance generator is one of an electroactive polymer, a shape memory alloy, an air bladder, and magnetorheological fluid. As an alternative to or in addition to one more of the examples disclosed above, in some examples the item is a parameter. As an alternative to or in addition to one more of the examples disclosed above, in some examples the item is a user interface (UI). As an alternative to or in addition to one more of the

examples disclosed above, in some examples the first variable resistance generator is affixed to the outer band and applies the modulated rotational resistance against the inner band. As an alternative to or in addition to one more of the examples disclosed above, in some examples the inner band and outer band are arranged as concentric bands, and the ring input device further comprises a second variable resistance generator disposed between the inner band and the outer band and located on an opposite side of the ring input device in relation to the first variable resistance generator, wherein the electronic jewel system is further configured for controlling the first variable resistance generator and the second variable resistance generator to apply complementary opposing forces within the ring input device. As an alternative to or in addition to one more of the examples disclosed above, in some examples the inner band and outer band are arranged as eccentric bands. As an alternative to or in addition to one more of the examples disclosed above, in some examples the first variable resistance generator is an electromagnetic rotational resistance generator having an array of coils formed on the inner band and an array of magnetic poles formed on the outer band. As an alternative to or in addition to one more of the examples disclosed above, in some examples the electromagnetic rotational resistance generator is affixed to a brake that applies frictional resistance to the outer band when magnetically influenced by the electromagnetic rotational resistance generator. As an alternative to or in addition to one more of the examples disclosed above, in some examples the inner band having a side rail for retaining the outer band and the outer band having a side wall adjacent to the side rail, wherein the first variable resistance generator is formed on the side rail of the inner band, and wherein the electronic jewel system is configured for controlling the first variable resistance generator to modulate the rotational resistance of the side rail of the inner band with respect to the side wall of the outer band.

(107) Some examples of the disclosure are directed to a method of controlling rotational input on a ring input device, comprising providing a first variable resistance between an inner band and a rotating outer band of the ring input device, and controlling the first variable resistance to modulate a rotational resistance of the outer band with respect to the inner band in accordance with an item being manipulated. As an alternative to or in addition to one more of the examples disclosed above, in some examples the method further comprises modulating the rotational resistance to produce a feeling of detents in the rotating outer band. As an alternative to or in addition to one more of the examples disclosed above, in some examples the method further comprises modulating the rotational resistance to prevent rotation of the outer band. As an alternative to or in addition to one more of the examples disclosed above, in some examples the method further comprises modulating the rotational resistance to increase the rotational resistance of the outer band at a beginning or an end of a rotational input. As an alternative to or in addition to one more of the examples disclosed above, in some examples the item is a parameter. As an alternative to or in addition to one more of the examples disclosed above, in some examples the item is a user interface (UI). As an alternative to or in addition to one more of the examples disclosed above, in some examples the first variable resistance is an electromagnetic rotational resistance.

(108) Some examples of the disclosure are directed to a ring input device for generating ring positional information, the ring input device comprising a band mechanism having an outer band and an inner band, the outer band configured for rotating with respect to the inner band, the outer band magnetized to form a single dipole, a magnetometer located proximate to the outer band, the magnetometer configured for measuring a magnetic field strength of the outer band along multiple axes, and an electronic system communicatively couplable to the band mechanism and the magnetometer, wherein the electronic system is configured for computing an absolute angle of rotational position of the outer band from the measured magnetic field strength along the multiple axes. As an alternative to or in addition to one more of the examples disclosed above, in some examples the magnetometer is further configured for capturing multiple measurements of the magnetic field strength of the outer band along the multiple axes over time, and the electronic system further configured for computing an amount and direction of rotation of the outer based

from the multiple captured magnetic field strength measurements. As an alternative to or in addition to one more of the examples disclosed above, in some examples the magnetometer is further configured for capturing multiple measurements of the magnetic field strength of the outer band along the multiple axes over time, and the electronic system further configured for computing a velocity of rotation of the outer based from the multiple magnetic field strength measurements. As an alternative to or in addition to one more of the examples disclosed above, in some examples the electronic system further configured for calibrating the computed absolute angle of rotational position of the outer band by applying a predetermined offset value to the computed absolute angle of rotational position. As an alternative to or in addition to one more of the examples disclosed above, in some examples the ring input device further comprises a lookup table containing the predetermined offset value for a plurality of computed absolute angles of rotational position. As an alternative to or in addition to one more of the examples disclosed above, in some examples the magnetometer further configured for measuring the magnetic field strength along a Y axis (Y) and measuring the magnetic field strength along a Z axis (Z), the electronic system further configured for computing the absolute angle of rotational position of the outer band as $\theta = \arctan 2(Y, Z)$. As an alternative to or in addition to one more of the examples disclosed above, in some examples the outer band includes a plurality of evenly spaced physical indicators configured to be sensed by a user to provide a tactile confirmation of the amount and direction of rotation of the outer band. As an alternative to or in addition to one more of the examples disclosed above, in some examples the ring input device further comprises a haptic feedback device communicatively coupled to the electronic system and configured for generating haptic feedback each time the physical indicator is sensed during rotation. As an alternative to or in addition to one more of the examples disclosed above, in some examples the ring input device further comprises a haptic feedback device communicatively coupled to the electronic system and configured for generating haptic feedback each time a particular amount of rotation of the outer band is detected. As an alternative to or in addition to one more of the examples disclosed above, in some examples the ring input device further comprises a inertial measurement unit (IMU) communicatively coupled to the electronic system and configured for generating positional information used to determine an orientation of the ring input device. As an alternative to or in addition to one more of the examples disclosed above, in some examples the electronic system is further configured for generating and wirelessly transmitting a cursor signal for manipulating a cursor based on the determined orientation of the ring input device.

(109) Some examples of the disclosure are directed to a method for determining positional information on a ring input device, comprising magnetizing an outer band of the ring input device to form a single dipole, measuring a magnetic field strength of the outer band rotating with respect to an inner band of the ring input device along multiple axes, and computing an absolute angle of rotational position of the outer band from the measured magnetic field strength along the multiple axes. As an alternative to or in addition to one more of the examples disclosed above, in some examples the method further comprises capturing multiple measurements of the magnetic field strength of the outer band along the multiple axes over time, and computing an amount and direction of rotation of the outer based from the multiple captured magnetic field strength measurements. As an alternative to or in addition to one more of the examples disclosed above, in some examples the method further comprises capturing multiple measurements of the magnetic field strength of the outer band along the multiple axes over time, and computing a velocity of rotation of the outer based from the multiple magnetic field strength measurements. As an alternative to or in addition to one more of the examples disclosed above, in some examples the method further comprises calibrating the computed absolute angle of rotational position of the outer band by applying a predetermined offset value to the computed absolute angle of rotational position. As an alternative to or in addition to one more of the examples disclosed above, in some examples the method further comprises measuring the magnetic field strength along a Y axis (Y)

and measuring the magnetic field strength along a Z axis (Z), and computing the absolute angle of rotational position of the outer band as $\theta = \arctan 2 (Y, Z)$. As an alternative to or in addition to one more of the examples disclosed above, in some examples the method further comprises providing a tactile confirmation of the amount and direction of rotation of the outer band. As an alternative to or in addition to one more of the examples disclosed above, in some examples the method further comprises generating haptic feedback each time a particular amount of rotation of the outer band is detected. As an alternative to or in addition to one more of the examples disclosed above, in some examples the method further comprises generating positional information used to determine an orientation of the ring input device. As an alternative to or in addition to one more of the examples disclosed above, in some examples the method further comprises generating and wirelessly transmitting a cursor signal for manipulating a cursor based on the determined orientation of the ring input device.

(110) Although the disclosed examples have been fully described with reference to the accompanying drawings, it is to be noted that various changes and modifications will become apparent to those skilled in the art. Such changes and modifications are to be understood as being included within the scope of the disclosed examples as defined by the appended claims.

Claims

1. A wearable ring input device configured for providing and controlling rotational input, comprising: a band mechanism having an outer band and an inner band, the outer band configured to rotate with respect to the inner band; a first variable resistance generator formed on one or both of the inner band and the outer band and at least partially disposed between the inner band and the outer band; and an electronic jewel system communicatively couplable to the band mechanism; wherein the electronic jewel system is configured for controlling the first variable resistance generator to modulate a rotational resistance of the outer band with respect to the inner band in accordance with an item being manipulated.
2. The wearable ring input device of claim 1, the electronic jewel system further configured to modulate the rotational resistance to produce a feeling of detents in rotation of the outer band.
3. The ring wearable input device of claim 1, the electronic jewel system further configured for controlling the first variable resistance generator to prevent rotation of the outer band.
4. The wearable ring input device of claim 1, the electronic jewel system further configured for controlling the first variable resistance generator to increase the rotational resistance of the outer band at a beginning or an end of a rotational input.
5. The wearable ring input device of claim 1, wherein the first variable resistance generator is one of an electroactive polymer, a shape memory alloy, an air bladder, and magnetorheological fluid.
6. The wearable ring input device of claim 1, wherein the item is a parameter.
7. The wearable ring input device of claim 1, wherein the item is a user interface (UI).
8. The wearable ring input device of claim 1, wherein the first variable resistance generator is affixed to the outer band and applies the modulated rotational resistance against the inner band.
9. The wearable ring input device of claim 1, wherein the inner band and outer band are arranged as concentric bands, the ring input device further comprising: a second variable resistance generator disposed between the inner band and the outer band and located on an opposite side of the ring input device in relation to the first variable resistance generator; wherein the electronic jewel system is further configured for controlling the first variable resistance generator and the second variable resistance generator to apply complementary opposing forces within the ring input device.
10. The wearable ring input device of claim 1, wherein the inner band and outer band are arranged as eccentric bands.
11. The wearable ring input device of claim 1, wherein the first variable resistance generator is an electromagnetic rotational resistance generator having an array of coils formed on the inner band

and an array of magnetic poles formed on the outer band.

12. The wearable ring input device of claim 11, wherein the electromagnetic rotational resistance generator is affixed to a brake that applies frictional resistance to the outer band when magnetically influenced by the electromagnetic rotational resistance generator.

13. The wearable ring input device of claim 1, the inner band having a side rail for retaining the outer band and the outer band having a side wall adjacent to the side rail; wherein the first variable resistance generator is formed on the side rail of the inner band, and wherein the electronic jewel system is configured for controlling the first variable resistance generator to modulate the rotational resistance of the side rail of the inner band with respect to the side wall of the outer band.

14. The wearable ring input device of claim 1, wherein controlling the first variable resistance generator to modulate the rotational resistance of the outer band with respect to the inner band in accordance with the item being manipulated includes: controlling the first variable resistance to modulate the rotational resistance of the outer band with respect to the inner band to a first rotational resistance in accordance with the item being manipulated corresponding to a first item; and controlling the first variable resistance to modulate the rotational resistance of the outer band with respect to the inner band to a second rotational resistance, different than the first rotation resistance, in accordance with the item being manipulated corresponding to a second item, different than the first item.

15. A method of controlling rotational input on a wearable ring input device including a first variable resistance generator formed on one or both of an inner band and a rotating outer band and at least partially disposed between the inner band and the rotating outer band, comprising: providing, using the first variable resistance generator, a first variable resistance between the inner band and the rotating outer band of the wearable ring input device; and controlling the first variable resistance to modulate a rotational resistance of the outer band with respect to the inner band in accordance with an item being manipulated.

16. The method of claim 15, further comprising modulating the rotational resistance to produce a feeling of detents in the rotating outer band.

17. The method of claim 15, further comprising modulating the rotational resistance to prevent rotation of the outer band.

18. The method of claim 15, further comprising modulating the rotational resistance to increase the rotational resistance of the outer band at a beginning or an end of a rotational input.

19. The method of claim 15, wherein the item is a parameter.

20. The method of claim 15, wherein the item is a user interface (UI).
