

US Patent & Trademark Office

Patent Public Search | Text View

United States Patent	12402108
Kind Code	B2
Date of Patent	August 26, 2025
Inventor(s)	Yang; Lin et al.

60 GHz physical layer convergence protocol (PLCP) protocol data unit (PPDU) formats

Abstract

This disclosure provides methods, devices and systems for increasing carrier frequencies for wireless communications in wireless local area networks (WLANs). Some implementations more specifically relate to packet designs that support wireless communications on carrier frequencies above 7 GHz. In some aspects, a wireless communication device may map a physical layer convergence protocol (PLCP) protocol data unit (PPDU) to orthogonal subcarriers according to existing tone plans associated with carrier frequencies below 7 GHz and may up-clock the PPDU for transmission on carrier frequencies above 7 GHz (such as by increasing the frequency of a clock signal used to convert the PPDU between the frequency domain and the time domain). In some implementations, the PPDU may conform to an existing PPDU format designed for sub-7 GHz wireless communications. In some other implementations, the PPDU may conform to a “green field” PPDU format optimized for wireless communications on carrier frequencies above 7 GHz.

Inventors: Yang; Lin (San Diego, CA), Chen; Jialing Li (San Diego, CA), Tian; Bin (San Diego, CA), Kim; Youhan (Saratoga, CA)

Applicant: QUALCOMM Incorporated (San Diego, CA)

Family ID: 1000008782380

Assignee: QUALCOMM Incorporated (San Diego, CA)

Appl. No.: 17/828085

Filed: May 31, 2022

Prior Publication Data

Document Identifier	Publication Date
US 20230388986 A1	Nov. 30, 2023

Publication Classification

Int. Cl.: H04W72/0453 (20230101); H04L5/00 (20060101); H04L27/26 (20060101)

U.S. Cl.:

CPC H04W72/0453 (20130101); H04L5/0044 (20130101); H04L5/0078 (20130101); H04L27/2602 (20130101);

Field of Classification Search

CPC: H04W (72/0453); H04L (5/0044); H04L (5/0078); H04L (27/2602); H04L (27/26132); H04L (27/2644); H04L (27/2603); H04L (27/26025); H04B (7/0617)

References Cited

U.S. PATENT DOCUMENTS

Patent No.	Issued Date	Patentee Name	U.S. Cl.	CPC
9451590	12/2015	Sampath et al.	N/A	N/A
2014/0307650	12/2013	Vermani	370/329	H04L 27/2613
2016/0173662	12/2015	Seok	370/252	H04L 1/1896
2017/0127440	12/2016	Chun	N/A	H04W 56/005
2017/0272976	12/2016	Yang	N/A	H04L 27/2613
2018/0007661	12/2017	Chun et al.	N/A	N/A
2019/0158333	12/2018	Zhang	N/A	H04L 27/26025
2019/0208463	12/2018	Lou	N/A	H04W 72/27
2019/0289612	12/2018	Chen	N/A	H04L 27/2613
2021/0385115	12/2020	Cao	N/A	H04L 69/22
2022/0159555	12/2021	Cariou et al.	N/A	N/A
2023/0119491	12/2022	Liu	370/330	H04L 27/2613
2023/0141111	12/2022	Ciochina	375/267	H04B 7/0626
2023/0284195	12/2022	Hu	370/329	H04L 27/26025
2024/0179737	12/2023	Tsai	N/A	H04L 27/0006

OTHER PUBLICATIONS

Partial International Search Report—PCT/US2023/066891—ISA/EPO—Aug. 18, 2023. cited by applicant

International Search Report and Written Opinion—PCT/US2023/066891—ISA/EPO—Oct. 31, 2023. cited by applicant

Primary Examiner: Chang; Yu-Wen

Attorney, Agent or Firm: Holland & Hart LLP

Background/Summary

TECHNICAL FIELD

(1) This disclosure relates generally to wireless communication, and more specifically, to physical layer convergence protocol (PLCP) protocol data unit (PPDU) formats for wireless communications in the 60 GHz frequency band.

DESCRIPTION OF THE RELATED TECHNOLOGY

(2) A wireless local area network (WLAN) may be formed by one or more access points (APs) that provide a shared wireless communication medium for use by a number of client devices also referred to as stations (STAs). The basic building block of a WLAN conforming to the Institute of Electrical and Electronics Engineers (IEEE) 802.11 family of standards is a Basic Service Set (BSS), which is managed by an AP. Each BSS is identified by a Basic Service Set Identifier (BSSID) that is advertised by the AP. An AP periodically broadcasts beacon frames to enable any STAs within wireless range of the AP to establish or maintain a communication link with the WLAN.

(3) Many existing WLAN communication protocols are designed for wireless communications on carrier frequencies below 7 GHz (such as in the 2.4 GHz, 5 GHz, or 6 GHz frequency bands). However, new WLAN communication protocols are being developed to enable enhanced WLAN communication features (such as higher throughput and wider bandwidth) that require even higher carrier frequencies (such as in the 45 GHz or 60 GHz frequency bands). Wireless communications on higher carrier frequencies may suffer from greater phase noise and greater path loss compared to wireless communications on lower carrier frequencies. Thus, as new WLAN communication protocols enable enhanced features, new packet designs and numerology are needed to support wireless communications on carrier frequencies above 7 GHz.

SUMMARY

(4) The systems, methods and devices of this disclosure each have several innovative aspects, no single one of which is solely responsible for the desirable attributes disclosed herein.

(5) One innovative aspect of the subject matter described in this disclosure can be implemented as a method of wireless communication. The method may be performed by a wireless communication device, and may include mapping a first portion of a physical layer (PHY) convergence protocol (PLCP) protocol data unit (PPDU) to a number (N) of subcarriers, where the first portion of the PPDU represents at least portion of a PHY preamble that includes a short training field (STF), a long training field (LTF), and one or more signal (SIG) fields that immediately follow the LTF and carry information for interpreting the PPDU; transforming the N subcarriers into a first time-varying signal at a sampling rate ($f_{\text{sub.s}}$) associated with a first subcarrier spacing (SCS) that is greater than 1.2 MHz, where the first SCS represents an amount of separation, in the frequency domain, between adjacent subcarriers of the N subcarriers; and transmitting the first time-varying signal over a wireless channel having a bandwidth (BW) associated with the sampling rate $f_{\text{sub.s}}$. In some aspects, the first time-varying signal may be transmitted on a carrier frequency above 7 GHz.

(6) In some aspects, the PPDU may conform to a PPDU format associated with wireless communications on a carrier frequency below 7 GHz. In some implementations, the one or more SIG fields may include a legacy SIG field (L-SIG) and a non-legacy SIG field immediately following L-SIG. In some other implementations, the one or more SIG fields may include an L-SIG, a repeat of L-SIG (RL-SIG) immediately following L-SIG, and a non-legacy SIG field immediately following RL-SIG. In some implementations, the STF and the non-legacy SIG field may each consist of two orthogonal frequency-division multiplexing (OFDM) symbols. In some other implementations, the STF may consist of two OFDM symbols that are repeated in time and the non-legacy SIG field may consist of four OFDM symbols.

(7) In some aspects, the PPDU may consist of only the first portion. In some other aspects, the method may further include mapping, to a number (M) of subcarriers, a second portion of the

PPDU including at least a data field, a packet extension, or one or more training fields (TRNs); transforming the M subcarriers into a second time-varying signal at the sampling rate $f_{\text{sub.s}}$; and transmitting the second time-varying signal over the wireless channel immediately following the first time-varying signal. In some implementations, the one or more SIG fields may consist of a single SIG field that is immediately followed by the data field, the packet extension, or the one or more TRNs. In some implementations, the second portion of the PPDU may further include one or more additional LTFs. In some implementations, the one or more SIG fields may consist of a single SIG field that is immediately followed by the one or more additional LTFs.

(8) In some implementations, M may be equal to N and BW may be equal to $f_{\text{sub.s}}$. In some other implementations, M may be equal to N and the PPDU may be duplicated for transmission on a number (m) of sub-bands each spanning a respective bandwidth portion equal to BW/m , where BW is equal to $m \cdot f_{\text{sub.s}}$. Still further, in some implementations, M may be greater than N . In some implementations, the first portion of the PPDU may be duplicated for transmission on a number (n) of sub-bands each spanning a respective bandwidth portion equal to BW/n , where BW is equal to $f_{\text{sub.s}}$. In some implementations, the transformation of the M subcarriers into the second time-varying signal may result in a second SCS equal to the first SCS, where the second SCS represents an amount of separation, in the frequency domain, between adjacent subcarriers of the M subcarriers. In some other implementations, the transformation of the M subcarriers into the second time-varying signal may result in a second SCS different than the first SCS, where the second SCS represents an amount of separation, in the frequency domain, between adjacent subcarriers of the M subcarriers.

(9) In some implementations, the LTF may be transmitted on the same subcarriers as the second portion of the PPDU as a result of duplicating the first portion of the PPDU for transmission on the n sub-bands. In some implementations, the LTF may include a first OFDM symbol and a second OFDM symbol identical to the first OFDM symbol. In some other implementations, the LTF may include a first OFDM symbol and a second OFDM symbol, where the method further includes applying a P -matrix to the LTF so that the first OFDM symbol is different than the second OFDM symbol. In some implementations, the STF may include a Golay sequence. In some implementations, the information carried in the one or more SIG fields may include an indication of whether the PPDU is associated with a beamforming training operation.

(10) Another innovative aspect of the subject matter described in this disclosure can be implemented in a wireless communication device. In some implementations, the wireless communication device may include at least one memory and at least one processor communicatively coupled with the at least one memory and configured to cause the wireless communication device to perform operations including mapping a first portion of a PPDU to a number (N) of subcarriers, where the first portion of the PPDU represents at least portion of a PHY preamble that includes an STF, an LTF, and one or more SIG fields that immediately follow the LTF and carry information for interpreting the PPDU; transforming the N subcarriers into a first time-varying signal at a sampling rate ($f_{\text{sub.s}}$) associated with a first SCS that is greater than 1.2 MHz, where the first SCS represents an amount of separation, in the frequency domain, between adjacent subcarriers of the N subcarriers; and transmitting the first time-varying signal over a wireless channel having a bandwidth (BW) associated with the sampling rate $f_{\text{sub.s}}$.

(11) Another innovative aspect of the subject matter described in this disclosure can be implemented as a method of wireless communication. The method may be performed by a wireless communication device and may include mapping a first portion of a PPDU to a number (N) of subcarriers, where the first portion of the PPDU represents at least portion of a PHY preamble that includes an STF and one or more SIG fields carrying information for interpreting the PPDU; mapping an LTF of the PHY preamble to a number (M) of subcarriers, where the LTF follows the STF and precedes the one or more SIG fields in the PHY preamble, where M is greater than N ; transforming the N subcarriers and the M subcarriers to a time-varying signal; and transmitting the

time-varying signal over a wireless channel. In some aspects, the wireless channel may be associated with a carrier frequency above 7 GHz.

(12) In some implementations, the method may further include mapping, to the M subcarriers, a second portion of the PPDU including at least a data field, a packet extension, or one or more TRNs. In some implementations, the N subcarriers and the M subcarriers may be transformed to the time-varying signal at a sampling rate ($f_{\text{sub.s}}$) associated with an SCS greater than 1.2 MHz, where the SCS represents an amount of separation, in the frequency domain, between adjacent subcarriers of the N subcarriers. In some implementations, the first portion of the PPDU may be duplicated for transmission on a number (n) of sub-bands each spanning a respective bandwidth portion equal to BW/n .

(13) Another innovative aspect of the subject matter described in this disclosure can be implemented in a wireless communication device. In some implementations, the wireless communication device may include at least one memory and at least one processor communicatively coupled with the at least one memory and configured to cause the wireless communication device to perform operations including mapping a first portion of a PPDU to a number (N) of subcarriers, where the first portion of the PPDU represents at least portion of a PHY preamble that includes an STF and one or more SIG fields carrying information for interpreting the PPDU; mapping an LTF of the PHY preamble to a number (M) of subcarriers, where the LTF follows the STF and precedes the one or more SIG fields in the PHY preamble, where $M > N$; transforming the N subcarriers and the M subcarriers to a time-varying signal; and transmitting the time-varying signal over a wireless channel.

Description

BRIEF DESCRIPTION OF THE DRAWINGS

(1) Details of one or more implementations of the subject matter described in this disclosure are set forth in the accompanying drawings and the description below. Other features, aspects, and advantages will become apparent from the description, the drawings and the claims. Note that the relative dimensions of the following figures may not be drawn to scale.

(2) FIG. 1 shows a pictorial diagram of an example wireless communication network.

(3) FIG. 2A shows an example protocol data unit (PDU) usable for communications between an access point (AP) and one or more wireless stations (STAs).

(4) FIG. 2B shows an example field in the PDU of FIG. 2A.

(5) FIG. 3 shows an example physical layer convergence protocol (PLCP) protocol data unit (PPDU) usable for communications between an AP and one or more STAs.

(6) FIG. 4 shows a block diagram of an example wireless communication device.

(7) FIG. 5A shows a block diagram of an example AP.

(8) FIG. 5B shows a block diagram of an example STA.

(9) FIG. 6 shows an example communication environment that includes an AP and a STA, according to some implementations.

(10) FIG. 7 shows a block diagram of an example transmit (TX) processing chain for a wireless communication device, according to some implementations.

(11) FIG. 8 shows a block diagram of an example orthogonal frequency-division multiplexing (OFDM) up-clocking system, according to some implementations.

(12) FIG. 9A shows an example PPDU formatted in accordance with a legacy PPDU format.

(13) FIG. 9B shows an example up-clocked PPDU based on the PPDU format depicted in FIG. 9A, according to some implementations.

(14) FIG. 9C shows another example up-clocked PPDU based on the PPDU format depicted in FIG. 9A, according to some implementations.

- (15) FIG. 9D shows another example up-clocked PPDU based on the PPDU format depicted in FIG. 9A, according to some implementations.
- (16) FIG. 10A shows an example PPDU formatted in accordance with a legacy PPDU format.
- (17) FIG. 10B shows an example up-clocked PPDU based on the PPDU format depicted in FIG. 10A, according to some implementations.
- (18) FIG. 11A shows an example PPDU formatted in accordance with a legacy PPDU format.
- (19) FIG. 11B shows an example up-clocked PPDU based on the PPDU format depicted in FIG. 11A, according to some implementations.
- (20) FIG. 11C shows another example up-clocked PPDU based on the PPDU format depicted in FIG. 11A, according to some implementations.
- (21) FIG. 11D shows another example up-clocked PPDU based on the PPDU format depicted in FIG. 11A, according to some implementations.
- (22) FIG. 12A shows an example PPDU formatted in accordance with a legacy PPDU format.
- (23) FIG. 12B shows an example up-clocked PPDU based on the PPDU format depicted in FIG. 12A, according to some implementations.
- (24) FIG. 12C shows another example up-clocked PPDU based on the PPDU format depicted in FIG. 12A, according to some implementations.
- (25) FIG. 12D shows another example up-clocked PPDU based on the PPDU format depicted in FIG. 12A, according to some implementations.
- (26) FIG. 13A shows an example PPDU formatted in accordance with a legacy PPDU format.
- (27) FIG. 13B shows an example up-clocked PPDU based on the PPDU format depicted in FIG. 13A, according to some implementations.
- (28) FIG. 13C shows another example up-clocked PPDU based on the PPDU format depicted in FIG. 13A, according to some implementations.
- (29) FIG. 13D shows another example up-clocked PPDU based on the PPDU format depicted in FIG. 13A, according to some implementations.
- (30) FIG. 14A shows an example PPDU conforming to a green field PPDU format, according to some implementations.
- (31) FIG. 14B shows another example PPDU conforming to a green field PPDU format, according to some implementations.
- (32) FIG. 14C shows another example PPDU conforming to a green field PPDU format, according to some implementations.
- (33) FIG. 15A shows an example PPDU conforming to a green field PPDU format, according to some implementations.
- (34) FIG. 15B shows another example PPDU conforming to a green field PPDU format, according to some implementations.
- (35) FIG. 15C shows another example PPDU conforming to a green field PPDU format, according to some implementations.
- (36) FIG. 16 shows a flowchart illustrating an example process for wireless communication that supports 60 GHz PPDU formats.
- (37) FIG. 17 shows a flowchart illustrating an example process for wireless communication that supports 60 GHz PPDU formats.
- (38) FIG. 18 shows a block diagram of an example wireless communication device according to some implementations.
- (39) FIG. 19 shows a block diagram of an example wireless communication device according to some implementations.
- (40) Like reference numbers and designations in the various drawings indicate like elements.
- DETAILED DESCRIPTION**
- (41) The following description is directed to certain implementations for the purposes of describing innovative aspects of this disclosure. However, a person having ordinary skill in the art will readily

recognize that the teachings herein can be applied in a multitude of different ways. The described implementations can be implemented in any device, system or network that is capable of transmitting and receiving radio frequency (RF) signals according to one or more of the Institute of Electrical and Electronics Engineers (IEEE) 802.11 standards, the IEEE 802.15 standards, the Bluetooth® standards as defined by the Bluetooth Special Interest Group (SIG), or the Long Term Evolution (LTE), 3G, 4G or 5G (New Radio (NR)) standards promulgated by the 3rd Generation Partnership Project (3GPP), among others. The described implementations can be implemented in any device, system or network that is capable of transmitting and receiving RF signals according to one or more of the following technologies or techniques: code division multiple access (CDMA), time division multiple access (TDMA), frequency division multiple access (FDMA), orthogonal FDMA (OFDMA), single-carrier FDMA (SC-FDMA), single-user (SU) multiple-input multiple-output (MIMO) and multi-user (MU) MIMO. The described implementations also can be implemented using other wireless communication protocols or RF signals suitable for use in one or more of a wireless personal area network (WPAN), a wireless local area network (WLAN), a wireless wide area network (WWAN), or an internet of things (JOT) network.

(42) As described above, new WLAN communication protocols are being developed to enable enhanced features for wireless communications on carrier frequencies above 7 GHz (such as in the 45 GHz or 60 GHz frequency bands). However, wireless communications on higher carrier frequencies may suffer from greater phase noise and path loss compared to wireless communications on lower frequency bands. For example, increasing the carrier frequency from 5.8 GHz to 60 GHz results in a $10\times$ increase in phase noise. Aspects of the present disclosure recognize that the phase noise can be mitigated by increasing the subcarrier spacing (SCS) between modulated subcarriers. Existing WLAN packet formats include a legacy short training field (L-STF) that is modulated on every 4^{sup}.th subcarrier spanning a given bandwidth to support carrier frequency offset (CFO) estimations up to 2 subcarriers apart. Aspects of the present disclosure also recognize that the local oscillators (LOs) implemented by existing WLAN transmitters and receivers are required to be accurate up to ± 20 ppm. As such, existing WLAN architectures can support CFOs up to ± 40 ppm (between the transmitter and the receiver), which is equivalent to ± 2.4 MHz in the 60 GHz frequency band and ± 1.8 MHz in the 45 GHz frequency band. To support CFOs up to ± 2.4 MHz, the SCS associated with L-STF should be greater than or equal to 1.2 MHz

(43) Various aspects relate generally to increasing carrier frequencies for wireless communications in WLANs, and more particularly, to packet designs that support wireless communications on carrier frequencies above 7 GHz. In some aspects, a wireless communication device may map a physical layer convergence protocol (PLCP) protocol data unit (PPDU) to orthogonal frequency-division multiplexing (OFDM) subcarriers according to existing tone plans associated with carrier frequencies below 7 GHz (also referred to as “sub-7 GHz” tone plans) and may up-clock the PPDU for transmission on carrier frequencies above 7 GHz. As used herein, the term “up-clocking” refers to increasing the frequency of a clock signal used to convert the PPDU between the frequency domain and the time domain (beyond a frequency ($f_{\text{sub}.0}$) associated with the existing sub-7 GHz tone plan), and the ratio (K) of the up-clocked frequency ($f_{\text{sub}.s}$) to $f_{\text{sub}.0}$ is referred to as the “up-clocking ratio” (where $K=f_{\text{sub}.s}/f_{\text{sub}.0}$). In some aspects, the up-clocking may result in an SCS greater than or equal to 1.2 MHz, where the SCS represents a spacing between the subcarriers to which at least a portion of the PPDU (including L-STF) is mapped. More specifically, the SCS as a result of up-clocking ($\text{SCS}_{\text{sub}.U}$) may be a multiple of an SCS associated with the existing sub-7 GHz tone plan ($\text{SCS}_{\text{sub}.0}$), where $\text{SCS}_{\text{sub}.U}=K*\text{SCS}_{\text{sub}.0}$. In some implementations, the up-clocked PPDU may conform to an existing PPDU format designed for sub-7 GHz wireless communications. In some other implementations, the up-clocked PPDU may conform to a new “green field” PPDU format optimized for wireless communications on carrier frequencies above 7 GHz.

(44) Particular implementations of the subject matter described in this disclosure can be

implemented to realize one or more of the following potential advantages. By up-clocking PPDU that are mapped to OFDM subcarriers according to existing sub-7 GHz tone plans, aspects of the present disclosure can leverage existing WLAN hardware to increase the carrier frequencies on which such PPDU are transmitted (such as to the 60 GHz or 45 GHz frequency bands). As described above, existing WLAN architectures can support CFO estimation in the 60 GHz frequency band if the SCS associated with L-STF is greater than or equal to 1.2 MHz. The SCS depends, in part, on the tone plan used to map the PPDU to the OFDM subcarriers, and more particularly, the size of the inverse fast Fourier transform (IFFT) associated with the tone plan. Aspects of the present disclosure recognize that, for any given IFFT size ($N_{\text{sub.IFFT}}$) associated with an existing sub-7 GHz tone plan, a suitable sampling rate $f_{\text{sub.s}}$ can be selected so that

(45) $\text{SCS} = \frac{f_s}{N_{\text{IFFT}}} \geq 1.2\text{MHz}.$

By up-clocking existing sub-7 GHz tone plans, aspects of the present disclosure can further reuse existing PPDU formats (associated with such tone plans) for wireless communications on carrier frequencies above 7 GHz, thereby reducing the cost and complexity of hardware that would otherwise be needed to support new PPDU formats. On the other hand, by designing new green field PPDU formats, aspects of the present disclosure can reduce the overhead of communications on carrier frequencies above 7 GHz by eliminating various fields, signaling, or other redundancies associated with legacy WLAN protocols (such as in existing PPDU formats).

(46) FIG. 1 shows a block diagram of an example wireless communication network **100**. According to some aspects, the wireless communication network **100** can be an example of a wireless local area network (WLAN) such as a Wi-Fi network (and will hereinafter be referred to as WLAN **100**). For example, the WLAN **100** can be a network implementing at least one of the IEEE 802.11 family of wireless communication protocol standards (such as that defined by the IEEE 802.11-2020 specification or amendments thereof including, but not limited to, 802.11ah, 802.11ad, 802.11ay, 802.11ax, 802.11az, 802.11ba and 802.11be). The WLAN **100** may include numerous wireless communication devices such as an access point (AP) **102** and multiple stations (STAs) **104**. While only one AP **102** is shown, the WLAN network **100** also can include multiple APs **102**.

(47) Each of the STAs **104** also may be referred to as a mobile station (MS), a mobile device, a mobile handset, a wireless handset, an access terminal (AT), a user equipment (UE), a subscriber station (SS), or a subscriber unit, among other possibilities. The STAs **104** may represent various devices such as mobile phones, personal digital assistant (PDAs), other handheld devices, netbooks, notebook computers, tablet computers, laptops, display devices (for example, TVs, computer monitors, navigation systems, among others), music or other audio or stereo devices, remote control devices (“remotes”), printers, kitchen or other household appliances, key fobs (for example, for passive keyless entry and start (PKES) systems), among other possibilities.

(48) A single AP **102** and an associated set of STAs **104** may be referred to as a basic service set (BSS), which is managed by the respective AP **102**. FIG. 1 additionally shows an example coverage area **108** of the AP **102**, which may represent a basic service area (BSA) of the WLAN **100**. The BSS may be identified to users by a service set identifier (SSID), as well as to other devices by a basic service set identifier (BSSID), which may be a medium access control (MAC) address of the AP **102**. The AP **102** periodically broadcasts beacon frames (“beacons”) including the BSSID to enable any STAs **104** within wireless range of the AP **102** to “associate” or re-associate with the AP **102** to establish a respective communication link **106** (hereinafter also referred to as a “Wi-Fi link”), or to maintain a communication link **106**, with the AP **102**. For example, the beacons can include an identification of a primary channel used by the respective AP **102** as well as a timing synchronization function for establishing or maintaining timing synchronization with the AP **102**. The AP **102** may provide access to external networks to various STAs **104** in the WLAN via respective communication links **106**.

(49) To establish a communication link **106** with an AP **102**, each of the STAs **104** is configured to perform passive or active scanning operations (“scans”) on frequency channels in one or more

frequency bands (for example, the 2.4 GHz, 5 GHz, 6 GHz or 60 GHz bands). To perform passive scanning, a STA **104** listens for beacons, which are transmitted by respective APs **102** at a periodic time interval referred to as the target beacon transmission time (TBTT) (measured in time units (TUs) where one TU may be equal to 1024 microseconds (vs)). To perform active scanning, a STA **104** generates and sequentially transmits probe requests on each channel to be scanned and listens for probe responses from APs **102**. Each STA **104** may be configured to identify or select an AP **102** with which to associate based on the scanning information obtained through the passive or active scans, and to perform authentication and association operations to establish a communication link **106** with the selected AP **102**. The AP **102** assigns an association identifier (AID) to the STA **104** at the culmination of the association operations, which the AP **102** uses to track the STA **104**.

(50) As a result of the increasing ubiquity of wireless networks, a STA **104** may have the opportunity to select one of many BSSs within range of the STA or to select among multiple APs **102** that together form an extended service set (ESS) including multiple connected BSSs. An extended network station associated with the WLAN **100** may be connected to a wired or wireless distribution system that may allow multiple APs **102** to be connected in such an ESS. As such, a STA **104** can be covered by more than one AP **102** and can associate with different APs **102** at different times for different transmissions. Additionally, after association with an AP **102**, a STA **104** also may be configured to periodically scan its surroundings to find a more suitable AP **102** with which to associate. For example, a STA **104** that is moving relative to its associated AP **102** may perform a “roaming” scan to find another AP **102** having more desirable network characteristics such as a greater received signal strength indicator (RSSI) or a reduced traffic load.

(51) In some cases, STAs **104** may form networks without APs **102** or other equipment other than the STAs **104** themselves. One example of such a network is an ad hoc network (or wireless ad hoc network). Ad hoc networks may alternatively be referred to as mesh networks or peer-to-peer (P2P) networks. In some cases, ad hoc networks may be implemented within a larger wireless network such as the WLAN **100**. In such implementations, while the STAs **104** may be capable of communicating with each other through the AP **102** using communication links **106**, STAs **104** also can communicate directly with each other via direct wireless links **110**. Additionally, two STAs **104** may communicate via a direct communication link **110** regardless of whether both STAs **104** are associated with and served by the same AP **102**. In such an ad hoc system, one or more of the STAs **104** may assume the role filled by the AP **102** in a BSS. Such a STA **104** may be referred to as a group owner (GO) and may coordinate transmissions within the ad hoc network. Examples of direct wireless links **110** include Wi-Fi Direct connections, connections established by using a Wi-Fi Tunneled Direct Link Setup (TDLS) link, and other P2P group connections.

(52) The APs **102** and STAs **104** may function and communicate (via the respective communication links **106**) according to the IEEE 802.11 family of wireless communication protocol standards (such as that defined by the IEEE 802.11-2016 specification or amendments thereof including, but not limited to, 802.11ah, 802.11ad, 802.11ay, 802.11ax, 802.11az, 802.11ba and 802.11be). These standards define the WLAN radio and baseband protocols for the PHY and medium access control (MAC) layers. The APs **102** and STAs **104** transmit and receive wireless communications (hereinafter also referred to as “Wi-Fi communications”) to and from one another in the form of physical layer convergence protocol (PLCP) protocol data units (PPDUs). The APs **102** and STAs **104** in the WLAN **100** may transmit PPDUs over an unlicensed spectrum, which may be a portion of spectrum that includes frequency bands traditionally used by Wi-Fi technology, such as the 2.4 GHz band, the 5 GHz band, the 60 GHz band, the 3.6 GHz band, and the 700 MHz band. Some implementations of the APs **102** and STAs **104** described herein also may communicate in other frequency bands, such as the 6 GHz band, which may support both licensed and unlicensed communications. The APs **102** and STAs **104** also can be configured to communicate over other frequency bands such as shared licensed frequency bands, where multiple operators may have a license to operate in the same or overlapping frequency band or bands.

(53) Each of the frequency bands may include multiple sub-bands or frequency channels. For example, PPDU's conforming to the IEEE 802.11n, 802.11ac, 802.11ax and 802.11be standard amendments may be transmitted over the 2.4, 5 GHz or 6 GHz bands, each of which is divided into multiple 20 MHz channels. As such, these PPDU's are transmitted over a physical channel having a minimum bandwidth of 20 MHz, but larger channels can be formed through channel bonding. For example, PPDU's may be transmitted over physical channels having bandwidths of 40 MHz, 80 MHz, 160 or 320 MHz by bonding together multiple 20 MHz channels.

(54) Each PPDU is a composite structure that includes a PHY preamble and a payload in the form of a PHY service data unit (PSDU). The information provided in the preamble may be used by a receiving device to decode the subsequent data in the PSDU. In instances in which PPDU's are transmitted over a bonded channel, the preamble fields may be duplicated and transmitted in each of the multiple component channels. The PHY preamble may include both a legacy portion (or "legacy preamble") and a non-legacy portion (or "non-legacy preamble"). The legacy preamble may be used for packet detection, automatic gain control and channel estimation, among other uses. The legacy preamble also may generally be used to maintain compatibility with legacy devices. The format of, coding of, and information provided in the non-legacy portion of the preamble is based on the particular IEEE 802.11 protocol to be used to transmit the payload.

(55) FIG. 2A shows an example protocol data unit (PDU) **200** usable for wireless communication between an AP **102** and one or more STAs **104**. For example, the PDU **200** can be configured as a PPDU. As shown, the PDU **200** includes a PHY preamble **202** and a PHY payload **204**. For example, the preamble **202** may include a legacy portion that itself includes a legacy short training field (L-STF) **206**, which may consist of two BPSK symbols, a legacy long training field (L-LTF) **208**, which may consist of two BPSK symbols, and a legacy signal field (L-SIG) **210**, which may consist of two BPSK symbols. The legacy portion of the preamble **202** may be configured according to the IEEE 802.11a wireless communication protocol standard. The preamble **202** may also include a non-legacy portion including one or more non-legacy fields **212**, for example, conforming to an IEEE wireless communication protocol such as the IEEE 802.11ac, 802.11ax, 802.11be or later wireless communication protocol protocols.

(56) The L-STF **206** generally enables a receiving device to perform automatic gain control (AGC) and coarse timing and frequency estimation. The L-LTF **208** generally enables a receiving device to perform fine timing and frequency estimation and also to perform an initial estimate of the wireless channel. The L-SIG **210** generally enables a receiving device to determine a duration of the PDU and to use the determined duration to avoid transmitting on top of the PDU. For example, the L-STF **206**, the L-LTF **208** and the L-SIG **210** may be modulated according to a binary phase shift keying (BPSK) modulation scheme. The payload **204** may be modulated according to a BPSK modulation scheme, a quadrature BPSK (Q-BPSK) modulation scheme, a quadrature amplitude modulation (QAM) modulation scheme, or another appropriate modulation scheme. The payload **204** may include a PSDU including a data field (DATA) **214** that, in turn, may carry higher layer data, for example, in the form of medium access control (MAC) protocol data units (MPDU's) or an aggregated MPDU (A-MPDU).

(57) FIG. 2B shows an example L-SIG **210** in the PDU **200** of FIG. 2A. The L-SIG **210** includes a data rate field **222**, a reserved bit **224**, a length field **226**, a parity bit **228**, and a tail field **230**. The data rate field **222** indicates a data rate (note that the data rate indicated in the data rate field **212** may not be the actual data rate of the data carried in the payload **204**). The length field **226** indicates a length of the packet in units of, for example, symbols or bytes. The parity bit **228** may be used to detect bit errors. The tail field **230** includes tail bits that may be used by the receiving device to terminate operation of a decoder (for example, a Viterbi decoder). The receiving device may utilize the data rate and the length indicated in the data rate field **222** and the length field **226** to determine a duration of the packet in units of, for example, microseconds (μ s) or other time units.

(58) FIG. 3 shows an example PPDU 300 usable for communications between an AP 102 and one or more STAs 104. As described above, each PPDU 300 includes a PHY preamble 302 and a PSDU 304. Each PSDU 304 may represent (or “carry”) one or more MAC protocol data units (MPDUs) 316. For example, each PSDU 304 may carry an aggregated MPDU (A-MPDU) 306 that includes an aggregation of multiple A-MPDU subframes 308. Each A-MPDU subframe 306 may include an MPDU frame 310 that includes a MAC delimiter 312 and a MAC header 314 prior to the accompanying MPDU 316, which comprises the data portion (“payload” or “frame body”) of the MPDU frame 310. Each MPDU frame 310 may also include a frame check sequence (FCS) field 318 for error detection (for example, the FCS field may include a cyclic redundancy check (CRC)) and padding bits 320. The MPDU 316 may carry one or more MAC service data units (MSDUs) 326. For example, the MPDU 316 may carry an aggregated MSDU (A-MSDU) 322 including multiple A-MSDU subframes 324. Each A-MSDU subframe 324 contains a corresponding MSDU 330 preceded by a subframe header 328 and in some cases followed by padding bits 332.

(59) Referring back to the MPDU frame 310, the MAC delimiter 312 may serve as a marker of the start of the associated MPDU 316 and indicate the length of the associated MPDU 316. The MAC header 314 may include multiple fields containing information that defines or indicates characteristics or attributes of data encapsulated within the frame body 316. The MAC header 314 includes a duration field indicating a duration extending from the end of the PPDU until at least the end of an acknowledgment (ACK) or Block ACK (BA) of the PPDU that is to be transmitted by the receiving wireless communication device. The use of the duration field serves to reserve the wireless medium for the indicated duration, and enables the receiving device to establish its network allocation vector (NAV). The MAC header 314 also includes one or more fields indicating addresses for the data encapsulated within the frame body 316. For example, the MAC header 314 may include a combination of a source address, a transmitter address, a receiver address or a destination address. The MAC header 314 may further include a frame control field containing control information. The frame control field may specify a frame type, for example, a data frame, a control frame, or a management frame.

(60) FIG. 4 shows a block diagram of an example wireless communication device 400. In some implementations, the wireless communication device 400 can be an example of a device for use in a STA such as one of the STAs 104 described with reference to FIG. 1. In some implementations, the wireless communication device 400 can be an example of a device for use in an AP such as the AP 102 described with reference to FIG. 1. The wireless communication device 400 is capable of transmitting (or outputting for transmission) and receiving wireless communications (for example, in the form of wireless packets). For example, the wireless communication device can be configured to transmit and receive packets in the form of physical layer convergence protocol (PLCP) protocol data units (PPDUs) and medium access control (MAC) protocol data units (MPDUs) conforming to an IEEE 802.11 wireless communication protocol standard, such as that defined by the IEEE 802.11-2016 specification or amendments thereof including, but not limited to, 802.11ah, 802.11ad, 802.11ay, 802.11ax, 802.11az, 802.11ba and 802.11be.

(61) The wireless communication device 400 can be, or can include, a chip, system on chip (SoC), chipset, package or device that includes one or more modems 402, for example, a Wi-Fi (IEEE 802.11 compliant) modem. In some implementations, the one or more modems 402 (collectively “the modem 402”) additionally include a WWAN modem (for example, a 3GPP 4G LTE or 5G compliant modem). In some implementations, the wireless communication device 400 also includes one or more radios 404 (collectively “the radio 404”). In some implementations, the wireless communication device 406 further includes one or more processors, processing blocks or processing elements 406 (collectively “the processor 406”) and one or more memory blocks or elements 408 (collectively “the memory 408”).

(62) The modem 402 can include an intelligent hardware block or device such as, for example, an application-specific integrated circuit (ASIC) among other possibilities. The modem 402 is

generally configured to implement a PHY layer. For example, the modem **402** is configured to modulate packets and to output the modulated packets to the radio **404** for transmission over the wireless medium. The modem **402** is similarly configured to obtain modulated packets received by the radio **404** and to demodulate the packets to provide demodulated packets. In addition to a modulator and a demodulator, the modem **402** may further include digital signal processing (DSP) circuitry, automatic gain control (AGC), a coder, a decoder, a multiplexer and a demultiplexer. For example, while in a transmission mode, data obtained from the processor **406** is provided to a coder, which encodes the data to provide encoded bits. The encoded bits are then mapped to points in a modulation constellation (using a selected MCS) to provide modulated symbols. The modulated symbols may then be mapped to a number $N_{\text{sub}} \cdot SS$ of spatial streams or a number $N_{\text{sub}} \cdot STS$ of space-time streams. The modulated symbols in the respective spatial or space-time streams may then be multiplexed, transformed via an inverse fast Fourier transform (IFFT) block, and subsequently provided to the DSP circuitry for Tx windowing and filtering. The digital signals may then be provided to a digital-to-analog converter (DAC). The resultant analog signals may then be provided to a frequency upconverter, and ultimately, the radio **404**. In implementations involving beamforming, the modulated symbols in the respective spatial streams are precoded via a steering matrix prior to their provision to the IFFT block.

(63) While in a reception mode, digital signals received from the radio **404** are provided to the DSP circuitry, which is configured to acquire a received signal, for example, by detecting the presence of the signal and estimating the initial timing and frequency offsets. The DSP circuitry is further configured to digitally condition the digital signals, for example, using channel (narrowband) filtering, analog impairment conditioning (such as correcting for UQ imbalance), and applying digital gain to ultimately obtain a narrowband signal. The output of the DSP circuitry may then be fed to the AGC, which is configured to use information extracted from the digital signals, for example, in one or more received training fields, to determine an appropriate gain. The output of the DSP circuitry also is coupled with the demodulator, which is configured to extract modulated symbols from the signal and, for example, compute the logarithm likelihood ratios (LLRs) for each bit position of each subcarrier in each spatial stream. The demodulator is coupled with the decoder, which may be configured to process the LLRs to provide decoded bits. The decoded bits from all of the spatial streams are then fed to the demultiplexer for demultiplexing. The demultiplexed bits may then be descrambled and provided to the MAC layer (the processor **406**) for processing, evaluation or interpretation.

(64) The radio **404** generally includes at least one radio frequency (RF) transmitter (or “transmitter chain”) and at least one RF receiver (or “receiver chain”), which may be combined into one or more transceivers. For example, the RF transmitters and receivers may include various DSP circuitry including at least one power amplifier (PA) and at least one low-noise amplifier (LNA), respectively. The RF transmitters and receivers may, in turn, be coupled to one or more antennas. For example, in some implementations, the wireless communication device **400** can include, or be coupled with, multiple transmit antennas (each with a corresponding transmit chain) and multiple receive antennas (each with a corresponding receive chain). The symbols output from the modem **402** are provided to the radio **404**, which then transmits the symbols via the coupled antennas. Similarly, symbols received via the antennas are obtained by the radio **404**, which then provides the symbols to the modem **402**.

(65) The processor **406** can include an intelligent hardware block or device such as, for example, a processing core, a processing block, a central processing unit (CPU), a microprocessor, a microcontroller, a digital signal processor (DSP), an application-specific integrated circuit (ASIC), a programmable logic device (PLD) such as a field programmable gate array (FPGA), discrete gate or transistor logic, discrete hardware components, or any combination thereof designed to perform the functions described herein. The processor **406** processes information received through the radio **404** and the modem **402**, and processes information to be output through the modem **402** and the

radio **404** for transmission through the wireless medium. For example, the processor **406** may implement a control plane and MAC layer configured to perform various operations related to the generation and transmission of MPDUs, frames or packets. The MAC layer is configured to perform or facilitate the coding and decoding of frames, spatial multiplexing, space-time block coding (STBC), beamforming, and OFDMA resource allocation, among other operations or techniques. In some implementations, the processor **406** may generally control the modem **402** to cause the modem to perform various operations described above.

(66) The memory **408** can include tangible storage media such as random-access memory (RAM) or read-only memory (ROM), or combinations thereof. The memory **408** also can store non-transitory processor- or computer-executable software (SW) code containing instructions that, when executed by the processor **406**, cause the processor to perform various operations described herein for wireless communication, including the generation, transmission, reception and interpretation of MPDUs, frames or packets. For example, various functions of components disclosed herein, or various blocks or steps of a method, operation, process or algorithm disclosed herein, can be implemented as one or more modules of one or more computer programs.

(67) FIG. 5A shows a block diagram of an example AP **502**. For example, the AP **502** can be an example implementation of the AP **102** described with reference to FIG. 1. The AP **502** includes a wireless communication device (WCD) **510** (although the AP **502** may itself also be referred to generally as a wireless communication device as used herein). For example, the wireless communication device **510** may be an example implementation of the wireless communication device **400** described with reference to FIG. 4. The AP **502** also includes multiple antennas **520** coupled with the wireless communication device **510** to transmit and receive wireless communications. In some implementations, the AP **502** additionally includes an application processor **530** coupled with the wireless communication device **510**, and a memory **540** coupled with the application processor **530**. The AP **502** further includes at least one external network interface **550** that enables the AP **502** to communicate with a core network or backhaul network to gain access to external networks including the Internet. For example, the external network interface **550** may include one or both of a wired (for example, Ethernet) network interface and a wireless network interface (such as a WWAN interface). Ones of the aforementioned components can communicate with other ones of the components directly or indirectly, over at least one bus. The AP **502** further includes a housing that encompasses the wireless communication device **510**, the application processor **530**, the memory **540**, and at least portions of the antennas **520** and external network interface **550**.

(68) FIG. 5B shows a block diagram of an example STA **504**. For example, the STA **504** can be an example implementation of the STA **104** described with reference to FIG. 1. The STA **504** includes a wireless communication device **515** (although the STA **504** may itself also be referred to generally as a wireless communication device as used herein). For example, the wireless communication device **515** may be an example implementation of the wireless communication device **400** described with reference to FIG. 4. The STA **504** also includes one or more antennas **525** coupled with the wireless communication device **515** to transmit and receive wireless communications. The STA **504** additionally includes an application processor **535** coupled with the wireless communication device **515**, and a memory **545** coupled with the application processor **535**. In some implementations, the STA **504** further includes a user interface (UI) **555** (such as a touchscreen or keypad) and a display **565**, which may be integrated with the UI **555** to form a touchscreen display. In some implementations, the STA **504** may further include one or more sensors **575** such as, for example, one or more inertial sensors, accelerometers, temperature sensors, pressure sensors, or altitude sensors. Ones of the aforementioned components can communicate with other ones of the components directly or indirectly, over at least one bus. The STA **504** further includes a housing that encompasses the wireless communication device **515**, the application processor **535**, the memory **545**, and at least portions of the antennas **525**, UI **555**, and

display 565.

(69) As described above, new WLAN communication protocols are being developed to enable enhanced features for wireless communications on carrier frequencies above 7 GHz (such as in the 45 GHz or 60 GHz frequency bands). However, wireless communications on higher carrier frequencies may suffer from greater phase noise and path loss compared to wireless communications on lower frequency bands. For example, increasing the carrier frequency from 5.8 GHz to 60 GHz results in a $10\times$ increase in phase noise. Aspects of the present disclosure recognize that the phase noise can be mitigated by increasing the SCS between modulated subcarriers.

Existing WLAN packet formats include an L-STF (such as the L-STF 206 of FIG. 2A) that is modulated on every 4^{sup}.th subcarrier spanning a given bandwidth to support CFO estimations up to 2 subcarriers apart. Aspects of the present disclosure also recognize that the LOs implemented by existing WLAN transmitters and receivers are required to be accurate up to ± 20 ppm. As such, existing WLAN architectures can support CFOs up to ± 40 ppm (between the transmitter and the receiver), which is equivalent to ± 2.4 MHz in the 60 GHz frequency band and ± 1.8 MHz in the 45 GHz frequency band. To support CFOs up to ± 2.4 MHz, the SCS associated with L-STF should be greater than or equal to 1.2 MHz

(70) Various aspects relate generally to increasing carrier frequencies for wireless communications in WLANs, and more particularly, to packet designs that support wireless communications on carrier frequencies above 7 GHz. In some aspects, a wireless communication device may map a PPDU to OFDM subcarriers according to existing tone plans associated with carrier frequencies below 7 GHz (also referred to as “sub-7 GHz” tone plans) and may up-clock the PPDU for transmission on carrier frequencies above 7 GHz. As used herein, the term “up-clocking” refers to increasing the frequency of a clock signal used to convert the PPDU between the frequency domain and the time domain (beyond a frequency ($f_{\text{sub}.0}$) associated with the existing sub-7 GHz tone plan), and the ratio (K) of the up-clocked frequency ($f_{\text{sub}.s}$) to $f_{\text{sub}.0}$ is referred to as the “up-clocking ratio”

(71) (where $K = \frac{f_s}{f_0}$).

In some aspects, the up-clocking may result in an SCS greater than or equal to 1.2 MHz, where the SCS represents a spacing between the subcarriers to which at least a portion of the PPDU (including L-STF) is mapped. More specifically, the SCS as a result of up-clocking ($\text{SCS}_{\text{sub}.U}$) may be a multiple of an SCS associated with the existing sub-7 GHz tone plan ($\text{SCS}_{\text{sub}.0}$), where $\text{SCS}_{\text{sub}.U} = K * \text{SCS}_{\text{sub}.0}$. In some implementations, the up-clocked PPDU may conform to an existing PPDU format designed for sub-7 GHz wireless communications. In some other implementations, the up-clocked PPDU may conform to a new “green field” PPDU format optimized for wireless communications on carrier frequencies above 7 GHz.

(72) Particular implementations of the subject matter described in this disclosure can be implemented to realize one or more of the following potential advantages. By up-clocking PDUs that are mapped to OFDM subcarriers according to existing sub-7 GHz tone plans, aspects of the present disclosure can leverage existing WLAN hardware to increase the carrier frequencies on which such PDUs are transmitted (such as to the 60 GHz or 45 GHz frequency bands). As described above, existing WLAN architectures can support CFO estimation in the 60 GHz frequency band if the SCS associated with L-STF is greater than or equal to 1.2 MHz. The SCS depends, in part, on the tone plan used to map the PPDU to the OFDM subcarriers, and more particularly, the size of the IFFT associated with the tone plan. Aspects of the present disclosure recognize that, for any given IFFT size ($N_{\text{sub}.IFFT}$) associated with an existing sub-7 GHz tone plan, a suitable sampling rate $f_{\text{sub}.s}$ can be selected so that

(73) $\text{SCS} = \frac{f_s}{N_{\text{IFFT}}} \geq 1.2 \text{ MHz}$.

By up-clocking existing sub-7 GHz tone plans, aspects of the present disclosure can further reuse existing PPDU formats (associated with such tone plans) for wireless communications on carrier

frequencies above 7 GHz, thereby reducing the cost and complexity of hardware that would otherwise be needed to support new PPDU formats. On the other hand, by designing new green field PPDU formats, aspects of the present disclosure can reduce the overhead of communications on carrier frequencies above 7 GHz by eliminating various fields, signaling, or other redundancies associated with legacy WLAN communication protocols (such as in existing PPDU formats).

(74) FIG. 6 shows an example communication environment 600 that includes an AP 610 and a STA 620, according to some implementations. In some implementations, the AP 610 may be one example of any of the APs 102 or 502 of FIGS. 1 and 5A, respectively. In some implementations, the STA 620 may be one example of any of the STAs 104 or 504 of FIGS. 1 and 5B, respectively. In the example of FIG. 6, the AP 610 is associated with a BSS that supports wireless communications at carrier frequencies above 7 GHz (such as in the 60 GHz frequency band).

(75) As described above, wireless communications in the 60 GHz frequency band may suffer from greater path loss compared to wireless communications in sub-7 GHz frequency bands. Aspects of the present disclosure recognize that analog beamforming (using a large number of antenna elements) can mitigate the effects of path loss and achieve greater wireless communication range on carrier frequencies above 7 GHz. Analog beamforming is a wireless communication technique by which a transmitting device and a receiving device can adjust the gains and phases of their transmit (TX) and receive (RX) antenna elements to achieve directionality in wireless communications. The process by which the transmitting device and the receiving device tune their antennas for beamforming is referred to as “beamforming training.”

(76) In some implementations, the AP 610 may use analog beamforming techniques to communicate with the STA 620. In the example of FIG. 6, the AP 610 is depicted as a transmitting device. As such, the AP 610 may tune a set of TX antennas to focus the energy of transmitted signals in a particular direction (referred to as “TX beamforming”). For example, the AP 610 may transmit packets or PPDU's via a number of antenna sectors T1-T7 (also referred to as “TX sectors”) configured or tuned for TX beamforming. The antenna elements associated with each TX sector are weighted so that the energy radiated by each antenna element combines along a particular beam direction. Accordingly, each of the TX sectors T1-T7 may be tuned to a respective TX beam direction. For simplicity, the AP 610 is shown to include 7 TX sectors T1-T7. However, in actual implementations, the AP 610 may include fewer or more TX sectors than those depicted in FIG. 6.

(77) In some implementations, the STA 620 also may use analog beamforming techniques to communicate with the AP 610. In the example of FIG. 6, the STA 620 is depicted as a receiving device. As such, the STA 620 may tune a set of RX antennas to focus the energy of received signals in a particular direction (referred to as “RX beamforming”). For example, the STA 620 may receive packets or PPDU's via a number of antenna sectors R1-R7 (also referred to as “RX sectors”) configured or tuned for RX beamforming. The antenna elements associated with each RX sector are weighted so that the energy received by each antenna element combines along a particular beam direction. Accordingly, each of the RX sectors R1-R7 may be tuned to a respective RX beam direction. For simplicity, the STA 620 is shown to include 7 RX sectors R1-R7. However, in actual implementations, the STA 620 may include fewer or more RX sectors than those depicted in FIG. 6.

(78) In some aspects, the AP 610 may perform a beamforming training operation with the STA 620 to determine TX and RX beam directions that optimize beamforming gains for wireless communications between the AP 610 and the STA 620. For example, the AP 610 may train its TX antennas for TX beamforming by transmitting a respective beamforming training (BFT) packet via each of the TX sectors T1-T7 and receiving feedback from the STA 620 indicating the TX beam direction associated with the highest TX beamforming gain. Further, the STA 620 may train its RX antennas for RX beamforming by listening for a respective BFT packet from the AP 610 via each of the RX sectors R1-R7 and determining the RX beam direction associated with the highest RX

beamforming gain based on the received BFT packets. In some implementations, the AP **610** may further train its RX antennas (not shown for simplicity) for RX beamforming and the STA **620** may further train its TX antennas (not shown for simplicity) for TX beamforming.

(79) In the example of FIG. **6**, the AP **610** and the STA **620** may achieve optimal beamforming gains for beams transmitted via the TX sector **T1** (of the AP **610**) and received via the RX sector **R7** (of the STA **620**). By contrast, beams transmitted by the AP **610** in other TX beam directions (such as via any of the TX sectors **T2-T7**) may fail to reach the STA **620**. The direction of the STA **620** is generally not known to the AP **610** prior to performing a beamforming training operation. In some aspects, the AP **610** may transmit beams in each of its TX beam directions while the STA **620** listens in an omnidirectional mode to increase the likelihood that at least one of the beams transmitted by the AP **610** will be received by the STA **620** prior to performing a beamforming training operation.

(80) Aspects of the present disclosure recognize that beamforming gains are significantly greater when TX beamforming is used at the transmitting device in combination with RX beamforming at the receiving device (also referred to as “full beamforming gains”) than when TX beamforming is used at the transmitting device while the receiving device operates in an omnidirectional mode (also referred to as “one-sided beamforming gains”). In some aspects, different PPDU formats may be used for wireless communications between the AP **610** and the STA **620** depending on the level of beamforming gains that can be achieved. More specifically, a “data PHY” (DPHY) PPDU format may be used when full beamforming gains are achievable and a “control PHY” (CPHY) PPDU format may be used when only one-sided beamforming gains are achievable.

(81) FIG. **7** shows a block diagram of an example TX processing chain **700** for a wireless communication device, according to some implementations. The TX processing chain **700** is configured to process a PPDU **701** for transmission, as a radio frequency (RF) signal **705**. In some aspects, the PPDU **701** may be one example of the PPDU **300** of FIG. **3**. In some implementations, the wireless communication device may be one example of the AP **610** of FIG. **6**. In some other implementations, the wireless communication device may be one example of the STA **620** of FIG. **6**. For simplicity, only a single spatial stream of the TX processing chain **700** is depicted in FIG. **7**. In actual implementations, the TX processing chain **700** may include any number of spatial streams.

(82) The TX processing chain **700** includes a constellation mapper **710**, an OFDM modulator **720**, an RF mixer **730**, and a power amplifier (PA) **740**. The constellation mapper **710** maps the PPDU **701** to one or more frequency-domain (FD) symbols **702** associated with a modulation scheme. Example suitable modulation schemes include binary phase-shift keying (BPSK), quadrature phase-shift keying (QPSK), and quadrature amplitude modulation (QAM). The OFDM modulator **720** modulates the FD symbols **702** onto a set of orthogonal subcarriers and converts the modulated subcarriers to a time-varying TX signal **703**. The RF mixer **730** up-converts the TX signal **703** to a carrier frequency, and the power amplifier **740** amplifies the resulting RF signal **705** for transmission via one or more antennas **750**. For example, the RF mixer **730** may modulate the TX signal **703** onto an LO signal **704** that oscillates at the carrier frequency. In some aspects, the carrier frequency associated with the LO signal **704** may be higher than 7 GHz. In some implementations, the carrier frequency may be in the 60 GHz frequency band. In some other implementations, the carrier frequency may be in the 45 GHz frequency band.

(83) As described above, many existing WLAN architectures are designed for wireless communications on carrier frequencies below 7 GHz (such as in the 2.4 GHz, 5 GHz, or 6 GHz frequency bands). In some aspects, existing WLAN hardware may be repurposed to support wireless communications on carrier frequencies above 7 GHz. For example, the TX processing chain **700** may receive the LO signal **704** from a local oscillator that is accurate up to ± 20 ppm. As described above, increasing the carrier frequency of the LO signal **704** also increases the phase noise associated with the RF signal **705**. For example, operating the local oscillator at 60 GHz can

result in a CFO of ± 2.4 MHz between the transmitter and the receiver. According to existing versions of the IEEE 802.11 standard, the PHY preamble of the PPDU **701** includes an L-STF having a $1\times$ symbol duration associated with an SCS equal to 312.5 KHz that can support CFO estimations up to 2 subcarriers apart. As used herein, the term “ $1\times$ SCS” refers to the subcarrier spacing between the subcarriers to which L-STF is mapped. Thus, to support CFOs up to ± 2.4 MHz, the $1\times$ SCS associated with the PPDU **701** should be greater than or equal to 1.2 MHz.

(84) Aspects of the present disclosure recognize that any SCS greater than or equal to 1.2 MHz may not be suitable for wireless communications on sub-7 GHz carrier frequencies. As such, existing WLAN communication protocols for sub-7 GHz wireless communications (such as the IEEE 802.11be, 11ax, 11ac, and earlier amendments of the IEEE 802.11 standard) do not define a PPDU format or tone plan associated with an SCS greater than or equal to 1.2 MHz. In some aspects, the TX processing chain **700** may receive a PPDU **701** that is formatted for transmission on a sub-7 GHz carrier frequency and may up-clock the PPDU **701** to a wider bandwidth that is suitable for transmission on a carrier frequency above 7 GHz (such as in the 60 GHz or 45 GHz frequency bands). For example, the wider bandwidth is achieved by spreading out the subcarriers to which the PPDU **701** is mapped. In some implementations, the TX processing chain **700** may up-clock the PPDU **701** so that the $1\times$ SCS associated with the PPDU **701** is greater than or equal to 1.2 MHz.

(85) In some implementations, the PPDU **701** may conform to a PPDU format defined by the IEEE 802.11ac amendment of the IEEE 802.11 standard (also referred to as an “11ac PPDU format”). For example, the PPDU **701** may conform to an 11ac PPDU format associated with a 20 MHz, 40 MHz, 80 MHz, 80+80 MHz, or 160 MHz channel bandwidth and may be up-clocked for transmission over an 80 MHz, 160 MHz, 320 MHz, 480 MHz, 640 MHz, 960 MHz, 1.28 GHz, 1.92 GHz, or 2.56 GHz bandwidth wireless channel in the 60 GHz or 45 GHz frequency band. In some other implementations, the PPDU **701** may conform to a PPDU format defined by the IEEE 802.11be (or 11ax) amendment of the IEEE 802.11 standard (also referred to as an “11be PPDU format”). For example, the PPDU **701** may conform to an 11be PPDU format associated with a 20 MHz, 40 MHz, or 80 MHz channel bandwidth and may be up-clocked for transmission over an 80 MHz, 160 MHz, 320 MHz, 480 MHz, 640 MHz, 960 MHz, 1.28 GHz, 1.92 GHz, or 2.56 GHz bandwidth wireless channel in the 60 GHz or 45 GHz frequency band. Still further, in some implementations, the PPDU **701** may conform to a new green field PPDU format that is optimized for communications in the 60 GHz or 45 GHz frequency band.

(86) FIG. **8** shows a block diagram of an example OFDM up-clocking system **800**, according to some implementations. In some aspects, the OFDM up-clocking system **800** may be configured to up-clock a PPDU **801** to a TX signal **806** suitable for transmission on carrier frequencies above 7 GHz (such as in the 60 GHz or 45 GHz frequency bands). More specifically, the OFDM up-clocking system **800** may map the PPDU **801** onto a set of orthogonal subcarriers associated with a $1\times$ SCS greater than or equal to 1.2 MHz. In some implementations, the OFDM up-clocking system **800** may be one example of the OFDM modulator **720** of FIG. **7**. In such implementations, the PPDU **801** and the TX signal **806** may be examples of the FD symbols **702** and the TX signal **703**, respectively, of FIG. **7**.

(87) The OFDM up-clocking system **800** includes a tone mapper **810**, an N-point IFFT **820**, a CP adder **830**, and a DAC **840**. The tone mapper **810** is configured to map the PPDU **801** to a number (N) of subcarriers associated with a sub-7 GHz tone plan to produce N modulated subcarriers **802**. In some implementations, the sub-7 GHz tone plan may include 64 subcarriers associated with a 20 MHz channel bandwidth (such as in accordance with an 11ac PPDU format). For example, the 64 subcarriers may include 52 data subcarriers, 4 pilot subcarriers, 7 guard subcarriers, and 1 direct current (DC) subcarrier. In some other implementations, the sub-7 GHz tone plan may include 128 subcarriers associated with a 40 MHz channel bandwidth (such as in accordance with an 11ac PPDU format). For example, the 128 subcarriers may include 108 data subcarriers, 6 pilot subcarriers, 11 guard subcarriers, and 3 DC subcarriers.

(88) In some implementations, the sub-7 GHz tone plan may include 256 subcarriers associated with an 80 MHz channel bandwidth (such as in accordance with an 11ac PPDU format) or a 20 MHz channel bandwidth (such as in accordance with an 11be PPDU format). For example, the 256 subcarriers may include 234 data subcarriers, 8 pilot subcarriers, 11 guard subcarriers, and 3 DC subcarriers. In some other implementations, the sub-7 GHz tone plan may include 512 subcarriers associated with a 160 MHz channel bandwidth (such as in accordance with an 11ac PPDU format). In such implementations, the 512 subcarriers may include 468 data subcarriers, 16 pilot subcarriers, 11 guard subcarriers, and 11 DC subcarriers. Still further, in some implementations, the sub-7 GHz tone plan may include 512 subcarriers associated with a 40 MHz channel bandwidth (such as in accordance with an 11be PPDU format). In such implementations, the 512 subcarriers may include 468 data subcarriers, 16 pilot subcarriers, 23 guard subcarriers, and 5 DC subcarriers.

(89) In some implementations, the sub-7 GHz tone plan may include 1024 subcarriers associated with a 80 MHz channel bandwidth (such as in accordance with an 11be PPDU format). In such implementations, the 1024 subcarriers may include 980 data subcarriers, 16 pilot subcarriers, 23 guard subcarriers, and 5 DC subcarriers. In some other implementations, the sub-7 GHz tone plan may include 2048 subcarriers associated with a 160 MHz channel bandwidth (such as in accordance with an 11be PPDU format). In such implementations, the 2048 subcarriers may include 1960 data subcarriers, 32 pilot subcarriers, 23 guard subcarriers, and 23 DC subcarriers. Still further, in some implementations, the sub-7 GHz tone plan may include 4096 subcarriers associated with a 320 MHz channel bandwidth (such as in accordance with an 11be PPDU format). In such implementations, the 4096 subcarriers may include 3920 data subcarriers, 64 pilot subcarriers, 23 guard subcarriers, and 23 DC subcarriers.

(90) The N-point IFFT **820** transforms the N modulated subcarriers **802**, from the frequency domain to the time domain, as N time-domain samples **803**. The CP adder **830** adds a cyclic prefix to the N time-domain samples **803** to produce a number of prefixed samples **804**. The DAC **840** converts the prefixed samples **804** to the TX signal **806** based on a clock signal **805**. More specifically, the frequency of the clock signal **805** controls the sampling rate (f.sub.s) of the DAC **840**. Further, the SCS associated with the TX signal **806** depends on the sampling rate f.sub.s of the DAC **840** (which is controlled by the frequency of the clock signal **805**) and the size (N.sub.IFFT) of the IFFT **820**, where

$$(91) \text{ SCS} = \frac{f_s}{N_{\text{IFFT}}}.$$

In some aspects, the clock signal **805** may be up-clocked so that the $1 \times \text{SCS}$ associated with the TX signal **806** is greater than or equal to $1.2 \text{ MHz} (f_{\text{sub.s}} N_{\text{sub.IFFT}} \times 1.2 \text{ MHz})$.

(92) Aspects of the present disclosure recognize that some existing versions of the IEEE 802.11 standard support channel bonding, whereby a PPDU can be transmitted concurrently over multiple channels to achieve gains similar to a wider bandwidth channel. For example, the IEEE 802.11ac amendment of the IEEE 802.11 standards defines a PPDU format that can be transmitted concurrently on two 80 MHz channels (also referred to as an 80+80 channel bandwidth) to achieve gains similar to a 160 MHz channel. In some aspects, the OFDM up-clocking system **800** may leverage existing channel bonding hardware to transmit PPDUs having wider bandwidths (without additional up-clocking). In such aspects, the PPDU **801** may represent a first PPDU segment configured to be transmitted over a first wireless channel. The OFDM up-clocking system **800** may further receive a second PPDU segment **801'** configured to be transmitted over a second wireless channel, where the PPDU segments **801** and **801'** collectively form a single PPDU.

(93) In some implementations, the OFDM up-clocking system **800** may include an additional tone mapper **850**, an additional N-point IFFT **860**, an additional CP adder **870**, and an additional DAC **880**. The tone mapper **850** is configured to map the second PPDU segment **801'** to N subcarriers associated with a sub-7 GHz tone plan to produce N modulated subcarriers **802'**. More specifically, the tone mappers **810** and **850** may implement the same sub-7 GHz tone plan. The N-point IFFT **860** transforms the N modulated subcarriers **802'**, from the frequency domain to the time domain,

as N time-domain samples **803'**. The CP adder **870** adds a cyclic prefix to the time-domain samples **803** to produce a number of prefixed samples **804**. The DAC **880** converts the prefixed samples **804'** to a TX signal **806'** based on the clock signal **805**. In some implementations, the TX signals **806** and **806'** can be concurrently transmitted on respective bandwidth portions of a wireless channel.

(94) FIG. **9A** shows an example PPDU **900** formatted in accordance with a legacy PPDU format. In the example of FIG. **9A**, the legacy PPDU format is an 11ac PPDU format associated with a 160 MHz channel bandwidth. More specifically, the PPDU **900** conforms to a non-High Throughput (non-HT) duplicate transmission (DUP) PPDU format. The PPDU **900** includes a PHY preamble **901** followed by a data portion **902**. The PHY preamble includes an L-STF, an L-LTF, and an L-SIG. As shown in FIG. **9A**, the PHY preamble **901** and the data portion **902** are duplicated on eight 20 MHz sub-bands spanning the 160 MHz bandwidth. As such, the bandwidth (BW) of the PPDU **900** is a multiple of the sampling rate ($f_{\text{sub.s}}$) of a clock signal used to convert the PPDU **900** from the frequency domain to the time domain ($\text{BW}=8*f_{\text{sub.s}}$). According to the 11ac PPDU format, the PPDU **900** is mapped to the data subcarriers associated with a 64-subcarrier tone plan (within each 20 MHz sub-band). In other words, the PHY preamble **901** is mapped to the same number of subcarriers as the data portion **902**.

(95) In some aspects, the PPDU **900** may be up-clocked as a CPHY PPDU for wireless communications on carrier frequencies above 7 GHz. More specifically, the PPDU **900** may be used for wireless communications when only one-sided beamforming gains are achievable between a transmitting device and a receiving device. In some implementations, the transmitting device may transmit the PPDU **900** prior to performing a beamforming training operation with the receiving device. In some other implementations, the transmitting device may transmit the PPDU **900** as part of a beamforming training operation with the receiving device. As such, the PPDU **900** may carry beam management information **905** indicating whether the PPDU **900** is associated with a beamforming training operation or various parameters associated with the beamforming training operation. Example beam management information **905** may include a PPDU type, a training direction, a beam tracking request, a training length, a countdown, a sector ID, an antenna ID, a best antenna ID, a best sector ID, a number of RX sectors or RX antennas of the transmitting device, or an SNR report, among other examples. In some implementations, the beam management information **905** may be carried in the data portion **902** (such as in a MAC payload).

(96) FIG. **9B** shows an example up-clocked PPDU **910** based on the PPDU format depicted in FIG. **9A**, according to some implementations. The PPDU **910** includes a PHY preamble **911** followed by a data portion **912**. In some aspects, the PPDU **910** may represent an up-clocking of the PPDU **900** by a factor of M. In such aspects, the PHY preamble **911** and the data portion **912** may be examples of the PHY preamble **901** and the data portion **902**, respectively, of FIG. **9A**. In some implementations, a packet extension (PE) or one or more training fields (TRNs) **913** may be added to the PPDU **910** to support enhanced features for wireless communications on carrier frequencies above 7 GHz (such as beamforming training operations). In some aspects, the up-clocking may be performed by the OFDM up-clocking system **800** of FIG. **8**.

(97) As a result of up-clocking, the PHY preamble **911**, the data portion **912**, and the PE or TRNs **913** are duplicated on eight $20*M$ MHz sub-bands spanning a $160*M$ MHz bandwidth. For example, given a $2\times$ up-clocking ratio ($M=2$), the PHY preamble **911**, the data portion **912**, and the PE or TRNs **913** are duplicated on eight 40 MHz sub-bands spanning a 320 MHz bandwidth. In some aspects, the PPDU **910** may be a CPHY PPDU that can be used for wireless communications on carrier frequencies above 7 GHz when only one-sided beamforming gains are achievable between a transmitting device and a receiving device. In some implementations, the data portion **912** may carry beam management information (such as the beam management information **905** of FIG. **9A**) indicating whether the PPDU **910** is associated with a beamforming training operation or various parameters associated with the beamforming training operation.

(98) Aspects of the present disclosure recognize that, because the CPHY PPDU format is used for wireless communications prior to (or during) the performance of a beamforming training operation between a transmitting device and a receiving device, the data portion **912** may not carry any user data. In some aspects, the overhead associated with the PPDU **910** (or delays in processing the PPDU **910**) may be reduced by moving the beam management information **905** from the MAC layer to the PHY layer. For example, L-SIG may be repurposed to carry at least a portion of the beam management information **905**. However, aspects of the present disclosure recognize that the length of L-SIG may not be sufficient to accommodate all of the beam management information **905**. In other words, the PHY preamble **911** may require one or more additional SIG fields (or symbols) to carry the beam management information **905** (in lieu of the data portion **912**).

(99) FIG. **9C** shows another example up-clocked PPDU **920** based on the PPDU format depicted in FIG. **9A**, according to some implementations. The PPDU **920** includes a PHY preamble having a first portion **921** and a second portion **922**. In contrast with the PPDU **910** of FIG. **9B**, the PPDU **920** does not include a data portion but adds two SIG symbols (SIG-A1 and SIG-A2) via the second preamble portion **922** (similar to the Very High Throughput (VHT) 11ac PPDU format). In some aspects, the PPDU **920** may represent an up-clocking of the PPDU **900** by a factor of M . In such aspects, the first preamble portion **921** may be an example of the PHY preamble **901** of FIG. **9A**. In some implementations, a PE or one or more TRNs **923** may be added to the PPDU **920** to support enhanced features for wireless communications on carrier frequencies above 7 GHz (such as beamforming training operations). In some aspects, the up-clocking may be performed by the OFDM up-clocking system **800** of FIG. **8**.

(100) As a result of up-clocking, the first preamble portion **921**, the second preamble portion **922**, and the PE or TRNs **923** are duplicated on eight $20 \times M$ MHz sub-bands spanning a $160 \times M$ MHz bandwidth. For example, given a $2 \times$ up-clocking ratio ($M=2$), the first preamble portion **921**, the second preamble portion **922**, and the PE or TRNs **923** are duplicated on eight 40 MHz sub-bands spanning a 320 MHz bandwidth. In some aspects, the PPDU **920** may be a CPHY PPDU that can be used for wireless communications on carrier frequencies above 7 GHz when only one-sided beamforming gains are achievable between a transmitting device and a receiving device. In some implementations, L-SIG, SIG-A1, and SIG-A2 may be repurposed to carry beam management information (such as the beam management information **905** of FIG. **9A**) indicating whether the PPDU **920** is associated with a beamforming training operation or various parameters associated with the beamforming training operation.

(101) FIG. **9D** shows another example up-clocked PPDU **930** based on the PPDU format depicted in FIG. **9A**, according to some implementations. The PPDU **930** includes a PHY preamble having a first portion **931** and a second portion **932**. In contrast with the PPDU **910** of FIG. **9B**, the PPDU **930** does not include a data portion but adds a repetition of L-SIG (RL-SIG) and two more SIG symbols (SIG1 and SIG2) via the second preamble portion **932** (similar to the 11be PPDU format). In some aspects, the PPDU **930** may represent an up-clocking of the PPDU **900** by a factor of M . In such aspects, the first preamble portion **931** may be an example of the PHY preamble **901** of FIG. **9A**. In some implementations, a PE or one or more TRNs **933** may be added to the PPDU **930** to support enhanced features for wireless communications on carrier frequencies above 7 GHz (such as beamforming training operations). In some aspects, the up-clocking may be performed by the OFDM up-clocking system **800** of FIG. **8**.

(102) As a result of up-clocking, the first preamble portion **931**, the second preamble portion **932**, and the PE or TRNs **933** are duplicated on eight $20 \times M$ MHz sub-bands spanning a $160 \times M$ MHz bandwidth. For example, given a $2 \times$ up-clocking ratio ($M=2$), the first preamble portion **931**, the second preamble portion **932**, and the PE or TRNs **933** are duplicated on eight 40 MHz sub-bands spanning a 320 MHz bandwidth. In some aspects, the PPDU **930** may be a CPHY PPDU that can be used for wireless communications on carrier frequencies above 7 GHz when only one-sided beamforming gains are achievable between a transmitting device and a receiving device. In some

implementations, L-SIG, RL-SIG, SIG1, and SIG2 may be repurposed to carry beam management information (such as the beam management information **905** of FIG. **9A**) indicating whether the PPDU **930** is associated with a beamforming training operation or various parameters associated with the beamforming training operation.

(103) FIG. **10A** shows an example PPDU **1000** formatted in accordance with a legacy PPDU format. In the example of FIG. **10A**, the legacy PPDU format is an 11be PPDU format associated with a 20 MHz channel bandwidth. More specifically, the PPDU **1000** conforms to an extended range (ER) single-user (SU) PPDU format. The PPDU **1000** includes a PHY preamble, having a first portion **1001** and a second portion **1002**, followed by a data portion **1003** and a PE **1004**. The first preamble portion **1001** includes an L-STF, an L-LTF, an L-SIG, an RL-SIG, and four non-legacy signal fields (SIG1-SIG4). The second preamble portion **1002** includes a non-legacy short training field (STF) and one or more non-legacy long training fields (LTFs).

(104) The IEEE 802.11be amendment of the IEEE 802.11 standard defines each of the non-legacy signal fields SIG1-SIG4 as a respective symbol of a universal signal field (U-SIG) and defines the remaining non-legacy fields STF and LTFs as Extremely High Throughput (EHT) fields EHT-STF and EHT-LTFs, respectively. Further, the STF sequence associated with L-STF is repeated ($2\times$) in the time domain to produce an “extended L-STF.” According to the 11be PPDU format, the data portion **1003** (and the PE **1004**) is mapped to each contiguous data subcarrier associated with a 256-subcarrier tone plan. In contrast, L-STF is mapped to every 4^{sup}.th data subcarrier associated with a 64-subcarrier tone plan while the remainder of the first preamble portion **1001** is mapped to each contiguous data subcarrier associated with the 64-subcarrier tone plan. Thus, while the bandwidth (BW) of the PPDU **1000** is equal to the sampling rate ($f_{\text{sub.s}}$) of a clock signal used to convert the PPDU **1000** from the frequency domain to the time domain ($BW=f_{\text{sub.s}}$), the SCS associated with L-STF is $4\times$ larger than the SCS associated with the data portion **1003**.

(105) In some aspects, the PPDU **1000** may be up-clocked as a CPHY PPDU for wireless communications on carrier frequencies above 7 GHz. More specifically, the PPDU **1000** may be used for wireless communications when only one-sided beamforming gains are achievable between a transmitting device and a receiving device. In some implementations, the transmitting device may transmit the PPDU **1000** prior to performing a beamforming training operation with the receiving device. In some other implementations, the transmitting device may transmit the PPDU **1000** as part of a beamforming training operation with the receiving device. As such, the PPDU **1000** may carry beam management information **1005** indicating whether the PPDU **1000** is associated with a beamforming training operation or various parameters associated with the beamforming training operation (such as described with reference to FIG. **9A**). In some implementations, the beam management information **1005** may be carried in one or more of the SIG fields L-SIG, RL-SIG, or SIG1-SIG4. In such implementations, the data portion **1003** and the PHY preamble fields associated therewith (such as the second preamble portion **1002**) can be omitted from the PPDU **1000** to reduce overhead.

(106) FIG. **10B** shows an example up-clocked PPDU **1010** based on the PPDU format depicted in FIG. **10A**, according to some implementations. In some aspects, the PPDU **1010** may be a CPHY PPDU that can be used for wireless communications on carrier frequencies above 7 GHz when only one-sided beamforming gains are achievable between a transmitting device and a receiving device. The PPDU **1010** includes a PHY preamble **1011** followed by a PE or one or more TRNs **1014**. In some aspects, the PPDU **1010** may represent an up-clocking of the PPDU **1000** by a factor of M . In such aspects, the PHY preamble **1011** and the PE or TRNs **1014** may be examples of the first preamble portion **1001** and the PE **1004**, respectively, of FIG. **10A**. However, in contrast with the PPDU format depicted in FIG. **10A**, the second preamble portion **1002** and the data portion **1003** of FIG. **10A** are omitted from the PPDU **1010**. In some aspects, the up-clocking may be performed by the OFDM up-clocking system **800** of FIG. **8**.

(107) As described with reference to FIG. **10A**, the SCS associated with L-STF is $4\times$ larger than

the SCS associated with the data portion **1003**. Thus, the first preamble portion **1001** can be up-clocked by a factor of $M/4$, and duplicated $4\times$ in the frequency domain, to achieve an SCS in L-STF greater than or equal to 1.2 MHz. In some implementations, the OFDM up-clocking system **800** may up-clock the first preamble portion **1001** by a factor of $M/4$ to achieve a PPDU bandwidth equal to $20\times M$ MHz. As a result, the PHY preamble **1011** is duplicated on four $5\times M$ MHz sub-bands spanning the $20\times M$ MHz bandwidth. For example, given a $16\times$ up-clocking ratio ($M=16$), the PHY preamble **1011** is duplicated on four 80 MHz sub-bands spanning the 320 MHz bandwidth. Duplicating the PHY preamble **1011** $4\times$ in the frequency domain results in a 6 dB frequency combining gain at the receiving device. Moreover, repeating various fields of the PHY preamble **1011** in the time domain (such as L-STF, L-LTF, and each of the SIG fields or symbols) results in an additional 3 dB gain at the receiving device. Such frequency-domain duplication and time-domain repetition of various fields of the PPDU **1010** may result in a combined gain of 9 dB at the receiving device, which can help compensate for one-sided beamforming gains.

(108) FIG. **11A** shows an example PPDU **1100** formatted in accordance with a legacy PPDU format. In the example of FIG. **11A**, the legacy PPDU format is an 11be PPDU format associated with a 20 MHz channel bandwidth. The PPDU **1100** includes a PHY preamble, having a first portion **1101** and a second portion **1102**, followed by a data portion **1103** and a PE **1104**. The first preamble portion **1101** includes an L-STF, an L-LTF, an L-SIG, an RL-SIG, a first non-legacy signal field (SIG1) and a second non-legacy signal field (SIG2). The second preamble portion **1102** includes a non-legacy short training field (STF) and one or more non-legacy long training fields (LTFs).

(109) The IEEE 802.11be amendment of the IEEE 802.11 standard defines the first non-legacy signal field SIG1 as a universal signal field (U-SIG) and defines the remaining non-legacy fields SIG2, STF, and LTFs as EHT fields EHT-SIG, EHT-STF, and EHT-LTFs, respectively. According to the 11be PPDU format, the data portion **1103** (and the PE **1104**) is mapped to each contiguous data subcarrier associated with a 256-subcarrier tone plan. In contrast, L-STF is mapped to every 4^{sup}.th data subcarrier associated with a 64-subcarrier tone plan while the remainder of the first preamble portion **1101** is mapped to each contiguous data subcarrier associated with the 64-subcarrier tone plan. Thus, while the bandwidth (BW) of the PPDU **1100** is equal to the sampling rate ($f_{\text{sub.s}}$) of a clock signal used to convert the PPDU **1100** from the frequency domain to the time domain ($BW=f_{\text{sub.s}}$), the SCS associated with L-STF is $4\times$ larger than the SCS associated with the data portion **1103**.

(110) In some aspects, the PPDU **1100** may be up-clocked as a DPHY PPDU for wireless communications on carrier frequencies above 7 GHz. More specifically, the PPDU **1100** may be used for wireless communications when full beamforming gains are achievable between a transmitting device and a receiving device. In other words, the transmitting device may transmit the PPDU **1100** after performing a beamforming training operation with the receiving device. In some other implementations, the transmitting device may transmit the PPDU **1100** as part of a beamforming training operation with the receiving device (such as when the transmitting device trains its TX antennas for TX beamforming while the receiving device concurrently trains its RX antennas for RX beamforming) or a beam refinement procedure associated with a beam tracking request. In some implementations, the PPDU **1100** may carry beam management information **1105** indicating whether the PPDU **1100** is associated with a beamforming training operation or various parameters associated with the beamforming training operation (such as described with reference to FIG. **9A**). In some implementations, the beam management information **1105** may be carried in one or more of the SIG fields L-SIG, RL-SIG, SIG1, or SIG2.

(111) In some implementations, the training sequence associated with L-STF may be replaced with a Golay sequence to simplify packet detection. For example, Golay sequences are sequence of bipolar symbols (+1 or -1) that are often used for channel estimation due to their auto-correlation characteristics. According to the 11be PPDU format, the non-legacy STF (in the second preamble

portion **1102**) provides AGC and CFO estimation for the data portion **1103**. However, aspects of the present disclosure recognize that because the channel (or beam) does not change between the transmission of the first preamble portion **1101** and the transmission of the data portion **1103**, a receiving device can perform AGC and CFO estimation for the data portion **1103** based on L-STF (in the first preamble portion **1101**). In some aspects, the non-legacy STF can be “turned off” or otherwise disregarded in the PPDU **1100**. In some implementations, turned-off fields may carry padding bits or non-essential information. In some other implementations, turned-off fields may be omitted entirely from the PPDU **1100**.

(112) FIG. **11B** shows an example up-clocked PPDU **1110** based on the PPDU format depicted in FIG. **11A**, according to some implementations. In some aspects, the PPDU **1110** may be a DPHY PPDU that can be used for wireless communications on carrier frequencies above 7 GHz when full beamforming gains are achievable between a transmitting device and a receiving device. The PPDU **1110** includes a PHY preamble, having a first portion **1111** and a second portion **1112**, followed by a data portion **1113** and a PE or one or more TRNs **1114**. In some aspects, the PPDU **1110** may represent an up-clocking of the PPDU **1100** by a factor of M . In such aspects, the first preamble portion **1111**, the second preamble portion **1112**, the data portion **1113**, and the PE or TRNs **1114** may be examples of the first preamble portion **1101**, the second preamble portion **1102**, the data portion **1103**, and the PE **1104**, respectively, of FIG. **11A**. In some aspects, the up-clocking may be performed by the OFDM up-clocking system **800** of FIG. **8**.

(113) As described with reference to FIG. **11A**, the SCS associated with L-STF is $4\times$ larger than the SCS associated with the data portion **1113**. Thus, the first preamble portion **1101** can be up-clocked by a factor of $M/4$, and duplicated $4\times$ in the frequency domain, to achieve the same SCS in L-STF as in the data portion **1103**. In some implementations, the OFDM up-clocking system **800** may up-clock the first preamble portion **1101** by a factor of $M/4$ and may up-clock the remainder of the PPDU **1100** by a factor of M to produce the PPDU **1110**. As a result, the second preamble portion **1112** and the data portion **1113** are spread over a $20*M$ MHz bandwidth and the first preamble portion **1111** is duplicated on four $5*M$ MHz sub-bands spanning the $20*M$ MHz bandwidth. For example, given a $16\times$ up-clocking ratio ($M=16$), the second preamble portion **1112** and the data portion **1113** are spread over a 320 MHz bandwidth while the first preamble portion **1111** is duplicated on four 80 MHz sub-bands spanning the 320 MHz bandwidth.

(114) As described with reference to FIG. **11A**, the non-legacy STF (in the second preamble portion **1112**) may be turned off to reduce the overhead associated with the PPDU **1110**. In the example of FIG. **11B**, the non-legacy LTFs are retained in the second preamble portion **1112**. The non-legacy LTFs provide channel estimation for the data portion **1113**. Aspects of the present disclosure recognize that because the channel (or beam) does not change between the transmission of the first preamble portion **1111** and the transmission of the data portion **1113**, a receiving device may estimate the channel associated with the data portion **1113** based on L-LTF (in the first preamble portion **1111**). In some aspects, the non-legacy LTFs can be turned off or otherwise disregarded to further reduce the overhead associated with the PPDU **1110** when the PPDU **1100** is transmitted on a single spatial stream ($N_{\text{sub.SS}}=1$). In some implementations, the non-legacy LTFs may carry padding bits or non-essential information. In some other implementations, the non-legacy LTFs may be omitted entirely from the PPDU **1110**.

(115) Aspects of the present disclosure further recognize that L-LTF and the non-legacy LTFs are mapped to different subcarriers, according to different tone plans. As described with reference to FIG. **11A**, L-LTF is mapped to the (52) data subcarriers associated with a 64-point IFFT (and duplicated $4\times$ in the frequency domain) whereas the non-legacy LTFs are mapped to the (234) data subcarriers associated with a 256-point IFFT. As such, L-LTF is mapped to fewer data subcarriers (across the bandwidth of the PPDU **1110**) than the non-legacy LTFs. In some implementations, the receiving device may need to interpolate the missing data subcarriers (such as the data subcarriers to which the data portion **1113** is mapped but L-LTF is not) when using the existing L-LTF to

estimate the channel associated with the data portion **1113**. However, such channel interpolations may result in a loss of performance. In some other implementations, L-LTF may be modified or redesigned to provide more accurate channel estimation for the data portion **1113**.

(116) FIG. **11C** shows another example up-clocked PPDU **1120** based on the PPDU format depicted in FIG. **11A**, according to some implementations. In some aspects, the PPDU **1120** may be a DPHY PPDU that can be used for wireless communications on carrier frequencies above 7 GHz when full beamforming gains are achievable between a transmitting device and a receiving device. The PPDU **1120** includes a PHY preamble, having a first portion **1121** and a second portion **1122**, followed by a data portion **1123** and a PE or one or more TRNs **1124**. In some aspects, the PPDU **1120** may represent an up-clocking of the PPDU **1100** by a factor of M . In such aspects, the first preamble portion **1121**, the second preamble portion **1122**, the data portion **1123**, and the PE or TRNs **1124** may be examples of the first preamble portion **1101**, the second preamble portion **1102**, the data portion **1103**, and the PE **1104**, respectively, of FIG. **11A**. In some aspects, the up-clocking may be performed by the OFDM up-clocking system **800** of FIG. **8**.

(117) As described with reference to FIG. **11A**, the SCS associated with L-STF is $4\times$ larger than the SCS associated with the data portion **1123**. Thus, the first preamble portion **1101** can be up-clocked by a factor of $M/4$, and duplicated $4\times$ in the frequency domain, to achieve the same SCS in L-STF as in the data portion **1103**. In some implementations, the OFDM up-clocking system **800** may up-clock the first preamble portion **1101** by a factor of $M/4$ and may up-clock the remainder of the PPDU **1100** by a factor of M to produce the PPDU **1120**. As a result, the second preamble portion **1122** and the data portion **1123** are spread over a $20*M$ MHz bandwidth and the PHY preamble **1121** is duplicated on four $5*M$ MHz sub-bands spanning the $20*M$ MHz bandwidth. For example, given a $16\times$ up-clocking ratio ($M=16$), the second preamble portion **1122** and the data portion **1123** are spread over a 320 MHz bandwidth and the first preamble portion **1121** are duplicated on four 80 MHz sub-bands spanning the 320 MHz bandwidth.

(118) As described with reference to FIG. **11A**, the non-legacy STF (in the second preamble portion **1122**) may be turned off to reduce the overhead associated with the PPDU **1120**. In some implementations, the non-legacy LTFs (in the second preamble portion **1122**) also may be turned off to further reduce the overhead associated with the PPDU **1120**. In the example of FIG. **11C**, L-LTF may be populated on the same subcarriers as the data portion **1123** to compensate for the lack of non-legacy LTFs. As described with reference to FIG. **11B**, existing L-LTFs are mapped to fewer data subcarriers than the data portion **1123** due to the differences in tone plans associated therewith. More specifically, the tone plan associated with the first preamble portion **1121** includes guard subcarriers at the boundaries of each $5*M$ MHz sub-band. In some aspects, non-zero values may be modulated on at least some of the guard subcarriers associated with the data subcarriers to which L-LTF is mapped. In other words, L-LTF may include non-zero values that are mapped to each data subcarrier of its associated tone plan and a number of the guard subcarriers at each sub-band boundary (which coincide with data subcarriers to which the data portion **1123** is mapped).

(119) Aspects of the present disclosure recognize that the mapping of non-zero values to guard subcarriers can be implemented by existing WLAN hardware (which operates on 20 MHz bandwidth portions). However, the resulting LTF values may increase the peak-to-average power ratio (PAPR) of the PPDU **1120**. Aspects of the present disclosure further recognize that additional LTFs may be needed to support multiple spatial streams. More specifically, the application of a P-matrix requires the LTF values to be the same for each spatial stream. Thus, in some implementations, the non-legacy LTFs may be included in the second preamble portion **1122** only when the PPDU **1120** is to be transmitted over more than one spatial stream ($N_{\text{sub.SS}} > 1$). In some other implementations, a P-matrix applied directly to L-LTF (in the first preamble portion **1121**) to produce two non-identical OFDM symbols that can support up to two spatial streams. In such implementations, the non-legacy LTFs may be included in the second preamble portion **1122** only when the PPDU **1120** is to be transmitted over more than two spatial streams ($N_{\text{sub.SS}} > 2$).

(120) FIG. 11D shows another example up-clocked PPDU **1130** based on the PPDU format depicted in FIG. 11A, according to some implementations. In some aspects, the PPDU **1130** may be a DPHY PPDU that can be used for wireless communications on carrier frequencies above 7 GHz when full beamforming gains are achievable between a transmitting device and a receiving device. The PPDU **1130** includes a PHY preamble, having a first portion **1131** and a second portion **1132**, followed by a data portion **1133** and a PE or one or more TRNs **1134**. In some aspects, the PPDU **1130** may represent an up-clocking of the PPDU **1100** by a factor of M . However, in contrast with the PPDU **1100** of FIG. 11A, the first preamble portion **1131** includes a non-legacy long training field (LTF) which replaces L-LTF and is mapped to the same data subcarriers (according to the same tone plan) as the data portion **1133**. In some aspects, the up-clocking may be performed by the OFDM up-clocking system **800** of FIG. 8.

(121) As described with reference to FIG. 11A, the SCS associated with L-STF is $4\times$ larger than the SCS associated with the data portion **1133**. Thus, the first preamble portion **1101** (excluding LTF) can be up-clocked by a factor of $M/4$, and duplicated $4\times$ in the frequency domain, to achieve the same SCS in L-STF as in the data portion **1103**. In some implementations, the OFDM up-clocking system **800** may up-clock the first preamble portion **1101** (excluding LTF) by a factor of $M/4$ and may up-clock the remainder of the PPDU **1100** (including LTF in the first preamble portion **1101**) by a factor of M to produce the PPDU **1130**. As a result, the non-legacy LTF in the first preamble portion **1131**, the second preamble portion **1132**, and the data portion **1133** are spread over a $20*M$ MHz bandwidth and the remainder of the first preamble portion **1131** is duplicated on four $5*M$ MHz sub-bands spanning the $20*M$ MHz bandwidth. For example, given a $16\times$ up-clocking ratio ($M=16$), the non-legacy LTF in the first preamble portion **1131**, the second preamble portion **1132**, and the data portion **1133** are spread over a 320 MHz bandwidth while the remainder of the first preamble portion **1131** is duplicated on four 80 MHz sub-bands spanning the 320 MHz bandwidth.

(122) As described with reference to FIG. 11A, the non-legacy STF (in the second preamble portion **1132**) may be turned off to reduce the overhead associated with the PPDU **1130**. In some implementations, the non-legacy LTFs (in the second preamble portion **1132**) also may be turned off to further reduce the overhead associated with the PPDU **1130**. In the example of FIG. 11D, the non-legacy LTF in the first preamble portion **1131** is populated on the same subcarriers as the data portion **1133** to compensate for the lack of non-legacy LTFs in the second preamble portion **1132**. In some implementations, the non-legacy LTF may be optimized for the bandwidth associated with the PPDU **1130**. With reference for example to FIG. 11C, the non-legacy LTF in the first preamble portion **1131** may yield a lower PAPR than the L-LTF mapping in the first preamble portion **1121** of the PPDU **1120**.

(123) Aspects of the present disclosure further recognize that additional LTFs may be needed to support multiple spatial streams (such as described with reference to FIG. 11C). Thus, in some implementations, additional non-legacy LTFs may be included in the second preamble portion **1132** only when the PPDU **1130** is to be transmitted over multiple spatial streams ($N_{\text{sub.SS}} > 1$). In some other implementations, a P-matrix may be applied directly to the non-legacy LTF in the first preamble portion **1131** to produce two non-identical OFDM symbols that can support up to two spatial streams. In such implementations, additional non-legacy LTFs may be included in the second preamble portion **1132** only when the PPDU **1130** is to be transmitted over more than two spatial streams ($N_{\text{sub.SS}} > 2$).

(124) FIG. 12A shows an example PPDU **1200** formatted in accordance with a legacy PPDU format. In the example of FIG. 12A, the legacy PPDU format is an 11ac PPDU format associated with an 80 MHz channel bandwidth. The PPDU **1200** includes a PHY preamble, having a first portion **1201** and a second portion **1202**, followed by a data portion **1203**. The first preamble portion **1201** includes an L-STF, an L-LTF, an L-SIG, and a first non-legacy signal field (SIG-A) spanning a first OFDM symbol (SIG-A1) and a second OFDM symbol (SIG-A2). The second preamble portion **1202** includes a non-legacy short training field (STF), one or more non-legacy

long training fields (LTFs), and a second non-legacy signal field (SIG-B).

(125) The IEEE 802.11ac amendment of the IEEE 802.11 standard defines the non-legacy fields SIG-A1, SIG-A2, STF, LTFs, and SIG-B as VHT fields VHT-SIG-A1, VHT-SIG-A2, VHT-STF, VHT-LTFs, and VHT-SIG-B, respectively. According to the 11ac PPDU format, the data portion **1203** is mapped to each contiguous data subcarrier associated with a 256-subcarrier tone plan spanning the 80 MHz bandwidth. In contrast, the first preamble portion **1201** is duplicated on four 20 MHz sub-bands spanning the 80 MHz bandwidth. More specifically, L-STF is mapped to every 4^{sup}.th data subcarrier associated with a 64-subcarrier tone plan while the remainder of the first preamble portion **1201** is mapped to each contiguous data subcarrier associated with the 64-subcarrier tone plan. Thus, the bandwidth (BW) of the PPDU **1200** is equal to the sampling rate ($f_{\text{sub.s}}$) of a clock signal used to convert the PPDU **1200** from the frequency domain to the time domain ($\text{BW} = f_{\text{sub.s}}$), and the SCS associated with L-STF is equal to the SCS associated with the data portion **1203**.

(126) In some aspects, the PPDU **1200** may be up-clocked as a DPHY PPDU for wireless communications on carrier frequencies above 7 GHz. More specifically, the PPDU **1200** may be used for wireless communications when full beamforming gains are achievable between a transmitting device and a receiving device. In other words, the transmitting device may transmit the PPDU **1200** after performing a beamforming training operation with the receiving device. In some implementations, the PPDU **1200** may carry beam management information **1205** indicating whether the PPDU **1200** is associated with a beamforming training operation or various parameters associated with the beamforming training operation (such as described with reference to FIG. 9A). In some implementations, the beam management information **1205** may be carried in one or more of the SIG fields in the first preamble portion **1201** (such as L-SIG, SIG-A1, or SIG-A2).

(127) In some implementations, the training sequence associated with L-STF may be replaced with a Golay sequence to simplify packet detection (such as described with reference to FIG. 11A). In some aspects, the non-legacy STF can be turned off to reduce the overhead associated with the PPDU **1200** (such as described with reference to FIG. 11A). According to the 11ac PPDU format, SIG-B (in the second preamble portion **1202**) provides signaling for multi-user (MU) communications. However, aspects of the present disclosure recognize that the PPDU **1200** may not support MU communications due to the narrow beams required to overcome path loss on carrier frequencies above 7 GHz (such as described with reference to FIG. 6). In some aspects, SIG-B also may be turned off to further reduce the overhead associated with the PPDU **1200**. In some implementations, turned-off fields may carry padding bits or non-essential information. In some other implementations, turned-off fields may be omitted entirely from the PPDU **1200**.

(128) FIG. 12B shows an example up-clocked PPDU **1210** based on the PPDU format depicted in FIG. 12A, according to some implementations. In some aspects, the PPDU **1210** may be a DPHY PPDU that can be used for wireless communications on carrier frequencies above 7 GHz when full beamforming gains are achievable between a transmitting device and a receiving device. The PPDU **1210** includes a PHY preamble, having a first portion **1211** and a second portion **1212**, followed by a data portion **1213**. In some aspects, the PPDU **1210** may represent an up-clocking of the PPDU **1200** by a factor of M. In such aspects, the first preamble portion **1211**, the second preamble portion **1212**, and the data portion **1213** may be examples of the first preamble portion **1201**, the second preamble portion **1202**, and the data portion **1203**, respectively, of FIG. 12A. In some aspects, the up-clocking may be performed by the OFDM up-clocking system **800** of FIG. 8.

(129) In some implementations, a PE or one or more TRNs **1214** may be added to the PPDU **1210** to support enhanced features for wireless communications on carrier frequencies above 7 GHz (such as beamforming training operations). As a result of up-clocking, the second preamble portion **1212** and the data portion **1213** are spread over an $80 \times M$ MHz bandwidth and the first preamble portion **1211** is duplicated on four $20 \times M$ MHz sub-bands spanning the $80 \times M$ MHz bandwidth. For example, given a $4 \times$ up-clocking ratio ($M=4$), the second preamble portion **1212** and the data

portion **1213** are spread over a 320 MHz bandwidth while the first preamble portion **1211** is duplicated on four 80 MHz sub-bands spanning the 320 MHz bandwidth.

(130) As described with reference to FIG. **12A**, the non-legacy STF and SIG-B (in the second preamble portion **1212**) may be turned off to reduce the overhead associated with the PPDU **1210**. In the example of FIG. **12B**, the non-legacy LTFs are retained in the second preamble portion **1212**. In some other aspects, the non-legacy LTFs can be turned off or otherwise disregarded to further reduce the overhead associated with the PPDU **1210** (such as described with reference to FIG. **11B**). In some implementations, the receiving device may estimate the channel associated with the data portion **1213** based on the existing L-LTF in the first preamble portion **1211** (such as through interpolation of the missing data subcarriers). In some other implementations, L-LTF may be modified or redesigned to provide more accurate channel estimation for the data portion **1213**.

(131) FIG. **12C** shows another example up-clocked PPDU **1220** based on the PPDU format depicted in FIG. **12A**, according to some implementations. In some aspects, the PPDU **1220** may be a DPHY PPDU that can be used for wireless communications on carrier frequencies above 7 GHz when full beamforming gains are achievable between a transmitting device and a receiving device. The PPDU **1220** includes a PHY preamble, having a first portion **1221** and a second portion **1222**, followed by a data portion **1223**. In some aspects, the PPDU **1220** may represent an up-clocking of the PPDU **1200** by a factor of M . In such aspects, the first preamble portion **1221**, the second preamble portion **1222**, and the data portion **1223** may be examples of the first preamble portion **1201**, the second preamble portion **1202**, and the data portion **1203**, respectively, of FIG. **12A**. In some aspects, the up-clocking may be performed by the OFDM up-clocking system **800** of FIG. **8**.

(132) In some implementations, a PE or one or more TRNs **1224** may be added to the PPDU **1220** to support enhanced features for wireless communications on carrier frequencies above 7 GHz (such as beamforming training operations). As a result of up-clocking, the second preamble portion **1222** and the data portion **1223** are spread over an $80 \times M$ MHz bandwidth and the first preamble portion **1221** is duplicated on four $20 \times M$ MHz sub-bands spanning the $80 \times M$ MHz bandwidth. For example, given a $4 \times$ up-clocking ratio ($M=4$), the second preamble portion **1222** and the data portion **1223** are spread over a 320 MHz bandwidth while the first preamble portion **1221** is duplicated on four 80 MHz sub-bands spanning the 320 MHz bandwidth.

(133) As described with reference to FIG. **12A**, the non-legacy STF and SIG-B (in the second preamble portion **1222**) may be turned off to reduce the overhead associated with the PPDU **1220**. In some implementations, the non-legacy LTFs (in the second preamble portion **1222**) also may be turned off to further reduce the overhead associated with the PPDU **1220**. In the example of FIG. **12C**, L-LTF may be populated on the same subcarriers as the data portion **1223** to compensate for the lack of non-legacy LTFs. In some aspects, non-zero values may be modulated on at least some of the guard subcarriers associated with the data subcarriers to which L-LTF is mapped (such as described with reference to FIG. **11C**). In some implementations, the non-legacy LTFs may be included in the second preamble portion **1222** only when the PPDU **1220** is to be transmitted over multiple spatial streams ($N_{\text{sub.SS}} > 1$). In some other implementations, a P-matrix may be applied directly to L-LTF (in the first preamble portion **1221**) to produce two non-identical OFDM symbols. In such implementations, the non-legacy LTFs may be included in the second preamble portion **1222** only when the PPDU **1220** is to be transmitted over more than two spatial streams ($N_{\text{sub.SS}} > 2$).

(134) FIG. **12D** shows another example up-clocked PPDU **1230** based on the PPDU format depicted in FIG. **12A**, according to some implementations. In some aspects, the PPDU **1230** may be a DPHY PPDU that can be used for wireless communications on carrier frequencies above 7 GHz when full beamforming gains are achievable between a transmitting device and a receiving device. The PPDU **1230** includes a PHY preamble, having a first portion **1231** and a second portion **1232**, followed by a data portion **1233**. In some aspects, the PPDU **1230** may represent an up-

clocking of the PPDU **1200** by a factor of M . However, in contrast with the PPDU **1200** of FIG. **12A**, the first preamble portion **1231** includes a non-legacy long training field (LTF) which replaces L-LTF and is mapped to the same data subcarriers (according to the same tone plan) as the data portion **1233**. In some aspects, the up-clocking may be performed by the OFDM up-clocking system **800** of FIG. **8**.

(135) In some implementations, a PE or one or more TRNs **1234** may be added to the PPDU **1230** to support enhanced features for wireless communications on carrier frequencies above 7 GHz (such as beamforming training operations). As a result of up-clocking, the non-legacy LTF in the first preamble portion **1231**, the second preamble portion **1232**, and the data portion **1233** are spread over an $80 \times M$ MHz bandwidth and the first preamble portion **1231** (excluding LTF) is duplicated on four $20 \times M$ MHz sub-bands spanning the $80 \times M$ MHz bandwidth. For example, given a $4 \times$ up-clocking ratio ($M=4$), the non-legacy LTF in the first preamble portion **1231**, the second preamble portion **1232**, and the data portion **1233** are spread over a 320 MHz bandwidth while the first preamble portion **1231** (excluding LTF) is duplicated on four 80 MHz sub-bands spanning the 320 MHz bandwidth.

(136) As described with reference to FIG. **12A**, the non-legacy STF and SIG-B (in the second preamble portion **1232**) may be turned off to reduce the overhead associated with the PPDU **1230**. In some implementations, the non-legacy LTFs (in the second preamble portion **1232**) also may be turned off to further reduce the overhead associated with the PPDU **1230**. In the example of FIG. **12D**, the non-legacy LTF in the first preamble portion **1231** is populated on the same subcarriers as the data portion **1233** to compensate for the lack of non-legacy LTFs in the second preamble portion **1232**. In some implementations, the non-legacy LTF may be optimized for the bandwidth associated with the PPDU **1230** (such as described with reference to FIG. **11D**). In some implementations, additional non-legacy LTFs may be added to the second preamble portion **1232** only when the PPDU **1230** is to be transmitted over multiple spatial streams ($N_{\text{sub.SS}} > 1$). In some other implementations, a P-matrix may be applied directly to the non-legacy LTF in the first preamble portion **1231** to produce two non-identical OFDM symbols. In such implementations, additional non-legacy LTFs may be included in the second preamble portion **1232** only when the PPDU **1230** is to be transmitted over more than two spatial streams ($N_{\text{sub.SS}} > 2$).

(137) FIG. **13A** shows an example PPDU **1300** formatted in accordance with a legacy PPDU format. In the example of FIG. **13A**, the legacy PPDU format is an 11ac PPDU format associated with an $80+80$ MHz channel bandwidth. The PPDU **1300** includes a PHY preamble, having a first portion **1301** and a second portion **1302**, followed by a data portion **1303**. The first preamble portion **1301** includes an L-STF, an L-LTF, an L-SIG, and a first non-legacy signal field (SIG-A) spanning a first OFDM symbol (SIG-A1) and a second OFDM symbol (SIG-A2). The second preamble portion **1302** includes a non-legacy short training field (STF), one or more non-legacy long training fields (LTFs), and a second non-legacy signal field (SIG-B).

(138) The IEEE 802.11ac amendment of the IEEE 802.11 standard defines the non-legacy fields SIG-A1, SIG-A2, STF, LTFs, and SIG-B as VHT fields VHT-SIG-A1, VHT-SIG-A2, VHT-STF, VHT-LTFs, and VHT-SIG-B, respectively. According to the 11ac PPDU format, the data portion **1303** is mapped to each contiguous data subcarrier associated with a 256-subcarrier tone plan spanning a first 80 MHz bandwidth and to each contiguous data subcarrier associated with a 256-subcarrier tone plan spanning a second 80 MHz bandwidth. In contrast, the first preamble portion **1301** is duplicated on four 20 MHz sub-bands spanning the first 80 MHz bandwidth and another four 20 MHz sub-bands spanning the second 80 MHz bandwidth. More specifically, L-STF is mapped to every 4^{sup}.th data subcarrier associated with a 64-subcarrier tone plan while the remainder of the first preamble portion **1301** is mapped to each contiguous data subcarrier associated with the 64-subcarrier tone plan. With reference for example to FIG. **12A**, each 80 MHz bandwidth portion of the PPDU **1300** mirrors the format of the PPDU **1200**.

(139) In some aspects, the PPDU **1300** may be up-clocked as a DPHY PPDU for wireless

communications on carrier frequencies above 7 GHz. More specifically, the PPDU **1300** may be used for wireless communications when full beamforming gains are achievable between a transmitting device and a receiving device. In other words, the transmitting device may transmit the PPDU **1300** after performing a beamforming training operation with the receiving device. In some implementations, the PPDU **1300** may carry beam management information **1305** indicating whether the PPDU **1300** is associated with a beamforming training operation or various parameters associated with the beamforming training operation (such as described with reference to FIG. **9A**). In some implementations, the beam management information **1305** may be carried in one or more of the SIG fields in the first preamble portion **1301** (such as L-SIG, SIG-A1, or SIG-A2).

(140) In some implementations, the training sequence associated with L-STF may be replaced with a Golay sequence to simplify packet detection (such as described with reference to FIG. **11A**). In some aspects, the non-legacy STF can be turned off to reduce the overhead associated with the PPDU **1300** (such as described with reference to FIG. **11A**). In some aspects, SIG-B also may be turned off to further reduce the overhead associated with the PPDU **1300** (such as described with reference to FIG. **12A**). In some implementations, turned-off fields may carry padding bits or non-essential information. In some other implementations, turned-off fields may be omitted entirely from the PPDU **1300**.

(141) FIG. **13B** shows an example up-clocked PPDU **1310** based on the PPDU format depicted in FIG. **13A**, according to some implementations. In some aspects, the PPDU **1310** may be a DPHY PPDU that can be used for wireless communications on carrier frequencies above 7 GHz when full beamforming gains are achievable between a transmitting device and a receiving device. The PPDU **1310** includes a PHY preamble, having a first portion **1311** and a second portion **1312**, followed by a data portion **1313**. In some aspects, the PPDU **1310** may represent an up-clocking of the PPDU **1300** by a factor of M . In such aspects, the first preamble portion **1311**, the second preamble portion **1312**, and the data portion **1313** may be examples of the first preamble portion **1301**, the second preamble portion **1302**, and the data portion **1303**, respectively, of FIG. **13A**. In some aspects, the up-clocking may be performed by the OFDM up-clocking system **800** of FIG. **8**.

(142) In some implementations, a PE or one or more TRNs **1314** may be added to the PPDU **1310** to support enhanced features for wireless communications on carrier frequencies above 7 GHz (such as beamforming training operations). As a result of up-clocking, the second preamble portion **1312** and the data portion **1313** are spread over two $80 \times M$ MHz bandwidth portions, and the first preamble portion **1311** is duplicated on four $20 \times M$ MHz sub-bands spanning the first $80 \times M$ MHz bandwidth and another four $20 \times M$ MHz sub-bands spanning the second $80 \times M$ MHz bandwidth. For example, given a $4 \times$ up-clocking ratio ($M=4$), the second preamble portion **1312** and the data portion **1313** are spread over a 640 MHz bandwidth while the first preamble portion **1311** is duplicated on eight 80 MHz sub-bands spanning the 640 MHz bandwidth. With reference for example to FIG. **12B**, each 80 MHz bandwidth portion of the PPDU **1310** mirrors the format of the PPDU **1210**.

(143) As described with reference to FIG. **13A**, the non-legacy STF and SIG-B (in the second preamble portion **1312**) may be turned off to reduce the overhead associated with the PPDU **1310**. In the example of FIG. **13B**, the non-legacy LTFs are retained in the second preamble portion **1312**. In some other aspects, the non-legacy LTFs can be turned off or otherwise disregarded to further reduce the overhead associated with the PPDU **1310** (such as described with reference to FIG. **11B**). In some implementations, the receiving device may estimate the channel associated with the data portion **1313** based on the existing L-LTF in the first preamble portion **1311** (such as through interpolation of the missing data subcarriers). In some other implementations, L-LTF may be modified or redesigned to provide more accurate channel estimation for the data portion **1313**.

(144) FIG. **13C** shows another example up-clocked PPDU **1320** based on the PPDU format depicted in FIG. **13A**, according to some implementations. In some aspects, the PPDU **1320** may be a DPHY PPDU that can be used for wireless communications on carrier frequencies above 7

GHz when full beamforming gains are achievable between a transmitting device and a receiving device. The PPDU **1320** includes a PHY preamble, having a first portion **1321** and a second portion **1322**, followed by a data portion **1323**. In some aspects, the PPDU **1320** may represent an up-clocking of the PPDU **1300** by a factor of M . In such aspects, the first preamble portion **1321**, the second preamble portion **1322**, and the data portion **1323** may be examples of the first preamble portion **1301**, the second preamble portion **1302**, and the data portion **1303**, respectively, of FIG. **13A**. In some aspects, the up-clocking may be performed by the OFDM up-clocking system **800** of FIG. **8**.

(145) In some implementations, a PE or one or more TRNs **1324** may be added to the PPDU **1320** to support enhanced features for wireless communications on carrier frequencies above 7 GHz (such as beamforming training operations). As a result of up-clocking, the second preamble portion **1322** and the data portion **1323** are spread over two $80 \times M$ MHz bandwidth portions, and the first preamble portion **1321** is duplicated on four $20 \times M$ MHz sub-bands spanning the first $80 \times M$ MHz bandwidth portion and another four $20 \times M$ MHz sub-bands spanning the second $80 \times M$ MHz bandwidth portion. For example, given a $4 \times$ up-clocking ratio ($M=4$), the second preamble portion **1322** and the data portion **1323** are spread over a 640 MHz bandwidth while the first preamble portion **1321** is duplicated on eight 80 MHz sub-bands spanning the 640 MHz bandwidth. With reference for example to FIG. **12C**, each 80 MHz bandwidth portion of the PPDU **1320** mirrors the format of the PPDU **1220**.

(146) As described with reference to FIG. **13A**, the non-legacy STF and SIG-B (in the second preamble portion **1322**) may be turned off to reduce the overhead associated with the PPDU **1320**. In some implementations, the non-legacy LTFs (in the second preamble portion **1322**) also may be turned off to further reduce the overhead associated with the PPDU **1320**. In the example of FIG. **13C**, L-LTF may be populated on the same subcarriers as the data portion **1323** to compensate for the lack of non-legacy LTFs. In some aspects, non-zero values may be modulated on at least some of the guard subcarriers associated with the data subcarriers to which L-LTF is mapped (such as described with reference to FIG. **11C**). In some implementations, the non-legacy LTFs may be included in the second preamble portion **1322** only when the PPDU **1320** is to be transmitted over multiple spatial streams ($N_{\text{sub.SS}} > 1$). In some other implementations, a P-matrix may be applied directly to L-LTF (in the first preamble portion **1321**) to produce two non-identical OFDM symbols. In such implementations, the non-legacy LTFs may be included in the second preamble portion **1322** only when the PPDU **1320** is to be transmitted over more than two spatial streams ($N_{\text{sub.SS}} > 2$).

(147) FIG. **13D** shows another example up-clocked PPDU **1330** based on the PPDU format depicted in FIG. **13A**, according to some implementations. In some aspects, the PPDU **1330** may be a DPHY PPDU that can be used for wireless communications on carrier frequencies above 7 GHz when full beamforming gains are achievable between a transmitting device and a receiving device. The PPDU **1330** includes a PHY preamble, having a first portion **1331** and a second portion **1332**, followed by a data portion **1333**. In some aspects, the PPDU **1330** may represent an up-clocking of the PPDU **1300** by a factor of M . However, in contrast with the PPDU **1300** of FIG. **13A**, the first preamble portion **1331** includes a non-legacy long training field (LTF) which replaces L-LTF and is mapped to the same data subcarriers (according to the same tone plan) as the data portion **1333**. In some aspects, the up-clocking may be performed by the OFDM up-clocking system **800** of FIG. **8**.

(148) In some implementations, a PE or one or more TRNs **1334** may be added to the PPDU **1330** to support enhanced features for wireless communications on carrier frequencies above 7 GHz (such as beamforming training operations). As a result of up-clocking, the non-legacy LTF in the first preamble portion **1331**, the second preamble portion **1332**, and the data portion **1333** are spread over two $80 \times M$ MHz bandwidth portions, and the first preamble portion **1331** (excluding LTF) is duplicated on four $20 \times M$ MHz sub-bands spanning the first $80 \times M$ MHz bandwidth portion

and another four 20*M MHz sub-bands spanning the second 80*M MHz bandwidth portion. For example, given a 4× up-clocking ratio ($M=4$), the non-legacy LTF in the first preamble portion **1331**, the second preamble portion **1332**, and the data portion **1333** are spread over a 640 MHz bandwidth while the first preamble portion **1331** (excluding LTF) is duplicated on eight 80 MHz sub-bands spanning the 640 MHz bandwidth. With reference for example to FIG. 12D, each 80 MHz bandwidth portion of the PPDU **1330** mirrors the format of the PPDU **1230**.

(149) As described with reference to FIG. 13A, the non-legacy STF and SIG-B (in the second preamble portion **1332**) may be turned off to reduce the overhead associated with the PPDU **1330**. In some implementations, the non-legacy LTFs (in the second preamble portion **1332**) also may be turned off to further reduce the overhead associated with the PPDU **1330**. In the example of FIG. 13D, the non-legacy LTF in the first preamble portion **1331** is populated on the same subcarriers as the data portion **1333** to compensate for the lack of non-legacy LTFs in the second preamble portion **1332**. In some implementations, the non-legacy LTF may be optimized for the bandwidth associated with the PPDU **1330** (such as described with reference to FIG. 11D). In some implementations, additional non-legacy LTFs may be included the second preamble portion **1332** only when the PPDU **1330** is to be transmitted over multiple spatial streams ($N_{subSS} > 1$). In some other implementations, a P-matrix may be applied directly to L-LTF (in the first preamble portion **1331**) to produce two non-identical OFDM symbols. In such implementations, additional non-legacy LTFs may be included in the second preamble portion **1332** only when the PPDU **1330** is to be transmitted over more than two spatial streams ($N_{subSS} > 2$).

(150) Aspects of the present disclosure recognize that the CPHY PPDU format of FIG. 10B and the DPHY PPDU format of FIG. 11B can be implemented using the same processing and up-clocking resources. For example, the PHY preamble **1011** and the first preamble portion **1111** each include an RL-SIG and have the same SCS and frequency repetition. As such, the CPHY PPDU format of FIG. 10B and the DPHY PPDU format of FIG. 11B may collectively represent a “harmonized” PPDU format. In some aspects, the harmonized PPDU format may include signaling to indicate whether the PPDU conforms to a CPHY PPDU format (which includes four L-STF symbols and four non-legacy SIG symbols SIG1-SIG4) or a DPHY PPDU format (which includes two L-STF symbols and two non-legacy SIG symbols SIG1 and SIG2).

(151) In some implementations, the PPDU format (CPHY or DPHY) may be signaled by the value of a length field (L_LEN) in L-SIG. For example, the PPDU may conform to either the DPHY PPDU format or the CPHY PPDU format depending on whether $L_LEN \% 3 = 0$. In some other implementations, the PPDU format (CPHY or DPHY) may be signaled by the modulation scheme associated with one of the non-legacy SIG fields (or SIG symbols). For example, the second SIG symbol SIG2 may be modulated according to either a BPSK modulation scheme or a quadrature BPSK (QBPSK) modulation scheme to indicate whether the PPDU conforms to the DPHY PPDU format or the CPHY PPDU format.

(152) As described with reference to FIGS. 9A-13D, many existing PPDU formats (including the 11ac PPDU format and the 11be PPDU format) include redundant fields or signaling. Such redundancies may provide backwards compatibility with legacy WLAN devices operating in sub-7 GHz frequency bands. However, aspects of the present disclosure recognize that there are currently no legacy WLAN devices operating at carrier frequencies above 7 GHz. Thus, in some aspects, a new “green field” PPDU format may be designed for carrier frequencies above 7 GHz. More specifically, the green field PPDU format may be optimized for communications on carrier frequencies above 7 GHz, for example, by reducing or eliminating redundant fields or signaling that would otherwise be included for backwards compatibility with legacy WLAN devices. In some implementations, the PHY preamble of the green field PPDU format may have the same symbol duration as the data portion. In some other implementations, the PHY preamble of the green field PPDU format may have a shorter symbol duration than the data portion (to further reduce the overhead of the PPDU).

(153) FIG. 14A shows an example PPDU **1400** conforming to a green field PPDU format, according to some implementations. In some implementations, the PPDU **1400** may be a DPHY PPDU that can be used for wireless communications on carrier frequencies above 7 GHz when full beamforming gains are achievable between a transmitting device and a receiving device. The PPDU **1400** includes a PHY preamble **1401** followed by a data portion **1402** and a PE or one or more TRNs **1403**. The PHY preamble **1401** includes a short training field (STF), a long training field (LTF), and a signal (SIG) field.

(154) In some implementations, the PHY preamble **1401** may have the same symbol duration as the data portion **1402**. In the example of FIG. 14A, the data portion **1402** is mapped to 256 subcarriers associated with a sub-7 GHz tone plan and the PHY preamble **1401** is also mapped to the same 256 subcarriers. As such, the SCS associated with the PHY preamble **1401** is equal to the SCS associated with the data portion **1402**. As described with reference to FIG. 8, a sub-7 GHz tone plan maps the subcarriers to a channel bandwidth suitable for wireless communications in a sub-7 GHz frequency band. For example, the tone plan associated with the 11ac PPDU format spreads the 256 subcarriers over an 80 MHz bandwidth. Thus, the PPDU **1400** may be further up-clocked to a wider bandwidth to achieve an SCS suitable for wireless communications on carrier frequencies above 7 GHz (such as described with reference to FIGS. 9A-13D). In some aspects, the up-clocking may be performed by the OFDM up-clocking system **800** of FIG. 8.

(155) In some aspects, the STF may span 2 OFDM symbols (similar to L-STF in existing PPDU formats). In some implementations, the STF may reuse an existing training sequence associated with wireless communications on carrier frequencies below 7 GHz (such as an STF sequence associated with the 11ac PPDU format or the 11be PPDU format). For example, the training sequence may be mapped to every 4.sup.th, 8.sup.th, or 16.sup.th data subcarrier associated with the 256-subcarrier tone plan (similar to the periodicity of L-STF in existing PPDU formats). In some implementations, the existing training sequence may be a trigger-based (TB) STF sequence associated with the up-clocked PPDU bandwidth. For example, when the PPDU **1400** is up-clocked 4× from an 80 MHz sub-7 GHz channel bandwidth, the STF may carry a TB STF sequence associated with a 320 MHz bandwidth. In some other implementations, the STF may include a Golay sequence to simplify packet detection (such as described with reference to FIG. 11A).

(156) In some aspects, the LTF may span 2 OFDM symbols (similar to L-LTF in existing PPDU formats). In some implementations, the LTF may reuse an existing training sequence associated with wireless communications on carrier frequencies below 7 GHz (such as an LTF sequence associated with the 11ac PPDU format or the 11be PPDU format). For example, the training sequence may be mapped to each of the (234) data plus (8) pilots subcarriers associated with the 256-subcarrier tone plan. In some implementations, the PHY preamble **1401** may include one or more additional LTFs (following the SIG field) when the PPDU **1400** is transmitted over multiple spatial streams ($N_{\text{sub.SS}} > 1$). In some other implementations, a P-matrix may be applied directly to the first LTF (preceding the SIG field) to produce two non-identical OFDM symbols. In such implementations, the PHY preamble **1401** may include one or more additional LTFs (following the SIG field) only when the PPDU **1400** is transmitted over more than two spatial streams ($N_{\text{sub.SS}} > 2$).

(157) The SIG field may carry any information needed to demodulate the PPDU **1400**. Example demodulation information may include an indication of bandwidth, length, MCS, $N_{\text{sub.SS}}$, BSS color, padding, PE ambiguity, or LDPC extra symbol, among other examples. In some implementations, the SIG field also may carry beam management information indicating whether the PPDU **1400** is associated with a beamforming training operation or various parameters associated with the beamforming training operation. Example beam management information may include a PPDU type, a training direction, a beam tracking request, a training length, a countdown, a sector ID, an antenna ID, a best antenna ID, a best sector ID, a number of RX sectors or RX antennas of the transmitting device, or an SNR report, among other examples. Information carried

in the SIG field may be modulated on each of the (234) data subcarriers associated with the 256-subcarrier tone plan. Aspects of the present disclosure recognize that 234 data subcarriers can carry 117 bits of information, which may be sufficient to capture the demodulation information and the beam management information. Thus, in some aspects, the SIG field may span 1 OFDM symbol. (158) FIG. 14B shows another example PPDU 1410 conforming to a green field PPDU format, according to some implementations. In some implementations, the PPDU 1410 may be a DPHY PPDU that can be used for wireless communications on carrier frequencies above 7 GHz when full beamforming gains are achievable between a transmitting device and a receiving device. The PPDU 1410 includes a PHY preamble 1411 followed by a data portion 1412 and a PE or one or more TRNs 1413. The PHY preamble 1411 includes a short training field (STF), a long training field (LTF), and a signal (SIG) field.

(159) In some implementations, the PHY preamble 1411 may have the same symbol duration as the data portion 1412. In the example of FIG. 14B, the data portion 1412 is mapped to 256 subcarriers associated with a sub-7 GHz tone plan whereas the PHY preamble 1411 is mapped to 128 subcarriers that are duplicated ($2\times$) in the frequency domain across the bandwidth associated with the data portion 1412. As such, the SCS associated with the PHY preamble 1411 is equal to the SCS associated with the data portion 1412. In contrast with the PPDU 1400 of FIG. 14A, the PHY preamble 1411 supports frequency combining at the receiving device, which improves the reliability of the SIG field but also requires more SIG symbols to carry the same amount of information (due to fewer data subcarriers). In some aspects, the PPDU 1410 may be up-clocked to a wider bandwidth to achieve an SCS suitable for wireless communications on carrier frequencies above 7 GHz (such as described with reference to FIGS. 9A-13D). In some implementations, the up-clocking may be performed by the OFDM up-clocking system 800 of FIG. 8.

(160) In some aspects, the STF may span 2 OFDM symbols (similar to L-STF in existing PPDU formats). In some implementations, the STF may reuse an existing training sequence associated with wireless communications on carrier frequencies below 7 GHz (such as an STF sequence associated with the 11ac PPDU format or the 11be PPDU format). For example, the training sequence may be mapped to every 4.sup.th, 8.sup.th, or 16.sup.th data subcarrier associated with the 128-subcarrier tone plan (similar to the periodicity of L-STF in existing PPDU formats). In some implementations, the existing training sequence may be a legacy STF sequence associated with the sub-7 GHz channel bandwidth. For example, when the PPDU 1410 is up-clocked from an 80 MHz sub-7 GHz channel bandwidth, the STF may carry a legacy STF sequence associated with a 40 MHz bandwidth. In some other implementations, the STF may include a Golay sequence to simplify packet detection (such as described with reference to FIG. 11A).

(161) In some aspects, the LTF may span 2 OFDM symbols (similar to L-LTF in existing PPDU formats). In some implementations, the PHY preamble 1411 may include one or more additional LTFs (following the SIG field) to support channel estimation for the data portion 1412. For example, the additional LTFs may be mapped according to the same 256-subcarrier tone plan as the data portion 1412. In some other implementations, the additional LTFs may be included in the PHY preamble 1411 only when the PPDU 1410 is transmitted over multiple spatial streams ($N_{\text{sub.SS}} > 1$). In some such implementations, non-zero values may be modulated on at least some of the guard subcarriers associated with the 128 subcarriers to which the first LTF (preceding the SIG field) is mapped so that the LTF is populated on the same subcarriers as the data portion 1412 (such as described with reference to FIGS. 11C, 12C, and 13C). In some other such implementations, the first LTF may be directly mapped to the same data subcarriers as the data portion 1412 (such as described with reference to FIGS. 11D, 12D, and 13D). Still further, in some other implementations, a P-matrix may be applied directly to the first LTF to produce two non-identical OFDM symbols. In such implementations, the additional LTFs may be included in the PHY preamble 1411 only when the PPDU 1410 is transmitted over more than two spatial streams ($N_{\text{sub.SS}} > 2$).

(162) The SIG field may carry any information needed to demodulate the PPDU **1410**. Example demodulation information may include an indication of bandwidth, length, MCS, N.sub.SS, BSS color, padding, PE ambiguity, or LDPC extra symbol, among other examples. In some implementations, the SIG field also may carry beam management information indicating whether the PPDU **1410** is associated with a beamforming training operation or various parameters associated with the beamforming training operation. Example beam management information may include a PPDU type, a training direction, a beam tracking request, a training length, a countdown, a sector ID, an antenna ID, a best antenna ID, a best sector ID, a number of RX sectors or RX antennas of the transmitting device, or an SNR report, among other examples. Information carried in the SIG field may be modulated on each of the (108) data subcarriers associated with the 128-subcarrier tone plan. Aspects of the present disclosure recognize that 108 data subcarriers can carry 54 bits of information, which may not be sufficient to capture the demodulation information and the beam management information. Thus, in some aspects, the SIG field may span 2 OFDM symbols.

(163) FIG. **14C** shows another example PPDU **1420** conforming to a green field PPDU format, according to some implementations. In some implementations, the PPDU **1420** may be a DPHY PPDU that can be used for wireless communications on carrier frequencies above 7 GHz when full beamforming gains are achievable between a transmitting device and a receiving device. The PPDU **1420** includes a PHY preamble **1421** followed by a data portion **1422** and a PE or one or more TRNs **1423**. The PHY preamble **1421** includes a short training field (STF), a long training field (LTF), and a signal (SIG) field.

(164) In some implementations, the PHY preamble **1421** may have the same symbol duration as the data portion **1422**. In the example of FIG. **14C**, the data portion **1422** is mapped to 256 subcarriers associated with a sub-7 GHz tone plan whereas the PHY preamble **1421** is mapped to 64 subcarriers that are duplicated (4×) in the frequency domain across the bandwidth associated with the data portion **1422**. As such, the SCS associated with the PHY preamble **1421** is equal to the SCS associated with the data portion **1422**. In contrast with the PPDU **1410** of FIG. **14B**, the PHY preamble **1421** supports greater frequency combining at the receiving device, which further improves the reliability of the SIG field but requires even more SIG symbols to carry the same amount information (due to fewer data subcarriers). In some aspects, the PPDU **1420** may be up-clocked to a wider bandwidth to achieve an SCS suitable for wireless communications on carrier frequencies above 7 GHz (such as described with reference to FIGS. **9A-13D**). In some implementations, the up-clocking may be performed by the OFDM up-clocking system **800** of FIG. **8**.

(165) In some aspects, the STF may span 2 OFDM symbols (similar to L-STF in existing PPDU formats). In some implementations, the STF may reuse an existing training sequence associated with wireless communications on carrier frequencies below 7 GHz (such as an STF sequence associated with the 11ac PPDU format or the 11be PPDU format). For example, the training sequence may be mapped to every 4.sup.th, 8.sup.th, or 16.sup.th data subcarrier associated with the 64-subcarrier tone plan (similar to the periodicity of L-STF in existing PPDU formats). In some implementations, the existing training sequence may be a legacy STF sequence associated with the sub-7 GHz channel bandwidth. For example, when the PPDU **1420** is up-clocked from an 80 MHz sub-7 GHz channel bandwidth, the STF may carry a legacy STF sequence associated with a 20 MHz bandwidth. In some other implementations, the STF may include a Golay sequence to simplify packet detection (such as described with reference to FIG. **11A**).

(166) In some aspects, the LTF may span 2 OFDM symbols (similar to L-LTF in existing PPDU formats). In some implementations, the PHY preamble **1421** may include one or more additional LTFs (following the SIG field) to support channel estimation for the data portion **1422**. For example, the additional LTFs may be mapped according to the same 256-subcarrier tone plan as the data portion **1422**. In some other implementations, the additional LTFs may be included in the PHY

preamble **1421** only when the PPDU **1420** is transmitted over multiple spatial streams ($N_{\text{sub.SS}} > 1$). In some such implementations, non-zero values may be modulated on at least some of the guard subcarriers associated with the 64 subcarriers to which the first LTF (preceding the SIG field) is mapped so that the LTF is populated on the same subcarriers as the data portion **1422** (such as described with reference to FIGS. **11C**, **12C**, and **13C**). In some other such implementations, the first LTF may be directly mapped to the same data subcarriers as the data portion **1422** (such as described with reference to FIGS. **11D**, **12D**, and **13D**). Still further, in some other implementations, a P-matrix may be applied directly to the first LTF to produce two non-identical OFDM symbols. In such implementations, the additional LTFs may be included in the PHY preamble **1421** only when the PPDU **1420** is transmitted over more than two spatial streams ($N_{\text{sub.SS}} > 2$).

(167) The SIG field may carry any information needed to demodulate the PPDU **1420**. Example demodulation information may include an indication of bandwidth, length, MCS, $N_{\text{sub.SS}}$, BSS color, padding, PE ambiguity, or LDPC extra symbol, among other examples. In some implementations, the SIG field also may carry beam management information indicating whether the PPDU **1420** is associated with a beamforming training operation or various parameters associated with the beamforming training operation. Example beam management information may include a PPDU type, a training direction, a beam tracking request, a training length, a countdown, a sector ID, an antenna ID, a best antenna ID, a best sector ID, a number of RX sectors or RX antennas of the transmitting device, or an SNR report, among other examples. Information carried in the SIG field may be modulated on each of the (48) data subcarriers associated with the 64-subcarrier tone plan. Aspects of the present disclosure recognize that 48 data subcarriers can carry 24 bits of information, which may not be sufficient to capture the demodulation information and the beam management information. Thus, in some aspects, the SIG field may span 3 or 4 OFDM symbols.

(168) FIG. **15A** shows an example PPDU **1500** conforming to a green field PPDU format, according to some implementations. In some implementations, the PPDU **1500** may be a DPHY PPDU that can be used for wireless communications on carrier frequencies above 7 GHz when full beamforming gains are achievable between a transmitting device and a receiving device. The PPDU **1500** includes a PHY preamble **1501** followed by a data portion **1502** and a PE or one or more TRNs **1503**. The PHY preamble **1501** includes a short training field (STF), a long training field (LTF), and a signal (SIG) field.

(169) In some implementations, the PHY preamble **1501** may have a shorter symbol duration than the data portion **1502**. In the example of FIG. **15A**, the data portion **1502** is mapped to 256 subcarriers associated with a sub-7 GHz tone plan whereas the PHY preamble **1501** is mapped to 64 subcarriers spanning the bandwidth associated with the data portion **1502**. As such, the SCS associated with the PHY preamble **1501** is $4\times$ larger than the SCS associated with the data portion **1502** (resulting in a $4\times$ shorter symbol duration). Compared to the PPDU **1400** of FIG. **14A**, the PHY preamble **1501** may be shorter than the PHY preamble **1401** but also may require more SIG symbols to carry the same amount of information (due to fewer data subcarriers). In some aspects, the PPDU **1500** may be up-clocked to a wider bandwidth to achieve an SCS suitable for wireless communications on carrier frequencies above 7 GHz (such as described with reference to FIGS. **9A-13D**). In some implementations, the up-clocking may be performed by the OFDM up-clocking system **800** of FIG. **8**.

(170) In some aspects, the STF may span 2 OFDM symbols (similar to L-STF in existing PPDU formats) or longer for AGC gain settling. In some implementations, the STF may reuse an existing training sequence associated with wireless communications on carrier frequencies below 7 GHz (such as an STF sequence associated with the 11ac PPDU format or the 11be PPDU format). For example, the training sequence may be mapped to every 4.sup.th, 8.sup.th, or 16.sup.th data subcarrier associated with the 64-subcarrier tone plan (similar to the periodicity of L-STF in

existing PPDU formats). In some implementations, the existing training sequence may be a TB STF sequence associated with the up-clocked PPDU bandwidth. For example, when the PPDU **1500** is up-clocked $16\times$ from a 20 MHz sub-7 GHz channel bandwidth, the STF may carry a TB STF sequence associated with a 320 MHz bandwidth. In some other implementations, the STF may include a Golay sequence to simplify packet detection (such as described with reference to FIG. **11A**).

(171) In some aspects, the LTF may span 2 OFDM symbols (similar to L-LTF in existing PPDU formats). In some implementations, the PHY preamble **1501** may include one or more additional LTFs (following the SIG field) to support channel estimation for the data portion **1502**. For example, the additional LTFs may be mapped according to the same 256-subcarrier tone plan as the data portion **1502**. In some other implementations, the additional LTFs may be included in the PHY preamble **1501** only when the PPDU **1500** is transmitted over multiple spatial streams ($N_{\text{sub.SS}} > 1$). In such implementations, the first LTF (preceding the SIG field) may be mapped to the same data subcarriers (according to the same 256-subcarrier tone plan) as the data portion **1502** (such as described with reference to FIGS. **11D**, **12D**, and **13D**). Still further, in some implementations, a P-matrix may be applied directly to the first LTF to produce two non-identical OFDM symbols. In such implementations, the additional LTFs may be included in the PHY preamble **1501** only when the PPDU **1500** is transmitted over more than two spatial streams ($N_{\text{sub.SS}} > 2$).

(172) The SIG field may carry any information needed to demodulate the PPDU **1500**. Example demodulation information may include an indication of bandwidth, length, MCS, $N_{\text{sub.SS}}$, BSS color, padding, PE ambiguity, or LDPC extra symbol, among other examples. In some implementations, the SIG field also may carry beam management information indicating whether the PPDU **1500** is associated with a beamforming training operation or various parameters associated with the beamforming training operation. Example beam management information may include a PPDU type, a training direction, a beam tracking request, a training length, a countdown, a sector ID, an antenna ID, a best antenna ID, a best sector ID, a number of RX sectors or RX antennas of the transmitting device, or an SNR report, among other examples. Information carried in the SIG field may be modulated on each of the (48) data subcarriers associated with the 64-subcarrier tone plan. Aspects of the present disclosure recognize that 48 data subcarriers can carry 24 bits of information, which may not be sufficient to capture the demodulation information and the beam management information. Thus, in some aspects, the SIG field may span 3 or 4 OFDM symbols.

(173) FIG. **15B** shows another example PPDU **1510** conforming to a green field PPDU format, according to some implementations. In some implementations, the PPDU **1510** may be a DPHY PPDU that can be used for wireless communications on carrier frequencies above 7 GHz when full beamforming gains are achievable between a transmitting device and a receiving device. The PPDU **1510** includes a PHY preamble **1511** followed by a data portion **1512** and a PE or one or more TRNs **1513**. The PHY preamble **1511** includes a short training field (STF), a long training field (LTF), and a signal (SIG) field.

(174) In some implementations, the PHY preamble **1511** may have a shorter symbol duration than the data portion **1512**. In the example of FIG. **15B**, the data portion **1512** is mapped to 256 subcarriers associated with a sub-7 GHz tone plan whereas the PHY preamble **1511** is mapped to 128 subcarriers spanning the bandwidth associated with the data portion **1512**. As such, the SCS associated with the PHY preamble **1511** is $2\times$ larger than the SCS associated with the data portion **1512** (resulting in a $2\times$ shorter symbol duration). Compared to the PPDU **1500** of FIG. **15A**, the PHY preamble **1511** may be longer than the PHY preamble **1501** but shorter than the data portion and also may require fewer SIG symbols than the PHY preamble **1501** to carry the same amount of information (due to more data subcarriers). In some aspects, the PPDU **1510** may be up-clocked to a wider bandwidth to achieve an SCS suitable for wireless communications on carrier frequencies

above 7 GHz (such as described with reference to FIGS. 9A-13D). In some implementations, the up-clocking may be performed by the OFDM up-clocking system **800** of FIG. **8**.

(175) In some aspects, the STF may span 2 OFDM symbols (similar to L-STF in existing PPDU formats) or longer for AGC gain settling. In some implementations, the STF may reuse an existing training sequence associated with wireless communications on carrier frequencies below 7 GHz (such as an STF sequence associated with the 11ac PPDU format or the 11be PPDU format). For example, the training sequence may be mapped to every 4.sup.th, 8.sup.th, or 16.sup.th data subcarrier associated with the 128-subcarrier tone plan (similar to the periodicity of L-STF in existing PPDU formats). In some implementations, the existing training sequence may be a TB STF sequence associated with the up-clocked PPDU bandwidth. For example, when the PPDU **1510** is up-clocked 16× from a 20 MHz sub-7 GHz channel bandwidth, the STF may carry a TB STF sequence associated with a 320 MHz bandwidth. In some other implementations, the STF may include a Golay sequence to simplify packet detection (such as described with reference to FIG. **11A**).

(176) In some aspects, the LTF may span 2 OFDM symbols (similar to L-LTF in existing PPDU formats). In some implementations, the PHY preamble **1511** may include one or more additional LTFs (following the SIG field) to support channel estimation for the data portion **1512**. For example, the additional LTFs may be mapped according to the same 256-subcarrier tone plan as the data portion **1512**. In some other implementations, the additional LTFs may be included in the PHY preamble **1511** only when the PPDU **1510** is transmitted over multiple spatial streams ($N_{\text{sub.SS}} > 1$). In such implementations, the first LTF (preceding the SIG field) may be mapped to the same data subcarriers (according to the same 256-subcarrier tone plan) as the data portion **1512** (such as described with reference to FIGS. **11D**, **12D**, and **13D**). Still further, in some implementations, a P-matrix may be applied directly to the first LTF to produce two non-identical OFDM symbols. In such implementations, the additional LTFs may be included in the PHY preamble **1511** only when the PPDU **1510** is transmitted over more than two spatial streams ($N_{\text{sub.SS}} > 2$).

(177) The SIG field may carry any information needed to demodulate the PPDU **1510**. Example demodulation information may include an indication of bandwidth, length, MCS, $N_{\text{sub.SS}}$, BSS color, padding, PE ambiguity, or LDPC extra symbol, among other examples. In some implementations, the SIG field also may carry beam management information indicating whether the PPDU **1510** is associated with a beamforming training operation or various parameters associated with the beamforming training operation. Example beam management information may include a PPDU type, a training direction, a beam tracking request, a training length, a countdown, a sector ID, an antenna ID, a best antenna ID, a best sector ID, a number of RX sectors or RX antennas of the transmitting device, or an SNR report, among other examples. Information carried in the SIG field may be modulated on each of the (108) data subcarriers associated with the 128-subcarrier tone plan. Aspects of the present disclosure recognize that 108 data subcarriers can carry 54 bits of information, which may not be sufficient to capture the demodulation information and the beam management information. Thus, in some aspects, the SIG field may span 2 OFDM symbols.

(178) FIG. **15C** shows another example PPDU **1520** conforming to a green field PPDU format, according to some implementations. In some implementations, the PPDU **1520** may be a DPHY PPDU that can be used for wireless communications on carrier frequencies above 7 GHz when full beamforming gains are achievable between a transmitting device and a receiving device. The PPDU **1520** includes a PHY preamble **1521** followed by a data portion **1522** and a PE or one or more TRNs **1523**. The PHY preamble **1521** includes a short training field (STF), a long training field (LTF), and a signal (SIG) field.

(179) In some implementations, the PHY preamble **1521** may have a shorter symbol duration than the data portion **1522**. In the example of FIG. **15B**, the data portion **1522** is mapped to 256

subcarriers associated with a sub-7 GHz tone plan whereas the PHY preamble **1521** is mapped to 64 subcarriers that are duplicated ($2\times$) in the frequency domain across the bandwidth associated with the data portion **1522**. As such, the SCS associated with the PHY preamble **1521** is $2\times$ larger (and has a $2\times$ shorter symbol duration) than the SCS associated with the data portion **1522**. In contrast with the PPDU **1510** of FIG. **15B**, the PHY preamble **1521** supports greater frequency combining at the receiving device, which further improves the reliability of the SIG field but requires even more SIG symbols to carry the same amount of information (due to fewer data subcarriers). In some aspects, the PPDU **1520** may be up-clocked to a wider bandwidth to achieve an SCS suitable for wireless communications on carrier frequencies above 7 GHz (such as described with reference to FIGS. **9A-13D**). In some implementations, the up-clocking may be performed by the OFDM up-clocking system **800** of FIG. **8**.

(180) In some aspects, the STF may span 2 OFDM symbols (similar to L-STF in existing PPDU formats) or longer for AGC gain settling. In some implementations, the STF may reuse an existing training sequence associated with wireless communications on carrier frequencies below 7 GHz (such as an STF sequence associated with the 11ac PPDU format or the 11be PPDU format). For example, the training sequence may be mapped to every 4.sup.th, 8.sup.th, or 16.sup.th data subcarrier associated with the 64-subcarrier tone plan (similar to the periodicity of L-STF in existing PPDU formats). In some implementations, the existing training sequence may be a legacy STF sequence associated with the sub-7 GHz channel bandwidth. For example, when the PPDU **1420** is up-clocked from a 20 MHz sub-7 GHz channel bandwidth, the STF may carry a legacy STF sequence associated with a 20 MHz bandwidth. In some other implementations, the STF may include a Golay sequence to simplify packet detection (such as described with reference to FIG. **11A**).

(181) In some aspects, the LTF may span 2 OFDM symbols (similar to L-LTF in existing PPDU formats). In some implementations, the PHY preamble **1521** may include one or more additional LTFs (following the SIG field) to support channel estimation for the data portion **1522**. For example, the additional LTFs may be mapped according to the same 256-subcarrier tone plan as the data portion **1522**. In some other implementations, the additional LTFs may be included in the PHY preamble **1521** only when the PPDU **1520** is transmitted over multiple spatial streams ($N_{\text{sub.SS}} > 1$). In such implementations, the first LTF (preceding the SIG field) may be mapped to the same data subcarriers (according to the same 256-subcarrier tone plan) as the data portion **1522** (such as described with reference to FIGS. **11D**, **12D**, and **13D**). Still further, in some implementations, a P-matrix may be applied directly to the first LTF to produce two non-identical OFDM symbols. In such implementations, the additional LTFs may be included in the PHY preamble **1521** only when the PPDU **1520** is transmitted over more than two spatial streams ($N_{\text{sub.SS}} > 2$).

(182) The SIG field may carry any information needed to demodulate the PPDU **1520**. Example demodulation information may include an indication of bandwidth, length, MCS, $N_{\text{sub.SS}}$, BSS color, padding, PE ambiguity, or LDPC extra symbol, among other examples. In some implementations, the SIG field also may carry beam management information indicating whether the PPDU **1520** is associated with a beamforming training operation or various parameters associated with the beamforming training operation. Example beam management information may include a PPDU type, a training direction, a beam tracking request, a training length, a countdown, a sector ID, an antenna ID, a best antenna ID, a best sector ID, a number of RX sectors or RX antennas of the transmitting device, or an SNR report, among other examples. Information carried in the SIG field may be modulated on each of the (48) data subcarriers associated with the 64-subcarrier tone plan. Aspects of the present disclosure recognize that 48 data subcarriers can carry 24 bits of information, which may not be sufficient to capture the demodulation information and the beam management information. Thus, in some aspects, the SIG field may span 3 or 4 OFDM symbols.

(183) Aspects of the present disclosure recognize that the CPHY PPDU format of FIG. 9B and the DPHY PPDU format of FIG. 14C can be implemented using the same processing and up-clocking resources. For example, the PHY preambles **911** and **1421** each include a single SIG field and have the same SCS and frequency repetition. As such, the CPHY PPDU format of FIG. 9B and the DPHY PPDU format of FIG. 14C may collectively represent a harmonized green field PPDU format. In some implementations, the SIG field of the PHY preamble **1421** may be repeated in the time domain or include additional OFDM symbols (such as described with reference to FIGS. 9C and 9D). In some aspects, the harmonized PPDU format may include signaling to indicate whether the PPDU conforms to a CPHY PPDU format or a DPHY PPDU format.

(184) In some implementations, the PPDU format (CPHY or DPHY) may be signaled by the value of a length field (L_LEN) in the SIG field (or L-SIG). For example, the PPDU may conform to either the DPHY PPDU format or the CPHY PPDU format depending on whether $L_LEN \% 3 = 0$. In some other implementations, the PPDU format (CPHY or DPHY) may be signaled by the modulation scheme associated with one of the SIG fields (or SIG symbols). For example, the second OFDM symbol of the SIG field may be modulated according to either a BPSK modulation scheme or a QPSK modulation scheme to indicate whether the PPDU conforms to the DPHY PPDU format or the CPHY PPDU format.

(185) FIG. 16 shows a flowchart illustrating an example process **1600** for wireless communication that supports 60 GHz PPDU formats. In some implementations, the process **1600** may be performed by a wireless communication device operating as or within an AP, such as any one of the APs **102** or **502** described above with reference to FIGS. 1 and 5A, respectively. In some other implementations, the process **1600** may be performed by a wireless communication device operating as or within a STA, such as any one of the STAs **104** or **504** described above with reference to FIGS. 1 and 5B, respectively.

(186) In some implementations, the process **1600** begins in block **1602** with mapping a first portion of a PPDU to a number (N) of subcarriers, where the first portion of the PPDU represents at least portion of a PHY preamble that includes an STF, an LTF, and one or more SIG fields that immediately follow the LTF and carry information for interpreting the PPDU. In block **1604**, the process **1600** proceeds with transforming the N subcarriers into a first time-varying signal at a sampling rate (f.sub.s) associated with a first SCS that is greater than 1.2 MHz, where the first SCS represents an amount of separation, in the frequency domain, between adjacent subcarriers of the N subcarriers. In block **1606**, the process **1600** proceeds with transmitting the first time-varying signal over a wireless channel having a bandwidth (BW) associated with the sampling rate f.sub.s.

(187) In some aspects, the PPDU may conform to a PPDU format associated with wireless communications on a carrier frequency below 7 GHz. In some implementations, the one or more SIG fields may include an L-SIG and a non-legacy SIG field immediately following L-SIG. In some other implementations, the one or more SIG fields may include an L-SIG, an RL-SIG immediately following L-SIG, and a non-legacy SIG field immediately following RL-SIG. In some implementations, the STF and the non-legacy SIG field may each consist of two OFDM symbols. In some other implementations, the STF may consist of two OFDM symbols that are repeated in time and the non-legacy SIG field may consist of four OFDM symbols.

(188) In some aspects, the PPDU may consist of only the first portion. In some other aspects, the process **1600** may further include mapping, to a number (M) of subcarriers, a second portion of the PPDU including at least a data field, a packet extension, or one or more TRNs; transforming the M subcarriers into a second time-varying signal at the sampling rate f.sub.s; and transmitting the second time-varying signal over the wireless channel immediately following the first time-varying signal. In some implementations, the one or more SIG fields may consist of a single SIG field that is immediately followed by the data field, the packet extension, or the one or more TRNs. In some implementations, the second portion of the PPDU may further include one or more additional LTFs. In some implementations, the one or more SIG fields may consist of a single SIG field that is

immediately followed by the one or more additional LTFs.

(189) In some implementations, M may be equal to N and BW may be equal to $f_{\text{sub.s}}$. In some other implementations, M may be equal to N and the PPDU may be duplicated for transmission on a number (m) of sub-bands each spanning a respective bandwidth portion equal to BW/m , where BW is equal to $m \cdot f_{\text{sub.s}}$. Still further, in some implementations, M may be greater than N . In some implementations, the first portion of the PPDU may be duplicated for transmission on a number (n) of sub-bands each spanning a respective bandwidth portion equal to BW/n , where BW is equal to $f_{\text{sub.s}}$. In some implementations, the transformation of the M subcarriers into the second time-varying signal may result in a second SCS equal to the first SCS, where the second SCS represents an amount of separation, in the frequency domain, between adjacent subcarriers of the M subcarriers. In some other implementations, the transformation of the M subcarriers into the second time-varying signal may result in a second SCS different than the first SCS, where the second SCS represents an amount of separation, in the frequency domain, between adjacent subcarriers of the M subcarriers.

(190) In some implementations, the LTF may be transmitted on the same subcarriers as the second portion of the PPDU as a result of duplicating the first portion of the PPDU for transmission on the n sub-bands. In some implementations, the LTF may include a first OFDM symbol and a second OFDM symbol identical to the first OFDM symbol. In some other implementations, the LTF may include a first OFDM symbol and a second OFDM symbol, where the process **1600** further includes applying a P-matrix to the LTF so that the first OFDM symbol is different than the second OFDM symbol. In some implementations, the STF may include a Golay sequence. In some implementations, the information carried in the one or more SIG fields may include an indication of whether the PPDU is associated with a beamforming training operation.

(191) FIG. **17** shows a flowchart illustrating an example process for wireless communication that supports 60 GHz PPDU formats. In some implementations, the process **1700** may be performed by a wireless communication device operating as or within an AP, such as any one of the APs **102** or **502** described above with reference to FIGS. **1** and **5A**, respectively. In some other implementations, the process **1700** may be performed by a wireless communication device operating as or within a STA, such as any one of the STAs **104** or **504** described above with reference to FIGS. **1** and **5B**, respectively.

(192) In some implementations, the process **1700** begins in block **1702** with mapping a first portion of a PPDU to a number (N) of subcarriers, where the first portion of the PPDU represents at least portion of a PHY preamble that includes an STF and one or more SIG fields carrying information for interpreting the PPDU. In block **1704**, the process **1700** proceeds with mapping an LTF of the PHY preamble to a number (M) of subcarriers, where the LTF follows the STF and precedes the one or more SIG fields in the PHY preamble, where $M > N$. In block **1706**, the process **1700** proceeds with transforming the N subcarriers and the M subcarriers to a time-varying signal. In block **1708**, the process **1700** proceeds with transmitting the time-varying signal over a wireless channel.

(193) In some implementations, the process **1700** may further include mapping, to the M subcarriers, a second portion of the PPDU including at least a data field, a packet extension, or one or more TRNs. In some implementations, the N subcarriers and the M subcarriers may be transformed to the time-varying signal at a sampling rate ($f_{\text{sub.s}}$) associated with an SCS greater than 1.2 MHz, where the SCS represents an amount of separation, in the frequency domain, between adjacent subcarriers of the N subcarriers. In some implementations, the first portion of the PPDU may be duplicated for transmission on a number (n) of sub-bands each spanning a respective bandwidth portion equal to BW/n .

(194) FIG. **18** shows a block diagram of an example wireless communication device **1800** according to some implementations. In some implementations, the wireless communication device **1800** is configured to perform the process **1600** described with reference to FIG. **16**. The wireless

communication device **1800** can be an example implementation of the wireless communication device **400** described above with reference to FIG. **4**. For example, the wireless communication device **1800** can be a chip, SoC, chipset, package or device that includes at least one processor and at least one modem (for example, a Wi-Fi (IEEE 802.11) modem or a cellular modem).

(195) The wireless communication device **1800** includes a reception component **1810**, a communication manager **1820**, and a transmission component **1830**. The communication manager **1820** further includes a PPDU mapping component **1822** and a time domain conversion component **1824**. Portions of one or more of the components **1822** and **1824** may be implemented at least in part in hardware or firmware. In some implementations, at least some of the components **1822** or **1824** are implemented at least in part as software stored in a memory (such as the memory **408**). For example, portions of one or more of the components **1822** and **1824** can be implemented as non-transitory instructions (or “code”) executable by a processor (such as the processor **406**) to perform the functions or operations of the respective component.

(196) The reception component **1810** is configured to receive RX signals, over a wireless channel, from one or more other wireless communication devices. The communication manager **1820** is configured to control or manage communications with one or more other wireless communication devices. In some implementations, the PPDU mapping component **1822** may map a first portion of a PPDU to a number (N) of subcarriers, where the first portion of the PPDU represents at least portion of a PHY preamble that includes a short training field (STF), a long training field (LTF), and one or more signal (SIG) fields that immediately follow the LTF and carry information for interpreting the PPDU; and the time domain conversion component **1824** may transform the N subcarriers into a time-varying signal at a sampling rate ($f_{\text{sub.s}}$) associated with a subcarrier spacing (SCS) that is greater than 1.2 MHz, where the SCS represents an amount of separation, in the frequency domain, between adjacent subcarriers of the N subcarriers. The transmission component **1830** is configured to transmit TX signals, over a wireless channel, to one or more other wireless communication devices. In some implementations, the transmission component **1830** may transmit the first time-varying signal over a wireless channel having a bandwidth (BW) associated with the sampling rate $f_{\text{sub.s}}$.

(197) FIG. **19** shows a block diagram of an example wireless communication device **1900** according to some implementations. In some implementations, the wireless communication device **1900** is configured to perform the process **1700** described with reference to FIG. **17**. The wireless communication device **1900** can be an example implementation of the wireless communication device **400** described above with reference to FIG. **4**. For example, the wireless communication device **1900** can be a chip, SoC, chipset, package or device that includes at least one processor and at least one modem (for example, a Wi-Fi (IEEE 802.11) modem or a cellular modem).

(198) The wireless communication device **1900** includes a reception component **1910**, a communication manager **1920**, and a transmission component **1930**. The communication manager **1920** further includes a PPDU mapping component **1922**, an LTF mapping component **1924**, and a time domain conversion component **1926**. Portions of one or more of the components **1922**, **1924**, and **1926** may be implemented at least in part in hardware or firmware. In some implementations, at least some of the components **1922**, **1924**, or **1926** are implemented at least in part as software stored in a memory (such as the memory **408**). For example, portions of one or more of the components **1922**, **1924**, and **1926** can be implemented as non-transitory instructions (or “code”) executable by a processor (such as the processor **406**) to perform the functions or operations of the respective component.

(199) The reception component **1910** is configured to receive RX signals, over a wireless channel, from one or more other wireless communication devices. The communication manager **1920** is configured to control or manage communications with one or more other wireless communication devices. In some implementations, the PPDU mapping component **1922** may map a first portion of a PPDU to a number (N) of subcarriers, where the first portion of the PPDU represents at least

portion of a PHY preamble that includes a short training field (STF) and one or more signal (SIG) fields carrying information for interpreting the PPDU; the LTF mapping component **1924** may map a long training field (LTF) of the PHY preamble to a number (M) of subcarriers, where the LTF follows the STF and precedes the one or more SIG fields in the PHY preamble, where $M > N$; and the time domain conversion component **1924** may transform the N subcarriers and the M subcarriers to a time-varying signal. The transmission component **1930** is configured to transmit TX signals, over a wireless channel, to one or more other wireless communication devices. In some implementations, the transmission component **1930** may transmit the time-varying signal over a wireless channel.

(200) Implementation examples are described in the following numbered clauses: 1. A method for wireless communication by a wireless communication device, including: mapping a first portion of a physical layer (PHY) convergence protocol (PLCP) protocol data unit (PPDU) to a number (N) of subcarriers, the first portion of the PPDU representing at least portion of a PHY preamble that includes a short training field (STF), a long training field (LTF), and one or more signal (SIG) fields that immediately follow the LTF and carry information for interpreting the PPDU; transforming the N subcarriers into a first time-varying signal at a sampling rate ($f_{\text{sub.s}}$) associated with a first subcarrier spacing (SCS) that is greater than 1.2 MHz, the first SCS representing an amount of separation, in the frequency domain, between adjacent subcarriers of the N subcarriers; and transmitting the first time-varying signal over a wireless channel having a bandwidth (BW) associated with the sampling rate $f_{\text{sub.s}}$. 2. The method of clause 1, where the first time-varying signal is transmitted on carrier frequency above 7 GHz. 3. The method of any of clauses 1 or 2, where the PPDU conforms to a PPDU format associated with wireless communications on a carrier frequency below 7 GHz. 4. The method of any of clauses 1-3, where the one or more SIG fields include a legacy SIG field (L-SIG) and a non-legacy SIG field immediately following L-SIG. 5. The method of any of clauses 1-3, where the one or more SIG fields include an L-SIG, a repeat of L-SIG (RL-SIG) immediately following L-SIG, and a non-legacy SIG field immediately following RL-SIG. 6. The method of any of clauses 1-3 or 5, where the STF and the non-legacy SIG field each consists of two orthogonal frequency-division multiplexing (OFDM) symbols. 7. The method of any of clauses 1-3 or 5, where the STF consists of two OFDM symbols that are repeated in time and the non-legacy SIG field consists of four OFDM symbols. 8. The method of any of clauses 1-7, where the PPDU consists of only the first portion. 9. The method of any of clauses 1-7, further including: mapping, to a number (M) of subcarriers, a second portion of the PPDU including at least a data field, a packet extension, or one or more training fields (TRNs); transforming the M subcarriers into a second time-varying signal at the sampling rate $f_{\text{sub.s}}$; and transmitting the second time-varying signal over the wireless channel immediately following the first time-varying signal. 10. The method of any of clauses 1-7 or 9, where the one or more SIG fields consist of a single SIG field that is immediately followed by the data field, the packet extension, or the one or more TRNs. 11. The method of any of clauses 1-7 or 9, where the second portion of the PPDU further includes one or more additional LTFs. 12. The method of any of clauses 1-7, 9, or 10, where the one or more SIG fields consist of a single SIG field that is immediately followed by the one or more additional LTFs. 13. The method of any of clauses 1-7 or 9-12, where $M = N$ and $BW = f_{\text{sub.s}}$. 14. The method of any of clauses 1-7, 9 or 10, where $M = N$ and the PPDU is duplicated for transmission on a number (m) of sub-bands each spanning a respective bandwidth portion equal to BW/m , where $BW = m * f_{\text{sub.s}}$. 15. The method of any of clauses 1-7 or 9-12, where $M > N$. 16. The method of any of clauses 1-7, 9-12, or 15, where the first portion of the PPDU is duplicated for transmission on a number (n) of sub-bands each spanning a respective bandwidth portion equal to BW/n , where $BW = f_{\text{sub.s}}$. 17. The method of any of clauses 1-7, 9-12, 15, or 16, where the transformation of the M subcarriers into the second time-varying signal results in a second SCS equal to the first SCS, the second SCS representing an amount of separation, in the frequency domain, between adjacent subcarriers of the M subcarriers. 18. The method of any of clauses 1-7,

9-12, 15, or 16, where the transformation of the M subcarriers into the second time-varying signal results in a second SCS different than the first SCS, the second SCS representing an amount of separation, in the frequency domain, between adjacent subcarriers of the M subcarriers. 19. The method of any of clauses 1-7, 9-12, or 15-18, where the LTF is transmitted on the same subcarriers as the second portion of the PPDU as a result of duplicating the first portion of the PPDU for transmission on the n sub-bands. 20. The method of any of clauses 1-19, where the LTF includes a first OFDM symbol and a second OFDM symbol identical to the first OFDM symbol. 21. The method of any of clauses 1-19, where the LTF includes a first OFDM symbol and a second OFDM symbol, the method further including: applying a P-matrix to the LTF so that the first OFDM symbol is different than the second OFDM symbol. 22. The method of any of clauses 1-21, where the STF includes a Golay sequence. 23. The method of any of clauses 1-22, where the information carried in the one or more SIG fields includes an indication of whether the PPDU is associated with a beamforming training operation. 24. A wireless communication device including: at least one memory; and at least one processor communicatively coupled with the at least one memory, the at least one processor configured to cause the wireless communication device to perform the method of any one or more of clauses 1-23. 25. A method for wireless communication by a wireless communication device, including: mapping a first portion of a physical layer (PHY) convergence protocol (PLCP) protocol data unit (PPDU) to a number (N) of subcarriers, the first portion of the PPDU representing at least portion of a PHY preamble that includes a short training field (STF) and one or more signal (SIG) fields carrying information for interpreting the PPDU; mapping a long training field (LTF) of the PHY preamble to a number (M) of subcarriers, the LTF following the STF and preceding the one or more SIG fields in the PHY preamble, where $M > N$; transforming the N subcarriers and the M subcarriers to a time-varying signal; and transmitting the time-varying signal over a wireless channel. 26. The method of clause 25, where the wireless channel is associated with a carrier frequency above 7 GHz. 27. The method of any of clauses 25 or 26, further including: mapping, to the M subcarriers, a second portion of the PPDU including at least a data field, a packet extension, or one or more training fields (TRNs). 28. The method of any of clauses 25-27, where the N subcarriers and the M subcarriers are transformed to the time-varying signal at a sampling rate ($f_{sub.s}$) associated with a subcarrier spacing (SCS) greater than 1.2 MHz, the SCS representing an amount of separation, in the frequency domain, between adjacent subcarriers of the N subcarriers. 29. The method of any of clauses 25-28, where the first portion of the PPDU is duplicated for transmission on a number (n) of sub-bands each spanning a respective bandwidth portion equal to BW/n . 30. A wireless communication device including: at least one memory; and at least one processor communicatively coupled with the at least one memory, the at least one processor configured to cause the wireless communication device to perform the method of any one or more of clauses 25-29.

(201) As used herein, a phrase referring to “at least one of” or “one or more of” a list of items refers to any combination of those items, including single members. For example, “at least one of: a, b, or c” is intended to cover the possibilities of: a only, b only, c only, a combination of a and b, a combination of a and c, a combination of b and c, and a combination of a and b and c. As used herein, “based on” is intended to be interpreted in the inclusive sense, unless otherwise explicitly indicated. For example, “based on” may be used interchangeably with “based at least in part on,” unless otherwise explicitly indicated. Specifically, unless a phrase refers to “based on only ‘a,’” or the equivalent in context, whatever it is that is “based on ‘a,’” or “based at least in part on ‘a,’” may be based on “a” alone or based on a combination of “a” and one or more other factors, conditions, or information.

(202) The various illustrative components, logic, logical blocks, modules, circuits, operations and algorithm processes described in connection with the implementations disclosed herein may be implemented as electronic hardware, firmware, software, or combinations of hardware, firmware or software, including the structures disclosed in this specification and the structural equivalents

thereof. The interchangeability of hardware, firmware and software has been described generally, in terms of functionality, and illustrated in the various illustrative components, blocks, modules, circuits and processes described above. Whether such functionality is implemented in hardware, firmware or software depends upon the particular application and design constraints imposed on the overall system.

(203) Various modifications to the implementations described in this disclosure may be readily apparent to persons having ordinary skill in the art, and the generic principles defined herein may be applied to other implementations without departing from the spirit or scope of this disclosure. Thus, the claims are not intended to be limited to the implementations shown herein, but are to be accorded the widest scope consistent with this disclosure, the principles and the novel features disclosed herein.

(204) Additionally, various features that are described in this specification in the context of separate implementations also can be implemented in combination in a single implementation. Conversely, various features that are described in the context of a single implementation also can be implemented in multiple implementations separately or in any suitable subcombination. As such, although features may be described above as acting in particular combinations, and even initially claimed as such, one or more features from a claimed combination can in some cases be excised from the combination, and the claimed combination may be directed to a subcombination or variation of a subcombination.

(205) Similarly, while operations are depicted in the drawings in a particular order, this should not be understood as requiring that such operations be performed in the particular order shown or in sequential order, or that all illustrated operations be performed, to achieve desirable results. Further, the drawings may schematically depict one more example processes in the form of a flowchart or flow diagram. However, other operations that are not depicted can be incorporated in the example processes that are schematically illustrated. For example, one or more additional operations can be performed before, after, simultaneously, or between any of the illustrated operations. In some circumstances, multitasking and parallel processing may be advantageous. Moreover, the separation of various system components in the implementations described above should not be understood as requiring such separation in all implementations, and it should be understood that the described program components and systems can generally be integrated together in a single software product or packaged into multiple software products.

Claims

1. A method for wireless communication performed by a wireless communication device, comprising: mapping a first portion of a physical layer (PHY) preamble of a PHY protocol data unit (PPDU) to a first number of data subcarriers in accordance with a first sub-7 GHz PPDU tone plan that comprises N subcarriers including the first number of data subcarriers, the first portion including a legacy short training field (L-STF), a legacy long training field (L-LTF), and one or more signal (SIG) fields; transforming the N subcarriers into a first time-varying signal using an N-point inverse fast Fourier transform (IFFT) and a sampling rate ($f_{\text{sub.s}}$) that is equal to a bandwidth (BW) associated with transmission of the PPDU on a carrier frequency above 7 GHz such that a first subcarrier spacing (SCS) associated with the first portion of the PHY preamble is greater than 1.2 MHz; and transmitting the PPDU including the first time-varying signal on the carrier frequency that is above 7 GHz.
2. The method of claim 1, wherein the first portion of the PHY preamble further includes a non-legacy SIG field immediately following L-SIG.
3. The method of claim 1, wherein the PPDU consists of only the first portion of the PHY preamble.
4. The method of claim 1, further comprising: mapping, to a number (M) of subcarriers, a second

portion of the PPDU including at least a data field, a packet extension, or one or more training fields (TRNs); transforming the M subcarriers into a second time-varying signal at the sampling rate $f_{\text{sub.s}}$; and transmitting the second time-varying signal immediately following the first time-varying signal.

5. The method of claim 4, wherein the one or more SIG fields consist of a single SIG field that is immediately followed by the data field, the packet extension, or the one or more TRNs.

6. The method of claim 4, wherein the second portion of the PPDU further includes one or more additional LTFs.

7. The method of claim 6, wherein the one or more SIG fields consist of a single SIG field that is immediately followed by the one or more additional LTFs.

8. The method of claim 4, wherein $M > N$.

9. The method of claim 8, wherein the first portion of the PPDU is duplicated for transmission on a number (n) of sub-bands each spanning a respective bandwidth portion equal to BW/n , where $BW = f_{\text{sub.s}}$.

10. The method of claim 9, wherein the transformation of the M subcarriers into the second time-varying signal results in a second SCS equal to the first SCS, the second SCS representing an amount of separation, in a frequency domain, between adjacent subcarriers of the M subcarriers.

11. The method of claim 9, wherein the transformation of the M subcarriers into the second time-varying signal results in a second SCS different than the first SCS, the second SCS representing an amount of separation, in a frequency domain, between adjacent subcarriers of the M subcarriers.

12. The method of claim 9, wherein the L-LTF is transmitted on the same subcarriers as the second portion of the PPDU as a result of duplicating the first portion of the PHY preamble of the PPDU for transmission on the n sub-bands.

13. The method of claim 1, wherein the L-LTF includes a first OFDM symbol and a second OFDM symbol identical to the first OFDM symbol.

14. The method of claim 1, wherein the L-LTF includes a first OFDM symbol and a second OFDM symbol, the method further comprising: applying a P-matrix to the L-LTF so that the first OFDM symbol is different than the second OFDM symbol.

15. The method of claim 1, wherein the L-STF comprises a Golay sequence.

16. The method of claim 1, wherein information carried in the one or more SIG fields includes an indication of whether the PPDU is associated with a beamforming training operation.

17. The method of claim 1, wherein: the PPDU further includes a data field and the method further includes mapping the data field to a second number of data subcarriers in accordance with a second sub-7 GHz PPDU tone plan that comprises M subcarriers including the second number of data subcarriers, N is equal to 64, M is equal to 256, the BW is equal to $20 \times X$ MHz, the first portion of the PHY preamble is duplicated in each of 4 sub-bands within the BW and upclocked by a factor of $X/4$, each sub-band has a bandwidth of $5 \times X$ MHz, and the data field is upclocked by a factor of X.

18. The method of claim 17, wherein the L-STF is mapped to only every 4^{sup.th} data subcarrier of the first number of data subcarriers while the L-LTF and one or more L-SIG fields are mapped to every data subcarrier of the first number of data subcarriers.

19. The method of claim 17, wherein the first sub-7 GHz tone plan conforms to an IEEE 802.11ac 20 MHz tone plan and the second sub-7 GHz tone plan conforms to an IEEE 802.11be 20 MHz tone plan.

20. The method of claim 1, wherein: the PPDU further includes a data field and the method further includes mapping the data field to a second number of data subcarriers in accordance with a second sub-7 GHz PPDU tone plan that comprises M subcarriers including the second number of data subcarriers, N is equal to 64, M is equal to 256, the BW is equal to $80 \times X$ MHz, the first portion of the PHY preamble is duplicated in each of 4 sub-bands within the BW, each sub-band has a bandwidth of $20 \times X$ MHz, and the data field is upclocked by a factor of X.

21. The method of claim 20, wherein the L-STF is mapped to only every 4^{sup.th} data subcarrier of

the first number of data subcarriers while the L-LTF and one or more L-SIG fields are mapped to every data subcarrier of the first number of data subcarriers.

22. The method of claim 20, wherein the first sub-7 GHz tone plan conforms to an IEEE 802.11ac 20 MHz tone plan and the second sub-7 GHz tone plan conforms to an IEEE 802.11ac 80 MHz tone plan.

23. A wireless communication device comprising: at least one memory; and at least one processor communicatively coupled with the at least one memory, the at least one processor configured to cause the wireless communication device to: map a first portion of a physical layer (PHY) preamble of a PHY protocol data unit (PPDU) to a first number of data subcarriers in accordance with a first sub-7 GHz PPDU tone plan that comprises N subcarriers including the first number of data subcarriers, the first portion including a legacy short training field (L-STF), a legacy long training field (L-LTF), and one or more signal (SIG) fields; transform the N subcarriers into a first time-varying signal using an N-point inverse fast Fourier transform (IFFT) and a sampling rate ($f_{\text{sub.s}}$) that is equal to a bandwidth (BW) associated with transmission of the PPDU on a carrier frequency above 7 GHz such that a first subcarrier spacing (SCS) associated with the first portion of the PHY preamble is greater than 1.2 MHz; and transmit the PPDU including the first time-varying signal on the carrier frequency that is above 7 GHz.

24. The wireless communication device of claim 23, wherein: the PPDU further includes a data field and the at least one processor is further configured to cause the wireless communication device to map the data field to a second number of data subcarriers in accordance with a second sub-7 GHz PPDU tone plan that comprises M subcarriers including the second number of data subcarriers, N is equal to 64, M is equal to 256, the BW is equal to $20 \times X$ MHz, the first portion of the PHY preamble is duplicated in each of 4 sub-bands within the BW and upclocked by a factor of $X/4$, each sub-band has a bandwidth of $5 \times X$ MHz, and the data field is upclocked by a factor of X.

25. The wireless communication device of claim 23, wherein: the PPDU further includes a data field and the at least one processor is further configured to cause the wireless communication device to map the data field to a second number of data subcarriers in accordance with a second sub-7 GHz PPDU tone plan that comprises M subcarriers including the second number of data subcarriers, N is equal to 64, M is equal to 256, the BW is equal to $80 \times X$ MHz, the first portion of the PHY preamble is duplicated in each of 4 sub-bands within the BW, each sub-band has a bandwidth of $20 \times X$ MHz, and the data field is upclocked by a factor of X.

26. A method of wireless communication performed by a wireless communication device comprising: mapping a first portion of a physical layer (PHY) preamble of a PHY protocol data unit (PPDU) to a number (N) of subcarriers, the first portion including a short training field (STF) and one or more signal (SIG) fields carrying information for interpreting the PPDU; mapping a second portion of the PHY preamble that includes a long training field (LTF) to a number (M) of subcarriers, where $M > N$; transforming the N subcarriers and the M subcarriers to a time-varying signal; and transmitting the PPDU including the time-varying signal on a carrier frequency above 7 GHz.

27. The method of claim 26, further comprising: mapping, to the M subcarriers, at least a data field, a packet extension, or one or more other training fields (TRNs) of the PPDU.

28. The method of claim 26, wherein the N subcarriers and the M subcarriers are transformed to the time-varying signal at a sampling rate ($f_{\text{sub.s}}$) associated with a subcarrier spacing (SCS) greater than 1.2 MHz, the SCS representing an amount of separation, in a frequency domain, between adjacent subcarriers of the N subcarriers.

29. Method of claim 28, wherein the first portion of the PPDU is duplicated for transmission on a number (n) of sub-bands each spanning a respective bandwidth portion of a bandwidth over which the PPDU is transmitted.

30. A wireless communication device comprising: at least one memory; and at least one processor communicatively coupled with the at least one memory, the at least one processor configured to

cause the wireless communication device to: map a first portion of a physical layer (PHY) preamble of a PHY protocol data unit (PPDU) to a number (N) of subcarriers, the first portion including a short training field (STF) and one or more signal (SIG) fields carrying information for interpreting the PPDU; map a second portion of the PHY preamble that includes a long training field (LTF) to a number (M) of subcarriers, where $M > N$; transform the N subcarriers and the M subcarriers to a time-varying signal; and transmit the time-varying signal.
