

US Patent & Trademark Office

Patent Public Search | Text View

United States Patent	12417815
Kind Code	B2
Date of Patent	September 16, 2025
Inventor(s)	Jeong; Jin Ho et al.

Memory device including error correction device

Abstract

A memory device includes a memory cell area including a plurality of cell blocks divided into a plurality of normal cell blocks, at least one ECC cell block, and at least one redundancy cell block, the plurality of cell blocks being configured to output data and error correction codes; an error correction circuit configured to generate error-corrected data by correcting errors in the data using the error correction codes; a first switch group configured to output the error-corrected data while performing, according to first repair control information, a shifting operation on the error-corrected data; and a second switch group configured to transfer the data from the memory cell area to the error correction circuit while performing, according to second repair control information, a zero-padding operation on the data output from one of the cell blocks.

Inventors: Jeong; Jin Ho (Gyeonggi-do, KR), Kim; Dae Suk (Gyeonggi-do, KR), Yoon; Sang Woo (Gyeonggi-do, KR), Rim; A Ram (Gyeonggi-do, KR), Jang; Mun Seon (Gyeonggi-do, KR)

Applicant: SK hynix Inc. (Gyeonggi-do, KR)

Family ID: 1000008820810

Assignee: SK hynix Inc. (Gyeonggi-do, KR)

Appl. No.: 18/314147

Filed: May 09, 2023

Prior Publication Data

Document Identifier	Publication Date
US 20240177793 A1	May. 30, 2024

Foreign Application Priority Data

KR	10-2022-0160360	Nov. 25, 2022
----	-----------------	---------------

Publication Classification

Int. Cl.: G11C29/44 (20060101); G11C29/00 (20060101); G11C29/52 (20060101)

U.S. Cl.:

CPC G11C29/52 (20130101); G11C29/44 (20130101); G11C29/789 (20130101);

Field of Classification Search

CPC: G11C (29/52); G11C (29/44); G11C (29/789); G11C (29/72); G11C (29/846); G11C (29/848); G11C (29/74); G11C (29/42); G11C (29/76); G11C (29/808); G06F (11/1048); G06F (30/32)

References Cited

U.S. PATENT DOCUMENTS

Patent No.	Issued Date	Patentee Name	U.S. Cl.	CPC
2014/0169092	12/2013	Miyamoto	365/185.05	G06F 11/1048
2017/0091027	12/2016	Sohn	N/A	G11C 29/4401
2020/0183781	12/2019	Nakai	N/A	N/A
2020/0365226	12/2019	Ryu	N/A	G06F 13/4022

FOREIGN PATENT DOCUMENTS

Patent No.	Application Date	Country	CPC
10-2018-0059149	12/2017	KR	N/A

Primary Examiner: Bashar; Mohammed A

Attorney, Agent or Firm: IP & T GROUP LLP

Background/Summary

CROSS-REFERENCE TO RELATED APPLICATION

(1) The present application claims priority under 35 U.S.C. § 119(a) to Korean Patent Application No. 10-2022-0160360, filed on Nov. 25, 2022, which is incorporated herein by reference in its entirety.

BACKGROUND

1. Field

(2) Various embodiments of the present invention relate to a semiconductor design technology, and more particularly, to a memory device including a memory cell array including a redundancy cell block and an error correction code (ECC) cell block.

2. Description of the Related Art

(3) In the early stage of a semiconductor memory industry, memory chips were produced with no defective memory cells through a semiconductor fabrication process. However, as the capacity of memory devices increases, it becomes difficult to fabricate a memory device having no defective memory cell. Currently, there is substantially no chance that a memory device can be fabricated without any defective memory cells. To address this issue, a repair method of replacing defective

memory cells with redundant memory cells, or an error correcting method for correcting errors in a memory device using an error correction circuit is being used.

SUMMARY

(4) Embodiments of the present invention are directed to a memory device capable of managing a miscorrection of an error correction device due to a defective sub-word line driver during a shifting operation for column repair, within a set specification range.

(5) According to an embodiment of the present invention, a memory device includes a memory cell area including a plurality of cell blocks divided into a plurality of normal cell blocks, at least one ECC cell block, and at least one redundancy cell block, the plurality of cell blocks being configured to output data and error correction codes; an error correction circuit configured to generate error-corrected data by correcting errors in the data using the error correction codes; a first switch group configured to output the error-corrected data while performing, according to first repair control information, a shifting operation on the error-corrected data; and a second switch group configured to transfer the data from the memory cell area to the error correction circuit while performing, according to second repair control information, a zero-padding operation on the data output from one of the cell blocks.

(6) According to an embodiment of the present invention, a memory device includes a memory cell area including a plurality of cell blocks divided into a plurality of normal cell blocks, at least one error correction code (ECC) cell block, and at least one redundancy cell block, the plurality of cell blocks being configured to output data and error correction codes; an error correction circuit including a plurality of code calculation circuits corresponding to the cell blocks and configured to generate error-corrected data by correcting errors in the data using the error correction codes while performing, according to second repair control information, a zero-padding operation on a result of calculating on a part of the data by any one of the code calculation circuits; and a first switch group configured to output the error-corrected data while performing, according to first repair control information, a shifting operation on the error-corrected data.

(7) According to an embodiment of the present invention, a memory device includes memory blocks arranged in a row and configured to store therein a zero-padded data piece, user data pieces and an error correction code (ECC) data piece, the zero-padded data piece being stored in a column-repaired one of the memory blocks and one of the user data pieces corresponding to the column-repaired memory block; a swapping circuit configured to swap, with each other, the ECC data piece and the user data piece from neighboring two among the memory blocks; a zero-padding circuit configured to generate a zero-padded data piece for the zero-padded data piece from the column-repaired memory block; an error-correcting circuit configured to error-correct, based on the ECC data piece from the swapping circuit, the zero-padded data piece from the zero-padding circuit and the user data pieces from the memory blocks and the swapping circuit; and a shifting circuit configured to output the error-corrected user data pieces by shifting the error-corrected user data pieces from the error-correcting circuit.

(8) The shifting circuit may be further configured to receive user data pieces from an external device to shift the received user data pieces, the zero-padding circuit may be further configured to generate a zero-padded data piece to be stored in the column-repaired memory block, the error-correcting circuit may be further configured to generate an ECC data piece for the generated zero-padded data piece and the shifted user data pieces, the swapping circuit may be further configured to swap, with each other, the generated ECC data piece and the shifted user data piece to be stored in the neighboring memory blocks, and the memory blocks may be further configured to store therein the generated zero-padded data piece, the shifted user data pieces and the swapped data pieces.

(9) According to an embodiment of the present invention, a memory device includes a shifting circuit configured to receive user data pieces from an external device to shift the user data pieces; a zero-padding circuit configured to generate a zero-padded data piece; an error-correcting circuit

configured to generate an error correction code (ECC) data piece for the zero-padded data piece and the shifted user data pieces; a swapping circuit configured to swap, with each other, the ECC data piece and the shifted user data piece to be stored in neighboring two among memory blocks; and the memory blocks arranged in a row and configured to store therein the zero-padded data piece, the shifted user data pieces and the ECC data piece, the memory blocks including a column-repaired memory block that the zero-padded data piece is to be stored in and a redundancy memory block that one of the shifted user data pieces corresponding to the column-repaired memory block is to be stored in.

(10) According to the embodiments of the present invention, the memory device may manage the error correction within a set range and maximize the error correction ability by performing the shifting operation for column repair after performing a zero-padding-based error correction.

Description

BRIEF DESCRIPTION OF THE DRAWINGS

- (1) FIG. 1 is a block diagram illustrating cell blocks included in a memory device.
- (2) FIGS. 2A and 2B are diagrams for describing a miscorrection of an error correction device due to a defect in a sub-word line driver.
- (3) FIG. 3 is a block diagram illustrating a memory device in accordance with an embodiment of the present invention.
- (4) FIG. 4 is a detailed configuration diagram illustrating a memory cell area and a column control circuit of FIG. 3 according to an embodiment of the present invention.
- (5) FIG. 5 is a detailed block diagram illustrating a repair control circuit of FIG. 3 according to an embodiment of the present invention.
- (6) FIGS. 6A and 6B are a block diagram and a table illustrating an information generation circuit of FIG. 5 according to an embodiment of the present invention.
- (7) FIG. 7 is a block diagram illustrating an error correction device of FIG. 3.
- (8) FIGS. 8A and 8B are diagrams illustrating the memory device of FIG. 3 in more detail according to an embodiment of the present invention.
- (9) FIGS. 9A to 12B are diagrams illustrating an operation of a memory device according to various embodiments of the present invention.
- (10) FIGS. 13A to 13C are diagrams illustrating a modified example of the memory device of FIGS. 8A and 8B according to an embodiment of the present invention.
- (11) FIGS. 14A and 14B are diagrams illustrating the memory device of FIG. 3 in more detail according to another embodiment of the present invention.
- (12) FIG. 15 is a detailed configuration diagram illustrating an error correction device of FIGS. 14A and 14B according to an embodiment of the present invention.
- (13) FIG. 16 is a circuit diagram for describing any one code calculation circuit of FIG. 15 according to an embodiment of the present invention.

DETAILED DESCRIPTION

- (14) Various embodiments of the present invention will be described below in more detail with reference to the accompanying drawings. The present invention may, however, be embodied in different forms and should not be construed as limited to the embodiments set forth herein. Rather, these embodiments are provided so that this disclosure will be thorough and complete, and will fully convey the scope of the present invention to those skilled in the art. Throughout this disclosure, like reference numerals refer to like parts throughout the various figures and embodiments of the present invention.
- (15) It will be understood that when an element is referred to as being “coupled” or “connected” to another element, it may mean that the two are directly coupled or the two are electrically connected

to each other with another circuit intervening therebetween. It will be further understood that the terms “comprise”, “include”, “have”, etc. when used in this specification, specify the presence of stated features, numbers, steps, operations, elements, components, and/or combinations of them but do not preclude the presence or addition of one or more other features, numbers, steps, operations, elements, components, and/or combinations thereof. In the present disclosure, the singular forms are intended to include the plural forms as well, unless the context clearly indicates otherwise.

(16) FIG. 1 is a block diagram illustrating cell blocks included in a memory device **10**.

(17) Referring to FIG. 1, the memory device **10** may include a plurality of cell blocks arranged in a row direction. The plurality of cell blocks may include a plurality of normal cell blocks MB0 to MB15 and an error correction code (ECC) cell block MBECC. Each cell block may include a plurality of memory cells connected between a plurality of word lines WL and a plurality of bit lines BL. For reference, the memory device **10** of FIG. 1 shows a case where data is input/output in 8-bit units for each cell block during a single write and read operation. That is, the memory device **10** of FIG. 1 may input/output 128-bit data and use an 8-bit error correction code ECC.

(18) Rectangles between the cell blocks MB0 to MB15, and MBECC may represent sub-word line drivers SWD, and lines extending left and right of the sub-word line drivers SWD may represent word lines (or sub-word lines, WL). In reality, there are far more sub-word line drivers and word lines, but only a few are shown here to represent a simple structure. Since adjacent cell regions among the cell blocks MB0 to MB15, and MBECC share sub-word line drivers, when a defect occurs in the sub-word line driver, an error is likely to occur in cell blocks at both sides of the sub-word line driver. For example, since the second normal cell block MB1 and the third normal cell block MB2 share a sub-word line driver, errors may occur simultaneously in the first to fourth normal cell blocks MB0 to MB3 when a defect occurs in the shared sub-word line driver.

(19) Meanwhile, a memory device such as DRAM may additionally include at least one redundancy cell block to repair column defects in addition to the normal cell blocks MB0 to MB15 and the ECC cell block MBECC. In this case, when a column of a specific normal cell block is repaired, the redundancy cell block may be selected instead of the repaired normal cell block indicated when accessing the repaired column. In this case, due to a physical distance between the repaired cell block and the redundancy cell block, a shifting operation is performed to replace all cell blocks in a direction to the redundancy cell block from the repaired cell block respectively with adjacent cell blocks. Due to the shifting operation and the defective sub-word line driver, a miscorrection of an error correction device may occur to cause errors, an amount of which exceeds a predetermined range, i.e., the error correction capability of the controller. Due to the miscorrection of the error correction device, which is caused by the shifting operation and the defective sub-word line driver, the controller may not be able to error-correct the data output from the memory device **10**.

(20) FIGS. 2A and 2B are diagrams for describing a miscorrection of an error correction device due to a defect in a sub-word line driver. FIGS. 2A and 2B illustrate a case where two cell blocks respectively output data BL07 and BL8F in 8-bit units through one pad, during a read operation.

(21) Referring to FIG. 2A, a case where errors occurred due to a defective sub-word line driver “SWD Fault”, but a column repair operation is not performed, is illustrated. The defective sub-word line driver “SWD Fault” is disposed between the fourth normal cell block MB3 and the fifth normal cell block MB4, and thus the errors may occur in the third to sixth normal cell blocks MB2 to MB5.

(22) A repair circuit **15** does not perform a shifting operation according to repair information indicating that the column repair operation is not performed, and thus, switches of the repair circuit **15** may transfer data output from the normal cell blocks MB0 to MB15 and the ECC cell block MBECC to an on-chip error correction device **16**. When the on-chip error correction device **16** is capable of 1-bit error correction, the on-chip error correction device **16** may not correct the errors due to the defective sub-word line driver “SWD Fault”, resulting in miscorrection. The on-chip

error correction device **16** outputs 128-bit data to an external controller through data pads DQ0 to DQ7.

(23) In this case, the errors due to the defective sub-word line driver “SWD Fault” may exist in data output through the second data pad DQ1 and the third data pad DQ2. When the controller's error correction ability set in the specification may cover errors of continuous 32-bit data, the errors in the data may be corrected by error correction of the controller. As a result, the miscorrection may occur due to the occurrence of an error exceeding the error correction capability of the on-chip error correction device **16**, but the error correction capability of the controller may cover the miscorrection. In other words, when a shifting operation for column repair is not performed, the miscorrection of the on-chip error correction device **16** due to the errors occurring in the defective sub-word line driver “SWD Fault” may occur within a specified specification (i.e., the error correction capability of the controller) to ensure a normal operation of the system.

(24) Referring to FIG. 2B, a case where errors occurred due to a defective sub-word line driver “SWD Fault” and, at the same time, a column repair operation is performed on the first normal cell block MB0, is illustrated.

(25) The repair circuit **15** performs a shifting operation according to repair information indicating that the column repair operation is performed. Since the column repair operation has occurred in the first normal cell block MB0, switches of the repair circuit **15** may shift and transfer data output from the remaining normal cell blocks MB1 to MBEC15, the ECC cell block MBECC, and the redundancy cell block MBRED to code calculation circuits H0 to H15 and HECC of the on-chip error correction device **16**. In this case, since possible error data due to the defective sub-word line driver “SWD Fault” may be shifted and transferred to the code calculation circuits H1 to H4 from the third to sixth normal cell blocks MB2 to MB5, the on-chip error correction device **16** may cause not only the miscorrection due to the defective sub-word line driver “SWD Fault” but also an additional miscorrection. For example, the on-chip error correction device **16** may incorrectly miscorrect the data to be transferred to the seventh data pad DQ6. The on-chip error correction device **16** may output 128-bit data to the external controller through the data pads DQ0 to DQ7.

(26) In this case, the errors due to the defective sub-word line driver “SWD Fault” may exist in data output through the first data pad DQ0, the second data pad DQ1 and the third data pad DQ2. Further, the error may also exist in the data output through the seventh data pad DQ6 due to the miscorrection of the on-chip error correction device **16**. The errors of data output through the seventh data pad DQ6 may be beyond the error correction capability of the controller and therefore may not be corrected by the controller to cause failure of read operation. As a result, the errors due to the miscorrection of the on-chip error correction device **16** becomes more serious due to the shifting operation, and these errors cannot be corrected by the controller. That is, due to the shifting operation and the defective sub-word line driver, the miscorrection of an error correction device may cause errors, an amount of which exceeds a predetermined range (i.e., the error correction capability of the controller).

(27) Therefore, for a memory device with a redundancy cell block MBRED, there is a need for a scheme for managing a miscorrection that causes additional errors due to the defective sub-word line driver, within a set specification range (or boundary) when a shifting operation for column repair is performed in the memory device with the redundancy cell block MBRED.

(28) FIG. 3 is a block diagram illustrating a memory device **100** in accordance with an embodiment of the present invention. FIG. 4 is a detailed configuration diagram illustrating a memory cell area **110** and a column control circuit **130** of FIG. 3 according to an embodiment of the present invention.

(29) Referring to FIG. 3, the memory device **100** may include a memory cell area **110**, a row control circuit **120**, a column control circuit **130**, a repair control circuit **140**, a repair circuit **150**, an error correction device **160**, a data input/output (I/O) circuit **170**, a command input circuit **182**, an address input circuit **184**, and a command decoder **186**.

(30) The command input circuit **182** may receive a command CMD, and the address input circuit **184** may receive an address ADD, from an external device e.g., a memory controller. The address input circuit **184** may receive the address ADD and output a row address RADD and a column address CADD. Each of the command CMD and the address ADD may include a multi-bit signal. The command decoder **186** may decode the command CMD input through the command input circuit **182** and may generate an active command ACT, a precharge command PCG, a read command RD, a write command WT, and the like. The command decoder **186** may generate a refresh command, and a mode register command, as well as other commands, by decoding received commands CMD.

(31) The memory cell area **110** may be coupled to the row control circuit **120** through a plurality of word lines WL, and may be coupled to the column control circuit **130** through a plurality of bit lines BL. Referring to FIG. 4, the memory cell area **110** may include a plurality of cell blocks MB0 to MB15, MBECC, and MBRED. Each of the plurality of cell blocks MB0 to MB15, MBECC, and MBRED may include a plurality of memory cells MC arranged in an array form between the plurality of word lines WL and the plurality of bit lines BL. In an embodiment of the present invention, a “cell block” may be defined as a set of memory cells that share word lines WL and bit lines BL and are arranged in the same shape.

(32) The plurality of cell blocks may include first to 16-th normal cell blocks MB0 to MB15, at least one error correction code (ECC) cell block MBECC, and at least one redundancy cell block MBRED. The first to 16-th normal cell blocks MB0 to MB15 may store data DO to D127 received from an external device through the data I/O circuit **170**. The first to 16-th normal cell blocks MB0 to MB15 may be regions for storing user data and are memory blocks for determining a memory capacity of the memory device **100**. The ECC cell block MBECC may store error correction codes P0 to P7 generated by the error correction device **160** for an error correction operation. As will be described later, when a shifting operation for column repair is performed, the error correction codes P0 to P7 may be stored in a normal cell block (e.g., the ninth normal cell block MB8) adjacent to the ECC cell block MBECC. The error correction codes P0 to P7 may include known parity bits. The redundancy cell block MBRED may be provided for a repair operation of the first to 16-th normal cell blocks MB0 to MB15 and the ECC cell block MBECC, and may include a plurality of redundancy cells (e.g., a plurality of redundancy bit lines) to replace defective cells (e.g., a plurality of defective bit lines) among the first to 16-th normal cell blocks MB0 to MB15 and the ECC cell block MBECC.

(33) In FIG. 4, one ECC cell block MBECC and one redundancy cell block MBRED are illustrated, but the present invention is not limited thereto, and one or more ECC cell blocks MBECC and redundancy cell blocks MBRED may be disposed. A plurality of normal cell blocks MB0 to MB15 may be divided into first to eighth normal cell blocks MB0 to MB7 corresponding to a lower group and ninth and 16-th normal cell blocks MB8 to MB15 corresponding to an upper group. In this case, the first to eighth normal cell blocks MB0 to MB7, the ECC cell block MBECC, the ninth and 16-th normal cell blocks MB8 to MB15, and the redundancy cell block MBRED may be sequentially disposed in a row direction.

(34) Referring back to FIG. 3, the row control circuit **120** may activate the word line WL corresponding to the row address RADD according to the active command ACT and may precharge the activated word line WL according to the precharge command PCG.

(35) The column control circuit **130** may select some bit lines from among the bit lines BL according to the column address CADD. For reference, a predetermined number of bit lines BL may be coupled to one column selection line (CSL of FIG. 4), and the column control circuit **130** may select at least one column selection line CSL from a plurality of column selection lines according to the column address CADD. As the bit lines are selected by the column control circuit **130**, the data DO to D127 and the error correction codes P0 to P15 may be read from the memory cell area **110** or written to the memory cell area **110**.

(36) Referring to FIG. 4, the column control circuit **130** may include a column decoder **132** and first to 18-th column switches CSW**0** to CSW**17**. The column decoder **132** may decode the column address CADD to generate a column selection signal YI. The first to 18-th column switches CSW**0** to CSW**17** may correspond to the first to eighth normal cell blocks MB**0** to MB**7**, the ECC cell block MBECC, the ninth to 16-th normal cell blocks MB**8** to MB**15**, and the redundancy cell block MBRED, respectively. Each of the first to 18-th column switches CSW**0** to CSW**17** may select one of the column selection lines CSL of the corresponding cell block according to the column selection signal YI. As one of the column selection lines CSL is selected, a predetermined number (e.g., 8) of bit lines may be selected. According to an embodiment, the column control circuit **130** may further include a sense amplifier circuit that senses and amplifies data of the selected column selection line according to the read command RD, and a write driver that writes data to the memory cell area **110** through the selected column selection line according to the write command WT.

(37) Referring back to FIG. 3, the repair control circuit **140** may store, as repair information R_INF, addresses of defective cells of the normal cell blocks MB**0** to MB**15** and the ECC cell block MBECC. The repair control circuit **140** may provide first to third repair control information C_REP**1** to C_REP**3** corresponding to the column address CADD to the first to third switch groups **152** to **156**, respectively, based on the stored repair information R_INF. Each of the first and second repair control information C_REP**1** and C_REP**2** may include multi-bit signals. A detailed configuration of the repair control circuit **140** will be described with reference to FIGS. 5 to 6B.

(38) The repair circuit **150** may include the first to third switch groups **152** to **156** with a configuration for performing a shifting operation for column repair, a zero-padding operation and a swap operation.

(39) The first switch group **152** may transfer data DO**0** to DO**127** between the data I/O circuit **170** and the error correction device **160** while performing a shifting operation for column repair according to the first repair control information C_REP**1**. The first switch group **152** may correspond to the repair circuit **15** described in FIGS. 2A and 2B. The repair circuit **15** of FIGS. 2A and 2B is disposed between the memory cell area **110** and the error correction device **160**, while the first switch group **152** of FIG. 3 is disposed between the data I/O circuit **170** (i.e., data pads DQ**0** to DQ**7**) and the error correction device **160**. For reference, since the shifting operation for column repair is performed after the error correction operation is performed during a read operation, 8-bit data R**0** to R**7** may be output from the redundancy cell block MBRED in addition to the 128-bit data DO to D**127** and the 8-bit error correction codes P**0** to P**7**.

(40) The second switch group **154** may be disposed in an input path of the error correction device **160** to perform a zero-padding operation according to the second repair control information C_REP**2**. The second switch group **154** may be disposed between the third switch group **156** and the error correction device **160** for a read operation, or between the first switch group **152** and the error correction device **160** for a write operation. For example, during the read operation, the second switch group **154** may transfer the data DO to D**127** and R**0** to R**7** from the third switch group **156** to the error correction device **160**, by replacing some of the data DO to D**127** and R**0** to R**7** with zero-data, according to the second repair control information C_REP**2**. During the write operation, the second switch group **154** may transfer the data DO**0** to DO**127** from the first switch group **152** to the error correction device **160** by adding the data DO**0** to DO**127** with zero-data, according to the second repair control information C_REP**2**. As a result, the data of 136-bit zero-padded by the second switch group **154** may be transferred to the error correction device **160**.

(41) During a read operation, the third switch group **156** may transfer the data DO to D**127** and R**0** to R**7** and the error correction codes P**0** to P**7** between the memory cell area **110** and the second switch group **154**, while performing a swap operation on data input to or output from the ECC cell block MBECC with data input to or output from the ninth normal cell block MB**8** adjacent to the ECC cell block MBECC, according to the third repair control information C_REP**3**. For example, during the read operation, the third switch group **156** may swap the data output from the ECC cell

block MBECC and the data output from the ninth normal cell block MB8 according to the third repair control information C_REP3, and transfer the swapped data to the second switch group 154. During the write operation, the third switch group 156 may swap and transfer the data input to the ECC cell block MBECC with the data input to the ninth normal cell block MB8 according to the third repair control information C_REP3. For reference, the error correction codes P0 to P7 generated from the error correction device 160 by the swap operation may be stored in one of the ECC cell block MBECC and the ninth normal cell block MB8.

(42) The error correction device 160 may generate the error correction codes P0 to P7 using the data DO0 to DO127 from the data I/O circuit 170 and zero-padded by the second switch group 154, in response to the write command WT. The error correction device 160 may correct errors of the zero-padded data DO to D127 and R0 to R7 transferred through the second switch group 154 from the memory cell area 110, using the error correction codes P0 to P7, in response to the read command RD. That is, during the read operation, the error correction device 160 may output the error corrected data DO0 to DO127 by correcting the errors of the data DO to D127 and R0 to R7 zero-padded by the second switch group 154, using the error correction codes P0 to P7. The error corrected data DO0 to DO127 may be output to the outside through the data pads DQ0 to DQ7 by the data I/O circuit 170. A detailed configuration of the error correction device 160 will be described with reference to FIG. 7.

(43) The data I/O circuit 170 may input/output the data DO0 to DO127 through the data pads DQ0 to DQ7. A unit of 16-bit data may be input through one data pad during the write operation, and a unit of 16-bit data may be output through one data pad during the read operation. When eight data pads DQ0 to DQ7 are disposed in the memory device 100, the 128-bit data DO0 to DO127 may be input to the memory device 100 during the write operation, and the 128-bit data DO0 to DO127 may be output from the memory device 100 during the read operation.

(44) FIG. 5 is a detailed block diagram illustrating the repair control circuit 140 of FIG. 3 according to an embodiment of the present invention. FIGS. 6A and 6B are a block diagram and a table illustrating an information generation circuit 146 of FIG. 5 according to an embodiment of the present invention.

(45) Referring to FIG. 5, the repair control circuit 140 may include first to 17-th address storing circuits 142_0 to 142_16, a shifting control circuit 144, and an information generation circuit 146.

(46) The first to 17-th address storing circuits may correspond to the first to eighth normal cell blocks MB0 to MB7, the ECC cell block MBECC, and the ninth and 16-th normal cell blocks MB8 to MB15, respectively, and may store one or more defective addresses of the respective blocks. The first to 17-th address storage circuits 142_0 to 142_16 may generate first to 17-th match signals HIT0 to HIT16 by respectively comparing the column address CADD with the stored defective addresses. Each of the first to 17-th address storage circuits 142_0 to 142_16 may activate a corresponding match signal to a logic high level when the column address CADD is identical to any of the stored defect addresses. For reference, that a specific match signal is activated may mean that a repair operation has been performed on the corresponding cell block. For example, when the second match signal HIT1 is activated, it may mean that the second normal cell block MB1 is repaired to use the redundancy cell block MBRED, and when the ninth match signal HIT8 is activated, it may mean that the ECC cell block is repaired MBECC to use the redundant cell block MBRED.

(47) The shifting control circuit 144 may generate first to 17-th shifting signals SH0 to SH16 respectively corresponding to the first to 17-th match signals HIT0 to HIT16. The shifting control circuit 144 may activate the first to 17-th shifting signals SH0 to SH16 to a logic high level when the first match signal HIT0 is activated, and in this way, activate the K-th to 17-th shifting signals SH(K-1) to SH16 to a logic high level when the K-th match signal HIT(K-1) is activated.

(48) In detail, the shifting control circuit 144 may include first to 16-th OR gates 144_1 to 144_16. The shifting control circuit 144 may output the first match signal HIT0 as the first shifting signal

SH0, and the first OR gate **144_1** may output the second shifting signal SH1 by performing a logic OR operation on the first shifting signal SH0 and the second match signal HIT1. In this way, the seventh OR gate **144_7** may output eighth shifting signal SH7 by performing a logic OR operation on the eighth match signal HIT7 and the seventh shifting signal SH6. That is, each of the first to 16-th OR gates **144_1** to **144_16** may perform a logic OR operation on a corresponding match signal and a shifting signal of a previous stage to output a corresponding shifting signal.

(49) The information generation circuit **146** may generate the first to third repair control information C_REP1 to C_REP3 according to the first to 17-th match signals HIT0 to HIT16 and the first to 17-th shifting signals SH0 to SH16.

(50) Referring to FIG. 6A, the information generation circuit **146** may include a first logic gate LG1, a second logic gate LG2, and first to third signal generation circuits **146_1** to **146_3**.

(51) The first logic gate LG1 may output an intermediate match signal HIT8_9 by performing a logic OR operation on the ninth match signal HIT8 and the tenth match signal HIT9. For reference, the ninth match signal HIT8 is a signal activated when the repair operation is performed in the ECC cell block MBECC, and the tenth match signal HIT9 is a signal activated when the repair operation is performed in the ninth normal cell blocks MB8. That is, the intermediate match signal HIT8_9 may be activated when the repair operation is performed in the ECC cell block MBECC or the ninth normal cell blocks MB8. The second logic gate LG2 may invert the 17-th shifting signal SH16 to output an inverted shifting signal SHB16. Since the 17-th shifting signal SH16 is a signal indicating that any one repair operation is performed and the redundancy cell block MBRED is used, the inverted shifting signal SHB16 may be activated when no repair occurs. Hereinafter, the inverted shifting signal SHB16 is defined as a no-repair signal SHB16.

(52) The first signal generation circuit **146_1** may configure the 16-bit first repair information C_REP1 using the first to eighth shifting signals SH0 to SH7 and the tenth to 17-th shifting signals SH9 to SH16. For example, as shown in FIG. 6B, in a case where the first match signal HIT0 is activated due to the repair operation in the first normal cell block MB0, and thus all of the first to 17-th shifting signals SH0 to SH16 are activated, the first signal generation circuit **146_1** may generate the first repair information C_REP1 of all high bits. In a case where the second match signal HIT1 is activated due to the repair operation in the second normal cell block MB1, and thus all of the second to 17-th shifting signals SH1 to SH16 are activated, the first signal generation circuit **146_1** may generate the first repair information C_REP1 in which bits except for a least significant bit (LSB) are all high bits. In a case where the ninth match signal HIT8 is activated due to the repair operation in the ECC cell block MBECC and thus all of the ninth to 17-th shifting signals SH8 to SH16 are activated, or the tenth match signal HIT9 is activated due to the repair operation in the ninth normal cell block MB8 and thus all of the tenth to 17-th shifting signals SH9 to SH16 are activated, the first signal generation circuit **146_1** may generate the first repair information C_REP1 in which only the upper 8 bits are all high bits. In a case where the 17-th match signal HIT16 is activated due to the repair operation in the 16-th cell block MB15 and thus the 17-th shifting signal SH16 is only activated, the first signal generation circuit **146_1** may generate the first repair information C_REP1 in which only a most significant bit (MSB) is a high bit. In a case where all match signals HIT0 to HIT16 are deactivated due to no repair and thus the first to 17-th shifting signals SH0 to SH16 are deactivated, the first signal generation circuit **146_1** may generate the first repair information C_REP1 of all low bits.

(53) The second signal generation circuit **146_2** may configure the 17-bit second repair information C_REP2 using the first to eighth match signals HIT0 to HIT7, the intermediate match signal HIT8_9, the eleventh to 17-th match signals HIT10 to HIT16, and the no-repair signal SHB16. For example, as shown in FIG. 6B, in a case where the first match signal HIT0 is activated due to the repair operation in the first normal cell block MB0, the second signal generation circuit **146_2** may generate the second repair information C_REP2 in which only a first bit is a high bit. In a case where the second match signal HIT1 is activated due to the repair operation in the second normal

cell block MB1, the second signal generation circuit **146_2** may generate the second repair information C_REP2 in which only a second bit is a high bit. In a case where the ninth match signal HIT8 is activated due to the repair operation in the ECC cell block MBECC or the tenth match signal HIT9 is activated due to the repair operation in the ninth normal cell block MB8, the second signal generation circuit **146_2** may generate the second repair information C_REP2 in which only a ninth bit is a high bit. In a case where the 17-th match signal HIT16 is activated due to the repair operation in the 16-th cell block MB15, the second signal generation circuit **146_2** may generate the second repair information C_REP2 in which only a 16-th bit is a high bit. In a case where all match signals HIT0 to HIT16 are deactivated due to no repair, the second signal generation circuit **146_2** may generate the second repair information C_REP2 in which only a 17-th bit is a high bit.

(54) The third signal generation circuit **146_3** may output the ninth shifting signal SH8 as the third repair information C_REP3. For example, as shown in FIG. 6B, the third signal generation circuit **146_3** may generate the third repair information C_REP3 of a high bit when the repair operation is performed in one of the first to eighth normal cell blocks MB0 to MB7 and the ECC cell block MBCC and thus the ninth shifting signal SH8 is activated. The third signal generation circuit **146_3** may generate the third repair information C_REP3 of a low bit when the repair operation is not performed, or the repair operation is performed in one of the ninth to 16-th normal cell blocks MB8 to MB15 and thus the ninth shifting signal SH8 is deactivated.

(55) FIG. 7 is a block diagram illustrating the error correction device **160** of FIG. 3 according to an embodiment of the present invention.

(56) Referring to FIG. 7, the error correction device **160** may include an error correction code generation circuit **162** and an error correction circuit **164**.

(57) The error correction code generation circuit **162** may generate the error correction codes P0 to P7 of 8-bit, using the zero-padded data DO0 to DO127, during the write operation in which the write command WT is input. Since the error correction codes P0 to P7 are generated by the error correction code generation circuit **162** without performing an error correction operation during the write operation, the data DO0 to DO127 input to the error correction code generation circuit **162** are the same as the data DO to D127 output from the error correction code generation circuit **162**.

(58) The error correction circuit **164** may correct errors in the zero-padded data DO to D127 and R0 to R7, using the error correction codes P0 to P7 of 8-bit, during the read operation in which the read command RD is input. Here, correcting the error may mean detecting the error of the data DO to D127 and R0 to R7 using the error correction codes P0 to P7 and correcting the error when the error is detected. The data DO0 to DO127 in which the error is corrected by the error correction circuit **164** may be output to the outside through the data pads DQ0 to DQ7 by the data I/O circuit **170**.

(59) The error correction code generation circuit **162** or the error correction circuit **164** may generate the error correction codes using a check matrix, also called an H matrix, which will be described below.

(60) Meanwhile, the error correction code generation circuit **162** and the error correction circuit **164** may generate the error correction code using a check matrix, also called an H matrix, and correct an error using the error correction codes. To this end, the error correction code generation circuit **162** and the error correction circuit **164** may include a plurality of check matrix calculation circuits (hereinafter, referred to as "code calculation circuits"). According to an embodiment, the error correction code generation circuit **162** and the error correction circuit **164** may use common code calculation circuits or may use separate code calculation circuits, respectively. The code calculation circuit may generate the error correction codes by applying a known BCH code, Hamming code, or RS code. The code calculation circuit may generate the error correction codes by applying another type of parity code.

(61) Hereinafter, detailed configurations of a memory device according to an embodiment of the

present invention and a connection relationship therebetween will be described with reference to the drawings.

(62) FIGS. **8A** and **8B** are diagrams illustrating the memory device **100** of FIG. **3** in more detail according to an embodiment of the present invention.

(63) Referring to FIG. **8A**, configurations for a read operation of the memory device **100** are illustrated. The error correction circuit **164** of the error correction device **160** may include a plurality of normal code calculation circuits **H0** to **H15**, at least one ECC code calculation circuit **HECC**, and at least one redundancy code calculation circuit **HRED**. The plurality of code calculation circuits may respectively correspond to the plurality of cell blocks. The on-chip error correction device **16** of FIGS. **2A** and **2B** includes the code calculation circuits **H0** to **H15** and **HECC** having the number (i.e., **17**) corresponding to the normal cell blocks **MB0** to **MB15** and the ECC cell block **MBECC**, whereas the error correction circuit **164** according to the embodiment of the present invention may include the code calculation circuits **H0** to **H15**, **HECC**, and **HRED** having the number (i.e., **18**) corresponding to the normal cell blocks **MB0** to **MB15**, the ECC cell block **MBECC**, and the redundancy cell block **MBRED**.

(64) During the read operation, the third switch group **156** may transfer the data **DO** to **D127** and **R0** to **R7** and the error correction codes **P0** to **P7** output from the memory cell area **110** to the second switch group **154**, while performing a swap operation on the data output from the ECC cell block **MBECC** with the data output from the ninth normal cell block **MB8**, according to the third repair control information **C_REP3**.

(65) In detail the third switch group **156** may include a first swap switch **S1** and a second swap switch **S2**. The first swap switch **S1** may transfer one of the data output from the ECC cell block **MBECC** and the data output from the ninth normal cell block **MB8** to the ECC code calculation circuit **HECC**, according to the third repair information **C_REP3**. The second swap switch **S2** may transfer the other one of the data output from the ECC cell block **MBECC** and the data output from the ninth normal cell block **MB8** to the second switch group **154**, according to the third repair information **C_REP3**.

(66) For example, when the third repair information **C_REP3** is set to a low bit, the first swap switch **S1** may transfer the data output from the ECC cell block **MBECC** to the ECC code calculation circuit **HECC**, and the second swap switch **S2** may transfer the data output from the ninth normal cell block **MB8** to the second switch group **154**. Accordingly, when the third repair information **C_REP3** is a low bit, the third switch group **156** may transfer, without swapping, the data output from the ECC cell block **MBECC** and the data output from the ninth normal cell block **MB8** respectively to the ECC code calculation circuit **HECC** and the second switch group **154**. On the other hand, when the third repair information **C_REP3** is set to a high bit, the first swap switch **S1** may transfer the data output from the ninth normal cell block **MB8** to the ECC code calculation circuit **HECC**, and the second swap switch **S2** may transfer the data output from the ECC cell block **MBECC** to the second switch group **154**. Accordingly, when the third repair information **C_REP3** is a high bit, the third switch group **156** may swap the data output from the ECC cell block **MBECC** with the data output from the ninth normal cell block **MB8** and transfer the swapped data respectively to the ECC code calculation circuit **HECC** and the second switch group **154**.

(67) The second switch group **154** may perform a zero-padding operation according to the second repair control information **C_REP2**. During the read operation, the second switch group **154** may select the data **DO** to **D127** and **R0** to **R7** transferred through the third switch group **156**, or zero-data, according to the second repair control information **C_REP2**, and transfer the selected data to the error correction circuit **164**.

(68) In detail, the second switch group **154** may include a plurality of second switches (hereinafter, referred to as “first to 17-th zero-padding switches **Z0** to **Z16**”) respectively corresponding to the normal code calculation circuits **H0** to **H15** and the redundancy code calculation circuit **HRED**. The first to 17-th zero-padding switches **Z0** to **Z16** may receive the respective bits of the second

repair control information C_REP2 in the order of a lowest bit LSB to a highest bit MSB. Each of the first to 17-th zero-padding switches Z0 to Z16 may select data output from the corresponding cell block, or zero-data “0”, according to a corresponding bit of the 17-bit second repair information C_REP2, and transfer the selected data to a corresponding code calculation circuit. For example, the first to 17-th zero-padding switches Z0 to Z16 may perform a zero-padding operation by inputting the zero-data “0” to the corresponding code calculation circuit instead of the data output from the corresponding cell block when the corresponding bit is a high bit. For reference, in FIG. 8A, the first to 17-th zero-padding switches Z0 to Z16 are each shown as one multiplexer, but each switch may include a number of multiplexers corresponding to the number of bits (i.e., 8-bit) of data.

(69) The code calculation circuits H0 to H15, HECC, and HRED of the error correction circuit 164 may calculate a syndrome using a check matrix, and correct an error based on the syndrome and the error correction codes. In this case, the error correction circuit 164 may correct an error of 136-bit data on which the zero-padding operation has been performed using the 8-bit error correction codes P0 to P7. The code calculation circuits H0 to H15, HECC, and HRED may transfer the error-corrected data DO0 to DO127 to the first switch group 152.

(70) The first switch group 152 may selectively perform a shifting operation for column repair according to the first repair control information C_REP1. During the read operation, the first switch group 152 may transfer the data DO0 to DO127 from the code calculation circuits H0 to H15 and HRED to the data I/O circuit 170 by shifting the data DO0 to DO127 according to the first repair control information C_REP1.

(71) In detail, the first switch group 152 may include a plurality of first switches (hereinafter, referred to as “first to 16-th repair switches C0 to C15”) respectively corresponding to the normal code calculation circuits H0 to H15. The first to 16-th repair switches C0 to C15 may receive the respective bits of the first repair control information C_REP1 in the order of a lowest bit LSB to a highest bit MSB. Each of the first to 16-th repair switches C0 to C15 may select data output from a corresponding normal code calculation circuit or data output from an adjacent code calculation circuit according to a corresponding bit of the 16-bit first repair information C_REP1, and transfer the selected data to the data I/O circuit 170. For example, each of the first to 16-th repair switches C0 to C15 may perform a shifting operation for column repair by transferring the data output from the corresponding normal code calculation circuit when the corresponding bit is a low bit, and by transferring the data output from the adjacent code calculation circuit when the corresponding bit is a high bit. For reference, in FIG. 8A, the first to 16-th repair switches C0 to C15 are each illustrated as one multiplexer, but each switch may include multiplexers corresponding to the number of bits (i.e., 8-bit) of data.

(72) The data I/O circuit 170 may include first to eighth input/output parts 171 to 178 for inputting/outputting the 128-bit data DO0 to DO127 through the data pads DQ0 to DQ7. The first to eighth input/output parts 171 to 178 each correspond to two adjacent switches among the first to 16-th repair switches C0 to C15, and 8-bit data output from two adjacent switches may be alternately output to a data pad during the read operation.

(73) Referring to FIG. 8B, configurations for a write operation of the memory device 100 are illustrated. The error correction code generation circuit 162 of the error correction device 160 may include a plurality of normal code calculation circuits H0 to H15, at least one ECC code calculation circuit HECC, and at least one redundancy code calculation circuit HRED. The plurality of code calculation circuits may respectively correspond to the plurality of cell blocks.

(74) During the write operation, the first to eighth input/output parts 171 to 178 of the data I/O circuit 170 may respectively receive 8-bit data input through the data pads DQ0 to DQ7, and alternately transfer the data to the first switch group 152.

(75) The first switch group 152 may selectively perform a shifting operation for column repair according to the first repair control information C_REP1. During the write operation, the first

switch group **152** may transfer the data **DO0** to **DO127** to the second switch group **154** by shifting the data transferred from the first to eighth input/output parts **171** to **178** according to the first repair control information **C_REP1**.

(76) In detail, the first switch group **152** may include first to 16-th repair switches **C'0** to **C'15**. The first repair switch **C'0** may correspond to the first input/output part **171** and may selectively receive 8-bit data among 16-bit data input through the first input/output part **171** according to the LSB of the first repair information **C_REP1**. Two adjacent switches among the second to 15-th repair switches **C'1** to **C'14** may correspond to the second to eighth input/output parts **172** to **178**, respectively, and may alternately receive 8-bit data among 16-bit data input through the second to eighth input/output parts **172** to **178**. Each of the second to 15-th repair switches **C'1** to **C'14** may select data transferred from a corresponding input/output part or an adjacent input/output part according to a corresponding bit of the first repair information **C_REP1** and transfer the selected data to the second switch group **154**. The 16-th repair switch **C'15** may receive 8-bit data among 16-bit data input through the eighth input/output part **178** according to the MSB of the first repair information **C_REP1**. Since both input terminals of the 16-th repair switch **C'15** receive the same data, the 16-th repair switch **C'15** may transfer the 8-bit data to the second switch group **154** regardless of a logic level of the MSB of the first repair information **C_REP1**.

(77) The second switch group **154** may perform a zero-padding operation according to the second repair control information **C_REP2**. During the write operation, the second switch group **154** may select the data **DO0** to **DO127** transferred from the first switch group **152**, or zero-data, according to the second repair control information **C_REP2** and transfer the selected data to the error correction code generation circuit **162**.

(78) In detail, the second switch group **154** may include first to 17-th zero-padding switches **Z'0** to **Z'16** respectively corresponding to the normal code calculation circuits **H0** to **H15** and the redundancy code calculation circuit **HRED**. Each of the first to 17-th zero-padding switches **Z'0** to **Z'16** may select the data **DO0** to **DO127** transferred from the first switch group **152**, or zero-data "0", according to a corresponding bit of the 17-bit second repair information **C_REP2** and transfer the selected data to a corresponding code calculation circuit. For example, when the corresponding bit is a high bit, the first to 17-th zero-padding switches **Z'0** to **Z'16** may perform a zero-padding operation by inputting the zero-data "0" to the corresponding code calculation circuit, respectively. For reference, the first zero-padding switch **Z'0** may directly receive the data transferred from the first input/output part **171**, and the second to 17-th zero-padding switches **Z'0** to **Z'16** may respectively receive data transferred from the first to 16-th repair switches **C'0** to **C'15**. According to an embodiment, the 16-th repair switch **C'15** may be omitted, and 8-bit data input through the eighth input/output part **178** may be directly provided to the 17-th zero-padding switch **Z'16**.

(79) The code calculation circuits **H0** to **H15**, **HECC**, and **HRED** of the error correction code generation circuit **162** may generate the error correction codes **P0** to **P7** of 8-bit, based on the zero-padded data **DO0** to **DO127** and **R0** to **R7**, using a check matrix, during the write operation.

(80) During the write operation, the third switch group **156** may transfer the zero-padded data **DO** to **D127** and **R0** to **R7** and the error correction codes **P0** to **P7** output from the code calculation circuits **H0** to **H15**, **HECC**, and **HRED** to the memory cell area **110**, while performing a swap operation on the data input to the ECC cell block **MBECC** with the data input to the ninth normal cell block **MB8**, according to the third repair control information **C_REP3**.

(81) In detail the third switch group **156** may include a first swap switch **S'1** and a second swap switch **S'2**. The first swap switch **S'1** may transfer one of the data output from the ECC code calculation circuit **HECC** and the data output from the ninth normal code calculation circuit **H8**, to the ECC cell block **MBECC**, according to the third repair information **C_REP3**. The second swap switch **S'2** may transfer the other one of the data output from the ECC code calculation circuit **HECC** and the data output from the ninth normal code calculation circuit **H8** to the ninth normal cell block **MB8**, according to the third repair information **C_REP3**.

(82) For example, when the third repair information C_REP3 is set to a low bit, the first swap switch S'1 may transfer the data output from the ECC code calculation circuit HECC to the data output from the ECC cell block MBECC, and the second swap switch S'2 may transfer the data output from the ninth normal code calculation circuit H8 to the ninth normal cell block MB8. On the other hand, when the third repair information C_REP3 is set to a high bit, the first swap switch S'1 may transfer the data output from the ninth normal code calculation circuit H8 to the ECC cell block MBECC, and the second swap switch S'2 may transfer the data output from the ECC code calculation circuit HECC to the ninth normal cell block MB8.

(83) Hereinafter, an operation of a memory device of the present invention according to various embodiments will be described with reference to the drawings. For convenience of description, a write operation under a specific condition will be described first, and then a read operation accordingly will be described.

(84) FIGS. 9A and 9B illustrate a write operation and a read operation when there is no defect in a sub-word line driver and a column repair operation is not performed. As described in FIG. 6B, the information generation circuit 146 may generate the first repair information C_REP1 of all low bits, the second repair information C_REP2 in which only MSB is a high bit, and the third repair information C_REP3 of a low bit.

(85) Referring to FIG. 9A, the first to eighth input/output parts 171 to 178 may receive 8-bit data among 16-bit data BL07 and BL8F input through a corresponding data pad, respectively, and alternately transfer the received data to the first switch group 152.

(86) The first to 16-th repair switches C'0 to C'15 of the first switch group 152 may transfer the data from the first to eighth input/output parts 171 to 178 to the second switch group 154 without performing a shifting operation, according to the first repair information C_REP1 of all low bits. The second switch group 154 may perform a zero-padding operation according to the second repair control information C_REP2. According to the second repair information C_REP2 in which only MSB is a high bit, only the 17-th zero-padding switch Z'16 among the first to 17-th zero-padding switches Z'0 to Z'16 may select the zero-data "0" and transfer the selected data, i.e., the zero-data R0 to R7 to the redundancy code calculation circuit HRED.

(87) The code calculation circuits H0 to H15, HECC, and HRED of the error correction code generation circuit 162 may generate the 8-bit error correction codes P0 to P7 based on the data DO0 to DO127 and R0 to R7 on which the zero-padding operation has been performed. The third switch group 156 may transfer the data DO to D127 and R0 to R7 and the error correction codes P0 to P7, output from the code calculation circuits H0 to H15, HECC, and HRED to the memory cell area 110 according to the third repair control information C_REP3. According to the third repair information C_REP3 of a low bit, the first swap switch S'1 may transfer the data output from the ECC code calculation circuit HECC to the ECC cell block MBECC, and the second swap switch S'2 may transfer the data output from the ninth normal code calculation circuit H8 to the ninth normal cell MB8. Accordingly, the 128-bit data input through the data pads DQ0 to DQ7 and the error correction codes P0 to P7 generated based on the 128-bit data are respectively written to the first to 16-th normal cell blocks MB0 to MB15 and the ECC cell block MBECC. In this case, the redundancy cell block MBRED is not used "UNUSED".

(88) Referring to FIG. 9B, the third switch group 156 may transfer the data DO to D127 and R0 to R7, and the error correction codes P0 to P7 output from the memory cell area 110 to the second switch group 154 according to the third repair control information C_REP3. According to the third repair information C_REP3 of a low bit, the first swap switch S1 may transfer the data output from the ECC cell block MBECC to the ECC code calculation circuit HECC, and the second swap switch S2 may transfer the data output from the ninth normal cell block MB8 to the second switch group 154. The second switch group 154 may perform a zero-padding operation according to the second repair control information C_REP2. According to the second repair information C_REP2 in which only MSB is a high bit, the 17-th zero-padding switch Z17 may select the zero-data "0"

instead of the data output from the redundancy cell block MBRED, and transfer the selected data to the redundancy code calculation circuit HRED.

(89) The code calculation circuits **H0** to **H15**, HECC, and HRED may correct errors of the 136-bit data on which the zero-padding operation has been performed using the 8-bit error correction code **P0** to **P7**. The code calculation circuits **H0** to **H15**, HECC, and HRED may transfer the error-corrected data **DO0** to **DO127** to the first switch group **152**. According to the first repair information **C_REP1** of all low bits, the first to 16-th repair switches **C0** to **C15** may transfer the data output from the respective normal code calculation circuits **H0** to **H15** without performing a shifting operation. Accordingly, the error-corrected data **DO0** to **DO127** are read from the first to 16-th normal cell blocks **MB0** to **MB15** and the ECC cell block MBECC through the data pads **DQ0** to **DQ7**.

(90) Referring to FIG. 9C, during the read operation described in FIG. 9B, a defect occurs in the sub-word line driver between the fourth normal cell block **MB3** and the fifth normal cell block **MB4**. Due to the defect in the sub-word line driver between the fourth normal cell block **MB3** and the fifth normal cell block **MB4**, errors may occur in the third to sixth normal cell blocks **MB2** to **MB5**.

(91) The error correction circuit **164** fails to correct the errors due to the defect in the sub-word line driver, and the first to 16-th repair switches **C0** to **C15** of the first switch group **152** may output the 128-bit data through the data pads **DQ0** to **DQ7** without performing a shifting operation. In this case, the errors due to the defect may exist in the data output through the second data pad **DQ1** and the third data pad **DQ2**. When the controller's error correction ability set in the specification may cover errors of continuous 32-bit data, the errors in the data may be corrected by error correction of the controller. That is, when the shifting operation is not performed, a miscorrection of the error correction circuit **164** due to the errors occurring in the defective sub-word line driver "SWD Fault" may occur within a set range.

(92) FIGS. 10A and 10B illustrate a write operation and a read operation when a defect occurs in a sub-word line driver between the ninth normal cell block **MB8** and the tenth normal cell block **MB9**, and the first normal cell block **MB0** is repaired according to an embodiment of the present invention. As described in FIG. 6B, the information generation circuit **146** may generate the first repair information **C_REP1** of all high bits, the second repair information **C_REP2** in which only LSB is a high bit, and the third repair information **C_REP3** of a high bit.

(93) Referring to FIG. 10A, the first to 16-th repair switches **C'0** to **C'15** of the first switch group **152** may transfer the data from the first to eighth input/output parts **171** to **178** to the second switch group **154** by performing a shifting operation, according to the first repair information **C_REP1** of all high bits. According to the second repair information **C_REP2** in which only LSB is a high bit, only the first zero-padding switch **Z'0** may select the zero-data "0" and transfer the selected zero-data "0" to the first normal code calculation circuit **H0**.

(94) The code calculation circuits **H0** to **H15**, HECC, and HRED of the error correction code generation circuit **162** may generate the 8-bit error correction codes **P0** to **P7** based on the data **DO0** to **DO127** on which the zero-padding operation has been performed. According to the third repair information **C_REP3** of a high bit, the first swap switch **S'1** may transfer the data output from the ECC code calculation circuit HECC to the ninth normal cell **MB8**, and the second swap switch **S'2** may transfer the data output from the ninth normal code calculation circuit **H8** to the ECC cell block MBECC.

(95) Accordingly, the 8-bit zero-data is written to the first normal cell block **MB0** and the 128-bit data input through the data pads **DQ0** to **DQ7** and the error correction codes **P0** to **P7** generated based on the zero-padded 136-bit data are respectively written to the second to 16-th normal cell blocks **MB1** to **MB15**, the ECC cell block MBECC and the redundancy cell block MBRED. In this case, the error correction codes **P0** to **P7** may be written to the ninth normal cell block **MB8**, not the ECC cell block MBECC.

(96) Referring to FIG. 10B, according to the third repair information C_REP3 of a high bit, the third switch group 156 may swap the data output from the ECC cell block MBECC with the data output from the ninth normal cell block MB8, and transfer the swapped data to the second switch group 154. According to the second repair information C_REP2 in which only LSB is a high bit, the first zero-padding switch Z0 may select the zero-data "0" instead of the data output from the first normal cell block MB0 and transfer the selected zero-data "0" to the first normal code calculation circuit H0. The code calculation circuits H0 to H15, HECC, and HRED may correct errors of 136-bit data on which the zero-padding operation has been performed using the 8-bit error correction codes P0 to P7. The code calculation circuits H0 to H15, HECC, and HRED may transfer the error-corrected data DO0 to DO127 to the first switch group 152. According to the first repair information C_REP1 of all high bits, the first to 16-th repair switches C0 to C15 may shift and transfer the data output from the code calculation circuits. Accordingly, the first normal cell block MB0 may be repaired.

(97) In this case, due to the defect in the sub-word line driver between the ninth normal cell block MB8 and the tenth normal cell block MB9, the errors may occur in the ninth to eleventh normal cell blocks MB8 to MB10. Since the errors due to the defect exist in the data output through the fifth data pad DQ4, the errors in the data may be corrected by error correction of the controller.

(98) Meanwhile, depending on the specifications of a memory device or memory system, a controller may not be able to correct errors if the errors occur in both of data transferred through a lower data pad group DQ0 to DQ3 and data transferred through an upper data pad group DQ4 to DQ7. For example, in FIG. 10B, when the third switch group 156 is omitted, the errors may exist not only in the data output through the fifth data pad DQ4 but also in the data output through the fourth data pad DQ3. Therefore, in an embodiment of the invention, the third switch group 156 may swap the data of the ECC cell block MBECC with the data of the ninth normal cell block MB8 so that the errors occur only in the data transferred through one of the upper and lower data pad groups.

(99) FIGS. 11A and 11B illustrate a write operation and a read operation when a defect occurs in a sub-word line driver between the fourth normal cell block MB3 and the fifth normal cell block MB4, and the ECC cell block MBECC is repaired according to an embodiment of the present invention. As described in FIG. 6B, the information generation circuit 146 may generate the first repair information C_REP1 in which only the upper 8 bits are all high bits, the second repair information C_REP2 in which only a ninth bit is a high bit, and the third repair information C_REP3 of a high bit.

(100) Referring to FIG. 11A, the ninth to 16-th repair switches C'8 to C'15 of the first switch group 152 may transfer the data to the second switch group 154 by performing a shifting operation, according to the first repair information C_REP1 in which only the upper 8 bits are all high bits. According to the second repair information C_REP2 in which only a ninth bit is a high bit, only the ninth zero-padding switch Z'8 may select the zero-data "0" and transfer the selected zero-data "0" to the ninth normal code calculation circuit H8. The code calculation circuits H0 to H15, HECC, and HRED of the error correction code generation circuit 162 may generate the 8-bit error correction codes P0 to P7 based on the data DO0 to DO127 on which the zero-padding operation has been performed. According to the third repair information C_REP3 of a high bit, the first swap switch S'1 may transfer the data output from the ECC code calculation circuit HECC to the ninth normal cell MB8, and the second swap switch S'2 may transfer the data output from the ninth normal code calculation circuit H8 to the ECC cell block MBECC.

(101) Accordingly, the 8-bit zero-data is written to the ECC cell block MBECC and the 128-bit data input through the data pads DQ0 to DQ7 and the error correction codes P0 to P7 generated based on the 136-bit zero-padded data are respectively written to the first to 16-th normal cell blocks MB0 to MB15, and the redundancy cell block MBRED. In this case, the error correction codes P0 to P7 may be written to the ninth normal cell block MB8, not the ECC cell block

MBECC.

(102) Referring to FIG. 11B, according to the third repair information C_REP3 of a high bit, the third switch group 156 may swap the data output from the ECC cell block MBECC with the data output from the ninth normal cell block MB8, and transfer the swapped data to the second switch group 154. According to the second repair information C_REP2 in which only a ninth bit is a high bit, the ninth zero-padding switch Z8 may select the zero-data "0" instead of the data output from the ECC cell block MBECC, and transfer the selected zero-data "0" to the ninth normal code calculation circuit H8. The code calculation circuits H0 to H15, HECC, and HRED may correct errors of 136-bit data on which the zero-padding operation has been performed using the 8-bit error correction codes P0 to P7. The code calculation circuits H0 to H15, HECC, and HRED may transfer the error-corrected data DO0 to DO127 to the first switch group 152. According to the first repair information C_REP1 in which only the upper 8 bits are all high bits, the ninth to 16-th repair switches C8 to C15 may shift and transfer the data output from the code calculation circuits.

(103) Accordingly, the ECC cell block MBECC may be repaired. Since the errors due to the defect in the sub-word line driver may exist in the data output through the second data pad DQ1 and the third data pad DQ2, the errors in the data may be corrected by error correction of the controller.

(104) FIGS. 12A and 12B illustrate a write operation and a read operation when a defect occurs in a sub-word line driver between the fourth normal cell block MB3 and the fifth normal cell block MB4, and the 16-th cell block MB15 is repaired according to an embodiment of the present invention. As described in FIG. 6B, the information generation circuit 146 may generate the first repair information C_REP1 in which only MSB is a high bit, the second repair information C_REP2 in which only a 16-th bit is a high bit, and the third repair information C_REP3 of a low bit.

(105) Referring to FIG. 12A, only the 16-th repair switch C'15 of the first switch group 152 may transfer the data to the second switch group 154 by performing a shifting operation, according to the first repair information C_REP1 in which only MSB is a high bit. According to the second repair information C_REP2 in which only a 16-th bit is a high bit, only the 16-th zero-padding switch Z'15 may select the zero-data "0" and transfer the selected zero-data "0" to the 16-th normal code calculation circuit H15. The code calculation circuits H0 to H15, HECC, and HRED of the error correction code generation circuit 162 may generate the 8-bit error correction codes P0 to P7 based on the data DO0 to DO127 on which the zero-padding operation has been performed. According to the third repair information C_REP3 of a low bit, the first swap switch S'1 may transfer the data output from the ECC code calculation circuit HECC to the ECC cell block MBECC, and the second swap switch S'2 may transfer the data output from the ninth normal code calculation circuit H8 to the ninth normal cell MB8.

(106) Accordingly, the 8-bit zero-data is written to the 16-th normal cell block MB15 and the 128-bit data input through the data pads DQ0 to DQ7 and the error correction codes P0 to P7 generated based on the zero-padded 136-bit data are respectively written to the first to 15-th normal cell blocks MB0 to MB14, the ECC cell block MBECC, and the redundancy cell block MBRED.

(107) Referring to FIG. 12B, according to the third repair information C_REP3 of a low bit, the third switch group 156 may transfer the data output from the ECC cell block MBECC and the data output from the ninth normal cell block MB8, to the second switch group 154, without performing a swapping operation. According to the second repair information C_REP2 in which only a 16-th bit is a high bit, the 16-th zero-padding switch Z15 may select the zero-data "0" instead of the data output from the 16-th normal cell block MB15 and transfer the selected zero-data "0" to the 16-th normal code calculation circuit H15. The code calculation circuits H0 to H15, HECC, and HRED may correct errors of 136-bit data on which the zero-padding operation has been performed using the 8-bit error correction codes P0 to P7. The code calculation circuits H0 to H15, HECC, and HRED may transfer the error-corrected data DO0 to DO127 to the first switch group 152.

According to the first repair information C_REP1 in which only MSB is a high bit, the 16-th repair

switch **C15** may shift and transfer the data output from the redundancy code calculation circuit **HRED**.

(108) Accordingly, the 16-th normal cell block **MB15** may be repaired. Since the errors due to the defect in the sub-word line driver may exist in the data output through the second data pad **DQ1** and the third data pad **DQ2**, the errors in the data may be corrected by error correction of the controller.

(109) As described above, the memory device **100** according to the embodiment of the invention may place the first switch group **152** between the error correction device **160** and the data pads **DQ0** to **DQ7**, and may place the second switch group **154** in the input path of the error correction device **160**. The memory device **100** may perform a zero-padding-based error correction operation using the second switch group **154** and then perform a shifting operation for column repair using the first switch group **152**. Accordingly, during the shifting operation for column repair, the miscorrection of the error correction device due to the defective sub-word line driver may be suppressed within the set specification range (or boundary), i.e., within the error correction capability of the controller. In addition, the memory device **100** may additionally place the third switch group **156** for swapping data input/output from the normal cell block **MB8** adjacent to the ECC cell block **MBECC** and manage errors only in data transferred through either the lower data pad group **DQ0** to **DQ3** or the upper data pad group **DQ4** to **DQ7**. Accordingly, the error correction capability according to the specification of the memory device or the memory system may be maximized.

(110) Meanwhile, the memory device **100** according to the above embodiment may control the errors to exist only in the data transferred through one of the lower data pad groups **DQ0** to **DQ3** and the upper data pad groups **DQ4** to **DQ7** by using the first and second swap switches **S1**, **S'1**, **S2** and **S'2**. In the following embodiment, a configuration of the memory device **100** will be described when the controller may correct errors even if the errors exist in the data transferred through both of the lower data pad groups **DQ0** to **DQ3** and the upper data pad groups **DQ4** to **DQ7**.

(111) FIGS. **13A** to **13C** are diagrams illustrating a modified example of the memory device **100** of FIGS. **8A** and **8B** according to an embodiment of the present invention.

(112) Referring to FIG. **13A**, configurations for a read operation of the memory device **100** are illustrated. Except for the configuration of the third switch group **156**, the configurations shown in FIG. **13A** are substantially the same as those shown in FIG. **8A**.

(113) During the read operation, the third switch group **156** may transfer the data **DO** to **D127** and **R0** to **R7** and the error correction codes **P0** to **P7** output from the memory cell area **110** to the second switch group **154**, while performing a swap operation on the data output from the ECC cell block **MBECC** with the data output from the ninth normal cell block **MB8**, according to the third repair control information **C_REP3**. In detail the third switch group **156** may include a first swap switch **S1**. The first swap switch **S1** may transfer one of the data output from the ECC cell block **MBECC** and the data output from the ninth normal cell block **MB8** to the ECC code calculation circuit **HECC**, according to the third repair information **C_REP3**. The first swap switch **S1** of FIG. **13A** may perform substantially the same configuration and operation as the first swap switch **S1** of FIG. **8A**.

(114) Referring to FIG. **13B**, configurations for a write operation of the memory device **100** are illustrated. Except for the configuration of the third switch group **156**, the configurations shown in FIG. **13B** are substantially the same as those shown in FIG. **8B**.

(115) During the write operation, the third switch group **156** may transfer the zero-padded data **DO** to **D127** and **R0** to **R7** and the error correction codes **P0** to **P7** output from the code calculation circuits **H0** to **H15**, **HECC**, and **HRED** to the memory cell area **110**, while performing a swap operation on the data output from the ECC code calculation circuit **HECC** with the data output from the ninth code calculation circuit **H8**, according to the third repair control information **C_REP3**. In detail the third switch group **156** may include a second swap switch **S'2**. The second

swap switch **S'2** may transfer the other one of the data output from the ECC code calculation circuit **HECC** and the data output from the ninth normal code calculation circuit **H8** to the ninth normal cell block **MB8**, according to the third repair information **C_REP3**. The second swap switch **S'2** of FIG. **13B** may perform substantially the same configuration and operation as the first swap switch **S'2** of FIG. **8B**.

(116) Referring to FIG. **13C**, the first to third repair control information **C_REP1** to **C_REP3** of FIGS. **13A** and **13B** generated by the repair control circuit **140** is shown. Except for the third repair control information **C_REP3** of FIG. **13C**, the first and second repair control information **C_REP1** and **C_REP2** are substantially the same as those of FIG. **6B**.

(117) In the embodiment, the third signal generation circuit **146_3** of the information generation circuit **146** may output the ninth match signal **HIT8** as the third repair information **C_REP3**. For example, as illustrated in FIG. **13C**, the third signal generation circuit **146_3** may generate the third repair information **C_REP3** of a high bit when the ninth match signal **HIT8** is activated due to repair in the ECC cell block **MBCC**. The third signal generation circuit **146_3** may generate the third repair information **C_REP3** of a low bit when no repair occurs or when the ninth match signal **HIT8** is deactivated due to repair in one of the first to 16-th normal cell blocks **MB0** to **MB15**.

(118) With the above configuration, if the repair occurs in the ECC cell block **MBCC**, the third repair information **C_REP3** of a high bit may be generated. During the write operation, the second swap switch **S'2** may transfer the data output from the ECC code calculation circuit **HECC** to the ninth normal cell block **MB8** according to the third repair information **C_REP3** of a high bit. At this time, the data output from the ECC code calculation circuit **HECC** is also transferred to the ECC cell block **MBECC**, but is not used because the ECC cell block **MBCC** has been repaired. During the read operation, the first swap switch **S1** may transfer the data output from the ninth normal cell block **MB8** to the ECC code calculation circuit **HECC**.

(119) Meanwhile, in the following embodiment, a method of merging the second switch group **154** performing a zero-padding operation into the error correction device **160** is proposed.

(120) FIGS. **14A** and **14B** are diagrams illustrating the memory device **100** of FIG. **3** in more detail according to another embodiment of the present invention.

(121) Referring to FIG. **14A**, configurations for a read operation of the memory device **100** are illustrated. The configurations shown in FIG. **14A** are substantially the same as those shown in FIG. **8A**, except that the second switch group **154** is omitted and the error correction circuit **164** of the error correction device **160** may receive the second repair information **C_REP2** to perform a zero-padding operation.

(122) Referring to FIG. **14B**, configurations for a write operation of the memory device **100** are illustrated. Similarly, the configurations shown in FIG. **14B** are substantially the same as those shown in FIG. **8B**, except that the second switch group **154** is omitted and the error correction code generation circuit **162** of the error correction device **160** may receive the second repair information **C_REP2** to perform a zero-padding operation.

(123) FIG. **15** is a detailed configuration diagram illustrating the error correction device **160** of FIGS. **14A** and **14B** according to an embodiment of the present invention.

(124) Referring to FIG. **15**, the error correction circuit **164** of the error correction device **160** is shown.

(125) The error correction circuit **164** may include a plurality of code calculation circuits, a syndrome generator **210**, and an error corrector **230**.

(126) For example, the plurality of code calculation circuits may be divided into a plurality of normal code calculation circuits **H0** to **H15**, at least one ECC code calculation circuit **HECC**, and at least one redundancy code calculation circuit **HRED**. The ECC code calculation circuit **HECC** may be included in the syndrome generator **210** in a configuration in which error correction codes **P0** to **P7** are input. However, the present invention is not limited thereto, and the ECC code operation circuit **HECC** may be implemented in a separate configuration from the syndrome generator **210**.

According to an embodiment, the error correction code generation circuit **162** (see FIG. 7) may include the plurality of code calculation circuits **H0** to **H15**, **HECC**, and **HRED** shown in FIG. 15. The code calculation circuits **H0** to **H15**, **HECC**, and **HRED** of the error correction circuit **164** and the code calculation circuits **H0** to **H15**, **HECC**, and **HRED** of the error correction code generation circuit **162** may be merged into one configuration and implemented.

(127) Each of the normal code calculation circuits **H0** to **H15** and the redundancy code calculation circuit **HRED** may generate partial preliminary error correction codes E^* based on the corresponding 8-bit data among the data **DO** to **D127** and **R0** to **R7** output from the memory cell area **110**. In an embodiment of the present invention, the first to eighth normal code calculation circuits **H0** to **H7**, the ECC code calculation circuit **HECC**, the ninth to 16-th normal code calculation circuits **H8** to **H15**, and the redundancy code calculation circuit **HRED** may receive respective bits of the second repair information **C_REP2** in the order of a lowest bit **LSB** to a highest bit **MSB**. Each of the code calculation circuits **H0** to **H15**, **HECC**, and **HRED** may perform a zero-padding operation on its calculation result according to a corresponding bit of the second repair control information **C_REP2**.

(128) The syndrome generator **210** may generate preliminary error correction codes by combining the partial preliminary error correction codes E^* provided from the normal code calculation circuits **H0** to **H15** and the redundancy code calculation circuit **HRED**, and generate syndrome data **SD** corresponding to information encoding an error location by comparing the preliminary error correction codes with the error correction codes **P0** to **P7** by bits.

(129) The error corrector **230** may be activated according to the read command **RD** to detect error positions of the data **DO** to **D127** and **R0** to **R7** based on the syndrome data **SD**. In this case, 8-bit data among 136-bit data **DO** to **D127** and **R0** to **R7** are zero-padded data and are substantially invalid. The error corrector **230** may decode the syndrome data **SD** to generate information indicating the error location information of the data **DO** to **D127** and **R0** to **R7**, and may correct the errors of the data **DO** to **D127** and **R0** to **R7** based on the information to output the error-corrected data **DO0** to **DO127**.

(130) FIG. 16 is a circuit diagram for describing any one code calculation circuit of FIG. 15 according to an embodiment of the present invention. Since the code operation circuits **H0** to **H15** and **HRED** have substantially the same configuration, the first normal code operation circuit **H0** will be described as an example.

(131) Referring to FIG. 16, the first normal code calculation circuit **H0** may include a preliminary code calculation unit **310** and a zero-padding switch **320**.

(132) The preliminary code operator **310** may generate preliminary codes **PRE1** to **PRE4** by comparing some bits of the data **DO** to **D7**. The preliminary code operator **310** may include first to tenth XOR gates **XR1** to **XR10**. The first to sixth XOR gates **XR1** to **XR6** may perform a logic XOR operation on two bits among the data **DO** to **D7** to output comparison codes **X01**, **X23**, **X17**, **X35**, **X45**, and **X67**. The seventh to tenth XOR gates **XR7** to **XR10** may perform a logic XOR operation on two codes among the comparison codes **X01**, **X23**, **X17**, **X35**, **X45**, and **X67** to output the preliminary codes **PRE1** to **PRE4**.

(133) The zero-padding switch **320** may include first to fourth multiplexers **M1** to **M4** that perform a zero-padding operation according to the second repair control information **C_REP2**. Each of the first to fourth multiplexers **M1** to **M4** may output some of the partial preliminary error correction codes E^* by selecting one of a corresponding preliminary bit of the preliminary codes **PRE1** to **PRE4**, and a low bit, according to the **LSB** **C_REP2<0>** of the second repair control information **C_REP2**.

(134) For reference, in FIG. 16, the first to fourth multiplexers **M1** to **M4** may correspond to one of the second switch group **154** of FIG. 8A. The zero-padding switches **Z0** to **Z16** of FIG. 8A require eight multiplexers corresponding to the number of bits of data, respectively. However, according to the present embodiment, by performing a zero-padding operation after calculating parity bits, the

zero-padding switch 320 may perform the zero-padding operation with only four multiplexers. Accordingly, in the present embodiment, the error correction capability may be improved while minimizing an increase in the area due to the zero-padding switches.

(135) Various embodiments of the present disclosure have been described in the drawings and specification. Although specific terminologies are used here, the terminologies are only to describe the embodiments of the present disclosure. Therefore, the present disclosure is not restricted to the above-described embodiments and many variations are possible within the spirit and scope of the present disclosure. It should be apparent to those skilled in the art that various modifications can be made on the basis of the technological scope of the present disclosure in addition to the embodiments disclosed herein. The embodiments may be combined to form additional embodiments.

(136) It should be noted that although the technical spirit of this disclosure has been described in connection with embodiments thereof, this is merely for description purposes and should not be interpreted as limiting. It should be appreciated by one of ordinary skill in the art that various changes may be made thereto without departing from the technical spirit of the disclosure and the following claims.

(137) For example, for the logic gates and transistors provided as examples in the above-described embodiments, different positions and types may be implemented depending on the polarity of the input signal.

Claims

1. A memory device comprising: a memory cell area including a plurality of cell blocks divided into a plurality of normal cell blocks, at least one error correction code (ECC) cell block, and at least one redundancy cell block, the plurality of cell blocks being configured to output data and error correction codes; an error correction circuit configured to generate error-corrected data by correcting errors in the data using the error correction codes; a first switch group disposed between the error correction circuit and data pads, configured to output the error-corrected data through the data pads while performing, according to first repair control information, a shifting operation on the error-corrected data; and a second switch group disposed between the memory cell area and the error correction circuit, configured to transfer the data from the memory cell area to the error correction circuit while performing, according to second repair control information, a zero-padding operation on the data output from one of the cell blocks.
2. The memory device of claim 1, wherein the zero-padding operation is performed prior to the shifting operation on the error-corrected data.
3. The memory device of claim 1, wherein the error correction circuit includes a plurality of code calculation circuits divided into a plurality of normal code calculation circuits, at least one ECC code calculation circuit and at least one redundancy code calculation circuit.
4. The memory device of claim 3, wherein the first switch group includes a plurality of first switches respectively corresponding to the normal code calculation circuits, and wherein each of the first switches is configured to select, according to a corresponding bit within the first repair control information, the data output from a corresponding normal code calculation circuit or the data output from an adjacent code calculation circuit to output the selected data.
5. The memory device of claim 1, wherein the second switch group includes a plurality of second switches respectively corresponding to the normal cell blocks and the redundancy cell block, and wherein each of the second switches is configured to select, according to a corresponding bit within the second repair control information, the data output from a corresponding one of the normal cell blocks or zero-data to transfer the selected data.
6. The memory device of claim 1, further comprising a third switch group configured to perform, according to third repair control information, a swap operation on the data output from the ECC

cell block with the data output from one of the normal cell blocks, which is adjacent to the ECC cell block.

7. The memory device of claim 6, wherein the third switch group includes a first swap switch configured to transfer, to the error correction circuit according to the third repair control information, one of the data output from the ECC cell block and the data output from the adjacent normal cell block.

8. The memory device of claim 7, wherein the third switch group further includes a second swap switch configured to transfer, to the second switch group according to the third repair control information, the other one of the data output from the ECC cell block and the data output from the adjacent normal cell block.

9. The memory device of claim 1, further comprising a repair control circuit configured to store defective addresses as repair information and configured to provide, based on the stored repair information, the first and second repair control information corresponding to an input address.

10. The memory device of claim 9, wherein the repair control circuit includes: a plurality of address storage circuits respectively corresponding to the normal cell blocks and the ECC cell block and configured to store the defective addresses of the respective blocks and configured to generate a plurality of match signals by comparing the input address with the stored defective addresses; a shifting control circuit configured to generate a plurality of shifting signals respectively corresponding to the match signals, each shifting signal being activated according to a corresponding match signal or a shifting signal of a previous stage; and an information generation circuit configured to generate the first and second repair control information according to the match signals and the shifting signals.

11. The memory device of claim 1, wherein the normal cell blocks are configured by first to 2m-th normal cell blocks, and wherein the first to m-th normal cell blocks, the ECC cell block, the (m+1)-th to 2m-th normal cell blocks, and the redundancy cell block may be sequentially disposed in a row direction.

12. A memory device comprising: a memory cell area including a plurality of cell blocks divided into a plurality of normal cell blocks, at least one error correction code (ECC) cell block, and at least one redundancy cell block, the plurality of cell blocks being configured to output data and error correction codes; an error correction circuit including a plurality of code calculation circuits corresponding to the cell blocks and configured to generate error-corrected data by correcting errors in the data using the error correction codes while performing, according to second repair control information, a zero-padding operation on a result of calculating on a part of the data by any one of the code calculation circuits; and a first switch group disposed between the error correction circuit and data pads, configured to output the error-corrected data through the data pads while performing, according to first repair control information, a shifting operation on the error-corrected data.

13. The memory device of claim 12, wherein the zero-padding operation is performed prior to the shifting operation on the error-corrected data.

14. The memory device of claim 12, wherein the error correction circuit includes: the plurality of code calculation circuits configured to generate partial preliminary error correction codes based on the data while performing the zero-padding operation according to the second repair control information; a syndrome generator configured to generate preliminary error correction codes by combining the partial preliminary error correction codes and configured to generate syndrome data by comparing the preliminary error correction codes with the error correction codes; and an error corrector configured to generate the error-corrected data by correcting, based on the syndrome data, the errors in the data.

15. The memory device of claim 14, wherein each of the code calculation circuits includes: a preliminary code operator configured to generate preliminary codes by comparing corresponding bits within the data; and a plurality of zero-padding switches configured to output the partial

preliminary error correction codes by selecting, according to a corresponding bit within the second repair control information, one of the preliminary codes and zero data.

16. The memory device of claim 12, wherein the code calculation circuits are divided into a plurality of normal code calculation circuits, at least one ECC code calculation circuit and at least one redundancy code calculation circuit.

17. The memory device of claim 16, wherein the first switch group includes a plurality of first switches respectively corresponding to the normal code calculation circuits, and wherein each of the first switches is configured to select, according to a corresponding bit within the first repair control information, the data output from a corresponding normal code calculation circuit or the data output from an adjacent code calculation circuit to output the selected data.

18. The memory device of claim 12, further comprising a third switch group configured to perform, according to third repair control information, a swap operation on the data output from the ECC cell block with the data output from one of the normal cell blocks, which is adjacent to the ECC cell block.

19. The memory device of claim 18, wherein the third switch group includes: a first swap switch configured to transfer, to the error correction circuit according to the third repair control information, one of the data output from the ECC cell block and the data output from the adjacent normal cell block.

20. The memory device of claim 19, wherein the third switch group further includes a second swap switch configured to transfer, to the error correction circuit according to the third repair control information, the other one of the data output from the ECC cell block and the data output from the adjacent normal cell block.

21. The memory device of claim 12, further comprising a repair control circuit configured to store defective addresses as repair information and configured to provide, based on the stored repair information, the first and second repair control information corresponding to an input address.

22. The memory device of claim 21, wherein the repair control circuit includes: a plurality of address storage circuits respectively corresponding to the normal cell blocks and the ECC cell block and configured to store the defective addresses of the respective blocks and configured to generate a plurality of match signals by comparing the input address with the stored defective addresses; a shifting control circuit configured to generate a plurality of shifting signals respectively corresponding to the match signals, each shifting signal being activated according to a corresponding match signal or a shifting signal of a previous stage; and an information generation circuit configured to generate the first and second repair control information according to the match signals and the shifting signals.

23. A memory device comprising: a shifting circuit configured to receive user data pieces through data pads from an external device to shift the user data pieces; a zero-padding circuit configured to generate a zero-padded data piece; an error-correcting circuit configured to generate an error correction code (ECC) data piece for the zero-padded data piece and the shifted user data pieces; a swapping circuit configured to swap, with each other, the ECC data piece and the shifted user data piece to be stored in neighboring two among memory blocks; and the memory blocks arranged in a row and configured to store therein the zero-padded data piece, the shifted user data pieces and the ECC data piece, the memory blocks including a column-repaired memory block that the zero-padded data piece is to be stored in and a redundancy memory block that one of the shifted user data pieces corresponding to the column-repaired memory block is to be stored in, wherein the shifting circuit is disposed between the error-correcting circuit and data pads, and the zero-padding circuit is disposed between the memory blocks and the error-correcting circuit.

24. The memory device of claim 23, wherein the swapping circuit is further configured to swap, with each other, the ECC data piece and the user data piece from the neighboring memory blocks, wherein the zero-padding circuit is further configured to generate a zero-padded data piece for the zero-padded data piece from the column-repaired memory block, wherein the error-correcting

circuit is further configured to error-correct, based on the ECC data piece from the swapping circuit, the zero-padded data piece from the zero-padding circuit and the user data pieces from the memory blocks and the swapping circuit, and wherein the shifting circuit is further configured to output the error-corrected user data pieces by shifting the error-corrected user data pieces from the error-correcting circuit.
