

US Patent & Trademark Office

Patent Public Search | Text View

United States Patent	12400956
Kind Code	B2
Date of Patent	August 26, 2025
Inventor(s)	Smith; Michael A. et al.

Reduced pitch memory subsystem for memory device

Abstract

A memory device includes an array of memory cells and a plurality of bit-lines with each bit-line connected to a respective set of memory cells of the array of memory cells. The memory device includes a memory subsystem having first and second memory circuits. Each first memory circuit can be disposed laterally adjacent to a second memory circuit. Each first memory circuit includes a first bit-line connection and each second memory circuit including a second bit-line connection, the first and second bit-line connections can connect to respective bit-lines. Each first bit-line connection is disposed on a first bit-line connection line of the memory subsystem and each second bit-line connection is disposed on a second bit-line connection line of the memory subsystem, and the second bit-line connection line can be offset from the first bit-line connection line by a predetermined distance that is greater than zero.

Inventors: Smith; Michael A. (Boise, ID), Liu; Haitao (Boise, ID), Mikhalev; Vladimir (Boise, ID)

Applicant: Micron Technology, Inc. (Boise, ID)

Family ID: 1000008778352

Assignee: Micron Technology, Inc. (Boise, ID)

Appl. No.: 18/610267

Filed: March 20, 2024

Prior Publication Data

Document Identifier	Publication Date
US 20240234311 A1	Jul. 11, 2024

Related U.S. Application Data

continuation parent-doc US 18083445 20221216 US 11973031 child-doc US 18610267

Publication Classification

Int. Cl.: **H01L23/528** (20060101); **H10B10/00** (20230101); **H10D30/01** (20250101); **H10D30/60** (20250101); **H10D30/63** (20250101); **H10D84/01** (20250101); **H10D84/03** (20250101); **H10D84/85** (20250101)

U.S. Cl.:

CPC **H01L23/528** (20130101); **H10B10/12** (20230201); **H10D30/025** (20250101); **H10D30/60** (20250101); **H10D30/63** (20250101); **H10D84/0195** (20250101); **H10D84/038** (20250101); **H10D84/85** (20250101);

Field of Classification Search

CPC: H01L (29/78); H01L (29/7827); H01L (29/66666); H01L (29/4232); H01L (27/092); H01L (27/1104); H01L (29/42372); H01L (29/4238); H01L (29/42376); H01L (21/823885); H01L (21/823828); H01L (23/528); H10B (10/12); H10D (30/025); H10D (30/60); H10D (30/63); H10D (84/0195); H10D (84/038); H10D (84/01); H10D (84/85); H10D (84/8311); H10D (84/8312); H10D (84/83135); H10D (84/83138); H10D (84/8314); H10D (84/8316); H10D (84/851); H10D (84/852)

References Cited

U.S. PATENT DOCUMENTS

Patent No.	Issued Date	Patentee Name	U.S. Cl.	CPC
5239196	12/1992	Ikeda	257/385	H10B 10/12
6229186	12/2000	Ishida	N/A	N/A
8692317	12/2013	Takeuchi	N/A	N/A
8766365	12/2013	Smith	257/500	H01L 27/0266
9251888	12/2015	Liaw	N/A	N/A
10163893	12/2017	Smith	N/A	N/A
10679982	12/2019	Smith	N/A	G11C 16/16
10741582	12/2019	Herner	N/A	H01L 29/0847
11152383	12/2020	Chen	N/A	H10B 41/35
11557537	12/2022	Smith et al.	N/A	N/A
11973031	12/2023	Smith	N/A	H01L 29/7827
2010/0219483	12/2009	Masuoka	257/369	H01L 27/1203
2011/0075470	12/2010	Liaw	365/189.05	H10B 10/00
2015/0236033	12/2014	Watanabe	N/A	N/A
2016/0071842	12/2015	Smith et al.	N/A	N/A
2018/0069016	12/2017	Barbato	N/A	N/A
2018/0122793	12/2017	Moroz et al.	N/A	N/A
2018/0175052	12/2017	Sim et al.	N/A	N/A
2018/0308853	12/2017	Bell et al.	N/A	N/A
2019/0067271	12/2018	Smith	N/A	N/A
2019/0096894	12/2018	Bell	N/A	H01L 21/76202
2022/0044994	12/2021	Smith et al.	N/A	N/A

OTHER PUBLICATIONS

International Application No. PCT/US2021/043093—International Search Report and Written Opinion, dated Nov. 18, 2021, 8 pages. cited by applicant

Primary Examiner: Trinh; Michael M

Attorney, Agent or Firm: Dorsey & Whitney LLP

Background/Summary

CROSS-REFERENCE TO RELATED APPLICATIONS (1) This application is a continuation of U.S. patent application Ser. No. 18/083,445, filed Dec. 16, 2022, now U.S. Pat. No. 11,973,031; which is a division of U.S. patent application Ser. No. 16/986,776, filed Aug. 6, 2020, now U.S. Pat. No. 11,557,537; each of which is incorporated herein by reference in its entirety.

TECHNICAL FIELD

(1) The present disclosure relates generally to memory devices, and, in particular, the present disclosure relates to reduced pitch memory subsystems for memory devices.

BACKGROUND

(2) Memory devices are typically provided as internal, semiconductor, integrated circuits in computers or other electronic devices. There are many different types of memory including random-access memory (RAM), read only memory (ROM), dynamic random access memory (DRAM), synchronous dynamic random access memory (SDRAM), static random access memory (SRAM), and flash memory. As memory devices advance, it is desirable to make memory devices, including memory subsystems, as small and/or as dense as possible.

(3) For the reasons stated above, and for other reasons stated below which will become apparent to those skilled in the art upon reading and understanding the present specification, there is a need in the art for memory subsystems that allow for smaller pitches.

Description

BRIEF DESCRIPTION OF THE DRAWINGS

(1) FIG. 1 illustrates a block diagram of an embodiment of a memory system in accordance with the present disclosure.

(2) FIGS. 2A and 2B illustrate top plan views of simplified layout diagrams of protection circuits in accordance with the present disclosure.

(3) FIGS. 3A to 3C illustrate top views of simplified block diagrams of portions of protection circuits in accordance with the present disclosure.

(4) FIG. 3D illustrates an alternate configuration for bit-line nodes and source nodes in accordance with the present disclosure.

(5) FIGS. 4A and 4B illustrate side and top views of an integrated planar NMOS-vertical PMOS inverter in accordance with the present disclosure.

(6) FIGS. 5A and 5B illustrate side and top views of an integrated vertical CMOS inverter in accordance with the present disclosure.

(7) FIGS. 6A to 6D illustrate top views of inverter interconnection that are in accordance with the present disclosure.

(8) FIGS. 7A and 7B illustrate alternate embodiments for the interconnection of FIG. 6D.

(9) FIGS. 8A to 8C illustrate intermediate components formed in an exemplary fabrication process for an integrated inverter in accordance with the present disclosure.

(10) FIGS. 9A to 9G illustrate intermediate components formed in an exemplary fabrication process for an integrated inverter in accordance with the present disclosure.

DETAILED DESCRIPTION

(11) In the following detailed description, reference is made to the accompanying drawings that form a part hereof, and in which is shown, by way of illustration, specific embodiments. In the drawings, like numerals describe substantially similar components throughout the several views. Other embodiments may be utilized and structural, logical, and electrical changes may be made without departing from the scope of the present disclosure. The following detailed description is, therefore, not to be taken in a limiting sense.

(12) The term “semiconductor” used herein can refer to, for example, a layer of material, a wafer, or a substrate, and includes any base semiconductor structure. “Semiconductor” is to be understood as including silicon-on-sapphire (SOS) technology, silicon-on-insulator (SOI) technology, thin film transistor (TFT) technology, doped and undoped semiconductors, epitaxial layers of a silicon supported by a base semiconductor structure, as well as other semiconductor structures well known to one skilled in the art. Furthermore, when reference is made to a semiconductor in the following description, previous process steps may have been utilized to form regions/junctions in the base semiconductor structure, and the term semiconductor can include the underlying layers containing such regions/junctions.

(13) Some exemplary embodiments of the present disclosure can be directed to a memory device such as, for example, a flash memory device. Flash memory devices (e.g., NAND, NOR, etc.) have developed into a popular source of non-volatile memory for a wide range of electronic applications. Non-volatile memory is memory that can retain its data values for some extended period without the application of power. Flash memory devices typically use a one-transistor memory cell that allows for high memory densities, high reliability, and low power consumption. Changes in threshold voltage of the memory cells, through programming (which is sometimes referred to as writing) of charge-storage structures (e.g., floating gates or charge traps) or other physical phenomena (e.g., phase change or polarization), determine the data value of each memory cell. Common uses for flash memory and other non-volatile memory may include personal computers, personal digital assistants (PDAs), digital cameras, digital media players, digital recorders, games, appliances, vehicles, wireless devices, mobile telephones, and removable memory modules, and the uses for non-volatile memory continue to expand.

(14) In a NOR flash architecture, memory cells, arranged in a column, are coupled in parallel, with each memory cell coupled to a data line, such as a bit line. A “column” refers to a group of memory cells that are commonly coupled to a local data line, such as a local bit line. It does not require any particular orientation or linear relationship, but instead refers to the logical relationship between memory cell and data line. Typically, the array of memory cells for NAND flash memory devices is arranged such that the control gate of each memory cell of a row of the array is connected together to form an access line, such as a word line. Columns of the array include strings (often termed NAND strings) of memory cells connected together in series, e.g., source to drain, between a pair of select lines, e.g., a source select line and a drain select line. The source select line includes a source select gate at each intersection between a NAND string and the source select line, and the drain select line includes a drain select gate at each intersection between a NAND string and the drain select line. Each source select gate is connected to a source line, while each drain select gate is connected to a data line, such as column bit line.

(15) The present disclosure is directed to a memory device having an array of memory cells. The memory device includes a plurality of bit-lines with each bit-line connected to a respective set of memory cells of the array of memory cells. The memory device can include a memory subsystem having a set of first memory circuits and a set of second memory circuits. Each first memory circuit

can be disposed laterally adjacent to a second memory circuit. Each first memory circuit includes a first bit-line connection and each second memory circuit including a second bit-line connection, the first and second bit-line connections can be adapted to connect to respective bit-lines of the plurality of bit-lines. In some embodiments, each of the first bit-line connections is disposed on a first bit-line connection line of the memory subsystem and each of the second bit-line connections is disposed on a second bit-line connection line of the memory subsystem, and the second bit-line connection line can be offset from the first bit-line connection line by a predetermined distance that is greater than zero.

(16) In another embodiment a memory device includes an array of memory cells and a plurality of bit-lines with each bit-line connected to a respective set of memory cells of the array of memory cells. The memory device includes a memory circuit having a memory latch. The memory latch includes a first integrated inverter having at least one vertical transistor and a second integrated inverter having at least one vertical transistor. In some embodiments, each integrated inverter includes a common input gate that has a gate-all-around configuration.

(17) FIG. 1 is a simplified block diagram of a NAND flash memory device **100** in communication with a processor **130** as part of an electronic system, according to an embodiment. The processor **130** may be a memory controller or other external host device. Memory device **100** includes an array of memory cells **104**. A row decoder **108** and a column decoder **110** are provided to decode address signals. Address signals are received and decoded to access memory array **104**.

(18) Memory device **100** also includes input/output (I/O) control circuitry **112** to manage input of commands, addresses, and data to the memory device **100** as well as output of data and status information from the memory device **100**. An address register **114** is in communication with I/O control circuitry **112**, and row decoder **108** and column decoder **110**, to latch the address signals prior to decoding. A command register **124** is in communication with I/O control circuitry **112** and control logic **116** to latch incoming commands. Control logic **116** controls access to the memory array **104** in response to the commands and generates status information for the external processor **130**. The control logic **116** is in communication with row decoder **108** and column decoder **110** to control the row decoder **108** and column decoder **110** in response to the addresses.

(19) Control logic **116** is also in communication with memory subsystem circuits that can include a cache register **118**, a data register **120**, and/or a circuit-protection subsystem **150**. Cache register **118** latches data, either incoming or outgoing, as directed by control logic **116** to temporarily store data while the memory array **104** is busy writing or reading, respectively, other data. During a write operation, data is passed from the cache register **118** to data register **120** for transfer to the memory array **104**; then new data is latched in the cache register **118** from the I/O control circuitry **112**. During a read operation, data is passed from the cache register **118** to the I/O control circuitry **112** for output to the external processor **130**; then new data is passed from the data register **120** to the cache register **118**. A status register **122** is in communication with I/O control circuitry **112** and control logic **116** to latch the status information for output to the processor **130**.

(20) A circuit-protection subsystem **150**, according to various embodiments, can be arranged between data register **120** (and/or cache register **118**) and memory array **104**. For example, low-voltage circuitry of data register **120** and/or cache register **118** may be coupled to one side (e.g., a low-voltage side) of the circuit-protection subsystem **150** and data lines or bit-lines of memory array **104** may be coupled to another side (e.g., a high-voltage side) of the circuit-protection subsystem **150**.

(21) Memory device **100** receives control signals at control logic **116** from processor **130** over a control link **132**. The control signals may include at least a chip enable CE #, a command latch enable CLE, an address latch enable ALE, and a write enable WE #. Memory device **100** receives command signals (which represent commands), address signals (which represent addresses), and data signals (which represent data) from processor **130** over a multiplexed input/output (I/O) bus **134** and outputs data to processor **130** over I/O bus **134**.

(22) For example, the commands are received over input/output (I/O) pins [7:0] of I/O bus **134** at I/O control circuitry **112** and are written into command register **124**. The addresses are received over input/output (I/O) pins [7:0] of bus **134** at I/O control circuitry **112** and are written into address register **114**. The data are received over input/output (I/O) pins [7:0] for an 8-bit device or input/output (I/O) pins [15:0] for a 16-bit device at I/O at control circuitry **112** and are written into cache register **118**. The data are subsequently written into data register **120** for programming memory array **104**. For another embodiment, cache register **118** may be omitted, and the data are written directly into data register **120**. Data are also output over input/output (I/O) pins [7:0] for an 8-bit device or input/output (I/O) pins [15:0] for a 16-bit device.

(23) It will be appreciated by those skilled in the art that additional circuitry and signals can be provided, and that the memory device of FIG. **1** has been simplified. It should be recognized that the functionality of the various block components described with reference to FIG. **1** may not necessarily be segregated to distinct components or component portions of an integrated circuit device. For example, a single component or component portion of an integrated circuit device could be adapted to perform the functionality of more than one block component of FIG. **1**. Alternatively, one or more components or component portions of an integrated circuit device could be combined to perform the functionality of a single block component of FIG. **1**.

(24) Additionally, while specific I/O pins are described in accordance with popular conventions for receipt and output of the various signals, it is noted that other combinations or numbers of I/O pins may be used in the various embodiments. The configuration of memory array **104** is known to those skilled in the art and thus will not be further discussed except as needed to describe the exemplary embodiments of the present disclosure. In addition, although the exemplary embodiments may be discussed in conjunction with a NAND flash architecture, the embodiments described herein are not limited to NAND flash, and exemplary embodiments can include other flash architectures, such as NOR flash, etc.

(25) Data lines are sometimes coupled to circuitry that may be configured to handle relatively low voltages (e.g., that may be referred to as low-voltage circuitry), such as data cache circuitry. The low-voltage circuitry may provide relatively low voltages (e.g., 0 V up to about 4 V) to the data lines during read or write operations. However, during erase operations (e.g., involving NAND memory arrays), memory cells may be erased a block at a time by grounding all of the access lines in the block, for example, while allowing the data lines to float. A relatively high erase voltage (e.g., about 20 V to 30 V) is then applied to a semiconductor on which the memory cells are formed, and thus to the channels of the memory cells, to remove the charge from the charge-storage structures. This can cause the data lines to float to about the erase voltage and can damage the low-voltage circuitry coupled to data lines.

(26) Protection devices, such as field-effect transistors (FETs), may be coupled between the bit lines and low-voltage circuitry, such as, for example, the low-voltage circuitry of data cache **118** and/or the low-voltage circuitry of data register **120**, to protect the low-voltage circuitry from the relatively high voltages that may be present on the bit lines during an erase operation. For example, an FET may be turned off during an erase operation to protect the low-voltage circuitry from the relatively high voltages that may be present on the bit lines, and the FET may be turned on during a read or write operation to pass the relatively low voltages between the low-voltage circuitry and the bit lines. Each circuit-protection device may be formed on an active region that is separated and electrically isolated from an adjacent active region, on which an adjacent circuit-protection device is formed, by an isolation region, such as a shallow-trench isolation (STI) region. A bit line may be coupled to a high-voltage side of a circuit-protection device, and the low-voltage circuitry may be coupled to a low-voltage side of a circuit-protection device. For example, for an FET, a contact (e.g., that may be referred to as a high-voltage-side contact) can couple a bit line to a source/drain region on the high-voltage side, and a contact (e.g., also referred to as a low-voltage-side contact) may couple low-voltage circuitry to a source/drain region on the low-voltage side. The circuit-

protection devices may be coupled on a one-to-one basis to the bit lines or one circuit-protection device to two or more data lines through a multiplexer. However, the pitch of the circuit-protection devices may be relatively large (e.g., 38 nm or greater) in order to avoid breakdown of the circuit-protection devices. The relatively large pitch uses up considerable area and thus may increase the size of the memory device.

(27) FIGS. 2A and 2B are top plan views of an exemplary embodiment of a portion of circuit-protection subsystem **150** that can include a plurality of protection circuits **210** to provide high-voltage isolation (e.g., isolating a 20V to 30V signal). Similar protection circuits are discussed in detail in Applicant's U.S. Pat. Nos. 8,766,365 and 10,163,893, which are incorporated herein by reference in their entirety as background. Accordingly, for brevity, description of the protection circuits herein focuses on the features of the present inventive technology. In addition, although exemplary embodiments of the present disclosure are provided using circuit-protection devices associated with the cache and/or data registers, those skilled in the art will understand that the present disclosure is applicable to other types of memory circuits such as, for example, circuits that connect to other types of data lines.

(28) In exemplary embodiments of the present disclosure, the circuit-protection subsystem **150** can include a set of one or more protection circuits **210** arranged in a line **212** (e.g., vertically arranged as shown in FIG. 2A) and another set of one or more protection circuits **210** arranged in a line **214** of protection circuits **210**. Representative protection circuits **210** are identified by dotted rectangles. Each protection circuit **210** can include a source/drain node **220**, a polysilicon gate **215** (also referred to herein as data gate **215**), and a source/drain node **222**. The node **220** (also referred to herein as low-voltage (LV) node **220**) can be coupled to low-voltage circuitry such as data cache **118** and/or data register **120** via, for example, contact **225** ("LV contact **225**"). Depending on the memory operation (e.g., erase, read, program, etc.), the node **222** can be coupled to circuitry that can have a relatively high voltage (e.g., about 20V to about 30V during, e.g., erase operation) and/or a relatively low voltage (e.g., about 0V to about 4V during, e.g., read or program operations). In some embodiments, each node **222** (also referred to herein as bit-line (BL) node **222**) can be connected to a respective bit line of the memory array **104** via, for example, contact **227** ("BL contact **227**"). In operation, the data gates **215** can be turned on to connect LV nodes **220** to BL nodes **222** when low-voltage memory operations, such as, for example, read/program operations, are taking place. When high-voltage memory operations, such as, for example, erase operations, are taking place, the data gates **215** can be turned off to isolate the LV nodes from the high-voltage on the BL nodes **222**. As used herein, a BL node and corresponding BL contact can also be referred to herein as BL connection.

(29) Portions of the protection circuits **210** can be respectively formed in individual active regions **228** that are defined by isolation regions **230**, e.g., STI regions, formed in the semiconductor. Each active region **228** can include the respective LV node **220**, the data gate **215**, and can extend to the corresponding BL node **222** surrounding the BL contact **227** (see, e.g., arrows **228** in FIG. 2A). The isolation regions **230** can be formed on either side of one or more active regions **228**. Each isolation region **230** electrically isolates and/or physically separates adjacent active regions **228** from each other. The semiconductor may be comprised of silicon, e.g., monocrystalline silicon, and, for example, may be conductively doped to have a conductivity type, e.g., a p-type conductivity, e.g., to form a p-well.

(30) In some embodiments, the circuit-protection subsystem **150** can include an active area **232** that is configured to form one or more transistors, such as, for example, FETs. The active area **232** can be covered by a polysilicon layer that forms a common gate **235** for the one or more transistors that can, in some embodiments, extend beyond the active region **232**. In some embodiments, the polysilicon layer can be segmented such that more than one gate (e.g., gates similar to common gate **235**) are formed. In some embodiments, the active region **232** can include one or more source (SRC) nodes **237** that can be formed in openings in the polysilicon layer. The SRC nodes **237** can

include contacts **239** that can be connected to a voltage source. As used herein, an SRC node and corresponding SRC contact can also be referred to herein as a SRC connection. In some embodiments, the active area **232** can include at least a portion of the BL nodes **222**. The one or more transistors defined by the common gate **235** can be configured such that, when the common gate **235** is on, the BL nodes **222** and the one or more SRC nodes **237** are connected and, when the common gate **235** is off, the BL nodes **222** and the one or more source nodes **237** are isolated from each other. In some embodiments, unlike the LV nodes **220**, the BL nodes **222** and/or the SRC nodes **237** are not separated from each other by isolation regions (e.g., STI) formed in the semiconductor. Instead, the BL nodes **222** are selectively and electrically coupled to each other and to the one or more SRC nodes **237** by the common gate **235**. In some embodiments, active regions **228** can be contiguous with active region **232**. That is, active regions **228** may extend from active region **232**, as shown in FIG. 2A. When BL nodes **222** are connected to low voltages (e.g., about 0V to about 4V), there is sufficient isolation between the BL nodes **222** when common gate **235** is turned off (e.g., by grounding the common gate contact **237**). Accordingly, the need to form isolation regions to create separate active regions for BL nodes **222** and/or the SRC nodes **237** can be avoided.

(31) In some embodiments, similar to the common gate **235**, the polysilicon for the data gate **215** can extend beyond the active area **228**. During read/program operations, the data gate **215** can be on to selectively couple the corresponding low-voltage circuitry (e.g., data cache **118** and/or data register **120**) to the respective bit line via BL node **222** and BL contact **227**. During this time, the common gate **235** is off to isolate the BL nodes **222** from the one or more SRC nodes **237**, which can be connected to a voltage source via respective SRC contacts **239**. During erase operations, the data gate **215** can be off to isolate the low-voltage circuitry (e.g., data cache **118** and/or data register **120**) from the respective bit line. During this time, the common gate **235** is on to connect the BL nodes **222** to a voltage source (e.g., a high voltage source) via SRC contacts **239** of the one or more SRC nodes **237**. In some embodiments, as shown on FIG. 2B, an n⁺ mask layer **270** (inner most shaded region) can be used to deposit n⁺ implant areas around the BL contacts **227** and the SRC contacts **239**. The n⁺ implant area provides a region of low resistivity around the contacts to ensure better and more reliable connections.

(32) As memory devices get smaller and/or denser such as in, for example, 3D NAND devices, it may be desirable to reduce the distance or pitch between the bit-lines of the memory array (e.g., memory array **104**). For example, in some memory circuits, the BL contacts are arranged laterally adjacent to each other in a straight line (also referred to herein as “non-offset BL line”). In such systems, the BL pitch is the distance between the BL contacts, and reducing the BL pitch means reducing the distance between the BL contacts. However, the BL contacts may already be at an effective distance that corresponds to a minimum effective distance. As used herein, “effective distance” means the shortest distance between adjacent BL contacts or n⁺ implants disposed around the adjacent BL contacts, whichever distance is shorter. That is, the effective distance may not necessarily be the shortest distance between the BL contacts themselves. This is because n⁺ implants have low resistivity, and thus the shortest distance between the n⁺ implants surrounding the BL contacts can be the limiting factor when reducing the BL pitch. A “minimum effective distance,” as used herein, means that a further reduction in the effective distance between the BL contacts will result in adversely affecting BL-BL leakage (isolation) and/or breakdown voltage (BV) to a point where the BL-BL leakage and/or BV falls outside a predetermined design value for the memory device. Bit-line to bit-line leakage affects the ability to properly read data from the bit-line and BV affects the maximum erase voltage and/or gate oxide reliability of the gate. For example, in some memory systems, a BL pitch of 38 nm can correspond to an effective distance of 5.76 nm. However, due to variations in high volume manufacturing, further reductions in the effective distance may not be possible while keeping the BV or the BL-BL leakage within the predetermined design value for the memory device. Thus, in traditional configurations where

adjacent BL contacts are disposed along a straight line, once the BL pitch of adjacent BL contacts corresponds to the minimum effective distance and/or falls within variations of high volume manufacturing, there is little or no BL pitch margin to sacrifice and a further reduction in the pitch of the protection circuits may not be achievable without exceeding design criteria with respect to BL-BL leakage and/or BV. For example, it is believed that a BL pitch below 37 nm (corresponding to an effective distance of 5.44 nm) may not be achievable in traditional systems.

(33) In some exemplary embodiments of the present disclosure, a BL contact **227** (and/or corresponding n⁺ implant) in the circuit-protection subsystem **150** can be located on a non-offset BL line while a laterally adjacent BL contact **227** (and/or corresponding n⁺ implant) can be disposed in a location that is offset from the non-offset BL line by a predetermined distance (e.g., an offset greater than zero). The predetermined distance or offset can be in a direction that is perpendicular to the non-offset BL line. A direction parallel to the non-offset BL line is referred herein as “width direction” and a direction perpendicular to the non-offset BL line can be referred to herein as “length direction.” For clarity, reference to the n⁺ implant may be omitted in the following description when discussing the BL contacts, but those skilled in the art understand that the BL contacts of the circuit-protection subsystem **150** can have surrounding n⁺ implants (or p⁺ implants or another type of doping depending on the type of transistor) in some embodiments. By offsetting some BL contacts **227** in the length direction, a BL pitch (“offset BL pitch”) in the width direction between the offset BL contact and a non-offset BL contact can be less than a BL pitch (“non-offset BL pitch”) of circuit-protection devices having adjacent non-offset BL contacts. The arrow labeled “P” in FIG. 2A illustrates a BL pitch, which in this case, corresponds to an offset BL pitch because the “B” BL contacts **227** are offset. By offsetting the “B” BL contact **227** (discussed further below), the offset BL pitch (e.g., pitch P) can be less than a non-offset BL pitch and the effective distance can remain the same between the offset and non-offset BL pitches. In some embodiments, the offset BL pitch can be less than the minimum effective distance while keeping the actual effective distance between BL contacts at or above the minimum effective distance.

(34) In some embodiments, more than one “B” BL contact **227** is offset and arranged on an offset bit-line connection line OBL (also referred to herein as “offset BL line OBL”) from an adjacent “A” BL contact **227** that is not offset and arranged on a non-offset bit-line connection line NOBL (also referred to herein as “non-offset BL NOBL”). The BL contacts **227** are arranged on the offset BL line OBL and non-offset BL line NOBL so as to form an offset stagger (or zig-zag) pattern along a width direction of circuit-protection subsystem **150**. Accordingly, a set of BL contacts can be formed along a non-offset BL line NOBL and another set of BL contacts can be formed along an offset BL line OBL. In some embodiments, a non-offset BL contact and a laterally adjacent offset BL contact can form a repeating alternating pattern. For example, as seen in FIGS. 2A and 2B, the “B” BL contacts **227** (and corresponding BL nodes **222**) of protection circuits **210** can be offset by a predetermined distance L1 (also referred to herein as “offset distance L1”) in the length-direction with respect to “A” BL contacts **227** (and corresponding BL nodes **222**) of laterally adjacent protection circuits **210**. In some exemplary embodiments, the BL contacts **227** of every other protection circuit **210** can be disposed at an offset distance L1. However, in other embodiments, other offset distance patterns can be used such as, for example, every second protection circuit **210**, every third protection circuit **210**, etc. In addition, in the exemplary embodiment of FIG. 2A, only a single offset distance (e.g., offset distance L1) is used in the offset stagger pattern. However, in other embodiments, the BL contacts of the respective protection circuits can be disposed in any number of predetermined offset distance patterns. For example, the protection circuits **210** can be disposed in a staggered pattern (e.g., a repeating staggered pattern) in which a first BL contact has an offset of zero (e.g., on the non-offset BL line NOBL), the next BL contact has a first predetermined offset distance (e.g., offset distance L1), the next BL contact has a second predetermined offset distance (not shown) that is different from offset distance L1 and not zero, etc. In some embodiments, by offsetting the BL contact **227** of one or more protection circuits **210**, the

length of a circuit-protection subsystem **150** can increase. However, because the pitch of the one or more protection circuits **210** can be reduced by offsetting the BL contacts, the overall area of the circuit-protection subsystem **150** can be reduced despite a possible increase in the length. In addition, because the offset pitch is reduced in comparison to a non-offset BL pitch, the memory array **104** can be denser and/or more memory cells can be added while shrinking the physical size of the memory array **104** (or, at a minimum, without increasing the physical size of the memory array **104**). By arranging the BL contacts **227** to have an offset stagger pattern, the offset BL pitch of the protection circuits **210** can be reduced in comparison to a non-offset BL pitch while keeping the same effective distance between adjacent BL contacts **227**. In some embodiments, while keeping the effective distance between adjacent BL contacts **227** at or greater than the minimum effective distance, the BL pitch can be reduced to a value that is less than 37 nm, less than 36 nm, between 35 nm to 37 nm, or between 35 nm to 36 nm. In some embodiments, while keeping the effective distance between adjacent BL contacts **227** at or greater than the minimum effective distance, the BL pitch can be reduced to a value that is less than the minimum effective distance.

(35) In some embodiments, the offset distance L1 is set such that the effective distance D1 (see FIG. 2B) between one or more adjacent BL contacts **227** (e.g., between an offset BL contact and a non-offset BL contact) equals the minimum effective distance. In some embodiments, the offset distance L1 is set such that the effective distance D1 is in a range of 5 nm to 7 nm. As seen in FIG. 2B, the BL contacts **227** are formed in an area having rectangular cutouts in the polysilicon of the common gate **235**. In the exemplary embodiment of FIG. 2B, the effective distance D1 is measured from a corner of an n+ implant of a non-offset BL contact **227** to the nearest corner of an n+ implant of an offset BL contact **227**. Of course, the polysilicon cutout shapes are not limited to rectangular shapes and can include other shapes such as, for example, circles, ovals, triangles, etc. In some embodiments, the offset distance L1 is set such that an effective distance D2 between SRC contact **239** and one or more adjacent offset BL contacts **227** equals or exceeds the minimum effective distance. In some embodiments, the offset distance L1 is set such that the effective distance D2 is in a range of 5 nm to 7 nm. The effective distance D2 can be an outer part (e.g., corner or another part of the perimeter) of an n+ implant of an SRC contact **239** to the nearest outer part (e.g., corner or another part of the perimeter) of an adjacent n+ implant of an offset BL contact **227**.

(36) In some embodiments, the offset distance L1 is set such that the effective distance D1 equals or exceeds the minimum effective distance and the length AA1 of the active area **232** is set such that the effective distance D2 equals or exceeds the minimum effective distance. However, in some embodiments, to maintain an effective distance D2 that is at or greater than the minimum effective distance, SRC nodes **237** can be selectively formed in regions of the common gate **235** that allow for an effective distance that equals or exceeds the minimum effective distance. For example, as seen in FIGS. 2A and 2B, the SRC nodes **237** can be disposed in locations where the opposing BL contacts **227** (and corresponding BL nodes **222**) are not offset (e.g., "A" BL contacts **227**). The number of SRC nodes **237** and the corresponding SRC contacts **239** can depend on factors such as number of individual polysilicon gates that form the continuous common gate **235**, the number of BL nodes **222** that are offset, the resistivity of the SRC contact **239** connections to the common gate **235**, and/or reliability of the SRC contact **239** connections to the common gate **235**. The number of SRC nodes **237** can be equal to or more than the number of BL nodes **222**. However, in other embodiments, the number of source nodes **237** can be less than the number of BL nodes **222**. For example, in the embodiment of FIGS. 2A and 2B, the number of SRC nodes **237** will be about 25% of the number of BL nodes **222**.

(37) FIG. 2B illustrates an exemplary embodiment of an n+ mask used to form the n+ implants around BL contacts **227** and the SRC contacts **239**. The n+ mask layer **270** is overlapped by the polysilicon gate **235**. In some exemplary embodiments, the n+ mask layer **270** can have a staggered configuration that corresponds to the offset staggered pattern of the BL contacts **227**. For example,

as seen in FIG. 2B, the n+ mask layer **270** has an edge outline **272** (e.g., a step-wise edge outline) that matches the offset stagger pattern on the BL contacts **227** of nodes **222**. Based on the n+ mask layer **270**, the area around the location of one or more BL contacts **227** and/or one or more SRC contacts **239** will include an n+ implant. By configuring the edge of the n+ mask layer **270** to match the offset stagger of the BL contacts **227**, a distance D3 from the BL contacts **227** to an exposed silicon portion of the node **222** remains constant between offset and non-offset BL nodes **222** of protection circuits **210**.

(38) As best seen in FIG. 2B, in some embodiments, the edge **229** of the active areas **228** that are adjacent to the active area **232** can be formed to match the stagger (e.g., offset) of the active area **232** and/or the BL contacts **227**. For example, the edge **229** can be formed under the polysilicon of the common gate **235** between the fingers **236** of the common gate **235** such that a distance D4 from the BL contacts **227** to the edge **229** of the active area **228** for each of the protection circuits **210** is at a same value. In some embodiments, similar to the edge **229** of the active area **228**, the polysilicon edges **237** of the common gates **235** can also have a pattern that corresponds to the offset stagger pattern of the BL nodes **222** and/or BL contacts **227**. Accordingly, in such embodiments, similar to the distance D4, a distance from the BL contact **227** to the polysilicon edge **236** of the respective common gates **235** can be the same for each protection circuit **210**.

(39) In some embodiments, a distance D5 from the BL contacts **227** to the data gate **215** can be equal between the protection circuits **210** in order to keep the total resistance of the BL nodes **222** (e.g., resistance from the data gate **215** to the respective BL contact **227**) equal among the protection circuits **210**. Accordingly, in some embodiments, the position of one or more data gates **215** can also be staggered by an offset distance (e.g., offset distance L1) that matches the offset stagger pattern of the respective BL contacts **227**.

(40) In some embodiments, if the data gates **215** are staggered, the LV nodes **220** and/or LV contacts **225** can also be staggered (not shown) so that the length of the LV nodes **220** and/or resistance of the LV nodes **220** can be set equal to each other. That is, the length of the LV nodes **220** and data gate **215** can be equal in some embodiments. In some embodiments (e.g., as shown in FIG. 2A), the LV nodes **220** and the contacts **225** are disposed in a straight line (e.g., not staggered) but the data gates **215** are staggered. Accordingly, to the extent equal resistance between the low-voltage nodes **220** is desired, the LV node **220** can be configured (e.g., composition or a physical dimension such as length, width, etc.) such that the resistance value is equal among the protection circuits **210**.

(41) FIG. 3A illustrates a simplified block diagram of a portion of the circuit-protection subsystem **150** that includes blocks representing the data gates **215** and a simplified section illustrating the common gate **235**. As seen in FIGS. 2A and 3A, the protection circuit **210** are mirrored along a centerline of the circuit-protection subsystem **150** containing the common gate **235**. In this embodiment, the n+ implant in the BL nodes **222** are equal due to the step-wise (or staggered) n+ mask edge **330**. Accordingly, the active areas **228** can also be staggered to maintain an equal resistance as discussed above. As seen in FIG. 3A, the common gate section **235** includes one or more p-well implant layers **310**. The p-well implant layers **310** can be disposed between the BL nodes **222** and/or the SRC nodes **237** and serve to define the boundaries between the BL nodes **222** and/or the boundaries between BL nodes **222** and the SRC nodes **237**. In some embodiments, the p-well implant layers **310** are disposed perpendicular to a line corresponding to the effective distance between the n+ implants of adjacent BL nodes **222** (e.g., line **320**) and/or a line corresponding to the shortest distance between the n+ implants of SRC node **237** and an adjacent BL node **222** (e.g., line **322**). In other embodiments (not shown), the p-well implants are disposed in straight lines between the BL nodes **222** and/or between BL nodes **222** and the SRC nodes **237** so that the p-well implants intersect at 90-degrees to each other. A portion of p-well implant layer **310** can be doped (e.g., lightly doped) to have p-type conductivity, where the doped portion has a desired threshold voltage (Vt) for the channel of the field-effect transistor formed between the BL nodes **222** and/or

the channel of the field-effect transistor formed between the BL nodes **222** and the SRC node **237**. (42) FIG. **3B** illustrates a simplified block diagram of a portion of another embodiment of the circuit-protection subsystem. The circuit-protection subsystem **150'** includes a block illustrating the data gates **215** and a simplified section illustrating a portion of the common gate **235**. In this embodiment, the n+ mask layer **340** is configured so as to have a straight edge (see dotted line). Accordingly, unlike the embodiment of FIG. **3A**, the edge of the n+ mask layer **340** does not include a stagger that matches the offsets of the "B" BL nodes **222**. Because of the straight edge, the n+ implant distribution **342** (see shaded region) in each of the of BL nodes **222** are not equal and the distance from the BL contacts **227** to the edge of the n+ mask layer **340** will be different. However, because the BL nodes **222** include a highly doped n+ implant area **342**, any difference in the resistances from the BL contact **227** to edge the n+ mask layer **340** between the protection circuits **210** is negligible. That is, only the resistance of the non-n+ doped regions of the active area **228** can be considered when configuring the protection circuits. Accordingly, in some embodiments, the protection circuits **210** can be configured such that the data gates **215** are not staggered and a distance D6 between the data gates **215** and the edge of the n+ mask layer **340** is set to be the same for each of the protection circuits **210**. The length from the BL contact **227** and the exposed portion of the active area **228** and/or to the data gates **215** not set to be equal, but this is not a problem because the n+ implant areas have negligible differences in resistance. Of course, to the extent the resistance of the active areas **228** would benefit from further equalization between the protection circuits **210**, the geometry (e.g., width, length, and/or shape) and/or composition (e.g., n/p doping) of each active area **228** can be changed such that the resistances are equal. (43) As discussed above, in some embodiments, the edge of the n+ implant layer **340** is not staggered to match a stagger of the BL contacts **227**. In such embodiments, however, it is possible that the effective distance between adjacent BL contacts **227** may no longer be a limiting dimension with respect to the pitch of the protection circuit **210**. Instead, in some embodiments, it is possible that a distance X1 between the BL nodes **222** in the fingers **345** is configured to be at or greater than the minimum effective distance in order to ensure that the bit-line to bit-line isolation and/or breakdown voltage falls within a predetermined design value for the memory device. Accordingly, to ensure the distance X1 is at or greater than the minimum effective distance, the polysilicon of the common gate **235** can extend into the active area **228** of the offset BL nodes **222**. For example, as seen in FIG. **3B**, polysilicon tabs **360** extend into the active areas **228** of the "B" or non-offset protection circuits **210** to ensure the distance X1 is at or greater than the minimum effective distance.

(44) FIG. **3C** illustrates another embodiment of the present disclosure. The embodiment in FIG. **3C** is similar to the embodiment of FIG. **3B** with respect to the n+ mask layer, which has a straight edge **340**. However, instead of a single polysilicon gate (e.g., common gate **235**), the circuit-protection subsystem **150''** includes a shared gate **235a''** for the protection circuits **210** in line **212** and a shared gate **235b''** for the protection circuits **210** in line **214**. The shared gates **235a''** and **235b''** can be disposed on either side of a continuous source area **335** that is disposed between the protection circuits **210** of line **212** and the protection circuits **210** of line **214**. In some embodiments, the continuous source area **335** can be doped with an n+ implant layer. In some embodiments, the protection circuits **210** on one side of the continuous source area **335** can be offset in comparison to the protection circuits **210** on the other side of the continuous source area **335**. In some embodiments, the offset of the protection circuits is such that a non-offset BL node **222** of the shared gate **235a''** is aligned with an offset BL node **222** of the shared gate **235b''** and vice versa. That is, the protection circuits **210** in the circuit-protection subsystem **150''** are not mirrored along a centerline extending through the SRC nodes **237** like in circuit-protection subsystem **150** discussed above. In some embodiments, each of the shared gates **235a''** and **235b''** can include one or more SRC nodes **237''**, with each SRC node **237''** having a contact **239''**. In some embodiments, one or more SRC nodes **237''** with the respective SRC contacts **239''** can be

disposed in the continuous source area **335** between opposing offset/non-offset pairs of BL nodes **222''**. For example, as seen in FIG. **3C**, an SRC node **237''** can be disposed between a non-offset BL node **222''** and an offset BL node **222''** on the opposing shared gate. In some embodiments, the continuous source area **335** and/or the SRC nodes **237''** include an n+ implant. By using an offset configuration for the opposing protection circuits **210**, an SRC node **237** with corresponding SRC contact **239** can be disposed between every pair of opposing protection circuits **210**. Thus, while circuit-protection subsystem **150''** may be larger than circuit-protection subsystems **150** and **150'**, the greater number of source contacts in circuit-protection subsystem **150''** can provide more reliability. FIG. **3C** shows a configuration in which a continuous source area **335** is added to circuit-protection subsystem **150''** that is similar in configuration to circuit-protection subsystem **150'**. However, those skilled in the art will understand that a continuous source area **335** can also be added to a circuit-protection device that is similar in configuration to circuit-protection subsystem **150**. In addition, those skilled in the art will understand that the other features of circuit-protection devices **150** and/or **150'**, discussed above, as be included in circuit-protection subsystem **150''**, as appropriate, and thus, for brevity, will not be repeated.

(45) In the embodiments discussed above, the openings in the polysilicon layer for the BL contacts and SRC contacts are shown having shapes with right-angles (e.g., rectangles or a portion thereof). However, the openings can have other types of shapes, such as for example, multi-sided shapes, circles, ovals, portions thereof, etc. For example, as seen in FIG. **3D**, in some embodiments, the opening in the polysilicon for BL contact **227** and/or SRC contact **239** can include facets **370**. The facets **370** can be disposed so as to increase the effective distance between adjacent BL contacts **227** (not shown) and/or the effective distance D2 between the BL contact **227** and the SRC contact **239** in comparison to openings that have right-angles as shown in FIGS. **2A** and **2B**.

(46) In some 3D-type memory devices, memory subsystems including control logic (e.g., control logic **116**) and/or page buffers (e.g., cache register **118**) can be disposed under the memory array (e.g., memory array **104**). This arrangement, known as CMOS under array (CUA), allows the memory subsystem to be smaller than systems in which the control logic and page buffer are located adjacent to the memory array. However, even configured as a CUA, there can be a limit with respect to how much smaller a memory device can get due to how some cache memory latches are fabricated. In some cache memory latches, the NMOS and PMOS components (e.g., p-channel low-voltage PLV and n-channel low-voltage NLV) of the CMOS inverters that make up the latch are formed in separate wells. Even though the wells may be closely spaced, the spacing requirements for the components will mean a greater area for the CMOS inverters than if the components are formed in the same well. The separate remote wells also mean that the metal routing between the components can get congested and complicates the ability to shrink the CUA.

(47) To reduce the pitch of the latches and thus the size of the page buffer, exemplary embodiments of the present disclosure include integrated CMOS inverters that can be incorporated into a NAND latch to create a memory cell (e.g., an SRAM cell). The integrated CMOS inverter can include a PMOS transistor and an NMOS transistor that share a common active area. Because the NMOS and/or PMOS transistors are floating body, an n-well implant is not needed. Accordingly, the integrated CMOS inverter uses less space than a traditional CMOS inverter. In some embodiments, the PMOS transistor and/or the NMOS transistor can be formed as a vertical transistor. In some embodiments, the integrated CMOS inverter can include a common gate, which can eliminate the need to connect the separate gates of each component. When one or both transistors are vertical, the integrated CMOS inverter of the present disclosure allows for neighboring CMOS inverters to be in close proximity without concern for polysilicon-polysilicon spacing of the gate end caps. Thus, the need for gaps between gate end caps (nibbles) that can exist in traditional page buffer latch layouts can be eliminated.

(48) FIG. **4A** illustrates a cross-sectional view of an integrated inverter **400** that includes a planar NMOS transistor **410** and a vertical PMOS transistor **440** with a common output contact **430**. The

integrated inverter **400** can be disposed on a silicon substrate **402**. The active area of the integrated inverter **400** is common to both the NMOS and PMOS transistors and can be defined by shallow-trench isolation **460** on each side of the integrated inverter **400**. As seen in FIG. **4A**, the NMOS transistor **410** includes an NMOS source **412** and a NMOS drain **422**, which can be an n+ diffusion layers disposed into the silicon substrate **402**. One or more metal layers (e.g., a tungsten layers) can be disposed on the NMOS source **412** to create an NMOS source contact **414**. One or more metal layers (e.g., a tungsten layers) can be disposed on the NMOS drain **422**, and the metal layer(s) can also connect to the PMOS drain **444** to form a common output contact **430**. A channel **413** can be disposed between NMOS source **412** and NMOS drain **422**. A portion of channel **413** can be doped with a different (e.g., higher) conductivity than that of the p-type substrate **402** such that the doped portion has a desired threshold voltage (V_t). The NMOS source **412** can be connected to ground potential GND via the NMOS source contact **414**. The NMOS transistor **410** can also include a silicon oxide layer **416** disposed above the source **412** and drain **422**. Between source **412** and the drain **422**, the silicon oxide layer **416** acts as the gate oxide for the planar NMOS transistor. The silicon oxide layer **416** can be deposited on the silicon substrate **402** so as to surround the metal layer **414**. In addition, one or more silicon oxide layers can be disposed on the silicon oxide layer **416** so as to isolate the metal layer **414** from the surrounding components. A gate **418** comprised of one or more layers of polysilicon and/or WSi_x (tungsten silicide) can be disposed on top of the silicon oxide layer **416**. In some embodiments, the gate **418** can have a gate-all-around (GAA) design that is common to both the planar NMOS transistor **410** and the vertical PMOS transistor **440**. One or more metal layers (e.g., a tungsten layers) can be disposed on the common gate **418** to serve as the input contact **420** (V_{in}) to the inverter **400**.

(49) The vertical PMOS transistor **440** includes a PMOS source **448**, which can be an p+ implant layer, disposed on a channel **450**. The channel **450** can be comprised of one or more layers of polysilicon, which can be n-type polysilicon. The channel **450** can be disposed on a PMOS drain **444**, which can be a p+ diffusion layer. The PMOS drain **444** can be formed on an n-type diffusion layer **404**, which can be formed on the substrate **402**. The PMOS drain **444** can connect to the common output contact **430**, which can be made of one or more metal layers (e.g., a tungsten layers). Thus, the common output contact **430** connects to both the NMOS drain **422** and the PMOS drain **444**. The silicon oxide layer **416** can be deposited on the silicon substrate **402** so as to surround the metal of the common output contact **430**. In addition, one or more silicon oxide layers **424** can be disposed on the silicon oxide layer **416** so as to surround the common output **430** and isolate the common output **430** from the common gate **418**. In some embodiments, the composition of the silicon oxide layer **424** and the silicon oxide layer **416** can be the same. One or more metal layers (e.g., a tungsten layer) can be disposed on the PMOS source **448** to serve as the PMOS source contact **452**. The PMOS source **448** can be connected to V_{cc} potential (e.g., 3.5 volts) via the PMOS source contact **452**. The silicon oxide layer **416** can be disposed on the silicon substrate **402** so as to surround the channel **450**. One or more lateral gate oxide layers **446** can be disposed on the silicon oxide layer **416** so as to surround the channel **450** (see also FIG. **4B**). In some embodiments, the composition of the lateral gate oxide layer **446** and the silicon oxide layer **416** can be the same.

(50) FIG. **4B** is a top view of the inverter **400**. As seen FIG. **4B**, the GAA-type gate **418** covers nearly all of the inverter **400**. The inverter **400** can be configured with one or more NMOS source contacts **414**, which can be isolated from the gate **418** by one or more silicon oxide layers **416**. In the embodiment of FIG. **4B**, there are two contacts **414**, but any number of contacts can be used based on design resistivity, reliability of the connections and complexity of the connections. For example, if only one contact is used and it is defective, the inverter **400** and, thus the memory cell, will be unusable. However, forming a large number of contacts may not be economical or technically feasible. Similarly, although shown with two contact each, there can be one or more contacts formed for the input contact **420** and/or common output contact **430**. The input contacts

420 are connected to the gate **418**, while the common output contacts **430** are isolated from the gate **418** by one or more silicon oxide layers **424**. As shown in FIG. 4B, a single PMOS source contact **452** is formed on the vertical PMOS transistor **440**. However, in some embodiments, more than one PMOS source contact can be formed. The PMOS source **448** is shown having a rectangular column (e.g., square column) shape in FIGS. 4A and 4B. The channel **450**, which is hidden, can also have a rectangular column (e.g., square column) shape. However, the PMOS source **448** and/or the channel **450** can have other shapes such as, for example, a cylindrical column shape. One or more gate oxide layers **446** can surround the channel **450** to isolate the channel **450** from the common gate **418** (see also FIG. 4A). The gate oxide layers **446** can have a geometry that corresponds to that of the channel **450**. For example, if the channel **450** is a rectangular column, the gate oxide layers **446** can be a rectangular tube, if the channel **450** is a cylindrical column, the gate oxide layers **446** can be a cylindrical tube, and so on.

(51) In operation, when the input contact **420** (V_{in}) has a high signal (e.g., high potential), the GAA-type common gate **418** is also at a high potential. With the gate **418** high, the planar NMOS transistor **410** is on and vertical PMOS transistor **440** is off. With NMOS transistor **410** on, the NMOS source **412**, which is at ground potential GND via NMOS source contact **414**, is connected to common output contact **430** (V_{out}) via channel **413** and NMOS drain **422**. Accordingly, when the input contact **420** (V_{in}) has a high signal, the common output contact **430** (V_{out}) has low signal. When the input contact **420** (V_{in}) has a low signal (e.g., low potential), the gate **418** is also at a low potential. With the gate **418** low, the planar NMOS transistor **410** is off and vertical PMOS transistor **440** is on. With PMOS transistor **410** on, the PMOS source **448**, which is at V_{cc} potential via PMOS source contact **452**, is connected to the common output contact **430** (V_{out}) via channel **450** and PMOS drain **444**. Accordingly, when the input contact **420** (V_{in}) has a low signal, the common output contact **430** (V_{out}) has high signal. Thus, the planar NMOS-vertical PMOS inverter **400** will behave similar to a traditional planar NMOS-planar PMOS inverter but will take up less space because, unlike all-planar CMOS inverters, separate wells are not needed. Although a planar NMOS and a vertical PMOS is described above, those skilled in the art understand that a planar PMOS and a vertical NMOS will have a similar configuration but with the p-type implants and n-type implants reversed. Accordingly, for brevity, a discussion of an inverter with a planar PMOS and a vertical NMOS is omitted.

(52) FIG. 5A illustrates a cross-sectional view of an integrated inverter **500** that includes a vertical PMOS transistor **510** and a vertical NMOS transistor **540**. The integrated inverter **500** can be disposed on a silicon substrate **502**. The active area of the integrated inverter **500** is common to both the PMOS and NMOS transistors and can be defined by shallow-trench isolation **560** on each side of the integrated inverter **500**. The vertical PMOS transistor **510** and a vertical NMOS transistor **540** include a common output contact **530** and a common gate **518**. The vertical PMOS transistor **510** includes a PMOS source **512**, which can be an p+ implant layer, disposed on a channel **555**. The channel **555** can be comprised of one or more layers of polysilicon, which can be n-type polysilicon. The channel **555** can be disposed on a PMOS drain **522**, which can be a p+ diffusion layer disposed into the silicon substrate **502**, which can be an n-type well. The silicon oxide layer **516** can be disposed on the silicon substrate **502** so as to surround the channel **555**. The PMOS drain **522** and an NMOS drain **544** can be connect to a common output contact **530**, which can be made of one or more metal layers (e.g., a tungsten layers). Thus, the common output contact **530** connects to both the PMOS drain **522** and the NMOS drain **544**. The silicon oxide layer **516** can be deposited on the silicon substrate **502** so as to surround the metal of the common output contact **530**. In addition, one or more silicon oxide layers **524** can be disposed on the silicon oxide layer **516** so as to surround the common output **530** and isolate the common output **530** from a common gate **518**. In some embodiments, the composition of the silicon oxide layer **516** and the silicon oxide layers **524** can be the same. One or more metal layers (e.g., a tungsten layer) can be disposed on the PMOS source **512** to serve as the PMOS source contact **514**. The PMOS source

512 can be connected to Vcc potential (e.g., 3.5 volts) via the PMOS source contact **514**. One or more lateral gate oxide layers **513** can be disposed on the silicon oxide layer **516** so as to surround the channel **555**. The common gate **518** can be comprised of one or more layers of polysilicon and/or WSi_x (tungsten silicide). The common gate **518** can be disposed on top of the silicon oxide layer **516**. The common gate **518** can be a gate-all-around design. One or more metal layers (e.g., a tungsten layers) can be disposed on the GAA-type gate **518** to serve as the input contact **520** (Vin) to the inverter **500**.

(53) The vertical NMOS transistor **540** of the integrated inverter **500** includes an NMOS source **548**, which can be an n+ implant layer, disposed on a channel **550**. The channel **550** can be comprised of one or more layers of polysilicon, which can be p-type polysilicon. The channel **550** can be disposed on an NMOS drain **544**, which can be a n+ diffusion layer disposed into a p-type diffusion layer **504**. The p-type diffusion layer **504** can be disposed in the silicon substrate **502**. The NMOS drain **544** can be connected to the common output contact **530**. One or more metal layers (e.g., a tungsten layer) can be disposed on the NMOS source **548** to serve as the NMOS source contact **552**. The NMOS source **548** can be connected to ground potential (GND) via the NMOS source contact **552**. The silicon oxide layer **516** can be disposed on the silicon substrate **502** so as to surround the channel **550**. One or more lateral gate oxide layers **546** can be disposed on the silicon oxide layer **516** so as to surround the channel **550**.

(54) FIG. 5B is a top view of the inverter **500**. As seen FIG. 5B, the GAA-type gate **518** covers nearly all of the inverter **500**. The inverter **500** can be configured with a single PMOS source contacts **514** that is formed on the vertical PMOS transistor **510**. However, in some embodiments, more than one PMOS source contact can be formed. That is, while there is one contact shown in FIG. 5B, any number of contacts can be used based on design resistivity, reliability of the connections and complexity of the connections. Similarly, although shown with two contacts each, there can be one or more contacts formed for the input contact **520** and/or common output contact **530**. The input contacts **520** are connected to the gate **518**, while the common output contacts **530** are isolated from the gate **518** by one or more silicon oxide layers **524**. As shown in FIG. 5B, a single NMOS source contact **552** is formed on the vertical NMOS transistor **540**. However, like the PMOS source contact, in some embodiments, more than one NMOS source contact can be formed. The PMOS source **512** and the NMOS source **548** are shown having a rectangular column (e.g., square column) shape in FIGS. 5A and 5B. One or both of the respective channels **555** and **550**, which are hidden under the sources **512** and **548**, can also have rectangular column (e.g., square column) shapes. However, one or both of the PMOS source **512** and the NMOS source **548** and/or one or both of the channels **555** and **550** can have other shapes such as, for example, cylindrical column shapes. One or more gate oxide layers **513** and **546** can surround the respective channels **555** and **550**. Of course, the gate oxide layers **513** and **546** can have geometries that correspond to the respective channels **555** and **550**. For example, if one or both of the channels **555**, **550** has a rectangular column configuration, the respective gate oxide layers **513**, **546** can be a rectangular tube, if one or both of the channels **555**, **550** has a cylindrical column configuration, the respective gate oxide layers **513**, **546** can be a cylindrical tube, and so on.

(55) In operation, when the input contact **520** (Vin) has a high signal (e.g., high potential), the GAA-type common gate **518** also has a high potential. With the common gate **518** high, the NMOS transistor **540** is on and the PMOS transistor **510** is off. With the NMOS transistor **540** on, the NMOS source **548**, which is at ground potential GND via PMOS source contact **552**, is connected to the common output contact **530** (Vout) via channel **550** and PMOS drain **544**. Accordingly, when the input contact **520** (Vin) has a high signal, the common output contact **530** (Vout) has a low signal. When the input contact **520** (Vin) has a low signal (e.g., low potential), the gate **518** also has a low potential. With the common gate **518** low, the NMOS transistor **540** is off and the PMOS transistor **510** is on. With the PMOS transistor **510** on, the PMOS source **512**, which is at Vcc potential via PMOS source contact **514**, is connected to common output contact **530** (Vout) via

channel 555 and PMOS drain 522. Accordingly, when the input contact 520 (Vin) has a low signal, the common output contact 530 (Vout) has a high signal. The vertical NMOS-vertical PMOS inverter 500 as disclosed above will behave similar to a traditional planar NMOS-planar PMOS inverter but will take up less space because separate wells are not needed. While a vertical-vertical inverter (e.g., inverter 500) can be more compact than a planar-vertical (e.g., inverter 400), in some cases inverter 400 can be more economical. Because one of the inverters is planar, a portion of the traditional fabrication process can be used when manufacturing planar-vertical inverters.

(56) FIG. 6A illustrates a memory cell 600, e.g., an SRAM cell, having two integrated inverters 610a,b that can be, for example, the same as inverter 500 having a PMOS transistor and an NMOS transistor, as discussed above. As seen in FIG. 6A, the integrated inverters 610a,b are oriented such that the input contact(s) 620a of inverter 610a aligns (e.g., linearly aligns) with the output contact(s) 630b of inverter 610b, and the input contact(s) 620b of inverter 610b aligns (e.g., linearly aligns) with the output contact(s) 630a of inverter 610a. In some embodiments, conductive contact strips 640a and 640b (e.g., metal layers) can be disposed such that the input contact(s) 620a and 620b are connected to output contacts 630b and 630a, respectively. By using an integrated inverter configuration, the routing of the contact strips between the connections of the inverters is direct (e.g., linear) and less congested, which allows for a more compact cache configuration.

(57) FIG. 6B illustrates a memory cell 600', e.g., an SRAM cell, having two integrated inverters 610a' and 610b'. Integrated inverter 610a' can be the same as integrated inverter 500 discussed above. Inverter 610b' can be similar to inverter 500 except that the orientation of input contact(s) 620b' and output contact(s) 630b' are reversed in comparison to the input contact(s) 620a' and output contact(s) 630a' of integrated inverter 610a'. By reversing the input and output contacts, one of the integrated inverters does not have to be rotated 180 degrees (as in the case of FIG. 6A) for the input contact(s) 620a' and 620b' to line up (e.g., linearly align) with the opposing output contact(s) 630b' and 630a', respectively, for easy strapping. In the memory cell 600', the PMOS transistors are aligned (e.g., linearly aligned) between the two inverters and the NMOS transistors are aligned (e.g., linearly aligned) between the two inverters. Accordingly, because like transistors are aligned, fabrication of the memory cells 600' can be less complex and easier than if like transistors are not aligned, while still keeping the advantage of the simplified and less congested routing.

(58) FIGS. 6C and 6D illustrate alternative layout and interconnection arrangements for a memory cell (e.g., an SRAM cell) with integrated inverters. In the embodiment of FIG. 6C, the memory cell 650 includes integrated inverters 660a and 660b. Integrated inverter 660a can be similar to integrated inverter 500 but the silicon layer 665a around the output contact 663a extends to an edge of the active area of the integrated inverter 660a. Integrated inverter 660b can also be the same as integrated inverter 660a in some embodiments. However, in the embodiment of FIG. 6C, integrated inverter 660b is similar to integrated inverter 500' with respect to the arrangement of the PMOS and NMOS inverters, but in integrated inverter 660b, the silicon layer 665b around the output contact 663b extends to an edge of the active area of the integrated inverter 660b. As seen in FIG. 6C, the connections between the integrated inverters can be done using a polysilicon connection rather than a metal connection. For example, a polysilicon connection strip 664a can extend from the polysilicon gate layer 668a corresponding to input contact(s) 662a to the extended silicon layer 665b corresponding to output contact 663b. Similarly, a polysilicon connection strip 664b can extend from the polysilicon gate layer 668b corresponding to input contact(s) 662b to the extended silicon layer 665a corresponding to output contact 663a. For example, the polysilicon connection strips 664a and 664b can be stitched to respective output contacts 663b and 663a. That is, the polysilicon connection strip is formed onto the respective extended silicon layer and the corresponding output contact (e.g., elongated output contact) is formed so as to overlap a portion of the polysilicon connection strip. For example, overlap portion 667a represents the overlap of contact 663a onto polysilicon connection strip 664b, and overlap portion 667b represents the

overlap of contact **663b** onto polysilicon connection strip **664a**.

(59) FIG. **6D** illustrates an embodiment of a memory cell (e.g., an SRAM cell). The memory cell **680** includes integrated inverters **690a** and **690b**. The PMOS and NMOS transistors are similar in arrangement to that of integrated inverter **500**. However, the input and output for the integrated inverter is formed on a same side of the PMOS and NMOS transistors instead of between the transistors. For example, as seen in FIG. **6D**, a polysilicon gate section **692a** corresponding to an input contact and a silicon oxide section **693a** corresponding to an output contact are formed on a same side of the PMOS and NMOS transistors of the integrated inverter **690a**. Similarly, a polysilicon gate section **692b** corresponding to an input contact and a silicon oxide section **693b** corresponding to an output contact are formed on a same side of the PMOS and NMOS transistors of the integrated inverter **690b**. In the embodiment of FIG. **6D**, the arrangement of the PMOS and NMOS transistors is the same for both the integrated transistors **690a** and **690b** thus one of the inverters is rotated 180 degrees. However, in other embodiments, the arrangement of the PMOS and NMOS transistors can be reversed in integrated transistor **690b** so that the transistors of the same type are linearly aligned similar to the embodiment of FIG. **6B**. In some embodiments, the input polysilicon gate sections **692a** and **692b** can be stitched into the respective output silicon oxide section **693b** and **693a** using corresponding contact strips **695a** and **695b** (e.g., an elongated output contact). The contact strips can be, for example, polysilicon, metal, and/or another appropriate material. Although integrated inverters having vertical PMOS and vertical NMOS configurations are shown in FIGS. **6A** to **6D**, those skilled in the art will recognize that integrated inverter **400** can be similarly arranged to form a compact memory cell. Accordingly, for brevity, discussion of the connections in a planar/vertical memory cell is omitted.

(60) As discussed above with reference to FIG. **6D**, the input connection and the output connection can be disposed on a same side of the integrated inverter so that corresponding inverters can be conveniently and compactly connected using, e.g., an elongated contact. However, instead of an elongated contact, in some embodiments, a modified pillar channel can be used to directly connect the input polysilicon gate layer of one of the integrated inverters to the output silicon layer of the other integrated inverter. For example, FIGS. **7A** and **7B** illustrate two embodiments of a pillar channel contact that can be used in place of an elongated contact configuration of FIG. **6D**. In the embodiment of FIG. **7A**, the input pillar connection of an integrated inverter **710** is deposited over an output silicon layer **742** of another integrated inverter **740**. To form the pillar channel connection **720**, an opening in the protective mask for forming the pillar channel **720** is larger than the diameter of the pillar channel **720** so that, when the polysilicon for the pillar channel **720** is deposited, the channel polysilicon overlaps a WSix layer **722** and/or a polysilicon layer **724** that corresponds to the input connection. In some embodiments, only one of the WSix layer **722** or the polysilicon layer **724** may be formed on top of a silicon oxide layer **726**. Once the pillar channel **720** is formed, an electrical connection with current path **730** is formed between the input WSix/polysilicon layer **722/724** of the inverter **710** to the output silicon **742** of the inverter **740**. In the embodiment of FIG. **7A**, a layer of sidewall silicon oxide **728** is formed such that the current path **730** is the full length of the pillar channel **720**. In the embodiment of FIG. **8B**, a pillar channel **752** of an integrated inverter **750** is formed without a sidewall silicon oxide so that the input WSix/polysilicon layer **722/724** of the inverter **750** comes into direct electrical contact with the polysilicon of the pillar channel **752** and a shorter current path **732** is formed between inverter **750** and the output silicon **742** of the inverter **740**. In some embodiments, the diameters of the pillar channel **720** and/or **752** are made as small as possible to keep the capacitance as small as possible while maintain a reliable electrical connection.

(61) FIGS. **8A-8C** illustrate a simplified high-level fabrication process for an integrated inverter having a planar NMOS and a vertical PMOS. Those skilled in that understand the details of a fabrication process for a CMOS inverter and thus, for brevity, details related to photoresist layers, masks, chemical and/or plasma etching, and other known details are omitted. Prior to the

deposition of the silicon oxide layer **808**, a shallow n-type implant layer **804** is deposited onto a p-type substrate **802**. The n-type implant layer **804** deposition provides for isolation of the vertical PMOS transistor. A p+ implant layer **806** can then be added on top of the n-type implant layer **804** to act as the drain for the vertical PMOS transistor. The arrangement of the n-type implant layer **804** and the p+ implant layer **806** is such that the n-type implant layer area is larger and extends out beyond the area of the p+ implant layer **806**. For example, in some embodiments, the n-type implant layer **804** is angled and/or a resist trim etch is performed after p+ implant layer **806** such that the n-type implant area extends out farther than the p+ implant layer area. In the case of a vertical NMOS transistor, only an n+ implant layer, which acts as a drain, may be deposited on the p-type substrate. For a vertical CMOS inverter, the steps for the vertical PMOS transistor and the vertical NMOS transistor discussed above can be performed. After the p+ implant layer **806** is deposited, one or more silicon oxide layers **808**, one or more polysilicon gate layers **810**, and/or one or more WSix (e.g., tungsten silicide) gate layers **812** can be deposited. The layers are added in the appropriate sequence and with an etching of at least the gate layers **810/812** to produce an intermediate component in which the silicon oxide layer **808** deposited over the active area is covered by the polysilicon gate layer **810** and the WSix gate layer **812** and the silicon oxide layer **808** in the STI areas **830** are covered by the WSix gate layer **812**.

(62) As seen in FIG. **8B**, a protective layer **814** with an opening for the channel **818** for the vertical PMOS transistor is deposited over the WSix gate layer **814**. The thickness of the protective layer **814** can be based on a desired amount that the polysilicon of the vertical channel should extend above the WSix gate layer **812**. After deposition of the protective layer **814**, an etch is performed on the WSix and polysilicon gate layers **812/814** to create the hole for the channel **818** of the vertical PMOS transistor. One or more layers of silicon oxide are deposited, and a gate sidewall etch is performed to create a hole and expose the bottom to the p+ implant layer **806**. With the creation of the lateral gate **816**, one or more layers of polysilicon is deposited to create the channel **818**. The intermediate component is then subject to chemical mechanical polishing (CMP) the top of protective layer **814**. The protective layer **814** is then etched away (not shown in FIG. **8B**).

(63) After the protective layer **814** is etched away, as seen in FIG. **8C**, a gate etch is performed to define the common gate configuration which includes an opening for the output contact area (Vout). The n+ implant layers **822** and **824** corresponding to the source and drain, respectively, can be deposited after the gate etching process. In addition, a p+ implant layer **820**, corresponding to the source of vertical PMOS transistor, can be deposited on the channel **818**. After silicon oxide build up and subsequent etching of the openings for the ground GND and Vout contacts, one or more layers of metal (e.g., tungsten) can be deposited to form the source Vcc, ground GND, Vin and Vout contacts.

(64) In some embodiments where the integrated CMOS inverter includes a planar NMOS and a vertical PMOS, the fabrication of the vertical PMOS can be accomplished by recess etching the silicon substrate to create the PMOS channel (e.g., a silicon mesa) rather than forming the channel by silicon deposition as discussed above. As seen in FIG. **9A**, an n-type silicon layer **908** is formed over a p-type silicon substrate **902**. As seen in FIG. **9B**, a hard mask **912** is deposited over an area that corresponds to the n-type channel for the PMOS transistor, and the n-type silicon layer **908** is then etched until the p-type substrate **902** is reached. Due to the hard mask **912**, a mesa **910** that corresponds to a n-type channel for a PMOS transistor is formed. After the etching process, an n-type tub is formed under a p-type implant layer. That is, one or more n-type dopant layers are deposited into the p-type substrate under the mesa **910** to create an n-type implant **904**. The n-type dopant layers of the n-type implant **904** can be angled such that the n-type implant **904** encases a p-type implant **906** that has been deposited under the mesa **910**.

(65) As seen in FIG. **9C**, after the etching process, a photoresist layer **922** is added with openings in the photoresist layer **922** that correspond to the drain of the PMOS transistor. The fabrication process then includes adding a p+ implant layer **914** into the p-type implant **906** (see FIG. **9B**). As

seen in FIG. 9D, the formation process includes depositing one or more silicon oxide layers **916** followed by one or more polysilicon layers **918** and one or more additional silicon oxide layers **920**. In addition, each STI is masked and etched. The silicon oxide layers **920** can include sacrificial oxide with stripe to fix any etch-induced damage. As seen in FIG. 9E, the silicon oxide **921** at the STI is recessed below the top of the polysilicon layer **918**. One or more WSix layers **924** can be deposited on top of the polysilicon layer **918**. In some embodiments, additional thin layer(s) of polysilicon can be deposited prior to the WSix layer **924** based on the topology of the active area-STI interface.

(66) After depositing the WSix layer **924**, as seen in FIG. 9F, an etch is performed to expose the hard mask **912** on the mesa **910**, and to expose the drain **930** and source **928** areas of an NMOS transistor on top of the silicon substrate **902**. A further wet etch can be performed to remove the hard mask **912** from the top of the mesa **910**. In addition, using appropriate masking, a p+ implant deposition can be performed to create the source **926** of the PMOS transistor, and an n+ implant deposition can be performed to create the source **928** and the drain **930** of the NMOS transistor. After the backend oxide fill and a CMP, as seen in FIG. 9G, the source contact (e.g., ground GND) for the NMOS source **928**, the input contact (e.g., Vin) for common gate **924**, the output contact (e.g., Vout) bridging the n+/p+ interface between NMOS drain **930** and PMOS drain **914**, and the source contact (e.g., Vcc) for the PMOS source **926** can be deposited.

(67) Although specific embodiments have been illustrated and described herein, it will be appreciated by those of ordinary skill in the art that any arrangement that is calculated to achieve a similar (e.g., the same) purpose may be substituted for the specific embodiments shown. For example, for other embodiments, enhancement-mode-field-effect transistors may be substituted for the depletion-mode-field-effect transistors described above. For example, metal-gate-enhancement-mode-field-effect transistors may be substituted for the metal-gate-depletion-mode-field-effect transistors, and lateral-gate-enhancement-mode-field-effect transistors may be substituted for the lateral-gate-depletion-mode-field-effect transistors. Accordingly, this application is intended to cover any adaptations or variations of the embodiments.

(68) The above detailed descriptions of embodiments of the technology are not intended to be exhaustive or to limit the technology to the precise form disclosed above. Although specific embodiments of, and examples for, the technology are described above for illustrative purposes, various equivalent modifications are possible within the scope of the technology as those of ordinary skill in the relevant art will recognize. For example, although steps are presented in a given order, alternative embodiments may perform steps in a different order. The various embodiments described herein may also be combined to provide further embodiments.

(69) From the foregoing, it will be appreciated that specific embodiments of the technology have been described herein for purposes of illustration, but well-known structures and functions have not been shown or described in detail to avoid unnecessarily obscuring the description of the embodiments of the technology. Where the context permits, singular or plural terms may also include the plural or singular term, respectively. Moreover, unless the word “or” is expressly limited to mean only a single item exclusive from the other items in reference to a list of two or more items, then the use of “or” in such a list is to be interpreted as including (a) any single item in the list, (b) all of the items in the list, or (c) any combination of the items in the list. For example, as used herein, including in the claims, “or” as used in a list of items (for example, a list of items prefaced by a phrase such as “at least one of” or “one or more of”) indicates an inclusive list such that, for example, a list of at least one of A, B, or C means A or B or C or AB or AC or BC or ABC (i.e., A and B and C). Also, as used herein, the phrase “based on” shall not be construed as a reference to a closed set of conditions. For example, an exemplary step that is described as “based on condition A” may be based on both a condition A and a condition B without departing from the scope of the present disclosure. In other words, as used herein, the phrase “based on” shall be construed in the same manner as the phrase “based at least in part on.” Additionally, the terms

“comprising,” “including,” “having,” and “with” are used throughout to mean including at least the recited feature(s) such that any greater number of the same feature and/or additional types of other features are not precluded.

(70) The processing device (e.g., processor **130** and/or another controller) represents one or more general-purpose processing devices such as a microprocessor, a central processing circuit, or the like. More particularly, the processing device can be complex instruction set computing (CISC) microprocessor, reduced instruction set computing (RISC) microprocessor, very long instruction word (VLIW) microprocessor, or processor implementing other instruction sets, or processors implementing a combination of instruction sets. Processing device (e.g., processor **130** and/or another controller) can also be one or more special-purpose processing devices such as an application specific integrated circuit (ASIC), a field programmable gate array (FPGA), a digital signal processor (DSP), network processor, or the like.

(71) The machine-readable storage medium (also known as a computer-readable medium) on which is stored one or more sets of instructions or software embodying any one or more of the methodologies or functions described herein. The machine-readable storage medium can be, for example, memory system **100** or another memory device. The term “machine-readable storage medium” should be taken to include a single medium or multiple media that store the one or more sets of instructions. The term “machine-readable storage medium” shall also be taken to include any medium that is capable of storing or encoding a set of instructions for execution by the machine and that cause the machine to perform any one or more of the methodologies of the present disclosure. The term “machine-readable storage medium” shall accordingly be taken to include, but not be limited to, solid-state memories, optical media and magnetic media.

(72) It will also be appreciated that various modifications may be made without deviating from the disclosure. For example, one of ordinary skill in the art will understand that various components of the technology can be further divided into subcomponents, or that various components and functions of the technology may be combined and integrated. In addition, certain aspects of the technology described in the context of particular embodiments may also be combined or eliminated in other embodiments. Furthermore, although advantages associated with certain embodiments of the new technology have been described in the context of those embodiments, other embodiments may also exhibit such advantages and not all embodiments need necessarily exhibit such advantages to fall within the scope of the technology. Accordingly, the disclosure and associated technology can encompass other embodiments not expressly shown or described.

Claims

1. An apparatus, comprising: an array of memory cells; a set of first memory circuits, each first memory circuit including a first bit-line connection; and a set of second memory circuits, each second memory circuit including a second bit-line connection, the first and second bit-line connections adapted to connect to memory cells in the array of memory cells, wherein one or more first memory circuits of the set of first memory circuits are disposed between consecutive second memory circuits of the set of second memory circuits in a width direction, wherein the first bit-line connections are disposed in-line to each other in the width direction and the second bit-line connections are disposed in-line to each other in the width direction, and wherein the second bit-line connections are offset from the first bit-line connections in a length direction perpendicular to the width direction by a predetermined distance that is greater than zero.
2. The apparatus of claim 1, wherein each first memory circuit of the set of first memory circuits is disposed adjacent to a second memory circuit of the set of second memory circuits to form an alternating pattern.
3. The apparatus of claim 1, wherein two or more of the first memory circuits are disposed between the consecutive second memory circuits in the width direction.

4. The apparatus of claim 1, further comprising: a set of third memory circuits, each third memory circuit including a third bit-line connection, the third bit-line connection adapted to connect to memory cells in the array of memory cells, wherein the third bit-line connections are offset from the first bit-line connections in a length direction perpendicular to the width direction by a second predetermined distance that is greater than zero and different from the predetermined distance.
5. The apparatus of claim 1, wherein a pitch distance between a first memory circuit and a second memory circuit in a width direction is less than 37 nm.
6. The apparatus of claim 1, wherein a pitch distance between a first memory circuit and a second memory circuit in a width direction is less than 36 nm.
7. The apparatus of claim 1, wherein a pitch distance between a first memory circuit and a second memory circuit in a width direction is between 35 nm to 37 nm.
8. The apparatus of claim 1, wherein the predetermined distance is such that an effective distance between a first bit-line connection of a first memory circuit and a second bit-line connection of an adjacent second memory circuit is between 5 nm to 7 nm.
9. The apparatus of claim 1, wherein the first and second memory circuits are configured to isolate low voltage circuits connected to the respective first and second memory circuits from harmful voltage on the first and second bit-line connections.
10. The apparatus of claim 1, wherein the first and second memory circuits are disposed so as to form opposing pairs of first memory circuits across a centerline and opposing pairs of second memory circuits across the centerline in a mirrored arrangement.
11. The apparatus of claim 10, further comprising: a common gate disposed along the centerline to connect the first and second bit-line connections, wherein the common gate includes at least one opening for a source connection, and wherein the at least one opening for a source connection is disposed between the opposing pairs of first memory circuits.
12. The apparatus of claim 11, wherein the common gate includes well implant layers that are disposed perpendicular to at least one of a line corresponding to an effective distance between adjacent first and second bit-line connections or a line corresponding to a second effective distance between the source connection and the corresponding second bit-line connection.
13. The apparatus of claim 12, wherein the at least one of the source connections and an adjacent opening for the second bit-line connection includes facets along the line corresponding to the second effective distance.
14. The apparatus of claim 1, wherein the first and second memory circuits are disposed so as to form opposing arrangements of first and second memory circuits across a centerline, and further comprising: at least two shared gates disposed along the centerline, the at least two gates separated by a continuous source implant area, each shared gate configured to connect respective first and second bit-line connections, wherein the continuous source implant area includes at least one source connection.
15. The apparatus of claim 14, wherein the at least two gates include a first gate and a second gate, and wherein the arrangement of first and second memory circuits on a side of the first gate are offset with the arrangement of first and second memory circuits on a side of the second gate, and wherein the circuit offset is such that the first memory circuits on the first gate side align with the second memory circuits on the second gate side and the second memory circuits on the first gate side align with the first memory circuits on the second gate side, and wherein a source connection of the at least one source connection is disposed in the continuous source implant area between each pair of opposing first and second memory circuits.
16. An apparatus, comprising: a set of first protection circuits that isolate corresponding first logic circuits from harmful voltage, each first protection circuit having a first connection; and a set of second protection circuits that isolate corresponding second logic circuits from harmful voltage, each second protection circuit having a second connection, wherein one or more first protection circuits of the set of first protection circuits are disposed between consecutive second memory

circuits of the set of second protection circuits in a first direction, wherein the first and second protection circuits are arranged such that each second connection is offset from each first connection in a second direction that is perpendicular to the first direction, the offset being a predetermined distance that is greater than zero.

17. The apparatus of claim 16, wherein a pitch distance between a first protection circuit and a second memory circuit in the first direction is less than 37 nm.

18. The apparatus of claim 16, wherein a pitch distance between a first memory circuit and a second memory circuit in the first direction is less than 36 nm.

19. The apparatus of claim 16, wherein a pitch distance between a first memory circuit and a second memory circuit in the first direction is between 35 nm to 37 nm.

20. The apparatus of claim 16, wherein the predetermined distance is such that an effective distance between a first connection on a first protection circuit and a second connection on a second protection circuit is between 5 nm to 7 nm.
