

US Patent & Trademark Office

Patent Public Search | Text View

United States Patent	12401301
Kind Code	B2
Date of Patent	August 26, 2025
Inventor(s)	Sato; Hiroaki et al.

Drive apparatus of synchronous motor and method for driving synchronous motor

Abstract

A drive apparatus of a synchronous motor includes a current detecting unit that detects a phase current flowing to the synchronous motor and a magnetic pole position estimating unit that estimates a magnetic pole position of a rotor of the synchronous motor. The magnetic pole position estimating unit includes a first peak-to-peak detector that detects a first peak-to-peak value representing a difference between a maximum value and a minimum value of the phase current, a quadrature component detector that detects a quadrature component of the phase current, and a second peak-to-peak detector that detects a second peak-to-peak value representing a difference between a maximum value and a minimum value of the quadrature component. The magnetic pole position estimating unit calculates a first magnetic pole position and estimates an initial magnetic pole position of the rotor, based on the first magnetic pole position.

Inventors:	Sato; Hiroaki (Tokyo, JP), Matsui; Hirokazu (Hitachinaka, JP), Mitsui; Toshisada (Hitachinaka, JP), Myoen; Kohei (Hitachinaka, JP)
Applicant:	Hitachi Astemo, Ltd. (Hitachinaka, JP)
Family ID:	1000008778250
Assignee:	Hitachi Astemo, Ltd. (Hitachinaka, JP)
Appl. No.:	18/279088
Filed (or PCT Filed):	August 31, 2021
PCT No.:	PCT/JP2021/032019
PCT Pub. No.:	WO2022/195921
PCT Pub. Date:	September 22, 2022

Prior Publication Data

Foreign Application Priority Data

JP 2021-042673 Mar. 16, 2021

Publication Classification

Int. Cl.: H02P21/18 (20160101); H02P21/22 (20160101)

U.S. Cl.:

CPC H02P21/18 (20160201); H02P21/22 (20160201); H02P2207/05 (20130101)

Field of Classification Search

CPC: H02P (21/18); H02P (21/22); H02P (2207/05); H02P (6/185); H02P (25/089); H02P (2203/03); H02P (21/32)

References Cited**U.S. PATENT DOCUMENTS**

Patent No.	Issued Date	Patentee Name	U.S. Cl.	CPC
6172498	12/2000	Schmidt	318/685	H02P 6/185
2006/0113948	12/2005	Kaneko et al.	N/A	N/A
2007/0296371	12/2006	Aoki	318/700	H02P 6/182
2011/0050140	12/2010	Sakai et al.	N/A	N/A
2016/0268936	12/2015	Chi	N/A	N/A
2020/0266745	12/2019	Tachibana	N/A	H02P 21/32
2020/0295688	12/2019	Yoshikawa et al.	N/A	N/A
2021/0399663	12/2020	Ho	N/A	H02P 27/06

FOREIGN PATENT DOCUMENTS

Patent No.	Application Date	Country	CPC
2437391	12/2011	EP	H02P 27/06
2002-78391	12/2001	JP	N/A
2006-158101	12/2005	JP	N/A
2011-50198	12/2010	JP	N/A
2015-15830	12/2014	JP	N/A
2016-171741	12/2015	JP	N/A
2020-150656	12/2019	JP	N/A

OTHER PUBLICATIONS

International Search Report (PCT/ISA/210) issued in PCT Application No. PCT/JP2021/032019 dated Nov. 9, 2021 with English translation (4 pages). cited by applicant
Japanese-language Written Opinion (PCT/ISA/237) issued in PCT Application No. PCT/JP2021/032019 dated Nov. 9, 2021 with English translation (6 pages). cited by applicant

Background/Summary

TECHNICAL FIELD

(1) The present invention relates to a drive apparatus of a synchronous motor and a method for driving a synchronous motor.

BACKGROUND ART

(2) A permanent magnet synchronous motor (hereinafter, synchronous motor) including a permanent magnet in a rotor is used in an electrified vehicle typified by a hybrid vehicle and an electric vehicle. Synchronous motors are mainly divided into an interior permanent magnet synchronous motor having a structure in which a permanent magnet is embedded in a rotor and a surface permanent magnet synchronous motor in which a permanent magnet is disposed on a surface of a rotor. In an electrified vehicle, the interior permanent magnet synchronous motor is used for driving the vehicle, and the surface permanent magnet synchronous motor is often used for an electric power steering device and an electric brake device. In order to control the synchronous motor, an inverter which is a power converter is generally used. As a method of controlling torque of the synchronous motor by an inverter, current vector control is generally known. In order to perform the current vector control, there is a need to accurately ascertain a magnetic pole position of a rotor of the synchronous motor. As one of means for ascertaining the magnetic pole position, a resolver which is a position sensor is often provided in the synchronous motor.

(3) However, the resolver provided in the synchronous motor results in an increase in the number of components of a system, an increase in size, and an increase in costs. In addition, an output winding for outputting a position signal is wound around the resolver, and there is a risk of a malfunction due to disconnection or short circuit of the output winding. In addition, the risk of a malfunction also causes a decrease in reliability of the system.

(4) In this respect, position sensorless vector control is generally known as a technology of driving a synchronous motor without using a sensor such as a resolver. The position sensorless vector control detects or estimates an induced voltage of a synchronous motor to obtain position information of a rotor and perform current vector control. When the position sensorless vector control is employed, there is no need to provide a position sensor such as a resolver, and thus, it is possible to prevent the above-described problems caused by the position sensor, such as an increase in size and costs and a decrease in reliability of the system.

(5) In order to perform the position sensorless vector control, it is necessary to detect a rotor position (initial magnetic pole position) while a synchronous motor is stopped; however, when the synchronous motor is stopped, it is not possible to detect or estimate an induced voltage of the synchronous motor. Therefore, it is necessary to detect or estimate the initial magnetic pole position by another method.

(6) As a method for estimating an initial magnetic pole position of a synchronous motor, technologies of Patent Literature 1 and 2 are known. Patent Literature 1 discloses a method for estimating an initial magnetic pole position using saliency of a synchronous motor. Patent Literature 2 discloses a method for estimating an initial magnetic pole position using magnetic saturation.

CITATION LIST

Patent Literatures

(7) PTL 1: JP 2002-78391 A PTL 2: JP 2016-171741 A

Technical Problem

(8) A synchronous motor having saliency has a property of changing inductance depending on a rotor position. In Patent Literature 1, using such rotor position dependency of the inductance, a harmonic voltage is applied to a synchronous motor, and an initial magnetic pole position is estimated from a detection result of a current generated in the synchronous motor at that time. However, in a case of a synchronous motor having no saliency like a surface permanent magnet synchronous motor, the rotor position dependency of the inductance cannot be obtained. Therefore, the method for estimating the initial magnetic pole position in Patent Literature 1 is applicable to an interior permanent magnet synchronous motor but is not applicable to the surface permanent magnet synchronous motor.

(9) In addition, when the voltages are sequentially applied to three phases of the synchronous motor, the inductance decreases due to magnetic saturation when the voltage is applied to a phase close to the initial magnetic pole position, and a magnitude of the current changes. In PTL 2, the initial magnetic pole position is estimated using the magnetic saturation of the synchronous motor. This method has an advantage of being applicable to both the interior permanent magnet synchronous motor and the surface permanent magnet synchronous motor. However, it is known that a magnetic flux in the same direction as a magnetic flux of a permanent magnet and a magnetic flux in a direction orthogonal thereto interfere with each other, and a problem arises in that a significant error occurs in estimation of a magnetic pole position due to the interference.

(10) In this respect, an object of the present invention is to provide a drive apparatus of a synchronous motor and a method for driving a synchronous motor that can be applied to both an interior permanent magnet synchronous motor and a surface permanent magnet synchronous motor and can estimate an initial magnetic pole position with high accuracy.

Solution to Problem

(11) According to the present invention, there is provided a drive apparatus of a synchronous motor including: a power converter that drives a synchronous motor by sequentially applying positive and negative voltages to phases of the synchronous motor; a current detecting unit that detects a phase current flowing to the synchronous motor; and a magnetic pole position estimating unit that estimates a magnetic pole position of a rotor of the synchronous motor, based on the phase current detected by the current detecting unit. The magnetic pole position estimating unit includes a first peak-to-peak detector that detects a first peak-to-peak value representing a difference between a maximum value and a minimum value of the phase current, a quadrature component detector that detects a quadrature component of the phase current, and a second peak-to-peak detector that detects a second peak-to-peak value representing a difference between a maximum value and a minimum value of the quadrature component. The magnetic pole position estimating unit calculates a first magnetic pole position, based on the first peak-to-peak value detected by the first peak-to-peak detector and the second peak-to-peak value detected by the second peak-to-peak detector while the synchronous motor is stopped, and estimates an initial magnetic pole position of the rotor, based on the first magnetic pole position.

(12) According to the present invention, there is provided a method for driving a synchronous motor in a drive apparatus of a synchronous motor which includes a power converter that drives a synchronous motor by sequentially applying positive and negative voltages to phases of the synchronous motor and a current detecting unit that detects a phase current flowing to the synchronous motor, the method including: acquiring a first peak-to-peak value representing a difference between a maximum value and a minimum value of the phase current detected by the current detecting unit and a second peak-to-peak value representing a difference between a maximum value and a minimum value of a quadrature component of the phase current while the synchronous motor is stopped; calculating a first magnetic pole position based on the first peak-to-peak value and the second peak-to-peak value; and estimating an initial magnetic pole position of a

rotor of the synchronous motor based on the first magnetic pole position.

Advantageous Effects of Invention

(13) According to the present invention, even when β synchronous motor is either an interior permanent magnet synchronous motor or a surface permanent magnet synchronous motor, an initial magnetic pole position of a rotor of the synchronous motor can be estimated with high accuracy while the synchronous motor is stopped.

Description

BRIEF DESCRIPTION OF DRAWINGS

- (1) FIG. 1 is a configuration diagram of a drive apparatus according to a first embodiment.
- (2) FIG. 2 is a detailed configuration diagram of a voltage pulse preparing unit according to the first embodiment.
- (3) FIGS. 3A to 3J are diagrams illustrating a relationship between a phase command, a voltage command, and a current flowing to a synchronous motor in the first embodiment.
- (4) FIG. 4 is a diagram for describing an influence of magnetic saturation.
- (5) FIG. 5 is a detailed configuration diagram of a magnetic pole position estimating unit according to the first embodiment.
- (6) FIG. 6 is a configuration diagram illustrating main functions of a first magnetic pole position calculating unit.
- (7) FIGS. 7A and 7B are diagrams for describing a principle of improving estimation accuracy of an initial magnetic pole position.
- (8) FIG. 8 is a configuration diagram illustrating main functions of a polarity discriminator.
- (9) FIG. 9 is a detailed configuration diagram of a magnetic pole position estimating unit according to a second embodiment.
- (10) FIG. 10 is a configuration diagram illustrating main functions of a third magnetic pole position calculating unit.
- (11) FIG. 11 is a configuration diagram illustrating main functions of a fourth magnetic pole position calculating unit.
- (12) FIG. 12 is a configuration diagram of a drive apparatus according to a third embodiment.
- (13) FIG. 13 is a detailed configuration diagram of a voltage pulse preparing unit according to the third embodiment.
- (14) FIGS. 14A to 14J are diagrams illustrating a relationship between a phase command, a voltage command, and a current flowing to the synchronous motor in the third embodiment.
- (15) FIG. 15 is a configuration diagram of a drive apparatus according to a fourth embodiment.

DESCRIPTION OF EMBODIMENTS

(16) Hereinafter, embodiments of the present invention will be described with reference to the accompanying drawings. The following description and drawings are examples for describing the present invention and have omissions and are simplified as appropriate for the sake of clarity of description. The present invention can be carried out in various other forms. Unless otherwise specified, each configurational component may be described by a singular or plural form.

First Embodiment

(17) FIG. 1 is a configuration diagram of a drive apparatus **100A** according to a first embodiment. The drive apparatus **100A** includes a power converter **300**, a voltage pulse preparing unit **400A**, a current detecting unit **500**, and a magnetic pole position estimating unit **600A**, and drives a synchronous motor **200**.

(18) The synchronous motor **200** is a permanent magnet synchronous motor and includes a permanent magnet (ferromagnet) in a rotor and an armature winding in a stator. Further, in this embodiment, a position sensor that detects a magnetic pole position of the synchronous motor **200**

is not provided. Instead, the magnetic pole position is estimated. A case of estimating the magnetic pole position enables to achieve a decrease in size and costs and an increase in reliability of the synchronous motor **200**.

(19) When the synchronous motor **200** is driven, the voltage pulse preparing unit **400A** prepares voltage commands V_u^* , V_v^* , and V_w^* for sequentially applying positive and negative voltages to phases of a u phase, a v phase, and a w phase of the synchronous motor **200** in response to an input torque command T^* and outputs the prepared voltage commands V_u^* , V_v^* , and V_w^* to the power converter **300**. The voltage pulse preparing unit **400A** prepares the voltage commands V_u^* , V_v^* , and V_w^* based on a magnetic pole position estimated by the magnetic pole position estimating unit **600A**. In addition, when an initial magnetic pole position of the synchronous motor **200** is estimated, the voltage pulse preparing unit **400A** prepares a predetermined phase command θ^* and outputs the phase command θ^* to the magnetic pole position estimating unit **600A**.

(20) The power converter **300** is, for example, an inverter and performs a pulse width modulation (PWM) on the voltage commands V_u^* , V_v^* , and V_w^* from the voltage pulse preparing unit **400A** to perform on/off control of a semiconductor switch element of the power converter when the synchronous motor **200** is driven. Consequently, voltages V_u , V_v , and V_w are applied to the synchronous motor **200** to drive the synchronous motor **200**.

(21) The current detecting unit **500** is configured to include current sensors **500u**, **500v**, and **500w** that detect three-phase currents flowing to the synchronous motor **200**. The current sensors **500u**, **500v**, and **500w** are disposed for the respective phases of the synchronous motor **200**. The current detecting unit **500** detects three-phase currents I_u , I_v , and I_w and outputs the three-phase currents I_u , I_v , and I_w to the magnetic pole position estimating unit **600A**. Further, although an example in which the current sensors **500u**, **500v**, and **500w** are respectively arranged for the three phases of the synchronous motor **200** is illustrated, the current sensors may be arranged only for two phases (for example, u phase and v phase) by utilizing the fact that a sum of the three-phase alternating currents is zero. In addition, the three-phase currents of the synchronous motor **200** may be obtained from the current flowing through the DC bus (not illustrated) on an input side of the power converter **300**. In these configurations, the number of current sensors can be reduced, and a cost reduction can be achieved.

(22) The magnetic pole position estimating unit **600A** estimates a magnetic pole position corresponding to a position of a rotor of the synchronous motor **200** based on the three-phase currents I_u , I_v , and I_w detected by the current detecting unit **500**. In addition, while the synchronous motor **200** is stopped, an initial magnetic pole position θ_{est} of the rotor of the synchronous motor **200** is estimated based on the three-phase currents I_u , I_v , and I_w detected by the current detecting unit **500** and the phase command θ^* output from the voltage pulse preparing unit **400A**. Details of the magnetic pole position estimating unit **600A** while the synchronous motor **200** is stopped will be described below.

(23) FIG. 2 is a detailed configuration diagram of the voltage pulse preparing unit **400A** according to the first embodiment. Further, this configuration diagram illustrates a configuration in a case where the initial magnetic pole position θ_{est} is estimated while the synchronous motor **200** is stopped. Since a configuration in a case where the voltage commands V_u^* , V_v^* , and V_w^* are generated in response to the torque command T^* during driving of the synchronous motor **200** is well known, the description thereof is omitted in this embodiment.

(24) The voltage pulse preparing unit **400A** includes a voltage command preparing unit **410**, a phase switch **420**, and a command coordinate transformation unit **430**.

(25) The voltage command preparing unit **410** outputs a d-axis voltage command V_d^* and a q-axis voltage command V_q^* . In this embodiment, the d-axis voltage command V_d^* to alternate positive and negative voltages shown in FIG. 3B to be described below are generated, and the q-axis voltage command V_q^* is zero.

(26) The phase switch **420** prepares the phase command θ^* for converting the d-axis voltage

command V_d^* and the q-axis voltage command V_q^* prepared by the voltage command preparing unit **410** into three-phase voltage commands. The phase switch **420** sequentially outputs 0 degrees (0 radians), 120 degrees ($\frac{2}{3}\pi$ radians), and 240 degrees ($\frac{4}{3}\pi$ radians) as the phase command θ^* . (27) The command coordinate transformation unit **430** receives, as inputs, the d-axis voltage command V_d^* and the q-axis voltage command V_q^* prepared by the voltage command preparing unit **410** and the phase command θ^* output from the phase switch **420** and performs coordinate transformation on these commands into three-phase voltage commands V_u^* , V_v^* , and V_w^* . The coordinate transformation is performed according to the following expressions (1), (2), and (3).

$$V_u^* = V_d^* \times \cos(\theta^*) - V_q^* \times \sin(\theta^*) \quad (1)$$

$$V_v^* = V_d^* \times \cos(\theta^* - 2\pi/3) - V_q^* \times \sin(\theta^* - 2\pi/3) \quad (2)$$

$$V_w^* = V_d^* \times \cos(\theta^* - 4\pi/3) - V_q^* \times \sin(\theta^* - 4\pi/3) \quad (3)$$

(28) FIG. 3 is a diagram illustrating a relationship between the phase command θ^* , the voltage command, and a current flowing to the synchronous motor **200** in the first embodiment. FIG. 3(A) illustrates the phase command θ^* output from the phase switch **420**, and FIG. 3(B) illustrates the d-axis voltage command V_d^* prepared by the voltage command preparing unit **410**. Further, as described above, the q-axis voltage command V_q^* is zero. FIGS. 3(C) to 3(E) illustrate three-phase voltage commands V_u^* , V_v^* , and V_w^* output from the command coordinate transformation unit **430**, respectively. FIGS. 3(F) to 3(H) illustrate three-phase currents I_u , I_v , and I_w detected by the current detecting unit **500** and input to the magnetic pole position estimating unit **600A**, respectively.

(29) As illustrated in FIG. 3(A), the phase command θ^* is output from the phase switch **420** in an order of 0 degrees (0 radians), 120 degrees ($\frac{2}{3}\pi$ radians), and 240 degrees ($\frac{4}{3}\pi$ radians). As illustrated in FIGS. 3(C) to 3(E), the three-phase voltage commands V_u^* , V_v^* , and V_w^* , which are outputs of the command coordinate transformation unit **430**, are applied as alternating positive and negative pulse voltages to the u phase when the phase command θ^* indicates 0 degrees, to the v phase when the phase command θ^* indicates 120 degrees, and to the w phase when the phase command θ^* indicates 240 degrees. Consequently, as illustrated in FIGS. 3(F) to 3(H), the three-phase currents I_u , I_v , and I_w flow to the synchronous motor **200**.

(30) FIG. 5 is a detailed configuration diagram of the magnetic pole position estimating unit **600A** according to the first embodiment.

(31) The magnetic pole position estimating unit **600A** includes a first peak-to-peak detector **610**, a second peak-to-peak detector **620**, a quadrature component detector **630**, a first magnetic pole position calculating unit **640**, a polarity discriminator **650**, and a second magnetic pole position calculating unit **660**.

(32) The first peak-to-peak detector **610** receives, as inputs, the current values I_u , I_v , and I_w detected by the current detecting unit **500** and detects peak-to-peak values I_{upp} , I_{vpp} , and I_{wpp} representing differences between maximum values and minimum values of phase currents.

(33) In FIG. 3(F), the peak-to-peak value I_{upp} of the u phase current is a difference between a maximum value I_{u+} of the u phase current when a positive voltage is applied to the u phase with the phase command θ^* of 0 degrees and a minimum value I_{u-} of the u phase current when a negative voltage is applied to the u phase with the phase command θ^* of 0 degrees.

(34) In FIG. 3(G), the peak-to-peak value I_{vpp} of the v phase current is a difference between a maximum value I_{v+} of the v phase current when a positive voltage is applied to the v phase with the phase command θ^* of 120 degrees and a minimum value I_{v-} of the v phase current when a negative voltage is applied to the v phase with the phase command θ^* of 120 degrees.

(35) In FIG. 3(H), the peak-to-peak value I_{wpp} of the w phase current is a difference between a maximum value I_{w+} of the w phase current when a positive voltage is applied to the w phase with the phase command θ^* of 240 degrees and a minimum value I_{w-} of the w phase current when a negative voltage is applied to the w phase with the phase command θ^* of 240 degrees.

(36) As illustrated in FIGS. 3(F) to 3(H), I_{upp} , I_{vpp} , and I_{wpp} represent the peak-to-peak values of

the phase currents. In general, a permanent magnet synchronous motor used for driving an electric motor vehicle such as an electric vehicle has saliency (rotor position dependency of inductance), and the inductance changes depending on a rotor position. Therefore, the peak-to-peak values I_{upp} , I_{vpp} , and I_{wpp} of the phase currents obtained while the synchronous motor **200** is stopped also change depending on the initial magnetic pole position θ_{est} . In addition, it is known that a change in current (change in inductance) due to saliency appears in a cycle of $\frac{1}{2}$ times the rotor position. Using these, the initial magnetic pole position θ_{est} can be calculated from I_{upp} , I_{vpp} , and I_{wpp} . (37) However, depending on the initial magnetic pole position, not only a change in current due to saliency but also a change in current due to magnetic saturation may be included in the peak-to-peak values I_{upp} , I_{vpp} , and I_{wpp} of the phase currents. This will be described below with reference to FIG. 4.

(38) For example, as illustrated in FIG. 4, when the initial magnetic pole position is at 30 degrees in the synchronous motor **200**, an N pole of a magnet which is the rotor is located at a position close to the +u phase and the -w phase. In this state, it is assumed that the voltage commands V_u^* , V_v^* , and V_w^* illustrated in FIGS. 3(C) to 3(E) are output from the voltage pulse preparing unit **400A**, and the voltages V_u , V_v , and V_w in response to these voltage commands are applied from the power converter **300** to the synchronous motor **200**. In this case, a magnetic flux of the magnet is superimposed on a magnetic flux generated by the current in a period in which a positive voltage is applied to the u phase in a u phase application zone which is a zone having the phase command θ^* of 0 degrees and a period in which a negative voltage is applied to the w phase in a w phase application zone which is a zone having the phase command θ^* of 240 degrees. Therefore, an overdense magnetic flux occurs in a stator of the synchronous motor **200**. As a result, magnetic saturation occurs, and the inductance decreases. Hence, as represented by I_{u+} in FIG. 3(F) and I_{w-} in FIG. 3(H), each current change may be larger than that in a case where magnetic saturation does not occur.

(39) As described above, depending on the initial magnetic pole position, regarding the peak-to-peak values I_{upp} , I_{vpp} , and I_{wpp} of the phase currents, not only a change in current due to saliency but also a change in current due to magnetic saturation may occur. This causes an increase in estimation error of the initial magnetic pole position θ_{est} in the magnetic pole position estimating unit **600A**.

(40) Moreover, a surface permanent magnet synchronous motor having no saliency is often used for a permanent magnet synchronous motor used for driving a brake system of an electrified vehicle or an electric power steering device. Since the surface permanent magnet synchronous motor does not have saliency, the magnetic pole position estimating unit **600A** cannot calculate the initial magnetic pole position by using a current change due to the saliency as described above. In a case where the synchronous motor **200** is the surface permanent magnet synchronous motor, an estimation error becomes large, when the initial magnetic pole position θ_{est} is estimated from changes in the peak-to-peak values I_{upp} , I_{vpp} , and I_{wpp} of the phase currents.

(41) Therefore, in this embodiment, the quadrature component detector **630** and the second peak-to-peak detector **620** are provided in the magnetic pole position estimating unit **600A**. As will be described below, the first magnetic pole position calculating unit **640** calculates a first magnetic pole position θ_{est1} based on the peak-to-peak values I_{upp} , I_{vpp} , and I_{wpp} of the phase currents output from the first peak-to-peak detector **610** and peak-to-peak values $I_{\delta upp}$, $I_{\delta vpp}$, and $I_{\delta wpp}$ of quadrature components of the phase currents output from the second peak-to-peak detector **620**. The initial magnetic pole position θ_{est} is estimated based on the first magnetic pole position θ_{est1} obtained as described above.

(42) The quadrature component detector **630** receives, as inputs, the current values I_u , I_v , and I_w detected by the current detecting unit **500** and the phase command θ^* and detects quadrature components for the phase currents based on these values and command. Here, quadrature biaxial components I_y and I_{δ} are calculated from the current values I_u , I_v , and I_w and the phase command

θ^* according to the following expressions (4) and (5), and thereby quadrature components for the phase currents are obtained.

$$I_y = \frac{2}{3} \times \{I_u \times \cos(\theta^*) + I_v \times \cos(\theta^* - 2\pi/3) + I_w \times \cos(\theta^* - 4\pi/3)\} \quad (4)$$

$$I_\delta = -\frac{2}{3} \times \{I_u \times \sin(\theta^*) + I_v \times \sin(\theta^* - 2\pi/3) + I_w \times \sin(\theta^* - 4\pi/3)\} \quad (5)$$

(43) After calculating the quadrature biaxial components I_y and I_δ , the quadrature component detector **630** outputs I_δ of the components to the second peak-to-peak detector **620**.

(44) The second peak-to-peak detector **620** receives, as input, the quadrature components I_δ of the phase currents calculated by the quadrature component detector **630** and detects the peak-to-peak values $I_{\delta up}$, $I_{\delta vp}$, and $I_{\delta wp}$ representing differences between maximum values and minimum values of the quadrature component I_δ .

(45) The peak-to-peak value $I_{\delta up}$ is a difference between the maximum value and the minimum value of the quadrature component I_δ when the phase command θ^* indicates 0 degrees. This corresponds to a difference between a peak value $I_{\delta u+}$ of I_δ when the positive voltage is applied to the u phase with the phase command θ^* of 0 degrees and a peak value $I_{\delta u-}$ of I_δ when the negative voltage is applied to the u phase with the phase command θ^* of 0 degrees in FIG. 3(J).

(46) The peak-to-peak value $I_{\delta vp}$ is a difference between the maximum value and the minimum value of the quadrature component I_δ when the phase command θ^* indicates 120 degrees. This corresponds to a difference between a peak value $I_{\delta v+}$ of I_δ when the positive voltage is applied to the v phase with the phase command θ^* of 120 degrees and a peak value $I_{\delta v-}$ of I_δ when the negative voltage is applied to the v phase with the phase command θ^* of 120 degrees in FIG. 3(J).

(47) The peak-to-peak value $I_{\delta wp}$ is a difference between the maximum value and the minimum value of the quadrature component I_δ when the phase command θ^* indicates 240 degrees. This corresponds to a difference between a peak value $I_{\delta w+}$ of I_δ when the positive voltage is applied to the w phase with the phase command θ^* of 240 degrees and a peak value $I_{\delta w-}$ of I_δ when the negative voltage is applied to the w phase with the phase command θ^* of 240 degrees in FIG. 3(J).

(48) The first magnetic pole position calculating unit **640** receives, as inputs, the peak-to-peak values I_{up} , I_{vp} , and I_{wp} of the phase currents, which are the outputs of the first peak-to-peak detector **610**, and the peak-to-peak values $I_{\delta up}$, $I_{\delta vp}$, and $I_{\delta wp}$ of the quadrature component I_δ , which are the outputs of the second peak-to-peak detector **620**, and calculates the first magnetic pole position θ_{est1} based on these values.

(49) The peak-to-peak values $I_{\delta up}$, $I_{\delta vp}$, and $I_{\delta wp}$ of the quadrature component I_δ are components electrically orthogonal to the peak-to-peak values I_{up} , I_{vp} , and I_{wp} of the phase currents. Hence, even when the inductance of the synchronous motor **200** decreases due to the influence of the above-described magnetic saturation and the peak-to-peak values I_{up} , I_{vp} , and I_{wp} of the phase currents increase according to the decrease in inductance, magnetic saturation does not occur in these quadrature components I_δ , and thus the peak-to-peak values $I_{\delta up}$, $I_{\delta vp}$, and $I_{\delta wp}$ of I_δ decrease. On the other hand, when the peak-to-peak values $I_{\delta up}$, $I_{\delta vp}$, and $I_{\delta wp}$ of I_δ increase under the influence of magnetic saturation, the peak-to-peak values I_{up} , I_{vp} , and I_{wp} of the phase currents decrease. As described above, the peak-to-peak values I_{up} , I_{vp} , and I_{wp} of the phase currents and the peak-to-peak values $I_{\delta up}$, $I_{\delta vp}$, and $I_{\delta wp}$ of the quadrature components I_δ have characteristics that are opposite to each other.

(50) In this embodiment, the first magnetic pole position calculating unit **640** performs quadrature biaxial component averaging processing to be described below using the above characteristics, thereby, canceling changes in the peak-to-peak values I_{up} , I_{vp} , and I_{wp} of the phase currents due to the influence of magnetic saturation. As a result, only a change in current due to saliency can be extracted.

(51) In addition, when the synchronous motor **200** is the surface permanent magnet synchronous motor, since the synchronous motor **200** does not have saliency, the quadrature components I_δ are originally constant, and the peak-to-peak values $I_{\delta up}$, $I_{\delta vp}$, and $I_{\delta wp}$ of I_δ are all 0. However, when the magnetic saturation according to the initial magnetic pole position occurs in the

synchronous motor **200** as described above, the inductance in a magnetic flux direction of the permanent magnet or a direction orthogonal thereto changes, and thus, the peak-to-peak values $I_{\delta upp}$, $I_{\delta vpp}$, and $I_{\delta wpp}$ of the quadrature components I_{δ} are generated. In this embodiment, the characteristics of the peak-to-peak values $I_{\delta upp}$, $I_{\delta vpp}$, and $I_{\delta wpp}$ of the quadrature components I_{δ} can be used to estimate the initial magnetic pole position θ_{est} even when the synchronous motor **200** is the surface permanent magnet synchronous motor.

(52) FIG. **6** is a configuration diagram illustrating main functions of the first magnetic pole position calculating unit **640**. The first magnetic pole position calculating unit **640** includes a first coordinate transformation unit **641**, a second coordinate transformation unit **642**, a quadrature biaxial component averaging processing unit **643**, and a position calculating unit **644**.

(53) The first coordinate transformation unit **641** receives, as inputs, the peak-to-peak values I_{upp} , I_{vpp} , and I_{wpp} of the phase currents, which are outputs of the first peak-to-peak detector **610**, and transforms coordinate systems thereof into an $\alpha\beta$ coordinate system to output $I_{\alpha pp}$ and $I_{\beta pp}$. Here, the transformation into the $\alpha\beta$ coordinate system is performed by the following expressions (6) and (7).

$$I_{\alpha pp} = \frac{2}{3} \times \{I_{upp} - \frac{1}{2} \times I_{vpp} - \frac{1}{2} \times I_{wpp}\} \quad (6)$$

$$I_{\beta pp} = \frac{2}{3} \times \{(\sqrt{3}/2) \times (I_{vpp} - I_{wpp})\} \quad (7)$$

(54) The second coordinate transformation unit **642** receives, as inputs, the peak-to-peak values $I_{\delta upp}$, $I_{\delta vpp}$, and $I_{\delta wpp}$ of the quadrature components I_{δ} , which are outputs of the second peak-to-peak detector **620**, and transforms coordinate systems thereof into an $\alpha\beta$ coordinate system to output $I_{\delta \alpha pp}$ and $I_{\delta \beta pp}$. Here, the transformation into the $\alpha\beta$ coordinate system is performed by the following expressions (8) and (9).

$$I_{\delta \alpha pp} = \frac{2}{3} \times \{I_{\delta upp} - \frac{1}{2} \times I_{\delta vpp} - \frac{1}{2} \times I_{\delta wpp}\} \quad (8)$$

$$I_{\delta \beta pp} = \frac{2}{3} \times \{(\sqrt{3}/2) \times (I_{\delta vpp} - I_{\delta wpp})\} \quad (9)$$

(55) The quadrature biaxial component averaging processing unit **643** receives, as inputs, $I_{\alpha pp}$ and $I_{\beta pp}$ which are outputs of the first coordinate transformation unit **641** and $I_{\delta \alpha pp}$ and $I_{\delta \beta pp}$ which are outputs of the second coordinate transformation unit **642** and performs quadrature biaxial component averaging processing on these outputs to output P_{α} and P_{β} .

(56) The quadrature biaxial component averaging processing unit **643** calculates P_{α} and P_{β} , according to the following expressions (10) and (11). Here, P_{α} is obtained by dividing the sum of $I_{\alpha pp}$ and $I_{\delta \beta pp}$ by 2, and P_{β} is obtained by dividing a difference between $I_{\delta \alpha pp}$ and $I_{\beta pp}$ by 2.

$$P_{\alpha} = \frac{1}{2} \times (I_{\alpha pp} + I_{\delta \beta pp}) \quad (10)$$

$$P_{\beta} = \frac{1}{2} \times (I_{\delta \alpha pp} - I_{\beta pp}) \quad (11)$$

(57) Here, a principle of improving the estimation accuracy of the initial magnetic pole position by the quadrature biaxial component averaging processing for the interior permanent magnet synchronous motor and the surface permanent magnet synchronous motor will be described below with reference to FIG. **7**.

(58) $I_{\alpha pp}$ and $I_{\beta pp}$ which are the outputs of the first coordinate transformation unit **641**, $I_{\delta \alpha pp}$ and $I_{\delta \beta pp}$ which are the outputs of the second coordinate transformation unit **642**, and P_{α} and P_{β} , which are the outputs of the quadrature biaxial component averaging processing unit **643** change depending on the initial magnetic pole position in a certain relationship for each of combinations thereof. FIG. **7** is a diagram illustrating a track of changes of these combinations with respect to the initial magnetic pole position. In FIG. **7**, a track of $I_{\alpha pp}$ and $I_{\beta pp}$ is illustrated to have $I_{\alpha pp}$ on the horizontal axis and $-I_{\beta pp}$ on the vertical axis. In addition, a track of $I_{\delta \alpha pp}$ and $I_{\delta \beta pp}$ is illustrated to have $I_{\delta \beta pp}$ on the horizontal axis and $I_{\delta \alpha pp}$ on the vertical axis. In addition, a track of P_{α} and P_{β} , is illustrated to have P_{α} on the horizontal axis and P_{β} , on the vertical axis. However, these tracks are rotated in a cycle of $\frac{1}{2}$ times the initial magnetic pole position. Therefore, in FIG. **7**, for example, a point on the vertical axis which is a boundary between a first quadrant and a second quadrant corresponds to an initial magnetic pole position at 45 degrees or 225 degrees.

(59) Here, the initial magnetic pole position of the synchronous motor **200** corresponds to a value

obtained by inputting a horizontal axis component and a vertical axis component of each track illustrated in FIG. 7 to an arctangent function. That is, as these tracks are closer to a circular shape, the initial magnetic pole position can be obtained with higher accuracy.

(60) FIG. 7(a) illustrates an example of the track of the combinations in a case where the synchronous motor **200** is the interior permanent magnet synchronous motor. As described above, when magnetic saturation occurs in the synchronous motor **200**, the inductance decreases, and thus each phase current increases. As a result, as shown in FIG. 7(a), the track of $I_{\alpha pp}$ and $I_{\beta pp}$ is not circular and forms a shape in which the initial magnetic pole position bulges around 30 degrees, 90 degrees, 150 degrees, 210 degrees, 270 degrees, and 330 degrees. On the other hand, since the magnetic saturation does not occur in a direction orthogonal to each phase current, the track of $I_{\delta \alpha pp}$ and $I_{\delta \beta pp}$ becomes smaller than the track of $I_{\alpha pp}$ and $I_{\beta pp}$.

(61) By using this, the track of P_{α} and P_{β} corresponding to an intermediate track between the track of $I_{\alpha pp}$ and $I_{\beta pp}$ and the track of $I_{\delta \alpha pp}$ and $I_{\delta \beta pp}$ is obtained, and thereby a circular track is obtained as illustrated in FIG. 7(a). That is, even when the magnetic saturation occurs in the interior permanent magnet synchronous motor, and thus the peak-to-peak values I_{upp} , I_{vpp} , and I_{wpp} of the phase currents increase, P_{α} and P_{β} , excluding the influence of magnetic saturation can be obtained. Hence, it can be found that the initial magnetic pole position can be obtained with high accuracy based on P_{α} and P_{β} .

(62) FIG. 7(b) illustrates an example of a track of the combinations in a case where the synchronous motor **200** is the surface permanent magnet synchronous motor. In the case of the surface permanent magnet synchronous motor having no saliency, $I_{\delta \alpha pp}$ and $I_{\delta \beta pp}$ are originally zero, but $I_{\delta \alpha pp}$ and $I_{\delta \beta pp}$ are generated when the inductance changes due to the occurrence of the magnetic saturation. The track of $I_{\delta \alpha pp}$ and $I_{\delta \beta pp}$ at this time has characteristics opposite to the track of $I_{\alpha pp}$ and $I_{\beta pp}$, similarly to the case of the interior permanent magnet synchronous motor illustrated in FIG. 7(a).

(63) By using this, the track of P_{α} and P_{β} , corresponding to an intermediate track between the track of $I_{\alpha pp}$ and $I_{\beta pp}$ and the track of $I_{\delta \alpha pp}$ and $I_{\delta \beta pp}$ is obtained, and thereby a circular track is obtained as illustrated in FIG. 7(b). Consequently, it can be found that the initial magnetic pole position can be obtained with high accuracy based on P_{α} and P_{β} , even when the synchronous motor **200** does not have saliency or has minute saliency.

(64) As described above, in this embodiment, the quadrature biaxial component averaging processing unit **643** included in the first magnetic pole position calculating unit **640** calculates P_{α} and P_{β} , excluding the influence of the magnetic saturation. The position calculating unit **644** calculates the first magnetic pole position θ_{est1} using P_{α} and P_{β} . Hence, even when the synchronous motor **200** is the interior permanent magnet synchronous motor or the surface permanent magnet synchronous motor, it is possible to improve the estimation accuracy of the initial magnetic pole position.

(65) The position calculating unit **644** receives, as inputs, P_{α} and P_{β} , which are outputs of the quadrature biaxial component averaging processing unit **643**, and calculates the first magnetic pole position θ_{est1} based on P_{α} and P_{β} . The first magnetic pole position θ_{est1} is obtained according to the following expression (12).

$$\theta_{est1} = \frac{1}{2} \times \{\arctan(P_{\beta}/P_{\alpha})\} \quad (12)$$

(66) In general, it is known that a change in inductance due to the saliency in the synchronous motor **200** appears in a cycle of $\frac{1}{2}$ times a rotation angle. That is, in an estimation method using the saliency, the initial magnetic pole position can be estimated only in the range of 0 to 180 degrees, and it is not possible to determine whether polarity of a magnet of a rotor is an N pole or an S pole. Therefore, as illustrated in FIG. 5, the magnetic pole position estimating unit **600A** of this embodiment includes a polarity discriminator **650** to discriminate polarity of a magnet of a rotor.

(67) FIG. 8 is a configuration diagram illustrating main functions of the polarity discriminator **650**. The polarity discriminator **650** according to this embodiment includes a peak value detector **651**, an

absolute value calculating unit **652**, a subtraction unit **653**, a coordinate transformation unit **654**, and a polarity calculating unit **655**.

(68) The peak value detector **651** receives, as inputs, the phase currents I_u , I_v , and I_w detected by the current detecting unit **500** and detects peak values I_{u+} , I_{u-} , I_{v+} , I_{v-} , I_{w+} , and I_{w-} of the phase currents.

(69) The current peak value I_{u+} is the maximum value of the u phase current when the positive voltage is applied to the u phase with the phase command θ^* of 0 degrees in FIG. 3(F). The current peak value I_{u-} is the minimum value of the u phase current when the negative voltage is applied to the u phase with the phase command θ^* of 0 degrees in FIG. 3(F).

(70) The current peak value I_{v+} is the maximum value of the v phase current when the positive voltage is applied to the v phase with the phase command θ^* of 120 degrees in FIG. 3(G). The current peak value I_{v-} is the minimum value of the v phase current when the negative voltage is applied to the v phase with the phase command θ^* of 120 degrees in FIG. 3(G).

(71) The current peak value I_{w+} is the maximum value of the w phase current when the positive voltage is applied to the w phase with the phase command θ^* of 240 degrees in FIG. 3(H). The current peak value I_{w-} is the minimum value of the w phase current when the negative voltage is applied to the w phase with the phase command θ^* of 240 degrees in FIG. 3(H).

(72) The absolute value calculating unit **652** receives, as inputs, the current peak values I_{u+} , I_{u-} , I_{v+} , I_{v-} , I_{w+} , and I_{w-} of the phases and calculates the respective absolute values.

(73) The subtraction unit **653** calculates differences between the absolute values of the current peak values of the phases according to the following expressions (13), (14), and (15) and outputs ΔI_u , ΔI_v , and ΔI_w .

$$\Delta I_u = |I_{u+}| - |I_{u-}| \quad (13)$$

$$\Delta I_v = |I_{v+}| - |I_{v-}| \quad (14)$$

$$\Delta I_w = |I_{w+}| - |I_{w-}| \quad (15)$$

(74) Since ΔI_u , ΔI_v , and ΔI_w are the differences between the absolute values of the current values obtained when the positive voltage is applied and the current values obtained when the negative voltage is applied, ΔI_u , ΔI_v , and ΔI_w are values indicating a degree of the magnetic saturation of the synchronous motor **200**.

(75) The coordinate transformation unit **654** converts ΔI_u , ΔI_v , and ΔI_w , which are the differences between the absolute values of the current peak values of the phases, using the following expressions (16) and (17), and outputs results as $\Delta P\alpha$ and $\Delta P\beta$.

$$\Delta P\alpha = \frac{2}{3} \times \{ \Delta I_u - \frac{1}{2} \times \Delta I_v - \frac{1}{2} \times \Delta I_w \} \quad (16)$$

$$\Delta P\beta = \frac{2}{3} \times \{ (\sqrt{3}/2) \times (\Delta I_v - \Delta I_w) \} \quad (17)$$

(76) Polarity calculating unit **655** receives $\Delta P\alpha$ and $\Delta P\beta$ as inputs and discriminates whether the polarity of the magnet is the N pole or the S pole based on second magnetic pole position θ_{est2} obtained by the following expression (18).

$$\theta_{est2} = \arctan\{ \Delta P\beta / \Delta P\alpha \} \quad (18)$$

(77) Here, $\Delta P\alpha$ and $\Delta P\beta$ are values obtained from ΔI_u , ΔI_v , and ΔI_w , which are differences in absolute values of the current peak values I_{u+} , I_{u-} , I_{v+} , I_{v-} , I_{w+} , and I_{w-} of the phases. When the synchronous motor **200** is magnetically saturated, the absolute values of the current peak values in a direction in which magnetic saturation occurs increase, and thus the differences ΔI_u , ΔI_v , and ΔI_w between the absolute values of the current peak values of the phases indicate degrees of the magnetic saturation.

(78) Since the degree of the magnetic saturation does not always appear in a sinusoidal shape, the magnetic pole position can be estimated in a range of 0 to 360 degrees (that is, including the polarity of the magnet of the rotor) in both the interior permanent magnet synchronous motor and the surface permanent magnet synchronous motor although the accuracy is not high. Using this, the polarity discriminator **650** discriminates the polarity of the second magnetic pole position θ_{est2} obtained from the degree of the magnetic saturation and outputs the discrimination result as

polarity NS. For example, when θ_{est2} is within a predetermined range, the polarity is determined as the N pole, and when θ_{est2} is out of the predetermined range, the polarity is determined as the S pole. Here, the predetermined range is, for example, a range in which θ_{est2} is 0 to 180 degrees. Specifically, when θ_{est2} is 0 to 180 degrees, the polarity is determined as the N pole, and when θ_{est2} is 180 to 360 degrees, the polarity is determined as the S pole.

(79) Returning to the description of FIG. 5, the second magnetic pole position calculating unit **660** calculates a rotor position of the synchronous motor **200** based on the first magnetic pole position θ_{est1} calculated by the first magnetic pole position calculating unit **640** and the polarity NS discriminated by calculating the second magnetic pole position θ_{est2} by the polarity discriminator **650**.

(80) Although the first magnetic pole position θ_{est1} can be obtained only in the range of 0 to 180 degrees, the second magnetic pole position calculating unit **660** estimates the initial magnetic pole position θ_{est} using the polarity NS which is a discrimination result by the polarity discriminator **650**. Specifically, when the polarity discriminator **650** determines that the polarity NS is the N pole, the first magnetic pole position θ_{est1} is output as it is as the initial magnetic pole position θ_{est} . On the other hand, when the polarity discriminator **650** determines that the polarity NS is the S pole, a value obtained by adding 180 degrees to the first magnetic pole position θ_{est1} is output as the initial magnetic pole position θ_{est} .

(81) According to this embodiment, the magnetic pole position estimating unit **600A** is configured to detect the peak-to-peak values of the phase currents and the peak-to-peak values of the quadrature components of the phase currents when the positive and negative voltages are sequentially applied to the phases of the synchronous motor **200** by the voltage pulse preparing unit **400A** while the synchronous motor **200** is stopped. Accordingly, using the detected peak-to-peak values of the phase currents and the detected peak-to-peak values of the quadrature components of the phase currents, a current change caused by the magnetic saturation is eliminated, and a current change caused by the saliency is obtained. In addition, even in a case where the synchronous motor **200** is the surface permanent magnet synchronous motor, a current change is obtained by utilizing the fact that the quadrature components of the phase currents are generated by an inductance change due to the magnetic saturation. Consequently, the initial magnetic pole position of the rotor can be accurately estimated regardless of whether the synchronous motor **200** is the interior permanent magnet type or the surface permanent magnet type. Hence, in this embodiment, it is possible to estimate the initial magnetic pole position with high accuracy while having versatility to be applicable to both the interior permanent magnet synchronous motor and the surface permanent magnet synchronous motor. Therefore, sensorless control of the synchronous motor **200** can also be performed with high accuracy. For example, even in a case where the synchronous motor **200** is used as a driving motor of an electric motor vehicle, the control performance as the vehicle driving motor is improved, and a comfortable ride for an occupant can be provided. In addition, when the synchronous motor **200** is used in an auxiliary device such as an electric power steering device or an electric brake device of an electric motor vehicle, control performance of the auxiliary device is improved, and drivability can be improved.

Second Embodiment

(82) FIG. 9 is a detailed configuration diagram of a magnetic pole position estimating unit **600B** according to a second embodiment. The same reference numerals are assigned to the same portions as those of the magnetic pole position estimating unit **600A** in the first embodiment, and the description thereof will be omitted. Further, the configuration diagram of the drive apparatus **100A** of the synchronous motor **200** illustrated in FIG. 1, the detailed configuration diagram of the voltage pulse preparing unit **400A** illustrated in FIG. 2, and the diagram illustrating the relationship between the three-phase voltage commands and the three-phase currents illustrated in FIG. 3 are the same in this embodiment.

(83) In the first embodiment, only the second magnetic pole position θ_{est2} obtained from the

differences ΔI_u , ΔI_v , and ΔI_w between the absolute values of the current peak values of the phases is used in the discrimination of the polarity NS performed by the second magnetic pole position calculating unit **660**; however, in this embodiment, the polarity NS is obtained from the first magnetic pole position θ_{est1} and the second magnetic pole position θ_{est2} .

(84) In this embodiment, as illustrated in FIG. **9**, the magnetic pole position estimating unit **600B** includes a third magnetic pole position calculating unit **670** and a fourth magnetic pole position calculating unit **680** instead of the polarity discriminator **650** and the second magnetic pole position calculating unit **660**. The third magnetic pole position calculating unit **670** calculates the second magnetic pole position θ_{est2} based on the phase currents I_u , I_v , and I_w detected by the current detecting unit **500**. The fourth magnetic pole position calculating unit **680** receives, as inputs, both the second magnetic pole position θ_{est2} from the third magnetic pole position calculating unit **670** and the first magnetic pole position θ_{est1} from the first magnetic pole position calculating unit **640**. The fourth magnetic pole position calculating unit **680** calculates the initial magnetic pole position θ_{est} based on these magnetic pole positions.

(85) FIG. **10** is a configuration diagram illustrating main functions of the third magnetic pole position calculating unit **670**. The third magnetic pole position calculating unit **670** in this embodiment includes a peak value detector **671**, an absolute value calculating unit **672**, a subtraction unit **673**, a coordinate transformation **674**, and a position calculating unit **675**.

(86) The peak value detector **671**, the absolute value calculating unit **672**, the subtraction unit **673**, and the coordinate transformation **674** perform processes similar to those of the peak value detector **651**, the absolute value calculating unit **652**, the subtraction unit **653**, and the coordinate transformation unit **654** of the polarity discriminator **650** in the first embodiment, respectively.

(87) The position calculating unit **675** receives, as inputs, ΔP_α and ΔP_β , output from the coordinate transformation **674** and calculates the second magnetic pole position θ_{est2} according to the above-described expression (18). The third magnetic pole position calculating unit **670** outputs the second magnetic pole position θ_{est2} calculated by the position calculating unit **675** to the fourth magnetic pole position calculating unit **680**.

(88) FIG. **11** is a configuration diagram illustrating main functions of the fourth magnetic pole position calculating unit **680**. The fourth magnetic pole position calculating unit **680** includes a subtraction processing unit **681**, an absolute value processing unit **682**, a threshold determining unit **683**, and an initial magnetic pole position calculating unit **684**.

(89) The subtraction processing unit **681** obtains a difference between the first magnetic pole position θ_{est1} and the second magnetic pole position θ_{est2} . The absolute value processing unit **682** obtains an absolute value of the difference between the first magnetic pole position θ_{est1} and the second magnetic pole position θ_{est2} . Accordingly, the threshold determining unit **683** determines the polarity as the S pole when the absolute value of the difference between the first magnetic pole position θ_{est1} and the second magnetic pole position θ_{est2} is within a predetermined range and determines the polarity as the N pole when the absolute value is out of the predetermined range. Here, the predetermined range may be set reflecting an error of the second magnetic pole position θ_{est2} and is, for example, a range in which the absolute value of the difference between the first magnetic pole position θ_{est1} and the second magnetic pole position θ_{est2} is 90 to 270 degrees.

(90) When the threshold determining unit **683** determines that the polarity is the S pole, the initial magnetic pole position calculating unit **684** outputs a value obtained by adding 180 degrees to the first magnetic pole position θ_{est1} as the initial magnetic pole position θ_{est} , and when the threshold determining unit **683** determines that the polarity is the N pole, the initial magnetic pole position calculating unit **684** outputs the first magnetic pole position θ_{est1} as the initial magnetic pole position θ_{est} .

(91) Here, as described in the first embodiment, when the polarity NS is discriminated only from the second magnetic pole position θ_{est2} , the polarity NS may be erroneously determined because the accuracy of the second magnetic pole position θ_{est2} is low. For example, when the polarity NS

is determined as the N pole when the second magnetic pole position θ_{est2} is 0 to 180 degrees, and the polarity NS is determined as the S pole when the second magnetic pole position θ_{est2} is 180 to 360 degrees, the polarity may be wrong when the initial magnetic pole position θ_{est} is around 180 degrees or 360 degrees, since there is an error between the actual initial magnetic pole position and the second magnetic pole position θ_{est2} .

(92) On the other hand, as described in this embodiment, by discriminating the polarity NS from the first magnetic pole position θ_{est1} and the second magnetic pole position θ_{est2} , the error in the second magnetic pole position θ_{est2} can be reflected, so that the initial magnetic pole position θ_{est} of the rotor can be estimated without making an error in the polarity NS.

(93) Since the discrimination of the polarity NS described in this embodiment is preferable in that the polarity can be determined during the application of the voltage pulse illustrated in FIG. 3, and thus it is possible to minimize the time required for estimating the initial magnetic pole position θ_{est} . However, it is needless to say that the polarity may be determined using a generally known method after the first magnetic pole position θ_{est1} is calculated.

Third Embodiment

(94) FIG. 12 is a configuration diagram of a drive apparatus **100B** according to a third embodiment. The drive apparatus **100B** of this embodiment performs pulse voltage application in which the power converter **300** sequentially applies positive and negative pulse voltages to phases of the synchronous motor **200**, a plurality of times with pulse widths different from each other while the synchronous motor **200** is stopped. Further, the same reference numerals are assigned to the same portions as those in the configuration diagram of the drive apparatus **100A** according to the first and second embodiments illustrated in FIG. 1, and the description thereof will be omitted.

(95) In the first and second embodiments, the phase switch **420** in the voltage pulse preparing unit **400A** prepares the phase command θ^* for converting the d-axis voltage command V_d^* and the q-axis voltage command V_q^* prepared by the voltage command preparing unit **410** into three-phase voltage commands. Specifically, 0 degrees (0 radians), 120 degrees ($\frac{2}{3}\pi$ radians), and 240 degrees ($\frac{4}{3}\pi$ radians) are sequentially output as the phase commands θ^* for estimating the initial magnetic pole position θ_{est} while the synchronous motor **200** is stopped. On the other hand, in this embodiment, as illustrated in FIG. 12, the drive apparatus **100B** includes a voltage pulse preparing unit **400B** instead of the voltage pulse preparing unit **400A**. The voltage pulse preparing unit **400B** generates and outputs the phase command θ^* so that the power converter **300** can apply a pulse voltage to the synchronous motor **200** a plurality of times with pulse widths different from each other while the synchronous motor **200** is stopped.

(96) The phase command θ^* output from the voltage pulse preparing unit **400B** is input to the magnetic pole position estimating unit **600A** described in the first embodiment or the magnetic pole position estimating unit **600B** described in the second embodiment. Further, in this embodiment, the initial magnetic pole position θ_{est} may be estimated using any of the magnetic pole position estimating units **600A** and **600B**.

(97) FIG. 13 is a detailed configuration diagram of the voltage pulse preparing unit **400B** according to the third embodiment. The voltage pulse preparing unit **400B** includes a voltage command preparing unit **410**, a phase switch **420**, a command coordinate transformation unit **430**, and a pulse width/repetition number setting unit **440**. Further, the voltage command preparing unit **410**, the phase switch **420**, and the command coordinate transformation unit **430** are the same as those included in the voltage pulse preparing unit **400A** in the first embodiment.

(98) In the drive apparatus **100B** of this embodiment, the initial magnetic pole position θ_{est} is estimated by repeatedly executing a series of operations described in the first or second embodiment in the magnetic pole position estimating unit **600A** or **600B**. In the voltage pulse preparing unit **400B** of this embodiment, the pulse width/repetition number setting unit **440** outputs the number of repetitions N_{max} of a series of operations performed by the magnetic pole position estimating unit **600A** or **600B** and a pulse width D_n of the d-axis voltage command V_d^* output

from the voltage command preparing unit **410** with respect to an n-th operation. Here, n is a natural number of 1 or more and Nmax or less. Further, the values of Nmax and Dn may be set in advance in the pulse width/repetition number setting unit **440** or may be optionally designated by the user.

(99) Operations of the drive apparatus **100B** in the third embodiment will be described with reference to FIG. **14**. FIG. **14** is a diagram illustrating a relationship between a phase command θ^* , a voltage command, and a current flowing to the synchronous motor **200** in the third embodiment. FIG. **14** illustrates an example of the phase command θ^* , the voltage command, and the current in a case where the number of repetitions Nmax output from the pulse width/repetition number setting unit **440** is 2. Further, FIGS. **14(A)** to **14(J)** illustrate the same as FIGS. **3 (A)** to **3 (J)**, respectively.

(100) In the case of FIG. **14**, since Nmax=2, the magnetic pole position estimating unit **600A** or **600B** performs a series of operations of the initial magnetic pole position estimation described in the first or second embodiment twice. In this case, the pulse width/repetition number setting unit **440** sets a pulse width of the d-axis voltage command V_d^* for the first operation (referred to as a first sequence) to D1. On the other hand, for the second operation (referred to as a second sequence), unlike the first sequence, a pulse width of the d-axis voltage command V_d^* is set to D2.

(101) In the voltage pulse preparing unit **400B** of this embodiment, the voltage command preparing unit **410** prepares the d-axis voltage command V_d^* according to the pulse widths in the first sequence and the second sequence as illustrated in FIG. **14(B)** based on the pulse widths D1 and D2 output from the pulse width/repetition number setting unit **440**. Consequently, as illustrated in FIGS. **14(C)** to **14(E)**, three-phase voltage commands V_u^* , V_v^* , and V_w^* to alternate positive and negative voltages with the pulse width D1 in the first sequence and the pulse width D2 in the second sequence are sequentially output from the command coordinate transformation unit **430**.

(102) In this embodiment, as illustrated in FIGS. **14(F)** to **14(H)**, in the first sequence and the second sequence, the three-phase currents I_u , I_v , and I_w according to the pulse widths D1 and D2 set for the first sequence and the second sequence, respectively, flow to the synchronous motor **200**. In addition, as illustrated in FIGS. **14(I)** to **14(J)**, in the first sequence and the second sequence, quadrature components I_γ and I_δ of the three-phase currents according to the pulse widths D1 and D2 set for the first sequence and the second sequence, respectively, flow to the synchronous motor **200**.

(103) As described in the first embodiment, in the case of the interior permanent magnet synchronous motor, in the peak-to-peak values $I_{u\text{pp}}$, $I_{v\text{pp}}$, and $I_{w\text{pp}}$ of the phase currents, not only a current change due to the saliency but also a current change due to the magnetic saturation occur, and these current changes become error factors in the initial magnetic pole position. In the first and second embodiments, the estimation accuracy of the initial magnetic pole position θ_{est} is improved by using the peak-to-peak values $I_{\delta\text{pp}}$, $I_{\delta v\text{pp}}$, and $I_{\delta w\text{pp}}$ of the quadrature components I_δ with respect to these error factors. However, even when a method for estimating the initial magnetic pole position θ_{est} by using the quadrature components of the phase currents is employed as described above, the influence of the magnetic saturation may not be completely eliminated depending on the structure of the synchronous motor **200**, variations in the semiconductor elements constituting the power converter **300**, and the like.

(104) In this respect, in the drive apparatus **100B** of this embodiment, by providing the pulse width/repetition number setting unit **440** in the voltage pulse preparing unit **400B**, the power converter **300** sequentially applies positive and negative pulse voltages to the phases of the synchronous motor **200** with the pulse widths D1 and D2 different from each other while the synchronous motor **200** is stopped. Accordingly, the magnetic pole position estimating unit **600A** or **600B** estimates the initial magnetic pole position θ_{est} based on the peak values I_{u+} , I_{u-} , I_{v+} , I_{v-} , I_{w+} , and I_{w-} of the phase currents detected with respect to the application of the respective pulse voltages.

(105) Specifically, with respect to the pulse voltage application performed with the pulse width D1 in the first sequence, the magnetic pole position estimating unit **600A** or **600B** calculates the first

magnetic pole position θ_{est1} by the first magnetic pole position calculating unit **640**, based on the peak-to-peak values I_{upp} , I_{vpp} , and I_{wpp} of the phase currents I_u , I_v , and I_w obtained by the first peak-to-peak detector **610** and the peak-to-peak values $I_{\delta upp}$, $I_{\delta vpp}$, and $I_{\delta wpp}$ of the quadrature components I_{δ} of the phase currents obtained by the second peak-to-peak detector **620**. In addition, the polarity discriminator **650** or the fourth magnetic pole position calculating unit **680** discriminates whether the polarity of the magnet of the rotor is the N pole or the S pole by obtaining the second magnetic pole position θ_{est2} according to the above-described expression (18) with respect to the pulse voltage application performed with the pulse width **D2** in the second sequence. The initial magnetic pole position θ_{est} can be estimated based on the first magnetic pole position θ_{est1} and the polarity discrimination result obtained as described above.

(106) In this case, the pulse width **D1** of the first sequence is made short to the extent that, for example, the magnetic saturation does not occur, and the influence of the magnetic saturation is made as small as possible in advance, so that it can be difficult to have the influence of the magnetic saturation. However, since the magnetic saturation does not occur, there is a risk of erroneous polarity discrimination. Therefore, in the second sequence, the pulse width **D2** is made larger than **D1** to generate magnetic saturation, and polarity discrimination is made reliable. Then, the initial magnetic pole position θ_{est} can be obtained with high accuracy by obtaining the initial magnetic pole position θ_{est} by using the first magnetic pole position θ_{est1} obtained in the first sequence and the polarity obtained in the second sequence.

(107) In this embodiment, as described above, the pulse width/repetition number setting unit **440** provided in the voltage pulse preparing unit **400B** enables the estimation accuracy of the initial magnetic pole position θ_{est} to be further improved.

(108) Further, in the drive apparatus **100B** of this embodiment, the number of repetitions N_{max} set by the pulse width/repetition number setting unit **440** of the voltage pulse preparing unit **400B** may be set to 2 or more, and the final estimation result of the initial magnetic pole position θ_{est} may be determined from the value of the initial magnetic pole positions θ_{est} estimated in the respective sequences by the magnetic pole position estimating unit **600A** or **600B**. Specifically, by storing the initial magnetic pole positions θ_{est} in the respective sequences in the magnetic pole position estimating unit **600A** or **600B**, a plurality of initial magnetic pole positions θ_{est} according to the number of repetitions N_{max} are acquired. Then, by performing predetermined statistical processing such as averaging processing or convergence calculation on the plurality of acquired initial magnetic pole positions θ_{est} , it is possible to obtain a final estimation result of the initial magnetic pole position θ_{est} . Besides this, various applications are possible.

Fourth Embodiment

(109) FIG. **15** is a configuration diagram of a drive apparatus **100C** according to a fourth embodiment. The drive apparatus **100C** of this embodiment includes a position sensor **210** that detects a magnetic pole position of the synchronous motor **200**, and the drive apparatus determines presence or absence of an anomaly of the position sensor **210** by comparing the initial magnetic pole position θ_{est} estimated while the synchronous motor **200** is stopped with a magnetic pole position detected by the position sensor **210**. Further, the same reference numerals are assigned to the same portions as those in the configuration diagram of the drive apparatus **100A** according to the first and second embodiments illustrated in FIG. **1** and the same portions as those in the configuration diagram of the drive apparatus **100B** according to the third embodiment illustrated in FIG. **12**, and the description thereof will be omitted.

(110) In this embodiment, the synchronous motor **200** includes the position sensor **210** that detects the magnetic pole position of the synchronous motor **200**. The magnetic pole position detected by the position sensor **210** is input to one of comparison units **700**. The initial magnetic pole position θ_{est} estimated by the magnetic pole position estimating unit **600A** described in the first embodiment or the magnetic pole position estimating unit **600B** described in the second embodiment is input to the other of the comparison units **700**. The magnetic pole position

estimating unit **600A** or **600B** estimates the initial magnetic pole position θ_{est} using the phase command θ^* output from the voltage pulse preparing unit **400A** described in the first embodiment or the voltage pulse preparing unit **400B** described in the third embodiment. Further, in this embodiment, the initial magnetic pole position θ_{est} may be estimated using any of the magnetic pole position estimating units **600A** and **600B**. The comparison units **700** compare the initial magnetic pole positions θ_{est} estimated while the synchronous motor **200** is stopped with the magnetic pole position detected by the position sensor **210** and determines the presence or absence of the anomaly of the position sensor **210** based on the comparison result.

(111) The position sensor **210** such as a resolver may malfunction due to disconnection or short circuit of an output winding thereof. When the synchronous motor **200** is rotating, the malfunction can be detected, but it is difficult to detect the malfunction while the synchronous motor **200** is stopped. Since the magnetic pole position estimating units **600A** and **600B** described in the first and second embodiments, respectively, can estimate the initial magnetic pole positions θ_{est} while the synchronous motor **200** is stopped, it is possible to detect the malfunction of the position sensor **210** even when the synchronous motor **200** is stopped. Consequently, it is possible to provide the drive apparatus **100C** of the synchronous motor **200** with higher reliability.

(112) In the first to fourth embodiments, the voltage pulse preparing units **400A** and **400B**, the magnetic pole position estimating units **600A** and **600B**, the comparison units **700**, and the like have been described as hardware, but the functions thereof may be realized by a computer and a program. Accordingly, the program can be processed by a computer including a CPU, a memory, and the like. All or part of the processing may be realized by a hard logic circuit. Moreover, the program may be supplied as various forms of computer readable computer program products such as a storage medium and a data signal (carrier wave).

(113) According to the embodiments described above, the following operational effects can be obtained.

(114) (1) The drive apparatus **100A**, **100B**, or **100C** of the synchronous motor **200** includes the power converter **300** that drives the synchronous motor **200** by sequentially applying positive and negative voltages to phases of the synchronous motor **200**, the current detecting unit **500** that detects phase currents flowing to the synchronous motor **200**, and the magnetic pole position estimating unit **600A** or **600B** that estimates the magnetic pole position of the rotor of the synchronous motor **200**, based on the phase currents detected by the current detecting unit **500**. The magnetic pole position estimating unit **600A** or **600B** includes the first peak-to-peak detector **610** that detects the first peak-to-peak values I_{upp} , I_{vpp} , and I_{wpp} representing differences between maximum values and minimum values of the phase currents, the quadrature component detector **630** that detects quadrature components I_δ with respect to the phase currents, and the second peak-to-peak detector **620** that detects second peak-to-peak values $I_{\delta upp}$, $I_{\delta vpp}$, and $I_{\delta wpp}$ representing differences between maximum values and minimum values of the quadrature components I_δ . Accordingly, the magnetic pole position estimating unit **600A** or **600B** calculates the first magnetic pole position θ_{est1} by the first magnetic pole position calculating unit **640**, based on the first peak-to-peak values I_{upp} , I_{vpp} , and I_{wpp} detected by the first peak-to-peak detector **610** and the second peak-to-peak values $I_{\delta upp}$, $I_{\delta vpp}$, and $I_{\delta wpp}$ detected by the second peak-to-peak detector **620** while the synchronous motor **200** is stopped, and estimates the initial magnetic pole position θ_{est} of the rotor by the second magnetic pole position calculating unit **660** or the fourth magnetic pole position calculating unit **680**, based on the first magnetic pole position θ_{est1} . With this configuration, even when the synchronous motor **200** is either the interior permanent magnet synchronous motor or the surface permanent magnet synchronous motor, the initial magnetic pole position θ_{est} of the rotor of the synchronous motor **200** can be estimated with high accuracy while the synchronous motor **200** is stopped.

(115) (2) The magnetic pole position estimating unit **600A** further includes the polarity discriminator **650** configured to discriminate the polarity NS of the magnet of the rotor and

estimates the initial magnetic pole position θ_{est} by the second magnetic pole position calculating unit **660**, based on the polarity NS discriminated by the polarity discriminator **650** and the first magnetic pole position θ_{est1} . With this configuration, the initial magnetic pole position θ_{est} can be accurately estimated from the first magnetic pole position θ_{est1} obtained by using the change in inductance due to the saliency that appears at a cycle of $\frac{1}{2}$ times the rotation angle.

(116) (3) The polarity discriminator **650** discriminates the polarity NS, based on the subtraction values ΔI_u , ΔI_v , and ΔI_w of the respective absolute values of the maximum values and the minimum values of the phase currents. With this configuration, the polarity NS can be accurately discriminated from the degree of the magnetic saturation of the synchronous motor **200**.

(117) (4) The magnetic pole position estimating unit **600B** calculates the second magnetic pole position θ_{est2} by the third magnetic pole position calculating unit **670** from the subtraction values ΔI_u , ΔI_v , and ΔI_w of the respective absolute values of the maximum values and the minimum values of the phase currents while the synchronous motor **200** is stopped, discriminates the polarity of the magnet of the rotor by the fourth magnetic pole position calculating unit **680** from the first magnetic pole position θ_{est1} and the second magnetic pole position θ_{est2} , and estimates the initial magnetic pole position θ_{est} of the rotor, based on the discriminated polarity and the first magnetic pole position θ_{est1} . With this configuration, the initial magnetic pole position θ_{est} can be estimated with high accuracy while minimizing the time required to estimate the initial magnetic pole position θ_{est} .

(118) (5) In the drive apparatus **100B**, the power converter **300** performs pulse voltage application a plurality of times with pulse widths different from each other to sequentially apply positive and negative pulse voltages to the phases of the synchronous motor **200** in response to the voltage commands V_u^* , V_v^* , and V_w^* output from the voltage pulse preparing unit **400B**, while the synchronous motor **200** is stopped. The magnetic pole position estimating unit **600A** or **600B** estimates the initial magnetic pole position θ_{est} , based on the maximum values and the minimum values of the phase currents detected for each of the plurality of times of the pulse voltage application performed by the power converter **300**. Specifically, the magnetic pole position estimating unit **600A** or **600B** calculates the first magnetic pole position θ_{est1} , based on the first peak-to-peak values I_{uppp} , I_{vpp} , and I_{wpp} based on the maximum values and the minimum values of the phase currents detected with respect to the pulse voltage application performed with the first pulse width **D1** and the second peak-to-peak values $I_{\delta uppp}$, $I_{\delta vpp}$, and $I_{\delta wpp}$ based on the maximum values and the minimum values of the quadrature components of the phase currents. In addition, the magnetic pole position estimating unit **600A** or **600B** discriminates the polarity NS of the magnet of the rotor, based on the subtraction values ΔI_u , ΔI_v , and ΔI_w of the absolute values of the maximum values and the minimum values of the phase currents detected with respect to the pulse voltage application performed with the second pulse width **D2** larger than the first pulse width **D1**. The initial magnetic pole position θ_{est} is estimated based on the calculation result of the first magnetic pole position θ_{est1} and the discrimination result of the polarity NS obtained as described above. The magnetic pole position estimating unit **600A** or **600B** acquires the plurality of initial magnetic pole positions θ_{est} by estimating the initial magnetic pole positions θ_{est} for a plurality of times of the pulse voltage application, respectively, and determines the estimation results of the initial magnetic pole positions θ_{est} , based on the plurality of acquired initial magnetic pole positions θ_{est} . With this configuration, the estimation accuracy of the initial magnetic pole position θ_{est} can be further improved.

(119) (6) In the drive apparatus **100C**, the synchronous motor **200** includes the position sensor **210** that detects the magnetic pole position of the synchronous motor **200**. In addition, the drive apparatus **100C** of the synchronous motor **200** includes the comparison units **700** that compare the initial magnetic pole position θ_{est} obtained by the magnetic pole position estimating unit **600A** or **600B** with the magnetic pole position obtained by the position sensor **210**. The comparison unit **700** determines presence or absence of an anomaly of the position sensor **210**, based on the

comparison result obtained by the comparison unit **700** while the synchronous motor **200** is stopped. With this configuration, it is possible to detect the malfunction of the position sensor **210**, even when the synchronous motor **200** is stopped, and to provide a more reliable drive apparatus of the synchronous motor **200**.

(120) (7) The method for driving the synchronous motor **200** is the method for driving the synchronous motor **200** in the drive apparatus **100A**, **100B**, or **100C** of the synchronous motor **200** including the power converter **300** that drives the synchronous motor **200** by sequentially applying positive and negative voltages to the phases of the synchronous motor **200**, and the current detecting unit **500** that detects the phase currents flowing to the synchronous motor **200**. The method for driving the synchronous motor **200** includes acquiring the first peak-to-peak values I_{lpp} , I_{vpp} , and I_{wpp} representing differences between the maximum values and the minimum values of the phase currents detected by the current detecting unit **500** and the second peak-to-peak values $I_{\delta lpp}$, $I_{\delta vpp}$, and $I_{\delta wpp}$ representing differences between the maximum values and the minimum values of the quadrature components of the phase currents while the synchronous motor **200** is stopped, calculating the first magnetic pole position θ_{est1} based on the acquired first peak-to-peak values I_{lpp} , I_{vpp} , and I_{wpp} and the acquired second peak-to-peak values $I_{\delta lpp}$, $I_{\delta vpp}$, and $I_{\delta wpp}$, and estimating the initial magnetic pole position θ_{est} of the rotor of the synchronous motor **200** based on the calculated first magnetic pole position θ_{est1} . Consequently, even when the synchronous motor **200** is either the interior permanent magnet synchronous motor or the surface permanent magnet synchronous motor, the initial magnetic pole position θ_{est} of the rotor of the synchronous motor **200** can be estimated with high accuracy while the synchronous motor **200** is stopped.

(121) The present invention is not limited to the above-described embodiments, and other forms conceivable within the scope of the technical idea of the present invention are also included within the scope of the present invention as long as the features of the present invention are not impaired. In addition, a part of the configuration of a certain embodiment may be replaced with a configuration of another embodiment, or the configuration of the other embodiment may be added to the configuration of a certain embodiment.

REFERENCE SIGNS LIST

(122) **100A**, **100B**, **100C** . . . drive apparatus **200** synchronous motor **210** position sensor **300** power converter **400A**, **400B** voltage pulse preparing unit **410** voltage command preparing unit **420** phase switch **430** command coordinate transformation unit **440** pulse width/repetition number setting unit **500** current detecting unit **600A**, **600B** magnetic pole position estimating unit **610** first peak-to-peak detector **620** second peak-to-peak detector **630** quadrature component detector **640** first magnetic pole position calculating unit **650** polarity discriminator **651** peak value detector **652** absolute value calculating unit **653** subtraction unit **654** coordinate transformation unit **655** polarity calculating unit **660** second magnetic pole position calculating unit **670** third magnetic pole position calculating unit **671** peak value detector **672** absolute value calculating unit **673** subtraction unit **674** coordinate transformation **675** position calculating unit **680** fourth magnetic pole position calculating unit **681** subtraction processing unit **682** absolute value processing unit **683** threshold determining unit **684** initial magnetic pole position calculating unit **700** comparison unit

Claims

1. A drive apparatus of a synchronous motor comprising: a power converter that drives the synchronous motor by sequentially applying positive and negative voltages to phases of the synchronous motor; a current detecting unit that detects a phase current flowing to the synchronous motor; and a magnetic pole position estimating unit that estimates a magnetic pole position of a rotor of the synchronous motor, based on the phase current detected by the current detecting unit,

wherein the magnetic pole position estimating unit includes a first peak-to-peak detector that detects a first peak-to-peak value representing a difference between a maximum value and a minimum value of the phase current, a quadrature component detector that detects a quadrature component of the phase current, and a second peak-to-peak detector that detects a second peak-to-peak value representing a difference between a maximum value and a minimum value of the quadrature component, wherein the magnetic pole position estimating unit calculates a first magnetic pole position, based on the first peak-to-peak value detected by the first peak-to-peak detector and the second peak-to-peak value detected by the second peak-to-peak detector while the synchronous motor is stopped, and wherein the magnetic pole position estimating unit estimates an initial magnetic pole position of the rotor, based on the first magnetic pole position.

2. The drive apparatus of the synchronous motor according to claim 1, wherein the magnetic pole position estimating unit further includes a polarity discriminator configured to discriminate a polarity of a magnet of the rotor and estimates the initial magnetic pole position, based on the polarity discriminated by the polarity discriminator and the first magnetic pole position.

3. The drive apparatus of the synchronous motor according to claim 2, wherein the polarity discriminator discriminates the polarity, based on a subtraction value of respective absolute values of the maximum value and the minimum value of the phase current.

4. The drive apparatus of the synchronous motor according to claim 1, wherein the magnetic pole position estimating unit calculates a second magnetic pole position from a subtraction value of respective absolute values of the maximum value and the minimum value of the phase current while the synchronous motor is stopped, discriminates a polarity of a magnet of the rotor from the first magnetic pole position and the second magnetic pole position, and estimates an initial magnetic pole position of the rotor, based on the discriminated polarity and the first magnetic pole position.

5. The drive apparatus of the synchronous motor according to claim 1, wherein the power converter performs pulse voltage application a plurality of times with pulse widths different from each other to sequentially apply positive and negative pulse voltages to the phases of the synchronous motor, while the synchronous motor is stopped, and wherein the magnetic pole position estimating unit estimates the initial magnetic pole position, based on the maximum value and the minimum value of the phase current detected for each of the plurality of times of the pulse voltage application performed by the power converter.

6. The drive apparatus of the synchronous motor according to claim 5, wherein the magnetic pole position estimating unit performs calculation of the first magnetic pole position, based on the first peak-to-peak value based on the maximum value and the minimum value of the phase current detected with respect to the pulse voltage application performed with a first pulse width and the second peak-to-peak value based on the maximum value and the minimum value of the quadrature component of the phase current, discrimination of the polarity of the magnet of the rotor, based on a subtraction value of respective absolute values of the maximum value and the minimum value of the phase current detected with respect to the pulse voltage application performed with a second pulse width larger than the first pulse width, and estimation of the initial magnetic pole position, based on a calculation result of the first magnetic pole position and a discrimination result of the polarity.

7. The drive apparatus of the synchronous motor according to claim 5, wherein the magnetic pole position estimating unit acquires a plurality of the initial magnetic pole positions by estimating the initial magnetic pole positions for a plurality of times of the pulse voltage application, respectively, and determines estimation results of the initial magnetic pole positions, based on the plurality of acquired initial magnetic pole positions.

8. The drive apparatus of the synchronous motor according to claim 1, wherein the synchronous motor includes a position sensor that detects a magnetic pole position of the synchronous motor, and wherein the drive apparatus of the synchronous motor includes a comparison unit that

compares the initial magnetic pole position obtained by the magnetic pole position estimating unit with the magnetic pole position obtained by the position sensor, and wherein the comparison unit determines presence or absence of an anomaly of the position sensor, based on a comparison result obtained by the comparison unit while the synchronous motor is stopped.

9. A method for driving a synchronous motor in a drive apparatus of a synchronous motor which includes a power converter that drives a synchronous motor by sequentially applying positive and negative voltages to phases of the synchronous motor and a current detecting unit that detects a phase current flowing to the synchronous motor, the method comprising: acquiring a first peak-to-peak value representing a difference between a maximum value and a minimum value of the phase current detected by the current detecting unit and a second peak-to-peak value representing a difference between a maximum value and a minimum value of a quadrature component of the phase current while the synchronous motor is stopped; calculating a first magnetic pole position based on the first peak-to-peak value and the second peak-to-peak value; and estimating an initial magnetic pole position of a rotor of the synchronous motor based on the first magnetic pole position.
