

US Patent & Trademark Office

Patent Public Search | Text View

United States Patent Application Publication

20250285578

Kind Code

A1

Publication Date

September 11, 2025

Inventor(s)

Jiao; Shengzhe et al.

Systems and Methods for Mitigating Micro-LED Failures

Abstract

A display system may include a plurality of light emitting diodes to emit light, where each of the light emitting diodes are connected in parallel and a plurality of first switches respectively coupled to the plurality of light emitting diodes. A first switch of the plurality of first switches is coupled in parallel to a first light emitting diode. The first switch may short the first light emitting diode of the plurality of light emitting diodes through a defined resistor having a defined value that therefore draws a defined short circuit current.

Inventors: Jiao; Shengzhe (San Diego, CA), Chaturbhuji; Arjunsimha (San Jose, CA), Chen; Chen (San Jose, CA), Shaeffer; Derek K (Redwood City, CA), Kwon; Dongwon (Cupertino, CA), Yu; Feng (Sunnyvale, CA), Zhou; Haojiang (San Jose, CA), Paudel; Hari P (Milpitas, CA), Jen; Henry C (Los Altos, CA), Bae; Hopil (Palo Alto, CA), Liu; Jialin (Cupertino, CA), Zhang; Ling (Saratoga, CA), Gharghi; Majid (San Carlos, CA), Acharya; Nikhil (Mountain View, CA), Moreno Galbis; Pablo (Burlingame, CA), Zhang; Ruofan (San Jose, CA), Wang; Stanley B (Cupertino, CA), Jang; Sunmin (Sunnyvale, CA), Yao; Wei H (Saratoga, CA), Xiong; Wei (Mountain View, CA), Li; Xia (San Jose, CA), Lu; Xiang (Saratoga, CA), Jiang; Yongjie (Santa Clara, CA)

Applicant: Apple Inc. (Cupertino, CA)

Family ID: 96949678

Appl. No.: 18/677639

Filed: May 29, 2024

Related U.S. Application Data

us-provisional-application US 63562038 20240306

Publication Classification

Int. Cl.: **G09G3/32** (20160101); **H05B47/17** (20200101); **H05B47/29** (20200101)

U.S. Cl.:

CPC **G09G3/32** (20130101); **H05B47/172** (20240101); **H05B47/29** (20200101);
G09G2320/0276 (20130101); G09G2320/0646 (20130101); G09G2330/10 (20130101);
G09G2330/12 (20130101)

Background/Summary

CROSS-REFERENCE TO RELATED APPLICATIONS [0001] This application claims priority to U.S. Provisional Application No. 63/562,038, filed Mar. 6, 2024, which is incorporated by reference herein in its entirety.

SUMMARY

[0002] The present disclosure relates generally to systems and devices for identifying and/or mitigating light emitting diodes (LEDs) that are operating unexpectedly in a display panel.

[0003] A summary of certain embodiments disclosed herein is set forth below. It should be understood that these aspects are presented merely to provide the reader with a brief summary of these certain embodiments and that these aspects are not intended to limit the scope of this disclosure. Indeed, this disclosure may encompass a variety of aspects that may not be set forth below.

[0004] Electronic displays may display images that present visual representations of information. Accordingly, numerous electronic systems—such as computers, mobile phones, portable media devices, tablets, televisions, virtual-reality headsets, and vehicle dashboards, among many others—often include or use electronic displays. In any case, an electronic display may generally display an image by actively controlling light emission from its display pixels. By adjusting the brightness of different color components of the display pixels, a variety of different colors may be generated that collectively produce a corresponding image.

[0005] The electronic display may take a variety of forms. For example, the electronic display may be a digital display such as a micro-light-emitting diode (LED) display. A micro-LED display includes active matrixes of micro-LEDs driven by pixel drivers (e.g., often referred to as micro-drivers). Each micro-driver may drive a number of display pixels on the electronic display. For example, each micro-driver may be connected to numerous anodes, and each anode may selectively connect to multiple different display pixels (one at a time). The display pixels may be connected in parallel on a respective anode. Thus, a collection of display pixels may share a common anode connected to a micro-driver. The micro-driver may drive a display pixel by providing a driving signal across the respective anode to one display pixel of the collection of display pixels.

[0006] The anode may attach to multiple micro-LEDs coupled in parallel that may be driven to emit light by the micro-driver. For example, the micro-driver may drive the micro-LEDs, usually one at a time, to emit light by providing a current and selecting one of the micro-LEDs to couple to a particular voltage. The micro-LEDs may correspond to the collection of display pixels described above. In some cases, a micro-LED of the anode may fail (e.g., malfunction, be defective). The failed micro-LED may continue to draw current from the micro-driver even when the failed micro-LED has not been selected. By drawing current away from a selected micro-LED, the failed micro-LED may cause the other micro-LED to emit the wrong amount of light (e.g., have a lower luminance). As a result, the micro-LEDs located along the same anode that includes the failed

micro-LED may have a perceivable visual image artifact. For example, a corresponding column of display pixels may appear darker than intended (e.g., in comparison to target luminance levels in image data, in comparison to surrounding luminance levels in one frame of image content) in the image content.

[0007] To reduce or eliminate these perceivable visual image artifacts, the failed micro-LED may be detected using a sensing scheme and the resulting current loss may be mitigated (e.g., compensated) using a compensation scheme (e.g., mitigation scheme). The failed micro-LED may be detected using sensing circuitry during manufacturing and/or in the field. The sensing circuitry that may be shared with (e.g., integrated with) other sensors, such as a touch sensor. For example, sensing circuitry may cause a first switch to open to stop current flow from the micro-driver and cause a second switch to close to provide a bias voltage to drive a respective micro-LED for testing. If the micro-LED is partially short-circuited, then the sensing circuitry may determine that the micro-LED may be malfunctioning. In other words, if the current flows across the micro-LED due to forward-biasing the micro-LED, then the micro-LED may be determined to be malfunctioning (e.g., failed). If the micro-LED does not return a current, then the sensing circuitry may determine that the micro-LED is operative (e.g., functional). The sensing circuitry may individually test the micro-LEDs along a respective anode to identify micro-LEDs that may be malfunctioning or otherwise not operating not as expected. Additionally or alternatively, the micro-LEDs may be tested by driving each micro-LED with a test current to determine if the micro-LED emits a particular brightness during manufacturing. As such, malfunctioning micro-LEDs may be identified during manufacturing and/or in the field.

[0008] If a failed micro-LED is identified, a switch coupled to the failed micro-LED may close to cause current to be shunted around the failed micro-LED. The switch may include defined resistor having a defined value that therefore draws a defined short circuit current. As such, perceivable visual image artifacts caused by the failed micro-LED may be reduced or eliminated. In certain instances, a cathode coupled to the failed micro-LED may be pre-charged and floated to mitigate the failed micro-LED. Additionally or alternatively, image data for micro-LEDs proximate the failed micro-LED (disposed on the same anode, disposed on neighboring anodes, disposed on the same cathode, disposed on neighboring cathodes) may be compensated accordingly. For example, a gain mask may be applied to image data for surrounding micro-LEDs (e.g., display pixels) of the failed micro-LED to adjust the image data, thereby reducing or eliminating the perceivable visual image artifact caused by the failed micro-LED. Additionally or alternatively, the image data for the failed micro-LED may be set to a gray level 0 (e.g., black) to reduce current stress and/or voltage stress on the failed micro-LED, which may reduce or eliminate additional degradation to the failed micro-LED. In another example, the gray level originally intended for the failed micro-LED may be distributed to other micro-LEDs along the anode and/or neighboring micro-LEDs on different anodes and/or different cathodes, which may reduce or eliminate perceivable image artifacts caused by the failed micro-LED. As such, the failed micro-LED may be identified and mitigated, thereby reducing or eliminating perceivable visual image artifacts.

[0009] Various refinements of the features noted above may exist in relation to various aspects of the present disclosure. Further, features may also be incorporated in these various aspects as well. For instance, various features discussed below in relation to one or more of the illustrated embodiments may be incorporated into any of the above-described aspects of the present disclosure alone or in any combination. The brief summary presented above is intended only to familiarize the reader with certain aspects and contexts of embodiments of the present disclosure without limitation to the claimed subject matter.

Description

BRIEF DESCRIPTION OF THE DRAWINGS

[0010] Various aspects of this disclosure may be better understood upon reading the following detailed description and upon reference to the drawings in which:

[0011] FIG. **1** is a block diagram of an electronic device with an electronic display, in accordance with an embodiment of the present disclosure;

[0012] FIG. **2** is a front view of a handheld device representing another embodiment of the electronic device of FIG. **1**;

[0013] FIG. **3** is a front view of another handheld device representing another embodiment of the electronic device of FIG. **1**;

[0014] FIG. **4** is a perspective view of a notebook computer representing an embodiment of the electronic device of FIG. **1**;

[0015] FIG. **5** is a front view and side view of a wearable electronic device representing another embodiment of the electronic device of FIG. **1**;

[0016] FIG. **6** is a front view of a desktop computer representing another embodiment of the electronic device of FIG. **1**;

[0017] FIG. **7** is a block diagram of a micro-LED display that employs micro-drivers to drive display pixels with controls signals, in accordance with an embodiment;

[0018] FIG. **8** is a block diagram schematically illustrating an operation of a micro-driver of FIG. **7**, in accordance with an embodiment of the present disclosure;

[0019] FIG. **9** is a timing diagram illustrating an example operation of the micro-driver of FIG. **8**, in accordance with an embodiment of the present disclosure;

[0020] FIG. **10** is a schematic illustration of the micro-LED display of FIG. **7**, where a micro-driver controls a collection of display pixels based on a digital code, in accordance with an embodiment of the present disclosure;

[0021] FIG. **11** is a schematic illustration depicting an image artifact that is less visible on the micro-LED display of FIG. **7** after mitigation, in accordance with an embodiment of the present disclosure;

[0022] FIG. **12** is a schematic diagram of an embodiment of a local passive matrix anode of the micro-LED display of FIG. **7** with a failed micro-LED, in accordance with an embodiment of the present disclosure;

[0023] FIG. **13** is a schematic diagram of an embodiment of a local passive matrix anode of the micro-LED display of FIG. **7** coupled to circuitry for identifying a failed micro-LED, in accordance with an embodiment of the present disclosure;

[0024] FIG. **14** is a schematic diagram of an embodiment of a local passive matrix anode of the micro-LED display of FIG. **7** for mitigating a failed micro-LED, in accordance with an embodiment of the present disclosure;

[0025] FIG. **15** is a timing diagram illustrating voltage levels of an anode, a first cathode, a second cathode, a third cathode, and logic control voltage of the micro-LED display of FIG. **7** during the mitigation scheme of FIG. **14**, in accordance with an embodiment of the present disclosure;

[0026] FIG. **16** is a schematic diagram of an embodiment of a local passive matrix anode coupled to circuitry to implement a sensing scheme to identify a failed micro-LED of the micro-LED display of FIG. **7**, in accordance with an embodiment of the present disclosure;

[0027] FIG. **17** is a schematic diagram of an embodiment of the local passive matrix anode coupled to circuitry to implement a sensing scheme to identify a failed micro-LED of the micro-LED display of FIG. **7**, in accordance with an embodiment of the present disclosure;

[0028] FIG. **18** is a schematic diagram of an embodiment of the local passive matrix cathode coupled to circuitry to implement a sensing scheme to identify a failed micro-LED of the micro-LED display of FIG. **7**, in accordance with an embodiment of the present disclosure;

[0029] FIG. **19** is a schematic diagram of an embodiment of the local passive matrix cathode

coupled to circuitry to implement a sensing scheme to identify a failed micro-LED of the micro-LED display of FIG. 7, in accordance with an embodiment of the present disclosure;

[0030] FIG. 20 is a schematic diagram of an embodiment of the local passive matrix cathode coupled to circuitry to implement a sensing scheme to identify a failed micro-LED of the micro-LED display of FIG. 7, in accordance with an embodiment of the present disclosure;

[0031] FIG. 21 is a schematic diagram of image data transmitted to the micro-LED display of FIG. 7 to implement a compensation scheme to mitigate for a failed micro-LED, in accordance with an embodiment of the present disclosure;

[0032] FIG. 22 is a flowchart of an example method for identifying and mitigating a failed micro-LED, in accordance with an embodiment of the present disclosure; and

[0033] FIG. 23 is a flowchart of an example method for compensating for a failed micro-LED, in accordance with an embodiment of the present disclosure.

DETAILED DESCRIPTION

[0034] One or more specific embodiments will be described below. In an effort to provide a concise description of these embodiments, not all features of an actual implementation are described in the specification. It should be appreciated that in the development of any such actual implementation, as in any engineering or design project, numerous implementation-specific decisions must be made to achieve the developers' specific goals, such as compliance with system-related and business-related constraints, which may vary from one implementation to another. Moreover, it should be appreciated that such a development effort might be complex and time consuming, but would nevertheless be a routine undertaking of design, fabrication, and manufacture for those of ordinary skill having the benefit of this disclosure.

[0035] When introducing elements of various embodiments of the present disclosure, the articles “a,” “an,” and “the” are intended to mean that there are one or more of the elements. The terms “including” and “having” are intended to be inclusive and mean that there may be additional elements other than the listed elements. Additionally, it should be understood that references to “one embodiment,” “an embodiment,” “embodiments,” and “some embodiments” of the present disclosure are not intended to be interpreted as excluding the existence of additional embodiments that also incorporate the recited features.

[0036] The present disclosure provides techniques for identifying (e.g., testing) and/or mitigating failed micro-light emitting diodes (micro-LEDs) of an electronic display. Some electronic displays may use multiple micro-LEDs that emit light at a target luminance level to create a frame of image content for display. The micro-LEDs may be organized in rows (e.g., cathodes) and columns (e.g., anodes). The anode may be coupled to a micro-driver that provides a current to drive the micro-LEDs to emit light at different times. In some cases, if a failed micro-LED draw current away from other micro-LEDs along the anode, thereby reducing current provided to the other micro-LEDs during operation. The failed micro-LED may not emit light and/or emit light at lower luminance levels (e.g., in comparison to target luminance levels), thereby causing perceivable visual image artifacts. Additionally or alternatively, the other micro-LEDs may emit light the wrong amount of light due to the failed micro-LED drawing current away from the other micro-LEDs.

[0037] As such, the systems and methods described herein disclose a sensing/compensation scheme for identifying a failed micro-LED, compensating for the failed micro-LED, or a combination thereof. In particular, a forward bias of a micro-LED during the sensing scheme may be controlled by setting a bias display voltage ($V_{\text{sub.bias_disp}}$). For example, sensing circuitry may individually test the micro-LEDs along a respective anode to identify failed micro-LEDs. This sensing circuitry may, in some embodiments, be shared with other sensors in the system, such as a touch sensor. The sensing circuitry may drive a respective micro-LED using a common mode bias voltage and determine if current flows through the respective micro-LED. The sensing circuitry may determine that the respective micro-LED is operational if current does not flow from the respective micro-LED. The sensing circuitry may determine that the respective micro-LED failed if current flows

from the respective micro-LED. In other words, the current may flow in an undesired short circuit parallel to the failed micro-LED. If the micro-LED failed, the sensing circuitry may close a switch with a defined resistor having a defined value to shunt current around the failed micro-LED with a defined short circuit current, which may reduce or eliminate perceivable image artifacts caused by the failed micro-LED. In some cases, the micro-driver may adjust the current provided to an anode with a failed micro-LED to compensate for the defined short circuit current. In fact, in some cases, the defined resistor may even draw additional current far more than the amount that the failed micro-LED had been drawing, but the defined resistor may draw a known amount of current. Thus, the current supplied to the anode may be the desired driving current plus the current that is known to be drawn over the defined resistor. In this way, perceivable visual image artifacts caused by the failed micro-LED may be reduced or eliminated.

[0038] Additionally or alternatively, image data for one or more micro-LEDs proximate the failed micro-LED may be adjusted to compensate for the failed micro-LED. For example, a gain mask may be applied to the image data intended for micro-LEDs along the same anode as the failed micro-LED. The gain mask may adjust the gray level and/or distribute the gray level intended for the micro-LED to the other micro-LEDs. For example, current provided to the other micro-LEDs along the same anode may be increased to drive the other micro-LEDs to a target luminance, thereby compensating for the failed micro-LED. Additionally or alternatively, the image data for the failed micro-LED may be set to gray level 0 (e.g., black) to reduce current stress on the failed micro-LED and/or a magnitude and a polarity of voltage stress on the failed micro-LED may be adjusted by a bias voltage. In certain instances, reducing current stress and/or voltage stress to a failed micro-LED may reduce additional degradation to the failed micro-LED. By compensating for the failed micro-LED, perceivable visual image artifacts caused by the failed micro-LED may be reduced or eliminated.

[0039] With the preceding in mind, an electronic device **10** including an electronic display **12** is shown in FIG. **1**. As is described in more detail below, the electronic device **10** may be any suitable electronic device, such as a computer, a mobile phone, a portable media device, a tablet, a television, a virtual-reality headset, a wearable device such as a watch, a vehicle dashboard, or the like. Thus, it should be noted that FIG. **1** is merely one example of a particular implementation and is intended to illustrate the types of components that may be present in an electronic device **10**.

[0040] The electronic device **10** includes the electronic display **12**, one or more input devices **14**, one or more input/output (I/O) ports **16**, a processor core complex **18** having one or more processing circuitry(s) or processing circuitry cores, local memory **20**, a main memory storage device **22**, a network interface **24**, and a power source **26** (e.g., power supply). The various components described in FIG. **1** may include hardware elements (e.g., circuitry), software elements (e.g., a tangible, non-transitory computer-readable medium storing executable instructions), or a combination of both hardware and software elements. It should be noted that the various depicted components may be combined into fewer components or separated into additional components. For example, the local memory **20** and the main memory storage device **22** may be included in a single component.

[0041] The processor core complex **18** is operably coupled with local memory **20** and the main memory storage device **22**. Thus, the processor core complex **18** may execute instructions stored in local memory **20** or the main memory storage device **22** to perform operations, such as generating or transmitting image data to display on the electronic display **12**. As such, the processor core complex **18** may include one or more general purpose microprocessors, one or more application specific integrated circuits (ASICs), one or more field programmable logic arrays (FPGAs), or any combination thereof.

[0042] In addition to program instructions, the local memory **20** or the main memory storage device **22** may store data to be processed by the processor core complex **18**. Thus, the local memory **20** and/or the main memory storage device **22** may include one or more tangible, non-

transitory, computer-readable media. For example, the local memory **20** may include random access memory (RAM) and the main memory storage device **22** may include read-only memory (ROM), rewritable non-volatile memory such as flash memory, hard drives, optical discs, or the like.

[0043] The network interface **24** may communicate data with another electronic device or a network. For example, the network interface **24** (e.g., a radio frequency system) may enable the electronic device **10** to communicatively couple to a personal area network (PAN), such as a Bluetooth network, a local area network (LAN), such as an 802.11x Wi-Fi network, or a wide area network (WAN), such as a 4G, Long-Term Evolution (LTE), or 5G cellular network. The power source **26** may provide electrical power to one or more components in the electronic device **10**, such as the processor core complex **18** or the electronic display **12**. Thus, the power source **26** may include any suitable source of energy, such as a rechargeable lithium polymer (Li-poly) battery or an alternating current (AC) power converter. The I/O ports **16** may enable the electronic device **10** to interface with other electronic devices. For example, when a portable storage device is connected, the I/O port **16** may enable the processor core complex **18** to communicate data with the portable storage device.

[0044] The input devices **14** may enable user interaction with the electronic device **10**, for example, by receiving user inputs via a button, a keyboard, a mouse, a trackpad, or the like. The input device **14** may include sensing components in the electronic display **12**. The touch sensing components (e.g., touch sensor) may receive user inputs by detecting occurrence or position of an object touching the surface of the electronic display **12**.

[0045] In addition to enabling user inputs, the electronic display **12** may include a display panel with one or more display pixels. The electronic display **12** may control light emission from the display pixels to present visual representations of information, such as a graphical user interface (GUI) of an operating system, an application interface, a still image, or video content, by displaying frames of image data. To display images, the electronic display **12** may include display pixels implemented on the display panel. The display pixels may represent sub-pixels that each control a luminance value of one color component (e.g., red, green, or blue for an RGB pixel arrangement or red, green, blue, or white for an RGBW arrangement).

[0046] The electronic display **12** may display an image by controlling light emission from its display pixels based on pixel or image data associated with corresponding image pixels (e.g., points) in the image. In some embodiments, pixel or image data may be generated by an image source, such as the processor core complex **18**, a graphics processing unit (GPU), or an image sensor. Additionally, in some embodiments, image data may be received from another electronic device **10**, for example, via the network interface **24** and/or an I/O port **16**. Similarly, the electronic display **12** may display frames based on pixel or image data generated by the processor core complex **18**, or the electronic display **12** may display frames based on pixel or image data received via the network interface **24**, an input device, or an I/O port **16**.

[0047] The electronic device **10** may be any suitable electronic device. To help illustrate, an example of the electronic device **10**, a handheld device **10A**, is shown in FIG. 2. The handheld device **10A** may be a portable phone, a media player, a personal data organizer, a handheld game platform, or the like. For illustrative purposes, the handheld device **10A** may be a smartphone, such as an iPhone® model available from Apple Inc.

[0048] The handheld device **10A** includes an enclosure **30** (e.g., housing). The enclosure **30** may protect interior components from physical damage or shield them from electromagnetic interference, such as by surrounding the electronic display **12**. The electronic display **12** may display a graphical user interface (GUI) **32** having an array of icons. When an icon **34** is selected either by an input device **14** or a touch-sensing component of the electronic display **12**, an application program may launch.

[0049] The input devices **14** may be accessed through openings in the enclosure **30**. The input

devices **14** may enable a user to interact with the handheld device **10A**. For example, the input devices **14** may enable the user to activate or deactivate the handheld device **10A**, navigate a user interface to a home screen, navigate a user interface to a user-configurable application screen, activate a voice-recognition feature, provide volume control, or toggle between vibrate and ring modes.

[0050] Another example of a suitable electronic device **10**, specifically a tablet device **10B**, is shown in FIG. **3**. The tablet device **10B** may be any iPad® model available from Apple Inc. A further example of a suitable electronic device **10**, specifically a computer **10C**, is shown in FIG. **4**. For illustrative purposes, the computer **10C** may be any MacBook® or iMac® model available from Apple Inc. Another example of a suitable electronic device **10**, specifically a watch **10D**, is shown in FIG. **5**. For illustrative purposes, the watch **10D** may be any Apple Watch® model available from Apple Inc. As depicted, the tablet device **10B**, the computer **10C**, and the watch **10D** each also includes an electronic display **12**, input devices **14**, I/O ports **16**, and an enclosure **30**. The electronic display **12** may display a GUI **32**. Here, the GUI **32** shows a visualization of a clock. When the visualization is selected either by the input device **14** or a touch-sensing component of the electronic display **12**, an application program may launch, such as to transition the GUI **32** to presenting the icons **34** discussed in FIGS. **2** and **3**.

[0051] Turning to FIG. **6**, a computer **10E** may represent another embodiment of the electronic device **10** of FIG. **1**. The computer **10E** may be any suitable computer, such as a desktop computer, a server, or a notebook computer, but may also be a standalone media player or video gaming machine. By way of example, the computer **10E** may be an iMac®, a MacBook®, or other similar device by Apple Inc. of Cupertino, California. It should be noted that the computer **10E** may also represent a personal computer (PC) by another manufacturer. A similar enclosure **36** may be provided to protect and enclose internal components of the computer **10E**, such as the electronic display **12**. In certain embodiments, a user of the computer **10E** may interact with the computer **10E** using various peripheral input structures (e.g., input devices **14**), such as the keyboard **14A** or mouse **14B**, which may connect to the computer **10E**.

[0052] FIG. **7** depicts a block diagram of an example architecture of the electronic display **12** (e.g., micro-LED display **12**). In the example of FIG. **7**, the micro-LED display **12** uses an RGB display panel **60** with pixels that include red, green, and blue micro-LEDs as display pixels. Support circuitry **62** may receive RGB-format video image data **64**. It should be appreciated, however, that the micro-LED display **12** may display other formats of image data, in which case the support circuitry **62** may receive image data of such different image format. In some embodiments, the support circuitry **62** may include a video timing controller (video TCON) and/or emission timing controller (emission TCON) that receives and uses the image data **64** in a serial bus to determine a data clock signal (DATA_CLK) and/or an emission clock signal (EM_CLK) to control the provision of the image data **64** in the micro-LED display **12**. The video TCON may also pass the image data **64** to a serial-to-parallel circuitry that may deserialize the image data **64** signal into several parallel image data signals. That is, the serial-to-parallel circuitry may collect the image data **64** into the particular data signals that are passed on to specific columns among a total of M respective columns in the display panel **60**. As noted above, the video TCON may generate the data clock signal (DATA_CLK), and the emission TCON may generate the emission clock signal (EM_CLK). Collectively, these may be referred to as Data/Row Scan Control signals, as illustrated in FIG. **7**. As such, the data is labeled DATA/ROW SCAN CONTROLS. The data/row scan controls respectively contain image data corresponding to pixels in the first column, second column, third column, fourth column . . . fourth-to-last column, third-to-last column, second-to-last column, and last column, respectively. The data/row scan controls may be collected into more or fewer columns depending on the number of columns that make up the display panel **60**.

[0053] In particular, the display panel **60** columns include micro-drivers **78**. The micro-drivers **78** are arranged in an array **79**. The micro-drivers **78** may receive and/or pass on various signals sent

from the support circuitry **62**. By way of example, micro-drivers **78** on the left-hand side of the display may receive row scan control signals and pass those signals that correspond to its particular row to other micro-drivers **78** in that row of micro-drivers. Each micro-driver **78** drives a number of display pixels **77**. Different display pixels (e.g., display sub-pixel) **77** may include different colored micro-LEDs (e.g., a red micro-LED, a green micro-LED, or a blue micro-LED) to represent the image data **64** in RGB format. Although one of the micro-drivers **78** of FIG. 7 is shown to drive twenty-six anodes **73** having eight display pixels **77** each, each micro-driver **78** may drive more or fewer anodes **73** (e.g., 8 anodes, 9 anodes, 10 anodes, 11 anodes, 12 anodes, 14 anodes, 15 anodes, 16 anodes, 17 anodes, 18 anodes, and so forth) and respective display pixels **77**. As illustrated, the subset of display pixels **77** located on each anode **73** may be associated with a particular color (e.g., red, green, or blue). As mentioned above, it should be noted that a respective cathode corresponds to a subset of display pixels **77** associated with a particular color even though each cathode for a particular color channel is not illustrated in FIG. 7. For example, cathode corresponds to a red color channel (e.g., subset of red display pixels **77**). There may be a second set of cathodes that couple to a green color channel (e.g., subset of green display pixels **77**) and a third set of cathodes that couple to a blue color channel (subset of blue display pixels **77**), but these are not expressly illustrated in FIG. 7 for ease of illustration.

[0054] The display pixels **77** driven by each micro-driver **78** may be arranged as a local passive matrix (LPM). In one example, each micro-driver **78** drives two local passive matrices (LPMs) of display pixels **77**, one above the micro-driver **78** and one below the micro-driver **78**. Before continuing, it should be appreciated that the array **79** may have LPM columns that include multiple different LPMs that are driven by different micro-drivers **78**. For each LPM, different display pixels **77** may include different combination of colored micro-LEDs (e.g., a red micro-LED, a green micro-LED, or a blue micro-LED) to represent the image data **64** in RGB format. For example, the combinations may include a red micro-LED and a green micro-LED, a blue micro-LED and a green micro-LED, a red micro-LED and a blue micro-LED, and so on.

[0055] A power supply **84** may provide a reference voltage (VREF) **86** to drive the micro-LEDs, a digital power signal **88**, and an analog power signal **90**. In some cases, the power supply **84** may provide more than one reference voltage (VREF) **86** signal. Namely, display pixels **77** of different colors may be driven using different reference voltages. As such, the power supply **84** may provide more than one reference voltage (VREF) **86**. Additionally or alternatively, other circuitry on the display panel **60** may step the reference voltage (VREF) **86** up or down to obtain different reference voltages to drive different colors of micro-LED.

[0056] A block diagram shown in FIG. 8 illustrates some of the components of one of the micro-drivers **78**. The micro-driver **78** shown in FIG. 7 includes pixel data buffer(s) **100** and a digital counter **102**. The pixel data buffer(s) **100** may include sufficient storage to hold image data **70** that is provided (e.g., as a digital code). For instance, the micro-driver **78** may include pixel data buffers to store image data **70** for a display pixel **77** at any one time (e.g., for 8-bit image data **70**, this may be 24 bits of storage). It should be appreciated, however, that the micro-driver **78** may include more or fewer buffers, depending on the data rate of the image data **70** and the number of display pixels **77** included in the image data **70**. The pixel data buffer(s) **100** may take any suitable logical structure based on the order that the column driver provides the image data **70**. For example, the pixel data buffer(s) **100** may include a first-in-first-out (FIFO) logical structure or a last-in-first-out (LIFO) structure.

[0057] When the pixel data buffer(s) **100** has received and stored the image data **70**, the micro-driver **78** may provide the emission clock signal (EM_CLK). A digital counter **102** may receive the emission clock signal (EM_CLK) as an input. The pixel data buffer(s) **100** may output enough of the stored image data **70** to output a digital data signal **104** represent a desired gray level for a particular display pixel **77** that is to be driven by the micro-driver **78**. The digital counter **102** may also output a digital counter signal **106** indicative of the number of edges (only rising, only falling,

or both rising and falling edges) of the emission clock signal (EM_CLK) **98**. The signals **104** and **106** may enter a comparator **108** that outputs an emission control signal **110** in an “on” state when the signal **106** does not exceed the digital data signal **104**, and an “off” state otherwise. The emission control signal **110** may be routed to driving circuitry (not shown) for the display pixel **77** being driven, which may cause light emission **112** from the selected display pixel **77** to be on or off. The longer the selected display pixel **77** is driven “on” by the emission control signal **110**, the greater the amount of light that will be perceived by the human eye as originating from the display pixel **77**.

[0058] A timing diagram **120**, shown in FIG. **9**, provides one brief example of the operation of the micro-driver **78**. The timing diagram **120** shows the digital data signal **104**, the digital counter signal **106**, the emission control signal **110**, and the emission clock signal (EM_CLK) represented by numeral **122**. In the example of FIG. **9**, the gray level for driving the selected display pixel **77** is gray level 4, and this is reflected in the digital data signal **104**. The emission control signal **110** drives the display pixel **77** “on” for a period of time defined as gray level 4 based on the emission clock signal (EM_CLK). Namely, as the emission clock signal (EM_CLK) rises and falls, the digital counter signal **106** gradually increases. The comparator **108** outputs the emission control signal **110** to an “on” state as long as the digital counter signal **106** remains less than the digital data signal **104**. When the digital counter signal **106** reaches the digital data signal **104**, the comparator **108** outputs the emission control signal **110** to an “off” state, thereby causing the selected display pixel **77** no longer to emit light.

[0059] It should be noted that the steps between gray levels are reflected by the steps between emission clock signal (EM_CLK) edges. That is, based on the way humans perceive light, to notice the difference between lower gray levels, the difference between the amounts of light emitted between two lower gray levels may be relatively small. To notice the difference between higher gray levels, however, the difference between the amounts of light emitted between two higher gray levels may be comparatively much greater. The emission clock signal (EM_CLK) therefore may use relatively short time intervals between clock edges at first. To account for the increase in the difference between light emitted as gray levels increase, the differences between edges (e.g., periods) of the emission clock signal (EM_CLK) may gradually lengthen. The particular pattern of the emission clock signal (EM_CLK), as generated by the emission TCON, may have increasingly longer differences between edges (e.g., periods) so as to provide a gamma encoding of the gray level of the display pixel **77** being driven.

[0060] With the preceding in mind, FIG. **10** illustrates the micro-driver **78** driving the display pixels **77** according to the image data **70** in the form of a digital code, and thereby enabling image content to be displayed by the micro-LED display **12**. As mentioned above, the micro-driver **78** may drive any suitable number of display pixels **77**, and a subset of display pixels **77** may be located on respective anodes **73** of the micro-LED display **12**. As illustrated, the subset of display pixels **77** located on each anode **73** may be associated with a particular color (e.g., red, green, blue). Further, it should be noted that a respective cathode corresponds to a subset of display pixels **77** associated with a particular color even though each cathode for a particular color channel is not illustrated in FIG. **10**. For example, as illustrated, a first set of cathodes corresponds to a red color channel (e.g., subset of red display pixels **77**). However, there may be a second set of cathodes that couple to a green color channel (e.g., subset of green display pixels **77**) and a third set of cathodes that couple to a blue color channel (subset of blue display pixels **77**). The second set of cathodes and the third set of cathodes are not expressly illustrated in FIG. **10** for ease of illustration.

[0061] As discussed with respect to FIG. **7**, the display pixels **77** may be arranged as an LPM. As illustrated, the micro-driver **78** may drive two LPMs of display pixels **77**. Each LPM may include twenty-six anode groups **73** having eight display pixels **77** each. It may be understood that each micro-driver **78** may drive more or fewer anode groups **73** and respective display pixels **77**. As illustrated, the subset of display pixels **77** located on each anode group **73** may be associated with a

particular color (e.g., red, green, blue). As mentioned above, it should be noted that a respective cathode corresponds to a subset of display pixels **77** associated with a particular color even though each cathode for a particular color channel is not illustrated in FIG. **10**. For example, anode **74** corresponds to a red color channel (e.g., subset of red display pixels **77**) and there may be a corresponding shared cathode for all color channels or a separate cathode corresponding to the red color channel. There are a second set of anodes that couple to a green color channel (e.g., subset of green display pixels **77**) and a third set of anodes that couple to a blue color channel (subset of blue display pixels **77**), but these are not expressly illustrated in FIG. **10** for ease of description. Each micro-driver **78** may drive one row of display pixels **77** of each LPM at a time.

[0062] In some cases, image content displayed on the micro-LED display **12** may include image artifacts, such as a dark display pixels and/or black display pixels due to a failed (e.g., defective, malfunctioning) micro-LED. FIG. **11** is a schematic illustration depicting an image artifact that is less visible on the micro-LED display **12** after applying a sensing/compensation scheme. In particular, FIG. **11** illustrates image content **150** before applying mitigation and image content **152** after applying the mitigation. As discussed herein, different display pixels **77** may include different colored micro-LEDs to represent the image data **64** in RGB format. Without applying the sensing/compensation scheme, image artifacts due to failed micro-LEDs, such as darker display pixels could appear when image content **150** is displayed on the micro-LED display **12**. For example, a failed micro-LED may not emit light, which may result in display pixel displaying a gray level 0 (black). However, the failed micro-LED may continue to draw current away from other micro-LEDs along the same anode. The other micro-LEDs may receive less current than intended and emit less light (e.g., lower luminance) in comparison to a target luminance level within image data. As such, the image content **150** may appear with a display pixel at gray level 0 corresponding to the failed micro-LED and a column of darker display pixels (e.g., lower gray level than the target gray level in the digital code **70**) corresponding to the other micro-LEDs along the anode. However, after applying the sensing/compensation scheme, the black display pixel and/or the darker display pixels may not be perceivable, as depicted by image content **152**. For example, after mitigating (e.g., compensating for) the failed micro-LED, the visibility of the image artifact may be reduced by 50%, 80%, 90%, 100%, and the like. The process for applying the sensing/compensation scheme to identify and/or mitigate a failed micro-LED will be described in greater detail below.

[0063] FIG. **12** is schematic diagram of an embodiment of a local passive matrix anode **180** of the micro-LED display **12** with a failed micro-LED. As discussed herein, an anode **73** may include a subset of display pixels **77** associated with a particular color. The local passive matrix anode **180** may correspond to at least a portion of the anode **73**. As illustrated, the local passive matrix anode **180** includes one or more micro-LEDs **182** (illustrated as **182A-182N**, collectively referred to as a micro-LED **182**) corresponding to the subset of display pixels **77**. For example, the local passive matrix anode **180** may include eight micro-LEDs **182**. It may be understood that the local passive matrix anode **180** may include any suitable number of micro-LEDs **182** coupled together in parallel, such as 2 or more micro-LEDs, 3 or more micro-LEDs, 4 or more micro-LEDs, 5 or more micro-LEDs, 6 or more micro-LEDs, 7 or more micro-LEDs, 9 or more micro-LEDs, 10 or more micro-LEDs, and so on. As will be described in further detail below, each micro-LED **182** may be part of a respective cathode and/or a cathode circuit corresponding to a respective cathode. For example, a first micro-LED **182A** may be part of a first cathode circuit, a second micro-LED **182B** may be part of a second cathode circuit, and so on.

[0064] The local passive matrix anode **180** may include or be coupled to an analog power supply **184** (AVDD) (e.g., the analog power signal **90** described with respect to FIG. **7**) and a current source **186** that drives the micro-LEDs **182** to emit light. For example, the current source **186** may be a component of the micro-driver **78** and/or receive signals from the micro-driver **78** to provide a current to the micro-LEDs **182**.

[0065] Returning to the micro-LEDs **182**, the local passive matrix anode **180** may include the micro-LEDs **182** coupled together in parallel. To display a frame of image content, for example, current may be provided to the first micro-LED **182A** to drive the first micro-LED **182A** to emit light, then current may be provided to the second micro-LED **182B**, then current may be provided to the third micro-LED **182C**, and so on. The local passive matrix anode **180** may include a voltage (e.g., anode voltage) that creates a voltage drop across the micro-LEDs **182**. The local passive matrix anode **180** may also be coupled to one or more cathodes that may be selectively coupled to bias voltages (V.sub.Bias) **188** and negative voltages (V.sub.Neg) **190**. It may be understood that each respective cathode may include and/or be coupled to a respective switch that selectively couples the respective cathode to the bias voltage **188** or the negative voltage **190** during operation (e.g., display of image data). For example, a row of micro-LEDs **182** (e.g., along a respective cathode) may be driven when the switch couples the row of micro-LEDs **182** to the negative voltage **190**. Each micro-LED **182** may include a turn-on voltage, which may be an amount of voltage used to drive the micro-LED **182** to emit light. If the voltage across the micro-LED **182** is greater than the turn-on voltage, then the micro-LED **182** may be driven to emit light. That is, by coupling the row of micro-LEDs **182** to the negative voltage **190**, a voltage drop may be formed and current driven across the row of micro-LEDs **182** may cause the row of micro-LEDs **182** to emit light. The remaining rows of micro-LEDs **182** may be coupled to the bias voltage **188** and may not emit light when current is driven along the anode. The bias voltage **188** may be greater than the negative voltage **190**. For example, the bias voltage **188** may be equal to V.sub.Neg+1.5 Volts (V). In another example, the bias voltage **188** may be equivalent to a voltage of the analog power supply **184**.

[0066] In certain instances, a micro-LED may fail such that the micro-LED **182** may not be operating and/or functioning as expected. For example, a failed micro-LED may not emit light at an intended brightness. As another example, the failed micro-LED may not emit any brightness or may continue to emit at a brightness level for longer or shorter than an intended time period. The failed micro-LED may draw current intended to go to the other micro-LEDs **182** along the local passive matrix anode **180**. As such, the remaining micro-LEDs **182** may receive less current, thus emitting less light or light at lower luminance levels in comparison to the target luminance levels in the digital code **70**, which may cause perceivable visual image artifacts in the image content displayed on the micro-LED display **12**.

[0067] By way of example, the first micro-LED **182A** may be a failed micro-LED, while the remaining micro-LEDs **182B-N** may be functioning micro-LEDs **182**. To illustrate the current drawn by the failed micro-LED in FIG. **12**, the first micro-LED **182A** is coupled to a resistor **192** in parallel. That is, the current drawn by the failed micro-LED may be equivalent to a resistance of the resistor **192**. For example, the micro-driver **78** may drive the second micro-LED **182B** to emit light, but the failed micro-LED may draw an amount of current equivalent to the resistance of the resistor **192** and the second micro-LED **182B** may receive the remaining amount of current. The remaining amount of current may be less than the amount of current provided by the current source **186** for driving the second micro-LED **182B**. In this way, the second micro-LED **182B** may receive less current and emit less light. As such, the image content displayed by the micro-LED display **12** may include perceivable image artifacts, such as the image artifacts within the image content **150** described with respect to FIG. **11**.

[0068] As discussed herein, the failed micro-LED (e.g., the first micro-LED **182A**) may not emit light when driven. That is, the failed micro-LED may emit a gray level 0. When the failed micro-LED is continuously driven, the failed micro-LED may experience current stress on and/or additional degradation. As such, identifying and/or mitigating the failed micro-LED may improve operation of the micro-LED display **12** and/or the local passive matrix anode **180**.

[0069] With the foregoing in mind, FIG. **13** is schematic diagram of an embodiment of a local passive matrix anode **220** of the micro-LED display **12** coupled to circuitry (e.g., testing circuitry,

sensing circuitry) **222** for identifying (e.g., sensing) a failed micro-LED. As illustrated, the micro-LED display **12** may include circuitry **222** for identifying failed micro-LEDs (e.g., the first micro-LED **182A**). The circuitry **222** may individually test the micro-LEDs **182** to identify the failed micro-LEDs. In some cases, the circuitry **222** may be at least partially integrated with touch analog front end (AFE) circuitry used for sensing (e.g., touch sensing) on the micro-LED display **12**. In other cases, the circuitry **222** may be at least partially integrated with the micro-driver **78** described with respect to FIGS. 7-10. That is, the circuitry **222** and/or the micro-driver **78** may perform a sensing scheme to identify a failed micro-LED. In other instances, the circuitry **222** and the micro-driver **78** may be separate components within the micro-LED display **12**. The sensing scheme may be performed during manufacturing and/or in the field to identify the failed micro-LEDs. In addition, the sensing scheme may be periodically performed when the electronic device **10** is within the field to identify micro-LEDs **182** that may become failed micro-LEDs over time.

[0070] The local passive matrix anode **220** may include the micro-LEDs **182** connected together in parallel, the analog power supply **184**, and/or the current source **186**. The local passive matrix anode **220** may be coupled to the circuitry **222** for identifying the failed micro-LED. The circuitry **222** may include an analog opamp **224** (e.g., analog buffer), a common mode bias voltage (V.sub.cm) **226**, a capacitor **228**, and a resistor **230**. The analog opamp **224** may include a first input (e.g., negative input) coupled to the common mode bias voltage **226** and a second input (e.g., positive input) coupled to a micro-LED **182** being tested. The second input may also be coupled to the capacitor **228** and the resistor **230**.

[0071] To perform the testing, the analog power supply **184** and/or the current source **186** may be disconnected from the micro-LEDs **182** and the circuitry **222** may be coupled to the micro-LEDs **182**. As illustrated, the local passive matrix anode **220** may include one or more switches **232** (illustrated as **232A-232N**, collectively referred to as a switch **232**) coupled to the micro-LEDs **182**, the current source **186**, the circuitry **222**, and the like. The switches **232** may be controlled by the circuitry **222**, the micro-driver **78**, and/or the processor core complex **18**. At the start of the sensing scheme, a first switch **232A** may open to disconnect the analog power supply **184** and/or the current source **186** from the micro-LEDs **182**, a second switch **232B** may close to couple the circuitry **222** to the micro-LEDs **182**, and/or a third switch **232C** may selectively couple the first micro-LED **182A** to the bias voltage **188**, a fourth switch **232D** may selectively couple the second micro-LED **182B** to the bias voltage **188**, and so on. To test the first micro-LED **182A**, for example, the third switch **232C** may close to couple the first micro-LED **182A** to the bias voltage **188**. The remaining switches **232** (e.g., switches **232D-N**) may be open to disconnect the bias voltage **188** from the remaining micro-LEDs **182B-N**. After testing the first micro-LED **182A**, the third switch **232C** may open and the fourth switch **232D** may close to couple the second micro-LED **182B** to the bias voltage **188** and test the second micro-LED **182B**. This process may continue and/or repeat until all micro-LEDs **182** along the local passive matrix anode **220** may be tested by the circuitry **222**. As such, the circuitry **222** may individually test each micro-LED **182** of the local passive matrix anode **220**, and moreover, each micro-LED **182** within the micro-LED display **12**. As such, failed micro-LEDs **182** may be identified.

[0072] If the first micro-LED **182A** is a failed micro-LED, for example, the analog opamp **224** may receive a current from the first micro-LED **182A** during the sensing scheme. The analog opamp **224** may convert the current into an analog voltage and output the analog voltage. In other words, the analog opamp **224** may output an analog voltage representation of micro-LED leakage current, which may indicate that the first micro-LED **182A** may have failed (e.g., malfunction). If the analog opamp **224** does not receive a current from the first micro-LED **182A** during the testing (e.g., sensing scheme), then the first micro-LED **182A** may be determined to be a functional micro-LED. In this way, the analog opamp **224** may operate as a trans-impedance amplifier (TIA). In certain instances, the analog opamp **224** may be coupled to an analog-to-digital converter to digitize the output analog voltage.

[0073] If the first micro-LED **182A** is a failed micro-LED, the circuitry **222** may identify a position of the first micro-LED **182A** (e.g., along the respective anode and/or the respective cathode) within the micro-LED display **12**. The circuitry **222** may provide an indication of the position of the first micro-LED **182A** to the processor core complex **18** and/or processing circuitry. The processor core complex **18** may adjust the image data based on the position of the first micro-LED **182A** to reduce or eliminate perceivable visual image artifacts.

[0074] FIG. **14** is a schematic diagram of a local passive matrix anode **250** of the micro-LED display **12** for mitigating (e.g., compensating) a failed micro-LED **251**. The local passive matrix anode **250** may include the micro-LEDs **182** connected together in parallel, the analog power supply **184**, and/or the current source **186**. As discussed herein, the sensing scheme may identify failed micro-LEDs **251** and a compensation scheme may mitigate for the failed micro-LEDs **251**, thereby reducing or eliminating perceivable visual image artifacts within image content being displayed.

[0075] By way of illustrative example, the first micro-LED **182A** be a failed micro-LED **251**. To illustrate the failure, the local passive matrix anode **250** includes a resistor **192** coupled in parallel to the first micro-LED **182A**. The failed micro-LED **251** may draw current equivalent to a resistance of the resistor **192**. That is, the failed micro-LED **251** may include a defined resistance (e.g., resistor). Additionally or alternatively, a cathode coupled to the failed micro-LED **251** may include a parasitic capacitance as illustrated by a capacitor **252**.

[0076] To mitigate the failed micro-LED **251**, the local passive matrix anode **180** may include a shunt switch **253** coupled to the failed micro-LED **251** in parallel. The shunt switch **253** may include a defined resistance with a defined value that therefore draws a defined short circuit current. As such, the shunt switch **253** may provide a low resistance path for the current. That is, the current flows through the shunt switch **253** instead of the failed micro-LED **251**. Although the illustrated example of the local passive matrix anode **180** includes the shunt switch **253** coupled to the failed micro-LED **251**, it may be understood that a respective shunt switch **253** may be coupled to each micro-LED **182B-N** in parallel. For the micro-LEDs **182B-N**, the respective shunt switches **253** may be open to cause the current to flow across the micro-LEDs **182B-N**. If one of the micro-LEDs **182B-N** may be identified as a failed micro-LED **251**, the respective shunt switch **253** may close to cause the current to be shunted around the failed micro-LED **251**. As such, current drawn by the failed micro-LED **251** may be reduced or eliminated, thereby mitigating for the failed micro-LED **251**.

[0077] The local passive matrix anode **250** may be coupled to one or more cathode circuits **255** (illustrated as **255A-N**, collectively referred to herein as a cathode circuit **255**). The cathode circuit **255** may include at least a portion of the cathode. In certain instances, a respective cathode with the failed micro-LED **251** may be pre-charged and/or floated to reduce or eliminate current flow to the failed micro-LED **251**. For example, the cathode circuit **255** may include a pre-charge switch **256** (e.g., the third switch **232C**, the remaining switches **232D-N**) respectively coupled between a micro-LED **182** and the bias voltage **188** and/or the negative voltage **190**. The pre-charge switch **256** may selectively couple the first micro-LED **182A** to the bias voltage **188** and/or the negative voltage **190**. For example, the cathode circuit **255** may be pre-charged to a pre-charge voltage ($V_{sub.pch}$), which may be equivalent to a voltage of the local passive matrix anode **250**. By pre-charging the cathode circuit **255** coupled to the failed micro-LED **251**, the current drawn by the failed micro-LED **251** may be reduced or eliminated. During operation, for example, the micro-driver **78** may drive a first row of micro-LEDs **182** coupled to a first cathode circuit **255A** to emit light and pre-charge a second row of micro-LEDs **182** coupled to a second cathode circuit **255B**. The micro-driver **78** may drive the second row of micro-LEDs **182** using the pre-charged voltage prior to driving the second row of micro-LEDs **182** using the current source **186**.

[0078] The compensation scheme may include increasing emission time and/or a duty cycle of the remaining micro-LEDs **182B-182N**. For example, increasing emission time may cause the micro-

LED **182** to emit light for a longer period of time, which may increase brightness. In another example, increasing the duty cycle of the micro-LED **182** may increase an amount of time the micro-LED **182** is on. The duty cycle may refer to a ratio between the time where the micro-LED **182** is on (e.g., emitting light) and the time where the micro-LED **182** is off (e.g., not emitting light). The longer a micro-LED **182** is on, the more light the micro-LED **182** may emit and the brighter the micro-LED **182** may visually appear to be. By increasing the brightness of the remaining micro-LEDs **182B-182N**, the visual appearance of the failed micro-LED **251** may be reduced or eliminated. As such, perceivable image artifacts due to the failed micro-LED **251** may be reduced or eliminated.

[0079] Additionally or alternatively, the compensation scheme may include driving the local passive matrix anode **250** with increased current. That is, each of the micro-LEDs **182** coupled to the local passive matrix anode **250** may receive increased current including the failed micro-LED **251**. As discussed herein, the shunt switch **253** coupled to the failed micro-LED **251** may include a defined resistor having defined value. Therefore, the current being drawn by the shunt switch **253** may be defined (e.g., known) by the micro-driver **78**. In other words, the shunt switch **253** may draw a defined short circuit current. The current drawn by the shunt switch **253** may be compensated for by increasing the overall current provided to the local passive matrix anode **250**. As the current is driven through the local passive matrix anode **250**, an amount may be drawn by the shunt switch **253** and the remaining amount may be used to drive a respective micro-LED **182** coupled to the local passive matrix anode **250**. The remaining amount may correspond to an amount of current intended to drive the respective micro-LED **182** to emit light at a target luminance level. Although the micro-LED display **12** may consume more power to compensate for the failed micro-LED, the visibility of perceivable image artifacts within image content displayed on the micro-LED display **12** may be reduced or eliminated.

[0080] In certain instances, a failed micro-LED **251** may stop failing, if current and/or voltage stress across the failed micro-LED **251** may be reduced or eliminated. That is, in certain instances, reducing or eliminating current flow and/or voltage across the failed micro-LED **251** may mitigate (e.g., fix) failed micro-LED **251**. For example, the bias voltage **188** may be adjusted to reduce or eliminate a magnitude and/or a polarity of voltage stress exerted on the failed micro-LED **251**. In another example, the image data corresponding to the failed micro-LED **251** may be set to a gray level 0 (black), thereby reducing current stress on the failed micro-LED **251**. Still in another example, coupling the cathode circuit **255** with the failed micro-LED **251** to a higher bias voltage **188** may reduce voltage stress on the failed micro-LED **251** by reducing voltage flow across the failed micro-LED **251**.

[0081] FIG. **15** is a timing diagram **280** illustrating voltage levels of an anode **282** (e.g., the local passive matrix anode **250** described with respect to FIG. **14**), a first cathode **284** (e.g., the cathode circuit **255** described with respect to FIG. **14**), a second cathode **286**, a third cathode **288**, and a logic control voltage **290** (e.g., the logic control voltage of the shunt switch **253** described with respect to FIG. **14**) during the mitigation scheme of FIG. **14**. The voltage level of the first cathode **284** may correspond a voltage level of a first row of micro-LEDs **182** including the failed micro-LED **251**, the voltage level of the second cathode **286** may correspond to a voltage level of a second row of micro-LEDs **182** including the second micro-LED **182B**, and so on. The timing diagram **280** may be used to describe the voltage changes of the components within the local passive matrix anode **250** and/or the cathode circuit **255** described with respect to FIG. **14**. For example, the anode **282** may correspond to the local passive matrix anode **250** with the failed micro-LED **251** and the first cathode **284** may correspond to a first cathode circuit **255** with the failed micro-LED **251** and the shunt switch **253** described with respect to FIG. **14**.

[0082] At time $t=0$, the anode **282** may be at a reset voltage and each of the cathodes **284**, **286**, **288** may be set to a bias voltage. The micro-LEDs **182** may not emit light when a respective cathode is set to the bias voltage. To drive a cathode **284**, **286**, **288** to emit light, the cathode **284**, **286**, **288**

may be set to a negative voltage. For example, at a time between $t=0$ and $t=t_1$, the first cathode **284** may be set to the negative voltage. As such, current from the anode **282** may drive the micro-LEDs **182** within the first cathode **284** to emit light.

[0083] After the micro-LEDs **182** within the first cathode **284** is driven, at time $t=t_1$ the first cathode **284** may be set to the bias voltage and the anode **282** may be set to the reset voltage. The first cathode **284** may be pre-charged with a voltage corresponding to the voltage of the anode **282**. For example, the first cathode **284** may be “floated,” or a capacitor within the first cathode **284** may store a pre-charge voltage. The pre-charge voltage may be equivalent to the voltage of the anode **282**. As such, the logic control voltage **290** may be pulled to a logic high (“1”). At a logic high, a biased cathode may draw current from the failed micro-LED **251**, thereby reducing and/or eliminating current draw by the failed micro-LED **251**. In addition, the biased cathode may be floated at the logic high. The anode **282** may also be pre-charged with a voltage. While the first cathode **284** may be floating, the second cathode **286** may be driven to emit light. For example, the second cathode **286** may be set to the negative voltage and current from the current source **186** may be used to drive the micro-LEDs **182** within the second cathode **286**.

[0084] At time $t=t_2$, the anode **282** may be set to the reset voltage and each of the cathodes **284**, **286**, and **288** may be set to the bias voltage. The logic control voltage **290** may be pulled to a logic low (“0”) in response to driving the second cathode **286** not emitting light.

[0085] At time $t=t_3$, the third cathode **288** may be driven to emit light. To this end, the third cathode **288** may be set to the negative voltage. While the third cathode **288** may be driven to emit light, the first cathode **284** may be pre-charged to reduce or eliminate current draw by the failed micro-LED **251**. The logic control voltage **290** may be pulled to a logic high (“1”) in response to pre-charging the first cathode **284**. As illustrated, the first cathode **284** may be pre-charged and floated to reduce or eliminate current draw by the failed micro-LED **251**. The logic control voltage **290** may be pulled to a logic high in response to floating the first cathode. As illustrated in FIG. 15, the first cathode **284** may be floating at time $t=t_3$ to time $t=t_4$. Since the second cathode **286** may not be driven to emit light, the second cathode **286** may be set to the bias voltage.

[0086] At time $t=t_4$, the anode **282** may be set to the reset voltage and each of the cathodes **284**, **286**, and **288** may be set to the bias voltage and the logic control voltage **290** may be pulled to a logic low (“0”).

[0087] FIG. 16 is a schematic diagram of an embodiment of a local passive matrix anode **320** coupled to the circuitry **322** (e.g., the circuitry **222** described with respect to FIG. 13) to implement the sensing scheme to identify the failed micro-LED **251**. The circuitry **322** may use current sensing to identify the failed micro-LED **251**, where the current may be a direct current. In the illustrated example, the circuitry **322** includes the analog opamp **224**, the capacitor **228**, and the resistor **230**. The analog opamp **224** may include a first input coupled to the micro-LEDs **182** and a second input coupled to the common mode bias voltage ($V_{sub,cm}$) **226**. The output of the analog opamp **224** may be an analog voltage representative of micro-LED leakage current. That is, the sum of the capacitance of the capacitor **228** and the resistance of the resistor **230** may be equivalent to the common mode bias voltage **226** received by the analog opamp **224**. The circuitry **322** may also include a reset switch **324** that opens and/or closes to reset a voltage of the analog opamp **224**. For example, the reset switch **324** may initialize the bias voltage on the negative input of the analog opamp **224** before the start of the sensing scheme.

[0088] The local passive matrix anode **320** may include the analog power supply (AVDD) **184** and the first micro-LED **182A**, which is illustrated as a failed micro-LED **251** by the resistor **192** coupled in parallel to the first micro-LED **182A**. It may be understood that the resistance of a failed micro-LED **251** may be less than the resistance of a functional micro-LED. As such, a failed micro-LED **251** may draw current away (e.g., current leakage) from other micro-LEDs **182B-N** along the local passive matrix anode **320**.

[0089] In the illustrated embodiment, the circuitry **322** may detect the failed micro-LED **251** using

an anode-side sensing scheme. For example, the reset switch **324** may open to couple the circuitry **322** to the micro-LEDs **182A-N** along the local passive matrix anode **320**. As such, the voltage of the local passive matrix anode **320** may be equivalent to the common mode bias voltage **226**. In certain instances, the bias display voltage **330** may be equivalent to the bias voltage **188** described with respect to FIGS. **12-14**. The bias display voltage **330** may be coupled to a micro-LED **182** that may be tested by the circuitry **322** via a bias voltage switch **332**. That is, the voltage of the cathode coupled to the tested micro-LED **182** may be equivalent to the bias display voltage **330**. In this way, the forward bias voltage of the tested micro-LED **182** may be controlled by the bias display voltage **330** and the bias voltage switch **332**.

[0090] The analog opamp **224** may receive a current from the first micro-LED **182A** via the second input. The analog opamp **224** may convert the current into an analog voltage, and in certain instances. If a tested micro-LED **182** is a failed micro-LED **251**, the analog opamp **224** may receive a current from the tested micro-LED **182** and output an analog voltage representative of the current leakage from the failed micro-LED **251**. If the tested micro-LED **182** is a functional micro-LED, the analog opamp **224** may not receive a current from the tested micro-LED **182** and may not output an analog voltage.

[0091] The circuitry **322** may include a virtual ground clamp **328** protect the circuitry **322** from over-voltage stress in the event of micro-LED failure (e.g., micro-LED shorting). When the cathode is connected to a bias display voltage **330** and/or a bias voltage switch **332**, a virtual ground clamp **328**, the resistor **334** may limit the amount of current going to the sensing circuit, thereby reducing the voltage stress on the circuitry **322** and protecting the circuitry **322**. The virtual ground clamp **328** may be an NMOS transistor and may be coupled to the third resistor **334** in series to reduce or eliminate current flow to the circuitry **322**. A first node of virtual ground clamp **328** may be coupled to the analog power supply (AVDD) **184**, a second node of the virtual ground clamp **328** may be coupled to a first input of the analog opamp **224**, and a gate of the virtual ground clamp **328** may be coupled to the common mode bias voltage (V.sub.cm) **226**.

[0092] As illustrated by the sensing scheme of FIG. **16**, the local passive matrix anode **320** may be virtually grounded and a cathode coupled to a micro-LED **182** being tested by the circuitry **322** may be connected to the bias display voltage **330**. In certain instances, coupling the cathode to a low impedance, such as the bias display voltage **330**, may reduce or eliminate settling issues.

[0093] FIG. **17** is a schematic diagram of an embodiment of the local passive matrix anode **360** coupled to the circuitry **322** to implement the sensing scheme to identify a failed micro-LED **251** of the micro-LED display **12**. In particular, FIG. **17** is intended to illustrate anode and cathode connections used to implement the sensing scheme disclosed herein. For example, FIG. **17** includes a first set of micro-LEDs **362A** coupled to a first anode **364A** and a second set of micro-LEDs **362B** coupled to a second anode **364B**. The first set of micro-LEDs **362A** may include the first micro-LED **182A**. The local passive matrix anode **360** may also include a second set of micro-LEDs **362B** with a the second micro-LED **182B**. The second anode **364B** may be coupled to a second cathode switch **366B** that couples and/or disconnects the second anode **364B** to the first input of the analog opamp **224**.

[0094] To test the micro-LEDs **182** along the local passive matrix anode **360**, both the first cathode switch **366A** and the second cathode switch **366B** may close. In this way, the untested micro-LEDs **182** may be bootstrapped to the sensing circuitry input voltage. Additionally or alternatively, the first input of the analog opamp **224** may be coupled to the micro-LEDs **182** along the local passive matrix anode **360**. To select a respective micro-LED **182** along the local passive matrix anode **360**, the bias voltage switch **332** may close to couple the respective micro-LED **172** to the bias display voltage **330**. The remaining micro-LEDs **182** along the local passive matrix anode **360** may not be coupled to the bias display voltage **330** via respective bias voltage switches **332** coupled to the respective cathodes. As such, the analog opamp **224** may receive a voltage from the micro-LED **182** coupled to the bias voltage **188** to determine if the micro-LED **182** is a failed micro-LED **251**

or a functional micro-LED.

[0095] As discussed herein, the circuitry **322** may include the virtual ground clamp **328** and the resistor **334** to limit the amount of current received by the circuitry **322**. For example, the virtual ground clamp **328** may conduct if the current from the failed micro-LED **251** exceeds a threshold current.

[0096] FIG. **18** is a schematic diagram of an embodiment of the local passive matrix cathode **390** coupled to the circuitry **322** to implement the sensing scheme to identify a failed micro-LED **251** of the micro-LED display **12**. That is, FIG. **18** illustrates a cathode sensing scheme that may be used, in certain embodiments, in at least part of the sensing scheme. The circuitry **322** may use current sensing to identify a failed micro-LED **251**, where the current may be a direct current. Although not illustrated in FIG. **18**, the circuitry **322** may include a virtual ground clamp **328** to limit the amount of current received by the circuitry **322**.

[0097] The cathode sensing scheme may include a cascoded current mirror **392** that receives a current from a tested micro-LED **182**. The cascoded current mirror **392** may include a first input coupled to the tested micro-LED **182** and a second input coupled to the first input of the analog opamp **224**. If the tested micro-LED **182** is a failed micro-LED **251**, the cascoded current mirror **392** may receive current going across the failed micro-LED **251**. Additionally or alternatively, the cascoded current mirror **392** may receive a cascode voltage **400** from a second analog opamp **396** for comparison with the common mode bias voltage **226**. As illustrated, the second analog opamp **396** may include a first input coupled to a voltage output of a respective micro-LED **182** being tested, a second input coupled to a bias display voltage **398**, and an output equivalent to a cascode voltage **400**. The output of the second analog opamp **396** may be used to set the cathode voltage of the micro-LED **182** to a desired voltage equivalent to the bias display voltage **398**. The cascode voltage **400** may be used as a comparison to determine if the cathode voltage may be equivalent to the bias display voltage **398**. If the tested micro-LED is a failed micro-LED **251**, the current going into the cascoded current mirror **392** may be reflected to the analog opamp **224**. As such, a failed micro-LED **251** may be identified.

[0098] FIG. **19** is a schematic diagram of an embodiment of the local passive matrix cathode **420** coupled to the circuitry **322** to implement the sensing scheme to identify a failed micro-LED **251** of the micro-LED display **12**. The circuitry **322** may use voltage sensing and/or alternating current (e.g., modulation) to identify the failed micro-LED **251**. The circuitry **322** may use a cathode sensing scheme to identify the failed micro-LED **251**. The local passive matrix cathode **420** may include a shunt **424** coupled to the bias display voltage **398** and the bias voltage switch **332**. The shunt **424** may include a resistor coupled in parallel to the bias voltage switch **332**. The shunt **424** may provide transient resistor/capacitor settling and may operate periodically. The shunt **424** may divert a portion of the current around it. The bias voltage switch **332** may selectively couple the bias display voltage **330** to the local passive matrix cathode **420** and/or a micro-LED **182** for testing by the circuitry **322**.

[0099] If the tested micro-LED **182** has failed, closing the bias voltage switch **332** may cause current to flow from the tested micro-LED **182**. Additionally or alternatively, voltage may flow until the voltage of the local passive matrix cathode **420** may be equal to the failed micro-LED **251** current multiplied by the resistance value of the shunt **424**. The circuitry **322** may receive the current from the tested micro-LED **182** and determine that the tested micro-LED **182** may be a failed micro-LED **251**.

[0100] The circuitry **322** may include a capacitor **422**. The voltage flow caused by the failed micro-LED **251** may be coupled through the capacitor **422** to the analog opamp **224** before the bias voltage switch **332** resets the voltage of the local passive matrix cathode **420** back to the bias display voltage **398**. The bias voltage switch **332** may be instructed to open and/or close at a set frequency. The frequency may be determined based on the components of the circuitry **322**. For example, the frequency may be based on the resistance of the resistor **230** and/or the capacitance of

the capacitor **228**. By way of example, a capacitance of the capacitor **228** may be between 1 and 10 picoFarads (pF) and/or a resistance of the resistor **230** may be between 1 and 4 megaohms (M).

[0101] As such, the bias voltage switch **332** may modulate the voltage of the local passive matrix cathode **420** during the sensing operation and/or operation of the micro-LED display **12**.

[0102] FIG. **20** is a schematic diagram of an embodiment of the local passive matrix cathode **450** coupled to the circuitry **322** to implement the sensing scheme to identify a failed micro-LED **251** of the micro-LED display **12**. The circuitry **322** may use voltage sensing and an alternating current to identify the failed micro-LED **251**. The schematic diagram of the local passive matrix cathode **450** and the circuitry **322** of FIG. **20** is substantially similar to the schematic diagram of the local passive matrix cathode **420** and the circuitry described with respect to FIG. **19** except the shunt **424** is coupled in series with the bias display voltage **398** and the local passive matrix cathode **450** includes a first modulated switch **492** and a second modulated switch **494**. In particular, a first end of the shunt **424** may be coupled to the failed micro-LED **251** and a second end of the shunt **424** may be coupled to a bias display voltage **398**. Additionally or alternatively, the first end of the shunt **424** may be coupled to the first modulated switch **492** and the second end of the shunt **424** may be coupled to the second modulated switch **494**. The first modulated switch **492** and the second modulated switch **494** may be modulated when testing a micro-LED **182** to identify a failed micro-LED **251**. For example, closing the first modulated switch **492** and opening the second modulated switch **494** may couple the local passive matrix cathode **450** to the circuitry **322** for testing, while opening the first modulated switch **492** and closing the second modulated switch **494** may disconnect the local passive matrix cathode **450** from the circuitry **322**. As such, the circuitry **322** may test the micro-LEDs **182** to identify a failed micro-LED **251**.

[0103] FIG. **21** is a schematic diagram of image data **500** transmitted to the micro-LED display **12** to implement a compensation scheme to mitigate (e.g., compensate) for a failed micro-LED **251**. For example, a 1×1 compensation scheme may be used to compensate for the failed micro-LED **251**, a 1×8 compensation scheme may be used to compensate for the failed micro-LED **251** and the other micro-LEDs along the same anode, and/or any suitable compensation may be used to reduce and/or eliminate perceivable visual image artifacts caused by the failed micro-LED **251**. The image data **500** may be adjusted to hide an isolated pixel defect caused by the failed micro-LED **251** by adjusting luminance of surrounding pixels.

[0104] As illustrated by FIG. **21**, a 7×7 compensation scheme may be applied to the image data **500** to reduce or eliminate image artifacts caused by a failed micro-LED **251**. The image data **500** may include data for the display pixels **77** positioned in columns and rows. As discussed herein, the display pixels **77** may correspond to respective micro-LEDs **182** in the micro-LED display **12**. For example, a failed display pixel **501** may correspond to the failed micro-LED **251** that may be identified using the compensation scheme discussed herein. The image data sent to the failed display pixel **501** may be set to a gray level 0 to reduce current stress on the respective micro-LED **182**. That is, the failed display pixel **501** may not emit light.

[0105] The failed display pixel **501** may be surrounded by functioning display pixels **502**. The image data **500** may be adjusted to adjust a luminance corresponding to the functional display pixels **502**. For example, image data corresponding to a first group **504** of display pixels directly adjacent to the failed display pixel **501** may include increased luminance, the image data corresponding to a second group **506** of display pixels adjacent to the first group **504** of display pixels may include decreased luminance, and the image data corresponding to a third group **508** of display pixels adjacent to the second group **506** may include increased luminance. To this end, a first gain mask may be applied to the image data corresponding to the first group **504** of display pixels, a second gain mask may be applied to image data corresponding to the second group **506** of display pixels, a third gain mask may be applied to image data corresponding to the third group **508** of display pixels. That is, current for the failed display pixel **501** may be reduced and distributed to the surrounding functioning display pixels **502**. In other instances, a gain map corresponding to a

7×7 arrangement of display pixels may be generated and applied to the image data. With the adjusted luminance, image artifacts may be reduced or eliminated from the frame of image content displayed on the micro-LED display **12**.

[0106] FIG. **22** is a flowchart of an example method **540** for identifying and mitigating (e.g., compensating) a failed micro-LED. While the process of FIG. **22** is described using process blocks in a specific sequence, it should be understood that the present disclosure contemplates that the described process blocks may be performed in different sequences than the sequence illustrated, and certain described process blocks may be skipped or not performed altogether.

[0107] At block **542**, processing circuitry (e.g., the processor core complex, image processing circuitry, image compensation circuitry, display circuitry) identifies a failed micro-LED. For example, the micro-LEDs of the micro-LED display may be individually tested to identify a failed micro-LED. For testing, a first switch corresponding to the current source and/or the analog power supply may open to block current from flowing to the micro-LEDs and a second switch corresponding to test circuitry for testing may close to create a path between the circuitry and the micro-LEDs. To test a micro-LED, a switch corresponding to the micro-LED may close to form a path between the testing circuitry and the micro-LED being tested. Additionally or alternatively, switches corresponding to micro-LEDs not being tested may open to block voltage from flowing to the remaining micro-LEDs. The micro-LED may be coupled to a bias voltage that provides a voltage to the micro-LED. If the analog opamp receives a current from the micro-LED and outputs an analog voltage, then the micro-LED may be determined to be failed. Additionally or alternatively, a position of the failed micro-LED may be determined.

[0108] At block **544**, the processing circuitry pre-charges a cathode corresponding to the failed micro-LED prior to operation. The cathode may be charged to a voltage equivalent to a voltage of the anode to reduce or eliminate current draw by the failed micro-LED. To this end, the micro-LED may be coupled to a capacitor in series, and the capacitor may store the pre-charge voltage. The cathode may be pre-charged and/or floated while other rows may be emitting light. As such, when the row including the failed micro-LED emits light, the cathode may be pre-charged and/or floated prior to driving the micro-LEDs coupled to the cathode to emit light, thereby reducing or eliminating current pull by the failed micro-LED.

[0109] At block **546**, the processing circuitry provides current compensation to an anode to offset current drawn by the failed micro-LED during the operation. In certain instances, the current provided to the anode containing the failed micro-LED may be increased to compensate for current drawn by the failed micro-LED. In other instances, the current directed to the failed micro-LED may be distributed to remaining micro-LEDs in the anode with the failed micro-LED. That is, the current may be redistributed to the micro-LEDs coupled with the failed micro-LED along the same anode. As such, image artifacts may be reduced and/or eliminated in a frame of image content displayed on the micro-LED.

[0110] FIG. **23** is a flowchart of an example method **570** for compensating for a failed micro-LED. While the process of FIG. **23** is described using process blocks in a specific sequence, it should be understood that the present disclosure contemplates that the described process blocks may be performed in different sequences than the sequence illustrated, and certain described process blocks may be skipped or not performed altogether.

[0111] At block **572**, processing circuitry identifies a failed micro-LED, similar to block **542** described with respect to FIG. **22**.

[0112] At block **574**, the processing circuitry closes a switch corresponding to a defective micro-LED to short circuit around the micro-LED. For example, the micro-LEDs may be coupled in parallel to a respective switch. If the switch is open, then current and/or voltage may flow to the micro-LED. If the switch is closed, then the current and/or voltage may flow through the switch, since the switch provides a path with less resistance in comparison to the path provided by the micro-LED. As such, the failed micro-LED may not be driven and may not emit light.

[0113] At block 576, the processing circuitry pre-charges a cathode corresponding to the failed micro-LED prior to operation, similar to block 544 described with respect to FIG. 22. For example, the cathode may be pre-charged and then floated while other rows may be emitting light.

[0114] At block 578, the processing circuitry provides current compensation to an anode to offset the current drawn by the short circuit during operation, similar to block 546 described with respect to FIG. 22. For example, the current source may increase the current provided to the anode. In another example, the current intended for the failed micro-LED may be distributed among the remaining micro-LEDs. Still in another example, the image data may be adjusted for surrounding micro-LEDs, as such, the current corresponding to the surrounding micro-LEDs may be adjusted.

[0115] The specific embodiments described above have been shown by way of example, and it should be understood that these embodiments may be susceptible to various modifications and alternative forms. It should be further understood that the claims are not intended to be limited to the particular forms disclosed, but rather to cover all modifications, equivalents, and alternatives falling within the spirit and scope of this disclosure.

[0116] It is well understood that the use of personally identifiable information should follow privacy policies and practices that are generally recognized as meeting or exceeding industry or governmental requirements for maintaining the privacy of users. In particular, personally identifiable information data should be managed and handled so as to minimize risks of unintentional or unauthorized access or use, and the nature of authorized use should be clearly indicated to users.

[0117] The techniques presented and claimed herein are referenced and applied to material objects and concrete examples of a practical nature that demonstrably improve the present technical field and, as such, are not abstract, intangible or purely theoretical. Further, if any claims appended to the end of this specification contain one or more elements designated as “means for [perform]ing [a function] . . . ” or “step for [perform]ing [a function] . . . ”, it is intended that such elements are to be interpreted under 35 U.S.C. 112(f). However, for any claims containing elements designated in any other manner, it is intended that such elements are not to be interpreted under 35 U.S.C. 112(f).

Claims

1. A display system, comprising: a plurality of light emitting diodes coupled to a common anode; and a plurality of first switches respectively coupled to the plurality of light emitting diodes, wherein a first switch of the plurality of first switches is coupled in parallel to a first light emitting diode of the plurality of light emitting diodes, and wherein the first switch is configured to short the first light emitting diode of the plurality of light emitting diodes through a defined resistance.
2. The display system of claim 1, wherein the first light emitting diode is configured to be coupled to a cathode, and wherein the cathode is configured to be pre-charged and floated based on the first light emitting diode being a failed light emitting diode.
3. The display system of claim 1, wherein the plurality of light emitting diodes are configured to be driven with an increased emission time based on the first light emitting diode being a failed light emitting diode.
4. The display system of claim 1, comprising sensing circuitry configured to: identify the first light emitting diode as a failed light emitting diode based on receiving a current from the first light emitting diode when the first light emitting diode is driven by a voltage less than a turn-on voltage of the first light emitting diode.
5. The display system of claim 4, comprising an additional switch configured to couple the plurality of light emitting diodes to a power source, and wherein the power source is configured to drive each light emitting diode of the plurality of light emitting diodes for the sensing circuitry to identify the failed light emitting diode.
6. The display system of claim 4, wherein the sensing circuitry comprises one or more light

emitting diode selection switches, a resistor, a capacitor, an analog opamp, a power switch, a cascode circuit mirror, and/or a modulated switch.

7. The display system of claim 1, comprising display circuitry configured to: receive image data for the first light emitting diode; and set the image data for the first light emitting diode to gray level zero based on the first light emitting diode being a failed light emitting diode.

8. A display, comprising: a plurality of light emitting diodes coupled to a common anode; a power source configured to drive a light emitting diode of the plurality of light emitting diodes to emit light; a switch configured to couple the light emitting diode to the power source; and sensing circuitry configured to identify the light emitting diode as a failed light emitting diode based on a current from the light emitting diode when the power source is driving the light emitting diode.

9. The display of claim 8, wherein the sensing circuitry comprises a virtual ground clamp coupled to the light emitting diode configured to limit a magnitude of a voltage received by the sensing circuitry from the light emitting diode.

10. The display of claim 8, comprising an additional switch coupled to the light emitting diode in parallel, wherein the additional switch is configured to short the light emitting diode based on identifying the failed light emitting diode, and wherein the additional switch comprises a defined resistance.

11. (canceled)

12. The display of claim 8, comprising a cathode coupled to the light emitting diode, wherein the cathode is configured to be pre-charged and floated based on identifying the failed light emitting diode.

13. The display of claim 8, comprising processing circuitry configured to: receive image data corresponding to the light emitting diode; identify a position corresponding to the light emitting diode within the image data; and set the image data corresponding to the light emitting diode to a gray level zero based on identifying the light emitting diode as the failed light emitting diode.

14. The display of claim 13, comprising a plurality of light emitting diodes, wherein the processing circuitry is configured to: apply a gain mask to additional image data adjacent to the image data corresponding to the failed light emitting diode, wherein the gain mask is configured to increase current for driving the plurality of light emitting diodes to emit light.

15. A display device, comprising: a plurality of light emitting diodes coupled to a common anode; and processing circuitry configured to: identify a first light emitting diode of the plurality of light emitting diodes as a failed light emitting diode based on a current leaked from the first light emitting diode; receive image data corresponding to the plurality of light emitting diodes; set a portion of the image data corresponding to the first light emitting diode to gray level zero based on identifying the first light emitting diode as the failed light emitting diode; and apply a gain mask to a remaining portion of the image data corresponding to a set of light emitting diodes of the plurality of light emitting diodes adjacent to the first light emitting diode.

16. The display device of claim 15, wherein the processing circuitry is configured to drive the set of light emitting diodes with an increased current based on the gain mask.

17. The display device of claim 15, comprising a switch coupled in parallel to the first light emitting diode, wherein the switch is configured to short the first light emitting diode through a defined resistance.

18. The display device of claim 17, wherein the processing circuitry is configured to drive the set of light emitting diodes with an increased duty cycle based on the first light emitting diode being the failed light emitting diode.

19. The display device of claim 15, wherein the processing circuitry is configured to identify the first light emitting diode as the failed light emitting diode by: instructing a switch to couple a power source to the first light emitting diode; instructing the power source to drive a voltage to the first light emitting diode; and receiving the current leaked from the first light emitting diode.

20. The display device of claim 15, wherein the processing circuitry is configured to instruct a

power source to pre-charge and float a cathode coupled to first light emitting diode.

21. The display of claim 12, wherein the cathode is selectively coupled to a bias voltage and a negative voltage, and wherein the plurality of light emitting diodes are configured to be driven to emit light when the cathode is coupled to the negative voltage.
