

US Patent & Trademark Office

Patent Public Search | Text View

United States Patent	12413076
Kind Code	B2
Date of Patent	September 09, 2025
Inventor(s)	Gopalakrishnan; Vishal Anand Aisur et al.

Systems and methods for microgrid-power distribution management when distributed energy resources transition between operating modes

Abstract

Systems and methods for microgrid-power distribution management when distributed energy resources transition between operating modes. The system includes a fuel cell system that generates DC power and a multi-mode inverter system that operates in one of the operating modes based on an availability status of grid, a site controller that receives electrical signal(s) facilitates the multi-mode inverter system to transition between the operating modes, generates a control signal based at least on an load operating input and transitioning of the multi-mode inverter system, a DC braking module that turns ON in response to receipt of the control signal, dissipates excess energy from the DC bus when the DC voltage value is greater than a threshold voltage value and energy storage module that turns ON in response to receipt of the control signal, supplies power to the DC bus, when the DC voltage value is less than the load operating input.

Inventors: Gopalakrishnan; Vishal Anand Aisur (San Jose, CA), Gurunathan; Ranganathan (San Jose, CA), Pmsvvsv; Prasad (San Jose, CA), Chennakesavula; Ranges Babu (San Jose, CA), Krishna; Borra Mohan (San Jose, CA), Govindan; Rajkannu (San Jose, CA)

Applicant: BLOOM ENERGY CORPORATION (San Jose, CA)

Family ID: 94125687

Assignee: BLOOM ENERGY CORPORATION (San Jose, CA)

Appl. No.: 18/755295

Filed: June 26, 2024

Prior Publication Data

Document Identifier	Publication Date
US 20250007293 A1	Jan. 02, 2025

Foreign Application Priority Data

IN 202341043106 Jun. 27, 2023

Publication Classification

Int. Cl.: H02J3/38 (20060101); H02J3/28 (20060101)

U.S. Cl.:

CPC H02J3/388 (20200101); H02J3/28 (20130101); H02J3/381 (20130101); H02J2300/30 (20200101)

Field of Classification Search

CPC: H02J (2300/30); H02J (3/28-322); H02J (3/38-50); H02J (1/10-12); H02J (1/14)

References Cited

U.S. PATENT DOCUMENTS

Patent No.	Issued Date	Patentee Name	U.S. Cl.	CPC
10596919	12/2019	Srinivasan et al.	N/A	N/A
10873099	12/2019	Gurunathan	N/A	H01M 8/04604
10998833	12/2020	Ilic et al.	N/A	N/A
11527964	12/2021	Naiknaware et al.	N/A	N/A
11990790	12/2023	Pmsvsv et al.	N/A	N/A
2002/0060556	12/2001	Wall	322/29	H02J 3/38
2011/0004357	12/2010	Mathiowetz	700/295	H02J 3/381
2011/0222320	12/2010	Delmerico	363/37	H02J 3/32
2019/0052083	12/2018	Lucas, Jr.	N/A	H02J 3/46
2020/0169088	12/2019	Myers	N/A	H02J 7/34
2022/0094160	12/2021	Zdrazil	N/A	H02J 7/0068
2022/0311354	12/2021	Gerçek	N/A	H02J 3/381
2023/0205146	12/2022	Williams	700/287	H02J 7/0047
2023/0261517	12/2022	Pulikanti	307/43	H02J 3/32
2023/0383729	12/2022	Shenoy	N/A	H02J 3/381

OTHER PUBLICATIONS

Chae et al., Cooperative operation method of two battery systems at Microgrid system, 3rd IEEE International Symposium on Power Electronics for Distributed Generation Systems (PEDG) 2012, Date of Conference: Jun. 25-28, 2012, pp. 872-877. cited by applicant

Khederzadeh et al., Frequency control of microgrids in autonomous mode by a novel control scheme based on droop characteristics, Electric Power Components and Systems, Electric Power Components and Systems, Dec. 10, 2012, pp. 16-30. cited by applicant

Goyal et al., Overload prevention in an autonomous microgrid using battery storage units, 2014 IEEE PES General Meeting | Conference & Exposition, Date of Conference: Jul. 27-31, 2014, 05 pages, IEEE. cited by applicant

Shi et al., A method for microgrid connected fuel cell inverters seamless transitions between

Primary Examiner: Barnie; Rexford N

Assistant Examiner: Shiao; David A

Attorney, Agent or Firm: Evergreen Valley Law Group

Background/Summary

TECHNICAL FIELD

(1) The present invention relates to the field of power systems and, more particularly, to systems and methods for managing power distribution in a microgrid site when distributed energy resources transition between operating modes such as a grid-following mode and a grid-forming mode.

BACKGROUND

(2) With the ever-increasing demand for energy consumption, Distributed Generation (DG) is continuing to play a crucial role in balancing the realm of energy supply and demand. DG technologies take advantage of Distributed Energy Resources (DERs). DERs may be micro-turbines, solar photovoltaic systems, fuel cells stack, wind energy systems, etc. Further, interconnection and interoperability of DERs with an electrical grid need to abide by certain standards set by the Institute of Electrical and Electronics Engineers (IEEE) Standards Association. Such standards ensure reliable and safe transmission grid facilities and facilitate their operations. Control and management strategies for appropriate supply and distribution of power to the grid and a load through a microgrid that is using such DERs are needed.

(3) With an ever-increasing incidence of blackouts in distribution systems connected to the grid caused by a range of natural and man-made calamities, frequent and essential isolation and reconnection of loads also increases. It is noted that due to the isolation and reconnection of the loads to the grid, the power conversion systems connected to the DERs transition between operating modes. These operating modes may be the grid-following mode (also termed as ‘grid parallel mode’) and the grid-forming mode (also termed as ‘island volt mode’). The grid-following mode involves some level of power export or import from the grid based on the loads connected, whereas, in grid-forming mode, the generated power only comes from the DERs and always follows the load, as the grid is disconnected from the load.

(4) Furthermore, the DERs and their associated power conversion systems are connected to the grid via grid isolation devices (also termed as ‘Intentional Island Interconnection Devices’) which basically are circuit breakers whose operation is controlled by a combination of a switch and a controller. Examples of grid isolation devices may include a Multi-mode Switch Board (MMSB) and an Automatic Transfer Switch Board (ATSB).

(5) FIG. 1A provides an example of a prior art environment **100** indicating operation and power flow in a microgrid site operating in a grid-following mode. FIG. 1B provides an example of a prior art environment **100** indicating operation and power flow in a microgrid site operating in a grid-forming mode. The prior art environment **100** includes the grid **102**, at least one load, e.g., a critical load **104** and a non-critical load **106**, and a DER such as a fuel cell system **108**. The connection of the at least one load **104** or **106** to the fuel cell system **108** forms the microgrid site. The prior art environment **100** also includes an ATSB **110** used as the grid isolation switch. The ATSB **110** includes an industry-standard Automatic Transfer Switch (ATS) **112**, an electrically operated Wrap Around Circuit Breaker (WACB) **114**, and one or more supporting auxiliary circuits

(not shown in FIG. 1A).

(6) Further, the ATS **112** is shown in FIG. 1A and FIG. 1B is a three-position ATS and is typically used in three positions, namely, a “position N” denoting Normal, a “position E” denoting Emergency, and an intermediate position (not shown) between the “position N” and the “position E”. The ATS **112** also includes a “terminal L” which is connected to the critical load **104**. The terminal ‘L’ is provided with a connector **116** that switches between the three positions as shown in FIG. 1A and FIG. 1B.

(7) Further, Input/Output (I/O) signals **118** are exchanged between the ATSB **110** and a controller (not shown in FIG. 1A and FIG. 1B) associated with the fuel cell system **108**. The I/O signals **118** assists the controller to determine the operating mode of the microgrid site or the power conversion system being one of the grid-following mode and the grid-forming mode.

(8) In the grid-following mode, the connector **116** connects the at least one load to the grid **102** as the connector **116** gets positioned at the “position N”. When the connector **116** is positioned at the “position N”, the fuel cell system **108** powers the at least one load such as the critical load **104** by operating as a current source through the WACB **114** as shown by a power flow signal **120** in FIG. 1A. If a load operating power requirement of the critical load **104** is less than a power supplying capacity of the fuel cell system **108**, then excess power is fed back to the grid **102** through the “position N” in the ATS **112**, as shown by a power flow signal **122** in FIG. 1A.

(9) During grid outage, the WACB **114** is opened and the ATS **112** transfers the connector **116** from the “position N” to the “position E” as shown in FIG. 1B, and the fuel cell system **108** begins to power the critical load **104** as a voltage source. This is because, during a power outage, there is a transition from the grid-following mode to the grid-forming mode. Further, the flow of power in the grid-forming mode is shown by a power flow signal **124** in FIG. 1B. Further, when the grid **102** is available again, there is a transition from the grid-forming mode to the grid-following mode, upon switching the position of the connector **116** from the “position E” to the “position N” by the ATS **112**.

(10) To that note, it may be observed that it takes a finite non-zero transfer time during these transitions since the ATS **112** has to switch the position of the connector **116** between the “position N” and the “position E”. During these transitions, the power output from the fuel cell system **108** shall drop to zero which is explained with the help of FIG. 2.

(11) FIG. 2 is a timing diagram **200** showing a sequence of events during the transition between the grid-following mode and the grid-forming mode in the prior art environment **100** of FIGS. 1A and 1B. The I/O signals **118** include a WACB Auxiliary (WACB Aux or WACB AUX) signal, a Grid Good (GRID GOOD) signal, and a WACB System Command (WACB SC) signal. The WACB Aux signal refers to a signal that indicates a status of the WACB **114** such as the WACB **114** being ‘ON’ or ‘OFF’, or ‘closed’ or ‘open’. The WACB Aux signal is transmitted from the WACB **114** of the ATSB **110** to the controller, for the controller of the fuel cell system **108** to know the status of the WACB **114**. The Grid Good signal refers to a signal that indicates whether the grid **102** is good and working or not. The Grid Good signal is transmitted from the ATS **112** of the ATSB **110** to the controller, for the controller to know whenever the grid **102** goes bad. Further, the WACB SC signal refers to a signal that corresponds to a system command transmitted from the controller to the WACB **114** commanding the WACB **114** to open or close based on the availability of the grid **102**.

(12) It may be observed from FIG. 2 that, the status of the I/O signals **118** such as the WACB Aux signal, the Grid Good signal, and the WACB SC signal collectively indicate whether the operating mode of the power conversion system of the fuel cell system **108** is transitioning from the grid-following mode to the grid-forming mode (see **202**) or from the grid-forming mode to the grid-following mode (see **204**). Therefore, when transitioning from the grid-following mode to the grid-forming mode, i.e., when the grid **102** goes bad, the I/O signals **118** transitions from “High” to “Low”. FIG. 2 shows finite time instances from “t.sub.1” to “t.sub.5” which correspond to a

sequence of events happening as the grid voltage (Grid V or GRID V) drops and the power conversion system of the fuel cell system **108** transitions from being a current source (in the grid-following mode) to being a voltage source (in the grid-forming mode).

(13) Some of the sequence of events includes transitioning the I/O signals **118** from “High” to “Low”. The events also include transitioning signals such as Emergency voltage (Emer V or EMER V), a load voltage (Load V or LOAD V), and a DER power (DER POWER) as illustrated in FIG. 2. Those signals correspond to Emergency voltage supplied to the critical load **104**, the load voltage at a terminal of the at least one load, and Direct Current (DC) power generated by the fuel cell system **108** respectively. Moreover, the total time for the transition from the grid-following mode to the grid-forming mode, corresponds to $t_{sub.GP_to_IV}$ which is given as $t_{sub.GP_to_IV}=t_{sub.1}+t_{sub.2}+t_{sub.3}+t_{sub.4}+t_{sub.5}$ ”.

(14) Subsequently, when the grid **102** is restored, the operating mode may transition from the grid-forming mode to the grid-following mode (see **204**). As soon as the grid voltage returns, the ATS112 automatically switches the connector **116** from the “position E” to the “position N”. The I/O signals **118** and other signals (Load V and DER power) shall changeover from “Low” to “High” (see **204**). The total time for transitioning from the grid-forming mode to the grid-following mode, corresponds to $t_{sub.IV_to_GP}$ which is given as $t_{sub.IV_to_GP}=t_{sub.6}+t_{sub.7}+t_{sub.8}+t_{sub.9}$ ”. For instance, a typical value of $t_{sub.GP_to_IV}$ for many of the micro-grid sites shall be between 1 to 15 seconds. The typical value of $t_{sub.IV_to_GP}$ shall be in the range of 300 seconds where the majority of time is dominated by the grid reconnect time, $t_{sub.9}$.

(15) Thus, in such prior art systems, it may be noted that, during these transitions (both grid-following mode to grid-forming mode (see **202**) and from grid-forming mode to grid-following mode (see **204**)), the power from the fuel cell system **108** (i.e., the DER power) changes from “Full load” to “No load” (see **206**) and hence the fuel cell system **108** is turned off instantly which is undesirable. These transients have a direct impact on the long-term life and reliability of power modules such as fuel cell systems. Also, any change in the power output of the fuel cell system **108** results in certain momentary temperature changes inside the fuel cell system **108**, for example, a Solid Oxide Fuel Cell (SOFC). This further results in the degradation of the SOFC as temperature changes have some reliability impact. Further, when transitioning from the grid-following mode to grid-forming mode (see **202**), as the fuel cell system **108** is instantly turned OFF, during the Black start period, the fuel cell system **108** is unable to supply power with its full capacity to the load, as it is ramping up during this process (see **208**). For example, the fuel cell system **108** may be limited to 100 kilowatts (kW) even though the supply capacity of the fuel cell system **108** is 300 kW.

(16) Further, in most of these kinds of sites, the operating requirements of the loads connected on the output bus are typically less than the grid supply capacity, yet, in most cases, more than the supply capacity of the DERs. In such cases, one approach is to manage load when transferring from the grid parallel mode to an island volt mode. Load management may be carried out by segregating loads such that loads less than the supply capacity of the DERs, are connected on a separate feeder and additional loads that can be shed during grid events shall be on the grid **102**. Moreover, power management of the fuel cell system **108** is also essential to match the load requirements.

(17) Hence, there exists a need for systems and methods for regulating the change in the power output of the DERs such as the fuel cell systems while switching between the operating modes (grid-following mode and the grid-forming mode).

SUMMARY

(18) Various embodiments of the present disclosure provide systems and methods for managing power distribution in a microgrid site when distributed energy resources transition between at least two operating modes.

(19) In an embodiment, a system is disclosed that includes a fuel cell system and a multi-mode inverter system electrically connected to the fuel cell system via a Direct Current (DC) bus. The

system further includes a site controller electronically coupled to a plurality of electrical points and a plurality of electrical components in a microgrid site. Further, the system includes a DC braking module and an energy storage module electrically connected to the DC bus. The fuel cell system is configured to generate DC power in the microgrid site. The multi-mode inverter system is configured to operate in one of the at least two operating modes based at least on an availability status of a grid electrically coupled to the microgrid site, for supplying power to at least one load. The at least two operating modes includes a grid-following mode and a grid-forming mode. The site controller is configured to receive at least one of a plurality of electrical signals from the plurality of electrical points and the plurality of electrical components, and a load operating input corresponding to the at least one load connected to the microgrid site. The site controller is further configured to facilitate the multi-mode inverter system to transition between the at least two operating modes based at least on the plurality of electrical signals. Further, the site controller is configured to generate a control signal based at least on the load operating input and the transitioning of the multi-mode inverter system between the at least two operating modes. The DC braking module is configured to turn ON in response to the receipt of the control signal generated by the site controller. The DC braking module is configured to receive a DC voltage value from the DC bus. The DC braking module is further configured to dissipate excess energy, via energy dissipating circuitry, from the DC bus when the DC voltage value is greater than a threshold voltage value. The energy storage module is configured to turn ON in response to the receipt of the control signal. The energy storage module is configured to supply power to the DC bus for supporting the at least one load, when the DC voltage value in the DC bus is less than the load operating input.

(20) In another embodiment, a method is disclosed that includes receiving at least one of a plurality of electrical signals from a plurality of electrical points and a plurality of electrical components, and a load operating input corresponding to at least one load connected to a microgrid site. The method further includes facilitating a multi-mode inverter system to transition between at least two operating modes based at least on the plurality of electrical signals. The at least two operating modes include a grid-following mode and a grid-forming mode. Further, the method includes generating a control signal based at least on the load operating input and the transitioning of the multi-mode inverter system between the at least two operating modes. Furthermore, the method includes transmitting the control signal to one of a DC braking module and an energy storage module based at least on the load operating input and the transitioning of the multi-mode inverter system between the at least two operating modes, the control signal indicating one of activation and deactivation of one of the DC braking module and the energy storage module for regulating DC voltage on the DC bus.

Description

BRIEF DESCRIPTION OF THE FIGURES

- (1) For a more complete understanding of example embodiments of the present technology, reference is now made to the following descriptions taken in connection with the accompanying drawings in which:
- (2) FIG. 1A provides an example of a prior art environment indicating operation and power flow in a microgrid site operating in a grid-following mode;
- (3) FIG. 1B provides an example of a prior art environment indicating operation and power flow in a microgrid site operating in a grid-forming mode;
- (4) FIG. 2 is a timing diagram showing a sequence of events during a transition between the grid-following mode and the grid-forming mode in the prior art environment of FIGS. 1A and 1B;
- (5) FIG. 3A illustrates an environment related to at least some examples of the present disclosure;

- (6) FIG. 3B represents an operating environment of a system proposed in the present disclosure;
- (7) FIG. 3C represents another operating environment indicating another scenario of the operation of a system proposed in the present disclosure;
- (8) FIG. 3D represents another environment of a system proposed in the present disclosure;
- (9) FIG. 4A represents an operating environment related to at least some examples of the present disclosure;
- (10) FIG. 4B is a timing diagram showing a sequence of events during the transition between the grid-following mode and the grid-forming mode for the environment of FIG. 4A in accordance with an embodiment of the present disclosure;
- (11) FIG. 5 is a single line diagram representing a circuitry of a Direct Current (DC) braking module positioned on a DC bus in accordance with an embodiment of the present disclosure;
- (12) FIG. 6 represents a DC braking module control architecture in accordance with an embodiment of the present disclosure;
- (13) FIG. 7 represents an environment illustrating different types of Distributed Energy Resources (DERs) powering a common load in accordance with an embodiment of the present disclosure; and
- (14) FIG. 8 is a flowchart illustrating a method for microgrid-power distribution management when transitioning between operating modes of the DERs in accordance with an embodiment of the present disclosure.
- (15) The drawings referred to in this description are not to be understood as being drawn to scale except if specifically noted, and such drawings are only exemplary in nature.

DETAILED DESCRIPTION

- (16) In the following description, for purposes of explanation, numerous specific details are set forth in order to provide a thorough understanding of the present disclosure. It will be apparent, however, to one skilled in the art that the present disclosure can be practiced without these specific details. In other instances, systems and methods are shown in block diagram form only in order to avoid obscuring the present disclosure.
- (17) Reference in this specification to “one embodiment” or “an embodiment” means that a particular feature, structure, or characteristic described in connection with the embodiment is included in at least one embodiment of the present disclosure. The appearance of the phrase “in one embodiment” in various places in the specification does not necessarily refer to the same embodiment, nor are separate or alternative embodiments mutually exclusive of other embodiments. Moreover, various features are described which may be exhibited by some embodiments and not by others. Similarly, various requirements are described which may be requirements for some embodiments but not for other embodiments.
- (18) Moreover, although the following description contains many specifics for the purposes of illustration, those skilled in the art will appreciate that many variations and/or alterations to those specific details are within the scope of the present disclosure. Similarly, although many of the features of the present disclosure are described in terms of each other, or in conjunction with each other, those skilled in the art will appreciate that many of these features can be provided independently of other features. Accordingly, this description of the present disclosure is set forth without any loss of generality to, and without imposing limitations upon, the present disclosure.
- (19) The terms “grid”, “public grid”, “electrical grid”, “main grid”, “power grid”, and “utility” are generally used interchangeably throughout the description, and they refer to an interconnected network of one or more components for electricity delivery from producers such as power stations to consumer loads.
- (20) The term “microgrid” refers to a local electrical grid with defined boundaries, acting as a single and controllable entity that is usually attached to a main grid but is also able to function independently.
- (21) The term “site controller” refers to a control unit configured to control one or more electrical devices, one or more electronic devices, one or more switches, one or more units, elements, or

components, a plurality of electrical sensors, and/or a plurality of electronic sensors, based on one or more operating modes and one or more operating parameters of the microgrid site. The one or more operating modes may include a grid-following mode and a grid-forming mode. The one or more operating parameters may include current, voltage, power, frequency, etc.

(22) The terms “grid-following mode” and “grid parallel mode” may be used interchangeably throughout the description, and they may refer to a mode of operation of an inverter in a power conversion system receiving power from a Distributed Energy Resource (DER) (e.g., a fuel cell), in which the inverter tracks a voltage angle of the grid or the microgrid via an inverter controller to control an output (synchronizing to the grid or the microgrid) of the inverter.

(23) The terms “grid-forming mode”, “grid isolation mode”, “island volt mode”, and “islanding mode” may be used interchangeably throughout the description, and they may refer to a mode of operation of an inverter in a power conversion system receiving power from a DER (e.g., a fuel cell), in which the inverter actively controls the frequency and voltage output of the inverter independent of the grid via the inverter controller.

(24) The terms “power conversion system” and “multi-mode inverter system” may be used interchangeably throughout the description, and they refer to an electrical circuit that changes the electric energy from one form to another desired form optimized for a specific load. The change of the electrical energy may include Direct Current (DC) to DC or DC to Alternating Current (AC) depending upon a type of load connected to the microgrid. Further, the multi-mode inverter system may include an inverter and an inverter controller along with circuitry elements such as resistors, capacitors, inductors, etc., if needed.

(25) The term “inverter” refers to an electronic device that changes Direct Current (DC) to Alternating Current (AC).

(26) The term “inverter controller” refers to a controller that controls an operation of the inverter for regulating an output of the inverter to match certain conditions, by taking feedback from the output of the inverter or by taking input from the site controller.

(27) The terms “fuel cell system” and “fuel cell” may be used interchangeably throughout the description, and they refer to an electrochemical cell that converts the chemical energy of a fuel (often hydrogen) and an oxidizing agent (often oxygen) into electricity through a pair of redox reactions. The fuel cell system may contain a stack of multiple fuel cells.

(28) The terms “load”, “electric load”, and “consumer load” may be used interchangeably throughout the description, and they refer to any component of a circuit that consumes power or energy.

(29) The terms “grid isolation device” and “grid isolation unit” may be used interchangeably throughout the description, and they refer to a switching device capable of closing, carrying, and breaking the current under normal and abnormal circuit conditions within a specified time while transitioning between the grid-forming mode and the grid-following mode.

(30) The term “DC bus” refers to a common connection between two or more devices that operate in DC.

(31) The terms “DC braking module”, “DCBM”, “DBM” and “braking module” may be used interchangeably throughout the description, and they refer to an electrical and electronic circuit used to regulate voltage on the DC bus.

(32) The term “Black start” refers to the ability of generators to restart parts of the power system to recover from a blackout. This entails isolated power stations being started individually and gradually reconnected to one another to form an interconnected system again. More specifically, the Black start in a microgrid is followed by the islanding mode operation. The challenge during islanding mode operation is to manage the active and reactive power demand that results from the load behavior, and the active and reactive infeed that results from the DERs in the microgrid.

Overview

(33) Various example embodiments of the present disclosure provide systems and methods for

managing power distribution in a microgrid site when Distributed Energy Resources (DERs) transition between operating modes such as a grid-following mode and a grid-forming mode. Since the development of the concept of distributed generation, loads, such as critical loads and non-critical loads, receive a supply of power from the DERs in the presence of a grid that is connected to microgrids having the DERs or with the grid being disconnected from the microgrids upon the occurrence of any faults in the grid. The DERs may need Power Conversion Systems (PCSs) for controlling the supply of energy from the DERs in terms of a type of supply (DC or AC), a voltage level, etc., based on an availability of the grid and load operating requirements associated with the loads connected to the microgrids.

(34) Generally, when DERs are supplying power in the presence of the grid, the PCSs may be operating in the grid-following mode, and in the absence of the grid, in the grid-forming mode. However, as mentioned above, typical problems arise when transitioning between the two operating modes. Thus, in order to address the above-mentioned problems, short-term energy, and power buffering may be needed either for a load management mechanism to start or for the DERs to graciously change output power transmitted to the loads from the DERs. The present disclosure proposes the systems and the methods for providing such short-term energy and power buffering to such microgrids. Examples of DERs include a solar photovoltaic system, a fuel cell system, a wind energy system, etc.

(35) In a non-limiting example, the microgrid site is connected to the grid via a grid isolation device. The grid isolation device may be used in scenarios where the microgrid site may be islanded intentionally from the grid based on technical or economical conditions. Generally, the microgrid site includes the DER such as the fuel cell system associated with the power conversion system, and the site controller. In accordance with the present disclosure, the system provides a DC braking module to the microgrid site for providing short-term power buffering to the microgrid site.

(36) Therefore, in other words, it may be noted that the system includes the fuel cell system that generates DC power in the microgrid site. The system further includes a multi-mode inverter system (can also be termed as the power conversion system) electrically connected to the fuel cell system via a DC bus. The multi-mode inverter system operates in one of at least two operating modes based at least on an availability status of the grid, for supplying power to at least one load. The at least two operating modes include the grid-following mode and the grid-forming mode.

(37) Further, the system includes the site controller electronically coupled to a plurality of electrical points and a plurality of electrical components in the microgrid site. The site controller receives at least one of a plurality of electrical signals from the plurality of electrical points and the plurality of electrical components, and a load operating input corresponding to the at least one load connected to the microgrid site. The site controller facilitates the multi-mode inverter system to transition between the at least two operating modes based at least on the load operating input and the plurality of electrical signals. The load operating input may include a range of values corresponding to operating parameters associated with the at least one load. Further, the site controller generates a control signal during a startup of the system based at least on the load operating input and the transitioning of the multi-mode inverter system between the at least two operating modes.

(38) The system also includes the DC braking module electrically connected to the DC bus. The DC braking module turns ON in response to the receipt of the control signal. The DC braking module receives a DC voltage value from the DC bus, upon turning ON. The DC braking module dissipates excess energy, via energy dissipating circuitry, from the DC bus when the DC voltage value is greater than a threshold voltage value. The system further includes an energy storage module electrically connected to the DC bus. The energy storage module turns ON in response to the receipt of the control signal. The energy storage module supplies power to the DC bus for supporting the at least one load, when the DC voltage value on the DC bus is less than the load operating input.

(39) It may be understood that the control signal may be transmitted to one of the DC braking

module and the energy storage module based at least on the transitioning of the load operating input and the multi-mode inverter system between the at least two operating modes. The control signal may be indicating one of activation (turn ON) and deactivation (turn OFF) of one of the DC braking module and the energy storage module for regulating DC voltage on the DC bus.

(40) In an embodiment, the DC braking module may include a DC mid-bus capacitor sub-module, a DBM controller sub-module, and a DC chopper sub-module electrically connected with each other. Also, the energy dissipating circuitry may correspond to the DC chopper sub-module.

(41) Various embodiments of the present disclosure offer multiple advantages and technical effects. For instance, the introduction of the DC braking module on the DC bus or the intermediate DC buses of the microgrid site provide benefits such as momentary buffering of the DERs when transitioning from the grid-following mode to the grid-forming mode. During this time, loads can be managed and decreased to the DERs' capacity, and then the switch to the grid-forming mode can be made smoothly without affecting the DERs' output power. Additionally, this offers the feature of enabling a full step load on the DERs during the Black start phase.

(42) Further, during the transition from the grid-forming mode to the grid-following mode, the DC braking module enables a graceful turn OFF of the DERs instead of sudden shutdown which can cause thermal shock to the DERs. Furthermore, the rating on DC braking resistors ensures a pulsed operation of the DC braking module for shorter periods of time, thereby providing intermittent pulse energy dissipation capability to the DERs for reducing excess energy on the intermediate DC buses.

(43) Therefore, the main technical advantage of the present invention is in the momentary support of the DERs to take up load equivalent to their rating if the amount of time for mode transitions is much smaller. Without the DC braking module, in order to achieve the same step load capability during mode transitions would require more energy buffer modules (energy storage modules). Also, the DC braking module plays a crucial role in absorbing energy in the microgrid sites when inverters from different manufacturers are powering a common load.

(44) FIG. 3A illustrates an environment **300** related to at least some examples of the present disclosure. Although the environment **300** is presented in one arrangement, other embodiments may include the parts of the environment **300** (or other parts) arranged differently depending on, for example, a system for management of power distribution in a microgrid site when transitioning between at least two operating modes of distributed energy resources (DERs). The at least two operating modes may include a grid-following mode and a grid-forming mode. For instance, the DERs may include a solar photovoltaic system, a fuel cell system, a wind energy system, etc.

(45) The environment **300** illustrated in FIG. 3A includes a plurality of fuel cell systems **302(1)**, **302(2)**, . . . **302(N)** ('N' is a natural number) (hereinafter, collectively referred to as 'fuel cell systems **302**'). Each of the fuel cell systems **302** is configured to generate Direct Current (DC) electrical power. Examples of the fuel cell systems **302** include Solid Oxide Fuel Cell (SOFC) systems, Proton Exchange Membrane Fuel Cell (PEMFC) systems, Molten Carbonate Fuel Cell (MCFC) systems, and/or combinations of SOFC, PEMFC and MCFC systems, etc.

(46) In one embodiment, the fuel cell systems **302** are connected to a central power conversion system (not shown). In another embodiment, each of the fuel cell systems **302(1)**-**302(N)** may be connected to a respective power conversion system (e.g., a power conversion system **304** connected to the fuel cell system **302(1)**). For the sake of brevity, in the environment **300** illustrated in FIG. 3A, only the fuel cell system **302(1)** is connected to the power conversion system **304**, and the rest are omitted.

(47) The power conversion system **304** in the environment **300** may be the DC-AC power conversion system (hereinafter, interchangeably referred to as "multi-mode inverter system **304**") that converts the DC electrical power generated by the fuel cell system **302(1)** to Alternating Current (AC) electrical power. The AC electrical power is supplied to the load **306** via an AC bus **308**.

(48) In some embodiments, apart from the multi-mode inverter system **304**, the microgrid site may be provided with one or more power conversion systems that are connected to a single fuel cell system (e.g., the fuel cell system **302(1)**). The one or more power conversion systems may include a DC-DC power conversion system or a DC-AC power conversion system depending upon a load **306**. For instance, if a DC load needs to receive power from the fuel cell system **302(1)**, the power that the DC load requires to operate may be more than the power supply capacity of the fuel cell system **302(1)**. In such scenarios, the one or more power conversion systems may include a DC-DC boost converter. Further, in some embodiments, along with the DC-DC boost converter, the microgrid site may also be provided with a DC-AC power conversion system for supplying power to AC loads and a grid **310**.

(49) The load **306** may be a critical load or a non-critical load. Any excess power generated may be transmitted to the grid **310**. Therefore, the environment **300** also includes at least one load (e.g., the load **306**), the AC bus **308**, and the grid **310**. For instance, the critical load may include data centers servers, life support systems at hospitals, and the like, which have a direct impact on the ability of an organization to operate and must either be kept running when the supply from the grid **310** fails or shut down gradually to avoid system failures, data corruption, life-shortening hardware damage, and the like. In order to keep a critical load running independently in absence of the supply of power from the grid **310**, or to reduce dependency and power consumption from the grid **310**, the critical load may be provided with power from the fuel cell system (e.g., the fuel cell system **302(1)**). However, a non-critical load may not need power from the fuel cell systems **302** and may be connected only to the grid **310**.

(50) In some embodiments, in presence of the grid **310**, the multi-mode inverter system **304** operates in the grid-following mode and operates as a current source for supplying the AC power to the load **306** and excess power to the grid **310**. In absence of the grid **310**, the multi-mode inverter system **304** operates in the grid-forming mode and operates as a voltage source for supplying the AC power to the load **306**.

(51) The environment **300** further includes a grid isolation device **312**. The grid isolation device **312** may operate to connect or disconnect the grid **310** with the microgrid site based on detection of any faults in the grid **310**. Examples of the grid isolation device **312** include a Multi-mode Switch Board (MMSB), an Automatic Transfer Switch Board (ATSB), etc. More specifically, the grid isolation device **312** operates to connect or disconnect the load **306** associated with the microgrid site. For instance, when the grid isolation device **312** connects the grid **310** to the load **306**, then the multi-mode inverter system **304** supplies power to the load **306** by operating in the grid-following mode. Alternatively, when the grid isolation device **312** disconnects the grid **310** from the load **306**, then the multi-mode inverter system **304** supplies power to the load **306** by operating in the grid-forming mode.

(52) Additionally, the environment **300** depicts a site controller **314** electronically coupled to a plurality of electrical points and a plurality of electrical components in the microgrid site. The plurality of electrical components may include at least one of the fuel cell systems **302**, the power conversion systems (e.g., the power conversion system **304**), the grid isolation device **312**, and the like. The plurality of electrical points may include one or more connection points on the AC bus **308**. The plurality of electrical points may also include other connection points in the microgrid site **314** from where one or more electrical parameters may have to be measured by the site controller **314** (in order for the site controller **314** to take certain decisions associated with an operation of the plurality of electrical components of the microgrid site). For instance, the one or more electrical parameters may include current, voltage, power, frequency, etc.

(53) The site controller **314** is configured to receive at least one of a plurality of electrical signals from the plurality of electrical points and the plurality of electrical components, and a load operating input corresponding to the at least one load (e.g., the load **306**) connected to the microgrid site. For instance, the plurality of electrical signals may correspond to electrical values

corresponding to the one or more electrical parameters. As used herein, the term “load operating input” refers to a range of values corresponding to an electrical parameter such as voltage, current, power, frequency, etc., that is required by the load for the proper functioning of the load. Therefore, the load operating input may include a range of values corresponding to operating parameters associated with the load **306**.

(54) The site controller **314** is further configured to facilitate the multi-mode inverter system **304** to transition between the at least two operating modes based at least on the plurality of electrical signals. The at least two operating modes may include the grid-following mode and the grid-forming mode. For instance, the site controller **314** may determine a status of the grid isolation device **312** based at least on the plurality of electrical signals. The status of the grid isolation device **312** may be one of ‘connected to grid’ and ‘disconnected from grid’. Further, based on the status of the grid isolation device **312**, the site controller **314** may transmit a control message to the multi-mode inverter system **304**, the control message indicating the multi-mode inverter system **304** to operate in one of the at least two operating modes based upon the status of the grid isolation device **312**. Further, the site controller **314** is configured to generate a control signal based at least on the load operating input and the transitioning of the multi-mode inverter system **304** between the at least two operating modes.

(55) The environment **300** further depicts an energy storage module **316** and a DC Braking Module (DBM) **318** electrically connected to a DC bus **320** as shown in FIG. 3A. The energy storage module **316** is configured to turn ON in response to the receipt of the control signal. The energy storage module **318** is further configured to supply power to the DC bus **320** for supporting the at least one load **306**, when a DC voltage value on the DC bus **320** is less than the load operating input. For instance, the energy storage module **316** includes a battery.

(56) The DBM **318** is configured to turn ON in response to the receipt of the control signal. The DBM **318** is configured to receive the DC voltage value from the DC bus **320**. The DBM **318** is further configured to dissipate the excess energy via energy dissipating circuitry (not shown in FIG. 3A) from the DC bus when the DC voltage value is greater than a threshold voltage value. The threshold voltage value may correspond to a maximum operating DC bus voltage value (specified in the drive settings) of the DC bus **320** beyond which a fault of DC bus overvoltage may be triggered. Thus, the excess energy in the DC bus may have to be discharged or dissipated to maintain optimum DC voltage on the DC bus for the proper functioning of the microgrid site which is done by the DBM **318**. Detailed working and use of the DBM **318** and the energy dissipating circuitry are explained in further parts of the description with reference to FIGS. 5 and 6.

(57) It may be understood that the DC bus **320** is subject to variation in the one or more electrical parameters based at least on the transition between the at least two operating modes and variation in the load operating input associated with the load **306**. More specifically, the DC bus voltage on the DC bus **320** tends to fluctuate when the operation of the multi-mode inverter system **304** transitions between the at least two operating modes based at least on faults in the grid **310**. In addition, the DC bus voltage tends to fluctuate when there is a fluctuation in the load **306**.

(58) Moreover, in some embodiments, the site controller **314** further transmits the control signal to one of the DBM **318** and the energy storage module **316** during a startup of a system based at least on the load operating input and the transitioning of the multi-mode inverter system **304** between the at least two operating modes. The control signal indicates one of activation (turn ON) and deactivation (turn OFF) of one of the DBM **318** and the energy storage module **316** for regulating DC voltage on the DC bus **318**.

(59) Further, based on the transition being from the grid-following mode to the grid-forming mode or from the grid-forming mode to the grid-following mode, and the fluctuation of the load **306**, one or more scenarios of the operation of the system proposed in the present disclosure may occur. The one or more scenarios are explained with reference to FIGS. 3B-3D. Moreover, it may be noted that the system includes the fuel cell system **302(1)**, the multi-mode inverter system **304**, the site

controller **314**, the DBM **318**, and the energy storage module **316**. The fuel cell system **302(1)**, the multi-mode inverter system **304**, and the energy storage module **316** are electrically coupled to the DC bus **320**, and electronically coupled to the site controller **314**.

(60) The site controller **314** may be communicatively coupled to the plurality of electrical components via a network (not shown in FIG. **3A**) such as a wireless or wired communication network. Further, the site controller **314** may transmit the control signal via the network. The network may include, without limitation, a light fidelity (Li-Fi) network, a local area network (LAN), a wide area network (WAN), a metropolitan area network (MAN), a satellite network, the Internet, a fiber optic network, a coaxial cable network, an infrared (IR) network, a radio frequency (RF) network, a virtual network, and/or another suitable public and/or private network capable of supporting communication among certain entities illustrated in FIG. **3A**, or any combination thereof.

(61) It should be noted that the number of the fuel cell systems **302**, the power conversion system **304**, the energy storage module **316**, the DBM **318**, the grid isolation device **312**, and the load **306** described herein are only used for exemplary purposes and do not limit the scope of the invention. The main objective of the invention is to facilitate the distribution of the power generated by the fuel cell system **302(1)** in the microgrid site and the management of the load **306** such that when transitioning from the grid-following mode to the grid-forming mode, step load capability of the fuel cell system **302(1)** is improved. Further, the system also provides a better regulated turn OFF of the fuel cell system **302(1)** when transitioning from the grid-forming mode to the grid-following mode. This is facilitated by the introduction of the DBM **318** on the DC bus **320** of the microgrid site.

(62) FIG. **3B** represents an operating environment **340** of the system proposed in the present disclosure. In some embodiments, the load operating input may indicate a condition of the load **306** in which a power supply capacity of the grid **310** is more than the operating requirements of the load **306**, whereas a power supply capacity of the fuel cell system (e.g., the fuel cell system **302(1)**) is less than the operating requirements of the load **306**. Under such conditions, when the load **306** is receiving power from the fuel cell system **302(1)** operating in the grid-following mode, since the grid **310** is also available, input power received by the load **306** is sufficient for the load **306** to function appropriately. Also, the supply of power is controlled to meet the requirements of the load **306**. However, upon transitioning from the grid-following mode to the grid-forming mode, since the grid **310** became unavailable and the DC bus voltage decreased, the input power received by the load **306** is less than its requirement to function appropriately. The fuel cell system **302(1)** experiences a Black start process as the grid **310** becomes unavailable and the microgrid site experiences a blackout because of the same reason. As used herein, the term “Black start” refers to the ability of generators to restart parts of the power system to recover from the blackout. Generally, the black start in the microgrid site is followed by the grid-forming mode. Thus, the load **306** needs to receive that additional power by some means to operate. Under such scenarios, power stored in the energy storage module **316** associated with the fuel cell system **302(1)** may be supplied to the load **306**. Such an embodiment corresponds to one of the one or more scenarios of the operation of the system proposed in the present disclosure.

(63) Energy storage modules (e.g., the energy storage module **316**) in the microgrid site are generally used for storing excess energy or power generated by the fuel cell system **302(1)**. Moreover, the energy storage module **316** is also capable of supplying stored energy whenever necessary upon receiving instructions from the site controller **314**. To that note, the energy storage module **316** is configured to supply power to the DC bus **320** for supporting the at least one load **306**, when the DC voltage value on the DC bus **320** is less than the load operating input, based at least on the control signal received from the site controller **314**.

(64) FIG. **3C** represents another operating environment **360** of the system proposed in the present disclosure. In some embodiments, the load operating input may indicate a condition of the load **306**

in which a power supply capacity of the fuel cell system (e.g., the fuel cell system **302(1)**) is more than operating requirements of the load **306**. Under such conditions, when the load **306** is receiving power from the fuel cell system **302(1)** operating in the grid-following mode, the supply of the power is controlled to meet the requirements of the load **306** and the input power received by the load **306** is sufficient for the load **306** to function appropriately. However, upon transitioning from the grid-following mode to the grid-forming mode, at an initial stage, over-voltage may appear on the DC bus **320** which is more than the threshold voltage value, until either the power generated by the fuel cell system **302(1)** is reduced to meet the load demand or the load is managed to match the power supply capacity of the fuel cell system **302(1)**. The threshold voltage value may correspond to a maximum operating DC bus voltage value (specified in the drive settings) of the DC bus **320** beyond which a fault of DC bus over voltage may be triggered. Thus, the excess energy on the DC bus **320** may have to be discharged or dissipated to maintain optimum DC voltage on the DC bus **320** for the proper functioning of the microgrid site. Under such scenarios, the DBM **318** dissipates the excess energy on the DC bus **320** until an additional load is applied or power generated by the fuel cell system **302(1)** is reduced to match the load demand. Such an embodiment corresponds to another scenario of the one or more scenarios of the operation of the system proposed in the present disclosure.

(65) FIG. **3D** represents another operating environment **380** of the system proposed in the present disclosure. In some embodiments, the load operating input may indicate a condition of the load **306** in which, when transitioning from the grid-forming mode to the grid-following mode, initially, the load **306** is turned OFF. Under such a scenario, the DC bus voltage on the DC bus **320** increases and may go beyond a threshold voltage value. Thus, the excess energy on the DC bus **320** is dissipated using the DBM **318** which may be electrically coupled to the DC bus **320**.

(66) FIG. **4A** represents an operating environment **400** related to at least some examples of the present disclosure. The environment **400** as illustrated in FIG. **4A** refers to a specific embodiment of the environment **300** disclosed in FIG. **3A**. In particular, the environment **400** includes a plurality of electrical components such as the fuel cell system **302(1)** electrically connected to the multi-mode inverter system **304** via the DC bus **320**, and the ATSB **402** positioned between the grid **310**, the load **306** and the multi-mode inverter system **304** for connecting or disconnecting the grid **310** to the load **306** and the multi-mode inverter system **304**. The plurality of electrical components further includes an energy storage module **316** and a DBM **318** electrically connected to the DC bus **320**. The environment **400** also depicts a site controller **314** electronically coupled to the above-mentioned plurality of electrical components and the plurality of electrical points in the microgrid site.

(67) The multi-mode inverter system **304** may further include an inverter **404** whose output is controlled by an inverter controller **406** based at least on a type and operation of the inverter **404**. Thus, the inverter **404** along with the inverter controller **406** within the multi-mode inverter system **304** enables the multi-mode inverter system **304** to convert DC power generated by the fuel cell system **302(1)** to AC power, before supplying power to the grid **310** or the load **306**.

(68) In the grid-following mode, inverter **404** may be operating as a current source (grid-following inverter) and the inverter controller **406** tracks a voltage angle of the grid **310** to control an output (synchronizing to the grid **310**) of the inverter **404**. In the grid-forming mode, the inverter **404** may be operating as a voltage source (grid-forming inverter) and the inverter controller **406** actively controls frequency and voltage output of the inverter **404**. One important difference is that, in the grid-forming mode, the fuel cell system (e.g., the fuel cell system **302(1)**) is constantly working to keep frequency and voltage stable at setpoints with the help of the multi-mode inverter system (e.g., the multi-mode inverter system **304**) associated with the fuel cell system **302(1)**, whereas in the grid-following mode, the fuel cell system (e.g., the fuel cell system **302(1)**) only responds to change in the frequency or the voltage when they deviate outside of a certain allowed range for synchronizing them as per grid connection standards with the help of the multi-mode inverter

system (e.g., the multi-mode inverter system **304**) associated with the fuel cell system **302(1)**.
(69) In the illustrated example, ATSB **402** is used as a grid isolation device **312** like that depicted in FIG. **3A**. However, other types of grid isolation devices may also be used, without limiting the scope of the invention. ATSB **402** is substantially similar to ATSB **110** of FIGS. **1A** and **1B**. Therefore, ATSB **402** can include an Automatic Transfer Switch (ATS) **408**, an electrically operated Wrap Around Circuit Breaker (WACB) **410**, and one or more supporting auxiliary circuits (not shown in FIG. **4A**).

(70) ATS **408** is a three-position ATS including a position “N” indicating Normal, a position “E” indicating Emergency, and an intermediate position (not shown in FIG. **4A**) between “N” and “E”. ATS **408** also includes a terminal “L” which is connected to the load **306** via AC bus **314**. The terminal “L” is provided with a connector **412** that switches between the three positions based at least on receiving instructions from the site controller **314**.

(71) Multiple control signals are exchanged between the ATSB **402** and the site controller **314** for connecting or disconnecting the grid **310** to the load **306**. The control signals are referred to as status Input/Output (I/O) signals (see **414**), and these signals assist the site controller **314** to determine an operating mode of the multi-mode inverter system **304** being one of the at least two operating modes as mentioned above.

(72) Multiple other control signals and electrical signals may be exchanged between the site controller **314** and the plurality of electrical components and the plurality of electrical points in the microgrid site. In FIG. **4A**, these signals are indicated by dotted lines. The variation in these signals and the I/O signals and how DBM **318** and the energy storage module **316** play their roles in managing the distribution of the power from the fuel cell system **302(1)** to the load **306** is explained in detail with reference to FIG. **4B**.

(73) FIG. **4B** is a timing diagram **420** showing a sequence of events during the transition between the grid-following mode and the grid-forming mode for the environment **400** of FIG. **4A**, in accordance with an embodiment of the present disclosure. The I/O signals include WACB Auxiliary (WACB Aux or WACB AUX) signal, a Grid Good (GRID GOOD) signal, and a WACB System Command (WACB SC) signal. The WACB Aux signal indicates a status of the WACB **410** being ‘ON’ or ‘OFF’, or ‘closed’ or ‘open’. The Grid Good signal indicates the availability status of the grid **310**, i.e., it indicates whether the grid **310** is working or not. The WACB SC signal instructs the WACB **410** to open or close based on the availability status of the grid **310**.

(74) Further, the I/O signals collectively indicate transitioning of the operating mode of the multi-mode inverter system **304** from the grid-following mode to the grid-forming mode (see **422**) or from the grid-forming mode to the grid-following mode (see **424**). Furthermore, the rest of the signals include a grid voltage (Grid V or GRID V) signal, an Emergency voltage (Emer V or EMER V) signal, a fuel cell system power (DER power or DER POWER) signal, a load voltage (Load V or LOAD V), and a DBM power (DBM POWER) signal as shown in FIG. **4B**. The Grid V signal indicates a voltage of the grid **310**, the Emer V signal indicates a supply of emergency voltage to the grid **310**, the DER power signal indicates the DC power from the fuel cell system **302(1)**, the Load V signal indicates the voltage at the load **306**, and the DBM power signal indicates the power that got dissipated in the DBM **318**.

(75) When the grid **310** is lost, the operating mode of the multi-mode inverter system **304** changes from the grid-following mode to the grid-forming mode. Thus, the status of all the I/O signals transition from “High” to “Low”, at finite time instances from “t.sub.1” to “t.sub.5” which corresponds to the occurrence of a sequence of events (E.sub.1 to E.sub.6) as the voltage of the grid **310** falls and the fuel cell system **302(1)** transitions from being a current source (in the grid parallel mode) to being a voltage source (in the island volt mode). The total time for transitioning from the grid-following to the grid-forming mode, t.sub.GP_to_IV is given as
“t.sub.GP_to_IV=t.sub.1+t.sub.2+t.sub.3+t.sub.4+t.sub.5”.

(76) The important point to be noted compared to prior art disclosed in FIG. **2** is that in the prior art

environment **100**, the power of the fuel cell system **302(1)** changes over from “Full Load” to “No Load” instantly during the transition from the grid parallel mode to the island volt mode. It is evident from FIG. **4A** (see **422**) that the DBM **318** provides momentary buffering, for a period, for example, close to about 20 seconds. During this time, the load **306** may be managed and reduced to the level of the power supply capacity of the fuel cell system **302(1)**. Further, the island volt mode may be transitioned seamlessly without changing an output power of the fuel cell system **302(1)**. This also provides an additional feature of enabling a complete step load on the fuel cell system **302(1)** during the Black start period.

(77) Similarly, the transition from the grid-forming mode to the grid-following mode shall happen once the grid voltage and frequency are within the limits. As soon as the grid voltage returns, the I/O signals shall changeover from “Low” to “High” as shown in FIG. **4B** (see **424**), at finite time instances from “t.sub.6” to “t.sub.9” which correspond to the occurrence of a sequence of events (E.sub.7 to E.sub.11) as the voltage of the grid **310** returns and the fuel cell system **302(1)** transitions from being a voltage source (in the island volt mode) to being a current source (in the grid parallel mode). The total time for the transitioning from the grid-forming mode to the grid-following mode, t.sub.IV_to_GP is given as “t.sub.IV_to_GP=t.sub.6+t.sub.7+t.sub.8+t.sub.9”. As shown in FIG. **4B** (see **424**), the use of the DBM **318** allows the system to gracefully “Turn OFF” the fuel cell system **302(1)** instead of a sudden shutdown which can cause thermal shock to the fuel cell system **302(1)**.

(78) The sequence of events (E.sub.1 to E.sub.6) that occurred during the transition from the grid-following mode to the grid-forming mode as shown in FIG. **4B** (see **422**) are as follows: At Event E.sub.1: The grid voltage (GRID V) falls below acceptable limits (e.g., $E < 0.2$ per-unit system (pu)), up to which the grid **310** is considered to be healthy. Initially, the grid voltage was 1 pu. Further, as the Load voltage (LOAD V) falls, the effective power output also falls, however, the input power (DER POWER) remains unchanged. Due to the imbalance between input power (DER POWER) and the output power, the DC voltage on the DC bus rises. The DBM **318** starts dissipating the excess energy into the braking resistor and the DBM power (DBM POWER) becomes equal to the fuel cell system power (DER POWER) (see **426**). At Event E.sub.2: In response to the grid voltage falling below acceptable limits, the grid good (GRID GOOD) signal goes from ‘HIGH’ to ‘LOW’ after a time delay, t.sub.1, and this is sent to the site controller **314**, thereby informing the site controller **314** that the grid **310** is lost. At Event E.sub.3: Based on the grid good signal received by the site controller **314**, the WACB System Command (WACB SC) signal goes from ‘HIGH’ to ‘LOW’ after a time delay, t.sub.2, and this signal is sent to the WACB **410**. Upon receiving this signal, the WACB **410** opens. At Event E.sub.4: The site controller **314** waits to receive a confirmation from the WACB **410**, that the WACB **410** has opened by reading the WACB auxiliary (WACB AUX) signal. The WACB auxiliary signal is received after the contacts of the circuit breaker of the WACB **410** have mechanically been separated after a time delay, t.sub.3. At Event E.sub.5: Starting from time instance t.sub.4 all the way to time instance t.sub.5, the output voltage shall be built in the grid-forming mode as shown in FIG. **4B**, at a time delay, t.sub.4. At Event E.sub.6: Once the loads on site are turned ON at this point in time, the power from the fuel cell system **302(1)** shall service the loads due to which the power being dissipated in the DBM (DBM POWER) becomes 0 after a time delay of t.sub.5 (see **426**). Thus, it may be noted that, during the transition, that is, from the grid-following mode to the grid-forming mode (see **422**), the power from the fuel cell system **302(1)** (i.e., the DER POWER) remains in “Full load” (see **426**) and hence avoids undesirable instant turning OFF of the fuel cell system **302(1)**.

(79) Further, the sequence of events (E.sub.7 to E.sub.11) that occur during the transition from the grid-forming mode to the grid-following mode as shown in FIG. **4B** (see **424**) are as follows: At Event E.sub.7: At this instant in time, the grid voltage (GRID V) recovers, and the system can now transition back to the grid-following mode after the reconnect time. At Event E.sub.8: The Grid

good signal is now changed from 'LOW' to 'HIGH' indicating the site controller **314** that the grid **310** is stable and ready to take the load **306** after a time interval, $t_{sub.6}$. The voltage being generated in the grid-forming mode is made 0 as the system is ready to transfer to the grid parallel mode. Also, as the output voltage of the system is made 0 the instantaneous output power becomes 0 whereas the input power is high. This causes the DC bus **320** to rise and the same is dissipated by the DBM **318**. The input fuel to the fuel cell system **302(1)** is now gradually reduced to ensure a graceful shutdown (see **428**) to prevent thermal shock on the fuel cells. At Event E.sub.9: Based on the grid good signal received by the site controller **314**, the WACB System Command (WACB SC) signal goes from 'LOW' to 'HIGH' after a time delay, $t_{sub.7}$, and this signal is sent to the WACB **410**. Upon receiving this signal, the WACB **410** closes for the fuel cell system **302(1)** to connect to the grid **310**. At Event E.sub.10: After a time delay of $t_{sub.8}$, the WACB auxiliary contact feedback is received from the WACB **410** which indicates that the actual contacts of the circuit breaker of the WACB **410** have closed. At Event E.sub.11: The site controller **314** waits for a reconnect time period of about $t_{sub.9}$ to ensure that the grid **310** is stable before the inverter **404** can start pushing power into the grid **310** within time, $t_{sub.9}$. After completion of all the time instances, the fuel cell system **302(1)** may ramp power back up.

(80) FIG. 5 is a single line diagram representation **500** of a circuitry of the DBM **318** positioned on the DC bus **320**, in accordance with an embodiment of the present disclosure. The single line diagram representation **500** indicates connections of an input, an output, and one or more internal components of the DBM **318**. The input and output of the DBM **318** are DC as shown in FIG. 5 as 'DC Input' and 'DC output' with a direction of power flow in the DBM **318**. Further, the input to the DBM **318** is provided through a fuse and a pre-charged relay/contactors (not shown in FIG. 5) to charge DC bus capacitors (e.g., DC bus capacitors **502a** and **502b**) (hereinafter, interchangeably referred to as a DC mid-bus capacitor **502a** or **502b**) in the DBM **318** with their capacitance being indicated by C.sub.DC farad (F).

(81) In some embodiments, the DC bus capacitors connected on the DC bus **320** before the inverter **404** of the multi-mode inverter system **304** act as junction capacitors for an input power ($P_{sub.IN}$) (DC input) from a source such as the fuel cell system **302(1)** and load power on an AC output ($P_{sub.OUT}$). Voltage on the DC bus capacitors gets affected if $P_{sub.IN}$ and $P_{sub.OUT}$ are not equal in magnitude. During step changes in the load power, power on AC output i.e., $P_{sub.OUT}$ may become even negative or very much less than the power from the fuel cell system **302(1)** i.e., $P_{sub.IN}$, and results in the DC bus **320** to charge over a threshold limit i.e., the threshold voltage value as mentioned above.

(82) A continuous rise in the DC Bus voltage may cause the fuel cell system **302(1)** to trip on DC Bus over voltage which is undesirable. The DBM **318** may absorb this excess energy (ΔE) to bring back the DC bus voltage within the desired limits. For the DBM **318** to be able to absorb this excess energy, the DBM **318** uses a half-bridge chopper circuit including a connection of at least one braking resistor ($R_{sub.BRAKE}$) **504**, at least one power transistor **506**, and at least one diode **508**. As used herein, the term "chopper circuit" refers to a DC-DC converter. In some embodiments, similar to transformers of AC circuits, choppers are used to step up and/or step down the DC power. However, typically, choppers are buck converters and very rarely boost converters. They change the fixed DC power to variable DC power. Using these, DC power supplied to the devices connected at an output end of the chopper circuit can be adjusted to the required amount. Similarly, the term "half-bridge chopper circuit" refers to a chopper circuit that is unable to switch the polarity of the voltage applied to the load.

(83) In an instance, at least one braking resistor **504** may appear at the output of the DBM **318**. At least one resistor **504** is designed to dissipate excess energy on the DC Bus **320** by converting it to heat. Further, at least one braking resistor becomes operational when the DC bus **320** temporarily exceeds a pre-set threshold voltage (e.g., the threshold voltage value). Furthermore, at least one braking transistor (e.g., the at least one power transistor **506**) shunts the current from the DC bus

320 across the at least one braking resistor **504** when a voltage threshold is exceeded.

(84) In the illustrated example, at least one power transistor **506** is an Insulated-Gate Bipolar Transistor (IGBT). However, any other power transistor may also be used, such as a Silicon Carbide Metal Oxide Semiconductor Field Effect Transistor (SiC MOSFET), without limiting the scope of the invention. Moreover, at least one power transistor **506** may be provided with a freewheeling diode connected in an anti-parallel direction to at least one power transistor **506**, to conduct current in an opposite direction.

(85) In an example, a current limiting series inductor **510** is used to reduce the rate of rise of current in the event of any short-circuit conditions. Therefore, the one or more internal components of the DBM **318** include the half-bridge chopper circuit and the current limiting series inductor **510**. Further details about the working of the DBM **318** and other components are explained with reference to FIG. 6.

(86) FIG. 6 represents a DBM control architecture **600**, in accordance with an embodiment of the present disclosure. It is understood that the power conversion system **304** processes the input power incoming from the source such as the fuel cell system **302(1)** and feeds the load **306**. Ideally, the input power is equal to the load power. However, there could be variations in the load **306** with respect to time, and thus the output power also varies with time.

(87) Further, dynamics in the load **306** may be much faster at times than the dynamics of the source which leads to excessive power on a DC link of the DC bus **320** that connects the source and the power conversion system **304**. Excess energy (ΔE) may be determined by using the following equation:

$$(88) \quad E = \frac{1}{2}C(V_{DC}^2 - V_{REF}^2) \quad (1)$$

(89) Here, 'C' refers to a capacitance of the DC mid-bus capacitor, 'V.sub.DC' refers to DC voltage on the DC bus that gets applied to the DC mid-bus capacitor, and 'V.sub.REF' refers to the maximum operating DC bus voltage value. Further, this excess energy ΔE is dissipated by the DBM **318**, via the energy dissipating circuitry, as the DBM **318** is provided at the DC link of the DC bus **320**. This enables the DC bus **320** to stay far away from rated limits of over-voltage and allows the source and the power conversion system **304** to recover to the new load condition.

(90) Moreover, with the input power P.sub.IN and the output power being P.sub.OUT, the DC bus power P.sub.B may be indicated by the following equation:

$$(91) \quad P_B = P_{OUT} - P_{IN} \quad (2) \quad P_B = - P_{OUT} \quad (3)$$

(92) Here, ' ΔP .sub.B' refers to a change in the DC bus power, and ' ΔP .sub.OUT' refers to a change in the output power. In some embodiments, the DBM control architecture **600** may correspond to a block diagram representation of a control system of the DBM **318**. Further, the architecture **600** indicates that the DBM **318** includes a DC mid-bus capacitor sub-module **602**, a DBM controller sub-module **604**, and a DC chopper sub-module **606**. The DC mid-bus capacitor sub-module **602** may include a summing point **608** followed by a DC mid-bus capacitor **610**. In the illustrated example, the summing point **608** performs the operation stated in the equation (2), and gives its output power to the DC mid-bus capacitor **610**. The DC mid-bus capacitor **610** charges and hence stores certain energy i.e., 'E' which is determined by the following equation:

$$(93) \quad E = \frac{1}{2}CV_{DC}^2 \quad (4)$$

(94) Since the energy 'E' in the DC mid-bus capacitor **610** is proportional to the square of the DC voltage (V.sub.DC) in the DC bus, a power flow control of the architecture **600** is designed to control the square of the DC voltage on the DC bus as shown in FIG. 6. This way of control ensures the control of the energy 'E' on the DC bus. Further, a voltage sensor such as a V.sub.DC sensor **612** as shown in FIG. 6, senses the square of the DC voltage (V.sub.DC) on the DC bus, and the same is fed back to the DBM controller sub-module **604**. Generally, a controller is basically a unit present in a control system that generates control signals to reduce the deviation of the actual value from the desired value to almost zero or the lowest possible value. It is responsible for the

control action of the system so as to get the accurate output.

(95) In some embodiments, the DBM controller sub-module **604** may be one of a proportional controller, a derivative controller, an integral controller, a Proportional-Integral (PI) controller, a Proportional-Derivative (PD) controller, a Proportional-Integral-Derivative (PID) controller, or the like. Therefore, based on the type of the DBM controller sub-module **604**, a corresponding transfer function may be applied to an error signal obtained upon a comparison of the feedback signal with a reference signal by a control system corresponding to the DBM controller sub-module **604**.

Therefore, the DBM controller sub-module **604** includes a summing point **614** which determines a difference between the feedback signal i.e., $V_{sub.DC.sup.2}$, and a reference signal (the maximum operating DC bus voltage value) i.e., $V_{sub.REF.sup.2}$. The output (error signal) of the summing point **614** is then applied to a transfer function $C(s)$ block **616**, which essentially provides a multiplying factor to the error signal obtained from the summing point **614**. For instance, the transfer function block **616** may be implemented in accordance with equation (1).

(96) Therefore, an output of the DBM controller sub-module **604** may be the excess energy ΔE , which is used as a duty cycle for control of the dissipation of energy via the DC chopper sub-module **606**. For instance, the DC chopper sub-module **606** may be a 3-leg DC chopper as shown in FIG. 6. The duty cycle 'D' of the output of the DBM controller sub-module **604** may be split into three duty cycles such as D1, D2, and D3, each cycle being fed to each leg of the 3-leg DC chopper. Each leg of the 3-leg DC chopper may correspond to a braking resistor. Further, the excess energy ΔE is dissipated through each braking resistor and the power transistor **618**.

(97) The DBM controller sub-module **604** may also measure other parameters such as pole current, Thermal Cut-Out (TCO), and other signals for protection of power modules such as the fuel cell systems **302**. Further, the DBM controller sub-module **604** may also calculate the instantaneous energy of the system and ensure that the DBM **318** is turned OFF once the maximum energy rating of the braking resistor is hit.

(98) The DBM controller sub-module **604** communicates with the site controller **314** to convey the status of the system and receive ON/OFF commands from the site controller **314**. The DBM controller sub-module **604** communicates with the site controller **314** using a Controller Area Network (CAN) communication interface.

(99) A resistor **620** shown in FIG. 6 corresponds to a resistor having an effective resistance of the three braking resistors connected in parallel with each other via which the excess energy ΔE is dissipated. For instance, the value of resistance corresponding to each braking resistor to each phase is equal in magnitude. Thus, in such a scenario, a duty cycle magnitude to all the three legs is also the same in magnitude. Further, the excess energy ΔE that is dissipated through the braking resistors may charge a capacitor **622**, and the power at the output of the 3-leg DC chopper may correspond to DC bus power ($P_{sub.B}$) which got generated as excess power in the DC bus **320** due to difference in the input power and the load power on the AC output. Thus, it may be understood that the energy dissipating circuitry includes the DC chopper sub-module **606**.

(100) FIG. 7 represents an environment **700** illustrating different types of Distributed Energy Resources (DERs) powering a common load (e.g., the load **306**), in accordance with an embodiment of the present disclosure. In some embodiments, a microgrid site may include different types of DERs powering the AC bus **308** to which the load **306** and the grid **310** may be connected as a point of common connection. For instance, a DER **702**, which may be a solar photovoltaic system, may be connected to the AC bus **308** via a multi-mode inverter system **704** designed specially to receive and process DC power from the solar photovoltaic system. The multi-mode inverter system **704** and the DER **702** are electrically connected with each other via a DC bus **706**.

(101) DER **702** may also be a fuel cell system but manufactured by a different manufacturer and hence may have different features and different operating parameters and conditions. Therefore, power P1 may be transmitted from the fuel cell system **302(1)** to the AC bus **308**, and power P2

may be transmitted from the DER **702** to the AC bus **308**. In such scenarios, i.e., when different types of DERs are connected to a common AC bus for supplying power to a common load, there could be conditions of reverse power flow (see **708**). This reverse power flow is typically high in magnitude but low in duration. These scenarios can cause DC bus Overvoltage (OV) conditions and trip many systems such as the fuel cell system **302(1)**, the power conversion system **304**, etc. The DBMs **318** and **710** are quick energy absorbers of high power rating which will enable these micro-grids to operate under these short-term scenarios.

(102) FIG. **8** is a flowchart illustrating a method **800** for microgrid-power distribution management when transitioning between operating modes of the DERs, in accordance with an embodiment of the present disclosure. The method **800** depicted in the flow diagram may be executed by, for example, the site controller **314**. Operations of the flow diagram of the method **800**, and combinations of operations in the flow diagram of the method **800**, may be implemented by, for example, hardware, firmware, processors, circuitry, and/or different devices associated with the execution of software that includes one or more computer program instructions. The method **800** starts at operation **802**.

(103) At **802**, the method **800** includes receiving, by the site controller **314** electronically coupled to a plurality of electrical points and a plurality of electrical components in a microgrid site, at least one of a plurality of electrical signals from the plurality of electrical points and the plurality of electrical components, and a load operating input corresponding to at least one load (e.g., the load **306**) connected to the microgrid site.

(104) In an embodiment, the load operating input includes a range of values corresponding to operating parameters associated with the at least one load **306**.

(105) At **804**, the method **800** includes facilitating, by the site controller **314**, a multi-mode inverter system **304** to transition between at least two operating modes based at least on the plurality of electrical signals, the at least two operating modes including a grid-following mode and a grid-forming mode.

(106) At **806**, the method **800** includes generating, by the site controller **314**, a control signal based at least on the transitioning of the multi-mode inverter system **304** between the at least two operating modes and the load operating input.

(107) At **808**, the method **800** includes transmitting, by the site controller **314**, the control signal to one of a DC braking module **318** and an energy storage module **316** based at least on the load operating input and the transitioning of the multi-mode inverter system **304** between the at least two operating modes, the control signal indicating one of activation (turn ON) and deactivation (turn OFF) of one of the DC braking module **318** and the energy storage module **316** for regulating DC voltage on a DC bus **320**.

(108) In an embodiment, when transitioning from the grid-following mode to the grid-forming mode and the load operating input corresponding to an indication that the load **306** requires power more than a power supply capacity of the fuel cell system **302(1)**, the DC voltage value on the DC bus **320** decreases, thereby causing the energy storage module **316** to support the at least one load **306**.

(109) Further, when transitioning from the grid-following mode to the grid-forming mode and the load operating input corresponding to an indication that the load **306** requires power less than a power supply capacity of the fuel cell system **302(1)**, the DC voltage value on the DC bus **320** increases, thereby causing the DC braking module **318** for dissipating the excess energy.

(110) Furthermore, when transitioning from the grid-forming mode to the grid-following mode, initially the DC voltage value on the DC bus **320** increases, causing the DC braking module **318** to dissipate the excess energy.

(111) Moreover, the method **800** may include receiving, by the DC braking module **318** electrically coupled on the DC bus **320**, a DC voltage value from the DC bus **320**. Herein, the DC braking module **318** may be turned ON in response to the receipt of the control signal from site controller

314. In an embodiment, receiving, by the DC braking module **318**, the DC voltage value from the DC bus **320** includes receiving the DC voltage value via a DC mid-bus capacitor **502a** or **502b**.

(112) The method **800** may also include dissipating, by the DC braking module **318**, the excess energy, via energy dissipating circuitry, from the DC bus **320** when the DC voltage value is greater than a threshold voltage value, based at least on the control signal received from the site controller **314**. In an embodiment, dissipating the excess energy, via the energy dissipating circuitry includes dissipating the excess energy, via the energy dissipating circuitry, wherein the energy dissipating circuitry includes a DC chopper sub-module **606**.

(113) Further, the method **800** includes supplying, by the energy storage module **316**, power to the DC bus **320** for supporting the at least one load **306**, when the DC voltage value on the DC bus **320** is less than the load operating input.

(114) The method **800** further includes determining, by the site controller **314**, the availability status of the grid **310** based at least on the plurality of electrical signals.

(115) The disclosed method **800** with reference to FIG. **8**, or one or more operations of the method **800** may be implemented using software including computer-executable instructions stored on one or more computer-readable media (e.g., non-transitory computer-readable media, such as one or more optical media discs, volatile memory components (e.g., DRAM or SRAM)), or nonvolatile memory or storage components (e.g., hard drives or solid-state nonvolatile memory components, such as Flash memory components) and executed on a computer (e.g., any suitable computer, such as a laptop computer, net book, Web book, tablet computing device, smart phone, or other mobile computing device). Such software may be executed, for example, on a single local computer or in a network environment (e.g., via the Internet, a wide-area network, a local-area network, a remote web-based server, a client-server network (such as a cloud computing network), or other such network) using one or more network computers. Additionally, any of the intermediate or final data created and used during implementation of the disclosed methods or systems may also be stored on one or more computer-readable media (e.g., non-transitory computer-readable media) and are considered to be within the scope of the disclosed technology. Furthermore, any of the software-based embodiments may be uploaded, downloaded, or remotely accessed through a suitable communication means. Such a suitable communication means includes, for example, the Internet, the World Wide Web, an intranet, software applications, cable (including fiber optic cable), magnetic communications, electromagnetic communications (including RF, microwave, and infrared communications), electronic communications, or other such communication means.

(116) Although the invention has been described with reference to specific exemplary embodiments, it is noted that various modifications and changes may be made to these embodiments without departing from the broad spirit and scope of the invention. For example, the various operations, blocks, etc., described herein may be enabled and operated using hardware circuitry (for example, complementary metal oxide semiconductor (CMOS) based logic circuitry), firmware, software and/or any combination of hardware, firmware, and/or software (for example, embodied in a machine-readable medium). For example, the apparatuses and methods may be embodied using transistors, logic gates, and electrical circuits (for example, application specific integrated circuit (ASIC) circuitry and/or in Digital Signal Processor (DSP) circuitry).

(117) Various embodiments of the invention may include one or more computer programs stored or otherwise embodied on a computer-readable medium, wherein the computer programs are configured to cause a processor or computer to perform one or more operations. A computer-readable medium storing, embodying, or encoded with a computer program, or similar language, may be embodied as a tangible data storage device storing one or more software programs that are configured to cause a processor or computer to perform one or more operations. Such operations may be, for example, any of the steps or operations described herein. In some embodiments, the computer programs may be stored and provided to a computer using any type of non-transitory computer readable media. Non-transitory computer readable media include any type of tangible

storage media. Examples of non-transitory computer readable media include magnetic storage media (such as floppy disks, magnetic tapes, hard disk drives, etc.), optical magnetic storage media (e.g. magneto-optical disks), CD-ROM (compact disc read only memory), CD-R (compact disc recordable), CD-R/W (compact disc rewritable), DVD (Digital Versatile Disc), BD (BLU-RAY® Disc), and semiconductor memories (such as mask ROM, PROM (programmable ROM), EPROM (erasable PROM), flash memory, RAM (random access memory), etc.). Additionally, a tangible data storage device may be embodied as one or more volatile memory devices, one or more non-volatile memory devices, and/or a combination of one or more volatile memory devices and non-volatile memory devices. In some embodiments, the computer programs may be provided to a computer using any type of transitory computer readable media. Examples of transitory computer readable media include electric signals, optical signals, and electromagnetic waves. Transitory computer readable media can provide the program to a computer via a wired communication line (e.g., electric wires, and optical fibers) or a wireless communication line.

(118) Various embodiments of the invention, as discussed above, may be practiced with steps and/or operations in a different order, and/or with hardware elements in configurations, which are different than those which are disclosed. Therefore, although the invention has been described based upon these exemplary embodiments, it is noted that certain modifications, variations, and alternative constructions may be apparent and well within the spirit and scope of the invention.

(119) Although various exemplary embodiments of the invention are described herein in a language specific to structural features and/or methodological acts, the subject matter defined in the appended claims is not necessarily limited to the specific features or acts described above. Rather, the specific features and acts described above are disclosed as exemplary forms of implementing the claims.

Claims

1. A system, comprising: a fuel cell system configured to generate Direct Current (DC) power in a microgrid site; a multi-mode inverter system electrically connected to the fuel cell system via a DC bus, the multi-mode inverter system configured to operate in one of at least two operating modes based at least on an availability status of a grid electrically coupled to the microgrid site, for supplying power to at least one load, the at least two operating modes comprising a grid-following mode and a grid-forming mode; a site controller electronically coupled to a plurality of electrical points and a plurality of electrical components in the microgrid site, the site controller configured to: receive at least one of a plurality of electrical signals from the plurality of electrical points and the plurality of electrical components, and a load operating input corresponding to the at least one load connected to the microgrid site; facilitate the multi-mode inverter system to transition between the at least two operating modes based at least on the plurality of electrical signals; and generate a control signal based at least on the load operating input and the transitioning of the multi-mode inverter system between the at least two operating modes; a DC braking module electrically connected to the DC bus, the DC braking module configured to: turn ON in response to the receipt of the control signal; receive a DC voltage value from the DC bus; and dissipate excess energy, via energy dissipating circuitry, from the DC bus when the DC voltage value is greater than a threshold voltage value and during transitioning of the multi-mode inverter system between the at least two operating modes; and an energy storage module electrically connected to the DC bus, the energy storage module configured to: turn ON in response to the receipt of the control signal; and supply power to the DC bus for supporting the at least one load, when the DC voltage value on the DC bus is less than the load operating input and during transitioning of the multi-mode inverter system between the at least two operating modes.

2. The system as claimed in claim 1, wherein the site controller is further configured to transmit the control signal to one of the DC braking module and the energy storage module during a startup of

the system based at least on the load operating input and the transitioning of the multi-mode inverter system between the at least two operating modes, the control signal indicating one of activation (turn ON) and deactivation (turn OFF) of one of the DC braking module and the energy storage module for regulating DC voltage on the DC bus.

3. The system as claimed in claim 1, wherein the site controller is further configured to determine the availability status of the grid based at least on the plurality of electrical signals.

4. The system as claimed in claim 1, wherein when transitioning from the grid-following mode to the grid-forming mode and the load operating input corresponding to an indication that the at least one load requires power more than a power supply capacity of the fuel cell system, the energy storage module is configured to supply power to the DC bus to support the at least one load.

5. The system as claimed in claim 1, wherein when transitioning from the grid-following mode to the grid-forming mode and the load operating input corresponding to an indication that the at least one load requires power less than a power supply capacity of the fuel cell system, the DC braking module is configured to dissipate the excess energy, via the energy dissipating circuitry, from the DC bus.

6. The system as claimed in claim 1, wherein when transitioning from the grid-forming mode to the grid-following mode, the DC braking module is configured to dissipate the excess energy, via the energy dissipating circuitry, from the DC bus.

7. The system as claimed in claim 1, wherein the load operating input comprises a range of values corresponding to operating parameters associated with the at least one load.

8. The system as claimed in claim 1, wherein the DC braking module is configured to receive the DC voltage value from the DC bus via a DC mid-bus capacitor.

9. The system as claimed in claim 1, wherein the DC braking module comprises: a DC mid-bus capacitor sub-module, a DC braking module (DBM) controller sub-module, and a DC chopper sub-module electrically connected with each other.

10. The system as claimed in claim 9, wherein the DC chopper sub-module comprises a 3-leg DC chopper.

11. A method, comprising: providing a fuel cell system to generate Direct Current (DC) power in a microgrid site, providing a multi-mode inverter system electrically connected to the fuel cell system via a DC bus, the multi-mode inverter system configured to operate in one of at least two operating modes based at least on an availability status of a grid electrically coupled to the microgrid site, for supplying power to at least one load; providing a DC braking module electrically connected to the DC bus; providing an energy storage module electrically connected to the DC bus; receiving, by a site controller electronically coupled to a plurality of electrical points and a plurality of electrical components in the microgrid site, at least one of a plurality of electrical signals from the plurality of electrical points and the plurality of electrical components, and a load operating input corresponding to the at least one load connected to the microgrid site; facilitating, by the site controller, the multi-mode inverter system to transition between the at least two operating modes based at least on the plurality of electrical signals, the at least two operating modes comprising a grid-following mode and a grid-forming mode; generating, by the site controller, a control signal based at least on the load operating input and the transitioning of the multi-mode inverter system between the at least two operating modes; transmitting, by the site controller, the control signal to at least one of the DC braking module and the energy storage module based at least on the load operating input and the transitioning of the multi-mode inverter system between the at least two operating modes; receiving, by the DC braking module, a DC voltage value from the DC bus, wherein the DC braking module is turned ON in response to receipt of the control signal, and dissipating, by the DC braking module via energy dissipating circuitry, excess energy from the DC bus when the DC voltage value is greater than a threshold voltage value and during transitioning of the multi-mode inverter system between the at least two operating modes; and supplying, by the energy storage module, power to the DC bus for supporting the at

least one load when the DC voltage value in the DC bus is less than the load operating input and during transitioning of the multi-mode inverter system between the at least two operating modes.

12. The method as claimed in claim 11, wherein when transitioning from the grid-following mode to the grid-forming mode and the load operating input corresponding to an indication that the at least one load requires power more than a power supply capacity of the fuel cell system, the control signal indicates the activation of the energy storage module for regulating the DC voltage on the DC bus.

13. The method as claimed in claim 11, wherein when transitioning from the grid-following mode to the grid-forming mode and the load operating input corresponding to an indication that the at least one load requires power less than a power supply capacity of the fuel cell system, the control signal indicates the activation of the DC braking module for regulating the DC voltage on the DC bus.

14. The method as claimed in claim 11, wherein when transitioning from the grid-forming mode to the grid-following mode, the control signal indicates the activation of the DC braking module for regulating the DC voltage on the DC bus.

15. The method as claimed in claim 11, wherein receiving, by the DC braking module, the DC voltage value from the DC bus comprises receiving the DC voltage value via a DC mid-bus capacitor.

16. The method as claimed in claim 11, wherein dissipating the excess energy, via the energy dissipating circuitry comprises dissipating the excess energy, via the energy dissipating circuitry, wherein the energy dissipating circuitry comprises a DC chopper sub-module.

17. The method as claimed in claim 11, further comprising: determining, by the site controller, the availability status of the grid based at least on the plurality of electrical signals.

18. The method as claimed in claim 11, wherein the load operating input comprises a range of values corresponding to operating parameters associated with the at least one load.
