

US Patent & Trademark Office

Patent Public Search | Text View

United States Patent	12407375
Kind Code	B2
Date of Patent	September 02, 2025
Inventor(s)	Arduini; Douglas Paul et al.

Initialization and synchronization for pulse power in a network system

Abstract

In one embodiment, a method includes receiving low voltage pulse power from power sourcing equipment at a powered device, synchronizing the powered device with a waveform of the low voltage pulse power received from the power sourcing equipment, and operating the powered device with high voltage pulse power received from the power sourcing equipment.

Inventors: Arduini; Douglas Paul (Florence, OR), Baek; Sung Kee (San Ramon, CA), O'Brien; Richard Anthony (Livermore, CA), Goergen; Joel Richard (Soulsville, CA), Jones; Chad M. (Doylestown, OH), Potterf; Jason DeWayne (Austin, TX), Li; Ruqi (Fremont, CA)

Applicant: Cisco Technology, Inc. (San Jose, CA)

Family ID: 73040367

Assignee: CISCO TECHNOLOGY, INC. (San Jose, CA)

Appl. No.: 18/769534

Filed: July 11, 2024

Prior Publication Data

Document Identifier	Publication Date
US 20240364383 A1	Oct. 31, 2024

Related U.S. Application Data

continuation parent-doc US 17171723 20210209 US 12113588 child-doc US 18769534
division parent-doc US 16671508 20191101 US 11063630 20210713 child-doc US 17171723

Publication Classification

Int. Cl.: H04B3/54 (20060101); **G01R31/08** (20200101); **G01R31/50** (20200101); **G05B9/02** (20060101); **G06F1/30** (20060101); **H02J13/00** (20060101); **H04L12/10** (20060101); **H04L12/40** (20060101)

U.S. Cl.:

CPC H04B3/54 (20130101); **G01R31/083** (20130101); **G01R31/50** (20200101); **G05B9/02** (20130101); **G06F1/305** (20130101); **H02J13/00** (20130101); **H02J13/00032** (20200101); **H04L12/10** (20130101); **H04L12/40045** (20130101);

Field of Classification Search

CPC: H04B (3/54); H02J (13/00032); H02J (13/00); H04L (12/10); H04L (12/40045); G06F (1/305); G05B (9/02); G01R (31/083)

References Cited

U.S. PATENT DOCUMENTS

Patent No.	Issued Date	Patentee Name	U.S. Cl.	CPC
3335324	12/1966	Buckeridge	N/A	N/A
3962529	12/1975	Kubo	N/A	N/A
4811187	12/1988	Nakajima et al.	N/A	N/A
4997388	12/1990	Dale et al.	N/A	N/A
5652893	12/1996	Ben-Meir et al.	N/A	N/A
6008631	12/1998	Johari	N/A	N/A
6220955	12/2000	Posa	N/A	N/A
6259745	12/2000	Chan	N/A	N/A
6295356	12/2000	De Nicolo	N/A	N/A
6448672	12/2001	Voegeli et al.	N/A	N/A
6636538	12/2002	Stephens	N/A	N/A
6685364	12/2003	Brezina et al.	N/A	N/A
6756881	12/2003	Bateman et al.	N/A	N/A
6784790	12/2003	Lester	N/A	N/A
6822457	12/2003	Borchert et al.	N/A	N/A
6826368	12/2003	Koren et al.	N/A	N/A
6855881	12/2004	Khoshnood	N/A	N/A
6860004	12/2004	Hirano et al.	N/A	N/A
7325150	12/2007	Lehr et al.	N/A	N/A
7417443	12/2007	Admon et al.	N/A	N/A
7420355	12/2007	Liu et al.	N/A	N/A
7490996	12/2008	Sommer	N/A	N/A
7492059	12/2008	Peker et al.	N/A	N/A
7509505	12/2008	Randall et al.	N/A	N/A
7564904	12/2008	Isachar et al.	N/A	N/A
7566987	12/2008	Black et al.	N/A	N/A
7583703	12/2008	Bowser et al.	N/A	N/A
7589435	12/2008	Metsker et al.	N/A	N/A
7593747	12/2008	Karam et al.	N/A	N/A
7603570	12/2008	Schindler et al.	N/A	N/A

7616465	12/2008	Vinciarelli	N/A	N/A
7813646	12/2009	Furey	N/A	N/A
7835389	12/2009	Yu et al.	N/A	N/A
7854634	12/2009	Filipon et al.	N/A	N/A
7881072	12/2010	DiBene, II et al.	N/A	N/A
7915761	12/2010	Jones et al.	N/A	N/A
7921307	12/2010	Karam et al.	N/A	N/A
7924579	12/2010	Arduini	N/A	N/A
7940787	12/2010	Karam	N/A	N/A
7973538	12/2010	Karam	N/A	N/A
8020043	12/2010	Karam	N/A	N/A
8037324	12/2010	Hussain	N/A	N/A
8068937	12/2010	Eaves	N/A	N/A
8081589	12/2010	Gilbrech et al.	N/A	N/A
8184525	12/2011	Karam	N/A	N/A
8276397	12/2011	Carlson et al.	N/A	N/A
8279883	12/2011	Diab et al.	N/A	N/A
8310089	12/2011	Schindler et al.	N/A	N/A
8319627	12/2011	Chan et al.	N/A	N/A
8345439	12/2012	Goergen et al.	N/A	N/A
8350538	12/2012	Cuk	N/A	N/A
8358893	12/2012	Sanderson et al.	N/A	N/A
8386820	12/2012	Diab	N/A	N/A
8638008	12/2013	Baldwin et al.	N/A	N/A
8700923	12/2013	Fung	N/A	N/A
8712324	12/2013	Corbridge et al.	N/A	N/A
8750710	12/2013	Hirt et al.	N/A	N/A
8768528	12/2013	Millar et al.	N/A	N/A
8781637	12/2013	Eaves	N/A	N/A
8787775	12/2013	Earnshaw	N/A	N/A
8793511	12/2013	Bishara	N/A	N/A
8829917	12/2013	Lo et al.	N/A	N/A
8836228	12/2013	Xu et al.	N/A	N/A
8842430	12/2013	Hellriegel et al.	N/A	N/A
8849471	12/2013	Daniel et al.	N/A	N/A
8898446	12/2013	Ronen et al.	N/A	N/A
8966747	12/2014	Vinciarelli et al.	N/A	N/A
8971399	12/2014	Kwon et al.	N/A	N/A
9001881	12/2014	Okamura et al.	N/A	N/A
9019895	12/2014	Li et al.	N/A	N/A
9024473	12/2014	Huff et al.	N/A	N/A
9184795	12/2014	Eaves	N/A	N/A
9189036	12/2014	Ghoshal et al.	N/A	N/A
9189043	12/2014	Vorenkamp et al.	N/A	N/A
9273906	12/2015	Goth et al.	N/A	N/A
9319101	12/2015	Lontka	N/A	N/A
9321362	12/2015	Woo et al.	N/A	N/A
9373963	12/2015	Kuznetsov	N/A	N/A
9419436	12/2015	Eaves et al.	N/A	N/A
9484771	12/2015	Braylovskiy et al.	N/A	N/A

9510479	12/2015	Vos	N/A	N/A
9531551	12/2015	Balasubramanian et al.	N/A	N/A
9590811	12/2016	Hunter, Jr. et al.	N/A	N/A
9618714	12/2016	Murray	N/A	N/A
9640998	12/2016	Dawson	N/A	N/A
9665148	12/2016	Hamdi et al.	N/A	N/A
9693244	12/2016	Maruhashi et al.	N/A	N/A
9734940	12/2016	McNutt et al.	N/A	N/A
9768978	12/2016	Coenen et al.	N/A	N/A
9823296	12/2016	Thanner et al.	N/A	N/A
9853689	12/2016	Eaves	N/A	N/A
9874930	12/2017	Vavilala et al.	N/A	N/A
9882656	12/2017	Sipes, Jr. et al.	N/A	N/A
9891678	12/2017	Butcher et al.	N/A	N/A
9893521	12/2017	Lowe et al.	N/A	N/A
9948198	12/2017	Imai	N/A	N/A
9979370	12/2017	Xu	N/A	N/A
9983267	12/2017	Fassnacht et al.	N/A	N/A
9985600	12/2017	Xu et al.	N/A	N/A
10007628	12/2017	Pitigoi-Aron et al.	N/A	N/A
10028417	12/2017	Schmidtke et al.	N/A	N/A
10128764	12/2017	Vinciarelli	N/A	N/A
10191100	12/2018	Blank et al.	N/A	N/A
10248178	12/2018	Brooks et al.	N/A	N/A
10263526	12/2018	Sandusky et al.	N/A	N/A
10281513	12/2018	Goergen et al.	N/A	N/A
10374813	12/2018	Sheffield	N/A	N/A
10407995	12/2018	Moeny	N/A	N/A
10439432	12/2018	Eckhardt et al.	N/A	N/A
10468879	12/2018	Eaves	N/A	N/A
10541543	12/2019	Eaves	N/A	N/A
10541758	12/2019	Goergen et al.	N/A	N/A
10631443	12/2019	Byers et al.	N/A	N/A
10671146	12/2019	Wendt et al.	N/A	N/A
10672537	12/2019	Goergen et al.	N/A	N/A
10714930	12/2019	Weiss et al.	N/A	N/A
10732688	12/2019	Goergen et al.	N/A	N/A
10735105	12/2019	Goergen et al.	N/A	N/A
10790997	12/2019	Jones et al.	N/A	N/A
10809134	12/2019	Bullock et al.	N/A	N/A
10958471	12/2020	Goergen et al.	N/A	N/A
2001/0024373	12/2000	Cuk	N/A	N/A
2002/0126967	12/2001	Panak et al.	N/A	N/A
2004/0000816	12/2003	Khoshnood	N/A	N/A
2004/0033076	12/2003	Song et al.	N/A	N/A
2004/0043651	12/2003	Bain et al.	N/A	N/A
2004/0073703	12/2003	Boucher et al.	N/A	N/A
2004/0264214	12/2003	Xu et al.	N/A	N/A
2005/0044431	12/2004	Lang	713/300	H04L 12/10
2005/0197018	12/2004	Lord	N/A	N/A

2005/0220021	12/2004	Sosnowski et al.	N/A	N/A
2005/0268120	12/2004	Schindler et al.	N/A	N/A
2006/0100799	12/2005	Karam	702/57	G06F 1/3228
2006/0202109	12/2005	Delcher et al.	N/A	N/A
2006/0209875	12/2005	Lum et al.	N/A	N/A
2006/0214253	12/2005	Camagna	257/499	G06F 1/266
2007/0103168	12/2006	Batten et al.	N/A	N/A
2007/0143508	12/2006	Linnman	N/A	N/A
2007/0236853	12/2006	Crawley	N/A	N/A
2007/0263675	12/2006	Lum et al.	N/A	N/A
2007/0284941	12/2006	Robbins	N/A	N/A
2007/0284946	12/2006	Robbins	N/A	N/A
2007/0288125	12/2006	Quaratiello	N/A	N/A
2007/0288771	12/2006	Robbins	N/A	N/A
2008/0054720	12/2007	Lum et al.	N/A	N/A
2008/0198635	12/2007	Hussain et al.	N/A	N/A
2008/0229120	12/2007	Diab	N/A	N/A
2008/0310067	12/2007	Diab et al.	N/A	N/A
2009/0027033	12/2008	Diab	N/A	N/A
2010/0077239	12/2009	Diab et al.	N/A	N/A
2010/0117808	12/2009	Karam	N/A	N/A
2010/0171602	12/2009	Kabbara et al.	N/A	N/A
2010/0190384	12/2009	Lanni	N/A	N/A
2010/0237846	12/2009	Vetteth	N/A	N/A
2010/0290190	12/2009	Chester et al.	N/A	N/A
2011/0004773	12/2010	Hussain et al.	N/A	N/A
2011/0007664	12/2010	Diab et al.	N/A	N/A
2011/0057612	12/2010	Taguchi et al.	N/A	N/A
2011/0083824	12/2010	Rogers	N/A	N/A
2011/0228578	12/2010	Serpa et al.	N/A	N/A
2011/0266867	12/2010	Schindler et al.	N/A	N/A
2011/0290497	12/2010	Stenevik	N/A	N/A
2012/0043935	12/2011	Dyer et al.	N/A	N/A
2012/0064745	12/2011	Ottliczky	N/A	N/A
2012/0170927	12/2011	Huang et al.	N/A	N/A
2012/0188796	12/2011	Randall	N/A	N/A
2012/0201089	12/2011	Barth et al.	N/A	N/A
2012/0231654	12/2011	Conrad	N/A	N/A
2012/0287984	12/2011	Lee	N/A	N/A
2012/0317426	12/2011	Hunter, Jr. et al.	N/A	N/A
2012/0319468	12/2011	Schneider et al.	N/A	N/A
2013/0077923	12/2012	Peeters Weem et al.	N/A	N/A
2013/0079633	12/2012	Peeters Weem et al.	N/A	N/A
2013/0103220	12/2012	Eaves	N/A	N/A
2013/0249292	12/2012	Blackwell, Jr. et al.	N/A	N/A
2013/0262887	12/2012	Biederman et al.	N/A	N/A
2013/0272721	12/2012	Van Veen et al.	N/A	N/A
2013/0329344	12/2012	Tucker et al.	N/A	N/A
2014/0111009	12/2013	Ruef	N/A	N/A

2014/0111180	12/2013	Vladan et al.	N/A	N/A
2014/0126151	12/2013	Campbell et al.	N/A	N/A
2014/0129850	12/2013	Paul	N/A	N/A
2014/0258742	12/2013	Chien et al.	N/A	N/A
2014/0258813	12/2013	Lusted et al.	N/A	N/A
2014/0265550	12/2013	Milligan et al.	N/A	N/A
2014/0372773	12/2013	Heath et al.	N/A	N/A
2015/0019884	12/2014	Huff et al.	N/A	N/A
2015/0078740	12/2014	Sipes, Jr. et al.	N/A	N/A
2015/0106539	12/2014	Leinonen et al.	N/A	N/A
2015/0115741	12/2014	Dawson	N/A	N/A
2015/0137841	12/2014	Thanner et al.	N/A	N/A
2015/0207317	12/2014	Radermacher et al.	N/A	N/A
2015/0215001	12/2014	Eaves	N/A	N/A
2015/0215131	12/2014	Paul et al.	N/A	N/A
2015/0219725	12/2014	Fassnacht et al.	N/A	N/A
2015/0333918	12/2014	White, III	N/A	N/A
2015/0340818	12/2014	Scherer et al.	N/A	N/A
2015/0365003	12/2014	Sadwick	N/A	N/A
2016/0018252	12/2015	Hanson et al.	N/A	N/A
2016/0020911	12/2015	Sipes, Jr. et al.	N/A	N/A
2016/0064938	12/2015	Balasubramanian et al.	N/A	N/A
2016/0069944	12/2015	Blank et al.	N/A	N/A
2016/0111877	12/2015	Eaves et al.	N/A	N/A
2016/0118784	12/2015	Saxena et al.	N/A	N/A
2016/0133355	12/2015	Glew et al.	N/A	N/A
2016/0134331	12/2015	Eaves	N/A	N/A
2016/0142217	12/2015	Gardner et al.	N/A	N/A
2016/0173008	12/2015	Waltuch	N/A	N/A
2016/0188427	12/2015	Chandrashekar et al.	N/A	N/A
2016/0197600	12/2015	Kuznetsov	N/A	N/A
2016/0241148	12/2015	Kizilyalli et al.	N/A	N/A
2016/0262288	12/2015	Chainer et al.	N/A	N/A
2016/0273722	12/2015	Crenshaw	N/A	N/A
2016/0294500	12/2015	Chawgo et al.	N/A	N/A
2016/0294568	12/2015	Chawgo et al.	N/A	N/A
2016/0308683	12/2015	Pischl et al.	N/A	N/A
2016/0334856	12/2015	Yseboodt et al.	N/A	N/A
2016/0352535	12/2015	Hiscock et al.	N/A	N/A
2016/0365967	12/2015	Tu et al.	N/A	N/A
2017/0041152	12/2016	Sheffield	N/A	N/A
2017/0041153	12/2016	Picard et al.	N/A	N/A
2017/0054296	12/2016	Daniel et al.	N/A	N/A
2017/0110871	12/2016	Foster	N/A	N/A
2017/0123466	12/2016	Carnevale	N/A	N/A
2017/0146260	12/2016	Ribbich et al.	N/A	N/A
2017/0155517	12/2016	Cao	N/A	N/A
2017/0155518	12/2016	Yang	N/A	N/A
2017/0164525	12/2016	Chapel et al.	N/A	N/A
2017/0214236	12/2016	Eaves	N/A	N/A

2017/0229886	12/2016	Eaves	N/A	N/A
2017/0234738	12/2016	Ross et al.	N/A	N/A
2017/0237580	12/2016	Radermacher et al.	N/A	N/A
2017/0244318	12/2016	Giuliano	N/A	N/A
2017/0248976	12/2016	Møller et al.	N/A	N/A
2017/0294966	12/2016	Jia et al.	N/A	N/A
2017/0325320	12/2016	Wendt et al.	N/A	N/A
2018/0020881	12/2017	Tessier	N/A	N/A
2018/0024964	12/2017	Mao et al.	N/A	N/A
2018/0053313	12/2017	Smith	N/A	N/A
2018/0054083	12/2017	Hick	N/A	N/A
2018/0060269	12/2017	Kessler	N/A	N/A
2018/0088648	12/2017	Otani	N/A	N/A
2018/0098201	12/2017	Torello et al.	N/A	N/A
2018/0102604	12/2017	Keith et al.	N/A	N/A
2018/0123360	12/2017	Eaves	N/A	N/A
2018/0159430	12/2017	Albert	N/A	N/A
2018/0188712	12/2017	MacKay	N/A	N/A
2018/0191513	12/2017	Hess et al.	N/A	N/A
2018/0254624	12/2017	Son	N/A	N/A
2018/0313886	12/2017	Mlyniec et al.	N/A	N/A
2018/0340840	12/2017	Bullock et al.	N/A	N/A
2019/0064890	12/2018	Donachy et al.	N/A	N/A
2019/0089467	12/2018	Goergen et al.	N/A	N/A
2019/0126764	12/2018	Fuhrer	N/A	N/A
2019/0214814	12/2018	Carty et al.	N/A	N/A
2019/0267804	12/2018	Matan et al.	N/A	N/A
2019/0272011	12/2018	Goergen et al.	N/A	N/A
2019/0277899	12/2018	Goergen et al.	N/A	N/A
2019/0277900	12/2018	Goergen et al.	N/A	N/A
2019/0278347	12/2018	Goergen et al.	N/A	N/A
2019/0280895	12/2018	Mather et al.	N/A	N/A
2019/0281725	12/2018	Byers et al.	N/A	N/A
2019/0304630	12/2018	Goergen et al.	N/A	N/A
2019/0312751	12/2018	Goergen et al.	N/A	N/A
2019/0342011	12/2018	Goergen et al.	N/A	N/A
2019/0363493	12/2018	Sironi et al.	N/A	N/A
2019/0380954	12/2018	Takahashi et al.	N/A	N/A
2020/0044751	12/2019	Goergen et al.	N/A	N/A
2020/0067720	12/2019	Hartnett et al.	N/A	N/A
2020/0153174	12/2019	Curtis et al.	N/A	N/A
2020/0235949	12/2019	Jones et al.	N/A	N/A
2020/0295955	12/2019	O'Brien et al.	N/A	N/A
2020/0389329	12/2019	Jones et al.	N/A	N/A
2022/0190587	12/2021	Eaves et al.	N/A	N/A

FOREIGN PATENT DOCUMENTS

Patent No.	Application Date	Country	CPC
1209880	12/2004	CN	N/A

201689347	12/2009	CN	N/A
204168139	12/2014	CN	N/A
104793544	12/2014	CN	N/A
105049216	12/2014	CN	N/A
204836199	12/2014	CN	N/A
205544597	12/2015	CN	N/A
104081237	12/2015	CN	N/A
106165342	12/2015	CN	N/A
103490907	12/2016	CN	N/A
207135120	12/2017	CN	N/A
104412541	12/2018	CN	N/A
209134431	12/2018	CN	N/A
1936861	12/2007	EP	N/A
2120443	12/2008	EP	N/A
2257009	12/2009	EP	N/A
2432134	12/2011	EP	N/A
2693688	12/2013	EP	N/A
2012003523	12/2011	JP	N/A
2016506711	12/2015	JP	N/A
2016525331	12/2015	JP	N/A
2017195763	12/2016	JP	N/A
20130062224	12/2012	KR	N/A
9316407	12/1992	WO	N/A
2006127916	12/2005	WO	N/A
2007030303	12/2006	WO	N/A
2010053542	12/2009	WO	N/A
2015075821	12/2014	WO	N/A
2017054030	12/2016	WO	N/A
2017167926	12/2016	WO	N/A
2018017544	12/2017	WO	N/A
2019023731	12/2018	WO	N/A
2019176173	12/2018	WO	N/A
2019212759	12/2018	WO	N/A

OTHER PUBLICATIONS

Voltserver Inc., v. Cisco Technology, Inc., “Decision Denying Institution of Post-Grant Review,” United States Patent and Trademark Office, PGR2021-00056, U.S. Pat. No. 10,735,105 B2, Aug. 23, 2021, 18 pages. cited by applicant

Voltserver Inc., v. Cisco Technology, Inc., “Declaration of David A. Durfee, Ph.D.,” United States Patent and Trademark Office, PGR2021-00055, U.S. Pat. No. 10,735,105, Feb. 16, 2021, 340 pages. cited by applicant

Voltserver Inc., v. Cisco Technology, Inc., “Declaration of Stephens S. Eaves,” United States Patent and Trademark Office, PGR2021-00056, U.S. Pat. No. 10,735,105, Feb. 16, 2021, 7 pages. cited by applicant

Yencheck M.R., et al., “Thermal Modeling of Portable Power Cables,” RI9463, 1993, 24 pages. cited by applicant

Ying J-P., “Research and Application of Power Over Ethernet Technology (Modern Communication.03),” Study and Application of Power Over Ethernet Technology, China Academic Journal Electronic Publishing House, Telecommunication Network, published Jun. 30, 2006, pp. 85-87. cited by applicant

Zhang K., et al., "Machine Learning-Based Temperature Prediction for Runtime Thermal Management across System Components," IEEE Transactions on Parallel and Distributed Systems, Mar. 2016, pp. 1-15. cited by applicant

Adapa R., et al., "Dynamic Thermal Rating of Substation Terminal Equipment," Cigre, Jan. 2004, 8 Pages. cited by applicant

Alexander, C.K., "Fundamentals of Electric Circuits," Indian Edition, McGraw Hill Education, MATLAB Examples, 2013, pp. 1-37. cited by applicant

Audio/video, Information and Communication Technology Equipment—Part 1: Safety requirements, International Standard, IEC 62368-1, Edition 2.0, Feb. 2014, ISBN 978-2-8322-1405-3, pp. 1-680. cited by applicant

Belden: "How Cable Temperature Impacts Cable Reach," Sep. 29, 2017, 02 pages. cited by applicant

"Berkeley Lab ETA," Touch-Safe, High Voltage Digital Electricity Transmission Using Packet Energy Transfer, Vimeo, <https://vimeo.com/172469008>, Mar. 8, 2016, 8 pages. cited by applicant

Chen H., et al., "Real-Time Temperature Estimation for Power MOSFETs Considering Thermal Aging Effects," IEEE Transactions on Device and Materials Reliability, Mar. 2014, vol. 14, No. 1, pp. 220-228. cited by applicant

Chen J., et al., "Buck-boost PWM Converters having Two Independently Controlled Switches," 32nd Annual IEEE Power Electronics Specialists Conference, Conference Proceedings, Vancouver, Canada, New York, NY: IEEE, US, Jun. 17-21, 2001, vol. 2, pp. 736-741, DOI: 10.1109/PESC.2001.954206, ISBN 978-0-7803-7067-8 paragraph Section III, XP010559317. cited by applicant

Cheng K.W.E., et al., "Constant Frequency, Two-Stage Quasiresonant Converter," Published in: IEE Proceedings B—Electric Power Applications, May 1, 1992, vol. 139, No. 3, pp. 227-237, 1271980 1, XP000292493, the whole document. cited by applicant

"Digital Electricity Gen2 Detailed Installation Manual," Voltserver Digital Electricity, Rev B.1, Nov. 29, 2017, 68 Pages. cited by applicant

Durfee D.A., "Curriculum Vitae," 4 pages. cited by applicant

Eaves S.S., et al., "Network Remote Power Using Packet Energy Transfer," Sep. 2012, 5 Pages, URL: www.voltserver.com. cited by applicant

Eaves S.S., "Network Remote Powering Using Packet Energy Transfer," Proceedings of IEEE International Conference on Telecommunications Energy (INTELEC), Sep. 30, 2012-Oct. 4, 2012, Scottsdale, AZ, pp. 1-5. cited by applicant

Edelstein S., "Updated 2016 Tesla Model S also Gets New 75-kWh Battery Option," Voltserver Exhibit 1018, May 5, 2016, Archived on Jun. 19, pp. 1-3, Retrieved on Feb. 6, 2021, 2016 by Internet Archive Wayback machine at https://web.archive.org/web/20160619001148/https://www.greencarreports.com/news/1103782_updated-2016-tesla-model-s-also-gets-new-75-kwh-battery-option. cited by applicant

Effects of Current on Human Beings and Livestock—Part 1: General Aspects, Technical Specification, Basic Safety Publication, IEC/TS 60479-1, Edition 4.0, Jul. 2005, ISBN 2-8318-8096-3, pp. 1-122. cited by applicant

"Electrical-Computer Conference Proceedings," Internet Archive WayBack Machine Search for Intelec 2012, Curran Associates, Inc., <http://www.proceedings.com/electrical-computer-proceedings.html>, 2012, 125 pages. cited by applicant

"E-Link Hybrid Connector—QPC Fiber Optic," QPC Engineered Fiber Optic Solutions, pp. 1-4, [Retrieved on Dec. 21, 2017] Retrieved from URL: <http://www.qpcfiber.com/product/connectors/e-link-hybrid-connector/>. cited by applicant

English Translation of Office Action in counterpart Japanese Application No. 2022-507587, mailed May 16, 2023, 3 pages. cited by applicant

Fisher Connectors: "FiberOptic Cable and Connector Solutions," pp. 1-5, [Retrieved on Dec. 21,

2017] Retrieved from URL: <https://www.fischerconnectors.com/us/en/products/fiberoptic>. cited by applicant

Hall S.H., et al., “High-Speed Digital System Design, A Handbook of Interconnect Theory and Design Practices,” Voltserver Exhibit 1030, Aug. 25, Sep. 2000, pp. 1-55. cited by applicant

Hirschmann: “Power over Ethernet (POE), IEE 802.3af,” White Paper, Aug. 2011, 08 Pages. cited by applicant

Hitachi Cable America: “Selecting Cables for Power over Ethernet,” Aug. 12, 2017, 07 pages. cited by applicant

Information Technology Equipment—Safety—Part 1: General Requirements, International Standard, IEC 60950-1, Edition 2.2, May 2013, ISBN 978-2-8322-0820-5, pp. 1-648. cited by applicant

International Search Report and Written Opinion in Counterpart International Application No. PCT/US2020/055532, mailed Mar. 15, 2021, 15 Pages. cited by applicant

“International Telecommunications Energy Conference: [proceedings] (Full Record),” Library Catalog, <https://catalog.oc.gov/vwebv/holdingsInfo?searchId=3810&recPointer=O&recCount=25&searchType=1&bibId=11348322>, retrieved from the Internet Feb. 12, 2021, 4 pages. cited by applicant

“International Telecommunications Energy Conference: [proceedings] (Marc Tags),” Library Catalog, <https://catalog.loc.gov/vwebv/staffView?searchId=3877&recPointer=O&recCount=25&searchType=1&bibId=11348322>, retrieved from the Internet Feb. 12, 2021, 3 pages. cited by applicant

Juniper Networks: “Virtual Chassis Technology Best Practices,” Implementation Guide, Jan. 2016, 29 pages, 8010018-009-EN, URL: <https://www.juniper.net/us/en/local/pdf/implementation-guides/8010018-en.pdf>. cited by applicant

Lathi B.P., et al., “Modern Digital and Analog Communication Systems,” Fourth Edition, Jan. 2009, pp. 1-15. cited by applicant

LC Catalog—Browse, <https://catalog.loc.gov/vwebv/searchBrowse>, retrieved from the Internet Feb. 12, 2021, 1 page. cited by applicant

“Low-voltage Switchgear and Controlgear—Part 1: General Rules,” International Standard, Amendment 2, IEC 60947-1, Edition 5.0, Sep. 2014, ISBN 978-2-8322-1798-6, pp. 1-106. cited by applicant

Lumentum: “Power Over Fiber,” 2015, accessed on Sep. 25, 2020, 8 Pages, Retrieved from URL: https://www.lumentum.com/sites/default/files/technical-library-items/poweroverfiber-tn-pv-ae_0.pdf. cited by applicant

Microsemi, “Understanding 802.3at PoE Plus Standard Increases Available Power,” Voltserver Exhibit 1033, Jun. 2011, pp. 1-7. cited by applicant

NCP1095: “PoE-PD Interface Controller, IEEE 802.3bt,” Jun. 2019, 17 pages. cited by applicant

“NFPA 70: National Electrical Code,” Voltserver Exhibit 1019, National Fire Protection Association, Voltserver Exhibit 1019, published Sep. 26, 2016, 2017 Edition, pp. 1-881. cited by applicant

Notification of Registration and Granting a Patent Right in Counterpart Chinese Application No. 202080070369.3, mailed Apr. 19, 2024, 8 Pages. cited by applicant

Office Action for Indian Application No. 202247007610, dated Mar. 26, 2024, 7 Pages. cited by applicant

Office Action in counterpart Chinese Application No. 202080070369.3, dated Nov. 8, 2023, 18 pages. cited by applicant

“Part VII: A Summary of Commonly Used MARC 21 Fields,” Marc, Understanding MARC, <https://www.loc.gov/marc/Umb/um07to10.html>, retrieved from Internet Feb. 13, 2021, 17 pages. cited by applicant

Petition for Post Grant Review of U.S. Pat. No. 10,735,105 [Public] with Exhibits, filed Feb. 16,

2021, PGR 2021-00055, pp. 1-132. cited by applicant

Petition for Post Grant Review of U.S. Pat. No. 10,735,105 [Public] with Exhibits, filed Feb. 16, 2021, PGR 2021-00056, pp. 1-116. cited by applicant

Planet: “24-Port Gigabit 60W Ultra PoE Managed Injector Hub (800 watts),” UPOE-2400G, Jan. 2016, 07 Pages. cited by applicant

Pluribus Networks: “Pluribus VirtualWire Solution,” Product Overview, PN-PO-VWS-05818, May 2018, 5 pages, URL: <https://www.pluribusnetworks.com/assets/Pluribus-VirtualWire-PO-50918.pdf>. cited by applicant

Rabe C., et al., “Data Center Power Equipment Thermal Guidelines and Best Practices,” ASHRAE Technical Committee (TC) 9.9 Mission Critical Facilities, Data Centers, Technology Spaces, and Electronic Equipment, 2016, pp. 1-60. cited by applicant

Sedra A.S., “Microelectronic Circuits,” Oxford, Seventh Edition, Voltserver Exhibit 1031, Jan. 2015, Published on Nov. 14, 2014, pp. 1-38. cited by applicant

Stallings W., “Data and Computer Communications,” Voltserver Exhibit 1028, Macmillan Publishing Company, Fourth Edition, Jan. 1994, pp. 1-14. cited by applicant

Stran Technologies: “TFOCA GenX Hybrid 2×2 Fiber Optic-Copper Connector,” Contact Strantech, pp. 1-2, [Retrieved on Dec. 21, 2017] Retrieved From URL: <https://www.strantech.com/products/tfoca-genx-hybrid-2x2-fiber-optic-copper-connector/>. cited by applicant

Tanenbaum A.S., “Computer Networks,” Voltserver Exhibit 1027, Prentice Hall PTR, Third Edition, Mar. 1996, pp. 1-12. cited by applicant

Texas Instruments: “IEEE 802.3af PoE Powered Device Controllers with Auto-Retry,” Apr. 2008, 28 pages. cited by applicant

Voltserver Inc., v. Cisco Systems, Inc., “Patent Owner's Preliminary Response to Post Grant Review under 35 U.S.C. 312 and 37 C.F.R. 42.107,” United States Patent and Trademark Office, PGR2021-00056, U.S. Pat. No. 10,735,105, 2021, Jun. 2, 2021, 46 pages. cited by applicant

Voltserver Inc., v. Cisco Systems, Inc., “Patent Owners Preliminary Response to Post Grant Review under 35 U.S.C. 312 and 37 C.F.R. 42.107,” United States Patent and Trademark Office, PGR2021-00055, U.S. Pat. No. 10,735,105, 2021, Jun. 2, 2021, 51 pages. cited by applicant

Voltserver Inc., v. Cisco Technology, Inc., “Decision Denying Institution of Post-Grant Review,” United States Patent and Trademark Office, PGR2021-00055, U.S. Pat. No. 10,735,105 B2, Aug. 19, 2021, 25 pages. cited by applicant

Office Action for counterpart Korean Application No. 1020227017997, dated Oct. 15, 2024, 6 pages. cited by applicant

Office Action for counterpart Japanese Application No. 2023156657, dated Sep. 19, 2024, 4 pages. cited by applicant

Search Report for counterpart European Application No. 20800518.1, dated Oct. 30, 2024, 8 pages. cited by applicant

Microsemi, “PD70101 & PD70201 Production Data Sheet, PD70101/PD70201: IEEE 802.3 af/at Power Over Ethernet PD Controller,” XP055239686, <http://www.electronicsdatasheets.com/download/94188.pdf?format=pdf&part=Microsemi-PD70101>, Sep. 25, 2011, 19 pages. cited by applicant

Primary Examiner: Tran; Khanh C

Background/Summary

STATEMENT OF RELATED APPLICATIONS (1) The present application is a continuation of U.S. patent application Ser. No. 17/171,723, filed Feb. 9, 2021, now U.S. Pat. No. 12,113,588, issued Oct. 8, 2024, which is a divisional of U.S. patent application Ser. No. 16/671,508, filed Nov. 1, 2019, now U.S. Pat. No. 11,063,630, issued Jul. 13, 2021, both of which are incorporated herein by reference in their entireties.

TECHNICAL FIELD

(1) The present disclosure relates generally to power transmittal in a network, and more particularly, to initialization and synchronization for pulse power in a network system.

BACKGROUND

(2) Power over Ethernet (POE) is a technology for providing electrical power over a wired telecommunications network from power sourcing equipment (PSE) to a powered device (PD) over a link section. In conventional PoE systems, power is delivered over the cables used by the data over a range from a few meters to about one hundred meters. When a greater distance is needed or fiber optic cables are used, power must be supplied through a local power source such as a wall outlet due to limitations with conventional PoE. Furthermore, today's PoE systems have limited power capacity, which may be inadequate for many classes of devices.

Description

BRIEF DESCRIPTION OF THE DRAWINGS

- (1) FIG. 1 illustrates an example of a communications network in which embodiments described herein may be implemented.
- (2) FIG. 2 depicts an example of a network device useful in implementing embodiments described herein.
- (3) FIG. 3 is a block diagram illustrating components of a pulse power system, in accordance with one embodiment.
- (4) FIG. 4 is a flowchart illustrating low voltage initialization for a pulse power system, in accordance with one embodiment.
- (5) FIG. 5 is a flowchart illustrating high voltage initialization for the pulse power system, in accordance with one embodiment.
- (6) FIG. 6 is a diagram illustrating high voltage initialization pulse limits within a safe region, in accordance with one embodiment.
- (7) FIG. 7 is a flowchart illustrating a cable capacitance and safety test, in accordance with one embodiment.
- (8) FIG. 8 is a block diagram illustrating an extended safe power system for delivering pulse power, in accordance with one embodiment.
- (9) FIG. 9A is an example of a circuit for use in the cable capacitance and safety test of FIG. 7, in accordance with one embodiment.
- (10) FIG. 9B illustrates current and voltage at a cable corresponding to changes in state of switches in the circuit of FIG. 9A.
- (11) FIG. 9C is an example of a circuit for use in another cable capacitance and safety test, in accordance with one embodiment.
- (12) FIG. 9D illustrates current and voltage at a cable corresponding to changes in state of switches in the circuit of FIG. 9C.
- (13) FIG. 10A is a block diagram illustrating a circuit for use in synchronization, in accordance with one embodiment.
- (14) FIG. 10B illustrates voltage at a cable corresponding to changes in state of switches in the circuit of FIG. 10A.

- (15) FIG. 11A is a block diagram illustrating a circuit for use in the low voltage initialization of FIG. 4, in accordance with one embodiment.
- (16) FIG. 11B illustrates cable voltage and housekeeping power corresponding to changes in state of a power sourcing equipment switch in the circuit of FIG. 11A.
- (17) FIG. 11C is an example of a low voltage start-up circuit, in accordance with one embodiment.
- (18) FIG. 12A is a block diagram illustrating details of a housekeeping power circuit of FIG. 11A.
- (19) FIG. 12B illustrates details of the housekeeping power circuit of FIG. 11C.
- (20) FIG. 12C is a block diagram of the housekeeping power circuit of FIG. 12B.
- (21) FIG. 13A is a block diagram illustrating a circuit for use in the high voltage initialization of FIG. 5, in accordance with one embodiment.
- (22) FIG. 13B illustrates cable voltage and housekeeping power corresponding to changes in state of a power sourcing equipment switch in the circuit of FIG. 13A.
- (23) FIG. 14 is a block diagram of a circuit illustrating a safety crowbar/shorting relay added to a high voltage source in the circuit of FIG. 8.
- (24) FIG. 15 shows a cable with optical fibers and two twisted pairs connecting power sourcing equipment to a powered device for delivery of extended safe power, in accordance with one embodiment.
- (25) FIG. 16 illustrates details of one of the twisted pairs shown in FIG. 15, in accordance with one embodiment.
- (26) FIG. 17 illustrates an example of power and data distribution to a plurality of powered devices, in accordance with one embodiment.
- (27) FIG. 18 is a simplified block diagram illustrating an example of voltage and power levels between the power sourcing equipment and powered device in an extended safe power system, in accordance with one embodiment.
- (28) FIG. 19 is another simplified block diagram illustrating an example of voltage and power levels between the power sourcing equipment and the powered device in the extended safe power system, in accordance with one embodiment.
- (29) FIG. 20 is a block diagram illustrating an example of a multi-node three-phase pulse power system, in accordance with one embodiment.
- (30) FIG. 21 illustrates an example of three-phase pulse power voltage and current for the system shown in FIG. 20 with constant power loading from endpoint nodes.
- (31) FIG. 22 illustrates a simplified circuit of a two-phase pulse power system on a cable with four-pair wire, in accordance with one embodiment.
- (32) FIG. 23 illustrates synchronization of power sourcing equipment and powered device modulator switches in a four-phase pulse power system.
- (33) FIG. 24 shows the four-phase pulse power system of FIG. 23 with one phase dropped.
- (34) FIG. 25 is a block diagram illustrating a point-to-point topology, in accordance with one embodiment.
- (35) FIG. 26 is a block diagram illustrating a daisy chain topology, in accordance with one embodiment.
- (36) FIG. 27 is a block diagram illustrating a multi-drop topology, in accordance with one embodiment.
- (37) FIG. 28 is a block diagram illustrating a hybrid multi-drop/daisy chain topology, in accordance with one embodiment.
- (38) FIG. 29 is a block diagram illustrating power sourcing equipment and two powered devices in a hybrid multi-drop/daisy chain topology in a powered off state, in accordance with one embodiment.
- (39) FIG. 30 shows the power sourcing equipment and powered devices of FIG. 29 during power sourcing equipment detection of a first powered device.
- (40) FIG. 31 shows the power sourcing equipment and powered devices of FIG. 29 during power

up of the first powered device.

(41) FIG. 32 shows a training phase for the first powered device.

(42) FIG. 33 shows an identification phase for the first powered device.

(43) FIG. 34 shows a final safety check before enabling high voltage pulse power at the power sourcing equipment.

(44) FIG. 35 shows the power sourcing equipment transmitting high voltage pulse power to the first powered device.

(45) FIG. 36 shows the power sourcing equipment establishing communications with the first powered device.

(46) FIG. 37 shows detection of a second powered device at the first powered device and initialization of the second powered device.

(47) FIG. 38 shows a safety check by the power sourcing equipment for the second powered device and transmission line.

(48) FIG. 39 shows the power sourcing equipment transmitting high voltage pulse power to both powered devices.

(49) FIG. 40 shows the power sourcing equipment delivering high voltage pulse power and communicating with both powered devices.

(50) Corresponding reference characters indicate corresponding parts throughout the several views of the drawings.

DESCRIPTION OF EXAMPLE EMBODIMENTS

Overview

(51) In one embodiment, a method generally comprises transmitting from power sourcing equipment, low voltage pulse power to a powered device, performing a safety test, enabling high voltage pulse power operation at the power sourcing equipment upon passing the safety test, and transmitting high voltage pulse power from the power sourcing equipment to the powered device. The powered device synchronizes with a waveform of the low voltage pulse power.

(52) In another embodiment, a method generally comprises receiving low voltage pulse power from power sourcing equipment at a powered device, synchronizing timing of a modulator at the powered device with a waveform of the low voltage pulse power received from the power sourcing equipment, and operating with high voltage pulse power received from the power sourcing equipment.

(53) In another embodiment, a method generally comprises receiving high voltage pulse power from power sourcing equipment at a powered device with a modulator switch open, coupling isolated voltage at the powered device when a pulse of the high voltage pulse power is on, energizing a housekeeping circuit at the powered device, and turning on the modulator switch at the powered device after a specified number of high voltage pulses are received.

(54) In yet another embodiment, a method generally comprises identifying at a first powered device in communication with power sourcing equipment, a second powered device in communication with the first powered device, wherein the first powered device is receiving high voltage pulse power from the power sourcing equipment, notifying the power sourcing equipment of the second powered device, and performing a low voltage power initialization at the first powered device with the second powered device before passing the high voltage pulse power to the second powered device.

(55) Further understanding of the features and advantages of the embodiments described herein may be realized by reference to the remaining portions of the specification and the attached drawings.

Example Embodiments

(56) The following description is presented to enable one of ordinary skill in the art to make and use the embodiments. Descriptions of specific embodiments and applications are provided only as examples, and various modifications will be readily apparent to those skilled in the art. The general

principles described herein may be applied to other applications without departing from the scope of the embodiments. Thus, the embodiments are not to be limited to those shown, but are to be accorded the widest scope consistent with the principles and features described herein. For purpose of clarity, details relating to technical material that is known in the technical fields related to the embodiments have not been described in detail. In conventional Power over Ethernet (POE) systems used to simultaneously transmit power and data communications, power is delivered over the same twisted pair cable used for data. These systems are limited in range to a few meters to about 100 m (meters). Conventional PoE over communications cabling is generally limited to about 90 W (Watts) based on IEEE 802.3bt, but many classes of powered devices would benefit from power delivery greater than 100 W and in some cases greater than 1000 W. For example, conventional PoE does not provide sufficient power for higher power communications systems such as remote radio heads or front haul routers as seen in cellular networks that typically need between 300 W and 1000 W to operate. Also, enterprise products that provide switching, routing, and power for access points and IP (Internet Protocol) phone systems often need about 1000 W to 1500 W of power. In conventional systems, when larger power delivery ratings are needed, power is supplied to a remote device through a local power source. However, in network communications systems such as 5G cellular build-outs or other communications systems and connected buildings with multiple non-centralized routers on each floor, AC (Alternating Current) grid power is not always available, may not be cost effective to build out at the start, or practical in some locations (e.g. wireless base stations), and in many cases cost prohibitive. For example, in locations that are listed as “co-location”, power is typically charged on a per connection basis, not consumed power, making each additional AC connection very expensive. AC grid power systems are often used because DC (Direct Current) power systems are not a good solution over long distances. There is a therefore a need for a means to deliver power to these and other devices without having to add an AC outlet or other type of secondary power feed.

(57) An increase in power available over multi-function cables to hundreds and even thousands of watts may enable many new choices in network deployments where major devices such as workgroup routers, multi-socket servers, large displays, wireless access points, fog nodes, or other devices are operated. This capability would greatly decrease installation complexity and improve the total cost of ownership of a much wider set of devices that have their power and data connectivity needs met from a central hub.

(58) In order to overcome the above issues, power and data delivery systems may be designed to carry higher data rates and higher power delivery (and may also carry integrated thermal management cooling) combined into a single cable, as described in U.S. patent application Ser. No. 15/910,203 (“Combined Power, Data, and Cooling Delivery in a Communications Network”), filed Mar. 2, 2018, which is incorporated herein by reference in its entirety. These connections may be point-to-point, such as from a central hub to one or more remote devices (e.g., full hub and spoke layout). In another example, a single combined function cable may run most of the way to a cluster of powered devices and then split, as described in U.S. patent application Ser. No. 15/918,972 (“Splitting of Combined Delivery Power, Data, and Cooling in a Communications Network”), filed Mar. 12, 2018, which is incorporated herein by reference in its entirety. With high power applications, further safety concerns arise, which may result in the need for additional testing or safety checks at start-up and during power transmittal.

(59) Embodiments described herein provide for safe delivery of high power over a data system (also referred to herein as advanced power over data or Extended Safe Power (ESP)) in a network system through the use of pulse power with fault detection and safety protection. The power may be transmitted in a network system (e.g., network communications system) with or without communications. The term “pulse power” as used herein refers to power that is delivered in pulses that vary between a very small voltage (e.g., close to 0V (volts), 3V) during a pulse off interval and a larger voltage (e.g., $\geq 12V$) during a pulse on interval. High voltage pulse power (e.g., $> 56V$,

$\geq 60\text{V}$, $\geq 300\text{V}$) may be transmitted from power sourcing equipment (PSE) to a powered device (PD) for use in powering the powered device, whereas low voltage pulse power (low voltage pulses) (e.g., $\sim 12\text{V}$, $\leq 30\text{V}$, $\leq 56\text{V}$) may be used over a short interval for start-up (e.g., initialization, synchronization, charging local energy storage, powering up a controller, testing, or any combination thereof). As described in detail below, an initialization process (low voltage or high voltage initialization process) may be performed prior to transmitting high voltage pulse power to synchronize the PSE and PD and provide a safe start-up. The initialization process may comprise, for example, a safety test including a cable capacitance test and synchronization of modulator switch (pulse) timing between the power sourcing equipment and the powered device. As described below, the initialization may be performed for multiple phases in a multi-phase pulse power system and in various network topologies.

(60) For example, one or more embodiments may use multiple phase (multi-phase) pulse power to achieve less loss, effectively 100% duty cycle power delivery (e.g., continuous uninterrupted power to the output with overlapping phase pulses) to a powered device, while enhancing reliability per power connection and providing safe operation over an extended length of cable to deliver high power, as described in U.S. patent application Ser. No. 16/380,954 (“Multiple Phase Pulse Power in a Network Communications System”), filed Apr. 10, 2019, which is incorporated herein by reference in its entirety. Multiple pair cabling may be used, for example, with a DC pulse on each pair, timed in such a manner as to provide 100% net duty cycle continuous power at the powered device (or load). Pulse power transmissions may be through cables, transmission lines, busbars, backplanes, PCBs (Printed Circuit Boards), and power distribution systems, for example.

(61) The ESP system may test the network devices or cables to identify faults or safety issues. The system may be configured, for example, to identify transmission errors, phase faults (in multi-phase systems), over current, arc events, time base control synchronization faults, MAC drops, or any other communication or power faults or errors. These faults may be identified on a per phase basis in a multi-phase system. As described below, a low voltage initialization may be used for startup (or restart) to test the network and components (as described below with respect to the flowchart of FIG. 4). A high voltage initialization (described below with respect to the flowchart of FIG. 5) may also be used to allow for adding a new PD or a hot-swap replacement of a PD without requiring a low voltage initialization process.

(62) In addition to performing testing during start-up and initialization, testing may continue to be performed during high voltage operation to safely deliver power in the ESP system. In one or more embodiments, fault sensing may be performed through a low voltage safety check combined with a digital interlock that uses the data system to provide feedback on the power system status and set a power operation mode, as described in U.S. patent application Ser. No. 15/971,729, (“High Power and Data Delivery in a Communications Network with Safety and Fault Protection”), filed May 4, 2018, which is incorporated herein by reference in its entirety. The fault sensing may be performed during a low voltage startup or between high power pulses in the pulse power system. The pulse power may comprise source voltage pulse power (unipolar or bipolar) or load current pulse power with low voltage fault detection between high voltage power pulses. Fault sensing may include, for example, line-to-line fault detection with low voltage sensing of the cable or powered device and line-to-ground fault detection with midpoint grounding. Touch-safe fault protection may also be provided through cable and connector designs that are touch-safe even with high voltage applied. The power safety features provide for safe system operation and installation and removal (disconnect) of components, including in some cases replacement of components without disturbing normal operation of the system (i.e., hot swappable).

(63) The Off-time between pulses may be used, for example, for line-to-line resistance testing for faults and the pulse width may be proportional to DC line-to-line voltage to provide touch-safe fault protection (e.g., about 1 ms at about 1000V). The testing (fault detection, fault protection, fault sensing, touch-safe protection) may comprise auto-negotiation between the PSE and PDs.

Low voltage (e.g., less than or equal to 24 VDC (volts direct current), 5-12 VDC, 56 VDC or any other suitable low voltage (e.g., <60 VDC)) resistance analysis may be used for auto-negotiation. The pulse power high voltage DC may be used with a pulse-to-pulse decision for touch-safe line-to-line fault interrogation between pulses for personal safety. Line-to-line touch shock protection may be provided with a source pulse Off-time between pulses for resistance across line detection between pulses.

(64) Ground-fault-detection (GFD) and ground-fault-isolation (GFI) line-to-ground fault detection may be performed to provide fast high voltage interruption with ground fault protection (shock protection) during high voltage operation as part of using a high-resistance mid-point ground circuit. A high voltage DC supply line-to-ground fault protection circuit may be used to turn off power quickly to provide touch-safe shock protection. GFD and GFI may provide shut off in approximately 10 μ s (microseconds), for example. A midpoint grounding method by the power source may also be used to allow higher peak pulse line-line voltage within the wire/conductor insulation and isolation ratings for line-ground protection and also provide touch-safe line-to-ground fault for personal safety and to meet safety standards. The system may also be designed for adjustable time and current versus voltage for personal shock protection.

(65) In one or more embodiments, the system may also test for thermal buildup using thermal modeling of the cable as described in U.S. patent application Ser. No. 15/604,344, entitled "Thermal Modeling for Cables Transmitting Data and Power", filed May 24, 2017, which is incorporated herein by reference in its entirety. For example, thermal buildup may be detected by tracking cable current change and calculating cable current temperature. The cable temperature is a function of amperage, cable gauge, and length of cable. By using known parameters and assuming a wire size (e.g., 22 AWG), the temperature limit of the cable in a bundle environment may be calculated. Temperature ranges may be defined, for example, as normal, minor, major, and critical (e.g., minor defined within 20° C. of cable temperature limit, major defined within 10° C. of cable temperature limit, and critical defined at cable temperature limit). If the temperature range is in the minor range, the system may force renegotiation of power to reduce current on the line. If the temperature is in the critical range, the port may be de-energized. The temperature may be calculated in each wire, each pair of wires, the four-pair cable, or any combination thereof.

(66) In one or more embodiments, the system may also perform a wire fault and electrical imbalance detection as described in U.S. patent application Ser. No. 16/020,881, entitled "Wire Fault and Electrical Imbalance Detection for Power over Communications Cabling", filed Jun. 27, 2018, which is incorporated by reference in its entirety.

(67) In one or more embodiments, the PSE may inform the PD of a power level that the PSE is capable of providing and the PD may then select the appropriate power level to use. The PSE and PD may negotiate power levels, for example, of 15 W, 30 W, 60 W, 90 W, 150 W, 200 W, 250 W, 300 W, or any other suitable power level. If no faults are detected, the system may auto-negotiate to maximum available power. Once the power is increased, fault detection may continue to be performed, as previously described. Fault detection may include for example, a check for thermal buildup, an electrical imbalance check (wire-to-wire imbalance check, pair-to-pair imbalance check), or short circuit/fault protection check. The system may be configured to perform one or more of these checks in any order or some steps may be performed simultaneously. One or more of the safety checks may be performed continuously or at specified intervals. For example, the wires may be monitored one by one in a continuous loop within a 10 ms window. If a fault is detected or a specified PSE voltage is exceeded, power output is shutdown. If the fault is minor (e.g., one or more parameters close to limit but not exceeding limit), power may be reduced through renegotiation of the power level. If the fault continues, the port may then be shutdown. An alarm may also be generated. In one or more embodiments, packet and idle (link) monitoring may be used to shut down the power. If a wire is lost, the link is lost and per wire faults are covered.

(68) Action may also be taken based on the monitored (or calculated) current. For example, if the

current in the cable exceeds the cable current maximum limit, the port may be shutdown. If the cable current reaches a specified range, the line card (PD) may be forced to perform power negotiation with the PSE to reduce current on the line. The current may be monitored per wire, per pair of wires, per cable, or any combination. Current ranges may be defined as normal, minor, major, and critical (e.g., minor defined within 20% maximum current, major defined within 10% maximum current, and critical defined at maximum current). If the range is minor, renegotiation may be performed to reduce current on the cable. If the critical current is reached, the port may be de-energized.

(69) In one or more embodiments, one or more parameters may be user defined. For example, cable impedance, cable length, cable gauge, and cable voltage rating may be set for an ESP system or link. The ESP system may set a maximum voltage, current, or power based on these parameters. As described herein, the system may perform cable safety tests based on cable capacitance. The system may also perform GFI fault tests and line-to-line fault tests as described above for low voltage and high voltage. If a fault is identified, the system may set a fault latch and attempt an auto-restart one or more times. One or more components in the ESP system may include one or more visual indicators (e.g., LED (Light Emitting Diode)) to identify low voltage operation, high voltage operation, or system/component/cable fault, for example.

(70) In one or more embodiments, machine learning may be performed by periodically monitoring and collecting data (e.g., current, voltage, cable capacitance, faults, temperature, etc.) to further define acceptable limits and account for variation in electrical performance based on changes in cable, environment, or components over time. For example, an analytical model may be defined and updated based on data trends for use in updating voltage and load current and operating limits to account for variations in electrical parameters and avoid false system faults.

(71) In one or more embodiments, the PSE may deliver >100 W to a plurality of PDs along with data (e.g., over copper wires or optical fibers) on a power and data combined cable, as described below. In one or more embodiments, the system may safely deliver 2000 W or more of power at cable lengths exceeding 1500 meters. The system may also safely deliver higher power (e.g., 6000 W) on cable lengths less than 25 meters, making it very valuable in de-centralizing large chassis systems to eliminate the back plane/large chassis system design. It is to be understood that the power levels and cable distances described herein are provided as examples and other power levels delivered over different cable lengths may be used without departing from the scope of the embodiments.

(72) The system may be configured to meet safety standards, including, for example, IEC (International Electrotechnical Commission) standard Nos. 62368-3:2017 (“Audio/video information and communication technology equipment—Part 3: Safety aspects for DC power transfer through communication cables and ports”), IEC 60950-1:2005 (“Information technology equipment—Safety—Part 1: General requirements”), IEC 60947 (“Low-voltage switchgear and control gear”), or any other applicable standard to provide touch-safe shock protection for personnel for high voltage (higher power) applications in the extended safe power system. The system may be configured, for example, to limit shock current with line-to-ground fault limit of about 5 mA (e.g., less than 10 mA) and line-to-line fault limit of about 0.5 A for 1 ms using about 2.5 kohms across HVDC power (e.g., 1100V, 550V, 380V) (e.g., for short reach cabling or smart digital sensing techniques). In another example, worst case shock exposure time may be 12 ms. Appropriate techniques (e.g., fail-safe Safety Agency Approved Listed components, redundant circuits or components) may be employed in order to meet safety standards.

(73) The Off-time of the pulses may be configured based on cable pair capacitance and maximum pulse power. On-time may be designed to be below limits set by body shock current and standards (e.g., as referenced in UL (Underwriters Laboratories) standards 62368 and 60950 or NFPA (National Fire Protection Association) NEC (National Electrical Code) 70 chapter 7, chapter 8, and tables 11A and 11B in chapter 9, IEC/TR 60479-5, 60479-1, IEC-60947-1, IEC-60947-2, IEC-

60947-3, IEC-60335-1, IEC-60990, IEC-60065, IEC-61000-4, or any other appropriate standard or requirement). In one or more embodiments, On-time and Off-time pulse widths may be set dynamically in response to changing cable characteristics. The need for continuous net current supply to the PD may determine the phase relationship of pulses on multiple transmission pair systems. The embodiments described herein may be configured to meet single fault protection or other safety requirements. It is to be understood that the standards and limits discussed herein are only provided as examples and other safety limits or standards may be used, without departing from the scope of the embodiments.

(74) Referring now to the drawings, and first to FIG. 1, an example of a communications network in which embodiments described herein may be implemented is shown. For simplification, only a small number of nodes are shown. The embodiments operate in the context of a data communications network including multiple network devices. The network may include any number of network devices in communication via any number of nodes (e.g., routers, switches, gateways, controllers, access points, or other network devices), which facilitate passage of data within the network. The network devices may communicate over or be in communication with one or more networks (e.g., local area network (LAN), metropolitan area network (MAN), wide area network (WAN), virtual private network (VPN) (e.g., Ethernet virtual private network (EVPN), layer 2 virtual private network (L2VPN)), virtual local area network (VLAN), wireless network, enterprise network, corporate network, data center, Internet of Things (IoT) network, Internet, intranet, or any other network).

(75) In one or more embodiments, the network is configured to pass electrical power along with data to provide both data connectivity and electric power to network devices such as switches **14**, routers, access points **15**, or other electronic components and devices. Signals may be exchanged among communications equipment and power transmitted from power sourcing equipment (PSE) **10** to powered devices (PDs) **14**, **15**, **17**, **19**. In one or more embodiments, the system delivers power to and from a network (e.g., switch/router system) using an interface module **16** (e.g., optical transceiver module) configured to receive and transmit both data (fiber delivered data) and electrical power (high power energy). In one or more embodiments, the power and data may be delivered over a cable comprising both optical fibers and electrical wires (e.g., copper wires), as described in U.S. patent application Ser. No. 15/707,976 (“Power Delivery Through an Optical System”), filed Sep. 18, 2017, which is incorporated herein by reference in its entirety. In one or more embodiments, the system may further provide cooling and deliver combined power, data, and cooling within a single hybrid cable system, as described, for example, in U.S. patent application Ser. Nos. 15/910,203 and 15/918,972, referenced above.

(76) As shown in the example of FIG. 1, the system may use building power supplied to a central network device (hub) (PSE) **10**, which may be located in a premise/entry room, for example. The power may be transmitted from a building entry point to end points (switches **14**, access points **15**), which may be located at distances greater than 100 meters (e.g., 1 km (kilometer), 10 km, or any other distance), and/or at greater power levels than 100 W (watts) (e.g., 250 W, 500 W, 1000 W, 2000 W or any other power level). The central network device **10** comprises one or more power supply unit (PSU) **11** for receiving and distributing power (e.g., building power from a power grid, renewable energy source, generator, or battery) and a network interface (e.g., fabric **12**, line cards **13**). In the example shown in FIG. 1, line card A receives data from outside of the building (e.g., from street or other location) and line cards B, C, and D distribute power and data.

(77) The central hub (combined power and data source) **10** is operable to provide high capacity power from an internal power system (e.g., PSU **11** capable of delivering power over and including 5 kW, 100 KW, etc., and driving the plurality of devices **14**, **15**, each in the 100 W-3000 W range (e.g., 100 W or greater, 900 W or greater, 1000 W or greater), or any other suitable power range. The PSU **11** may provide, for example, PoE (Power over Ethernet), PoF (Power over Fiber), HVDC (high voltage direct current), pulse power HVDC, or AC (alternating current). The central

network device **10** is operable to receive external power and transmit power over combined delivery power and data cables **18** in the communications network (e.g., network comprising central hub **10** (PSE) and a plurality of network devices **14**, **15**, **17**, **19** (PDs)). The central network device **10** may comprise, for example, a router, convergence system, or any other suitable line card system. It is to be understood that this is only an example and any other network device operable to transmit power and optical data may be used. One or more of the line cards **13** may also include the interface module **16** (shown at the remote network devices **14**, **15**) operable to transmit power and data on the cables **18**.

(78) The network may include any number or arrangement of network communications devices (e.g., switches **14**, access points **15**, routers, or other devices operable to route (switch, forward) data communications). In one example, the network comprises a plurality of groups of access points **15**, with each group located on a different floor or zone. One or more of the network devices **14**, **15** may also deliver power to a downstream node (e.g., PoE device **19**) using PoE. For example, one or more of the network devices **14**, **15** may deliver power using PoE to electronic components such as IP (Internet Protocol) cameras, VoIP (Voice over IP) phones, video cameras, point-of-sale devices, security access control devices, residential devices, building automation devices, industrial automation devices, factory equipment, lights (building lights, streetlights), traffic signals, fog nodes, IoT devices, sensors, and many other electrical components and devices. In one or more embodiments, a redundant central hub (not shown) may provide backup or additional power or bandwidth, as needed in the network. In this case, the remote network device **14**, **15** would include another interface module **16** for connection with another cable **18** delivering power and data from the redundant central hub. As described in detail below, the network may be arranged in various topologies, including for example, point-to-point, daisy chain, multi-drop, or hybrid multi-drop/daisy chain for delivering high voltage pulse power to a downstream device (e.g., PD **17** in communication with switch **14**).

(79) As previously noted, the central hub **10** may deliver power and data directly to each network device **14** (point-to-point connection as shown for the switches **14** connected to line cards B and D in FIG. 1) or one or more splitting devices (not shown) may be used to connect a plurality of network devices and allow the network to go beyond point-to-point topologies and build passive stars, busses, tapers, multi-layer trees, etc. For example, a single long cable **18** may run to a conveniently located intermediary splitter device (e.g., passive splitter) servicing a cluster of physically close endpoint devices. One or more control systems for the power and data may interact between the central hub **10** and the remote devices **15** (and their interface modules **16**) to ensure that each device receives its fair share of each resource from the splitting device, as described in U.S. patent application Ser. No. 15/918,972, referenced above.

(80) In one or more embodiments, cables (combined cable, multi-function cable, multi-use cable, hybrid cable) **18** extending from the network device **10** to the switches **14** and access points **15** are configured to transmit power and data, and include both optical fibers and electrical wires. The cable **18** may include, for example, two power lines (conductors) and two data lines (optical fibers). It is to be understood that this is only an example and the cable **18** may contain any number of power or data lines. For example, instead of using two optical fiber paths to transfer data from the central hub **10** to the remote device **14**, **15** and from the remote device to the central hub, a bidirectional optical system may be utilized with one wavelength of light going downstream (from central hub **10** to remote device **14**, **15**) and a different wavelength of light going upstream (from remote device **14**, **15** to central hub **10**), thereby reducing the fiber count in the cable from two to one. The cable **18** may also include additional optical fibers or power lines. The cables **18** may be formed from any material suitable to carry both electrical power and optical data (e.g., copper, fiber) and may carry any number of electrical wires and optical fibers in any arrangement. The cable **18** may transmit one or more of power, data (electrical), data (optical), and cooling.

(81) As previously noted, the cables **18** may also carry cooling for thermal management of the

remote network communications devices **14**, **15**. For example, in one or more embodiments, the cables **18** extending from the central hub **10** to the remote network devices **14**, **15** may be configured to transmit combined delivery power, data, and cooling in a single cable. In this embodiment, the cables **18** may be formed from any material suitable to carry electrical power, data (e.g., copper, fiber), and coolant (liquid, gas, or multi-phase) and may carry any number of electrical wires, optical fibers, and cooling tubes in any arrangement.

(82) The cables **18** comprise a connector at each end configured to couple with the interface module **16** at the network devices **10**, **14**, **15**. The connector may comprise, for example, a combined power and data connector (hybrid copper and fiber) configured to connect to an optical transceiver, as described in U.S. patent application Ser. No. 15/707,976, referenced above. The connector may comprise, for example, a modified RJ-45 type connector.

(83) In one or more embodiments, the connectors and cable **18** are configured to meet standard safety requirements for line-to-ground protection and line-to-line protection at relevant high voltage by means including clearance and creepage distances, and touch-safe techniques. The connector may comprise safety features, including, for example, short-pin for hot-plug and hot-unplug without current surge or interruption for connector arcing protection. The connector may further include additional insulation material for hot-plug and hot-unplug with current surge or interruption with arc-flash protection and reliability life with arcing. The insulated cable power connector terminals are preferably configured to meet touch voltage or current accessibility requirements.

(84) As previously noted, one or more of the network devices **10**, **14**, **15** may comprise an interface module **16** operable to deliver the combined power and data from the PSE **10** or receive the combined power and data at the PD **14**, **15**. In one or more embodiments, the interface module **16** may comprise an optical transceiver module configured to deliver (or receive) power along with the optical data. For example, in one embodiment, the interface module **16** comprises a transceiver module modified along with a fiber connector system to incorporate copper wires to deliver power through the optical transceiver to the powered device **14**, **15** for use by the network communications devices, as described in U.S. patent application Ser. No. 15/707,976, referenced above or in U.S. patent application Ser. No. 15/942,015 (“Interface Module for Combined Delivery Power, Data, and Cooling at a Network Device”), filed Mar. 30, 2018, which is incorporated herein by reference in its entirety. It is to be understood that these are only examples of interface modules that may be used to deliver or receive high power and optical data.

(85) The interface module **16** (optical module, optical transceiver, optical transceiver module, optical device, optics module, silicon photonics module) is configured to source or receive power. The interface module **16** operates as an engine that bidirectionally converts optical signals to electrical signals or in general as an interface to the network element copper wire or optical fiber. In one or more embodiments, the interface module **16** may comprise a pluggable transceiver module in any form factor (e.g., SFP (Small Form-Factor Pluggable), QSFP (Quad Small Form-Factor Pluggable), CFP (C Form-Factor Pluggable), and the like), and may support data rates up to 400 Gbps, for example. Hosts for these pluggable optical modules include line cards **13** on the central network device **10**, switches **14**, access points **15**, or other network devices. The host may include a printed circuit board (PCB) and electronic components and circuits operable to interface telecommunications lines in a telecommunications network. The host may be configured to perform one or more operations and receive any number or type of pluggable transceiver modules configured for transmitting and receiving signals.

(86) Also, it may be noted that the interface module **16** may be configured for operation in point-to-multipoint or multipoint-to-point topology. For example, QFSP may breakout to SFP+. One or more embodiments may be configured to allow for load shifting. The interface module **16** may also be configured for operation with AOC (Active Optical Cable) and form factors used in UWB (Ultra-Wideband) applications, including for example, Ultra HDMI (High-Definition Multimedia

Interface), serial high bandwidth cables (e.g., thunderbolt), and other form factors.

(87) The interface module **16** provides for power to be delivered to the switches **14** and access points **15** in locations where standard power is not available. The interface module **16** may be configured to tap some of the energy and make intelligent decisions so that the power source **10** knows when it is safe to increase power on the wires without damaging the system or endangering an operator, as described below. The interface module **16** may include one or more sensors, monitors, or controllers for use in monitoring and controlling the power and data, as described in detail below with respect to FIG. 3.

(88) In one or more embodiments, there is no need for additional electrical wiring for the communications network and all of the network communications devices operate using the power provided by the extended safe power system. In addition to the network devices **10**, **14**, **15** comprising interface modules **16** operable to receive and transmit power over electrical wires and optical data over fibers, the network may also include one or more network devices comprising conventional optical modules that only process and transmit the optical data. These network devices would receive electrical power from a local power source such as a wall outlet. Similarly, specialized variants of transceivers **16** may eliminate the optical data interfaces, and only interconnect power (e.g., moving data interconnection to wireless networks). As previously noted, one or more of the network devices may also receive cooling over cable **18** in addition to power, data, or power and data.

(89) In one or more embodiments, a distributed control system comprising components located on the central hub's controller and on the remote device's processor may communicate over the fiber links in the combined cable **18**. Monitoring information from power sensors (e.g., current, voltage) or data usage (e.g., bandwidth, buffer/queue size) may be used by the control system in managing or allocating power or data.

(90) The system may be configured to deliver POE, PoF, high voltage DC (HVDC), AC power, pulse power, multi-phase pulse power, or any combination thereof. The HVDC power may comprise steady state HVDC or pulse power HVDC. The steady state and pulse power HVDC may be unipolar or bipolar (switching DC), as described in U.S. patent application Ser. No. 15/971,729, referenced above. In one or more embodiments, the system may employ a dual-power mode that detects and negotiates between the power source **10** and powered device **14**, **15**. This negotiation distinguishes between and accommodates different power-delivery schemes, such as standard PoE or PoF, high power, pulse power, or other power modes capable of power delivery through the interface module **16**. For example, standard PoE distribution may be used for remote network devices rated less than about 100 W. For higher power remote powered devices, pulse power or other higher voltage techniques may be used to create an efficient energy distribution network.

(91) As described in detail below, the remote network device **14**, **15**, **17** may use a small amount of power at startup to communicate its power and data requirements to the central network device **10**. The powered device **14**, **15**, **17** may then configure itself accordingly for full power operation. In one example, power type, safety operation of the module, and data rates are negotiated between the central hub (PSE) **10** and the network device **14**, **15**, **17** through data communications signals on the optical fiber. The interface module **16** communicates any operational fault, including the loss of data. Such fault may result in power immediately being turned off or switching to a low power (low voltage) mode. Full power supply may not be reestablished until the powered device is able to communicate back in low power mode that higher power may be safely applied.

(92) It is to be understood that the network devices and topology shown in FIG. 1, and described above is only an example and the embodiments described herein may be implemented in networks comprising different network topologies or network devices, without departing from the scope of the embodiments. The network (or one or more portions of the network) may be configured for only power delivery or for power and communications. The network may comprise any number or type of network communications devices that facilitate passage of data over the network (e.g.,

routers, switches, gateways, controllers), network elements that operate as endpoints or hosts (e.g., servers, virtual machines, clients), and any number of network sites or domains in communication with any number of networks. Thus, network nodes may be used in any suitable network topology, which may include any number of servers, virtual machines, switches, routers, or other nodes interconnected to form a large and complex network, which may include cloud or fog computing. Nodes may be coupled to other nodes or networks through one or more interfaces employing any suitable connection, which provides a viable pathway for electronic communications along with power.

(93) FIG. 2 illustrates an example of a network device **20** (e.g., central hub (PSE) **10**, switch (PD) **14**, access point (PD) **15** in FIG. 1) that may be used to implement the embodiments described herein. In one embodiment, the network device **20** is a programmable machine that may be implemented in hardware, software, or any combination thereof. The network device **20** includes one or more processor **22**, sensors **23** (e.g., power sensor (e.g., voltage, current sensor), communications sensor, thermal sensor), memory **24**, interface **26**, optical module **28** (e.g., power+optics interface module **16** in FIG. 1), and power module/controller **29**. The network device may also comprise one or more cooling components **21** (sensors, control valves, pumps, etc.) if the system is configured for combined power, data, and cooling delivery.

(94) Memory **24** may be a volatile memory or non-volatile storage, which stores various applications, operating systems, modules, and data for execution and use by the processor **22**. For example, components of the optical module **28** or controller **29** (e.g., code, logic, or firmware, etc.) may be stored in the memory **24**. The network device **20** may include any number of memory components.

(95) The network device **20** may include any number of processors **22** (e.g., single or multi-processor computing device or system), which may communicate with a forwarding engine or packet forwarder operable to process a packet or packet header. The processor **22** may receive instructions from a software application or module, which causes the processor to perform functions of one or more embodiments described herein. The processor **22** may also operate one or more components of the power control module **29** for fault detection, auto-negotiation, digital interlock, synchronization, multi-phase control, pulse power control, low voltage, high voltage control, modulator switch control, etc.

(96) The controller (power module/controller) **29** may be configured for auto-negotiation, fault detection, initialization, digital interlock, synchronization, multi-phase control, pulse power control, or other control or management functions. The control system **29** may comprise components (modules, code, software, logic) located at the central hub **10** and the remote device **14**, **15**, and interconnected through the combined power and data cable **18** (FIGS. 1 and 2). The control system **29** may also receive input from power sensors or data monitoring devices, as described below with respect to FIG. 3. The power module/controller **29** at the PD may communicate with the control system at the PSE **10** to initialize operation, synchronize operation (e.g., pulse waveforms, current, voltage), auto-negotiate the status of the power system, identify any faults in the power system (e.g., cables or powered device), select a power operating mode, or any combination thereof. As previously noted, the auto-negotiation may be performed during a low voltage startup or between pulses in a pulse power system. One or more control system or power module components may be located at the optical module **28**.

(97) Logic may be encoded in one or more tangible media for execution by the processor **22**. For example, the processor **22** may execute codes stored in a computer-readable medium such as memory **24**. The computer-readable medium may be, for example, electronic (e.g., RAM (random access memory), ROM (read-only memory), EPROM (Erasable programmable read-only memory)), magnetic, optical (e.g., CD, DVD), electromagnetic, semiconductor technology, or any other suitable medium. In one example, the computer-readable medium comprises a non-transitory computer-readable medium. Logic may be used to perform one or more functions described below

with respect to the flowcharts of FIGS. 4, 5, and 7

(98) The interface **26** may comprise any number of network interfaces (line cards, ports, connectors) for receiving data or power, or transmitting data or power to other devices. The network interface may be configured to transmit or receive data using a variety of different communications protocols and may include mechanical, electrical, and signaling circuitry for communicating data over physical links coupled to the network interfaces. For example, line cards may include port processors and port processor controllers. The interface **26** may comprise one or more optical and electrical interfaces. The interface **26** may also comprise fluid ports if the system is configured for cooling. One or more of the interfaces **26** may be configured for PoE+F+C (Power over Ethernet+Fiber+Cooling), PoE+F, POE, PoF, high voltage pulse power, multi-phase pulse power, or similar operation.

(99) The optical module **28** may include logic, firmware, software, etc. for use in monitoring or controlling the extended safe power system. For example, the optical module **28** may comprise hardware or software for use in power detection, system start-up, synchronization, power monitor and control, or power enable/disable. The optical module **28** may further comprise one or more of the processor or memory components, or interface **26** for receiving or delivering power and data. As previously described, in one or more embodiments, power is supplied to the optical module by power supply **27** and the optical module **28** provides power to the rest of the components at the network device **20**.

(100) It is to be understood that the network device **20** shown in FIG. 2 and described above is only an example and that different configurations of network devices may be used. For example, the network device **20** may further include any suitable combination of hardware, software, algorithms, processors, devices, components, or elements operable to facilitate the capabilities described herein.

(101) FIG. 3 is a block diagram illustrating components for use in power monitor and control, start-up, synchronization, auto-negotiation, and fault protection at a network device **30**, in accordance with one embodiment. One or more of the components shown in FIG. 3 may be located at the interface module **16** or in communication with one or more components of the interface module (FIGS. 1 and 3). The cable **18** carrying both the high power and data is shown with cable connector **36** coupled to the interface module in FIG. 3. The power is received at an electrical interface **37a** and the data is received and transmitted at an optical interface **37b**, which may both be located at the optical module **16**. Connector **36** may comprise a single physical component or a single component with modular parts for each function, for example.

(102) The network device **30** includes optical/electrical components **31** for receiving optical data and converting it to electrical signals (or converting electrical signals to optical data) and power components including, power detection modules **32a**, **32b**, power monitor and control modules **33**, and power enable/disable modules **34**. Although PoE and pulse power are described in conjunction with detection elements **32a**, **32b**, it should be understood that other power delivery schemes including AC, DC, and USB may be supported with similar elements. Also, the type of power may be split between high voltage power and low voltage power. The power components may be isolated from the optical components **31** via an isolation component (e.g., isolation material or element), which electromagnetically isolates the power circuit from the optical components to prevent interference with operation of the optics. The network device **30** may include an auto detection module **35** that operates with the pulse power detection module **32a** and PoE detection module **32b**. Module **35** may also operate to select a power delivery mode (e.g., PoE or pulse power) based on which delivery mode is more efficient based on network device operations. One or more functions of the detection elements **32a**, **32b**, auto detection module **35**, power monitor and control modules **33**, or auto-negotiation module **39** may be combined into a power module and operate within the interface module.

(103) The auto-negotiate/digital interlock module **39** may be used in performing one or more fault

detection, auto-negotiation, or digital interlock processes. As described in detail below, auto-negotiation may include communication between the PSE and the PD and interaction between controllers at the central network device and remote network device. A gate control/modulator **40** may be provided to isolate one or more circuits during system initialization or testing and modulate the pulse power, as described below with respect to FIGS. **10A-13B**. The network device **30** may further include a bootstrap/housekeeping circuit **38** used during start-up and testing of the device, as described below. One or more control signals or monitoring information may be transmitted over the data line (e.g., optical fibers) or over the power line in the hybrid power and data cable **18** to provide an operating status (e.g., fault/no fault) of the network device, cable, or power circuit.

(104) In the example shown in FIG. **3**, each module **32a**, **32b** is in communication with its own power monitor and control module **33** and power enable/disable module **34**. The circuit detects the type of power applied to the network device **30**, determines if PoE or pulse power is a more efficient power delivery method, and then uses the selected power delivery mode. In one or more embodiments, PoE or high voltage pulse power may be transmitted over the same cable **18**.

(105) The network device **30** is configured to calculate available power and prevent the cabling system from being energized when it should not be powered. The power monitor and control modules **33** continuously monitor power delivery to ensure that the system can support the needed power delivery and no safety limits (e.g., voltage, current) are exceeded. The power monitor and control modules **33** may also monitor optical signaling and disable power if there is a lack of optical transitions or communication with the power source. Power monitor and control functions may sense the voltage and current flow, and report these readings to a central control function. In one embodiment, the network device **30** uses a small amount of low voltage power (e.g., $\leq 12V$, $\leq 24V$, $\leq 60V$) at startup or restart to communicate its power and data requirements and status. The network device **30** may then be configured for full power operation (e.g., $> 60V$, $\geq 300V$, $\geq 500V$, $\geq 1000V$) (e.g., at high power enable/disable module **34**) if no faults or safety conditions are detected. If a fault is detected, full power operation may not be established until the network device communicates in low power mode that high power can be safely applied. The auto-negotiation module **39** communicates with a control system at the central network device to select a safe operating mode (e.g., determine that it is safe to apply high voltage power), identify a fault in the circuit (e.g., line-to-line or line-to-ground fault detection), and shutdown power if a fault is identified at start-up or during testing between high voltage pulse power during normal operation. As described below, power may be delivered with or without communications.

(106) It is to be understood that the system shown in FIG. **3** is only an example and components may be added, removed, combined, or rearranged without departing from the scope of the embodiments. For example, as previously noted, network devices may also be configured without an optical interface **37b** and optical components **31**.

(107) As described below, an initialization process may be performed with low voltage (FIG. **4**) or high voltage (FIG. **5**). The high voltage initialization process may be used, for example, for adding a new PD or a hot-swap PD replacement or to simplify the power initialization process, while providing another layer of high voltage safety in place of low voltage safety initialization. FIG. **7** illustrates a cable capacitance and shock fault test that may be performed upon start-up or at any other time to check if additional cable lengths have been added. Simplified block diagrams and circuits are shown for cable capacitance and shock fault test (FIGS. **9A** and **9C**), synchronization after initial power up (FIG. **10A**), initial low voltage start-up (FIGS. **11A**, **11C**, **12A**, **12B**, and **12C**), and initial high voltage start-up (FIG. **13A**), in accordance with one or more embodiments. It is to be understood that the processes and circuits shown in FIGS. **4-14** and described herein are illustrated for one phase, for simplification, and that these processes and circuits may be duplicated for each phase of a multi-phase system as described below with respect to FIGS. **20-22**.

(108) As described in detail below, PD initialization may include power-up for initial PD housekeeping voltage with a PD modulator switch Off for power to transceiver, PD modulator gate,

and microcontroller/DSP. PD housekeeping voltage may be developed during the PSE modulator On-time by synchronizing a power converter load operation with a cable voltage waveform. As previously noted, the initialization may comprise a low voltage or high voltage initialization. In one low voltage initialization example, a low voltage (e.g., 24 VDC) may be applied before switching to high voltage (e.g., 380 VDC). This may include a long initial On-time period to power up a DC housekeeping capacitor fully for faster start-up time before only drawing power during high voltage pulsing. For high voltage initialization, a short-time high voltage pulse may be used for added high voltage protection during initialization. In another high voltage initialization example, a nominal-time (normal operating pulse width) operation high voltage pulse and duty/frequency may be used as needed for a safety test, including a cable capacitance test. This high voltage initialization process may be used, for example, for PD hot-swap replacement or addition of a new PD to cable with high voltage pulsing (high voltage pulse power on cable).

(109) In one or more embodiments, low voltage initialization at the PSE comprises transmitting low voltage pulse power from the PSE to the PD, performing a safety test (e.g., safety body shock protection test, cable capacitance test), and enabling high voltage pulse power operation at the power sourcing equipment upon passing the safety test. During the low voltage initialization, the PD synchronizes with a waveform of the low voltage pulse power. For example, a modulator switch at the PD may synchronize with a modulator switch at the PSE. The term “modulator switch” as used herein may refer to one or more modulator switches (e.g., one or more switches with common control), power modulator, pulse modulator, pulse power modulator, control switch, gate control, isolation switch, or similar component or group of components operable to perform the functions described herein. The synchronization may continue during high voltage pulse power operation.

(110) In one or more embodiments, low voltage initialization at the PD comprises receiving low voltage pulse power at the PD from the PSE, synchronizing the powered device with a waveform of the low voltage pulse power received from the power sourcing equipment, and operating the PD with high voltage pulse power received from the power sourcing equipment. During initialization at the PD, a modulator switch may be open while energizing a housekeeping circuit at the PD. The modulator switch may then be turned on while the capacitance and safety test are performed by the PSE.

(111) It is to be understood that the term “synchronize” as used herein refers to coordination of the pulses at the PSE and PD through coordination of the PSE and PD modulator switch drives or of one of the modulator switches with a voltage waveform, for example. Synchronization is used to align the pulses (modulator switches) at the PSE and PD, and may result in differences between pulse width (modulator switching) at the PSE and PD. For example, as described below with respect to FIGS. 23 and 24, the synchronization may provide a smaller pulse width at the PD than the pulse width at the PSE. As described below, Off/On synchronization between the PSE and PD may be performed during initialization and updated based on PSE safety testing or changes in the network (e.g., changes in cable, addition of new network device), for example.

(112) FIG. 4 illustrates an overview of a low voltage initialization process, in accordance with one embodiment. At step 41, the PSE (e.g., PSE 10 in FIG. 1) turns on. In one example, the PSU 11 provides 24 VDC through a diode to a PSE modulator switch input (as shown in FIG. 11A). The low voltage is provided to the PSE modulator switch input and the modulator switch begins switching at a start-up duty cycle, thereby transmitting low voltage pulse power (low voltage pulses) to the PD (step 42). In one example the duty cycle comprises 8 ms (milliseconds) on, 4 ms off over a 12 ms period (66.7% duty cycle). The PD starts up at step 43. As described below with respect to FIG. 11A, the PD may use a 12/3.3V housekeeping and floating gate voltage. The PD modulator switch synchronizes with the PSE modulator switch based on the PSE voltage waveform received at the PD (step 45). This allows the PD and PSE to agree on modulator switch timing before high voltage pulse power is enabled. A PD transceiver and DSP (Digital Signal Processor)

(shown in FIG. 8 (85b, 86b)) (or MCU (microcontroller)) begin operation and the PD starts PLL (Phase Lock Loop) or DLL (Digital Locked Loop, Delay Locked Loop) and synchronizes the PD modulator switch on/off with the PSE voltage waveform. Synchronization details are described below with respect to FIGS. 10A, and 10B. In one example, the PD and PSE begin to communicate (step 44) when the PD modulator switch is turned on until turn-off/on with modulation (after step 43 and before PD starts PLL and synchronizes modulator at step 45). In another example, the PD and PSE transceivers start communication (step 44) during On-time of PD/PSE modulators (after PD starts PLL and synchronizes modulator at step 45). It is to be understood that reference to the modulator switch being on refers to a closed switch (current transmitted through the switch) and reference to the modulator switch being off refers to an open switch (no current transmitted through the switch).

(113) The PD and PSE may optionally auto-negotiate modulator switch timing (synchronize modulator switches) (step 46) if communications are available. The PSE performs a capacitance test (step 47a) and a safety test (step 47b). It is to be understood that the capacitance test (step 47a) and safety test (step 47b) may be collectively referred to as a “safety test”. Results of the capacitance test may be used to adjust the modulator pulse timing of the PSE and PD for the safety test calibration and timing. For example, results of the capacitance test may be used to identify a minimum Off-time and high voltage exposure time, adjust high voltage exposure time, and set safety fault sense level as described below with respect to FIG. 7. The PSE may also gather transmission line parameters (e.g., capacitance) during this test. In one example, the PSE performs a cable leakage test to see if the cable leakage is greater than a specified resistance value (e.g., 100 kohm). Static timing parameters may be used if communications are not available. Additional details of a cable capacitance and shock fault test are described below with respect to the flowchart of FIG. 7 and circuits of FIGS. 9A and 9C. If the PSE safety test does not pass, an auto-restart may be tried for a set number of times (e.g., two times) (steps 42-47b). If the safety test is passed, the PSE enables high voltage operation (step 48) (e.g., ≥ 300 VDC). A PD input voltage above low voltage start-up no-load level (e.g., ~ 360 VDC) turns on DC/DC load. The PSE and PD may then agree on voltage and load current synchronization and high voltage pulse power operation continues with the PSE transmitting high voltage pulse power to the PD (step 49). Additional synchronization details are described below with respect to circuits shown in FIG. 10A.

(114) FIG. 5 is an overview of a high voltage initialization process, in accordance with one embodiment. As previously noted, high voltage initialization may be used, for example, while adding a new PD or a hot-swap (hot plug-in) PD replacement without using the low voltage initialization procedure described above. High voltage initialization may also be used to simplify the power initialization start-up process and reduce cost and complexity, while providing another layer of high voltage safety in place of low voltage initialization. In one or more embodiments, auxiliary power may be provided to the PSE during the initialization phase (LV or HV) to establish the PSE modulator switch control and synchronization, and communication, which need the switch to be on. As described below, the cable capacitance and shock fault test may be followed by a sequence to establish modulator switch operation and communication (if used), then syncing of the modulator switches for high power high voltage pulse widths.

(115) In one or more embodiments, the powered device receives high voltage pulse power from the power sourcing equipment with a modulator switch at the powered device open, couples isolated housekeeping voltage at the powered device when a pulse of the high voltage pulse power is on, energizes a housekeeping circuit at the powered device, and turns on a modulator switch at the powered device after a specified number of high voltage pulses are received to power the powered device with the high voltage pulse power.

(116) Referring now to FIG. 5, initial PD housekeeping voltage and first PD modulator switch operation to establish a communication link during high voltage on-pulse to the PD load is described. At step 50, the PSE transmits high voltage pulse power to the PD with the PD modulator

switch open. In one or more embodiments, an initial PSE high voltage modulator may provide a short on-pulse (i.e., shorter pulse than used during normal operation) within a safer part of a safe region (described below with respect to FIG. 6) for an added level of safety with no PD housekeeping voltage and the PD modulator switch open. For example, high voltage power received at the PD with the modulator switch open may comprise a short pulse On-time (pulse width) and once the modulator switch is turned on, the high voltage pulse power received comprises normal operation pulse On-time (nominal width pulse). Isolated housekeeping voltage is coupled to PD side without affecting cable voltage charge when high voltage pulse is on during auto-negotiation (step 51). The PSE may wait for a number of high voltage pulses to auto turn on the PD modulator switch (step 52). The PSE checks to see if the PD modulator switch is turned on (step 53). In one example, the PSE waits for three high voltage pulses over approximately 40 ms to auto-turn on the PD modulator switch until it is told to turn off at the end of the high voltage On pulse load period through the communication link. If the PD modulator switch turns on, normal operation continues (step 54). Otherwise, power shuts down until restart is attempted (step 55). (117) FIG. 6 is a graph 60 illustrating duration of current flow (ms) versus body current (mA). The graph shows a safe region, in which there is normally no perception by humans or little pain with no dangerous effect. In the danger region there may be reversible effects such as muscular contraction and respiratory compromise or critical effects on humans. As shown in the graph 60, pulsing limits and maximum exposure time for high voltage initialization are maintained within the safe region. In one or more embodiments, during a high voltage initialization start-up period where there is no need for any PD load requirements, a shorter high voltage pulse is possible without affecting the load power requirement. With a shorter high voltage On-time and shorter Off-time detection time of high voltage exposure period and less shock energy shown in the examples, an added higher level of shock protection is possible.

(118) As previously described with respect to FIG. 4, one or more safety tests may be performed before enabling high voltage pulse power operation at the PSE. Testing may include a safety body shock protection test with cable capacitance testing, and calibration adjustment based on the testing. In one example, PSE safety/capacitance testing and analysis may be used to determine a shortest high voltage exposure within a duty/period between pulses for auto-negotiation of the next high voltage pulse, with accurate capacitance test and accurate cable voltage droop threshold for safety body current from calibration analysis of cable voltage droop with switching in a known discharge resistor for a specified time with first 10% (or other suitable percentage) of RC-time in near-linear dv/dt region, as described below. One or two known resistors may be switched in for a known time for faster, accurate calculation of cable capacitance. The capacitance test described below may be performed for safety test level and time only on initialization or on a pulse-to-pulse basis, which adds the ability to identify cable capacitance changes on the fly and provides large cable voltage dv/dt droop levels for easier synchronization and timing analysis.

(119) FIG. 7 is an overview of a process for a capacitance test of cable interposed between the PSE and PD. At step 70, a known high voltage pulse is transmitted from the PSE modulator switch on an open and unloaded cable. In one or more embodiments, the cable capacitance voltage is modulated with a known discharge resistor load (e.g., 100 kohm or other suitable resistance) and RC time (time constant of resistor/capacitance circuit) to discharge to measure the time of the voltage discharge with the first 10% of droop (step 71). This is approximately a linear relationship of $\Delta t = RC$ for the first 0.1RC time interval, as described below with respect to FIG. 9B. A maximum resistance value of 100Kohm is chosen in this example as maximum body resistance to be used as a fault for body shock protection of 3.8 mA maximum body current protection at a 380 VDC high voltage level. A 10% droop voltage level is also chosen in this example for a clean sensing level without noise after a high voltage pulse and load current turn-Off. With a long cable of high capacitance, the sensing time is longest to provide a longer Off-time for sensing and a longer high voltage On-time for power within a given duty cycle. In this example, the maximum

cable length may have 300 nF of capacitance, thus with 100Kohm test resistor the time to 10% RC time is 3 ms, and 4 ms may be used as a maximum Off-time and for sensing margin with an 8 ms high voltage On-time with a 67% duty cycle. Then at worst case the high voltage exposure time in this example is 11-12 ms to detect a body fault to latch-Off high voltage power or another high voltage pulse. For lower body resistance conditions the current may be higher and the maximum exposure time may be the same. For this reason a shorter Off-time is chosen for 10% droop with less capacitance and cable length for shorter Off-time and total exposure period. Other methods may be used to accurately and reliably measure a shallower droop voltage than 10% (e.g., 1-2%) for much shorter Off-time and total exposure period. This value is compared to dv/dt without the 100 kohm load to determine the additional resistance across the cable and identify if there is a fault (step 72). In one example, greater than 100 kohm passes the test and less than 100 kohm signifies a fault.

(120) If a fault is identified, fault mode is entered until reset (step 74). If the test passes, the cable capacitance is calculated and the 100 kohm load voltage threshold is set to the fault dv/dt to inhibit additional fault during auto-negotiation high voltage pulse Off-time (step 75). A maximum high voltage pulse Off-time is determined for the 100 kohm fault dv/dt voltage threshold (step 76). This value preferably includes a margin (e.g., fault threshold of $dv/dt=10\%$ plus another 5% margin). A desired duty cycle is determined for On-time for desired power, cable loss, and RMS (Root Mean Square) current (step 77).

(121) The above described process may be performed only at initialization (low voltage or high voltage start-up) or may be repeated at fixed intervals or pulse-to-pulse to identify if additional cable lengths have been added. The cable capacitance and shock fault test may be performed for each phase in a multi-phase system described below. It is to be understood that the resistance values, margins, and discharge times described above are only examples and other values may be used without departing from the scope of the embodiments. Additional details of the capacitance test are described below with respect to FIGS. 9A-9D.

(122) It is to be understood that the processes shown in FIGS. 4, 5, and 7 are only examples and one or more steps may be added, removed, combined, or reordered, without departing from the scope of the embodiments.

(123) Referring now to FIG. 8, a simplified block diagram of the extended safe power system is shown. The block diagram includes circuits for power sourcing equipment **81** providing a power source and smart control and a powered device **82** comprising a PON (Passive Optical Network) endpoint. The components shown within block **83** represent a single phase and may be duplicated for each phase of a multi-phase system as described below. Modulator switches **84b**, **84c**, **84d**, sensing components **89a**, **89b**, and start up power circuit **87b** may be duplicated for each cable pair/phase.

(124) The PSE **81** includes an isolated high voltage source (e.g., 380 VDC) and a modulator switch **84a** with gate. The DSP (Digital Signal Processor) **85a**, **85b** may comprise a microcontroller or FPGA (Field Programmable Gate Array) digital control and software/firmware. Tx/Rx **86a**, **86b** at the PSE and PD represent transceivers with a coupling network. An isolated power supply **87a** is provided for PSE housekeeping. An isolated power supply **87b** is provided for PD housekeeping with 24 VDC input example for low voltage initialization and testing. The PD **82** also includes a DC/DC isolated converter **87c** for generating 12V/3.3V housekeeping voltage with 60-380 VDC input from the output of the PD (high voltage pulse power operation) example. In this example, current sense transformer/Hall-effect sensors (CS/CT) **88a**, **88b** are included at the PSE and PD. A safety sensing circuit (Vsense safety) **89a** and PD sync voltage sensor (Vsense sync) **89b** are located in the PSE and PD, respectively. As shown in FIG. 8, the PSE includes two PSE modulator switches **84b**, **84c**, and the PD includes one PD modulator switch **84d** shown as bidirectional switches to totally isolate the cable pair during high voltage pulse Off-time for accurate voltage droop sensing proportional to RC time of a body resistance across the cable during the auto-

negotiation safety test between high voltage pulses. The switches may comprise, for example, a solid state switch or any other suitable device to provide pulse power modulation, which is synchronized between the PSE and PD, as previously described.

(125) Additional details of operation of portions of the circuit shown in FIG. 8 are described below for cable capacitance testing (FIGS. 9A and 9C), synchronization (FIG. 10A), low voltage initialization (FIGS. 11A and 11C), low voltage housekeeping (FIGS. 12A, 12B, and 12C), and high voltage initialization (FIG. 13A).

(126) FIG. 9A is a simplified representation of a circuit 90 for use in cable capacitance and shock fault testing (described above with respect to the flowchart of FIG. 7). In this example, the PSE includes resistors R1a, R1b, R2a, R2b, and R3. R3 is a known calibration resistor switched across the cable for known time for accurate calculation of the cable resistance and capacitance from the dv/dt voltage droop. The PD includes capacitor Cf, inductors LF1 and LF2, and diode D. Switches S1a, S1b (PSE modulator switch) and switch S2 (test switch) are located at the PSE. The PD includes switch S3 (PD modulator switch). Capacitance C.sub.cable represents cable capacitance, inductance L.sub.cable represents cable inductance, and resistance R.sub.cable represents cable resistance. It is to be understood that the simplified circuit shown in FIG. 9A is only an example and components may be added, removed, or rearranged without departing from the scope of the embodiments. For example, resistors R1a and R1b may be located to the right (as viewed in FIG. 9A) of the switches S1a and S1b.

(127) FIG. 9B illustrates timing waveforms with one pulse at the PSE test switch S2 for cable current i.sub.c(t) and voltage v.sub.c(t), and current at the PSE test switch S2 i.sub.s2(t) and PD switch S3 i.sub.s3(t) over time with changes in state of the PSE switch S1 (S1a and S1b in FIG. 9A, shown as S.sub.1 in FIG. 9B), test switch S2 (S.sub.2 in FIG. 9B) and PD switch S3 (S3 in FIG. 9B) in the circuit shown in FIG. 9A, in accordance with a first embodiment. The waveform diagram also shows V.sub.in and I.sub.c_peak. As previously described, a known resistor R3 is switched in to determine cable capacitance. After the PSE modulator switch S1 opens, the voltage at the cable begins to drop as represented by dv.sub.c/dt.sub.(a-b), which represents cable droop from leakage for fault body resistance (R.sub.unknown). The voltage continues to drop as switch S2 is closed as shown by dv.sub.c/dt.sub.(b-c), which represents cable droop from R3 plus cable leakage or body resistance (R.sub.unknown). Switch S2 is then opened and the change in cable voltage represents cable droop from leakage or fault body resistance (R.sub.unknown).

(128) A smart digital system may be used to increase the accuracy and reliability and minimize the Off-time. As previously described with respect to FIG. 7, the PSE modulator may switch On to transmit a pulse on an open/unloaded cable and cable capacitance voltage may be modulated with a known test resistor of maximum body resistance for safety shock protection. The cable resistance and capacitance may then be tested within 10% RC time constant, which is approximately a linear relationship of $dv/V_{sub.0} \approx dt/T \approx dt/RC$ for the first 0.1RC time where the discharge voltage dv.sub.c from initial voltage V.sub.0 and actual time constant T is from $e^{sup.}(-t/RC)$. The dv/dt with unknown leakage resistance may then be compared with the dv/dt with known test resistance added.

(129) FIGS. 9C and 9D illustrate another example for use in performing initial cable safety and capacitance testing. FIG. 9C is a block diagram of a circuit, generally indicated at 91. The PSE includes modulator switches S1a, S1b (collectively referred to as S.sub.1 in FIG. 9D), and test switches S2 (S2 in FIG. 9D) and S4 (S4 in FIG. 9D) in parallel. The PD includes switch S3 (S3 in FIG. 9D). Similar to described above with respect to FIG. 9C, FIG. 9D shows timing waveform diagrams for cable current i.sub.c(t) and voltage v.sub.c(t), and current at the PD switch S3 i.sub.s3(t) over time with changes in state of the PSE switch S1, test switches S2 and S4, and PD switch S3 in the circuit shown in FIG. 9B. Also shown is the current at the test switches i.sub.s2(t) and i.sub.s2(t)+i.sub.s4(t). In this example, two known switch resistances (R2, R4) provide another calibrated method with larger dv/dt voltage steps for signal-to-noise measurement for faster and

more accurate measurements, allowing for less Off-time duty cycle and high voltage period of shock exposure for a higher level of safety. With two known resistances steps, dv/dt differences may be used to calculate the unknown resistance and the cable capacitance from pulse-to-pulse. The S2 and S4 gate may operate together initially than later for a faster initial dv/dt slope for faster detection of the high voltage Off-time event.

(130) It is to be understood that the circuits shown in FIGS. 9A and 9C, waveform diagrams shown in FIGS. 9B and 9D, and test calculations described above are only examples and other circuits (e.g., combination of switches, resistors, etc.) may be used to test the safety and capacitance of the cable.

(131) As previously discussed with respect to steps 45 and 46 of FIG. 4, the PD performs synchronization with the PSE using cable voltage waveform initialization. This process may start with the PD modulator switch turning on for communications to control Off/On synchronization. The PD may then develop a PLL (or DLL) control of the PD modulator switch to control Off/On synchronization. The PD may initially turn on the PD modulator switch for a default period within the PSE modulator default On-time. The modulator switch timing may be modified in accordance with changes made based on PSE safety/capacitance testing and analysis. In one or more embodiments, synchronization may include a time delay PD modulator switch-On loading after PSE modulator high voltage switch-On, and PD modulator switch-Off unloading before PSE modulator high voltage switch-Off, as described below with respect to FIGS. 23 and 24, to minimize cable voltage ringing on cable voltage droop safety testing during high voltage Off-period.

(132) FIG. 10A illustrates a simplified synchronization control circuit 100 for use after initial power up. High voltage control is provided at gate control 101 and high voltage switch 102. PSE modulator switches (switch 1 and switch 2) 103 are coupled to PSE gate control 104. As previously described with respect to FIG. 8, the PD includes PD modulator switch 109 coupled to PD gate control 107 and Vsense sync 106. The PD endpoint load is shown at 108. As previously described with respect to the flowchart of FIG. 4, control of the PD modulator may be performed with pulse-pulse off/on command communications after initial power up (steps 44.fwdarw.45), or PD modulator control may be performed with PLL synchronization without communication (steps 45.fwdarw.44), or PD modulator control may be performed with default timing know between the PDE and the PD without communication (steps 45.fwdarw.44). Three different examples of synchronization methods are described below for the circuit shown in FIG. 10A.

(133) FIG. 10B shows Vccable with switch transitions (PSE Gate (switch 103), PD Gate (switch 109)) and PLL Sync (at Vsense Sync 106). Voltage Vccable is measured at the cable, as shown in FIG. 10A. PLL (or DLL) sync shows the current at the Vsense sync circuit 106.

(134) In a first example, PD modulator control is provided with pulse-pulse off/on command communications after initial power up. The PSE modulator control 104 turns on with low voltage (e.g., 24V) without pulsing. The PD modulator control 107 turns on until it is told to turn off with no load other than housekeeping power. A communications link is then established between the PSE and PD. The PSE modulator 103 starts pulsing at an established On-time and Off-time duty cycle and frequency. The PSE sends a command at the end of a data stream period of modulator On-time to turn off PD modulator for Xms and then turn back on. The Off-time command may be sent earlier in the data stream and changed pulse-to-pulse, then the last word sent may be a turn-off-now command at a specified time (knowing that there will be some turn off delay).

(135) A second synchronization method provides PD modulator control and PLL synchronization without communication. The Vsense sync circuit 106 senses the cable capacitance (C.sub.cable) voltage waveform droop (Vccable) when PSE gate switch 102 is off due to cable resistance (i.e., mid-point ground resistance and sensing circuits). The Vsense circuit 106 develops pulses from Vccable positive transition after droop with PSE gate switches on (FIG. 10B). The Vsense pulses are input to PLL to develop Voltage Controlled Oscillator (VCO) sync pulses. PLL VCO pulses

develop pulse shaping for PD gate modulator control, which are synchronized as desired with the PSE gate switch control **104**. Voltage waveform droop (VCcable) with the PSE gate switch off is shown in FIG. **10B**. As previously described, VCcable has a positive transition after droop when the PSE gate **104** switches on.

(136) A third synchronization method provides a pre-established default On-time between the PSE and the PD modulators. One or more embodiments utilize a one-shot monostable multi-vibrator (MV) default pulse width and default delay time to synchronize with the PSE default modulator On-time triggered from the cable capacitor voltage waveform fast-rising dv/dt at the start of the PSE Modulator pulse On-time. The circuit may include, for example a differentiator circuit, bias average trigger threshold circuit, and op-amp. The circuit may further include an adjustable delay-On **105a** (e.g., 100 μ s default) and an adjustable one-shot multi-vibrator **105b** (e.g., 7.8 ns default). In this example, PD modulator control is provided with pulse-pulse default On-time until updated On-time command for next pulse during communication. The PSE modulator first pulses a default On-time duty cycle (e.g., 8 ms) and period (e.g., 12 ms) to cable phase/pair with voltage waveform droop (VCcable) to the PD Vsense sync circuit **106**. The Vsense sync circuit **106** triggers on the VCcable positive transition with a delayed pulse width desired for the PD modulator switch control with a default On-time duty cycle. During the On-time duty cycle, data communications may update or modify the sync delay time, pulse width, and period, as needed to sync with the PD modulator On-time duty cycle for each next pulse period. The above steps may then be repeated. This provides pulse-pulse change for on-the-fly synchronization changes in On/Off time, duty cycle, and frequency from the PSE and keeps the PD in sync for each phase/pair. This sequence also ensures the PSE modulator voltage is On-first before the PD modulator switches-On and then Off-first before the PSE modulator voltage switches-Off for noise transient mitigation.

(137) FIG. **11A** is a block diagram illustrating a simplified PD initial low voltage start-up circuit **110**. As described above with respect to the flowchart of FIG. **4**, the low voltage (e.g., 24V) start-up sequence for PD housekeeping power may be performed before PD modulator control or communications. As previously described with respect to FIG. **10A**, high voltage control is provided at gate control **111** and high voltage switch **112**. PSE modulator switches (switch **1** and switch **2**) **113** are coupled to PSE gate control **114**. The PD includes PD modulator switches **113** coupled to PD gate control **117** and Vsense sync **116**. The PD endpoint load is shown at **118**. The circuit shown in FIG. **11A** includes a DC/DC housekeeping circuit **120** (e.g., 24V to 12/3.3V transformer) (also referred to as local energy storage). The PSE modulator switch **119** may provide low voltage (e.g., 24V) On-time for a fixed time (e.g., 100 ms) for initial start-up power to the cable and PD DC/DC housekeeping circuit **120**. The PD DC/DC housekeeping circuit **120** starts-up and operates for the fixed time of the PSE modulator switch **113**. The PSE modulator **113** then starts pulsing low voltage at an established On-time and Off-time duty cycle and frequency (as shown in PSE gate current in FIG. **11B**).

(138) The Vsense circuit **116** develops an enable pulse width from VCcable positive transition after the voltage droop from PSE gate switches on to operate the DC/DC housekeeping converter **120** for continued housekeeping power (FIGS. **11A** and **11B**). The 24V DC/DC converter provides housekeeping power to the PD circuits, starts PD modulator switch **119** and communication, and then enables 380 VDC high voltage modulator switching to the cable. An OVP (Over Voltage Protection) circuit disables the DC/DC converter above ~27 VDC when the high voltage turns on. The PD may include a 380V high voltage DC/DC converter (**87c** in FIG. **8**) for housekeeping, which takes over housekeeping power from the 24V DC/DC converter **120**.

(139) FIG. **11B** shows voltage waveform droop (VCcable) (measured at the cable start at PSE) with the PSE gate control **114** off (modulator switches **113** open). The PSE gate trace shows modulation of the PSE switch **113**. DC/DC power is measured at the DC/DC housekeeping circuit **120**. As previously described, VCcable has a positive transition after droop when the PSE gate **114** switches on. The Vsense circuit **116** develops an enable pulse width from VCcable positive transition after

the voltage droop when the PSE gate switches on to operate the DC/DC housekeeping converter **120** for continued housekeeping power.

(140) FIG. **11C** is a simplified circuit design for use in low voltage start-up. Two twisted pairs are shown with the PSE modulator switches **113** and PD modulator switch **119** shown for each pair. The enable switch **112** is closed for high voltage operation (e.g., 380 VDC, >300V, >200 VDC). In one example low voltage operation may be less than or equal to 56V (e.g., 24V). The PSE includes a low voltage cable capacitance and fault test circuit **115**. In one or more embodiments, the low voltage power-up circuit at the PD is configured with 0V shut-off above approximately 27V (with low voltage operation of 24V) to allow for hot-swap without an isolation circuit. An alternate start-up power may be provided with a battery at the PD for initial power-up. The PD includes the low voltage DC/DC converter **120** for each wire pair, as previously described. Details of the low voltage housekeeping circuit are described below with respect to FIGS. **12A** and **12B**.

(141) FIG. **12A** is a block diagram illustrating an example of a low voltage housekeeping power circuit **121**. The circuit **121** includes a gate bias and control circuit **122**, with input enable 1 (from **125**), enable 2 (from **126**), and disable from PD housekeeping (24/12V DC/DC converter **123**), and switch **124** (described above with respect to FIGS. **11A** and **11C**). As shown in FIGS. **11A** and **11C**, the housekeeping circuit receives power from the cable pair and provides power to the PD modulator switch **119**. The converter **123** provides housekeeping power to the PD circuits, starts the PD modulator switch and communication, and then enables high voltage modulator switching.

(142) FIG. **12B** illustrates a simplified low voltage start-up housekeeping power circuit **127**. The circuit provides low voltage DC/DC self-starting housekeeping power to the PD end of the cable pair with over voltage protection to shut off with high voltage MOSFET switch M1. In one example, resistors R1, R2, R3, R4, R5, and R6 may each comprise a 1 or 2Mohm (Megaohm) resistor. Diode D1 and switch Q1 may provide over voltage protection above 27V, for example. In one example, capacitor C1 is rated at 100 μ F.

(143) It may be noted that for long cable resistance voltage drop for 5 W, the start-up low voltage may be increased from 24V to 56 VDC. In one or more embodiments, the low voltage may be less than or equal to 56V and a difference between the high voltage power (at power on pulse at PSE) and low voltage power may be greater than 200V (e.g., ~324V, ~368V). It is to be understood that these voltage levels are only examples and other levels may be used. The low voltage is preferably rated to prevent any safety issues during low voltage start-up (e.g., initialization and synchronization) and the high voltage is preferably rated to provide sufficient power to power the powered device, while providing safety checks during off pulse intervals. As described below, the high voltage power level may be based on the number of phases in a multi-phase power system in which the pulses are offset from one another between phases.

(144) FIG. **12C** illustrates a block diagram of a circuit **128** corresponding to the circuit **127** shown in FIG. **12B**. In this example, the circuit includes a 28V gate enable, gate bias and DC/DC converter (e.g., 16V/5 W) for housekeeping power.

(145) FIGS. **13A-13B** illustrate high voltage start-up in accordance with one embodiment. As described above with respect to FIG. **5**, high voltage start-up may be used as a high voltage initialization start-up with short high voltage On-pulse for an added safety protection or with normal high voltage pulsing to hot-swap a PD without requiring a low voltage initialization process. The high voltage initialization provides safe operation through use of short on pulses (within safe region as described above with respect to FIG. **6**).

(146) Referring first to FIG. **13A**, a block diagram illustrating a simplified initial high voltage start up circuit **130** is shown, in accordance with one embodiment. High voltage control is provided at gate control **131** and high voltage switch **132**. PSE modulator switches (switch **1** and switch **2**) **133** are coupled to PSE gate control **134**. As previously described, the PD includes PD modulator switches **139** coupled to PD gate control **137**, and Vsense sync circuit **136**. The PD endpoint load is shown at **138**. The circuit **130** shown in FIG. **13A** includes a high voltage DC/DC housekeeping

circuit **140** (e.g., 380V to 12/3.3V DC/DC converter) in place of the low voltage housekeeping circuit **120** of FIG. **11A**. In one example, the high voltage is pulsed on for less than 8 ms during the PSE modulator switch high-voltage On-time to charge the output to a minimum output housekeeping voltage with hold-up time until the next high voltage phase, as described below.

(147) The PSE modulator switch **133** starts pulsing high voltage at an established On-time (e.g., 8 ms) and Off-time (e.g., 4 ms) duty cycle and frequency. The DC/DC initial startup circuit **140** at the PD is energized on the first high voltage On-time cycle for a fixed operating time (e.g., 6-8 ms). The Vsense circuit **136** develops an enable pulse width (e.g., 6 ms) from VCable positive transition after the voltage droop when PSE gate switches on to operate the DC/DC housekeeping converter **140** for continued housekeeping power (FIGS. **13A** and **13B**). The high voltage DC/DC converter **138** provides housekeeping power to the PD circuits, starts PD modulator and communication, then enables high voltage modulator switching to the cable.

(148) FIG. **13B** shows voltage waveform droop (VCable) (measured at the cable start at PSE) with the PSE gate control **134** off (modulator switches **133** open). The PSE gate trace shows modulation of the PSE switch **133**. DC/DC power is measured at the DC/DC housekeeping circuit **140**. As previously described, VCable has a positive transition after droop when the PSE gate **134** switches on. The Vsense circuit **136** develops an enable pulse width from VCable positive transition after the voltage droop when the PSE gate switches on to operate the DC/DC housekeeping converter **140** for continued housekeeping power.

(149) FIG. **14** is a block diagram of a system **140** showing simplified circuits for the PSE **141** and PD **142** with a crowbar/shorting relay **150** included at the PSE for safety. As previously described with respect to FIG. **8**, the components shown within block **143** represent a single phase and may be duplicated for each phase of a multi-phase system. The PSE **141** includes an isolated high voltage source (e.g., 380 VDC) and a switch **144a** and gate. Tx/Rx **146a**, **146b** at the PSE and PD represent transceivers with a coupling network. The DSP (Digital Signal Processor) **145a**, **145b** may be a microcontroller or FPGA (Field Programmable Gate Arrays) digital control and software/firmware. An isolated power supply **147a** is provided for PSE housekeeping. An isolated power supply **147b** is provided for PD housekeeping with 24 VDC input for low voltage initialization and testing. A PD DC/DC isolated converter **147c** is provided for Vout and for 12/3.3V housekeeping with 280-380 VDC input. Current sense transformer/Hall-effect sensors (CS/CT) **148a**, **148b** are located at the PSE and PD. A safety sensing circuit (Vsense safety) **149a** and PD sync voltage sensor (Vsense sync) **149b** are located in the PSE and PD, respectively. The PSE includes PSE modulator switches **144b**, **144c**, and the PD includes PD modulator switch **144d**, as previously described.

(150) In the example shown in FIG. **14**, a shorting switch (safety crowbar) **150** is installed in the PSE **141** for added high voltage safety. The shorting switch **150** may comprise, for example, a solid-state device (e.g., MOSFET), which is energized with a body shock fault to discharge cable voltage charge energy. A high voltage relay may also be used. The shorting switch **150** may be manually energized (e.g., at a button on PSE) as a high voltage lockout by maintenance personnel when installing or maintaining equipment. The shorting switch may be energized with a cable connector safety interlock when disconnected, for example.

(151) It is to be understood that the circuits and block diagrams shown in FIGS. **8**, **9A**, **9C**, **10A**, **11A**, **11C**, **12A**, **12B**, **12C**, **13A**, and **14** are only examples and that other arrangements or combinations of components (e.g., resistors, capacitors, diodes, inductors, switches, gates, isolated power supplies, transformers (converters), or sensing circuits), pulse timing, or voltage or power levels may be used without departing from the scope of the embodiments. For example, the low voltage pulse power may comprise pulses of power transmitted (i.e., pulse on) at or above 24V, at or below 56V and the high voltage pulse power may comprise pulses of power transmitted at or above 200V, at or above 380V or any other suitable levels. In one or more embodiments, the difference between the low and high voltage power is at least 170V.

(152) FIGS. **15-19** illustrate simplified examples of extended safe power (ESP) systems for delivering power on a copper pair with a data fiber pair. As previously noted and described below, the extended safe power may be delivered on a combined cable with one or more optical fibers for data delivery. FIG. **15** is a simplified block diagram showing a cable extending between a PSE and PD and carrying two twisted pairs and optical fibers. FIG. **16** is a block diagram illustrating additional functional components at the PSE and PD for a single twisted pair. FIG. **17** is a block diagram illustrating multi-point distribution of ESP to multiple low power PD endpoint loads. FIGS. **18** and **19** show simplified block diagrams illustrating examples of power and voltage levels at input and output of the PSE and PD.

(153) Referring now to FIG. **15**, a simplified example of a data and power delivery system comprising a PSE **150** in communication with a PD **152** providing power to a load **153**, over a combined power and data cable (e.g., Power over Fiber (PoF) cable) **154** is shown. In this example, the cable **154** includes two optical fibers **155** (e.g., 2-fiber single mode) and two twisted pairs **156** (e.g., copper wires). Control data shown at **157** may be delivered over the optical fibers **155** or copper wires (twisted pairs) **156**, or a separate transmission line. The control data may comprise, for example, isolation switch synchronization control data, modulator switch control data, bidirectional control data, or other PSE/PD synchronization data. Bidirectional communications data may also be transmitted over the optical fibers **155** or wires **156**. In one example, 10 MB communications are provided over a copper pair during high voltage on pulse (e.g., on high voltage data link). Input power (e.g., AC, HVAC, HVDC, line card 48-56 VDC) may be provided at the PSE **150**. The cable **154** may comprise any number of optical fibers and wires or wire pairs for delivering data and high voltage pulse power over different cable lengths.

(154) In one or more embodiments, PoE or high voltage power (e.g., ESP, pulse power, multi-phase pulse power) may be delivered over the same cable and connectors. Depending on a capability of the PSE **150** and PD **152**, the PD may operate in one or more different modes. If the PSE **150** and PD **152** are not compatible (i.e., one only configured for PoE and the other one only configured for ESP) the circuit will be not be powered. If both the PSE **150** and PD **152** are capable of ESP operation, the PSE will supply high voltage pulse power and the PD will operate using the high voltage pulse power. In another example, the PSE, PD, or both PD and PSE may select an operating mode based on the most efficient delivery mode (e.g., using auto-negotiation between PD and PSE).

(155) FIG. **16** illustrates additional details of one of the twisted pairs shown in FIG. **15**, in accordance with one embodiment. A PoF (Power over Fiber) cable extends between a PSE **160** and PD **162**. In this example, the PD **162** powers a 56 VDC load **169** (e.g., PoE, PON endpoint, access point, switch). In the simplified example shown in FIG. **16**, the cable includes two optical fibers and one twisted pair. As previously described, the cable may comprise any number of wire pairs (e.g., N twisted pairs). In this example, the system provides high resistance mid-point grounding for shock protection. In one example, mid-point grounding drops the line to ground voltage (e.g., 275V line-to-ground, 550V line-to-line; 190V line-to-ground, 380V line-to-line). In one or more embodiments, both feed and return of each transmission pair is switched to implement effective control and line-to-ground fault detection is between 10-100 μ s. As previously described, cable sensing may be provided at the PSE **160**. The system may provide line-to-ground (GFI (Ground Fault Interrupters)) shock protection and line-to-line shock protection for any cable fault condition during auto-negotiation with high-voltage pulse Off-time, as described above. One or more embodiments provide single point of failure and redundancy for any high-voltage path to cable. In one or more embodiments, the system may use 12-56 VDC low voltage for initial start-up conditions and default condition to establish data link and safety interlock before enabling high voltage operation, as previously described. In one example, 10 MB communications are provided over the twisted pair during high voltage on pulse as shown at transceiver **168**.

(156) FIG. **17** illustrates an example of ESP multi-point distribution to multiple low power

endpoint loads (e.g., 5G radio sets or other devices). A PSE source **170** delivers high power and data over a PoF cable assembly **174** comprising fibers and wires to a plurality of PDs **172**. In one or more embodiments, multi-phase pulse power is delivered at a voltage of at least 200V on the cable **174**. In one example, 1-2 kW of power is provided on copper pairs with data fiber pairs over 1-10 km with 550 VDC pulse power. As previously described, the pulse power may comprise any number of phases. As noted above, the system may use 24 VDC or 56 VDC low voltage for initial start-up conditions and default condition to establish data link and safety interlock before enabling high voltage operation. In the example shown in FIG. **17**, 550 VDC pulse power may be distributed to multiple low power PD PON endpoint loads such as 5G radio sets, for example. In one example, the system provides 1-2 kW power on copper pair with data fiber pair over 1-10 km with 380/550 VDC extended safe power with >70% efficiency. Transmittal of power from the PSE **170** to the plurality of downstream PDs **172** in a daisy chain topology (also referred to herein as a hybrid multi-/drop daisy chain topology) is described below with respect to FIGS. **29-40**.

(157) FIGS. **18** and **19** are block diagrams illustrating simplified systems with examples of power input and output at the different sections of the ESP system. FIG. **18** illustrates a PSE with two PSUs **180** receiving 115 VAC power at plugs **181**. The PSE includes low voltage/high voltage control, PSE modulator, digital control, safety sensing, and transmitters/receivers for communication as shown at block **182**. The PSE is coupled to the PD with a power cable **184** (e.g., 14AWG). In this example, output at the PSE comprises 380 VDC, 2000 W power. In this example the PD is a 1400 W PON (Passive Optical Network) end point comprising a PD modulator, digital control, and transceiver/receiver at block **186**. Input at the PDU in this example is 380-280 VDC and 1474 W and output at the PSU **188** is 50 VDC, 28 A, and 1400 W.

(158) FIG. **19** illustrates a PSE comprising two PSUs **190** and module **192** for low voltage/high voltage control, modulation, and communications as previously described. PD **196** (comprising PD modulator, digital control, transceiver/receiver) is coupled to an endpoint comprising a rack component **198** (e.g., fabric interconnect, blade server, etc.). Power is received at 115 VAC plug **191**. In this example, the PD **196** provides 192-400 VDC (1492 W) power to rack component **198**.

(159) It is to be understood that the power inputs and outputs shown in the simplified block diagrams of FIGS. **18** and **19** are only examples and other voltage and power levels may be used, without departing from the scope of the embodiments. Also, the cable may comprise any number of wires or optical fibers and the system may be configured for single point of failure tolerance for continuous operation with N+N or N+1 redundancy. In one or more embodiments fail safe from high voltage to low voltage operation may be provided.

(160) As previously described, the pulse power system may operate as a multiple phase (multi-phase) system. The initialization, synchronization, testing, and fault detection described herein may be performed on each phase of the multi-phase system. In one or more embodiments, the pulse power system may comprise a multi-phase pulse power system as described in U.S. patent application Ser. No. 16/380,954, referenced above. In one example, single conductor pair cable is replaced with 2-phase pulse power transmission system cable with two pairs of power lines, busbars, power planes, or cable wired pairs. For example, one or more embodiments may comprise a 2-phase pulse power transmission system cable with 3-wire, busbars, power planes, or a cable wire trio. Multi-phase (three or more phase) operation may further reduce RMS current per phase and effectively provide continuous DC voltage without bulky filter components. In one or more embodiments, high or effectively 100% duty cycle to the output and split ground (e.g., mid-point high-resistance ground) may provide higher efficiency with lower RMS current cable losses, allow fast and effective phase to ground fault detection, allow for higher voltage and power to the load from limited cable voltage rating, and implement common mode systems (separate ground connection) with lower peak currents for lower EMI/EMC noise radiated and susceptible fields.

(161) In one or more embodiments, the multiple phase approach allows for a significant Off-time in a 10 ms window, for example, to verify the cable for shorts, opens, unreported power loss (e.g., low

current short), or human or animal added resistance. This extended Off-time allows for a significant improvement in safety. The multi-phase pulse power also allows for a lower source voltage to be used to meet 100% of the powered device requirements. As previously noted, in a single phase system, the Off-time may need to be filtered out with bulky filters, and even then, power efficiency/effectivity is about 80% on high loads. Use of multiple phases at a higher duty cycle and higher efficiency provides a significant component advantage and may also provide increased power delivery and reliability. For example, the loss of a single phase in a three or more phase system does not impact the 100% continuous duty cycle power effectivity at the powered device. As described below, loss of a sourced phase front end circuit may not impact operation with redundant power sources.

(162) Referring now to FIG. 20, a multi-node multi-phase pulse power block diagram is shown, in accordance with one embodiment. The simplified example shown in FIG. 20 includes a PSE node 200 delivering power to three or more PDs (e.g., pulse power tap/receiver 212 and node endpoint 214). In this example the pulse power tap/receiver 212 is separate from the endpoint equipment 214, however, these nodes may be combined. Also, there may be more than one node 214 connected to one or more of the pulse power tap/receivers 212.

(163) The PSE network device 200 comprises an input power interface (e.g., three PSUs 205 receiving power cords 209 in the example shown in FIG. 1A) for receiving input power, a power control system 207 for receiving the input power and transmitting DC pulse power on multiple phases over a cable 211 to a plurality of the powered devices 212, 214 and verifying cable operation within Off-time of pulses in the DC pulse power, and a cable interface (e.g., power interface 208) for delivery of the multi-phase DC pulse power and data (e.g., control data, bidirectional communications, on copper wire or optical fiber) over the cable 211.

(164) The pulse power tap/receiver 212 comprises an input cable interface 213a for receiving the multiple phase DC pulse power and data from the PSE 200, an isolation switch (described below), and an interface 213b for transmitting power to the endpoint node 214. The interface 213b may be, for example, an interface connected to HVDC cable 222, pulse power cable, or a direct interface to the endpoint node. The tap/receiver 212 may supply power to one or more nodes 214 along a pulse power cable system. The tap/receivers 212 may be sized to support individual node power and may implement disconnect for fault isolation or node control based on data link communications. The multiple phase (multi-phase) DC pulse power comprises at least two phases to provide continuous DC voltage at the endpoint node 214. In one or more embodiments, the multi-phase pulse power comprises at least three phases to provide continuous power in case of loss of one phase. One or more of the pulse power tap/receivers 212 also comprises an output cable interface 213c for transmitting the multiple phase DC pulse power and data on the cable to a downstream tap node 212 in a taper topology (tap node configuration).

(165) In the example shown in FIG. 20, the PSE 200 comprises three PSUs 205 and a pulse power module 206 comprising the control system 207 and the power interface 208. As shown in FIG. 20, each PSU 205 may be in power communication with the pulse power module 206 over a high voltage rail, PM (Power Management) bus line, 56V line, or any combination thereof. In one example, each PSU 205 is configured for 1200 W power to provide redundancy and allow for the use of standard 15 A (amp) power cords/branch circuits. In one example, the PSE 200 is operable to deliver >1500 W total power to the nodes 214. In one example 190V line-to-ground (380V total) eliminates the need for intermediate power conversions.

(166) The pulse power module control system 207 may provide, for example, timing and sequencing, line detection and characterization, voltage and current sensing, mid-point high resistance grounding, fault sensing, communications to PSUs, and data link/control to remote nodes. As described herein, the control system 207 may verify cable operation (e.g., verify cable operational integrity) during the Off-time of pulses in the DC pulse power. The pulse power module 206 may include a pulse power modulator, safety circuits, initialization circuits, PMBus,

PMBus I2C (I2C (Inter-Integrated Circuit)), logic, FPGA (Field-Programmable Gate Array), DSP (Digital Signal Processor), or any combination of these or other components configured to perform the functions described herein.

(167) As shown in the example of FIG. 20, the PSUs 205 receive AC power on cables 209 and deliver pulse power on cable 211. In one or more embodiments, the pulse power tap/receiver 212 may combine the phases and deliver high voltage (HV) DC power to the node/endpoint 214 on cable 222. In another embodiment, the pulse power tap/receiver 212 may deliver pulse power to the endpoint 214 on the cable 222. In one or more embodiments, the pulse power cable 211 includes two or more optical fibers for delivering data in the combined power and data cable, as described below. In one example, there may be a dedicated fiber (or fibers) per branch.

(168) The wires within cable 211 may comprise two conductor, twisted pair (with or without shielding), coaxial or triaxial cable, depending on EMC considerations. A separate ground conductor may be provided to address potential common-mode noise issues. It is to be understood that the term wire as used herein may refer to a single wire or a pair of wires. As described below, the power system may comprise any number of wires, which may be bundled with fiber or other communications transmission media.

(169) Power is supplied to the endpoint 214 through the pulse power tap/receiver 212 (also referred to as a branch tap, smart branch tap, receiver/converter). In one or more embodiments, the smart branch taps 212 allow branch fault isolation. The tap/receiver 212 may include, for example, an isolation switch (disconnect switch), data link, and logic/timing controller. The tap/receiver 212 may be used for initializing an auto-negotiation process, fault branch isolation algorithm, power initialization, and faulty PD replacements. The data link over the pulse power wires allows for implementation of the smart branch taps 212 for each node 214 and independent control (disconnect) of each branch for fault isolation or node management.

(170) Each of the endpoints 214 may include an HVDC PSU for powering equipment at the endpoint. The endpoint 214 may comprise, for example, a 56 VDC load and may operate, for example, as a PON (Passive Optical Network) endpoint, 5G node, access point, router, switch, or other type of equipment. The endpoint 214 may also power one or more other nodes (e.g., PoE node, IoT (Internet of Things) device).

(171) It is to be understood that the system shown in FIG. 20 is only an example, and the system may comprise any number of PSUs 205 (e.g., two or more) for providing multi-phase pulse power. The network topology and nodes shown in FIG. 20 is only an example and the network may comprise different topologies and network devices without departing from the scope of the embodiments.

(172) The multiple PSUs allow for multi-phase operation and may also provide redundancy. For example, if one phase is lost in a system comprising three or more phases, continuous power may still be delivered to the PD nodes 214. Each phase is preferably sized to supply higher peak power to maintain full power to the PD nodes 214. Further redundancy may be provided by utilizing N+1 Front End Power (FEP) supplies. For example, in the case of a 1500 W total PD power system, three 1200 W FEPs can power the system with full redundancy of N+N or N+1, with each FEP needing only a common 120V, 15 A feed.

(173) As shown in FIG. 21 and described below, the multi-phase pulse power comprises a plurality of sequences of voltage pulses, each sequence of voltage pulses forming a phase of the multi-phase pulse power. FIG. 21 illustrates an example of 3-phase pulse power voltage and current with a 75% duty cycle with phase drop, delivered in the system shown in FIG. 20, for example. Idealized waveforms are shown and net PD voltage and line current include line loss effect with constant power loading from the nodes/endpoints 214. In the example shown in FIG. 21, phase B drops out for two cycles. The three phase voltages (A, B, and C) (223a, 223b, 223c) are shown with auto-negotiation line sensing 224.

(174) As shown in FIG. 21, during pulse On-time high voltage power is delivered from the PSE to

the PDs and during pulse Off-time while the high voltage power is off, a low voltage may be applied on each phase for use in low voltage sensing (indicated at **224**) to check wire integrity.

(175) The net PD voltage is shown combined for the three phase voltages at **225**. The corresponding phase currents (A, B, C) (**226a**, **226b**, **226c**) are shown below the voltages. The net line current corresponding to the three phase currents is shown at **227**. As shown in FIG. **21**, if one phase is lost (as shown at phase B drop), continuous power is still delivered to the PD nodes. Each phase may be sized to supply higher peak power to maintain full power to the PDs.

(176) As shown in FIGS. **21**, two or more transmission wires (e.g., wires or wire pairs) enable phasing of the conduction on each wire (e.g., wire or pair) so that at least one wire is ON at any time. When OR'd at the PD, the result is continuous DC voltage as shown at **225**, thereby eliminating the need for bulky filter components. During phase overlap in the multi-phase systems, the total cable current is shared across all ON wires. Individual transmission wire current is proportionally reduced, lowering total transmission cable losses.

(177) In one or more embodiments, the Off-time may be fixed, based on worst case cable length and characteristics or actively controlled based on detected cable characterization (for higher efficiency/longer range). The On-time (power delivery) for each phase may be fixed based on total pulse power voltage and shock hazard limits based on appropriate body resistance data. This approach may be used to achieve maximum pulse overlap, thereby reducing cable RMS current and maximizing power transmission distance (or minimizing conductor wire size).

(178) As previously noted, idealized waveforms are shown in FIG. **21**. Inductance in the PSE **200**, cable **211**, and PD receiver **212** may create some averaging of cable currents, raising overlap currents and lowering current during pulse Off-time (FIG. **20**). This effect may vary with cable length and type (inductance). Phase currents shown in FIG. **21**.

(179) As shown in FIG. **21**, each of the phases are offset from one another (phase shifted duty cycle) and provides pulse power comprising on-pulses and an off-pulses. The off-pulse may be a small voltage (e.g., close to 0V, 3V), or any value that is significantly less than the on-pulse power (e.g., at least 170V difference between power levels for on-pulse and off-pulse). As previously described, the on-pulse time and off-pulse time (pulse width, pulse duty cycle) may be selected based on system design (e.g., number of phases, amount of power delivered) and safety requirements. The pulse duty cycle may also vary between an initialization phase, synchronization phase, testing phase, or normal operation. In one example, a startup duty cycle may comprise 8 ms on-pulse and 4 ms off-pulse for a 12 ms time period. In another example, the on-pulse may be only 0.5 ms or 1 ms during high voltage initialization. In one example, the off-pulse may be 1 ms, which includes a resistance analysis and auto-negotiation time of 100 μ s, as described in U.S. patent application Ser. No. 15/971,729, referenced above. In another example, a 2 ms to 4 ms off-pulse (between power pulses) may be needed to properly assess environmental safety within a 10 ms time window.

(180) In one or more embodiments, a central controller at the PSE may coordinate offset between phases and adapt pulse width for optimization (or following loss of a phase as needed). Any changes in pulse timing are communicated to the PD for synchronization.

(181) It is to be understood that the currents, voltages, pulse widths, duty cycles, and phase overlaps shown in FIG. **21** and described above are only examples and may be different than shown or described herein. For example, there may be a higher pulse current during overlap and lower current during non-overlap. The differences may be dependent on pulse power transmission inductance and capacitance (e.g., length of run or type of cable), for example.

(182) As previously noted, the multi-phase pulse power system may comprise two or more wires or wire pairs. It is to be understood that the multi-phase system described herein may be implemented on systems comprising a different number of wires or wire pairs and the three phase system shown in FIGS. **20** and **21** is only an example. The pulse power system may operate with any number of phases (e.g., two, three, four, etc.), without departing from the scope of the embodiments. Also, as

previously described, the cable may include any number of optical fibers or additional copper wires for data transmission. In one or more embodiments, the cable may also carry cooling, as previously described.

(183) FIG. 22 is a simplified circuit of a multi-phase power system for delivery of safe power at higher power levels than conventional PoE, in accordance with one embodiment. The PSE is coupled to the PD through a four-pair cable with connectors 232 (e.g., RJ-45 or modified RJ-45). In one example 56V 2-phase ESP may be used to provide approximately one and a half times more current and power than conventional PoE. In another example 112V 2-phase ESP may be used to provide approximately three times more current and power than 56 VDC PoE. In yet another example, 150V 2-phase ESP provides approximately four times more current and power than 56 VDC PoE.

(184) As previously described, PD and PSE modulators may be synchronized during low voltage or high voltage initialization or during high power operation for each phase in a multi-phase system. In one or more embodiments, PSE and PD modulator (control) switches (described above) may include timing control such that a PSE pulse is turned on before a PD modulator switch is turned on, and PD modulator switch is turned off before the PSE modulator switch is turned off for each pulse, as shown in FIGS. 23 and 24. This may be used to minimize transients on the distribution system, thereby reducing EMI and producing cleaner current waveforms for more accurate current detection.

(185) FIGS. 23 and 24 illustrate simplified voltage waveforms and phase current in a four phase system, in accordance with one embodiment. FIG. 23 illustrates four phase 75% duty cycle operation. Voltage pulses are shown at 264a for phase A, 264b for phase B, 264c for phase C, and 264d for phase D. The cumulative phase current is shown at 266. As shown in FIG. 23, the PSE switch drive is turned on before the PD switch drive at the start of the pulse and at the end of the pulse on interval, the PD switch drive is turned off before the PSE switch drive for each phase.

(186) FIG. 24 illustrates operation with one dropped phase (phase B). Voltage pulses are shown at 274a for phase A, 274c for phase C, and 274d for phase D. The cumulative phase current is shown at 276. As can be seen in FIG. 24, continuous power is still provided, even with loss of phase B by adjusting the relative time of the three functional phases.

(187) As previously discussed with respect to FIGS. 1, 17, and 20, the PSE and PD may communicate in networks comprising various topologies (number and arrangement of PSEs and PDs). The extended safe power (ESP) system described herein may comprise, for example, one or more PSE nodes and one or more PD nodes in a point-to-point topology, daisy chain topology, multi-drop topology, hybrid multi-drop/daisy chain topology, or any combination thereof.

(188) FIG. 25 is a simplified block diagram illustrating an ESP PSE node 280 in communication with an ESP PD node 282 in a point-to-point topology. The PSE node 280 includes a PSE isolation switch 284 and the PD node includes a PD isolation switch 286 in communication over a transmission line 288. The isolation switches 284, 286 isolate the device during initialization, synchronization, and testing as described below. The point-to-point topology is shown in the simplified circuits described above with respect to FIGS. 8-16 and 18-19.

(189) FIG. 26 is a simplified block diagram illustrating a PSE 280a in communication with a PD 282a via a first transmission line 288a. The PD 282a is also in communication with a downstream PSE node 280b through an internal bus 290. The PSE node 280b delivers power to another PD 282b through a second transmission line 288b. The PD 282a and PSE 280b may be located at the same network device and coupled through the internal bus 290. The first PSE 280a performs initialization, synchronization, and safety tests with the first PD 282a. The second PSE 280b performs initialization, synchronization, and safety tests with the second PD 282b.

(190) FIG. 27 illustrates an example of a multi-drop topology. PSE 280 is in communication with two PDs 282a, 282b via transmission line 288. PSE 280 includes isolation switch 284 and each PD includes its own isolation switch 286a, 286b.

(191) FIG. 28 illustrates a hybrid multi-drop/daisy chain topology, in accordance with one embodiment. The PSE 280 and PSE isolation switch 284 are coupled to a first PD 282a through transmission line 288a. PD 282a includes a local isolation switch 286a and an output isolation switch 300a, which may communicate with downstream PD 282b via transmission line 288b. As described in detail below, the PSE 280 performs safety checks and synchronizes with the first PD 282a through the local isolation switch 286a. When the second PD 282b is connected to the network, the PD performs initialization and synchronization with the first PD 282a and after safety checks are passed, receives high voltage pulse power through the output isolation switch 300a at the first powered device 282a via transmission line 288b. This arrangement provides one transmission line for the PSE to monitor as in the multi-drop case, with downstream enrollment controlled by the PD as in the daisy chain case, but using a subset of the PSE's functionality.

(192) Details of an initialization process for the PSE and PDs in the hybrid multi-drop/daisy chain topology (FIG. 28) are described below with respect to FIGS. 29-40, in accordance with one embodiment. As described below, the PSE and PD nodes operate in a hybrid multi-drop daisy chain topology due to functionality within the PD that allows it to internally perform functions typically performed by the PSE (e.g., low voltage initialization). However, from a network device topology perspective (i.e., looking only at the external network device and links), the PSE and PDs form a daisy chain topology (transmission line passes through first PD and directly to second PD).

(193) It is to be understood that while FIGS. 25-40 illustrate only a single phase and the initialization process described below is for the single phase for simplification, the process described herein may be repeated for each phase in a multi-phase system. For example, the transmission line 288 may comprise multiple wire pairs for multi-phase operation and the process described herein may be performed for each phase in the multi-phase system.

(194) In one or more embodiments, a first powered device 322a in communication with power sourcing equipment 320 identifies a second powered device 322b in communication with the first powered device, while the first powered device is receiving high voltage pulse power from the power sourcing equipment (FIG. 37). The first powered device 322a previously performed a (first) low voltage initialization with the power sourcing equipment before receiving the high voltage pulse power (FIGS. 30-36). The first powered device 322a notifies the power sourcing equipment 320 of the second powered device 322b and performs low voltage power initialization with the second powered device before passing the high voltage pulse power to the second powered device 322b (FIGS. 37-40).

(195) Referring now to FIG. 29, a block diagram of a hybrid multi-drop/daisy chain topology is shown. In this example, the PSE 320 is connected to the first PD 322a, which is connected to the second PD 322b. The PSE 320 includes a transceiver 326, high voltage source 328, low voltage source 330, and transmission line monitor 334 in communication with an output isolation switch 332. Each PD 322a, 322b includes upstream detection signaling 336a, 336b, bootstrap power supply 338a, 338b (e.g., housekeeping power circuit described above), and a transceiver 342a, 342b in communication with a local isolation switch 340a, 340b. Each PD 322a, 322b further includes a high voltage receiver 344a, 344b in communication with equipment load output 346a, 346b. The first PD 322a includes an output isolation switch 348a for communication with the second PD 322b. In this example, the second PD 322b also includes an output isolation switch 348b for providing power and data to another downstream PD (using downstream device detector 350b), however, the PD 322b may also be configured without the output isolation switch and downstream detector for operation as an endpoint with no pass through capability. In the example shown in FIG. 29, the PSE 320 and PD nodes 322a, 322b are all in a powered off state with the isolation switch at the PSE in an open position.

(196) FIG. 30 illustrates PSE detection and transmission line discovery for the first PD 322a. In this example, the PSE powers up (output isolation switch 332 closed) and begins sending low voltage pulse power (a low voltage detection pulse train) and gathers transmission line parameters

(e.g., capacitance). The PSE **320** may perform a capacitance test on the cable between the PSE and PD as previously described.

(197) FIG. **31** illustrates the first PD **322a** bringing up power. The PD **322a** powers up by charging local energy storage (bootstrap power supply **338a**), which powers up the PD controller.

(198) FIG. **32** illustrates a PD training phase. The PD **322a** recovers timing parameters (frequency, phase) from the PSE's low voltage pulse train (waveform **333** of the low voltage pulse power) and uses this for the PD isolation switch gate drive waveform to synchronize the PSE and PD modulator switches (described above with respect to FIG. **4**).

(199) FIG. **33** illustrates an identification phase for the PD **322a**. As shown at upstream detection signaling module **336a**, the PD **322a** may send identification data through modulation of load current while receiving the low voltage pulse train. The identification data is received at the transmission line monitor **334** at the PSE **320**.

(200) FIG. **34** illustrates a final PSE safety check in which the PSE **320** isolates the transmission line after disconnecting the low voltage source **330**.

(201) High voltage operation is enabled at the PSE **320** as shown in FIG. **35**. The PSE **320** shifts from PD gate drive low voltage pulse train at low voltage source **330** to high voltage pulse train at high voltage source **328** with no frequency or phase shift. The high voltage source **328** at the PSE **320** is now connected to the transmission line through output isolation switch **332** and the high voltage pulse power is transmitted to the high voltage receiver **344a** through local isolation switch **340a** at the first PD **322a**.

(202) FIG. **36** illustrates PSE-PD communications link up. The transceiver **326** at the PSE **320** establishes communications with the PD **322a** at transceiver **342a**. The PSE **320** and PD **322a** use the communications link to continue negotiation, set power limits, send telemetry, etc.

(203) FIG. **37** illustrates downstream detection of the second PD **322b** at the first PD **322a**. As previously described, the first PD **322a** has already performed a first low power voltage initialization with the PSE **320** through use of its local isolation switch **340a** and is now receiving high voltage pulse power at this local isolation switch. The first PD **322a** detects and then notifies the PSE **320** of the incoming PD (second PD) **322b**. The PD **322a** may also notify the PSE **320** of any necessary timing adjustments due to line capacitance change. If there are any timing changes, the PSE **320** and PD **322a** may re-synchronize, as needed. Downstream device classification and synchronization is then performed for the PD **322b**. The first PD **322a** performs a low voltage synchronization and classification operation with the second PD **322b** using a reduced PSE capability inside of the first PDs controller. The low voltage power received at the second PD **322b** is used to charge bootstrap power supply **338b** and power up the PD controller (upstream detection signaling **336b**).

(204) FIG. **38** illustrates a downstream device safety check. The output isolation switch **348** at the first PD **322a** is closed and a safety check is performed at the PSE **320** for the entire transmission line to the isolation switches **340b**, **348b** at the second PD **322b**.

(205) As shown at FIG. **39**, if the safety check passes, high voltage pulse power is transmitted to the high voltage receiver **344b** at the second PD **322b** through the first PD **322a** and delivery of high voltage pulse power continues with the added node.

(206) A communications link is brought up at the second PD **322b**, as shown in FIG. **40**. The transceivers **326**, **342a**, **342b** link up between all three nodes (PSE **320**, PD **322a**, PD **322b**) and the system reaches steady state.

(207) As previously noted, the above described process may be performed for multi-phase pulse power with synchronization and checks performed for each phase. Also, the network may comprise any number of nodes in any topology with one or more end nodes configured for pulse power operation, one or more nodes configured for pulse power or PoE, and one or more endpoints configured only for PoE. Also, one or more of the PDs may include capability to operate as a PSE for a downstream node as shown in FIG. **26**.

(208) Although the method and apparatus have been described in accordance with the embodiments shown, one of ordinary skill in the art will readily recognize that there could be variations made to the embodiments without departing from the scope of the embodiments. Accordingly, it is intended that all matter contained in the above description and shown in the accompanying drawings shall be interpreted as illustrative and not in a limiting sense.

Claims

1. A method comprising: receiving first pulse power from power sourcing equipment at a powered device; synchronizing the powered device with a waveform of the first pulse power received from the power sourcing equipment such that a modulator switch at the power sourcing equipment is turned on before a modulator switch at the powered device is turned on and the modulator switch at the powered device is turned off before the modulator switch at the power sourcing equipment is turned off; operating the powered device with second pulse power received from the power sourcing equipment, wherein the first pulse power is at a power level lower than a power level of the second pulse power; and starting up a transceiver at the powered device for communication with the power sourcing equipment before receiving the second pulse power.
2. The method of claim 1, wherein the receiving and the synchronizing are performed for each phase of a multi-phase pulse power system.
3. The method of claim 1, further comprising starting up a housekeeping circuit upon receiving the first pulse power from the power sourcing equipment over a fixed time period.
4. The method of claim 1, further comprising disabling a first housekeeping circuit upon receiving the second pulse power and operating a second housekeeping circuit for the second pulse power.
5. The method of claim 1, wherein the first pulse power comprises a first waveform of pulses of a first level with on and off periods of a duty cycle, and the second pulse power comprises a second waveform of pulses of a second level with on and off periods of a duty cycle.
6. The method of claim 1, wherein the first pulse power comprises pulses of power transmitted at or below 60 volts.
7. The method of claim 1, wherein a difference between the first pulse power and the second pulse power is at least 170 volts.
8. The method of claim 1, further comprising negotiating a power level with the power sourcing equipment.
9. The method of claim 1, wherein the power sourcing equipment performs a safety test before transmitting the second pulse power.
10. The method of claim 1, further comprising transmitting the second pulse power to a second powered device.
11. The method of claim 1, wherein the power sourcing equipment checks for normal operation of the modulator switch at the powered device and turns power if normal operation is not confirmed.
12. A method comprising: receiving pulse power from power sourcing equipment at a powered device with a modulator switch open; coupling isolated voltage at the powered device when a pulse of the pulse power is on; and turning on the modulator switch at the powered device after a specified number of pulses of the pulse power are received to power the powered device with the pulse power.
13. The method of claim 12, wherein the power sourcing equipment checks for normal operation of the modulator switch at the powered device and turns off the pulse power if normal operation is not confirmed.
14. The method of claim 12, wherein the powered device is hot swapped into a network comprising the power sourcing equipment before receiving the pulse power.
15. The method of claim 12, wherein the pulse power received with the modulator switch open comprises a short pulse On-time and wherein the pulse power received after the modulator switch

is turned on comprises a normal operation pulse On-time.

16. The method of claim 12, further comprising synchronizing timing of the modulator switch with a power sourcing equipment modulator switch.

17. A powered device comprising: an input for receiving pulse power from power sourcing equipment; a modulator switch; and a controller for synchronizing the powered device with a waveform of the pulse power received from the power sourcing equipment, wherein the controller is configured to turn on the modulator switch after a specified number of pulses of the pulse power are received.

18. The powered device of claim 17, wherein the controller is operable to start up a transceiver at the powered device for communication with the power sourcing equipment.

19. The powered device of claim 17, wherein the controller is operable to start up a housekeeping circuit upon receiving low voltage power from the power sourcing equipment over a fixed time period before receiving the pulse power.

20. The powered device of claim 17, wherein the pulse power comprises a first waveform of pulses of a first level with on and off periods of a duty cycle.
