

US Patent & Trademark Office

Patent Public Search | Text View

United States Patent	12407873
Kind Code	B2
Date of Patent	September 02, 2025
Inventor(s)	Ivanovic; Boris et al.

Metric driven adaptive processing for video encoders

Abstract

A method includes obtaining, at a data reduction module, metrics of a first block of an input video frame and a second block of a reference frame. The data reduction module includes an analysis module and a filter. A perceptual importance of the first block of the input video frame is determined at the analysis module using the metrics. An entropy of the input video frame provided to an encoder is adjusted at the filter of the data reduction module based on the perceptual importance of the first block of the input video frame.

Inventors:	Ivanovic; Boris (Markham, CA), Saeedi; Mehdi (Markham, CA)
Applicant:	ATI TECHNOLOGIES ULC (Markham, CA)
Family ID:	74044884
Assignee:	ATI TECHNOLOGIES ULC (Markham, CA)
Appl. No.:	16/453377
Filed:	June 26, 2019

Prior Publication Data

Document Identifier	Publication Date
US 20200413105 A1	Dec. 31, 2020

Publication Classification

Int. Cl.: **H04N19/91** (20140101); **H04N19/117** (20140101); **H04N19/176** (20140101);
H04N19/60 (20140101)

U.S. Cl.:

CPC **H04N19/91** (20141101); **H04N19/117** (20141101); **H04N19/176** (20141101);

Field of Classification Search

USPC: None

References Cited**U.S. PATENT DOCUMENTS**

Patent No.	Issued Date	Patentee Name	U.S. Cl.	CPC
6002801	12/1998	Strongin	375/240.18	H04N 19/60
6895048	12/2004	Boice	375/240	H04N 19/159
8179974	12/2011	Tu	375/240.24	H04N 19/176
9955160	12/2017	Yadav	N/A	H04N 19/117
10694178	12/2019	Jun	N/A	H04N 19/115
2006/0034539	12/2005	Nachlieli	382/260	H04N 19/60
2007/0116125	12/2006	Wada	375/240.16	H04N 19/85
2007/0206871	12/2006	Jalil	382/233	H04N 19/527
2010/0166073	12/2009	Schmit	375/240.16	H04N 19/51
2013/0094571	12/2012	Zhang	375/240.03	H04N 19/152
2016/0366413	12/2015	Zhang	N/A	H04N 19/82
2017/0155924	12/2016	Gokhale	N/A	H04N 19/1883
2018/0176562	12/2017	Iwamura	N/A	H04N 19/625
2019/0045217	12/2018	Gokhale	N/A	H04N 19/142
2019/0089957	12/2018	Zhang	N/A	H04N 19/146
2019/0246138	12/2018	Terterov	N/A	H04N 19/86
2020/0413105	12/2019	Ivanovic	N/A	H04N 19/10

OTHER PUBLICATIONS

Richardson, Iain E., "The H.264 Advanced Video Compression Standard", Chapter 6, Second Edition, 2010, pp. 137-177. cited by applicant

Primary Examiner: Anyikire; Chikaodili E

Background/Summary**BACKGROUND**

(1) In wireless and computer-based video devices, users of video applications typically use vast amounts of video data in order to attain their daily intake of video content. As a result, providers of video content, as well as the manufacturers of the electronic devices that render video applications, are striving to reduce the cost associated with encoding the video applications, since encoding of the video data is a primary bottleneck in video delivery systems. In order to save costs, some manufacturers utilize conventional video encoding techniques that compress the video content only at the encoder and rely primarily on the modification of quantization parameters (QP). Other video encoding techniques limit the bandwidth of video applications but tend to change the resolution of the video, thereby reducing the quality of the video in order to compress the video data. However, such conventional techniques are non-optimal because they generally compress the entire video

image at the same rate, potentially reducing quality even in areas where universal video compression is not required.

Description

BRIEF DESCRIPTION OF THE DRAWINGS

- (1) The present disclosure may be better understood, and its numerous features and advantages made apparent to those skilled in the art by referencing the accompanying drawings. The use of the same reference symbols in different drawings indicates similar or identical items.
- (2) FIG. 1 is a block diagram of a video processing system configured to encode video based on pre-encoding analysis and filtering in accordance with some embodiments.
- (3) FIG. 2 is a block diagram of an encoding system configured to encode video based on transform domain filtering in accordance with some embodiments.
- (4) FIG. 3 is a block diagram of an encoding system configured to encode video based on lossy entropy shaping in accordance with some embodiments.
- (5) FIG. 4 is a flow diagram illustrating a method for encoding video based on pre-encoding analysis and filtering in accordance with some embodiments.
- (6) FIG. 5 is a flow diagram illustrating a method for encoding video based on transform domain filtering in accordance with some embodiments.
- (7) FIG. 6 is a flow diagram illustrating a method for encoding video based on lossy entropy shaping in accordance with some embodiments.

DETAILED DESCRIPTION

(8) FIGS. 1-6 illustrate systems and techniques for encoding video in a video processing system in a manner that reduce the bandwidth required to render the video content. Prior to an encoder receiving input video frames, the input video frames undergo pre-encoding analysis and, based on the results of the analysis, either provide the input video frames to the encoder or filter the input video frames at a data analysis and reduction module. Filtering the input video frames allows the data analysis and reduction module to reduce the entropy of the input video frames as provided to the encoder. During a data analysis and reduction stage, an analysis module generates a perceptual importance parameter related to macroblocks, sub-blocks, or localities of current input video frames and previously processed reference frames using metrics or parameters of both the current input video frames and the reference frames. A filter uses the perceptual importance parameter to reduce or not reduce the entropy represented in the input video frame provided to the encoder prior to undergoing the encoding process. In addition to the ability to reduce entropy of the input video frame to the input of the encoder, in some embodiments the video processing system employs a transform domain filter or a lossy entropy shaper to reduce the bandwidth required during the encoding process. The transform domain filter uses transform coefficients output by the transform module of the encoding system and an energy calculation of the transform coefficients indicative of the perceptual importance of the current macroblock to generate a new set of transform coefficients that are provided to the quantizing module of the encoder at a reduced bitrate. The lossy entropy shaper uses a comparison of a set of quantized transform coefficients output from the quantization module to sets of alternative quantized transform coefficients generated at the lossy entropy shaper to render a set of alternative quantized transform coefficients at the entropy module that are at a reduced bitrate compared to the original set of quantized transform coefficients. Both transform domain filtering and lossy entropy shaping may be used in combination with the data reduction module to generate an encoded frame at a reduced bitrate at the output of the encoder for view by a user of the video processing system.

- (9) FIG. 1 illustrates a block diagram of a video processing system **100** configured to encode video based on pre-encoding analysis and filtering in accordance with some embodiments. The video

processing system **100** includes a data reduction module **115**, an encoder **110**, a decoder **150**, and a display **160**. Data reduction module **115** includes an analysis module **120** and a filter **122**. Encoder **110** includes a decoded buffer **130**, a motion estimation (ME) module **190**, a motion compensation (MC) module **192**, an intra prediction module **132**, a switching module **198**, an adder module **180**, an adder module **182**, a transform module **170**, a quantization module **172**, an inverse transform module **176**, an inverse quantization module **178**, and an entropy module **174**. The modules described herein may be implemented as hardwired or hardcoded logic and other circuitry, programmable logic, one or more processors executing one or more sets of instructions configured to manipulate the one or more processors to implement the functionality described herein, or a combination thereof.

(10) The encoder **110** of video processing system **100** is configured to receive digital information from a video source (not shown), where the digital information represents a stream or sequence of image frames, such as input video frame **102**, in a multimedia stream. The term “multimedia” refers to either video only or a combination of video and audio. The encoder **110** encodes the digital information for transmission over a communication channel such as a wide area network (WAN), an intranet, an internet, a wireless network, and the like. For example, in some embodiments the encoder **110** is used to encode the digital information according to an encoding standard such as Moving Picture Expert Group (“MPEG”)-2, MPEG-4, Advanced Video Coding (“AVC”), and the like. In some embodiments, the encoder **110** is a hardware encoder or software executed by the one or more processors. In some embodiments, encoder **110** compresses video content using a two-dimensional (2D) video codec or a multiview video codec (MVCs) such as, but not limited to, H.264/MVC, H.265 (HEVC), VP8, VP9, AV1.

(11) During operation, the input video frame **102** is presented at video processing system **100** from the video source (not shown) for data analysis and reduction. In order to reduce the bandwidth required of encoder **110** during the encoding process, the input video frames **102** are initially input to filter **122** and analysis module **120** of data reduction module **115** prior to being input into encoder **110** to perform bandwidth reduction. The analysis module **120** receives the input video frames **102** from the video source and the reference frames **109** from the encoder **110** and produces analysis output **104**, which is used by filter **122** to reduce the entropy of the input video frames **102** to yield filtered frames **108** that are provided to encoder **110**. In various embodiments, filter **122** may be, for example, a low-pass filter, a high pass filter, or other type of filter used for filtering out various video content. In various embodiments, filtering may depend on, for example, local content and may not be the same for the entire frame. In various embodiments, entropy reduction or detail reduction, may include, for example, 2D blur or noise reduction, 3D blur or noise reduction, or some combination thereof.

(12) In order to generate analysis output **104**, analysis module **120** examines current input video frames (input video frames **102**) and previous video frames (reference frames **109**) to eliminate unnecessary data from the macroblocks that formulate the input video frames **102**. In various embodiments, the input video frames **102** and reference frames **109** are examined as an entire frame, macroblock, sub-block, or locality (combination of sub-blocks) based on metrics (or parameters) specified in, for example, a look-up table (LUT) **107**. The metrics are features of the video content or input video frames **102** or reference frames **109** that include, for example, contrast content, flesh-tone content, memory color content, frequency content, energy content, motion content, and other parameters that influence the human visual system. For example, in various embodiments, analysis module **120** compares the contrast content of the current macroblock of input video frame **102** with the contrast content of a macroblock of the reference frame **109** to ascertain the contrast content difference between the current macroblock and reference frame macroblock. Analysis module **120** uses the calculated difference to generate analysis output **104**, which is indicative of the perceptual importance of the macroblock of the input video frame **102**. That is, analysis module **120** uses the resulting difference to determine whether the current

macroblock is perceptually important to the user of the video content. The output of analysis module **120** (analysis output **104**) is the perceptual importance of the macroblock of the input video frame **102** or a perceptual importance of the sub-block or locality of the input video frame **102**. (13) In various embodiments, when the difference between the metrics of a macroblock, sub-block, or locality of the input video frame **102** and the metrics of a macroblock, sub-block, or locality of the reference frame **109** is less than a difference value of a plurality of difference values specified in the LUT **107**, then the perceptual importance of the macroblock, sub-block, or locality is deemed significant and the filter **122** does not remove the macroblock, sub-block, or locality from the input video frame **102** that is provided encoder **110**. When the difference between the metrics of a macroblock, sub-block, or locality of the input video frame **102** and the metrics of a macroblock, sub-block, or locality of the reference frame **109** is greater than the difference value specified in the LUT **107**, then the perceptual importance of the macroblock, sub-block, or locality is deemed insignificant and the macroblock, sub-block, or locality is removed by filter **122** to generate filtered frame **108**. Analysis module **120** provides the analysis output **104** to filter **122** and control settings **106** to encoder **110**.

(14) Concurrent to providing analysis output **104** to filter **122**, analysis module **120** provides control settings **106** to encoder **110**. The control settings **106** are generated by analysis module **120** and are configured to provide encode options, video quality, bit-rate, and rate-control to encoder **110**. The control settings **106** generated by analysis module **120** may be global control settings or per-block or per locality control settings and may also be generated using the LUT **107**. Per-block or per-locality control settings include local quality settings such as, quantization parameters (QP) of a macroblock, coding tree blocks (CTB), largest coding module (LCU), in addition to mode parameters and partitioning parameters of the various codecs listed above. The output of analysis module **120**, i.e., control settings **106** and analysis output **104**, are provided to encoder **110** and filter **122**, respectively.

(15) Filter **122** receives the output from the analysis module **120** and uses analysis output **104** to generate a filtered version of the input video frames **102** (filtered video frames **108**) that have been reduced in bandwidth. Thus, the function of filter **122** is to use the perceptual importance provided by analysis module **120** to remove detail, noise or entropy within macroblocks, sub-blocks, or localities from the input video frame **102** that are perceptually insignificant to the viewer of the video content. In various embodiments, by removing the perceptually insignificant features of the input video frame **102**, filter **122** is configured to remove unwanted noise or frequency signals that correspond to the perceptually insignificant features of the video content, which typically includes the lower frequencies of the input video frame **102**. Thus, filter **122** may include, for example, a low pass filter or noise filter or combination thereof capable of removing a specific band or type of frequencies and/or noise from the input video frame **102**. The output of filter **122** (filtered frames **108**) are provided at a reduced bit rate (compared to the input video frames **102**) to encoder **110**.

(16) After undergoing the data reduction process at data reduction module **115**, the filtered frames **108** are received by encoder **110** at adder module **180**, motion estimation module **190**, and intra prediction module **132**. The output of motion estimation module **190** is provided to motion compensation module **192**, whose output is selectively provided, along with the output of intra prediction module **132**, to adder module **180**. Adder module **180** combines the output of filter **122** with the output of either motion compensation module **192** or intra prediction module **132**. That is, the output of the output of either motion compensation module **192** or intra prediction module **132** is combined with the filtered input video frames **108** and taken through a transform process (T) at transform module **170**, such as a forward discrete cosine transform (fDCT) module, and a quantization process (Q) at quantization module **172**. The quantized data output by quantization module **172** is provided to entropy module **174** and also processed through an inverse quantization process (Q.sup.-1) and an inverse transform process (T.sup.-1), such as iDCT. The inversely transformed data is then combined with the motion compensation output or intra prediction module

132 output to generate reference frames **109** that are provided to decoded buffer **130** for storage, whose output is used as input for motion estimation (in motion estimation module **190**) and motion compensation module **192**. The output of quantization module **172** is provided to entropy module **174**, that generates the encoded output frame **140** that has been reduced in bandwidth by analysis module **120** and filter **122** for use by decoder **150** on display **160**. In various embodiments, the entropy of pixels of the input video frame **102** for each macroblock, sub-block, or locality have been modified, deleted, or reduced adaptively, thereby reducing the bandwidth utilized by encoder **110** and by reducing the number of bits in areas that are perceptually unnoticeable or acceptable by the viewer of the video content on display **160**.

(17) FIG. 2 illustrates a block diagram of an encoding system **200** configured to encode video based on transform domain filtering in accordance with some embodiments. Encoder **210** includes a transform domain filter **215**, a decoded buffer **230**, an ME module **290**, an MC module **292**, an intra prediction module **232**, a switching module **298**, an adder module **280**, an adder module **282**, a transform module **270**, a quantization module **272**, an inverse transform module **276**, an inverse quantization module **278**, and an entropy module **274**.

(18) During operation, an input video frame **202** is presented at encoder **210** for encoding. The motion estimation module **290**, adder module **280**, and intra prediction module **232** receive the input video frame **202**. Intra prediction module **232**, whose function is to predict pixels or macroblocks in the current input video frame **202** from similar pixels or macroblocks in reference frames **209**, uses the input video frame **202** and output of adder **282** to generate a prediction macroblock. The intra prediction output (prediction macroblock) is provided to adder module **280** and adder module **282**. When using motion compensation, MC module **292** uses the output of ME module **290** (which locates a macroblock in reference frame **209** that closely matches the current macroblock in the input video frame **202** and generates a motion vector that is provided to MC module **292**) to generate a motion compensated prediction macroblock.

(19) Adder module **280** receives the current macroblock from the input video frame **202** and the prediction macroblock (output of the intra prediction module **232** or MC module **292**) and subtracts the prediction macroblock from the current macroblock to generate a residual macroblock. Adder module **280** provides the residual macroblock to transform module **270**. Transform module **270** uses a transform process such as, for example, a forward discrete cosine transform (fDCT), to generate a set of transform coefficients **211** that are in the frequency or transform domain. However, instead of being provided directly to quantization module **272** as is typical in the art, the transform coefficients **211** are provided to transform domain filter **215** to be altered or zero'd out in order to reduce the bandwidth required of encoder **210**. Thus, the input to transform domain filter **215** are the transform coefficients **211** from transform module **270** that are to undergo entropy reduction.

(20) In various embodiments, transform domain filter **215** receives the transform coefficients **211** and, in order to commence the process of data reduction by encoder **210**, determines the energy associated with each transform coefficient. Transform domain filter **215** determines the energy associated with a transform coefficient of transform coefficients **211** using, for example, a heuristic algorithm. That is, transform domain filter **215** may use the heuristic algorithm to determine the amount of energy associated with the varying frequencies (e.g., low frequency and high frequency) of the received transform coefficients **211**. In various embodiments, the amount of energy associated with a transform coefficient is indicative of the perceptual importance of the underlying video content. Thus, making such an energy determination allows transform domain filter **215** to decide whether to zero out or alter the transform coefficient using the perceptual importance of the transform coefficient input into transform domain filter **215**.

(21) In various embodiments, in order to determine the perceptual importance using the results of the energy determination, transform domain filter **215** compares the energy of the transform coefficient with an energy look-up table **219** containing the energy associated with prior transform

coefficients. Based on the results of the comparison, transform domain filter **215** is able to determine whether to zero-out, alter, or not zero-out the transform coefficient prior to providing the altered transform coefficients **213** to quantization module **272** for quantization.

(22) In various embodiments, when transform domain filter **215** determines the perceptual importance of the transform coefficient is of significance (based on the amount of energy associated with the transform coefficient being, for example, above a certain energy amount or being listed as perceptually important in the look-up table **219**), the transform coefficient remains unchanged and is not altered or removed by transform domain filter **215** before being provided to quantization module **272**. When transform domain filter **215** determines the perceptual importance of the transform coefficient is insignificant, i.e., the amount of energy associated with the transform coefficient is below a certain energy amount listed in the look-up table **219** as being perceptually unimportant, the transform coefficient is zero'd-out or adjusted such that, when quantized by quantization module **272**, the quantized data is represented by a reduced number of bits. The altered or unaltered transform coefficients **213** are then provided to quantization module **272**. The encoding process then continues at a reduced entropy rate using quantization module **272**. The output of quantization module **272** is provided to entropy module **274** and inverse quantization module **278**.

(23) After generating the reduced entropy transform coefficients **213**, transform domain filter **215** provides the transform coefficients **213** to quantization module **272** that executes the quantization process (Q) and generates quantized data. In addition to quantized data being processed by entropy module **274** to generate encoded frame **240**, quantization data is processed through the inverse quantization process (Q.sup.-1) at inverse quantization module **278** and an inverse transform process (T.sup.-1) at inverse transform module **276**. The inversely transformed data is then combined with the motion compensation output or intra prediction module **232** output to generate reference frames **209** that are provided to decoded buffer **230** for storage, whose output is used as input for motion estimation (in motion estimation module **290**) and motion compensation module **292**. The output of quantization module **272** is provided to entropy module **274** to be used to generate the encoded output frame **240** for use by decoder **150** on display **160** of FIG. 1.

(24) In addition to using the transform coefficients **211** for data reduction, in some embodiments transform domain filter **215** uses the filter settings **295**, analysis input **204**, and motion estimation output **214** for data reduction. In various embodiments, the filter settings **295** provided to transform domain filter **215** may, for example, dictate the type of algorithm to be used when determining the perceptual importance of the transform coefficient **211**. The analysis input **205** may provide information that is used by transform domain filter **215** to adjust or provide the energy settings in look-up table **217**. For example, analysis input **205** may provide the values in look-up table **219** that are indicative of being insignificant (e.g., a transform coefficient indicative of a cloud setting or nighttime setting), thereby dictating that the corresponding transform coefficients are insignificant. In various embodiments, a quality setting may be used to render the perceptual importance of a block or sub-block of the input video frame **202** and to control the adaptive filtering performed by transform domain filter **215**. That is, a bit or bits located in, for example, look-up table **219** associated with transform domain filter **215** or provided in the filter settings **113** may dictate whether transform domain filter **215** performs filtering or the level of filtering performed by transform domain filter **215**. In various embodiments, transform domain filter **215** uses analysis input **204**, filter settings **295**, or motion estimation output **214** from motion estimation module **290**, or combination thereof, to adjust the quality setting.

(25) In various embodiments, whether or not a transform coefficient is zero'd-out or altered may be based the amount of error associated with or permitted for the macroblock that is currently being evaluated by transform domain filter **215**. That is, the error introduced by zeroing out or altering a transform coefficient may be required to fit within a permitted error amount provided by filter setting **213** or in the look-up table **219**. The permitted error amount may be based on, for example,

the human visual system, where errors are permitted for portions of the macroblocks that have transform coefficients associated with visual content that are less sensitive to errors, such as losses at higher frequencies imperceptible to the human eye. In various embodiments, the permitted error for the macroblock or sub-block being evaluated may be a transfer function, where at least one of the following parameters are evaluated by the transfer function: motion parameters provided by motion estimation output **214** from ME module **290**; motion parameters provided by analysis module **120** of FIG. **1**; and energy or noise within specific frequencies evident by transform coefficients **211**. In various embodiments, the error parameters may be measured using, for example, decibels (dB), mean square error (MSE), Structural Similarity Index (SSIM), or other well-known metric measuring units as are generally known in the art.

(26) Since transform domain filter **215** is able to estimate the perceptual importance of the transform coefficients that are related to a macroblock or sub-block of the input video frame **202** (as indicated by an assessment of the transform or frequency coefficients by transform domain filter **215**), transform domain filter **215** is able to perform adaptive filtering that reduces bits in areas of the input video frames **202** that are perceptually unnoticeable, acceptable, or tolerable to a user of the video image. Thus, transform domain filter **215** is configured to adaptively determine activity or strength of a range of frequencies and selectively alter the data from the transform module **270** before passing the altered data to the quantization module **272**.

(27) FIG. **3** illustrates a block diagram of an encoding system **300** configured to encode video based on lossy entropy shaping in accordance with some embodiments. Encoder **310** includes a lossy entropy shaper **375**, a decoded buffer **330**, an ME module **390**, an MC module **392**, an intra prediction module **332**, a switching module **398**, an adder module **380**, an adder module **382**, a transform module **370**, a quantization module **372**, an inverse transform module **376**, an inverse quantization module **378**, and an entropy module **374**.

(28) During operation, an input video frame **302** is presented at encoder **310** for encoding. The motion estimation module **390**, adder module **380**, and intra prediction module **332** receive the input video frame **302**. Intra prediction module **332** uses the input video frame **302** and output of adder **382** to generate a prediction macroblock. The intra prediction output (prediction macroblock) is provided to adder module **380** and adder module **382**. When using motion compensation, MC module **392** uses the output of ME module **390** to generate a motion compensated prediction macroblock that is provided to adder module **380** and adder module **382**.

(29) Adder module **380** receives the current macroblock from the input video frame **302** and the prediction macroblock (output of the intra prediction module **332** or MC module **392**) and subtracts the prediction macroblock from the current macroblock to generate a residual macroblock. Adder module **380** provides the residual macroblock to transform module **370**. Transform module **370** receives the residual macroblock and generates a set of transform coefficients for use by quantization module **372**. The transform coefficients are provided to quantization module **372** to generate quantized transform coefficients **317**. The quantized transform coefficients **317** are provided to lossy entropy shaper **375** as an original set of quantized transform coefficients for entropy reduction.

(30) Lossy entropy shaper **375** receives the original set of quantized transform coefficients **317**, and in some embodiments, analysis output **304** and motion estimation output **314**, in order to generate lossy entropy shaper output **397** (lossy or altered quantized transform coefficients **397**). Lossy entropy shaper **375** adjusts or zeros out a quantized transform coefficient of the original set of quantized transform coefficients **317** and creates a set of altered quantized transform coefficients. In various embodiments, a set of heuristics or algorithm may be used to zero out, alter, or reduce the quantized transform coefficient, such as, for example, quantized transform coefficients that represent higher frequencies. In some embodiments, a plurality of sets of altered quantized transform coefficients may be created by lossy entropy shaper **375**. Lossy entropy shaper **375** determines a metric (e.g., SSIM, MSE, or PSNR, or other metric) of the original set of quantized

transform coefficients and the set of altered quantized transform coefficients. For example, in various embodiments, each coefficient or sets of quantized transform coefficients is tested to determine the encoded size in bits, PSNR, SSIM, or other metric.

(31) The metric of the original set of quantized transform coefficients **317** is compared to the metric of a first set of altered quantized transform coefficients in order to shape the received quantized transform coefficients **317** to generate the entropy reduced lossy quantized transform coefficients **397**. In various embodiments, lossy entropy shaper **375** compares the set of original quantized transform coefficients **317** to a set or series of sets or blocks of quantized transform coefficients that have a reduced encoding size compared to the received block of quantized transform coefficients **317**. In various embodiments, the sets of quantized transform coefficient blocks and the metrics associated with the sets of quantized transform coefficient blocks are stored in, for example, a look-up table **319** associated with lossy entropy shaper **375**. In various embodiments, the series of sets or blocks located in look-up table **319** includes, for example, a first set of quantized transform coefficients, a second set of quantized transform coefficients, and a third set of quantized transform coefficients. In various embodiments, the first set of quantized transform coefficients, second set of quantized transform coefficients, and third set of quantized transform coefficients differ from the original set of quantized transform coefficients **317** by one, two, or three coefficients. In various embodiments, look-up table **319** may include an additional or reduced number of sets of quantized transform coefficients depending on, for example, the processing capabilities of the processor use for encoder **310**.

(32) In various embodiments, when the metric associated with the set of altered quantized transform coefficients exceeds a quality requirement or threshold, the altered quantized transform coefficients are provided as the lossy entropy shaper output **397**. In various embodiments, when metric associated with the set of altered quantized transform coefficients does not exceed the quality requirement or threshold, the original altered quantized transform coefficients (and not the altered quantized transform coefficients) are provided as the lossy entropy shaper output **397**. In various embodiments, the set of quantized transform coefficients that is selected is the set of quantized transform coefficients that has the lowest encoded size and meets the quality requirement. In various embodiments, the quality requirement may be a static number (e.g., 35 dB) that is selected for the product or use-case. In various embodiments, the quality requirement may be an adaptive number, based on, for example, analog output **304** or and motion estimation output **314**. In various embodiments, based on, for example, a minimum local perceptual quality (i.e., the acceptable visual quality of encoder **310**), lossy entropy shaper **375** may select one of the first, second, or third blocks of quantized transform coefficients to replace the quantized transform coefficients **317** that are provided to entropy module **374** to reduce the amount of data output by the encoder.

(33) In various embodiments, lossy entropy shaper **375** selects the block set or set of altered of quantized transform coefficients based on, for example, estimating the local error associated with the selected block of quantized transform coefficients, the number of bits saved by selecting the alternative set of quantized transform coefficients, or the return on investment (ROI) provided by the selected set of quantized transform coefficients, or combination thereof. In various embodiments, a single or multiple sets of alternative quantized transform coefficients may be examined. In various embodiments, the ROI may be determined by assessing whether the minimum local perceptual quality has been attained.

(34) In various embodiments, in order to select the quantized transform coefficients that are included in the alternative block of quantized transform coefficients, lossy entropy shaper **375** examines the quantized transform coefficients **317** provided from quantization module **372** to determine which transform coefficient (and thus the associated bit stream), if any, within the quantized data may be zero'd out prior to being provided to entropy module **374**. The lossy entropy shaper **375** may use, depending on type of assessment made by lossy entropy shaper **375**, the

heuristic algorithm described above, a regressive model, or machine learning to determine which quantized transform coefficient (and associated bits) may be adjusted in the block of quantized transform coefficients. In various embodiments, lossy entropy shaper 375 uses metrics stored in LUT 319 or provided to lossy entropy shaper 375 by filter settings 395 to determine which quantized transform coefficient in the alternative block of quantized transform coefficients are insignificant and not necessary for entropy module 374 to generate acceptable video content. The output of lossy entropy shaper 375, i.e., lossy quantized transform coefficients 397, are provided to entropy module 374, which may be, for example, a standards-compliant entropy module.

(35) In various embodiments, lossy entropy shaper 375 is configured to perform the adaptive filtering described above in the frequency space or transform space including, for example, selective transform coefficient removal and alternative quantize transform coefficient set selection. In various embodiments, lossy entropy shaper 375 is configured to evaluate both the error introduced by selecting the alternative set of transform coefficients and the number of bits saved by selecting the alternative set of transform coefficients (i.e., the introduced error and saved bits in the output bitstream) for the reduced set of quantized transform coefficient alternatives. In various embodiments, the alternative set of quantized transform coefficients may be selected based upon a strength parameter provided from filter settings 395, where the strength parameter indicates the weight associated with the transform coefficient. In various embodiments, the strength parameter may be, for example, a set of parameters that are defined for each local region and may be adaptive based on, for example, various criteria that indicate the weight associated with the transform coefficient. In various embodiments, weights provided by the filter settings 395 to lossy entropy shaper 375 may be used to provide an assigned value to the metrics. The weights may be user-controlled weights or coefficients that weigh the metrics used in data reduction, where the coefficients relate to each metric using a transfer function.

(36) After performing the coefficient modification using lossy entropy shaping, lossy entropy shaper 375 provides the lossy entropy shaper output 397 to entropy module 374 and inverse quantization module 378. In addition to lossy entropy shaper output 397 being processed by entropy module 374 to generate encoded frame 340, lossy entropy shaper output 397 is processed through the inverse quantization process (Q.sup.-1) at inverse quantization module 378 and an inverse transform process (T.sup.-1) at inverse transform process module 376. The inversely transformed data is then combined with the motion compensation output or intra prediction module 332 output to generate reference frames 309 that are provided to decoded buffer 330 for storage, whose output is used as input for motion estimation (in motion estimation module 390) and motion compensation module 392. The output of lossy entropy shaper 375 is provided to entropy module 374 to generate the encoded output frame 340 for use by, for example, decoder 150 of display 160 of FIG. 1.

(37) In various embodiments, encoder 310 of FIG. 3 or encoder 210 of FIG. 2 or combination thereof may be used in the data reduction process configuration depicted in FIG. 1. For example, encoder 210 and encoder 310 may receive as input video frames 202, filtered frames 108, and proceed with performing the data reduction encoding process stated above and referenced in FIGS. 2 and 3. That is, the data reduction processes described in both FIG. 1, FIG. 2, and FIG. 3 may be combined to provide a dual or triple data reduction process, taking advantage of the data reduction processes of the configurations depicted in FIG. 1, FIG. 2, and FIG. 3.

(38) FIG. 4 depicts a method for 400 for encoding video based on pre-encoding analysis and filtering in accordance with some embodiments. With reference to FIG. 1, at block 405, an input video frame 102 and a reference frame 109 is provided to analysis module 120 of data reduction module 115. At block 410, metrics of a macroblock, sub-block, or a locality of the input video frame 102 and the reference frame 109 are obtained. At block 415, the metrics are utilized by analysis module 120 to determine the perceptual importance of the macroblock, sub-block, or locality of the input video frame 102. At block 420, control settings 106 are provided to encoder

110 and the macroblock, sub-block, or locality and perceptual importance of the macroblock, sub-block, or locality is provided to filter **122** as analysis output **104**. At block **425**, filtered frames **108** are generated that may or may not have been altered based on the perceptual importance indicated by analysis output **104** and corresponding macroblock, sub-block, or locality of input video frame **102**. At block **430**, the filtered frames **102** and control settings **106** are provided to encoder **110**. At block **430**, encoder **110** encodes the filtered frames **102** at a reduced bitrate or bandwidth.

(39) FIG. 5 depicts a method **500** for encoding video based on transform domain filtering in accordance with some embodiments. With reference to FIG. 2, at block **510**, transform coefficients **211** are received at transform domain filter **215** from transform module **270** to commence data reduction. At block **515**, the energy associated with the transform coefficients **211** are determined. At block **520**, the energy determined for the transform coefficients is used to determine whether to zero out, alter, or not alter the corresponding transform coefficient of transform coefficients **211**. At block **525**, based on the results of the determination, the corresponding transform coefficient of transform coefficients **211** is either zero'd, altered, or not altered. At block **530**, the updated transform coefficients **213** are provided to quantization module **272** at a reduced bitrate for quantization. At block **535**, the encoding process continues in encoder **210** at the reduced bitrate.

(40) FIG. 6 depicts a method **600** for encoding video based on lossy entropy shaping in accordance with some embodiments. With reference to FIG. 3, at block **610**, an original set of quantized transform coefficients **317** are received at lossy entropy shaper **375** from quantization module **372**. At block **615**, the original set of quantized transform coefficients **317** are compared to a first set of altered quantized transform coefficients and a second set of altered quantized transform derived indirectly using LUT **319**. At block **620**, based on the results of the comparison at block **615**, the bandwidth of encoder **310** is can be reduced by replacing the original set of quantized transform coefficients **317** with either the first set of altered quantized transform coefficients or the second set of altered quantized transform coefficients that shall result in reduced bitrate compared to the original set of quantized transform coefficients **317**. At block **625**, when either the first set of altered quantized transform coefficients or the second set of altered quantized transform coefficients is selected, the altered set of quantized transform coefficients **397** are encoded by encoder **310** at the reduced bitrate.

(41) In various embodiments, a method includes: obtaining, at a data reduction module, metrics of a first block of an input video frame and a second block of a reference frame; determining, at the data reduction module, a perceptual importance of the first block of the input video frame using the metrics; and adjusting, at the data reduction module, an entropy of the input video frame provided to an encoder based on the perceptual importance of the first block of the input video frame. In various embodiments of the method, the metrics include a first metric associated with the first block and a second metric associated with the second block. In various embodiments of the method, determining the perceptual importance of the first block of the input video frame includes: calculating, at an analysis module, a difference between the first metric associated with the first block with the second metric associated with the second block; and comparing the difference with a plurality of difference values located in a look-up table (LUT) that are indicative of perceptual performance. In various embodiments of the method, in response to the difference being less than a first difference value of the plurality of difference values, the method includes identifying the first block as not perceptually important, and in response to the difference being greater than the first difference value, identifying the first block as perceptually important. In various embodiments, other techniques may be used to render the difference value specified above, such as, for example, using an equation or a trained machine to ascertain the difference value and render the significance decision (i.e., perceptually important or not perceptually important).

(42) In various embodiments of the method, responsive to identifying the first block as not perceptually important, the method includes removing the first block from the input video frame, and responsive to identifying the first block as perceptually important, maintaining the first block

in the input video frame. In various embodiments of the method, the first metric and second metric are indicative of at least one of a contrast content, flesh-tone content, memory color content, frequency content, energy content, and motion content of the first block of the input video frame and the second block of the reference frame. In various embodiments, the method further includes generating a control setting indicative of a bit-rate or quality of the first block, the control setting to control the bit-rate of the encoder or the quality of the input video frame provided to the encoder. In various embodiments of the method, the first block and second block each is a macroblock, sub-block, or a locality. In various embodiments of the method, adjusting the entropy includes using a low-pass filter to reduce the entropy on the input video frame. In various embodiments, in removing the first block from the input video frame, highly detailed areas may be removed. In various embodiments, in removing the first block from the input video frame, perceptually flat areas may be removed, which may include areas deemed unimportant, such as, for example, flat walls, etc.

(43) In various embodiments, a method includes: obtaining a plurality of transform coefficients from a transform module; determining, at a transform domain filter, an energy associated with each transform coefficient of the plurality of transform coefficients; and reducing a bandwidth of an encoder based on the energy determination of each transform coefficient of the plurality of the transform coefficients. In various embodiments of the method, reducing the bandwidth of the encoder based on the energy determination includes comparing the energy associated with each transform coefficient of the plurality of transform coefficients to a specified amount of energy in an energy look-up table (LUT). In various embodiments, the method further includes altering at least one of the plurality of transform coefficients to an altered transform coefficient value based on the comparing of the energy associated with each transform coefficient to the specified amount of energy in the energy LUT. In various embodiments, the method further includes using a heuristic algorithm to determine the energy associated with each transform coefficient of the plurality of transform coefficients. In various embodiments of the method, the transform domain filter uses a quality setting to determine whether to reduce the bandwidth. In various embodiments, the method further includes altering at least one of the plurality of transform coefficients to an altered transform coefficient value based on a permissible error amount of the encoder. In various embodiments of the method, a low-pass filter is used to alter the transform coefficient.

(44) In various embodiments, an encoder includes a quantization module, a lossy entropy shaper coupled to the quantization module, and an entropy module coupled to the lossy entropy shaper. The lossy entropy shaper obtains an original set of quantized transform coefficients from the quantization module. The lossy entropy shaper compares an original metric of the original set of quantized transform coefficients to at least a first metric of a first set of altered quantized transform coefficients, and as a result of the comparison, provides either the original set of quantized transform coefficients or the first set of altered quantized transform coefficients, the first set of altered quantized transform coefficients providing a reduced entropy compared to the original set of quantized transform coefficients. In various embodiments of the encoder, the lossy entropy shaper determines a number of quantized transform coefficients that may be adjusted in order to select the first set of altered quantized transform coefficients. In various embodiments of the encoder, the lossy entropy shaper selects at least one of the first set of altered quantized transform coefficients and a second set of quantized altered transform coefficients based on the determination of the number of quantized transform coefficients that may be adjusted. In various embodiments of the encoder, the lossy entropy shaper uses a heuristic algorithm to determine which quantized transform coefficient in the first set of altered quantized transform coefficients to alter.

(45) In various embodiments, an apparatus includes an analysis module, a filter coupled to the analysis module, and an encoder coupled to the filter. The analysis module obtains metrics of a first block of an input video frame and a second block of a reference frame, and based on the metrics, determines a perceptual importance of the first block of the input video frame, the perceptual

importance being used by the filter to adjust an entropy of the input video frame provided to the encoder. In various embodiments of the apparatus, the metrics include a first metric associated with the first block and a second metric associated with the second block. In various embodiments of the apparatus, the perceptual importance of the first block of the input video frame is determined by calculating, at the analysis module, a difference between the first metric associated with the first block with the second metric associated with the second block and comparing the difference with a plurality of difference values located in a look-up table (LUT) that are indicative of perceptual performance.

(46) In various embodiments, if the metrics of the first block are spatial, a reference frame may not be required and the importance map may be determined based on local/spatial metrics. In various embodiments, the metrics may be adaptive and have an associated model that specifies if the region should be filtered or not. The features (or the whole region) may be introduced as input to the model and the model produces strengths of the filter. A direct relationship may not be known between the feature set and the output, but there may be a non-linear relationship based on various parameters, including, for example, the training dataset and the manner in which the model is trained.

(47) In some embodiments, the apparatus and techniques described above are implemented in a system including one or more integrated circuit (IC) devices (also referred to as integrated circuit packages or microchips), such as the encoding system described above with reference to FIGS. 1-6. Electronic design automation (EDA) and computer aided design (CAD) software tools may be used in the design and fabrication of these IC devices. These design tools typically are represented as one or more software programs. The one or more software programs include code executable by a computer system to manipulate the computer system to operate on code representative of circuitry of one or more IC devices so as to perform at least a portion of a process to design or adapt a manufacturing system to fabricate the circuitry. This code can include instructions, data, or a combination of instructions and data. The software instructions representing a design tool or fabrication tool typically are stored in a computer readable storage medium accessible to the computing system. Likewise, the code representative of one or more phases of the design or fabrication of an IC device may be stored in and accessed from the same computer readable storage medium or a different computer readable storage medium.

(48) A computer readable storage medium may include any non-transitory storage medium, or combination of non-transitory storage media, accessible by a computer system during use to provide instructions and/or data to the computer system. Such storage media can include, but is not limited to, optical media (e.g., compact disc (CD), digital versatile disc (DVD), Blu-Ray disc), magnetic media (e.g., floppy disc, magnetic tape, or magnetic hard drive), volatile memory (e.g., random access memory (RAM) or cache), non-volatile memory (e.g., read-only memory (ROM) or Flash memory), or microelectromechanical systems (MEMS)-based storage media. The computer readable storage medium may be embedded in the computing system (e.g., system RAM or ROM), fixedly attached to the computing system (e.g., a magnetic hard drive), removably attached to the computing system (e.g., an optical disc or Universal Serial Bus (USB)-based Flash memory), or coupled to the computer system via a wired or wireless network (e.g., network accessible storage (NAS)).

(49) In some embodiments, certain aspects of the techniques described above may implemented by one or more processors of a processing system executing software. The software includes one or more sets of executable instructions stored or otherwise tangibly embodied on a non-transitory computer readable storage medium. The software can include the instructions and certain data that, when executed by the one or more processors, manipulate the one or more processors to perform one or more aspects of the techniques described above. The non-transitory computer readable storage medium can include, for example, a magnetic or optical disk storage device, solid state storage devices such as Flash memory, a cache, random access memory (RAM) or other non-

volatile memory device or devices, and the like. The executable instructions stored on the non-transitory computer readable storage medium may be in source code, assembly language code, object code, or other instruction format that is interpreted or otherwise executable by one or more processors.

(50) Note that not all of the activities or elements described above in the general description are required, that a portion of a specific activity or device may not be required, and that one or more further activities may be performed, or elements included, in addition to those described. Still further, the order in which activities are listed are not necessarily the order in which they are performed. Also, the concepts have been described with reference to specific embodiments. However, one of ordinary skill in the art appreciates that various modifications and changes can be made without departing from the scope of the present disclosure as set forth in the claims below. Accordingly, the specification and figures are to be regarded in an illustrative rather than a restrictive sense, and all such modifications are intended to be included within the scope of the present disclosure.

(51) Benefits, other advantages, and solutions to problems have been described above with regard to specific embodiments. However, the benefits, advantages, solutions to problems, and any feature(s) that may cause any benefit, advantage, or solution to occur or become more pronounced are not to be construed as a critical, required, or essential feature of any or all the claims. Moreover, the particular embodiments disclosed above are illustrative only, as the disclosed subject matter may be modified and practiced in different but equivalent manners apparent to those skilled in the art having the benefit of the teachings herein. No limitations are intended to the details of construction or design herein shown, other than as described in the claims below. It is therefore evident that the particular embodiments disclosed above may be altered or modified and all such variations are considered within the scope of the disclosed subject matter. Accordingly, the protection sought herein is as set forth in the claims below.

Claims

1. A method, comprising: obtaining, at a data reduction module, metrics of a first block of an input video frame to be an input to an encoder and a second block of an encoding reference frame, the encoding reference frame being fed back to the data reduction module from a quantization module of the encoder; determining, at the data reduction module, a perceptual importance of the first block of the input video frame to be an input to the encoder using the metrics; and adjusting, at the data reduction module, an entropy of the input video frame to be an input to the encoder based on the perceptual importance of the first block of the input video frame to be an input to the encoder.
2. The method of claim 1, wherein: the metrics include a first metric associated with the first block and a second metric associated with the second block.
3. The method of claim 2, wherein: determining the perceptual importance of the first block of the input video frame to be an input to the encoder comprises: calculating, at an analysis module, a difference between the first metric associated with the first block with the second metric associated with the second block; and comparing the difference with a plurality of difference values indicative of perceptual performance.
4. The method of claim 3, wherein: in response to the difference being less than a first difference value of the plurality of difference values, identifying the first block as not perceptually important, and in response to the difference being greater than the first difference value, identifying the first block as perceptually important.
5. The method of claim 4, wherein: responsive to identifying the first block as not perceptually important, removing the first block from the input video frame to be an input to the encoder, and responsive to identifying the first block as perceptually important, maintaining the first block in the input video frame to be an input to the encoder.

6. The method of claim 2, wherein: the first metric and second metric are indicative of at least one of a contrast content, flesh-tone content, memory color content, frequency content, energy content, and motion content of the first block of the input video frame to be an input to the encoder and the second block of the encoding reference frame.
7. The method of claim 1, further comprising: generating a control setting indicative of a bit-rate or quality of the first block, the control setting to control the bit-rate of the encoder or the quality of the input video frame to be an input to the encoder.
8. The method of claim 1, wherein: the first block and second block each is a macroblock, sub-block, or a locality.
9. The method of claim 2, wherein: adjusting the entropy comprises using a low-pass filter to reduce the entropy on the input video frame to be an input to the encoder.
10. A method, comprising: obtaining a plurality of transform coefficients from a transform module; determining, at a transform domain filter, an energy indicating a visual importance of video content associated with each transform coefficient of the plurality of transform coefficients; providing altered transform coefficients to a quantization module from the transform domain filter; and reducing a bandwidth of an encoder based on the energy determination of each transform coefficient of the plurality of the transform coefficients.
11. The method of claim 10, wherein: reducing the bandwidth of the encoder based on the energy determination comprises: comparing the energy associated with each transform coefficient of the plurality of transform coefficients to a specified amount of energy.
12. The method of claim 11, further comprising: altering at least one of the plurality of transform coefficients to an altered transform coefficient value based on the comparing of the energy associated with each transform coefficient to the specified amount of energy.
13. The method of claim 11, further comprising: using a heuristic algorithm to determine the energy associated with each transform coefficient of the plurality of transform coefficients.
14. The method of claim 11, wherein: the transform domain filter uses a quality setting to determine whether to reduce the bandwidth.
15. The method of claim 11, further comprising: altering at least one of the plurality of transform coefficients to an altered transform coefficient value based on a permissible error amount of the encoder.
16. The method of claim 11, wherein: a low-pass filter is used to alter the transform coefficient.
17. An encoder, comprising: a quantization module; a lossy entropy shaper coupled to the quantization module, the lossy entropy shaper obtaining an original set of quantized transform coefficients from the quantization module; and an entropy module coupled to the lossy entropy shaper, wherein the lossy entropy shaper compares an original metric of the original set of quantized transform coefficients to at least a first metric of a first set of altered quantized transform coefficients, and as a result of the comparison, provides either the original set of quantized transform coefficients or the first set of altered quantized transform coefficients, the first set of altered quantized transform coefficients providing a reduced entropy compared to the original set of quantized transform coefficients.
18. The encoder of claim 17, wherein: the lossy entropy shaper determines a number of quantized transform coefficients that may be adjusted in order to select the first set of altered quantized transform coefficients.
19. The encoder of claim 18, wherein: the lossy entropy shaper selects at least one of the first set of altered quantized transform coefficients and a second set of quantized altered transform coefficients based on the determination of the number of quantized transform coefficients that may be adjusted.
20. The encoder of claim 19, wherein: the lossy entropy shaper uses a heuristic algorithm to determine which quantized transform coefficient in the first set of altered quantized transform coefficients to alter.
21. An apparatus, comprising: an analysis module; a filter coupled to the analysis module; and an

encoder coupled to the filter, wherein the analysis module obtains metrics of a first block of an input video frame to be an input to the encoder and a second block of an encoding reference frame, the encoding reference frame being fed back to the analysis module from a quantization module of the encoder and based on the metrics, determines a perceptual importance of the first block of the input video frame to be an input to the encoder, the perceptual importance being used by the filter to adjust an entropy of the input video frame to be input to the encoder.

22. The apparatus of claim 21, wherein: the metrics include a first metric associated with the first block and a second metric associated with the second block.

23. The apparatus of claim 22, wherein: the perceptual importance of the first block of the input video frame to be input to the encoder is determined by calculating, at the analysis module, a difference between the first metric associated with the first block with the second metric associated with the second block and comparing the difference with a plurality of difference values indicative of perceptual performance.
