

US Patent & Trademark Office

Patent Public Search | Text View

United States Patent	12400811
Kind Code	B2
Date of Patent	August 26, 2025
Inventor(s)	Dimberg; Chris

Retrofit remote control device

Abstract

A control device may be configured to be mounted over a bezel portion of an electrical device and to control a lighting load. The control device may comprise a base portion having planar extensions removably attached or affixed thereto. The planar extensions may be adapted to be received in a gap between a faceplate of the electrical device and the bezel portion for holding the control device against the faceplate. The planar extensions may comprise barbs that allow for insertion of the extensions in the gap, and may bite into the faceplate to hinder removal of the control device. The planar extensions may be defined by a mounting structure that is configured to be received in the gap between the bezel portion and the faceplate. The mounting structure may protrude beyond a front surface of the faceplate.

Inventors:	Dimberg; Chris (Easton, PA)
Applicant:	Lutron Technology Company LLC (Coopersburg, PA)
Family ID:	1000008780002
Assignee:	Lutron Technology Company LLC (Coopersburg, PA)
Appl. No.:	18/737084
Filed:	June 07, 2024

Prior Publication Data

Document Identifier	Publication Date
US 20240321536 A1	Sep. 26, 2024

Related U.S. Application Data

continuation parent-doc US 18144489 20230508 US 12040142 child-doc US 18737084
continuation parent-doc US 17553910 20211217 US 11682534 20230620 child-doc US 18144489
continuation parent-doc US 17072972 20201016 US 11251002 20220215 child-doc US 17553910
continuation parent-doc US 16777365 20200130 US 10832880 20201110 child-doc US 17072972

continuation parent-doc US 16257134 20190125 US 10586667 20200310 child-doc US 16777365
continuation parent-doc US 15612130 20170602 US 10211013 20190219 child-doc US 16257134
us-provisional-application US 62356053 20160629
us-provisional-application US 62345485 20160603

Publication Classification

Int. Cl.: **H01H23/14** (20060101); **G08C17/02** (20060101); **H01H3/02** (20060101); **H01H19/14** (20060101); **H05B47/19** (20200101)

U.S. Cl.:

CPC **H01H23/145** (20130101); **G08C17/02** (20130101); **H01H3/02** (20130101); **H05B47/19** (20200101); **H01H19/14** (20130101)

Field of Classification Search

USPC: None

References Cited

U.S. PATENT DOCUMENTS

Patent No.	Issued Date	Patentee Name	U.S. Cl.	CPC
5264761	12/1992	Johnson et al.	N/A	N/A
5905442	12/1998	Mosebrook et al.	N/A	N/A
7573208	12/2008	Newman et al.	N/A	N/A
7834856	12/2009	Grinshpoon et al.	N/A	N/A
7940167	12/2010	Steiner et al.	N/A	N/A
8009042	12/2010	Steiner et al.	N/A	N/A
8084700	12/2010	Massaro et al.	N/A	N/A
8167457	12/2011	Forster et al.	N/A	N/A
8199010	12/2011	Sloan et al.	N/A	N/A
8330638	12/2011	Altonen et al.	N/A	N/A
8410706	12/2012	Steiner et al.	N/A	N/A
8445779	12/2012	Gretz	174/53	H02G 3/123
8451116	12/2012	Steiner et al.	N/A	N/A
8917024	12/2013	Kessler et al.	N/A	N/A
9208965	12/2014	Busby et al.	N/A	N/A
D761277	12/2015	Harvell	N/A	N/A
9418802	12/2015	Romano et al.	N/A	N/A
9520247	12/2015	Finnegan et al.	N/A	N/A
9583288	12/2016	Jones et al.	N/A	N/A
9746138	12/2016	Thomas et al.	N/A	N/A
9799469	12/2016	Bailey et al.	N/A	N/A
9959997	12/2017	Bailey et al.	N/A	N/A
2003/0019733	12/2002	Sato	N/A	N/A
2003/0019734	12/2002	Sato et al.	N/A	N/A
2003/0230982	12/2002	Pagano et al.	N/A	N/A
2008/0111491	12/2007	Spira et al.	N/A	N/A

2008/0315798	12/2007	Diederiks et al.	N/A	N/A
2009/0206983	12/2008	Knode et al.	N/A	N/A
2009/0256483	12/2008	Gehman et al.	N/A	N/A
2010/0084996	12/2009	Van De Sluis et al.	N/A	N/A
2010/0127626	12/2009	Altonen et al.	N/A	N/A
2010/0244706	12/2009	Steiner et al.	N/A	N/A
2010/0244709	12/2009	Steiner et al.	N/A	N/A
2011/0139965	12/2010	Sloan et al.	N/A	N/A
2011/0259722	12/2010	Alderson et al.	N/A	N/A
2012/0292174	12/2011	Mah et al.	N/A	N/A
2013/0099011	12/2012	Matsuoka et al.	N/A	N/A
2013/0099124	12/2012	Filson et al.	N/A	N/A
2013/0222122	12/2012	Killo et al.	N/A	N/A
2013/0338839	12/2012	Rogers et al.	N/A	N/A
2014/0117859	12/2013	Swatsky et al.	N/A	N/A
2014/0117871	12/2013	Swatsky et al.	N/A	N/A
2014/0138235	12/2013	Savicki, Jr.	200/558	H01H 23/168
2014/0145646	12/2013	Zhang et al.	N/A	N/A
2014/0152186	12/2013	Zhang	N/A	N/A
2014/0266669	12/2013	Fadell et al.	N/A	N/A
2015/0077021	12/2014	McCarthy et al.	N/A	N/A
2015/0189725	12/2014	Karc et al.	N/A	N/A
2015/0294816	12/2014	Evers et al.	N/A	N/A
2015/0371534	12/2014	Dimberg et al.	N/A	N/A
2016/0007431	12/2015	Bosua et al.	N/A	N/A
2016/0073479	12/2015	Erchak et al.	N/A	N/A
2016/0111813	12/2015	Ye	N/A	N/A
2017/0105176	12/2016	Finnegan et al.	N/A	N/A
2017/0226799	12/2016	Hebeisen et al.	N/A	N/A
2017/0278652	12/2016	Dimberg et al.	N/A	N/A
2018/0190451	12/2017	Scruggs	N/A	N/A

FOREIGN PATENT DOCUMENTS

Patent No.	Application Date	Country	CPC
2596671	12/2002	CN	N/A
101347050	12/2008	CN	N/A
102293060	12/2010	CN	N/A
202940744	12/2012	CN	N/A
203491998	12/2013	CN	N/A
204005375	12/2013	CN	N/A
2014066269	12/2013	WO	N/A
2017165858	12/2016	WO	N/A

Primary Examiner: Dsouza; Adolf

Attorney, Agent or Firm: Flaster Greenberg PC

Background/Summary

CROSS-REFERENCE TO RELATED APPLICATIONS (1) This application is a continuation of U.S. patent application Ser. No. 18/144,489, filed May 8, 2023, which is a continuation of U.S. patent application Ser. No. 17/553,910, filed Dec. 17, 2021, now U.S. Pat. No. 11,682,534, issued on Jun. 20, 2023, which is a continuation of U.S. patent application Ser. No. 17/072,972, filed Oct. 16, 2020, now U.S. Pat. No. 11,251,002, issued on Feb. 15, 2022, which is a continuation of U.S. patent application Ser. No. 16/777,365, filed Jan. 30, 2020, now U.S. Pat. No. 10,832,880, issued on Nov. 10, 2020, which is a continuation of U.S. patent application Ser. No. 16/257,134, filed Jan. 25, 2019, now U.S. Pat. No. 10,586,667, issued on Mar. 10, 2020, which is a continuation of U.S. patent application Ser. No. 15/612,130, filed Jun. 2, 2017, now U.S. Pat. No. 10,211,013, issued on Feb. 19, 2019, which claims the benefit of U.S. Provisional Patent Application No. 62/345,485, filed Jun. 3, 2016, and U.S. Provisional Patent Application No. 62/356,053, filed Jun. 29, 2016, the entire disclosures of which are incorporated by reference herein.

BACKGROUND

- (1) A standard switch (e.g., a mechanical toggle switch) in a load control system may be replaced by a load control device (e.g., a dimmer switch). Such a load control device may operate to control an amount of power delivered from an alternative current (AC) power source to an electrical load.
- (2) The procedure of replacing a standard switch (e.g., a mechanical toggle switch) with a load control device typically requires disconnecting electrical wiring, removing the standard switch from an electrical wallbox, installing the load control device into the wallbox, and reconnecting the electrical wiring to the load control device.
- (3) Often, the aforementioned procedure is performed by an electrical contractor or other skilled installer. Average consumers may not feel comfortable undertaking the electrical wiring to complete installation of a load control device. Accordingly, there is a demand for a load control device that may be installed into an existing electrical system (e.g., a system with a standard mechanical toggle switch), with limited or no electrical wiring work.

SUMMARY

- (4) As described herein, a remote control device may provide a simple retrofit solution for an existing switched control system. Implementation of the remote control device, for example in an existing switched control system, may enable energy savings and/or advanced control features, for example without requiring any electrical re-wiring and/or without requiring the replacement of any existing mechanical switches.
- (5) The remote control device may be configured to associate with, and control, a load control device of a load control system, without requiring access to the electrical wiring of the load control system. An electrical load may be electrically connected to the load control device such that the remote control device may control an amount of power delivered to the electrical load, via the load control device. When the electrical load is a lighting load, the remote control device may also control a color of the lighting load.
- (6) The remote control device may be configured to be mounted over the toggle actuator of a mechanical switch that controls whether power is delivered to the electrical load. The remote control device may be configured to maintain the toggle actuator in an on position when mounted over the toggle actuator, such that a user of the remote control device is not able to mistakenly switch the toggle actuator to the off position, which may cause the electrical load to be unpowered such that the electrical load cannot be controlled by one or more remote control devices.
- (7) The remote control device may include a base portion that is configured to be mounted over the toggle actuator of the switch, and a control portion that is supported by the base portion. The remote control device may be configured such that the base portion does not actuate the actuator of the electrical load when a force is applied to the control portion.
- (8) The remote control device may include a wireless communication circuit for transmitting and/or receiving wireless control signals to and/or from the electrical load. The wireless control signals

may carry commands for controlling one or more operational settings of the electrical load.

(9) The remote control device may comprise a base portion having planar extensions adapted to be received in a gap between the faceplate and the toggle actuator for holding the remote control device against the faceplate. The extensions may comprise barbs that allow for insertion of the extensions in the gap, but may bite into the faceplate to hinder removal of the remote control device.

(10) The planar extensions may be removably attached to a base portion of the remote control device. For example, the planar extensions may be defined by a mounting structure. The mounting structure may be configured to be disposed between a yoke of the mechanical switch and the faceplate, and that protrudes beyond a front surface of the faceplate. The planar extensions may define engagement members that are configured to engage with complimentary features of the base portion to secure the base portion in an attached position relative to the mechanical switch.

Description

BRIEF DESCRIPTION OF THE DRAWINGS

(1) FIG. 1 depicts an example load control system that includes an example remote control device.

(2) FIGS. 2 and 3 are perspective views of an example remote control device.

(3) FIG. 4 is a front view of the example remote control device illustrated in FIGS. 2 and 3.

(4) FIG. 5 is a right side view of the example remote control device illustrated in FIGS. 2 and 3.

(5) FIG. 6 shows a perspective view of the example remote control device with a control module detached from a base portion.

(6) FIG. 7 is a front perspective view of the example remote control device illustrated in FIGS. 2 and 3, with the remote control device unmounted from the light switch.

(7) FIG. 8 is a rear perspective view of the example remote control device illustrated in FIGS. 2 and 3, with the remote control device unmounted from the light switch.

(8) FIG. 9 is a front view of the example remote control device illustrated in FIGS. 2 and 3, with the remote control device unmounted from the light switch.

(9) FIG. 10 is a right side view of the example remote control device illustrated in FIGS. 2 and 3, with the remote control device unmounted from the light switch.

(10) FIG. 11 is a bottom view of the example remote control device illustrated in FIGS. 2 and 3, with the remote control device unmounted from the light switch.

(11) FIG. 12 is a rear view of the example remote control device illustrated in FIGS. 2 and 3, with the remote control device unmounted from the light switch.

(12) FIG. 13 is a left side sectional view of the example remote control device illustrated in FIGS. 2 and 3.

(13) FIG. 14 is an enlarged portion of the sectional view depicted in FIG. 13.

(14) FIG. 15 is a right side sectional view of the example remote control device illustrated in FIGS. 2 and 3.

(15) FIG. 16 is an enlarged portion of the sectional view depicted in FIG. 15.

(16) FIG. 17 is a bottom sectional view of the example remote control device illustrated in FIGS. 2 and 3.

(17) FIG. 18 is an enlarged portion of the sectional view depicted in FIG. 17.

(18) FIG. 19 is a perspective view of another example remote control device.

(19) FIG. 20 is a perspective view of the example remote control device illustrated in FIG. 19, with a control module of the remote control device detached.

(20) FIG. 21 is a partially exploded view of the example remote control device illustrated in FIG. 19.

(21) FIG. 22 shows a perspective view of another example remote control device.

(22) FIG. 23 shows a perspective view of the example remote control device of FIG. 22 with a control module detached from a base portion.

(23) FIG. 24 shows a rear view of the control module depicted in FIG. 23.

(24) FIG. 25 shows a simplified equivalent schematic diagram of an example control module for the example remote control devices depicted in FIGS. 2, 19, and 22.

DETAILED DESCRIPTION

(25) FIG. 1 depicts an example load control system **100**. As shown, the load control system **100** may be configured as a lighting control system that may include an electrical load (e.g., such as a controllable light source **110**), and a remote control device **120** (e.g., such as a battery-powered rotary remote control device). The remote control device **120** may include a wireless transmitter (e.g., a radio frequency (RF) transmitter). The load control system **100** may include a standard, single pole single throw (SPST) maintained mechanical switch **104** (e.g., a toggle switch, a paddle switch, a pushbutton switch, a “light switch,” or other suitable switch). The switch **104** may be in place prior to installation of the remote control device **120** (e.g., pre-existing in the load control system **100**). The switch **104** may be electrically coupled (e.g., in series) between an alternating current (AC) power source **102** and the controllable light source **110**. The switch **104** may include a toggle actuator **106** that may be actuated to toggle (e.g., to turn on and/or turn off) the controllable light source **110**. The controllable light source **110** may be electrically coupled to the AC power source **102** when the switch **104** is closed (e.g., conductive), and may be disconnected from the AC power source **102** when the switch **104** is open (e.g., nonconductive).

(26) The remote control device **120** may be operable to transmit wireless signals, for example radio frequency (RF) signals **108**, to the controllable light source **110**. The wireless signals may be used to control the intensity of the controllable light source **110**. The wireless signals may be used to control the color of the light emitted by the controllable light source **110**. The controllable light source **110** may be associated with the remote control device **120** (e.g., during a configuration procedure of the load control system **100**) such that the controllable light source **110** may be responsive to the RF signals **108** transmitted by the remote control device **120**. An example of a configuration procedure for associating a remote control device with a load control device is described in greater detail in commonly-assigned U.S. Patent Publication No. 2008/0111491, published May 15, 2008, entitled “Radio-Frequency Lighting Control System,” the entire disclosure of which is hereby incorporated by reference.

(27) The controllable light source **110** may include an internal lighting load (not shown), such as, for example, a light-emitting diode (LED) light engine, a compact fluorescent lamp, an incandescent lamp, a halogen lamp, or other suitable light sources. The controllable light source **110** may include a housing **112**. The housing **112** may comprise an end portion **114** through which light emitted from the lighting load may shine. The controllable light source **110** may include an enclosure **115** configured to house one or more electrical components of the controllable light source **110** (e.g., such as an integral load control circuit (not shown)). The one or more electrical components may be operable to control the intensity of the lighting load between a low-end intensity (e.g., approximately 1%) and a high-end intensity (e.g., approximately 100%). The one or more electrical components may be operable to control the color of the light emitted by the controllable light source **110**. For example, when the controllable light source **110** is an LED light source, the one or more electrical components may be operable to control the color of the LED in a color temperature control mode or a full-color control mode.

(28) The controllable light source **110** may include a wireless communication circuit (not shown) housed inside the enclosure **115**, such that the controllable light source **110** may be operable to receive the RF signals **108** transmitted by the remote control device **120**, and to control the intensity and/or color of the lighting load in response to the received RF signals. The enclosure **115** may be attached to the housing **112** (e.g., as shown in FIG. 1). The enclosure **115** may be integral with (e.g., monolithic with) the housing **112**, such that the enclosure **115** may define an enclosure

portion of the housing **112**. The controllable light source **110** may include a screw-in base **116** configured to be screwed into a standard Edison socket, such that the controllable light source may be coupled to the AC power source **102**. The controllable light source **110** may be configured as a downlight (e.g., as shown in FIG. **1**) that may be installed in a recessed light fixture. The controllable light source **110** may not be limited to the illustrated screw-in base **116**, and may include any suitable base (e.g., a bayonet-style base or other suitable base providing electrical connections).

(29) As described herein, the switch **104** may be in place prior to installation of the remote control device **120** (e.g., pre-existing in the load control system **100**). The switch **104** may be configured to perform simple tasks such as turning on and/or turning off (e.g., via the toggle actuator **106**) the controllable light source **110**. An example purpose of the remote control device **120** may be to allow a user to control additional aspects of the controllable light source **110** (e.g., such as light intensity and color). Another example purpose of the remote control device **120** may be to provide a user with feedback regarding the type and/or outcome of the control exercised by the user. As described herein, both of the foregoing purposes may be fulfilled with limited or no additional electrical wiring work.

(30) The remote control device **120** may be configured to be mounted over the toggle actuator **106** of the switch **104**. For example, the remote control device **120** may be mounted over the toggle actuator **106** when it is in the on position and when the switch **104** is closed and conductive. As shown in FIG. **1**, the remote control device **120** may include a control portion **122** (e.g., including one or more actuators, a rotating portion, and/or a touch sensitive surface) and a base portion **124**. The base portion **124** may be configured to be mounted over the toggle actuator **106** of the switch **104**, and the control portion **122** may be supported by the base portion **124**. The base portion **124** may be configured to maintain the toggle actuator **106** in the on position. In this regard, the base portion **124** may be configured such that a user is not able to inadvertently switch the toggle actuator **106** to the off position when the remote control device **120** is attached to the switch **104**. Greater detail of examples of the remote control device **120** will be provided herein, after a brief discussion of other components that may be included in the load control system **100**.

(31) The load control system **100** may include one or more other devices configured to communicate (e.g., wirelessly communicate) with the controllable light source **110**. For example, the load control system **100** may include a battery-powered, remote control device **130** (e.g., as shown in FIG. **1**) for controlling the controllable light source **110**. The remote control device **130** may include one or more buttons, for example, an on button **132**, an off button **134**, a raise button **135**, a lower button **136**, and a preset button **138**, as shown in FIG. **1**. The remote control device **130** may include a wireless communication circuit (not shown) for transmitting digital messages (e.g., including commands to control the light source **110**) to the controllable light source **110** (e.g., via the RF signals **108**) responsive to actuations of one or more of the buttons **132**, **134**, **135**, **136**, and **138**. The remote control device **130** may be handheld or mounted to a wall or supported by a pedestal (e.g., a pedestal configured to be mounted on a tabletop). Examples of battery-powered remote controls are described in greater detail in commonly assigned U.S. Pat. No. 8,330,638, issued Dec. 11, 2012, entitled "Wireless Battery Powered Remote Control Having Multiple Mounting Means," and U.S. Pat. No. 7,573,208, issued Aug. 11, 2009, entitled "Method Of Programming A Lighting Preset From A Radio-Frequency Remote Control," the entire disclosures of which are hereby incorporated by reference.

(32) The load control system **100** may include one or more of a remote occupancy sensor or a remote vacancy sensor (not shown) for detecting occupancy and/or vacancy conditions in a space surrounding the sensors. The occupancy or vacancy sensors may be configured to transmit digital messages to the controllable light source **110**, for example via the RF signals **108**, in response to detecting occupancy or vacancy conditions. Examples of RF load control systems having occupancy and vacancy sensors are described in greater detail in commonly-assigned U.S. Pat. No.

7,940,167, issued May 10, 2011, entitled “Battery Powered Occupancy Sensor,” U.S. Pat. No. 8,009,042, issued Aug. 30, 2011, entitled “Radio Frequency Lighting Control System With Occupancy Sensing,” and U.S. Pat. No. 8,199,010, issued Jun. 12, 2012, entitled “Method And Apparatus For Configuring A Wireless Sensor,” the entire disclosures of which are hereby incorporated by reference.

(33) The load control system **100** may include a remote daylight sensor (not shown) for measuring a total light intensity in the space around the daylight sensor. The daylight sensor may be configured to transmit digital messages, such as a measured light intensity, to the controllable light source **110**, for example via the RF signals **108**, such that the controllable light source **110** is operable to control the intensity of the lighting load in response to the measured light intensity. Examples of RF load control systems having daylight sensors are described in greater detail in commonly assigned U.S. Pat. No. 8,451,116, issued May 28, 2013, entitled “Wireless Battery-Powered Daylight Sensor,” and U.S. Pat. No. 8,410,706, issued Apr. 2, 2013, entitled “Method Of Calibrating A Daylight Sensor,” the entire disclosures of which are hereby incorporated by reference.

(34) The load control system **100** may include other types of devices capable of communicating signals for load control, for example, radiometers, cloudy-day sensors, temperature sensors, humidity sensors, pressure sensors, smoke detectors, carbon monoxide detectors, air-quality sensors, security sensors, proximity sensors, fixture sensors, partition sensors, keypads, kinetic or solar-powered remote controls, key fobs, cell phones, smart phones, tablets, personal digital assistants, personal computers, laptops, time clocks, audio-visual controls, safety devices, power monitoring devices (such as power meters, energy meters, utility submeters, utility rate meters), central control transmitters, residential, commercial, or industrial controllers, or any combination of these devices.

(35) The controllable light source **110** may be associated with a wireless control device (e.g., the remote control device **120**) during a configuration procedure of the load control system **100**. For example, the association may be accomplished by actuating an actuator on the controllable light source **110** and actuating (e.g., pressing and holding) an actuator on the wireless remote control device (e.g., a rotating portion **222** of a control module **220** shown in FIG. 3) for a predetermined amount of time (e.g., approximately 10 seconds).

(36) Digital messages transmitted by the remote control device **120** (e.g., messages directed to the controllable light source **110**) may include a command and identifying information, such as a unique identifier (e.g., a serial number) associated with the remote control device **120**. After being associated with the remote control device **120**, the controllable light source **110** may be responsive to messages containing the unique identifier of the remote control device **120**. The controllable light source **110** may be associated with one or more other wireless control devices of the load control system **100** (e.g., the remote control device **130**, the occupancy sensor, the vacancy sensor, and/or the daylight sensor), for example using similar association process.

(37) After a remote control device (e.g., the remote control device **120** or the remote control device **130**) is associated with the controllable light source **110**, the remote control device may be used to associate the controllable light source **110** with the occupancy sensor, the vacancy sensor, and/or the daylight sensor (e.g., without actuating the actuator **118** of the controllable light source **110**). Examples for associating an electrical load with one or more sensors are described in greater detail in commonly-assigned U.S. Patent Application Publication No. 2013/0222122, published Aug. 29, 2013, entitled “Two Part Load Control System Mountable To A Single Electrical Wallbox,” the entire disclosure of which is hereby incorporated by reference.

(38) In an example configuration, the remote control device **120** may be mounted over a toggle actuator of a switch (e.g., the toggle actuator **106**). In such a configuration, the base portion **124** may function to secure the toggle actuator **106** from being toggled. For example, the base portion **124** may be configured to maintain the toggle actuator **106** in an on position, such that a user of the

remote control device **120** is not able to mistakenly switch the toggle actuator **106** to the off position (which may disconnect the controllable light source **110** from the AC power source **102**). Maintaining the toggle actuator **106** in the on position may also prevent the controllable light source **110** from being controlled by one or more remote control devices of the load control system **100** (e.g., the remote control devices **120** and/or **130**), which may cause user confusion.

(39) The remote control device **120** may be battery-powered (e.g., not wired in series electrical connection between the AC power source **102** and the controllable light source **110**). Since the mechanical switch **104** is kept closed (e.g., conductive), the controllable light source **110** may continue to receive a full AC voltage waveform from the AC power source **102** (e.g., the controllable light source **110** does not receive a phase-control voltage that may be created by a standard dimmer switch). Because the controllable light source **110** receives the full AC voltage waveform, multiple controllable light sources (e.g., more than one controllable light sources **110**) may be coupled in parallel on a single electrical circuit (e.g., coupled to the mechanical switch **104**). The multiple controllable light sources may include light sources of different types (e.g., incandescent lamps, fluorescent lamps, and/or LED light sources). The remote control device **120** may be configured to control one or more of the multiple controllable light sources, for example substantially in unison. In addition, if there are multiple controllable light sources coupled in parallel on a single circuit, each controllable light source may be zoned, for example to provide individual control of each controllable light source. For example, a first controllable light **110** source may be controlled by the remote control device **120**, while a second controllable light source **110** may be controlled by the remote control device **130**.

(40) The remote control device **120** may be part of a larger RF load control system than that depicted in FIG. **1**. Examples of RF load control systems are described in commonly-assigned U.S. Pat. No. 5,905,442, issued on May 18, 1999, entitled “Method And Apparatus For Controlling And Determining The Status Of Electrical Devices From Remote Locations,” and commonly-assigned U.S. Patent Application Publication No. 2009/0206983, published Aug. 20, 2009, entitled “Communication System For A Radio Frequency Load Control System,” the entire disclosures of which are incorporated herein by reference.

(41) While the load control system **100** was described with reference to the single-pole system shown in FIG. **1**, one or both of the controllable light source **110** and the remote control device **120** may be implemented in a “three-way” lighting system having two single-pole double-throw (SPDT) mechanical switches (e.g., a “three-way” switch) for controlling a single electrical load. For example, the system could comprise two remote control devices **120**, with one remote control device **120** connected to the toggle actuator of each SPDT switch. The toggle actuators of the respective SPDT switches may be positioned such that the SPDT switches form a complete circuit between the AC source and the electrical load before the remote control devices **120** are installed on the toggle actuators.

(42) The load control system **100** shown in FIG. **1** may provide a retrofit solution for an existing load control system. The load control system **100** may provide energy savings and/or advanced control features, for example without requiring significant electrical re-wiring and/or without requiring the replacement of existing mechanical switches. As an example, to install and use the load control system **100** of FIG. **1**, a consumer may replace an existing lamp with the controllable light source **110**, switch the toggle actuator **106** of the mechanical switch **104** to the on position, install (e.g., mount) the remote control device **120** onto the toggle actuator **106**, and associate the remote control device **120** with the controllable light source **110**, as described herein.

(43) It should be appreciated that the load control system **100** is not limited to including the controllable light source **110**. For example, in lieu of the controllable light source **110**, the load control system **100** may alternatively include a plug-in load control device for controlling an external lighting load. For example, the plug-in load control device may be configured to be plugged into a receptacle of a standard electrical outlet that is electrically connected to an AC

power source. The plug-in load control device may have one or more receptacles to which one or more plug-in electrical loads (e.g., a table lamp or a floor lamp) may be plugged. The plug-in load control device may be configured to control the intensity and/or light color of the lighting loads plugged into the receptacles of the plug-in load control device. It should further be appreciated that the remote control device **120** is not limited to being associated with, and controlling, a single load control device. For example, the remote control device **120** may be configured to control multiple controllable load control devices (e.g., substantially in unison).

(44) Examples of remote control devices configured to be mounted over existing switches (e.g., light switches) are described in greater detail in commonly-assigned U.S. Patent Application Publication No. 2014/0117871, published May 1, 2014, and U.S. Patent Application Publication No. 2015/0371534, published Dec. 24, 2015, both entitled “Battery-Powered Retrofit Remote Control Device,” the entire disclosures of which are hereby incorporated by reference.

(45) FIGS. **2-8** depict an example remote control device **200** (e.g., a battery-powered remote control device) that may be deployed as the remote control device **120** of the load control system **100** shown in FIG. **1**. The remote control device **200** may be configured to be mounted over an actuator (e.g., a paddle actuator) of a standard light switch, such as the paddle actuator **204** of a standard decorator paddle style light switch **202** shown in FIG. **6**. As shown, the paddle actuator **204** may be surrounded by a bezel portion **205**. The light switch **202** may include a faceplate **206**. The faceplate **206** may define an opening **208** (e.g., a decorator-type opening) that extends therethrough. The faceplate **206** may be mounted via faceplate screws **209**, for instance to a yoke (not shown) of the switch **202**. The standard light switch **202** may be coupled in series electrical connection between an alternating current (AC) power source and one or more electrical loads.

(46) As shown, the remote control device **200** may include a base portion **212** and an actuation portion **210** that is configured to be mounted to the base portion **212**. The actuation portion **210** may include an actuator **211**. The actuator **211** may comprise a front surface **214** that defines a user interface of the actuation portion **210**. As shown, the actuator **211** may be configured such that the front surface **214** includes an upper portion **216** and a lower portion **218**. The actuation portion **210** may include a light bar **220** that is configured to visibly display information at the front surface **214**. The base portion **212** of the remote control device **200** may be mounted over the paddle actuator **204** of the light switch **202** when the paddle actuator is in the on position.

(47) The actuation portion **210** may be configured for mechanical actuation of the actuator **211**. For example, the actuator **211** may be supported about a pivot axis **P1** that extends laterally between the upper and lower portions **216**, **218**. The actuation portion **210** may include mechanical switches **260** (e.g., as shown in FIG. **35**) disposed in respective interior portions of the actuator **211** that correspond to the upper and lower portions **216**, **218** of the front surface **214**. Actuations of the upper portion **216** of the front surface **214**, for example via the application of a force to the upper portion **216** (e.g., resulting from a finger press) may cause the actuator **211** to rotate about the pivot axis **P1** such that the upper portion **216** moves inward towards the base portion **212** and actuates a corresponding mechanical switch **260**. Actuations of the lower portion **218** of the front surface **214**, for example via the application of a force to the lower portion **218** (e.g., resulting from a finger press) may cause the actuator **211** to rotate about the pivot axis **P1** such that the lower portion **218** moves inward towards the base portion **212** and actuates a corresponding mechanical switch **260**. The actuation portion **210** may be configured such that actuations of actuator **211** are tactile actuations. For instance, actuations of the actuator **211** may provide tactile feedback to a user of the remote control device **200**. The actuator **211** may be configured to resiliently reset to a rest position after actuations of the upper and lower portions **216**, **218**.

(48) The remote control device **200** may transmit commands to one or more controlled electrical loads (e.g., one or more lighting loads that are associated with the remote control device **200**) in response to actuations applied to the actuation portion **210**, for instance via the actuator **211**. The remote control device **200** may transmit commands to turn on one or more associated lighting loads

in response to actuations applied to the upper portion **216** of the front surface **214**, and may transmit commands to turn off one or more lighting loads in response to actuations applied to the lower portion **218** of the front surface **214**. In accordance with an example implementation, the remote control device **200** may be configured to transmit commands in response to receiving predetermined actuations at the actuation portion (e.g., via the actuator **211**). For example, the remote control device **200** may be configured to transmit a command to turn one or more associated lighting loads on to full (e.g., 100% intensity) in response to a double tap applied to the upper portion **216** of the front surface **214** (e.g., two actuations applied to the upper portion **216** in quick succession). The remote control device **200** may be configured to transmit a command to perform a relative adjustment of intensity (e.g., relative to a starting intensity) in response to respective press and hold actuations applied to the upper and/or lower portions **216**, **218** of the front surface **214**. For example, the remote control device **200** may cause the respective intensities of one or more associated lighting loads to continually be adjusted (e.g., relative to corresponding starting intensities) while one of the upper or lower portions **216**, **218** is continuously actuated.

(49) The front surface **214** of the actuator **211** may further be configured as a touch sensitive surface (e.g., may include or define a capacitive touch surface). The capacitive touch surface may extend into portions of both the upper and lower surfaces **216**, **218** of the front surface **214**. This may allow the actuation portion **210** (e.g., the actuator **211**) to receive and recognize actuations (e.g., touches) of the front surface **214** that do not cause the actuator **211** to move at all or to move such that the respective mechanical switches **260** that correspond to the upper and lower portions **216**, **218** are not actuated. For example, such actuations of the front surface **214** (e.g., adjacent the light bar **220**) may cause the remote control device **200** to transmit commands to adjust the intensity of a lighting load that is associated with the remote control device **200**.

(50) To illustrate, the remote control device **200** may be configured such that when a user of the remote control device **200** touches the light bar **220** at a location along a length of the light bar **220**, the lighting load be set to an intensity that is dependent upon the location of the actuation along the light bar **220**. The remote control device **200** may be configured such that when a user slides a finger along the light bar **220**, the intensity of an associated lighting load may be raised or lowered according to the position of the finger along the length of the light bar **220**. In response to a touch received on the front surface **214** (e.g., adjacent the light bar **220**) the light bar **220** may be configured to illuminate along a length that extends from the bottom of the light bar **220** to a position along the length of the light bar **220**. The length of such an illumination (e.g., as defined by an amount of the light bar **220** that is illuminated) may correspond to and be indicative of an intensity of an associated lighting load that results from the actuation.

(51) The remote control device **200** may be configured to, if more than one actuation is received via the actuator **211** within a short interval of time (e.g., at substantially the same time), determine which actuation should be responded to, for example by transmitting a command, and which actuation or actuations may be ignored. To illustrate, a user of the remote control device **200** may press the front surface **214** at a location proximate to the light bar **220**, with sufficient force such that the actuator **211** pivots about the pivot axis and activates a corresponding one of the mechanical switches **260**. Such an operation of the actuator **211** may comprise multiple actuations of the actuation portion **210**. For instance, the location of the press of the front surface **214** along the light bar **220** may correspond to an indication of a desired intensity level of an associated lighting load, while the actuation of the mechanical switch **260** may be correspond to an indication by the user to turn on the lighting load to a last-known intensity. The remote control device **200** may be configured to in response to such actuations, ignore the capacitive touch input indication of intensity, and to transmit a command to the associated lighting load to turn on at the last-known intensity. It should be appreciated that the above is merely one illustration of how the remote control device **200** may be configured to respond to multiple such multi-part actuations of the actuation portion **210**.

(52) In accordance with the illustrated actuator **211**, the upper portion **216** and the lower portion **218** of the front surface **214** define respective planar surfaces that are angularly offset relative to each other. In this regard, the touch sensitive portion of the front surface **214** of the actuator **211** may define and operate as a non-planar slider control of the remote control device **200**. However, it should be appreciated that the actuator **211** is not limited to the illustrated geometry defining the upper and lower portions **216**, **218**. For example, the actuator **211** may be alternatively configured to define a front surface having any suitable touch sensitive geometry, for instance such as a curved or wave-shaped touch sensitive surface.

(53) FIGS. 7-12 depict the example remote control device **200**, with the remote control device **200** unmounted from the light switch **202**. As shown, the remote control device **200** may include a carrier **230** that may be configured to be attached to a rear surface of the actuation portion **210**. The carrier **230** may support a flexible printed circuit board (PCB) **232** on which a control circuit (not shown) may be mounted. The remote control device **200** may include a battery **234** for powering the control circuit. The battery **234** may be received within a battery opening **236** defined by the carrier **230**. The remote control device **200** may include a plurality of light-emitting diodes (LEDs) that may be mounted to the printed circuit board **232**. The LEDs may be arranged to illuminate the light bar **220**.

(54) With reference to FIGS. 13 and 14, the actuator **211** may be pivotally coupled to, or supported by, the base portion **212**. For example, as shown the base portion **212** may define cylindrical protrusions **240** that extend outward from opposed sidewalls **242** of the base portion **212**. The protrusions **240** may be received within openings **244** that extend into rear surfaces **248** of corresponding sidewalls **246** of the actuator **211**. The protrusions **240** may define the pivot axis P1 about which the actuator **211** may pivot. As shown, each protrusion **240** may be held in place within a corresponding opening **244** by a respective hinge plate **250** (e.g., thin metal hinge plates). Each hinge plate **250** may be connected to the rear surface **248** of a respective sidewall **246**, for example via heat stakes **252**. It should be appreciated that for the sake of simplicity and clarity, the heat stakes **252** are illustrated in FIGS. 32 and 33 in an undeformed or unmelted state. The hinge plates **250** may be sized and located to maintain a distance between the hinge plate **250** and the bezel portion **205** of the light switch **202**. The hinge plates **250** may be thin to minimize the total depth of the remote control device **200** (e.g., the distance between the front surface of the actuation portion **210** and the front surface of the faceplate **206**).

(55) Referring now to FIGS. 15 and 16, as shown the protruding portion of the paddle actuator **204** of the light switch **202** may be located in a recess **254** in the rear of the actuation portion **210** when the remote control device **200** is mounted over the paddle actuator (e.g., in the portion of the remote control device that is not occupied by the battery **234**). The flexible PCB **232** may be located immediately behind the front surface **214** of the actuation portion **210** and may include capacitive touch traces such that the front surface **214** defines a capacitive touch surface. Actuations applied to the upper and lower portions **216**, **218** of the front surface **214** of the actuation portion **210** may also provide tactile feedback, for instance as described herein. The remote control device **200** may include one or more mechanical tactile switches **260** (e.g., side-actuating tactile switches) that may be mounted to and electrically coupled to the flexible PCB **232**. For example, the remote control device **200** may include a first mechanical tactile switch **260** that is mounted so as to be activated by an actuation applied to the upper portion **216** of the front surface **214** and a second mechanical tactile switch **260** that is mounted so as to be activated by an actuation applied to the lower portion **218** of the front surface **214**. The mechanical tactile switches **260** may be positioned such that respective actuation portions of the mechanical tactile switches **260** are positioned proximate to corresponding contact surfaces **262** defined by the base portion **212**. Each mechanical tactile switch **260** may include a foot **264** that is captively retained in a corresponding opening of the actuator **211**.

(56) The flexible PCB **232** may bend towards the locations in which the mechanical tactile

switches **260** are located. In accordance with the illustrated configuration, when a force is applied to the lower portion **218** of the front surface **214** that causes the lower portion **218** to pivot inward about the pivot axis **P1** towards the base portion **212**, the actuation portion of the corresponding mechanical tactile switch **260** may make contact with the contact surface **262**, thereby causing activation of the mechanical tactile switch **260**. The mechanical tactile switch **260** may operate to return the actuator **211** to a rest position. Return of the actuator **211** to the rest position may provide tactile feedback indicative of activation of the mechanical tactile switch **260**. The mechanical tactile switch **260** may be electrically coupled to the control circuit on the flexible PCB **232**, such that the control circuit is responsive to the actuation of the mechanical tactile switch **260**.

(57) Alternatively, the mechanical tactile switches **260** may not be electrically coupled to the flexible PCB **232** and may operate merely to provide tactile feedback responsive to actuations of the actuator **211**. In such an implementation, the control circuit may be responsive to the capacitive touch surface of the front surface **214** to determine a location of an actuation, for instance to determine whether the upper portion **216** or the lower portion **218** of the front surface **214** was actuated. Further, the mechanical tactile switches **260** may be coupled to the base portion **212** rather than the actuator **211** for providing tactile feedback.

(58) The actuation portion **210** of the remote control device **200** shown in FIGS. 2-5 may be configured to pivot about a pivot axis to allow for actuations of upper and lower portions (e.g., to turn the controlled electrical load on and off, respectively). The remote control device **200** may include mechanical tactile switches to provide tactile feedback in response to actuations of the upper and lower portions of the actuation portion **210**. In addition, the remote control device **200** may be configured to raise and lower the intensity of the controlled lighting load in response to actuations of the upper and lower portions, respectively. The actuation portion may include a touch-sensitive surface (e.g., a capacitive touch surface).

(59) The remote control device **200** may include a mounting structure that is configured to enable attachment of the remote control device **200** to a standard light switch, such as the standard decorator style light switch **202** shown in FIG. 6. For example, as shown the remote control device **200** may include a mounting structure having a plurality of extensions **270** (e.g., thin, flat planar extensions) that protrude outward from the base portion **212**. The mounting structure may be configured to be attached to the base portion **212**. Alternatively, the mounting structure may be monolithic with the base portion **212**.

(60) The extensions **270** may be configured to be disposed into a gap **272** defined between the bezel portion **205** and the opening **208** of the faceplate **206** of the light switch **202**. The extensions **270** may operate to maintain the remote control device **200** in a mounted position relative to the light switch **202**, for example such that the base portion **212** abuts corresponding portions of the faceplate **206**. Each extension **270** may be configured to allow insertion of the extension **270** into the gap **272** and to resist removal of the extensions from the gap **272** once the remote control device **200** is secured in a mounted position relative to the light switch. For example, as shown in FIG. 18, each extension **270** may define a plurality of barbs **274**. The barbs **274** may be configured as spring-style barbs that are configured to deflect and slide along structure of the faceplate **206** as the extensions **270** are inserted into the gap **272** along a first direction, and to bite into surrounding structure of the faceplate **206** when pulled in an opposed second direction to hinder removal of the remote control device **200** from the light switch **202**. The mounting structure may be made of any suitable material, such as metal.

(61) The remote control device **200** may be mounted to the light switch **202** in either orientation, for example, with the light bar **220** on the right side of the actuation portion **210** (e.g., as shown in FIGS. 2 and 3) or with the light bar on the left side of the actuation portion depending on the location of the protruding portion of the paddle actuator **204** of the light switch **202** in the on position. For example, the remote control device **200** may be configured to determine its orientation and determine what commands to transmit in response to actuations and/or how to

illuminate the light bar **220** in response to the determined orientation.

(62) As shown in FIG. **8**, the mounting structure may include extensions **270** that extend along each side of the base portion **212**. However, it should be appreciated that the mounting structure of the remote control device **200** is not limited to the illustrated number or configurations of extensions **270**. For example, the mounting structure of the remote control device **200** may alternatively include extensions **270** along two sides (e.g., opposing sides) of the base portion **212**, or may include extensions **270** along three sides of the base portion **212**.

(63) As described herein, the extensions **270** are provided on the remote control device **200** having the actuator **211** that may pivot to allow for actuations of upper and lower portions **216**, **218** and may define a touch sensitive surface. However, the extensions **270** may be provided on remote control devices having other sorts of user interfaces. For example, the extensions **270** may be provided on a remote control device having a touch sensitive surface that is non-planar and does not pivot. The extensions **270** may be provided on a remote control device having one or more buttons for receiving user inputs. The extensions **270** may be provided on a remote control device having an intensity adjustment actuator that moves with respect to the light switch to which the remote control is mounted, such as a rotary knob or a linear slider.

(64) While the remote control device **200** shown in FIGS. **2-18** and described herein has a rectangular shape with a non-planar surface, the remote control device **200** could have other shapes. For example, the remote control device **200** (e.g., the actuation portion **210**) may have a square shape, a diamond shape, a triangular shape, a circular shape, an oval shape, or any suitable shape. The front surface **214** of the actuations portion **210** may be planar or curved. In addition, the light bar **220** may have alternative shapes, such as a curved shape. The light bar **220** may also be a piece-wise arrangement of multiple visual indicators that may have many shapes, such as a circular shape, a square shape, a rectangular shape, a diamond shape, a triangular shape, an oval shape, or any suitable shape. The surfaces of the control module **420** may be characterized by various colors, finishes, designs, patterns, etc.

(65) FIGS. **19-21** depict another example remote control device **300** (e.g., a battery-powered remote control device) that may be deployed as the remote control device **120** of the load control system **100** shown in FIG. **1**. The remote control device **300** may be configured to be mounted over a paddle actuator of a standard light switch, such as the paddle actuator **204** of the standard decorator paddle style light switch **202** shown in FIG. **20**. As shown, the remote control device **300** may include a control module **302** (e.g., a control unit). The control module **302** may comprise an actuation portion **304** that may be a touch sensitive surface (e.g., may include or define a capacitive touch surface). The control module **302** may also include a light bar **306** that is configured to visibly display information at the touch sensitive surface. The control module **302** may be configured similarly, for example, to the example control modules described in greater detail in commonly assigned U.S. patent application Ser. No. 15/469,079, filed Mar. 24, 2017, entitled "Retrofit Remote Control Device," the entire disclosure of which is incorporated herein by reference.

(66) The remote control device **300** may include a mounting structure that is configured to enable attachment of the remote control device **300** to a standard light switch, such as the light switch **202**. For example, as shown the remote control device **300** may include a mounting structure **310**. The mounting structure **310** may include a plate shaped base **312** that defines an opening **314** that extends therethrough. The mounting structure may include one or more extensions **316** that extend outward from the base **312**. As shown, the extensions **316** may be configured as thin, flat planar extensions that extend perpendicular to the base **312** along respective inner perimeter edges of the opening **314**.

(67) The opening **314** may be sized to receive the bezel portion **205** of the light switch **202**. The extensions **316** may define one or more alignment features that may abut corresponding portions of the bezel portion **205** of the light switch **202**. For example, each extension **316** may define one or

more tabs **318** that extend inward towards the opening **314**. As shown, each tab **318** be angularly offset relative to its corresponding extension **316**, and may extend from a fixed end to a free end **320** that is configured to abut a front surface **203** of the bezel portion **205** when the mounting structure **310** is mounted over the bezel portion **205** (e.g., as shown in FIG. **21**).

(68) The extensions **316** may be configured to be disposed into the gap **272** between the bezel portion **205** of the light switch **202** and the opening **208** of the faceplate **206**. In an example of installing the mounting structure **310**, the opening **314** may be disposed over the bezel portion **205** of the light switch **202** such that the free ends **320** of the tabs **318** abut the front surface **203** of the bezel portion **205**. With the mounting structure **310** in place over the bezel portion **205** of the light switch **202**, the faceplate **206** may be attached to a yoke **201** of the light switch **202**, for instance using screws **209**. When the faceplate **206** is attached to the yoke **201**, the base **312** of the mounting structure **310** may abut an inner surface of the faceplate **206**.

(69) As shown in FIG. **20**, when the mounting structure **310** is mounted to the bezel portion **205** and the faceplate **206** is attached to the yoke **201**, the extensions **316** may protrude past a front surface **207** of the faceplate **206**. The mounting structure **310** may be configured such that the control module **302** is releasably attachable to the portions of the extensions **316** that protrude beyond the front surface **207** of the faceplate **206**. For example, as shown the extensions **316** may define one or more engagement members **322** that are configured to engage with complementary features (not shown) of the control module **302** to allow attachment of the control module **302** to the light switch **202** via the mounting structure **310**. The engagement members **322** may engage a base portion **308** of the control module **302**. The extensions **316** may operate to maintain the control module **302** of the remote control device **300** in a mounted position relative to the light switch **202**, for example such that portions of the control module **302** abut corresponding portions of the faceplate **206**. The mounting structure **310** may be made of any suitable material, such as metal.

(70) The control module **302** may be mounted to the light switch **202** in one of two orientations (e.g., orientations that are 180° apart) depending on the location of the protruding portion of the paddle actuator **204** of the light switch **202** in the on position. For example, the control module **302** may be configured to determine its orientation and determine what commands to transmit in response to actuations and/or how to illuminate the light bar **306** in response to the determined orientation.

(71) As shown, the mounting structure **310** may include extensions **316** that extend along each side of the opening **314**. However, it should be appreciated that the mounting structure **310** is not limited to the illustrated number or configurations of extensions **316**. For example, the mounting structure **310** may alternatively include extensions **316** along two sides (e.g., opposing sides) of the opening **314**, or may include extensions **316** along three sides of the opening **314**.

(72) It should be appreciated that the remote control devices illustrated and described herein, such as the remote control devices **200**, **300**, are not limited to mounting to the light switch **202** via the corresponding illustrated mounting structures. For example, the remote control device **200** may be alternatively configured to be mounted to the light switch **202** via the mounting structure **310**, and the control module **302** of the remote control device **300** may be alternatively configured with a mounting structure resembling that of the remote control device **200**. In addition, the mounting structure **310** may be used to mount a remote control having one or more buttons for receiving user inputs, and/or a remote control device having an intensity adjustment actuator that moves with respect to the light switch to which the remote control is mounted, such as a rotary knob or a linear slider.

(73) While the remote control device **300** shown in FIGS. **2-18** and described herein has a rectangular shape, the remote control device **300** could have other shapes. For example, the remote control device **300** may a square shape, a diamond shape, a triangular shape, a circular shape, an oval shape, or any suitable shape. The actuation portion **304** may be non-planar (e.g., curved). In

addition, the light bar **306** may have alternative shapes, such as a curved shape. The light bar **306** may also be a piece-wise arrangement of multiple visual indicators that may have many shapes, such a circular shape, a square shape, a rectangular shape, a diamond shape, a triangular shape, an oval shape, or any suitable shape. The surfaces of the remote control device **300** may be characterized by various colors, finishes, designs, patterns, etc.

(74) FIG. **22** is a perspective view of an example remote control device **400** (e.g., a battery-powered rotary remote control device) that may be deployed as the remote control device **120** of the load control system **100** shown in FIG. **1**. The remote control device **400** may be configured to be mounted over an actuator **404** of a standard light switch **402** (e.g., the toggle actuator **106** of the SPST maintained mechanical switch **104** shown in FIG. **1**). The remote control device **400** may be installed over of an existing faceplate **406** that is mounted to the light switch **404** (e.g., via faceplate screws **408**).

(75) The remote control device **400** may include a base portion **410** and a control module **420** that may be operably coupled to the base portion **410**. The control module **420** may be supported by the base portion **410** and may include a rotating portion **422** (e.g., an annular rotating portion) that is rotatable with respect to the base portion **410**. FIG. **23** is a perspective view of the remote control device **400** with the control module **420** detached from the base portion **410**. The base portion **410** may be configured to maintain the toggle actuator **204** in the on position. The toggle actuator **404** may be received through a toggle actuator opening **212** in the base portion **410**. In this regard, the base portion **210** may be configured to prevent a user from inadvertently switching the toggle actuator **204** to the off position when the remote control device **200** is attached to the light switch **202**.

(76) The base portion **410** may be provided with a mounting structure (not shown) including extensions (e.g., similarly configured to extensions **270**) that are configured to be disposed into a gap between the faceplate **406** and the toggle actuator **404**. In addition, the base portion **410** may be configured to be attached to a mounting structure including extensions (e.g., similarly configured to extensions **316**) that are configured to be disposed into a gap between the faceplate **406** and the toggle actuator **404**. The base portion **410** of the remote control device **400** may be configured to define complementary features configured to engage with such extensions.

(77) The control module **420** may be released from the base portion **410**. For example, a control module release tab **416** may be provided on the base portion **410**. By actuating the control module release tab **416** (e.g., pushing up towards the base portion or pulling down away from the base portion), a user may remove the control module **420** from the base portion **410**. FIG. **24** provides a rear view of the control module **420** of the remote control device **400**. The control module **420** may comprise one or more clips **428** that may be retained by respective locking members (not shown) connected to the control module release tab **416** when the base portion **410** is in a locked position. The one or more clips **428** may be released from the respective locking members of the base portion **410** when the control module release tab **416** is actuated (e.g., pushed up towards the base portion or pulled down away from the base portion) to put the base portion **410** in an unlocked position. In an example, the locking members may be spring biased into the locked position and may automatically return to the locked position after the control module release tab **416** is actuated and released. In an example, the locking members may not be spring biased, in which case the control module release tab **416** may be actuated to return the base portion **410** to the locked position.

(78) The control module **420** may be installed on the base portion **410** without adjusting the base portion **410** to the unlocked position. For example, the one or more clips **428** of the control module **420** may be configured to flex around the respective locking members of the base portion and snap into place, such that the control module is fixedly attached to the base portion.

(79) The control module **420** may be released from the base portion **410** to access a battery **430** (e.g., as shown in FIG. **24**) that provides power to at least the remote control device **400**. The

battery **430** may be held in place in various ways. For example, the battery **430** may be held by a battery retention strap **432**, which may also operate as an electrical contact for the batteries. The battery retention strap **432** may be loosened by untightening a battery retention screw **434** to allow the battery **430** to be removed and replaced. Although FIG. **24** depicts the battery **430** as being located in the control module **420**, it should be appreciated that the battery **430** may be placed elsewhere in the remote control device **400** (e.g., in the base portion **410**) without affecting the functionality of the remote control device **400**. Further, more than one battery may be provided. For instance, a spare battery may be provided (e.g., stored inside the control module **420**) as replacement for the battery **430**.

(80) When the control module **420** is coupled to the base portion **410** as shown in FIG. **22**, the rotating portion **422** may be rotatable in opposed directions about the base portion **410** (e.g., in the clockwise or counter-clockwise directions). The base portion **410** may be configured to be mounted over the toggle actuator **404** of the switch **402** such that the rotational movement of the rotating portion **422** may not change the operational state of the toggle actuator **404** (e.g., the toggle actuator **404** may remain in the on position to maintain functionality of the remote control device **400**).

(81) The control module **420** may comprise an actuation portion **424**. The actuation portion **424** may in turn comprise a part or an entirety of a front surface of the control module **420**. For example, the control module **420** may have a circular surface within an opening defined by the rotating portion **422**. The actuation portion **424** may comprise a part of the circular surface (e.g., a central area of the circular surface) or approximately the entire circular surface. In an example, the actuation portion **424** may be configured to move towards the light switch **402** to actuate a mechanical switch (not shown) inside the control module **420** as will be described in greater detail below. The actuation portion **424** may return to an idle position (e.g., as shown in FIG. **22**) after being actuated. In an example, the front surface of the actuation portion **424** may be a touch sensitive surface (e.g., a capacitive touch surface). The actuation portion **424** may comprise a touch sensitive element (e.g., a capacitive touch element) adjacent to the rear surface of the actuation portion. The touch sensitive element may be actuated in response to a touch of the touch sensitive surface of the actuation portion **424**. In addition, the actuation portion **424** may be replaced by two or more buttons.

(82) The remote control device **400** may be configured to transmit one or more wireless communication signals (e.g., the RF signals **108**) to a load control device (e.g., the load control devices of the load control system **100**, such as the controllable light source **110**). The remote control device **400** may include a wireless communication circuit (e.g., an RF transceiver or transmitter (not shown)) via which one or more wireless communication signals may be sent and/or received. The control module **420** may be configured to transmit digital messages (e.g., including commands to the control the controllable light source **110**) via the wireless communication signals (e.g., the RF signals **108**). For example, the control module **420** may be configured to transmit a command to raise the intensity of the controllable light source **110** in response to a clockwise rotation of the rotating portion **422** and to transmit a command to lower the intensity of the controllable light source in response to a counterclockwise rotation of the rotating portion **422**.

(83) The control module **420** may be configured to transmit a command to toggle the controllable light source **110** (e.g., from off to on or vice versa) in response to an actuation of the actuation portion **424**. In addition, the control module **420** may be configured to transmit a command to turn the controllable light source **110** on in response to an actuation of the actuation portion **424** (e.g., if the control module **420** possesses information indicating that the controllable light source is presently off). The control module **420** may be configured to transmit a command to turn the controllable light source **110** off in response to an actuation of the actuation portion **424** (e.g., if the control module possesses information indicating that the controllable light source is presently on). The control module **420** may be configured to transmit a command to turn the controllable light

source on to full intensity in response to a double tap of the actuation portion **424** (e.g., two actuations in quick succession).

(84) The control module **420** may be configured to adjust the intensity of the lighting load to a minimum intensity in response to rotation of the rotating portion **422** and may only turn off the lighting load in response to an actuation of the actuation portion **424**. The control module **420** may also be configured in a spin-to-off mode, in which the control module **420** may turn off the lighting load after the intensity of the lighting load is controlled to a minimum intensity in response to a rotation of the rotating portion **422**. The control module **420** may be configured to transmit a command (e.g., via one or more wireless communication signals such as the RF signal **118**) to adjust the color of the controllable light source **110**.

(85) The control module **420** may comprise a light bar **426** that may be illuminated, for example, to provide feedback to a user of the remoted control device **400**. The light bar **426** may be located in various areas of the remote control device **400**. For example, the light bar **426** may be located between the rotating portion **422** and the actuation portion **424**. The light bar may form different shapes. For example, the light bar **426** may form a full circle (e.g., a substantially full circle) as shown in FIGS. **22** and **23**. The light bar **426** may be attached to a periphery of the actuation portion **424** and move with the actuation portion **424** (e.g., when the actuation portion is actuated). The light bar **426** may have a certain width (e.g., a same width along the entire length of the light bar). The exact value of the width may vary, for example, depending on the size of the remote control device **400** and/or the intensity of the light source(s) that illuminates the light bar **426**.

(86) The actuation portion **424** of the remote control device **400** may be configured to pivot about a pivot axis to allow for actuations of upper and lower portions (e.g., to turn the controlled electrical load on and off, respectively). The remote control device **400** may include mechanical tactile switches to provide tactile feedback in response to actuations of the upper and lower portions of the actuation portion **424**. In addition, the remote control device **400** may be configured to raise and lower the intensity of the controlled lighting load in response to actuations of the upper and lower portions, respectively. The actuation portion may include a touch-sensitive surface (e.g., a capacitive touch surface).

(87) The base portion **410** and the control module **420** may be mounted to the switch **402** in one of two orientations (e.g., orientations that are 180° apart) depending on the location of the protruding portion of the toggle actuator **404** of the light switch **402** in the on position. For example, the control module **420** may be configured to determine its orientation and determine what commands to transmit in response to actuations and/or how to illuminate the light bar **426** in response to the determined orientation.

(88) While the control module **420** shown and described herein has a circular shape, the control module **420** could have other shapes. For example, the control module **420** (e.g., the rotating portion **422** and/or the actuation portion **424**) may have a rectangular shape, a square shape, a diamond shape, a triangular shape, an oval shape, a star shape, or any suitable shape. The front surface of the actuations portion **424** and/or the side surfaces of the rotating portions **422** may be planar or non-planar. In addition, the light bar **426** may have alternative shapes, such as a rectangular shape, a square shape, a diamond shape, a triangular shape, an oval shape, a star shape, or any suitable shape. The light bar **426** may be continuous loops, partial loops, broken loops, a single linear bar, a linear or circular array of visual indicators, and/or other suitable arrangement. The surfaces of the control module **420** may be characterized by various colors, finishes, designs, patterns, etc.

(89) FIG. **25** is a simplified equivalent schematic diagram of an example control module **520** for a remote control device (e.g., the control module **220** of the remote control device **200**, the control module **302** of the remote control device **300**, and/or the control module **420** of the remote control device **200**). The control module **520** may include a control circuit **530**, input devices **532**, a wireless communication circuit **534**, a memory **536**, a battery **538**, and one or more LEDs **540**. The

input devices **532** may include an actuation portion a rotating portion (e.g., a rotary knob), and/or a touch sensitive circuit (e.g., a capacitive touch circuit). The input devices **532** may be configured to translate a received user input (e.g., a force applied to the actuation portion(s), a force and/or time of user contact with the touch sensitive surface, a rotational speed and/or direction of a rotary knob, etc.) into input signals, and provide the input signals to the control circuit **530**.

(90) The control circuit **530** may be configured to translate the input signals into control signals for transmission to a load control device via the wireless communication circuit **534**. For example, the control circuit **530** may be configured to translate the input signals received from the input devices **532** into control data for transmission to one or more external electrical loads via the wireless communication circuit **534**. The LEDs **540** may be configured to illuminate a light bar (e.g., such as the light bar **226**) and/or to serve as indicators of various conditions. The memory **536** may be configured to store one or more operating parameters (e.g., such as a preconfigured color scene or a preset light intensity) of the remote control device. The battery **538** may provide power to one or more of the components shown in FIG. **25**.

Claims

1. A remote control device adapted to be mounted over an actuator of a mechanical switch, the mechanical switch having a faceplate mounted thereto, the faceplate having an opening through which the actuator is received, the opening of the faceplate defining a gap between the faceplate and the actuator, the remote control device comprising: a base portion having a rectangular shape with a top wall, a bottom wall, and opposed sidewalls, the base portion defining one or more cylindrical protrusions that extend from a respective one of the sidewalls, wherein the one or more cylindrical protrusions define a pivot axis; a plurality of planar extensions that extend from two or more of the top wall, the bottom wall, or the opposed sidewalls of the base portion, the plurality of planar extensions adapted to be received in the gap between the faceplate and the actuator for holding the remote control device against the faceplate; an actuation portion pivotally supported by the base portion such that the actuation portion pivots about the pivot axis with respect to the base portion, the actuation portion defining one or more openings that are configured to receive the one or more cylindrical protrusions; and a plate attached to a rear surface of the actuation portion, the plate configured to secure a respective one of the one or more cylindrical protrusions within a corresponding one of the one or more openings.
2. The remote control device of claim 1, wherein the actuation portion is configured to be pivotally coupled to the one or more cylindrical protrusions.
3. The remote control device of claim 1, wherein the plate is connected to the rear surface of the respective sidewall via one or more heat stakes.
4. The remote control device of claim 1, wherein the plate is configured to maintain a distance between the plate and a bezel portion of the mechanical switch.
5. The remote control device of claim 1, wherein each of the plurality of planar extensions comprise barbs that allow for insertion of the planar extensions in the gap, the barbs configured to bite into the faceplate to hinder removal of the remote control device.
6. The remote control device of claim 5, wherein the barbs are spring-style barbs that are configured to deflect as the planar extensions are inserted into the gap.
7. The remote control device of claim 1, wherein the actuator comprises a toggle actuator or a paddle actuator.
8. The remote control device of claim 1, wherein the planar extensions extend from each of the top wall, the bottom wall, and the opposed sidewalls.
9. The remote control device of claim 1, wherein the planar extensions extend along each side of the base portion.
10. The remote control device of claim 9, wherein the planar extensions are thin and flat to enable

insertion within the gap.

11. The remote control device of claim 1, further comprising: a wireless communication circuit; and a control circuit configured to transmit a digital message via the wireless communication circuit in response to an actuation of the actuation portion.

12. A remote control device adapted to be mounted over an actuator of a mechanical switch, the mechanical switch having a faceplate mounted thereto, the faceplate defining an opening through which the actuator is received, the remote control device comprising: a mounting structure having a rectangular shape with a top wall, a bottom wall, and opposed sidewalls, the mounting structure configured to be disposed between a yoke of the mechanical switch and the faceplate, the mounting structure defining a plurality of planar extensions that extend from two or more of the top wall, the bottom wall, or the opposed sidewalls, wherein the plurality of planar extensions are configured to be disposed into a gap between the opening of the faceplate and the actuator and protrude beyond a front surface of the faceplate, the mounting structure defining one or more cylindrical protrusions that extend from a respective one of the sidewalls, wherein the one or more cylindrical protrusions define a pivot axis; an actuation portion pivotally supported by the mounting structure such that the actuation portion pivots about the pivot axis with respect to the mounting structure, the actuation portion defining one or more openings that are configured to receive the one or more cylindrical protrusions; and a plate attached to a rear surface of the actuation portion, the plate configured to secure a respective one of the one or more cylindrical protrusions within a corresponding one of the one or more openings.

13. The remote control device of claim 12, wherein the actuation portion is configured to be pivotally coupled to the one or more cylindrical protrusions.

14. The remote control device of claim 12, wherein the plate is connected to the rear surface of the respective sidewall via one or more heat stakes.

15. The remote control device of claim 12, wherein the plate is configured to maintain a distance between the plate and a bezel portion of the mechanical switch.

16. The remote control device of claim 12, wherein the mounting structure defines four extensions that are configured to be disposed along corresponding portions of an inner perimeter of the opening.

17. The remote control device of claim 12, wherein the planar extensions extend from each of the top wall, the bottom wall, and the opposed sidewalls.

18. The remote control device of claim 12, wherein the planar extensions extend along each side of the base portion.

19. The remote control device of claim 18, wherein the planar extensions are thin and flat to enable insertion within the gap.

20. The remote control device of claim 12, further comprising: a wireless communication circuit; and a control circuit configured to transmit a digital message via the wireless communication circuit in response to an actuation of the actuation portion.
