

# US Patent & Trademark Office

## Patent Public Search | Text View

United States Patent  
Kind Code  
Date of Patent  
Inventor(s)

12388016  
B2  
August 12, 2025  
Lai; Wei-An et al.

### Deep lines and shallow lines in signal conducting paths

#### Abstract

An integrated circuit includes a plurality of first layer deep lines, a plurality of first layer shallow lines, a plurality of second layer deep lines, and a plurality of second layer shallow lines. The integrated circuit also includes a first active device and a second active device coupled between a conducting path that has a low resistivity portion and a low capacitivity portion. The first active device has an output coupled to a first layer deep line that is in the low resistivity portion. The second active device has an input coupled to a first layer shallow line that is in the low capacitivity portion. The low resistivity portion excludes the first layer shallow lines and the second layer shallow lines, and the low capacitivity portion excludes the first layer deep lines and the second layer deep lines.

**Inventors:** Lai; Wei-An (Hsinchu, TW), Chiu; Te-Hsin (Hsinchu, TW), Peng; Shih-Wei (Hsinchu, TW), Lin; Wei-Cheng (Hsinchu, TW), Tzeng; Jiann-Tyng (Hsinchu, TW), Wu; Chia-Tien (Hsinchu, TW)

**Applicant:** TAIWAN SEMICONDUCTOR MANUFACTURING COMPANY, LTD.  
(Hsinchu, TW)

**Family ID:** 81772204

**Assignee:** TAIWAN SEMICONDUCTOR MANUFACTURING COMPANY, LTD.  
(Hsinchu, TW)

**Appl. No.:** 18/521210

**Filed:** November 28, 2023

#### Prior Publication Data

| Document Identifier | Publication Date |
|---------------------|------------------|
| US 20240105601 A1   | Mar. 28, 2024    |

#### Related U.S. Application Data

## Publication Classification

**Int. Cl.:** H01L23/528 (20060101); H01L21/768 (20060101); H01L23/522 (20060101)

**U.S. Cl.:**

**CPC** H01L23/528 (20130101); H01L21/76802 (20130101); H01L21/76877 (20130101);  
H01L23/5226 (20130101);

## Field of Classification Search

**CPC:** H01L (23/528); H01L (21/76802); H01L (21/76877); H01L (23/5226); H01L (23/5222);  
H01L (23/5283); H01L (21/76807); H01L (27/0207); H01L (21/76895); H01L (21/76816)

---

## References Cited

### U.S. PATENT DOCUMENTS

| Patent No.   | Issued Date | Patentee Name   | U.S. Cl. | CPC           |
|--------------|-------------|-----------------|----------|---------------|
| 7260442      | 12/2006     | Hwang et al.    | N/A      | N/A           |
| 9256709      | 12/2015     | Yu et al.       | N/A      | N/A           |
| 2012/0193785 | 12/2011     | Lin et al.      | N/A      | N/A           |
| 2014/0040838 | 12/2013     | Liu et al.      | N/A      | N/A           |
| 2015/0278429 | 12/2014     | Chang           | N/A      | N/A           |
| 2016/0358967 | 12/2015     | Madurawe et al. | N/A      | N/A           |
| 2021/0407907 | 12/2020     | Yoo             | N/A      | H01L 21/76877 |

### FOREIGN PATENT DOCUMENTS

| Patent No.      | Application Date | Country | CPC |
|-----------------|------------------|---------|-----|
| 10-2001-0075398 | 12/2000          | KR      | N/A |
| 10-2017-0102410 | 12/2016          | KR      | N/A |
| 201742228       | 12/2016          | TW      | N/A |
| 202022950       | 12/2019          | TW      | N/A |

---

*Primary Examiner:* Kusumakar; Karen

*Attorney, Agent or Firm:* Hauptman Ham, LLP

---

## Background/Summary

**PRIORITY CLAIM AND CROSS-REFERENCE** (1) The present application is a continuation of U.S. application Ser. No. 17/344,530, filed Jun. 10, 2021, now U.S. Pat. No. 11,854,789, issued Dec. 26, 2023, which claims the priority of U.S. Provisional Application No. 63/148,883, filed Feb. 12, 2021, which is incorporated herein by reference in its entirety.

## BACKGROUND

(1) The recent trend in miniaturizing integrated circuits (ICs) has resulted in smaller devices which consume less power yet provide more functionality at higher speeds. The miniaturization process has also resulted in stricter design and manufacturing specifications as well as reliability challenges. Various electronic design automation (EDA) tools generate, optimize and verify standard cell layout designs for integrated circuits while ensuring that the standard cell layout design and manufacturing specifications are met.

---

## Description

### BRIEF DESCRIPTION OF THE DRAWINGS

(1) Aspects of the present disclosure are best understood from the following detailed description when read with the accompanying figures. It is noted that, in accordance with the standard practice in the industry, various features are not drawn to scale. In fact, the dimensions of the various features may be arbitrarily increased or low for clarity of discussion.

(2) FIG. 1 is a layout diagram of an integrated circuit, in accordance with some embodiments.

(3) FIGS. 2A-2D are cross-sectional views of integrated circuit in FIG. 1, in accordance with some embodiments.

(4) FIG. 3A is a cross-sectional view of deep lines and shallow lines with labeled depth dimensions, in accordance with some embodiments.

(5) FIG. 3B is a diagram of a resistivity graph and capacitivity plotted against the changes in the depths of the conducting lines, in accordance with some embodiments.

(6) FIGS. 4A-4C are cross-sectional views of the integrated circuit in FIG. 1, in accordance with some embodiments.

(7) FIG. 5 is a layout diagram of an integrated circuit having a signal conducting path formed with a combination of deep lines and shallow lines, in accordance with some embodiments.

(8) FIGS. 6A-6F are layout diagrams of integrated circuits having signal conducting paths formed with different configurations of the low resistivity portion, the low capacitivity portion, and the mutation point, in accordance with some embodiments.

(9) FIG. 7 is a layout diagram of an integrated circuit having multiple signal conducting paths formed with combinations of deep lines and shallow lines, in accordance with some embodiments.

(10) FIGS. 8A-8B are schematic diagrams of integrated circuits having multiple signal conducting paths formed with combinations of deep lines and shallow lines, in accordance with some embodiments.

(11) FIG. 9 is a layout diagram of an integrated circuit having multiple signal conducting paths formed with deep lines, in accordance with some embodiments.

(12) FIG. 10 is a flowchart of a method of manufacturing an integrated circuit, in accordance with some embodiments.

(13) FIG. 11 is a flowchart of a method of fabricating deep lines and shallow lines, in accordance with some embodiments.

(14) FIGS. 12A-12E are cross-sectional views of example device structures, in accordance with some embodiments.

(15) FIG. 13 is a block diagram of an electronic design automation (EDA) system, in accordance with some embodiments.

(16) FIG. 14 is a block diagram of an integrated circuit (IC) manufacturing system, and an IC manufacturing flow associated therewith, in accordance with some embodiments.

### DETAILED DESCRIPTION

(17) The following disclosure provides many different embodiments, or examples, for implementing different features of the provided subject matter. Specific examples of components,

values, operations, materials, arrangements, or the like, are described below to simplify the present disclosure. These are, of course, merely examples and are not intended to be limiting. Other components, values, operations, materials, arrangements, or the like, are contemplated. For example, the formation of a first feature over or on a second feature in the description that follows may include embodiments in which the first and second features are formed in direct contact, and may also include embodiments in which additional features may be formed between the first and second features, such that the first and second features may not be in direct contact. In addition, the present disclosure may repeat reference numerals and/or letters in the various examples. This repetition is for the purpose of simplicity and clarity and does not in itself dictate a relationship between the various embodiments and/or configurations discussed.

(18) Further, spatially relative terms, such as “beneath,” “below,” “lower,” “above,” “upper” and the like, may be used herein for ease of description to describe one element or feature's relationship to another element(s) or feature(s) as illustrated in the figures. The spatially relative terms are intended to encompass different orientations of the device in use or operation in addition to the orientation depicted in the figures. The apparatus may be otherwise oriented (rotated 90 degrees or at other orientations) and the spatially relative descriptors used herein may likewise be interpreted accordingly.

(19) In some embodiments, an integrated circuit includes deep lines and shallow lines in both a first conductive layer and a second conductive layer. The selection of the deep lines and shallow lines for constructing various signal conducting paths allow performance improvements for the integrated circuit. In some embodiments, the resistance capacitance (RC) constant of the signal conducting path from a first active device to a second active device is reduced. In some embodiments, the time delay of the signal propagation in the signal conducting path from a first active device to a second active device is reduced. In some embodiments, the signal conducting path includes a mutation point between a low resistivity portion of the signal conducting path and a low capacitivity portion of the signal conducting path. In some embodiments, the signal conducting path changes from a deep line to a shallow line at the mutation point. In some embodiments, the signal propagation time delay in a signal conducting path from a first active device to a second active device is reduced when a mutation point is selected from several mutation point candidates on the signal conducting path.

(20) FIG. 1 is a layout diagram of an integrated circuit **100**, in accordance with some embodiments. FIGS. 2A-2D are cross-sectional views of the integrated circuit in FIG. 1, in accordance with some embodiments. The integrated circuit **100** includes first layer deep lines and first layer shallow lines extending in the X-direction. The integrated circuit **100** also includes second layer deep lines and second layer shallow lines extending in the Y-direction. The first layer deep lines (**111D**, **112D**, **113D**, **115D**, **117D**, **118D**, and **119D**) and the first layer shallow lines (**111S**, **112S**, **117S**, and **118S**) are in a first conductive layer. The second layer deep lines (**123D** and **128D**) and the second layer shallow lines (**122S**, **123S**, **127S**, and **128S**) are in a second conductive layer.

(21) The integrated circuit **100** includes a first active device **D1** and a second active device **D2**. The output of the first active device **D1** is electrically connected to an input of the second active device **D2** through a conducting path **101**. The conducting path **101** includes segments of the first layer deep line **112D**, the second layer deep line **123D**, the first layer deep line **115D**, the second layer deep line **128D**, and the first layer deep line **118D**. The via-connector **1V1** electrically connects the first layer deep line **112D** with the second layer deep line **123D**. The via-connector **1V2** electrically connects the second layer deep line **123D** with the first layer deep line **115D**. The via-connector **1V3** electrically connects the first layer deep line **115D** with the second layer deep line **128D**. The via-connector **1V4** electrically connects the second layer deep line **128D** with the first layer deep line **118D**. The output of the first active device **D1** is electrically connected to the first layer deep line **112D**, and the input of the second active device **D2** is electrically connected to the first layer deep line **118D**.

(22) In FIG. 1, the conducting path **101** includes the first layer deep lines and the second layer deep lines, while the conducting path **101** excludes the first layer shallow lines and the second layer shallow lines. That is, the first layer shallow lines and the second layer shallow lines are absent from the conducting path **101**. The resistive value of a first layer deep line per unit length is smaller than the resistive value of a first layer shallow line per unit length, while the capacitive value of a first layer deep line per unit length is larger than the capacitive value of a first layer shallow line per unit length. Similarly, the resistive value of a second layer deep line per unit length is smaller than the resistive value of a second layer shallow line per unit length, while the capacitive value of a second layer deep line per unit length is larger than the capacitive value of a second layer shallow line per unit length. The geometric distinctions between the first layer deep lines and the first layer shallow lines are recognizable in the cross-sectional views of FIGS. 2A-2D. The geometric distinctions between the second layer deep lines and the second layer shallow lines are also recognizable in the cross-sectional views of FIGS. 2A-2D.

(23) The cross-sectional views of integrated circuit **100** in cutting planes as specified by the lines AA', BB', and CC' in FIG. 1 are correspondingly depicted in FIG. 2A, FIG. 2B, and FIG. 2C. In FIGS. 2A-2C, the first layer deep lines **111D** and **112D** and the first layer shallow lines **111S** and **112S** are deposited above an insulation layer **205**. Each of the first layer deep lines **111D** and **112D** extends into the interlayer dielectric **210** with the depth  $d1$  along the Z-direction. Each of the first layer shallow lines **111S** and **112S** extends into the interlayer dielectric **210** with the depth  $s1$  along the Z-direction. The depth  $d1$  of the first layer deep lines is larger than the depth  $s1$  of the first layer shallow lines.

(24) In FIGS. 2A-2C, the interlayer dielectric **220** is deposited above the interlayer dielectric **210** and above the first layer deep lines and the first layer shallow lines. In FIG. 2A, the second layer shallow line **122S** extends along the Y-direction and is embedded in the interlayer dielectric **220** with the depth  $s2$ . In FIG. 2B, the second layer deep line **123D** extends along the Y-direction and is embedded in the interlayer dielectric **220** with the depth  $d2$ . Furthermore, the second layer deep line **123D** is electrically connected to the first layer deep line **112D** through the via-connector **1V1**. In FIG. 2C, the cross-sections of the second layer deep lines and the second layer shallow lines do not appear in the cross-sectional view along the cutting plane as specified by the line CC' of FIG. 1.

(25) The cross-sectional view of integrated circuit **100** in cutting plane as specified by the line PP' in FIG. 1 is depicted in FIG. 2D. In FIG. 2D, the second layer deep line **122D** and the second layer shallow lines **122S** and **123S** are deposited above the interlayer dielectric **210**. The second layer deep line **123D** extends into the interlayer dielectric **220** with the depth  $d2$  along the Z-direction. Each of the second layer shallow lines **122S** and **123S** extends into the interlayer dielectric **220** with the depth  $s2$  along the Z-direction. The depth  $d2$  of the second layer deep lines is larger than the depth  $s2$  of the second layer shallow lines. In FIG. 2D, the first layer deep line **112D** extends along the X-direction and is embedded in the interlayer dielectric **210**. The second layer deep line **123D** is electrically connected to the first layer deep line **112D** through the via-connector **1V1**.

(26) In FIGS. 2A-2D, the depths of the first layer deep lines and the first layer shallow lines are adjusted based on design specification, and the depths of the second layer deep lines and the second layer shallow lines are also adjusted based on design specification. The difference between the depth  $d1$  of the first layer deep lines and the depth  $s1$  of the first layer shallow lines are related to the resistive value and the capacitive value differences between the first layer deep lines and the first layer shallow lines. The difference between the depth  $d2$  of the second layer deep lines and the depth  $s2$  of the second layer shallow lines are related to the resistive value and the capacitive value differences between the second layer deep lines and the second layer shallow lines. The depth difference between the depth  $d1$  and the depth  $d2$  and the depth difference between the depth  $s1$  and the depth  $s2$  are both related to other design considerations, as well. In some embodiments, the depth  $d1$  differs from the depth  $d2$ . In some embodiments, the depth  $d1$  is the same as the depth  $d2$ . In some embodiments, the depth  $s1$  differs from the depth  $s2$ . In some embodiments, the depth  $s1$  is

the same as the depth  $s_2$ .

(27) FIG. 3A is a cross-sectional view of deep lines and shallow lines with labeled depth dimensions, in accordance with some embodiments. FIG. 3B is a diagram of a graph of the resistivity and the capacitivity plotted against the change in the depths of the conducting lines, in accordance with some embodiments. In the example of FIG. 3A, the deep lines labeled with letter "A" are modified from uniform lines by extending the deep lines into the interlayer dielectric **210** further than the uniform lines extend, and the shallow lines labeled with letter "B" are modified from uniform lines by extending the shallow lines into the interlayer dielectric **210** less than the uniform lines extend. The uniform lines appear in designs in which all conducting lines in the interlayer dielectric **210** have a same depth "h". In FIGS. 3A-3B, the depth "d" of the deep lines and the depth "s" of the shallow lines are compared with the depth "h" of the uniform lines.

(28) In FIG. 3B, the curve **310D** is a plot of the relative capacitance change  $\Delta C_t$  as a function of the relative height change  $LA=(d-h)/h$  of the deep line, and the curve **320D** is a plot of the relative resistance change  $\Delta R_s$  as a function of the relative height change  $LA=(d-h)/h$  of the deep line. As the depth of the deep line increases, the capacitance value in the curve **310D** increases, and the resistance value in the curve **320D** decreases. For example, when the depth of the deep line increases by 30%, the capacitance value in the curve **310D** increases by 14%, and the resistance value in the curve **320D** decreases by 30%. As the depth of the deep line increases, the changes in the capacitance value and the resistance value consequently cause a change in the RC constant of the deep line. In the example of FIG. 3B, when the depth of the deep line increases by 30%, the RC constant of a deep line per unit length decreases by 20%.

(29) In FIG. 3B, the curve **310S** is a plot of the relative capacitance change  $\Delta C_t$  as a function of the relative height change  $LB=(s-h)/h$  of the shallow line, and the curve **320S** is a plot of the relative resistance change  $\Delta R_s$  as a function of the relative height change  $LB=(s-h)/h$  of the shallow line. As the depth of the shallow line decreases, the capacitance value in the curve **310S** decreases, and the resistance value in the curve **320S** increases. For example, when the depth of the shallow line decreases by 30%, the capacitance value in the curve **310S** decreases by 16%, and the resistance value in the curve **320S** increases by 65%. As the depth of the shallow line decreases, the changes in the capacitance value and the resistance value consequently cause a change in the RC constant of the shallow line. In the example of FIG. 3B, when the depth of the shallow line decreases by 30%, the RC constant of a shallow line per unit length increases by 39%.

(30) In the example of FIG. 3B, the RC constant of a deep line is smaller than the RC constant of a shallow line, in some embodiments, deep lines are selected for forming signal conducting paths which require reduced time delays due to the RC constant of the conducting lines. In the embodiments of FIG. 1, the conducting path **101** between the first active device **D1** and the second active device **D2** is formed by the first layer deep line **112D**, the second layer deep line **123D**, the first layer deep line **115D**, the second layer deep line **128D**, and the first layer deep line **118D**. The conducting path **101** is expected to have a smaller RC constant, as compared with the RC constant of an alternative path formed by a combination of the first layer shallow lines and/or the second layer shallow lines for connecting the first active device **D1** with the second active device **D2**. On the other hand, an alternative conducting path formed by a combination of the first layer shallow lines and/or the second layer shallow lines is expected to have smaller stray capacitances.

(31) Because the properties of a conducting path formed by deep lines are different from the properties of a conducting path formed by shallow lines, the selection of deep lines and shallow lines for various conducting paths in an integrated circuit would allow some performance improvements for the integrated circuit. In some embodiments, conducting paths of interests in an integrated circuit are ranked based on delay time of each conducting path, and the conducting paths having a delay time longer than a critical delay time are selected to form a list of selected paths for speed improvements. In some embodiments, the critical delay time is the delay time corresponding to the slack time that is zero. Here, the slack time is the time that a task can be delayed without

causing another task to be delayed, or without impacting the completion of the overall task of a circuit system. In some embodiments, a selected path from the list for speed improvements is formed based on deep lines (e.g., the conducting path **101** in FIG. **1**). In some embodiments, the auto placement and routing (APR) program is configured to find first layer deep lines and second layer deep lines to form the selected path for speed improvements. In some embodiments, the APR program is also configured to find first layer shallow lines and the second layer shallow lines to form one or more conducting paths which are the subjects of stray capacitance reduction.

(32) In FIGS. **2A-2D**, the first layer deep lines **111D-112D** and the first layer shallow lines **111S-112S** are in a first conductive layer above an insulation layer **205**, and the second layer deep line **123D** and the second layer shallow lines **122S** and **123S** are in a second conductive layer above the first conductive layer. In some embodiments, the insulation layer **205** is a top insulation layer fabricated in the front-end-of-line (FEOL) process, and the first conductive layer (having the first layer deep lines and the first layer shallow lines) is a first metal layer M0 that is immediately above the fabricated transistors in the integrated circuit, while the second conductive layer (having the second layer deep lines and the second layer shallow lines) is a second metal layer M1 that is immediately above the first metal layer M0.

(33) In some alternative embodiments, the insulation layer **205** is the layer of interlayer dielectric that covers the first metal layer M0, and the first conductive layer (having the first layer deep lines and the first layer shallow lines) is a second metal layer M1 that is immediately above the first metal layer M0, while the second conductive layer (having the second layer deep lines and the second layer shallow lines) is a third metal layer M2 that is immediately above second metal layer M1. In still some alternative embodiments, the first conductive layer and the second conductive layer in FIGS. **2A-2D** are correspondingly a fourth metal layer M3 and a third metal layer M2. In still some alternative embodiments, the first conductive layer in FIGS. **2A-2D** is a metal layer above the fourth metal layer M3, while the second conductive layer in FIGS. **2A-2D** is a metal layer above the third metal layer M2. Furthermore, unlike the embodiments of FIGS. **2A-2D** in which the second conductive layer is above the first conductive layer, in some alternative embodiments, the second conductive layer is below the first conductive layer.

(34) In FIGS. **2A-2D**, two conductive layers that have both deep lines and shallow lines are depicted. In some embodiments, however, the integrated circuit **100** in FIG. **1** also include additional conductive layers. Some of the additional conductive layers also have both deep lines and shallow lines, while some of the additional conductive layers of the integrated circuit **100** include only uniform lines. For example, in the embodiments as shown in FIG. **4A-4C**, there are three conductive layers that have both deep lines and shallow lines.

(35) FIGS. **4A-4C** are cross-sectional views of the integrated circuit in FIG. **1**, in accordance with some embodiments. The cross-sectional views in FIGS. **4A-4C** are correspondingly in the same cutting planes as the cross-sectional views in FIGS. **2A-2C**. The cross-sectional views in FIGS. **4A-4C** and FIGS. **2A-2C** have the same first conductive layer and the same second conductive layer. In FIGS. **4A-4C** and FIGS. **2A-2C**, the first conductive layer has the first layer deep lines **111D-112D** and the first layer shallow lines **111S-112S** embedded in the interlayer dielectric **210**, and the second conductive layer has the second layer deep line **123D** and the second layer shallow line **122S** embedded in the interlayer dielectric **220**. In FIGS. **4A-4C**, the third conductive layers is also depicted. The third conductive layer has the third layer deep lines **431D-432D** and the third layer shallow lines **431S-432S** embedded in the interlayer dielectric **430**.

(36) In some alternative embodiments, the stacked positions of the first conductive layer, the second conductive layer, and the third conductive layer are different from the stacked positions as depicted in FIG. **4A-4C**. For example, in some alternative embodiments, the third conductive layer is between the first conductive layer and the second conductive layer. In some alternative embodiments, the third conductive layer is below both the first conductive layer and the second conductive layer. In contrast, the third conductive layer in FIG. **4A-4C** is above both the first

conductive layer and the second conductive layer. Additionally, while the third conductive layer in FIG. 4A-4C is formed with both deep lines and shallow lines, the third conductive layer in some alternative embodiments is formed with only uniform lines. In some alternative embodiments, the third conductive layer with only uniform lines is below both the first conductive layer and the second conductive layer. In some alternative embodiments, the third conductive layer with only uniform lines is between the first conductive layer and the second conductive layer.

(37) In some embodiments, in addition to the three conductive layers depicted in FIG. 4A-4C, the integrated circuit **100** in FIG. 1 also includes more conductive layers which are either formed with uniform lines or formed with both deep lines and shallow lines. In some alternative embodiments, at least two conductive layers are deposited between the first conductive layer and the second conductive layer. Each of the at least two conductive layers are either formed with uniform lines or formed with both deep lines and shallow lines. In some alternative embodiments, at least two conductive layers are deposited above the first conductive layer and the second conductive layer. In some alternative embodiments, at least two conductive layers are deposited below the first conductive layer and the second conductive layer.

(38) In some embodiments, a signal conducting path is formed with a combination of the deep lines in the first conductive layer, in the second conductive layer, and/or in other conductive layers, to reduce the RC constant of the signal conducting path. In some embodiments, a signal conducting path is formed with a combination of the shallow lines in the first conductive layer, in the second conductive layer, and/or in other conductive layers, to reduce the stray capacitances at various segments of the signal conducting path. In some embodiments, a signal conducting path connecting the output of a first active device with the input of a second active device is formed with a combination of the deep lines and the shallow lines in the various conductive layers, to reduce the total time delay of the signal propagation from the first active device to the second active device along the signal conducting path.

(39) FIG. 5 is a layout diagram of an integrated circuit **500** having a signal conducting path formed with a combination of deep lines and shallow lines, in accordance with some embodiments. The integrated circuit **500** includes first layer deep lines and first layer shallow lines extending in the X-direction. The integrated circuit **500** also includes second layer deep lines and second layer shallow lines extending in the Y-direction. The first layer deep lines (**512D**, **513D**, **514D**, **518D**, and **519D**) and the first layer shallow lines (**512S**, **517S**, and **518S**) are in a first conductive layer. The second layer deep lines (**523D**, **525D**, **527D**, and **528D**) and the second layer shallow lines (**522S**, **523S**, **526S**, and **527S**) are in a second conductive layer.

(40) The integrated circuit **500** includes a first active device **D1** and a second active device **D2**. The output of the first active device **D1** is electrically connected to the input of the second active device **D2** through a conducting path that includes a low resistivity portion **501** and a low capacitivity portion **502**. The low resistivity portion **501** of the conducting path includes the first layer deep lines **512D** and **514D** and the second layer deep lines **523D** and **525D**. The low capacitivity portion **502** of the conducting path includes the first layer shallow lines **517S** and **518S** and the second layer shallow line **527S**. In the low resistivity portion **501**, the first layer deep line **512D** is electrically connected to the second layer deep line **523D** through the via-connector **5V1**, the second layer deep line **523D** is electrically connected to the first layer deep line **514D** through the via-connector **5V2**, and the first layer deep line **514D** is electrically connected to the second layer deep line **525D** through the via-connector **5V3**. In the low capacitivity portion **502**, the first layer shallow line **517S** is electrically connected to the second layer shallow line **527S** through the via-connector **5V5**, and the second layer shallow line **527S** is electrically connected to the first layer shallow line **518S** through the via-connector **5V6**.

(41) When the second layer deep line **525D** is electrically connected to the first layer shallow line **517S** through the via-connector **5V4**, the low resistivity portion **501** of the conducting path is electrically connected to the low capacitivity portion **502** of the conducting path. The mutation



point 5MP is at the via-connector 5V4 between the low resistivity portion 501 of the conducting path and the low capacitivity portion 502 of the conducting path. The low resistivity portion 501 is electrically connected between the output of the first active device D1 and the mutation point 5MP, and the low capacitivity portion 502 is electrically connected between the mutation point 5MP and the input of the second active device D2.

(42) The low resistivity portion 501 having the deep lines and the low capacitivity portion 502 having the shallow lines are selected to increase the speed of the signals transmitted from the first active device D1 to the second active device D2, as compared with the speed of the signals in some alternative designs in which the signal path from the first active device D1 to the second active device D2 is formed with uniform lines (which have the depth smaller than the depth of the deep lines but larger than the depth of the shallow lines).

(43) In some embodiments, such as in the embodiments as shown in FIGS. 6A-6F, different configurations of the low resistivity portion, the low capacitivity portion, and the mutation point are compared to find an optimized configuration. In some embodiments, the optimized configuration is selected to reduce the total time delay of the signal propagation from the first active device to the second active device along the signal conducting path. In addition to the total time delay, in some embodiments, the selection of the optimized configuration also includes the balance of other factors, such as electromigration due to the IR-drop and cross couplings due to the stray capacitance.

(44) FIGS. 6A-6F are layout diagrams of integrated circuits having signal conducting paths formed with different configurations of the low resistivity portion, the low capacitivity portion, and the mutation point, in accordance with some embodiments. In each of the layout diagrams in FIGS. 6A-6F, a different position on a signal conducting path is selected as the position for the mutation point. Based on the layout diagrams in FIGS. 6A-6F, different configurations of the signal conducting path are compared, with respect to the reduction of the signal propagation time from the first active device D1 to the second active device D2.

(45) In a first configuration as shown in FIG. 6A, the conducting path from the first active device D1 to the second active device D2 includes a low resistivity portion 601A and a low capacitivity portion 602A. The low resistivity portion 601A includes the first layer deep line 512D. The low capacitivity portion 602A includes the second layer shallow line 522S, the first layer shallow lines 614S, the second layer shallow line 625S, the first layer shallow line 517S, the second layer shallow line 527S, and the first layer shallow line 518S (which are correspondingly connected together through the via-connectors 6V2, 6V3, 6V4, 6V5, and 6V6). The mutation point 6MP is at the via-connector 6V1 that electrically connects the first layer deep line 512D with the second layer shallow line 522S. The low resistivity portion 601A is between the output of the first active device D1 and the mutation point 6MP. The low capacitivity portion 602A is between the mutation point 6MP and the input of the second active device D2.

(46) In a second configuration as shown in FIG. 6B, the conducting path from the first active device D1 to the second active device D2 includes a low resistivity portion 601B and a low capacitivity portion 602B. The low resistivity portion 601B includes the first layer deep line 512D and the second layer deep line 523D connected together through the via-connector 6V1. The low capacitivity portion 602B includes the first layer shallow lines 614S, the second layer shallow line 625S, the first layer shallow line 517S, the second layer shallow line 527S, and the first layer shallow line 518S (which are correspondingly connected together through the via-connectors 6V3, 6V4, 6V5, and 6V6). The mutation point 6MP is at the via-connector 6V2 that electrically connects the second layer deep line 523D with the first layer shallow lines 614S. The low resistivity portion 601B is between the output of the first active device D1 and the mutation point 6MP. The low capacitivity portion 602B is between the mutation point 6MP and the input of the second active device D2.

(47) In a third configuration as shown in FIG. 6C, the conducting path from the first active device

D1 to the second active device D2 includes a low resistivity portion **601C** and a low capacitivity portion **602C**. The low resistivity portion **601C** includes the first layer deep line **512D**, the second layer deep line **523D**, and the first layer deep line **514D** (which are correspondingly connected together through the via-connectors **6V1** and **6V2**). The low capacitivity portion **602C** includes the second layer shallow line **625S**, the first layer shallow line **517S**, the second layer shallow line **527S**, and the first layer shallow line **518S** (which are correspondingly connected together through the via-connectors **6V4**, **6V5**, and **6V6**). The mutation point **6MP** is at the via-connector **6V3** that electrically connects the first layer deep line **514D** with the second layer shallow line **625S**. The low resistivity portion **601C** is between the output of the first active device **D1** and the mutation point **6MP**. The low capacitivity portion **602C** is between the mutation point **6MP** and the input of the second active device **D2**.

(48) In a fourth configuration as shown in FIG. **6D**, the conducting path from the first active device **D1** to the second active device **D2** includes a low resistivity portion **601D** and a low capacitivity portion **602D**. The low resistivity portion **601D** includes the first layer deep line **512D**, the second layer deep line **523D**, the first layer deep line **514D**, and the second layer deep line **525D** (which are correspondingly connected together through the via-connectors **6V1**, **6V2**, and **6V3**). The low capacitivity portion **602D** includes the first layer shallow line **517S**, the second layer shallow line **527S**, and the first layer shallow line **518S** (which are correspondingly connected together through the via-connectors **6V5** and **6V6**). The mutation point **6MP** is at the via-connector **6V4** that electrically connects the second layer deep line **525D** with the first layer shallow line **517S**. The low resistivity portion **601D** is between the output of the first active device **D1** and the mutation point **6MP**. The low capacitivity portion **602D** is between the mutation point **6MP** and the input of the second active device **D2**.

(49) In a fifth configuration as shown in FIG. **6E**, the conducting path from the first active device **D1** to the second active device **D2** includes a low resistivity portion **601E** and a low capacitivity portion **602E**. The low resistivity portion **601E** includes the first layer deep line **512D**, the second layer deep line **523D**, the first layer deep line **514D**, the second layer deep line **525D**, and the first layer deep line **517D** (which are correspondingly connected together through the via-connectors **6V1**, **6V2**, **6V3**, and **6V4**). The low capacitivity portion **602E** includes the second layer shallow line **527S** and the first layer shallow line **518S** electrically connected together through the via-connector **6V6**. The mutation point **6MP** is at the via-connector **6V5** that electrically connects the first layer deep line **517D** with the second layer shallow line **527S**. The low resistivity portion **601E** is between the output of the first active device **D1** and the mutation point **6MP**. The low capacitivity portion **602E** is between the mutation point **6MP** and the input of the second active device **D2**.

(50) In a sixth configuration as shown in FIG. **6F**, the conducting path from the first active device **D1** to the second active device **D2** includes a low resistivity portion **601F** and a low capacitivity portion **602F**. The low resistivity portion **601F** includes the first layer deep line **512D**, the second layer deep line **523D**, the first layer deep line **514D**, the second layer deep line **525D**, the first layer deep line **517D**, and the second layer deep line **527D** (which are correspondingly connected together through the via-connectors **6V1**, **6V2**, **6V3**, and **6V4**, and **6V5**). The low capacitivity portion **602F** includes the first layer shallow line **518S**. The mutation point **6MP** is at the via-connector **6V6** that electrically connects the second layer deep line **527D** with the first layer shallow line **518S**. The low resistivity portion **601F** is between the output of the first active device **D1** and the mutation point **6MP**. The low capacitivity portion **602F** is between the mutation point **6MP** and the input of the second active device **D2**.

(51) In some embodiments, the auto placement and routing (APR) program compares the total time delay of the signal propagation from the first active device **D1** to the second active device **D2** in each of the configurations in FIGS. **6A-6F**, and the APR program then selects one of the configurations in FIGS. **6A-6F** which has the smallest total time delay of the signal propagation.

The mutation point 6MP selected by the APR program is at one of the via-connectors (such as 6V1, 6V2, 6V3, 6V4, 6V5, or 6V6).

(52) In some embodiments, multiple signal conducting paths share a common portion of the signal conducting paths. The selection of the mutation point for each signal conducting path involves the comparison of the total time delay of the signal propagation in each signal conducting path with different configurations.

(53) FIG. 7 is a layout diagram of an integrated circuit 700 having multiple signal conducting paths formed with combinations of deep lines and shallow lines, in accordance with some embodiments. In FIG. 7, the output of the first active device D1 is electrically connected to the input of the second active device D2 through a first conducting path that includes a low resistivity portion 701 and a low capacitivity portion 702, and the output of the first active device D1 is electrically connected to the input of the third active device D3 through a second conducting path that includes a low resistivity portion 703 and a low capacitivity portion 704.

(54) In FIG. 7, the low resistivity portion 701 of the first conducting path in FIG. 7 is the same as the low resistivity portion 501 in FIG. 5. The low capacitivity portion 702 of the first conducting path in FIG. 7 is the same as the low capacitivity portion 502 in FIG. 5. The first mutation point 7MP1 for the first conducting path in FIG. 7 is at the via-connector 5V4. The low resistivity portion 701 is electrically connected between the output of the first active device D1 and first mutation point 7MP1, and the low capacitivity portion 702 is electrically connected between the first mutation point 7MP1 and the input of the second active device D2.

(55) In FIG. 7, the low resistivity portion 703 of the second conducting path includes the first layer deep line 512D, the second layer deep line 523D, the first layer deep line 514D, and the second layer deep line 525D (which are correspondingly connected together through the via-connectors 5V1, 5V2, and 5V3). The low capacitivity portion 704 of the second conducting path includes the first layer shallow line 715S, the second layer shallow line 727S, and the first layer shallow line 718S (which are correspondingly connected together through the via-connectors 7V5 and 7V6). The second mutation point 7MP2 for the second conducting path in FIG. 7 is at the via-connector 7V4 that electrically connects the second layer deep line 525D with the first layer shallow line 715S. The low resistivity portion 703 is electrically connected between the output of the first active device D1 and second mutation point 7MP2, and the low capacitivity portion 704 is electrically connected between the second mutation point 7MP2 and the input of the third active device D3.

(56) In FIG. 7, when the first conducting path is from the first active device D1 to the second active device D2 and the second conducting path is from the first active device D1 to the third active device D3, the first conducting path and the second conducting path share a common conducting path which is from the output of the first active device D1 to the second layer deep line 525D. Here, the second layer deep line 525D is a fan-out node which branches the common conducting path into the first conducting path and the second conducting path. The low capacitivity portion 702 of the first conducting path forms at least a portion of a first branched conducting path between the fan-out node and the input of the second active device D2. The low capacitivity portion 704 of the second conducting path forms at least a portion of a second branched conducting path between the fan-out node and the input of the third active device D3. Each of first branched conducting path and the second branched conducting path is a conducting path that excludes first layer deep lines and second layer deep lines. In some embodiments, each branched conducting path not only excludes deep lines in the first conducting layer and in the second conducting layer, but also excludes deep lines in other conducting layers. In some embodiments, while each branched conducting path excludes deep lines in the first conducting layer and in the second conducting layer, each branched conducting path nevertheless includes deep lines in one or more other conducting layers.

(57) In each of the conducting path from the first active device D1 to the second active device D2 in FIG. 1, FIG. 5, and FIGS. 6A-6F, a mutation point is between a low resistivity portion of the

conducting path and a low capacitivity portion of the conducting path. In some embodiments, the mutation point is at a via-connector. In some embodiments, such as in each of the conducting paths in FIGS. **8A-8B**, the mutation point is a fan-out node that joins at least two branched conducting paths, and each of the at least two branched conducting paths includes a low capacitivity portion of the conducting path.

(58) FIGS. **8A-8B** are schematic diagrams of integrated circuits having multiple signal conducting paths formed with combinations of deep lines and shallow lines, in accordance with some embodiments. In FIG. **8A**, a first conducting path from the first active device **D1** to the second active device **D2** includes a low resistivity portion and a low capacitivity portion. The low resistivity portion of the first conducting path includes a first layer deep line **862D** and a second layer deep line **872D** electrically connected together through a via-connector **8V67**. The low capacitivity portion of the first conducting path includes a first layer shallow line **868S** and a second layer shallow line **878S** electrically connected together through a via-connector **8V76**. The first layer deep line **862D** and the first layer shallow line **868S** are in a first conductive layer. The second layer deep line **872D** and the second layer shallow line **878S** are in a second conductive layer. In some embodiments, the integrated circuits includes at least eight metal layers (from **M0** to **M7**) above the top insulation layer fabricated in the front-end-of-line (FEOL) process. The first conductive layer is the seventh metal layer **M6** (which is above the other six metal layers **M0-M5**), and the second conductive layer is the eighth metal layer **M7** (which is above the other seven metal layers **M0-M6**).

(59) In FIG. **8A**, the low resistivity portion of the first conducting path is electrically connected with the low capacitivity portion of the first conducting path through the second layer conducting line **874**. In some embodiments, the second layer conducting line **874** is a second layer deep line. In some embodiments, the second layer conducting line **874** is a second layer shallow line. In some embodiments, the second layer conducting line **874** is a second layer uniform line (which has a depth that is larger than the depth of a second layer shallow line but smaller than the depth of a second layer deep line). In FIG. **8A**, the second layer conducting line **874** is a fan-out node. The first conducting path includes a first mutation point **8MP1** at the fan-out node between the low resistivity portion and the low capacitivity portion. The second conducting path from the first active device **D1** to the third active device **D3** branches out from the first conducting path (which is from the first active device **D1** to the second active device **D2**) at the fan-out node (i.e., the second layer conducting line **874**). The second conducting path includes a low resistivity portion and a low capacitivity portion. The low resistivity portion is between the first active device **D1** and a second mutation point **8MP2** at the fan-out node. The low capacitivity portion is between the second mutation point **8MP2** and the input of the third active device **D3**. The low resistivity portion of the second conducting path includes the first layer deep line **862D** and the second layer deep line **872D**. The low capacitivity portion of the second conducting path includes a first layer shallow line **866S** and a second layer shallow line **876S** electrically connected together through a corresponding via-connector.

(60) In some embodiments, in addition to the first layer deep line **862D** in the seventh metal layer **M6** and the second layer deep line **872D** in the eighth metal layer **M7**, the low resistivity portion of the first conducting path also includes conducting lines **822D**, **832D**, **842D**, and **852D** electrically connected together through the corresponding via-connectors **8V23**, **8V34**, and **8V45**. The conducting line **852D** is electrically connected to the first layer deep line **862D** through the via-connector **8V56**. The conducting line **822D** is electrically connected to the output of the first active device **D1**. In some embodiments, the conducting line **822D** is electrically connected to the output of the first active device **D1** through some via-connectors and the conducting lines in the first metal layer **M0** and in the second metal layer **M1** (which are not shown in the figure). In some embodiments, the conducting line **822D** is a deep line in the third metal layer **M2**, the conducting line **832D** is a deep line in the fourth metal layer **M3**, the conducting line **842D** is a deep line in the

fifth metal layer M4, and the conducting line **852D** is a deep line in the sixth metal layer M5. In some embodiments, one or more of the conducting lines **822D**, **832D**, **842D**, and **852D** are not deep lines. In some embodiments, one or more of the conducting lines **822D**, **832D**, **842D**, and **852D** are shallow lines or uniform lines.

(61) In some embodiments, in addition to the first layer shallow line **868S** in the seventh metal layer M6 and the second layer shallow line **878S** in the eighth metal layer M7, the low capacitivity portion of the first conducting path connecting to the second active device D2 also includes conducting lines **828S**, **838S**, **848S**, and **858S** electrically connected together through the corresponding via-connectors **8V32**, **8V43**, and **8V54**. The conducting line **858S** is electrically connected to the first layer shallow line **868S** through the via-connector **8V65**. The conducting line **828S** is electrically connected to the input of the second active device D2. In some embodiments, the conducting line **828S** is electrically connected to the input of the second active device D2 through some via-connectors and some conducting lines in the first metal layer M0 and in the second metal layer M1 (which are not shown in the figure). In some embodiments, the conducting line **828S** is a shallow line in the third metal layer M2, the conducting line **838S** is a shallow line in the fourth metal layer M3, the conducting line **848S** is a shallow line in the fifth metal layer M4, and the conducting line **858S** is a shallow line in the sixth metal layer M5. In some embodiments, one or more of the conducting lines **828S**, **838S**, **848S**, and **858S** are not shallow lines. In some embodiments, one or more of the conducting lines **828S**, **838S**, **848S**, and **858S** are deep lines or uniform lines.

(62) In some embodiments, in addition to the first layer shallow line **866S** in the seventh metal layer M6 and the second layer shallow line **876S** in the eighth metal layer M7, the low capacitivity portion of the second conducting path connecting to the third active device D3 also includes conducting lines **826S**, **836S**, **846S**, and **856S** electrically connected together through various via-connectors. The conducting line **856S** is electrically connected to the first layer shallow line **866S** through a corresponding via-connector. The conducting line **826S** is electrically connected to the input of the third active device D3. In some embodiments, the conducting line **826S** is electrically connected to the input of the third active device D3 through some via-connectors and some conducting lines in the first metal layer M0 and in the second metal layer M1. In some embodiments, the conducting line **826S** is a shallow line in the third metal layer M2, the conducting line **836S** is a shallow line in the fourth metal layer M3, the conducting line **846S** is a shallow line in the fifth metal layer M4, and the conducting line **856S** is a shallow line in the sixth metal layer M5. In some embodiments, one or more of the conducting lines **826S**, **836S**, **846S**, and **856S** are not shallow lines. In some embodiments, one or more of the conducting lines **826S**, **836S**, **846S**, and **856S** are deep lines or uniform lines.

(63) When the first conducting path from the first active device D1 to the second active device D2 is implemented with a low resistivity portion and a low capacitivity portion, the time delay of the signal propagation along the first conducting path is reduced. In one specific example as shown in FIG. 8A, the time delay of the signal propagation in the first conducting path having the low resistivity portion and the low capacitivity portion is reduced by 5.4%, as compared with an alternative design in which all conducting lines in the first conducting path are implemented as uniform lines. The 5.4% reduction is a sum of the individual reductions 1.5%, 1.8%, 0.2%, 0.4%, 0.4%, and 1.1% correspondingly in metal layers M7, M6, M5, M4, M3, and M2.

(64) In the specific example as shown in FIG. 8A, the second layer deep line **872D** in the low resistivity portion and the second layer shallow line **878S** in the low capacitivity portion are in the eighth metal layer M7. The reduction of the time delay due to the second layer deep line **872D** and the second layer shallow line **878S** is 1.5%, as compared with the alternative design of uniform conducting lines. In the specific example as shown in FIG. 8A, the first layer deep line **862D** in the low resistivity portion and the first layer shallow line **868S** in the low capacitivity portion are in the seventh metal layer M6. The reduction of the time delay due to the first layer deep line **862D** and

the first layer shallow line **868S** is 1.8%, as compared with the alternative design of uniform conducting lines.

(65) In the specific example as shown in FIG. **8A**, the deep line **852D** and the shallow line **858S** are in the sixth metal layer M5. The reduction of the time delay due to the deep line **852D** and the shallow line **858S** is 0.2%, as compared with the alternative design of uniform conducting lines. In the specific example as shown in FIG. **8A**, the deep line **842D** and the shallow line **848S** are in the fifth metal layer M4. The reduction of the time delay due to the deep line **842D** and the shallow line **848S** is 0.4%, as compared with the alternative design of uniform conducting lines. In the specific example as shown in FIG. **8A**, the deep line **832D** and the shallow line **838S** are in the fourth metal layer M3. The reduction of the time delay due to the deep line **832D** and the shallow line **838S** is 0.4%, as compared with the alternative design of uniform conducting lines. In the specific example as shown in FIG. **8A**, the deep line **822D** and the shallow line **828S** are in the third metal layer M2. The reduction of the time delay due to the deep line **822D** and the shallow line **828S** is 1.1%, as compared with the alternative design of uniform conducting lines.

(66) In the embodiments as shown in FIG. **8A**, the reduction of the time delay of the signal propagation in the first conducting path includes the contributions from the time delay reductions in metal layers M7, M6, M5, M4, M3, and M2. In some embodiments, such as in the specific example in FIG. **8B**, the reduction of the time delay of the signal propagation in the first conducting path is dominated by the time delay reductions in the first conductive layer and in the second conductive layer, when the low resistivity portion and the low capacitivity portion of the first conducting path implemented in the first conductive layer and the second conductive layer have a total length much larger than the total length of the conducting lines for the same path in all other conductive layers. In FIG. **8B**, the first conductive layer is in the ninth metal layer M8, and the second conductive layer is in the tenth metal layer M9.

(67) In FIG. **8B**, the first conducting path from the first active device D1 to the second active device D2 includes a low resistivity portion and a low capacitivity portion. The low resistivity portion of the first conducting path includes a first layer deep line **882D** in the ninth metal layer M8 and a second layer deep line **892D** in the tenth metal layer M9. The first layer deep line **882D** and the second layer deep line **892D** are electrically connected together through the via-connector **8V89**. The first layer deep line **882D** in the low resistivity portion is electrically connected to the output of the first active device D1 through the via-connector **8V78** and through other via-connectors/conducting lines in various metal layers (from M0 to M7). The low capacitivity portion of the first conducting path includes a first layer shallow line **888S** in the ninth metal layer M8 and a second layer shallow line **898S** in the tenth metal layer M9. The first layer shallow line **888S** and the second layer shallow line **898S** are electrically connected together through the via-connector **8V98**. The first layer shallow line **888S** in the low capacitivity portion is electrically connected to the input of the second active device D2 through the via-connector **8V87** and through other via-connectors/conducting lines in various metal layers (from M0 to M7).

(68) In FIG. **8B**, the low resistivity portion of the first conducting path is electrically connected with the low capacitivity portion of the first conducting path through the second layer conducting line **894**. In some embodiments, the second layer conducting line **894** is a second layer deep line. In some embodiments, the second layer conducting line **894** is a second layer shallow line. In some embodiments, the second layer conducting line **894** is a second layer uniform line. The second layer conducting line **894** is a fan-out node. The first conducting path (which is from the first active device D1 to the second active device D2) and the second conducting path (which is from the first active device D1 to the third active device D3) branch out from each other at the fan-out node (i.e., the second layer conducting line **894**).

(69) In FIG. **8B**, the second conducting path also includes a low resistivity portion and a low capacitivity portion. The low resistivity portion is between the first active device D1 and the second layer conducting line **894**. The low capacitivity portion is between the second layer conducting line

**894** and the third active device **D3**. The low resistivity portion of the second conducting path includes the first layer deep line **882D** and the second layer deep line **892D**. The low capacitivity portion of the second conducting path includes a first layer shallow line **886S** and a second layer shallow line **896S** electrically connected together through a corresponding via-connector.

(70) In FIG. **8B**, when the first conducting path from the first active device **D1** to the second active device **D2** is implemented with a low resistivity portion and a low capacitivity portion, the time delay of the signal propagation along the first conducting path is reduced. In the specific example as shown in FIG. **8B**, the reduction of the time delay of the signal propagation in the first conducting path is dominated by the time delay reductions in the ninth metal layer **M8** and in the tenth metal layer **M9**. In the specific example as shown in FIG. **8B**, the reduction of the time delay due to the first layer deep line **882D** and the first layer shallow line **888S** in the ninth metal layer **M8** is 2.8%, as compared with the alternative design of uniform conducting lines. In the specific example as shown in FIG. **8B**, the reduction of the time delay due to the second layer deep line **892D** and the second layer shallow line **898S** in the tenth metal layer **M9** is 2.0%, as compared with the alternative design of uniform conducting lines. In the specific example as shown in FIG. **8B**, the total time delay of the signal propagation in the first conducting path is reduced by 4.7%, as compared with an alternative design in which all conducting lines in the first conducting path are implemented as uniform lines.

(71) In some embodiments, when the total length of the first conducting path from the first active device **D1** to the second active device **D2** is smaller than a predetermined distance, each of the conducting lines in the first conducting path is implemented as a deep line. In some embodiments, the value of the predetermined distance that is used by the APR program is set by the user. In some embodiments, the value of the predetermined distance that is used by the APR program is read from a database or a technology file.

(72) In some embodiments, as shown in FIG. **9**, the output of the first active device **D1** is electrically coupled to multiple receiving devices (such as **D2A**, **D2B**, **D2C**, and **D2D**). In some embodiments, when the total length of a conducting path from the first active device **D1** to each receiving device (such as **D2A**, **D2B**, **D2C**, or **D2D**) is smaller than a predetermined distance, the conducting lines in all of the conducting paths from the output of the first active device **D1** to the multiple receiving devices **D2A-D2D** are implemented with deep lines in at least two conductive layers. In FIG. **9**, the conducting paths from the first active device **D1** to the multiple receiving devices **D2A-D2D** breach out at the fan-out node, which is the conducting line **934D**. The common portion of the conducting paths from first active device **D1** to the multiple receiving devices **D2A-D2D** is from the output of the first active device **D1** to the conducting line **934D**.

(73) In FIG. **9**, the common portion of the conducting paths includes the first layer deep line **922D** in the third metal layer **M2** and the second layer deep line **932D** in the fourth metal layer **M3**. The first layer deep line **922D** and the second layer deep line **932D** are electrically connected together through the via-connector **9V23**. The first layer deep line **922D** is electrically connected to the output of the first active device **D1** through various via-connectors and various conducting lines (which include the deep line **912D** in the second metal layer **M1**). The common portion of the conducting paths is electrically connected to the branched path to each receiving device (such as **D2A**, **D2B**, **D2C**, or **D2D**) through the conducting line **934D**. In FIG. **9**, the conducting line **934D** is implemented as a deep line in the fourth metal layer **M3**.

(74) In FIG. **9**, the branched path to each receiving device (such as **D2A**, **D2B**, **D2C**, or **D2D**) includes a deep line (correspondingly **929D**, **928D**, **927D**, or **926D**) in the third metal layer **M2** and a deep line (correspondingly **939D**, **938D**, **937D**, or **936D**) in the fourth metal layer **M3**. Each of the deep lines **939D**, **938D**, **937D**, and **936D** is electrically connected between the fan-out node (i.e., the conducting line **934D**) and one of the corresponding deep lines **929D**, **928D**, **927D**, or **926D**. Each of the deep lines **929D**, **928D**, **927D**, and **926D** is electrically connected to the input of one of the corresponding receiving devices **D2A**, **D2B**, **D2C**, or **D2D** through various via-

connectors and various conducting lines (such as through one of the corresponding deep lines **919D**, **918D**, **917D**, or **916D** in the second metal layer **M1**).

(75) In FIG. **9**, when the total length of the deep lines in the metal layers **M2** and **M3** for the conducting path from the first active device **D1** to a receiving device (such as **D2A**, **D2B**, **D2C**, or **D2D**) is longer than the total length of the conducting lines for the same conducting path in all other conductive layers, the reduction of the time delay of the signal propagation in the conducting path to each receiving device is dominated by the time delay reductions in the third metal layer **M2** and in the fourth metal layer **M3**.

(76) In the specific example as shown in FIG. **9**, the reduction of the time delay due to the deep line **922D** in the third metal layer **M2** is 2.7%, and the reduction of the time delay due to the deep line **932D** in the fourth metal layer **M3** is 1.1%, as compared with the alternative design of uniform conducting lines. In the specific example as shown in FIG. **9**, the reduction of the time delay due to the deep line (**929D**, **928D**, **927D**, or **926D**) in the third metal layer **M2** on a branched path is 0.2%, and the reduction of the time delay due to the deep line (**939D**, **938D**, **937D**, or **936D**) in the fourth metal layer **M3** on a branched path is -0.3%, as compared with the alternative design of uniform conducting lines. In the specific example as shown in FIG. **9**, the total time delay of the signal propagation in the conducting path from the first active device **D1** to one of the receiving devices (such as **D2A**, **D2B**, **D2C**, or **D2D**) is reduced by 3.7%, as compared with an alternative design in which all conducting lines in the conducting path are implemented as uniform lines.

(77) FIG. **10** is a flowchart of a method **1000** of manufacturing an integrated circuit, in accordance with some embodiments. The sequence in which the operations of method **1000** are depicted in FIG. **10** is for illustration only; the operations of method **1000** are capable of being executed in sequences that differ from that depicted in FIG. **10**. It is understood that additional operations may be performed before, during, and/or after the method **1000** depicted in FIG. **10**, and that some other processes may only be briefly described herein.

(78) In operation **1010** of method **1000**, a conducting path connecting a first active with a second active device is selected. In some embodiments, the selected conducting path is selected for speed improvements, because the selected conducting path has a delay time that is longer than a critical delay time if the selected conducting path is implemented with uniform lines.

(79) In operation **1015** of method **1000**, the length the conducting path is compared in an APR program with a predetermined value. If the length the conducting path is smaller than the predetermined value, the process flow of method **1000** proceeds to operation **1018**. On the other hand, if the length the conducting path is not smaller than the predetermined value, the process flow of method **1000** proceeds to operation **1020**.

(80) In operation **1018** of method **1000**, which follows the flow of the decision “YES” from operation **1015**, deep lines are selected for the conducting path in at least two conductive layers. In the example embodiments of FIG. **9**, when the total length of a conducting path from the first active device **D1** to each receiving device (such as **D2A**, **D2B**, **D2C**, or **D2D**) is smaller than a predetermined distance, the conducting lines in the metal layers **M2** and **M3** for all of the conducting paths from the output of the first active device **D1** to the multiple receiving devices **D2A-D2D** are implemented with deep lines.

(81) In operation **1020** of method **1000**, which follows the flow of the decision “NO” from operation **1015**, a group of mutation point candidates is generated. In the example embodiments of FIGS. **6A-6F**, the group of mutation point candidates include the via-connectors **6V1**, **6V2**, **6V3**, **6V4**, **6V5**, and **6V6**. In some example embodiments, one or more mutation point candidates is at a fan-out node. Examples of the fan-out node include the second layer deep line **525D** in FIG. **7**, the second layer conducting line **874** in FIG. **8A**, or the second layer conducting line **894** in FIG. **8B**.

(82) In operation **1030** of method **1000**, evaluating time delays of a signal propagation in the conducting path for at least two mutation point candidates are evaluated. In the example embodiments of FIGS. **6A-6F**, the time delay of a signal propagation in the conducting path is



evaluated for each of the situations when one of the via-connectors **6V1**, **6V2**, **6V3**, **6V4**, **6V5**, and **6V6** is selected as the mutation point **6MP**. In some embodiments, only some of the via-connectors **6V1**, **6V2**, **6V3**, **6V4**, **6V5**, and **6V6** are evaluated for implementing as the mutation point **6MP**.

(83) In operation **1040** of method **1000**, a mutation point candidate having a smallest time delay is selected as a mutation point, based on time delays obtained in operation **1030**. In the example embodiments of FIGS. **6A-6F**, after each of the via-connectors **6V1**, **6V2**, **6V3**, **6V4**, **6V5**, and **6V6** are evaluated for implementing as the mutation point **6MP**, the mutation point candidate that has the smallest time delay is selected. In one example, when the via-connectors **6V4** is selected as the mutation point **6MP**, the conducting path from the first active device **D1** to the second active device **D2** has the smallest time delay. In the example embodiments of FIGS. **8A-8B**, the selected mutation point is at a fan-out node (i.e., the second layer conducting line **874** in FIG. **8A**, or the second layer conducting line **894** in FIG. **8B**).

(84) In some embodiments, after the mutation point is selected, the layout patterns for a low resistivity portion of the conducting path and the layout patterns for a low capacitivity portion of the conducting path are generated by an APR program. Then, the process flow proceeds to operation **1050**.

(85) In operation **1050** of method **1000**, a low resistivity portion and a low capacitivity portion of the conducting path are fabricated. The low resistivity portion of the conducting path includes one or more deep lines between the output of the first active device and the mutation point. The low capacitivity portion of the conducting path includes one or more shallow lines between the mutation point and the input of the second active device. In the example embodiments of FIG. **6D**, the low resistivity portion **601D** fabricated in operation **1050** includes the first layer deep line **512D**, the second layer deep line **523D**, the first layer deep line **514D**, and the second layer deep line **525D**. In the example embodiments of FIG. **6D**, the low capacitivity portion **602D** fabricated in operation **1050** includes the first layer shallow line **517S**, the second layer shallow line **527S**, and the first layer shallow line **518S**. In the example embodiments of FIG. **6D**, the low resistivity portion **601D** is between the output of the first active device **D1** and the mutation point **6MP**, and the low capacitivity portion **602D** is between the mutation point **6MP** and the input of the second active device **D2**.

(86) FIG. **11** is a flowchart of a method **1100** of fabricating at least one deep line and at least one shallow line, in accordance with some embodiments. The sequence in which the operations of method **1100** are depicted in FIG. **11** is for illustration only; the operations of method **1100** are capable of being executed in sequences that differ from that depicted in FIG. **11**. It is understood that additional operations may be performed before, during, and/or after the method **1100** depicted in FIG. **11**, and that some other processes may only be briefly described herein.

(87) FIGS. **12A-12E** are cross-sectional views of example device structures fabricated during the operations of the method **1100**, in accordance with some embodiments. The cross-sectional views of the integrated circuit in FIG. **6F** within the cutting planes **MM'** and **NN'** (correspondingly specified by the lines **MM'** and **NN'** in FIG. **6F**) are depicted in FIG. **12E**. In the cross-sectional view in the cutting plane **NN'** of FIG. **12E**, the first layer shallow line **518S** and the first layer deep lines **517D-519D** embedded in the interlayer dielectric **210** are fabricated above an insulation layer **205**. The depth of each first layer deep line (e.g., **517D**, **518D**, **519D**) is larger than the depth of the first layer shallow line **518S**. The interlayer dielectric **220** is deposited above the interlayer dielectric **210** and above the first layer deep lines and the first layer shallow lines. The second layer deep line **527D** extending along the Y-direction is embedded in the interlayer dielectric **220**. Furthermore, the second layer deep line **527D** is electrically connected to the first layer shallow line **518S** through the via-connector **6V6** and electrically connected to the first layer deep line **517D** through the via-connector **6V5**.

(88) In the cross-sectional view in the cutting plane **MM'** of FIG. **12E**, the first layer shallow line

**518S** embedded in the interlayer dielectric **210** is fabricated above the insulation layer **205**. The interlayer dielectric **220** is deposited above the interlayer dielectric **210** and above the first layer shallow line **518S**. The second layer shallow lines **526S-527S** and the second layer deep lines **527D-528D** are fabricated in the interlayer dielectric **220** above the interlayer dielectric **210**. Furthermore, the second layer deep line **527D** is electrically connected to the first layer shallow line **518S** through the via-connector **6V6**.

(89) The method **1100** in FIG. **11** includes operations **1110**, **1120**, **1130**, **1140**, **1150**, **1160**, and **1170**. In operation **1110** of method **1100**, a first insulation layer is deposited on another base insulation layer. In some embodiments, the deposition processes include chemical vapor deposition (CVD), physical vapor deposition (PVD), atomic layer deposition (ALD), sputtering or another suitable deposition process. In some embodiments, the base insulation layer is a top insulation layer fabricated in the front-end-of-line (FEOL) process. In some embodiments, the base insulation layer is one of the interlayer dielectric (ILD) layers fabricated after the FEOL process. In one example embodiment, as shown in FIG. **12A**, the interlayer dielectric **210** is deposited atop the insulation layer **205**.

(90) In operation **1120** of method **1100**, deep trenches and shallow trenches are formed in the first insulation layer. In some embodiments, the patterns of the deep trenches and the shallow trenches are defined by a mask layer fabricated above the first insulation layer with lithography techniques. In some embodiments, the etching processes for forming the deep trenches and the shallow trenches include deep reactive-ion etching or another suitable etching process. In one example embodiment, as shown in FIG. **12A**, shallow trench **1218S** and deep trenches **1217D-1219D** are formed in the interlayer dielectric **210**.

(91) In operation **1130** of method **1100**, first layer deep lines are formed in the deep trenches and first layer shallow lines are formed in the shallow trenches. In some embodiments, metallic materials are deposited into the deep trenches and the shallow trenches, and followed by a polish process, such as chemical mechanical polishing (CMP) process, for planarization and for removing the excess metallic materials. In some embodiments, the deposition processes for metallic materials include chemical vapor deposition (CVD), physical vapor deposition (PVD), atomic layer deposition (ALD), sputtering or another suitable deposition process. In one example embodiment, as shown in FIG. **12B**, after metallic materials are deposited into the shallow trench **1218S** and the deep trenches **1217D-1219D** (as shown in FIG. **12A**), the first layer shallow line **518S** and the first layer deep lines **517D-519D** are formed in the interlayer dielectric **210**.

(92) In operation **1140** of method **1100**, a second insulation layer is deposited above the first insulation layer. In some embodiments, the deposition processes include chemical vapor deposition (CVD), physical vapor deposition (PVD), atomic layer deposition (ALD), sputtering or another suitable deposition process. In one example embodiment, as shown in FIG. **12C**, the interlayer dielectric **210** is deposited atop the interlayer dielectric **210**.

(93) In operation **1150** of method **1100**, via openings are formed in the second insulation layer. In operation **1160** of method **1100**, deep trenches and shallow trenches are formed in the second insulation layer. In some embodiments, the via openings, the deep trenches, and the shallow trenches are formed in multiple steps of pattern formation processes and etching processes. In some embodiments, pattern formation processes includes forming a mask layer above the second insulation layer with lithography techniques. In some embodiments, the etching processes for forming via openings, the deep trenches, and the shallow trenches include deep reactive-ion etching or another suitable etching process. In one example embodiment, as shown in FIG. **12D**, the via openings **12V5-12V6**, the shallow trenches **1226S-1227S**, and the deep trenches **1227D-1228D** are formed in the interlayer dielectric **220**.

(94) In operation **1170** of method **1100**, metallic materials are deposited into the via openings, the deep trenches, and the shallow trenches, whereby second layer deep lines and second layer shallow lines are correspondingly formed in the deep trenches and the shallow trenches in the second

insulation layer. In one example embodiment, as shown in FIG. 12E, after metallic materials are deposited into the via openings **12V5-12V6** (in FIG. 12D) and deposited into the shallow trenches **1226S-1227S** and the deep trenches **1227D-1228D** (in FIG. 12D), the second layer shallow lines **526S-527S** and the second layer deep lines **527D-528D** are formed in the interlayer dielectric **220**. In addition, the via-connector **6V5** is formed connecting the second layer deep line **527D** with the first layer deep line **517D**, and the via-connector **6V5** is formed connecting the second layer deep line **527D** with the first layer shallow line **518S**.

(95) FIG. 13 is a block diagram of an electronic design automation (EDA) system **1300** in accordance with some embodiments.

(96) In some embodiments, EDA system **1300** includes an APR system. Methods described herein of designing layout diagrams represent wire routing arrangements, in accordance with one or more embodiments, are implementable, for example, using EDA system **1300**, in accordance with some embodiments.

(97) In some embodiments, EDA system **1300** is a general purpose computing device including a hardware processor **1302** and a non-transitory, computer-readable storage medium **1304**. Storage medium **1304**, among other things, is encoded with, i.e., stores, computer program code **1306**, i.e., a set of executable instructions. Execution of instructions **1306** by hardware processor **1302** represents (at least in part) an EDA tool which implements a portion or all of the methods described herein in accordance with one or more embodiments (hereinafter, the noted processes and/or methods).

(98) Processor **1302** is electrically coupled to computer-readable storage medium **1304** via a bus **1308**. Processor **1302** is also electrically coupled to an I/O interface **1310** by bus **1308**. A network interface **1312** is also electrically connected to processor **1302** via bus **1308**. Network interface **1312** is connected to a network **1314**, so that processor **1302** and computer-readable storage medium **1304** are capable of connecting to external elements via network **1314**. Processor **1302** is configured to execute computer program code **1306** encoded in computer-readable storage medium **1304** in order to cause system **1300** to be usable for performing a portion or all of the noted processes and/or methods. In one or more embodiments, processor **1302** is a central processing unit (CPU), a multi-processor, a distributed processing system, an application specific integrated circuit (ASIC), and/or a suitable processing unit.

(99) In one or more embodiments, computer-readable storage medium **1304** is an electronic, magnetic, optical, electromagnetic, infrared, and/or a semiconductor system (or apparatus or device). For example, computer-readable storage medium **1304** includes a semiconductor or solid-state memory, a magnetic tape, a removable computer diskette, a random access memory (RAM), a read-only memory (ROM), a rigid magnetic disk, and/or an optical disk. In one or more embodiments using optical disks, computer-readable storage medium **1304** includes a compact disk-read only memory (CD-ROM), a compact disk-read/write (CD-R/W), and/or a digital video disc (DVD).

(100) In one or more embodiments, storage medium **1304** stores computer program code **1306** configured to cause system **1300** (where such execution represents (at least in part) the EDA tool) to be usable for performing a portion or all of the noted processes and/or methods. In one or more embodiments, storage medium **1304** also stores information which facilitates performing a portion or all of the noted processes and/or methods. In one or more embodiments, storage medium **1304** stores library **1307** of standard cells including such standard cells as disclosed herein. In one or more embodiments, storage medium **1304** stores one or more layout diagrams **1309** corresponding to one or more layouts disclosed herein.

(101) EDA system **1300** includes I/O interface **1310**. I/O interface **1310** is coupled to external circuitry. In one or more embodiments, I/O interface **1310** includes a keyboard, keypad, mouse, trackball, trackpad, touchscreen, and/or cursor direction keys for communicating information and commands to processor **1302**.

(102) EDA system **1300** also includes network interface **1312** coupled to processor **1302**. Network interface **1312** allows system **1300** to communicate with network **1314**, to which one or more other computer systems are connected. Network interface **1312** includes wireless network interfaces such as BLUETOOTH, WIFI, WIMAX, GPRS, or WCDMA; or wired network interfaces such as ETHERNET, USB, or IEEE-1364. In one or more embodiments, a portion or all of noted processes and/or methods, is implemented in two or more systems **1300**.

(103) System **1300** is configured to receive information through I/O interface **1310**. The information received through I/O interface **1310** includes one or more of instructions, data, design rules, libraries of standard cells, and/or other parameters for processing by processor **1302**. The information is transferred to processor **1302** via bus **1308**. EDA system **1300** is configured to receive information related to a UI through I/O interface **1310**. The information is stored in computer-readable medium **1304** as user interface (UI) **1342**.

(104) In some embodiments, a portion or all of the noted processes and/or methods is implemented as a standalone software application for execution by a processor. In some embodiments, a portion or all of the noted processes and/or methods is implemented as a software application that is a part of an additional software application. In some embodiments, a portion or all of the noted processes and/or methods is implemented as a plug-in to a software application. In some embodiments, at least one of the noted processes and/or methods is implemented as a software application that is a portion of an EDA tool. In some embodiments, a portion or all of the noted processes and/or methods is implemented as a software application that is used by EDA system **1300**. In some embodiments, a layout diagram which includes standard cells is generated using a tool such as VIRTUOSO® available from CADENCE DESIGN SYSTEMS, Inc., or another suitable layout generating tool.

(105) In some embodiments, the processes are realized as functions of a program stored in a non-transitory computer readable recording medium. Examples of a non-transitory computer readable recording medium include, but are not limited to, external/removable and/or internal/built-in storage or memory unit, e.g., one or more of an optical disk, such as a DVD, a magnetic disk, such as a hard disk, a semiconductor memory, such as a ROM, a RAM, a memory card, and the like.

(106) FIG. **14** is a block diagram of an integrated circuit (IC) manufacturing system **1400**, and an IC manufacturing flow associated therewith, in accordance with some embodiments. In some embodiments, based on a layout diagram, at least one of (A) one or more semiconductor masks or (B) at least one component in a layer of a semiconductor integrated circuit is fabricated using manufacturing system **1400**.

(107) In FIG. **14**, IC manufacturing system **1400** includes entities, such as a design house **1420**, a mask house **1430**, and an IC manufacturer/fabricator (“fab”) **1450**, that interact with one another in the design, development, and manufacturing cycles and/or services related to manufacturing an IC device **1460**. The entities in system **1400** are connected by a communications network. In some embodiments, the communications network is a single network. In some embodiments, the communications network is a variety of different networks, such as an intranet and the Internet. The communications network includes wired and/or wireless communication channels. Each entity interacts with one or more of the other entities and provides services to and/or receives services from one or more of the other entities. In some embodiments, two or more of design house **1420**, mask house **1430**, and IC fab **1450** is owned by a single larger company. In some embodiments, two or more of design house **1420**, mask house **1430**, and IC fab **1450** coexist in a common facility and use common resources.

(108) Design house (or design team) **1420** generates an IC design layout diagram **1422**. IC design layout diagram **1422** includes various geometrical patterns designed for an IC device **1460**. The geometrical patterns correspond to patterns of metal, oxide, or semiconductor layers that make up the various components of IC device **1460** to be fabricated. The various layers combine to form various IC features. For example, a portion of IC design layout diagram **1422** includes various IC

features, such as an active region, gate electrode, source and drain, metal lines or vias of an interlayer interconnection, and openings for bonding pads, to be formed in a semiconductor substrate (such as a silicon wafer) and various material layers disposed on the semiconductor substrate. Design house **1420** implements a proper design procedure to form IC design layout diagram **1422**. The design procedure includes one or more of logic design, physical design or place and route. IC design layout diagram **1422** is presented in one or more data files having information of the geometrical patterns. For example, IC design layout diagram **1422** can be expressed in a GDSII file format or DFII file format.

(109) Mask house **1430** includes data preparation **1432** and mask fabrication **1444**. Mask house **1430** uses IC design layout diagram **1422** to manufacture one or more masks **1445** to be used for fabricating the various layers of IC device **1460** according to IC design layout diagram **1422**. Mask house **1430** performs mask data preparation **1432**, where IC design layout diagram **1422** is translated into a representative data file (RDF). Mask data preparation **1432** provides the RDF to mask fabrication **1444**. Mask fabrication **1444** includes a mask writer. A mask writer converts the RDF to an image on a substrate, such as a mask (reticle) **1445** or a semiconductor wafer **1453**. The design layout diagram **1422** is manipulated by mask data preparation **1432** to comply with particular characteristics of the mask writer and/or requirements of IC fab **1450**. In FIG. **14**, mask data preparation **1432** and mask fabrication **1444** are illustrated as separate elements. In some embodiments, mask data preparation **1432** and mask fabrication **1444** can be collectively referred to as mask data preparation.

(110) In some embodiments, mask data preparation **1432** includes optical proximity correction (OPC) which uses lithography enhancement techniques to compensate for image errors, such as those that can arise from diffraction, interference, other process effects and the like. OPC adjusts IC design layout diagram **1422**. In some embodiments, mask data preparation **1432** includes further resolution enhancement techniques (RET), such as off-axis illumination, sub-resolution assist features, phase-shifting masks, other suitable techniques, and the like or combinations thereof. In some embodiments, inverse lithography technology (ILT) is also used, which treats OPC as an inverse imaging problem.

(111) In some embodiments, mask data preparation **1432** includes a mask rule checker (MRC) that checks the IC design layout diagram **1422** that has undergone processes in OPC with a set of mask creation rules which contain certain geometric and/or connectivity restrictions to ensure sufficient margins, to account for variability in semiconductor manufacturing processes, and the like. In some embodiments, the MRC modifies the IC design layout diagram **1422** to compensate for limitations during mask fabrication **1444**, which may undo part of the modifications performed by OPC in order to meet mask creation rules.

(112) In some embodiments, mask data preparation **1432** includes lithography process checking (LPC) that simulates processing that will be implemented by IC fab **1450** to fabricate IC device **1460**. LPC simulates this processing based on IC design layout diagram **1422** to create a simulated manufactured device, such as IC device **1460**. The processing parameters in LPC simulation can include parameters associated with various processes of the IC manufacturing cycle, parameters associated with tools used for manufacturing the IC, and/or other aspects of the manufacturing process. LPC takes into account various factors, such as aerial image contrast, depth of focus (DOF), mask error enhancement factor (MEEF), other suitable factors, and the like or combinations thereof. In some embodiments, after a simulated manufactured device has been created by LPC, if the simulated device is not close enough in shape to satisfy design rules, OPC and/or MRC are repeated to further refine IC design layout diagram **1422**.

(113) It should be understood that the above description of mask data preparation **1432** has been simplified for the purposes of clarity. In some embodiments, data preparation **1432** includes additional features such as a logic operation (LOP) to modify the IC design layout diagram **1422** according to manufacturing rules. Additionally, the processes applied to IC design layout diagram

**1422** during data preparation **1432** may be executed in a variety of different orders.

(114) After mask data preparation **1432** and during mask fabrication **1444**, a mask **1445** or a group of masks **1445** are fabricated based on the modified IC design layout diagram **1422**. In some embodiments, mask fabrication **1444** includes performing one or more lithographic exposures based on IC design layout diagram **1422**. In some embodiments, an electron-beam (e-beam) or a mechanism of multiple e-beams is used to form a pattern on a mask (photomask or reticle) **1445** based on the modified IC design layout diagram **1422**. Mask **1445** can be formed in various technologies. In some embodiments, mask **1445** is formed using binary technology. In some embodiments, a mask pattern includes opaque regions and transparent regions. A radiation beam, such as an ultraviolet (UV) beam, used to expose the image sensitive material layer (e.g., photoresist) which has been coated on a wafer, is blocked by the opaque region and transmits through the transparent regions. In one example, a binary mask version of mask **1445** includes a transparent substrate (e.g., fused quartz) and an opaque material (e.g., chromium) coated in the opaque regions of the binary mask. In another example, mask **1445** is formed using a phase shift technology. In a phase shift mask (PSM) version of mask **1445**, various features in the pattern formed on the phase shift mask are configured to have proper phase difference to enhance the resolution and imaging quality. In various examples, the phase shift mask can be attenuated PSM or alternating PSM. The mask(s) generated by mask fabrication **1444** is used in a variety of processes. For example, such a mask(s) is used in an ion implantation process to form various doped regions in semiconductor wafer **1453**, in an etching process to form various etching regions in semiconductor wafer **1453**, and/or in other suitable processes.

(115) IC fab **1450** is an IC fabrication business that includes one or more manufacturing facilities for the fabrication of a variety of different IC products. In some embodiments, IC Fab **1450** is a semiconductor foundry. For example, there may be a manufacturing facility for the front end fabrication of a plurality of IC products (front-end-of-line (FEOL) fabrication), while a second manufacturing facility may provide the back end fabrication for the interconnection and packaging of the IC products (back-end-of-line (BEOL) fabrication), and a third manufacturing facility may provide other services for the foundry business.

(116) IC fab **1450** includes fabrication tools **1452** configured to execute various manufacturing operations on semiconductor wafer **1453** such that IC device **1460** is fabricated in accordance with the mask(s), e.g., mask **1445**. In various embodiments, fabrication tools **1452** include one or more of a wafer stepper, an ion implanter, a photoresist coater, a process chamber, e.g., a CVD chamber or LPCVD furnace, a CMP system, a plasma etch system, a wafer cleaning system, or other manufacturing equipment capable of performing one or more suitable manufacturing processes as discussed herein.

(117) IC fab **1450** uses mask(s) **1445** fabricated by mask house **1430** to fabricate IC device **1460**. Thus, IC fab **1450** at least indirectly uses IC design layout diagram **1422** to fabricate IC device **1460**. In some embodiments, semiconductor wafer **1453** is fabricated by IC fab **1450** using mask(s) **1445** to form IC device **1460**. In some embodiments, the IC fabrication includes performing one or more lithographic exposures based at least indirectly on IC design layout diagram **1422**. Semiconductor wafer **1453** includes a silicon substrate or other proper substrate having material layers formed thereon. Semiconductor wafer **1453** further includes one or more of various doped regions, dielectric features, multilevel interconnects, and the like (formed at subsequent manufacturing steps).

(118) Details regarding an integrated circuit (IC) manufacturing system (e.g., system **1400** of FIG. **14**), and an IC manufacturing flow associated therewith are found, e.g., in U.S. Pat. No. 9,256,709, granted Feb. 9, 2016, U.S. Pre-Grant Publication No. 20150278429, published Oct. 1, 2015, U.S. Pre-Grant Publication No. 20140040838, published Feb. 6, 2014, and U.S. Pat. No. 7,260,442, granted Aug. 21, 2007, the entireties of each of which are hereby incorporated by reference.

(119) An aspect of the present disclosure relates to an integrated circuit. The integrated circuit

includes a plurality of first layer deep lines, a plurality of first layer shallow lines, a plurality of second layer deep lines, a plurality of second layer shallow lines, and a conducting path having a low resistivity portion and a low capacitivity portion. Each of the first layer deep lines and the first layer shallow lines is in a first conductive layer on an insulation layer immediately above transistors on a substrate. Each of the second layer deep lines and the second layer shallow lines is in a second conductive layer above the first conductive layer. The low resistivity portion includes a first layer deep line and excludes the first layer shallow lines and the second layer shallow lines, and the low capacitivity portion includes a first layer shallow line and excludes the first layer deep lines and the second layer deep lines. The integrated circuit also includes a first active device and a second active device. The first active device has an output coupled to the first layer deep line that is in the low resistivity portion. The second active device has an input coupled to the first layer shallow line that is in the low capacitivity portion.

(120) Another aspect of the present disclosure relates to an integrated circuit. The integrated circuit includes a plurality of first layer deep lines, a plurality of first layer shallow lines, and a conducting path which has a low resistivity portion and a low capacitivity portion. Each of the first layer deep lines and the first layer shallow lines is in a first conductive layer on an insulation layer fabricated in a front-end-of-line (FEOL) process. The low resistivity portion of the conducting path excludes the first layer shallow lines, and the low capacitivity portion of the conducting path excludes the first layer deep lines. The integrated circuit also includes a first active device and a second active device. The first active device has an output coupled to the first layer deep line that is in the low resistivity portion. The second active device has an input coupled to the first layer shallow line that is in the low capacitivity portion.

(121) Still another aspect of the present disclosure relates to an integrated circuit. The integrated circuit includes a plurality of first layer deep lines, a plurality of first layer shallow lines, a plurality of second layer deep lines, a plurality of second layer shallow lines, and a conducting path having a low resistivity portion and a low capacitivity portion connected together through a fan-out node. Each of the first layer deep lines and the first layer shallow lines is in a first conductive layer above transistors on a substrate. Each of the second layer deep lines and the second layer shallow lines is in a second conductive layer above the first conductive layer. The low resistivity portion includes at least one first layer deep line or at least one second layer deep line and excludes the first layer shallow lines and the second layer shallow lines. The low capacitivity portion includes at least one first layer shallow line or at least one second layer shallow line and excludes the first layer deep lines and the second layer deep lines.

(122) The foregoing outlines features of several embodiments so that those skilled in the art may better understand the aspects of the present disclosure. Those skilled in the art should appreciate that they may readily use the present disclosure as a basis for designing or modifying other processes and structures for carrying out the same purposes and/or achieving the same advantages of the embodiments introduced herein. Those skilled in the art should also realize that such equivalent constructions do not depart from the spirit and scope of the present disclosure, and that they may make various changes, substitutions, and alterations herein without departing from the spirit and scope of the present disclosure.

## Claims

1. An integrated circuit comprising: a plurality of first layer deep lines and a plurality of first layer shallow lines, wherein each of the first layer deep lines and the first layer shallow lines is in a first conductive layer on an insulation layer immediately above transistors on a substrate; a plurality of second layer deep lines and a plurality of second layer shallow lines, wherein each of the second layer deep lines and the second layer shallow lines is in a second conductive layer above the first conductive layer; a conducting path having a low resistivity portion and a low capacitivity portion,

wherein the low resistivity portion includes a first layer deep line and excludes the first layer shallow lines and the second layer shallow lines, and wherein the low capacitivity portion includes a first layer shallow line and excludes the first layer deep lines and the second layer deep lines; a first active device having an output coupled to the first layer deep line that is in the low resistivity portion; and a second active device having an input coupled to the first layer shallow line that is in the low capacitivity portion.

2. The integrated circuit of claim 1, wherein the low resistivity portion further includes one of the second layer deep lines.

3. The integrated circuit of claim 1, wherein the low capacitivity portion further includes one of the second layer shallow lines.

4. The integrated circuit of claim 1, wherein the low resistivity portion is connected to the low capacitivity portion through a via-connector between the first conductive layer and the second conductive layer.

5. The integrated circuit of claim 1, wherein the low resistivity portion is connected to the low capacitivity portion through a fan-out node.

6. The integrated circuit of claim 5, further comprising: a third active device on the substrate; a branched conducting path between the fan-out node and an input of the third active device; and wherein the branched conducting path includes at least another first layer shallow line or another second layer shallow line and excludes the first layer deep lines and the second layer deep lines.

7. The integrated circuit of claim 1, further comprising: a plurality of third layer deep lines and a plurality of third layer shallow lines, wherein each of the third layer deep lines and the third layer shallow lines is in a third conductive layer.

8. The integrated circuit of claim 7, wherein the third conductive layer is above the second conductive layer.

9. The integrated circuit of claim 7, wherein the third conductive layer is between the first conductive layer and the second conductive layer.

10. The integrated circuit of claim 7, wherein the third conductive layer is above the transistors but underneath the first conductive layer.

11. The integrated circuit of claim 1, further comprising: a plurality of conducting lines in a third conductive layer between the first conductive layer and the second conductive layer.

12. An integrated circuit comprising: a plurality of first layer deep lines and a plurality of first layer shallow lines, wherein each of the first layer deep lines and the first layer shallow lines is in a first conductive layer on an insulation layer fabricated in a front-end-of-line (FEOL) process; a conducting path having a low resistivity portion which excludes the first layer shallow lines and a low capacitivity portion which excludes the first layer deep lines; a first active device having an output coupled to the first layer deep line that is in the low resistivity portion; and a second active device having an input coupled to the first layer shallow line that is in the low capacitivity portion.

13. The integrated circuit of claim 12, further comprising: a plurality of second layer deep lines and a plurality of second layer shallow lines, wherein each of the second layer deep lines and the second layer shallow lines is in a second conductive layer above the first conductive layer; wherein the low resistivity portion also includes at least one second layer deep line and excludes the second layer shallow lines; and wherein the low capacitivity portion also includes at least one second layer shallow line and excludes the second layer deep lines.

14. The integrated circuit of claim 13, wherein the low resistivity portion and the low capacitivity portion is connected at a via-connector between the first conductive layer and the second conductive layer.

15. An integrated circuit comprising: a plurality of first layer deep lines and a plurality of first layer shallow lines, wherein each of the first layer deep lines and the first layer shallow lines is in a first conductive layer above transistors on a substrate; a plurality of second layer deep lines and a plurality of second layer shallow lines, wherein each of the second layer deep lines and the second



layer shallow lines is in a second conductive layer above the first conductive layer; a conducting path having a low resistivity portion and a low capacitivity portion connected together through a fan-out node; wherein the low resistivity portion includes at least one first layer deep line or at least one second layer deep line and excludes the first layer shallow lines and the second layer shallow lines; and wherein the low capacitivity portion includes at least one first layer shallow line or at least one second layer shallow line and excludes the first layer deep lines and the second layer deep lines.

16. The integrated circuit of claim 15, wherein the low resistivity portion is coupled to an output of a first active device, and wherein the low capacitivity portion is coupled to an input of a second active device.

17. The integrated circuit of claim 15, wherein: the low resistivity portion includes at least one first layer deep line and at least one second layer deep line; and the low capacitivity portion includes at least one first layer shallow line and at least one second layer shallow line.

18. The integrated circuit of claim 15, further comprising: a third active device on the substrate; a branched conducting path between the fan-out node and an input of the third active device; and wherein the branched conducting path includes at least another first layer shallow line or another second layer shallow line and excludes the first layer deep lines and the second layer deep lines.

19. The integrated circuit of claim 15, further comprising: a plurality of third layer deep lines and a plurality of third layer shallow lines, wherein each of the third layer deep lines and the third layer shallow lines is in a third conductive layer.

20. The integrated circuit of claim 19, wherein the third conductive layer is above the second conductive layer.

---