

US Patent & Trademark Office

Patent Public Search | Text View

United States Patent

12389007

Kind Code

B2

Date of Patent

August 12, 2025

Inventor(s)

Filippov; Alexey Konstantinovich et al.

Method and apparatus for intra prediction

Abstract

A method for intra prediction is provided, the method including: obtaining a predicted sample value for a sample of the block; obtaining a scaling factor value according to an intra prediction mode for the current coding block, and according to at least one of: a height of the current coding block, or a width of the current coding block, or a size of a subpartition of the current coding block; determining a first weight value based on the scaling factor value; determining a second weight value based on the scaling factor value; calculating an additional value as a weighted sum of a top reference sample value and a left reference sample value, by weighting the top reference sample value with the first weight and the left reference sample value with the second weight; and obtaining a modified predicted sample value according to the additional value and the predicted sample value.

Inventors: Filippov; Alexey Konstantinovich (Moscow, RU), Rufitskiy; Vasily Alexeevich (Moscow, RU), Alshina; Elena Alexandrovna (Moscow, RU)

Applicant: HUAWEI TECHNOLOGIES CO., LTD. (Guangdong, CN)

Family ID: 74853458

Assignee: HUAWEI TECHNOLOGIES CO., LTD. (Shenzhen, CN)

Appl. No.: 17/853920

Filed: June 30, 2022

Prior Publication Data

Document Identifier

Publication Date

US 20220345712 A1

Oct. 27, 2022

Related U.S. Application Data

continuation parent-doc WO PCT/RU2020/050404 20201230 PENDING child-doc US 17853920

us-provisional-application US 62955469 20191231

Publication Classification

Int. Cl.: H04N19/132 (20140101); H04N19/105 (20140101); H04N19/159 (20140101); H04N19/176 (20140101)

U.S. Cl.:

CPC **H04N19/132** (20141101); **H04N19/105** (20141101); **H04N19/159** (20141101); **H04N19/176** (20141101);

Field of Classification Search

CPC: H04N (19/132); H04N (19/105); H04N (19/159); H04N (19/176); H04N (19/157); H04N (19/119);
H04N (19/11)

References Cited

U.S. PATENT DOCUMENTS

Patent No.	Issued Date	Patentee Name	U.S. Cl.	CPC
2016/0057448	12/2015	Bossen et al.	N/A	N/A
2017/0214940	12/2016	Chien et al.	N/A	N/A
2022/0303541	12/2021	Rath	N/A	H04N 19/593
2022/0360774	12/2021	Bossen	N/A	H04N 19/105

FOREIGN PATENT DOCUMENTS

Patent No.	Application Date	Country	CPC
110234008	12/2018	CN	N/A

OTHER PUBLICATIONS

F. Bossen (Sharp), On general intra sample prediction, Jul. 2, 2019, JVET-O0364 (Year: 2019). cited by examiner
JVET-M0122-v4, Alexey Filippov et al., Non-CE3: On block size restrictions for PDPC, Joint Video Experts Team (JVET) of ITU-T SG 16 WP 3 and ISO/IEC JTC 1/SC 29/WG 11, 13th Meeting: Marrakech, MA, 9 Jan. 18, 2019, 7 pages. cited by applicant

Document: JVET-M0102-v5, Valeri George et al, CE3: Intra Sub-Partitions Coding Mode (Tests 1.1.1 and 1.1.2), Joint Video Experts Team (JVET) of ITU-T SG 16 WP 3 and ISO/IEC JTC1/SC 29/WG 11, 13th Meeting: Marrakech, MA, Jan. 9-18, 2019, 9 pages. cited by applicant

Document: JVET-P2001-vE, Benjamin Bross et al, Versatile Video Coding (Draft 7), Joint Video Experts Team (JVET) of ITU-T SG 16 WP 3 and ISO/IEC JTC 1/SC 29/WG 11, 16th Meeting: Geneva, CH, Oct. 1-11, 2019, 492 pages. cited by applicant

Document: JVET-N0313-v2, Rahul Vanam et al, CE3-related: Low latency intra sub-partitions, Joint Video Experts Team (JVET) of ITU-T SG 16 WP 3 and ISO/IEC JTC 1 /SC 29/WG 11, 14th Meeting: Geneva, CH, Mar. 19-27, 2019, 7 pages. cited by applicant

ITU-T H.264(Jun. 2019), Series H: Audiovisual and Multimedia Systems, Infrastructure of audiovisual services—Coding of moving video, Advanced video coding for generic audiovisual services, total 836 pages. cited by applicant

ITU-T H.265(Jun. 2019), Series H: Audiovisual and Multimedia Systems, Infrastructure of audiovisual services—Coding of moving video, High efficiency video coding, total 696 pages. cited by applicant

Primary Examiner: Abouzahra; Hesham K

Attorney, Agent or Firm: WOMBLE BOND DICKINSON (US) LLP

Background/Summary

CROSS-REFERENCE TO RELATED APPLICATIONS (1) This application is a continuation of International Application No. PCT/RU2020/050404, filed on Dec. 30, 2020, which claims the priority to U.S. provisional Application No. 62/955,469, filed on Dec. 31, 2019. The disclosures of the aforementioned applications are hereby incorporated by reference in their entireties.

TECHNICAL FIELD

(1) Embodiments of the present application (disclosure) generally relate to the field of picture processing and more particularly to method and apparatus for intra prediction.

BACKGROUND

(2) Video coding (video encoding and decoding) is used in a wide range of digital video applications, for example broadcast digital TV, video transmission over internet and mobile networks, real-time conversational applications such as video chat, video conferencing, DVD and Blu-ray discs, video content acquisition and editing systems, and camcorders of security applications.

(3) The amount of video data needed to depict even a relatively short video can be substantial, which may result in difficulties when the data is to be streamed or otherwise communicated across a communications network with limited bandwidth capacity. Thus, video data is generally compressed before being communicated across modern day telecommunications networks. The size of a video could also be an issue when the video is stored on a storage device because memory resources may be limited. Video compression devices often use software and/or hardware at the source to code the video data prior to transmission or storage, thereby decreasing the quantity of data needed to represent digital video images. The compressed data is then received at the destination by a video decompression device that decodes the video data. With limited network resources and ever increasing demands of higher video quality, improved compression and decompression techniques that improve compression ratio with little to no sacrifice in picture quality are desirable.

SUMMARY

(4) Embodiments of the present application provide apparatuses and methods for encoding and decoding.

(5) According to a first aspect the application relates to a method for intra predicting process of a video (or picture, frame) block (a block may be a current coding block or a subpartition of the current coding block), the method comprising: obtaining a predicted sample value for a sample of the block (in an example, the predicted sample value is obtained from one or more reference sample values, by using an intra prediction mode which is selected from one of a DC intra-prediction mode, a planar intra prediction mode, and an angular intra-prediction mode); obtaining a scaling factor value according to an intra prediction mode for the current coding block, and according to a height of the current coding block or a width of the current coding block (this process is for angular mode. When the intra prediction mode for the current coding block is not a horizontal mode and is not a vertical mode, the scaling factor value is obtained according to a height of the block or a width of the block for DC mode, planar mode, horizontal and vertical angular modes. In an example, both of the height and the width are used to obtain the scaling factor); determining a first weight value based on the scaling factor value; determining a second weight value based on the scaling factor value; calculating an additional value as a weighted sum of a top reference sample value and a left reference sample value, by weighting the top reference sample value with the first weight value and the left reference sample value with the second weight value; obtaining a modified predicted sample value according to the additional value and the predicted sample value (in some embodiments, the predicted sample value is processed by using a sample weighting factor to obtain a weighted predicted value, the modified predicted sample value is obtained according to the additional value and the weighted predicted sample value) (in an example, the method further comprises: normalizing the modified predicted sample value, by an arithmetic right shift of an integer representation of the modified predicted sample value, resulting in a normalized modified predicted sample value).

(6) In a possible implementation form, wherein the height of the current coding block is equal to a value of $\text{refH} - \text{nTbH}$, the variable refH indicates height of reference samples, and the variable nTbH indicates height of transform block.

(7) In a possible implementation form, wherein the width of the current coding block is equal to a value of $\text{refW} - \text{nTbW}$, the variable refW indicates width of reference samples, and variable nTbW indicates width of transform block.

(8) According to a second aspect the application relates to a method for intra predicting process of a video (or picture, frame) block, the method comprising: obtaining a predicted sample value for a sample of the block (in an example, the predicted sample value is obtained from one or more reference sample values, by using an intra prediction mode which is selected from one of a DC intra-prediction mode, a planar intra prediction mode, and an angular intra-prediction mode); obtaining a scaling factor value according to an intra prediction mode for the current coding block, and according to a height of the current coding block or a width of the current coding block (in an example, both of the height and the width are used to obtain the scaling factor); when the scaling factor value is greater than or equal to 0, performing the following processes: determining a first weight value based on the scaling factor value; determining a second weight value based on the scaling factor value; calculating an additional value as a weighted sum of a top reference sample value and a left reference sample value, by weighting the top reference sample value with the first weight and the left reference sample value with the second weight; obtaining a modified predicted sample value according to the additional value and the predicted sample value (in some embodiments, the predicted sample value is processed by using a sample weighting factor to obtain a weighted predicted value, the modified predicted sample value is obtained according to the additional value and the weighted predicted sample value) (in an example, the method further comprises: normalizing the modified predicted sample value, by an arithmetic right shift of an integer representation of the modified predicted sample value).

value, resulting in a normalized modified predicted sample value).

(9) In a possible implementation form, wherein the method further comprises: when the scaling factor value is less than 0, output the predicted sample value.

(10) According to a third aspect the application relates to a method for intra predicting process of a video (or picture, frame) block, the method comprising: obtaining a predicted sample value for a sample of the block (in an example, the predicted sample value is obtained from one or more reference sample values, by using an intra prediction mode which is selected from one of a DC intra-prediction mode, a planar intra prediction mode, and an angular intra-prediction mode); obtaining a scaling factor value according to an intra prediction mode for the current coding block, and according to a height of the current coding block or a width of the current coding block (in an example, both of the height and the width are used to obtain the scaling factor); when the intra prediction mode for the current coding block is angular mode (but the intra prediction mode for the current coding block is not a horizontal mode and is not a vertical mode), and when the scaling factor value is less than 0, output the predicted sample value; otherwise (the intra prediction mode for the current coding block is not angular mode, or the intra prediction mode for the current coding block is a horizontal mode, or the intra prediction mode for the current coding block is a vertical mode, or the scaling factor value is greater than or equal to 0), performing the following processes: determining a first weight value based on the scaling factor value, determining a second weight value based on the scaling factor value, calculating an additional value as a weighted sum of a top reference sample value and a left reference sample value, by weighting the top reference sample value with the first weight and the left reference sample value with the second weight, obtaining a modified predicted sample value according to the additional value and the predicted sample value (in some embodiments, the predicted sample value is processed by using a sample weighting factor to obtain a weighted predicted value, the modified predicted sample value is obtained according to the additional value and the weighted predicted sample value) (in an example, the method further comprises: normalizing the modified predicted sample value, by an arithmetic right shift of an integer representation of the modified predicted sample value, resulting in a normalized modified predicted sample value).

(11) In a possible implementation form, wherein the height of the current coding block is equal to a value of $\text{refH} - \text{nTbH}$, the variable refH indicates height of reference samples, and the variable nTbH indicates height of transform block.

(12) In a possible implementation form, wherein the width of the current coding block is equal to a value of $\text{refW} - \text{nTbW}$, the variable refW indicates width of reference samples, and variable nTbW indicates width of transform block.

(13) According to a fourth aspect the application relates to an encoder, which comprising processing circuitry for carrying out the method according to method embodiments.

(14) According to a fifth aspect the application relates to a decoder, which comprising processing circuitry for carrying out the method according to method embodiments.

(15) According to a sixth aspect the application relates to a computer program product comprising program code for performing the method according to any one of the preceding embodiments when executed on a computer or a processor.

(16) According to a seventh aspect the application relates to a decoder, comprising: one or more processors; and a non-transitory computer-readable storage medium coupled to the processors and storing programming for execution by the processors, wherein the programming, when executed by the processors, configures the decoder to carry out the method according to any one of the preceding embodiments.

(17) According to an eighth aspect the application relates to an encoder, comprising: one or more processors; and a non-transitory computer-readable storage medium coupled to the processors and storing programming for execution by the processors, wherein the programming, when executed by the processors, configures the encoder to carry out the method according to any one of the preceding embodiments.

(18) According to a ninth aspect the application relates to a non-transitory computer-readable medium carrying a program code which, when executed by a computer device, causes the computer device to perform the method of any one of the preceding embodiments.

(19) The scaling factor value in the above embodiments, for example, is a position dependent prediction combination (PDPC) scaling parameter ("nScale"). By the method and device, the PDPC scaling parameter ("nScale") is determined by two values. One of these values is derived from the block size and the other one is derived from the value of the inverse intra prediction angle. Moreover, Intra subpartition mode (ISP) is considered during the deriving the nScale parameter. Thereby, method and apparatus may harmonize PDPC for directional intra prediction with ISP coding mode.

(20) Details of one or more embodiments are set forth in the accompanying drawings and the description below. Other features, objects, and advantages will be apparent from the description, drawings, and claims.

Description

BRIEF DESCRIPTION OF THE DRAWINGS

- (1) In the following embodiments of the application are described in more detail with reference to the attached figures and drawings, in which:
- (2) FIG. 1A is a block diagram showing an example of a video coding system configured to implement embodiments of the application;
- (3) FIG. 1B is a block diagram showing another example of a video coding system configured to implement embodiments of the application;
- (4) FIG. 2 is a block diagram showing an example of a video encoder configured to implement embodiments of the application;
- (5) FIG. 3 is a block diagram showing an example structure of a video decoder configured to implement embodiments of the application;
- (6) FIG. 4 is a block diagram illustrating an example of an encoding apparatus or a decoding apparatus;
- (7) FIG. 5 is a block diagram illustrating another example of an encoding apparatus or a decoding apparatus;
- (8) FIG. 6 is an illustration of the 93 prediction directions, where the dashed directions are associated with the wide-angle modes that are applied to non-square blocks;
- (9) FIG. 7 is an illustration of ISP subpartitioning with vertical splitting;
- (10) FIG. 8 is an illustration of ISP subpartitioning with horizontal splitting;
- (11) FIG. 9A illustrates a method for intra predicting process of a current coding block according to an embodiment of the present application;
- (12) FIG. 9B illustrates a method for intra predicting process of a current coding block according to another embodiment of the present application;
- (13) FIG. 10 is a block diagram showing an embodiment for deriving the nScale parameter;
- (14) FIG. 11 is a block diagram showing another embodiment for deriving the nScale parameter;
- (15) FIG. 12 is a block diagram showing an embodiment for deriving the nScale parameter;
- (16) FIG. 13 illustrates an encoding or decoding device according to an embodiment of the present application;
- (17) FIG. 14 is a block diagram showing an example structure of a content supply system **3100** which realizes a content delivery service; and
- (18) FIG. 15 is a block diagram showing a structure of an example of a terminal device.
- (19) In the following identical reference signs refer to identical or at least functionally equivalent features if not explicitly specified otherwise.

DETAILED DESCRIPTION OF THE EMBODIMENTS

(20) In the following description, reference is made to the accompanying figures, which form part of the disclosure, and which show, by way of illustration, specific aspects of embodiments of the application or specific aspects in which embodiments of the present application may be used. It is understood that embodiments of the application may be used in other aspects and comprise structural or logical changes not depicted in the figures. The following detailed description, therefore, is not to be taken in a limiting sense, and the scope of the present application is defined by the appended claims.

(21) For instance, it is understood that a disclosure in connection with a described method may also hold true for a corresponding device or system configured to perform the method and vice versa. For example, if one or a plurality of specific method operations are described, a corresponding device may include one or a plurality of units, e.g. functional units, to perform the described one or plurality of method operations (e.g. one unit performing the one or plurality of operations, or a plurality of units each performing one or more of the plurality of operations), even if such one or more units are not explicitly described or illustrated in the figures. On the other hand, for example, if a specific apparatus is described based on one or a plurality of units, e.g. functional units, a corresponding method may include one operation to perform the functionality of the one or plurality of units (e.g. one operation performing the functionality of the one or plurality of units, or a plurality of operations each performing the functionality of one or more of the plurality of units), even if such one or plurality of operations are not explicitly described or illustrated in the figures. Further, it is understood that the features of the various exemplary embodiments and/or aspects described herein may be combined with each other, unless specifically noted otherwise.

(22) Video coding typically refers to the processing of a sequence of pictures, which form the video or video sequence. Instead of the term “picture” the term “frame” or “image” may be used as synonyms in the field of video coding. Video coding (or coding in general) comprises two parts video encoding and video decoding. Video encoding is performed at the source side, typically comprising processing (e.g. by compression) the original video pictures to reduce the amount of data required for representing the video pictures (for more efficient storage and/or

transmission). Video decoding is performed at the destination side and typically comprises the inverse processing compared to the encoder to reconstruct the video pictures. Embodiments referring to “coding” of video pictures (or pictures in general) shall be understood to relate to “encoding” or “decoding” of video pictures or respective video sequences. The combination of the encoding part and the decoding part is also referred to as CODEC (Coding and Decoding).

(23) In case of lossless video coding, the original video pictures can be reconstructed, i.e. the reconstructed video pictures have the same quality as the original video pictures (assuming no transmission loss or other data loss during storage or transmission). In case of lossy video coding, further compression, e.g. by quantization, is performed, to reduce the amount of data representing the video pictures, which cannot be completely reconstructed at the decoder, i.e. the quality of the reconstructed video pictures is lower or worse compared to the quality of the original video pictures.

(24) Several video coding standards belong to the group of “lossy hybrid video codecs” (i.e. combine spatial and temporal prediction in the sample domain and 2D transform coding for applying quantization in the transform domain). Each picture of a video sequence is typically partitioned into a set of non-overlapping blocks and the coding is typically performed on a block level. In other words, at the encoder the video is typically processed, i.e. encoded, on a block (video block) level, e.g. by using spatial (intra picture) prediction and/or temporal (inter picture) prediction to generate a prediction block, subtracting the prediction block from the current block (block currently processed/to be processed) to obtain a residual block, transforming the residual block and quantizing the residual block in the transform domain to reduce the amount of data to be transmitted (compression), whereas at the decoder the inverse processing compared to the encoder is applied to the encoded or compressed block to reconstruct the current block for representation. Furthermore, the encoder duplicates the decoder processing loop such that both will generate identical predictions (e.g. intra- and inter predictions) and/or re-constructions for processing, i.e. coding, the subsequent blocks.

(25) In the following embodiments of a video coding system **10**, a video encoder **20** and a video decoder **30** are described based on FIGS. **1** to **3**.

(26) FIG. **1A** is a schematic block diagram illustrating an example coding system **10**, e.g. a video coding system **10** (or short coding system **10**) that may utilize techniques of this present application. Video encoder **20** (or short encoder **20**) and video decoder **30** (or short decoder **30**) of video coding system **10** represent examples of devices that may be configured to perform techniques in accordance with various examples described in the present application.

(27) As shown in FIG. **1A**, the coding system **10** comprises a source device **12** configured to provide encoded picture data **21** e.g. to a destination device **14** for decoding the encoded picture data **13**.

(28) The source device **12** comprises an encoder **20**, and may additionally, i.e. optionally, comprise a picture source **16**, a pre-processor (or pre-processing unit) **18**, e.g. a picture pre-processor **18**, and a communication interface or communication unit **22**.

(29) The picture source **16** may comprise or be any kind of picture capturing device, for example a camera for capturing a real-world picture, and/or any kind of a picture generating device, for example a computer-graphics processor for generating a computer animated picture, or any kind of other device for obtaining and/or providing a real-world picture, a computer generated picture (e.g. a screen content, a virtual reality (VR) picture) and/or any combination thereof (e.g. an augmented reality (AR) picture). The picture source may be any kind of memory or storage storing any of the aforementioned pictures.

(30) In distinction to the pre-processor **18** and the processing performed by the pre-processing unit **18**, the picture or picture data **17** may also be referred to as raw picture or raw picture data **17**.

(31) Pre-processor **18** is configured to receive the (raw) picture data **17** and to perform pre-processing on the picture data **17** to obtain a pre-processed picture **19** or pre-processed picture data **19**. Pre-processing performed by the pre-processor **18** may, e.g., comprise trimming, color format conversion (e.g. from RGB to YCbCr), color correction, or de-noising. It can be understood that the pre-processing unit **18** may be optional component.

(32) The video encoder **20** is configured to receive the pre-processed picture data **19** and provide encoded picture data **21** (further details will be described below, e.g., based on FIG. **2**).

(33) Communication interface **22** of the source device **12** may be configured to receive the encoded picture data **21** and to transmit the encoded picture data **21** (or any further processed version thereof) over communication channel **13** to another device, e.g. the destination device **14** or any other device, for storage or direct reconstruction.

(34) The destination device **14** comprises a decoder **30** (e.g. a video decoder **30**), and may additionally, i.e. optionally, comprise a communication interface or communication unit **28**, a post-processor **32** (or post-processing unit **32**) and a display device **34**.

(35) The communication interface **28** of the destination device **14** is configured receive the encoded picture data **21** (or any further processed version thereof), e.g. directly from the source device **12** or from any other source, e.g. a storage device, e.g. an encoded picture data storage device, and provide the encoded picture data **21** to the

decoder **30**.

(36) The communication interface **22** and the communication interface **28** may be configured to transmit or receive the encoded picture data **21** or encoded data **13** via a direct communication link between the source device **12** and the destination device **14**, e.g. a direct wired or wireless connection, or via any kind of network, e.g. a wired or wireless network or any combination thereof, or any kind of private and public network, or any kind of combination thereof.

(37) The communication interface **22** may be, e.g., configured to package the encoded picture data **21** into an appropriate format, e.g. packets, and/or process the encoded picture data using any kind of transmission encoding or processing for transmission over a communication link or communication network.

(38) The communication interface **28**, forming the counterpart of the communication interface **22**, may be, e.g., configured to receive the transmitted data and process the transmission data using any kind of corresponding transmission decoding or processing and/or de-packaging to obtain the encoded picture data **21**.

(39) Both, communication interface **22** and communication interface **28** may be configured as unidirectional communication interfaces as indicated by the arrow for the communication channel **13** in FIG. **1A** pointing from the source device **12** to the destination device **14**, or bi-directional communication interfaces, and may be configured, e.g. to send and receive messages, e.g. to set up a connection, to acknowledge and exchange any other information related to the communication link and/or data transmission, e.g. encoded picture data transmission.

(40) The decoder **30** is configured to receive the encoded picture data **21** and provide decoded picture data **31** or a decoded picture **31** (further details will be described below, e.g., based on FIG. **3** or FIG. **5**).

(41) The post-processor **32** of destination device **14** is configured to post-process the decoded picture data **31** (also called reconstructed picture data), e.g. the decoded picture **31**, to obtain post-processed picture data **33**, e.g. a post-processed picture **33**. The post-processing performed by the post-processing unit **32** may comprise, e.g. color format conversion (e.g. from YCbCr to RGB), color correction, trimming, or re-sampling, or any other processing, e.g. for preparing the decoded picture data **31** for display, e.g. by display device **34**.

(42) The display device **34** of the destination device **14** is configured to receive the post-processed picture data **33** for displaying the picture, e.g. to a user or viewer. The display device **34** may be or comprise any kind of display for representing the reconstructed picture, e.g. an integrated or external display or monitor. The displays may, e.g. comprise liquid crystal displays (LCD), organic light emitting diodes (OLED) displays, plasma displays, projectors, micro LED displays, liquid crystal on silicon (LCoS), digital light processor (DLP) or any kind of other display.

(43) Although FIG. **1A** depicts the source device **12** and the destination device **14** as separate devices, embodiments of devices may also comprise both or both functionalities, the source device **12** or corresponding functionality and the destination device **14** or corresponding functionality. In such embodiments the source device **12** or corresponding functionality and the destination device **14** or corresponding functionality may be implemented using the same hardware and/or software or by separate hardware and/or software or any combination thereof.

(44) As will be apparent for the skilled person based on the description, the existence and (exact) split of functionalities of the different units or functionalities within the source device **12** and/or destination device **14** as shown in FIG. **1A** may vary depending on the actual device and application.

(45) The encoder **20** (e.g. a video encoder **20**) or the decoder **30** (e.g. a video decoder **30**) or both encoder **20** and decoder **30** may be implemented via processing circuitry as shown in FIG. **1B**, such as one or more microprocessors, digital signal processors (DSPs), application-specific integrated circuits (ASICs), field-programmable gate arrays (FPGAs), discrete logic, hardware, video coding dedicated or any combinations thereof. The encoder **20** may be implemented via processing circuitry **46** to embody the various modules as discussed with respect to encoder **20** of FIG. **2** and/or any other encoder system or subsystem described herein. The decoder **30** may be implemented via processing circuitry **46** to embody the various modules as discussed with respect to decoder **30** of FIG. **3** and/or any other decoder system or subsystem described herein. The processing circuitry may be configured to perform the various operations as discussed later. As shown in FIG. **5**, if the techniques are implemented partially in software, a device may store instructions for the software in a suitable, non-transitory computer-readable storage medium and may execute the instructions in hardware using one or more processors to perform the techniques of this disclosure. Either of video encoder **20** and video decoder **30** may be integrated as part of a combined encoder/decoder (CODEC) in a single device, for example, as shown in FIG. **1B**.

(46) Source device **12** and destination device **14** may comprise any of a wide range of devices, including any kind of handheld or stationary devices, e.g. notebook or laptop computers, mobile phones, smart phones, tablets or tablet computers, cameras, desktop computers, set-top boxes, televisions, display devices, digital media players, video gaming consoles, video streaming devices (such as content services servers or content delivery servers), broadcast receiver device, broadcast transmitter device, or the like and may use no or any kind of operating system. In some cases, the source device **12** and the destination device **14** may be equipped for wireless

communication. Thus, the source device **12** and the destination device **14** may be wireless communication devices. (47) In some cases, video coding system **10** illustrated in FIG. **1A** is merely an example and the techniques of the present application may apply to video coding settings (e.g., video encoding or video decoding) that do not necessarily include any data communication between the encoding and decoding devices. In other examples, data is retrieved from a local memory, streamed over a network, or the like. A video encoding device may encode and store data to memory, and/or a video decoding device may retrieve and decode data from memory. In some examples, the encoding and decoding is performed by devices that do not communicate with one another, but simply encode data to memory and/or retrieve and decode data from memory.

(48) For convenience of description, embodiments of the application are described herein, for example, by reference to High-Efficiency Video Coding (HEVC) or to the reference software of Versatile Video coding (VVC), the next generation video coding standard developed by the Joint Collaboration Team on Video Coding (JCT-VC) of ITU-T Video Coding Experts Group (VCEG) and ISO/IEC Motion Picture Experts Group (MPEG). One of ordinary skill in the art will understand that embodiments of the application are not limited to HEVC or VVC.

(49) Encoder and Encoding Method

(50) FIG. **2** shows a schematic block diagram of an example video encoder **20** that is configured to implement the techniques of the present application. In the example of FIG. **2**, the video encoder **20** comprises an input **201** (or input interface **201**), a residual calculation unit **204**, a transform processing unit **206**, a quantization unit **208**, an inverse quantization unit **210**, and inverse transform processing unit **212**, a reconstruction unit **214**, a loop filter unit **220**, a decoded picture buffer (DPB) **230**, a mode selection unit **260**, an entropy encoding unit **270** and an output **272** (or output interface **272**). The mode selection unit **260** may include an inter prediction unit **244**, an intra prediction unit **254** and a partitioning unit **262**. Inter prediction unit **244** may include a motion estimation unit and a motion compensation unit (not shown). A video encoder **20** as shown in FIG. **2** may also be referred to as hybrid video encoder or a video encoder according to a hybrid video codec.

(51) The residual calculation unit **204**, the transform processing unit **206**, the quantization unit **208**, the mode selection unit **260** may be referred to as forming a forward signal path of the encoder **20**, whereas the inverse quantization unit **210**, the inverse transform processing unit **212**, the reconstruction unit **214**, the buffer **216**, the loop filter **220**, the decoded picture buffer (DPB) **230**, the inter prediction unit **244** and the intra-prediction unit **254** may be referred to as forming a backward signal path of the video encoder **20**, wherein the backward signal path of the video encoder **20** corresponds to the signal path of the decoder (see video decoder **30** in FIG. **3**). The inverse quantization unit **210**, the inverse transform processing unit **212**, the reconstruction unit **214**, the loop filter **220**, the decoded picture buffer (DPB) **230**, the inter prediction unit **244** and the intra-prediction unit **254** are also referred to forming the “built-in decoder” of video encoder **20**.

(52) Pictures & Picture Partitioning (Pictures & Blocks)

(53) The encoder **20** may be configured to receive, e.g. via input **201**, a picture **17** (or picture data **17**), e.g. picture of a sequence of pictures forming a video or video sequence. The received picture or picture data may also be a pre-processed picture **19** (or pre-processed picture data **19**). For sake of simplicity the following description refers to the picture **17**. The picture **17** may also be referred to as current picture or picture to be coded (in particular in video coding to distinguish the current picture from other pictures, e.g. previously encoded and/or decoded pictures of the same video sequence, i.e. the video sequence which also comprises the current picture).

(54) A (digital) picture is or can be regarded as a two-dimensional array or matrix of samples with intensity values. A sample in the array may also be referred to as pixel (short form of picture element) or a pel. The number of samples in horizontal and vertical direction (or axis) of the array or picture define the size and/or resolution of the picture. For representation of color, typically three color components are employed, i.e. the picture may be represented or include three sample arrays. In RGB format or color space a picture comprises a corresponding red, green and blue sample array. However, in video coding each pixel is typically represented in a luminance and chrominance format or color space, e.g. YCbCr, which comprises a luminance component indicated by Y (sometimes also L is used instead) and two chrominance components indicated by Cb and Cr. The luminance (or short luma) component Y represents the brightness or grey level intensity (e.g. like in a grey-scale picture), while the two chrominance (or short chroma) components Cb and Cr represent the chromaticity or color information components. Accordingly, a picture in YCbCr format comprises a luminance sample array of luminance sample values (Y), and two chrominance sample arrays of chrominance values (Cb and Cr). Pictures in RGB format may be converted or transformed into YCbCr format and vice versa, the process is also known as color transformation or conversion. If a picture is monochrome, the picture may comprise only a luminance sample array. Accordingly, a picture may be, for example, an array of luma samples in monochrome format or an array of luma samples and two corresponding arrays of chroma samples in 4:2:0, 4:2:2, and 4:4:4 colour format.

(55) Embodiments of the video encoder **20** may comprise a picture partitioning unit (not depicted in FIG. **2**) configured to partition the picture **17** into a plurality of (typically non-overlapping) picture blocks **203**. These blocks may also be referred to as root blocks, macro blocks (H.264/AVC) or coding tree blocks (CTB) or coding

tree units (CTU) (H.265/HEVC and VVC). The picture partitioning unit may be configured to use the same block size for all pictures of a video sequence and the corresponding grid defining the block size, or to change the block size between pictures or subsets or groups of pictures, and partition each picture into the corresponding blocks.

(56) In further embodiments, the video encoder may be configured to receive directly a block **203** of the picture **17**, e.g. one, several or all blocks forming the picture **17**. The picture block **203** may also be referred to as current picture block or picture block to be coded.

(57) Like the picture **17**, the picture block **203** again is or can be regarded as a two-dimensional array or matrix of samples with intensity values (sample values), although of smaller dimension than the picture **17**. In other words, the block **203** may comprise, e.g., one sample array (e.g. a luma array in case of a monochrome picture **17**, or a luma or chroma array in case of a color picture) or three sample arrays (e.g. a luma and two chroma arrays in case of a color picture **17**) or any other number and/or kind of arrays depending on the color format applied. The number of samples in horizontal and vertical direction (or axis) of the block **203** define the size of block **203**. Accordingly, a block may, for example, an $M \times N$ (M -column by N -row) array of samples, or an $M \times N$ array of transform coefficients.

(58) Embodiments of the video encoder **20** as shown in FIG. 2 may be configured to encode the picture **17** block by block, e.g. the encoding and prediction is performed per block **203**.

(59) Embodiments of the video encoder **20** as shown in FIG. 2 may be further configured to partition and/or encode the picture by using slices (also referred to as video slices), wherein a picture may be partitioned into or encoded using one or more slices (typically non-overlapping), and each slice may comprise one or more blocks (e.g. CTUs).

(60) Embodiments of the video encoder **20** as shown in FIG. 2 may be further configured to partition and/or encode the picture by using tile groups (also referred to as video tile groups) and/or tiles (also referred to as video tiles), wherein a picture may be partitioned into or encoded using one or more tile groups (typically non-overlapping), and each tile group may comprise, e.g. one or more blocks (e.g. CTUs) or one or more tiles, wherein each tile, e.g. may be of rectangular shape and may comprise one or more blocks (e.g. CTUs), e.g. complete or fractional blocks.

(61) Residual Calculation

(62) The residual calculation unit **204** may be configured to calculate a residual block **205** (also referred to as residual **205**) based on the picture block **203** and a prediction block **265** (further details about the prediction block **265** are provided later), e.g. by subtracting sample values of the prediction block **265** from sample values of the picture block **203**, sample by sample (pixel by pixel) to obtain the residual block **205** in the sample domain.

(63) Transform

(64) The transform processing unit **206** may be configured to apply a transform, e.g. a discrete cosine transform (DCT) or discrete sine transform (DST), on the sample values of the residual block **205** to obtain transform coefficients **207** in a transform domain. The transform coefficients **207** may also be referred to as transform residual coefficients and represent the residual block **205** in the transform domain.

(65) The transform processing unit **206** may be configured to apply integer approximations of DCT/DST, such as the transforms specified for H.265/HEVC. Compared to an orthogonal DCT transform, such integer approximations are typically scaled by a certain factor. In order to preserve the norm of the residual block which is processed by forward and inverse transforms, additional scaling factors are applied as part of the transform process. The scaling factors are typically chosen based on certain constraints like scaling factors being a power of two for shift operations, bit depth of the transform coefficients, tradeoff between accuracy and implementation costs, etc. Specific scaling factors are, for example, specified for the inverse transform, e.g. by inverse transform processing unit **212** (and the corresponding inverse transform, e.g. by inverse transform processing unit **312** at video decoder **30**) and corresponding scaling factors for the forward transform, e.g. by transform processing unit **206**, at an encoder **20** may be specified accordingly.

(66) Embodiments of the video encoder **20** (respectively transform processing unit **206**) may be configured to output transform parameters, e.g. a type of transform or transforms, e.g. directly or encoded or compressed via the entropy encoding unit **270**, so that, e.g., the video decoder **30** may receive and use the transform parameters for decoding.

(67) Quantization

(68) The quantization unit **208** may be configured to quantize the transform coefficients **207** to obtain quantized coefficients **209**, e.g. by applying scalar quantization or vector quantization. The quantized coefficients **209** may also be referred to as quantized transform coefficients **209** or quantized residual coefficients **209**.

(69) The quantization process may reduce the bit depth associated with some or all of the transform coefficients **207**. For example, an n -bit transform coefficient may be rounded down to an m -bit Transform coefficient during quantization, where n is greater than m . The degree of quantization may be modified by adjusting a quantization parameter (QP). For example for scalar quantization, different scaling may be applied to achieve finer or coarser

quantization. Smaller quantization operation sizes correspond to finer quantization, whereas larger quantization operation sizes correspond to coarser quantization. The applicable quantization operation size may be indicated by a quantization parameter (QP). The quantization parameter may for example be an index to a predefined set of applicable quantization operation sizes. For example, small quantization parameters may correspond to fine quantization (small quantization operation sizes) and large quantization parameters may correspond to coarse quantization (large quantization operation sizes) or vice versa. The quantization may include division by a quantization operation size and a corresponding and/or the inverse dequantization, e.g. by inverse quantization unit **210**, may include multiplication by the quantization operation size. Embodiments according to some standards, e.g. HEVC, may be configured to use a quantization parameter to determine the quantization operation size. Generally, the quantization operation size may be calculated based on a quantization parameter using a fixed point approximation of an equation including division. Additional scaling factors may be introduced for quantization and dequantization to restore the norm of the residual block, which might get modified because of the scaling used in the fixed point approximation of the equation for quantization operation size and quantization parameter. In one example implementation, the scaling of the inverse transform and dequantization might be combined. Alternatively, customized quantization tables may be used and signaled from an encoder to a decoder, e.g. in a bitstream. The quantization is a lossy operation, wherein the loss increases with increasing quantization operation sizes.

(70) Embodiments of the video encoder **20** (respectively quantization unit **208**) may be configured to output quantization parameters (QP), e.g. directly or encoded via the entropy encoding unit **270**, so that, e.g., the video decoder **30** may receive and apply the quantization parameters for decoding.

(71) Inverse Quantization

(72) The inverse quantization unit **210** is configured to apply the inverse quantization of the quantization unit **208** on the quantized coefficients to obtain dequantized coefficients **211**, e.g. by applying the inverse of the quantization scheme applied by the quantization unit **208** based on or using the same quantization operation size as the quantization unit **208**. The dequantized coefficients **211** may also be referred to as dequantized residual coefficients **211** and correspond—although typically not identical to the transform coefficients due to the loss by quantization—to the transform coefficients **207**.

(73) Inverse Transform

(74) The inverse transform processing unit **212** is configured to apply the inverse transform of the transform applied by the transform processing unit **206**, e.g. an inverse discrete cosine transform (DCT) or inverse discrete sine transform (DST) or other inverse transforms, to obtain a reconstructed residual block **213** (or corresponding dequantized coefficients **213**) in the sample domain. The reconstructed residual block **213** may also be referred to as transform block **213**.

(75) Reconstruction

(76) The reconstruction unit **214** (e.g. adder or summer **214**) is configured to add the transform block **213** (i.e. reconstructed residual block **213**) to the prediction block **265** to obtain a reconstructed block **215** in the sample domain, e.g. by adding—sample by sample—the sample values of the reconstructed residual block **213** and the sample values of the prediction block **265**.

(77) Filtering

(78) The loop filter unit **220** (or short “loop filter” **220**), is configured to filter the reconstructed block **215** to obtain a filtered block **221**, or in general, to filter reconstructed samples to obtain filtered samples. The loop filter unit is, e.g., configured to smooth pixel transitions, or otherwise improve the video quality. The loop filter unit **220** may comprise one or more loop filters such as a de-blocking filter, a sample-adaptive offset (SAO) filter or one or more other filters, e.g. a bilateral filter, an adaptive loop filter (ALF), a sharpening, a smoothing filters or a collaborative filters, or any combination thereof. Although the loop filter unit **220** is shown in FIG. 2 as being an in loop filter, in other configurations, the loop filter unit **220** may be implemented as a post loop filter. The filtered block **221** may also be referred to as filtered reconstructed block **221**.

(79) Embodiments of the video encoder **20** (respectively loop filter unit **220**) may be configured to output loop filter parameters (such as sample adaptive offset information), e.g. directly or encoded via the entropy encoding unit **270**, so that, e.g., a decoder **30** may receive and apply the same loop filter parameters or respective loop filters for decoding.

(80) Decoded Picture Buffer

(81) The decoded picture buffer (DPB) **230** may be a memory that stores reference pictures, or in general reference picture data, for encoding video data by video encoder **20**. The DPB **230** may be formed by any of a variety of memory devices, such as dynamic random access memory (DRAM), including synchronous DRAM (SDRAM), magnetoresistive RAM (MRAM), resistive RAM (RRAM), or other types of memory devices. The decoded picture buffer (DPB) **230** may be configured to store one or more filtered blocks **221**. The decoded picture buffer **230** may be further configured to store other previously filtered blocks, e.g. previously reconstructed and filtered

blocks **221**, of the same current picture or of different pictures, e.g. previously reconstructed pictures, and may provide complete previously reconstructed, i.e. decoded, pictures (and corresponding reference blocks and samples) and/or a partially reconstructed current picture (and corresponding reference blocks and samples), for example for inter prediction. The decoded picture buffer (DPB) **230** may be also configured to store one or more unfiltered reconstructed blocks **215**, or in general unfiltered reconstructed samples, e.g. if the reconstructed block **215** is not filtered by loop filter unit **220**, or any other further processed version of the reconstructed blocks or samples.

(82) Mode Selection (Partitioning & Prediction)

(83) The mode selection unit **260** comprises partitioning unit **262**, inter-prediction unit **244** and intra-prediction unit **254**, and is configured to receive or obtain original picture data, e.g. an original block **203** (current block **203** of the current picture **17**), and reconstructed picture data, e.g. filtered and/or unfiltered reconstructed samples or blocks of the same (current) picture and/or from one or a plurality of previously decoded pictures, e.g. from decoded picture buffer **230** or other buffers (e.g. line buffer, not shown). The reconstructed picture data is used as reference picture data for prediction, e.g. inter-prediction or intra-prediction, to obtain a prediction block **265** or predictor **265**.

(84) Mode selection unit **260** may be configured to determine or select a partitioning for a current block prediction mode (including no partitioning) and a prediction mode (e.g. an intra or inter prediction mode) and generate a corresponding prediction block **265**, which is used for the calculation of the residual block **205** and for the reconstruction of the reconstructed block **215**.

(85) Embodiments of the mode selection unit **260** may be configured to select the partitioning and the prediction mode (e.g. from those supported by or available for mode selection unit **260**), which provide the best match or in other words the minimum residual (minimum residual means better compression for transmission or storage), or a minimum signaling overhead (minimum signaling overhead means better compression for transmission or storage), or which considers or balances both. The mode selection unit **260** may be configured to determine the partitioning and prediction mode based on rate distortion optimization (RDO), i.e. select the prediction mode which provides a minimum rate distortion. Terms like “best”, “minimum”, “optimum” etc. in this context do not necessarily refer to an overall “best”, “minimum”, “optimum”, etc. but may also refer to the fulfillment of a termination or selection criterion like a value exceeding or falling below a threshold or other constraints leading potentially to a “sub-optimum selection” but reducing complexity and processing time.

(86) In other words, the partitioning unit **262** may be configured to partition the block **203** into smaller block partitions or sub-blocks (which form again blocks), e.g. iteratively using quad-tree-partitioning (QT), binary partitioning (BT) or triple-tree-partitioning (TT) or any combination thereof, and to perform, e.g., the prediction for each of the block partitions or sub-blocks, wherein the mode selection comprises the selection of the tree-structure of the partitioned block **203** and the prediction modes are applied to each of the block partitions or sub-blocks.

(87) In the following the partitioning (e.g. by partitioning unit **260**) and prediction processing (by inter-prediction unit **244** and intra-prediction unit **254**) performed by an example video encoder **20** will be explained in more detail.

(88) Partitioning

(89) The partitioning unit **262** may partition (or split) a current block **203** into smaller partitions, e.g. smaller blocks of square or rectangular size. These smaller blocks (which may also be referred to as sub-blocks) may be further partitioned into even smaller partitions. This is also referred to tree-partitioning or hierarchical tree-partitioning, wherein a root block, e.g. at root tree-level 0 (hierarchy-level 0, depth 0), may be recursively partitioned, e.g. partitioned into two or more blocks of a next lower tree-level, e.g. nodes at tree-level 1 (hierarchy-level 1, depth 1), wherein these blocks may be again partitioned into two or more blocks of a next lower level, e.g. tree-level 2 (hierarchy-level 2, depth 2), etc. until the partitioning is terminated, e.g. because a termination criterion is fulfilled, e.g. a maximum tree depth or minimum block size is reached. Blocks which are not further partitioned are also referred to as leaf-blocks or leaf nodes of the tree. A tree using partitioning into two partitions is referred to as binary-tree (BT), a tree using partitioning into three partitions is referred to as ternary-tree (TT), and a tree using partitioning into four partitions is referred to as quad-tree (QT).

(90) As mentioned before, the term “block” as used herein may be a portion, in particular a square or rectangular portion, of a picture. With reference, for example, to HEVC and VVC, the block may be or correspond to a coding tree unit (CTU), a coding unit (CU), prediction unit (PU), and transform unit (TU) and/or to the corresponding blocks, e.g. a coding tree block (CTB), a coding block (CB), a transform block (TB) or prediction block (PB).

(91) For example, a coding tree unit (CTU) may be or comprise a CTB of luma samples, two corresponding CTBs of chroma samples of a picture that has three sample arrays, or a CTB of samples of a monochrome picture or a picture that is coded using three separate colour planes and syntax structures used to code the samples.

Correspondingly, a coding tree block (CTB) may be an $N \times N$ block of samples for some value of N such that the

division of a component into CTBs is a partitioning. A coding unit (CU) may be or comprise a coding block of luma samples, two corresponding coding blocks of chroma samples of a picture that has three sample arrays, or a coding block of samples of a monochrome picture or a picture that is coded using three separate colour planes and syntax structures used to code the samples. Correspondingly a coding block (CB) may be an $M \times N$ block of samples for some values of M and N such that the division of a CTB into coding blocks is a partitioning.

(92) In embodiments, e.g., according to HEVC, a coding tree unit (CTU) may be split into CUs by using a quad-tree structure denoted as coding tree. The decision whether to code a picture area using inter-picture (temporal) or intra-picture (spatial) prediction is made at the CU level. Each CU can be further split into one, two or four PUs according to the PU splitting type. Inside one PU, the same prediction process is applied and the relevant information is transmitted to the decoder on a PU basis. After obtaining the residual block by applying the prediction process based on the PU splitting type, a CU can be partitioned into transform units (TUs) according to another quadtree structure similar to the coding tree for the CU.

(93) In embodiments, e.g., according to the latest video coding standard currently in development, which is referred to as Versatile Video Coding (VVC), a combined Quad-tree and binary tree (QTBT) partitioning is for example used to partition a coding block. In the QTBT block structure, a CU can have either a square or rectangular shape. For example, a coding tree unit (CTU) is first partitioned by a quadtree structure. The quadtree leaf nodes are further partitioned by a binary tree or ternary (or triple) tree structure. The partitioning tree leaf nodes are called coding units (CUs), and that segmentation is used for prediction and transform processing without any further partitioning. This means that the CU, PU and TU have the same block size in the QTBT coding block structure. In parallel, multiple partition, for example, triple tree partition may be used together with the QTBT block structure.

(94) In one example, the mode selection unit **260** of video encoder **20** may be configured to perform any combination of the partitioning techniques described herein.

(95) As described above, the video encoder **20** is configured to determine or select the best or an optimum prediction mode from a set of (e.g. pre-determined) prediction modes. The set of prediction modes may comprise, e.g., intra-prediction modes and/or inter-prediction modes.

(96) Intra-Prediction

(97) The set of intra-prediction modes may comprise 35 different intra-prediction modes, e.g. non-directional modes like DC (or mean) mode and planar mode, or directional modes, e.g. as defined in HEVC, or may comprise 67 different intra-prediction modes, e.g. non-directional modes like DC (or mean) mode and planar mode, or directional modes, e.g. as defined for VVC.

(98) The intra-prediction unit **254** is configured to use reconstructed samples of neighboring blocks of the same current picture to generate an intra-prediction block **265** according to an intra-prediction mode of the set of intra-prediction modes.

(99) The intra prediction unit **254** (or in general the mode selection unit **260**) is further configured to output intra-prediction parameters (or in general information indicative of the selected intra prediction mode for the block) to the entropy encoding unit **270** in form of syntax elements **266** for inclusion into the encoded picture data **21**, so that, e.g., the video decoder **30** may receive and use the prediction parameters for decoding.

(100) Inter-Prediction

(101) The set of (or possible) inter-prediction modes depends on the available reference pictures (i.e. previous at least partially decoded pictures, e.g. stored in DBP **230**) and other inter-prediction parameters, e.g. whether the whole reference picture or only a part, e.g. a search window area around the area of the current block, of the reference picture is used for searching for a best matching reference block, and/or e.g. whether pixel interpolation is applied, e.g. half/semi-pel and/or quarter-pel interpolation, or not.

(102) Additional to the above prediction modes, skip mode and/or direct mode may be applied.

(103) The inter prediction unit **244** may include a motion estimation (ME) unit and a motion compensation (MC) unit (both not shown in FIG. 2). The motion estimation unit may be configured to receive or obtain the picture block **203** (current picture block **203** of the current picture **17**) and a decoded picture **231**, or at least one or a plurality of previously reconstructed blocks, e.g. reconstructed blocks of one or a plurality of other/different previously decoded pictures **231**, for motion estimation. E.g. a video sequence may comprise the current picture and the previously decoded pictures **231**, or in other words, the current picture and the previously decoded pictures **231** may be part of or form a sequence of pictures forming a video sequence.

(104) The encoder **20** may, e.g., be configured to select a reference block from a plurality of reference blocks of the same or different pictures of the plurality of other pictures and provide a reference picture (or reference picture index) and/or an offset (spatial offset) between the position (x, y coordinates) of the reference block and the position of the current block as inter prediction parameters to the motion estimation unit. This offset is also called motion vector (MV).

(105) The motion compensation unit is configured to obtain, e.g. receive, an inter prediction parameter and to

perform inter prediction based on or using the inter prediction parameter to obtain an inter prediction block **265**. Motion compensation, performed by the motion compensation unit, may involve fetching or generating the prediction block based on the motion/block vector determined by motion estimation, possibly performing interpolations to sub-pixel precision. Interpolation filtering may generate additional pixel samples from known pixel samples, thus potentially increasing the number of candidate prediction blocks that may be used to code a picture block. Upon receiving the motion vector for the PU of the current picture block, the motion compensation unit may locate the prediction block to which the motion vector points in one of the reference picture lists. (106) The motion compensation unit may also generate syntax elements associated with the blocks and video slices for use by video decoder **30** in decoding the picture blocks of the video slice. In addition or as an alternative to slices and respective syntax elements, tile groups and/or tiles and respective syntax elements may be generated or used.

(107) Entropy Coding

(108) The entropy encoding unit **270** is configured to apply, for example, an entropy encoding algorithm or scheme (e.g. a variable length coding (VLC) scheme, an context adaptive VLC scheme (CAVLC), an arithmetic coding scheme, a binarization, a context adaptive binary arithmetic coding (CABAC), syntax-based context-adaptive binary arithmetic coding (SBAC), probability interval partitioning entropy (PIPE) coding or another entropy encoding methodology or technique) or bypass (no compression) on the quantized coefficients **209**, inter prediction parameters, intra prediction parameters, loop filter parameters and/or other syntax elements to obtain encoded picture data **21** which can be output via the output **272**, e.g. in the form of an encoded bitstream **21**, so that, e.g., the video decoder **30** may receive and use the parameters for decoding. The encoded bitstream **21** may be transmitted to video decoder **30**, or stored in a memory for later transmission or retrieval by video decoder **30**.

(109) Other structural variations of the video encoder **20** can be used to encode the video stream. For example, a non-transform based encoder **20** can quantize the residual signal directly without the transform processing unit **206** for certain blocks or frames. In another implementation, an encoder **20** can have the quantization unit **208** and the inverse quantization unit **210** combined into a single unit.

(110) Decoder and Decoding Method

(111) FIG. **3** shows an example of a video decoder **30** that is configured to implement the techniques of this present application. The video decoder **30** is configured to receive encoded picture data **21** (e.g. encoded bitstream **21**), e.g. encoded by encoder **20**, to obtain a decoded picture **331**. The encoded picture data or bitstream comprises information for decoding the encoded picture data, e.g. data that represents picture blocks of an encoded video slice (and/or tile groups or tiles) and associated syntax elements.

(112) In the example of FIG. **3**, the decoder **30** comprises an entropy decoding unit **304**, an inverse quantization unit **310**, an inverse transform processing unit **312**, a reconstruction unit **314** (e.g. a summer **314**), a loop filter **320**, a decoded picture buffer (DPB) **330**, a mode application unit **360**, an inter prediction unit **344** and an intra prediction unit **354**. Inter prediction unit **344** may be or include a motion compensation unit. Video decoder **30** may, in some examples, perform a decoding pass generally reciprocal to the encoding pass described with respect to video encoder **100** from FIG. **2**.

(113) As explained with regard to the encoder **20**, the inverse quantization unit **210**, the inverse transform processing unit **212**, the reconstruction unit **214** the loop filter **220**, the decoded picture buffer (DPB) **230**, the inter prediction unit **344** and the intra prediction unit **354** are also referred to as forming the “built-in decoder” of video encoder **20**. Accordingly, the inverse quantization unit **310** may be identical in function to the inverse quantization unit **110**, the inverse transform processing unit **312** may be identical in function to the inverse transform processing unit **212**, the reconstruction unit **314** may be identical in function to reconstruction unit **214**, the loop filter **320** may be identical in function to the loop filter **220**, and the decoded picture buffer **330** may be identical in function to the decoded picture buffer **230**. Therefore, the explanations provided for the respective units and functions of the video **20** encoder apply correspondingly to the respective units and functions of the video decoder **30**.

(114) Entropy Decoding

(115) The entropy decoding unit **304** is configured to parse the bitstream **21** (or in general encoded picture data **21**) and perform, for example, entropy decoding to the encoded picture data **21** to obtain, e.g., quantized coefficients **309** and/or decoded coding parameters (not shown in FIG. **3**), e.g. any or all of inter prediction parameters (e.g. reference picture index and motion vector), intra prediction parameter (e.g. intra prediction mode or index), transform parameters, quantization parameters, loop filter parameters, and/or other syntax elements. Entropy decoding unit **304** maybe configured to apply the decoding algorithms or schemes corresponding to the encoding schemes as described with regard to the entropy encoding unit **270** of the encoder **20**. Entropy decoding unit **304** may be further configured to provide inter prediction parameters, intra prediction parameter and/or other syntax elements to the mode application unit **360** and other parameters to other units of the decoder **30**. Video decoder **30** may receive the syntax elements at the video slice level and/or the video block level. In addition or as an

alternative to slices and respective syntax elements, tile groups and/or tiles and respective syntax elements may be received and/or used.

(116) Inverse Quantization

(117) The inverse quantization unit **310** may be configured to receive quantization parameters (QP) (or in general information related to the inverse quantization) and quantized coefficients from the encoded picture data **21** (e.g. by parsing and/or decoding, e.g. by entropy decoding unit **304**) and to apply based on the quantization parameters an inverse quantization on the decoded quantized coefficients **309** to obtain dequantized coefficients **311**, which may also be referred to as transform coefficients **311**. The inverse quantization process may include use of a quantization parameter determined by video encoder **20** for each video block in the video slice (or tile or tile group) to determine a degree of quantization and, likewise, a degree of inverse quantization that should be applied.

(118) Inverse Transform

(119) Inverse transform processing unit **312** may be configured to receive dequantized coefficients **311**, also referred to as transform coefficients **311**, and to apply a transform to the dequantized coefficients **311** in order to obtain reconstructed residual blocks **213** in the sample domain. The reconstructed residual blocks **213** may also be referred to as transform blocks **313**. The transform may be an inverse transform, e.g., an inverse DCT, an inverse DST, an inverse integer transform, or a conceptually similar inverse transform process. The inverse transform processing unit **312** may be further configured to receive transform parameters or corresponding information from the encoded picture data **21** (e.g. by parsing and/or decoding, e.g. by entropy decoding unit **304**) to determine the transform to be applied to the dequantized coefficients **311**.

(120) Reconstruction

(121) The reconstruction unit **314** (e.g. adder or summer **314**) may be configured to add the reconstructed residual block **313**, to the prediction block **365** to obtain a reconstructed block **315** in the sample domain, e.g. by adding the sample values of the reconstructed residual block **313** and the sample values of the prediction block **365**.

(122) Filtering

(123) The loop filter unit **320** (either in the coding loop or after the coding loop) is configured to filter the reconstructed block **315** to obtain a filtered block **321**, e.g. to smooth pixel transitions, or otherwise improve the video quality. The loop filter unit **320** may comprise one or more loop filters such as a de-blocking filter, a sample-adaptive offset (SAO) filter or one or more other filters, e.g. a bilateral filter, an adaptive loop filter (ALF), a sharpening, a smoothing filters or a collaborative filters, or any combination thereof. Although the loop filter unit **320** is shown in FIG. 3 as being an in loop filter, in other configurations, the loop filter unit **320** may be implemented as a post loop filter.

(124) Decoded Picture Buffer

(125) The decoded video blocks **321** of a picture are then stored in decoded picture buffer **330**, which stores the decoded pictures **331** as reference pictures for subsequent motion compensation for other pictures and/or for output respectively display.

(126) The decoder **30** is configured to output the decoded picture **311**, e.g. via output **312**, for presentation or viewing to a user.

(127) Prediction

(128) The inter prediction unit **344** may be identical to the inter prediction unit **244** (in particular to the motion compensation unit) and the intra prediction unit **354** may be identical to the inter prediction unit **254** in function, and performs split or partitioning decisions and prediction based on the partitioning and/or prediction parameters or respective information received from the encoded picture data **21** (e.g. by parsing and/or decoding, e.g. by entropy decoding unit **304**). Mode application unit **360** may be configured to perform the prediction (intra or inter prediction) per block based on reconstructed pictures, blocks or respective samples (filtered or unfiltered) to obtain the prediction block **365**.

(129) When the video slice is coded as an intra coded (I) slice, intra prediction unit **354** of mode application unit **360** is configured to generate prediction block **365** for a picture block of the current video slice based on a signaled intra prediction mode and data from previously decoded blocks of the current picture. When the video picture is coded as an inter coded (i.e., B, or P) slice, inter prediction unit **344** (e.g. motion compensation unit) of mode application unit **360** is configured to produce prediction blocks **365** for a video block of the current video slice based on the motion vectors and other syntax elements received from entropy decoding unit **304**. For inter prediction, the prediction blocks may be produced from one of the reference pictures within one of the reference picture lists. Video decoder **30** may construct the reference frame lists, List 0 and List 1, using default construction techniques based on reference pictures stored in DPB **330**. The same or similar may be applied for or by embodiments using tile groups (e.g. video tile groups) and/or tiles (e.g. video tiles) in addition or alternatively to slices (e.g. video slices), e.g. a video may be coded using I, P or B tile groups and/or tiles.

(130) Mode application unit **360** is configured to determine the prediction information for a video block of the current video slice by parsing the motion vectors or related information and other syntax elements, and uses the

prediction information to produce the prediction blocks for the current video block being decoded. For example, the mode application unit **360** uses some of the received syntax elements to determine a prediction mode (e.g., intra or inter prediction) used to code the video blocks of the video slice, an inter prediction slice type (e.g., B slice, P slice, or GPB slice), construction information for one or more of the reference picture lists for the slice, motion vectors for each inter encoded video block of the slice, inter prediction status for each inter coded video block of the slice, and other information to decode the video blocks in the current video slice. The same or similar may be applied for or by embodiments using tile groups (e.g. video tile groups) and/or tiles (e.g. video tiles) in addition or alternatively to slices (e.g. video slices), e.g. a video may be coded using I, P or B tile groups and/or tiles.

(131) Embodiments of the video decoder **30** as shown in FIG. **3** may be configured to partition and/or decode the picture by using slices (also referred to as video slices), wherein a picture may be partitioned into or decoded using one or more slices (typically non-overlapping), and each slice may comprise one or more blocks (e.g. CTUs).

(132) Embodiments of the video decoder **30** as shown in FIG. **3** may be configured to partition and/or decode the picture by using tile groups (also referred to as video tile groups) and/or tiles (also referred to as video tiles), wherein a picture may be partitioned into or decoded using one or more tile groups (typically non-overlapping), and each tile group may comprise, e.g. one or more blocks (e.g. CTUs) or one or more tiles, wherein each tile, e.g. may be of rectangular shape and may comprise one or more blocks (e.g. CTUs), e.g. complete or fractional blocks.

(133) Other variations of the video decoder **30** can be used to decode the encoded picture data **21**. For example, the decoder **30** can produce the output video stream without the loop filtering unit **320**. For example, a non-transform based decoder **30** can inverse-quantize the residual signal directly without the inverse-transform processing unit **312** for certain blocks or frames. In another implementation, the video decoder **30** can have the inverse-quantization unit **310** and the inverse-transform processing unit **312** combined into a single unit.

(134) It should be understood that, in the encoder **20** and the decoder **30**, a processing result of a current operation may be further processed and then output to the next operation. For example, after interpolation filtering, motion vector derivation or loop filtering, a further operation, such as Clip or shift, may be performed on the processing result of the interpolation filtering, motion vector derivation or loop filtering.

(135) It should be noted that further operations may be applied to the derived motion vectors of current block (including but not limit to control point motion vectors of affine mode, sub-block motion vectors in affine, planar, ATMVP modes, temporal motion vectors, and so on). For example, the value of motion vector is constrained to a predefined range according to its representing bit. If the representing bit of motion vector is bitDepth, then the range is $-2^{\text{bitDepth}-1}$ to $2^{\text{bitDepth}-1}-1$, where “ $2^{\text{bitDepth}-1}$ ” means exponentiation. For example, if bitDepth is set equal to 16, the range is -32768 to 32767 ; if bitDepth is set equal to 18, the range is -131072 to 131071 . For example, the value of the derived motion vector (e.g. the MVs of four 4×4 sub-blocks within one 8×8 block) is constrained such that the max difference between integer parts of the four 4×4 sub-block MVs is no more than N pixels, such as no more than 1 pixel. Here provides two methods for constraining the motion vector according to the bitDepth.

(136) Method 1: remove the overflow MSB (most significant bit) by flowing operations

$$ux = (mvx + 2.\text{sup.bitDepth}) \% 2.\text{sup.bitDepth} \quad (1)$$

$$mvx = (ux \geq 2.\text{sup.bitDepth}-1) ? (ux - 2.\text{sup.bitDepth}) : ux \quad (2)$$

$$uy = (mvy + 2.\text{sup.bitDepth}) \% 2.\text{sup.bitDepth} \quad (3)$$

$$mvy = (uy \geq 2.\text{sup.bitDepth}-1) ? (uy - 2.\text{sup.bitDepth}) : uy \quad (4)$$

where mvx is a horizontal component of a motion vector of an image block or a sub-block, mvy is a vertical component of a motion vector of an image block or a sub-block, and ux and uy indicates an intermediate valued.

(137) For example, if the value of mvx is -32769 , after applying formula (1) and (2), the resulting value is 32767 . In computer system, decimal numbers are stored as two's complement. The two's complement of -32769 is $1,0111,1111,1111,1111$ (17 bits), then the MSB is discarded, so the resulting two's complement is $0111,1111,1111,1111$ (decimal number is 32767), which is same as the output by applying formula (1) and (2).

$$ux = (mvp_x + mvd_x + 2.\text{sup.bitDepth}) \% 2.\text{sup.bitDepth} \quad (5)$$

$$mvx = (ux \geq 2.\text{sup.bitDepth}-1) ? (ux - 2.\text{sup.bitDepth}) : ux \quad (6)$$

$$uy = (mvp_y + mvd_y + 2.\text{sup.bitDepth}) \% 2.\text{sup.bitDepth} \quad (7)$$

$$mvy = (uy \geq 2.\text{sup.bitDepth}-1) ? (uy - 2.\text{sup.bitDepth}) : uy \quad (8)$$

(138) The operations may be applied during the sum of mvp and mvd, as shown in formula (5) to (8).

(139) Method 2: Remove the Overflow MSB by Clipping the Value

$$vx = \text{Clip3}(-2.\text{sup.bitDepth}-1, 2.\text{sup.bitDepth}-1-1, vx)$$

$$vy = \text{Clip3}(-2.\text{sup.bitDepth}-1, 2.\text{sup.bitDepth}-1-1, vy)$$

where vx is a horizontal component of a motion vector of an image block or a sub-block, vy is a vertical component of a motion vector of an image block or a sub-block; x, y and z respectively correspond to three input value of the MV clipping process, and the definition of function Clip3 is as follows:

x; z < x
 (140) i . Clip3(x, y, z) = { y; z > y
 z; otherwise

(141) FIG. 4 is a schematic diagram of a video coding device **400** according to an embodiment of the disclosure. The video coding device **400** is suitable for implementing the disclosed embodiments as described herein. In an embodiment, the video coding device **400** may be a decoder such as video decoder **30** of FIG. 1A or an encoder such as video encoder **20** of FIG. 1A.

(142) The video coding device **400** comprises ingress ports **410** (or input ports **410**) and receiver units (Rx) **420** for receiving data; a processor, logic unit, or central processing unit (CPU) **430** to process the data; transmitter units (Tx) **440** and egress ports **450** (or output ports **450**) for transmitting the data; and a memory **460** for storing the data. The video coding device **400** may also comprise optical-to-electrical (OE) components and electrical-to-optical (EO) components coupled to the ingress ports **410**, the receiver units **420**, the transmitter units **440**, and the egress ports **450** for egress or ingress of optical or electrical signals.

(143) The processor **430** is implemented by hardware and software. The processor **430** may be implemented as one or more CPU chips, cores (e.g., as a multi-core processor), FPGAs, ASICs, and DSPs. The processor **430** is in communication with the ingress ports **410**, receiver units **420**, transmitter units **440**, egress ports **450**, and memory **460**. The processor **430** comprises a coding module **470**. The coding module **470** implements the disclosed embodiments described above. For instance, the coding module **470** implements, processes, prepares, or provides the various coding operations. The inclusion of the coding module **470** therefore provides a substantial improvement to the functionality of the video coding device **400** and effects a transformation of the video coding device **400** to a different state. Alternatively, the coding module **470** is implemented as instructions stored in the memory **460** and executed by the processor **430**.

(144) The memory **460** may comprise one or more disks, tape drives, and solid-state drives and may be used as an over-flow data storage device, to store programs when such programs are selected for execution, and to store instructions and data that are read during program execution. The memory **460** may be, for example, volatile and/or non-volatile and may be a read-only memory (ROM), random access memory (RAM), ternary content-addressable memory (TCAM), and/or static random-access memory (SRAM).

(145) FIG. 5 is a simplified block diagram of an apparatus **500** that may be used as either or both of the source device **12** and the destination device **14** from FIG. 1 according to an exemplary embodiment.

(146) A processor **502** in the apparatus **500** can be a central processing unit. Alternatively, the processor **502** can be any other type of device, or multiple devices, capable of manipulating or processing information now-existing or hereafter developed. Although the disclosed implementations can be practiced with a single processor as shown, e.g., the processor **502**, advantages in speed and efficiency can be achieved using more than one processor.

(147) A memory **504** in the apparatus **500** can be a read only memory (ROM) device or a random access memory (RAM) device in an implementation. Any other suitable type of storage device can be used as the memory **504**. The memory **504** can include code and data **506** that is accessed by the processor **502** using a bus **512**. The memory **504** can further include an operating system **508** and application programs **510**, the application programs **510** including at least one program that permits the processor **502** to perform the methods described here. For example, the application programs **510** can include applications **1** through **N**, which further include a video coding application that performs the methods described here.

(148) The apparatus **500** can also include one or more output devices, such as a display **518**. The display **518** may be, in one example, a touch sensitive display that combines a display with a touch sensitive element that is operable to sense touch inputs. The display **518** can be coupled to the processor **502** via the bus **512**.

(149) Although depicted here as a single bus, the bus **512** of the apparatus **500** can be composed of multiple buses. Further, the secondary storage **514** can be directly coupled to the other components of the apparatus **500** or can be accessed via a network and can comprise a single integrated unit such as a memory card or multiple units such as multiple memory cards. The apparatus **500** can thus be implemented in a wide variety of configurations.

(150) Position-dependent intra prediction combination, PDPC, (also known as position-dependent intra prediction sample filtering process) is a post-prediction filtering process applied to predicted blocks, these predicted blocks are generated according to intra prediction modes such as DC mode (INTRA_DC), planer mode (INTRA_PLANAR), and a subset of directional (angular) modes including horizontal (INTRA_ANGULAR18) mode and vertical (INTRA_ANGULAR50) mode. Directional modes excluding horizontal (INTRA_ANGULAR18) and vertical (INTRA_ANGULAR50) are referred to as oblique directional (angular) modes or skew directional (angular) modes. The current version of the VVC specification draft (document JVET-P2001-vE: B. Bross, J. Chen, S. Liu, Y.-K. Wang, "Versatile Video Coding (Draft 7)," output document JVET-P2001 of the 16.sup.th JVET meeting, Geneva, Switzerland; this document is contained in file JVET-P2001-v14: http://phenix.it-sudparis.eu/jvet/doc_end_user/documents/16_Geneva/wg11/JVET-P2001-v14.zip) prescribes the

following sequence of operations in Section 8.4.5.2.14 “Position-dependent intra prediction sample filtering process” to perform PDPC:

(151) Specification of INTRA_ANGULAR2 . . . INTRA_ANGULAR66 Intra Prediction Modes

(152) Inputs to this process are: the intra prediction mode `predModeIntra`, a variable `nTbW` specifying the transform block width, a variable `nTbH` specifying the transform block height, a variable `refW` specifying the reference samples width, a variable `refH` specifying the reference samples height, the predicted samples `predSamples[x][y]`, with $x=0 \dots nTbW-1$, $y=0 \dots nTbH-1$, the neighbouring samples `p[x][y]`, with $x=-1$, $y=-1 \dots refH-1$ and $x=0 \dots refW-1$, $y=-1$. Outputs of this process are the modified predicted samples `predSamples[x][y]` with $x=0 \dots nTbW-1$, $y=0 \dots nTbH-1$. The variable `nScale` is derived as follows: If `predModeIntra` is greater than INTRA_ANGULAR50, `nScale` is set equal to $\text{Min}(2, \text{Log } 2(nTbH) - \text{Floor}(\text{Log } 2(3 * \text{invAngle} - 2)) + 8)$, using `invAngle` as specified in clause 8.4.5.2.12. Otherwise, if `predModeIntra` is less than INTRA_ANGULAR18, not equal to INTRA_PLANAR and not equal to INTRA_DC, `nScale` is set equal to $\text{Min}(2, \text{Log } 2(nTbW) - \text{Floor}(\text{Log } 2(3 * \text{invAngle} - 2)) + 8)$, using `invAngle` as specified in clause 8.4.5.2.12. Otherwise, `nScale` is set to $((\text{Log } 2(nTbW) + \text{Log } 2(nTbH) - 2) >> 2)$. The reference sample arrays `mainRef[x]` and `sideRef[y]`, with $x=0 \dots refW-1$ and $y=0 \dots refH-1$ are derived as follows:

`mainRef[x]=p[x][-1]`

`sideRef[y]=p[-1][y]` The variables `refL[x][y]`, `refT[x][y]`, `wT[y]`, and `wL[x]` with $x=0 \dots nTbW-1$, $y=0 \dots nTbH-1$ are derived as follows: If `predModeIntra` is equal to INTRA_PLANAR or INTRA_DC, the following applies:

`refL[x][y]=p[-1][y]`

`refT[x][y]=p[x][-1]`

`wT[y]=32>>((y<<1)>>nScale)`

`wL[x]=32>>((x<<1)>>nScale)` Otherwise, if `predModeIntra` is equal to INTRA_ANGULAR18 or INTRA_ANGULAR50, the following applies:

`refL[x][y]=p[-1][y]-p[-1][-1]+predSamples[x][y]`

`refT[x][y]=p[x][-1]-p[-1][-1]+predSamples[x][y]`

`wT[y]=(predModeIntra==INTRA_ANGULAR18)?`

`32>>((y>>1)>>nScale):0`

`wL[x]=(predModeIntra==INTRA_ANGULAR50)?32>>((x<<1)>>nScale):0` Otherwise, if `predModeIntra` is less than INTRA_ANGULAR18 and `nScale` is equal to or greater than 0, the following ordered operations apply: 1.

The variables `dXInt[y]` and `dX[x][y]` are derived as follows using `invAngle` as specified in clause 8.4.5.2.12 depending on `intraPredMode`:

`dXInt[y]=((y+1)*invAngle+256)>>9`

`dX[x][y]=x+dXInt[y]` 2. The variables `refL[x][y]`, `refT[x][y]`, `wT[y]`, and `wL[x]` are derived as follows:

`refL[x][y]=0`

`refT[x][y]=(y<(3<<nScale))?mainRef[dX[x][y]]:0`

`wT[y]=32>>((y<<1)>>nScale)`

`wL[x]=0` Otherwise, if `predModeIntra` is greater than INTRA_ANGULAR50 and `nScale` is equal to or greater than 0, the following ordered operations apply: 1. The variables `dYInt[x]` and `dY[x][y]` are derived as follows using `invAngle` as specified in clause 8.4.5.2.12 depending on `intraPredMode`:

`dYInt[x]=((x+1)*invAngle+256)>>9`

`dY[x][y]=y+dYInt[x]` 2. The variables `refL[x][y]`, `refT[x][y]`, `wT[y]`, and `wL[x]` are derived as follows:

`refL[x][y]=(x<(3<<nScale))?sideRef[dY[x][y]]:0`

`refT[x][y]=0`

`wT[y]=0`

`wL[x]=32>>((x<<1)>>nScale)` Otherwise, `refL[x][y]`, `refT[x][y]`, `wT[y]`, and `wL[x]` are all set equal to 0. The values of the modified predicted samples `predSamples[x][y]`, with $x=0 \dots nTbW-1$, $y=0 \dots nTbH-1$ are derived as follows:

`predSamples[x][y]=Clip1((refL[x][y]*wL[x]+refT[x][y]*wT[y]+(64-wL[x]-wT[y])*predSamples[x][y]+32)>>6)`

Clause 8.4.5.2.12 “Specification of INTRA_ANGULAR2 . . . INTRA_ANGULAR66 intra prediction modes” of the current VVC specification draft (document JVET-P2001-vE: B. Bross, J. Chen, S. Liu, Y.-K. Wang, “Versatile Video Coding (Draft 7),” output document JVET-P2001 of the 16.sup.th JVET meeting, Geneva, Switzerland) is given below:

Specification of INTRA_ANGULAR2 . . . INTRA_ANGULAR66 Intra Prediction Modes

(153) the intra prediction mode `predModeIntra`, a variable `refIdx` specifying the intra prediction reference line index, a variable `nTbW` specifying the transform block width, a variable `nTbH` specifying the transform block height, a variable `refW` specifying the reference samples width, a variable `refH` specifying the reference samples height, a variable `nCbW` specifying the coding block width, a variable `nCbH` specifying the coding block height, a

variable refFilterFlag specifying the value of reference filter flag, a variable cIdx specifying the colour component of the current block, the neighbouring samples $p[x][y]$, with $x=-1-\text{refIdx}$, $y=-1-\text{refIdx} \dots \text{refH}-1$ and $x=-\text{refIdx} \dots \text{refW}-1$, $y=-1-\text{refIdx}$. Outputs of this process are the predicted samples $\text{predSamples}[x][y]$, with $x=0 \dots \text{nTbW}-1$, $y=0 \dots \text{nTbH}-1$. The variable nTbS is set equal to $(\text{Log } 2(\text{nTbW}) + \text{Log } 2(\text{nTbH})) >> 1$. The variable filterFlag is derived as follows: If one or more of the following conditions is true, filterFlag is set equal to 0: refFilterFlag is equal to 1; refIdx is not equal to 0; $\text{IntraSubPartitionsSplitType}$ is not equal to ISP_NO_SPLIT . Otherwise, the following applies: The variable minDistVerHor is set equal to $\text{Min}(\text{Abs}(\text{predModeIntra}-50), \text{Abs}(\text{predModeIntra}-18))$. The variable $\text{intraHorVerDistThres}[\text{nTbS}]$ is specified in Table 1. The variable filterFlag is derived as follows: If minDistVerHor is greater than $\text{intraHorVerDistThres}[\text{nTbS}]$, filterFlag is set equal to 1. Otherwise, filterFlag is set equal to 0.

(154) TABLE-US-00001 TABLE 1 Specification of $\text{intraHorVerDistThres}[\text{nTbS}]$ for various transform block sizes nTbS

nTbS	2	3	4	5	6	7
$\text{intraHorVerDistThres}$	24	14	2	0	0	0

(155) FIG. 6 illustrates the 93 prediction directions, where the dashed directions are associated with the wide-angle modes that are only applied to non-square blocks. Table 2 specifies the mapping table between predModeIntra and the angle parameter intraPredAngle .

(156) TABLE-US-00002 TABLE 2 Specification of intraPredAngle

predModeIntra	-14	-13	-12	-11	-10	-9	-8	-7	-6	-5	-4	-3	-2	-1	2	3	4
intraPredAngle	512	341	256	171	128	102	86	73	64	57	51	45	39	35	32	29	26
predModeIntra	5	6	7	8	9	10	11	12	13	14	15	16	17	18	19	20	21
intraPredAngle	23	20	18	16	14	12	10	8	6	4	3	2	1	0	-1	-2	-3
predModeIntra	22	23	24	25	26	27	28	29	30	31	32	33	34	35	36	37	38
intraPredAngle	-4	-6	-8	-10	-12	-14	-16	-18	-20	-23	-26	-29	-32	-29	-26	-23	-20
predModeIntra	39	40	41	42	43	44	45	46	47	48	49	50	51	52	53	54	55
intraPredAngle	-18	-16	-14	-12	-10	-8	-6	-4	-3	-2	-1	0	1	2	3	4	6
predModeIntra	56	57	58	59	60	61	62	63	64	65	66	67	68	69	70	71	72
intraPredAngle	8	10	12	14	16	18	20	23	26	29	32	35	39	45	51	57	64
predModeIntra	73	74	75	76	77	78	79	80									
intraPredAngle	73	86	102	128	171	256	341	512									

(157) The inverse angle parameter invAngle is derived based on intraPredAngle as follows:
 $\text{invAngle} = \text{Round}$

(158) The interpolation filter coefficients $\text{fC}[\text{phase}][j]$ and $\text{fG}[\text{phase}][j]$ with $\text{phase}=0 \dots 31$ and $j=0 \dots 3$ are specified in Table 3.

(159) TABLE-US-00003 TABLE 3 Specification of interpolation filter coefficients fC and fG

Fractional sample position p	$\text{f.sub.C}[p][0]$	$\text{f.sub.C}[p][1]$	$\text{f.sub.C}[p][2]$	$\text{f.sub.C}[p][3]$	$\text{fG}[p][0]$	$\text{fG}[p][1]$	$\text{fG}[p][2]$	$\text{fG}[p][3]$
0	0	0	0	0	0	0	0	0
1	64	0	0	16	32	16	0	-1
2	63	2	0	16	32	16	0	-2
3	62	4	0	15	31	17	1	-3
4	60	7	-1	15	31	17	4	-2
5	58	10	-2	14	30	18	2	5
6	57	12	-2	14	30	18	2	6
7	56	14	-2	13	29	19	3	7
8	55	15	-2	13	29	19	3	8
9	54	16	-2	12	28	20	4	9
10	53	18	-2	12	28	20	4	10
11	52	20	-4	10	26	22	6	14
12	50	25	-4	9	25	23	7	15
13	49	24	-3	11	27	21	5	12
14	48	23	-4	9	25	23	7	16
15	47	22	-4	8	24	24	8	17
16	46	21	-3	24	49	-6	6	22
17	45	20	-4	28	46	-6	6	22
18	44	19	-4	28	46	-6	6	22
19	43	18	-5	21	27	11	23	-2
20	42	17	-5	21	27	11	23	-2
21	41	16	-4	20	28	12	25	-2
22	40	15	-4	20	28	12	25	-2
23	39	14	-4	20	28	12	25	-2
24	38	13	-4	19	29	13	27	-2
25	37	12	-4	19	29	13	27	-2
26	36	11	-4	19	29	13	27	-2
27	35	10	-4	18	30	14	29	-1
28	34	9	-4	18	30	14	29	-1
29	33	8	-4	17	31	15	31	0
30	32	7	-4	17	31	15	31	0
31	31	6	-4	17	31	15	31	0

(160) The values of the prediction samples $\text{predSamples}[x][y]$, with $x=0 \dots \text{nTbW}-1$, $y=0 \dots \text{nTbH}-1$ are derived as follows: If predModeIntra is greater than or equal to 34, the following ordered operations apply: 1. The reference sample array $\text{ref}[x]$ is specified as follows: The following applies:

$\text{ref}[x] = p[-1-\text{refIdx}+x][-1-\text{refIdx}]$, with $x=0 \dots \text{nTbW}+\text{refIdx}+1$. If intraPredAngle is less than 0, the main reference sample array is extended as follows:

$\text{ref}[x] = p[-1-\text{refIdx}][-1-\text{refIdx}+\text{Min}((x*\text{invAngle}+256)>>9, \text{nTbH})]$, with $x=-\text{nTbH} \dots -1$. Otherwise,

$\text{ref}[x] = p[-1-\text{refIdx}+x][-1-\text{refIdx}]$, with $x=\text{nTbW}+2+\text{refIdx} \dots \text{refW}+\text{refIdx}$. The additional samples $\text{ref}[\text{refW}+\text{refIdx}+x]$ with $x=1 \dots (\text{Max}(1, \text{nTbW}/\text{nTbH})*\text{refIdx}+1)$ are derived as follows:

$\text{ref}[\text{refW}+\text{refIdx}+x] = p[-1+\text{refW}][-1-\text{refIdx}]$. 2. The values of the prediction samples $\text{predSamples}[x][y]$, with $x=0 \dots \text{nTbW}-1$, $y=0 \dots \text{nTbH}-1$ are derived as follows: The index variable $i\text{Idx}$ and the multiplication factor $i\text{Fact}$ are derived as follows:

$i\text{Idx} = (((y+1+\text{refIdx})*\text{intraPredAngle})>>5) + \text{refIdx}$

$i\text{Fact} = ((y+1+\text{refIdx})*\text{intraPredAngle}) \& 31$ If cIdx is equal to 0, the following applies: The interpolation filter coefficients $\text{fT}[j]$ with $j=0 \dots 3$ are derived as follows:

$\text{fT}[j] = \text{filterFlag} ? \text{fG}[i\text{Fact}][j] : \text{fC}[i\text{Fact}][j]$. The value of the prediction samples $\text{predSamples}[x][y]$ is derived as follows: $\text{predSamples}[x][y] = \text{Clip1}((() + 32) >> 6)$.

$i\text{Fact} = ((y+1+\text{refIdx})*\text{intraPredAngle}) \& 31$ Otherwise (cIdx is not equal to 0), depending on the value of $i\text{Fact}$, the following applies: If $i\text{Fact}$ is not equal to 0, the value of the prediction samples $\text{predSamples}[x][y]$ is derived as follows:

$\text{predSamples}[x][y] = ((32-i\text{Fact})*\text{ref}[x+i\text{Idx}+1] + i\text{Fact}*\text{ref}[x+i\text{Idx}+2] + 16) >> 5$. Otherwise, the value of the

prediction samples $\text{predSamples}[x][y]$ is derived as follows:
 $\text{predSamples}[x][y] = \text{ref}[x+i\text{Idx}+1]$. Otherwise (predModeIntra is less than 34), the following ordered operations apply: The reference sample array $\text{ref}[x]$ is specified as follows: The following applies:
 $\text{ref}[x] = p[-1-\text{refIdx}][-1-\text{refIdx}+x]$, with $x=0 \dots n\text{TbH}+\text{refIdx}+1$; If intraPredAngle is less than 0, the main reference sample array is extended as follows:
 $\text{ref}[x] = p[-1-\text{refIdx}+\text{Min}((x*\text{invAngle}+256)>>9, n\text{TbW})][-1-\text{refIdx}]$, with $x=-n\text{TbW} \dots -1$. Otherwise,
 $\text{ref}[x] = p[-1-\text{refIdx}][-1-\text{refIdx}+x]$, with $x=n\text{TbH}+2+\text{refIdx} \dots \text{refH}+\text{refIdx}$. The additional samples $\text{ref}[\text{refH}+\text{refIdx}+x]$ with $x=1 \dots (\text{Max}(1, n\text{TbH}/n\text{TbW})*\text{refIdx}+1)$ are derived as follows:
 $\text{ref}[\text{refH}+\text{refIdx}+x] = p[-1+\text{refH}][-1-\text{refIdx}]$. The values of the prediction samples $\text{predSamples}[x][y]$, with $x=0 \dots n\text{TbW}-1, y=0 \dots n\text{TbH}-1$ are derived as follows: The index variable $i\text{Idx}$ and the multiplication factor $i\text{Fact}$ are derived as follows:
 $i\text{Idx} = (((x+1+\text{refIdx})*\text{intraPredAngle})>>5) + \text{refIdx}$
 $i\text{Fact} = ((x+1+\text{refIdx})*\text{intraPredAngle}) \& 31$ If cIdx is equal to 0, the following applies: The interpolation filter coefficients $fT[j]$ with $j=0 \dots 3$ are derived as follows:
 $fT[j] = \text{filterFlag} ? fG[i\text{Fact}][j] : fC[i\text{Fact}][j]$. The value of the prediction samples $\text{predSamples}[x][y]$ is derived as follows: $\text{predSamples}[x][y] = \text{Clip1}((()+32)>>6)$. Otherwise (cIdx is not equal to 0), depending on the value of $i\text{Fact}$, the following applies: If $i\text{Fact}$ is not equal to 0, the value of the prediction samples $\text{predSamples}[x][y]$ is derived as follows:
 $\text{predSamples}[x][y] = ((32-i\text{Fact})*\text{ref}[y+i\text{Idx}+1] + i\text{Fact}*\text{ref}[y+i\text{Idx}+2]+16)>>5$; Otherwise, the value of the prediction samples $\text{predSamples}[x][y]$ is derived as follows:
 $\text{predSamples}[x][y] = \text{ref}[y+i\text{Idx}+1]$.

(161) Embodiments below describe a mechanism to terminate PDPC for oblique directional modes, when a derived value of the variable $n\text{Scale}$ is less than 0. For these embodiments, Section 8.4.5.2.14 “Position-dependent intra prediction sample filtering process” can be rewritten as follows:

Embodiment 1

(162) Specification of INTRA_ANGULAR2 ... INTRA_ANGULAR66 Intra Prediction Modes

(163) Inputs to this process are: the intra prediction mode predModeIntra , a variable $n\text{TbW}$ specifying the transform block width, a variable $n\text{TbH}$ specifying the transform block height, a variable refW specifying the reference samples width, a variable refH specifying the reference samples height, the predicted samples $\text{predSamples}[x][y]$, with $x=0 \dots n\text{TbW}-1, y=0 \dots n\text{TbH}-1$, the neighbouring samples $p[x][y]$, with $x=-1, y=-1 \dots \text{refH}-1$ and $x=0 \dots \text{refW}-1, y=-1$.

(164) Outputs of this process are the modified predicted samples $\text{predSamples}[x][y]$ with $x=0 \dots n\text{TbW}-1, y=0 \dots n\text{TbH}-1$.

(165) The variable $n\text{Scale}$ is derived as follows: If predModeIntra is greater than INTRA_ANGULAR50, $n\text{Scale}$ is set equal to $\text{Min}(2, \text{Log } 2(n\text{TbH}) - \text{Floor}(\text{Log } 2(3*\text{invAngle}-2))+8)$, using invAngle as specified in clause 8.4.5.2.12. Otherwise, if predModeIntra is less than INTRA_ANGULAR18, not equal to INTRA_PLANAR and not equal to INTRA_DC, $n\text{Scale}$ is set equal to $\text{Min}(2, \text{Log } 2(n\text{TbW}) - \text{Floor}(\text{Log } 2(3*\text{invAngle}-2))+8)$, using invAngle as specified in clause 8.4.5.2.12. Otherwise, $n\text{Scale}$ is set to $((\text{Log } 2(n\text{TbW}) + \text{Log } 2(n\text{TbH}) - 2)>>2)$.

(166) If the value of $n\text{Scale}$ is less than 0, process 8.4.5.2.14 is terminated, and outputs of this process are set equal to the input predicted samples $\text{predSamples}[x][y]$, with $x=0 \dots n\text{TbW}-1, y=0 \dots n\text{TbH}-1$.

(167) The reference sample arrays $\text{mainRef}[x]$ and $\text{sideRef}[y]$, with $x=0 \dots \text{refW}-1$ and $y=0 \dots \text{refH}-1$ are derived as follows:

$\text{mainRef}[x] = p[x][-1]$

$\text{sideRef}[y] = p[-1][y]$

(168) The variables $\text{refL}[x][y]$, $\text{refT}[x][y]$, $wT[y]$, and $wL[x]$ with $x=0 \dots n\text{TbW}-1, y=0 \dots n\text{TbH}-1$ are derived as follows: If predModeIntra is equal to INTRA_PLANAR or INTRA_DC, the following applies:

$\text{refL}[x][y] = p[-1][y]$

$\text{refT}[x][y] = p[x][-1]$

$wT[y] = 32 >> ((y < 1) >> n\text{Scale})$

$wL[x] = 32 >> ((x < 1) >> n\text{Scale})$ Otherwise, if predModeIntra is equal to INTRA_ANGULAR18 or INTRA_ANGULAR50, the following applies:

$\text{refL}[x][y] = p[-1][y] - p[-1][-1] + \text{predSamples}[x][y]$

$\text{refT}[x][y] = p[x][-1] - p[-1][-1] + \text{predSamples}[x][y]$

$wT[y] = (\text{predModeIntra} == \text{INTRA_ANGULAR18}) ? 32 >> ((y < 1) >> n\text{Scale}) : 0$

$wL[x] = (\text{predModeIntra} == \text{INTRA_ANGULAR50}) ? 32 >> ((x < 1) >> n\text{Scale}) : 0$ Otherwise, if predModeIntra is less than INTRA_ANGULAR18, the following ordered operations apply:

(169) The variables $dX\text{Int}[y]$ and $dX[x][y]$ are derived as follows using invAngle as specified in clause 8.4.5.2.12 depending on intraPredMode :

$dXInt[y] = ((y+1) * invAngle + 256) >> 9$

$dX[x][y] = x + dXInt[y]$

(170) The variables $refL[x][y]$, $refT[x][y]$, $wT[y]$, and $wL[x]$ are derived as follows:

$refL[x][y] = 0$

$refT[x][y] = (y < (3 << nScale)) ? mainRef[dX[x][y]] : 0$

$wT[y] = 32 >> ((y < 1) >> nScale)$

$wL[x] = 0$ Otherwise, if $predModeIntra$ is greater than $INTRA_ANGULAR50$, the following ordered operations apply: The variables $dYInt[x]$ and $dY[x][y]$ are derived as follows using $invAngle$ as specified in clause 8.4.5.2.12 depending on $intraPredMode$:

$dYInt[x] = ((x+1) * invAngle + 256) >> 9$

$dY[x][y] = y + dYInt[x]$ The variables $refL[x][y]$, $refT[x][y]$, $wT[y]$, and $wL[x]$ are derived as follows:

$refL[x][y] = (x < (3 << nScale)) ? sideRef[dY[x][y]] : 0$

$refT[x][y] = 0$

$wT[y] = 0$

$wL[x] = 32 >> ((x < 1) >> nScale)$.

(171) The values of the modified predicted samples $predSamples[x][y]$, with $x=0 \dots nTbW-1$, $y=0 \dots nTbH-1$ are derived as follows:

$predSamples[x][y] = Clip1((refL[x][y] * wL[x] + refT[x][y] * wT[y] + (64 - wL[x] - wT[y]) * predSamples[x][y] + 32) >> 6)$.
Embodiment 2

(172) Specification of $INTRA_ANGULAR2 \dots INTRA_ANGULAR66$ Intra Prediction Modes

(173) Inputs to this process are: the intra prediction mode $predModeIntra$, a variable $nTbW$ specifying the transform block width, a variable $nTbH$ specifying the transform block height, a variable $refW$ specifying the reference samples width, a variable $refH$ specifying the reference samples height, the predicted samples $predSamples[x][y]$, with $x=0 \dots nTbW-1$, $y=0 \dots nTbH-1$, the neighbouring samples $p[x][y]$, with $x=-1$, $y=-1 \dots refH-1$ and $x=0 \dots refW-1$, $y=-1$.

(174) Outputs of this process are the modified predicted samples $predSamples[x][y]$ with $x=0 \dots nTbW-1$, $y=0 \dots nTbH-1$.

(175) The variable $nScale$ is derived as follows: If $predModeIntra$ is equal to $INTRA_PLANAR$, $INTRA_DC$, $INTRA_ANGULAR18$, or $INTRA_ANGULAR50$, $nScale$ is set to $((\log_2(nTbW) + \log_2(nTbH) - 2) >> 2)$. Otherwise, $nScale$ is set equal to $\min(2, \log_2(predModeIntra > INTRA_ANGULAR50 ? nTbH : nTbW) - \text{Floor}(\log_2(3 * invAngle - 2)) + 8)$, using $invAngle$ as specified in clause 8.4.5.2.12. If the value of $nScale$ is less than 0, process 8.4.5.2.14 is terminated, and outputs of this process are set equal to the input predicted samples $predSamples[x][y]$, with $x=0 \dots nTbW-1$, $y=0 \dots nTbH-1$.

(176) The reference sample arrays $mainRef[x]$ and $sideRef[y]$, with $x=0 \dots refW-1$ and $y=0 \dots refH-1$ are derived as follows:

$mainRef[x] = p[x][-1]$

$sideRef[y] = p[-1][y]$

(177) The variables $refL[x][y]$, $refT[x][y]$, $wT[y]$, and $wL[x]$ with $x=0 \dots nTbW-1$, $y=0 \dots nTbH-1$ are derived as follows: If $predModeIntra$ is equal to $INTRA_PLANAR$ or $INTRA_DC$, the following applies:

$refL[x][y] = p[-1][y]$

$refT[x][y] = p[x][-1]$

$wT[y] = 32 >> ((y < 1) >> nScale)$

$wL[x] = 32 >> ((x < 1) >> nScale)$ Otherwise, if $predModeIntra$ is equal to $INTRA_ANGULAR18$ or $INTRA_ANGULAR50$, the following applies:

$refL[x][y] = p[-1][y] - p[-1][-1] + predSamples[x][y]$

$refT[x][y] = p[x][-1] - p[-1][-1] + predSamples[x][y]$

$wT[y] = (predModeIntra == INTRA_ANGULAR18) ? 32 >> ((y < 1) >> nScale) : 0$

$wL[x] = (predModeIntra == INTRA_ANGULAR50) ? 32 >> ((x < 1) >> nScale) : 0$ Otherwise, if $predModeIntra$ is less than $INTRA_ANGULAR18$, the following ordered operations apply: 1. The variables $dXInt[y]$ and $dX[x][y]$ are derived as follows using $invAngle$ as specified in clause 8.4.5.2.12 depending on $intraPredMode$:

$dXInt[y] = ((y+1) * invAngle + 256) >> 9$

$dX[x][y] = x + dXInt[y]$ 2. The variables $refL[x][y]$, $refT[x][y]$, $wT[y]$, and $wL[x]$ are derived as follows:

$refL[x][y] = 0$

$refT[x][y] = (y < (3 << nScale)) ? mainRef[dX[x][y]] : 0$

$wT[y] = 32 >> ((y < 1) >> nScale)$

$wL[x] = 0$ Otherwise, if $predModeIntra$ is greater than $INTRA_ANGULAR50$, the following ordered operations apply: 1. The variables $dYInt[x]$ and $dY[x][y]$ are derived as follows using $invAngle$ as specified in clause 8.4.5.2.12 depending on $intraPredMode$:

$dYInt[x] = ((x+1) * invAngle + 256) >> 9$

$dY[x][y] = y + dYInt[x]$ 2. The variables $refL[x][y]$, $refT[x][y]$, $wT[y]$, and $wL[x]$ are derived as follows:

$refL[x][y] = (x < (3 < nScale)) ? sideRef[dY[x][y]] : 0$

$refT[x][y] = 0$

$wT[y] = 0$

$wL[x] = 32 >> ((x < 1) >> nScale)$.

(178) The values of the modified predicted samples $predSamples[x][y]$, with $x=0 \dots nTbW-1$, $y=0 \dots nTbH-1$ are derived as follows:

$predSamples[x][y] = Clip1((refL[x][y] * wL[x] + refT[x][y] * wT[y] + (64 - wL[x] - wT[y]) * predSamples[x][y] + 32) >> 6)$.

Embodiment 3

(179) Specification of INTRA_ANGULAR2 ... INTRA_ANGULAR66 Intra Prediction Modes

(180) Inputs to this process are: the intra prediction mode $predModeIntra$, a variable $nTbW$ specifying the transform block width, a variable $nTbH$ specifying the transform block height, a variable $refW$ specifying the reference samples width, a variable $refH$ specifying the reference samples height, the predicted samples $predSamples[x][y]$, with $x=0 \dots nTbW-1$, $y=0 \dots nTbH-1$, the neighbouring samples $p[x][y]$, with $x=-1$, $y=-1 \dots refH-1$ and $x=0 \dots refW-1$, $y=-1$.

(181) Outputs of this process are the modified predicted samples $predSamples[x][y]$ with $x=0 \dots nTbW-1$, $y=0 \dots nTbH-1$.

(182) The variable $nScale$ is derived as follows: If $predModeIntra$ is equal to INTRA_PLANAR, INTRA_DC, INTRA_ANGULAR18, or INTRA_ANGULAR50, $nScale$ is set to $((\log_2(nTbW) + \log_2(nTbH) - 2) >> 2)$.

Otherwise, $nScale$ is set equal to $\min(2, \log_2(nTbS) - \text{Floor}(\log_2(3 * \text{invAngle} - 2)) + 8)$, using $nTbS$ equal to $predModeIntra > INTRA_ANGULAR50 ? nTbH : nTbW$ and $invAngle$ as specified in clause 8.4.5.2.12. If the value of $nScale$ is less than 0, process 8.4.5.2.14 is terminated, and outputs of this process are set equal to the input predicted samples $predSamples[x][y]$, with $x=0 \dots nTbW-1$, $y=0 \dots nTbH-1$.

(183) The reference sample arrays $mainRef[x]$ and $sideRef[y]$, with $x=0 \dots refW-1$ and $y=0 \dots refH-1$ are derived as follows:

$mainRef[x] = p[x][-1]$

$sideRef[y] = p[-1][y]$

(184) The variables $refL[x][y]$, $refT[x][y]$, $wT[y]$, and $wL[x]$ with $x=0 \dots nTbW-1$, $y=0 \dots nTbH-1$ are derived as follows: If $predModeIntra$ is equal to INTRA_PLANAR or INTRA_DC, the following applies:

$refL[x][y] = p[-1][y]$

$refT[x][y] = p[x][-1]$

$wT[y] = 32 >> ((y < 1) >> nScale)$

$wL[x] = 32 >> ((x < 1) >> nScale)$ Otherwise, if $predModeIntra$ is equal to INTRA_ANGULAR18 or INTRA_ANGULAR50, the following applies:

$refL[x][y] = p[-1][y] - p[-1][-1] + predSamples[x][y]$

$refT[x][y] = p[x][-1] - p[-1][-1] + predSamples[x][y]$

$wT[y] = (predModeIntra == INTRA_ANGULAR18) ? 32 >> ((y < 1) >> nScale) : 0$

$wL[x] = (predModeIntra == INTRA_ANGULAR50) ? 32 >> ((x < 1) >> nScale) : 0$ Otherwise, if $predModeIntra$ is less than INTRA_ANGULAR18, the following ordered operations apply: 1. The variables $dXInt[y]$ and $dX[x][y]$ are derived as follows using $invAngle$ as specified in clause 8.4.5.2.12 depending on $intraPredMode$:

$dXInt[y] = ((y+1) * invAngle + 256) >> 9$

$dX[x][y] = x + dXInt[y]$ 2. The variables $refL[x][y]$, $refT[x][y]$, $wT[y]$, and $wL[x]$ are derived as follows:

$refL[x][y] = 0$

$refT[x][y] = (y < (3 < nScale)) ? mainRef[dX[x][y]] : 0$

$wT[y] = 32 >> ((y < 1) >> nScale)$

$wL[x] = 0$ Otherwise, if $predModeIntra$ is greater than INTRA_ANGULAR50, the following ordered operations apply: 1. The variables $dYInt[x]$ and $dY[x][y]$ are derived as follows using $invAngle$ as specified in clause 8.4.5.2.12 depending on $intraPredMode$:

$dYInt[x] = ((x+1) * invAngle + 256) >> 9$

$dY[x][y] = y + dYInt[x]$ 2. The variables $refL[x][y]$, $refT[x][y]$, $wT[y]$, and $wL[x]$ are derived as follows:

$refL[x][y] = (x < (3 < nScale)) ? sideRef[dY[x][y]] : 0$

$refT[x][y] = 0$

$wT[y] = 0$

$wL[x] = 32 >> ((x < 1) >> nScale)$.

(185) The values of the modified predicted samples $predSamples[x][y]$, with $x=0 \dots nTbW-1$, $y=0 \dots nTbH-1$ are derived as follows:

$predSamples[x][y] = Clip1((refL[x][y] * wL[x] + refT[x][y] * wT[y] + (64 - wL[x] - wT[y]) * predSamples[x][y] + 32) >> 6)$.

(186) Other embodiments are a harmonization of PDPC with ISP (intra subpartition coding mode also known as intra prediction with subpartitions). In clause 8.4.5.2.5 “General intra sample prediction” of the current VVC specification draft (document JVET-P2001-vE: B. Bross, J. Chen, S. Liu, Y-K. Wang, “Versatile Video Coding (Draft 7),” output document JVET-P2001 of the 16th JVET meeting, Geneva, Switzerland), the variables refW and refH are defined as follows:

(187) General Intra Sample Prediction

(188) Inputs to this process are: a sample location (xTbCmp, yTbCmp) specifying the top-left sample of the current transform block relative to the top-left sample of the current picture, a variable predModeIntra specifying the intra prediction mode, a variable nTbW specifying the transform block width, a variable nTbH specifying the transform block height, a variable nCbW specifying the coding block width, a variable nCbH specifying the coding block height, a variable cIdx specifying the colour component of the current block.

Outputs of this process are the predicted samples predSamples[x][y], with $x=0 \dots nTbW-1$, $y=0 \dots nTbH-1$.

The variables refW and refH are derived as follows: If IntraSubPartitionsSplitType is equal to ISP_NO_SPLIT or cIdx is not equal to 0, the following applies:

$refW=nTbW*2$

$refH=nTbH*2$ Otherwise (IntraSubPartitionsSplitType is not equal to ISP_NO_SPLIT and cIdx is equal to 0), the following applies:

$refW=nCbW+nTbW$.

$refH=nCbH+nTbH$.

(189) Hence, the length of top and left reference sample sides is defined differently when ISP is enabled (IntraSubPartitionsSplitType is not equal to ISP_NO_SPLIT and cIdx is equal to 0) or when ISP is disabled (if IntraSubPartitionsSplitType is equal to ISP_NO_SPLIT or cIdx is not equal to 0). It results in extended number of available reference samples that can be used for performing PDPC for some oblique directional intra prediction modes.

(190) FIG. 7 and FIG. 8 illustrate two examples. Coding blocks **701** and **801** are split into 2 or 4 subpartitions also referred to as subblocks (exemplified as **702** and **802** in FIG. 7 and FIG. 8, respectively). Top row of reference samples is denoted as **711** and **811** in FIG. 7 and FIG. 8, respectively. Left column of reference samples is denoted as **712** and **812** in FIG. 7 and FIG. 8, respectively. Top-left reference sample is denoted as **713** and **813** in FIG. 7 and FIG. 8, respectively. When IntraSubPartitionsSplitType is not equal to ISP_NO_SPLIT and cIdx is equal to 0, either horizontal (ISP_HOR_SPLIT) or vertical (ISP_VER_SPLIT) splits are applied to a coding block. If vertical split (ISP_VER_SPLIT) is selected, nCbW is greater than nTbW as shown in FIG. 7. If horizontal split (ISP_HOR_SPLIT) is selected, nCbH is greater than nTbH as shown in FIG. 8.

(191) The following methods and embodiments implemented by an encoding device or a decoding device are provided. The encoding device may be video encoder **20** of FIG. 1A, 1B, or encoder **20** of FIG. 2. The decoding device may be video decoder **30** of FIG. 1A, 1B, or decoder **30** of FIG. 3. In accordance with the solution it is provided a method for intra predicting process of a video (or picture, frame) block (a block may be a current coding block or a subpartition of the current coding block) according to an embodiment **900** of the present application as it is illustrated in FIG. 9A. The method can be part of a method of encoding a video sequence or decoding an encoded video sequence.

(192) As shown in FIG. 9A, the device obtains a predicted sample value for a sample of the current coding block in operation **901**. In an example, the predicted sample value is obtained from one or more reference sample values, by using an intra prediction mode which is selected from one of a DC intra-prediction mode, a planar intra prediction mode, and an angular intra-prediction mode.

(193) In operation **902**, the device obtains a scaling factor value according to an intra prediction mode for the current coding block, and also according to at least one of: a height of the current coding block, or a width of the current coding block, or a size of a subpartition of the current coding block. The below embodiments provide detailed information on how to obtain the scaling factor.

(194) In operation **903**, the device determines a first weight value based on the scaling factor value. In operation **904**, the device determines a second weight value based on the scaling factor value. In operation **905**, the method includes calculating an additional value as a weighted sum of a top reference sample value and a left reference sample value, by weighting the top reference sample value with the first weight value and the left reference sample value with the second weight value.

(195) In operation **906**, the method further includes obtaining a modified predicted sample value according to the additional value and the predicted sample value.

(196) In some embodiments, the predicted sample value is processed by using a sample weighting factor to obtain a weighted predicted value, the modified predicted sample value is obtained according to the additional value and the weighted predicted sample value.

(197) The method may further includes: normalizing the modified predicted sample value, by an arithmetic right

shift of an integer representation of the modified predicted sample value, resulting in a normalized modified predicted sample value.

(198) In accordance with the solution it is provided another method for intra predicting process of a video (or picture, frame) block (a block may be a current coding block or a subpartition of the current coding block) according to an embodiment **910** of the present application as it is illustrated in FIG. **9B**. The method can be part of a method of encoding a video sequence or decoding an encoded video sequence.

(199) As shown in FIG. **9B**, the device obtains a predicted sample value for a sample of the current coding block in operation **911**. In an example, the predicted sample value is obtained from one or more reference sample values, by using an intra prediction mode which is selected from one of a DC intra-prediction mode, a planar intra prediction mode, and an angular intra-prediction mode.

(200) In operation **912**, the device obtains a scaling factor (i.e., scale (nScale) parameter) value according to an intra prediction mode for the coding block, and also according to at least one of: a size of a subpartition, or a variable refH indicating the height of the reference samples, or a variable refW indicating the width of the reference samples. The below embodiments provide detailed information on how to obtain the scaling factor.

(201) In operation **913**, the method includes calculating an additional value according to the obtained scale parameter. In operation **914**, the method further includes obtaining a modified predicted sample value according to the additional value and the predicted sample value.

(202) In some embodiments, the predicted sample value is processed by using a sample weighting factor to obtain a weighted predicted value, the modified predicted sample value is obtained according to the additional value and the weighted predicted sample value.

(203) The method may further includes: normalizing the modified predicted sample value, by an arithmetic right shift of an integer representation of the modified predicted sample value, resulting in a normalized modified predicted sample value.

(204) To enable PDPC for the extended subset of oblique directional modes, the formulas used to derive values of the variable nScale should be modified in Section 8.4.5.2.14 “Position-dependent intra prediction sample filtering process” as follows: If predModeIntra is greater than INTRA_ANGULAR50, nScale is set equal to $\text{Min}(2, \text{Log } 2(\text{refH}-\text{nTbH})-\text{Floor}(\text{Log } 2(3*\text{invAngle}-2))+8)$, using invAngle as specified in clause 8.4.5.2.12. Otherwise, if predModeIntra is less than INTRA_ANGULAR18, not equal to INTRA_PLANAR and not equal to INTRA_DC, nScale is set equal to $\text{Min}(2, \text{Log } 2(\text{refW}-\text{nTbW})-\text{Floor}(\text{Log } 2(3*\text{invAngle}-2))+8)$, using invAngle as specified in clause 8.4.5.2.12.

(205) Thus, in the above formulas to compute the variable nScale for oblique angular modes, the coding block height nCbH and the coding block width nCbW are used instead of the transform block height nTbH and the transform block width nTbW, respectively. In the formulas above, the coding block height nCbH is calculated as (refH-nTbH) and the coding block width nCbW as (refW-nTbW). Below, relevant embodiments are shown.

Embodiment 4

(206) Specification of INTRA_ANGULAR2 . . . INTRA_ANGULAR66 Intra Prediction Modes

(207) Inputs to this process are: the intra prediction mode predModeIntra, a variable nTbW specifying the transform block width, a variable nTbH specifying the transform block height, a variable refW specifying the reference samples width, a variable refH specifying the reference samples height, the predicted samples predSamples[x][y], with $x=0 \dots \text{nTbW}-1$, $y=0 \dots \text{nTbH}-1$, the neighbouring samples p[x][y], with $x=-1$, $y=-1 \dots \text{refH}-1$ and $x=0 \dots \text{refW}-1$, $y=-1$.

(208) Outputs of this process are the modified predicted samples predSamples[x][y] with $x=0 \dots \text{nTbW}-1$, $y=0 \dots \text{nTbH}-1$.

(209) The variable nScale is derived as follows: If predModeIntra is greater than INTRA_ANGULAR50, nScale is set equal to $\text{Min}(2, \text{Log } 2(\text{refH}-\text{nTbH})-\text{Floor}(\text{Log } 2(3*\text{invAngle}-2))+8)$, using invAngle as specified in clause 8.4.5.2.12. Otherwise, if predModeIntra is less than INTRA_ANGULAR18, not equal to INTRA_PLANAR and not equal to INTRA_DC, nScale is set equal to $\text{Min}(2, \text{Log } 2(\text{refW}-\text{nTbW})-\text{Floor}(\text{Log } 2(3*\text{invAngle}-2))+8)$, using invAngle as specified in clause 8.4.5.2.12. Otherwise, nScale is set to $((\text{Log } 2(\text{nTbW})+\text{Log } 2(\text{nTbH})-2)>>2)$.

(210) The reference sample arrays mainRef[x] and sideRef[y], with $x=0 \dots \text{refW}-1$ and $y=0 \dots \text{refH}-1$ are derived as follows:

$\text{mainRef}[x]=p[x][-1]$ $\text{sideRef}[y]=p[-1][y]$ The variables refL[x][y], refT[x][y], wT[y], and wL[x] with $x=0 \dots \text{nTbW}-1$, $y=0 \dots \text{nTbH}-1$ are derived as follows: If predModeIntra is equal to INTRA_PLANAR or INTRA_DC, the following applies:

$\text{refL}[x][y]=p[-1][y]$
 $\text{refT}[x][y]=p[x][-1]$

$wT[y]=32>>((y<<1)>>n\text{Scale})$
 $wL[x]=32>>((x<<1)>>n\text{Scale})$

Otherwise, if predModeIntra is equal to INTRA_ANGULAR18 or

INTRA_ANGULAR50, the following applies:

$refL[x][y] = p[-1][y] - p[-1][-1] + predSamples[x][y]$

$refT[x][y] = p[x][-1] - p[-1][-1] + predSamples[x][y]$

$wT[y] = (predModeIntra == INTRA_ANGULAR18) ? 32 >> ((y < 1) >> nScale) : 0$

$wL[x] = (predModeIntra == INTRA_ANGULAR50) ? 32 >> ((x < 1) >> nScale) : 0$ Otherwise, if $predModeIntra$ is less than $INTRA_ANGULAR18$ and $nScale$ is equal to or greater than 0, the following ordered operations apply: 1. The variables $dXInt[y]$ and $dX[x][y]$ are derived as follows using $invAngle$ as specified in clause 8.4.5.2.12 depending on $intraPredMode$:

$dXInt[y] = ((y + 1) * invAngle + 256) >> 9$

$dX[x][y] = x + dXInt[y]$ 2. The variables $refL[x][y]$, $refT[x][y]$, $wT[y]$, and $wL[x]$ are derived as follows:

$refL[x][y] = 0$

$refT[x][y] = (y < (3 < nScale)) ? mainRef[dX[x][y]] : 0$

$wT[y] = 32 >> ((y < 1) >> nScale)$

$wL[x] = 0$ Otherwise, if $predModeIntra$ is greater than $INTRA_ANGULAR50$ and $nScale$ is equal to or greater than 0, the following ordered operations apply: 1. The variables $dYInt[x]$ and $dY[x][y]$ are derived as follows using $invAngle$ as specified in clause 8.4.5.2.12 depending on $intraPredMode$:

$dYInt[x] = ((x + 1) * invAngle + 256) >> 9$

$dY[x][y] = y + dYInt[x]$ 2. The variables $refL[x][y]$, $refT[x][y]$, $wT[y]$, and $wL[x]$ are derived as follows:

$refL[x][y] = (x < (3 < nScale)) ? sideRef[dY[x][y]] : 0$

$refT[x][y] = 0$

$wT[y] = 0$

$wL[x] = 32 >> ((x < 1) >> nScale)$ Otherwise, $refL[x][y]$, $refT[x][y]$, $wT[y]$, and $wL[x]$ are all set equal to 0.

(211) The values of the modified predicted samples $predSamples[x][y]$, with $x = 0 \dots nTbW - 1$, $y = 0 \dots nTbH - 1$ are derived as follows:

$predSamples[x][y] = Clip1((refL[x][y] * wL[x] + refT[x][y] * wT[y] + (64 - wL[x] - wT[y]) * predSamples[x][y] + 32) >> 6)$.

Embodiment 5 (On Top of Embodiment 1)

(212) Specification of $INTRA_ANGULAR2 \dots INTRA_ANGULAR66$ Intra Prediction Modes

(213) Inputs to this process are: the intra prediction mode $predModeIntra$, a variable $nTbW$ specifying the transform block width, a variable $nTbH$ specifying the transform block height, a variable $refW$ specifying the reference samples width, a variable $refH$ specifying the reference samples height, the predicted samples $predSamples[x][y]$, with $x = 0 \dots nTbW - 1$, $y = 0 \dots nTbH - 1$, the neighbouring samples $p[x][y]$, with $x = -1$, $y = -1 \dots refH - 1$ and $x = 0 \dots refW - 1$, $y = -1$.

(214) Outputs of this process are the modified predicted samples $predSamples[x][y]$ with $x = 0 \dots nTbW - 1$, $y = 0 \dots nTbH - 1$.

(215) The variable $nScale$ is derived as follows: If $predModeIntra$ is greater than $INTRA_ANGULAR50$, $nScale$ is set equal to $Min(2, Log\ 2(refH - nTbH) - Floor(Log\ 2(3 * invAngle - 2)) + 8)$, using $invAngle$ as specified in clause 8.4.5.2.12. Otherwise, if $predModeIntra$ is less than $INTRA_ANGULAR18$, not equal to $INTRA_PLANAR$ and not equal to $INTRA_DC$, $nScale$ is set equal to $Min(2, Log\ 2(refW - nTbW) - Floor(Log\ 2(3 * invAngle - 2)) + 8)$, using $invAngle$ as specified in clause 8.4.5.2.12. Otherwise, $nScale$ is set to $((Log\ 2(nTbW) + Log\ 2(nTbH) - 2) >> 2)$.

(216) If the value of $nScale$ is less than 0, process 8.4.5.2.14 is terminated, and outputs of this process are set equal to the input predicted samples $predSamples[x][y]$, with $x = 0 \dots nTbW - 1$, $y = 0 \dots nTbH - 1$.

(217) The reference sample arrays $mainRef[x]$ and $sideRef[y]$, with $x = 0 \dots refW - 1$ and $y = 0 \dots refH - 1$ are derived as follows:

$mainRef[x] = p[x][-1]$

$sideRef[y] = p[-1][y]$

(218) The variables $refL[x][y]$, $refT[x][y]$, $wT[y]$, and $wL[x]$ with $x = 0 \dots nTbW - 1$, $y = 0 \dots nTbH - 1$ are derived as follows: If $predModeIntra$ is equal to $INTRA_PLANAR$ or $INTRA_DC$, the following applies:

$refL[x][y] = p[-1][y]$

$refT[x][y] = p[x][-1]$

$wT[y] = 32 >> ((y < 1) >> nScale)$

$wL[x] = 32 >> ((x < 1) >> nScale)$ Otherwise, if $predModeIntra$ is equal to $INTRA_ANGULAR18$ or $INTRA_ANGULAR50$, the following applies:

$refL[x][y] = p[-1][y] - p[-1][-1] + predSamples[x][y]$

$refT[x][y] = p[x][-1] - p[-1][-1] + predSamples[x][y]$

$wT[y] = (predModeIntra == INTRA_ANGULAR18) ? 32 >> ((y < 1) >> nScale) : 0$

$wL[x] = (predModeIntra == INTRA_ANGULAR50) ? 32 >> ((x < 1) >> nScale) : 0$ Otherwise, if $predModeIntra$ is less than $INTRA_ANGULAR18$, the following ordered operations apply: 1. The variables $dXInt[y]$ and $dX[x][y]$ are

derived as follows using invAngle as specified in clause 8.4.5.2.12 depending on intraPredMode:

$dXInt[y] = ((y+1) * invAngle + 256) >> 9$

$dX[x][y] = x + dXInt[y]$ 2. The variables $refL[x][y]$, $refT[x][y]$, $wT[y]$, and $wL[x]$ are derived as follows:

$refL[x][y] = 0$

$refT[x][y] = (y < (3 << nScale)) ? mainRef[dX[x][y]] : 0$

$wT[y] = 32 >> ((y < 1) >> nScale)$

$wL[x] = 0$ Otherwise, if $predModeIntra$ is greater than $INTRA_ANGULAR50$, the following ordered operations apply: 1. The variables $dYInt[x]$ and $dY[x][y]$ are derived as follows using $invAngle$ as specified in clause 8.4.5.2.12 depending on $intraPredMode$:

$dYInt[x] = ((x+1) * invAngle + 256) >> 9$

$dY[x][y] = y + dYInt[x]$ 2. The variables $refL[x][y]$, $refT[x][y]$, $wT[y]$, and $wL[x]$ are derived as follows:

$refL[x][y] = (x < (3 << nScale)) ? sideRef[dY[x][y]] : 0$

$refT[x][y] = 0$

$wT[y] = 0$

$wL[x] = 32 >> ((x < 1) >> nScale)$.

(219) The values of the modified predicted samples $predSamples[x][y]$, with $x=0 \dots nTbW-1$, $y=0 \dots nTbH-1$ are derived as follows:

$predSamples[x][y] = Clip1((refL[x][y] * wL[x] + refT[x][y] * wT[y] + (64 - wL[x] - wT[y]) * predSamples[x][y] + 32) >> 6)$.

Embodiment 6 (On Top of Embodiment 2)

(220) Specification of $INTRA_ANGULAR2 \dots INTRA_ANGULAR66$ Intra Prediction Modes

(221) Inputs to this process are: the intra prediction mode $predModeIntra$, a variable $nTbW$ specifying the transform block width, a variable $nTbH$ specifying the transform block height, a variable $refW$ specifying the reference samples width, a variable $refH$ specifying the reference samples height, the predicted samples $predSamples[x][y]$, with $x=0 \dots nTbW-1$, $y=0 \dots nTbH-1$, the neighbouring samples $p[x][y]$, with $x=-1$, $y=-1 \dots refH-1$ and $x=0 \dots refW-1$, $y=-1$.

(222) Outputs of this process are the modified predicted samples $predSamples[x][y]$ with $x=0 \dots nTbW-1$, $y=0 \dots nTbH-1$.

(223) The variable $nScale$ is derived as follows: If $predModeIntra$ is equal to $INTRA_PLANAR$, $INTRA_DC$, $INTRA_ANGULAR18$, or $INTRA_ANGULAR50$, $nScale$ is set to $((\log_2(nTbW) + \log_2(nTbH) - 2) >> 2)$. Otherwise, $nScale$ is set equal to $\min(2, \log_2(predModeIntra > INTRA_ANGULAR50 ? refH - nTbH : refW - nTbW) \text{ Floor}(\log_2(3 * invAngle - 2)) + 8)$, using $invAngle$ as specified in clause 8.4.5.2.12. If the value of $nScale$ is less than 0, process 8.4.5.2.14 is terminated and outputs of this process are set equal to the input predicted samples $predSamples[x][y]$, with $x=0 \dots nTbW-1$, $y=0 \dots nTbH-1$.

(224) The reference sample arrays $mainRef[x]$ and $sideRef[y]$, with $x=0 \dots refW-1$ and $y=0 \dots refH-1$ are derived as follows:

$mainRef[x] = p[x][-1]$

$sideRef[y] = p[-1][y]$

(225) The variables $refL[x][y]$, $refT[x][y]$, $wT[y]$, and $wL[x]$ with $x=0 \dots nTbW-1$, $y=0 \dots nTbH-1$ are derived as follows: If $predModeIntra$ is equal to $INTRA_PLANAR$ or $INTRA_DC$, the following applies:

$refL[x][y] = p[-1][y]$

$refT[x][y] = p[x][-1]$

$wT[y] = 32 >> ((y < 1) >> nScale)$

$wL[x] = 32 >> ((x < 1) >> nScale)$ Otherwise, if $predModeIntra$ is equal to $INTRA_ANGULAR18$ or $INTRA_ANGULAR50$, the following applies:

$refL[x][y] = p[-1][y] - p[-1][-1] + predSamples[x][y]$

$refT[x][y] = p[x][-1] - p[-1][-1] + predSamples[x][y]$

$wT[y] = (predModeIntra == INTRA_ANGULAR18) ? 32 >> ((y < 1) >> nScale) : 0$.

$wL[x] = (predModeIntra == INTRA_ANGULAR50) ? 32 >> ((x < 1) >> nScale) : 0$ Otherwise, if $predModeIntra$ is less than $INTRA_ANGULAR18$, the following ordered operations apply: 1. The variables $dXInt[y]$ and $dX[x][y]$ are derived as follows using $invAngle$ as specified in clause 8.4.5.2.12 depending on $intraPredMode$:

$dXInt[y] = ((y+1) * invAngle + 256) >> 9$

$dX[x][y] = x + dXInt[y]$ 2. The variables $refL[x][y]$, $refT[x][y]$, $wT[y]$, and $wL[x]$ are derived as follows:

$refL[x][y] = 0$

$refT[x][y] = (y < (3 << nScale)) ? mainRef[dX[x][y]] : 0$

$wT[y] = 32 >> ((y < 1) >> nScale)$

$wL[x] = 0$ Otherwise, if $predModeIntra$ is greater than $INTRA_ANGULAR50$, the following ordered operations apply: 1. The variables $dYInt[x]$ and $dY[x][y]$ are derived as follows using $invAngle$ as specified in clause 8.4.5.2.12 depending on $intraPredMode$:

$dYInt[x] = ((x+1) * invAngle + 256) >> 9$

$dY[x][y] = y + dYInt[x]$ 2. The variables $refL[x][y]$, $refT[x][y]$, $wT[y]$, and $wL[x]$ are derived as follows:

$refL[x][y] = (x < (3 < nScale)) ? sideRef[dY[x][y]] : 0$

$refT[x][y] = 0$

$wT[y] = 0$

$wL[x] = 32 >> ((x < 1) >> nScale)$.

(226) The values of the modified predicted samples $predSamples[x][y]$, with $x=0 \dots nTbW-1$, $y=0 \dots nTbH-1$ are derived as follows:

$predSamples[x][y] = Clip1((refL[x][y] * wL[x] + refT[x][y] * wT[y] + (64 - wL[x] - wT[y]) * predSamples[x][y] + 32) >> 6)$.

Embodiment 7 (On Top of Embodiment 3)

(227) Specification of INTRA_ANGULAR2 ... INTRA_ANGULAR66 Intra Prediction Modes

(228) Inputs to this process are: the intra prediction mode $predModeIntra$, a variable $nTbW$ specifying the transform block width, a variable $nTbH$ specifying the transform block height, a variable $refW$ specifying the reference samples width, a variable $refH$ specifying the reference samples height, the predicted samples $predSamples[x][y]$, with $x=0 \dots nTbW-1$, $y=0 \dots nTbH-1$, the neighbouring samples $p[x][y]$, with $x=-1$, $y=-1 \dots refH-1$ and $x=0 \dots refW-1$, $y=-1$.

(229) Outputs of this process are the modified predicted samples $predSamples[x][y]$ with $x=0 \dots nTbW-1$, $y=0 \dots nTbH-1$.

(230) The variable $nScale$ is derived as follows: If $predModeIntra$ is equal to INTRA_PLANAR, INTRA_DC, INTRA_ANGULAR18, or INTRA_ANGULAR50, $nScale$ is set to $((\log_2(nTbW) + \log_2(nTbH) - 2) >> 2)$.

Otherwise, $nScale$ is set equal to $\min(2, \log_2(nCbS) - \text{Floor}(\log_2(3 * \text{invAngle} - 2)) + 8)$, using $nCbS$ equal to $predModeIntra > INTRA_ANGULAR50 ? refH - nTbH : refW - nTbW$ and $invAngle$ as specified in clause 8.4.5.2.12. If the value of $nScale$ is less than 0, process 8.4.5.2.14 is terminated, and outputs of this process are set equal to the input predicted samples $predSamples[x][y]$, with $x=0 \dots nTbW-1$, $y=0 \dots nTbH-1$.

(231) The reference sample arrays $mainRef[x]$ and $sideRef[y]$, with $x=0 \dots refW-1$ and $y=0 \dots refH-1$ are derived as follows:

$mainRef[x] = p[x][-1]$

$sideRef[y] = p[-1][y]$

(232) The variables $refL[x][y]$, $refT[x][y]$, $wT[y]$, and $wL[x]$ with $x=0 \dots nTbW-1$, $y=0 \dots nTbH-1$ are derived as follows: If $predModeIntra$ is equal to INTRA_PLANAR or INTRA_DC, the following applies:

$refL[x][y] = p[-1][y]$

$refT[x][y] = p[x][-1]$

$wT[y] = 32 >> ((y < 1) >> nScale)$

$wL[x] = 32 >> ((x < 1) >> nScale)$ Otherwise, if $predModeIntra$ is equal to INTRA_ANGULAR18 or INTRA_ANGULAR50, the following applies:

$refL[x][y] = p[-1][y] - p[-1][-1] + predSamples[x][y]$

$refT[x][y] = p[x][-1] - p[-1][-1] + predSamples[x][y]$

$wT[y] = (predModeIntra == INTRA_ANGULAR18) ? 32 >> ((y < 1) >> nScale) : 0$

$wL[x] = (predModeIntra == INTRA_ANGULAR50) ? 32 >> ((x < 1) >> nScale) : 0$ Otherwise, if $predModeIntra$ is less than INTRA_ANGULAR18, the following ordered operations apply: 1. The variables $dXInt[y]$ and $dX[x][y]$ are derived as follows using $invAngle$ as specified in clause 8.4.5.2.12 depending on $intraPredMode$:

$dXInt[y] = ((y+1) * invAngle + 256) >> 9$

$dX[x][y] = x + dXInt[y]$ 2. The variables $refL[x][y]$, $refT[x][y]$, $wT[y]$, and $wL[x]$ are derived as follows:

$refL[x][y] = 0$

$refT[x][y] = (y < (3 < nScale)) ? mainRef[dX[x][y]] : 0$

$wT[y] = 32 >> ((y < 1) >> nScale)$

$wL[x] = 0$ Otherwise, if $predModeIntra$ is greater than INTRA_ANGULAR50, the following ordered operations apply: 1. The variables $dYInt[x]$ and $dY[x][y]$ are derived as follows using $invAngle$ as specified in clause 8.4.5.2.12 depending on $intraPredMode$:

$dYInt[x] = ((x+1) * invAngle + 256) >> 9$

$dY[x][y] = y + dYInt[x]$ 2. The variables $refL[x][y]$, $refT[x][y]$, $wT[y]$, and $wL[x]$ are derived as follows:

$refL[x][y] = (x < (3 < nScale)) ? sideRef[dY[x][y]] : 0$

$refT[x][y] = 0$

$wT[y] = 0$

$wL[x] = 32 >> ((x < 1) >> nScale)$.

(233) The values of the modified predicted samples $predSamples[x][y]$, with $x=0 \dots nTbW-1$, $y=0 \dots nTbH-1$ are derived as follows:

$predSamples[x][y] = Clip1((refL[x][y] * wL[x] + refT[x][y] * wT[y] + (64 - wL[x] - wT[y]) * predSamples[x][y] + 32) >> 6)$.

(234) Based on the disclosure provided above, the PDPC scaling parameter (“nScale”) is determined by two values. One of these values is derived from the block size and the other one is derived from the value of the inverse intra prediction angle, wherein this angle is determined by intra prediction mode and block aspect ratio. (235) Embodiments of this application are to calculate the value of the scaling parameter with respect to the intra subpartition mode.

(236) FIG. 10 is a block diagram showing an embodiment for deriving the nScale parameter.

(237) The operations of an embodiment are as follows:

(238) In operation **1001**, a size of side reference (refSide) is determined based on the intra prediction mode. Selection of the side of the block is done on the basis of whether the intra prediction mode is lower than a predetermined value. Particularly, this predetermined value could be equal to 34: when an intra prediction mode is lower than 34, top side is used as a side reference; otherwise, left side is used as side reference.

(239) The first value (based on the size of the block, also called as size-dependent value) is calculated (i.e., determined) depending on the intra subpartition mode. The first value (“V1”) could be derived as follows (see FIG. 10): when a coding block (Cb) comprises a single transform block (Tb) having the same size with the coding block, the first value (“V1”) is determined based on the reference side of the transform block (refSide=Log 2(nTbS)); otherwise, when a coding block (Cb) comprises several transform blocks (Tb), the first value (“V1”) is determined based on the reference side of the coding block (refSide=Log 2(nCbS)). Decision of whether a coding block (Cb) comprises a single transform block is verified using “Intra subpartition mode” variable, that is coded in the bitstream (e.g. by the means of intra_subpartitions_mode_flag and intra_subpartitions_split_flag syntax elements).

(240) In operation **1002**, the second value (based on the intra mode angle of the block, also called as angle-dependent value) is derived as follows:

$V2 = 8 - \text{Floor}(\text{Log } 2(3 * \text{invAngle} - 2))$.

(241) In operation **1003**, the nScale parameter is calculated based on the first value and the second value.

(242) In an embodiment, as shown in operation **1004**, in this embodiment the final value of nScale is further clipped.

Embodiment 8

(243) In this embodiment, the final value of nScale is defined as follows:

$nScale = \min(2, V1 + V2)$

(244) In the VVC specification, this embodiment corresponds to the following excerpt:

(245) The variable nScale is derived as follows:

(246) If predModeIntra is greater than INTRA_ANGULAR50, nScale is set equal to $\text{Min}(2, \text{Log } 2(\text{refH} - \text{nTbH}) - \text{Floor}(\text{Log } 2(3 * \text{invAngle} - 2)) + 8)$, using invAngle as specified in clause 8.4.5.2.12. Otherwise, if predModeIntra is less than INTRA_ANGULAR18, not equal to INTRA_PLANAR and not equal to INTRA_DC, nScale is set equal to $\text{Min}(2, \text{Log } 2(\text{refW} - \text{nTbW}) - \text{Floor}(\text{Log } 2(3 * \text{invAngle} - 2)) + 8)$, using invAngle as specified in clause 8.4.5.2.12. Otherwise, nScale is set to $((\text{Log } 2(\text{nTbW}) + \text{Log } 2(\text{nTbH}) - 2) >> 2)$.

(247) Alternative excerpt of the specification (on the top of Embodiment 3) is as follows: The variable nScale is derived as follows: If predModeIntra is equal to INTRA_PLANAR, INTRA_DC, INTRA_ANGULAR18, or INTRA_ANGULAR50, nScale is set to $((\text{Log } 2(\text{nTbW}) + \text{Log } 2(\text{nTbH}) - 2) >> 2)$. Otherwise, nScale is set equal to $\text{Min}(2, \text{Log } 2(\text{nTbS}) - \text{Floor}(\text{Log } 2(3 * \text{invAngle} - 2)) + 8)$, using nTbS equal to $\text{predModeIntra} > \text{INTRA_ANGULAR50} ? \text{refH} - \text{nTbH} : \text{refW} - \text{nTbW}$ and invAngle as specified in clause 8.4.5.2.12. If the value of nScale is less than 0, process 8.4.5.2.14 is terminated, and outputs of this process are set equal to the input predicted samples predSamples[x][y], with $x = 0 \dots \text{nTbW} - 1$, $y = 0 \dots \text{nTbH} - 1$.

Embodiment 9 (On Top of Embodiment 1)

(248) In this embodiment the final value of nScale is further clipped depending on whether intra subpartitioning is used.

(249) In particular, when a block is a sub partition of a larger coding block, the following initial value of nScale is defined as:

$nScale = \min(2, \text{Log } 2(\text{nTbS}) + V2)$.

(250) The final value of nScale is calculated as:

$nScale = nScale < 0 ? \min(0, V1 + V2) : \min(2, V1 + V2)$.

(251) FIG. 11 shows a flowchart for this embodiment. In this figure it is shown, that ISP flag is used to perform clipping of the obtained nScale parameter. This additional dependency of the clipping operation on ISP (as compared to the flowchart shown in FIG. 10) is represented by condition “nScale<0” given above. The other operations **1101-1103** are similar as operations **1001-1003** described in FIG. 10.

(252) In the VVC specification, this embodiment corresponds to the following excerpt:

(253) The variable nScale is derived as follows:

(254) If predModeIntra is greater than INTRA_ANGULAR50, nScale is set equal to $\text{Min}(2, \text{Log } 2(\text{nTbH})$

$-\text{Floor}(\text{Log } 2(3 * \text{invAngle} - 2)) + 8$), using invAngle as specified in clause 8.4.5.2.12. When $\text{refH}! = 2 * \text{nTbH}$, nScale is updated as follows:

$\text{nScaleC} = \text{Log } 2(\text{refH} - \text{nTbH}) - \text{Floor}(\text{Log } 2(3 * \text{invAngle} - 2)) + 8$

$\text{nScale} = \text{nScale} < 0 ? \min(0, \text{nScaleCb}) : \min(2, \text{nScaleCb})$ Otherwise, if predModeIntra is less than

INTRA_ANGULAR18 , not equal to INTRA_PLANAR and not equal to INTRA_DC , nScale is set equal to $\text{Min}(2, \text{Log } 2(\text{nTbW}) - \text{Floor}(\text{Log } 2(3 * \text{invAngle} - 2)) + 8)$, using invAngle as specified in clause 8.4.5.2.12. When $\text{refW}! = 2 * \text{nTbW}$, nScale is updated as follows:

$\text{nScaleCb} = \text{Log } 2(\text{refW} - \text{nTbW}) - \text{Floor}(\text{Log } 2(3 * \text{invAngle} - 2)) + 8$

$\text{nScale} = \text{nScale} < 0 ? \min(0, \text{nScaleCb}) : \min(2, \text{nScaleCb})$ Otherwise, nScale is set to $((\text{Log } 2(\text{nTbW}) + \text{Log } 2(\text{nTbH}) - 2) > 2)$.

(255) Alternative excerpt of the specification (on the top of Embodiment 3) is as follows: The variable nScale is derived as follows: If predModeIntra is equal to INTRA_PLANAR , INTRA_DC , INTRA_ANGULAR18 , or INTRA_ANGULAR50 , nScale is set to $((\text{Log } 2(\text{nTbW}) + \text{Log } 2(\text{nTbH}) - 2) > 2)$.

Otherwise, the following is performed: nTbS is set equal to $\text{predModeIntra} > \text{INTRA_ANGULAR50}?$

$\text{refH} - \text{nTbH} : \text{refW} - \text{nTbW}$ and nTbS0 equal to $\text{predModeIntra} > \text{INTRA_ANGULAR50} ? \text{nTbH} : \text{nTbW}$ when

$\text{nTbS} = \text{nTbS0}$, nScale is set equal to $\text{Min}(2, \text{Log } 2(\text{nTbS}) - \text{Floor}(\text{Log } 2(3 * \text{invAngle} - 2)) + 8)$, otherwise

$(\text{nTbS} \neq \text{nTbS0})$, the following is performed: a. $\text{nScaleCb} = \text{Log } 2(\text{nTbS}) - \text{Floor}(\text{Log } 2(3 * \text{invAngle} - 2)) + 8$ b.

$\text{nScale} = \text{Log } 2(\text{nTbS0}) - \text{Floor}(\text{Log } 2(3 * \text{invAngle} - 2)) + 8$ c. $\text{nScale} = \text{nScale} < 0 ? \min(0, \text{nScaleCb}) : \min(2, \text{nScaleCb})$;

wherein invAngle as specified in clause 8.4.5.2.12. If the value of nScale is less than 0, process 8.4.5.2.14 is

terminated, and outputs of this process are set equal to the input predicted samples $\text{predSamples}[x][y]$, with $x = 0 \dots$

$\text{nTbW} - 1$, $y = 0 \dots \text{nTbH} - 1$.

Embodiment 10

(256) In this embodiment the final value of nScale is defined using comparison operation. In particular, when a block is a sub partition of a larger coding block, the following comparison operation is performed:

$\text{nScale} = V1 < V2 ? -1 : 0$.

(257) In this embodiment, only two values of nScale parameter are available for the case when a block is a sub partition of a larger coding block. These values are -1 and 0 .

(258) FIG. 12 shows a flowchart for this embodiment. In this figure it is shown, that for the case of an intra subpartition, nScale parameter is obtained using comparison operation (“CMP”) in operation 1204. The result of comparison is the nScale value is assigned to -1 or 0 value. For the non-ISP blocks, no modifications are introduced. Difference in processing in FIG. 12 is implemented using a demultiplexing operation (“DEMUX”) as shown in operation 1203, that is controlled by the intra subpartition mode. The other operations 1201-1202, 1205-1206 are similar as operations 1001-1004 described in FIG. 10.

(259) In the VVC specification, this embodiment corresponds to the following excerpt: The variable nScale is derived as follows: If predModeIntra is greater than INTRA_ANGULAR50 , the following is performed: When $\text{refH}! = 2 * \text{nTbH}$, nScale is set equal to $\text{Log } 2(\text{refH} - \text{nTbH}) < \text{Floor}(\text{Log } 2(3 * \text{invAngle} - 2)) + 8 ? -1 : 0$, Otherwise, nScale is set equal to $\text{Min}(2, \text{Log } 2(\text{nTbH}) - \text{Floor}(\text{Log } 2(3 * \text{invAngle} - 2)) + 8)$, using invAngle as specified in clause 8.4.5.2.12. Otherwise, if predModeIntra is less than INTRA_ANGULAR18 , not equal to INTRA_PLANAR and not equal to INTRA_DC , the following is performed: When $\text{refW}! = 2 * \text{nTbW}$, nScale is set equal to $\text{Log } 2(\text{refW} - \text{nTbW}) < \text{Floor}(\text{Log } 2(3 * \text{invAngle} - 2)) + 8 ? -1 : 0$, Otherwise, nScale is set equal to $\text{Min}(2, \text{Log } 2(\text{nTbW}) - \text{Floor}(\text{Log } 2(3 * \text{invAngle} - 2)) + 8)$, using invAngle as specified in clause 8.4.5.2.12. Otherwise, nScale is set to $((\text{Log } 2(\text{nTbW}) + \text{Log } 2(\text{nTbH}) - 2) > 2)$.

(260) Alternative excerpt of the specification (on the top of Embodiment 3) is as follows: The variable nScale is derived as follows: If predModeIntra is equal to INTRA_PLANAR , INTRA_DC , INTRA_ANGULAR18 , or INTRA_ANGULAR50 , nScale is set equal to $((\text{Log } 2(\text{nTbW}) + \text{Log } 2(\text{nTbH}) - 2) > 2)$. Otherwise, the following is performed: nTbS is set equal to $\text{predModeIntra} > \text{INTRA_ANGULAR50} ? \text{refH} - \text{nTbH} : \text{refW} - \text{nTbW}$ and nTbS0 equal to $\text{predModeIntra} > \text{INTRA_ANGULAR50} ? \text{nTbH} : \text{nTbW}$ if $\text{nTbS} = \text{nTbS0}$, nScale is set to $\text{Log } 2(\text{nTbS0}) - \text{Floor}(\text{Log } 2(3 * \text{invAngle} - 2)) + 8$ Otherwise, if $\text{Log } 2(\text{nTbS}) < \text{Floor}(\text{Log } 2(3 * \text{invAngle} - 2)) + 8$, nScale is set to -1 , Otherwise nScale is set to 0 using invAngle as specified in clause 8.4.5.2.12. If the value of nScale is less than 0, process 8.4.5.2.14 is terminated, and outputs of this process are set equal to the input predicted samples $\text{predSamples}[x][y]$, with $x = 0 \dots \text{nTbW} - 1$, $y = 0 \dots \text{nTbH} - 1$.

(261) Following is an explanation of the applications of the encoding method as well as the decoding method as shown in the above-mentioned embodiments, and a system using them. The above described embodiments can be implemented in a coding (i.e, encoding or decoding) device 1300 as it is illustrated in FIG. 13. The encoding or decoding device 1300 includes:

(262) an obtaining unit 1301, configured to obtain a predicted sample value for a sample of the current coding block, and to obtain a scaling factor value according to an intra prediction mode for the current coding block, and according to at least one of: a height of the current coding block, or a width of the current coding block, or a size

of a subpartition of the current coding block;

(263) a determining unit **1302**, configured to determine a first weight value and a second weight value based on the scaling factor value;

(264) a calculating unit **1303**, configured to calculate an additional value as a weighted sum of a top reference sample value and a left reference sample value, by weighting the top reference sample value with the first weight value and the left reference sample value with the second weight value; and

(265) the obtaining unit **1301**, further configured to obtain a modified predicted sample value according to the additional value and the predicted sample value.

(266) The determining unit **1302** may further be configured to:

(267) determine whether a first condition meets, wherein the first condition includes at least one of:

(268) the intra prediction mode for the current coding block is not angular mode, or

(269) the intra prediction mode for the current coding block is a horizontal mode, or

(270) the intra prediction mode for the current coding block is a vertical mode, or

(271) the scaling factor value is greater than or equal to 0;

(272) determine the first weight value and the second weight value based on the scaling factor value when the first condition meets.

(273) By the method and device, the position dependent prediction combination (PDPC) scaling parameter ("nScale") is determined by two values. One of these values is derived from the block size and the other one is derived from the value of the inverse intra prediction angle. Moreover, Intra subpartition mode (ISP) is considered during the deriving the nScale parameter. Thereby, method and apparatus can harmonize PDPC for directional intra prediction with ISP coding mode.

(274) Particularly, the following embodiments are provided herein:

(275) Embodiment 1. A method for intra predicting process of a video (or picture, frame) block (a block may be a current coding block or a subpartition of the current coding block), the method comprising: obtaining a predicted sample value for a sample of the current coding block (in an example, the predicted sample value is obtained from one or more reference sample values, by using an intra prediction mode which is selected from one of a DC intra-prediction mode, a planar intra prediction mode, and an angular intra-prediction mode); obtaining a scaling factor value according to an intra prediction mode for the current coding block, and according to a height of the current coding block or a width of the current coding block (this process is for angular mode. And when the intra prediction mode for the current coding block is not a horizontal mode and is not a vertical mode, the scaling factor value is obtained according to a height of the block or a width of the block for DC mode, planar mode, horizontal and vertical angular modes) (in an example, both of the height and the width are used to obtain the scaling factor); determining a first weight value based on the scaling factor value; determining a second weight value based on the scaling factor value; calculating an additional value as a weighted sum of a top reference sample value and a left reference sample value, by weighting the top reference sample value with the first weight and the left reference sample value with the second weight; obtaining a modified predicted sample value according to the additional value and the predicted sample value (in some embodiments, the predicted sample value is processed by using a sample weighting factor to obtain a weighted predicted value, the modified predicted sample value is obtained according to the additional value and the weighted predicted sample value).

(276) In an example, the method further comprises: normalizing the modified predicted sample value, by an arithmetic right shift of an integer representation of the modified predicted sample value, resulting in a normalized modified predicted sample value.

(277) Embodiment 2. The method according to embodiment 1, wherein the height of the current coding block is equal to a value of $\text{refH}-\text{nTbH}$, the variable refH indicates height of reference samples, and the variable nTbH indicates height of transform block.

(278) Embodiment 3. The method according to embodiment 1 or 2, wherein the width of the current coding block is equal to a value of $\text{refW}-\text{nTbW}$, the variable refW indicates width of reference samples, and variable nTbW indicates width of transform block.

(279) Embodiment 4. The method of embodiments 1-3, wherein the nScale parameter is calculated as follows:

$$\text{nScale}=\min(2, \text{V1}+\text{V2}),$$

wherein the first value "V1" is derived from the size of a subpartition, the size of the coding block to which the subpartition belongs to; and the second value is derived as follows:

$$\text{V2}=8-\text{Floor}(\text{Log } 2(3*\text{invAngle}-2)),$$

wherein invAngle is the inverse angle parameter.

(280) Embodiment 5. The method of embodiments 1-3, the method comprising: Obtaining initial value of parameter nScale (nScale.sub.0) based on the size of the subpartition (nTbS): $\text{nScale.sub.0}=\min(2, \text{Log } 2(\text{nTbS})+\text{V2})$; and Obtaining the final value of the parameter nScale based on the initial value of parameter nScale: $\text{nScale}=\text{nScale.sub.0}<0?\min(0, \text{V1}+\text{V2}):\min(2, \text{V1}+\text{V2})$, wherein the first value "V1" is derived from the

size of a subpartition, the size of the coding block to which the subpartition belongs to; and the second value is derived as follows: $V2=8-\text{Floor}(\text{Log } 2(3*\text{invAngle}-2))$

(281) Embodiment 6. The method of embodiments 1-3, wherein the nScale parameter is calculated as follows: $nScale=V1<V2?-1:0$,

wherein the first value “V1” is derived from the size of a subpartition, the size of the coding block to which the subpartition belongs to; and the second value is derived as follows: $V2=8-\text{Floor}(\text{Log } 2(3*\text{invAngle}-2))$.

(282) Embodiment 7. A method for intra predicting process of a video (or picture, frame) block (a block may be a current coding block or a subpartition of the current coding block), the method comprising: obtaining a predicted sample value for a sample of the current coding block (in an example, the predicted sample value is obtained from one or more reference sample values, by using an intra prediction mode which is selected from one of a DC intra-prediction mode, a planar intra prediction mode, and an angular intra-prediction mode); obtaining a scaling factor value according to an intra prediction mode for the current coding block, and according to a height of the current coding block or a width of the current coding block (this process is for angular mode. And when the intra prediction mode for the current coding block is not a horizontal mode and is not a vertical mode, the scaling factor value is obtained according to a height of the block or a width of the block for DC mode, planar mode, horizontal and vertical angular modes) (in an example, both of the height and the width are used to obtain the scaling factor); when the scaling factor value is greater than or equal to 0, performing the following processes: determining a first weight value based on the scaling factor value; determining a second weight value based on the scaling factor value; calculating an additional value as a weighted sum of a top reference sample value and a left reference sample value, by weighting the top reference sample value with the first weight and the left reference sample value with the second weight; obtaining a modified predicted sample value according to the additional value and the predicted sample value (in some embodiments, the predicted sample value is processed by using a sample weighting factor to obtain a weighted predicted value, the modified predicted sample value is obtained according to the additional value and the weighted predicted sample value).

(283) In an example, the method further comprises: normalizing the modified predicted sample value, by an arithmetic right shift of an integer representation of the modified predicted sample value, resulting in a normalized modified predicted sample value.

(284) Embodiment 8. The method of embodiment 7, wherein the method further comprises:

(285) when the scaling factor value is less than 0, output the predicted sample value.

(286) Embodiment 9. A method for intra predicting process of a video (or picture, frame) block (a block may be a current coding block or a subpartition of the current coding block), the method comprising: obtaining a predicted sample value for a sample of the current coding block (in an example, the predicted sample value is obtained from one or more reference sample values, by using an intra prediction mode which is selected from one of a DC intra-prediction mode, a planar intra prediction mode, and an angular intra-prediction mode); obtaining a scaling factor value according to an intra prediction mode for the current coding block, and according to a height of the current coding block or a width of the current coding block (this process is for angular mode. And when the intra prediction mode for the current coding block is not a horizontal mode and is not a vertical mode, the scaling factor value is obtained according to a height of the block or a width of the block for DC mode, planar mode, horizontal and vertical angular modes) (in an example, both of the height and the width are used to obtain the scaling factor); when the intra prediction mode for the current coding block is angular mode (but the intra prediction mode for the current coding block is not a horizontal mode and is not a vertical mode), and when the scaling factor value is less than 0, output the predicted sample value; otherwise (the intra prediction mode for the current coding block is not angular mode, or the intra prediction mode for the current coding block is a horizontal mode, or the intra prediction mode for the current coding block is a vertical mode, or the scaling factor value is greater than or equal to 0), performing the following processes: determining a first weight value based on the scaling factor value, determining a second weight value based on the scaling factor value, calculating an additional value as a weighted sum of a top reference sample value and a left reference sample value, by weighting the top reference sample value with the first weight and the left reference sample value with the second weight, obtaining a modified predicted sample value according to the additional value and the predicted sample value (in some embodiments, the predicted sample value is processed by using a sample weighting factor to obtain a weighted predicted value, the modified predicted sample value is obtained according to the additional value and the weighted predicted sample value).

(287) In an example, the method further comprises: normalizing the modified predicted sample value, by an arithmetic right shift of an integer representation of the modified predicted sample value, resulting in a normalized modified predicted sample value.

(288) Embodiment 10. The method according to one of embodiments 7 to 9, wherein the height of the current coding block is equal to a value of $\text{refH}-n\text{TbH}$, the variable refH indicates height of reference samples, and the variable nTbH indicates height of transform block.

(289) Embodiment 11. The method according to one of embodiments 7 to 10, wherein the width of the current

coding block is equal to a value of $\text{refW}-\text{nTbW}$, the variable refW indicates width of reference samples, and variable nTbW indicates width of transform block.

(290) Embodiment 12. A method for intra predicting process of a block, the method comprising: obtaining a predicted sample value from one or more reference sample values by using an intra prediction mode of a coding block; obtaining a scale parameter (nScale) according to the intra prediction mode for the coding block and a size of a subpartition; calculating an additional value according to the obtained scale parameter; obtaining a modified predicted sample value according to the additional value and the predicted sample value.

(291) Embodiment 13. The method of embodiment 12, wherein the nScale parameter meets:

$\text{nScale}=\min(2, V1+V2)$,

(292) wherein the first value “V1” is derived from the size of the subpartition, the size of the coding block to which the subpartition belongs to; and the second value is derived as follows:

$V2=8-\text{Floor}(\text{Log } 2(3*\text{invAngle}-2))$,

(293) wherein invAngle is the inverse angle parameter.

(294) Embodiment 14. The method of embodiment 12, the method comprising: obtaining initial value of parameter nScale (nScale.sub.0) based on the size of the subpartition (nTbS): $\text{nScale.sub.0}=\min(2, \text{Log } 2(\text{nTbS})+V2)$; and obtaining the final value of the parameter nScale based on the initial value of parameter

nScale : $\text{nScale}=\text{nScale.sub.0}<0?\min(0, V1+V2):\min(2, V1+V2)$,

(295) wherein the first value “V1” is derived from the size of the subpartition, the size of the coding block to which the subpartition belongs to; and the second value is derived as follows:

$V2=8-\text{Floor}(\text{Log } 2(3*\text{invAngle}-2))$,

(296) wherein invAngle is the inverse angle parameter.

(297) Embodiment 15. The method of embodiment 12, wherein the nScale parameter meets:

$\text{nScale}=V1<V2?-1:0$,

(298) wherein the first value “V1” is derived from the size of the subpartition, the size of the coding block to which the subpartition belongs to; and the second value is derived as follows:

(299) $V2=8-\text{Floor}(\text{Log } 2(3*\text{invAngle}-2))$, wherein invAngle is the inverse angle parameter.

(300) Embodiment 16. A method for intra predicting process of a block, the method comprising: obtaining a predicted sample value from one or more reference sample values by using an intra prediction mode of a current coding block; obtaining a scale parameter (nScale) according to the intra prediction mode for the current coding block, and according to at least one of a variable refH which indicates height of reference samples or a variable refW which indicates width of reference samples; calculating an additional value according to the obtained scale parameter; obtaining a modified predicted sample value according to the additional value and the predicted sample value.

(301) Embodiment 17. The method of embodiment 16, wherein when predModeIntra is greater than INTRA_ANGULAR50 , nScale is set equal to

(302) $\text{Min}(2, \text{Log } 2(\text{refH}-\text{nTbH})-\text{Floor}(\text{Log } 2(3*\text{invAngle}-2))+8)$, wherein the variable refH indicates height of reference samples, the variable nTbH indicates the transform block height, and invAngle is the inverse angle parameter.

(303) Embodiment 18. The method of embodiment 16, wherein when predModeIntra is less than

INTRA_ANGULAR18 , not equal to INTRA_PLANAR and not equal to INTRA_DC , nScale is set equal to

(304) $\text{Min}(2, \text{Log } 2(\text{refW}-\text{nTbW})-\text{Floor}(\text{Log } 2(3*\text{invAngle}-2))+8)$, wherein the variable refW indicates width of reference samples, the variable nTbW indicates the transform block width, and invAngle is the inverse angle parameter.

(305) Embodiment 19. The method of embodiment 16, wherein when predModeIntra is equal to INTRA_PLANAR , INTRA_DC , INTRA_ANGULAR18 , or INTRA_ANGULAR50 , nScale is set to $((\text{Log } 2(\text{nTbW})+\text{Log } 2(\text{nTbH})-2)>>2)$;

(306) Otherwise, nScale is set equal to $\text{Min}(2, \text{Log } 2(\text{nTbS})-\text{Floor}(\text{Log } 2(3*\text{invAngle}-2))+8)$, wherein nTbS equals to $\text{predModeIntra}>\text{INTRA_ANGULAR50}?\text{refH}-\text{nTbH}:\text{refW}-\text{nTbW}$, the variable refH indicates height of reference samples, the variable nTbH indicates the transform block height, the variable refW indicates width of reference samples, the variable nTbW indicates the transform block width, and invAngle is the inverse angle parameter.

(307) Embodiment 20. The method of embodiment 16, wherein when the predModeIntra is greater than INTRA_ANGULAR50 , nScale is set equal to

$\text{Min}(2, \text{Log } 2(\text{nTbH})-\text{Floor}(\text{Log } 2(3*\text{invAngle}-2))+8)$,

(308) When $\text{refH}\neq 2*\text{nTbH}$, nScale is updated as follows:

$\text{nScaleCb}=\text{Log } 2(\text{refH}-\text{nTbH})-\text{Floor}(\text{Log } 2(3*\text{invAngle}-2))+8$

$\text{nScale}=\text{nScale}<0?\min(0, \text{nScaleCb}):\min(2, \text{nScaleCb})$.

(309) Embodiment 21. The method of embodiment 16, wherein when predModeIntra is less than

INTRA_ANGULAR18, not equal to INTRA_PLANAR and not equal to INTRA_DC, nScale is set equal to $\text{Min}(2, \text{Log } 2(n\text{TbW}) - \text{Floor}(\text{Log } 2(3 * \text{invAngle} - 2)) + 8)$;

(310) when $\text{refW} \neq 2 * n\text{TbW}$, nScale is updated as follows:
 $n\text{ScaleCb} = \text{Log } 2(\text{refW} - n\text{TbW}) - \text{Floor}(\text{Log } 2(3 * \text{invAngle} - 2)) + 8$
 $n\text{Scale} = n\text{Scale} < 0 ? \text{min}(0, n\text{ScaleCb}) : \text{min}(2, n\text{ScaleCb})$.

(311) Embodiment 22. The method of embodiment 16, wherein when predModeIntra is equal to INTRA_PLANAR, INTRA_DC, INTRA_ANGULAR18, or INTRA_ANGULAR50: nScale is set to $((\text{Log } 2(n\text{TbW}) + \text{Log } 2(n\text{TbH}) - 2) > 2)$;

(312) otherwise, when $n\text{TbS} = n\text{TbS0}$:

(313) nScale is set equal to $\text{Min}(2, \text{Log } 2(n\text{TbS}) - \text{Floor}(\text{Log } 2(3 * \text{invAngle} - 2)) + 8)$, nTbS is set equal to $\text{predModeIntra} > \text{INTRA_ANGULAR50} ? \text{refH} - n\text{TbH} : \text{refW} - n\text{TbW}$, and nTbS0 is set equal to $\text{predModeIntra} > \text{INTRA_ANGULAR50} ? n\text{TbH} : n\text{TbW}$

(314) otherwise, when $n\text{TbS} \neq n\text{TbS0}$:
 $n\text{ScaleCb} = \text{Log } 2(n\text{TbS}) - \text{Floor}(\text{Log } 2(3 * \text{invAngle} - 2)) + 8$
 $n\text{Scale} = \text{Log } 2(n\text{TbS0}) - \text{Floor}(\text{Log } 2(3 * \text{invAngle} - 2)) + 8$
 $n\text{Scale} = n\text{Scale} < 0 ? \text{min}(0, n\text{ScaleCb}) : \text{min}(2, n\text{ScaleCb})$.

(315) Embodiment 23. The method of embodiment 16, wherein when predModeIntra is greater than INTRA_ANGULAR50, the following is performed:

(316) When $\text{refH} \neq 2 * n\text{TbH}$, nScale is set equal to $\text{Log } 2(\text{refH} - n\text{TbH}) < \text{Floor}(\text{Log } 2(3 * \text{invAngle} - 2)) + 8 ? -1 : 0$,

(317) Otherwise, nScale is set equal to $\text{Min}(2, \text{Log } 2(n\text{TbH}) - \text{Floor}(\text{Log } 2(3 * \text{invAngle} - 2)) + 8)$.

(318) Embodiment 24. The method of embodiment 16, wherein when predModeIntra is less than INTRA_ANGULAR18, not equal to INTRA_PLANAR and not equal to INTRA_DC, the following is performed:

(319) When $\text{refW} \neq 2 * n\text{TbW}$, nScale is set equal to $\text{Log } 2(\text{refW} - n\text{TbW}) < \text{Floor}(\text{Log } 2(3 * \text{invAngle} - 2)) + 8 ? -1 : 0$,

(320) Otherwise, nScale is set equal to $\text{Min}(2, \text{Log } 2(n\text{TbW}) - \text{Floor}(\text{Log } 2(3 * \text{invAngle} - 2)) + 8)$.

(321) FIG. 14 is a block diagram showing a content supply system **3100** for realizing content distribution service. This content supply system **3100** includes capture device **3102**, terminal device **3106**, and optionally includes display **3126**. The capture device **3102** communicates with the terminal device **3106** over communication link **3104**. The communication link may include the communication channel **13** described above. The communication link **3104** includes but not limited to WIFI, Ethernet, Cable, wireless (3G/4G/5G), USB, or any kind of combination thereof, or the like.

(322) The capture device **3102** generates data, and may encode the data by the encoding method as shown in the above embodiments. Alternatively, the capture device **3102** may distribute the data to a streaming server (not shown in the Figures), and the server encodes the data and transmits the encoded data to the terminal device **3106**. The capture device **3102** includes but not limited to camera, smart phone or Pad, computer or laptop, video conference system, PDA, vehicle mounted device, or a combination of any of them, or the like. For example, the capture device **3102** may include the source device **12** as described above. When the data includes video, the video encoder **20** included in the capture device **3102** may actually perform video encoding processing. When the data includes audio (i.e., voice), an audio encoder included in the capture device **3102** may actually perform audio encoding processing. For some practical scenarios, the capture device **3102** distributes the encoded video and audio data by multiplexing them together. For other practical scenarios, for example in the video conference system, the encoded audio data and the encoded video data are not multiplexed. Capture device **3102** distributes the encoded audio data and the encoded video data to the terminal device **3106** separately.

(323) In the content supply system **3100**, the terminal device **310** receives and reproduces the encoded data. The terminal device **3106** could be a device with data receiving and recovering capability, such as smart phone or Pad **3108**, computer or laptop **3110**, network video recorder (NVR)/digital video recorder (DVR) **3112**, TV **3114**, set top box (STB) **3116**, video conference system **3118**, video surveillance system **3120**, personal digital assistant (PDA) **3122**, vehicle mounted device **3124**, or a combination of any of them, or the like capable of decoding the above-mentioned encoded data. For example, the terminal device **3106** may include the destination device **14** as described above. When the encoded data includes video, the video decoder **30** included in the terminal device is prioritized to perform video decoding. When the encoded data includes audio, an audio decoder included in the terminal device is prioritized to perform audio decoding processing.

(324) For a terminal device with its display, for example, smart phone or Pad **3108**, computer or laptop **3110**, network video recorder (NVR)/digital video recorder (DVR) **3112**, TV **3114**, personal digital assistant (PDA) **3122**, or vehicle mounted device **3124**, the terminal device can feed the decoded data to its display. For a terminal

device equipped with no display, for example, STB **3116**, video conference system **3118**, or video surveillance system **3120**, an external display **3126** is contacted therein to receive and show the decoded data.

(325) When each device in this system performs encoding or decoding, the picture encoding device or the picture decoding device, as shown in the above-mentioned embodiments, can be used.

(326) FIG. **15** is a diagram showing a structure of an example of the terminal device **3106**. After the terminal device **3106** receives stream from the capture device **3102**, the protocol proceeding unit **3202** analyzes the transmission protocol of the stream. The protocol includes but not limited to Real Time Streaming Protocol (RTSP), Hyper Text Transfer Protocol (HTTP), HTTP Live streaming protocol (HLS), MPEG-DASH, Real-time Transport protocol (RTP), Real Time Messaging Protocol (RTMP), or any kind of combination thereof, or the like.

(327) After the protocol proceeding unit **3202** processes the stream, stream file is generated. The file is outputted to a demultiplexing unit **3204**. The demultiplexing unit **3204** can separate the multiplexed data into the encoded audio data and the encoded video data. As described above, for some practical scenarios, for example in the video conference system, the encoded audio data and the encoded video data are not multiplexed. In this situation, the encoded data is transmitted to video decoder **3206** and audio decoder **3208** without through the demultiplexing unit **3204**.

(328) Via the demultiplexing processing, video elementary stream (ES), audio ES, and optionally subtitle are generated. The video decoder **3206**, which includes the video decoder **30** as explained in the above mentioned embodiments, decodes the video ES by the decoding method as shown in the above-mentioned embodiments to generate video frame, and feeds this data to the synchronous unit **3212**. The audio decoder **3208**, decodes the audio ES to generate audio frame, and feeds this data to the synchronous unit **3212**. Alternatively, the video frame may store in a buffer (not shown in FIG. **15**) before feeding it to the synchronous unit **3212**. Similarly, the audio frame may store in a buffer (not shown in FIG. **15**) before feeding it to the synchronous unit **3212**.

(329) The synchronous unit **3212** synchronizes the video frame and the audio frame, and supplies the video/audio to a video/audio display **3214**. For example, the synchronous unit **3212** synchronizes the presentation of the video and audio information. Information may code in the syntax using time stamps concerning the presentation of coded audio and visual data and time stamps concerning the delivery of the data stream itself

(330) If subtitle is included in the stream, the subtitle decoder **3210** decodes the subtitle, and synchronizes it with the video frame and the audio frame, and supplies the video/audio/subtitle to a video/audio/subtitle display **3216**.

(331) The present application is not limited to the above-mentioned system, and either the picture encoding device or the picture decoding device in the above-mentioned embodiments can be incorporated into other system, for example, a car system.

(332) Mathematical Operators

(333) The mathematical operators used in this application are similar to those used in the C programming language. However, the results of integer division and arithmetic shift operations are defined more precisely, and additional operations are defined, such as exponentiation and real-valued division. Numbering and counting conventions generally begin from 0, e.g., “the first” is equivalent to the 0-th, “the second” is equivalent to the 1-th, etc.

(334) Arithmetic Operators

(335) The following arithmetic operators are defined as follows:

(336) + Addition – Subtraction (as a two-argument operator) or negation (as a unary prefix operator) *

Multiplication, including matrix multiplication $x \cdot y$ Exponentiation. Specifies x to the power of y . In other contexts, such notation is used for superscripting not intended for interpretation as exponentiation. / Integer division with truncation of the result toward zero. For example, $7/4$ and $-7/-4$ are truncated to 1 and $-7/4$ and $7/-4$ are truncated to -1 . $\div$ Used to denote division in mathematical equations where no truncation or rounding is intended.

(337) $\frac{x}{y}$ Used to denote division in mathematical equations where no truncation or rounding is intended.

(338) $\sum_{i=x}^y f(i)$ The summation of $f(i)$ with i taking all integer values from x up to and including y . $x \% y$

Modulus. Remainder of x divided by y , defined only for integers x and y with $x \geq 0$ and $y > 0$.

Logical Operators

The following logical operators are defined as follows: $x \&\& y$ Boolean logical “and” of x and y $x \parallel y$ Boolean logical “or” of x and y $!x$ Boolean logical “not” $x?y:z$ If x is TRUE or not equal to 0, evaluates to the value of y ; otherwise, evaluates to the value of z .

Relational Operators

The following relational operators are defined as follows:

Greater than $>$ Greater than or equal to $\geq$ Less than $<$ Less than or equal to $\leq$ Equal to $==$ Not equal to $!=$

(339) When a relational operator is applied to a syntax element or variable that has been assigned the value “na” (not applicable), the value “na” is treated as a distinct value for the syntax element or variable. The value “na” is

considered not to be equal to any other value.

(340) Bit-Wise Operators

(341) The following bit-wise operators are defined as follows:

(342) & Bit-wise “and”. When operating on integer arguments, operates on a two's complement representation of the integer value. When operating on a binary argument that contains fewer bits than another argument, the shorter argument is extended by adding more significant bits equal to 0.

(343) || Bit-wise “or”. When operating on integer arguments, operates on a two's complement representation of the integer value. When operating on a binary argument that contains fewer bits than another argument, the shorter argument is extended by adding more significant bits equal to 0.

(344) {circumflex over ()} Bit-wise “exclusive or”. When operating on integer arguments, operates on a two's complement representation of the integer value. When operating on a binary argument that contains fewer bits than another argument, the shorter argument is extended by adding more significant bits equal to 0.

(345) x>>y Arithmetic right shift of a two's complement integer representation of x by y binary digits. This function is defined only for non-negative integer values of y. Bits shifted into the most significant bits (MSBs) as a result of the right shift have a value equal to the MSB of x prior to the shift operation.

(346) x<<y Arithmetic left shift of a two's complement integer representation of x by y binary digits. This function is defined only for non-negative integer values of y. Bits shifted into the least significant bits (LSBs) as a result of the left shift have a value equal to 0.

(347) Assignment Operators

(348) The following arithmetic operators are defined as follows: = Assignment operator ++ Increment, i.e., x++ is equivalent to x=x+1; when used in an array index, evaluates to the value of the variable prior to the increment operation. -- Decrement, i.e., x-- is equivalent to x=x-1; when used in an array index, evaluates to the value of the variable prior to the decrement operation. += Increment by amount specified, i.e., x+=3 is equivalent to x=x+3, and x+=(-3) is equivalent to x=x+(-3). -= Decrement by amount specified, i.e., x-=3 is equivalent to x=x-3, and x-=(-3) is equivalent to x=x-(-3).

Range Notation

(349) The following notation is used to specify a range of values:

(350) x=y . . . zx takes on integer values starting from y to z, inclusive, with x, y, and z being integer numbers and z being greater than y.

(351) Mathematical Functions

(352) The following mathematical functions are defined:

(353)
$$\text{Abs}(x) = \begin{cases} x; & x \geq 0 \\ -x; & x < 0 \end{cases}$$
 A sin(x) the trigonometric inverse sine function, operating on an argument x that is

in the range of -1.0 to 1.0 , inclusive, with an output value in the range of $-\pi/2$ to $\pi/2$, inclusive, in units of radians A tan(x) the trigonometric inverse tangent function, operating on an argument x, with an output value in the range of $-\pi/2$ to $\pi/2$, inclusive, in units of radians

$$\text{Atan}(\frac{y}{x}); \quad x > 0$$

$$\text{Atan}(\frac{y}{x}) + \frac{\pi}{2}; \quad x < 0 \ \&\& \ y \geq 0$$

(354)
$$\text{Atan2}(y, x) = \begin{cases} \text{Atan}(\frac{y}{x}) - \frac{\pi}{2}; & x < 0 \ \&\& \ y < 0 \\ \text{Atan}(\frac{y}{x}); & x == 0 \ \&\& \ y \geq 0 \\ -\frac{\pi}{2}; & \text{otherwise} \end{cases}$$
 Ceil(x) the smallest integer greater than or equal to x.

Clip1.sub.Y(x)=Clip3(0,(1<<BitDepth.sub.Y)-1,x)

Clip1.sub.C(x)=Clip3(0,(1<<BitDepth.sub.C)-1,x)

$$x; \quad z < x$$

(355)
$$\text{Clip3}(x, y, z) = \begin{cases} y; & z > y \\ z; & \text{otherwise} \end{cases}$$
 Cos(x) the trigonometric cosine function operating on an argument x in

units of radians Floor(x) the largest integer less than or equal to x.

$$c + d; \quad b - a \geq d / 2$$

(356)
$$\text{GetCurrMsb}(a, b, c, d) = \begin{cases} c - d; & a - b > d / 2 \\ c; & \text{otherwise} \end{cases}$$
 Ln(x) the natural logarithm of x (the base-e logarithm,

where e is the natural logarithm base constant 2.718 281 828 . . .). Log 2(x) the base-2 logarithm of x. Log 10(x) the base-10 logarithm of x.

(357)

$$\text{Min}(x, y) = \begin{cases} x; & x \leq y \\ y; & x > y \end{cases} \quad \text{Max}(x, y) = \begin{cases} x; & x \geq y \\ y; & x < y \end{cases} \quad \text{Round}(x) = \text{Sign}(x) * \text{Floor}(\text{Abs}(x) + 0.5) \quad \text{Sign}(x) = \begin{cases} 1; & x > 0 \\ 0; & x == 0 \\ -1; & x < 0 \end{cases}$$

Sin(x) the trigonometric sine function operating on an argument x in units of radians

Sqrt(x)=√{square root over (x)}

Swap(x, y)=(y, x) Tan(x) the trigonometric tangent function operating on an argument x in units of radians

Order of Operation Precedence

(358) When an order of precedence in an expression is not indicated explicitly by use of parentheses, the following rules apply: Operations of a higher precedence are evaluated before any operation of a lower precedence.

Operations of the same precedence are evaluated sequentially from left to right.

(359) The table below specifies the precedence of operations from highest to lowest; a higher position in the table indicates a higher precedence.

(360) For those operators that are also used in the C programming language, the order of precedence used in this Specification is the same as used in the C programming language.

(361) TABLE-US-00004 TABLE Operation precedence from highest (at top of table) to lowest (at bottom of table) operations (with operands x, y, and z) "x++", "x--", "!", "x", "-x" (as a unary prefix operator) x.sup.y

"x * y", "x / y", "x ÷ y", "x/y", "x%y" 0 "x + y", "x - y" (as a two - argument operator), ".Math. f(i)" "x << y", "x >> y" "x < y", "x <= y", "x > y", "x >= y" "x = y", "x != y" "x & y" "x | y" "x && y" "x || y" "x ? y : z" "x ... y" "x = y", "x += y", "x -= y"

Text Description of Logical Operations

In the text, a statement of logical operations as would be described mathematically in the following form:

(362) TABLE-US-00005 if(condition 0) statement 0 else if(condition 1) statement 1 ... else /* informative remark on remaining condition */ statement n

may be described in the following manner:

(363) TABLE-US-00006 ... as follows / ... the following applies: If condition 0, statement 0 Otherwise, if condition 1, statement 1 ...

(364) Otherwise (informative remark on remaining condition), statement n.

(365) Each "If ... Otherwise, if ... Otherwise, ..." statement in the text is introduced with "... as follows" or "... the following applies" immediately followed by "If ...". The last condition of the "If ... Otherwise, if ... Otherwise, ..." is always an "Otherwise, ...". Interleaved "If ... Otherwise, if ... Otherwise, ..." statements can be identified by matching "... as follows" or "... the following applies" with the ending "Otherwise, ...".

(366) In the text, a statement of logical operations as would be described mathematically in the following form:

(367) TABLE-US-00007 if(condition 0a && condition 0b) statement 0 else if(condition 1a || condition 1b) statement 1 ... else statement n

may be described in the following manner:

(368) ... as follows/ ... the following applies: If all of the following conditions are true, statement 0: condition 0a condition 0b Otherwise, if one or more of the following conditions are true, statement 1: condition 1a condition 1b ... Otherwise, statement n

(369) In the text, a statement of logical operations as would be described mathematically in the following form:

(370) TABLE-US-00008 if(condition 0) statement 0 if(condition 1) statement 1

(371) may be described in the following manner:

(372) When condition 0, statement 0

(373) When condition 1, statement 1.

(374) Embodiments, e.g. of the encoder **20** and the decoder **30**, and functions described herein, e.g. with reference to the encoder **20** and the decoder **30**, may be implemented in hardware, software, firmware, or any combination thereof. If implemented in software, the functions may be stored on a computer-readable medium or transmitted over communication media as one or more instructions or code and executed by a hardware-based processing unit. Computer-readable media may include computer-readable storage media, which corresponds to a tangible medium such as data storage media, or communication media including any medium that facilitates transfer of a computer program from one place to another, e.g., according to a communication protocol. In this manner, computer-readable media generally may correspond to (1) tangible computer-readable storage media which is non-transitory or (2) a communication medium such as a signal or carrier wave. Data storage media may be any available media that can be accessed by one or more computers or one or more processors to retrieve instructions, code and/or data structures for implementation of the techniques described in this disclosure. A computer program product may include a computer-readable medium.

(375) By way of example, and not limiting, such computer-readable storage media can comprise RAM, ROM,

EEPROM, CD-ROM or other optical disk storage, magnetic disk storage, or other magnetic storage devices, flash memory, or any other medium that can be used to store desired program code in the form of instructions or data structures and that can be accessed by a computer. Also, any connection is properly termed a computer-readable medium. For example, if instructions are transmitted from a website, server, or other remote source using a coaxial cable, fiber optic cable, twisted pair, digital subscriber line (DSL), or wireless technologies such as infrared, radio, and microwave, then the coaxial cable, fiber optic cable, twisted pair, DSL, or wireless technologies such as infrared, radio, and microwave are included in the definition of medium. It should be understood, however, that computer-readable storage media and data storage media do not include connections, carrier waves, signals, or other transitory media, but are instead directed to non-transitory, tangible storage media. Disk and disc, as used herein, includes compact disc (CD), laser disc, optical disc, digital versatile disc (DVD), floppy disk and Blu-ray disc, where disks usually reproduce data magnetically, while discs reproduce data optically with lasers. Combinations of the above should also be included within the scope of computer-readable media.

(376) Instructions may be executed by one or more processors, such as one or more digital signal processors (DSPs), general purpose microprocessors, application specific integrated circuits (ASICs), field programmable logic arrays (FPGAs), or other equivalent integrated or discrete logic circuitry. Accordingly, the term “processor,” as used herein may refer to any of the foregoing structure or any other structure suitable for implementation of the techniques described herein. In addition, in some aspects, the functionality described herein may be provided within dedicated hardware and/or software modules configured for encoding and decoding, or incorporated in a combined codec. Also, the techniques could be fully implemented in one or more circuits or logic elements.

(377) The techniques of this disclosure may be implemented in a wide variety of devices or apparatuses, including a wireless handset, an integrated circuit (IC) or a set of ICs (e.g., a chip set). Various components, modules, or units are described in this disclosure to emphasize functional aspects of devices configured to perform the disclosed techniques, but do not necessarily require realization by different hardware units. Rather, as described above, various units may be combined in a codec hardware unit or provided by a collection of interoperative hardware units, including one or more processors as described above, in conjunction with suitable software and/or firmware.

Claims

1. A method for intra predicting process of a current coding block, the method comprising: obtaining a predicted sample value for a sample of the current coding block; obtaining a scaling factor value according to an intra prediction mode for the current coding block, and according to at least one of: a height of the current coding block, or a width of the current coding block, or a size of a subpartition of the current coding block; determining a first weight value based on the scaling factor value; determining a second weight value based on the scaling factor value; weighting a top reference sample value with the first weight value to produce a weighted top reference sample; weighting a left reference sample value with the second weight value to produce a weighted left reference sample; combining the weighted top reference sample value with the weighted left reference sample value to produce an additional value; and obtaining a modified predicted sample value according to the additional value and the predicted sample value, wherein the scaling factor value (nScale) is calculated as follows: obtaining an initial value of parameter nScale0 based on the size of the subpartition (nTbS): $nScale0 = \min(2, \log_2(nTbS) + V2)$; and obtaining a final value of the parameter nScale based on the initial value of parameter nScale0: $nScale = nScale0 < 0 ? \min(0, V1 + V2) : \min(2, V1 + V2)$, wherein first value “V1” is derived from the size of the subpartition, and a size of the current coding block to which the subpartition belongs to; and second value “V2” is derived as follows: $V2 = 8 - \text{Floor}(\log_2(3 * \text{invAngle} - 2))$, and wherein the invAngle is an inverse angle parameter depending on the intra prediction mode for the current coding block; or $nScale = V1 < V2 ? -1 : 0$, wherein the first value “V1” is derived from the size of the subpartition, and the size of the current coding block to which the subpartition belongs to; and the second value “V2” is derived as follows: $V2 = 8 - \text{Floor}(\log_2(3 * \text{invAngle} - 2))$, wherein the invAngle is an inverse angle parameter depending on the intra prediction mode for the current coding block.

2. The method according to claim 1, wherein the height of the current coding block is equal to a value of $\text{refH} - nTbH$, the variable refH indicates a height of reference samples, and the variable nTbH indicates a height of a transform block.

3. The method according to claim 1, wherein the width of the current coding block is equal to a value of $\text{refW} - nTbW$, the variable refW indicates a width of reference samples, and the variable nTbW indicates a width of a transform block.

4. The method according to claim 1, wherein the method further comprises: determining whether a first condition is met, wherein the first condition includes at least one of: the intra prediction mode for the current coding block is

not angular mode, or the intra prediction mode for the current coding block is a horizontal mode, or the intra prediction mode for the current coding block is a vertical mode, or the scaling factor value is greater than or equal to 0; and determining the first weight value and the second weight value based on the scaling factor value when the first condition is met.

5. The method according to claim 1, wherein the predicted sample value is processed by using a sample weighting factor to obtain a weighted predicted value, and the modified predicted sample value is obtained according to the additional value and the weighted predicted sample value.

6. The method according to claim 1, wherein the method further comprises: normalizing the modified predicted sample value, by an arithmetic right shift of an integer representation of the modified predicted sample value, resulting in a normalized modified predicted sample value.

7. A method for intra predicting process of a block, the method comprising: obtaining a predicted sample value from one or more reference sample values by using an intra prediction mode of a coding block; obtaining a scale (nScale) parameter according to the intra prediction mode for the coding block, and according to at least one of: a size of a subpartition, or a variable refH indicating a height of reference samples, or a variable refW indicating a width of the reference samples; weighting a top reference sample value with a first weight value to produce a weighted top reference sample; weighting a left reference sample value with a second weight value to produce a weighted left reference sample; combining the weighted top reference sample value with the weighted left reference sample value to produce an additional value; and obtaining a modified predicted sample value according to the additional value and the predicted sample value, wherein the nScale is calculated as follows: obtaining an initial value of parameter nScale0 based on the size of the subpartition ($nTbS$): $nScale0 = \min(2, \log_2(nTbS) + V2)$; and obtaining a final value of the parameter nScale based on the initial value of parameter nScale0: $nScale = nScale0 < 0 ? \min(0, V1 + V2) : \min(2, V1 + V2)$, wherein first value "V1" is derived from the size of the subpartition, and a size of the coding block to which the subpartition belongs to; and second value "V2" is derived as follows: $V2 = 8 - \text{Floor}(\log_2(3 * \text{invAngle} - 2))$, and wherein the invAngle is an inverse angle parameter depending on the intra prediction mode for the coding block; or $nScale = V1 < V2 ? -1 : 0$, wherein the first value "V1" is derived from the size of the subpartition, and the size of the coding block to which the subpartition belongs to; and the second value "V2" is derived as follows: $V2 = 8 - \text{Floor}(\log_2(3 * \text{invAngle} - 2))$, wherein invAngle is an inverse angle parameter depending on the intra prediction mode for the coding block.

8. The method according to claim 7, wherein when a value of an intra prediction mode predModeIntra of the coding block is greater than INTRA_ANGULAR50, wherein nScale is set equal to $\text{Min}(2, \log_2(\text{refH} - nTbH) - \text{Floor}(\log_2(3 * \text{invAngle} - 2)) + 8)$, wherein the variable refH indicates a height of the reference samples, the variable nTbH indicates a height of a transform block.

9. The method according to claim 7, wherein when a value of an intra prediction mode predModeIntra of the coding block is less than INTRA_ANGULAR18, not equal to INTRA_PLANAR and not equal to INTRA_DC, nScale is set equal to $\text{Min}(2, \log_2(\text{refW} - nTbW) - \text{Floor}(\log_2(3 * \text{invAngle} - 2)) + 8)$, wherein the variable refW indicates a width of the reference samples, the variable nTbW indicates a width of a transform block.

10. The method according to claim 7, wherein when a value of an intra prediction mode predModeIntra of the coding block is equal to INTRA_PLANAR, INTRA_DC, INTRA_ANGULAR18, or INTRA_ANGULAR50, nScale is set to $((\log_2(nTbW) + \log_2(nTbH) - 2) >> 2)$; Otherwise, nScale is set equal to $\text{Min}(2, \log_2(nTbS) - \text{Floor}(\log_2(3 * \text{invAngle} - 2)) + 8)$, wherein nTbS equals to $\text{predModeIntra} > \text{INTRA_ANGULAR50} ? \text{refH} - nTbH : \text{refW} - nTbW$, the variable refH indicates a height of the reference samples, the variable nTbH indicates a height of a transform block, the variable refW indicates the width of the reference samples, the variable nTbW indicates a width of the transform block.

11. The method according to claim 7, wherein when a value of an intra prediction mode predModeIntra of the coding block is greater than INTRA_ANGULAR50, nScale is set equal to $\text{Min}(2, \log_2(nTbH) - \text{Floor}(\log_2(3 * \text{invAngle} - 2)) + 8)$, when $\text{refH} \neq 2 * nTbH$, nScale is updated as follows: $nScaleCb = \log_2(\text{refH} - nTbH) - \text{Floor}(\log_2(3 * \text{invAngle} - 2)) + 8$ $nScale = nScale < 0 ? \min(0, nScaleCb) : \min(2, nScaleCb)$, wherein the variable refH indicates a height of the reference samples, the variable nTbH indicates a height of a transform block.

12. The method according to claim 7, wherein when a value of an intra prediction mode predModeIntra of the coding block is less than INTRA_ANGULAR18, not equal to INTRA_PLANAR and not equal to INTRA_DC, nScale is set equal to

$\text{Min}(2, \log_2(nTbW) - \text{Floor}(\log_2(3 * \text{invAngle} - 2)) + 8)$; when $\text{refW} \neq 2 * nTbW$, nScale is updated as follows: $nScaleCb = \log_2(\text{refW} - nTbW) - \text{Floor}(\log_2(3 * \text{invAngle} - 2)) + 8$ $nScale = nScale < 0 ? \min(0, nScaleCb) : \min(2, nScaleCb)$, wherein the variable refW indicates a width of the reference samples, the variable nTbW indicates a width of a transform block.

13. The method according to claim 7, wherein when a value of an intra prediction mode predModeIntra of the coding block is equal to INTRA_PLANAR, INTRA_DC, INTRA_ANGULAR18, or INTRA_ANGULAR50: nScale is set to $((\log_2(nTbW) + \log_2(nTbH) - 2) >> 2)$; otherwise, when $nTbS = nTbS0$:

$nScale$ is set equal to $\text{Min}(2, \text{Log } 2(nTbS) - \text{Floor}(\text{Log } 2(3 * \text{invAngle} - 2)) + 8)$, $nTbS$ is set equal to $\text{predModeIntra} > \text{INTRA_ANGULAR50}$? $\text{refH} - nTbH$: $\text{refW} - nTbW$, and $nTbS0$ is set equal to $\text{predModeIntra} > \text{INTRA_ANGULAR50}$? $nTbH : nTbW$ otherwise, when $nTbS \neq nTbS0$:
 $nScaleCb = \text{Log } 2(nTbS) - \text{Floor}(\text{Log } 2(3 * \text{invAngle} - 2)) + 8$
 $nScale = \text{Log } 2(nTbS0) - \text{Floor}(\text{Log } 2(3 * \text{invAngle} - 2)) + 8$ $nScale = nScale < 0$? $\text{min}(0, nScaleCb) : \text{min}(2, nScaleCb)$, wherein the variable refH indicates a height of the reference samples, the variable $nTbH$ indicates a height of a transform block, the variable refW indicates a width of the reference samples, the variable $nTbW$ indicates a width of the transform block.

14. The method according to claim 7, wherein when a value of an intra prediction mode predModeIntra of the coding block is greater than INTRA_ANGULAR50 , the following is performed: When $\text{refH} \neq 2 * nTbH$, $nScale$ is set equal to

$\text{Log } 2(\text{refH} - nTbH) < \text{Floor}(\text{Log } 2(3 * \text{invAngle} - 2)) + 8$? $-1 : 0$, Otherwise, $nScale$ is set equal to $\text{Min}(2, \text{Log } 2(nTbH) - \text{Floor}(\text{Log } 2(3 * \text{invAngle} - 2)) + 8)$, wherein the variable refH indicates a height of the reference samples, the variable $nTbH$ indicates a height of a transform block.

15. The method according to claim 7, wherein when a value of an intra prediction mode predModeIntra of the coding block is less than INTRA_ANGULAR18 , not equal to INTRA_PLANAR and not equal to INTRA_DC , the following is performed: when $\text{refW} \neq 2 * nTbW$, $nScale$ is set equal to

$\text{Log } 2(\text{refW} - nTbW) < \text{Floor}(\text{Log } 2(3 * \text{invAngle} - 2)) + 8$? $-1 : 0$, Otherwise, $nScale$ is set equal to $\text{Min}(2, \text{Log } 2(nTbW) - \text{Floor}(\text{Log } 2(3 * \text{invAngle} - 2)) + 8)$, wherein the variable refW indicates a width of the reference samples, the variable $nTbW$ indicates a width of a transform block.

16. A decoder, comprising: one or more processors; and a memory coupled to the one or more processors and storing program instructions, which, when executed by the one or more processors, cause the decoder to: obtain a predicted sample value for a sample of a current coding block; obtain a scaling factor value according to an intra prediction mode for the current coding block, and according to at least one of: a height of the current coding block, or a width of the current coding block, or a size of a subpartition of the current coding block; determine a first weight value based on the scaling factor value; determine a second weight value based on the scaling factor value; weight a top reference sample value with the first weight value to produce a weighted top reference sample; weight a left reference sample value with the second weight value to produce a weighted left reference sample; combine the weighted top reference sample value with the weighted left reference sample value to produce an additional value; and obtain a modified predicted sample value according to the additional value and the predicted sample value, wherein the scaling factor value ($nScale$) is calculated as follows: obtain an initial value of parameter $nScale0$ based on the size of the subpartition ($nTbS$): $nScale0 = \text{min}(2, \text{Log } 2(nTbS) + V2)$; and obtain a final value of the parameter $nScale$ based on the initial value of parameter $nScale0$: $nScale = nScale0 < 0$? $\text{min}(0, V1 + V2) : \text{min}(2, V1 + V2)$, wherein first value “ $V1$ ” is derived from the size of the subpartition, and a size of the current coding block to which the subpartition belongs to; and second value “ $V2$ ” is derived as follows: $V2 = 8 - \text{Floor}(\text{Log } 2(3 * \text{invAngle} - 2))$, and wherein the invAngle is an inverse angle parameter depending on the intra prediction mode for the current coding block; or $nScale = V1 < V2$? $-1 : 0$, wherein the first value “ $V1$ ” is derived from the size of the subpartition, and the size of the current coding block to which the subpartition belongs to; and the second value “ $V2$ ” is derived as follows: $V2 = 8 - \text{Floor}(\text{Log } 2(3 * \text{invAngle} - 2))$, wherein the invAngle is an inverse angle parameter depending on the intra prediction mode for the current coding block.

17. An encoder, comprising: one or more processors; and a memory coupled to the one or more processors and storing program instructions, when executed by the one or more processors, cause the encoder to carry out the method according to claim 7.

18. The decoder according to claim 16, wherein the height of the current coding block is equal to a value of $\text{refH} - nTbH$, the variable refH indicates a height of reference samples, and the variable $nTbH$ indicates a height of a transform block.

19. The decoder according to claim 16, wherein the width of the current coding block is equal to a value of $\text{refW} - nTbW$, the variable refW indicates a width of reference samples, and the variable $nTbW$ indicates a width of a transform block.

20. The decoder according to claim 16, wherein the predicted sample value is processed by using a sample weighting factor to obtain a weighted predicted value, and the modified predicted sample value is obtained according to the additional value and the weighted predicted sample value.
